LinuxQMISDK

SLQS04.00.22

Generated by Doxygen 1.8.6

Wed Sep 11 2019 08:39:43

Contents

1 Welcome to the Sierra Wireless Linux QMI SDK API Reference Guide **1**

1.1 Important Notice 1

1.2 Limitation of Liability 1

1.3 Patents 1

1.4 Copyright 2

1.5 Trademarks 2

1.6 Contact Information 2

2 Module Index **3**

2.1 Modules 3

3 Namespace Index **5**

3.1 Namespace List 5

4 Data Structure Index **7**

4.1 Data Structures 7

5 File Index **39**

5.1 File List 39

6 Module Documentation **43**

6.1 Device Connectivity Service (DCS) 43

6.1.1 Detailed Description 43

6.2 Wireless Data Service (WDS) 44

6.2.1 Detailed Description 44

6.3 Device Management Service (DMS) 45

6.3.1 Detailed Description 45

6.4 Network Access Service (NAS) 46

6.4.1 Detailed Description 46

6.5 CallBacK registration (CBK) 47

6.5.1 Detailed Description 47

6.6 Short Message Service (SMS) 48

6.6.1 Detailed Description 48

6.7 Position Determination Service (PDS) . . . 49
6.7.1 Detailed Description . . . 49
6.8 Card Application Toolkit (CAT) . . . 50
6.8.1 Detailed Description . . . 50
6.9 Remote Management Service (RMS) . . . 51
6.9.1 Detailed Description . . . 51
6.10 Firmware Management Service (FMS) . . . 52
6.10.1 Detailed Description . . . 52
6.11 Open Mobile Alliance Service (OMA) . . . 53
6.11.1 Detailed Description . . . 53
6.12 Specific Absorption Rate (SAR) . . . 54
6.12.1 Detailed Description . . . 54
6.13 SWI Open Mobile Alliance Service (SWIOMA) . . . 55
6.13.1 Detailed Description . . . 55
6.14 Voice Service (VOICE) . . . 56
6.14.1 Detailed Description . . . 56
6.15 Non-service specific APIs (SWI) . . . 57
6.15.1 Detailed Description . . . 57
6.16 User Identity Module Service (UIM) . . . 58
6.16.1 Detailed Description . . . 58
6.17 Audio Service (AUDIO) . . . 59
6.17.1 Detailed Description . . . 59
6.18 Quality of Service (QOS) . . . 60
6.18.1 Detailed Description . . . 60
6.19 IMS Service (IMS) . . . 61
6.19.1 Detailed Description . . . 61
6.20 SWI Audio Service(SWIAUDIO) . . . 62
6.20.1 Detailed Description . . . 62
6.21 Location Service(LOC) . . . 63
6.21.1 Detailed Description . . . 63
6.22 Thermal Mitigation Device(TMD) . . . 64
6.22.1 Detailed Description . . . 64
6.23 AVMS (SWIAVMS) . . . 65
6.23.1 Detailed Description . . . 65
6.24 SWIDMS . . . 66
6.24.1 Detailed Description . . . 66

7 Namespace Documentation **67**
7.1 Tables Namespace Reference . . . 67
7.1.1 Detailed Description . . . 67

8 Data Structure Documentation **69**

8.1 _getIndicationRegResp Struct Reference . . . 69

8.1.1 Detailed Description . . . 69

8.1.2 Field Documentation . . . 70

8.1.2.1 pRegCallStatInfoEvt . . . 70

8.1.2.2 pRegTransLayerInfoEvt . . . 70

8.1.2.3 pRegTransNWRegInfoEvt . . . 70

8.2 _GetProfileSettingIn Struct Reference . . . 70

8.2.1 Detailed Description . . . 70

8.2.2 Field Documentation . . . 70

8.2.2.1 ProfileID . . . 70

8.2.2.2 ProfileType . . . 70

8.3 _GetProfileSettingOut Struct Reference . . . 70

8.3.1 Detailed Description . . . 70

8.3.2 Field Documentation . . . 71

8.3.2.1 curProfile . . . 71

8.3.2.2 pExtErrCode . . . 71

8.4 _getResetInfoNotification Struct Reference . . . 71

8.4.1 Detailed Description . . . 71

8.4.2 Field Documentation . . . 72

8.4.2.1 source . . . 72

8.4.2.2 type . . . 72

8.5 _getTransLayerInfoResp Struct Reference . . . 72

8.5.1 Detailed Description . . . 72

8.5.2 Field Documentation . . . 72

8.5.2.1 pRegInd . . . 72

8.5.2.2 pTransLayerInfo . . . 72

8.6 _getTransNWRegInfoResp Struct Reference . . . 72

8.6.1 Detailed Description . . . 72

8.6.2 Field Documentation . . . 73

8.6.2.1 pRegStatus . . . 73

8.7 _MitigationDevInfo Struct Reference . . . 73

8.7.1 Detailed Description . . . 73

8.7.2 Field Documentation . . . 73

8.7.2.1 deviceID . . . 73

8.7.2.2 deviceIdLen . . . 73

8.8 _modemTempNotification Struct Reference . . . 73

8.8.1 Detailed Description . . . 74

8.8.2 Field Documentation . . . 74

8.8.2.1 ModemTemperature . . . 74

8.8.2.2 ModemTempState . . . 74
8.9 _modemUIMStatusNotification Struct Reference . . . 74
8.9.1 Detailed Description . . . 74
8.9.2 Field Documentation . . . 75
8.9.2.1 ModemUIMStatusEvent . . . 75
8.9.2.2 ModemUIMStatusInterface . . . 75
8.10 _packetSrvStatus Struct Reference . . . 75
8.10.1 Detailed Description . . . 75
8.10.2 Field Documentation . . . 76
8.10.2.1 bearerID . . . 76
8.10.2.2 connStatus . . . 76
8.10.2.3 ipFamily . . . 76
8.10.2.4 pQmiInterfaceInfo . . . 76
8.10.2.5 reconfigReqd . . . 76
8.10.2.6 sessionEndReason . . . 77
8.10.2.7 techName . . . 77
8.10.2.8 verboseSessnEndReason . . . 77
8.10.2.9 verboseSessnEndReasonType . . . 77
8.11 _qaQmi3GPP2BroadcastCfgInfo Struct Reference . . . 77
8.11.1 Detailed Description . . . 77
8.11.2 Field Documentation . . . 77
8.11.2.1 activated_ind . . . 77
8.11.2.2 CDMABroadcastConfig . . . 77
8.11.2.3 num_instances . . . 77
8.12 _qaQmi3GPPBroadcastCfgInfo Struct Reference . . . 77
8.12.1 Detailed Description . . . 78
8.12.2 Field Documentation . . . 78
8.12.2.1 activated_ind . . . 78
8.12.2.2 broadcastConfig . . . 78
8.12.2.3 num_instances . . . 78
8.13 _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp Struct Reference . . . 78
8.13.1 Detailed Description . . . 79
8.13.2 Field Documentation . . . 79
8.13.2.1 bBinaryType . . . 79
8.13.2.2 bSerity . . . 79
8.13.2.3 bState . . . 79
8.13.2.4 bUserInputRequest . . . 79
8.13.2.5 szDescription . . . 80
8.13.2.6 szName . . . 80
8.13.2.7 szVersion . . . 80

8.13.2.8 TlvPresent . . . 80
8.13.2.9 ulPkgDownloadComplete . . . 80
8.13.2.10 ulPkgDownloadSize . . . 80
8.13.2.11 wDescriptionLength . . . 80
8.13.2.12 wNameLength . . . 80
8.13.2.13 wUpdateCompeteStatus . . . 80
8.13.2.14 wUserInputTimeout . . . 80
8.13.2.15 wVersionLength . . . 80
8.14 _QmiSwiAvmsEventReportConfigResp Struct Reference . . . 80
8.14.1 Detailed Description . . . 80
8.14.2 Field Documentation . . . 81
8.14.2.1 bState . . . 81
8.14.2.2 bUserInputRequest . . . 81
8.14.2.3 szAlertMsg . . . 81
8.14.2.4 TlvPresent . . . 81
8.14.2.5 wAlertMsgLength . . . 81
8.14.2.6 wUserInputTimeout . . . 81
8.15 _QmiSwiAvmsEventReportConnectionRequestResp Struct Reference . . . 81
8.15.1 Detailed Description . . . 81
8.15.2 Field Documentation . . . 81
8.15.2.1 bUserInputRequest . . . 81
8.15.2.2 TlvPresent . . . 81
8.15.2.3 wUserInputTimeout . . . 81
8.16 _QmiSwiAvmsEventReportDataSessionStatusResp Struct Reference . . . 81
8.16.1 Detailed Description . . . 81
8.16.2 Field Documentation . . . 82
8.16.2.1 bType . . . 82
8.16.2.2 TlvPresent . . . 82
8.16.2.3 wErrorCode . . . 82
8.17 _QmiSwiAvmsEventReportHTTPStatusResp Struct Reference . . . 82
8.17.1 Detailed Description . . . 82
8.17.2 Field Documentation . . . 83
8.17.2.1 TlvPresent . . . 83
8.17.2.2 wHTTPStatus . . . 84
8.18 _QmiSwiAvmsEventReportNotificationResp Struct Reference . . . 84
8.18.1 Detailed Description . . . 84
8.18.2 Field Documentation . . . 84
8.18.2.1 bNotification . . . 84
8.18.2.2 TlvPresent . . . 85
8.18.2.3 wSessionStatus . . . 85

8.19 _QmiSwiAvmsEventReportPackageIDResp Struct Reference . . . 85
8.19.1 Detailed Description . . . 85
8.19.2 Field Documentation . . . 85
8.19.2.1 bPackageID . . . 85
8.19.2.2 TlvPresent . . . 85
8.20 _QmiSwiAvmsEventReportRegStatusResp Struct Reference . . . 85
8.20.1 Detailed Description . . . 85
8.20.2 Field Documentation . . . 85
8.20.2.1 bRegStatus . . . 85
8.20.2.2 TlvPresent . . . 85
8.21 _QmiSwiAvmsEventReportSessionTypeResp Struct Reference . . . 85
8.21.1 Detailed Description . . . 86
8.21.2 Field Documentation . . . 86
8.21.2.1 bType . . . 86
8.21.2.2 TlvPresent . . . 86
8.22 _QmiSwiAvmsEventReportWAMSParamChangeResp Struct Reference . . . 86
8.22.1 Detailed Description . . . 86
8.22.2 Field Documentation . . . 86
8.22.2.1 TlvPresent . . . 86
8.22.2.2 wWamsChangeMask . . . 86
8.23 _QmiSwiAvmsSetSettingsAPNInfo Struct Reference . . . 86
8.23.1 Field Documentation . . . 87
8.23.1.1 bAPNLength . . . 87
8.23.1.2 bPWDLength . . . 87
8.23.1.3 bUnameLength . . . 87
8.23.1.4 szAPN . . . 87
8.23.1.5 szPWD . . . 87
8.23.1.6 szUname . . . 87
8.24 _QmiSwiAvmsSetSettingsConnectionRetryTimers Struct Reference . . . 87
8.24.1 Field Documentation . . . 87
8.24.1.1 Timers . . . 87
8.25 _QmiSwiAvmsSetSettingsPeriodInfo Struct Reference . . . 87
8.25.1 Field Documentation . . . 87
8.25.1.1 ulMax . . . 87
8.25.1.2 ulMin . . . 87
8.26 _setIndicationRegReq Struct Reference . . . 87
8.26.1 Detailed Description . . . 88
8.26.2 Field Documentation . . . 88
8.26.2.1 pRegCallStatInfoEvt . . . 88
8.26.2.2 pRegTransLayerInfoEvt . . . 88

8.26.2.3 pRegTransNWRegInfoEvt . . . 88
8.27 _slqs3GPPConfigItem Struct Reference . . . 88
8.27.1 Detailed Description . . . 89
8.27.2 Field Documentation . . . 90
8.27.2.1 LTEAttachProfileListLen . . . 90
8.27.2.2 p3gppRelease . . . 90
8.27.2.3 pDefaultPDNEnabled . . . 90
8.27.2.4 pLTEAttachProfile . . . 90
8.27.2.5 pLTEAttachProfileList . . . 90
8.27.2.6 pProfileList . . . 90
8.28 _SLQSAVMSSetSettingsReqPara Struct Reference . . . 90
8.28.1 Detailed Description . . . 90
8.28.2 Field Documentation . . . 92
8.28.2.1 pAPNInfo . . . 92
8.28.2.2 pAutoConnect . . . 92
8.28.2.3 pAutoReboot . . . 92
8.28.2.4 pConnectionRetryTimers . . . 92
8.28.2.5 pFwAutoSDM . . . 92
8.28.2.6 pFwPromptdownload . . . 92
8.28.2.7 pFwPromptUpdate . . . 92
8.28.2.8 pNotifStore . . . 92
8.28.2.9 pPeroidInfo . . . 92
8.28.2.10 pPollingTimer . . . 92
8.29 _SLQSAVMSSetSettingsReqPara_v2 Struct Reference . . . 92
8.29.1 Detailed Description . . . 92
8.29.2 Field Documentation . . . 93
8.29.2.1 pAPNInfo . . . 93
8.29.2.2 pAutoConnect . . . 93
8.29.2.3 pAutoReboot . . . 94
8.29.2.4 pConnectionRetryTimers . . . 94
8.29.2.5 pFwAutoSDM . . . 94
8.29.2.6 pFwPromptdownload . . . 94
8.29.2.7 pFwPromptUpdate . . . 94
8.29.2.8 pNotifStore . . . 94
8.29.2.9 pPeroidInfo . . . 94
8.29.2.10 pPollingTimer . . . 94
8.30 _SLQSAVMSSettings Struct Reference . . . 94
8.30.1 Field Documentation . . . 94
8.30.1.1 pAPNInfo . . . 94
8.30.1.2 pAutoConnect . . . 94

8.30.1.3 pAutoReboot . . . 94
8.30.1.4 pConnectionRetryTimers . . . 94
8.30.1.5 pFwAutoSDM . . . 94
8.30.1.6 pFwPromptdownload . . . 94
8.30.1.7 pFwPromptUpdate . . . 94
8.30.1.8 pNotificationStore . . . 94
8.30.1.9 pOMADMEnabled . . . 94
8.30.1.10 pPeroidsInfo . . . 94
8.30.1.11 pPollingTimer . . . 95
8.31 _SLQSAVMSSettings_v2 Struct Reference . . . 95
8.31.1 Field Documentation . . . 95
8.31.1.1 pAPNInfo . . . 95
8.31.1.2 pAutoConnect . . . 95
8.31.1.3 pAutoReboot . . . 95
8.31.1.4 pConnectionRetryTimers . . . 95
8.31.1.5 pFwAutoSDM . . . 95
8.31.1.6 pFwPromptdownload . . . 95
8.31.1.7 pFwPromptUpdate . . . 95
8.31.1.8 pNotificationStore . . . 95
8.31.1.9 pOMADMEnabled . . . 95
8.31.1.10 pPeroidsInfo . . . 95
8.31.1.11 pPollingTimer . . . 95
8.32 _SLQSAVMSSettingsAPNInfo Struct Reference . . . 95
8.32.1 Field Documentation . . . 96
8.32.1.1 bAPNLength . . . 96
8.32.1.2 bPWDLength . . . 96
8.32.1.3 bUnameLength . . . 96
8.32.1.4 pAPN . . . 96
8.32.1.5 pPWD . . . 96
8.32.1.6 pUname . . . 96
8.33 _SLQSAVMSSettingsConnectionRetryTimers Struct Reference . . . 96
8.33.1 Field Documentation . . . 96
8.33.1.1 Timers . . . 96
8.34 _SLQSAVMSSettingsPeriodsInfo Struct Reference . . . 96
8.34.1 Field Documentation . . . 96
8.34.1.1 max . . . 96
8.34.1.2 min . . . 96
8.35 _SlqsNas3GppNetworkRAT_ Struct Reference . . . 96
8.35.1 Detailed Description . . . 96
8.35.2 Field Documentation . . . 97

8.35.2.1 MCC . . . 97
8.35.2.2 MNC . . . 97
8.35.2.3 RAT . . . 97
8.36 _slqsNetworkScanInfo Struct Reference . . . 97
8.36.1 Detailed Description . . . 97
8.36.2 Field Documentation . . . 98
8.36.2.1 has_PCIInfo . . . 98
8.36.2.2 pLteOpModeTlv . . . 98
8.36.2.3 pNetworkInfo . . . 98
8.36.2.4 pNetworkInfoInstances . . . 98
8.36.2.5 pPCIInfo . . . 98
8.36.2.6 pPCSDigitInfo . . . 98
8.36.2.7 pPCSDigitInstances . . . 98
8.36.2.8 pRATInfo . . . 99
8.36.2.9 pRATInstances . . . 99
8.36.2.10 pScanResult . . . 99
8.37 _slqsNetworkScanInfoReq Struct Reference . . . 99
8.37.1 Detailed Description . . . 99
8.37.2 Field Documentation . . . 101
8.37.2.1 pCiotOpModePref . . . 101
8.37.2.2 pLteM1BandPref . . . 102
8.37.2.3 pLteNB1BandPref . . . 102
8.37.2.4 pNetworkType . . . 102
8.37.2.5 pScanType . . . 102
8.38 _SLQSOMADMSessionInfo Struct Reference . . . 102
8.38.1 Detailed Description . . . 102
8.38.2 Field Documentation . . . 104
8.38.2.1 pDate . . . 104
8.38.2.2 pDateLength . . . 104
8.38.2.3 pPkgDescLength . . . 104
8.38.2.4 pPkgDescription . . . 104
8.38.2.5 pPkgName . . . 104
8.38.2.6 pPkgNameLength . . . 104
8.38.2.7 pRetryCount . . . 104
8.38.2.8 pSessionState . . . 104
8.38.2.9 pSessionType . . . 104
8.38.2.10 pSeverity . . . 104
8.38.2.11 pSource . . . 104
8.38.2.12 pSourceLength . . . 104
8.38.2.13 pStatus . . . 104

8.38.2.14 pTime . . . 104
8.38.2.15 pTimeLength . . . 104
8.38.2.16 pUpdateCompleteStatus . . . 104
8.39 _SLQSOMADMSettings Struct Reference . . . 104
8.39.1 Detailed Description . . . 105
8.39.2 Field Documentation . . . 106
8.39.2.1 pAutosdm . . . 106
8.39.2.2 pFOTAdownload . . . 106
8.39.2.3 pFOTAUpdate . . . 106
8.39.2.4 pFwAutoCheck . . . 106
8.39.2.5 pOMADMEnabled . . . 106
8.40 _SLQSOMADMSettingsReqParams Struct Reference . . . 106
8.40.1 Detailed Description . . . 106
8.40.2 Field Documentation . . . 107
8.40.2.1 FOTAdownload . . . 107
8.40.2.2 FOTAUpdate . . . 107
8.40.2.3 pAutosdm . . . 107
8.41 _SLQSOMADMSettingsReqParams3 Struct Reference . . . 107
8.41.1 Detailed Description . . . 107
8.41.2 Field Documentation . . . 108
8.41.2.1 FOTAdownload . . . 108
8.41.2.2 FOTAUpdate . . . 108
8.41.2.3 pAutosdm . . . 108
8.41.2.4 pFwAutoCheck . . . 108
8.42 _SLQSSwiGetHostDevInfoParams Struct Reference . . . 108
8.42.1 Detailed Description . . . 108
8.42.2 Field Documentation . . . 109
8.42.2.1 bHostIDSize . . . 109
8.42.2.2 bManSize . . . 109
8.42.2.3 bModelSize . . . 109
8.42.2.4 bPlasmaIDSize . . . 109
8.42.2.5 bSWVerSize . . . 109
8.42.2.6 pHostID . . . 109
8.42.2.7 pManString . . . 109
8.42.2.8 pModelString . . . 109
8.42.2.9 pPlasmaIDString . . . 109
8.42.2.10 pSWVerString . . . 109
8.43 _SLQSSwiGetOSInfoParams Struct Reference . . . 109
8.43.1 Detailed Description . . . 109
8.43.2 Field Documentation . . . 110

8.43.2.1 bNameSize . . . 110
8.43.2.2 bVersionSize . . . 110
8.43.2.3 pNameString . . . 110
8.43.2.4 pVersionString . . . 110
8.44 _SLQSSwiGetSerialNoExtParams Struct Reference . . . 110
8.44.1 Detailed Description . . . 110
8.44.2 Field Documentation . . . 110
8.44.2.1 meidLength . . . 110
8.44.2.2 pMeidString . . . 110
8.45 _SLQSSwiSetHostDevInfoParams Struct Reference . . . 110
8.45.1 Detailed Description . . . 111
8.45.2 Field Documentation . . . 111
8.45.2.1 bHostIDSize . . . 111
8.45.2.2 bManSize . . . 111
8.45.2.3 bModelSize . . . 111
8.45.2.4 bPlasmaIDSize . . . 111
8.45.2.5 bSWVerSize . . . 111
8.45.2.6 pHostID . . . 112
8.45.2.7 pManString . . . 112
8.45.2.8 pModelString . . . 112
8.45.2.9 pPlasmaIDString . . . 112
8.45.2.10 pSWVerString . . . 112
8.46 _SLQSSwiSetOSInfoParams Struct Reference . . . 112
8.46.1 Detailed Description . . . 112
8.46.2 Field Documentation . . . 112
8.46.2.1 bNameSize . . . 112
8.46.2.2 bVersionSize . . . 112
8.46.2.3 pNameString . . . 112
8.46.2.4 pVersionString . . . 112
8.47 _SwiAvmsEventInd Struct Reference . . . 112
8.47.1 Field Documentation . . . 113
8.47.1.1 BinaryUpdateSessionInfo . . . 113
8.47.1.2 Config . . . 113
8.47.1.3 ConnectionRequest . . . 113
8.47.1.4 DataSessionStatus . . . 113
8.47.1.5 HTTPStatus . . . 113
8.47.1.6 Notification . . . 113
8.47.1.7 PackageID . . . 113
8.47.1.8 RegStatus . . . 113
8.47.1.9 SessionType . . . 113

8.47.1.10 WAMSParaChanged . . . 113
8.48 _sysSelectPrefExtInfo Struct Reference . . . 113
8.48.1 Detailed Description . . . 113
8.48.2 Field Documentation . . . 114
8.48.2.1 pAcqOrderPref . . . 114
8.48.2.2 pCiotAcqOrderPref . . . 114
8.48.2.3 pCiotLteOpModePref . . . 114
8.48.2.4 pLTEBandPrefExt . . . 114
8.48.2.5 pLteM1BandPref . . . 114
8.48.2.6 pLteNb1BandPref . . . 115
8.48.2.7 pNr5gBandPref . . . 115
8.48.2.8 pRatDisabledMask . . . 115
8.48.2.9 pSysSelectPrefInfo . . . 115
8.49 _sysSelectPrefInfo Struct Reference . . . 115
8.49.1 Detailed Description . . . 115
8.49.2 Field Documentation . . . 119
8.49.2.1 pBandPref . . . 119
8.49.2.2 pEmerMode . . . 119
8.49.2.3 pGWAcqOrderPref . . . 119
8.49.2.4 pLTEBandPref . . . 119
8.49.2.5 pModePref . . . 119
8.49.2.6 pNetSelPref . . . 119
8.49.2.7 pPRLPref . . . 119
8.49.2.8 pRoamPref . . . 119
8.49.2.9 pSrvDomainPref . . . 119
8.50 _sysSelectPrefParams Struct Reference . . . 120
8.50.1 Detailed Description . . . 120
8.50.2 Field Documentation . . . 125
8.50.2.1 pAcqOrderPref . . . 125
8.50.2.2 pBandPref . . . 125
8.50.2.3 pChgDuration . . . 125
8.50.2.4 pCSGID . . . 125
8.50.2.5 pEmerMode . . . 125
8.50.2.6 pGWAcqOrderPref . . . 125
8.50.2.7 pLTEBandPref . . . 125
8.50.2.8 pMNCIncPCSDigStat . . . 125
8.50.2.9 pModePref . . . 125
8.50.2.10 pNetSelPref . . . 125
8.50.2.11 pPRLPref . . . 126
8.50.2.12 pRAT . . . 126

8.50.2.13 pRoamPref . . . 126
8.50.2.14 pSrvDomainPref . . . 126
8.50.2.15 pSrvRegRestriction . . . 126
8.50.2.16 pTdscdmaBandPref . . . 126
8.51 _transLayerinfo Struct Reference . . . 126
8.51.1 Detailed Description . . . 126
8.51.2 Field Documentation . . . 126
8.51.2.1 TransCap . . . 126
8.51.2.2 TransType . . . 126
8.52 _transLayerInfoNotification Struct Reference . . . 126
8.52.1 Detailed Description . . . 127
8.52.2 Field Documentation . . . 127
8.52.2.1 pTransLayerInfo . . . 127
8.52.2.2 regInd . . . 127
8.52.2.3 results . . . 127
8.53 _transNWRegInfoNotification Struct Reference . . . 127
8.53.1 Detailed Description . . . 127
8.53.2 Field Documentation . . . 128
8.53.2.1 NWRegStat . . . 128
8.53.2.2 results . . . 128
8.54 accelAcceptReady_s Struct Reference . . . 128
8.54.1 Detailed Description . . . 128
8.54.2 Field Documentation . . . 128
8.54.2.1 batchPerSec . . . 128
8.54.2.2 injectEnable . . . 128
8.54.2.3 samplesPerBatch . . . 128
8.55 accelTempAcceptReady_s Struct Reference . . . 128
8.55.1 Detailed Description . . . 129
8.55.2 Field Documentation . . . 129
8.55.2.1 batchPerSec . . . 129
8.55.2.2 injectEnable . . . 129
8.55.2.3 samplesPerBatch . . . 129
8.56 acqOrderPref Struct Reference . . . 129
8.56.1 Detailed Description . . . 129
8.56.2 Field Documentation . . . 130
8.56.2.1 acqOrdeLen . . . 130
8.56.2.2 pAcqOrder . . . 130
8.57 AcqOrderPrefTlv Struct Reference . . . 130
8.57.1 Detailed Description . . . 130
8.57.2 Field Documentation . . . 130

8.57.2.1 acqOrdeLen . . . 131
8.57.2.2 pAcqOrder . . . 131
8.57.2.3 TlvPresent . . . 131
8.58 ActPilotPNElement Struct Reference . . . 131
8.58.1 Detailed Description . . . 131
8.58.2 Field Documentation . . . 131
8.58.2.1 ActSetPilotPN . . . 131
8.58.2.2 ActSetPilotPNStrength . . . 131
8.59 AddCDMASysInfo Struct Reference . . . 131
8.59.1 Detailed Description . . . 131
8.59.2 Field Documentation . . . 132
8.59.2.1 geoSysIdx . . . 132
8.59.2.2 regPrd . . . 132
8.60 AddSysInfo Struct Reference . . . 132
8.60.1 Detailed Description . . . 132
8.60.2 Field Documentation . . . 132
8.60.2.1 cellBroadcastCap . . . 132
8.60.2.2 geoSysIdx . . . 132
8.61 airTimer Struct Reference . . . 132
8.61.1 Detailed Description . . . 132
8.61.2 Field Documentation . . . 133
8.61.2.1 airTimerValue . . . 133
8.61.2.2 namID . . . 133
8.62 allCallsAlphaIDInfo Struct Reference . . . 133
8.62.1 Detailed Description . . . 133
8.62.2 Field Documentation . . . 133
8.62.2.1 AlphaIDInfo . . . 133
8.62.2.2 callID . . . 133
8.63 allCallsDiagInfo Struct Reference . . . 133
8.63.1 Detailed Description . . . 134
8.63.2 Field Documentation . . . 134
8.63.2.1 callID . . . 134
8.63.2.2 DiagInfo . . . 134
8.64 allCallsUUSInfo Struct Reference . . . 134
8.64.1 Detailed Description . . . 134
8.64.2 Field Documentation . . . 134
8.64.2.1 callID . . . 134
8.64.2.2 uusInfo . . . 134
8.65 alphaIDInfo Struct Reference . . . 134
8.65.1 Detailed Description . . . 135

8.65.2 Field Documentation . . . 135
8.65.2.1 alphaDcs . . . 135
8.65.2.2 alphaLen . . . 135
8.65.2.3 alphaText . . . 135
8.66 altitudeSrcInfo Struct Reference . . . 135
8.66.1 Detailed Description . . . 135
8.66.2 Field Documentation . . . 136
8.66.2.1 coverage . . . 136
8.66.2.2 linkage . . . 136
8.66.2.3 source . . . 136
8.67 altSrcInfo_t Struct Reference . . . 136
8.67.1 Detailed Description . . . 136
8.67.2 Field Documentation . . . 137
8.67.2.1 coverage . . . 137
8.67.2.2 linkage . . . 137
8.67.2.3 source . . . 137
8.68 appStats Struct Reference . . . 137
8.68.1 Detailed Description . . . 138
8.68.2 Field Documentation . . . 140
8.68.2.1 aidLength . . . 140
8.68.2.2 aidVal . . . 140
8.68.2.3 appState . . . 140
8.68.2.4 appType . . . 140
8.68.2.5 persoFeature . . . 140
8.68.2.6 persoRetries . . . 140
8.68.2.7 persoState . . . 140
8.68.2.8 persoUnblockRetries . . . 140
8.68.2.9 pin1Retries . . . 140
8.68.2.10 pin1State . . . 140
8.68.2.11 pin2Retries . . . 140
8.68.2.12 pin2State . . . 140
8.68.2.13 puk1Retries . . . 140
8.68.2.14 puk2Retries . . . 140
8.68.2.15 univPin . . . 140
8.69 appStatus Struct Reference . . . 140
8.69.1 Detailed Description . . . 141
8.69.2 Field Documentation . . . 143
8.69.2.1 aidLength . . . 143
8.69.2.2 aidVal . . . 143
8.69.2.3 appState . . . 143

8.69.2.4 appType . . . 143
8.69.2.5 persoFeature . . . 143
8.69.2.6 persoRetries . . . 143
8.69.2.7 persoState . . . 143
8.69.2.8 persoUnblockRetries . . . 143
8.69.2.9 pin1Retries . . . 143
8.69.2.10 pin1State . . . 143
8.69.2.11 pin2Retries . . . 143
8.69.2.12 pin2State . . . 143
8.69.2.13 puk1Retries . . . 143
8.69.2.14 puk2Retries . . . 143
8.69.2.15 univPin . . . 143
8.70 arrAlertingPattern Struct Reference . . . 143
8.70.1 Detailed Description . . . 144
8.70.2 Field Documentation . . . 144
8.70.2.1 alertingPattern . . . 144
8.70.2.2 callID . . . 144
8.70.2.3 numInstances . . . 144
8.71 arrAlertingType Struct Reference . . . 144
8.71.1 Detailed Description . . . 144
8.71.2 Field Documentation . . . 145
8.71.2.1 AlertingType . . . 145
8.71.2.2 callID . . . 145
8.71.2.3 numInstances . . . 145
8.72 arrAlphaID Struct Reference . . . 145
8.72.1 Detailed Description . . . 145
8.72.2 Field Documentation . . . 145
8.72.2.1 allCallsAlphaIDInfoArr . . . 145
8.72.2.2 numInstances . . . 145
8.73 arrCalledPartyNum Struct Reference . . . 145
8.73.1 Detailed Description . . . 146
8.73.2 Field Documentation . . . 146
8.73.2.1 CalledPartyNum . . . 146
8.73.2.2 numInstances . . . 146
8.74 arrCallEndReason Struct Reference . . . 146
8.74.1 Detailed Description . . . 146
8.74.2 Field Documentation . . . 147
8.74.2.1 callEndReason . . . 147
8.74.2.2 callID . . . 147
8.74.2.3 numInstances . . . 147

8.75 arrCallInfo Struct Reference . . . 147
8.75.1 Detailed Description . . . 147
8.75.2 Field Documentation . . . 147
8.75.2.1 getAllCallInfo . . . 147
8.75.2.2 numInstances . . . 147
8.76 arrConnectPartyNum Struct Reference . . . 147
8.76.1 Detailed Description . . . 147
8.76.2 Field Documentation . . . 148
8.76.2.1 ConnectedPartyNum . . . 148
8.76.2.2 numInstances . . . 148
8.77 arrDiagInfo Struct Reference . . . 148
8.77.1 Detailed Description . . . 148
8.77.2 Field Documentation . . . 148
8.77.2.1 DiagInfo . . . 148
8.77.2.2 numInstances . . . 148
8.78 arrRedirPartyNum Struct Reference . . . 148
8.78.1 Detailed Description . . . 148
8.78.2 Field Documentation . . . 149
8.78.2.1 numInstances . . . 149
8.78.2.2 RedirPartyNum . . . 149
8.79 arrRemotePartyName Struct Reference . . . 149
8.79.1 Detailed Description . . . 149
8.79.2 Field Documentation . . . 149
8.79.2.1 GetAllCallRmtPtyName . . . 149
8.79.2.2 numInstances . . . 149
8.80 arrRemotePartyNum Struct Reference . . . 149
8.80.1 Detailed Description . . . 150
8.80.2 Field Documentation . . . 150
8.80.2.1 numInstances . . . 150
8.80.2.2 RmtPtyNum . . . 150
8.81 arrSvcOption Struct Reference . . . 150
8.81.1 Detailed Description . . . 150
8.81.2 Field Documentation . . . 150
8.81.2.1 callID . . . 150
8.81.2.2 numInstances . . . 150
8.81.2.3 srvOption . . . 151
8.82 arrUUSInfo Struct Reference . . . 151
8.82.1 Detailed Description . . . 151
8.82.2 Field Documentation . . . 151
8.82.2.1 AllCallsUUSInfo . . . 151

8.82.2.2 numInstances . . . 151
8.83 authenticateResult Struct Reference . . . 151
8.83.1 Detailed Description . . . 151
8.83.2 Field Documentation . . . 152
8.83.2.1 content . . . 152
8.83.2.2 contentLen . . . 152
8.84 authenticationData Struct Reference . . . 152
8.84.1 Detailed Description . . . 152
8.84.2 Field Documentation . . . 152
8.84.2.1 context . . . 153
8.84.2.2 data . . . 153
8.84.2.3 dataLen . . . 153
8.85 BandCapabilityResp Struct Reference . . . 153
8.85.1 Detailed Description . . . 153
8.85.2 Field Documentation . . . 156
8.85.2.1 bandCapability . . . 156
8.85.2.2 pLteBandCapability . . . 156
8.85.2.3 pTdsBandCapability . . . 156
8.86 BandPrefTlv Struct Reference . . . 156
8.86.1 Detailed Description . . . 156
8.86.2 Field Documentation . . . 156
8.86.2.1 bits_129_192 . . . 157
8.86.2.2 bits_193_256 . . . 157
8.86.2.3 bits_1_64 . . . 157
8.86.2.4 bits_65_128 . . . 157
8.86.2.5 TlvPresent . . . 157
8.87 BdsSV Struct Reference . . . 157
8.87.1 Detailed Description . . . 157
8.87.2 Field Documentation . . . 157
8.87.2.1 id . . . 157
8.87.2.2 mask . . . 157
8.88 BdsSVInfo Struct Reference . . . 157
8.88.1 Detailed Description . . . 157
8.88.2 Field Documentation . . . 158
8.88.2.1 len . . . 158
8.88.2.2 pSV . . . 158
8.89 BroadcastConfig Struct Reference . . . 158
8.89.1 Detailed Description . . . 158
8.89.2 Field Documentation . . . 158
8.89.2.1 fromServiceId . . . 158

8.89.2.2 selected . . . 158
8.89.2.3 toServiceId . . . 158
8.90 burstDTMFInfo Struct Reference . . . 158
8.90.1 Detailed Description . . . 159
8.90.2 Field Documentation . . . 159
8.90.2.1 digitCnt . . . 159
8.90.2.2 pCallID . . . 159
8.90.2.3 pDigitBuff . . . 159
8.91 CallBarringSysInfo Struct Reference . . . 159
8.91.1 Detailed Description . . . 159
8.91.2 Field Documentation . . . 160
8.91.2.1 csBarStatus . . . 160
8.91.2.2 psBarStatus . . . 160
8.92 callBarStatus Struct Reference . . . 160
8.92.1 Detailed Description . . . 160
8.92.2 Field Documentation . . . 161
8.92.2.1 csBarStatus . . . 161
8.92.2.2 psBarStatus . . . 161
8.93 calledPartyInfo Struct Reference . . . 161
8.93.1 Detailed Description . . . 161
8.93.2 Field Documentation . . . 162
8.93.2.1 number . . . 162
8.93.2.2 numLen . . . 162
8.93.2.3 numPlan . . . 162
8.93.2.4 numType . . . 162
8.93.2.5 PI . . . 162
8.93.2.6 SI . . . 162
8.94 calledPartySubAdd Struct Reference . . . 162
8.94.1 Detailed Description . . . 163
8.94.2 Field Documentation . . . 163
8.94.2.1 extBit . . . 163
8.94.2.2 oddEvenInd . . . 163
8.94.2.3 subAddr . . . 163
8.94.2.4 subAddrLen . . . 163
8.94.2.5 subAddrType . . . 163
8.95 callerIDInfo Struct Reference . . . 163
8.95.1 Detailed Description . . . 164
8.95.2 Field Documentation . . . 164
8.95.2.1 callerID . . . 164
8.95.2.2 callerIDLen . . . 164

8.95.2.3 PI . . . 164
8.96 callFwdTypeAndPlan Struct Reference . . . 164
8.96.1 Detailed Description . . . 164
8.96.2 Field Documentation . . . 165
8.96.2.1 numberPlan . . . 165
8.96.2.2 numberType . . . 165
8.97 callFWExtInfo Struct Reference . . . 165
8.97.1 Detailed Description . . . 165
8.97.2 Field Documentation . . . 166
8.97.2.1 noReplyTimer . . . 166
8.97.2.2 number . . . 166
8.97.2.3 numLen . . . 167
8.97.2.4 numPlan . . . 167
8.97.2.5 numType . . . 167
8.97.2.6 PI . . . 167
8.97.2.7 SI . . . 167
8.97.2.8 SvcClass . . . 167
8.97.2.9 SvcStatus . . . 167
8.98 callFWInfo Struct Reference . . . 167
8.98.1 Detailed Description . . . 167
8.98.2 Field Documentation . . . 167
8.98.2.1 noReplyTimer . . . 167
8.98.2.2 number . . . 168
8.98.2.3 numLen . . . 168
8.98.2.4 SvcClass . . . 168
8.98.2.5 SvcStatus . . . 168
8.99 callInfo Struct Reference . . . 168
8.99.1 Detailed Description . . . 168
8.99.2 Field Documentation . . . 169
8.99.2.1 callID . . . 169
8.99.2.2 callState . . . 169
8.99.2.3 callType . . . 169
8.99.2.4 direction . . . 169
8.99.2.5 mode . . . 169
8.100 callingPartyInfo Struct Reference . . . 169
8.100.1 Detailed Description . . . 170
8.100.2 Field Documentation . . . 171
8.100.2.1 number . . . 171
8.100.2.2 numLen . . . 171
8.100.2.3 numPlan . . . 171

8.100.2.4 numType . . . 171
8.100.2.5 PI . . . 171
8.100.2.6 SI . . . 171
8.101 cardResult Struct Reference . . . 171
8.101.1 Detailed Description . . . 171
8.101.2 Field Documentation . . . 171
8.101.2.1 sw1 . . . 171
8.101.2.2 sw2 . . . 171
8.102 cardStatus Struct Reference . . . 171
8.102.1 Detailed Description . . . 172
8.102.2 Field Documentation . . . 172
8.102.2.1 index1xPri . . . 172
8.102.2.2 index1xSec . . . 172
8.102.2.3 indexGwPri . . . 172
8.102.2.4 indexGwSec . . . 172
8.102.2.5 numSlot . . . 172
8.102.2.6 SlotInfo . . . 173
8.103 CarrierImage_t Struct Reference . . . 173
8.103.1 Detailed Description . . . 173
8.103.2 Field Documentation . . . 173
8.103.2.1 m_FwBuildId . . . 173
8.103.2.2 m_FwImageId . . . 173
8.103.2.3 m_nCarrierId . . . 174
8.103.2.4 m_nFolderId . . . 174
8.103.2.5 m_nStorage . . . 174
8.103.2.6 m_PriBuildId . . . 174
8.103.2.7 m_PriImageId . . . 174
8.104 CatAlPhaIdentifierTlv Struct Reference . . . 174
8.104.1 Detailed Description . . . 174
8.104.2 Field Documentation . . . 174
8.104.2.1 AlphaID . . . 174
8.104.2.2 AlphaIDLength . . . 174
8.104.2.3 ReferenceID . . . 174
8.105 CatCommonEventTlv Struct Reference . . . 174
8.105.1 Field Documentation . . . 174
8.105.1.1 CatEvent . . . 174
8.105.1.2 EventID . . . 174
8.105.1.3 EventLength . . . 174
8.105.1.4 TlvPresent . . . 175
8.106 CatEndProactiveSessionTlv Struct Reference . . . 175

8.106.1 Detailed Description . . . 175
8.106.2 Field Documentation . . . 175
8.106.2.1 EndProactiveSession . . . 175
8.107 CATEventDataType Struct Reference . . . 175
8.107.1 Field Documentation . . . 175
8.107.1.1 eventMask . . . 175
8.107.1.2 pErrorMask . . . 175
8.108 CatEventIDDataTlv Struct Reference . . . 175
8.108.1 Detailed Description . . . 175
8.108.2 Field Documentation . . . 176
8.108.2.1 Data . . . 176
8.108.2.2 DataLength . . . 176
8.108.2.3 ReferenceID . . . 176
8.109 CatEventListTlv Struct Reference . . . 176
8.109.1 Detailed Description . . . 176
8.109.2 Field Documentation . . . 176
8.109.2.1 SetupEventList . . . 176
8.110 CatRefreshTlv Struct Reference . . . 176
8.110.1 Detailed Description . . . 176
8.110.2 Field Documentation . . . 177
8.110.2.1 RefreshMode . . . 177
8.110.2.2 RefreshStage . . . 177
8.111 ccSUPSType Struct Reference . . . 177
8.111.1 Detailed Description . . . 177
8.111.2 Field Documentation . . . 177
8.111.2.1 reason . . . 177
8.111.2.2 svcType . . . 177
8.112 CDMABroadcastConfig Struct Reference . . . 177
8.112.1 Detailed Description . . . 178
8.112.2 Field Documentation . . . 178
8.112.2.1 language . . . 178
8.112.2.2 selected . . . 178
8.112.2.3 serviceCategory . . . 178
8.113 CDMAChannel Struct Reference . . . 178
8.113.1 Detailed Description . . . 178
8.113.2 Field Documentation . . . 179
8.113.2.1 priChA . . . 179
8.113.2.2 priChB . . . 179
8.113.2.3 secChA . . . 179
8.113.2.4 secChB . . . 179

8.114 CDMAECIOThresh Struct Reference . . . 179
8.114.1 Detailed Description . . . 179
8.114.2 Field Documentation . . . 179
8.114.2.1 CDMAECIOThreshListLen . . . 179
8.114.2.2 pCDMAECIOThreshList . . . 179
8.115 CDMAInfo Struct Reference . . . 179
8.115.1 Detailed Description . . . 180
8.115.2 Field Documentation . . . 180
8.115.2.1 baseId . . . 180
8.115.2.2 baseLat . . . 180
8.115.2.3 baseLong . . . 180
8.115.2.4 nid . . . 180
8.115.2.5 refpn . . . 180
8.115.2.6 sid . . . 180
8.116 cdmaMsgDecodingParams Struct Reference . . . 180
8.116.1 Detailed Description . . . 181
8.116.2 Field Documentation . . . 182
8.116.2.1 absoluteValidity . . . 182
8.116.2.2 mcTimeStamp . . . 183
8.116.2.3 messageLength . . . 183
8.116.2.4 pAlertPriority . . . 183
8.116.2.5 pCallbkAddr . . . 183
8.116.2.6 pCallbkAddrLength . . . 183
8.116.2.7 pDisplayMode . . . 183
8.116.2.8 pLanguage . . . 183
8.116.2.9 pMessage . . . 183
8.116.2.10 pMessageID . . . 183
8.116.2.11 pPriority . . . 183
8.116.2.12 pPrivacy . . . 183
8.116.2.13 pReadAcknowledgementReq . . . 183
8.116.2.14 pRelativeValidity . . . 183
8.116.2.15 pSenderAddrLength . . . 183
8.116.2.16 pTextMsgLength . . . 183
8.116.2.17 pUserAcknowledgementReq . . . 183
8.116.2.18 senderAddr . . . 183
8.116.2.19 textMsg . . . 183
8.117 cdmaMsgDecodingParamsExt Struct Reference . . . 183
8.117.1 Detailed Description . . . 184
8.117.2 Field Documentation . . . 186
8.117.2.1 absoluteValidity . . . 186

8.117.2.2 mcTimeStamp . . . 186
8.117.2.3 messageLength . . . 186
8.117.2.4 pAlertPriority . . . 186
8.117.2.5 pCallbkAddr . . . 186
8.117.2.6 pCallbkAddrLength . . . 186
8.117.2.7 pDisplayMode . . . 186
8.117.2.8 pIsUDHPresent . . . 186
8.117.2.9 pLanguage . . . 186
8.117.2.10 pMessage . . . 186
8.117.2.11 pMessageID . . . 186
8.117.2.12 pPartNum . . . 186
8.117.2.13 pPriority . . . 186
8.117.2.14 pPrivacy . . . 186
8.117.2.15 pReadAcknowledgementReq . . . 186
8.117.2.16 pReferenceNum . . . 186
8.117.2.17 pRelativeValidity . . . 186
8.117.2.18 pSenderAddr . . . 186
8.117.2.19 pSenderAddrLength . . . 186
8.117.2.20 pTextMsg . . . 186
8.117.2.21 pTextMsgLength . . . 186
8.117.2.22 pTotalNum . . . 186
8.117.2.23 pUserAcknowledgementReq . . . 186
8.118 cdmaMsgEncodingParams Struct Reference . . . 187
8.118.1 Detailed Description . . . 187
8.118.2 Field Documentation . . . 188
8.118.2.1 messageId . . . 188
8.118.2.2 pCallbackAddr . . . 188
8.118.2.3 pDestAddr . . . 188
8.118.2.4 pEncodingAlphabet . . . 188
8.118.2.5 pMessage . . . 188
8.118.2.6 pMessageSize . . . 188
8.118.2.7 pPriority . . . 188
8.118.2.8 pRelValidity . . . 188
8.118.2.9 pTextMsg . . . 188
8.118.2.10 textMsgLength . . . 188
8.119 CDMARSSIThresh Struct Reference . . . 188
8.119.1 Detailed Description . . . 188
8.119.2 Field Documentation . . . 189
8.119.2.1 CDMARSSIThreshListLen . . . 189
8.119.2.2 pCDMARSSIThreshList . . . 189

8.120 cdmaSSInfo Struct Reference . . . 189
8.120.1 Detailed Description . . . 189
8.120.2 Field Documentation . . . 189
8.120.2.1 ecio . . . 189
8.120.2.2 rssi . . . 189
8.121 CDMASSInfo Struct Reference . . . 189
8.121.1 Detailed Description . . . 190
8.121.2 Field Documentation . . . 190
8.121.2.1 ecio . . . 190
8.121.2.2 rssi . . . 190
8.122 CDMASysInfo Struct Reference . . . 190
8.122.1 Detailed Description . . . 190
8.122.2 Field Documentation . . . 193
8.122.2.1 baseId . . . 193
8.122.2.2 baseLat . . . 193
8.122.2.3 baseLong . . . 193
8.122.2.4 bsInfoValid . . . 193
8.122.2.5 bsPRev . . . 193
8.122.2.6 bsPRevValid . . . 193
8.122.2.7 ccsSupported . . . 193
8.122.2.8 ccsSupportedValid . . . 193
8.122.2.9 cdmaSysIdValid . . . 193
8.122.2.10 isSysPrlMatch . . . 193
8.122.2.11 isSysPrlMatchValid . . . 193
8.122.2.12 MCC . . . 193
8.122.2.13 MNC . . . 193
8.122.2.14 networkID . . . 193
8.122.2.15 networkIdValid . . . 193
8.122.2.16 packetZone . . . 193
8.122.2.17 packetZoneValid . . . 193
8.122.2.18 pRevInUse . . . 194
8.122.2.19 pRevInUseValid . . . 194
8.122.2.20 sysInfoCDMA . . . 194
8.122.2.21 systemID . . . 194
8.123 CDMASysInfoExt Struct Reference . . . 194
8.123.1 Detailed Description . . . 194
8.123.2 Field Documentation . . . 194
8.123.2.1 imsi_11_12 . . . 194
8.123.2.2 MCC . . . 194
8.124 CellDb Struct Reference . . . 194

8.124.1 Detailed Description . . . 194
8.124.2 Field Documentation . . . 195
8.124.2.1 mask . . . 195
8.125cellParams Struct Reference . . . 195
8.125.1 Detailed Description . . . 195
8.125.2 Field Documentation . . . 196
8.125.2.1 pci . . . 196
8.125.2.2 rsrp . . . 196
8.125.2.3 rsrq . . . 196
8.125.2.4 rssi . . . 196
8.125.2.5 srxlev . . . 196
8.126changeUIMPIN Struct Reference . . . 196
8.126.1 Detailed Description . . . 196
8.126.2 Field Documentation . . . 197
8.126.2.1 oldPINLen . . . 197
8.126.2.2 oldPINVal . . . 197
8.126.2.3 pinID . . . 197
8.126.2.4 pinLen . . . 197
8.126.2.5 pinVal . . . 197
8.127ChannelRate Struct Reference . . . 197
8.127.1 Detailed Description . . . 197
8.127.2 Field Documentation . . . 197
8.127.2.1 CurrChanRxRate . . . 197
8.127.2.2 CurrChanTxRate . . . 197
8.127.2.3 MaxChanRxRate . . . 197
8.127.2.4 MaxChanTxRate . . . 198
8.128channelRate Struct Reference . . . 198
8.128.1 Detailed Description . . . 198
8.128.2 Field Documentation . . . 198
8.128.2.1 CurrChanRxRate . . . 198
8.128.2.2 CurrChanTxRate . . . 198
8.129ciotAcqOrderPref Struct Reference . . . 198
8.129.1 Detailed Description . . . 198
8.129.2 Field Documentation . . . 199
8.129.2.1 ciotAcqOrderLen . . . 199
8.129.2.2 pCiotAcqOrder . . . 199
8.130CiotAcqOrderPrefTlv Struct Reference . . . 199
8.130.1 Detailed Description . . . 199
8.130.2 Field Documentation . . . 200
8.130.2.1 ciotAcqOrderLen . . . 200

8.130.2.2 pCiotAcqOrder . . . 200
8.130.2.3 TlvPresent . . . 200
8.131 CiotLteOpModePrefTlv Struct Reference . . . 200
8.131.1 Detailed Description . . . 200
8.131.2 Field Documentation . . . 200
8.131.2.1 ciotLteOpModePref . . . 200
8.131.2.2 TlvPresent . . . 200
8.132 CLIPResp Struct Reference . . . 200
8.132.1 Detailed Description . . . 201
8.132.2 Field Documentation . . . 201
8.132.2.1 ActiveStatus . . . 201
8.132.2.2 ProvisionStatus . . . 201
8.133 CLIRResp Struct Reference . . . 201
8.133.1 Detailed Description . . . 201
8.133.2 Field Documentation . . . 202
8.133.2.1 ActiveStatus . . . 202
8.133.2.2 ProvisionStatus . . . 202
8.134 ClkInfo Struct Reference . . . 202
8.134.1 Detailed Description . . . 202
8.134.2 Field Documentation . . . 203
8.134.2.1 mask . . . 203
8.135 CNAPResp Struct Reference . . . 203
8.135.1 Detailed Description . . . 204
8.135.2 Field Documentation . . . 204
8.135.2.1 ActiveStatus . . . 204
8.135.2.2 ProvisionStatus . . . 204
8.136 COLPResp Struct Reference . . . 204
8.136.1 Detailed Description . . . 204
8.136.2 Field Documentation . . . 205
8.136.2.1 ActiveStatus . . . 205
8.136.2.2 ProvisionStatus . . . 205
8.137 COLRResp Struct Reference . . . 205
8.137.1 Detailed Description . . . 205
8.137.2 Field Documentation . . . 205
8.137.2.1 ActiveStatus . . . 205
8.137.2.2 ProvisionStatus . . . 205
8.138 CommInfo Struct Reference . . . 205
8.138.1 Detailed Description . . . 206
8.138.2 Field Documentation . . . 207
8.138.2.1 imsRegState . . . 207

8.138.2.2 modemMode . . . 207
8.138.2.3 psState . . . 207
8.138.2.4 systemMode . . . 207
8.138.2.5 temperature . . . 207
8.139 connectionStatus Struct Reference . . . 207
8.139.1 Detailed Description . . . 207
8.139.2 Field Documentation . . . 208
8.139.2.1 MDMCallDuration . . . 208
8.139.2.2 MDMConnStatus . . . 208
8.140 ConnectionStatus Struct Reference . . . 208
8.140.1 Detailed Description . . . 208
8.140.2 Field Documentation . . . 208
8.140.2.1 MDMCallDuration . . . 208
8.140.2.2 MDMConnStatus . . . 208
8.141 connectNumInfo Struct Reference . . . 208
8.141.1 Detailed Description . . . 209
8.141.2 Field Documentation . . . 210
8.141.2.1 callerID . . . 210
8.141.2.2 callerIDLen . . . 210
8.141.2.3 numPlan . . . 210
8.141.2.4 numPresInd . . . 210
8.141.2.5 numType . . . 210
8.141.2.6 screeningInd . . . 210
8.142 CrashInfo Struct Reference . . . 210
8.142.1 Detailed Description . . . 210
8.142.2 Field Documentation . . . 211
8.142.2.1 crashData . . . 211
8.142.2.2 crashId . . . 211
8.142.2.3 crashStrLen . . . 211
8.142.2.4 gcDumpStrLen . . . 211
8.142.2.5 numCrashes . . . 211
8.142.2.6 pCrashString . . . 211
8.142.2.7 pGCDumpString . . . 211
8.143 CrashInfoParams Struct Reference . . . 211
8.143.1 Detailed Description . . . 211
8.143.2 Field Documentation . . . 212
8.143.2.1 pCrashInfo . . . 212
8.143.2.2 pDevCrashStatus . . . 212
8.144 crashInfoParams Struct Reference . . . 212
8.144.1 Detailed Description . . . 212

8.144.2 Field Documentation . . . 212
8.144.2.1 crashInfo . . . 212
8.144.2.2 crashStatus . . . 212
8.145 crashInformation Struct Reference . . . 212
8.145.1 Detailed Description . . . 213
8.145.2 Field Documentation . . . 213
8.145.2.1 crashData . . . 213
8.145.2.2 crashId . . . 213
8.145.2.3 crashString . . . 213
8.145.2.4 crashStrlen . . . 213
8.145.2.5 gcdumpString . . . 213
8.145.2.6 gcdumpStrlen . . . 213
8.145.2.7 numCrashes . . . 213
8.146 CreateProfileIn Struct Reference . . . 213
8.146.1 Detailed Description . . . 214
8.146.2 Field Documentation . . . 214
8.146.2.1 curProfile . . . 214
8.146.2.2 pProfileID . . . 214
8.146.2.3 pProfileType . . . 214
8.147 CreateProfileOut Struct Reference . . . 214
8.147.1 Detailed Description . . . 214
8.147.2 Field Documentation . . . 215
8.147.2.1 pExtErrorCode . . . 215
8.147.2.2 pProfileIndex . . . 215
8.147.2.3 pProfileType . . . 215
8.148 CsgId Struct Reference . . . 215
8.148.1 Detailed Description . . . 215
8.148.2 Field Documentation . . . 215
8.148.2.1 csgId . . . 215
8.148.2.2 TlvPresent . . . 215
8.149 CSGID Struct Reference . . . 215
8.149.1 Detailed Description . . . 216
8.149.2 Field Documentation . . . 216
8.149.2.1 id . . . 216
8.149.2.2 mcc . . . 216
8.149.2.3 mnc . . . 216
8.149.2.4 mncPcsDigits . . . 216
8.149.2.5 rat . . . 216
8.150 CUGInfo Struct Reference . . . 216
8.150.1 Detailed Description . . . 217

8.150.2 Field Documentation . . . 217
8.150.2.1 CUGIndex . . . 217
8.150.2.2 SuppOA . . . 217
8.150.2.3 SuppPrefCUG . . . 217
8.151 curAMRConfig Struct Reference . . . 217
8.151.1 Detailed Description . . . 217
8.151.2 Field Documentation . . . 218
8.151.2.1 gsmAmrStat . . . 218
8.151.2.2 wcdmaAmrStat . . . 218
8.152 CurrDataSysStat Struct Reference . . . 218
8.152.1 Detailed Description . . . 218
8.152.2 Field Documentation . . . 219
8.152.2.1 pCurrNetworkInfo . . . 219
8.152.2.2 pNetworkInfoLen . . . 219
8.152.2.3 pPrefNetwork . . . 219
8.153 currentCatEvent Union Reference . . . 219
8.153.1 Detailed Description . . . 219
8.153.2 Field Documentation . . . 219
8.153.2.1 CatAlphaIdtfr . . . 219
8.153.2.2 CatEndPS . . . 219
8.153.2.3 CatEventLst . . . 219
8.153.2.4 CatEvIDData . . . 219
8.153.2.5 CatRefresh . . . 219
8.154 CurrentImgList Struct Reference . . . 219
8.154.1 Detailed Description . . . 220
8.154.2 Field Documentation . . . 220
8.154.2.1 carrier . . . 220
8.154.2.2 fwvers . . . 220
8.154.2.3 numEntries . . . 220
8.154.2.4 pCurrImgInfo . . . 220
8.154.2.5 pkgver . . . 220
8.154.2.6 priver . . . 220
8.155 currentPLMN Struct Reference . . . 220
8.155.1 Detailed Description . . . 221
8.155.2 Field Documentation . . . 221
8.155.2.1 MCC . . . 221
8.155.2.2 MNC . . . 221
8.155.2.3 netDescr . . . 221
8.155.2.4 netDescrLength . . . 221
8.156 CurrImageInfo Struct Reference . . . 221

8.156.1 Detailed Description . . . 222
8.156.2 Field Documentation . . . 222
8.156.2.1 buildID . . . 222
8.156.2.2 buildIDLen . . . 222
8.156.2.3 imageType . . . 222
8.156.2.4 uniqueID . . . 222
8.157 CurrNetworkInfo Struct Reference . . . 222
8.157.1 Detailed Description . . . 222
8.157.2 Field Documentation . . . 223
8.157.2.1 NetworkType . . . 224
8.157.2.2 RATMask . . . 224
8.157.2.3 SOMask . . . 224
8.158 currNetworkInfo Struct Reference . . . 224
8.158.1 Detailed Description . . . 224
8.158.2 Field Documentation . . . 224
8.158.2.1 NetworkType . . . 224
8.158.2.2 RATMask . . . 224
8.158.2.3 SOMask . . . 224
8.159 custFeaturesInfo Struct Reference . . . 224
8.159.1 Detailed Description . . . 224
8.159.2 Field Documentation . . . 226
8.159.2.1 GpsEnable . . . 226
8.159.2.2 pDHCPRelayEnabled . . . 226
8.159.2.3 pDisableIMSI . . . 226
8.159.2.4 pGPSLPM . . . 226
8.159.2.5 pGPSSel . . . 226
8.159.2.6 pIPFamSupport . . . 226
8.159.2.7 pIsVoiceEnabled . . . 226
8.159.2.8 pRMAutoConnect . . . 226
8.159.2.9 pSMSSupport . . . 227
8.160 custFeaturesSetting Struct Reference . . . 227
8.160.1 Detailed Description . . . 227
8.160.2 Field Documentation . . . 228
8.160.2.1 pDHCPRelayEnabled . . . 228
8.160.2.2 pGPSEnable . . . 228
8.160.2.3 pGPSLPM . . . 228
8.160.2.4 pGPSSel . . . 228
8.160.2.5 pIsVoiceEnabled . . . 228
8.161 custSettingInfo Struct Reference . . . 228
8.161.1 Detailed Description . . . 228

8.161.2 Field Documentation . . . 229
8.161.2.1 cust_attr . . . 229
8.161.2.2 cust_id . . . 229
8.161.2.3 cust_value . . . 229
8.161.2.4 id_length . . . 229
8.161.2.5 value_length . . . 229
8.162 custSettingList Struct Reference . . . 229
8.162.1 Detailed Description . . . 229
8.162.2 Field Documentation . . . 229
8.162.2.1 custSetting . . . 229
8.162.2.2 list_type . . . 230
8.162.2.3 num_instances . . . 230
8.163 dataBearers Struct Reference . . . 230
8.163.1 Detailed Description . . . 230
8.163.2 Field Documentation . . . 230
8.163.2.1 dataBearerMask . . . 230
8.163.2.2 pCurDataBearerTechnology . . . 230
8.163.2.3 pLastCallDataBearerTechnology . . . 230
8.164 DataBearerTech Struct Reference . . . 230
8.164.1 Detailed Description . . . 230
8.164.2 Field Documentation . . . 232
8.164.2.1 ratValue . . . 232
8.164.2.2 soMask . . . 232
8.164.2.3 techType . . . 232
8.165 DataBearerTechExt Struct Reference . . . 232
8.165.1 Detailed Description . . . 233
8.165.2 Field Documentation . . . 233
8.165.2.1 pBearerTech . . . 233
8.165.2.2 pLastBearerTech . . . 233
8.166 dataBearerTechnology Struct Reference . . . 233
8.166.1 Detailed Description . . . 233
8.166.2 Field Documentation . . . 234
8.166.2.1 currentNetwork . . . 235
8.166.2.2 ratMask . . . 235
8.166.2.3 soMask . . . 235
8.167 dataRate Struct Reference . . . 235
8.167.1 Detailed Description . . . 235
8.167.2 Field Documentation . . . 235
8.167.2.1 dataRateMax . . . 235
8.167.2.2 guaranteedRate . . . 235

8.168 dataSrvCapabilities Struct Reference . . . 235
8.168.1 Detailed Description . . . 235
8.168.2 Field Documentation . . . 236
8.168.2.1 dataCapabilities . . . 236
8.168.2.2 dataCapabilitiesLen . . . 236
8.169 DataStatusDetail Struct Reference . . . 236
8.169.1 Detailed Description . . . 236
8.169.2 Field Documentation . . . 237
8.169.2.1 IPAddress . . . 237
8.169.2.2 LastErrCode . . . 237
8.170 DataULongLongTlv Struct Reference . . . 238
8.170.1 Field Documentation . . . 238
8.170.1.1 TlvPresent . . . 238
8.170.1.2 ullData . . . 238
8.171 DataULongTlv Struct Reference . . . 238
8.171.1 Field Documentation . . . 238
8.171.1.1 TlvPresent . . . 238
8.171.1.2 ulData . . . 238
8.172 DcsUsbPortNames Struct Reference . . . 238
8.172.1 Field Documentation . . . 238
8.172.1.1 AtCmdPort . . . 238
8.172.1.2 DmPort . . . 238
8.172.1.3 NmeaPort . . . 238
8.173 delAssistDataStatus Struct Reference . . . 238
8.173.1 Detailed Description . . . 239
8.173.2 Field Documentation . . . 239
8.173.2.1 results . . . 239
8.173.2.2 status . . . 239
8.174 depersonalizationInformation Struct Reference . . . 239
8.174.1 Detailed Description . . . 239
8.174.2 Field Documentation . . . 240
8.174.2.1 ckLen . . . 240
8.174.2.2 ckVal . . . 240
8.174.2.3 feature . . . 240
8.174.2.4 operation . . . 240
8.175 detailSvcInfo Struct Reference . . . 240
8.175.1 Detailed Description . . . 240
8.175.2 Field Documentation . . . 241
8.175.2.1 hdrHybrid . . . 241
8.175.2.2 hdrSrvStatus . . . 241

8.175.2.3 isSysForbidden . . . 241
8.175.2.4 srvCapability . . . 242
8.175.2.5 srvStatus . . . 242
8.176 DeviceConfigDetail Struct Reference . . . 242
8.176.1 Detailed Description . . . 242
8.176.2 Field Documentation . . . 242
8.176.2.1 Chipset . . . 242
8.176.2.2 HWVersion . . . 243
8.176.2.3 QLIC . . . 243
8.176.2.4 Technology . . . 243
8.177 DHCPOption Struct Reference . . . 243
8.177.1 Detailed Description . . . 243
8.177.2 Field Documentation . . . 243
8.177.2.1 optCode . . . 243
8.177.2.2 optValLen . . . 243
8.177.2.3 pOptVal . . . 243
8.178 DHCPOptionList Struct Reference . . . 243
8.178.1 Detailed Description . . . 243
8.178.2 Field Documentation . . . 244
8.178.2.1 numOpt . . . 244
8.178.2.2 pOptions . . . 244
8.179 diagInfo Struct Reference . . . 244
8.179.1 Detailed Description . . . 244
8.179.2 Field Documentation . . . 244
8.179.2.1 diagInfoLen . . . 244
8.179.2.2 diagnosticInfo . . . 244
8.180 dirNum Struct Reference . . . 244
8.180.1 Detailed Description . . . 245
8.180.2 Field Documentation . . . 245
8.180.2.1 dirNum . . . 245
8.180.2.2 dirNumLen . . . 245
8.181 dms_ActivationStatusTlv Struct Reference . . . 245
8.181.1 Detailed Description . . . 245
8.181.2 Field Documentation . . . 246
8.181.2.1 activationStatus . . . 246
8.181.2.2 TlvPresent . . . 246
8.182 dms_OperatingModeTlv Struct Reference . . . 246
8.182.1 Detailed Description . . . 246
8.182.2 Field Documentation . . . 246
8.182.2.1 operatingMode . . . 246

8.182.2.2 TlvPresent . . . 246
8.183 dms_PSMActiveTimerIndTlv Struct Reference . . . 246
8.183.1 Detailed Description . . . 246
8.183.2 Field Documentation . . . 247
8.183.2.1 ActiveTimerInd . . . 247
8.183.2.2 TlvPresent . . . 247
8.184 dms_PSMActiveTimerTlv Struct Reference . . . 247
8.184.1 Detailed Description . . . 247
8.184.2 Field Documentation . . . 247
8.184.2.1 activeTimer . . . 247
8.184.2.2 TlvPresent . . . 247
8.185 dms_PSMDurationDueToOOSTlv Struct Reference . . . 247
8.185.1 Detailed Description . . . 247
8.185.2 Field Documentation . . . 248
8.185.2.1 durationDueToOOS . . . 248
8.185.2.2 TlvPresent . . . 248
8.186 dms_PSMDurationThresholdTlv Struct Reference . . . 248
8.186.1 Detailed Description . . . 248
8.186.2 Field Documentation . . . 248
8.186.2.1 durationThreshold . . . 248
8.186.2.2 TlvPresent . . . 248
8.187 dms_PSMEarlyWakeupTimeTlv Struct Reference . . . 248
8.187.1 Detailed Description . . . 248
8.187.2 Field Documentation . . . 249
8.187.2.1 earlyWakeupTime . . . 249
8.187.2.2 TlvPresent . . . 249
8.188 dms_PSMEnableStateIndTlv Struct Reference . . . 249
8.188.1 Detailed Description . . . 249
8.188.2 Field Documentation . . . 249
8.188.2.1 EnableStateInd . . . 249
8.188.2.2 TlvPresent . . . 249
8.189 dms_PSMEnableStateTlv Struct Reference . . . 249
8.189.1 Detailed Description . . . 250
8.189.2 Field Documentation . . . 250
8.189.2.1 enableState . . . 250
8.189.2.2 TlvPresent . . . 250
8.190 dms_PSMPeriodicUpdateTimerIndTlv Struct Reference . . . 250
8.190.1 Detailed Description . . . 250
8.190.2 Field Documentation . . . 250
8.190.2.1 PeriodicUpdateTimerInd . . . 250

8.190.2.2 TlvPresent . . . 250
8.191 dms_PSMPeriodicUpdateTimerTlv Struct Reference . . . 250
8.191.1 Detailed Description . . . 251
8.191.2 Field Documentation . . . 251
8.191.2.1 periodicUpdateTimer . . . 251
8.191.2.2 TlvPresent . . . 251
8.192 dms_PSMRandomizationWindowTlv Struct Reference . . . 251
8.192.1 Detailed Description . . . 251
8.192.2 Field Documentation . . . 251
8.192.2.1 randomizationWindow . . . 251
8.192.2.2 TlvPresent . . . 251
8.193 dms_TemperatureTlv Struct Reference . . . 251
8.193.1 Detailed Description . . . 252
8.193.2 Field Documentation . . . 252
8.193.2.1 Temperature . . . 252
8.193.2.2 TempStat . . . 252
8.193.2.3 TlvPresent . . . 252
8.194 dms_UimAutoSwitchActSlotTlv Struct Reference . . . 252
8.194.1 Detailed Description . . . 252
8.194.2 Field Documentation . . . 253
8.194.2.1 TlvPresent . . . 253
8.194.2.2 uimAutoSwitchActSlot . . . 253
8.195 dms_UimStatusTlv Struct Reference . . . 253
8.195.1 Detailed Description . . . 253
8.195.2 Field Documentation . . . 253
8.195.2.1 event . . . 253
8.195.2.2 intf . . . 253
8.195.2.3 TlvPresent . . . 253
8.196 dms_VoltageTlv Struct Reference . . . 253
8.196.1 Detailed Description . . . 254
8.196.2 Field Documentation . . . 254
8.196.2.1 TlvPresent . . . 254
8.196.2.2 Voltage . . . 254
8.196.2.3 VoltStat . . . 254
8.197 dmsCurrentPRLInfo Struct Reference . . . 254
8.197.1 Detailed Description . . . 254
8.197.2 Field Documentation . . . 254
8.197.2.1 pPRLPreference . . . 255
8.197.2.2 pPRLVersion . . . 255
8.198 DMScustSettingInfo Struct Reference . . . 255

8.198.1 Detailed Description . . . 255
8.198.2 Field Documentation . . . 255
8.198.2.1 cust_attr . . . 255
8.198.2.2 cust_id . . . 255
8.198.2.3 cust_value . . . 255
8.198.2.4 id_length . . . 255
8.198.2.5 value_length . . . 255
8.199 DMScustSettingList Struct Reference . . . 256
8.199.1 Detailed Description . . . 256
8.199.2 Field Documentation . . . 256
8.199.2.1 custSetting . . . 256
8.199.2.2 list_type . . . 256
8.199.2.3 num_instances . . . 256
8.200 DMSgetCustomFeatureV2 Struct Reference . . . 256
8.200.1 Detailed Description . . . 256
8.200.2 Field Documentation . . . 257
8.200.2.1 pCustSettingInfo . . . 257
8.200.2.2 pCustSettingList . . . 257
8.200.2.3 pGetCustomInput . . . 257
8.201 DMSgetCustomInput Struct Reference . . . 257
8.201.1 Detailed Description . . . 257
8.201.2 Field Documentation . . . 257
8.201.2.1 cust_id . . . 257
8.201.2.2 list_type . . . 257
8.202 dmsIndicationRegisterReq Struct Reference . . . 257
8.202.1 Detailed Description . . . 257
8.202.2 Field Documentation . . . 258
8.202.2.1 pSwiGetResetInd . . . 258
8.203 dmsPsmCfgParamChange Struct Reference . . . 258
8.203.1 Detailed Description . . . 258
8.203.2 Field Documentation . . . 258
8.203.2.1 pActiveTimer . . . 258
8.203.2.2 pEnableState . . . 258
8.203.2.3 pPeriodicUpdateTimer . . . 259
8.204 dmsSwiGetPCInfo Struct Reference . . . 259
8.204.1 Detailed Description . . . 259
8.204.2 Field Documentation . . . 260
8.204.2.1 opMode . . . 260
8.204.2.2 pLpmFlag . . . 260
8.204.2.3 pPersistentLpm . . . 260

8.204.2.4 pPowerOffMode . . . 260
8.204.2.5 pWdisable . . . 260
8.205 dmsSwiGetResetInfo Struct Reference . . . 260
8.205.1 Detailed Description . . . 260
8.205.2 Field Documentation . . . 261
8.205.2.1 source . . . 261
8.205.2.2 type . . . 261
8.206 dmsSwiGetUIMSelection Struct Reference . . . 261
8.206.1 Detailed Description . . . 261
8.206.2 Field Documentation . . . 261
8.206.2.1 pUimAutoSwitchActSlot . . . 261
8.206.2.2 uimSelect . . . 261
8.207 Domain Struct Reference . . . 262
8.207.1 Detailed Description . . . 262
8.207.2 Field Documentation . . . 262
8.207.2.1 domainLen . . . 262
8.207.2.2 domainName . . . 262
8.208 DomainNameList Struct Reference . . . 262
8.208.1 Detailed Description . . . 262
8.208.2 Field Documentation . . . 262
8.208.2.1 domain . . . 262
8.208.2.2 numInstances . . . 262
8.209 DRCParams Struct Reference . . . 263
8.209.1 Detailed Description . . . 263
8.209.2 Field Documentation . . . 263
8.209.2.1 DRCCover . . . 263
8.209.2.2 DRCValue . . . 263
8.210 DTMFInfo Struct Reference . . . 263
8.210.1 Detailed Description . . . 263
8.210.2 Field Documentation . . . 264
8.210.2.1 callID . . . 264
8.210.2.2 digitBuff . . . 264
8.210.2.3 digitCnt . . . 264
8.210.2.4 DTMFEvent . . . 264
8.211 DTMFLengths Struct Reference . . . 264
8.211.1 Detailed Description . . . 264
8.211.2 Field Documentation . . . 264
8.211.2.1 DTMFInterdigitInterval . . . 265
8.211.2.2 DTMFPulseWidth . . . 265
8.212 DUNCallInfoInd Struct Reference . . . 265

8.212.1 Field Documentation . . . 265
8.212.1.1 CallEndReason . . . 265
8.212.1.2 ChannelRate . . . 265
8.212.1.3 DataBearerTech . . . 265
8.212.1.4 DormancyStatus . . . 265
8.212.1.5 MdmConnStatus . . . 265
8.212.1.6 RXOKBytesCount . . . 265
8.212.1.7 TXOKBytesCount . . . 265
8.213dunchannelRate Struct Reference . . . 265
8.213.1 Detailed Description . . . 265
8.213.2 Field Documentation . . . 266
8.213.2.1 CurrChanRxRate . . . 266
8.213.2.2 CurrChanTxRate . . . 266
8.213.2.3 MaxChanRxRate . . . 266
8.213.2.4 MaxChanTxRate . . . 266
8.214ecioListElement Struct Reference . . . 266
8.214.1 Detailed Description . . . 266
8.214.2 Field Documentation . . . 266
8.214.2.1 ecio . . . 267
8.214.2.2 radioIf . . . 267
8.215ECIOThresh Struct Reference . . . 267
8.215.1 Detailed Description . . . 267
8.215.2 Field Documentation . . . 267
8.215.2.1 ECIOThresListLen . . . 267
8.215.2.2 pECIOThresList . . . 267
8.216ECTNum Struct Reference . . . 267
8.216.1 Detailed Description . . . 267
8.216.2 Field Documentation . . . 268
8.216.2.1 ECTCallState . . . 268
8.216.2.2 number . . . 268
8.216.2.3 presentationInd . . . 268
8.217EdrxCiotLteMode Struct Reference . . . 268
8.217.1 Detailed Description . . . 268
8.217.2 Field Documentation . . . 269
8.217.2.1 lteOpMode . . . 269
8.217.2.2 TlvPresent . . . 269
8.218EdrxCycleLength Struct Reference . . . 269
8.218.1 Detailed Description . . . 269
8.218.2 Field Documentation . . . 269
8.218.2.1 cycleLength . . . 269

8.218.2.2 TlvPresent . . . 269
8.219 EdrxEnableType Struct Reference . . . 269
8.219.1 Detailed Description . . . 269
8.219.2 Field Documentation . . . 270
8.219.2.1 edrxEnabled . . . 270
8.219.2.2 TlvPresent . . . 270
8.220 EdrxPagingTimeWindow Struct Reference . . . 270
8.220.1 Detailed Description . . . 270
8.220.2 Field Documentation . . . 270
8.220.2.1 edrxPtw . . . 270
8.220.2.2 TlvPresent . . . 270
8.221 EdrxRatType Struct Reference . . . 270
8.221.1 Detailed Description . . . 270
8.221.2 Field Documentation . . . 271
8.221.2.1 edrxRatType . . . 271
8.221.2.2 TlvPresent . . . 271
8.222 ehrpdMTUSizeTlv Struct Reference . . . 271
8.222.1 Detailed Description . . . 271
8.222.2 Field Documentation . . . 271
8.222.2.1 ehrpdMTUSize . . . 271
8.222.2.2 TlvPresent . . . 272
8.223 encryptedPIN1 Struct Reference . . . 272
8.223.1 Detailed Description . . . 272
8.223.2 Field Documentation . . . 272
8.223.2.1 pin1Len . . . 272
8.223.2.2 pin1Val . . . 272
8.224 eriDataparams Struct Reference . . . 272
8.224.1 Detailed Description . . . 272
8.224.2 Field Documentation . . . 273
8.224.2.1 eriData . . . 273
8.224.2.2 eriDataLen . . . 273
8.225 ERIFileparams Struct Reference . . . 273
8.225.1 Detailed Description . . . 273
8.225.2 Field Documentation . . . 273
8.225.2.1 pFile . . . 273
8.225.2.2 pFileSize . . . 273
8.226 errorRateListElement Struct Reference . . . 273
8.226.1 Detailed Description . . . 273
8.226.2 Field Documentation . . . 274
8.226.2.1 errorRate . . . 274

8.226.2.2 radioIf . . . 274
8.227 eTWSPLMNInfoTlv Struct Reference . . . 274
8.227.1 Detailed Description . . . 274
8.227.2 Field Documentation . . . 275
8.227.2.1 ETWSPLMNInfo . . . 275
8.227.2.2 TlvPresent . . . 275
8.228 extDispRecInfo Struct Reference . . . 275
8.228.1 Detailed Description . . . 275
8.228.2 Field Documentation . . . 275
8.228.2.1 dispType . . . 275
8.228.2.2 extDispInfo . . . 275
8.228.2.3 extDispInfoLen . . . 275
8.229 FactorySequenceNumber Struct Reference . . . 275
8.229.1 Detailed Description . . . 276
8.229.2 Field Documentation . . . 276
8.229.2.1 FSNumber . . . 276
8.230 fileAttributes Struct Reference . . . 276
8.230.1 Detailed Description . . . 276
8.230.2 Field Documentation . . . 279
8.230.2.1 fileID . . . 279
8.230.2.2 fileSize . . . 279
8.230.2.3 fileType . . . 279
8.230.2.4 rawLen . . . 279
8.230.2.5 rawValue . . . 279
8.230.2.6 recordCount . . . 279
8.230.2.7 recordSize . . . 279
8.230.2.8 secActivate . . . 279
8.230.2.9 secActivateMask . . . 279
8.230.2.10 secDeactivate . . . 279
8.230.2.11 secDeactivateMask . . . 279
8.230.2.12 secIncrease . . . 279
8.230.2.13 secIncreaseMask . . . 279
8.230.2.14 secRead . . . 279
8.230.2.15 secReadMask . . . 279
8.230.2.16 secWrite . . . 279
8.230.2.17 secWriteMask . . . 279
8.231 fileInfo Struct Reference . . . 279
8.231.1 Detailed Description . . . 279
8.231.2 Field Documentation . . . 280
8.231.2.1 fileID . . . 280

8.231.2.2 path . . . 280
8.231.2.3 pathLen . . . 280
8.232 FirmwareUpdatStat Struct Reference . . . 280
8.232.1 Detailed Description . . . 280
8.232.2 Field Documentation . . . 281
8.232.2.1 pImgType . . . 281
8.232.2.2 pLogString . . . 282
8.232.2.3 pLogStringLen . . . 282
8.232.2.4 pRefData . . . 282
8.232.2.5 pRefString . . . 282
8.232.2.6 pRefStringLen . . . 282
8.232.2.7 ResCode . . . 282
8.233 FMSImageElement Struct Reference . . . 282
8.233.1 Detailed Description . . . 282
8.233.2 Field Documentation . . . 282
8.233.2.1 buildId . . . 282
8.233.2.2 buildIdLength . . . 282
8.233.2.3 imageId . . . 282
8.233.2.4 imageType . . . 282
8.234 FMSImageIdElement Struct Reference . . . 282
8.234.1 Detailed Description . . . 283
8.234.2 Field Documentation . . . 283
8.234.2.1 buildID . . . 283
8.234.2.2 buildIDLength . . . 283
8.234.2.3 failureCount . . . 283
8.234.2.4 imageID . . . 283
8.234.2.5 storageIndex . . . 283
8.235 FMSImageIDEntries Struct Reference . . . 283
8.235.1 Detailed Description . . . 284
8.235.2 Field Documentation . . . 284
8.235.2.1 executingImage . . . 284
8.235.2.2 imageIDElement . . . 284
8.235.2.3 imageIDSize . . . 284
8.235.2.4 imageType . . . 284
8.235.2.5 maxImages . . . 284
8.236 FMSImageList Struct Reference . . . 284
8.236.1 Detailed Description . . . 284
8.236.2 Field Documentation . . . 285
8.236.2.1 imageIDEntries . . . 285
8.236.2.2 listSize . . . 285

8.237 FMSPrefImageList Struct Reference . . . 285
8.237.1 Detailed Description . . . 285
8.237.2 Field Documentation . . . 285
8.237.2.1 listEntries . . . 285
8.237.2.2 listSize . . . 285
8.238 ForbiddenNetworks3GPP Struct Reference . . . 285
8.238.1 Detailed Description . . . 285
8.238.2 Field Documentation . . . 286
8.238.2.1 forbiddenNwInstLen . . . 286
8.238.2.2 MCC . . . 286
8.238.2.3 MNC . . . 286
8.238.2.4 TlvPresent . . . 286
8.239 fwinfo_s Struct Reference . . . 286
8.239.1 Detailed Description . . . 286
8.239.2 Field Documentation . . . 287
8.239.2.1 Carrier . . . 287
8.239.2.2 FirmwareID . . . 287
8.239.2.3 GPSCapability . . . 287
8.239.2.4 Region . . . 287
8.239.2.5 Technology . . . 287
8.240 GERANInfo Struct Reference . . . 287
8.240.1 Detailed Description . . . 287
8.240.2 Field Documentation . . . 288
8.240.2.1 arfcn . . . 288
8.240.2.2 bsic . . . 288
8.240.2.3 cellID . . . 288
8.240.2.4 insNmrCellInfo . . . 288
8.240.2.5 lac . . . 288
8.240.2.6 nmrInst . . . 288
8.240.2.7 plmn . . . 289
8.240.2.8 rxLev . . . 289
8.240.2.9 timingAdvance . . . 289
8.241 geranInstInfo Struct Reference . . . 289
8.241.1 Detailed Description . . . 289
8.241.2 Field Documentation . . . 289
8.241.2.1 geranArfcn . . . 289
8.241.2.2 geranBsicBcc . . . 289
8.241.2.3 geranBsicNcc . . . 289
8.241.2.4 geranRssi . . . 289
8.242 getAllCallInformation Struct Reference . . . 289

8.242.1 Detailed Description . . . 290
8.242.2 Field Documentation . . . 290
8.242.2.1 ALS . . . 290
8.242.2.2 CallInfo . . . 290
8.242.2.3 isEmpty . . . 290
8.243 getAllCallRmtPtyName Struct Reference . . . 290
8.243.1 Detailed Description . . . 290
8.243.2 Field Documentation . . . 290
8.243.2.1 callID . . . 290
8.243.2.2 RemotePartyName . . . 291
8.244 getAllCallRmtPtyNum Struct Reference . . . 291
8.244.1 Detailed Description . . . 291
8.244.2 Field Documentation . . . 291
8.244.2.1 callID . . . 291
8.244.2.2 RemotePartyNum . . . 291
8.245 GetAudioPathConfigReq Struct Reference . . . 291
8.245.1 Detailed Description . . . 291
8.245.2 Field Documentation . . . 292
8.245.2.1 Item . . . 292
8.245.2.2 Profile . . . 292
8.246 GetAudioPathConfigResp Struct Reference . . . 292
8.246.1 Detailed Description . . . 292
8.246.2 Field Documentation . . . 293
8.246.2.1 pCodecSTGain . . . 294
8.246.2.2 pDTMFTXGain . . . 294
8.246.2.3 pECMode . . . 294
8.246.2.4 pMICGainSelect . . . 294
8.246.2.5 pNSEnable . . . 294
8.246.2.6 pRXAGCList . . . 294
8.246.2.7 pRXAVCAGCSwitch . . . 294
8.246.2.8 pRXAVCList . . . 294
8.246.2.9 pRXPCMIIRFltr . . . 294
8.246.2.10 pTXAGCList . . . 294
8.246.2.11 pTXAVCSwitch . . . 294
8.246.2.12 pTXGain . . . 294
8.246.2.13 pTXPCMIIRFltr . . . 294
8.247 GetAudioProfileReq Struct Reference . . . 294
8.247.1 Detailed Description . . . 294
8.247.2 Field Documentation . . . 294
8.247.2.1 Generator . . . 294

8.248 GetAudioProfileResp Struct Reference . . . 294
8.248.1 Detailed Description . . . 295
8.248.2 Field Documentation . . . 295
8.248.2.1 EarMute . . . 295
8.248.2.2 MicMute . . . 295
8.248.2.3 Profile . . . 295
8.248.2.4 Volume . . . 295
8.249 GetAudioVolTLBConfigReq Struct Reference . . . 296
8.249.1 Detailed Description . . . 296
8.249.2 Field Documentation . . . 296
8.249.2.1 Generator . . . 296
8.249.2.2 Item . . . 296
8.249.2.3 Profile . . . 296
8.249.2.4 Volume . . . 296
8.250 GetAudioVolTLBConfigResp Struct Reference . . . 296
8.250.1 Detailed Description . . . 297
8.250.2 Field Documentation . . . 297
8.250.2.1 ResCode . . . 297
8.251 getCallFWExtInfo Struct Reference . . . 297
8.251.1 Detailed Description . . . 297
8.251.2 Field Documentation . . . 297
8.251.2.1 CallFWExtInfo . . . 297
8.251.2.2 numInstances . . . 297
8.252 getCallFWInfo Struct Reference . . . 297
8.252.1 Detailed Description . . . 297
8.252.2 Field Documentation . . . 298
8.252.2.1 CallFWInfo . . . 298
8.252.2.2 numInstances . . . 298
8.253 getCustomFeatureV2 Struct Reference . . . 298
8.253.1 Detailed Description . . . 298
8.253.2 Field Documentation . . . 298
8.253.2.1 pCustSettingInfo . . . 298
8.253.2.2 pCustSettingList . . . 298
8.253.2.3 pGetCustomInput . . . 298
8.254 getCustomInput Struct Reference . . . 299
8.254.1 Detailed Description . . . 299
8.254.2 Field Documentation . . . 299
8.254.2.1 cust_id . . . 299
8.254.2.2 list_type . . . 299
8.255 getDUNCallInfoReq Struct Reference . . . 299

8.255.1 Detailed Description . . . 299
8.255.2 Field Documentation . . . 300
8.255.2.1 Mask . . . 300
8.255.2.2 pReportChannelRate . . . 300
8.255.2.3 pReportConnStatus . . . 300
8.255.2.4 pReportDataBearerTech . . . 300
8.255.2.5 pReportDormStatus . . . 300
8.255.2.6 pTransferStatInd . . . 300
8.256 getDUNCallInfoResp Struct Reference . . . 301
8.256.1 Detailed Description . . . 301
8.256.2 Field Documentation . . . 303
8.256.2.1 pCallEndReason . . . 303
8.256.2.2 pChannelRate . . . 303
8.256.2.3 pConnectionStatus . . . 303
8.256.2.4 pDataBearerTech . . . 303
8.256.2.5 pDormancyStatus . . . 303
8.256.2.6 pLastCallDataBearerTech . . . 303
8.256.2.7 pLastCallRXOKBytesCnt . . . 303
8.256.2.8 pLastCallTXOKBytesCnt . . . 303
8.256.2.9 pMdmCallDurationActive . . . 303
8.256.2.10 pRXOKBytesCount . . . 303
8.256.2.11 pTXOKBytesCount . . . 303
8.257 getDyingGaspCfg Struct Reference . . . 303
8.257.1 Detailed Description . . . 304
8.257.2 Field Documentation . . . 304
8.257.2.1 pDestSMSContent . . . 304
8.257.2.2 pDestSMSNum . . . 304
8.258 getDyingGaspStatistics Struct Reference . . . 304
8.258.1 Detailed Description . . . 304
8.258.2 Field Documentation . . . 304
8.258.2.1 pSMSAttemptedFlag . . . 305
8.258.2.2 pTimeStamp . . . 305
8.259 GetErrRateResp Struct Reference . . . 305
8.259.1 Detailed Description . . . 305
8.259.2 Field Documentation . . . 305
8.259.2.1 pCDMAFrameErrRate . . . 305
8.259.2.2 pGSMBER . . . 305
8.259.2.3 pHDRPackErrRate . . . 305
8.259.2.4 pWCDMABER . . . 305
8.260 GetHRPDStatsResp Struct Reference . . . 306

8.260.1 Detailed Description . . . 306
8.260.2 Field Documentation . . . 306
8.260.2.1 pDRCParams . . . 306
8.260.2.2 pPilotSetData . . . 306
8.260.2.3 pUATI . . . 306
8.261 GetIMSSMSConfigParams Struct Reference . . . 306
8.261.1 Detailed Description . . . 306
8.261.2 Field Documentation . . . 307
8.261.2.1 pPhoneCtxtURI . . . 307
8.261.2.2 pPhoneCtxtURILen . . . 307
8.261.2.3 pSettingResp . . . 307
8.261.2.4 pSMSFormat . . . 307
8.261.2.5 pSMSOverIPNwInd . . . 307
8.262 GetIMSUserConfigParams Struct Reference . . . 307
8.262.1 Detailed Description . . . 307
8.262.2 Field Documentation . . . 308
8.262.2.1 pIMSDomain . . . 308
8.262.2.2 pIMSDomainLen . . . 308
8.262.2.3 pSettingResp . . . 308
8.263 GetIMSVoIPConfigResp Struct Reference . . . 308
8.263.1 Detailed Description . . . 308
8.263.2 Field Documentation . . . 310
8.263.2.1 pAmrMode . . . 310
8.263.2.2 pAmrOctetAligned . . . 310
8.263.2.3 pAmrWbEnable . . . 310
8.263.2.4 pAmrWBMode . . . 310
8.263.2.5 pAmrWBOctetAligned . . . 310
8.263.2.6 pMinSessionExpiryTimer . . . 310
8.263.2.7 pRingBackTimer . . . 310
8.263.2.8 pRingingTimer . . . 310
8.263.2.9 pRTPRTCPInactTimer . . . 310
8.263.2.10 pScrAmrEnable . . . 310
8.263.2.11 pScrAmrWbEnable . . . 310
8.263.2.12 pSessionExpiryTimer . . . 310
8.263.2.13 pSettingResp . . . 310
8.264 GetInstIDResp Struct Reference . . . 310
8.264.1 Field Documentation . . . 310
8.264.1.1 pInstanceID . . . 310
8.264.1.2 pIPFamily . . . 311
8.265 GetM2MAudioProfileReq Struct Reference . . . 311

8.265.1 Detailed Description . . . 311
8.265.2 Field Documentation . . . 311
8.265.2.1 pGenerator . . . 311
8.266 GetM2MAudioProfileResp Struct Reference . . . 311
8.266.1 Detailed Description . . . 311
8.266.2 Field Documentation . . . 312
8.266.2.1 CwtMute . . . 312
8.266.2.2 EarMute . . . 312
8.266.2.3 Generator . . . 312
8.266.2.4 MicMute . . . 312
8.266.2.5 Profile . . . 312
8.266.2.6 Volume . . . 312
8.267 GetM2MAudioVolumeReq Struct Reference . . . 312
8.267.1 Detailed Description . . . 312
8.267.2 Field Documentation . . . 313
8.267.2.1 Generator . . . 313
8.267.2.2 Profile . . . 313
8.268 GetM2MAudioVolumeResp Struct Reference . . . 313
8.268.1 Detailed Description . . . 313
8.268.2 Field Documentation . . . 313
8.268.2.1 Level . . . 313
8.269 GetM2MAVMuteReq Struct Reference . . . 313
8.269.1 Detailed Description . . . 313
8.269.2 Field Documentation . . . 313
8.269.2.1 Profile . . . 314
8.270 GetM2MAVMuteResp Struct Reference . . . 314
8.270.1 Detailed Description . . . 314
8.270.2 Field Documentation . . . 314
8.270.2.1 CwtMute . . . 314
8.270.2.2 EarMute . . . 314
8.270.2.3 MicMute . . . 314
8.271 GetM2MSpkrGainReq Struct Reference . . . 314
8.271.1 Detailed Description . . . 314
8.271.2 Field Documentation . . . 315
8.271.2.1 Profile . . . 315
8.272 GetM2MSpkrGainResp Struct Reference . . . 315
8.272.1 Detailed Description . . . 315
8.272.2 Field Documentation . . . 315
8.272.2.1 Value . . . 315
8.273 getMsgWaitingInfo Struct Reference . . . 315

8.273.1 Detailed Description . . . 315
8.273.2 Field Documentation . . . 316
8.273.2.1 msgWaitInfo . . . 316
8.273.2.2 numInstances . . . 316
8.274 GetNetworkTimeResp Struct Reference . . . 316
8.274.1 Detailed Description . . . 316
8.274.2 Field Documentation . . . 316
8.274.2.1 p3GPP2TimeInfo . . . 316
8.274.2.2 p3GPPTimeInfo . . . 316
8.275 GetRegMgrConfigParams Struct Reference . . . 316
8.275.1 Detailed Description . . . 316
8.275.2 Field Documentation . . . 317
8.275.2.1 pIMSTestMode . . . 317
8.275.2.2 pPCSCFPort . . . 317
8.275.2.3 pPriCSCFPortName . . . 317
8.275.2.4 pPriCSCFPortNameLen . . . 317
8.275.2.5 pSettingResp . . . 317
8.276 GetSessionIDResp Struct Reference . . . 317
8.276.1 Field Documentation . . . 317
8.276.1.1 pSessionIDv4 . . . 317
8.276.1.2 pSessionIDv6 . . . 317
8.277 GetSIPConfigResp Struct Reference . . . 317
8.277.1 Detailed Description . . . 318
8.277.2 Field Documentation . . . 318
8.277.2.1 pSettingResp . . . 318
8.277.2.2 pSigCompEnabled . . . 318
8.277.2.3 pSIPLocalPort . . . 318
8.277.2.4 pSubscribeTimer . . . 318
8.277.2.5 pTimerSIPReg . . . 318
8.277.2.6 pTimerT1 . . . 318
8.277.2.7 pTimerT2 . . . 318
8.277.2.8 pTimerTf . . . 318
8.278 GnssData Struct Reference . . . 319
8.278.1 Detailed Description . . . 319
8.278.2 Field Documentation . . . 320
8.278.2.1 mask . . . 320
8.279 gnssSvInfoNotification Struct Reference . . . 320
8.279.1 Detailed Description . . . 321
8.279.2 Field Documentation . . . 321
8.279.2.1 bAltitudeAssumed . . . 321

8.279.2.2 pSatelliteInfo . . . 321
8.279.2.3 results . . . 321
8.280 GPRSQoS Struct Reference . . . 321
8.280.1 Detailed Description . . . 321
8.280.2 Field Documentation . . . 322
8.280.2.1 delayClass . . . 322
8.280.2.2 meanThroughputClass . . . 322
8.280.2.3 peakThroughputClass . . . 322
8.280.2.4 precedenceClass . . . 322
8.280.2.5 reliabilityClass . . . 322
8.281 GPRSRequestedQoS Struct Reference . . . 322
8.281.1 Detailed Description . . . 322
8.281.2 Field Documentation . . . 323
8.281.2.1 delayClass . . . 323
8.281.2.2 meanThroughputClass . . . 323
8.281.2.3 peakThroughputClass . . . 323
8.281.2.4 precedenceClass . . . 323
8.281.2.5 reliabilityClass . . . 323
8.282 GPSStateInfo Struct Reference . . . 323
8.282.1 Detailed Description . . . 324
8.282.2 Field Documentation . . . 326
8.282.2.1 Altitude . . . 326
8.282.2.2 EngineState . . . 326
8.282.2.3 glo_almanac_sv_msk . . . 326
8.282.2.4 glo_ephemeris_sv_msk . . . 326
8.282.2.5 glo_health_sv_msk . . . 326
8.282.2.6 glo_visible_sv_msk . . . 326
8.282.2.7 gps_almanac_sv_msk . . . 326
8.282.2.8 gps_ephemeris_sv_msk . . . 326
8.282.2.9 gps_health_sv_msk . . . 326
8.282.2.10 gps_visible_sv_msk . . . 326
8.282.2.11 HorizontalUncertainty . . . 326
8.282.2.12 iono_valid . . . 326
8.282.2.13 Latitude . . . 326
8.282.2.14 Longitude . . . 326
8.282.2.15 sbas_almanac_sv_msk . . . 326
8.282.2.16 sbas_ephemeris_sv_msk . . . 326
8.282.2.17 sbas_health_sv_msk . . . 327
8.282.2.18 sbas_visible_sv_msk . . . 327
8.282.2.19 Time_uncert_ms . . . 327

8.282.2.20 TimeStmp_gps_week . . . 327
8.282.2.21 TimeStmp_tow_ms . . . 327
8.282.2.22 ValidMask . . . 327
8.282.2.23 VerticalUncertainty . . . 327
8.282.2.24 xtra_start_gps_minutes . . . 327
8.282.2.25 xtra_start_gps_week . . . 327
8.282.2.26 xtra_valid_duration_hours . . . 327
8.283 gpsTime_s Struct Reference . . . 327
8.283.1 Detailed Description . . . 327
8.283.2 Field Documentation . . . 327
8.283.2.1 gpsTimeOfWeekMs . . . 327
8.283.2.2 gpsWeek . . . 327
8.284 gsmCellInfo Struct Reference . . . 327
8.284.1 Detailed Description . . . 328
8.284.2 Field Documentation . . . 328
8.284.2.1 arfcn . . . 328
8.284.2.2 band1900 . . . 328
8.284.2.3 bsicId . . . 328
8.284.2.4 cellIdValid . . . 328
8.284.2.5 rssi . . . 328
8.284.2.6 srxlev . . . 328
8.285 GSMRSSIThresh Struct Reference . . . 329
8.285.1 Detailed Description . . . 329
8.285.2 Field Documentation . . . 329
8.285.2.1 GSMRSSIThreshListLen . . . 329
8.285.2.2 pGSMRSSIThreshList . . . 329
8.286 GSMSrvStatusInfo Struct Reference . . . 329
8.286.1 Detailed Description . . . 329
8.286.2 Field Documentation . . . 330
8.286.2.1 isPrefDataPath . . . 330
8.286.2.2 srvStatus . . . 330
8.286.2.3 trueSrvStatus . . . 330
8.287 GSMSysInfo Struct Reference . . . 330
8.287.1 Detailed Description . . . 330
8.287.2 Field Documentation . . . 332
8.287.2.1 cellId . . . 332
8.287.2.2 cellIdValid . . . 332
8.287.2.3 dtmSupp . . . 332
8.287.2.4 dtmSuppValid . . . 332
8.287.2.5 egprsSupp . . . 332

8.287.2.6 egprsSuppValid . . . 332
8.287.2.7 lac . . . 333
8.287.2.8 lacValid . . . 333
8.287.2.9 MCC . . . 333
8.287.2.10 MNC . . . 333
8.287.2.11 networkIdValid . . . 333
8.287.2.12 regRejectInfoValid . . . 333
8.287.2.13 rejCause . . . 333
8.287.2.14 rejectSrvDomain . . . 333
8.287.2.15 sysInfoGSM . . . 333
8.288 gyroAcceptReady_s Struct Reference . . . 333
8.288.1 Detailed Description . . . 333
8.288.2 Field Documentation . . . 333
8.288.2.1 batchPerSec . . . 333
8.288.2.2 injectEnable . . . 334
8.288.2.3 samplesPerBatch . . . 334
8.289 gyroTempAcceptReady_s Struct Reference . . . 334
8.289.1 Detailed Description . . . 334
8.289.2 Field Documentation . . . 334
8.289.2.1 batchPerSec . . . 334
8.289.2.2 injectEnable . . . 334
8.289.2.3 samplesPerBatch . . . 334
8.290 HDRECIOThresh Struct Reference . . . 334
8.290.1 Detailed Description . . . 335
8.290.2 Field Documentation . . . 335
8.290.2.1 HDRECIOThreshListLen . . . 335
8.290.2.2 pHDRECIOThreshList . . . 335
8.291 HDRIOThresh Struct Reference . . . 335
8.291.1 Detailed Description . . . 335
8.291.2 Field Documentation . . . 335
8.291.2.1 HDRIOThreshListLen . . . 335
8.291.2.2 pHDRIOThreshList . . . 335
8.292 HDRPersonalityInd Struct Reference . . . 335
8.292.1 Field Documentation . . . 336
8.292.1.1 pCurrentPersonality . . . 336
8.292.1.2 pPersonalityListLength . . . 336
8.292.1.3 pProtocolSubtypeElement . . . 336
8.293 HDRPersonalityResp Struct Reference . . . 336
8.293.1 Detailed Description . . . 336
8.293.2 Field Documentation . . . 336

8.293.2.1 pCurrentPersonality . . . 336
8.293.2.2 pPersonalityListLength . . . 336
8.293.2.3 pProtocolSubtypeElement . . . 336
8.294 HDRProtSubtypResp Struct Reference . . . 336
8.294.1 Detailed Description . . . 337
8.294.2 Field Documentation . . . 337
8.294.2.1 pAppSubType . . . 337
8.294.2.2 pCurrentPrsnlty . . . 337
8.294.2.3 pPersonalityListLength . . . 337
8.294.2.4 pProtoSubTypElmnt . . . 337
8.295 HDRRSSIThresh Struct Reference . . . 337
8.295.1 Detailed Description . . . 337
8.295.2 Field Documentation . . . 338
8.295.2.1 HDRRSSIThreshListLen . . . 338
8.295.2.2 pHDRRSSIThreshList . . . 338
8.296 HDRSINRThresh Struct Reference . . . 338
8.296.1 Detailed Description . . . 338
8.296.2 Field Documentation . . . 338
8.296.2.1 HDRSINRThresListLen . . . 338
8.296.2.2 pHDRSINRThresList . . . 338
8.297 HDRSINRThreshold Struct Reference . . . 338
8.297.1 Detailed Description . . . 339
8.297.2 Field Documentation . . . 339
8.297.2.1 HDRSINRThreshListLen . . . 339
8.297.2.2 pHDRSINRThreshList . . . 339
8.298 hdrSSInfo Struct Reference . . . 339
8.298.1 Detailed Description . . . 339
8.298.2 Field Documentation . . . 340
8.298.2.1 ecio . . . 340
8.298.2.2 io . . . 340
8.298.2.3 rssi . . . 340
8.298.2.4 sinr . . . 340
8.299 HDRSSInfo Struct Reference . . . 340
8.299.1 Detailed Description . . . 340
8.299.2 Field Documentation . . . 341
8.299.2.1 ecio . . . 341
8.299.2.2 io . . . 341
8.299.2.3 rssi . . . 341
8.299.2.4 sinr . . . 341
8.300 HDRSysInfo Struct Reference . . . 341

8.300.1 Detailed Description . . . 342
8.300.2 Field Documentation . . . 343
8.300.2.1 hdrActiveProt . . . 343
8.300.2.2 hdrActiveProtValid . . . 343
8.300.2.3 hdrPersonality . . . 343
8.300.2.4 hdrPersonalityValid . . . 343
8.300.2.5 is856SysId . . . 343
8.300.2.6 is856SysIdValid . . . 343
8.300.2.7 isSysPrlMatch . . . 343
8.300.2.8 isSysPrlMatchValid . . . 343
8.300.2.9 sysInfoHDR . . . 343
8.301 homeSIDNID Struct Reference . . . 343
8.301.1 Detailed Description . . . 343
8.301.2 Field Documentation . . . 344
8.301.2.1 numInstances . . . 344
8.301.2.2 SidNid . . . 344
8.302 hotSwapStatus Struct Reference . . . 344
8.302.1 Detailed Description . . . 344
8.302.2 Field Documentation . . . 344
8.302.2.1 hotSwap . . . 344
8.302.2.2 hotSwapLength . . . 344
8.303 hrpdMTUSizeTlv Struct Reference . . . 344
8.303.1 Detailed Description . . . 344
8.303.2 Field Documentation . . . 345
8.303.2.1 hrpdMTUSize . . . 345
8.303.2.2 TlvPresent . . . 345
8.304 image_info_t Struct Reference . . . 345
8.304.1 Detailed Description . . . 345
8.304.2 Field Documentation . . . 345
8.304.2.1 buildID . . . 345
8.304.2.2 buildIDLen . . . 345
8.304.2.3 imageType . . . 345
8.304.2.4 uniqueID . . . 346
8.305 ImageElement Struct Reference . . . 346
8.305.1 Detailed Description . . . 346
8.305.2 Field Documentation . . . 346
8.305.2.1 buildId . . . 346
8.305.2.2 buildIdLength . . . 346
8.305.2.3 imageId . . . 346
8.305.2.4 imageType . . . 346

8.306 ImageIdElement Struct Reference . . . 346
8.306.1 Detailed Description . . . 347
8.306.2 Field Documentation . . . 347
8.306.2.1 buildID . . . 347
8.306.2.2 buildIDLength . . . 347
8.306.2.3 failureCount . . . 347
8.306.2.4 imageID . . . 347
8.306.2.5 storageIndex . . . 347
8.307 ImageIDEntries Struct Reference . . . 347
8.307.1 Detailed Description . . . 347
8.307.2 Field Documentation . . . 348
8.307.2.1 executingImage . . . 348
8.307.2.2 imageIDElement . . . 348
8.307.2.3 imageIDSize . . . 348
8.307.2.4 imageType . . . 348
8.307.2.5 maxImages . . . 348
8.308 ImageList Struct Reference . . . 348
8.308.1 Detailed Description . . . 348
8.308.2 Field Documentation . . . 348
8.308.2.1 imageIDEntries . . . 349
8.308.2.2 listSize . . . 349
8.309 IMSAIndRegisterInfo Struct Reference . . . 349
8.309.1 Detailed Description . . . 349
8.309.2 Field Documentation . . . 349
8.309.2.1 pPdpStatusConfig . . . 349
8.309.2.2 pRatHandoverStatusConfig . . . 350
8.309.2.3 pRegStatusConfig . . . 350
8.309.2.4 pServiceStatusConfig . . . 350
8.310 imsaPdpStatusInfo Struct Reference . . . 350
8.310.1 Detailed Description . . . 350
8.310.2 Field Documentation . . . 350
8.310.2.1 connetionState . . . 350
8.310.2.2 pFailErrorCode . . . 350
8.311 imsaRatStatusInfo Struct Reference . . . 350
8.311.1 Detailed Description . . . 350
8.311.2 Field Documentation . . . 351
8.311.2.1 pErrorCodeStr . . . 351
8.311.2.2 pRATStatus . . . 351
8.311.2.3 pSrcRAT . . . 351
8.311.2.4 pTgtRAT . . . 351

8.312 IMSARegistrationStatus Struct Reference . . . 351
8.312.1 Detailed Description . . . 351
8.312.2 Field Documentation . . . 352
8.312.2.1 pImsRegErrCode . . . 352
8.312.2.2 pImsRegStatus . . . 352
8.312.2.3 pNewImsRegStatus . . . 352
8.313 imsaRegStatusInfo Struct Reference . . . 352
8.313.1 Detailed Description . . . 352
8.313.2 Field Documentation . . . 352
8.313.2.1 pbIMSRegistered . . . 352
8.313.2.2 pImsRegStatus . . . 352
8.313.2.3 pRegStatusErrorCode . . . 352
8.314 IMSAServiceStatus Struct Reference . . . 352
8.314.1 Detailed Description . . . 353
8.314.2 Field Documentation . . . 354
8.314.2.1 pSmsServiceRat . . . 354
8.314.2.2 pSmsServiceStatus . . . 354
8.314.2.3 pUtServiceRat . . . 354
8.314.2.4 pUtServiceStatus . . . 354
8.314.2.5 pVoipServiceRat . . . 354
8.314.2.6 pVoipServiceStatus . . . 354
8.314.2.7 pVsServiceRat . . . 354
8.314.2.8 pVsServiceStatus . . . 354
8.314.2.9 pVtServiceRat . . . 355
8.314.2.10 pVtServiceStatus . . . 355
8.315 IMSASupportedFieldsResp Struct Reference . . . 355
8.315.1 Detailed Description . . . 355
8.315.2 Field Documentation . . . 355
8.315.2.1 pIndFieldsList . . . 355
8.315.2.2 pReqFieldsList . . . 355
8.315.2.3 pRespFieldsList . . . 355
8.316 IMSASupportedMsgInfo Struct Reference . . . 355
8.316.1 Detailed Description . . . 355
8.316.2 Field Documentation . . . 356
8.316.2.1 pSupportedMsgList . . . 356
8.317 imsaSvcStatusInfo Struct Reference . . . 356
8.317.1 Detailed Description . . . 356
8.317.2 Field Documentation . . . 356
8.317.2.1 pSMSSvcRAT . . . 356
8.317.2.2 pSMSSvcStatus . . . 356

8.317.2.3 pUTSvcRAT . . . 356
8.317.2.4 pUTSvcStatus . . . 356
8.317.2.5 pVOIPSvcRAT . . . 357
8.317.2.6 pVOIPSvcStatus . . . 357
8.317.2.7 pVTSvcRAT . . . 357
8.317.2.8 pVTSvcStatus . . . 357
8.318 imsCfgIndRegisterInfo Struct Reference . . . 357
8.318.1 Detailed Description . . . 357
8.318.2 Field Documentation . . . 358
8.318.2.1 pRegMgrConfigEvents . . . 358
8.318.2.2 pSIPConfigEvents . . . 358
8.318.2.3 pSMSConfigEvents . . . 358
8.318.2.4 pUserConfigEvents . . . 358
8.318.2.5 pVoIPConfigEvents . . . 358
8.319 imsRegMgrConfigInfo Struct Reference . . . 358
8.319.1 Detailed Description . . . 358
8.319.2 Field Documentation . . . 359
8.319.2.1 pCSCFPortName . . . 359
8.319.2.2 pIMSTestMode . . . 359
8.319.2.3 pPriCSCFPort . . . 359
8.320 imsSIPConfigInfo Struct Reference . . . 359
8.320.1 Detailed Description . . . 359
8.320.2 Field Documentation . . . 360
8.320.2.1 pSigCompEnabled . . . 360
8.320.2.2 pSIPLocalPort . . . 360
8.320.2.3 pSubscribeTimer . . . 360
8.320.2.4 pTimerSIPReg . . . 360
8.320.2.5 pTimerT1 . . . 360
8.320.2.6 pTimerT2 . . . 360
8.320.2.7 pTimerTf . . . 360
8.321 imsSMSConfigInfo Struct Reference . . . 360
8.321.1 Detailed Description . . . 360
8.321.2 Field Documentation . . . 360
8.321.2.1 pPhoneCtxtURI . . . 360
8.321.2.2 pSMSFormat . . . 360
8.321.2.3 pSMSOverIPNwInd . . . 360
8.322 imsUserConfigInfo Struct Reference . . . 361
8.322.1 Detailed Description . . . 361
8.322.2 Field Documentation . . . 361
8.322.2.1 pIMSDomain . . . 361

8.323 imsVoIPConfigInfo Struct Reference . . . 361
8.323.1 Detailed Description . . . 361
8.323.2 Field Documentation . . . 363
8.323.2.1 pAmrMode . . . 363
8.323.2.2 pAmrOctetAligned . . . 363
8.323.2.3 pAmrWbEnable . . . 363
8.323.2.4 pAmrWBMode . . . 363
8.323.2.5 pAmrWBOctetAligned . . . 363
8.323.2.6 pMinSessionExpiryTimer . . . 363
8.323.2.7 pRingBackTimer . . . 363
8.323.2.8 pRingingTimer . . . 363
8.323.2.9 pRTPRTCPInactTimer . . . 363
8.323.2.10 pScrAmrEnable . . . 363
8.323.2.11 pScrAmrWbEnable . . . 363
8.323.2.12 pSessionExpiryTimer . . . 363
8.324 IndFieldsList Struct Reference . . . 363
8.324.1 Detailed Description . . . 364
8.324.2 Field Documentation . . . 364
8.324.2.1 indicationFields . . . 364
8.324.2.2 indicationFieldsLen . . . 364
8.325 infoInterFreq Struct Reference . . . 364
8.325.1 Detailed Description . . . 364
8.325.2 Field Documentation . . . 365
8.325.2.1 cell_resel_priority . . . 365
8.325.2.2 cellInterFreqParams . . . 365
8.325.2.3 cells_len . . . 365
8.325.2.4 earfcn . . . 365
8.325.2.5 threshXHigh . . . 365
8.325.2.6 threshXLow . . . 365
8.326 intfaceCfgTlv Struct Reference . . . 365
8.326.1 Detailed Description . . . 365
8.326.2 Field Documentation . . . 366
8.326.2.1 CfgValue . . . 366
8.326.2.2 CurrentCfgType . . . 366
8.326.2.3 TlvPresent . . . 366
8.327 IOThresh Struct Reference . . . 366
8.327.1 Detailed Description . . . 366
8.327.2 Field Documentation . . . 367
8.327.2.1 IOThresListLen . . . 367
8.327.2.2 pIOThresList . . . 367

8.328 IPv4Addr Struct Reference . . . 367
8.328.1 Detailed Description . . . 367
8.328.2 Field Documentation . . . 367
8.328.2.1 addr . . . 367
8.328.2.2 subnetMask . . . 367
8.329 IPv4Config Struct Reference . . . 367
8.329.1 Detailed Description . . . 368
8.329.2 Field Documentation . . . 368
8.329.2.1 IPv4Addr . . . 368
8.329.2.2 IPv4Port . . . 368
8.330 IPv4Info Struct Reference . . . 368
8.330.1 Detailed Description . . . 368
8.330.2 Field Documentation . . . 368
8.330.2.1 address . . . 368
8.330.2.2 port . . . 368
8.330.2.3 TlvPresent . . . 368
8.331 IPv6Addr Struct Reference . . . 368
8.331.1 Detailed Description . . . 369
8.331.2 Field Documentation . . . 369
8.331.2.1 addr . . . 369
8.331.2.2 prefixLen . . . 369
8.332 ipv6AddressInfo Struct Reference . . . 369
8.332.1 Detailed Description . . . 369
8.332.2 Field Documentation . . . 369
8.332.2.1 IPAddressV6 . . . 369
8.332.2.2 IPV6PrefixLen . . . 369
8.333 IPV6AddressInfo Struct Reference . . . 369
8.333.1 Detailed Description . . . 370
8.333.2 Field Documentation . . . 370
8.333.2.1 IPAddressV6 . . . 370
8.333.2.2 IPV6PrefixLen . . . 370
8.334 IPv6Config Struct Reference . . . 370
8.334.1 Detailed Description . . . 370
8.334.2 Field Documentation . . . 370
8.334.2.1 IPv6Addr . . . 370
8.334.2.2 IPv6Port . . . 370
8.335 IPV6GWAddressInfo Struct Reference . . . 370
8.335.1 Detailed Description . . . 371
8.335.2 Field Documentation . . . 371
8.335.2.1 gwAddressV6 . . . 371

8.335.2.2 gwV6PrefixLen . . . 371
8.336 IPv6Info Struct Reference . . . 371
8.336.1 Detailed Description . . . 371
8.336.2 Field Documentation . . . 371
8.336.2.1 address . . . 372
8.336.2.2 port . . . 372
8.336.2.3 TlvPresent . . . 372
8.337 IPv6TrafCls Struct Reference . . . 372
8.337.1 Detailed Description . . . 372
8.337.2 Field Documentation . . . 372
8.337.2.1 mask . . . 372
8.337.2.2 val . . . 372
8.338 LibPackGPRSRequestedQoS Struct Reference . . . 372
8.338.1 Detailed Description . . . 372
8.338.2 Field Documentation . . . 373
8.338.2.1 delayClass . . . 373
8.338.2.2 meanThroughputClass . . . 373
8.338.2.3 peakThroughputClass . . . 373
8.338.2.4 precedenceClass . . . 373
8.338.2.5 reliabilityClass . . . 373
8.339 LibpackProfile3GPP Struct Reference . . . 373
8.339.1 Detailed Description . . . 374
8.339.2 Field Documentation . . . 379
8.339.2.1 pAddrAllocPref . . . 379
8.339.2.2 pAPNClass . . . 379
8.339.2.3 pAPNDisabledFlag . . . 379
8.339.2.4 pAPNName . . . 379
8.339.2.5 pAPNnameSize . . . 379
8.339.2.6 pAuthenticationPref . . . 379
8.339.2.7 pGPRSMinimumQoS . . . 379
8.339.2.8 pGPRSRequestedQos . . . 379
8.339.2.9 pImCnFlag . . . 379
8.339.2.10 pIPv4AddrPref . . . 379
8.339.2.11 pIPv6AddPref . . . 379
8.339.2.12 pPassword . . . 379
8.339.2.13 pPasswordSize . . . 379
8.339.2.14 pPcscfAddrUsingDhcp . . . 379
8.339.2.15 pPcscfAddrUsingPCO . . . 379
8.339.2.16 pPDNInactivTimeout . . . 379
8.339.2.17 pPdpAccessConFlag . . . 379

8.339.2.18 pPdpContext . . . 379
8.339.2.19 pPdpDataCompType . . . 379
8.339.2.20 pPdpHdrCompType . . . 379
8.339.2.21 pPDPtype . . . 379
8.339.2.22 pPriDNSIPv4AddPref . . . 379
8.339.2.23 pPriDNSIPv6addpref . . . 379
8.339.2.24 pPrimaryID . . . 379
8.339.2.25 pProfilename . . . 379
8.339.2.26 pProfilenameSize . . . 379
8.339.2.27 pQosClassID . . . 379
8.339.2.28 pSecDNSIPv4AddPref . . . 380
8.339.2.29 pSecDNSIPv6addpref . . . 380
8.339.2.30 pSecondaryFlag . . . 380
8.339.2.31 pSupportEmergencyCalls . . . 380
8.339.2.32 pTFTID1Params . . . 380
8.339.2.33 pTFTID2Params . . . 380
8.339.2.34 pUMTSMinQoS . . . 380
8.339.2.35 pUMTSMinQosSigInd . . . 380
8.339.2.36 pUMTSReqQoS . . . 380
8.339.2.37 pUMTSReqQoSSigInd . . . 380
8.339.2.38 pUsername . . . 380
8.339.2.39 pUsernameSize . . . 380
8.340 LibpackProfile3GPP2 Struct Reference . . . 380
8.340.1 Detailed Description . . . 381
8.340.2 Field Documentation . . . 385
8.340.2.1 pAllowLinger . . . 385
8.340.2.2 pAPNClass3GPP2 . . . 385
8.340.2.3 pAPNEnabled3GPP2 . . . 385
8.340.2.4 pApnString . . . 385
8.340.2.5 pApnStringSize . . . 385
8.340.2.6 pAppPriority . . . 385
8.340.2.7 pAppType . . . 385
8.340.2.8 pAuthPassword . . . 385
8.340.2.9 pAuthPasswordSize . . . 385
8.340.2.10 pAuthProtocol . . . 385
8.340.2.11 pAuthRetryCount . . . 385
8.340.2.12 pAuthTimeout . . . 385
8.340.2.13 pDataMode . . . 385
8.340.2.14 pDataRate . . . 385
8.340.2.15 pIpcpAckTimeout . . . 385

8.340.2.16 pIpcpCreqRetryCount . . . 385
8.340.2.17 pIsPcscfAddressNedded . . . 385
8.340.2.18 pLcpAckTimeout . . . 385
8.340.2.19 pLcpCreqRetryCount . . . 385
8.340.2.20 pNegoDnsSrvrPref . . . 385
8.340.2.21 pPDNInactivTimeout3GPP2 . . . 385
8.340.2.22 pPdnType . . . 385
8.340.2.23 pPppSessCloseTimer1x . . . 386
8.340.2.24 pPppSessCloseTimerDO . . . 386
8.340.2.25 pPrimaryV4DnsAddress . . . 386
8.340.2.26 pPriV6DnsAddress . . . 386
8.340.2.27 pRATType . . . 386
8.340.2.28 pSecondaryV4DnsAddress . . . 386
8.340.2.29 pSecV6DnsAddress . . . 386
8.340.2.30 pUserId . . . 386
8.340.2.31 pUserIdSize . . . 386
8.341 LibPackprofile_3GPP Struct Reference . . . 386
8.341.1 Detailed Description . . . 387
8.341.2 Field Documentation . . . 390
8.341.2.1 pAddrAllocPref . . . 390
8.341.2.2 pAPNClass . . . 390
8.341.2.3 pAPNDisabledFlag . . . 390
8.341.2.4 pAPNName . . . 391
8.341.2.5 pAPNnameSize . . . 391
8.341.2.6 pAuthenticationPref . . . 391
8.341.2.7 pGPRSMinimumQoS . . . 391
8.341.2.8 pGPRSRequestedQos . . . 391
8.341.2.9 pImCnFlag . . . 391
8.341.2.10 pIPv4AddrPref . . . 391
8.341.2.11 pIPv6AddPref . . . 391
8.341.2.12 pPassword . . . 391
8.341.2.13 pPasswordSize . . . 391
8.341.2.14 pPcscfAddrUsingDhcp . . . 391
8.341.2.15 pPcscfAddrUsingPCO . . . 391
8.341.2.16 pPDNInactivTimeout . . . 391
8.341.2.17 pPdpAccessConFlag . . . 391
8.341.2.18 pPdpContext . . . 391
8.341.2.19 pPdpDataCompType . . . 391
8.341.2.20 pPdpHdrCompType . . . 391
8.341.2.21 pPDPtype . . . 391

8.341.2.22 pPriDNSIPv4AddPref . . . 391
8.341.2.23 pPriDNSIPv6addpref . . . 391
8.341.2.24 pPrimaryID . . . 391
8.341.2.25 pProfilename . . . 391
8.341.2.26 pProfilenameSize . . . 391
8.341.2.27 pQosClassID . . . 391
8.341.2.28 pSecDNSIPv4AddPref . . . 391
8.341.2.29 pSecDNSIPv6addpref . . . 391
8.341.2.30 pSecondaryFlag . . . 391
8.341.2.31 pSupportEmergencyCalls . . . 391
8.341.2.32 pTFTID1Params . . . 392
8.341.2.33 pTFTID2Params . . . 392
8.341.2.34 pUMTSMinQoS . . . 392
8.341.2.35 pUMTSMinQosSigInd . . . 392
8.341.2.36 pUMTSReqQoS . . . 392
8.341.2.37 pUMTSReqQoSSigInd . . . 392
8.341.2.38 pUsername . . . 392
8.341.2.39 pUsernameSize . . . 392
8.342 LibPackprofile_3GPP2 Struct Reference . . . 392
8.342.1 Detailed Description . . . 393
8.342.2 Field Documentation . . . 396
8.342.2.1 pAllowLinger . . . 396
8.342.2.2 pAPNClass3GPP2 . . . 396
8.342.2.3 pAPNEnabled3GPP2 . . . 396
8.342.2.4 pApnString . . . 396
8.342.2.5 pApnStringSize . . . 396
8.342.2.6 pAppPriority . . . 396
8.342.2.7 pAppType . . . 396
8.342.2.8 pAuthPassword . . . 396
8.342.2.9 pAuthPassword_tSize . . . 396
8.342.2.10 pAuthProtocol . . . 396
8.342.2.11 pAuthRetryCount . . . 396
8.342.2.12 pAuthTimeout . . . 396
8.342.2.13 pDataMode . . . 396
8.342.2.14 pDataRate . . . 396
8.342.2.15 pIpcpAckTimeout . . . 397
8.342.2.16 pIpcpCreqRetryCount . . . 397
8.342.2.17 pIsPcscfAddressNedded . . . 397
8.342.2.18 pLcpAckTimeout . . . 397
8.342.2.19 pLcpCreqRetryCount . . . 397

8.342.2.20 pNegoDnsSrvrPref . . . 397
8.342.2.21 pPDNInactivTimeout3GPP2 . . . 397
8.342.2.22 pPdnType . . . 397
8.342.2.23 pPppSessCloseTimer1x . . . 397
8.342.2.24 pPppSessCloseTimerDO . . . 397
8.342.2.25 pPrimaryV4DnsAddress . . . 397
8.342.2.26 pPriV6DnsAddress . . . 397
8.342.2.27 pRATType . . . 397
8.342.2.28 pSecondaryV4DnsAddress . . . 397
8.342.2.29 pSecV6DnsAddress . . . 397
8.342.2.30 pUserId . . . 397
8.342.2.31 pUserIdSize . . . 397
8.343 LibPackQosClassID Struct Reference . . . 397
8.343.1 Detailed Description . . . 397
8.343.2 Field Documentation . . . 398
8.343.2.1 gDlBitRate . . . 398
8.343.2.2 gUlBitRate . . . 398
8.343.2.3 maxDlBitRate . . . 398
8.343.2.4 maxUlBitRate . . . 398
8.343.2.5 QCI . . . 398
8.344 LibPackTFTIDParams Struct Reference . . . 398
8.344.1 Detailed Description . . . 398
8.344.2 Field Documentation . . . 399
8.344.2.1 destPortRangeEnd . . . 399
8.344.2.2 destPortRangeStart . . . 399
8.344.2.3 eValid . . . 400
8.344.2.4 filterId . . . 400
8.344.2.5 flowLabel . . . 400
8.344.2.6 IPSECSPI . . . 400
8.344.2.7 ipVersion . . . 400
8.344.2.8 nextHeader . . . 400
8.344.2.9 pSourceIP . . . 400
8.344.2.10 sourceIPMask . . . 400
8.344.2.11 srcPortRangeEnd . . . 400
8.344.2.12 srcPortRangeStart . . . 400
8.344.2.13 tosMask . . . 400
8.345 LibPackUMTSQoS Struct Reference . . . 400
8.345.1 Detailed Description . . . 400
8.345.2 Field Documentation . . . 402
8.345.2.1 deliveryErrSDU . . . 402

8.345.2.2 grntDownlinkBitrate . . . 402
8.345.2.3 grntUplinkBitrate . . . 402
8.345.2.4 maxDownlinkBitrate . . . 402
8.345.2.5 maxSDUSize . . . 402
8.345.2.6 maxUplinkBitrate . . . 402
8.345.2.7 qosDeliveryOrder . . . 402
8.345.2.8 resBerRatio . . . 402
8.345.2.9 sduErrorRatio . . . 402
8.345.2.10 trafficClass . . . 402
8.345.2.11 trafficPriority . . . 402
8.345.2.12 transferDelay . . . 402
8.346 LibPackUMTSReqQoSSigInd Struct Reference . . . 403
8.346.1 Detailed Description . . . 403
8.346.2 Field Documentation . . . 403
8.346.2.1 SigInd . . . 403
8.346.2.2 UMTSReqQoS . . . 403
8.347 lineCtrlInfo Struct Reference . . . 403
8.347.1 Detailed Description . . . 403
8.347.2 Field Documentation . . . 404
8.347.2.1 polarityIncluded . . . 404
8.347.2.2 pwrDenialTime . . . 404
8.347.2.3 revPolarity . . . 404
8.347.2.4 toggleMode . . . 404
8.348 loc_accelAcceptReady Struct Reference . . . 404
8.348.1 Detailed Description . . . 404
8.348.2 Field Documentation . . . 404
8.348.2.1 batchPerSec . . . 404
8.348.2.2 injectEnable . . . 405
8.348.2.3 samplesPerBatch . . . 405
8.349 loc_accelTempAcceptReady Struct Reference . . . 405
8.349.1 Detailed Description . . . 405
8.349.2 Field Documentation . . . 405
8.349.2.1 batchPerSec . . . 405
8.349.2.2 injectEnable . . . 405
8.349.2.3 samplesPerBatch . . . 405
8.350 loc_BdsSV Struct Reference . . . 405
8.350.1 Detailed Description . . . 406
8.350.2 Field Documentation . . . 406
8.350.2.1 id . . . 406
8.350.2.2 mask . . . 406

8.351 loc_BdsSVInfo Struct Reference . . . 406
8.351.1 Detailed Description . . . 406
8.351.2 Field Documentation . . . 406
8.351.2.1 len . . . 406
8.351.2.2 pSV . . . 406
8.352 loc_CellDb Struct Reference . . . 406
8.352.1 Detailed Description . . . 407
8.352.2 Field Documentation . . . 407
8.352.2.1 mask . . . 407
8.353 loc_ClkInfo Struct Reference . . . 407
8.353.1 Detailed Description . . . 407
8.353.2 Field Documentation . . . 408
8.353.2.1 mask . . . 408
8.354 loc_GnssData Struct Reference . . . 408
8.354.1 Detailed Description . . . 409
8.354.2 Field Documentation . . . 409
8.354.2.1 mask . . . 410
8.355 loc_gpsTime Struct Reference . . . 410
8.355.1 Detailed Description . . . 410
8.355.2 Field Documentation . . . 410
8.355.2.1 gpsTimeOfWeekMs . . . 410
8.355.2.2 gpsWeek . . . 410
8.356 loc_gyroAcceptReady Struct Reference . . . 410
8.356.1 Detailed Description . . . 410
8.356.2 Field Documentation . . . 411
8.356.2.1 batchPerSec . . . 411
8.356.2.2 injectEnable . . . 411
8.356.2.3 samplesPerBatch . . . 411
8.357 loc_gyroTempAcceptReady Struct Reference . . . 411
8.357.1 Detailed Description . . . 411
8.357.2 Field Documentation . . . 412
8.357.2.1 batchPerSec . . . 412
8.357.2.2 injectEnable . . . 412
8.357.2.3 samplesPerBatch . . . 412
8.358 loc_IPv4Config Struct Reference . . . 412
8.358.1 Detailed Description . . . 412
8.358.2 Field Documentation . . . 412
8.358.2.1 IPv4Addr . . . 412
8.358.2.2 IPv4Port . . . 412
8.359 loc_IPv4Info Struct Reference . . . 412

8.359.1 Detailed Description . . . 412
8.359.2 Field Documentation . . . 413
8.359.2.1 address . . . 413
8.359.2.2 port . . . 413
8.359.2.3 TlvPresent . . . 413
8.360 loc_IPv6Config Struct Reference . . . 413
8.360.1 Detailed Description . . . 413
8.360.2 Field Documentation . . . 413
8.360.2.1 IPv6Addr . . . 413
8.360.2.2 IPv6Port . . . 413
8.361 loc_IPv6Info Struct Reference . . . 413
8.361.1 Detailed Description . . . 413
8.361.2 Field Documentation . . . 414
8.361.2.1 address . . . 414
8.361.2.2 port . . . 414
8.361.2.3 TlvPresent . . . 414
8.362 loc_LocApplicationInfo Struct Reference . . . 414
8.362.1 Detailed Description . . . 414
8.362.2 Field Documentation . . . 415
8.362.2.1 appNameLength . . . 415
8.362.2.2 appProviderLength . . . 415
8.362.2.3 appVersionLength . . . 415
8.362.2.4 appVersionValid . . . 415
8.362.2.5 pAppName . . . 415
8.362.2.6 pAppProvider . . . 415
8.362.2.7 pAppVersion . . . 415
8.363 loc_precisionDilution Struct Reference . . . 415
8.363.1 Detailed Description . . . 415
8.363.2 Field Documentation . . . 416
8.363.2.1 HDOP . . . 416
8.363.2.2 PDOP . . . 416
8.363.2.3 VDOP . . . 416
8.364 loc_satelliteInfo Struct Reference . . . 416
8.364.1 Detailed Description . . . 416
8.364.2 Field Documentation . . . 418
8.364.2.1 azimuth . . . 418
8.364.2.2 elevation . . . 418
8.364.2.3 gnssSvId . . . 418
8.364.2.4 healthStatus . . . 418
8.364.2.5 snr . . . 418

8.364.2.6 svInfoMask . . . 418
8.364.2.7 svListLen . . . 418
8.364.2.8 svStatus . . . 418
8.364.2.9 system . . . 418
8.364.2.10 validMask . . . 418
8.365 loc_sensorDataUsage Struct Reference . . . 418
8.365.1 Detailed Description . . . 418
8.365.2 Field Documentation . . . 419
8.365.2.1 aidingIndicatorMask . . . 419
8.365.2.2 usageMask . . . 419
8.366 loc_SV Struct Reference . . . 419
8.366.1 Detailed Description . . . 419
8.366.2 Field Documentation . . . 420
8.366.2.1 id . . . 420
8.366.2.2 mask . . . 420
8.366.2.3 system . . . 420
8.367 loc_SVInfo Struct Reference . . . 420
8.367.1 Detailed Description . . . 420
8.367.2 Field Documentation . . . 420
8.367.2.1 len . . . 420
8.367.2.2 pSV . . . 420
8.368 loc_svUsedforFix Struct Reference . . . 420
8.368.1 Detailed Description . . . 420
8.368.2 Field Documentation . . . 421
8.368.2.1 gnssSvUsedList . . . 421
8.368.2.2 gnssSvUsedList_len . . . 421
8.369 loc_urlAddr Struct Reference . . . 421
8.369.1 Detailed Description . . . 421
8.369.2 Field Documentation . . . 421
8.369.2.1 address . . . 421
8.369.2.2 TlvPresent . . . 421
8.370 loc_URLAddrInfo Struct Reference . . . 421
8.370.1 Detailed Description . . . 422
8.370.2 Field Documentation . . . 422
8.370.2.1 urlAddr . . . 422
8.371 LocApplicationInfo Struct Reference . . . 422
8.371.1 Detailed Description . . . 422
8.371.2 Field Documentation . . . 423
8.371.2.1 appNameLength . . . 423
8.371.2.2 appProviderLength . . . 423

8.371.2.3 appVersionLength . . . 423
8.371.2.4 appVersionValid . . . 423
8.371.2.5 pAppName . . . 423
8.371.2.6 pAppProvider . . . 423
8.371.2.7 pAppVersion . . . 423
8.372 LocDelAssDataReq Struct Reference . . . 423
8.372.1 Detailed Description . . . 423
8.372.2 Field Documentation . . . 424
8.372.2.1 pBdsSVInfo . . . 424
8.372.2.2 pCellDb . . . 424
8.372.2.3 pClkInfo . . . 424
8.372.2.4 pGnssData . . . 424
8.372.2.5 pSVInfo . . . 424
8.373 LOCEventRegisterReqResp Struct Reference . . . 424
8.373.1 Detailed Description . . . 424
8.373.2 Field Documentation . . . 426
8.373.2.1 eventRegister . . . 426
8.374 LOCExtPowerStateReqResp Struct Reference . . . 426
8.374.1 Detailed Description . . . 426
8.374.2 Field Documentation . . . 426
8.374.2.1 extPowerState . . . 426
8.375 LocGetServerReq Struct Reference . . . 426
8.375.1 Detailed Description . . . 426
8.375.2 Field Documentation . . . 427
8.375.2.1 pServerAddrTypeMask . . . 427
8.375.2.2 serverType . . . 427
8.376 LocInjectPositionReq Struct Reference . . . 427
8.376.1 Detailed Description . . . 427
8.376.2 Field Documentation . . . 430
8.376.2.1 pAltitudeSrcInfo . . . 430
8.376.2.2 pAltitudeWrtEllipsoid . . . 430
8.376.2.3 pAltitudeWrtMeanSeaLevel . . . 430
8.376.2.4 pHorConfidence . . . 431
8.376.2.5 pHorReliability . . . 431
8.376.2.6 pHorUncCircular . . . 431
8.376.2.7 pLatitude . . . 431
8.376.2.8 pLongitude . . . 431
8.376.2.9 pPositionSrc . . . 431
8.376.2.10 pRawHorConfidence . . . 431
8.376.2.11 pRawHorUncCircular . . . 431

8.376.2.12 pTimestampAge . . . 431
8.376.2.13 pTimestampUtc . . . 431
8.376.2.14 pVertConfidence . . . 431
8.376.2.15 pVertReliability . . . 431
8.376.2.16 pVertUnc . . . 431
8.377 LocInjectSensorDataReq Struct Reference . . . 431
8.377.1 Detailed Description . . . 431
8.377.2 Field Documentation . . . 432
8.377.2.1 pAcceleroData . . . 432
8.377.2.2 pAcceleroTempData . . . 432
8.377.2.3 pAcceleroTimeSrc . . . 432
8.377.2.4 pGyroData . . . 432
8.377.2.5 pGyroTempData . . . 432
8.377.2.6 pGyroTimeSrc . . . 432
8.377.2.7 pOpaqueIdentifier . . . 432
8.378 LocSetCradleMountReq Struct Reference . . . 432
8.378.1 Detailed Description . . . 433
8.378.2 Field Documentation . . . 433
8.378.2.1 pConfidence . . . 433
8.378.2.2 state . . . 433
8.379 LocSetServerReq Struct Reference . . . 433
8.379.1 Detailed Description . . . 433
8.379.2 Field Documentation . . . 434
8.379.2.1 pIPv4Config . . . 434
8.379.2.2 pIPv6Config . . . 434
8.379.2.3 pURLAddr . . . 434
8.379.2.4 serverType . . . 434
8.380 LOCStartReq Struct Reference . . . 434
8.380.1 Detailed Description . . . 434
8.380.2 Field Documentation . . . 435
8.380.2.1 pApplicationInfo . . . 435
8.380.2.2 pConfigAltitudeAssumed . . . 435
8.380.2.3 pHorizontalAccuracyLvl . . . 435
8.380.2.4 pIntermediateReportState . . . 435
8.380.2.5 pMinIntervalTime . . . 435
8.380.2.6 pRecurrenceType . . . 435
8.380.2.7 SessionId . . . 436
8.381 LOCStopReq Struct Reference . . . 436
8.381.1 Detailed Description . . . 436
8.381.2 Field Documentation . . . 436

8.381.2.1 sessionId . . . 436
8.382 IteBandPrefExt Struct Reference . . . 436
8.382.1 Detailed Description . . . 436
8.382.2 Field Documentation . . . 437
8.382.2.1 bits_129_192 . . . 437
8.382.2.2 bits_193_256 . . . 437
8.382.2.3 bits_1_64 . . . 437
8.382.2.4 bits_65_128 . . . 437
8.383 LteCiotOpModeTlv Struct Reference . . . 437
8.383.1 Detailed Description . . . 437
8.383.2 Field Documentation . . . 437
8.383.2.1 campedCiotLteOpMode . . . 437
8.383.2.2 TlvPresent . . . 437
8.384 LteCQIParm Struct Reference . . . 437
8.384.1 Detailed Description . . . 438
8.384.2 Field Documentation . . . 438
8.384.2.1 CQIValueCW0 . . . 438
8.384.2.2 CQIValueCW1 . . . 438
8.384.2.3 ValidityCW0 . . . 438
8.384.2.4 ValidityCW1 . . . 438
8.385 IteEARFCN Struct Reference . . . 438
8.385.1 Detailed Description . . . 438
8.385.2 Field Documentation . . . 439
8.385.2.1 earfcn0 . . . 439
8.385.2.2 earfcn1 . . . 439
8.385.2.3 status . . . 439
8.386 IteGsmCellInfo Struct Reference . . . 439
8.386.1 Detailed Description . . . 439
8.386.2 Field Documentation . . . 440
8.386.2.1 cellReselPriority . . . 440
8.386.2.2 cells_len . . . 440
8.386.2.3 GsmCellInfo . . . 440
8.386.2.4 nccPermitted . . . 440
8.386.2.5 threshGsmHigh . . . 440
8.386.2.6 threshGsmLow . . . 440
8.387 LTEInfo Struct Reference . . . 440
8.387.1 Detailed Description . . . 440
8.387.2 Field Documentation . . . 442
8.387.2.1 band . . . 442
8.387.2.2 bandwidth . . . 442

8.387.2.3 emmConnState . . . 442
8.387.2.4 emmState . . . 442
8.387.2.5 emmSubState . . . 442
8.387.2.6 RXChan . . . 442
8.387.2.7 TXChan . . . 442
8.388 LTEInfoInterfreq Struct Reference . . . 443
8.388.1 Detailed Description . . . 443
8.388.2 Field Documentation . . . 443
8.388.2.1 freqsLen . . . 443
8.388.2.2 InfoInterfreq . . . 443
8.388.2.3 ueInIdle . . . 443
8.389 LTEInfoIntrafreq Struct Reference . . . 443
8.389.1 Detailed Description . . . 444
8.389.2 Field Documentation . . . 445
8.389.2.1 CellParams . . . 445
8.389.2.2 cellReselPriority . . . 445
8.389.2.3 cellsLen . . . 445
8.389.2.4 earfcn . . . 445
8.389.2.5 globalCellId . . . 445
8.389.2.6 plmn . . . 445
8.389.2.7 servingCellId . . . 445
8.389.2.8 sIntraSearch . . . 445
8.389.2.9 sNonIntraSearch . . . 445
8.389.2.10 tac . . . 445
8.389.2.11 threshServingLow . . . 445
8.389.2.12 ueInIdle . . . 445
8.390 LTEInfoNeighboringGSM Struct Reference . . . 445
8.390.1 Detailed Description . . . 446
8.390.2 Field Documentation . . . 446
8.390.2.1 freqsLen . . . 446
8.390.2.2 LteGsmCellInfo . . . 446
8.390.2.3 ueInIdle . . . 446
8.391 LTEInfoNeighboringWCDMA Struct Reference . . . 446
8.391.1 Detailed Description . . . 446
8.391.2 Field Documentation . . . 447
8.391.2.1 freqsLen . . . 447
8.391.2.2 LTEWCDMACellInfo . . . 447
8.391.2.3 ueInIdle . . . 447
8.392 LteM1BandPrefTlv Struct Reference . . . 447
8.392.1 Detailed Description . . . 447

8.392.2 Field Documentation . . . 448
8.392.2.1 lteM1BandPref . . . 449
8.392.2.2 TlvPresent . . . 449
8.393 LteNasReleaseInfo_s Struct Reference . . . 449
8.393.1 Detailed Description . . . 449
8.393.2 Field Documentation . . . 449
8.393.2.1 nas_major . . . 449
8.393.2.2 nas_minor . . . 449
8.393.2.3 nas_release . . . 449
8.394 LteNb1BandPrefTlv Struct Reference . . . 449
8.394.1 Detailed Description . . . 449
8.394.2 Field Documentation . . . 451
8.394.2.1 lteNb1BandPref . . . 451
8.394.2.2 TlvPresent . . . 451
8.395 LTEOperationMode Struct Reference . . . 451
8.395.1 Detailed Description . . . 451
8.395.2 Field Documentation . . . 451
8.395.2.1 pLTEOperationMode . . . 451
8.395.2.2 TlvPresent . . . 451
8.396 LteOpMode Struct Reference . . . 451
8.396.1 Detailed Description . . . 451
8.396.2 Field Documentation . . . 452
8.396.2.1 lteOpMode . . . 452
8.396.2.2 TlvPresent . . . 452
8.397 lteOpModeTlv Struct Reference . . . 452
8.397.1 Detailed Description . . . 452
8.397.2 Field Documentation . . . 453
8.397.2.1 lteOpMode . . . 453
8.397.2.2 lteOpModeLen . . . 453
8.397.2.3 MCC . . . 453
8.397.2.4 MNC . . . 453
8.397.2.5 TlvPresent . . . 453
8.398 ltePCI Struct Reference . . . 453
8.398.1 Detailed Description . . . 453
8.398.2 Field Documentation . . . 453
8.398.2.1 earfcn . . . 454
8.398.2.2 pci . . . 454
8.398.2.3 status . . . 454
8.399 lteRsrpinformation Struct Reference . . . 454
8.399.1 Detailed Description . . . 454

8.399.2 Field Documentation . . . 454
8.399.2.1 rsrplevel . . . 454
8.400 LTERSRPThresh Struct Reference . . . 454
8.400.1 Detailed Description . . . 454
8.400.2 Field Documentation . . . 454
8.400.2.1 LTERSRPThreshListLen . . . 454
8.400.2.2 pLTERSRPThreshList . . . 455
8.401 LTERSRQThresh Struct Reference . . . 455
8.401.1 Detailed Description . . . 455
8.401.2 Field Documentation . . . 455
8.401.2.1 LTERSRQThreshListLen . . . 455
8.401.2.2 pLTERSRQThreshList . . . 455
8.402 LTERSSIThresh Struct Reference . . . 455
8.402.1 Detailed Description . . . 455
8.402.2 Field Documentation . . . 456
8.402.2.1 LTERSSIThreshListLen . . . 456
8.402.2.2 pLTERSSIThreshList . . . 456
8.403 LteSccRxInfoResp Struct Reference . . . 456
8.403.1 Detailed Description . . . 456
8.403.2 Field Documentation . . . 456
8.403.2.1 pSccRxInfo . . . 456
8.404 LTESigRptCfg Struct Reference . . . 456
8.404.1 Detailed Description . . . 456
8.404.2 Field Documentation . . . 457
8.404.2.1 avgPeriod . . . 457
8.404.2.2 rptRate . . . 457
8.405 LTESigRptConfig Struct Reference . . . 457
8.405.1 Detailed Description . . . 457
8.405.2 Field Documentation . . . 458
8.405.2.1 avgPeriod . . . 458
8.405.2.2 rptRate . . . 458
8.406 lteSnrinformation Struct Reference . . . 458
8.406.1 Detailed Description . . . 458
8.406.2 Field Documentation . . . 458
8.406.2.1 snrlevel . . . 458
8.407 LTESNRThresh Struct Reference . . . 458
8.407.1 Detailed Description . . . 459
8.407.2 Field Documentation . . . 459
8.407.2.1 LTESNRThresListLen . . . 459
8.407.2.2 pLTESNRThresList . . . 459

8.408 LTESNRThreshold Struct Reference . . . 459
8.408.1 Detailed Description . . . 459
8.408.2 Field Documentation . . . 459
8.408.2.1 LTESNRThreshListLen . . . 459
8.408.2.2 pLTESNRThreshList . . . 460
8.409 lteSSInfo Struct Reference . . . 460
8.409.1 Detailed Description . . . 460
8.409.2 Field Documentation . . . 460
8.409.2.1 rsrp . . . 460
8.409.2.2 rsrq . . . 460
8.409.2.3 rssi . . . 460
8.409.2.4 snr . . . 460
8.410 LTESSInfo Struct Reference . . . 460
8.410.1 Detailed Description . . . 461
8.410.2 Field Documentation . . . 461
8.410.2.1 rsrp . . . 461
8.410.2.2 rsrq . . . 461
8.410.2.3 rssi . . . 461
8.410.2.4 snr . . . 461
8.411 LTESysInfo Struct Reference . . . 461
8.411.1 Detailed Description . . . 462
8.411.2 Field Documentation . . . 463
8.411.2.1 cellId . . . 463
8.411.2.2 cellIdValid . . . 463
8.411.2.3 lac . . . 463
8.411.2.4 lacValid . . . 463
8.411.2.5 MCC . . . 463
8.411.2.6 MNC . . . 463
8.411.2.7 networkIdValid . . . 463
8.411.2.8 regRejectInfoValid . . . 463
8.411.2.9 rejCause . . . 463
8.411.2.10 rejectSrvDomain . . . 463
8.411.2.11 sysInfoLTE . . . 463
8.411.2.12 tac . . . 464
8.411.2.13 tacValid . . . 464
8.412 lteWcdmaCellInfo Struct Reference . . . 464
8.412.1 Detailed Description . . . 464
8.412.2 Field Documentation . . . 464
8.412.2.1 cellReselPriority . . . 464
8.412.2.2 cellsLen . . . 464

8.412.2.3 threshXhigh . . . 465
8.412.2.4 threshXlow . . . 465
8.412.2.5 uarfcn . . . 465
8.412.2.6 WCDMACellInfo . . . 465
8.413 messageModeTlv Struct Reference . . . 465
8.413.1 Detailed Description . . . 465
8.413.2 Field Documentation . . . 465
8.413.2.1 MessageModeInfo . . . 465
8.413.2.2 TlvPresent . . . 465
8.414 messageWaitingInfoContent Struct Reference . . . 465
8.414.1 Detailed Description . . . 465
8.414.2 Field Documentation . . . 466
8.414.2.1 activeInd . . . 466
8.414.2.2 msgCount . . . 466
8.414.2.3 msgType . . . 466
8.415 minBasedIMSI Struct Reference . . . 466
8.415.1 Detailed Description . . . 466
8.415.2 Field Documentation . . . 467
8.415.2.1 imsiM1112 . . . 467
8.415.2.2 imsiMS1 . . . 467
8.415.2.3 imsiMS2 . . . 467
8.415.2.4 mccM . . . 467
8.416 mitigationDevList Struct Reference . . . 467
8.416.1 Detailed Description . . . 467
8.416.2 Field Documentation . . . 467
8.416.2.1 maxMitigationLevel . . . 467
8.416.2.2 mitigationDevId . . . 467
8.416.2.3 mitigationDevIdLen . . . 467
8.417 MNRInfo Struct Reference . . . 467
8.417.1 Detailed Description . . . 468
8.417.2 Field Documentation . . . 468
8.417.2.1 mcc . . . 468
8.417.2.2 mnc . . . 468
8.417.2.3 rat . . . 468
8.418 ModifyProfileIn Struct Reference . . . 468
8.418.1 Detailed Description . . . 468
8.418.2 Field Documentation . . . 469
8.418.2.1 curProfile . . . 469
8.418.2.2 pProfileID . . . 469
8.418.2.3 pProfileType . . . 469

8.419 ModifyProfileOut Struct Reference . . . 469
8.419.1 Detailed Description . . . 469
8.419.2 Field Documentation . . . 469
8.419.2.1 pExtErrorCode . . . 469
8.420 msgWaitingInfo Struct Reference . . . 469
8.420.1 Detailed Description . . . 469
8.420.2 Field Documentation . . . 470
8.420.2.1 msgWaitInfo . . . 470
8.420.2.2 numInstances . . . 470
8.420.2.3 results . . . 470
8.421 mtuSize3gppTlv Struct Reference . . . 470
8.421.1 Detailed Description . . . 470
8.421.2 Field Documentation . . . 470
8.421.2.1 MTUSize3gpp . . . 470
8.421.2.2 TlvPresent . . . 470
8.422 MTUSizeReq Struct Reference . . . 470
8.422.1 Detailed Description . . . 470
8.422.2 Field Documentation . . . 471
8.422.2.1 MTUSize . . . 471
8.423 namName Struct Reference . . . 471
8.423.1 Detailed Description . . . 471
8.423.2 Field Documentation . . . 471
8.423.2.1 namName . . . 471
8.423.2.2 namNameLen . . . 471
8.424 nas_acqOrderPref Struct Reference . . . 471
8.424.1 Detailed Description . . . 471
8.424.2 Field Documentation . . . 472
8.424.2.1 acqOrdeLen . . . 472
8.424.2.2 pAcqOrder . . . 472
8.425 nas_AcqOrderPrefTlv Struct Reference . . . 472
8.425.1 Detailed Description . . . 472
8.425.2 Field Documentation . . . 473
8.425.2.1 acqOrdeLen . . . 473
8.425.2.2 pAcqOrder . . . 473
8.425.2.3 TlvPresent . . . 473
8.426 nas_ActPilotPNElement Struct Reference . . . 473
8.426.1 Detailed Description . . . 473
8.426.2 Field Documentation . . . 473
8.426.2.1 ActSetPilotPN . . . 473
8.426.2.2 ActSetPilotPNStrength . . . 473

8.427 nas_AddCDMASysInfo Struct Reference . . . 473
8.427.1 Detailed Description . . . 473
8.427.2 Field Documentation . . . 474
8.427.2.1 geoSysIdx . . . 474
8.427.2.2 regPrd . . . 474
8.428 nas_AddSysInfo Struct Reference . . . 474
8.428.1 Detailed Description . . . 474
8.428.2 Field Documentation . . . 474
8.428.2.1 cellBroadcastCap . . . 474
8.428.2.2 geoSysIdx . . . 474
8.429 nas_BandPrefInfoTlv Struct Reference . . . 474
8.429.1 Detailed Description . . . 475
8.429.2 Field Documentation . . . 475
8.429.2.1 bits_129_192 . . . 475
8.429.2.2 bits_193_256 . . . 475
8.429.2.3 bits_1_64 . . . 475
8.429.2.4 bits_65_128 . . . 475
8.429.2.5 TlvPresent . . . 475
8.430 nas_BandPrefTlv Struct Reference . . . 475
8.430.1 Detailed Description . . . 475
8.430.2 Field Documentation . . . 477
8.430.2.1 BandPref . . . 477
8.430.2.2 TlvPresent . . . 477
8.431 nas_CallBarringSysInfo Struct Reference . . . 477
8.431.1 Detailed Description . . . 477
8.431.2 Field Documentation . . . 477
8.431.2.1 csBarStatus . . . 477
8.431.2.2 psBarStatus . . . 477
8.432 nas_callBarStatus Struct Reference . . . 477
8.432.1 Detailed Description . . . 478
8.432.2 Field Documentation . . . 478
8.432.2.1 csBarStatus . . . 478
8.432.2.2 psBarStatus . . . 478
8.433 nas_CDMAChannel Struct Reference . . . 478
8.433.1 Detailed Description . . . 478
8.433.2 Field Documentation . . . 479
8.433.2.1 priChA . . . 479
8.433.2.2 priChB . . . 479
8.433.2.3 secChA . . . 479
8.433.2.4 secChB . . . 479

8.434 nas_CDMAECIOThresh Struct Reference . . . 479
8.434.1 Detailed Description . . . 479
8.434.2 Field Documentation . . . 479
8.434.2.1 CDMAECIOThreshListLen . . . 479
8.434.2.2 pCDMAECIOThreshList . . . 480
8.435 nas_CDMAInfo Struct Reference . . . 480
8.435.1 Detailed Description . . . 480
8.435.2 Field Documentation . . . 480
8.435.2.1 baseId . . . 480
8.435.2.2 baseLat . . . 480
8.435.2.3 baseLong . . . 480
8.435.2.4 nid . . . 481
8.435.2.5 refpn . . . 481
8.435.2.6 sid . . . 481
8.436 nas_CDMARSSIThresh Struct Reference . . . 481
8.436.1 Detailed Description . . . 481
8.436.2 Field Documentation . . . 481
8.436.2.1 CDMARSSIThreshListLen . . . 481
8.436.2.2 pCDMARSSIThreshList . . . 481
8.437 nas_CDMASysInfo Struct Reference . . . 481
8.437.1 Detailed Description . . . 482
8.437.2 Field Documentation . . . 484
8.437.2.1 baseId . . . 484
8.437.2.2 baseLat . . . 484
8.437.2.3 baseLong . . . 484
8.437.2.4 bsInfoValid . . . 484
8.437.2.5 bsPRev . . . 484
8.437.2.6 bsPRevValid . . . 484
8.437.2.7 ccsSupported . . . 484
8.437.2.8 ccsSupportedValid . . . 484
8.437.2.9 cdmaSysIdValid . . . 484
8.437.2.10 isSysPrlMatch . . . 484
8.437.2.11 isSysPrlMatchValid . . . 484
8.437.2.12 MCC . . . 484
8.437.2.13 MNC . . . 484
8.437.2.14 networkID . . . 484
8.437.2.15 networkIdValid . . . 485
8.437.2.16 packetZone . . . 485
8.437.2.17 packetZoneValid . . . 485
8.437.2.18 pRevInUse . . . 485

8.437.2.19 pRevInUseValid . . . 485
8.437.2.20 sysInfoCDMA . . . 485
8.437.2.21 systemID . . . 485
8.438 nas_CDMASysInfoExt Struct Reference . . . 485
8.438.1 Detailed Description . . . 485
8.438.2 Field Documentation . . . 485
8.438.2.1 imsi_11_12 . . . 485
8.438.2.2 MCC . . . 485
8.439 nas_cellParams Struct Reference . . . 485
8.439.1 Detailed Description . . . 486
8.439.2 Field Documentation . . . 486
8.439.2.1 pci . . . 486
8.439.2.2 rsrp . . . 486
8.439.2.3 rsrq . . . 486
8.439.2.4 rssi . . . 486
8.439.2.5 srxlev . . . 486
8.440 nas_ciotAcqOrderPref Struct Reference . . . 486
8.440.1 Detailed Description . . . 486
8.440.2 Field Documentation . . . 487
8.440.2.1 ciotAcqOrderLen . . . 487
8.440.2.2 pCiotAcqOrder . . . 487
8.441 nas_CiotAcqOrderPrefTlv Struct Reference . . . 487
8.441.1 Detailed Description . . . 487
8.441.2 Field Documentation . . . 488
8.441.2.1 ciotAcqOrderLen . . . 488
8.441.2.2 pCiotAcqOrder . . . 488
8.441.2.3 TlvPresent . . . 488
8.442 nas_CiotLteOpModePrefTlv Struct Reference . . . 488
8.442.1 Detailed Description . . . 488
8.442.2 Field Documentation . . . 488
8.442.2.1 ciotLteOpModePref . . . 488
8.442.2.2 TlvPresent . . . 488
8.443 nas_CommInfo Struct Reference . . . 488
8.443.1 Detailed Description . . . 489
8.443.2 Field Documentation . . . 490
8.443.2.1 imsRegState . . . 490
8.443.2.2 modemMode . . . 490
8.443.2.3 psState . . . 490
8.443.2.4 systemMode . . . 490
8.443.2.5 temperature . . . 490

8.444 nas_CsgId Struct Reference . . . 490
8.444.1 Detailed Description . . . 490
8.444.2 Field Documentation . . . 490
8.444.2.1 csgId . . . 490
8.444.2.2 TlvPresent . . . 490
8.445 nas_CSGID Struct Reference . . . 490
8.445.1 Detailed Description . . . 491
8.445.2 Field Documentation . . . 491
8.445.2.1 id . . . 491
8.445.2.2 mcc . . . 491
8.445.2.3 mnc . . . 491
8.445.2.4 mncPcsDigits . . . 491
8.445.2.5 rat . . . 491
8.446 nas_currentPLMN Struct Reference . . . 491
8.446.1 Detailed Description . . . 492
8.446.2 Field Documentation . . . 492
8.446.2.1 MCC . . . 492
8.446.2.2 MNC . . . 492
8.446.2.3 netDescr . . . 492
8.446.2.4 netDescrLength . . . 492
8.447 nas_dataSrvCapabilities Struct Reference . . . 492
8.447.1 Detailed Description . . . 492
8.447.2 Field Documentation . . . 493
8.447.2.1 dataCapabilities . . . 493
8.447.2.2 dataCapabilitiesLen . . . 493
8.448 nas_DataStatusDetail Struct Reference . . . 493
8.448.1 Detailed Description . . . 493
8.448.2 Field Documentation . . . 494
8.448.2.1 IPAddress . . . 494
8.448.2.2 LastErrCode . . . 494
8.449 nas_detailSvcInfo Struct Reference . . . 495
8.449.1 Detailed Description . . . 495
8.449.2 Field Documentation . . . 496
8.449.2.1 hdrHybrid . . . 496
8.449.2.2 hdrSrvStatus . . . 496
8.449.2.3 isSysForbidden . . . 496
8.449.2.4 srvCapability . . . 496
8.449.2.5 srvStatus . . . 496
8.450 nas_DeviceConfigDetail Struct Reference . . . 496
8.450.1 Detailed Description . . . 496

8.450.2 Field Documentation . . . 497
8.450.2.1 Chipset . . . 497
8.450.2.2 HWVersion . . . 497
8.450.2.3 QLIC . . . 497
8.450.2.4 Technology . . . 497
8.451 nas_dirNum Struct Reference . . . 497
8.451.1 Detailed Description . . . 497
8.451.2 Field Documentation . . . 497
8.451.2.1 dirNum . . . 497
8.451.2.2 dirNumLen . . . 497
8.452 nas_DRCParams Struct Reference . . . 497
8.452.1 Detailed Description . . . 498
8.452.2 Field Documentation . . . 498
8.452.2.1 DRCCover . . . 498
8.452.2.2 DRCValue . . . 498
8.453 nas_ecioListElement Struct Reference . . . 498
8.453.1 Detailed Description . . . 498
8.453.2 Field Documentation . . . 498
8.453.2.1 ecio . . . 499
8.453.2.2 radioIf . . . 499
8.454 nas_ECIOThresh Struct Reference . . . 499
8.454.1 Detailed Description . . . 499
8.454.2 Field Documentation . . . 499
8.454.2.1 ECIOThresListLen . . . 499
8.454.2.2 pECIOThresList . . . 499
8.455 nas_EdrxCiotLteMode Struct Reference . . . 499
8.455.1 Detailed Description . . . 499
8.455.2 Field Documentation . . . 500
8.455.2.1 lteOpMode . . . 500
8.455.2.2 TlvPresent . . . 500
8.456 nas_EdrxCycleLength Struct Reference . . . 500
8.456.1 Detailed Description . . . 500
8.456.2 Field Documentation . . . 500
8.456.2.1 cycleLength . . . 500
8.456.2.2 TlvPresent . . . 500
8.457 nas_EdrxEnableType Struct Reference . . . 500
8.457.1 Detailed Description . . . 501
8.457.2 Field Documentation . . . 501
8.457.2.1 edrxEnabled . . . 501
8.457.2.2 TlvPresent . . . 501

8.458 nas_EdrxPagingTimeWindow Struct Reference . . . 501
8.458.1 Detailed Description . . . 501
8.458.2 Field Documentation . . . 501
8.458.2.1 edrxPtw . . . 501
8.458.2.2 TlvPresent . . . 501
8.459 nas_EdrxRatType Struct Reference . . . 501
8.459.1 Detailed Description . . . 502
8.459.2 Field Documentation . . . 502
8.459.2.1 edrxRatType . . . 502
8.459.2.2 TlvPresent . . . 502
8.460 nas_EmerModeTlv Struct Reference . . . 502
8.460.1 Detailed Description . . . 502
8.460.2 Field Documentation . . . 503
8.460.2.1 EmerMode . . . 503
8.460.2.2 TlvPresent . . . 503
8.461 nas_errorRateListElement Struct Reference . . . 503
8.461.1 Detailed Description . . . 503
8.461.2 Field Documentation . . . 504
8.461.2.1 errorRate . . . 504
8.461.2.2 radioIf . . . 504
8.462 nas_ForbiddenNetworks3GPP Struct Reference . . . 504
8.462.1 Detailed Description . . . 504
8.462.2 Field Documentation . . . 505
8.462.2.1 forbiddenNwInstLen . . . 505
8.462.2.2 MCC . . . 505
8.462.2.3 MNC . . . 505
8.462.2.4 TlvPresent . . . 505
8.463 nas_GERANInfo Struct Reference . . . 505
8.463.1 Detailed Description . . . 505
8.463.2 Field Documentation . . . 506
8.463.2.1 arfcn . . . 506
8.463.2.2 bsic . . . 506
8.463.2.3 cellID . . . 506
8.463.2.4 insNmrCellInfo . . . 506
8.463.2.5 lac . . . 506
8.463.2.6 nmrInst . . . 506
8.463.2.7 plmn . . . 506
8.463.2.8 rxLev . . . 506
8.463.2.9 timingAdvance . . . 506
8.464 nas_geranInstInfo Struct Reference . . . 506

8.464.1 Detailed Description . . . 507
8.464.2 Field Documentation . . . 507
8.464.2.1 geranArfcn . . . 507
8.464.2.2 geranBsicBcc . . . 507
8.464.2.3 geranBsicNcc . . . 507
8.464.2.4 geranRssi . . . 507
8.465 nas_gsmCellInfo Struct Reference . . . 507
8.465.1 Detailed Description . . . 507
8.465.2 Field Documentation . . . 508
8.465.2.1 arfcn . . . 508
8.465.2.2 band1900 . . . 508
8.465.2.3 bsicId . . . 508
8.465.2.4 cellIdValid . . . 508
8.465.2.5 rssi . . . 508
8.465.2.6 srxlev . . . 508
8.466 nas_GSMRSSIThresh Struct Reference . . . 508
8.466.1 Detailed Description . . . 508
8.466.2 Field Documentation . . . 509
8.466.2.1 GSMRSSIThreshListLen . . . 509
8.466.2.2 pGSMRSSIThreshList . . . 509
8.467 nas_GSMSrvStatusInfo Struct Reference . . . 509
8.467.1 Detailed Description . . . 509
8.467.2 Field Documentation . . . 510
8.467.2.1 isPrefDataPath . . . 510
8.467.2.2 srvStatus . . . 510
8.467.2.3 trueSrvStatus . . . 510
8.468 nas_GSMSysInfo Struct Reference . . . 510
8.468.1 Detailed Description . . . 510
8.468.2 Field Documentation . . . 512
8.468.2.1 cellId . . . 512
8.468.2.2 cellIdValid . . . 512
8.468.2.3 dtmSupp . . . 512
8.468.2.4 dtmSuppValid . . . 512
8.468.2.5 egprsSupp . . . 512
8.468.2.6 egprsSuppValid . . . 512
8.468.2.7 lac . . . 512
8.468.2.8 lacValid . . . 512
8.468.2.9 MCC . . . 512
8.468.2.10 MNC . . . 512
8.468.2.11 networkIdValid . . . 512

8.468.2.12 regRejectInfoValid . . . 512
8.468.2.13 rejCause . . . 513
8.468.2.14 rejectSrvDomain . . . 513
8.468.2.15 sysInfoGSM . . . 513
8.469 nas_GWAcqOrderPrefTlv Struct Reference . . . 513
8.469.1 Detailed Description . . . 513
8.469.2 Field Documentation . . . 513
8.469.2.1 GWAcqOrderPref . . . 513
8.469.2.2 TlvPresent . . . 513
8.470 nas_HDRECIOThresh Struct Reference . . . 513
8.470.1 Detailed Description . . . 513
8.470.2 Field Documentation . . . 514
8.470.2.1 HDRECIOThreshListLen . . . 514
8.470.2.2 pHDRECIOThreshList . . . 514
8.471 nas_HDRIOThresh Struct Reference . . . 514
8.471.1 Detailed Description . . . 514
8.471.2 Field Documentation . . . 514
8.471.2.1 HDRIOThreshListLen . . . 514
8.471.2.2 pHDRIOThreshList . . . 514
8.472 nas_HDRPersonality_Ind_Data Struct Reference . . . 514
8.472.1 Detailed Description . . . 515
8.472.2 Field Documentation . . . 515
8.472.2.1 pCurrentPersonality . . . 515
8.472.2.2 pPersonalityListLength . . . 515
8.472.2.3 pProtocolSubtypeElement . . . 515
8.473 nas_HDRRSSIThresh Struct Reference . . . 515
8.473.1 Detailed Description . . . 515
8.473.2 Field Documentation . . . 515
8.473.2.1 HDRRSSIThreshListLen . . . 515
8.473.2.2 pHDRRSSIThreshList . . . 516
8.474 nas_HDRSINRThresh Struct Reference . . . 516
8.474.1 Detailed Description . . . 516
8.474.2 Field Documentation . . . 516
8.474.2.1 HDRSINRThresListLen . . . 516
8.474.2.2 pHDRSINRThresList . . . 516
8.475 nas_HDRSINRThreshold Struct Reference . . . 516
8.475.1 Detailed Description . . . 516
8.475.2 Field Documentation . . . 517
8.475.2.1 HDRSINRThreshListLen . . . 517
8.475.2.2 pHDRSINRThreshList . . . 517

8.476 nas_HDRSysInfo Struct Reference . . . 517
8.476.1 Detailed Description . . . 517
8.476.2 Field Documentation . . . 519
8.476.2.1 hdrActiveProt . . . 519
8.476.2.2 hdrActiveProtValid . . . 519
8.476.2.3 hdrPersonality . . . 519
8.476.2.4 hdrPersonalityValid . . . 519
8.476.2.5 is856SysId . . . 519
8.476.2.6 is856SysIdValid . . . 519
8.476.2.7 isSysPrlMatch . . . 519
8.476.2.8 isSysPrlMatchValid . . . 519
8.476.2.9 sysInfoHDR . . . 519
8.477 nas_homeSIDNID Struct Reference . . . 519
8.477.1 Detailed Description . . . 519
8.477.2 Field Documentation . . . 519
8.477.2.1 numInstances . . . 519
8.477.2.2 SidNid . . . 519
8.478 nas_infoInterFreq Struct Reference . . . 519
8.478.1 Detailed Description . . . 520
8.478.2 Field Documentation . . . 520
8.478.2.1 cell_resel_priority . . . 520
8.478.2.2 cellInterFreqParams . . . 520
8.478.2.3 cells_len . . . 520
8.478.2.4 earfcn . . . 520
8.478.2.5 threshXHigh . . . 521
8.478.2.6 threshXLow . . . 521
8.479 nas_IOThresh Struct Reference . . . 521
8.479.1 Detailed Description . . . 521
8.479.2 Field Documentation . . . 521
8.479.2.1 IOThresListLen . . . 521
8.479.2.2 pIOThresList . . . 521
8.480 nas_lteBandPrefExt Struct Reference . . . 521
8.480.1 Detailed Description . . . 521
8.480.2 Field Documentation . . . 522
8.480.2.1 bits_129_192 . . . 522
8.480.2.2 bits_193_256 . . . 522
8.480.2.3 bits_1_64 . . . 522
8.480.2.4 bits_65_128 . . . 522
8.481 nas_LTEBandPrefTlv Struct Reference . . . 522
8.481.1 Detailed Description . . . 522

8.481.2 Field Documentation . . . 523
8.481.2.1 LTEBandPref . . . 524
8.481.2.2 TlvPresent . . . 524
8.482 nas_LteCiotOpModeTlv Struct Reference . . . 524
8.482.1 Detailed Description . . . 524
8.482.2 Field Documentation . . . 524
8.482.2.1 campedCiotLteOpMode . . . 524
8.482.2.2 TlvPresent . . . 524
8.483 nas_lteEARFCN Struct Reference . . . 524
8.483.1 Detailed Description . . . 524
8.483.2 Field Documentation . . . 525
8.483.2.1 earfcn0 . . . 525
8.483.2.2 earfcn1 . . . 525
8.483.2.3 status . . . 525
8.484 nas_lteGsmCellInfo Struct Reference . . . 525
8.484.1 Detailed Description . . . 525
8.484.2 Field Documentation . . . 526
8.484.2.1 cellReselPriority . . . 526
8.484.2.2 cells_len . . . 526
8.484.2.3 GsmCellInfo . . . 526
8.484.2.4 nccPermitted . . . 526
8.484.2.5 threshGsmHigh . . . 526
8.484.2.6 threshGsmLow . . . 526
8.485 nas_LTEInfo Struct Reference . . . 526
8.485.1 Detailed Description . . . 526
8.485.2 Field Documentation . . . 528
8.485.2.1 band . . . 528
8.485.2.2 bandwidth . . . 528
8.485.2.3 emmConnState . . . 528
8.485.2.4 emmState . . . 528
8.485.2.5 emmSubState . . . 528
8.485.2.6 RXChan . . . 528
8.485.2.7 TXChan . . . 528
8.486 nas_LTEInfoInterfreq Struct Reference . . . 529
8.486.1 Detailed Description . . . 529
8.486.2 Field Documentation . . . 529
8.486.2.1 freqsLen . . . 529
8.486.2.2 InfoInterfreq . . . 529
8.486.2.3 ueInIdle . . . 529
8.487 nas_LTEInfoIntrafreq Struct Reference . . . 529

8.487.1 Detailed Description . . . 530
8.487.2 Field Documentation . . . 531
8.487.2.1 CellParams . . . 531
8.487.2.2 cellReselPriority . . . 531
8.487.2.3 cellsLen . . . 531
8.487.2.4 earfcn . . . 531
8.487.2.5 globalCellId . . . 531
8.487.2.6 plmn . . . 531
8.487.2.7 servingCellId . . . 531
8.487.2.8 sIntraSearch . . . 531
8.487.2.9 sNonIntraSearch . . . 531
8.487.2.10 tac . . . 531
8.487.2.11 threshServingLow . . . 531
8.487.2.12 ueInIdle . . . 531
8.488 nas_LTEInfoNeighboringGSM Struct Reference . . . 531
8.488.1 Detailed Description . . . 532
8.488.2 Field Documentation . . . 532
8.488.2.1 freqsLen . . . 532
8.488.2.2 LteGsmCellInfo . . . 532
8.488.2.3 ueInIdle . . . 532
8.489 nas_LTEInfoNeighboringWCDMA Struct Reference . . . 532
8.489.1 Detailed Description . . . 532
8.489.2 Field Documentation . . . 533
8.489.2.1 freqsLen . . . 533
8.489.2.2 LTEWCDMACellInfo . . . 533
8.489.2.3 ueInIdle . . . 533
8.490 nas_LteM1BandPrefTlv Struct Reference . . . 533
8.490.1 Detailed Description . . . 533
8.490.2 Field Documentation . . . 534
8.490.2.1 lteM1BandPref . . . 535
8.490.2.2 TlvPresent . . . 535
8.491 nas_LteNb1BandPrefTlv Struct Reference . . . 535
8.491.1 Detailed Description . . . 535
8.491.2 Field Documentation . . . 536
8.491.2.1 lteNb1BandPref . . . 537
8.491.2.2 TlvPresent . . . 537
8.492 nas_LTEOperationMode Struct Reference . . . 537
8.492.1 Detailed Description . . . 537
8.492.2 Field Documentation . . . 537
8.492.2.1 pLTEOperationMode . . . 537

8.492.2.2 TlvPresent . . . 537
8.493 nas_LteOpMode Struct Reference . . . 537
8.493.1 Detailed Description . . . 537
8.493.2 Field Documentation . . . 538
8.493.2.1 lteOpMode . . . 538
8.493.2.2 TlvPresent . . . 538
8.494 nas_lteOpModeTlv Struct Reference . . . 538
8.494.1 Detailed Description . . . 538
8.494.2 Field Documentation . . . 539
8.494.2.1 lteOpMode . . . 539
8.494.2.2 lteOpModeLen . . . 539
8.494.2.3 MCC . . . 539
8.494.2.4 MNC . . . 539
8.494.2.5 TlvPresent . . . 539
8.495 nas_ltePCI Struct Reference . . . 539
8.495.1 Detailed Description . . . 539
8.495.2 Field Documentation . . . 539
8.495.2.1 earfcn . . . 539
8.495.2.2 pci . . . 539
8.495.2.3 status . . . 539
8.496 nas_lteRsrpinformation Struct Reference . . . 539
8.496.1 Detailed Description . . . 540
8.496.2 Field Documentation . . . 540
8.496.2.1 rsrplevel . . . 540
8.497 nas_LTERSRPThresh Struct Reference . . . 540
8.497.1 Detailed Description . . . 540
8.497.2 Field Documentation . . . 540
8.497.2.1 LTERSRPThreshListLen . . . 540
8.497.2.2 pLTERSRPThreshList . . . 540
8.498 nas_LTERSRQThresh Struct Reference . . . 540
8.498.1 Detailed Description . . . 541
8.498.2 Field Documentation . . . 541
8.498.2.1 LTERSRQThreshListLen . . . 541
8.498.2.2 pLTERSRQThreshList . . . 541
8.499 nas_LTERSSIThresh Struct Reference . . . 541
8.499.1 Detailed Description . . . 541
8.499.2 Field Documentation . . . 541
8.499.2.1 LTERSSIThreshListLen . . . 541
8.499.2.2 pLTERSSIThreshList . . . 541
8.500 nas_LTESigRptCfg Struct Reference . . . 542

8.500.1 Detailed Description . . . 542
8.500.2 Field Documentation . . . 542
8.500.2.1 avgPeriod . . . 542
8.500.2.2 rptRate . . . 542
8.501 nas_LTESigRptConfig Struct Reference . . . 542
8.501.1 Detailed Description . . . 543
8.501.2 Field Documentation . . . 543
8.501.2.1 avgPeriod . . . 543
8.501.2.2 rptRate . . . 543
8.502 nas_lteSnrinformation Struct Reference . . . 543
8.502.1 Detailed Description . . . 543
8.502.2 Field Documentation . . . 544
8.502.2.1 snrlevel . . . 544
8.503 nas_LTESNRThresh Struct Reference . . . 544
8.503.1 Detailed Description . . . 544
8.503.2 Field Documentation . . . 544
8.503.2.1 LTESNRThresListLen . . . 544
8.503.2.2 pLTESNRThresList . . . 544
8.504 nas_LTESNRThreshold Struct Reference . . . 544
8.504.1 Detailed Description . . . 544
8.504.2 Field Documentation . . . 545
8.504.2.1 LTESNRThreshListLen . . . 545
8.504.2.2 pLTESNRThreshList . . . 545
8.505 nas_LTESysInfo Struct Reference . . . 545
8.505.1 Detailed Description . . . 545
8.505.2 Field Documentation . . . 547
8.505.2.1 cellId . . . 547
8.505.2.2 cellIdValid . . . 547
8.505.2.3 lac . . . 547
8.505.2.4 lacValid . . . 547
8.505.2.5 MCC . . . 547
8.505.2.6 MNC . . . 547
8.505.2.7 networkIdValid . . . 547
8.505.2.8 regRejectInfoValid . . . 547
8.505.2.9 rejCause . . . 547
8.505.2.10 rejectSrvDomain . . . 547
8.505.2.11 sysInfoLTE . . . 547
8.505.2.12 tac . . . 547
8.505.2.13 tacValid . . . 547
8.506 nas_lteWcdmaCellInfo Struct Reference . . . 547

8.506.1 Detailed Description . . . 548
8.506.2 Field Documentation . . . 548
8.506.2.1 cellReselPriority . . . 548
8.506.2.2 cellsLen . . . 548
8.506.2.3 threshXhigh . . . 548
8.506.2.4 threshXlow . . . 548
8.506.2.5 uarfcn . . . 548
8.506.2.6 WCDMACellInfo . . . 548
8.507 nas_minBasedIMSI Struct Reference . . . 548
8.507.1 Detailed Description . . . 549
8.507.2 Field Documentation . . . 549
8.507.2.1 imsiM1112 . . . 549
8.507.2.2 imsiMS1 . . . 549
8.507.2.3 imsiMS2 . . . 549
8.507.2.4 mccM . . . 549
8.508 nas_MNRInfo Struct Reference . . . 549
8.508.1 Detailed Description . . . 549
8.508.2 Field Documentation . . . 550
8.508.2.1 mcc . . . 550
8.508.2.2 mnc . . . 550
8.508.2.3 rat . . . 550
8.509 nas_ModePrefTlv Struct Reference . . . 550
8.509.1 Detailed Description . . . 550
8.509.2 Field Documentation . . . 550
8.509.2.1 ModePref . . . 550
8.509.2.2 TlvPresent . . . 550
8.510 nas_namName Struct Reference . . . 550
8.510.1 Detailed Description . . . 551
8.510.2 Field Documentation . . . 551
8.510.2.1 namName . . . 551
8.510.2.2 namNameLen . . . 551
8.511 nas_netSelectionPref Struct Reference . . . 551
8.511.1 Detailed Description . . . 551
8.511.2 Field Documentation . . . 552
8.511.2.1 mcc . . . 552
8.511.2.2 mnc . . . 552
8.511.2.3 netReg . . . 552
8.512 nas_NetSelPrefTlv Struct Reference . . . 552
8.512.1 Detailed Description . . . 552
8.512.2 Field Documentation . . . 552

8.512.2.1 NetSelPref . . . 552
8.512.2.2 TlvPresent . . . 552
8.513 nas_NetworkStat1x Struct Reference . . . 552
8.513.1 Detailed Description . . . 553
8.513.2 Field Documentation . . . 554
8.513.2.1 ActSetCnt . . . 554
8.513.2.2 NeighborSetCnt . . . 554
8.513.2.3 pActPilotPNElements . . . 554
8.513.2.4 pNeighborSetPilotPN . . . 554
8.513.2.5 RX_EC_IO . . . 554
8.513.2.6 RX_PWR . . . 554
8.513.2.7 SO . . . 554
8.513.2.8 State . . . 554
8.513.2.9 TX_PWR . . . 554
8.514 nas_NetworkStatEVDO Struct Reference . . . 554
8.514.1 Detailed Description . . . 555
8.514.2 Field Documentation . . . 556
8.514.2.1 MACIndex . . . 556
8.514.2.2 PER . . . 556
8.514.2.3 PilotEnergy . . . 556
8.514.2.4 pSectorID . . . 556
8.514.2.5 RX_PWR . . . 556
8.514.2.6 SectorIDLen . . . 556
8.514.2.7 SNR . . . 556
8.514.2.8 State . . . 556
8.515 nas_nmrCellInfo Struct Reference . . . 556
8.515.1 Detailed Description . . . 556
8.515.2 Field Documentation . . . 557
8.515.2.1 nmrArfcn . . . 557
8.515.2.2 nmrBsic . . . 557
8.515.2.3 nmrCellID . . . 557
8.515.2.4 nmrLac . . . 557
8.515.2.5 nmrPlmn . . . 557
8.515.2.6 nmrRxLev . . . 557
8.516 nas_nr5gBandPref Struct Reference . . . 557
8.516.1 Detailed Description . . . 557
8.516.2 Field Documentation . . . 558
8.516.2.1 bits_129_192 . . . 558
8.516.2.2 bits_193_256 . . . 558
8.516.2.3 bits_1_64 . . . 558

8.516.2.4 bits_65_128 . . . 558
8.517 nas_NR5GCellStatusTlv Struct Reference . . . 558
8.517.1 Detailed Description . . . 558
8.517.2 Field Documentation . . . 558
8.517.2.1 nr5gCellStatus . . . 558
8.517.2.2 TlvPresent . . . 558
8.518 nas_NR5GSerStatTlv Struct Reference . . . 559
8.518.1 Detailed Description . . . 559
8.518.2 Field Documentation . . . 559
8.518.2.1 isPrefDataPath . . . 559
8.518.2.2 srvStatus . . . 559
8.518.2.3 TlvPresent . . . 559
8.518.2.4 trueSrvStatus . . . 559
8.519 nas_NR5GSystemInfoTlv Struct Reference . . . 560
8.519.1 Detailed Description . . . 560
8.519.2 Field Documentation . . . 562
8.519.2.1 cellId . . . 562
8.519.2.2 cellIdValid . . . 562
8.519.2.3 lac . . . 562
8.519.2.4 lacValid . . . 562
8.519.2.5 MCC . . . 562
8.519.2.6 MNC . . . 562
8.519.2.7 nwIdValid . . . 563
8.519.2.8 regRejectInfoValid . . . 563
8.519.2.9 rejCause . . . 563
8.519.2.10 rejectSrvDomain . . . 563
8.519.2.11 roamStatus . . . 563
8.519.2.12 roamStatusValid . . . 563
8.519.2.13 srvcapability . . . 563
8.519.2.14 srvCapValid . . . 563
8.519.2.15 srvDomain . . . 563
8.519.2.16 srvDomainValid . . . 563
8.519.2.17 sysForbidden . . . 563
8.519.2.18 sysForbiddenValid . . . 563
8.519.2.19 tac . . . 563
8.519.2.20 tacValid . . . 563
8.519.2.21 TlvPresent . . . 563
8.520 nas_operatorNameString Struct Reference . . . 563
8.520.1 Detailed Description . . . 563
8.520.2 Field Documentation . . . 563

8.520.2.1 PLMNName . . . 563
8.521 nas_OperatorPLMNData Struct Reference . . . 563
8.521.1 Detailed Description . . . 564
8.521.2 Field Documentation . . . 564
8.521.2.1 lac1 . . . 564
8.521.2.2 lac2 . . . 564
8.521.2.3 mcc . . . 564
8.521.2.4 mnc . . . 564
8.521.2.5 PLMNRecID . . . 564
8.522 nas_operatorPLMNList Struct Reference . . . 564
8.522.1 Detailed Description . . . 565
8.522.2 Field Documentation . . . 565
8.522.2.1 numInstance . . . 565
8.522.2.2 PLMNData . . . 565
8.523 nas_PhyCaAggPcellInfo Struct Reference . . . 565
8.523.1 Detailed Description . . . 565
8.523.2 Field Documentation . . . 566
8.523.2.1 dl_bw_value . . . 566
8.523.2.2 freq . . . 566
8.523.2.3 iLTEbandValue . . . 566
8.523.2.4 pci . . . 566
8.523.2.5 TlvPresent . . . 566
8.524 nas_PhyCaAggScellDlBw Struct Reference . . . 566
8.524.1 Detailed Description . . . 566
8.524.2 Field Documentation . . . 566
8.524.2.1 dl_bw_value . . . 566
8.524.2.2 TlvPresent . . . 566
8.525 nas_PhyCaAggScellIndex Struct Reference . . . 566
8.525.1 Detailed Description . . . 566
8.525.2 Field Documentation . . . 567
8.525.2.1 scell_idx . . . 567
8.525.2.2 TlvPresent . . . 567
8.526 nas_PhyCaAggScellIndType Struct Reference . . . 567
8.526.1 Detailed Description . . . 567
8.526.2 Field Documentation . . . 567
8.526.2.1 freq . . . 567
8.526.2.2 pci . . . 567
8.526.2.3 scell_state . . . 567
8.526.2.4 TlvPresent . . . 567
8.527 nas_PhyCaAggScellInfo Struct Reference . . . 568

8.527.1 Detailed Description . . . 568
8.527.2 Field Documentation . . . 570
8.527.2.1 dl_bw_value . . . 570
8.527.2.2 freq . . . 570
8.527.2.3 iLTEbandValue . . . 570
8.527.2.4 pci . . . 570
8.527.2.5 scell_state . . . 570
8.527.2.6 TlvPresent . . . 570
8.528 nas_PilotSetData Struct Reference . . . 570
8.528.1 Detailed Description . . . 570
8.528.2 Field Documentation . . . 570
8.528.2.1 NumPilots . . . 570
8.528.2.2 pPilotSetInfo . . . 570
8.529 nas_PilotSetParams Struct Reference . . . 571
8.529.1 Detailed Description . . . 571
8.529.2 Field Documentation . . . 571
8.529.2.1 PilotPN . . . 571
8.529.2.2 PilotStrength . . . 571
8.529.2.3 PilotType . . . 571
8.530 nas_PlmnID Struct Reference . . . 571
8.530.1 Detailed Description . . . 571
8.530.2 Field Documentation . . . 572
8.530.2.1 mcc . . . 572
8.530.2.2 mnc . . . 572
8.530.2.3 pcsDigit . . . 572
8.530.2.4 TlvPresent . . . 572
8.531 nas_PLMNNetworkName Struct Reference . . . 572
8.531.1 Detailed Description . . . 572
8.531.2 Field Documentation . . . 572
8.531.2.1 numInstance . . . 572
8.531.2.2 PLMNNetName . . . 572
8.532 nas_PLMNNetworkNameData Struct Reference . . . 572
8.532.1 Detailed Description . . . 573
8.532.2 Field Documentation . . . 574
8.532.2.1 codingScheme . . . 574
8.532.2.2 countryInitials . . . 574
8.532.2.3 longName . . . 574
8.532.2.4 longNameLen . . . 574
8.532.2.5 longNameSpareBits . . . 574
8.532.2.6 shortName . . . 574

8.532.2.7 shortNameLen . . . 574
8.532.2.8 shortNameSpareBits . . . 574
8.533 nas_PRLPrefTlv Struct Reference . . . 574
8.533.1 Detailed Description . . . 574
8.533.2 Field Documentation . . . 575
8.533.2.1 PRLPref . . . 575
8.533.2.2 TlvPresent . . . 575
8.534 nas_protocolSubtypeElement Struct Reference . . . 575
8.534.1 Detailed Description . . . 575
8.534.2 Field Documentation . . . 576
8.534.2.1 AccessMac . . . 576
8.534.2.2 AuthProt . . . 576
8.534.2.3 ControlMac . . . 576
8.534.2.4 EncryptProt . . . 576
8.534.2.5 ForwardMac . . . 576
8.534.2.6 IdleState . . . 576
8.534.2.7 KeyExchange . . . 576
8.534.2.8 MultDisc . . . 576
8.534.2.9 PhysicalLayer . . . 576
8.534.2.10 ReverseMac . . . 576
8.534.2.11 SecProt . . . 576
8.534.2.12 VirtStream . . . 576
8.535 nas_qaQmi3Gpp2TimeZone Struct Reference . . . 576
8.535.1 Detailed Description . . . 577
8.535.2 Field Documentation . . . 577
8.535.2.1 daylightSavings . . . 577
8.535.2.2 leapSeconds . . . 577
8.535.2.3 localTimeOffset . . . 577
8.536 nas_QmiNas3GppNetworkInfo Struct Reference . . . 577
8.536.1 Detailed Description . . . 577
8.536.2 Field Documentation . . . 578
8.536.2.1 Desription . . . 578
8.536.2.2 Forbidden . . . 578
8.536.2.3 InUse . . . 578
8.536.2.4 MCC . . . 578
8.536.2.5 MNC . . . 578
8.536.2.6 Preferred . . . 578
8.536.2.7 Roaming . . . 578
8.537 nas_QmiNas3GppNetworkRAT Struct Reference . . . 578
8.537.1 Detailed Description . . . 579

8.537.2 Field Documentation . . . 579
8.537.2.1 MCC . . . 579
8.537.2.2 MNC . . . 579
8.537.2.3 RAT . . . 579
8.538 nas_QmisNasPcsDigit Struct Reference . . . 579
8.538.1 Detailed Description . . . 579
8.538.2 Field Documentation . . . 580
8.538.2.1 includes_pcs_digit . . . 580
8.538.2.2 MCC . . . 580
8.538.2.3 MNC . . . 580
8.539 nas_QmisNasSlqsNasPCICellInfo Struct Reference . . . 580
8.539.1 Detailed Description . . . 580
8.539.2 Field Documentation . . . 580
8.539.2.1 cellID . . . 580
8.539.2.2 freq . . . 580
8.539.2.3 GlobalCellID . . . 580
8.539.2.4 nasQmisNasPcsDigit . . . 580
8.539.2.5 PlmnLen . . . 580
8.540 nas_QmisNasSlqsNasPCIInfo Struct Reference . . . 581
8.540.1 Detailed Description . . . 581
8.540.2 Field Documentation . . . 581
8.540.2.1 nasQmisNasSlqsNasPCICellInfo . . . 581
8.540.2.2 PCICellInfoLen . . . 581
8.540.2.3 rsrp . . . 581
8.540.2.4 rsrpRx0 . . . 581
8.540.2.5 rsrpRx1 . . . 582
8.540.2.6 rsrq . . . 582
8.540.2.7 rsrqRx0 . . . 582
8.540.2.8 rsrqRx1 . . . 582
8.541 nas_RankIndicatorTlv Struct Reference . . . 582
8.541.1 Detailed Description . . . 582
8.541.2 Field Documentation . . . 582
8.541.2.1 count0 . . . 582
8.541.2.2 count1 . . . 582
8.541.2.3 TlvPresent . . . 582
8.542 nas_RatDisabledMaskTlv Struct Reference . . . 582
8.542.1 Detailed Description . . . 582
8.542.2 Field Documentation . . . 583
8.542.2.1 ratDisabledMask . . . 583
8.542.2.2 TlvPresent . . . 583

8.543 nas_RejectReasonTlv Struct Reference . . . 583
8.543.1 Detailed Description . . . 583
8.543.2 Field Documentation . . . 583
8.543.2.1 rejectCause . . . 583
8.543.2.2 serviceDomain . . . 583
8.543.2.3 TlvPresent . . . 583
8.544 nas_RFBandInfoElements Struct Reference . . . 583
8.544.1 Detailed Description . . . 584
8.544.2 Field Documentation . . . 584
8.544.2.1 activeBandClass . . . 584
8.544.2.2 activeChannel . . . 584
8.544.2.3 radioInterface . . . 584
8.545 nas_RfBandInfoExtFormat Struct Reference . . . 584
8.545.1 Detailed Description . . . 584
8.545.2 Field Documentation . . . 585
8.545.2.1 pInstancesSize . . . 585
8.545.2.2 pRfBandInfoExtFormatParam . . . 585
8.545.2.3 TlvPresent . . . 585
8.546 nas_RfBandInfoExtFormatElements Struct Reference . . . 585
8.546.1 Detailed Description . . . 585
8.546.2 Field Documentation . . . 585
8.546.2.1 activeBand . . . 585
8.546.2.2 activeChannel . . . 585
8.546.2.3 radioInterface . . . 586
8.547 nas_RfBandInfoList Struct Reference . . . 586
8.547.1 Detailed Description . . . 586
8.547.2 Field Documentation . . . 586
8.547.2.1 pInstanceSize . . . 586
8.547.2.2 pRFBandInfoParam . . . 586
8.548 nas_RfBandwidthInfo Struct Reference . . . 586
8.548.1 Detailed Description . . . 586
8.548.2 Field Documentation . . . 587
8.548.2.1 pInstancesSize . . . 587
8.548.2.2 pRfBandwidthInfoParam . . . 587
8.548.2.3 TlvPresent . . . 587
8.549 nas_RfBandwidthInfoElements Struct Reference . . . 587
8.549.1 Detailed Description . . . 587
8.549.2 Field Documentation . . . 587
8.549.2.1 bandwidth . . . 587
8.549.2.2 radioInterface . . . 588

8.550 nas_RfDedicatedBandInfo Struct Reference . . . 588
8.550.1 Detailed Description . . . 588
8.550.2 Field Documentation . . . 588
8.550.2.1 pInstancesSize . . . 588
8.550.2.2 pRfDedicatedBandInfoParam . . . 588
8.550.2.3 TlvPresent . . . 588
8.551 nas_RfDedicatedBandInfoElements Struct Reference . . . 588
8.551.1 Detailed Description . . . 588
8.551.2 Field Documentation . . . 589
8.551.2.1 dedicatedBand . . . 589
8.551.2.2 radioInterface . . . 589
8.552 nas_RFInfoTlv Struct Reference . . . 589
8.552.1 Detailed Description . . . 589
8.552.2 Field Documentation . . . 590
8.552.2.1 activeBandClass . . . 590
8.552.2.2 activeChannel . . . 590
8.552.2.3 radioInterface . . . 590
8.552.2.4 radioInterfaceSize . . . 590
8.552.2.5 TlvPresent . . . 590
8.553 nas_roamIndList Struct Reference . . . 590
8.553.1 Detailed Description . . . 590
8.553.2 Field Documentation . . . 590
8.553.2.1 numInstances . . . 591
8.553.2.2 radioInterface . . . 591
8.553.2.3 roamIndicator . . . 591
8.554 nas_RoamPrefTlv Struct Reference . . . 591
8.554.1 Detailed Description . . . 591
8.554.2 Field Documentation . . . 591
8.554.2.1 RoamPref . . . 591
8.554.2.2 TlvPresent . . . 591
8.555 nas_RSRPThresh Struct Reference . . . 591
8.555.1 Detailed Description . . . 591
8.555.2 Field Documentation . . . 592
8.555.2.1 pRSRPThresList . . . 592
8.555.2.2 RSRPThresListLen . . . 592
8.556 nas_rsrqInformation Struct Reference . . . 592
8.556.1 Detailed Description . . . 592
8.556.2 Field Documentation . . . 592
8.556.2.1 radioIf . . . 592
8.556.2.2 rsrq . . . 592

8.557 nas_RSRQThresh Struct Reference . . . 592
8.557.1 Detailed Description . . . 593
8.557.2 Field Documentation . . . 593
8.557.2.1 pRSRQThresList . . . 593
8.557.2.2 RSRQThresListLen . . . 593
8.558 nas_RSSIThresh Struct Reference . . . 593
8.558.1 Detailed Description . . . 593
8.558.2 Field Documentation . . . 594
8.558.2.1 pRSSIThresList . . . 594
8.558.2.2 RSSIThresListLen . . . 594
8.559 nas_rxInfo Struct Reference . . . 594
8.559.1 Detailed Description . . . 594
8.559.2 Field Documentation . . . 595
8.559.2.1 ecio . . . 595
8.559.2.2 isRadioTuned . . . 595
8.559.2.3 phase . . . 595
8.559.2.4 rscp . . . 595
8.559.2.5 rsrp . . . 595
8.559.2.6 rxPower . . . 595
8.560 nas_RxSigInfo Struct Reference . . . 595
8.560.1 Detailed Description . . . 595
8.560.2 Field Documentation . . . 596
8.560.2.1 isRadioTuned . . . 596
8.560.2.2 rsrp . . . 596
8.560.2.3 rxChainIndex . . . 596
8.560.2.4 rxPower . . . 596
8.561 nas_rxSignalStrengthListElement Struct Reference . . . 596
8.561.1 Detailed Description . . . 596
8.561.2 Field Documentation . . . 597
8.561.2.1 radioIf . . . 597
8.561.2.2 rxSignalStrength . . . 597
8.562 nas_SccRxInfo Struct Reference . . . 597
8.562.1 Detailed Description . . . 597
8.562.2 Field Documentation . . . 598
8.562.2.1 numInstances . . . 598
8.562.2.2 rsrq . . . 598
8.562.2.3 sigInfo . . . 598
8.562.2.4 snr . . . 598
8.562.2.5 TlvPresent . . . 598
8.563 nas_serviceProviderName Struct Reference . . . 598

8.563.1 Detailed Description . . . 598
8.563.2 Field Documentation . . . 598
8.563.2.1 displayCondition . . . 598
8.563.2.2 spn . . . 598
8.563.2.3 spnLength . . . 598
8.564 nas_servSystem Struct Reference . . . 599
8.564.1 Detailed Description . . . 599
8.564.2 Field Documentation . . . 600
8.564.2.1 csAttachState . . . 600
8.564.2.2 numRadioInterfaces . . . 600
8.564.2.3 psAttachState . . . 600
8.564.2.4 radioInterface . . . 600
8.564.2.5 regState . . . 600
8.564.2.6 selNetwork . . . 600
8.565 nas_sidNid Struct Reference . . . 600
8.565.1 Detailed Description . . . 600
8.565.2 Field Documentation . . . 600
8.565.2.1 nid . . . 600
8.565.2.2 sid . . . 600
8.566 nas_SignalStrengthTlv Struct Reference . . . 601
8.566.1 Detailed Description . . . 601
8.566.2 Field Documentation . . . 601
8.566.2.1 radioInterface . . . 601
8.566.2.2 signalStrength . . . 601
8.566.2.3 TlvPresent . . . 601
8.567 nas_SLQSSignalStrengthsIndReq Struct Reference . . . 601
8.567.1 Detailed Description . . . 601
8.567.2 Field Documentation . . . 602
8.567.2.1 ecioDelta . . . 602
8.567.2.2 ecioThresholdList . . . 602
8.567.2.3 ecioThresholdListLen . . . 603
8.567.2.4 ioDelta . . . 603
8.567.2.5 lteRsrpDelta . . . 603
8.567.2.6 lteSnrDelta . . . 603
8.567.2.7 rsrqDelta . . . 603
8.567.2.8 rxSignalStrengthDelta . . . 603
8.567.2.9 sinrDelta . . . 603
8.567.2.10 sinrThresholdList . . . 603
8.567.2.11 sinrThresholdListLen . . . 603
8.568 nas_SLQSSignalStrengthsInformation Struct Reference . . . 603

8.568.1 Detailed Description . . . 603
8.568.2 Field Documentation . . . 604
8.568.2.1 ecioInfo . . . 604
8.568.2.2 errorRateInfo . . . 604
8.568.2.3 io . . . 604
8.568.2.4 lteRsrpinfo . . . 604
8.568.2.5 lteSnrinfo . . . 604
8.568.2.6 rsrqInfo . . . 604
8.568.2.7 rxSignalStrengthInfo . . . 604
8.568.2.8 sinr . . . 604
8.569 nas_SLQSSignalStrengthsTlv Struct Reference . . . 604
8.569.1 Detailed Description . . . 604
8.569.2 Field Documentation . . . 605
8.569.2.1 sSLQSSignalStrengthsInfo . . . 605
8.569.2.2 TlvPresent . . . 605
8.570 nas_SrvDomainPrefTlv Struct Reference . . . 605
8.570.1 Detailed Description . . . 605
8.570.2 Field Documentation . . . 605
8.570.2.1 SrvDomainPref . . . 605
8.570.2.2 TlvPresent . . . 605
8.571 nas_SrvStatusInfo Struct Reference . . . 605
8.571.1 Detailed Description . . . 605
8.571.2 Field Documentation . . . 606
8.571.2.1 isPrefDataPath . . . 606
8.571.2.2 srvStatus . . . 606
8.572 nas_sysInfoCommon Struct Reference . . . 606
8.572.1 Detailed Description . . . 606
8.572.2 Field Documentation . . . 608
8.572.2.1 isSysForbidden . . . 608
8.572.2.2 isSysForbiddenValid . . . 608
8.572.2.3 roamStatus . . . 608
8.572.2.4 roamStatusValid . . . 608
8.572.2.5 srvCapability . . . 608
8.572.2.6 srvCapabilityValid . . . 608
8.572.2.7 srvDomain . . . 608
8.572.2.8 srvDomainValid . . . 608
8.573 nas_TDSCDMAECIOThresh Struct Reference . . . 609
8.573.1 Detailed Description . . . 609
8.573.2 Field Documentation . . . 609
8.573.2.1 pTDSCDMAECIOThreshList . . . 609

8.573.2.2 TDSCDMAECIOThreshListLen . . . 609
8.574 nas_TDSCDMARSCPThresh Struct Reference . . . 609
8.574.1 Detailed Description . . . 609
8.574.2 Field Documentation . . . 609
8.574.2.1 pTDSCDMARSCPThreshList . . . 609
8.574.2.2 TDSCDMARSCPThreshListLen . . . 610
8.575 nas_TDSCDMARSSIThresh Struct Reference . . . 610
8.575.1 Detailed Description . . . 610
8.575.2 Field Documentation . . . 610
8.575.2.1 pTDSCDMARSSIThreshList . . . 610
8.575.2.2 TDSCDMARSSIThreshListLen . . . 610
8.576 nas_TDSCDMASINRCONFThresh Struct Reference . . . 610
8.576.1 Detailed Description . . . 610
8.576.2 Field Documentation . . . 610
8.576.2.1 pTDSCDMASINRCONFThreshList . . . 611
8.576.2.2 TDSCDMASINRCONFThreshListLen . . . 611
8.577 nas_TDSCDMASINRThresh Struct Reference . . . 611
8.577.1 Detailed Description . . . 611
8.577.2 Field Documentation . . . 611
8.577.2.1 pTDSCDMASINRThreshList . . . 611
8.577.2.2 TDSCDMASINRThreshListLen . . . 611
8.578 nas_timeInfo Struct Reference . . . 611
8.578.1 Detailed Description . . . 611
8.578.2 Field Documentation . . . 613
8.578.2.1 day . . . 613
8.578.2.2 dayLtSavingAdj . . . 613
8.578.2.3 dayOfWeek . . . 613
8.578.2.4 hour . . . 613
8.578.2.5 minute . . . 613
8.578.2.6 month . . . 613
8.578.2.7 radioInterface . . . 613
8.578.2.8 second . . . 613
8.578.2.9 timeZone . . . 613
8.578.2.10 TlvPresent . . . 613
8.578.2.11 year . . . 613
8.579 nas_trueIMSI Struct Reference . . . 613
8.579.1 Detailed Description . . . 613
8.579.2 Field Documentation . . . 614
8.579.2.1 imsiT1112 . . . 614
8.579.2.2 imsiTaddrNum . . . 614

8.579.2.3 imsiTS1 . . . 614
8.579.2.4 imsiTS2 . . . 614
8.579.2.5 mccT . . . 614
8.580 nas_txInfo Struct Reference . . . 614
8.580.1 Detailed Description . . . 614
8.580.2 Field Documentation . . . 614
8.580.2.1 isInTraffic . . . 614
8.580.2.2 txPower . . . 614
8.581 nas_UMTSInfo Struct Reference . . . 614
8.581.1 Detailed Description . . . 615
8.581.2 Field Documentation . . . 616
8.581.2.1 cellID . . . 616
8.581.2.2 ecio . . . 616
8.581.2.3 geranInst . . . 616
8.581.2.4 GeranInstInfo . . . 616
8.581.2.5 lac . . . 616
8.581.2.6 plmn . . . 616
8.581.2.7 psc . . . 616
8.581.2.8 rscp . . . 616
8.581.2.9 uarfcn . . . 616
8.581.2.10 umtsInst . . . 616
8.581.2.11 UMTSInstInfo . . . 616
8.582 nas_UMTSinstInfo Struct Reference . . . 616
8.582.1 Detailed Description . . . 616
8.582.2 Field Documentation . . . 617
8.582.2.1 umtsEcio . . . 617
8.582.2.2 umtsPsc . . . 617
8.582.2.3 umtsRscp . . . 617
8.582.2.4 umtsUarfcn . . . 617
8.583 nas_umtsLTENbrCell Struct Reference . . . 617
8.583.1 Detailed Description . . . 617
8.583.2 Field Documentation . . . 618
8.583.2.1 cellIsTDD . . . 618
8.583.2.2 earfcn . . . 618
8.583.2.3 pci . . . 618
8.583.2.4 rsrp . . . 618
8.583.2.5 rsrq . . . 618
8.583.2.6 srxlev . . . 618
8.584 nas_UniversalTime Struct Reference . . . 618
8.584.1 Detailed Description . . . 618

8.584.2 Field Documentation . . . 619
8.584.2.1 day . . . 619
8.584.2.2 dayOfWeek . . . 619
8.584.2.3 hour . . . 619
8.584.2.4 minute . . . 619
8.584.2.5 month . . . 619
8.584.2.6 second . . . 619
8.584.2.7 year . . . 619
8.585 nas_wcdmaCellInfo Struct Reference . . . 619
8.585.1 Detailed Description . . . 619
8.585.2 Field Documentation . . . 620
8.585.2.1 cpich_ecno . . . 620
8.585.2.2 cpich_rscp . . . 620
8.585.2.3 psc . . . 620
8.585.2.4 srxlev . . . 620
8.586 nas_WCDMAECIOThresh Struct Reference . . . 620
8.586.1 Detailed Description . . . 620
8.586.2 Field Documentation . . . 620
8.586.2.1 pWCDMAECIOThreshList . . . 620
8.586.2.2 WCDMAECIOThreshListLen . . . 620
8.587 nas_WCDMAInfoLTENeighborCell Struct Reference . . . 620
8.587.1 Detailed Description . . . 621
8.587.2 Field Documentation . . . 621
8.587.2.1 UMTSLTENbrCell . . . 621
8.587.2.2 umtsLTENbrCellLen . . . 621
8.587.2.3 wcdmaRRCState . . . 621
8.588 nas_WCDMARSSIThresh Struct Reference . . . 621
8.588.1 Detailed Description . . . 621
8.588.2 Field Documentation . . . 622
8.588.2.1 pWCDMARSSIThreshList . . . 622
8.588.2.2 WCDMARSSIThreshListLen . . . 622
8.589 nas_WCDMASysInfo Struct Reference . . . 622
8.589.1 Detailed Description . . . 622
8.589.2 Field Documentation . . . 624
8.589.2.1 cellId . . . 625
8.589.2.2 cellIdValid . . . 625
8.589.2.3 hsCallStatus . . . 625
8.589.2.4 hsCallStatusValid . . . 625
8.589.2.5 hsInd . . . 625
8.589.2.6 hsIndValid . . . 625

8.589.2.7 lac . . . 625
8.589.2.8 lacValid . . . 625
8.589.2.9 MCC . . . 625
8.589.2.10 MNC . . . 625
8.589.2.11 networkIdValid . . . 625
8.589.2.12 psc . . . 625
8.589.2.13 pscValid . . . 625
8.589.2.14 regRejectInfoValid . . . 625
8.589.2.15 rejCause . . . 625
8.589.2.16 rejectSrvDomain . . . 625
8.589.2.17 sysInfoWCDMA . . . 625
8.590 nas_wcdmaUARFCN Struct Reference . . . 625
8.590.1 Detailed Description . . . 625
8.590.2 Field Documentation . . . 626
8.590.2.1 status . . . 626
8.590.2.2 uarfcn . . . 626
8.591 NASAcqOrderPrefTlv Struct Reference . . . 626
8.591.1 Detailed Description . . . 626
8.591.2 Field Documentation . . . 626
8.591.2.1 AcqOrderLen . . . 626
8.591.2.2 AcqOrderPref . . . 626
8.591.2.3 TlvPresent . . . 626
8.592 NASBandPreferenceTlv Struct Reference . . . 626
8.592.1 Detailed Description . . . 626
8.592.2 Field Documentation . . . 626
8.592.2.1 band_pref . . . 626
8.592.2.2 TlvPresent . . . 626
8.593 nasCellLocationInfoResp Struct Reference . . . 627
8.593.1 Detailed Description . . . 627
8.593.2 Field Documentation . . . 627
8.593.2.1 pCDMAInfo . . . 627
8.593.2.2 pGERANInfo . . . 628
8.593.2.3 pLTEInfoInterfreq . . . 628
8.593.2.4 pLTEInfoIntrafreq . . . 628
8.593.2.5 pLTEInfoNeighboringGSM . . . 628
8.593.2.6 pLTEInfoNeighboringWCDMA . . . 628
8.593.2.7 pUMTSCellID . . . 628
8.593.2.8 pUMTSInfo . . . 628
8.593.2.9 pWCDMAInfoLTENeighborCell . . . 628
8.594 NASCiotAcqOrderPrefTlv Struct Reference . . . 628

8.594.1 Detailed Description . . . 628
8.594.2 Field Documentation . . . 628
8.594.2.1 CiotAcqOrderLen . . . 628
8.594.2.2 CiotAcqOrderPref . . . 628
8.594.2.3 TlvPresent . . . 628
8.595 NASCiotLteOpModePrefTlv Struct Reference . . . 628
8.595.1 Detailed Description . . . 628
8.595.2 Field Documentation . . . 629
8.595.2.1 CiotLteOpModePref . . . 629
8.595.2.2 TlvPresent . . . 629
8.596 NASEmergencyModeTlv Struct Reference . . . 629
8.596.1 Detailed Description . . . 629
8.596.2 Field Documentation . . . 629
8.596.2.1 EmerMode . . . 629
8.596.2.2 TlvPresent . . . 629
8.597 nasGet3GPP2SubscriptionInfoReq Struct Reference . . . 629
8.597.1 Detailed Description . . . 629
8.597.2 Field Documentation . . . 629
8.597.2.1 namID . . . 630
8.598 nasGet3GPP2SubscriptionInfoResp Struct Reference . . . 630
8.598.1 Detailed Description . . . 630
8.598.2 Field Documentation . . . 630
8.598.2.1 pCDMAChannel . . . 630
8.598.2.2 pDirNum . . . 630
8.598.2.3 pHomeSIDNID . . . 630
8.598.2.4 pMinBasedIMSI . . . 630
8.598.2.5 pNAMNameInfo . . . 630
8.598.2.6 pTrueIMSI . . . 630
8.599 nasGeteDRXParamsReq Struct Reference . . . 631
8.599.1 Detailed Description . . . 631
8.599.2 Field Documentation . . . 631
8.599.2.1 pEdrxRAT . . . 631
8.599.2.2 pLteOpMode . . . 631
8.600 nasGeteDRXParamsResp Struct Reference . . . 631
8.600.1 Detailed Description . . . 632
8.600.2 Field Documentation . . . 633
8.600.2.1 has_CycleLen . . . 633
8.600.2.2 has_EdrxEnable . . . 633
8.600.2.3 has_EdrxRAT . . . 633
8.600.2.4 has_LteOpMode . . . 633

8.600.2.5 has_PagingTimeWindow . . . 633
8.600.2.6 pCycleLen . . . 633
8.600.2.7 pEdrxEnable . . . 633
8.600.2.8 pEdrxRAT . . . 634
8.600.2.9 pLteOpMode . . . 634
8.600.2.10 pPagingTimeWindow . . . 634
8.601 nasGetForbiddenNetworksResp Struct Reference . . . 634
8.601.1 Detailed Description . . . 634
8.601.2 Field Documentation . . . 634
8.601.2.1 pForbiddenNetworks3GPP . . . 634
8.602 nasGetHDRColorCodeResp Struct Reference . . . 634
8.602.1 Detailed Description . . . 634
8.602.2 Field Documentation . . . 634
8.602.2.1 pColorCode . . . 634
8.603 nasGetLTECphyCa Struct Reference . . . 634
8.603.1 Field Documentation . . . 635
8.603.1.1 sPhyCaAggPcellInfo . . . 635
8.603.1.2 sPhyCaAggScellArray . . . 635
8.603.1.3 sPhyCaAggScellDlBw . . . 635
8.603.1.4 sPhyCaAggScellIndex . . . 635
8.603.1.5 sPhyCaAggScellIndType . . . 635
8.603.1.6 sPhyCaAggScellInfo . . . 635
8.604 NasGetLTECphyCaInfo Struct Reference . . . 635
8.604.1 Detailed Description . . . 635
8.604.2 Field Documentation . . . 636
8.604.2.1 PhyCaAggPcellInfo . . . 636
8.604.2.2 PhyCaAggScellArray . . . 636
8.604.2.3 PhyCaAggScellDlBw . . . 636
8.604.2.4 PhyCaAggScellIndex . . . 636
8.604.2.5 PhyCaAggScellIndType . . . 636
8.604.2.6 PhyCaAggScellInfo . . . 636
8.605 nasGetLTECphyCaResp Struct Reference . . . 636
8.605.1 Field Documentation . . . 636
8.605.1.1 pPhyCaAggPcellInfo . . . 636
8.605.1.2 pPhyCaAggScellArray . . . 636
8.605.1.3 pPhyCaAggScellDlBw . . . 636
8.605.1.4 pPhyCaAggScellIndex . . . 636
8.605.1.5 pPhyCaAggScellIndType . . . 636
8.605.1.6 pPhyCaAggScellInfo . . . 636
8.606 NasGetRFInfoResp Struct Reference . . . 637

8.606.1 Detailed Description . . . 637
8.606.2 Field Documentation . . . 637
8.606.2.1 pLTEOperationMode . . . 637
8.606.2.2 pRfBandInfoExtFormat . . . 637
8.606.2.3 pRfBandwidthInfo . . . 637
8.606.2.4 pRfDedicatedBandInfo . . . 637
8.606.2.5 rfbandInfoList . . . 637
8.607 nasGetSigInfoResp Struct Reference . . . 637
8.607.1 Detailed Description . . . 638
8.607.2 Field Documentation . . . 638
8.607.2.1 pCDMASSInfo . . . 638
8.607.2.2 pGSMSSInfo . . . 638
8.607.2.3 pHDRSSInfo . . . 638
8.607.2.4 pLTESSInfo . . . 638
8.607.2.5 pTDSCDMASigInfoExt . . . 638
8.607.2.6 pTDSCDMASigInfoRscp . . . 638
8.607.2.7 pWCDMASSInfo . . . 638
8.608 nasGetSysInfoResp Struct Reference . . . 638
8.608.1 Detailed Description . . . 639
8.608.2 Field Documentation . . . 641
8.608.2.1 pAddCDMASysInfo . . . 641
8.608.2.2 pAddGSMSysInfo . . . 641
8.608.2.3 pAddHDRSysInfo . . . 641
8.608.2.4 pAddLTESysInfo . . . 641
8.608.2.5 pAddWCDMASysInfo . . . 641
8.608.2.6 pCampedCiotLteOpMode . . . 641
8.608.2.7 pCDMASrvStatusInfo . . . 641
8.608.2.8 pCDMASysInfo . . . 641
8.608.2.9 pGSMCallBarringSysInfo . . . 641
8.608.2.10 pGSMCipherDomainSysInfo . . . 641
8.608.2.11 pGSMSrvStatusInfo . . . 641
8.608.2.12 pGSMSysInfo . . . 641
8.608.2.13 pHDRSrvStatusInfo . . . 641
8.608.2.14 pHDRSysInfo . . . 641
8.608.2.15 pLTESrvStatusInfo . . . 641
8.608.2.16 pLTESysInfo . . . 641
8.608.2.17 pLTEVoiceSupportSysInfo . . . 641
8.608.2.18 pWCDMACallBarringSysInfo . . . 641
8.608.2.19 pWCDMACipherDomainSysInfo . . . 641
8.608.2.20 pWCDMASrvStatusInfo . . . 641

8.608.2.21 pWCDMASysInfo . . . 641
8.609 nasGetTxRxInfoReq Struct Reference . . . 642
8.609.1 Detailed Description . . . 642
8.609.2 Field Documentation . . . 642
8.609.2.1 radio_if . . . 642
8.610 nasGetTxRxInfoResp Struct Reference . . . 642
8.610.1 Detailed Description . . . 642
8.610.2 Field Documentation . . . 642
8.610.2.1 pRXChain0Info . . . 643
8.610.2.2 pRXChain1Info . . . 643
8.610.2.3 pTXInfo . . . 643
8.611 NASGWAcqOrderPrefTlv Struct Reference . . . 643
8.611.1 Detailed Description . . . 643
8.611.2 Field Documentation . . . 643
8.611.2.1 GWAcqOrderPref . . . 643
8.611.2.2 TlvPresent . . . 643
8.612 nasIndicationRegisterReq Struct Reference . . . 643
8.612.1 Detailed Description . . . 643
8.612.2 Field Documentation . . . 646
8.612.2.1 pDDTMInd . . . 646
8.612.2.2 pDualStandByPrefInd . . . 646
8.612.2.3 pEdrxChangeInfoInd . . . 646
8.612.2.4 pErrorRateInd . . . 646
8.612.2.5 pHDRNewUATIAssInd . . . 646
8.612.2.6 pHDRSessionCloseInd . . . 646
8.612.2.7 pLTECphyCa . . . 646
8.612.2.8 pManagedRoamingInd . . . 646
8.612.2.9 pNetworkRejectInd . . . 646
8.612.2.10 pNetworkTimeInd . . . 646
8.612.2.11 pServingSystemInd . . . 646
8.612.2.12 pSignalStrengthInd . . . 646
8.612.2.13 pSubscriptionInfoInd . . . 646
8.612.2.14 pSuppressSysInfoInd . . . 646
8.612.2.15 pSysInfoInd . . . 646
8.612.2.16 pSystemSelectionInd . . . 646
8.613 nasInitNetworkReg Struct Reference . . . 646
8.613.1 Detailed Description . . . 647
8.613.2 Field Documentation . . . 647
8.613.2.1 pChangeDuration . . . 647
8.613.2.2 pMncPcsDigitStatus . . . 647

8.613.2.3 pMNRInfo . . . 647
8.613.2.4 regAction . . . 647
8.614 NASLTEBandPreferenceTlv Struct Reference . . . 647
8.614.1 Detailed Description . . . 647
8.614.2 Field Documentation . . . 648
8.614.2.1 LTEBandPref . . . 648
8.614.2.2 TlvPresent . . . 648
8.615 NASLteM1BandPrefTlv Struct Reference . . . 648
8.615.1 Detailed Description . . . 648
8.615.2 Field Documentation . . . 648
8.615.2.1 LteM1BandPref . . . 648
8.615.2.2 TlvPresent . . . 648
8.616 NASLteNasReleaseInfoTlv Struct Reference . . . 648
8.616.1 Detailed Description . . . 648
8.616.2 Field Documentation . . . 649
8.616.2.1 nas_major . . . 649
8.616.2.2 nas_minor . . . 649
8.616.2.3 nas_release . . . 649
8.616.2.4 TlvPresent . . . 649
8.617 NASLteNB1BandPrefTlv Struct Reference . . . 649
8.617.1 Detailed Description . . . 649
8.617.2 Field Documentation . . . 649
8.617.2.1 LteNB1BandPref . . . 649
8.617.2.2 TlvPresent . . . 649
8.618 NASModePreferenceTlv Struct Reference . . . 649
8.618.1 Detailed Description . . . 649
8.618.2 Field Documentation . . . 650
8.618.2.1 ModePref . . . 650
8.618.2.2 TlvPresent . . . 650
8.619 NASNetSelPreferenceTlv Struct Reference . . . 650
8.619.1 Detailed Description . . . 650
8.619.2 Field Documentation . . . 650
8.619.2.1 NetSelPref . . . 650
8.619.2.2 TlvPresent . . . 650
8.620 nasNetworkReject Struct Reference . . . 650
8.620.1 Detailed Description . . . 650
8.620.2 Field Documentation . . . 653
8.620.2.1 pCsgId . . . 653
8.620.2.2 pLteOpMode . . . 653
8.620.2.3 pPlmnId . . . 653

8.620.2.4 radioIf . . . 653
8.620.2.5 rejectCause . . . 653
8.620.2.6 results . . . 653
8.620.2.7 serviceDomain . . . 653
8.621 nasNetworkTime Struct Reference . . . 653
8.621.1 Detailed Description . . . 653
8.621.2 Field Documentation . . . 654
8.621.2.1 pDayltSavAdj . . . 654
8.621.2.2 pRadioInterface . . . 654
8.621.2.3 pTimeZone . . . 654
8.621.2.4 results . . . 654
8.621.2.5 universalTime . . . 654
8.622 NASNr5gBandPrefTlv Struct Reference . . . 654
8.622.1 Detailed Description . . . 654
8.622.2 Field Documentation . . . 654
8.622.2.1 Nr5gBandPrefbits1_64 . . . 654
8.622.2.2 Nr5gBandPrefbits_129_192 . . . 654
8.622.2.3 Nr5gBandPrefbits_193_256 . . . 654
8.622.2.4 Nr5gBandPrefbits_65_128 . . . 654
8.622.2.5 TlvPresent . . . 655
8.623 nasOperatorNameResp Struct Reference . . . 655
8.623.1 Detailed Description . . . 655
8.623.2 Field Documentation . . . 655
8.623.2.1 pNITZInformation . . . 655
8.623.2.2 pOperatorNameString . . . 655
8.623.2.3 pOperatorPLMNList . . . 655
8.623.2.4 pPLMNNetworkName . . . 655
8.623.2.5 pSrvcProviderName . . . 655
8.624 NASOTAMessageTlv Struct Reference . . . 655
8.624.1 Detailed Description . . . 656
8.624.2 Field Documentation . . . 656
8.624.2.1 data_buf . . . 656
8.624.2.2 data_len . . . 656
8.624.2.3 message_type . . . 656
8.624.2.4 TlvPresent . . . 656
8.625 NASPhyCaAggPcellInfo Struct Reference . . . 656
8.625.1 Detailed Description . . . 657
8.625.2 Field Documentation . . . 657
8.625.2.1 dl_bw_value . . . 657
8.625.2.2 freq . . . 657

8.625.2.3 iLTEbandValue . . . 657
8.625.2.4 pci . . . 657
8.625.2.5 TlvPresent . . . 657
8.626 NASPhyCaAggScellArray Struct Reference . . . 657
8.626.1 Detailed Description . . . 657
8.626.2 Field Documentation . . . 658
8.626.2.1 band . . . 658
8.626.2.2 cphy_ca_dl_bandwidth . . . 658
8.626.2.3 cphy_scell_info_list_len . . . 658
8.626.2.4 freq . . . 658
8.626.2.5 pci . . . 658
8.626.2.6 scell_idx . . . 658
8.626.2.7 scell_state . . . 659
8.626.2.8 TlvPresent . . . 659
8.627 NASPhyCaAggScellDlBw Struct Reference . . . 659
8.627.1 Detailed Description . . . 659
8.627.2 Field Documentation . . . 659
8.627.2.1 dl_bw_value . . . 659
8.627.2.2 TlvPresent . . . 659
8.628 NASPhyCaAggScellIndex Struct Reference . . . 659
8.628.1 Detailed Description . . . 659
8.628.2 Field Documentation . . . 659
8.628.2.1 scell_idx . . . 660
8.628.2.2 TlvPresent . . . 660
8.629 NASPhyCaAggScellIndType Struct Reference . . . 660
8.629.1 Detailed Description . . . 660
8.629.2 Field Documentation . . . 660
8.629.2.1 freq . . . 660
8.629.2.2 pci . . . 660
8.629.2.3 scell_state . . . 660
8.629.2.4 TlvPresent . . . 660
8.630 NASPhyCaAggScellInfo Struct Reference . . . 660
8.630.1 Detailed Description . . . 661
8.630.2 Field Documentation . . . 661
8.630.2.1 dl_bw_value . . . 661
8.630.2.2 freq . . . 661
8.630.2.3 iLTEbandValue . . . 661
8.630.2.4 pci . . . 661
8.630.2.5 scell_state . . . 661
8.630.2.6 TlvPresent . . . 661

8.631 nasPLMNNameReq Struct Reference . . . 661
8.631.1 Detailed Description . . . 662
8.631.2 Field Documentation . . . 662
8.631.2.1 mcc . . . 662
8.631.2.2 mnc . . . 662
8.631.2.3 pMncPcsStatus . . . 662
8.632 nasPLMNNameResp Struct Reference . . . 662
8.632.1 Detailed Description . . . 663
8.632.2 Field Documentation . . . 664
8.632.2.1 longName . . . 664
8.632.2.2 longNameCI . . . 664
8.632.2.3 longNameEn . . . 664
8.632.2.4 longNameLen . . . 664
8.632.2.5 longNameSB . . . 664
8.632.2.6 shortName . . . 664
8.632.2.7 shortNameCI . . . 664
8.632.2.8 shortNameEn . . . 664
8.632.2.9 shortNameLen . . . 664
8.632.2.10 shortNameSB . . . 664
8.632.2.11 spn . . . 664
8.632.2.12 spnEncoding . . . 665
8.632.2.13 spnLength . . . 665
8.633 NASPRLPreferenceTlv Struct Reference . . . 665
8.633.1 Detailed Description . . . 665
8.633.2 Field Documentation . . . 665
8.633.2.1 PRLPref . . . 665
8.633.2.2 TlvPresent . . . 665
8.634 NASQmiCbkNasSwiOTAMessageInd Struct Reference . . . 665
8.634.1 Detailed Description . . . 665
8.634.2 Field Documentation . . . 666
8.634.2.1 nasRelInfoTlv . . . 666
8.634.2.2 otaMsgTlv . . . 666
8.634.2.3 timeTlv . . . 666
8.635 NASQmiCbkNasSystemSelPrefInd Struct Reference . . . 666
8.635.1 Detailed Description . . . 666
8.635.2 Field Documentation . . . 667
8.635.2.1 AOPTlv . . . 667
8.635.2.2 BPTlv . . . 667
8.635.2.3 CiotAOPTlv . . . 668
8.635.2.4 CiotOpMPTlv . . . 668

8.635.2.5 EMTlv . . . 668
8.635.2.6 GWAOPTlv . . . 668
8.635.2.7 LBPTlv . . . 668
8.635.2.8 M1BandPTlv . . . 668
8.635.2.9 MPTlv . . . 668
8.635.2.10 NB1BandPTlv . . . 668
8.635.2.11 NR5gBandPTlv . . . 668
8.635.2.12 NSPTlv . . . 668
8.635.2.13 PRLPTlv . . . 668
8.635.2.14 RatDMTlv . . . 668
8.635.2.15 RPTlv . . . 668
8.635.2.16 SDPTlv . . . 668
8.636 NASRatDisabledMaskTlv Struct Reference . . . 668
8.636.1 Detailed Description . . . 668
8.636.2 Field Documentation . . . 668
8.636.2.1 RatDisabledMask . . . 668
8.636.2.2 TlvPresent . . . 668
8.637 NASRoamPreferenceTlv Struct Reference . . . 668
8.637.1 Detailed Description . . . 669
8.637.2 Field Documentation . . . 669
8.637.2.1 RoamPref . . . 669
8.637.2.2 TlvPresent . . . 669
8.638 NASServDomainPrefTlv Struct Reference . . . 669
8.638.1 Detailed Description . . . 669
8.638.2 Field Documentation . . . 669
8.638.2.1 SrvDomainPref . . . 669
8.638.2.2 TlvPresent . . . 669
8.639 NASServingSystemInfo Struct Reference . . . 669
8.639.1 Detailed Description . . . 670
8.639.2 Field Documentation . . . 670
8.639.2.1 csAttachState . . . 670
8.639.2.2 hdrPersonality . . . 671
8.639.2.3 psAttachState . . . 671
8.639.2.4 radioInterfaceList . . . 671
8.639.2.5 radioInterfaceNo . . . 671
8.639.2.6 registrationState . . . 671
8.639.2.7 selectedNetwork . . . 671
8.640 nasSeteDRXParamsReq Struct Reference . . . 671
8.640.1 Detailed Description . . . 671
8.640.2 Field Documentation . . . 672

8.640.2.1 pCycleLen . . . 672
8.640.2.2 pEdrxCiotLteMode . . . 672
8.640.2.3 pEdrxEnable . . . 672
8.640.2.4 pEdrxRatType . . . 672
8.640.2.5 pPagingTimeWindow . . . 672
8.641 nasSigInfo Struct Reference . . . 672
8.641.1 Detailed Description . . . 673
8.641.2 Field Documentation . . . 673
8.641.2.1 pCDMASigInfo . . . 673
8.641.2.2 pGSMSigInfo . . . 673
8.641.2.3 pHDRSigInfo . . . 673
8.641.2.4 pLTESigInfo . . . 673
8.641.2.5 pRscp . . . 673
8.641.2.6 pTDSCDMASigInfoExt . . . 673
8.641.2.7 pWCDMASigInfo . . . 673
8.641.2.8 results . . . 673
8.642 nasSwiGetChannelLockResp Struct Reference . . . 673
8.642.1 Detailed Description . . . 674
8.642.2 Field Documentation . . . 674
8.642.2.1 pLteEARFCN . . . 674
8.642.2.2 pLtePCI . . . 674
8.642.2.3 pWcdmaUARFCN . . . 674
8.643 NasSwiIndReg Struct Reference . . . 674
8.643.1 Detailed Description . . . 674
8.643.2 Field Documentation . . . 675
8.643.2.1 gsmUmtsDl . . . 675
8.643.2.2 gsmUmtsUl . . . 675
8.643.2.3 lteEmmDl . . . 675
8.643.2.4 lteEmmUl . . . 675
8.643.2.5 lteEsmDl . . . 675
8.643.2.6 lteEsmUl . . . 675
8.643.2.7 pRankIndicatorInd . . . 675
8.643.2.8 pTimer . . . 675
8.644 nasSwiSetChannelLockReq Struct Reference . . . 675
8.644.1 Detailed Description . . . 676
8.644.2 Field Documentation . . . 676
8.644.2.1 pLteEARFCN . . . 676
8.644.2.2 pLtePCI . . . 676
8.644.2.3 pWcdmaUARFCN . . . 676
8.645 nasSysInfo Struct Reference . . . 676

8.645.1 Detailed Description . . . 677
8.645.2 Field Documentation . . . 678
8.645.2.1 pAddCDMASysInfo . . . 678
8.645.2.2 pAddGSMSysInfo . . . 679
8.645.2.3 pAddHDRSysInfo . . . 679
8.645.2.4 pAddLTESysInfo . . . 679
8.645.2.5 pAddWCDMASysInfo . . . 679
8.645.2.6 pCDMASrvStatusInfo . . . 679
8.645.2.7 pCDMASysInfo . . . 679
8.645.2.8 pGSMCallBarringSysInfo . . . 679
8.645.2.9 pGSMCipherDomainSysInfo . . . 679
8.645.2.10 pGSMSrvStatusInfo . . . 679
8.645.2.11 pGSMSysInfo . . . 679
8.645.2.12 pHDRSrvStatusInfo . . . 679
8.645.2.13 pHDRSysInfo . . . 679
8.645.2.14 pLteCiotOpModeTlv . . . 679
8.645.2.15 pLTESrvStatusInfo . . . 679
8.645.2.16 pLTESysInfo . . . 679
8.645.2.17 pLTEVoiceSupportSysInfo . . . 679
8.645.2.18 pNR5GCellStatus . . . 679
8.645.2.19 pNR5GSerStatTlv . . . 679
8.645.2.20 pNR5GSystemInfoTlv . . . 679
8.645.2.21 pSysInfoNoChange . . . 679
8.645.2.22 pWCDMACallBarringSysInfo . . . 679
8.645.2.23 pWCDMACipherDomainSysInfo . . . 679
8.645.2.24 pWCDMASrvStatusInfo . . . 679
8.645.2.25 pWCDMASysInfo . . . 679
8.645.2.26 results . . . 679
8.646 NASTimeInfoTlv Struct Reference . . . 679
8.646.1 Detailed Description . . . 680
8.646.2 Field Documentation . . . 680
8.646.2.1 time . . . 680
8.646.2.2 TlvPresent . . . 680
8.647 nasTimers Struct Reference . . . 680
8.647.1 Detailed Description . . . 680
8.647.2 Field Documentation . . . 680
8.647.2.1 results . . . 680
8.647.2.2 t3396_apn . . . 680
8.647.2.3 t3396_plmn_id . . . 680
8.647.2.4 t3396_val . . . 680

8.648 netSelectionPref Struct Reference . . . 681
8.648.1 Detailed Description . . . 681
8.648.2 Field Documentation . . . 681
8.648.2.1 mcc . . . 681
8.648.2.2 mnc . . . 681
8.648.2.3 netReg . . . 681
8.649 NetStats Struct Reference . . . 681
8.649.1 Detailed Description . . . 681
8.649.2 Field Documentation . . . 682
8.649.2.1 rx_bytes . . . 682
8.649.2.2 rx_errors . . . 682
8.649.2.3 rx_overflows . . . 682
8.649.2.4 rx_packets . . . 682
8.649.2.5 tx_bytes . . . 682
8.649.2.6 tx_errors . . . 682
8.649.2.7 tx_overflows . . . 682
8.649.2.8 tx_packets . . . 682
8.650 NetworkDebugResp Struct Reference . . . 682
8.650.1 Detailed Description . . . 683
8.650.2 Field Documentation . . . 683
8.650.2.1 pDataStatusDetail . . . 683
8.650.2.2 pDeviceConfigDetail . . . 683
8.650.2.3 pNetworkStat1x . . . 683
8.650.2.4 pNetworkStatEVDO . . . 683
8.650.2.5 pObjectVer . . . 683
8.651 NetworkStat1x Struct Reference . . . 683
8.651.1 Detailed Description . . . 683
8.651.2 Field Documentation . . . 685
8.651.2.1 ActSetCnt . . . 685
8.651.2.2 NeighborSetCnt . . . 685
8.651.2.3 pActPilotPNElements . . . 685
8.651.2.4 pNeighborSetPilotPN . . . 685
8.651.2.5 RX_EC_IO . . . 685
8.651.2.6 RX_PWR . . . 685
8.651.2.7 SO . . . 685
8.651.2.8 State . . . 685
8.651.2.9 TX_PWR . . . 685
8.652 NetworkStatEVDO Struct Reference . . . 685
8.652.1 Detailed Description . . . 686
8.652.2 Field Documentation . . . 687

8.652.2.1 MACIndex . . . 687
8.652.2.2 PER . . . 687
8.652.2.3 PilotEnergy . . . 687
8.652.2.4 pSectorID . . . 687
8.652.2.5 RX_PWR . . . 687
8.652.2.6 SectorIDLen . . . 687
8.652.2.7 SNR . . . 687
8.652.2.8 State . . . 687
8.653 newMTMessageTlv Struct Reference . . . 687
8.653.1 Detailed Description . . . 687
8.653.2 Field Documentation . . . 687
8.653.2.1 MTMessageInfo . . . 687
8.653.2.2 TlvPresent . . . 687
8.654 newPwdData Struct Reference . . . 687
8.654.1 Detailed Description . . . 688
8.654.2 Field Documentation . . . 688
8.654.2.1 newPwd . . . 688
8.654.2.2 newPwdAgain . . . 688
8.655 nmrCellInfo Struct Reference . . . 688
8.655.1 Detailed Description . . . 688
8.655.2 Field Documentation . . . 689
8.655.2.1 nmrArfcn . . . 689
8.655.2.2 nmrBsic . . . 689
8.655.2.3 nmrCellID . . . 689
8.655.2.4 nmrLac . . . 689
8.655.2.5 nmrPlmn . . . 689
8.655.2.6 nmrRxLev . . . 689
8.656 nr5gBandPref Struct Reference . . . 689
8.656.1 Detailed Description . . . 689
8.656.2 Field Documentation . . . 690
8.656.2.1 bits_129_192 . . . 690
8.656.2.2 bits_193_256 . . . 690
8.656.2.3 bits_1_64 . . . 690
8.656.2.4 bits_65_128 . . . 690
8.657 NR5GCellStatusTlv Struct Reference . . . 690
8.657.1 Detailed Description . . . 690
8.657.2 Field Documentation . . . 691
8.657.2.1 nr5gCellStatus . . . 691
8.657.2.2 TlvPresent . . . 691
8.658 NR5GSerStatTlv Struct Reference . . . 691

8.658.1 Detailed Description . . . 691
8.658.2 Field Documentation . . . 691
8.658.2.1 isPrefDataPath . . . 691
8.658.2.2 srvStatus . . . 692
8.658.2.3 TlvPresent . . . 692
8.658.2.4 trueSrvStatus . . . 692
8.659 NR5GSystemInfoTlv Struct Reference . . . 692
8.659.1 Detailed Description . . . 692
8.659.2 Field Documentation . . . 694
8.659.2.1 cellId . . . 694
8.659.2.2 cellIdValid . . . 694
8.659.2.3 lac . . . 694
8.659.2.4 lacValid . . . 694
8.659.2.5 MCC . . . 694
8.659.2.6 MNC . . . 694
8.659.2.7 nwIdValid . . . 695
8.659.2.8 regRejectInfoValid . . . 695
8.659.2.9 rejCause . . . 695
8.659.2.10 rejectSrvDomain . . . 695
8.659.2.11 roamStatus . . . 695
8.659.2.12 roamStatusValid . . . 695
8.659.2.13 srvcapability . . . 695
8.659.2.14 srvCapValid . . . 695
8.659.2.15 srvDomain . . . 695
8.659.2.16 srvDomainValid . . . 695
8.659.2.17 sysForbidden . . . 695
8.659.2.18 sysForbiddenValid . . . 695
8.659.2.19 tac . . . 695
8.659.2.20 tacValid . . . 695
8.659.2.21 TlvPresent . . . 695
8.660 NSSAudioCtrl Struct Reference . . . 695
8.660.1 Detailed Description . . . 695
8.660.2 Field Documentation . . . 695
8.660.2.1 downLink . . . 695
8.660.2.2 upLink . . . 696
8.661 NWProfile Struct Reference . . . 696
8.661.1 Detailed Description . . . 696
8.661.2 Field Documentation . . . 696
8.661.2.1 pProfSz . . . 696
8.661.2.2 pProfValues . . . 696

8.661.2.3 tech . . . 696
8.662 omaDmConfigTlv Struct Reference . . . 696
8.662.1 Detailed Description . . . 696
8.662.2 Field Documentation . . . 697
8.662.2.1 alertmsg . . . 697
8.662.2.2 alertmsglength . . . 697
8.662.2.3 state . . . 697
8.662.2.4 userInputReq . . . 697
8.662.2.5 userInputTimeout . . . 697
8.663 omaDmConfigTlvExt Struct Reference . . . 697
8.663.1 Detailed Description . . . 697
8.663.2 Field Documentation . . . 699
8.663.2.1 alertmsg . . . 699
8.663.2.2 alertmsglength . . . 699
8.663.2.3 state . . . 699
8.663.2.4 userInputReq . . . 699
8.663.2.5 userInputTimeout . . . 699
8.664 omaDmFotaTlv Struct Reference . . . 699
8.664.1 Detailed Description . . . 699
8.664.2 Field Documentation . . . 700
8.664.2.1 description . . . 700
8.664.2.2 descriptionlength . . . 700
8.664.2.3 fwdloadsize . . . 701
8.664.2.4 fwloadComplete . . . 701
8.664.2.5 namelength . . . 701
8.664.2.6 package_name . . . 701
8.664.2.7 sessionType . . . 701
8.664.2.8 severity . . . 701
8.664.2.9 state . . . 701
8.664.2.10 updateCompleteStatus . . . 701
8.664.2.11 userInputReq . . . 701
8.664.2.12 userInputTimeout . . . 701
8.664.2.13 version . . . 701
8.664.2.14 versionlength . . . 701
8.665 omaDmFotaTlvExt Struct Reference . . . 701
8.665.1 Detailed Description . . . 701
8.665.2 Field Documentation . . . 703
8.665.2.1 description . . . 703
8.665.2.2 descriptionlength . . . 703
8.665.2.3 fumoResultCode . . . 703

8.665.2.4 namelength . . . 703
8.665.2.5 package_name . . . 703
8.665.2.6 packageSize . . . 703
8.665.2.7 receivedBytes . . . 703
8.665.2.8 reserved . . . 703
8.665.2.9 state . . . 703
8.665.2.10 userInputTimeout . . . 703
8.665.2.11 version . . . 703
8.665.2.12 versionlength . . . 703
8.666 omaDmNotificationsTlv Struct Reference . . . 703
8.666.1 Detailed Description . . . 703
8.666.2 Field Documentation . . . 704
8.666.2.1 notification . . . 704
8.666.2.2 sessionStatus . . . 704
8.667 operatorNameString Struct Reference . . . 704
8.667.1 Detailed Description . . . 704
8.667.2 Field Documentation . . . 704
8.667.2.1 PLMNName . . . 705
8.668 OperatorPLMNData Struct Reference . . . 705
8.668.1 Detailed Description . . . 705
8.668.2 Field Documentation . . . 705
8.668.2.1 lac1 . . . 705
8.668.2.2 lac2 . . . 705
8.668.2.3 mcc . . . 705
8.668.2.4 mnc . . . 705
8.668.2.5 PLMNRecID . . . 705
8.669 operatorPLMNList Struct Reference . . . 705
8.669.1 Detailed Description . . . 706
8.669.2 Field Documentation . . . 706
8.669.2.1 numInstance . . . 706
8.669.2.2 PLMNData . . . 706
8.670 pack_dms_ActivateAutomatic_t Struct Reference . . . 706
8.670.1 Detailed Description . . . 706
8.670.2 Field Documentation . . . 706
8.670.2.1 actCode . . . 706
8.671 pack_dms_GetCustFeaturesV2_t Struct Reference . . . 706
8.671.1 Detailed Description . . . 707
8.671.2 Field Documentation . . . 707
8.671.2.1 cust_id . . . 707
8.671.2.2 list_type . . . 707

8.671.2.3 Tlvresult . . . 707
8.672 pack_dms_ResetToFactoryDefaults_t Struct Reference . . . 707
8.672.1 Detailed Description . . . 707
8.672.2 Field Documentation . . . 707
8.672.2.1 spc . . . 707
8.673 pack_dms_SetActivationStatusCallback_t Struct Reference . . . 707
8.673.1 Detailed Description . . . 708
8.673.2 Field Documentation . . . 708
8.673.2.1 activationState . . . 708
8.674 pack_dms_SetCrashAction_t Struct Reference . . . 708
8.674.1 Detailed Description . . . 708
8.674.2 Field Documentation . . . 708
8.674.2.1 crashAction . . . 708
8.675 pack_dms_SetCustFeature_t Struct Reference . . . 708
8.675.1 Detailed Description . . . 709
8.675.2 Field Documentation . . . 710
8.675.2.1 DHCPRelayEnabled . . . 710
8.675.2.2 DisableIMSI . . . 710
8.675.2.3 GpsEnable . . . 710
8.675.2.4 GPSLPM . . . 710
8.675.2.5 GPSSel . . . 710
8.675.2.6 IPFamSupport . . . 710
8.675.2.7 IsVoiceEnabled . . . 710
8.675.2.8 RMAutoConnect . . . 710
8.675.2.9 SMSSupport . . . 710
8.676 pack_dms_SetCustFeaturesV2_t Struct Reference . . . 710
8.676.1 Detailed Description . . . 711
8.676.2 Field Documentation . . . 711
8.676.2.1 cust_id . . . 711
8.676.2.2 cust_value . . . 711
8.676.2.3 Tlvresult . . . 711
8.676.2.4 value_length . . . 711
8.677 pack_dms_SetEventReport_t Struct Reference . . . 711
8.677.1 Detailed Description . . . 711
8.677.2 Field Documentation . . . 711
8.677.2.1 mode . . . 711
8.678 pack_dms_SetIndicationRegister_t Struct Reference . . . 712
8.678.1 Detailed Description . . . 712
8.678.2 Field Documentation . . . 712
8.678.2.1 PSMCfgChangeInfo . . . 712

8.678.2.2 PSMStatus . . . 712
8.678.2.3 RptIMSCapability . . . 712
8.679 pack_dms_SetPower_t Struct Reference . . . 712
8.679.1 Detailed Description . . . 713
8.679.2 Field Documentation . . . 713
8.679.2.1 mode . . . 713
8.679.2.2 Tlvresult . . . 713
8.680 pack_dms_SetUSBComp_t Struct Reference . . . 713
8.680.1 Detailed Description . . . 713
8.680.2 Field Documentation . . . 714
8.680.2.1 Tlvresult . . . 714
8.680.2.2 USBComp . . . 714
8.681 pack_dms_SLQSDmsSwiIndicationRegister_t Struct Reference . . . 714
8.681.1 Detailed Description . . . 714
8.681.2 Field Documentation . . . 715
8.681.2.1 resetInfoInd . . . 715
8.682 pack_dms_SLQSSetPowerSaveModeConfig_t Struct Reference . . . 715
8.682.1 Detailed Description . . . 715
8.682.2 Field Documentation . . . 715
8.682.2.1 pActiveTimer . . . 715
8.682.2.2 pPeriodicUpdateTimer . . . 715
8.682.2.3 pPsmEnableState . . . 715
8.683 pack_dms_SLQSSwiGetCrashInfo_t Struct Reference . . . 715
8.683.1 Detailed Description . . . 716
8.683.2 Field Documentation . . . 716
8.683.2.1 clear . . . 716
8.684 pack_dms_SLQSSwiSetDyingGaspCfg_t Struct Reference . . . 716
8.684.1 Detailed Description . . . 716
8.684.2 Field Documentation . . . 716
8.684.2.1 pDestSMSContent . . . 716
8.684.2.2 pDestSMSNum . . . 716
8.685 pack_dms_SLQSSwiSetHostDevInfo_t Struct Reference . . . 716
8.685.1 Detailed Description . . . 717
8.685.2 Field Documentation . . . 717
8.685.2.1 hostID . . . 717
8.685.2.2 manString . . . 717
8.685.2.3 modelString . . . 717
8.685.2.4 plasmaIDString . . . 717
8.685.2.5 swVerString . . . 717
8.686 pack_dms_SLQSSwiSetOSInfo_t Struct Reference . . . 717

8.686.1 Detailed Description . . . 717
8.686.2 Field Documentation . . . 718
8.686.2.1 nameString . . . 718
8.686.2.2 versionString . . . 718
8.687 pack_dms_SwiSetEventReport_t Struct Reference . . . 718
8.687.1 Detailed Description . . . 718
8.687.2 Field Documentation . . . 718
8.687.2.1 pTempReport . . . 718
8.687.2.2 pUIMStatusReport . . . 718
8.687.2.3 pVoltReport . . . 718
8.688 pack_dms_SwiUimSelect_t Struct Reference . . . 719
8.688.1 Detailed Description . . . 719
8.688.2 Field Documentation . . . 719
8.688.2.1 uim_select . . . 719
8.689 pack_dms_UIMChangePIN_t Struct Reference . . . 719
8.689.1 Detailed Description . . . 719
8.689.2 Field Documentation . . . 720
8.689.2.1 id . . . 720
8.689.2.2 newValue . . . 720
8.689.2.3 oldValue . . . 720
8.690 pack_dms_UIMGetControlKeyStatus_t Struct Reference . . . 720
8.690.1 Detailed Description . . . 720
8.690.2 Field Documentation . . . 720
8.690.2.1 facility . . . 720
8.691 pack_dms_UIMGetICCID_t Struct Reference . . . 720
8.691.1 Detailed Description . . . 720
8.691.2 Field Documentation . . . 720
8.691.2.1 ParamPresenceMask . . . 721
8.691.2.2 Tlvresult . . . 721
8.692 pack_dms_UIMSetControlKeyProtection_t Struct Reference . . . 721
8.692.1 Detailed Description . . . 721
8.692.2 Field Documentation . . . 721
8.692.2.1 facility . . . 721
8.692.2.2 facilityCk . . . 721
8.692.2.3 facilityState . . . 721
8.693 pack_dms_UIMSetPINProtection_t Struct Reference . . . 721
8.693.1 Detailed Description . . . 722
8.693.2 Field Documentation . . . 722
8.693.2.1 bEnable . . . 722
8.693.2.2 id . . . 722

8.693.2.3 value . . . 722
8.694 pack_dms_UIMUnblockControlKey_t Struct Reference . . . 722
8.694.1 Detailed Description . . . 722
8.694.2 Field Documentation . . . 722
8.694.2.1 facility . . . 723
8.694.2.2 facilityCk . . . 723
8.695 pack_dms_UIMUnblockPIN_t Struct Reference . . . 723
8.695.1 Detailed Description . . . 723
8.695.2 Field Documentation . . . 723
8.695.2.1 id . . . 723
8.695.2.2 newPin . . . 723
8.695.2.3 pukValue . . . 723
8.696 pack_dms_UIMVerifyPIN_t Struct Reference . . . 723
8.696.1 Detailed Description . . . 723
8.696.2 Field Documentation . . . 724
8.696.2.1 id . . . 724
8.696.2.2 value . . . 724
8.697 pack_fms_GetImagesPreference_t Struct Reference . . . 724
8.697.1 Detailed Description . . . 724
8.697.2 Field Documentation . . . 724
8.697.2.1 Tlvresult . . . 724
8.698 pack_fms_GetStoredImages_t Struct Reference . . . 724
8.698.1 Detailed Description . . . 724
8.698.2 Field Documentation . . . 725
8.698.2.1 Tlvresult . . . 725
8.699 pack_fms_SetImagesPreference_t Struct Reference . . . 725
8.699.1 Detailed Description . . . 725
8.699.2 Field Documentation . . . 725
8.699.2.1 bForceDownload . . . 725
8.699.2.2 imageListSize . . . 725
8.699.2.3 modemindex . . . 725
8.699.2.4 pImageList . . . 725
8.699.2.5 Tlvresult . . . 725
8.700 pack_loc_Delete_Assist_Data_t Struct Reference . . . 725
8.700.1 Detailed Description . . . 726
8.700.2 Field Documentation . . . 726
8.700.2.1 pBdsSVInfo . . . 726
8.700.2.2 pCellDb . . . 726
8.700.2.3 pClkInfo . . . 726
8.700.2.4 pGnssData . . . 726

8.700.2.5 pSVInfo . . . 726
8.700.2.6 Tlvresult . . . 726
8.701 pack_loc_EventRegister_t Struct Reference . . . 726
8.701.1 Detailed Description . . . 727
8.701.2 Field Documentation . . . 729
8.701.2.1 eventRegister . . . 729
8.701.2.2 Tlvresult . . . 729
8.702 pack_loc_SetExtPowerState_t Struct Reference . . . 729
8.702.1 Detailed Description . . . 729
8.702.2 Field Documentation . . . 729
8.702.2.1 extPowerState . . . 729
8.702.2.2 Tlvresult . . . 729
8.703 pack_loc_SetOperationMode_t Struct Reference . . . 729
8.703.1 Detailed Description . . . 730
8.703.2 Field Documentation . . . 730
8.703.2.1 mode . . . 730
8.703.2.2 Tlvresult . . . 730
8.704 pack_loc_SLQSLOCGetBestAvailPos_t Struct Reference . . . 730
8.704.1 Detailed Description . . . 730
8.704.2 Field Documentation . . . 730
8.704.2.1 Tlvresult . . . 730
8.704.2.2 xid . . . 731
8.705 pack_loc_SLQSLOCGetServer_t Struct Reference . . . 731
8.705.1 Detailed Description . . . 731
8.705.2 Field Documentation . . . 731
8.705.2.1 has_serverAddrTypeMask . . . 731
8.705.2.2 serverAddrTypeMask . . . 731
8.705.2.3 serverType . . . 731
8.706 pack_loc_SLQSLOCInjectPosition_t Struct Reference . . . 731
8.706.1 Detailed Description . . . 732
8.706.2 Field Documentation . . . 735
8.706.2.1 altitudeSrcInfo . . . 735
8.706.2.2 altitudeWrtEllipsoid . . . 735
8.706.2.3 altitudeWrtMeanSeaLevel . . . 735
8.706.2.4 has_altitudeSrcInfo . . . 735
8.706.2.5 has_altitudeWrtEllipsoid . . . 735
8.706.2.6 has_altitudeWrtMeanSeaLevel . . . 735
8.706.2.7 has_horConfidence . . . 735
8.706.2.8 has_horReliability . . . 735
8.706.2.9 has_horUncCircular . . . 735

8.706.2.10 has_latitude . . . 735
8.706.2.11 has_longitude . . . 735
8.706.2.12 has_positionSrc . . . 735
8.706.2.13 has_rawHorConfidence . . . 735
8.706.2.14 has_rawHorUncCircular . . . 735
8.706.2.15 has_timestampAge . . . 735
8.706.2.16 has_timestampUtc . . . 735
8.706.2.17 has_vertConfidence . . . 735
8.706.2.18 has_vertRelicability . . . 736
8.706.2.19 has_vertUnc . . . 736
8.706.2.20 horConfidence . . . 736
8.706.2.21 horReliability . . . 736
8.706.2.22 horUncCircular . . . 736
8.706.2.23 latitude . . . 736
8.706.2.24 longitude . . . 736
8.706.2.25 positionSrc . . . 736
8.706.2.26 rawHorConfidence . . . 736
8.706.2.27 rawHorUncCircular . . . 736
8.706.2.28 timestampAge . . . 736
8.706.2.29 timestampUtc . . . 736
8.706.2.30 vertConfidence . . . 736
8.706.2.31 vertReliability . . . 736
8.706.2.32 vertUnc . . . 736
8.707 pack_loc_SLQSLOCInjectSensorData_t Struct Reference . . . 736
8.707.1 Detailed Description . . . 736
8.707.2 Field Documentation . . . 737
8.707.2.1 acceleroData . . . 737
8.707.2.2 acceleroTimeSrc . . . 737
8.707.2.3 accelTemp . . . 737
8.707.2.4 gyroData . . . 737
8.707.2.5 gyroTemp . . . 738
8.707.2.6 gyroTimeSrc . . . 738
8.707.2.7 has_acceleroTimeSrc . . . 738
8.707.2.8 has_accelTemp . . . 738
8.707.2.9 has_accleroData . . . 738
8.707.2.10 has_gyroData . . . 738
8.707.2.11 has_gyroTemp . . . 738
8.707.2.12 has_gyroTimeSrc . . . 738
8.707.2.13 has_opaqueId . . . 738
8.707.2.14 opaqueId . . . 738

8.708 pack_loc_SLQSLOCInjectUTCTime_t Struct Reference . . . 738
8.708.1 Detailed Description . . . 738
8.708.2 Field Documentation . . . 738
8.708.2.1 timeMsec . . . 738
8.708.2.2 timeUncMsec . . . 738
8.709 pack_loc_SLQSLOCSetCradleMountConfig_t Struct Reference . . . 738
8.709.1 Detailed Description . . . 739
8.709.2 Field Documentation . . . 739
8.709.2.1 confidence . . . 739
8.709.2.2 has_confidence . . . 739
8.709.2.3 state . . . 739
8.710 pack_loc_SLQSLOCSetServer_t Struct Reference . . . 739
8.710.1 Detailed Description . . . 739
8.710.2 Field Documentation . . . 740
8.710.2.1 pIPv4Config . . . 740
8.710.2.2 pIPv6Config . . . 740
8.710.2.3 pURLAddr . . . 740
8.710.2.4 serverType . . . 740
8.711 pack_loc_Start_t Struct Reference . . . 740
8.711.1 Detailed Description . . . 740
8.711.2 Field Documentation . . . 741
8.711.2.1 pApplicationInfo . . . 741
8.711.2.2 pConfigAltitudeAssumed . . . 741
8.711.2.3 pHorizontalAccuracyLvl . . . 741
8.711.2.4 pIntermediateReportState . . . 741
8.711.2.5 pMinIntervalTime . . . 741
8.711.2.6 pRecurrenceType . . . 742
8.711.2.7 SessionId . . . 742
8.711.2.8 Tlvresult . . . 742
8.712 pack_loc_Stop_t Struct Reference . . . 742
8.712.1 Detailed Description . . . 742
8.712.2 Field Documentation . . . 742
8.712.2.1 SessionId . . . 742
8.712.2.2 Tlvresult . . . 742
8.713 pack_nas_InitiateDomainAttach_t Struct Reference . . . 742
8.713.1 Detailed Description . . . 742
8.713.2 Field Documentation . . . 742
8.713.2.1 action . . . 743
8.714 pack_nas_PerformNetworkScanPCI_t Struct Reference . . . 743
8.714.1 Field Documentation . . . 743

8.714.1.1 pCiotOpModePref . . . 743
8.714.1.2 pLteM1BandPref . . . 743
8.714.1.3 pLteNB1BandPref . . . 743
8.714.1.4 pNetworkType . . . 743
8.714.1.5 pScanType . . . 743
8.715 pack_nas_SetACCOLC_t Struct Reference . . . 743
8.715.1 Detailed Description . . . 743
8.715.2 Field Documentation . . . 743
8.715.2.1 accolc . . . 743
8.715.2.2 spc . . . 743
8.716 pack_nas_SetCDMANetworkParameters_t Struct Reference . . . 743
8.716.1 Detailed Description . . . 744
8.716.2 Field Documentation . . . 745
8.716.2.1 pApplication . . . 745
8.716.2.2 pBroadcast . . . 745
8.716.2.3 pCustomSCP . . . 745
8.716.2.4 pForceRev0 . . . 745
8.716.2.5 pProtocol . . . 745
8.716.2.6 pRoaming . . . 745
8.716.2.7 pSPC . . . 745
8.717 pack_nas_SetNetworkPreference_t Struct Reference . . . 745
8.717.1 Detailed Description . . . 745
8.717.2 Field Documentation . . . 746
8.717.2.1 Duration . . . 746
8.717.2.2 TechnologyPref . . . 746
8.717.2.3 Tlvresult . . . 746
8.718 pack_nas_SLQSConfigSigInfo_t Struct Reference . . . 746
8.718.1 Detailed Description . . . 746
8.718.2 Field Documentation . . . 747
8.718.2.1 pECIOThresh . . . 747
8.718.2.2 pHDRSINRThresh . . . 747
8.718.2.3 pIOThresh . . . 747
8.718.2.4 pLTESigRptCfg . . . 747
8.718.2.5 pLTESNRThresh . . . 747
8.718.2.6 pRSRPThresh . . . 747
8.718.2.7 pRSRQThresh . . . 747
8.718.2.8 pRSSIThresh . . . 747
8.718.2.9 pTDSCDMASINRCONFThresh . . . 747
8.719 pack_nas_SLQSGetPLMNName_t Struct Reference . . . 747
8.719.1 Detailed Description . . . 748

8.719.2 Field Documentation . . . 748
8.719.2.1 mcc . . . 748
8.719.2.2 mnc . . . 748
8.719.2.3 pMncPcsStatus . . . 748
8.720 pack_nas_SLQSInitiateNetworkRegistration_t Struct Reference . . . 748
8.720.1 Detailed Description . . . 748
8.720.2 Field Documentation . . . 749
8.720.2.1 pChangeDuration . . . 749
8.720.2.2 pMncPcsDigitStatus . . . 749
8.720.2.3 pMNRInfo . . . 749
8.720.2.4 regAction . . . 749
8.721 pack_nas_SLQSNasConfigSigInfo2_t Struct Reference . . . 749
8.721.1 Detailed Description . . . 750
8.721.2 Field Documentation . . . 752
8.721.2.1 pCDMAECIODelta . . . 752
8.721.2.2 pCDMAECIOThresh . . . 752
8.721.2.3 pCDMARSSIDelta . . . 753
8.721.2.4 pCDMARSSIThresh . . . 753
8.721.2.5 pGSMRSSIDelta . . . 753
8.721.2.6 pGSMRSSIThresh . . . 753
8.721.2.7 pHDRECIODelta . . . 753
8.721.2.8 pHDRECIOThresh . . . 753
8.721.2.9 pHDRIODelta . . . 753
8.721.2.10 pHDRIOThresh . . . 753
8.721.2.11 pHDRRSSIDelta . . . 753
8.721.2.12 pHDRRSSIThresh . . . 753
8.721.2.13 pHDRSINRDelta . . . 753
8.721.2.14 pHDRSINRThresh . . . 753
8.721.2.15 pLTERSRPDelta . . . 753
8.721.2.16 pLTERSRPThresh . . . 753
8.721.2.17 pLTERSRQDelta . . . 753
8.721.2.18 pLTERSRQThresh . . . 753
8.721.2.19 pLTERSSIDelta . . . 753
8.721.2.20 pLTERSSIThresh . . . 753
8.721.2.21 pLTESigRptConfig . . . 753
8.721.2.22 pLTESNRDelta . . . 753
8.721.2.23 pLTESNRThresh . . . 753
8.721.2.24 pTDSCDMAECIODelta . . . 753
8.721.2.25 pTDSCDMAECIOThresh . . . 753
8.721.2.26 pTDSCDMARSCPDelta . . . 753

8.721.2.27 pTDSCDMARSCPThresh . . . 753
8.721.2.28 pTDSCDMARSSIDelta . . . 753
8.721.2.29 pTDSCDMARSSIThresh . . . 753
8.721.2.30 pTDSCDMASINRDelta . . . 753
8.721.2.31 pTDSCDMASINRThresh . . . 754
8.721.2.32 pWCDMAECIODelta . . . 754
8.721.2.33 pWCDMAECIOThresh . . . 754
8.721.2.34 pWCDMARSSIDelta . . . 754
8.721.2.35 pWCDMARSSIThresh . . . 754
8.722 pack_nas_SLQSNasGet3GPP2Subscription_t Struct Reference . . . 754
8.722.1 Detailed Description . . . 754
8.722.2 Field Documentation . . . 754
8.722.2.1 namID . . . 754
8.723 pack_nas_SLQSNASGeteDRXParamsExt_t Struct Reference . . . 754
8.723.1 Detailed Description . . . 754
8.723.2 Field Documentation . . . 755
8.723.2.1 pEdrxRAT . . . 755
8.723.2.2 pLteOpMode . . . 755
8.724 pack_nas_SLQSNasGetTxRxInfo_t Struct Reference . . . 755
8.724.1 Detailed Description . . . 755
8.724.2 Field Documentation . . . 756
8.724.2.1 radio_if . . . 756
8.725 pack_nas_SLQSNasIndicationRegisterExt_t Struct Reference . . . 756
8.725.1 Detailed Description . . . 756
8.725.2 Field Documentation . . . 758
8.725.2.1 pDDTMInd . . . 758
8.725.2.2 pDualStandByPrefInd . . . 758
8.725.2.3 pEdrxChangeInfoInd . . . 758
8.725.2.4 pErrorRateInd . . . 758
8.725.2.5 pHDRNewUATIAssInd . . . 758
8.725.2.6 pHDRSessionCloseInd . . . 758
8.725.2.7 pLTECphyCa . . . 758
8.725.2.8 pManagedRoamingInd . . . 759
8.725.2.9 pNetworkRejectInd . . . 759
8.725.2.10 pNetworkTimeInd . . . 759
8.725.2.11 pServingSystemInd . . . 759
8.725.2.12 pSignalStrengthInd . . . 759
8.725.2.13 pSubscriptionInfoInd . . . 759
8.725.2.14 pSuppressSysInfoInd . . . 759
8.725.2.15 pSysInfoInd . . . 759

8.725.2.16 pSystemSelectionInd . . . 759
8.726 pack_nas_SLQSNASSeteDRXParams_t Struct Reference . . . 759
8.726.1 Detailed Description . . . 759
8.726.2 Field Documentation . . . 760
8.726.2.1 pCycleLen . . . 760
8.726.2.2 pEdrxCiotLteMode . . . 760
8.726.2.3 pEdrxEnable . . . 760
8.726.2.4 pEdrxRatType . . . 760
8.726.2.5 pPagingTimeWindow . . . 760
8.727 pack_nas_SLQSNasSwiIndicationRegister_t Struct Reference . . . 760
8.727.1 Detailed Description . . . 761
8.727.2 Field Documentation . . . 761
8.727.2.1 gsmUmtsDl . . . 761
8.727.2.2 gsmUmtsUl . . . 761
8.727.2.3 lteEmmDl . . . 761
8.727.2.4 lteEmmUl . . . 761
8.727.2.5 lteEsmDl . . . 761
8.727.2.6 lteEsmUl . . . 762
8.727.2.7 pRankIndicatorInd . . . 762
8.727.2.8 pTimer . . . 762
8.728 pack_nas_SLQSNASSwiSetChannelLock_t Struct Reference . . . 762
8.728.1 Detailed Description . . . 762
8.728.2 Field Documentation . . . 762
8.728.2.1 pLteEARFCN . . . 762
8.728.2.2 pLtePCI . . . 762
8.728.2.3 pWcdmaUARFCN . . . 762
8.729 pack_nas_SLQSSetBandPreference_t Struct Reference . . . 762
8.729.1 Detailed Description . . . 762
8.729.2 Field Documentation . . . 763
8.729.2.1 bandPref . . . 764
8.730 pack_nas_SLQSSetSignalStrengthsCallback_t Struct Reference . . . 764
8.730.1 Detailed Description . . . 764
8.730.2 Field Documentation . . . 764
8.730.2.1 bEnable . . . 764
8.730.2.2 pSigIndReq . . . 764
8.731 pack_nas_SLQSSetSysSelectionPref_t Struct Reference . . . 764
8.731.1 Detailed Description . . . 764
8.731.2 Field Documentation . . . 769
8.731.2.1 pAcqOrderPref . . . 769
8.731.2.2 pBandPref . . . 769

8.731.2.3 pChgDuration . . . 769
8.731.2.4 pCSGID . . . 769
8.731.2.5 pEmerMode . . . 769
8.731.2.6 pGWAcqOrderPref . . . 769
8.731.2.7 pLTEBandPref . . . 769
8.731.2.8 pMNCIncPCSDigStat . . . 769
8.731.2.9 pModePref . . . 769
8.731.2.10 pNetSelPref . . . 769
8.731.2.11 pPRLPref . . . 769
8.731.2.12 pRAT . . . 769
8.731.2.13 pRoamPref . . . 769
8.731.2.14 pSrvDomainPref . . . 769
8.731.2.15 pSrvRegRestriction . . . 770
8.731.2.16 pTdscdmaBandPref . . . 770
8.732 pack_nas_SLQSSetSysSelectionPrefExt_t Struct Reference . . . 770
8.732.1 Detailed Description . . . 770
8.732.2 Field Documentation . . . 779
8.732.2.1 pAcqOrderPref . . . 779
8.732.2.2 pBandPref . . . 779
8.732.2.3 pChgDuration . . . 779
8.732.2.4 pCiotAcqOrderPref . . . 779
8.732.2.5 pCiotLteOpMode . . . 779
8.732.2.6 pCiotLteOpModePref . . . 779
8.732.2.7 pCSGID . . . 779
8.732.2.8 pEmerMode . . . 779
8.732.2.9 pGWAcqOrderPref . . . 779
8.732.2.10 pLTEBandPref . . . 779
8.732.2.11 pLTEBandPrefExt . . . 779
8.732.2.12 pLteM1BandPref . . . 779
8.732.2.13 pLteNb1BandPref . . . 779
8.732.2.14 pMNCIncPCSDigStat . . . 779
8.732.2.15 pModePref . . . 779
8.732.2.16 pNetSelPref . . . 779
8.732.2.17 pNr5gBandPref . . . 779
8.732.2.18 pPRLPref . . . 780
8.732.2.19 pRAT . . . 780
8.732.2.20 pRoamPref . . . 780
8.732.2.21 pSrvDomainPref . . . 780
8.732.2.22 pSrvRegRestriction . . . 780
8.732.2.23 pTdscdmaBandPref . . . 780

8.733 pack_nas_SLQSSwiPSDetach_t Struct Reference . . . 780
8.733.1 Detailed Description . . . 780
8.733.2 Field Documentation . . . 780
8.733.2.1 pDetachAction . . . 780
8.734 pack_pds_PDSInjectTimeReference_t Struct Reference . . . 780
8.734.1 Detailed Description . . . 780
8.734.2 Field Documentation . . . 781
8.734.2.1 systemDiscontinuities . . . 781
8.734.2.2 systemTime . . . 781
8.735 pack_pds_ResetPDSData_t Struct Reference . . . 781
8.735.1 Detailed Description . . . 781
8.735.2 Field Documentation . . . 781
8.735.2.1 pCellDataMask . . . 782
8.735.2.2 pGPSDataMask . . . 782
8.736 pack_pds_SetEventReportCallback_t Struct Reference . . . 782
8.736.1 Detailed Description . . . 782
8.736.2 Field Documentation . . . 782
8.736.2.1 posDataNmea . . . 782
8.736.2.2 rptPosData . . . 782
8.737 pack_pds_SetPDSDefaults_t Struct Reference . . . 782
8.737.1 Detailed Description . . . 782
8.737.2 Field Documentation . . . 783
8.737.2.1 accuracy . . . 783
8.737.2.2 interval . . . 783
8.737.2.3 operation . . . 783
8.737.2.4 timeout . . . 783
8.738 pack_pds_SetPDSState_t Struct Reference . . . 783
8.738.1 Detailed Description . . . 783
8.738.2 Field Documentation . . . 783
8.738.2.1 enable . . . 783
8.739 pack_pds_SetPortAutomaticTracking_t Struct Reference . . . 783
8.739.1 Detailed Description . . . 784
8.739.2 Field Documentation . . . 784
8.739.2.1 bAuto . . . 784
8.740 pack_pds_SetServiceAutomaticTracking_t Struct Reference . . . 784
8.740.1 Detailed Description . . . 784
8.740.2 Field Documentation . . . 784
8.740.2.1 bAuto . . . 784
8.741 pack_pds_SetXTRAAutomaticDownload_t Struct Reference . . . 784
8.741.1 Detailed Description . . . 785

8.741.2 Field Documentation . . . 785
8.741.2.1 bEnabled . . . 785
8.741.2.2 interval . . . 785
8.742 pack_pds_SetXTRANetwork_t Struct Reference . . . 785
8.742.1 Detailed Description . . . 785
8.742.2 Field Documentation . . . 785
8.742.2.1 preference . . . 785
8.743 pack_pds_SLQSGetAGPSConfig_t Struct Reference . . . 785
8.743.1 Detailed Description . . . 786
8.743.2 Field Documentation . . . 786
8.743.2.1 pNetworkMode . . . 786
8.744 pack_pds_SLQSPDSInjectAbsoluteTimeReference_t Struct Reference . . . 786
8.744.1 Detailed Description . . . 786
8.744.2 Field Documentation . . . 786
8.744.2.1 forceFlag . . . 786
8.744.2.2 timeBase . . . 786
8.744.2.3 timeMsec . . . 787
8.744.2.4 timeUncMsec . . . 787
8.745 pack_pds_SLQSPDSInjectPositionData_t Struct Reference . . . 787
8.745.1 Detailed Description . . . 787
8.745.2 Field Documentation . . . 788
8.745.2.1 pAltitudeWrtEllipsoid . . . 788
8.745.2.2 pAltitudeWrtSealevel . . . 788
8.745.2.3 pHorizontalConfidence . . . 788
8.745.2.4 pHorizontalUncCircular . . . 788
8.745.2.5 pLatitude . . . 788
8.745.2.6 pLongitude . . . 788
8.745.2.7 pPositionSource . . . 788
8.745.2.8 pTimeStamp . . . 788
8.745.2.9 pTimeType . . . 788
8.745.2.10 pVerticalConfidence . . . 788
8.745.2.11 pVerticalUnc . . . 789
8.746 pack_pds_SLQSSetAGPSConfig_t Struct Reference . . . 789
8.746.1 Detailed Description . . . 789
8.746.2 Field Documentation . . . 789
8.746.2.1 pNetworkMode . . . 789
8.746.2.2 pServerAddress . . . 789
8.746.2.3 pServerPort . . . 789
8.746.2.4 pServerURL . . . 789
8.746.2.5 pServerURLLength . . . 789

8.747 pack_pds_SLQSSetPositionMethodState_t Struct Reference . . . 789
8.747.1 Detailed Description . . . 790
8.747.2 Field Documentation . . . 790
8.747.2.1 pWifiState . . . 790
8.747.2.2 pXtraDataState . . . 790
8.747.2.3 pXtraTimeState . . . 790
8.748 pack_pds_StartPDSTrackingSessionExt_t Struct Reference . . . 790
8.748.1 Detailed Description . . . 790
8.748.2 Field Documentation . . . 791
8.748.2.1 fixAccuracy . . . 791
8.748.2.2 fixCount . . . 791
8.748.2.3 fixInterval . . . 791
8.748.2.4 fixTimeout . . . 791
8.748.2.5 sessionControl . . . 791
8.748.2.6 sessionOperation . . . 791
8.748.2.7 sessionServerOption . . . 791
8.748.2.8 sessionType . . . 791
8.749 pack_qmi_t Struct Reference . . . 791
8.749.1 Detailed Description . . . 792
8.749.2 Field Documentation . . . 792
8.749.2.1 msgid . . . 792
8.749.2.2 svc . . . 792
8.749.2.3 timeout . . . 792
8.749.2.4 xid . . . 792
8.750 pack_qos_BindDataPort_t Struct Reference . . . 792
8.750.1 Detailed Description . . . 792
8.750.2 Field Documentation . . . 793
8.750.2.1 pMuxID . . . 793
8.750.2.2 pPeripheralEndPointID . . . 793
8.750.2.3 pSIODataPort . . . 793
8.751 pack_qos_SLQSQosSwiReadApnExtraParams_t Struct Reference . . . 793
8.751.1 Detailed Description . . . 793
8.751.2 Field Documentation . . . 793
8.751.2.1 apnId . . . 793
8.752 pack_qos_SLQSQosSwiReadDataStats_t Struct Reference . . . 793
8.752.1 Detailed Description . . . 793
8.752.2 Field Documentation . . . 793
8.752.2.1 apnId . . . 793
8.753 pack_qos_SLQSSetQosEventCallback_t Struct Reference . . . 793
8.753.1 Detailed Description . . . 794

8.753.2 Field Documentation . . . 794
8.753.2.1 enable . . . 794
8.754 pack_rms_SetSMSWake_t Struct Reference . . . 794
8.754.1 Detailed Description . . . 794
8.754.2 Field Documentation . . . 794
8.754.2.1 enabled . . . 794
8.754.2.2 wake_mask . . . 794
8.755 pack_sar_SLQSSetRfSarState_t Struct Reference . . . 794
8.755.1 Detailed Description . . . 795
8.755.2 Field Documentation . . . 795
8.755.2.1 RfSarState . . . 795
8.756 pack_sms_SaveSMS_t Struct Reference . . . 795
8.756.1 Detailed Description . . . 795
8.756.2 Field Documentation . . . 796
8.756.2.1 messageFormat . . . 796
8.756.2.2 messageSize . . . 796
8.756.2.3 pMessage . . . 796
8.756.2.4 storageType . . . 796
8.757 pack_sms_SendSMS_t Struct Reference . . . 796
8.757.1 Detailed Description . . . 796
8.757.2 Field Documentation . . . 796
8.757.2.1 messageFormat . . . 796
8.757.2.2 messageSize . . . 796
8.757.2.3 pLinktimer . . . 797
8.757.2.4 pMessage . . . 797
8.758 pack_sms_SetNewSMSCallback_t Struct Reference . . . 797
8.758.1 Detailed Description . . . 797
8.758.2 Field Documentation . . . 797
8.758.2.1 status . . . 797
8.759 pack_sms_SetSMSCAddress_t Struct Reference . . . 797
8.759.1 Detailed Description . . . 797
8.759.2 Field Documentation . . . 797
8.759.2.1 pSMSCAddress . . . 797
8.759.2.2 pSMSCType . . . 797
8.760 pack_sms_SLQSDeleteSMS_t Struct Reference . . . 797
8.760.1 Detailed Description . . . 798
8.760.2 Field Documentation . . . 798
8.760.2.1 pMessageIndex . . . 798
8.760.2.2 pMessageMode . . . 798
8.760.2.3 pMessageTag . . . 798

8.760.2.4 storageType . . . 798
8.761 pack_sms_SLQSGetSMS_t Struct Reference . . . 798
8.761.1 Detailed Description . . . 799
8.761.2 Field Documentation . . . 799
8.761.2.1 messageIndex . . . 799
8.761.2.2 pMessageMode . . . 799
8.761.2.3 storageType . . . 799
8.762 pack_sms_SLQSGetSmsBroadcastConfig_t Struct Reference . . . 799
8.762.1 Detailed Description . . . 799
8.762.2 Field Documentation . . . 799
8.762.2.1 mode . . . 799
8.763 pack_sms_SLQSGetSMSList_t Struct Reference . . . 799
8.763.1 Detailed Description . . . 800
8.763.2 Field Documentation . . . 800
8.763.2.1 pMessageMode . . . 800
8.763.2.2 pRequestedTag . . . 800
8.763.2.3 storageType . . . 800
8.764 pack_sms_SLQSModifySMSStatus_t Struct Reference . . . 800
8.764.1 Detailed Description . . . 800
8.764.2 Field Documentation . . . 801
8.764.2.1 messageIndex . . . 801
8.764.2.2 messageTag . . . 801
8.764.2.3 pMessageMode . . . 801
8.764.2.4 storageType . . . 801
8.765 pack_sms_SLQSSendAsyncSMS_t Struct Reference . . . 801
8.765.1 Detailed Description . . . 801
8.765.2 Field Documentation . . . 801
8.765.2.1 pSendSmsParams . . . 801
8.766 pack_sms_SLQSSetIndicationRegister_t Struct Reference . . . 801
8.766.1 Detailed Description . . . 802
8.766.2 Field Documentation . . . 802
8.766.2.1 pSetIndicationRegReq . . . 802
8.767 pack_sms_SLQSSetSmsBroadcastActivation_t Struct Reference . . . 802
8.767.1 Detailed Description . . . 802
8.767.2 Field Documentation . . . 802
8.767.2.1 broadcastActivate . . . 802
8.767.2.2 mode . . . 802
8.768 pack_sms_SLQSSetSmsBroadcastConfig_t Struct Reference . . . 802
8.768.1 Detailed Description . . . 803
8.768.2 Field Documentation . . . 803

8.768.2.1 mode . . . 803
8.768.2.2 pBroadcastConfig . . . 803
8.768.2.3 pCDMABroadcastConfig . . . 803
8.769 pack_sms_SLQSSetSmsStorage_t Struct Reference . . . 803
8.769.1 Detailed Description . . . 803
8.769.2 Field Documentation . . . 803
8.769.2.1 smsStorage . . . 804
8.770 pack_sms_SLQSSmsGetMaxStorageSize_t Struct Reference . . . 804
8.770.1 Detailed Description . . . 804
8.770.2 Field Documentation . . . 804
8.770.2.1 pMaxStorageSizeReq . . . 804
8.771 pack_sms_SLQSSmsSetRoutes_t Struct Reference . . . 804
8.771.1 Detailed Description . . . 804
8.771.2 Field Documentation . . . 804
8.771.2.1 pSetRoutesReq . . . 804
8.772 pack_swidms_SLQSSwiDmsSetHWWatchdog_t Struct Reference . . . 804
8.772.1 Detailed Description . . . 805
8.772.2 Field Documentation . . . 805
8.772.2.1 enable . . . 805
8.772.2.2 resetDelay . . . 805
8.772.2.3 timeout . . . 805
8.773 pack_swidms_SLQSSwiDmsSetMTU_t Struct Reference . . . 805
8.773.1 Detailed Description . . . 805
8.773.2 Field Documentation . . . 805
8.773.2.1 MTUSize . . . 805
8.774 pack_swidms_SLQSSwiDmsSetUsbComp_t Struct Reference . . . 805
8.774.1 Detailed Description . . . 806
8.774.2 Field Documentation . . . 806
8.774.2.1 CfgValue . . . 806
8.775 pack_swidms_SLQSSwiDmsSetUsbNetNum_t Struct Reference . . . 806
8.775.1 Detailed Description . . . 806
8.775.2 Field Documentation . . . 807
8.775.2.1 nUsbNetNum . . . 807
8.776 pack_swiloc_SwiLocSetAutoStart_t Struct Reference . . . 807
8.776.1 Detailed Description . . . 807
8.776.2 Field Documentation . . . 808
8.776.2.1 fix_rate . . . 808
8.776.2.2 fix_type . . . 808
8.776.2.3 function . . . 808
8.776.2.4 max_dist . . . 808

8.776.2.5 max_time . . . 808
8.776.2.6 set_fix_rate . . . 808
8.776.2.7 set_fix_type . . . 808
8.776.2.8 set_function . . . 808
8.776.2.9 set_max_dist . . . 808
8.776.2.10 set_max_time . . . 808
8.777 pack_swioma_SLQSOMADMCancelSession_t Struct Reference . . . 808
8.777.1 Detailed Description . . . 809
8.777.2 Field Documentation . . . 809
8.777.2.1 sessionType . . . 809
8.778 pack_swioma_SLQSOMADMGetSessionInfo_t Struct Reference . . . 809
8.778.1 Detailed Description . . . 809
8.778.2 Field Documentation . . . 809
8.778.2.1 SessionType . . . 809
8.779 pack_swioma_SLQSOMADMSendSelection_t Struct Reference . . . 809
8.779.1 Detailed Description . . . 809
8.779.2 Field Documentation . . . 810
8.779.2.1 pDeferTime . . . 810
8.779.2.2 pRejectReason . . . 810
8.779.2.3 selection . . . 810
8.780 pack_swioma_SLQSOMADMSetSettings_t Struct Reference . . . 810
8.780.1 Detailed Description . . . 810
8.780.2 Field Documentation . . . 811
8.780.2.1 FOTAdownload . . . 811
8.780.2.2 FOTAUpdate . . . 811
8.780.2.3 pAutosdm . . . 811
8.780.2.4 pFwAutoCheck . . . 811
8.781 pack_swioma_SLQSOMADMStartSession_t Struct Reference . . . 811
8.781.1 Detailed Description . . . 811
8.781.2 Field Documentation . . . 811
8.781.2.1 sessionType . . . 811
8.782 pack_uim_ChangePin_t Struct Reference . . . 811
8.782.1 Detailed Description . . . 812
8.782.2 Field Documentation . . . 812
8.782.2.1 changePIN . . . 812
8.782.2.2 EncryptedPIN1 . . . 812
8.782.2.3 pIndicationToken . . . 812
8.782.2.4 pKeyReferenceID . . . 812
8.782.2.5 sessionInfo . . . 812
8.782.2.6 Tlvresult . . . 812

8.783 pack_uim_ReadTransparent_t Struct Reference . . . 812
8.783.1 Detailed Description . . . 813
8.783.2 Field Documentation . . . 813
8.783.2.1 fileIndex . . . 813
8.783.2.2 pEncryptData . . . 813
8.783.2.3 pIndicationToken . . . 813
8.783.2.4 readTransparent . . . 813
8.783.2.5 sessionInfo . . . 813
8.783.2.6 Tlvresult . . . 813
8.784 pack_uim_SetPinProtection_t Struct Reference . . . 814
8.784.1 Detailed Description . . . 814
8.784.2 Field Documentation . . . 814
8.784.2.1 EncryptedPIN1 . . . 814
8.784.2.2 pIndicationToken . . . 814
8.784.2.3 pinProtection . . . 814
8.784.2.4 pKeyReferenceID . . . 814
8.784.2.5 sessionInfo . . . 814
8.784.2.6 Tlvresult . . . 815
8.785 pack_uim_SLQSUIMAuthenticate_t Struct Reference . . . 815
8.785.1 Detailed Description . . . 815
8.785.2 Field Documentation . . . 815
8.785.2.1 authData . . . 815
8.785.2.2 pIndicationToken . . . 815
8.785.2.3 sessionInfo . . . 815
8.786 pack_uim_SLQSUIMDepersonalization_t Struct Reference . . . 815
8.786.1 Detailed Description . . . 815
8.786.2 Field Documentation . . . 816
8.786.2.1 depersonilisationInfo . . . 816
8.787 pack_uim_SLQSUIMEventRegister_t Struct Reference . . . 816
8.787.1 Detailed Description . . . 816
8.787.2 Field Documentation . . . 816
8.787.2.1 eventMask . . . 816
8.788 pack_uim_SLQSUIMGetConfiguration_t Struct Reference . . . 816
8.788.1 Detailed Description . . . 816
8.788.2 Field Documentation . . . 816
8.788.2.1 pConfigurationMask . . . 816
8.789 pack_uim_SLQSUIMGetFileAttributes_t Struct Reference . . . 817
8.789.1 Detailed Description . . . 817
8.789.2 Field Documentation . . . 817
8.789.2.1 fileIndex . . . 817

8.789.2.2 pIndicationToken . . . 817
8.789.2.3 sessionInfo . . . 817
8.790 pack_uim_SLQSUIMPowerDown_t Struct Reference . . . 817
8.790.1 Detailed Description . . . 817
8.790.2 Field Documentation . . . 818
8.790.2.1 slot . . . 818
8.791 pack_uim_SLQSUIMPowerUp_t Struct Reference . . . 818
8.791.1 Detailed Description . . . 818
8.791.2 Field Documentation . . . 818
8.791.2.1 pIgnoreHotSwapSwitch . . . 818
8.791.2.2 slot . . . 818
8.792 pack_uim_SLQSUIMRefreshComplete_t Struct Reference . . . 818
8.792.1 Detailed Description . . . 818
8.792.2 Field Documentation . . . 819
8.792.2.1 refreshComplete . . . 819
8.792.2.2 sessionInfo . . . 819
8.793 pack_uim_SLQSUIMRefreshGetLastEvent_t Struct Reference . . . 819
8.793.1 Detailed Description . . . 819
8.793.2 Field Documentation . . . 819
8.793.2.1 sessionInfo . . . 819
8.794 pack_uim_SLQSUIMRefreshOK_t Struct Reference . . . 819
8.794.1 Detailed Description . . . 819
8.794.2 Field Documentation . . . 820
8.794.2.1 OKtoRefresh . . . 820
8.794.2.2 sessionInfo . . . 820
8.795 pack_uim_SLQSUIMRefreshRegister_t Struct Reference . . . 820
8.795.1 Detailed Description . . . 820
8.795.2 Field Documentation . . . 820
8.795.2.1 regRefresh . . . 820
8.795.2.2 sessionInfo . . . 820
8.796 pack_uim_SLQSUIMSwitchSlot_t Struct Reference . . . 820
8.796.1 Detailed Description . . . 820
8.796.2 Field Documentation . . . 821
8.796.2.1 bLogicalSlot . . . 821
8.796.2.2 ulPhysicalSlot . . . 821
8.797 pack_uim_UnblockPin_t Struct Reference . . . 821
8.797.1 Detailed Description . . . 821
8.797.2 Field Documentation . . . 822
8.797.2.1 EncryptedPIN1 . . . 822
8.797.2.2 pIndicationToken . . . 822

8.797.2.3 pinProtection . . . 822
8.797.2.4 pKeyReferenceID . . . 822
8.797.2.5 sessionInfo . . . 822
8.797.2.6 Tlvresult . . . 822
8.798 pack_uim_VerifyPin_t Struct Reference . . . 822
8.798.1 Detailed Description . . . 822
8.798.2 Field Documentation . . . 823
8.798.2.1 pEncryptedPIN1 . . . 823
8.798.2.2 pIndicationToken . . . 823
8.798.2.3 pKeyReferenceID . . . 823
8.798.2.4 sessionInfo . . . 823
8.798.2.5 Tlvresult . . . 823
8.798.2.6 verifyPIN . . . 823
8.799 pack_voice_AnswerUSSD_t Struct Reference . . . 823
8.799.1 Detailed Description . . . 823
8.799.2 Field Documentation . . . 824
8.799.2.1 pInfo . . . 824
8.800 pack_voice_OriginateUSSD_t Struct Reference . . . 824
8.800.1 Detailed Description . . . 824
8.800.2 Field Documentation . . . 824
8.800.2.1 pInfo . . . 824
8.801 pack_voice_SLQSOriginateUSSD_t Struct Reference . . . 824
8.801.1 Detailed Description . . . 824
8.801.2 Field Documentation . . . 825
8.801.2.1 ussData . . . 825
8.801.2.2 ussDCS . . . 825
8.801.2.3 ussLen . . . 825
8.802 pack_voice_SLQSVoiceALSSelectLine_t Struct Reference . . . 825
8.802.1 Detailed Description . . . 825
8.802.2 Field Documentation . . . 825
8.802.2.1 lineValue . . . 825
8.803 pack_voice_SLQSVoiceALSSetLineSwitching_t Struct Reference . . . 825
8.803.1 Detailed Description . . . 825
8.803.2 Field Documentation . . . 825
8.803.2.1 switchOption . . . 825
8.804 pack_voice_SLQSVoiceAnswerCall_t Struct Reference . . . 826
8.804.1 Detailed Description . . . 826
8.804.2 Field Documentation . . . 826
8.804.2.1 pCallId . . . 826
8.805 pack_voice_SLQSVoiceBindSubscription_t Struct Reference . . . 826

8.805.1 Detailed Description . . . 826
8.805.2 Field Documentation . . . 826
8.805.2.1 subsType . . . 826
8.806 pack_voice_SLQSVoiceBurstDTMF_t Struct Reference . . . 826
8.806.1 Detailed Description . . . 827
8.806.2 Field Documentation . . . 827
8.806.2.1 BurstDTMFInfo . . . 827
8.806.2.2 pBurstDTMFLengths . . . 827
8.807 pack_voice_SLQSVoiceDialCall_t Struct Reference . . . 827
8.807.1 Detailed Description . . . 827
8.807.2 Field Documentation . . . 828
8.807.2.1 callNumber . . . 828
8.807.2.2 pCallPartySubAdd . . . 828
8.807.2.3 pCallType . . . 828
8.807.2.4 pCLIRType . . . 828
8.807.2.5 pCUGInfo . . . 828
8.807.2.6 pEmergencyCategory . . . 829
8.807.2.7 pSvcType . . . 829
8.807.2.8 pUUSInFo . . . 829
8.808 pack_voice_SLQSVoiceEndCall_t Struct Reference . . . 829
8.808.1 Detailed Description . . . 829
8.808.2 Field Documentation . . . 829
8.808.2.1 pCallId . . . 829
8.809 pack_voice_SLQSVoiceGetCallBarring_t Struct Reference . . . 829
8.809.1 Detailed Description . . . 829
8.809.2 Field Documentation . . . 830
8.809.2.1 pSvcClass . . . 830
8.809.2.2 reason . . . 830
8.810 pack_voice_SLQSVoiceGetCallForwardingStatus_t Struct Reference . . . 830
8.810.1 Detailed Description . . . 830
8.810.2 Field Documentation . . . 831
8.810.2.1 pSvcClass . . . 831
8.810.2.2 Reason . . . 831
8.811 pack_voice_SLQSVoiceGetCallInfo_t Struct Reference . . . 831
8.811.1 Detailed Description . . . 831
8.811.2 Field Documentation . . . 831
8.811.2.1 callID . . . 831
8.812 pack_voice_SLQSVoiceGetCallWaiting_t Struct Reference . . . 831
8.812.1 Detailed Description . . . 832
8.812.2 Field Documentation . . . 832

8.812.2.1 pSvcClass . . . 832
8.813 pack_voice_SLQSVoiceGetConfig_t Struct Reference . . . 832
8.813.1 Detailed Description . . . 832
8.813.2 Field Documentation . . . 833
8.813.2.1 pAirTimer . . . 833
8.813.2.2 pAMRStatus . . . 833
8.813.2.3 pAutoAnswer . . . 833
8.813.2.4 pNamID . . . 833
8.813.2.5 pPrefVoicePrivacy . . . 833
8.813.2.6 pPrefVoiceSO . . . 833
8.813.2.7 pRoamTimer . . . 833
8.813.2.8 pTTYMode . . . 833
8.813.2.9 pVoiceDomainPref . . . 833
8.814 pack_voice_SLQSVoiceIndicationRegister_t Struct Reference . . . 834
8.814.1 Detailed Description . . . 834
8.814.2 Field Documentation . . . 834
8.814.2.1 pRegDTMFEvents . . . 834
8.814.2.2 pRegVoicePrivacyEvents . . . 834
8.814.2.3 pSuppsNotifEvents . . . 834
8.815 pack_voice_SLQSVoiceManageCalls_t Struct Reference . . . 834
8.815.1 Detailed Description . . . 835
8.815.2 Field Documentation . . . 835
8.815.2.1 pCallID . . . 835
8.815.2.2 SUPSType . . . 835
8.816 pack_voice_SLQSVoiceOrigUSSDNoWait_t Struct Reference . . . 835
8.816.1 Detailed Description . . . 835
8.816.2 Field Documentation . . . 836
8.816.2.1 USSInformation . . . 836
8.817 pack_voice_SLQSVoiceSendFlash_t Struct Reference . . . 836
8.817.1 Detailed Description . . . 836
8.817.2 Field Documentation . . . 836
8.817.2.1 pCallID . . . 836
8.817.2.2 pFlashPayLd . . . 836
8.817.2.3 pFlashType . . . 836
8.818 pack_voice_SLQSVoiceSetCallBarringPassword_t Struct Reference . . . 836
8.818.1 Detailed Description . . . 837
8.818.2 Field Documentation . . . 837
8.818.2.1 newPasswd . . . 837
8.818.2.2 newPasswdAgain . . . 837
8.818.2.3 oldPasswd . . . 837

8.818.2.4 Reason . . . 837
8.819 pack_voice_SLQSVoiceSetConfig_t Struct Reference . . . 837
8.819.1 Detailed Description . . . 838
8.819.2 Field Documentation . . . 839
8.819.2.1 pAirTimerConfig . . . 839
8.819.2.2 pAutoAnswer . . . 839
8.819.2.3 pPrefVoiceDomain . . . 839
8.819.2.4 pPrefVoiceSO . . . 839
8.819.2.5 pRoamTimerConfig . . . 839
8.819.2.6 pTTYMode . . . 839
8.820 pack_voice_SLQSVoiceSetPreferredPrivacy_t Struct Reference . . . 839
8.820.1 Detailed Description . . . 839
8.820.2 Field Documentation . . . 839
8.820.2.1 privacyPref . . . 839
8.821 pack_voice_SLQSVoiceSetSUPSService_t Struct Reference . . . 839
8.821.1 Detailed Description . . . 839
8.821.2 Field Documentation . . . 841
8.821.2.1 pCallBarringPasswd . . . 841
8.821.2.2 pCallForwardingNumber . . . 841
8.821.2.3 pCallFwdTypeAndPlan . . . 841
8.821.2.4 pServiceClass . . . 841
8.821.2.5 pTimerVal . . . 841
8.821.2.6 reason . . . 841
8.821.2.7 voiceSvc . . . 841
8.822 pack_voice_SLQSVoiceStartContDTMF_t Struct Reference . . . 841
8.822.1 Detailed Description . . . 841
8.822.2 Field Documentation . . . 842
8.822.2.1 DTMFdigit . . . 842
8.822.2.2 pCallID . . . 842
8.823 pack_voice_SLQSVoiceStopContDTMF_t Struct Reference . . . 842
8.823.1 Detailed Description . . . 842
8.823.2 Field Documentation . . . 842
8.823.2.1 callID . . . 842
8.824 pack_wds_DHCPv4ClientLeaseChange_t Struct Reference . . . 842
8.824.1 Detailed Description . . . 842
8.824.2 Field Documentation . . . 843
8.824.2.1 pEnableNotification . . . 843
8.825 pack_wds_GetDefaultProfile_t Struct Reference . . . 843
8.825.1 Detailed Description . . . 843
8.825.2 Field Documentation . . . 843

8.825.2.1 profiletype . . . 843
8.826 pack_wds_GetDefaultProfileNum_t Struct Reference . . . 843
8.826.1 Detailed Description . . . 843
8.826.2 Field Documentation . . . 843
8.826.2.1 family . . . 843
8.826.2.2 type . . . 844
8.827 pack_wds_GetDormancyState_t Struct Reference . . . 844
8.827.1 Detailed Description . . . 844
8.828 pack_wds_GetLastMobileIPError_t Struct Reference . . . 844
8.828.1 Detailed Description . . . 844
8.829 pack_wds_GetMobileIP_t Struct Reference . . . 844
8.829.1 Detailed Description . . . 844
8.830 pack_wds_GetMobileIPProfile_t Struct Reference . . . 844
8.830.1 Detailed Description . . . 844
8.830.2 Field Documentation . . . 845
8.830.2.1 index . . . 845
8.831 pack_wds_GetPacketStatistics_t Struct Reference . . . 845
8.831.1 Detailed Description . . . 845
8.831.2 Field Documentation . . . 845
8.831.2.1 pStatMask . . . 845
8.832 pack_wds_GetPacketStatus_t Struct Reference . . . 845
8.832.1 Detailed Description . . . 845
8.832.2 Field Documentation . . . 846
8.832.2.1 statmask . . . 846
8.833 pack_wds_GetSessionDuration_t Struct Reference . . . 846
8.833.1 Detailed Description . . . 846
8.834 pack_wds_RMSetTransferStatistics_t Struct Reference . . . 846
8.834.1 Detailed Description . . . 846
8.834.2 Field Documentation . . . 846
8.834.2.1 RmTrasnferStaticsReq . . . 846
8.835 pack_wds_SetAutoconnect_t Struct Reference . . . 847
8.835.1 Detailed Description . . . 847
8.835.2 Field Documentation . . . 847
8.835.2.1 acroamsetting . . . 847
8.835.2.2 acsetting . . . 847
8.836 pack_wds_SetDefaultProfile_t Struct Reference . . . 847
8.836.1 Detailed Description . . . 847
8.836.2 Field Documentation . . . 848
8.836.2.1 authentication . . . 849
8.836.2.2 ipAddress . . . 849

8.836.2.3 pApnname . . . 849
8.836.2.4 pdpType . . . 849
8.836.2.5 pName . . . 849
8.836.2.6 pPassword . . . 849
8.836.2.7 primaryDNS . . . 849
8.836.2.8 profileType . . . 849
8.836.2.9 pUsername . . . 849
8.836.2.10 secondaryDNS . . . 849
8.837 pack_wds_SetDefaultProfileNum_t Struct Reference . . . 849
8.837.1 Detailed Description . . . 849
8.837.2 Field Documentation . . . 849
8.837.2.1 family . . . 849
8.837.2.2 index . . . 849
8.837.2.3 type . . . 849
8.838 pack_wds_SetMobileIP_t Struct Reference . . . 850
8.838.1 Detailed Description . . . 850
8.838.2 Field Documentation . . . 850
8.838.2.1 mode . . . 850
8.839 pack_wds_SetMobileIPParameters_t Struct Reference . . . 850
8.839.1 Detailed Description . . . 850
8.839.2 Field Documentation . . . 851
8.839.2.1 pHA2002bis . . . 851
8.839.2.2 pHAAuthenticator . . . 851
8.839.2.3 pMode . . . 851
8.839.2.4 pReRegPeriod . . . 851
8.839.2.5 pReRegTraffic . . . 851
8.839.2.6 pRetryInterval . . . 851
8.839.2.7 pRetryLimit . . . 851
8.839.2.8 pSPC . . . 851
8.840 pack_wds_SetMobileIPProfile_t Struct Reference . . . 851
8.840.1 Detailed Description . . . 852
8.840.2 Field Documentation . . . 852
8.840.2.1 index . . . 853
8.840.2.2 pAAASPI . . . 853
8.840.2.3 pAddress . . . 853
8.840.2.4 pEnabled . . . 853
8.840.2.5 pHASPI . . . 853
8.840.2.6 pMNAAA . . . 853
8.840.2.7 pMNHA . . . 853
8.840.2.8 pNAI . . . 853

8.840.2.9 pPrimaryHA . . . 853
8.840.2.10 pRevTunneling . . . 853
8.840.2.11 pSecondaryHA . . . 853
8.840.2.12 spc . . . 853
8.841 pack_wds_SLQSCreateProfile_t Struct Reference . . . 853
8.841.1 Detailed Description . . . 853
8.841.2 Field Documentation . . . 854
8.841.2.1 pCurProfile . . . 854
8.841.2.2 pProfileId . . . 854
8.841.2.3 pProfileType . . . 854
8.842 pack_wds_SLQSDeleteProfile_t Struct Reference . . . 854
8.842.1 Detailed Description . . . 854
8.842.2 Field Documentation . . . 854
8.842.2.1 profileIndex . . . 854
8.842.2.2 profileType . . . 854
8.843 pack_wds_SLQSGetCurrDataSystemStat_t Struct Reference . . . 854
8.843.1 Detailed Description . . . 854
8.844 pack_wds_SLQSGetDataBearerTechnology_t Struct Reference . . . 855
8.844.1 Detailed Description . . . 855
8.845 pack_wds_SLQSGetDUNCallInfo_t Struct Reference . . . 855
8.845.1 Detailed Description . . . 855
8.845.2 Field Documentation . . . 856
8.845.2.1 Mask . . . 856
8.845.2.2 pReportChannelRate . . . 856
8.845.2.3 pReportConnStatus . . . 856
8.845.2.4 pReportDataBearerTech . . . 856
8.845.2.5 pReportDormStatus . . . 856
8.845.2.6 pTransferStatInd . . . 856
8.846 pack_wds_SLQSGetProfileSettings_t Struct Reference . . . 856
8.846.1 Detailed Description . . . 856
8.846.2 Field Documentation . . . 857
8.846.2.1 ProfileId . . . 857
8.846.2.2 ProfileType . . . 857
8.847 pack_wds_SLQSGetRuntimeSettings_t Struct Reference . . . 857
8.847.1 Detailed Description . . . 857
8.847.2 Field Documentation . . . 858
8.847.2.1 pReqSettings . . . 858
8.848 pack_wds_SLQSModifyProfile_t Struct Reference . . . 858
8.848.1 Detailed Description . . . 858
8.848.2 Field Documentation . . . 859

8.848.2.1 curProfile . . . 859
8.848.2.2 pProfileId . . . 859
8.848.2.3 pProfileType . . . 859
8.849 pack_wds_SLQSSet3GPPConfigItem_t Struct Reference . . . 859
8.849.1 Detailed Description . . . 859
8.849.2 Field Documentation . . . 860
8.849.2.1 LTEAttachProfileListLen . . . 860
8.849.2.2 p3gppRelease . . . 860
8.849.2.3 pDefaultPDNEnabled . . . 860
8.849.2.4 pLTEAttachProfile . . . 860
8.849.2.5 pLTEAttachProfileList . . . 860
8.849.2.6 pProfileList . . . 861
8.850 pack_wds_SLQSSetIPFamilyPreference_t Struct Reference . . . 861
8.850.1 Detailed Description . . . 861
8.850.2 Field Documentation . . . 861
8.850.2.1 IPFamilyPreference . . . 861
8.851 pack_wds_SLQSSetWdsEventCallback_t Struct Reference . . . 861
8.851.1 Detailed Description . . . 861
8.851.2 Field Documentation . . . 862
8.851.2.1 currentDataBearer . . . 862
8.851.2.2 dataBearer . . . 862
8.851.2.3 dataBearerTechExt . . . 862
8.851.2.4 dataSystemStatus . . . 862
8.851.2.5 dormancyStatus . . . 862
8.851.2.6 interval . . . 862
8.851.2.7 mobileIP . . . 862
8.851.2.8 transferStats . . . 862
8.852 pack_wds_SLQSSGetDHCPv4ClientConfig_t Struct Reference . . . 862
8.852.1 Detailed Description . . . 862
8.852.2 Field Documentation . . . 862
8.852.2.1 pProfileId . . . 862
8.853 pack_wds_SLQSSSetDHCPv4ClientConfig_t Struct Reference . . . 862
8.853.1 Detailed Description . . . 862
8.853.2 Field Documentation . . . 863
8.853.2.1 pHwConfig . . . 863
8.853.2.2 pProfileId . . . 863
8.853.2.3 pRequestOptionList . . . 863
8.854 pack_wds_SLQSSSetLoopback_t Struct Reference . . . 863
8.854.1 Detailed Description . . . 863
8.854.2 Field Documentation . . . 863

8.854.2.1 loopbackMode . . . 863
8.854.2.2 loopbackMultiplier . . . 863
8.855 pack_wds_SLQSStartDataSession_t Struct Reference . . . 863
8.855.1 Detailed Description . . . 864
8.855.2 Field Documentation . . . 864
8.855.2.1 pAuth . . . 864
8.855.2.2 pPass . . . 864
8.855.2.3 pprofileid3gpp . . . 864
8.855.2.4 pprofileid3gpp2 . . . 864
8.855.2.5 pTech . . . 864
8.855.2.6 pUser . . . 865
8.856 pack_wds_SLQSStopDataSession_t Struct Reference . . . 865
8.856.1 Detailed Description . . . 865
8.856.2 Field Documentation . . . 865
8.856.2.1 psid . . . 865
8.857 pack_wds_SLQSWdsSetEventReport_t Struct Reference . . . 865
8.857.1 Detailed Description . . . 865
8.857.2 Field Documentation . . . 866
8.857.2.1 pCurrChannelRateInd . . . 866
8.857.2.2 pCurrDataBearerTechInd . . . 866
8.857.2.3 pCurrPrefDataSysInd . . . 866
8.857.2.4 pDataBearerTechInd . . . 866
8.857.2.5 pDataCallStatusChangeInd . . . 866
8.857.2.6 pDataSystemStatusChangeInd . . . 867
8.857.2.7 pDormancyStatusInd . . . 867
8.857.2.8 pEVDOPageMonPerChangeInd . . . 867
8.857.2.9 pMIPStatusInd . . . 867
8.857.2.10 pTransferStatInd . . . 867
8.858 pack_wds_SLQSWdsSwiPDPRuntimeSettings_t Struct Reference . . . 867
8.858.1 Detailed Description . . . 867
8.858.2 Field Documentation . . . 867
8.858.2.1 contextId . . . 867
8.858.2.2 contextType . . . 867
8.859 PackCreateProfileOut Struct Reference . . . 867
8.859.1 Detailed Description . . . 867
8.859.2 Field Documentation . . . 868
8.859.2.1 ExtErrorCode . . . 868
8.859.2.2 ProfileIndex . . . 868
8.859.2.3 ProfileType . . . 868
8.860 packgetDyingGaspCfg Struct Reference . . . 868

8.860.1 Detailed Description . . . 868
8.860.2 Field Documentation . . . 868
8.860.2.1 pDestSMSContent . . . 868
8.860.2.2 pDestSMSNum . . . 868
8.861 packgetDyingGaspStatistics Struct Reference . . . 868
8.861.1 Detailed Description . . . 869
8.861.2 Field Documentation . . . 869
8.861.2.1 pSMSAttemptedFlag . . . 869
8.861.2.2 pTimeStamp . . . 869
8.862 PCMparams Struct Reference . . . 869
8.862.1 Detailed Description . . . 869
8.862.2 Field Documentation . . . 869
8.862.2.1 iFaceTab . . . 869
8.862.2.2 iFaceTabLen . . . 870
8.863 PCSCFFQDNAddress Struct Reference . . . 870
8.863.1 Detailed Description . . . 870
8.863.2 Field Documentation . . . 870
8.863.2.1 fqdnAddr . . . 870
8.863.2.2 fqdnLen . . . 870
8.864 PCSCFFQDNAddressList Struct Reference . . . 870
8.864.1 Detailed Description . . . 870
8.864.2 Field Documentation . . . 870
8.864.2.1 numInstances . . . 870
8.864.2.2 pcsfFQDNAddress . . . 871
8.865 PCSCFIPv4ServerAddressList Struct Reference . . . 871
8.865.1 Detailed Description . . . 871
8.865.2 Field Documentation . . . 871
8.865.2.1 numInstances . . . 871
8.865.2.2 pscsfIPv4Addr . . . 871
8.866 PDSPositionData Struct Reference . . . 871
8.866.1 Detailed Description . . . 871
8.866.2 Field Documentation . . . 873
8.866.2.1 pAltitudeWrtEllipsoid . . . 873
8.866.2.2 pAltitudeWrtSealevel . . . 873
8.866.2.3 pHorizontalConfidence . . . 873
8.866.2.4 pHorizontalUncCircular . . . 873
8.866.2.5 pLatitude . . . 873
8.866.2.6 pLongitude . . . 873
8.866.2.7 pPositionSource . . . 873
8.866.2.8 pTimeStamp . . . 873

8.866.2.9 pTimeType . . . 873
8.866.2.10 pVerticalConfidence . . . 873
8.866.2.11 pVerticalUnc . . . 873
8.867 PDSPosMethodStateReq Struct Reference . . . 873
8.867.1 Detailed Description . . . 873
8.867.2 Field Documentation . . . 874
8.867.2.1 pWifiState . . . 874
8.867.2.2 pXtraDataState . . . 874
8.867.2.3 pXtraTimeState . . . 874
8.868 peerNumberInfo Struct Reference . . . 874
8.868.1 Detailed Description . . . 874
8.868.2 Field Documentation . . . 875
8.868.2.1 callID . . . 875
8.868.2.2 number . . . 875
8.868.2.3 numLen . . . 875
8.868.2.4 numPI . . . 875
8.868.2.5 numPlan . . . 875
8.868.2.6 numSI . . . 876
8.868.2.7 numType . . . 876
8.869 personalizationStatus Struct Reference . . . 876
8.869.1 Detailed Description . . . 876
8.869.2 Field Documentation . . . 876
8.869.2.1 feature . . . 876
8.869.2.2 numFeatures . . . 876
8.869.2.3 unblockLeft . . . 876
8.869.2.4 verifyLeft . . . 876
8.870 PhyCaAggPcellInfo Struct Reference . . . 877
8.870.1 Detailed Description . . . 877
8.870.2 Field Documentation . . . 877
8.870.2.1 dl_bw_value . . . 877
8.870.2.2 freq . . . 877
8.870.2.3 iLTEbandValue . . . 877
8.870.2.4 pci . . . 877
8.870.2.5 TlvPresent . . . 877
8.871 PhyCaAggScellArray Struct Reference . . . 877
8.871.1 Detailed Description . . . 878
8.871.2 Field Documentation . . . 878
8.871.2.1 band . . . 879
8.871.2.2 cphy_ca_dl_bandwidth . . . 879
8.871.2.3 cphy_scell_info_list_len . . . 879

8.871.2.4 freq . . . 879
8.871.2.5 pci . . . 879
8.871.2.6 scell_idx . . . 879
8.871.2.7 scell_state . . . 879
8.871.2.8 TlvPresent . . . 879
8.872 PhyCaAggScellDlBw Struct Reference . . . 879
8.872.1 Detailed Description . . . 879
8.872.2 Field Documentation . . . 879
8.872.2.1 dl_bw_value . . . 879
8.872.2.2 TlvPresent . . . 879
8.873 PhyCaAggScellIndex Struct Reference . . . 879
8.873.1 Detailed Description . . . 879
8.873.2 Field Documentation . . . 880
8.873.2.1 scell_idx . . . 880
8.873.2.2 TlvPresent . . . 880
8.874 PhyCaAggScellIndType Struct Reference . . . 880
8.874.1 Detailed Description . . . 880
8.874.2 Field Documentation . . . 880
8.874.2.1 freq . . . 880
8.874.2.2 pci . . . 880
8.874.2.3 scell_state . . . 881
8.874.2.4 TlvPresent . . . 881
8.875 PhyCaAggScellInfo Struct Reference . . . 881
8.875.1 Detailed Description . . . 881
8.875.2 Field Documentation . . . 883
8.875.2.1 dl_bw_value . . . 883
8.875.2.2 freq . . . 883
8.875.2.3 iLTEbandValue . . . 883
8.875.2.4 pci . . . 883
8.875.2.5 scell_state . . . 883
8.875.2.6 TlvPresent . . . 883
8.876 PilotSetData Struct Reference . . . 883
8.876.1 Detailed Description . . . 883
8.876.2 Field Documentation . . . 883
8.876.2.1 NumPilots . . . 883
8.876.2.2 pPilotSetInfo . . . 883
8.877 PilotSetParams Struct Reference . . . 884
8.877.1 Detailed Description . . . 884
8.877.2 Field Documentation . . . 884
8.877.2.1 PilotPN . . . 884

8.877.2.2 PilotStrength . . . 884
8.877.2.3 PilotType . . . 884
8.878 pktErrRate Struct Reference . . . 884
8.878.1 Detailed Description . . . 884
8.878.2 Field Documentation . . . 884
8.878.2.1 exponent . . . 884
8.878.2.2 multiplier . . . 885
8.879 PlmnID Struct Reference . . . 885
8.879.1 Detailed Description . . . 885
8.879.2 Field Documentation . . . 885
8.879.2.1 mcc . . . 885
8.879.2.2 mnc . . . 885
8.879.2.3 pcsDigit . . . 885
8.879.2.4 TlvPresent . . . 885
8.880 PLMNNetworkName Struct Reference . . . 885
8.880.1 Detailed Description . . . 886
8.880.2 Field Documentation . . . 886
8.880.2.1 numInstance . . . 886
8.880.2.2 PLMNNetName . . . 886
8.881 PLMNNetworkNameData Struct Reference . . . 886
8.881.1 Detailed Description . . . 886
8.881.2 Field Documentation . . . 887
8.881.2.1 codingScheme . . . 887
8.881.2.2 countryInitials . . . 887
8.881.2.3 longName . . . 887
8.881.2.4 longNameLen . . . 887
8.881.2.5 longNameSpareBits . . . 887
8.881.2.6 shortName . . . 887
8.881.2.7 shortNameLen . . . 888
8.881.2.8 shortNameSpareBits . . . 888
8.882 Port Struct Reference . . . 888
8.882.1 Detailed Description . . . 888
8.882.2 Field Documentation . . . 888
8.882.2.1 port . . . 888
8.882.2.2 range . . . 888
8.883 PowerSaveModeConfigReq Struct Reference . . . 888
8.883.1 Detailed Description . . . 888
8.883.2 Field Documentation . . . 889
8.883.2.1 pActiveTimer . . . 889
8.883.2.2 pPeriodicUpdateTimer . . . 889

8.883.2.3 pPsmEnableState . . . 889
8.884 PowerSaveModeConfigResp Struct Reference . . . 889
8.884.1 Detailed Description . . . 889
8.884.2 Field Documentation . . . 890
8.884.2.1 pActiveTimer . . . 890
8.884.2.2 pDurationDueToOOS . . . 890
8.884.2.3 pDurationThreshold . . . 890
8.884.2.4 pEarlyWakeupTime . . . 890
8.884.2.5 pPeriodicUpdateTimer . . . 890
8.884.2.6 pPsmEnableState . . . 890
8.884.2.7 pRandomizationWindow . . . 890
8.885 precisionDilution_s Struct Reference . . . 890
8.885.1 Detailed Description . . . 890
8.885.2 Field Documentation . . . 890
8.885.2.1 HDOP . . . 890
8.885.2.2 PDOP . . . 890
8.885.2.3 VDOP . . . 890
8.886 PrefImageList Struct Reference . . . 891
8.886.1 Detailed Description . . . 891
8.886.2 Field Documentation . . . 891
8.886.2.1 listEntries . . . 891
8.886.2.2 listSize . . . 891
8.887 prefVoiceSO Struct Reference . . . 891
8.887.1 Detailed Description . . . 891
8.887.2 Field Documentation . . . 893
8.887.2.1 evrcCapability . . . 893
8.887.2.2 homeOrigVoiceSO . . . 893
8.887.2.3 homePageVoiceSO . . . 893
8.887.2.4 namID . . . 893
8.887.2.5 roamOrigVoiceSO . . . 893
8.888 Profile3GPP Struct Reference . . . 893
8.888.1 Detailed Description . . . 894
8.888.2 Field Documentation . . . 898
8.888.2.1 pAddrAllocPref . . . 898
8.888.2.2 pAPNClass . . . 898
8.888.2.3 pAPNDisabledFlag . . . 898
8.888.2.4 pAPNName . . . 898
8.888.2.5 pAPNnameSize . . . 898
8.888.2.6 pAuthenticationPref . . . 898
8.888.2.7 pGPRSMinimumQoS . . . 898

8.888.2.8 pGPRSRequestedQos . . . 898
8.888.2.9 pImCnFlag . . . 898
8.888.2.10 pIPv4AddrPref . . . 898
8.888.2.11 pIPv6AddPref . . . 898
8.888.2.12 pPassword . . . 898
8.888.2.13 pPasswordSize . . . 898
8.888.2.14 pPcscfAddrUsingDhcp . . . 898
8.888.2.15 pPcscfAddrUsingPCO . . . 898
8.888.2.16 pPDNInactivTimeout . . . 898
8.888.2.17 pPdpAccessConFlag . . . 898
8.888.2.18 pPdpContext . . . 898
8.888.2.19 pPdpDataCompType . . . 898
8.888.2.20 pPdpHdrCompType . . . 899
8.888.2.21 pPDPtype . . . 899
8.888.2.22 pPriDNSIPv4AddPref . . . 899
8.888.2.23 pPriDNSIPv6addpref . . . 899
8.888.2.24 pPrimaryID . . . 899
8.888.2.25 pProfilename . . . 899
8.888.2.26 pProfilenameSize . . . 899
8.888.2.27 pQosClassID . . . 899
8.888.2.28 pSecDNSIPv4AddPref . . . 899
8.888.2.29 pSecDNSIPv6addpref . . . 899
8.888.2.30 pSecondaryFlag . . . 899
8.888.2.31 pSupportEmergencyCalls . . . 899
8.888.2.32 pTFTID1Params . . . 899
8.888.2.33 pTFTID2Params . . . 899
8.888.2.34 pUMTSMinQoS . . . 899
8.888.2.35 pUMTSMinQosSigInd . . . 899
8.888.2.36 pUMTSReqQoS . . . 899
8.888.2.37 pUMTSReqQoSSigInd . . . 899
8.888.2.38 pUsername . . . 899
8.888.2.39 pUsernameSize . . . 899
8.889 Profile3GPP2 Struct Reference . . . 899
8.889.1 Detailed Description . . . 900
8.889.2 Field Documentation . . . 903
8.889.2.1 pAllowLinger . . . 903
8.889.2.2 pAPNClass3GPP2 . . . 903
8.889.2.3 pAPNEnabled3GPP2 . . . 903
8.889.2.4 pApnString . . . 903
8.889.2.5 pApnStringSize . . . 903

8.889.2.6 pAppPriority . . . 903
8.889.2.7 pAppType . . . 903
8.889.2.8 pAuthPassword . . . 904
8.889.2.9 pAuthPasswordSize . . . 904
8.889.2.10 pAuthProtocol . . . 904
8.889.2.11 pAuthRetryCount . . . 904
8.889.2.12 pAuthTimeout . . . 904
8.889.2.13 pDataMode . . . 904
8.889.2.14 pDataRate . . . 904
8.889.2.15 pIpcpAckTimeout . . . 904
8.889.2.16 pIpcpCreqRetryCount . . . 904
8.889.2.17 pIsPcscfAddressNedded . . . 904
8.889.2.18 pLcpAckTimeout . . . 904
8.889.2.19 pLcpCreqRetryCount . . . 904
8.889.2.20 pNegoDnsSrvrPref . . . 904
8.889.2.21 pPDNInactivTimeout3GPP2 . . . 904
8.889.2.22 pPdnType . . . 904
8.889.2.23 pPppSessCloseTimer1x . . . 904
8.889.2.24 pPppSessCloseTimerDO . . . 904
8.889.2.25 pPrimaryV4DnsAddress . . . 904
8.889.2.26 pPriV6DnsAddress . . . 904
8.889.2.27 pRATType . . . 904
8.889.2.28 pSecondaryV4DnsAddress . . . 904
8.889.2.29 pSecV6DnsAddress . . . 904
8.889.2.30 pUserId . . . 904
8.889.2.31 pUserIdSize . . . 904
8.890 ProfileIdentifier Struct Reference . . . 904
8.890.1 Detailed Description . . . 905
8.890.2 Field Documentation . . . 905
8.890.2.1 profileIndex . . . 905
8.890.2.2 profileType . . . 905
8.891 protocolSubtypeElement Struct Reference . . . 905
8.891.1 Detailed Description . . . 905
8.891.2 Field Documentation . . . 906
8.891.2.1 AccessMac . . . 906
8.891.2.2 AuthProt . . . 906
8.891.2.3 ControlMac . . . 906
8.891.2.4 EncryptProt . . . 906
8.891.2.5 ForwardMac . . . 906
8.891.2.6 IdleState . . . 906

8.891.2.7 KeyExchange . . . 906
8.891.2.8 MultDisc . . . 906
8.891.2.9 PhysicalLayer . . . 906
8.891.2.10 ReverseMac . . . 906
8.891.2.11 SecProt . . . 907
8.891.2.12 VirtStream . . . 907
8.892 PSDetachReq Struct Reference . . . 907
8.892.1 Detailed Description . . . 907
8.892.2 Field Documentation . . . 907
8.892.2.1 pDetachAction . . . 907
8.893 PSMActiveTimerTlv Struct Reference . . . 907
8.893.1 Detailed Description . . . 907
8.893.2 Field Documentation . . . 907
8.893.2.1 activeTimer . . . 907
8.893.2.2 TlvPresent . . . 907
8.894 PSMDurationDueToOOSTlv Struct Reference . . . 908
8.894.1 Detailed Description . . . 908
8.894.2 Field Documentation . . . 908
8.894.2.1 durationDueToOOS . . . 908
8.894.2.2 TlvPresent . . . 908
8.895 PSMDurationThresholdTlv Struct Reference . . . 908
8.895.1 Detailed Description . . . 908
8.895.2 Field Documentation . . . 908
8.895.2.1 durationThreshold . . . 908
8.895.2.2 TlvPresent . . . 908
8.896 PSMEarlyWakeupTimeTlv Struct Reference . . . 909
8.896.1 Detailed Description . . . 909
8.896.2 Field Documentation . . . 909
8.896.2.1 earlyWakeupTime . . . 909
8.896.2.2 TlvPresent . . . 909
8.897 PSMEnableStateTlv Struct Reference . . . 909
8.897.1 Detailed Description . . . 909
8.897.2 Field Documentation . . . 909
8.897.2.1 enableState . . . 909
8.897.2.2 TlvPresent . . . 910
8.898 PSMPeriodicUpdateTimerTlv Struct Reference . . . 910
8.898.1 Detailed Description . . . 910
8.898.2 Field Documentation . . . 910
8.898.2.1 periodicUpdateTimer . . . 910
8.898.2.2 TlvPresent . . . 910

8.899 PSMRandomizationWindowTlv Struct Reference . . . 910
8.899.1 Detailed Description . . . 910
8.899.2 Field Documentation . . . 910
8.899.2.1 randomizationWindow . . . 910
8.899.2.2 TlvPresent . . . 911
8.900 qaQmi3Gpp2TimeZone Struct Reference . . . 911
8.900.1 Detailed Description . . . 911
8.900.2 Field Documentation . . . 911
8.900.2.1 daylightSavings . . . 911
8.900.2.2 leapSeconds . . . 911
8.900.2.3 localTimeOffset . . . 911
8.901 qaQmiInterfaceInfo Struct Reference . . . 911
8.901.1 Detailed Description . . . 911
8.901.2 Field Documentation . . . 912
8.901.2.1 qaQmiinstanceid . . . 912
8.901.2.2 qaQmisvctype . . . 912
8.901.2.3 v4sessionId . . . 912
8.901.2.4 v6sessionId . . . 912
8.902 qaQmiServingSystemParam Struct Reference . . . 912
8.902.1 Detailed Description . . . 913
8.902.2 Field Documentation . . . 915
8.902.2.1 BasestationID . . . 915
8.902.2.2 BasestationLatitude . . . 915
8.902.2.3 BasestationLongitude . . . 915
8.902.2.4 CallBarStatus . . . 915
8.902.2.5 CDMA_P_Rev . . . 915
8.902.2.6 CDMASystemInfoExt . . . 915
8.902.2.7 CellID . . . 915
8.902.2.8 concSvcInfo . . . 915
8.902.2.9 CurrentPLMN . . . 915
8.902.2.10 DataSrvCapabilities . . . 915
8.902.2.11 defaultRoamInd . . . 915
8.902.2.12 DetailedSvcInfo . . . 915
8.902.2.13 DTMInd . . . 915
8.902.2.14 Gpp2TimeZone . . . 915
8.902.2.15 GppNetworkDSTAdjustment . . . 915
8.902.2.16 GppTimeZone . . . 915
8.902.2.17 hdrPersonality . . . 916
8.902.2.18 Lac . . . 916
8.902.2.19 NetworkID . . . 916

8.902.2.20 PRLInd . . . 916
8.902.2.21 roamIndicatorVal . . . 916
8.902.2.22 RoamingIndicatorList . . . 916
8.902.2.23 ServingSystem . . . 916
8.902.2.24 SystemID . . . 916
8.902.2.25 trackAreaCode . . . 916
8.903 QmiCbkCatEventStatusReportInd Struct Reference . . . 916
8.903.1 Field Documentation . . . 916
8.903.1.1 CCETlv . . . 916
8.903.1.2 event_Index . . . 916
8.903.1.3 results . . . 916
8.904 QmiCbkLocBestAvailPosInd Struct Reference . . . 916
8.904.1 Detailed Description . . . 917
8.904.2 Field Documentation . . . 921
8.904.2.1 pAltitudeWrtEllipsoid . . . 921
8.904.2.2 pAltitudeWrtMeanSeaLevel . . . 921
8.904.2.3 pGpsTime . . . 921
8.904.2.4 pHeading . . . 921
8.904.2.5 pHeadingUnc . . . 921
8.904.2.6 pHorCirConf . . . 921
8.904.2.7 pHorEllpConf . . . 921
8.904.2.8 pHorReliability . . . 921
8.904.2.9 pHorUncCircular . . . 921
8.904.2.10 pHorUncEllipseOrientAzimuth . . . 921
8.904.2.11 pHorUncEllipseSemiMajor . . . 921
8.904.2.12 pHorUncEllipseSemiMinor . . . 921
8.904.2.13 pLatitude . . . 921
8.904.2.14 pLongitude . . . 921
8.904.2.15 pMagneticDeviation . . . 921
8.904.2.16 pPrecisionDilution . . . 921
8.904.2.17 pSensorDataUsage . . . 921
8.904.2.18 pSpeedHorizontal . . . 921
8.904.2.19 pSpeedUnc . . . 921
8.904.2.20 pSpeedVertical . . . 921
8.904.2.21 pSpeedVerticalUnc . . . 921
8.904.2.22 pSvUsedforFix . . . 921
8.904.2.23 pTechnologyMask . . . 921
8.904.2.24 pTimeSrc . . . 921
8.904.2.25 pTimestampUtc . . . 921
8.904.2.26 pTimeUnc . . . 921

8.904.2.27 pVertConfidence . . . 921
8.904.2.28 pVertReliability . . . 922
8.904.2.29 pVertUnc . . . 922
8.904.2.30 pXid . . . 922
8.904.2.31 results . . . 922
8.904.2.32 status . . . 922
8.905 QmiCbkLocCradleMountInd Struct Reference . . . 922
8.905.1 Detailed Description . . . 922
8.905.2 Field Documentation . . . 922
8.905.2.1 cradleMountConfigStatus . . . 922
8.905.2.2 results . . . 922
8.906 QmiCbkLocEngineStateInd Struct Reference . . . 922
8.906.1 Detailed Description . . . 923
8.906.2 Field Documentation . . . 923
8.906.2.1 engineState . . . 923
8.906.2.2 results . . . 923
8.907 QmiCbkLocEventNMEAInd Struct Reference . . . 923
8.907.1 Detailed Description . . . 923
8.907.2 Field Documentation . . . 923
8.907.2.1 pNMEAData . . . 923
8.907.2.2 results . . . 923
8.908 QmiCbkLocEventTimeSyncInd Struct Reference . . . 923
8.908.1 Detailed Description . . . 924
8.908.2 Field Documentation . . . 924
8.908.2.1 results . . . 924
8.908.2.2 timeSyncRefCounter . . . 924
8.909 QmiCbkLocGetOpModeInd Struct Reference . . . 924
8.909.1 Detailed Description . . . 924
8.909.2 Field Documentation . . . 925
8.909.2.1 pMode . . . 925
8.909.2.2 results . . . 925
8.909.2.3 status . . . 925
8.910 QmiCbkLocGetServerInd Struct Reference . . . 925
8.910.1 Detailed Description . . . 925
8.910.2 Field Documentation . . . 926
8.910.2.1 pIPv4AddrInfo . . . 926
8.910.2.2 pIPv6AddrInfo . . . 926
8.910.2.3 pURL . . . 926
8.910.2.4 results . . . 926
8.910.2.5 serverStatus . . . 926

8.910.2.6 serverType . . . 926
8.911 QmiCbkLocInjectPositionInd Struct Reference . . . 927
8.911.1 Detailed Description . . . 927
8.911.2 Field Documentation . . . 927
8.911.2.1 results . . . 927
8.911.2.2 status . . . 927
8.912 QmiCbkLocInjectSensorDataInd Struct Reference . . . 927
8.912.1 Detailed Description . . . 928
8.912.2 Field Documentation . . . 928
8.912.2.1 injectSensorDataStatus . . . 928
8.912.2.2 pAccelSamplesAccepted . . . 928
8.912.2.3 pAccelTempSamplesAccepted . . . 928
8.912.2.4 pGyroSamplesAccepted . . . 928
8.912.2.5 pGyroTempSamplesAccepted . . . 929
8.912.2.6 pOpaqueIdentifier . . . 929
8.912.2.7 results . . . 929
8.913 QmiCbkLocInjectTimeInd Struct Reference . . . 929
8.913.1 Detailed Description . . . 929
8.913.2 Field Documentation . . . 929
8.913.2.1 injectTimeSyncStatus . . . 929
8.913.2.2 results . . . 929
8.914 QmiCbkLocInjectUTCTimeInd Struct Reference . . . 929
8.914.1 Detailed Description . . . 929
8.914.2 Field Documentation . . . 930
8.914.2.1 results . . . 930
8.914.2.2 status . . . 930
8.915 QmiCbkLocOpModeInd Struct Reference . . . 930
8.915.1 Detailed Description . . . 930
8.915.2 Field Documentation . . . 931
8.915.2.1 mode . . . 931
8.915.2.2 results . . . 931
8.916 QmiCbkLocPositionReportInd Struct Reference . . . 931
8.916.1 Detailed Description . . . 932
8.916.2 Field Documentation . . . 936
8.916.2.1 pAltitudeAssumed . . . 936
8.916.2.2 pAltitudeWrtEllipsoid . . . 936
8.916.2.3 pAltitudeWrtMeanSeaLevel . . . 936
8.916.2.4 pFixId . . . 936
8.916.2.5 pGpsTime . . . 936
8.916.2.6 pHeading . . . 936

8.916.2.7 pHeadingUnc . . . 936
8.916.2.8 pHorConfidence . . . 936
8.916.2.9 pHorReliability . . . 936
8.916.2.10 pHorUncCircular . . . 936
8.916.2.11 pHorUncEllipseOrientAzimuth . . . 936
8.916.2.12 pHorUncEllipseSemiMajor . . . 936
8.916.2.13 pHorUncEllipseSemiMinor . . . 936
8.916.2.14 pLatitude . . . 936
8.916.2.15 pLeapSeconds . . . 936
8.916.2.16 pLongitude . . . 936
8.916.2.17 pMagneticDeviation . . . 936
8.916.2.18 pPrecisionDilution . . . 936
8.916.2.19 pSensorDataUsage . . . 936
8.916.2.20 pSpeedHorizontal . . . 936
8.916.2.21 pSpeedUnc . . . 936
8.916.2.22 pSpeedVertical . . . 936
8.916.2.23 pSvUsedforFix . . . 936
8.916.2.24 pTechnologyMask . . . 936
8.916.2.25 pTimeSrc . . . 937
8.916.2.26 pTimestampUtc . . . 937
8.916.2.27 pTimeUnc . . . 937
8.916.2.28 pVertConfidence . . . 937
8.916.2.29 pVertReliability . . . 937
8.916.2.30 pVertUnc . . . 937
8.916.2.31 results . . . 937
8.916.2.32 sessionId . . . 937
8.916.2.33 sessionStatus . . . 937
8.917 QmiCbkLocSensorStreamingInd Struct Reference . . . 937
8.917.1 Detailed Description . . . 937
8.917.2 Field Documentation . . . 937
8.917.2.1 pAccelAcceptReady . . . 937
8.917.2.2 pAccelTempAcceptReady . . . 937
8.917.2.3 pGyroAcceptReady . . . 938
8.917.2.4 pGyroTempAcceptReady . . . 938
8.917.2.5 results . . . 938
8.918 QmiCbkLocSetExtPowerConfigInd Struct Reference . . . 938
8.918.1 Detailed Description . . . 938
8.918.2 Field Documentation . . . 938
8.918.2.1 results . . . 938
8.918.2.2 status . . . 938

8.919 QmiCbkLocSetServerInd Struct Reference . . . 938
8.919.1 Detailed Description . . . 938
8.919.2 Field Documentation . . . 939
8.919.2.1 results . . . 939
8.919.2.2 serverStatus . . . 939
8.920 QmiCbkNasEdrxChangeInfo Struct Reference . . . 939
8.920.1 Detailed Description . . . 939
8.920.2 Field Documentation . . . 940
8.920.2.1 results . . . 940
8.920.2.2 sEdrxCiotLteMode . . . 940
8.920.2.3 sEdrxCycleLength . . . 940
8.920.2.4 sEdrxEnableType . . . 940
8.920.2.5 sEdrxPagingTimeWindow . . . 940
8.920.2.6 sEdrxRatType . . . 940
8.921 QmiCbkNasLTECphyCaInfo Struct Reference . . . 940
8.921.1 Detailed Description . . . 940
8.921.2 Field Documentation . . . 941
8.921.2.1 results . . . 941
8.921.2.2 sPhyCaAggPcellInfo . . . 941
8.921.2.3 sPhyCaAggScellDlBw . . . 941
8.921.2.4 sPhyCaAggScellIndex . . . 941
8.921.2.5 sPhyCaAggScellIndType . . . 941
8.921.2.6 sPhyCaAggScellInfo . . . 941
8.922 QmiCbkSwiOmaDmEventStatusReportInd Struct Reference . . . 941
8.922.1 Field Documentation . . . 941
8.922.1.1 results . . . 941
8.922.1.2 SITlv . . . 941
8.923 QmiCbkSwiOmaDmEventStatusReportIndExt Struct Reference . . . 941
8.923.1 Field Documentation . . . 941
8.923.1.1 SITlv . . . 941
8.924 QmiCbkTmdMitiLvlRptInd Struct Reference . . . 941
8.924.1 Detailed Description . . . 942
8.924.2 Field Documentation . . . 942
8.924.2.1 currentMitigationLvl . . . 942
8.924.2.2 MitigationDevInfo . . . 942
8.924.2.3 results . . . 942
8.925 QmiCbkWdsStatisticsIndState Struct Reference . . . 942
8.925.1 Detailed Description . . . 942
8.925.2 Field Documentation . . . 943
8.925.2.1 results . . . 943

8.925.2.2 RxDropConutTlv . . . 943
8.925.2.3 RxOkByteCountTlv . . . 943
8.925.2.4 RxOkConutTlv . . . 943
8.925.2.5 TxDropConutTlv . . . 943
8.925.2.6 TxOkByteCountTlv . . . 943
8.925.2.7 TxOkConutTlv . . . 943
8.926 qmifwinfo_s Struct Reference . . . 943
8.926.1 Detailed Description . . . 943
8.926.2 Field Documentation . . . 944
8.926.2.1 dev . . . 944
8.926.2.2 g . . . 944
8.926.2.3 s . . . 944
8.927 QmiNas3GppNetworkInfo Struct Reference . . . 944
8.927.1 Detailed Description . . . 944
8.927.2 Field Documentation . . . 945
8.927.2.1 pDesription . . . 945
8.927.2.2 pForbidden . . . 945
8.927.2.3 pInUse . . . 945
8.927.2.4 pMCC . . . 945
8.927.2.5 pMNC . . . 945
8.927.2.6 pPreferred . . . 945
8.927.2.7 pRoaming . . . 945
8.928 QmiNasGetRFBandInfoResp Struct Reference . . . 945
8.928.1 Field Documentation . . . 945
8.928.1.1 pInstancesSize . . . 946
8.928.1.2 pLTEOperationMode . . . 946
8.928.1.3 pRFBandInfoElements . . . 946
8.928.1.4 pRfBandInfoExtFormat . . . 946
8.928.1.5 pRfBandwidthInfo . . . 946
8.928.1.6 pRfDedicatedBandInfo . . . 946
8.928.1.7 results . . . 946
8.929 QmiNasPerformNetworkScanResp Struct Reference . . . 946
8.929.1 Field Documentation . . . 946
8.929.1.1 pInstances . . . 946
8.929.1.2 pInstanceSize . . . 946
8.929.1.3 results . . . 946
8.930 qmiSmsMessageList Struct Reference . . . 946
8.930.1 Detailed Description . . . 946
8.930.2 Field Documentation . . . 946
8.930.2.1 messageIndex . . . 947

8.930.2.2 messageTag . . . 947
8.931 qmiWDSDataBearerTechnology Struct Reference . . . 947
8.931.1 Detailed Description . . . 947
8.931.2 Field Documentation . . . 947
8.931.2.1 currentNetwork . . . 947
8.931.2.2 ratMask . . . 947
8.931.2.3 soMask . . . 947
8.932 QmiWdsIpAddressInfo Struct Reference . . . 947
8.932.1 Detailed Description . . . 947
8.932.2 Field Documentation . . . 948
8.932.2.1 pIPAddressV4 . . . 948
8.932.2.2 pIPAddressV6 . . . 948
8.932.2.3 pIPv6prefixlen . . . 948
8.933 qmiWdsRunTimeSettings Struct Reference . . . 948
8.933.1 Detailed Description . . . 949
8.933.2 Field Documentation . . . 951
8.933.2.1 pAPNName . . . 951
8.933.2.2 pAuthentication . . . 951
8.933.2.3 pDomainList . . . 951
8.933.2.4 pGPRSGrantedQoS . . . 951
8.933.2.5 pGWAddressV4 . . . 951
8.933.2.6 pIMCNflag . . . 951
8.933.2.7 pIPAddressV4 . . . 951
8.933.2.8 pIPFamilyPreference . . . 951
8.933.2.9 pIPV6AddrInfo . . . 951
8.933.2.10 pIPV6GWAddrInfo . . . 951
8.933.2.11 pMtu . . . 951
8.933.2.12 pPCSCFAddrPCO . . . 951
8.933.2.13 pPCSCFFQDNAddrList . . . 951
8.933.2.14 pPDPType . . . 951
8.933.2.15 pPrimaryDNSV4 . . . 951
8.933.2.16 pPrimaryDNSV6 . . . 951
8.933.2.17 pProfileID . . . 951
8.933.2.18 pProfileName . . . 952
8.933.2.19 pSecondaryDNSV4 . . . 952
8.933.2.20 pSecondaryDNSV6 . . . 952
8.933.2.21 pServerAddrList . . . 952
8.933.2.22 pSubnetMaskV4 . . . 952
8.933.2.23 pTechnology . . . 952
8.933.2.24 pUMTSGrantedQoS . . . 952

8.933.2.25 pUsername . . . 952
8.934 qmTlvResult Struct Reference . . . 952
8.934.1 Field Documentation . . . 952
8.934.1.1 DeviceError . . . 952
8.934.1.2 DeviceResult . . . 952
8.934.1.3 TlvPresenceMask . . . 952
8.934.1.4 TlvResultCode . . . 952
8.935 qos_BindDataPortMuxID_t Struct Reference . . . 952
8.935.1 Detailed Description . . . 952
8.935.2 Field Documentation . . . 952
8.935.2.1 MuxID . . . 953
8.936 qos_BindDataPortPeripheralEndPointID_t Struct Reference . . . 953
8.936.1 Detailed Description . . . 953
8.936.2 Field Documentation . . . 953
8.936.2.1 EndPointType . . . 953
8.936.2.2 IfaceID . . . 953
8.937 qos_BindDataPortSIODataPort_t Struct Reference . . . 953
8.937.1 Detailed Description . . . 953
8.937.2 Field Documentation . . . 953
8.937.2.1 SIODataPort . . . 953
8.938 QosClassID Struct Reference . . . 953
8.938.1 Detailed Description . . . 954
8.938.2 Field Documentation . . . 954
8.938.2.1 gDlBitRate . . . 954
8.938.2.2 gUlBitRate . . . 954
8.938.2.3 maxDlBitRate . . . 954
8.938.2.4 maxUlBitRate . . . 954
8.938.2.5 QCI . . . 954
8.939 QosEventInfo Struct Reference . . . 954
8.939.1 Detailed Description . . . 955
8.939.2 Field Documentation . . . 955
8.939.2.1 pDataBearer . . . 956
8.939.2.2 pPacketsCountRX . . . 956
8.939.2.3 pPacketsCountTX . . . 956
8.939.2.4 pTotalBytesRX . . . 956
8.939.2.5 pTotalBytesTX . . . 956
8.940 QosFlowInfo Struct Reference . . . 956
8.940.1 Detailed Description . . . 956
8.940.2 Field Documentation . . . 956
8.940.2.1 pBearerID . . . 956

8.940.2.2 pQFlowState . . . 957
8.940.2.3 pRxQFilter . . . 957
8.940.2.4 pRxQFlowGranted . . . 957
8.940.2.5 pTxQFilter . . . 957
8.940.2.6 pTxQFlowGranted . . . 957
8.941 QosFlowInfoState Struct Reference . . . 957
8.941.1 Detailed Description . . . 957
8.941.2 Field Documentation . . . 957
8.941.2.1 id . . . 957
8.941.2.2 isNewFlow . . . 957
8.941.2.3 state . . . 957
8.942 QosMap Struct Reference . . . 957
8.942.1 Detailed Description . . . 958
8.942.2 Field Documentation . . . 958
8.942.2.1 dscp . . . 958
8.942.2.2 qos_id . . . 958
8.942.2.3 state . . . 958
8.943 RankIndicatorInd Struct Reference . . . 958
8.943.1 Field Documentation . . . 958
8.943.1.1 Count1 . . . 958
8.943.1.2 Count2 . . . 958
8.944 RatDisabledMaskTlv Struct Reference . . . 958
8.944.1 Detailed Description . . . 958
8.944.2 Field Documentation . . . 959
8.944.2.1 ratDisabledMask . . . 959
8.944.2.2 TlvPresent . . . 959
8.945 readResult Struct Reference . . . 959
8.945.1 Detailed Description . . . 959
8.945.2 Field Documentation . . . 959
8.945.2.1 content . . . 959
8.945.2.2 contentLen . . . 959
8.946 readTransparentInfo Struct Reference . . . 960
8.946.1 Detailed Description . . . 960
8.946.2 Field Documentation . . . 960
8.946.2.1 length . . . 960
8.946.2.2 offset . . . 960
8.947 redirNumInfo Struct Reference . . . 960
8.947.1 Detailed Description . . . 960
8.947.2 Field Documentation . . . 961
8.947.2.1 number . . . 961

8.947.2.2 numLen . . . 961
8.947.2.3 numPlan . . . 962
8.947.2.4 numType . . . 962
8.947.2.5 PI . . . 962
8.947.2.6 reason . . . 962
8.947.2.7 SI . . . 962
8.948 registerRefresh Struct Reference . . . 962
8.948.1 Detailed Description . . . 962
8.948.2 Field Documentation . . . 962
8.948.2.1 arrfileInfo . . . 962
8.948.2.2 numFiles . . . 962
8.948.2.3 registerFlag . . . 963
8.948.2.4 voteForInit . . . 963
8.949 remainingRetries Struct Reference . . . 963
8.949.1 Detailed Description . . . 963
8.949.2 Field Documentation . . . 963
8.949.2.1 unblockLeft . . . 963
8.949.2.2 verifyLeft . . . 963
8.950 remotePartyName Struct Reference . . . 963
8.950.1 Detailed Description . . . 963
8.950.2 Field Documentation . . . 964
8.950.2.1 callerName . . . 964
8.950.2.2 codingScheme . . . 964
8.950.2.3 nameLen . . . 964
8.950.2.4 namePI . . . 964
8.951 remotePartyNum Struct Reference . . . 964
8.951.1 Detailed Description . . . 964
8.951.2 Field Documentation . . . 965
8.951.2.1 numLen . . . 965
8.951.2.2 presentationInd . . . 965
8.951.2.3 remPartyNumber . . . 965
8.952 ReqFieldsList Struct Reference . . . 965
8.952.1 Detailed Description . . . 965
8.952.2 Field Documentation . . . 965
8.952.2.1 requestFields . . . 965
8.952.2.2 requestFieldsLen . . . 966
8.953 RespFieldsList Struct Reference . . . 966
8.953.1 Detailed Description . . . 966
8.953.2 Field Documentation . . . 966
8.953.2.1 responseFields . . . 966

8.953.2.2 responseFieldsLen . . . 966
8.954 RFBandInfoElements Struct Reference . . . 966
8.954.1 Detailed Description . . . 966
8.954.2 Field Documentation . . . 967
8.954.2.1 activeBandClass . . . 967
8.954.2.2 activeBandClass . . . 967
8.954.2.3 activeChannel . . . 967
8.954.2.4 activeChannel . . . 967
8.954.2.5 radioInterface . . . 967
8.954.2.6 radioInterface . . . 967
8.955 RfBandInfoExtFormat Struct Reference . . . 967
8.955.1 Detailed Description . . . 967
8.955.2 Field Documentation . . . 968
8.955.2.1 pInstancesSize . . . 968
8.955.2.2 pRfBandInfoExtFormatParam . . . 968
8.955.2.3 TlvPresent . . . 968
8.956 RfBandInfoExtFormatElements Struct Reference . . . 968
8.956.1 Detailed Description . . . 968
8.956.2 Field Documentation . . . 968
8.956.2.1 activeBand . . . 968
8.956.2.2 activeChannel . . . 968
8.956.2.3 radioInterface . . . 968
8.957 RfBandInfoList Struct Reference . . . 969
8.957.1 Detailed Description . . . 969
8.957.2 Field Documentation . . . 969
8.957.2.1 pInstanceSize . . . 969
8.957.2.2 pRFBandInfoParam . . . 969
8.958 RfBandwidthInfo Struct Reference . . . 969
8.958.1 Detailed Description . . . 969
8.958.2 Field Documentation . . . 970
8.958.2.1 pInstancesSize . . . 970
8.958.2.2 pRfBandwidthInfoParam . . . 970
8.958.2.3 TlvPresent . . . 970
8.959 RfBandwidthInfoElements Struct Reference . . . 970
8.959.1 Detailed Description . . . 970
8.959.2 Field Documentation . . . 970
8.959.2.1 bandwidth . . . 970
8.959.2.2 radioInterface . . . 970
8.960 RfDedicatedBandInfo Struct Reference . . . 970
8.960.1 Detailed Description . . . 971

8.960.2 Field Documentation . . . 971
8.960.2.1 pInstancesSize . . . 971
8.960.2.2 pRfDedicatedBandInfoParam . . . 971
8.960.2.3 TlvPresent . . . 971
8.961 RfDedicatedBandInfoElements Struct Reference . . . 971
8.961.1 Detailed Description . . . 971
8.961.2 Field Documentation . . . 972
8.961.2.1 dedicatedBand . . . 972
8.961.2.2 radioInterface . . . 972
8.962 rmTrasnferStaticsReq Struct Reference . . . 972
8.962.1 Detailed Description . . . 972
8.962.2 Field Documentation . . . 972
8.962.2.1 bResetStatistics . . . 972
8.962.2.2 ulMask . . . 972
8.963 roamIndList Struct Reference . . . 972
8.963.1 Detailed Description . . . 973
8.963.2 Field Documentation . . . 973
8.963.2.1 numInstances . . . 973
8.963.2.2 radioInterface . . . 973
8.963.2.3 roamIndicator . . . 973
8.964 RoamingInfo Struct Reference . . . 973
8.964.1 Field Documentation . . . 973
8.964.1.1 roaming_ind . . . 973
8.964.1.2 TlvPresent . . . 973
8.965 roamTimer Struct Reference . . . 973
8.965.1 Detailed Description . . . 974
8.965.2 Field Documentation . . . 974
8.965.2.1 namID . . . 974
8.965.2.2 roamTimerValue . . . 974
8.966 RSRPThresh Struct Reference . . . 974
8.966.1 Detailed Description . . . 974
8.966.2 Field Documentation . . . 975
8.966.2.1 pRSRPThresList . . . 975
8.966.2.2 RSRPThresListLen . . . 975
8.967 rsrqInformation Struct Reference . . . 975
8.967.1 Detailed Description . . . 975
8.967.2 Field Documentation . . . 975
8.967.2.1 radioIf . . . 975
8.967.2.2 rsrq . . . 975
8.968 RSRQThresh Struct Reference . . . 975

8.968.1 Detailed Description . . . 976
8.968.2 Field Documentation . . . 976
8.968.2.1 pRSRQThresList . . . 976
8.968.2.2 RSRQThresListLen . . . 976
8.969 RSSIThresh Struct Reference . . . 976
8.969.1 Detailed Description . . . 976
8.969.2 Field Documentation . . . 977
8.969.2.1 pRSSIThresList . . . 977
8.969.2.2 RSSIThresListLen . . . 977
8.970 RXAGCList Struct Reference . . . 977
8.970.1 Detailed Description . . . 977
8.970.2 Field Documentation . . . 978
8.970.2.1 pRXAIG . . . 978
8.970.2.2 pRXComprSlope . . . 978
8.970.2.3 pRXComprThres . . . 978
8.970.2.4 pRXExpSlope . . . 978
8.970.2.5 pRXExpThres . . . 978
8.970.2.6 pRXStaticGain . . . 978
8.971 RXAVCList Struct Reference . . . 978
8.971.1 Detailed Description . . . 978
8.971.2 Field Documentation . . . 978
8.971.2.1 pAVRXAVCHeadroom . . . 978
8.971.2.2 pAVRXAVCSens . . . 978
8.972 rxInfo Struct Reference . . . 978
8.972.1 Detailed Description . . . 979
8.972.2 Field Documentation . . . 979
8.972.2.1 ecio . . . 979
8.972.2.2 isRadioTuned . . . 979
8.972.2.3 phase . . . 979
8.972.2.4 rscp . . . 979
8.972.2.5 rsrp . . . 979
8.972.2.6 rxPower . . . 979
8.973 RXPCMIIRFltr Struct Reference . . . 980
8.973.1 Detailed Description . . . 980
8.973.2 Field Documentation . . . 981
8.973.2.1 pFlag . . . 981
8.973.2.2 pStage0Val . . . 981
8.973.2.3 pStage1Val . . . 981
8.973.2.4 pStage2Val . . . 981
8.973.2.5 pStage3Val . . . 981

8.973.2.6 pStage4Val . . . 981
8.973.2.7 pStageCnt . . . 981
8.974 RxSigInfo Struct Reference . . . 981
8.974.1 Detailed Description . . . 981
8.974.2 Field Documentation . . . 982
8.974.2.1 isRadioTuned . . . 982
8.974.2.2 rsrp . . . 982
8.974.2.3 rxChainIndex . . . 982
8.974.2.4 rxPower . . . 982
8.975 rxSignalStrengthListElement Struct Reference . . . 982
8.975.1 Detailed Description . . . 982
8.975.2 Field Documentation . . . 983
8.975.2.1 radioIf . . . 983
8.975.2.2 rxSignalStrength . . . 983
8.976 sApnExtraParams Struct Reference . . . 983
8.976.1 Detailed Description . . . 983
8.976.2 Field Documentation . . . 984
8.976.2.1 ambr_dl . . . 984
8.976.2.2 ambr_dl_ext . . . 984
8.976.2.3 ambr_dl_ext2 . . . 984
8.976.2.4 ambr_ul . . . 984
8.976.2.5 ambr_ul_ext . . . 984
8.976.2.6 ambr_ul_ext2 . . . 984
8.976.2.7 apnId . . . 984
8.977 satelliteInfo Struct Reference . . . 984
8.977.1 Detailed Description . . . 985
8.977.2 Field Documentation . . . 986
8.977.2.1 azimuth . . . 986
8.977.2.2 elevation . . . 986
8.977.2.3 gnssSvId . . . 986
8.977.2.4 healthStatus . . . 986
8.977.2.5 snr . . . 986
8.977.2.6 svInfoMask . . . 986
8.977.2.7 svListLen . . . 986
8.977.2.8 svStatus . . . 986
8.977.2.9 system . . . 986
8.977.2.10 validMask . . . 986
8.978 SccRxInfo Struct Reference . . . 987
8.978.1 Detailed Description . . . 987
8.978.2 Field Documentation . . . 987

8.978.2.1 numInstances . . . 987
8.978.2.2 rsrq . . . 987
8.978.2.3 sigInfo . . . 987
8.978.2.4 snr . . . 987
8.978.2.5 TlvPresent . . . 987
8.979 sensorData Struct Reference . . . 987
8.979.1 Detailed Description . . . 988
8.979.2 Field Documentation . . . 989
8.979.2.1 flags . . . 989
8.979.2.2 sensorDataLen . . . 989
8.979.2.3 timeOfFirstSample . . . 989
8.979.2.4 timeOffset . . . 989
8.979.2.5 xAxis . . . 989
8.979.2.6 yAxis . . . 989
8.979.2.7 zAxis . . . 989
8.980 sensorData_t Struct Reference . . . 989
8.980.1 Detailed Description . . . 989
8.980.2 Field Documentation . . . 990
8.980.2.1 flags . . . 990
8.980.2.2 sensorDataLen . . . 990
8.980.2.3 timeOfFirstSample . . . 990
8.980.2.4 timeOffset . . . 990
8.980.2.5 xAxis . . . 990
8.980.2.6 yAxis . . . 990
8.980.2.7 zAxis . . . 990
8.981 sensorDataUsage_s Struct Reference . . . 991
8.981.1 Detailed Description . . . 991
8.981.2 Field Documentation . . . 991
8.981.2.1 aidingIndicatorMask . . . 991
8.981.2.2 usageMask . . . 991
8.982 serialNumbersInfo Struct Reference . . . 991
8.982.1 Detailed Description . . . 992
8.982.2 Field Documentation . . . 992
8.982.2.1 esnSize . . . 992
8.982.2.2 imeiSize . . . 992
8.982.2.3 imeiSvnSize . . . 992
8.982.2.4 meidSize . . . 992
8.982.2.5 pESNString . . . 992
8.982.2.6 pIMEIString . . . 992
8.982.2.7 pImeiSvnString . . . 992

8.982.2.8 pMEIDString . . . 992
8.983 serviceProviderName Struct Reference . . . 993
8.983.1 Detailed Description . . . 993
8.983.2 Field Documentation . . . 993
8.983.2.1 displayCondition . . . 993
8.983.2.2 spn . . . 993
8.983.2.3 spnLength . . . 993
8.984 ServingSystemInfo Struct Reference . . . 993
8.984.1 Detailed Description . . . 993
8.984.2 Field Documentation . . . 994
8.984.2.1 csAttachState . . . 994
8.984.2.2 hdrPersonality . . . 994
8.984.2.3 psAttachState . . . 994
8.984.2.4 radioInterfaceList . . . 995
8.984.2.5 radioInterfaceNo . . . 995
8.984.2.6 registrationState . . . 995
8.984.2.7 selectedNetwork . . . 995
8.985 servSystem Struct Reference . . . 995
8.985.1 Detailed Description . . . 995
8.985.2 Field Documentation . . . 996
8.985.2.1 csAttachState . . . 996
8.985.2.2 numRadioInterfaces . . . 996
8.985.2.3 psAttachState . . . 996
8.985.2.4 radioInterface . . . 996
8.985.2.5 regState . . . 996
8.985.2.6 selNetwork . . . 996
8.986 sessionInfo Union Reference . . . 996
8.986.1 Detailed Description . . . 996
8.986.2 Field Documentation . . . 997
8.986.2.1 omaDmConfig . . . 997
8.986.2.2 omaDmFota . . . 997
8.986.2.3 omaDmNotifications . . . 997
8.987 sessionInfoExt Union Reference . . . 997
8.987.1 Detailed Description . . . 997
8.987.2 Field Documentation . . . 997
8.987.2.1 omaDmConfig . . . 997
8.987.2.2 omaDmFota . . . 997
8.988 sessionInfoTlv Struct Reference . . . 997
8.988.1 Detailed Description . . . 997
8.988.2 Field Documentation . . . 997

8.988.2.1 sessionInfo . . . 997
8.988.2.2 sessionType . . . 997
8.988.2.3 TlvPresent . . . 997
8.989 sessionInfoTlvExt Struct Reference . . . 998
8.989.1 Detailed Description . . . 998
8.989.2 Field Documentation . . . 998
8.989.2.1 sessionInfo . . . 998
8.989.2.2 sessionType . . . 998
8.989.2.3 TlvPresent . . . 998
8.990 SetAudioPathConfigReq Struct Reference . . . 998
8.990.1 Detailed Description . . . 998
8.990.2 Field Documentation . . . 999
8.990.2.1 pCodecSTGain . . . 999
8.990.2.2 pDTMFTXGain . . . 1000
8.990.2.3 pECMode . . . 1000
8.990.2.4 pNSEnable . . . 1000
8.990.2.5 Profile . . . 1000
8.990.2.6 pRXAGCList . . . 1000
8.990.2.7 pRXAVCAGCSwitch . . . 1000
8.990.2.8 pRXAVCList . . . 1000
8.990.2.9 pRXPCMIIRFltr . . . 1000
8.990.2.10 pTXAGCList . . . 1000
8.990.2.11 pTXAVCSwitch . . . 1000
8.990.2.12 pTXGain . . . 1000
8.990.2.13 pTXPCMIIRFltr . . . 1000
8.991 SetAudioProfileReq Struct Reference . . . 1000
8.991.1 Detailed Description . . . 1000
8.991.2 Field Documentation . . . 1001
8.991.2.1 EarMute . . . 1001
8.991.2.2 Generator . . . 1001
8.991.2.3 MicMute . . . 1001
8.991.2.4 Profile . . . 1001
8.991.2.5 Volume . . . 1001
8.992 SetAudioVolTLBConfigReq Struct Reference . . . 1001
8.992.1 Detailed Description . . . 1001
8.992.2 Field Documentation . . . 1002
8.992.2.1 Generator . . . 1002
8.992.2.2 Item . . . 1002
8.992.2.3 Profile . . . 1002
8.992.2.4 Volume . . . 1002

8.992.2.5 VolValue . . . 1002
8.993 SetAudioVolTLBConfigResp Struct Reference . . . 1002
8.993.1 Detailed Description . . . 1002
8.993.2 Field Documentation . . . 1002
8.993.2.1 ResCode . . . 1002
8.994 setCustomSettingV2 Struct Reference . . . 1003
8.994.1 Detailed Description . . . 1003
8.994.2 Field Documentation . . . 1003
8.994.2.1 cust_id . . . 1003
8.994.2.2 cust_value . . . 1003
8.994.2.3 value_length . . . 1003
8.995 setDyingGaspCfg Struct Reference . . . 1003
8.995.1 Detailed Description . . . 1003
8.995.2 Field Documentation . . . 1004
8.995.2.1 pDestSMSContent . . . 1004
8.995.2.2 pDestSMSNum . . . 1004
8.996 SetIMSSMSConfigReq Struct Reference . . . 1004
8.996.1 Detailed Description . . . 1004
8.996.2 Field Documentation . . . 1004
8.996.2.1 pPhoneCtxtURI . . . 1004
8.996.2.2 pPhoneCtxtURILen . . . 1004
8.996.2.3 pSMSFormat . . . 1004
8.996.2.4 pSMSOverIPNwInd . . . 1004
8.997 SetIMSSMSConfigResp Struct Reference . . . 1004
8.997.1 Detailed Description . . . 1005
8.997.2 Field Documentation . . . 1005
8.997.2.1 pSettingResp . . . 1005
8.998 SetIMSUserConfigReq Struct Reference . . . 1005
8.998.1 Detailed Description . . . 1005
8.998.2 Field Documentation . . . 1005
8.998.2.1 pIMSDomain . . . 1005
8.998.2.2 pIMSDomainLen . . . 1005
8.999 SetIMSUserConfigResp Struct Reference . . . 1005
8.999.1 Detailed Description . . . 1006
8.999.2 Field Documentation . . . 1006
8.999.2.1 pSettingResp . . . 1006
8.1000 SetIMSVoIPConfigReq Struct Reference . . . 1006
8.1000.1 Detailed Description . . . 1006
8.1000.2 Field Documentation . . . 1008
8.1000.2.1 pAmrMode . . . 1008

8.1000.2.2 pAmrOctetAligned . . . 1008
8.1000.2.3 pAmrWbEnable . . . 1008
8.1000.2.4 pAmrWBMode . . . 1008
8.1000.2.5 pAmrWBOctetAligned . . . 1008
8.1000.2.6 pMinSessionExpiryTimer . . . 1008
8.1000.2.7 pRingBackTimer . . . 1008
8.1000.2.8 pRingingTimer . . . 1008
8.1000.2.9 pRTPRTCPInactTimer . . . 1008
8.1000.2.10 pScrAmrEnable . . . 1008
8.1000.2.11 pScrAmrWbEnable . . . 1008
8.1000.2.12 pSessionExpiryTimer . . . 1008
8.1001 SetIMSVoIPConfigResp Struct Reference . . . 1008
8.1001.1 Detailed Description . . . 1008
8.1001.2 Field Documentation . . . 1009
8.1001.2.1 pSettingResp . . . 1009
8.1002 SetIntfaceCfgTlv Struct Reference . . . 1009
8.1002.1 Detailed Description . . . 1009
8.1002.2 Field Documentation . . . 1009
8.1002.2.1 CfgValue . . . 1010
8.1003 SetLocGetServerCallbackPara Struct Reference . . . 1010
8.1003.1 Detailed Description . . . 1010
8.1003.2 Field Documentation . . . 1010
8.1003.2.1 pCallback . . . 1010
8.1003.2.2 pReq . . . 1010
8.1004 SetLocSetServerCallbackParam Struct Reference . . . 1010
8.1004.1 Detailed Description . . . 1010
8.1004.2 Field Documentation . . . 1010
8.1004.2.1 pCallback . . . 1011
8.1004.2.2 pReq . . . 1011
8.1005 SetM2MAudioAVCFGReq Struct Reference . . . 1011
8.1005.1 Detailed Description . . . 1011
8.1005.2 Field Documentation . . . 1011
8.1005.2.1 Device . . . 1011
8.1005.2.2 PIFACEId . . . 1011
8.1005.2.3 pPCMParams . . . 1011
8.1005.2.4 Profile . . . 1011
8.1006 SetM2MAudioLPBKReq Struct Reference . . . 1011
8.1006.1 Detailed Description . . . 1012
8.1006.2 Field Documentation . . . 1012
8.1006.2.1 Enable . . . 1012

8.1007 SetM2MAudioProfileReq Struct Reference . . . 1012
8.1007.1 Detailed Description . . . 1012
8.1007.2 Field Documentation . . . 1013
8.1007.2.1 pCwtMute . . . 1013
8.1007.2.2 pEarMute . . . 1013
8.1007.2.3 pGenerator . . . 1013
8.1007.2.4 pMicMute . . . 1013
8.1007.2.5 Profile . . . 1013
8.1007.2.6 pVolume . . . 1013
8.1008 SetM2MAudioVolumeReq Struct Reference . . . 1013
8.1008.1 Detailed Description . . . 1013
8.1008.2 Field Documentation . . . 1014
8.1008.2.1 Generator . . . 1014
8.1008.2.2 Level . . . 1014
8.1008.2.3 Profile . . . 1014
8.1009 SetM2MAVMuteReq Struct Reference . . . 1014
8.1009.1 Detailed Description . . . 1014
8.1009.2 Field Documentation . . . 1014
8.1009.2.1 EarMute . . . 1014
8.1009.2.2 MicMute . . . 1014
8.1009.2.3 pCwtMute . . . 1014
8.1009.2.4 Profile . . . 1014
8.1010 SetM2MSpkrGainReq Struct Reference . . . 1014
8.1010.1 Detailed Description . . . 1015
8.1010.2 Field Documentation . . . 1015
8.1010.2.1 Profile . . . 1015
8.1010.2.2 Value . . . 1015
8.1011 setPINProtection Struct Reference . . . 1015
8.1011.1 Detailed Description . . . 1015
8.1011.2 Field Documentation . . . 1016
8.1011.2.1 pinID . . . 1016
8.1011.2.2 pinLength . . . 1016
8.1011.2.3 pinOperation . . . 1016
8.1011.2.4 pinValue . . . 1016
8.1012 SetRegMgrConfigReq Struct Reference . . . 1016
8.1012.1 Detailed Description . . . 1016
8.1012.2 Field Documentation . . . 1016
8.1012.2.1 pCSCFPortName . . . 1017
8.1012.2.2 pCSCFPortNameLen . . . 1017
8.1012.2.3 pIMSTestMode . . . 1017

8.1012.2.4 pPriCSCFPort . . . 1017
8.1013 SetRegMgrConfigResp Struct Reference . . . 1017
8.1013.1 Detailed Description . . . 1017
8.1013.2 Field Documentation . . . 1017
8.1013.2.1 pSettingResp . . . 1017
8.1014 SetSignalStrengthInfo Struct Reference . . . 1017
8.1014.1 Detailed Description . . . 1018
8.1014.2 Field Documentation . . . 1021
8.1014.2.1 pCDMAECIODelta . . . 1021
8.1014.2.2 pCDMAECIOThresh . . . 1021
8.1014.2.3 pCDMARSSIDelta . . . 1021
8.1014.2.4 pCDMARSSIThresh . . . 1021
8.1014.2.5 pGSMRSSIDelta . . . 1021
8.1014.2.6 pGSMRSSIThresh . . . 1021
8.1014.2.7 pHDRECIODelta . . . 1021
8.1014.2.8 pHDRECIOThresh . . . 1021
8.1014.2.9 pHDRIODelta . . . 1021
8.1014.2.10 pHDRIOThresh . . . 1021
8.1014.2.11 pHDRRSSIDelta . . . 1021
8.1014.2.12 pHDRRSSIThresh . . . 1021
8.1014.2.13 pHDRSINRDelta . . . 1021
8.1014.2.14 pHDRSINRThresh . . . 1021
8.1014.2.15 pLTERSRPDelta . . . 1021
8.1014.2.16 pLTERSRPThresh . . . 1021
8.1014.2.17 pLTERSRQDelta . . . 1021
8.1014.2.18 pLTERSRQThresh . . . 1021
8.1014.2.19 pLTERSSIDelta . . . 1021
8.1014.2.20 pLTERSSIThresh . . . 1021
8.1014.2.21 pLTESigRptConfig . . . 1021
8.1014.2.22 pLTESNRDelta . . . 1021
8.1014.2.23 pLTESNRThresh . . . 1021
8.1014.2.24 pTDSCDMAECIODelta . . . 1021
8.1014.2.25 pTDSCDMAECIOThresh . . . 1021
8.1014.2.26 pTDSCDMARSCPDelta . . . 1021
8.1014.2.27 pTDSCDMARSCPThresh . . . 1021
8.1014.2.28 pTDSCDMARSSIDelta . . . 1022
8.1014.2.29 pTDSCDMARSSIThresh . . . 1022
8.1014.2.30 pTDSCDMASINRDelta . . . 1022
8.1014.2.31 pTDSCDMASINRThresh . . . 1022
8.1014.2.32 pWCDMAECIODelta . . . 1022

8.1014.2.33 pWCDMAECIOThresh . . . 1022
8.1014.2.34 pWCDMARSSIDelta . . . 1022
8.1014.2.35 pWCDMARSSIThresh . . . 1022
8.1015 SetSIPConfigReq Struct Reference . . . 1022
8.1015.1 Detailed Description . . . 1022
8.1015.2 Field Documentation . . . 1023
8.1015.2.1 pSigCompEnabled . . . 1023
8.1015.2.2 pSIPLocalPort . . . 1023
8.1015.2.3 pSubscribeTimer . . . 1023
8.1015.2.4 pTimerSIPReg . . . 1023
8.1015.2.5 pTimerT1 . . . 1023
8.1015.2.6 pTimerT2 . . . 1023
8.1015.2.7 pTimerTf . . . 1023
8.1016 SetSIPConfigResp Struct Reference . . . 1023
8.1016.1 Detailed Description . . . 1023
8.1016.2 Field Documentation . . . 1023
8.1016.2.1 pSettingResp . . . 1023
8.1017 GetDeviceSeriesResult Struct Reference . . . 1023
8.1017.1 Detailed Description . . . 1024
8.1017.2 Field Documentation . . . 1024
8.1017.2.1 eDevice . . . 1024
8.1017.2.2 uResult . . . 1024
8.1018 sidNid Struct Reference . . . 1024
8.1018.1 Detailed Description . . . 1024
8.1018.2 Field Documentation . . . 1024
8.1018.2.1 nid . . . 1024
8.1018.2.2 sid . . . 1024
8.1019 SigInfo Struct Reference . . . 1024
8.1019.1 Detailed Description . . . 1025
8.1019.2 Field Documentation . . . 1025
8.1019.2.1 pECIOThresh . . . 1025
8.1019.2.2 pHDRSINRThresh . . . 1025
8.1019.2.3 pIOThresh . . . 1026
8.1019.2.4 pLTESigRptCfg . . . 1026
8.1019.2.5 pLTESNRThresh . . . 1026
8.1019.2.6 pRSRPThresh . . . 1026
8.1019.2.7 pRSRQThresh . . . 1026
8.1019.2.8 pRSSIThresh . . . 1026
8.1019.2.9 pTDSCDMASINRCONFThresh . . . 1026
8.1020 SignalInfo Struct Reference . . . 1026

8.1020.1 Detailed Description . . . 1026
8.1020.2 Field Documentation . . . 1026
8.1020.2.1 alertPitch . . . 1026
8.1020.2.2 signal . . . 1026
8.1020.2.3 signalType . . . 1026
8.1021 SignalStrengthDataType Struct Reference . . . 1026
8.1021.1 Field Documentation . . . 1027
8.1021.1.1 thresholds . . . 1027
8.1021.1.2 thresholdsSize . . . 1027
8.1022 SimBusyStatus Struct Reference . . . 1027
8.1022.1 Detailed Description . . . 1027
8.1022.2 Field Documentation . . . 1027
8.1022.2.1 simBusy . . . 1027
8.1022.2.2 simBusyLength . . . 1027
8.1023 Slot_t Struct Reference . . . 1027
8.1023.1 Detailed Description . . . 1027
8.1023.2 Field Documentation . . . 1028
8.1023.2.1 bICCID . . . 1028
8.1023.2.2 bICCIDLength . . . 1028
8.1023.2.3 bLogicalSlot . . . 1028
8.1023.2.4 uPhyCardStatus . . . 1028
8.1023.2.5 uPhySlotStatus . . . 1028
8.1024 SlotInf Struct Reference . . . 1028
8.1024.1 Detailed Description . . . 1029
8.1024.2 Field Documentation . . . 1030
8.1024.2.1 AppStatus . . . 1030
8.1024.2.2 cardState . . . 1030
8.1024.2.3 errorState . . . 1030
8.1024.2.4 numApp . . . 1030
8.1024.2.5 upinRetries . . . 1030
8.1024.2.6 upinState . . . 1030
8.1024.2.7 upukRetries . . . 1030
8.1025 SlotInfo Struct Reference . . . 1030
8.1025.1 Detailed Description . . . 1030
8.1025.2 Field Documentation . . . 1031
8.1025.2.1 AppStatus . . . 1031
8.1025.2.2 cardState . . . 1031
8.1025.2.3 errorState . . . 1031
8.1025.2.4 numApp . . . 1031
8.1025.2.5 upinRetries . . . 1031

8.1025.2.6 upinState . . . 1031
8.1025.2.7 upukRetries . . . 1031
8.1026 slots_t Struct Reference . . . 1031
8.1026.1 Detailed Description . . . 1032
8.1026.2 Field Documentation . . . 1032
8.1026.2.1 uimSlotStatus . . . 1032
8.1027 slqsautoconnect Struct Reference . . . 1032
8.1027.1 Detailed Description . . . 1032
8.1027.2 Field Documentation . . . 1032
8.1027.2.1 acroamsetting . . . 1032
8.1027.2.2 acsetting . . . 1032
8.1027.2.3 action . . . 1032
8.1028 SLQSDeleteProfileParams Struct Reference . . . 1033
8.1028.1 Detailed Description . . . 1033
8.1028.2 Field Documentation . . . 1033
8.1028.2.1 profileIndex . . . 1033
8.1028.2.2 profileType . . . 1033
8.1029 slqsfwinfo_s Struct Reference . . . 1033
8.1029.1 Detailed Description . . . 1033
8.1029.2 Field Documentation . . . 1034
8.1029.2.1 appversion_str . . . 1034
8.1029.2.2 bootversion_str . . . 1034
8.1029.2.3 carrier_str . . . 1034
8.1029.2.4 cur_carr_name . . . 1034
8.1029.2.5 cur_carr_rev . . . 1034
8.1029.2.6 modelid_str . . . 1034
8.1029.2.7 packageid_str . . . 1034
8.1029.2.8 priversion_str . . . 1034
8.1029.2.9 sku_str . . . 1034
8.1030 slqsfwpartno_s Struct Reference . . . 1034
8.1030.1 Detailed Description . . . 1035
8.1030.2 Field Documentation . . . 1035
8.1030.2.1 partno_str . . . 1035
8.1031 SlqsNas3GppNetworkInfo Struct Reference . . . 1035
8.1031.1 Detailed Description . . . 1035
8.1031.2 Field Documentation . . . 1036
8.1031.2.1 Description . . . 1036
8.1031.2.2 Forbidden . . . 1036
8.1031.2.3 InUse . . . 1036
8.1031.2.4 MCC . . . 1036

8.1031.2.5 MNC . . . 1036
8.1031.2.6 Preferred . . . 1036
8.1031.2.7 Roaming . . . 1036
8.1032 SlqsNasPCICellInfo Struct Reference . . . 1036
8.1032.1 Detailed Description . . . 1036
8.1032.2 Field Documentation . . . 1037
8.1032.2.1 cellID . . . 1037
8.1032.2.2 freq . . . 1037
8.1032.2.3 GlobalCellID . . . 1037
8.1032.2.4 PlmnLen . . . 1037
8.1032.2.5 slqsNasPcsDigit . . . 1037
8.1033 SlqsNasPCIInfo Struct Reference . . . 1037
8.1033.1 Detailed Description . . . 1037
8.1033.2 Field Documentation . . . 1038
8.1033.2.1 PCICellInfo . . . 1038
8.1033.2.2 PCICellInfoLen . . . 1038
8.1033.2.3 rsrp . . . 1038
8.1033.2.4 rsrpRx0 . . . 1038
8.1033.2.5 rsrpRx1 . . . 1038
8.1033.2.6 rsrq . . . 1038
8.1033.2.7 rsrqRx0 . . . 1038
8.1033.2.8 rsrqRx1 . . . 1038
8.1034 SlqsNasPcsDigit Struct Reference . . . 1038
8.1034.1 Detailed Description . . . 1038
8.1034.2 Field Documentation . . . 1039
8.1034.2.1 includes_pcs_digit . . . 1039
8.1034.2.2 MCC . . . 1039
8.1034.2.3 MNC . . . 1039
8.1035 slqssendasyncsmsparams_s Struct Reference . . . 1039
8.1035.1 Detailed Description . . . 1039
8.1035.2 Field Documentation . . . 1040
8.1035.2.1 messageFormat . . . 1041
8.1035.2.2 messageSize . . . 1041
8.1035.2.3 pFollowOnDC . . . 1041
8.1035.2.4 pForceOnDC . . . 1041
8.1035.2.5 pLinktimer . . . 1041
8.1035.2.6 pMessage . . . 1041
8.1035.2.7 pRetryMessage . . . 1041
8.1035.2.8 pRetryMessageId . . . 1041
8.1035.2.9 pServiceOption . . . 1041

8.1035.2.10 pSmsOnIms . . . 1041
8.1035.2.11 pUserData . . . 1041
8.1036 qlqssendsmsparams_s Struct Reference . . . 1041
8.1036.1 Detailed Description . . . 1041
8.1036.2 Field Documentation . . . 1042
8.1036.2.1 messageFailureCode . . . 1042
8.1036.2.2 messageFormat . . . 1042
8.1036.2.3 messageID . . . 1042
8.1036.2.4 messageSize . . . 1042
8.1036.2.5 pLinktimer . . . 1042
8.1036.2.6 pMessage . . . 1042
8.1036.2.7 pSmsOnIms . . . 1042
8.1037 qlqsSessionStateInfo Struct Reference . . . 1042
8.1037.1 Detailed Description . . . 1042
8.1037.2 Field Documentation . . . 1043
8.1037.2.1 pQmiInterfaceInfo . . . 1043
8.1037.2.2 reconfiguration_required . . . 1043
8.1037.2.3 sessionEndReason . . . 1043
8.1037.2.4 state . . . 1043
8.1038 SLQSSetDHCPv4ClientLeaseStatusCallbackParam Struct Reference . . . 1043
8.1038.1 Detailed Description . . . 1043
8.1038.2 Field Documentation . . . 1043
8.1038.2.1 instance . . . 1043
8.1038.2.2 pCallback . . . 1043
8.1039 qlqsSignalStrengthInfo Struct Reference . . . 1044
8.1039.1 Detailed Description . . . 1044
8.1039.2 Field Documentation . . . 1045
8.1039.2.1 ecioList . . . 1045
8.1039.2.2 ecioListLen . . . 1045
8.1039.2.3 errorRateList . . . 1045
8.1039.2.4 errorRateListLen . . . 1045
8.1039.2.5 io . . . 1045
8.1039.2.6 rsrp . . . 1045
8.1039.2.7 rsnr . . . 1046
8.1039.2.8 srqInfo . . . 1046
8.1039.2.9 rxSignalStrengthList . . . 1046
8.1039.2.10 rxSignalStrengthListLen . . . 1046
8.1039.2.11 signalStrengthReqMask . . . 1046
8.1039.2.12 snr . . . 1046
8.1040 SLQSSignalStrengthsIndReq Struct Reference . . . 1046

8.1040.1 Detailed Description . . . 1046
8.1040.2 Field Documentation . . . 1047
8.1040.2.1 ecioDelta . . . 1047
8.1040.2.2 ecioThresholdList . . . 1047
8.1040.2.3 ecioThresholdListLen . . . 1047
8.1040.2.4 ioDelta . . . 1047
8.1040.2.5 lteRsrpDelta . . . 1047
8.1040.2.6 lteSnrDelta . . . 1047
8.1040.2.7 rsrqDelta . . . 1047
8.1040.2.8 rxSignalStrengthDelta . . . 1047
8.1040.2.9 sinrDelta . . . 1047
8.1040.2.10 sinrThresholdList . . . 1047
8.1040.2.11 sinrThresholdListLen . . . 1048
8.1041 SLQSSignalStrengthsInformation Struct Reference . . . 1048
8.1041.1 Detailed Description . . . 1048
8.1041.2 Field Documentation . . . 1049
8.1041.2.1 ecioInfo . . . 1049
8.1041.2.2 errorRateInfo . . . 1049
8.1041.2.3 io . . . 1049
8.1041.2.4 lteRsrpinfo . . . 1049
8.1041.2.5 lteSnrinfo . . . 1049
8.1041.2.6 rsrqInfo . . . 1049
8.1041.2.7 rxSignalStrengthInfo . . . 1049
8.1041.2.8 sinr . . . 1049
8.1042 SLQSTmdMitigationLvlRptCallbackParam Struct Reference . . . 1049
8.1042.1 Detailed Description . . . 1049
8.1042.2 Field Documentation . . . 1049
8.1042.2.1 pCallback . . . 1049
8.1042.2.2 pReq . . . 1049
8.1043 slqsWdsEventInfo Struct Reference . . . 1049
8.1043.1 Detailed Description . . . 1050
8.1043.2 Field Documentation . . . 1050
8.1043.2.1 pDataBearer . . . 1051
8.1043.2.2 pDormancyStatus . . . 1051
8.1043.2.3 pPacketsCountRX . . . 1051
8.1043.2.4 pPacketsCountTX . . . 1051
8.1043.2.5 pQmiInterfaceInfo . . . 1051
8.1043.2.6 pTotalBytesRX . . . 1051
8.1043.2.7 pTotalBytesTX . . . 1051
8.1044 sms_BroadcastConfig Struct Reference . . . 1051

8.1044.1 Detailed Description . . . 1051
8.1044.2 Field Documentation . . . 1051
8.1044.2.1 fromServiceId . . . 1051
8.1044.2.2 selected . . . 1051
8.1044.2.3 toServiceId . . . 1051
8.1045 sms_CDMABroadcastConfig Struct Reference . . . 1051
8.1045.1 Detailed Description . . . 1052
8.1045.2 Field Documentation . . . 1052
8.1045.2.1 language . . . 1052
8.1045.2.2 selected . . . 1052
8.1045.2.3 serviceCategory . . . 1052
8.1046 sms_DateTime Struct Reference . . . 1052
8.1046.1 Field Documentation . . . 1052
8.1046.1.1 data . . . 1052
8.1047 sms_getIndicationReg Struct Reference . . . 1052
8.1047.1 Detailed Description . . . 1052
8.1047.2 Field Documentation . . . 1053
8.1047.2.1 pRegCallStatInfoEvt . . . 1053
8.1047.2.2 pRegTransLayerInfoEvt . . . 1053
8.1047.2.3 pRegTransNWRegInfoEvt . . . 1053
8.1048 sms_getMsgWaitingInfo Struct Reference . . . 1053
8.1048.1 Detailed Description . . . 1053
8.1048.2 Field Documentation . . . 1053
8.1048.2.1 msgWaitInfo . . . 1054
8.1048.2.2 numInstances . . . 1054
8.1049 sms_getTransLayerInfo Struct Reference . . . 1054
8.1049.1 Detailed Description . . . 1054
8.1049.2 Field Documentation . . . 1054
8.1049.2.1 pRegInd . . . 1054
8.1049.2.2 pTransLayerInfo . . . 1054
8.1050 sms_getTransNWRegInfo Struct Reference . . . 1054
8.1050.1 Detailed Description . . . 1054
8.1050.2 Field Documentation . . . 1055
8.1050.2.1 pRegStatus . . . 1055
8.1051 sms_maxStorageSizeReq Struct Reference . . . 1055
8.1051.1 Detailed Description . . . 1055
8.1051.2 Field Documentation . . . 1055
8.1051.2.1 pMessageMode . . . 1055
8.1051.2.2 storageType . . . 1055
8.1052 sms_maxStorageSizeResp Struct Reference . . . 1055

8.1052.1 Detailed Description . . . 1056
8.1052.2 Field Documentation . . . 1056
8.1052.2.1 freeSlots . . . 1056
8.1052.2.2 maxStorageSize . . . 1056
8.1053 sms_messageWaitingInfoContent Struct Reference . . . 1056
8.1053.1 Detailed Description . . . 1056
8.1053.2 Field Documentation . . . 1057
8.1053.2.1 activeInd . . . 1057
8.1053.2.2 msgCount . . . 1057
8.1053.2.3 msgType . . . 1057
8.1054 sms_msgProtocolResp Struct Reference . . . 1057
8.1054.1 Detailed Description . . . 1057
8.1054.2 Field Documentation . . . 1057
8.1054.2.1 msgProtocol . . . 1057
8.1055 sms_qaQmi3GPP2BroadcastCfgInfo Struct Reference . . . 1057
8.1055.1 Detailed Description . . . 1057
8.1055.2 Field Documentation . . . 1058
8.1055.2.1 activated_ind . . . 1058
8.1055.2.2 CDMABroadcastConfig . . . 1058
8.1055.2.3 num_instances . . . 1058
8.1056 sms_qaQmi3GPPBroadcastCfgInfo Struct Reference . . . 1058
8.1056.1 Detailed Description . . . 1058
8.1056.2 Field Documentation . . . 1059
8.1056.2.1 activated_ind . . . 1059
8.1056.2.2 broadcastConfig . . . 1059
8.1056.2.3 num_instances . . . 1059
8.1057 sms_routeEntry Struct Reference . . . 1059
8.1057.1 Detailed Description . . . 1059
8.1057.2 Field Documentation . . . 1060
8.1057.2.1 messageClass . . . 1060
8.1057.2.2 messageType . . . 1060
8.1057.2.3 receiptAction . . . 1060
8.1057.2.4 routeStorage . . . 1060
8.1058 sms_sendAsyncsmsParams Struct Reference . . . 1060
8.1058.1 Detailed Description . . . 1060
8.1058.2 Field Documentation . . . 1062
8.1058.2.1 messageFormat . . . 1062
8.1058.2.2 messageSize . . . 1062
8.1058.2.3 pFollowOnDC . . . 1062
8.1058.2.4 pForceOnDC . . . 1062

8.1058.2.5 pLinktimer . . . 1062
8.1058.2.6 pMessage . . . 1062
8.1058.2.7 pRetryMessage . . . 1062
8.1058.2.8 pRetryMessageId . . . 1062
8.1058.2.9 pServiceOption . . . 1062
8.1058.2.10 pSmsOnIms . . . 1062
8.1058.2.11 pUserData . . . 1062
8.1059 sms_setIndicationReg Struct Reference . . . 1062
8.1059.1 Detailed Description . . . 1062
8.1059.2 Field Documentation . . . 1063
8.1059.2.1 pRegCallStatInfoEvt . . . 1063
8.1059.2.2 pRegTransLayerInfoEvt . . . 1063
8.1059.2.3 pRegTransNWRegInfoEvt . . . 1063
8.1060 sms_setRoutesReq Struct Reference . . . 1063
8.1060.1 Detailed Description . . . 1063
8.1060.2 Field Documentation . . . 1063
8.1060.2.1 numOfRoutes . . . 1063
8.1060.2.2 pTransferStatusReport . . . 1063
8.1060.2.3 routeList . . . 1063
8.1061 sms_timestemp Struct Reference . . . 1063
8.1061.1 Field Documentation . . . 1064
8.1061.1.1 data . . . 1064
8.1062 sms_transLayerInfo Struct Reference . . . 1064
8.1062.1 Detailed Description . . . 1064
8.1062.2 Field Documentation . . . 1064
8.1062.2.1 TransCap . . . 1064
8.1062.2.2 TransType . . . 1064
8.1063 SMSAsyncRawSend_s Struct Reference . . . 1064
8.1063.1 Detailed Description . . . 1065
8.1063.2 Field Documentation . . . 1066
8.1063.2.1 alphaIDLen . . . 1066
8.1063.2.2 causeCode . . . 1066
8.1063.2.3 errorClass . . . 1066
8.1063.2.4 messageID . . . 1066
8.1063.2.5 msgDelFailureCause . . . 1066
8.1063.2.6 msgDelFailureType . . . 1066
8.1063.2.7 pAlphaID . . . 1066
8.1063.2.8 results . . . 1066
8.1063.2.9 RPCause . . . 1066
8.1063.2.10 sendStatus . . . 1066

8.1063.2.11TPCause . . . 1066
8.1063.2.12UserData . . . 1066
8.1064SMSCAddress Struct Reference . . . 1066
8.1064.1Detailed Description . . . 1066
8.1064.2Field Documentation . . . 1066
8.1064.2.1data . . . 1067
8.1064.2.2length . . . 1067
8.1065SMSCAddressInfo Struct Reference . . . 1067
8.1065.1Detailed Description . . . 1067
8.1065.2Field Documentation . . . 1067
8.1065.2.1data . . . 1067
8.1065.2.2length . . . 1067
8.1066SMSCAddressTlv Struct Reference . . . 1067
8.1066.1Detailed Description . . . 1067
8.1066.2Field Documentation . . . 1067
8.1066.2.1SMSCInfo . . . 1068
8.1066.2.2TlvPresent . . . 1068
8.1067SMSEtwsMessage Struct Reference . . . 1068
8.1067.1Detailed Description . . . 1068
8.1067.2Field Documentation . . . 1068
8.1067.2.1data . . . 1068
8.1067.2.2length . . . 1068
8.1067.2.3notificationType . . . 1068
8.1068SMSEtwsMessageInfo Struct Reference . . . 1068
8.1068.1Detailed Description . . . 1068
8.1068.2Field Documentation . . . 1069
8.1068.2.1data . . . 1069
8.1068.2.2length . . . 1069
8.1068.2.3notificationType . . . 1069
8.1069SMSEtwsMessageTlv Struct Reference . . . 1069
8.1069.1Detailed Description . . . 1069
8.1069.2Field Documentation . . . 1069
8.1069.2.1EtwsMessageInfo . . . 1069
8.1069.2.2TlvPresent . . . 1069
8.1070SMSEtwsPlmn Struct Reference . . . 1069
8.1070.1Detailed Description . . . 1070
8.1070.2Field Documentation . . . 1070
8.1070.2.1mobileCountryCode . . . 1070
8.1070.2.2mobileNetworkCode . . . 1070
8.1071SMSEtwsPlmnInfo Struct Reference . . . 1070

8.1071.1 Detailed Description . . . 1070
8.1071.2 Field Documentation . . . 1070
8.1071.2.1 mobileCountryCode . . . 1070
8.1071.2.2 mobileNetworkCode . . . 1070
8.1072 SMSEventInfo_s Struct Reference . . . 1070
8.1072.1 Detailed Description . . . 1071
8.1072.2 Field Documentation . . . 1071
8.1072.2.1 pEtwsMessageInfo . . . 1071
8.1072.2.2 pEtwsPlmnInfo . . . 1071
8.1072.2.3 pMessageModeInfo . . . 1071
8.1072.2.4 pMTMessageInfo . . . 1071
8.1072.2.5 pSMSCAddressInfo . . . 1072
8.1072.2.6 pSMSOnIMSInfo . . . 1072
8.1072.2.7 pTransferRouteMTMessageInfo . . . 1072
8.1072.2.8 smsEventType . . . 1072
8.1073 smsMaxStorageSizeReq Struct Reference . . . 1072
8.1073.1 Detailed Description . . . 1072
8.1073.2 Field Documentation . . . 1072
8.1073.2.1 pMessageMode . . . 1072
8.1073.2.2 storageType . . . 1072
8.1074 smsMaxStorageSizeResp Struct Reference . . . 1072
8.1074.1 Detailed Description . . . 1072
8.1074.2 Field Documentation . . . 1073
8.1074.2.1 freeSlots . . . 1073
8.1074.2.2 maxStorageSize . . . 1073
8.1075 SMSMemoryInfo Struct Reference . . . 1073
8.1075.1 Detailed Description . . . 1073
8.1075.2 Field Documentation . . . 1073
8.1075.2.1 messageMode . . . 1073
8.1075.2.2 results . . . 1073
8.1075.2.3 storageType . . . 1073
8.1076 SMSMessageMode Struct Reference . . . 1073
8.1076.1 Detailed Description . . . 1074
8.1076.2 Field Documentation . . . 1074
8.1076.2.1 messageMode . . . 1074
8.1077 SMSMessageModeInfo Struct Reference . . . 1074
8.1077.1 Detailed Description . . . 1074
8.1077.2 Field Documentation . . . 1074
8.1077.2.1 messageMode . . . 1074
8.1078 smsMsgprotocolResp Struct Reference . . . 1074

8.1078.1 Detailed Description . . . 1074
8.1078.2 Field Documentation . . . 1075
8.1078.2.1 msgProtocol . . . 1075
8.1079 SMSMTMessage Struct Reference . . . 1075
8.1079.1 Detailed Description . . . 1075
8.1079.2 Field Documentation . . . 1075
8.1079.2.1 messageIndex . . . 1075
8.1079.2.2 storageType . . . 1075
8.1080 SMSMTMessageInfo Struct Reference . . . 1075
8.1080.1 Detailed Description . . . 1075
8.1080.2 Field Documentation . . . 1076
8.1080.2.1 messageIndex . . . 1076
8.1080.2.2 storageType . . . 1076
8.1081 SMSOnIMS Struct Reference . . . 1076
8.1081.1 Detailed Description . . . 1076
8.1081.2 Field Documentation . . . 1076
8.1081.2.1 smsOnIMS . . . 1076
8.1082 SMSOnIMSInfo Struct Reference . . . 1076
8.1082.1 Detailed Description . . . 1076
8.1082.2 Field Documentation . . . 1076
8.1082.2.1 smsOnIMS . . . 1076
8.1083 SMSOnIMSTlv Struct Reference . . . 1077
8.1083.1 Detailed Description . . . 1077
8.1083.2 Field Documentation . . . 1077
8.1083.2.1 IMSInfo . . . 1077
8.1083.2.2 TlvPresent . . . 1077
8.1084 smsRouteEntry Struct Reference . . . 1077
8.1084.1 Detailed Description . . . 1077
8.1084.2 Field Documentation . . . 1078
8.1084.2.1 messageClass . . . 1078
8.1084.2.2 messageType . . . 1078
8.1084.2.3 receiptAction . . . 1078
8.1084.2.4 routeStorage . . . 1078
8.1085 smsSetRoutesReq Struct Reference . . . 1078
8.1085.1 Detailed Description . . . 1079
8.1085.2 Field Documentation . . . 1079
8.1085.2.1 numOfRoutes . . . 1079
8.1085.2.2 pTransferStatusReport . . . 1079
8.1085.2.3 routeList . . . 1079
8.1086 SMSTransferRouteMTMessage Struct Reference . . . 1079

8.1086.1 Detailed Description . . . 1079
8.1086.2 Field Documentation . . . 1080
8.1086.2.1 ackIndicator . . . 1080
8.1086.2.2 data . . . 1080
8.1086.2.3 format . . . 1080
8.1086.2.4 length . . . 1080
8.1086.2.5 transactionID . . . 1080
8.1087 SMSTransferRouteMTMessageInfo Struct Reference . . . 1080
8.1087.1 Detailed Description . . . 1080
8.1087.2 Field Documentation . . . 1080
8.1087.2.1 ackIndicator . . . 1081
8.1087.2.2 data . . . 1081
8.1087.2.3 format . . . 1081
8.1087.2.4 length . . . 1081
8.1087.2.5 transactionID . . . 1081
8.1088 QosFlowStat Struct Reference . . . 1081
8.1088.1 Detailed Description . . . 1081
8.1088.2 Field Documentation . . . 1081
8.1088.2.1 bearerId . . . 1081
8.1088.2.2 tx_bytes . . . 1081
8.1088.2.3 tx_bytes_drp . . . 1081
8.1088.2.4 tx_pkt . . . 1081
8.1088.2.5 tx_pkt_drp . . . 1081
8.1089 QosStat Struct Reference . . . 1082
8.1089.1 Detailed Description . . . 1082
8.1089.2 Field Documentation . . . 1082
8.1089.2.1 apnId . . . 1083
8.1089.2.2 numQosFlow . . . 1083
8.1089.2.3 qosFlow . . . 1083
8.1089.2.4 total_rx_bytes . . . 1083
8.1089.2.5 total_rx_pkt . . . 1083
8.1089.2.6 total_tx_bytes . . . 1083
8.1089.2.7 total_tx_bytes_drp . . . 1083
8.1089.2.8 total_tx_pkt . . . 1083
8.1089.2.9 total_tx_pkt_drp . . . 1083
8.1090 SrvStatusInfo Struct Reference . . . 1083
8.1090.1 Detailed Description . . . 1083
8.1090.2 Field Documentation . . . 1083
8.1090.2.1 isPrefDataPath . . . 1083
8.1090.2.2 srvStatus . . . 1083

8.1091 wdsdatasession_params Struct Reference . . . 1084
8.1091.1 Detailed Description . . . 1084
8.1091.2 Field Documentation . . . 1086
8.1091.2.1 action . . . 1086
8.1091.2.2 failureReason . . . 1086
8.1091.2.3 failureReasonv4 . . . 1086
8.1091.2.4 failureReasonv6 . . . 1086
8.1091.2.5 instanceId . . . 1086
8.1091.2.6 ipfamily . . . 1086
8.1091.2.7 pAuthentication . . . 1086
8.1091.2.8 pPassword . . . 1086
8.1091.2.9 pProfileId3GPP . . . 1086
8.1091.2.10 pProfileId3GPP2 . . . 1086
8.1091.2.11 pTechnology . . . 1086
8.1091.2.12 pUsername . . . 1086
8.1091.2.13 pv4 . . . 1086
8.1091.2.14 pv6 . . . 1086
8.1091.2.15 sessionId . . . 1086
8.1091.2.16 v4sessionId . . . 1086
8.1091.2.17 v6sessionId . . . 1086
8.1091.2.18 verbFailReason . . . 1086
8.1091.2.19 verbFailReasonType . . . 1086
8.1092 SupportedIntBitmaskTlv Struct Reference . . . 1086
8.1092.1 Detailed Description . . . 1087
8.1092.2 Field Documentation . . . 1087
8.1092.2.1 TlvPresent . . . 1087
8.1092.2.2 ValidBitmasks . . . 1087
8.1093 SupportedMsgList Struct Reference . . . 1087
8.1093.1 Detailed Description . . . 1087
8.1093.2 Field Documentation . . . 1087
8.1093.2.1 supportedMsgLen . . . 1087
8.1093.2.2 supportedMsgs . . . 1087
8.1094 SUPSInfo Struct Reference . . . 1087
8.1094.1 Detailed Description . . . 1088
8.1094.2 Field Documentation . . . 1088
8.1094.2.1 isModByCC . . . 1088
8.1094.2.2 svcType . . . 1088
8.1095 SV Struct Reference . . . 1088
8.1095.1 Detailed Description . . . 1088
8.1095.2 Field Documentation . . . 1089

8.1095.2.1id . . . 1089
8.1095.2.2mask . . . 1089
8.1095.2.3system . . . 1089
8.1096SVInfo Struct Reference . . . 1089
8.1096.1Detailed Description . . . 1089
8.1096.2Field Documentation . . . 1089
8.1096.2.1len . . . 1090
8.1096.2.2pSV . . . 1090
8.1097SvUsedforFix_s Struct Reference . . . 1090
8.1097.1Detailed Description . . . 1090
8.1097.2Field Documentation . . . 1090
8.1097.2.1gnssSvUsedList . . . 1090
8.1097.2.2gnssSvUsedList_len . . . 1090
8.1098SWI_STRUCT_CarrierImage Struct Reference . . . 1090
8.1098.1Detailed Description . . . 1090
8.1098.2Field Documentation . . . 1091
8.1098.2.1m_FwBuildId . . . 1091
8.1098.2.2m_FwImageId . . . 1091
8.1098.2.3m_nCarrierId . . . 1091
8.1098.2.4m_nFolderId . . . 1091
8.1098.2.5m_nStorage . . . 1091
8.1098.2.6m_PriBuildId . . . 1091
8.1098.2.7m_PriImageId . . . 1091
8.1099swi_uint256_t Struct Reference . . . 1091
8.1099.1Detailed Description . . . 1091
8.1099.2Field Documentation . . . 1092
8.1099.2.1word . . . 1092
8.1100swidms_ehrpdMTUSizeTlv Struct Reference . . . 1092
8.1100.1Detailed Description . . . 1092
8.1100.2Field Documentation . . . 1092
8.1100.2.1ehrpdMTUSize . . . 1092
8.1100.2.2TlvPresent . . . 1092
8.1101swidms_hrpdMTUSizeTlv Struct Reference . . . 1092
8.1101.1Detailed Description . . . 1092
8.1101.2Field Documentation . . . 1092
8.1101.2.1hrpdMTUSize . . . 1093
8.1101.2.2TlvPresent . . . 1093
8.1102swidms_intfaceCfgTlv Struct Reference . . . 1093
8.1102.1Detailed Description . . . 1093
8.1102.2Field Documentation . . . 1094

8.1102.2.1 CfgValue . . . 1094
8.1102.2.2 CurrentCfgType . . . 1094
8.1102.2.3 TlvPresent . . . 1094
8.1103 swidms_mtuSize3gppTlv Struct Reference . . . 1094
8.1103.1 Detailed Description . . . 1094
8.1103.2 Field Documentation . . . 1095
8.1103.2.1 MTUSize3gpp . . . 1095
8.1103.2.2 TlvPresent . . . 1095
8.1104 swidms_supportedIntBitmaskTlv Struct Reference . . . 1095
8.1104.1 Detailed Description . . . 1095
8.1104.2 Field Documentation . . . 1095
8.1104.2.1 TlvPresent . . . 1095
8.1104.2.2 ValidBitmasks . . . 1095
8.1105 swidms_SwiDmsGetHWWatchdog Struct Reference . . . 1095
8.1105.1 Detailed Description . . . 1095
8.1105.2 Field Documentation . . . 1096
8.1105.2.1 count . . . 1096
8.1105.2.2 enable . . . 1096
8.1105.2.3 resetDelay . . . 1096
8.1105.2.4 timeout . . . 1096
8.1106 swidms_usbMTUSizeTlv Struct Reference . . . 1096
8.1106.1 Detailed Description . . . 1096
8.1106.2 Field Documentation . . . 1096
8.1106.2.1 TlvPresent . . . 1096
8.1106.2.2 UsbMTUSize . . . 1096
8.1107 SwiDmsGetHWWatchdog Struct Reference . . . 1097
8.1107.1 Detailed Description . . . 1097
8.1107.2 Field Documentation . . . 1097
8.1107.2.1 count . . . 1097
8.1107.2.2 enable . . . 1097
8.1107.2.3 resetDelay . . . 1097
8.1107.2.4 timeout . . . 1097
8.1108 SwiDmsGetMTUResp Struct Reference . . . 1097
8.1108.1 Detailed Description . . . 1097
8.1108.2 Field Documentation . . . 1098
8.1108.2.1 pEhrpdMTUSize . . . 1098
8.1108.2.2 pHrpdMTUSize . . . 1098
8.1108.2.3 pMTUSize3gpp . . . 1098
8.1108.2.4 pUsbMTUSize . . . 1098
8.1109 SwiDmsGetSecureInfoResp Struct Reference . . . 1098

8.1109.1 Detailed Description . . . 1098
8.1109.2 Field Documentation . . . 1098
8.1109.2.1 jtagAccessAllowed . . . 1098
8.1109.2.2 memoryDumpAllowed . . . 1098
8.1109.2.3 secureBootEnabled . . . 1098
8.1110 SwiDmsGetUsbCompResp Struct Reference . . . 1099
8.1110.1 Detailed Description . . . 1099
8.1110.2 Field Documentation . . . 1099
8.1110.2.1 pInterfaceCfg . . . 1099
8.1110.2.2 pSupportedBitmasks . . . 1099
8.1111 SwiDmsSetHWWatchdog Struct Reference . . . 1099
8.1111.1 Detailed Description . . . 1099
8.1111.2 Field Documentation . . . 1099
8.1111.2.1 enable . . . 1100
8.1111.2.2 resetDelay . . . 1100
8.1111.2.3 timeout . . . 1100
8.1112 SwiDmsSLQSGetUsbNetNum Struct Reference . . . 1100
8.1112.1 Detailed Description . . . 1100
8.1112.2 Field Documentation . . . 1100
8.1112.2.1 usbNetNum . . . 1100
8.1113 SwiDmsUIMSelectReq Struct Reference . . . 1100
8.1113.1 Detailed Description . . . 1100
8.1113.2 Field Documentation . . . 1101
8.1113.2.1 uim_select . . . 1101
8.1114 SwiLocGetAutoStartResp Struct Reference . . . 1101
8.1114.1 Detailed Description . . . 1101
8.1114.2 Field Documentation . . . 1102
8.1114.2.1 fix_rate . . . 1102
8.1114.2.2 fix_rate_reported . . . 1102
8.1114.2.3 fix_type . . . 1102
8.1114.2.4 fix_type_reported . . . 1102
8.1114.2.5 function . . . 1102
8.1114.2.6 function_reported . . . 1102
8.1114.2.7 max_dist . . . 1102
8.1114.2.8 max_dist_reported . . . 1102
8.1114.2.9 max_time . . . 1102
8.1114.2.10 max_time_reported . . . 1102
8.1115 SwiLocSetAutoStartReq Struct Reference . . . 1102
8.1115.1 Detailed Description . . . 1103
8.1115.2 Field Documentation . . . 1103

8.1115.2.1 fix_rate . . . 1104
8.1115.2.2 fix_type . . . 1104
8.1115.2.3 function . . . 1104
8.1115.2.4 max_dist . . . 1104
8.1115.2.5 max_time . . . 1104
8.1115.2.6 set_fix_rate . . . 1104
8.1115.2.7 set_fix_type . . . 1104
8.1115.2.8 set_function . . . 1104
8.1115.2.9 set_max_dist . . . 1104
8.1115.2.10 set_max_time . . . 1104
8.1116 swiModemStatusResp Struct Reference . . . 1104
8.1116.1 Detailed Description . . . 1104
8.1116.2 Field Documentation . . . 1104
8.1116.2.1 commonInfo . . . 1104
8.1116.2.2 pLTEInfo . . . 1104
8.1117 SwiOTAMsg_s Struct Reference . . . 1104
8.1117.1 Detailed Description . . . 1105
8.1117.2 Field Documentation . . . 1105
8.1117.2.1 data . . . 1105
8.1117.2.2 data_len . . . 1105
8.1117.2.3 pLteNasRelInfo . . . 1105
8.1117.2.4 pTime . . . 1105
8.1117.2.5 type . . . 1105
8.1118 swiPDPRuntimeSettingsReq Struct Reference . . . 1105
8.1118.1 Detailed Description . . . 1105
8.1118.2 Field Documentation . . . 1106
8.1118.2.1 contextId . . . 1106
8.1118.2.2 contextType . . . 1106
8.1119 swiPDPRuntimeSettingsResp Struct Reference . . . 1106
8.1119.1 Detailed Description . . . 1106
8.1119.2 Field Documentation . . . 1108
8.1119.2.1 pAPNName . . . 1108
8.1119.2.2 pBearerId . . . 1108
8.1119.2.3 pContextId . . . 1108
8.1119.2.4 pIPv4Address . . . 1108
8.1119.2.5 pIPv4GWAddress . . . 1108
8.1119.2.6 pIPv6Address . . . 1108
8.1119.2.7 pIPv6GWAddress . . . 1108
8.1119.2.8 pPrDNSIPv4Address . . . 1108
8.1119.2.9 pPrDNSIPv6Address . . . 1108

8.1119.2.10 pPrPCSCFIPv4Address . . . 1108
8.1119.2.11 pPrPCSCFIPv6Address . . . 1108
8.1119.2.12 pSeDNSIPv4Address . . . 1108
8.1119.2.13 pSeDNSIPv6Address . . . 1108
8.1119.2.14 pSePCSCFIPv4Address . . . 1108
8.1119.2.15 pSePCSCFIPv6Address . . . 1108
8.1120 swiQosFilter Struct Reference . . . 1108
8.1120.1 Detailed Description . . . 1109
8.1120.2 Field Documentation . . . 1110
8.1120.2.1 index . . . 1110
8.1120.2.2 pEspSpi . . . 1110
8.1120.2.3 pId . . . 1110
8.1120.2.4 pIPv4DstAddr . . . 1110
8.1120.2.5 pIPv4SrcAddr . . . 1110
8.1120.2.6 pIPv6DstAddr . . . 1110
8.1120.2.7 pIPv6Label . . . 1110
8.1120.2.8 pIPv6SrcAddr . . . 1110
8.1120.2.9 pIPv6TrafCls . . . 1110
8.1120.2.10 pNxtHdrProto . . . 1110
8.1120.2.11 pPrecedence . . . 1110
8.1120.2.12 pTCPDstPort . . . 1110
8.1120.2.13 pTCPSrcPort . . . 1110
8.1120.2.14 pTos . . . 1110
8.1120.2.15 pTranDstPort . . . 1110
8.1120.2.16 pTranSrcPort . . . 1110
8.1120.2.17 pUDPDstPort . . . 1110
8.1120.2.18 pUDPSrcPort . . . 1111
8.1120.2.19 version . . . 1111
8.1121 swiQosFlow Struct Reference . . . 1111
8.1121.1 Detailed Description . . . 1111
8.1121.2 Field Documentation . . . 1113
8.1121.2.1 index . . . 1113
8.1121.2.2 p3GPP2Pri . . . 1113
8.1121.2.3 p3GPPImCn . . . 1113
8.1121.2.4 p3GPPResResidualBER . . . 1113
8.1121.2.5 p3GPPSigInd . . . 1113
8.1121.2.6 p3GPPTraHdlPri . . . 1113
8.1121.2.7 pDataRate . . . 1113
8.1121.2.8 pJitter . . . 1113
8.1121.2.9 pLatency . . . 1113

8.1121.2.10 pLteQci . . . 1113
8.1121.2.11 pMaxAllowedPktSz . . . 1114
8.1121.2.12 pMinPolicedPktSz . . . 1114
8.1121.2.13 pPktErrRate . . . 1114
8.1121.2.14 pProfileId3GPP2 . . . 1114
8.1121.2.15 pTokenBucket . . . 1114
8.1121.2.16 pTrafficClass . . . 1114
8.1122 swiQosGranted Struct Reference . . . 1114
8.1122.1 Detailed Description . . . 1114
8.1122.2 Field Documentation . . . 1114
8.1122.2.1 pRxFlow . . . 1114
8.1122.2.2 pTxFlow . . . 1114
8.1123 swiQosIds Struct Reference . . . 1114
8.1123.1 Detailed Description . . . 1114
8.1123.2 Field Documentation . . . 1114
8.1123.2.1 pIds . . . 1115
8.1123.2.2 sz . . . 1115
8.1124 swiQosModifyReq Struct Reference . . . 1115
8.1124.1 Detailed Description . . . 1115
8.1124.2 Field Documentation . . . 1115
8.1124.2.1 id . . . 1115
8.1124.2.2 pRxFilter . . . 1115
8.1124.2.3 pRxFlow . . . 1115
8.1124.2.4 pTxFilter . . . 1115
8.1124.2.5 pTxFlow . . . 1115
8.1125 swiQosReq Struct Reference . . . 1115
8.1125.1 Detailed Description . . . 1115
8.1125.2 Field Documentation . . . 1116
8.1125.2.1 index . . . 1116
8.1125.2.2 pRxFilter . . . 1116
8.1125.2.3 pRxFlow . . . 1116
8.1125.2.4 pTxFilter . . . 1116
8.1125.2.5 pTxFlow . . . 1116
8.1126 swiRMTrasnferStaticsReq Struct Reference . . . 1116
8.1126.1 Detailed Description . . . 1116
8.1126.2 Field Documentation . . . 1117
8.1126.2.1 bResetStatistics . . . 1117
8.1126.2.2 ulMask . . . 1117
8.1127 sysInfoCommon Struct Reference . . . 1117
8.1127.1 Detailed Description . . . 1117

8.1127.2 Field Documentation . . . 1119
8.1127.2.1 isSysForbidden . . . 1119
8.1127.2.2 isSysForbiddenValid . . . 1119
8.1127.2.3 roamStatus . . . 1119
8.1127.2.4 roamStatusValid . . . 1119
8.1127.2.5 srvCapability . . . 1119
8.1127.2.6 srvCapabilityValid . . . 1119
8.1127.2.7 srvDomain . . . 1119
8.1127.2.8 srvDomainValid . . . 1119
8.1128 sysSelectPrefParamsExt Struct Reference . . . 1119
8.1128.1 Detailed Description . . . 1119
8.1128.2 Field Documentation . . . 1123
8.1128.2.1 pCiotAcqOrderPref . . . 1123
8.1128.2.2 pCiotLteOpMode . . . 1123
8.1128.2.3 pCiotLteOpModePref . . . 1123
8.1128.2.4 pLTEBandPrefExt . . . 1123
8.1128.2.5 pLteM1BandPref . . . 1123
8.1128.2.6 pLteNb1BandPref . . . 1123
8.1128.2.7 pNr5gBandPref . . . 1123
8.1128.2.8 pSysSelectPrefParams . . . 1123
8.1129 _gpsTime Struct Reference . . . 1123
8.1129.1 Field Documentation . . . 1123
8.1129.1.1 gpsTimeOfWeekMs . . . 1123
8.1129.1.2 gpsWeek . . . 1123
8.1130 _sensor Struct Reference . . . 1123
8.1130.1 Field Documentation . . . 1124
8.1130.1.1 aidingIndicatorMask . . . 1124
8.1130.1.2 usageMask . . . 1124
8.1131 _Sv Struct Reference . . . 1124
8.1131.1 Field Documentation . . . 1124
8.1131.1.1 entries . . . 1124
8.1131.1.2 len . . . 1124
8.1132 TDSCDMAECIOThresh Struct Reference . . . 1124
8.1132.1 Detailed Description . . . 1124
8.1132.2 Field Documentation . . . 1124
8.1132.2.1 pTDSCDMAECIOThreshList . . . 1124
8.1132.2.2 TDSCDMAECIOThreshListLen . . . 1124
8.1133 TDSCDMARSCPThresh Struct Reference . . . 1125
8.1133.1 Detailed Description . . . 1125
8.1133.2 Field Documentation . . . 1125

8.1133.2.1 pTDSCDMARSCPThreshList . . . 1125
8.1133.2.2 TDSCDMARSCPThreshListLen . . . 1125
8.1134 TDSCDMARSSIThresh Struct Reference . . . 1125
8.1134.1 Detailed Description . . . 1125
8.1134.2 Field Documentation . . . 1125
8.1134.2.1 pTDSCDMARSSIThreshList . . . 1125
8.1134.2.2 TDSCDMARSSIThreshListLen . . . 1126
8.1135 tdscdmaSigInfoExt Struct Reference . . . 1126
8.1135.1 Detailed Description . . . 1126
8.1135.2 Field Documentation . . . 1126
8.1135.2.1 ecio . . . 1126
8.1135.2.2 rscp . . . 1126
8.1135.2.3 rssi . . . 1126
8.1135.2.4 sinr . . . 1126
8.1136 TDSCDMASigInfoExt Struct Reference . . . 1126
8.1136.1 Detailed Description . . . 1126
8.1136.2 Field Documentation . . . 1127
8.1136.2.1 ecio . . . 1127
8.1136.2.2 rscp . . . 1127
8.1136.2.3 rssi . . . 1127
8.1136.2.4 sinr . . . 1127
8.1137 TDSCDMASINRCONFThresh Struct Reference . . . 1127
8.1137.1 Detailed Description . . . 1127
8.1137.2 Field Documentation . . . 1127
8.1137.2.1 pTDSCDMASINRCONFThreshList . . . 1127
8.1137.2.2 TDSCDMASINRCONFThreshListLen . . . 1127
8.1138 TDSCDMASINRThresh Struct Reference . . . 1128
8.1138.1 Detailed Description . . . 1128
8.1138.2 Field Documentation . . . 1128
8.1138.2.1 pTDSCDMASINRThreshList . . . 1128
8.1138.2.2 TDSCDMASINRThreshListLen . . . 1128
8.1139 tempData_t Struct Reference . . . 1128
8.1139.1 Detailed Description . . . 1128
8.1139.2 Field Documentation . . . 1129
8.1139.2.1 temperature . . . 1129
8.1139.2.2 temperatureDataLen . . . 1129
8.1139.2.3 timeOfFirstSample . . . 1129
8.1139.2.4 timeOffset . . . 1129
8.1139.2.5 timeSource . . . 1129
8.1140 temprateData Struct Reference . . . 1129

8.1140.1 Detailed Description . . . 1129
8.1140.2 Field Documentation . . . 1130
8.1140.2.1 temperature . . . 1130
8.1140.2.2 temperatureDataLen . . . 1130
8.1140.2.3 timeOfFirstSample . . . 1130
8.1140.2.4 timeOffset . . . 1130
8.1140.2.5 timeSource . . . 1130
8.1141 TFTIDParams Struct Reference . . . 1130
8.1141.1 Detailed Description . . . 1131
8.1141.2 Field Documentation . . . 1132
8.1141.2.1 destPortRangeEnd . . . 1132
8.1141.2.2 destPortRangeStart . . . 1132
8.1141.2.3 eValid . . . 1132
8.1141.2.4 filterId . . . 1132
8.1141.2.5 flowLabel . . . 1132
8.1141.2.6 IPSECSPI . . . 1132
8.1141.2.7 ipVersion . . . 1132
8.1141.2.8 nextHeader . . . 1132
8.1141.2.9 pSourceIP . . . 1132
8.1141.2.10 sourceIPMask . . . 1132
8.1141.2.11 srcPortRangeEnd . . . 1132
8.1141.2.12 srcPortRangeStart . . . 1132
8.1141.2.13 tosMask . . . 1132
8.1142 TimeInfo Struct Reference . . . 1132
8.1142.1 Detailed Description . . . 1132
8.1142.2 Field Documentation . . . 1134
8.1142.2.1 day . . . 1134
8.1142.2.2 dayLtSavingAdj . . . 1134
8.1142.2.3 dayOfWeek . . . 1134
8.1142.2.4 hour . . . 1134
8.1142.2.5 minute . . . 1134
8.1142.2.6 month . . . 1134
8.1142.2.7 radioInterface . . . 1134
8.1142.2.8 second . . . 1134
8.1142.2.9 timeZone . . . 1134
8.1142.2.10 TlvPresent . . . 1134
8.1142.2.11 year . . . 1134
8.1143 TmdDeRegNotMitigationLvlReq Struct Reference . . . 1134
8.1143.1 Detailed Description . . . 1134
8.1143.2 Field Documentation . . . 1134

8.1143.2.1 mitigationDevID . . . 1134
8.1143.2.2 mitigationDevIDLen . . . 1134
8.1144 TmdGetMitigationDevListResp Struct Reference . . . 1134
8.1144.1 Detailed Description . . . 1135
8.1144.2 Field Documentation . . . 1135
8.1144.2.1 pMitigationDevList . . . 1135
8.1144.2.2 pMitigationDevListLen . . . 1135
8.1145 TmdGetMitigationLvlReq Struct Reference . . . 1135
8.1145.1 Detailed Description . . . 1135
8.1145.2 Field Documentation . . . 1135
8.1145.2.1 mitigationDevID . . . 1135
8.1145.2.2 mitigationDevIDLen . . . 1136
8.1146 TmdGetMitigationLvlResp Struct Reference . . . 1136
8.1146.1 Detailed Description . . . 1136
8.1146.2 Field Documentation . . . 1136
8.1146.2.1 pCurrentmitigationLvl . . . 1136
8.1146.2.2 pReqMitigationLvl . . . 1136
8.1147 TmdMitigationLvlIndReq Struct Reference . . . 1136
8.1147.1 Detailed Description . . . 1136
8.1147.2 Field Documentation . . . 1137
8.1147.2.1 mitigationDevID . . . 1137
8.1147.2.2 mitigationDevIDLen . . . 1137
8.1148 TmdRegNotMitigationLvlReq Struct Reference . . . 1137
8.1148.1 Detailed Description . . . 1137
8.1148.2 Field Documentation . . . 1137
8.1148.2.1 mitigationDevID . . . 1137
8.1148.2.2 mitigationDevIDLen . . . 1137
8.1149 TokenBucket Struct Reference . . . 1137
8.1149.1 Detailed Description . . . 1137
8.1149.2 Field Documentation . . . 1138
8.1149.2.1 bucketSz . . . 1138
8.1149.2.2 peakRate . . . 1138
8.1149.2.3 tokenRate . . . 1138
8.1150 Tos Struct Reference . . . 1138
8.1150.1 Detailed Description . . . 1138
8.1150.2 Field Documentation . . . 1138
8.1150.2.1 mask . . . 1138
8.1150.2.2 val . . . 1138
8.1151 TransferRouteMessageTlv Struct Reference . . . 1138
8.1151.1 Detailed Description . . . 1138

8.1151.2 Field Documentation . . . 1139
8.1151.2.1 TlvPresent . . . 1139
8.1151.2.2 TransferRouteMTMessageInfo . . . 1139
8.1152 TransferStatInd Struct Reference . . . 1139
8.1152.1 Detailed Description . . . 1139
8.1152.2 Field Documentation . . . 1139
8.1152.2.1 StatsMask . . . 1139
8.1152.2.2 StatsPeriod . . . 1139
8.1153 TransferStatsDataType Struct Reference . . . 1139
8.1153.1 Field Documentation . . . 1139
8.1153.1.1 interval . . . 1140
8.1154 TrStatInd Struct Reference . . . 1140
8.1154.1 Detailed Description . . . 1140
8.1154.2 Field Documentation . . . 1140
8.1154.2.1 statsMask . . . 1140
8.1154.2.2 statsPeriod . . . 1140
8.1155 TrueIMSI Struct Reference . . . 1140
8.1155.1 Detailed Description . . . 1141
8.1155.2 Field Documentation . . . 1141
8.1155.2.1 imsiT1112 . . . 1141
8.1155.2.2 imsiTaddrNum . . . 1141
8.1155.2.3 imsiTS1 . . . 1141
8.1155.2.4 imsiTS2 . . . 1141
8.1155.2.5 mccT . . . 1141
8.1156 TXAGCList Struct Reference . . . 1141
8.1156.1 Detailed Description . . . 1141
8.1156.2 Field Documentation . . . 1142
8.1156.2.1 pTXAIG . . . 1142
8.1156.2.2 pTXComprSlope . . . 1142
8.1156.2.3 pTXComprThres . . . 1142
8.1156.2.4 pTXExpSlope . . . 1142
8.1156.2.5 pTXExpThres . . . 1142
8.1156.2.6 pTXStaticGain . . . 1142
8.1157 TxInfo Struct Reference . . . 1142
8.1157.1 Detailed Description . . . 1142
8.1157.2 Field Documentation . . . 1143
8.1157.2.1 isInTraffic . . . 1143
8.1157.2.2 txPower . . . 1143
8.1158 TXPCMIIRFltr Struct Reference . . . 1143
8.1158.1 Detailed Description . . . 1143

8.1158.2 Field Documentation . . . 1144
8.1158.2.1 pFlag . . . 1144
8.1158.2.2 pStage0Val . . . 1144
8.1158.2.3 pStage1Val . . . 1144
8.1158.2.4 pStage2Val . . . 1144
8.1158.2.5 pStage3Val . . . 1144
8.1158.2.6 pStage4Val . . . 1144
8.1158.2.7 pStageCnt . . . 1144
8.1159 uim_appStatus Struct Reference . . . 1144
8.1159.1 Detailed Description . . . 1145
8.1159.2 Field Documentation . . . 1147
8.1159.2.1 aidLength . . . 1147
8.1159.2.2 aidVal . . . 1147
8.1159.2.3 appState . . . 1147
8.1159.2.4 appType . . . 1147
8.1159.2.5 persoFeature . . . 1147
8.1159.2.6 persoRetries . . . 1147
8.1159.2.7 persoState . . . 1147
8.1159.2.8 persoUnblockRetries . . . 1147
8.1159.2.9 pin1Retries . . . 1147
8.1159.2.10 pin1State . . . 1147
8.1159.2.11 pin2Retries . . . 1147
8.1159.2.12 pin2State . . . 1147
8.1159.2.13 puk1Retries . . . 1147
8.1159.2.14 puk2Retries . . . 1147
8.1159.2.15 univPin . . . 1147
8.1160 uim_authenticateResult Struct Reference . . . 1147
8.1160.1 Detailed Description . . . 1148
8.1160.2 Field Documentation . . . 1148
8.1160.2.1 content . . . 1148
8.1160.2.2 contentLen . . . 1148
8.1161 uim_authenticationData Struct Reference . . . 1148
8.1161.1 Detailed Description . . . 1148
8.1161.2 Field Documentation . . . 1149
8.1161.2.1 context . . . 1149
8.1161.2.2 data . . . 1149
8.1161.2.3 dataLen . . . 1149
8.1162 uim_cardResult Struct Reference . . . 1149
8.1162.1 Detailed Description . . . 1149
8.1162.2 Field Documentation . . . 1150

8.1162.2.1 sw1 . . . 1150
8.1162.2.2 sw2 . . . 1150
8.1163 uim_cardStatus Struct Reference . . . 1150
8.1163.1 Detailed Description . . . 1150
8.1163.2 Field Documentation . . . 1151
8.1163.2.1 index1xPri . . . 1151
8.1163.2.2 index1xSec . . . 1151
8.1163.2.3 indexGwPri . . . 1151
8.1163.2.4 indexGwSec . . . 1151
8.1163.2.5 numSlot . . . 1151
8.1163.2.6 SlotInfo . . . 1151
8.1164 uim_changeUIMPIN Struct Reference . . . 1151
8.1164.1 Detailed Description . . . 1151
8.1164.2 Field Documentation . . . 1152
8.1164.2.1 oldPINLen . . . 1152
8.1164.2.2 oldPINVal . . . 1152
8.1164.2.3 pinID . . . 1152
8.1164.2.4 pinLen . . . 1152
8.1164.2.5 pinVal . . . 1152
8.1165 uim_depersonalizationInformation Struct Reference . . . 1152
8.1165.1 Detailed Description . . . 1152
8.1165.2 Field Documentation . . . 1153
8.1165.2.1 ckLen . . . 1153
8.1165.2.2 ckVal . . . 1153
8.1165.2.3 feature . . . 1153
8.1165.2.4 operation . . . 1153
8.1166 uim_encryptedPIN1 Struct Reference . . . 1153
8.1166.1 Detailed Description . . . 1153
8.1166.2 Field Documentation . . . 1154
8.1166.2.1 pin1Len . . . 1154
8.1166.2.2 pin1Val . . . 1154
8.1167 uim_fileAttributes Struct Reference . . . 1154
8.1167.1 Detailed Description . . . 1154
8.1167.2 Field Documentation . . . 1157
8.1167.2.1 fileID . . . 1157
8.1167.2.2 fileSize . . . 1157
8.1167.2.3 fileType . . . 1157
8.1167.2.4 rawLen . . . 1157
8.1167.2.5 rawValue . . . 1157
8.1167.2.6 recordCount . . . 1157

8.1167.2.7 recordSize . . . 1157
8.1167.2.8 secActivate . . . 1157
8.1167.2.9 secActivateMask . . . 1157
8.1167.2.10 secDeactivate . . . 1157
8.1167.2.11 secDeactivateMask . . . 1157
8.1167.2.12 secIncrease . . . 1157
8.1167.2.13 secIncreaseMask . . . 1157
8.1167.2.14 secRead . . . 1157
8.1167.2.15 secReadMask . . . 1157
8.1167.2.16 secWrite . . . 1157
8.1167.2.17 secWriteMask . . . 1157
8.1168 qmi_fileInfo Struct Reference . . . 1157
8.1168.1 Detailed Description . . . 1157
8.1168.2 Field Documentation . . . 1158
8.1168.2.1 fileID . . . 1158
8.1168.2.2 path . . . 1158
8.1168.2.3 pathLen . . . 1158
8.1169 qmi_hotSwapStatus Struct Reference . . . 1158
8.1169.1 Detailed Description . . . 1158
8.1169.2 Field Documentation . . . 1158
8.1169.2.1 hotSwap . . . 1158
8.1169.2.2 hotSwapLength . . . 1158
8.1170 qmi_personalizationStatus Struct Reference . . . 1158
8.1170.1 Detailed Description . . . 1159
8.1170.2 Field Documentation . . . 1159
8.1170.2.1 feature . . . 1159
8.1170.2.2 numFeatures . . . 1159
8.1170.2.3 unblockLeft . . . 1159
8.1170.2.4 verifyLeft . . . 1159
8.1171 qmi_readResult Struct Reference . . . 1159
8.1171.1 Detailed Description . . . 1160
8.1171.2 Field Documentation . . . 1160
8.1171.2.1 content . . . 1160
8.1171.2.2 contentLen . . . 1160
8.1172 qmi_readTransparentInfo Struct Reference . . . 1160
8.1172.1 Detailed Description . . . 1160
8.1172.2 Field Documentation . . . 1160
8.1172.2.1 length . . . 1160
8.1172.2.2 offset . . . 1160
8.1173 qmi_refreshevent Struct Reference . . . 1160

8.1173.1 Detailed Description . . . 1161
8.1173.2 Field Documentation . . . 1162
8.1173.2.1 aid . . . 1162
8.1173.2.2 aidLength . . . 1162
8.1173.2.3 arrfileInfo . . . 1162
8.1173.2.4 mode . . . 1162
8.1173.2.5 numOfFiles . . . 1162
8.1173.2.6 sessionType . . . 1162
8.1173.2.7 stage . . . 1162
8.1174 uim_registerRefresh Struct Reference . . . 1162
8.1174.1 Detailed Description . . . 1162
8.1174.2 Field Documentation . . . 1163
8.1174.2.1 arrfileInfo . . . 1163
8.1174.2.2 numFiles . . . 1163
8.1174.2.3 registerFlag . . . 1163
8.1174.2.4 voteForInit . . . 1163
8.1175 uim_remainingRetries Struct Reference . . . 1163
8.1175.1 Detailed Description . . . 1163
8.1175.2 Field Documentation . . . 1163
8.1175.2.1 unblockLeft . . . 1163
8.1175.2.2 verifyLeft . . . 1164
8.1176 uim_sessionInformation Struct Reference . . . 1164
8.1176.1 Detailed Description . . . 1164
8.1176.2 Field Documentation . . . 1164
8.1176.2.1 aid . . . 1164
8.1176.2.2 aidLength . . . 1164
8.1176.2.3 sessionType . . . 1164
8.1177 uim_setPINProtection Struct Reference . . . 1164
8.1177.1 Detailed Description . . . 1165
8.1177.2 Field Documentation . . . 1165
8.1177.2.1 pinID . . . 1165
8.1177.2.2 pinLength . . . 1165
8.1177.2.3 pinOperation . . . 1165
8.1177.2.4 pinValue . . . 1165
8.1178 uim_simBusyStatus Struct Reference . . . 1165
8.1178.1 Detailed Description . . . 1165
8.1178.2 Field Documentation . . . 1166
8.1178.2.1 simBusy . . . 1166
8.1178.2.2 simBusyLength . . . 1166
8.1179 uim_slotInfo Struct Reference . . . 1166

8.1179.1 Detailed Description . . . 1166
8.1179.2 Field Documentation . . . 1167
8.1179.2.1 AppStatus . . . 1167
8.1179.2.2 cardState . . . 1167
8.1179.2.3 errorState . . . 1167
8.1179.2.4 numApp . . . 1167
8.1179.2.5 upinRetries . . . 1167
8.1179.2.6 upinState . . . 1167
8.1179.2.7 upukRetries . . . 1167
8.1180 uim_UIMSessionInformation Struct Reference . . . 1167
8.1180.1 Detailed Description . . . 1168
8.1180.2 Field Documentation . . . 1168
8.1180.2.1 aid . . . 1168
8.1180.2.2 aidLength . . . 1168
8.1180.2.3 sessionType . . . 1168
8.1181 uim_unblockUIMPIN Struct Reference . . . 1168
8.1181.1 Detailed Description . . . 1168
8.1181.2 Field Documentation . . . 1169
8.1181.2.1 newPINLen . . . 1169
8.1181.2.2 newPINVal . . . 1169
8.1181.2.3 pinID . . . 1169
8.1181.2.4 pukLen . . . 1169
8.1181.2.5 pukVal . . . 1169
8.1182 uim_validCardStatus Struct Reference . . . 1169
8.1182.1 Detailed Description . . . 1169
8.1182.2 Field Documentation . . . 1170
8.1182.2.1 validCard . . . 1170
8.1182.2.2 validCardLength . . . 1170
8.1183 uim_verifyUIMPIN Struct Reference . . . 1170
8.1183.1 Detailed Description . . . 1170
8.1183.2 Field Documentation . . . 1170
8.1183.2.1 pinID . . . 1170
8.1183.2.2 pinLen . . . 1170
8.1183.2.3 pinVal . . . 1171
8.1184 UIMAuthenticateReq Struct Reference . . . 1171
8.1184.1 Detailed Description . . . 1171
8.1184.2 Field Documentation . . . 1171
8.1184.2.1 authData . . . 1171
8.1184.2.2 pIndicationToken . . . 1171
8.1184.2.3 sessionInfo . . . 1171

8.1185 UIMAuthenticateResp Struct Reference . . . 1171
8.1185.1 Detailed Description . . . 1171
8.1185.2 Field Documentation . . . 1172
8.1185.2.1 pAuthenticateResult . . . 1172
8.1185.2.2 pCardResult . . . 1172
8.1185.2.3 pIndicationToken . . . 1172
8.1186 UimAutoSwitchActSlotTlv Struct Reference . . . 1172
8.1186.1 Detailed Description . . . 1172
8.1186.2 Field Documentation . . . 1172
8.1186.2.1 TlvPresent . . . 1172
8.1186.2.2 uimAutoSwitchActSlot . . . 1173
8.1187 UIMChangePinReq Struct Reference . . . 1173
8.1187.1 Detailed Description . . . 1173
8.1187.2 Field Documentation . . . 1173
8.1187.2.1 changePIN . . . 1173
8.1187.2.2 pIndicationToken . . . 1173
8.1187.2.3 pKeyReferenceID . . . 1173
8.1187.2.4 sessionInfo . . . 1173
8.1188 UIMDepersonalizationReq Struct Reference . . . 1173
8.1188.1 Detailed Description . . . 1174
8.1188.2 Field Documentation . . . 1174
8.1188.2.1 depersonilisationInfo . . . 1174
8.1189 UIMDepersonalizationResp Struct Reference . . . 1174
8.1189.1 Detailed Description . . . 1174
8.1189.2 Field Documentation . . . 1174
8.1189.2.1 pRemainingRetries . . . 1174
8.1190 UIMEventRegisterReqResp Struct Reference . . . 1174
8.1190.1 Detailed Description . . . 1174
8.1190.2 Field Documentation . . . 1175
8.1190.2.1 eventMask . . . 1175
8.1191 UIMGetCardStatusResp Struct Reference . . . 1175
8.1191.1 Detailed Description . . . 1175
8.1191.2 Field Documentation . . . 1175
8.1191.2.1 pCardStatus . . . 1175
8.1191.2.2 pHotSwapStatus . . . 1175
8.1192 UIMGetCardStatusRespV2 Struct Reference . . . 1175
8.1192.1 Detailed Description . . . 1176
8.1192.2 Field Documentation . . . 1176
8.1192.2.1 pCardStatus . . . 1176
8.1192.2.2 pHotSwapStatus . . . 1176

8.1192.2.3 pSimBusyStatus . . . 1176
8.1192.2.4 pValidCardStatus . . . 1176
8.1193 UIMGetConfigurationReq Struct Reference . . . 1176
8.1193.1 Detailed Description . . . 1176
8.1193.2 Field Documentation . . . 1177
8.1193.2.1 pConfigurationMask . . . 1177
8.1194 UIMGetConfigurationResp Struct Reference . . . 1177
8.1194.1 Detailed Description . . . 1177
8.1194.2 Field Documentation . . . 1177
8.1194.2.1 pAutoSelection . . . 1177
8.1194.2.2 pHaltSubscription . . . 1177
8.1194.2.3 pPersonalizationStatus . . . 1177
8.1195 UIMGetFileAttributesReq Struct Reference . . . 1177
8.1195.1 Detailed Description . . . 1178
8.1195.2 Field Documentation . . . 1178
8.1195.2.1 fileIndex . . . 1178
8.1195.2.2 pIndicationToken . . . 1178
8.1195.2.3 sessionInfo . . . 1178
8.1196 UIMGetFileAttributesResp Struct Reference . . . 1178
8.1196.1 Detailed Description . . . 1178
8.1196.2 Field Documentation . . . 1179
8.1196.2.1 pCardResult . . . 1179
8.1196.2.2 pFileAttributes . . . 1179
8.1196.2.3 pIndicationToken . . . 1179
8.1197 UIMGetSlotsStatusResp Struct Reference . . . 1179
8.1197.1 Detailed Description . . . 1179
8.1197.2 Field Documentation . . . 1179
8.1197.2.1 pNumberOfPhySlot . . . 1179
8.1197.2.2 pUimSlotsStatus . . . 1179
8.1198 UIMPinResp Struct Reference . . . 1179
8.1198.1 Detailed Description . . . 1179
8.1198.2 Field Documentation . . . 1180
8.1198.2.1 pEncryptedPIN1 . . . 1180
8.1198.2.2 pIndicationToken . . . 1180
8.1198.2.3 pRemainingRetries . . . 1180
8.1199 UIMPinRespV2 Struct Reference . . . 1180
8.1199.1 Detailed Description . . . 1180
8.1199.2 Field Documentation . . . 1181
8.1199.2.1 pCardResult . . . 1181
8.1199.2.2 pEncryptedPIN1 . . . 1181

8.1199.2.3 pIndicationToken . . . 1181
8.1199.2.4 pRemainingRetries . . . 1181
8.1200 UIMPowerDownReq Struct Reference . . . 1181
8.1200.1 Detailed Description . . . 1181
8.1200.2 Field Documentation . . . 1181
8.1200.2.1 slot . . . 1181
8.1201 UIMPowerUpReq Struct Reference . . . 1181
8.1201.1 Detailed Description . . . 1181
8.1201.2 Field Documentation . . . 1182
8.1201.2.1 pIgnoreHotSwapSwitch . . . 1182
8.1201.2.2 slot . . . 1182
8.1202 UIMReadTransparentReq Struct Reference . . . 1182
8.1202.1 Detailed Description . . . 1182
8.1202.2 Field Documentation . . . 1182
8.1202.2.1 fileIndex . . . 1183
8.1202.2.2 pEncryptData . . . 1183
8.1202.2.3 pIndicationToken . . . 1183
8.1202.2.4 readTransparent . . . 1183
8.1202.2.5 sessionInfo . . . 1183
8.1203 UIMReadTransparentResp Struct Reference . . . 1183
8.1203.1 Detailed Description . . . 1183
8.1203.2 Field Documentation . . . 1183
8.1203.2.1 pCardResult . . . 1183
8.1203.2.2 pEncryptedData . . . 1183
8.1203.2.3 pIndicationToken . . . 1183
8.1203.2.4 pReadResult . . . 1183
8.1204 UIMRefreshCompleteReq Struct Reference . . . 1184
8.1204.1 Detailed Description . . . 1184
8.1204.2 Field Documentation . . . 1184
8.1204.2.1 refreshComplete . . . 1184
8.1204.2.2 sessionInfo . . . 1184
8.1205 UIMRefreshEvent Struct Reference . . . 1184
8.1205.1 Detailed Description . . . 1184
8.1205.2 Field Documentation . . . 1185
8.1205.2.1 aid . . . 1185
8.1205.2.2 aidLength . . . 1185
8.1205.2.3 arrfileInfo . . . 1185
8.1205.2.4 mode . . . 1185
8.1205.2.5 numOfFiles . . . 1186
8.1205.2.6 results . . . 1186

8.1205.2.7 sessionType . . . 1186
8.1205.2.8 stage . . . 1186
8.1206 UIMRefreshGetLastEventReq Struct Reference . . . 1186
8.1206.1 Detailed Description . . . 1186
8.1206.2 Field Documentation . . . 1186
8.1206.2.1 sessionInfo . . . 1186
8.1207 UIMRefreshGetLastEventResp Struct Reference . . . 1186
8.1207.1 Detailed Description . . . 1186
8.1207.2 Field Documentation . . . 1186
8.1207.2.1 pRefreshEvent . . . 1186
8.1208 UIMRefreshOKReq Struct Reference . . . 1186
8.1208.1 Detailed Description . . . 1187
8.1208.2 Field Documentation . . . 1187
8.1208.2.1 OKtoRefresh . . . 1187
8.1208.2.2 sessionInfo . . . 1187
8.1209 UIMRefreshRegisterReq Struct Reference . . . 1187
8.1209.1 Detailed Description . . . 1187
8.1209.2 Field Documentation . . . 1187
8.1209.2.1 regRefresh . . . 1187
8.1209.2.2 sessionInfo . . . 1188
8.1210 UIMSessionInformation Struct Reference . . . 1188
8.1210.1 Detailed Description . . . 1188
8.1210.2 Field Documentation . . . 1188
8.1210.2.1 aid . . . 1188
8.1210.2.2 aidLength . . . 1188
8.1210.2.3 sessionType . . . 1188
8.1211 UIMSetPinProtectionReq Struct Reference . . . 1188
8.1211.1 Detailed Description . . . 1189
8.1211.2 Field Documentation . . . 1189
8.1211.2.1 pIndicationToken . . . 1189
8.1211.2.2 pinProtection . . . 1189
8.1211.2.3 pKeyReferenceID . . . 1189
8.1211.2.4 sessionInfo . . . 1189
8.1212 UIMSlotsStatus Struct Reference . . . 1189
8.1212.1 Detailed Description . . . 1189
8.1212.2 Field Documentation . . . 1190
8.1212.2.1 uimSlotStatus . . . 1190
8.1213 UIMSlotStatus Struct Reference . . . 1190
8.1213.1 Detailed Description . . . 1190
8.1213.2 Field Documentation . . . 1190

8.1213.2.1 bICCID . . . 1190
8.1213.2.2 bICCIDLength . . . 1190
8.1213.2.3 bLogicalSlot . . . 1191
8.1213.2.4 uPhyCardStatus . . . 1191
8.1213.2.5 uPhySlotStatus . . . 1191
8.1214 UIMSlotStatusChangeInfo Struct Reference . . . 1191
8.1214.1 Detailed Description . . . 1191
8.1214.2 Field Documentation . . . 1191
8.1214.2.1 bNumberOfPhySlots . . . 1191
8.1214.2.2 results . . . 1191
8.1214.2.3 slotsstatusChange . . . 1191
8.1215 UIMStatusChangeInfo Struct Reference . . . 1191
8.1215.1 Detailed Description . . . 1191
8.1215.2 Field Documentation . . . 1192
8.1215.2.1 results . . . 1192
8.1215.2.2 statusChange . . . 1192
8.1216 UIMSwitchSlotReq Struct Reference . . . 1192
8.1216.1 Detailed Description . . . 1192
8.1216.2 Field Documentation . . . 1192
8.1216.2.1 bLogicalSlot . . . 1192
8.1216.2.2 ulPhysicalSlot . . . 1192
8.1217 UIMUnblockPinReq Struct Reference . . . 1192
8.1217.1 Detailed Description . . . 1193
8.1217.2 Field Documentation . . . 1193
8.1217.2.1 pIndicationToken . . . 1193
8.1217.2.2 pKeyReferenceID . . . 1193
8.1217.2.3 sessionInfo . . . 1193
8.1217.2.4 unblockPIN . . . 1193
8.1218 UIMVerifyPinReq Struct Reference . . . 1193
8.1218.1 Detailed Description . . . 1193
8.1218.2 Field Documentation . . . 1194
8.1218.2.1 pEncryptedPIN1 . . . 1194
8.1218.2.2 pIndicationToken . . . 1194
8.1218.2.3 pKeyReferenceID . . . 1194
8.1218.2.4 sessionInfo . . . 1194
8.1218.2.5 verifyPIN . . . 1194
8.1219 UMTSInfo Struct Reference . . . 1194
8.1219.1 Detailed Description . . . 1195
8.1219.2 Field Documentation . . . 1195
8.1219.2.1 cellID . . . 1195

8.1219.2.2 ecio . . . 1196
8.1219.2.3 geranInst . . . 1196
8.1219.2.4 GeranInstInfo . . . 1196
8.1219.2.5 lac . . . 1196
8.1219.2.6 plmn . . . 1196
8.1219.2.7 psc . . . 1196
8.1219.2.8 rscp . . . 1196
8.1219.2.9 uarfcn . . . 1196
8.1219.2.10 umtsInst . . . 1196
8.1219.2.11 UMTSInstInfo . . . 1196
8.1220 UMTSinstInfo Struct Reference . . . 1196
8.1220.1 Detailed Description . . . 1196
8.1220.2 Field Documentation . . . 1196
8.1220.2.1 umtsEcio . . . 1196
8.1220.2.2 umtsPsc . . . 1196
8.1220.2.3 umtsRscp . . . 1197
8.1220.2.4 umtsUarfcn . . . 1197
8.1221 umtsLTENbrCell Struct Reference . . . 1197
8.1221.1 Detailed Description . . . 1197
8.1221.2 Field Documentation . . . 1197
8.1221.2.1 cellIsTDD . . . 1197
8.1221.2.2 earfcn . . . 1197
8.1221.2.3 pci . . . 1197
8.1221.2.4 rsrp . . . 1197
8.1221.2.5 rsrq . . . 1198
8.1221.2.6 srxlev . . . 1198
8.1222 UMTSMinQoS Struct Reference . . . 1198
8.1222.1 Detailed Description . . . 1198
8.1222.2 Field Documentation . . . 1199
8.1222.2.1 deliveryErrSDU . . . 1199
8.1222.2.2 grntDownlinkBitrate . . . 1200
8.1222.2.3 grntUplinkBitrate . . . 1200
8.1222.2.4 maxDownlinkBitrate . . . 1200
8.1222.2.5 maxSDUSize . . . 1200
8.1222.2.6 maxUplinkBitrate . . . 1200
8.1222.2.7 qosDeliveryOrder . . . 1200
8.1222.2.8 resBerRatio . . . 1200
8.1222.2.9 sduErrorRatio . . . 1200
8.1222.2.10 trafficClass . . . 1200
8.1222.2.11 trafficPriority . . . 1200

8.1222.2.12 transferDelay . . . 1200
8.1223 UMTSQoS Struct Reference . . . 1200
8.1223.1 Detailed Description . . . 1200
8.1223.2 Field Documentation . . . 1202
8.1223.2.1 deliveryErrSDU . . . 1202
8.1223.2.2 grntDownlinkBitrate . . . 1202
8.1223.2.3 grntUplinkBitrate . . . 1202
8.1223.2.4 maxDownlinkBitrate . . . 1202
8.1223.2.5 maxSDUSize . . . 1202
8.1223.2.6 maxUplinkBitrate . . . 1202
8.1223.2.7 qosDeliveryOrder . . . 1202
8.1223.2.8 resBerRatio . . . 1202
8.1223.2.9 sduErrorRatio . . . 1202
8.1223.2.10 trafficClass . . . 1202
8.1223.2.11 trafficPriority . . . 1202
8.1223.2.12 transferDelay . . . 1202
8.1224 UMTSReqQoSSigInd Struct Reference . . . 1202
8.1224.1 Detailed Description . . . 1203
8.1224.2 Field Documentation . . . 1203
8.1224.2.1 SigInd . . . 1203
8.1224.2.2 UMTSReqQoS . . . 1203
8.1225 UnblockUIMPIN Struct Reference . . . 1203
8.1225.1 Detailed Description . . . 1203
8.1225.2 Field Documentation . . . 1204
8.1225.2.1 newPINLen . . . 1204
8.1225.2.2 newPINVal . . . 1204
8.1225.2.3 pinID . . . 1204
8.1225.2.4 pukLen . . . 1204
8.1225.2.5 pukVal . . . 1204
8.1226 UniversalTime Struct Reference . . . 1204
8.1226.1 Detailed Description . . . 1204
8.1226.2 Field Documentation . . . 1205
8.1226.2.1 day . . . 1205
8.1226.2.2 dayOfWeek . . . 1205
8.1226.2.3 hour . . . 1205
8.1226.2.4 minute . . . 1205
8.1226.2.5 month . . . 1205
8.1226.2.6 second . . . 1205
8.1226.2.7 year . . . 1205
8.1227 unpack_dms_GetActivationState_t Struct Reference . . . 1205

8.1227.1 Detailed Description . . . 1205
8.1227.2 Field Documentation . . . 1206
8.1227.2.1 ParamPresenceMask . . . 1206
8.1227.2.2 state . . . 1206
8.1228 unpack_dms_GetBandCapability_t Struct Reference . . . 1206
8.1228.1 Detailed Description . . . 1206
8.1228.2 Field Documentation . . . 1208
8.1228.2.1 BandCapability . . . 1208
8.1228.2.2 ParamPresenceMask . . . 1208
8.1228.2.3 Tlvresult . . . 1208
8.1229 unpack_dms_GetCrashAction_t Struct Reference . . . 1208
8.1229.1 Detailed Description . . . 1208
8.1229.2 Field Documentation . . . 1208
8.1229.2.1 DevCrashState . . . 1208
8.1229.2.2 ParamPresenceMask . . . 1209
8.1229.2.3 Tlvresult . . . 1209
8.1230 unpack_dms_GetCustFeature_t Struct Reference . . . 1209
8.1230.1 Detailed Description . . . 1209
8.1230.2 Field Documentation . . . 1211
8.1230.2.1 DHCPRelayEnabled . . . 1211
8.1230.2.2 DisableIMSI . . . 1211
8.1230.2.3 GpsEnable . . . 1211
8.1230.2.4 GPSLPM . . . 1211
8.1230.2.5 GPSSel . . . 1211
8.1230.2.6 IPFamSupport . . . 1211
8.1230.2.7 IsVoiceEnabled . . . 1211
8.1230.2.8 ParamPresenceMask . . . 1211
8.1230.2.9 RMAutoConnect . . . 1211
8.1230.2.10 SMSSupport . . . 1211
8.1230.2.11 Tlvresult . . . 1211
8.1231 unpack_dms_GetCustFeaturesV2_t Struct Reference . . . 1211
8.1231.1 Detailed Description . . . 1211
8.1231.2 Field Documentation . . . 1212
8.1231.2.1 GetCustomFeatureV2 . . . 1212
8.1231.2.2 ParamPresenceMask . . . 1212
8.1231.2.3 Tlvresult . . . 1212
8.1232 unpack_dms_GetDeviceCap_t Struct Reference . . . 1212
8.1232.1 Detailed Description . . . 1212
8.1232.2 Field Documentation . . . 1213
8.1232.2.1 DataServiceCapability . . . 1213

8.1232.2.2 MaxRXChannelRate . . . 1213
8.1232.2.3 MaxTXChannelRate . . . 1213
8.1232.2.4 ParamPresenceMask . . . 1213
8.1232.2.5 RadioIfaces . . . 1213
8.1232.2.6 RadioIfacesSize . . . 1213
8.1232.2.7 SimCapability . . . 1213
8.1232.2.8 Tlvresult . . . 1213
8.1233 unpack_dms_GetDeviceCapabilities_t Struct Reference . . . 1213
8.1233.1 Detailed Description . . . 1214
8.1233.2 Field Documentation . . . 1214
8.1233.2.1 dataServiceCaCapability . . . 1215
8.1233.2.2 maxRxChannelRate . . . 1215
8.1233.2.3 maxTxChannelRate . . . 1215
8.1233.2.4 ParamPresenceMask . . . 1215
8.1233.2.5 RadioIfaces . . . 1215
8.1233.2.6 radioIfacesSize . . . 1215
8.1233.2.7 simCapability . . . 1215
8.1234 unpack_dms_GetDeviceHardwareRev_t Struct Reference . . . 1215
8.1234.1 Detailed Description . . . 1215
8.1234.2 Field Documentation . . . 1215
8.1234.2.1 ParamPresenceMask . . . 1215
8.1234.2.2 String . . . 1215
8.1234.2.3 stringSize . . . 1215
8.1234.2.4 Tlvresult . . . 1216
8.1235 unpack_dms_GetDeviceMfr_t Struct Reference . . . 1216
8.1235.1 Detailed Description . . . 1216
8.1235.2 Field Documentation . . . 1216
8.1235.2.1 ParamPresenceMask . . . 1216
8.1235.2.2 String . . . 1216
8.1235.2.3 stringSize . . . 1216
8.1235.2.4 Tlvresult . . . 1216
8.1236 unpack_dms_GetDeviceSerialNumbers_t Struct Reference . . . 1216
8.1236.1 Detailed Description . . . 1217
8.1236.2 Field Documentation . . . 1218
8.1236.2.1 esnSize . . . 1218
8.1236.2.2 ESNString . . . 1218
8.1236.2.3 meiSize . . . 1218
8.1236.2.4 MEIString . . . 1218
8.1236.2.5 meiSvnSize . . . 1218
8.1236.2.6 meiSvnString . . . 1218

8.1236.2.7 meidSize . . . 1218
8.1236.2.8 MEIDString . . . 1218
8.1236.2.9 ParamPresenceMask . . . 1218
8.1236.2.10 Tlvresult . . . 1218
8.1237 unpack_dms_GetFirmwareInfo_t Struct Reference . . . 1218
8.1237.1 Detailed Description . . . 1219
8.1237.2 Field Documentation . . . 1219
8.1237.2.1 appversion_str . . . 1219
8.1237.2.2 bootversion_str . . . 1219
8.1237.2.3 carrier_str . . . 1220
8.1237.2.4 cur_carr_name . . . 1220
8.1237.2.5 cur_carr_rev . . . 1220
8.1237.2.6 modelid_str . . . 1220
8.1237.2.7 packageid_str . . . 1220
8.1237.2.8 ParamPresenceMask . . . 1220
8.1237.2.9 priversion_str . . . 1220
8.1237.2.10 sku_str . . . 1220
8.1237.2.11 Tlvresult . . . 1220
8.1238 unpack_dms_GetFirmwareRevision_t Struct Reference . . . 1220
8.1238.1 Detailed Description . . . 1220
8.1238.2 Field Documentation . . . 1221
8.1238.2.1 amssSize . . . 1221
8.1238.2.2 AMSSString . . . 1221
8.1238.2.3 ParamPresenceMask . . . 1221
8.1238.2.4 PRIString . . . 1221
8.1238.2.5 Tlvresult . . . 1221
8.1239 unpack_dms_GetFirmwareRevisions_t Struct Reference . . . 1221
8.1239.1 Detailed Description . . . 1221
8.1239.2 Field Documentation . . . 1222
8.1239.2.1 amssSize . . . 1222
8.1239.2.2 AMSSString . . . 1222
8.1239.2.3 bootSize . . . 1222
8.1239.2.4 BootString . . . 1222
8.1239.2.5 ParamPresenceMask . . . 1222
8.1239.2.6 priSize . . . 1222
8.1239.2.7 PRIString . . . 1222
8.1239.2.8 Tlvresult . . . 1222
8.1240 unpack_dms_GetFSN_t Struct Reference . . . 1222
8.1240.1 Detailed Description . . . 1222
8.1240.2 Field Documentation . . . 1223

8.1240.2.1 ParamPresenceMask . . . 1223
8.1240.2.2 String . . . 1223
8.1240.2.3 Tlvresult . . . 1223
8.1241 unpack_dms_GetHardwareRevision_t Struct Reference . . . 1223
8.1241.1 Detailed Description . . . 1223
8.1241.2 Field Documentation . . . 1223
8.1241.2.1 hwVer . . . 1223
8.1241.2.2 ParamPresenceMask . . . 1223
8.1242 unpack_dms_GetIMSI_t Struct Reference . . . 1223
8.1242.1 Detailed Description . . . 1223
8.1242.2 Field Documentation . . . 1224
8.1242.2.1 imsi . . . 1224
8.1242.2.2 ParamPresenceMask . . . 1224
8.1242.2.3 Tlvresult . . . 1224
8.1243 unpack_dms_GetManufacturer_t Struct Reference . . . 1224
8.1243.1 Detailed Description . . . 1224
8.1243.2 Field Documentation . . . 1224
8.1243.2.1 manufacturer . . . 1224
8.1243.2.2 ParamPresenceMask . . . 1224
8.1243.2.3 Tlvresult . . . 1224
8.1244 unpack_dms_GetModelID_t Struct Reference . . . 1225
8.1244.1 Detailed Description . . . 1225
8.1244.2 Field Documentation . . . 1225
8.1244.2.1 modelid . . . 1225
8.1244.2.2 ParamPresenceMask . . . 1225
8.1244.2.3 Tlvresult . . . 1225
8.1245 unpack_dms_GetNetworkTime_t Struct Reference . . . 1225
8.1245.1 Detailed Description . . . 1225
8.1245.2 Field Documentation . . . 1226
8.1245.2.1 ParamPresenceMask . . . 1226
8.1245.2.2 source . . . 1226
8.1245.2.3 timestamp . . . 1226
8.1245.2.4 Tlvresult . . . 1226
8.1246 unpack_dms_GetOfflineReason_t Struct Reference . . . 1226
8.1246.1 Detailed Description . . . 1226
8.1246.2 Field Documentation . . . 1227
8.1246.2.1 ParamPresenceMask . . . 1227
8.1246.2.2 pbPlatform . . . 1227
8.1246.2.3 pReasonMask . . . 1227
8.1246.2.4 Tlvresult . . . 1227

8.1247 unpack_dms_GetPower_t Struct Reference . . . 1227
8.1247.1 Detailed Description . . . 1227
8.1247.2 Field Documentation . . . 1228
8.1247.2.1 HardwareControlledMode . . . 1228
8.1247.2.2 OfflineReason . . . 1228
8.1247.2.3 OperationMode . . . 1228
8.1247.2.4 ParamPresenceMask . . . 1228
8.1247.2.5 Tlvresult . . . 1228
8.1248 unpack_dms_GetPRLVersion_t Struct Reference . . . 1228
8.1248.1 Detailed Description . . . 1228
8.1248.2 Field Documentation . . . 1229
8.1248.2.1 ParamPresenceMask . . . 1229
8.1248.2.2 Tlvresult . . . 1229
8.1248.2.3 u16PRLVersion . . . 1229
8.1248.2.4 u8PRLPreference . . . 1229
8.1249 unpack_dms_GetSerialNumbers_t Struct Reference . . . 1229
8.1249.1 Detailed Description . . . 1229
8.1249.2 Field Documentation . . . 1230
8.1249.2.1 esn . . . 1230
8.1249.2.2 mei_no . . . 1230
8.1249.2.3 meisv_svn . . . 1230
8.1249.2.4 meid . . . 1230
8.1249.2.5 ParamPresenceMask . . . 1230
8.1250 unpack_dms_GetUSBComp_t Struct Reference . . . 1230
8.1250.1 Detailed Description . . . 1230
8.1250.2 Field Documentation . . . 1232
8.1250.2.1 NumSupUSBComps . . . 1232
8.1250.2.2 ParamPresenceMask . . . 1232
8.1250.2.3 SupUSBComps . . . 1232
8.1250.2.4 Tlvresult . . . 1232
8.1250.2.5 USBComp . . . 1232
8.1251 unpack_dms_GetVoiceNumber_t Struct Reference . . . 1232
8.1251.1 Detailed Description . . . 1233
8.1251.2 Field Documentation . . . 1233
8.1251.2.1 MIN . . . 1233
8.1251.2.2 minSize . . . 1233
8.1251.2.3 ParamPresenceMask . . . 1233
8.1251.2.4 Tlvresult . . . 1233
8.1251.2.5 VoiceNumber . . . 1233
8.1251.2.6 voiceNumberSize . . . 1233

8.1252 qmi_dms_PSMCfgChange_ind_t Struct Reference . . . 1234
8.1252.1 Detailed Description . . . 1234
8.1252.2 Field Documentation . . . 1234
8.1252.2.1 ActiveTimer . . . 1234
8.1252.2.2 EnableState . . . 1234
8.1252.2.3 ParamPresenceMask . . . 1234
8.1252.2.4 PeriodicUpdateTimer . . . 1234
8.1252.2.5 Tlvresult . . . 1234
8.1253 qmi_dms_ResetToFactoryDefaults_t Struct Reference . . . 1234
8.1253.1 Detailed Description . . . 1235
8.1253.2 Field Documentation . . . 1235
8.1253.2.1 ParamPresenceMask . . . 1235
8.1253.2.2 Tlvresult . . . 1235
8.1254 qmi_dms_SetActivationStatusCallback_t Struct Reference . . . 1235
8.1254.1 Detailed Description . . . 1235
8.1254.2 Field Documentation . . . 1235
8.1254.2.1 ParamPresenceMask . . . 1235
8.1254.2.2 Tlvresult . . . 1235
8.1255 qmi_dms_SetCrashAction_t Struct Reference . . . 1235
8.1255.1 Detailed Description . . . 1236
8.1255.2 Field Documentation . . . 1236
8.1255.2.1 notused . . . 1236
8.1255.2.2 ParamPresenceMask . . . 1236
8.1256 qmi_dms_SetCustFeature_t Struct Reference . . . 1236
8.1256.1 Detailed Description . . . 1236
8.1256.2 Field Documentation . . . 1236
8.1256.2.1 ParamPresenceMask . . . 1236
8.1256.2.2 Tlvresult . . . 1236
8.1257 qmi_dms_SetCustFeaturesV2_t Struct Reference . . . 1236
8.1257.1 Detailed Description . . . 1237
8.1257.2 Field Documentation . . . 1237
8.1257.2.1 ParamPresenceMask . . . 1237
8.1257.2.2 Tlvresult . . . 1237
8.1258 qmi_dms_SetEventReport_ind_t Struct Reference . . . 1237
8.1258.1 Detailed Description . . . 1237
8.1258.2 Field Documentation . . . 1237
8.1258.2.1 ActivationStatusTlv . . . 1237
8.1258.2.2 OperatingModeTlv . . . 1238
8.1258.2.3 ParamPresenceMask . . . 1238
8.1258.2.4 Tlvresult . . . 1238

8.1259 unpack_dms_SetEventReport_t Struct Reference . . . 1238
8.1259.1 Detailed Description . . . 1238
8.1259.2 Field Documentation . . . 1238
8.1259.2.1 ParamPresenceMask . . . 1238
8.1259.2.2 Tlvresult . . . 1238
8.1260 unpack_dms_SetFirmwarePreference_t Struct Reference . . . 1238
8.1260.1 Detailed Description . . . 1238
8.1260.2 Field Documentation . . . 1239
8.1260.2.1 ParamPresenceMask . . . 1239
8.1260.2.2 Tlvresult . . . 1239
8.1261 unpack_dms_SetIndicationRegister_t Struct Reference . . . 1239
8.1261.1 Detailed Description . . . 1239
8.1261.2 Field Documentation . . . 1239
8.1261.2.1 ParamPresenceMask . . . 1239
8.1261.2.2 Tlvresult . . . 1239
8.1262 unpack_dms_SetPower_t Struct Reference . . . 1239
8.1262.1 Detailed Description . . . 1239
8.1262.2 Field Documentation . . . 1240
8.1262.2.1 ParamPresenceMask . . . 1240
8.1262.2.2 Tlvresult . . . 1240
8.1263 unpack_dms_SetUSBComp_t Struct Reference . . . 1240
8.1263.1 Detailed Description . . . 1240
8.1263.2 Field Documentation . . . 1240
8.1263.2.1 ParamPresenceMask . . . 1240
8.1263.2.2 Tlvresult . . . 1240
8.1264 unpack_dms_SLQSDmsSwiGetPCInfo_t Struct Reference . . . 1240
8.1264.1 Detailed Description . . . 1240
8.1264.2 Field Documentation . . . 1242
8.1264.2.1 has_LpmFlag . . . 1242
8.1264.2.2 has_PersistentLpm . . . 1242
8.1264.2.3 has_PowerOffMode . . . 1242
8.1264.2.4 has_Wdisable . . . 1243
8.1264.2.5 LpmFlag . . . 1243
8.1264.2.6 opMode . . . 1243
8.1264.2.7 ParamPresenceMask . . . 1243
8.1264.2.8 PersistentLpm . . . 1243
8.1264.2.9 PowerOffMode . . . 1243
8.1264.2.10 Wdisable . . . 1243
8.1265 unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t Struct Reference . . . 1243
8.1265.1 Detailed Description . . . 1243

8.1265.2 Field Documentation . . . 1244
8.1265.2.1 ParamPresenceMask . . . 1244
8.1265.2.2 source . . . 1244
8.1265.2.3 Tlvresult . . . 1244
8.1265.2.4 type . . . 1244
8.1266 unpack_dms_SLQSDmsSwiGetResetInfo_t Struct Reference . . . 1244
8.1266.1 Detailed Description . . . 1244
8.1266.2 Field Documentation . . . 1245
8.1266.2.1 ParamPresenceMask . . . 1245
8.1266.2.2 source . . . 1245
8.1266.2.3 Tlvresult . . . 1245
8.1266.2.4 type . . . 1245
8.1267 unpack_dms_SLQSDmsSwiGetUimSelection_t Struct Reference . . . 1245
8.1267.1 Detailed Description . . . 1245
8.1267.2 Field Documentation . . . 1246
8.1267.2.1 ParamPresenceMask . . . 1246
8.1267.2.2 pUimAutoSwitchActSlot . . . 1246
8.1267.2.3 uimSelect . . . 1246
8.1268 unpack_dms_SLQSDmsSwiIndicationRegister_t Struct Reference . . . 1246
8.1268.1 Detailed Description . . . 1246
8.1268.2 Field Documentation . . . 1247
8.1268.2.1 ParamPresenceMask . . . 1247
8.1268.2.2 Tlvresult . . . 1247
8.1269 unpack_dms_SLQSGetBandCapability_t Struct Reference . . . 1247
8.1269.1 Detailed Description . . . 1247
8.1269.2 Field Documentation . . . 1251
8.1269.2.1 bandCapability . . . 1251
8.1269.2.2 is_LteBandCapability_Available . . . 1251
8.1269.2.3 is_TdsBandCapability_Available . . . 1251
8.1269.2.4 LteBandCapability . . . 1251
8.1269.2.5 ParamPresenceMask . . . 1251
8.1269.2.6 TdsBandCapability . . . 1251
8.1270 unpack_dms_SLQSGetERIFile_t Struct Reference . . . 1251
8.1270.1 Detailed Description . . . 1251
8.1270.2 Field Documentation . . . 1252
8.1270.2.1 eriFile . . . 1252
8.1270.2.2 ParamPresenceMask . . . 1252
8.1270.2.3 Tlvresult . . . 1252
8.1271 unpack_dms_SLQSGetPowerSaveModeConfig_t Struct Reference . . . 1252
8.1271.1 Detailed Description . . . 1252

8.1271.2 Field Documentation . . . 1253
8.1271.2.1 pActiveTimer . . . 1253
8.1271.2.2 ParamPresenceMask . . . 1253
8.1271.2.3 pDurationDueToOOS . . . 1253
8.1271.2.4 pDurationThreshold . . . 1253
8.1271.2.5 pEarlyWakeupTime . . . 1253
8.1271.2.6 pPeriodicUpdateTimer . . . 1253
8.1271.2.7 pPsmEnableState . . . 1253
8.1271.2.8 pRandomizationWindow . . . 1253
8.1272 unpack_dms_SLQSSetPowerSaveModeConfig_t Struct Reference . . . 1253
8.1272.1 Detailed Description . . . 1253
8.1272.2 Field Documentation . . . 1254
8.1272.2.1 ParamPresenceMask . . . 1254
8.1272.2.2 Tlvresult . . . 1254
8.1273 unpack_dms_SLQSSwiClearDyingGaspStatistics_t Struct Reference . . . 1254
8.1273.1 Detailed Description . . . 1254
8.1273.2 Field Documentation . . . 1254
8.1273.2.1 ParamPresenceMask . . . 1254
8.1273.2.2 Tlvresult . . . 1254
8.1274 unpack_dms_SLQSSwiGetCrashInfo_t Struct Reference . . . 1254
8.1274.1 Detailed Description . . . 1254
8.1274.2 Field Documentation . . . 1255
8.1274.2.1 crashInfoParam . . . 1255
8.1274.2.2 ParamPresenceMask . . . 1255
8.1274.2.3 Tlvresult . . . 1255
8.1275 unpack_dms_SLQSSwiGetDyingGaspCfg_t Struct Reference . . . 1255
8.1275.1 Detailed Description . . . 1255
8.1275.2 Field Documentation . . . 1256
8.1275.2.1 ParamPresenceMask . . . 1256
8.1275.2.2 pGetDyingGaspCfg . . . 1256
8.1275.2.3 Tlvresult . . . 1256
8.1276 unpack_dms_SLQSSwiGetDyingGaspStatistics_t Struct Reference . . . 1256
8.1276.1 Detailed Description . . . 1256
8.1276.2 Field Documentation . . . 1256
8.1276.2.1 ParamPresenceMask . . . 1256
8.1276.2.2 pGetDyingGaspStatistics . . . 1256
8.1276.2.3 Tlvresult . . . 1256
8.1277 unpack_dms_SLQSSwiGetFirmwareCurr_t Struct Reference . . . 1256
8.1277.1 Detailed Description . . . 1257
8.1277.2 Field Documentation . . . 1257

8.1277.2.1 carrier . . . 1257
8.1277.2.2 fwvers . . . 1257
8.1277.2.3 numEntries . . . 1257
8.1277.2.4 ParamPresenceMask . . . 1257
8.1277.2.5 pCurrImgInfo . . . 1257
8.1277.2.6 pkgver . . . 1257
8.1277.2.7 priver . . . 1257
8.1278 unpack_dms_SLQSSwiGetFwUpdateStatus_t Struct Reference . . . 1257
8.1278.1 Detailed Description . . . 1258
8.1278.2 Field Documentation . . . 1259
8.1278.2.1 imgType . . . 1259
8.1278.2.2 logString . . . 1259
8.1278.2.3 ParamPresenceMask . . . 1259
8.1278.2.4 refData . . . 1259
8.1278.2.5 refString . . . 1259
8.1278.2.6 ResCode . . . 1259
8.1278.2.7 Tlvresult . . . 1259
8.1279 unpack_dms_SLQSSwiGetHostDevInfo_t Struct Reference . . . 1259
8.1279.1 Detailed Description . . . 1259
8.1279.2 Field Documentation . . . 1260
8.1279.2.1 hostID . . . 1260
8.1279.2.2 manString . . . 1260
8.1279.2.3 modelString . . . 1260
8.1279.2.4 ParamPresenceMask . . . 1260
8.1279.2.5 plasmaIDString . . . 1260
8.1279.2.6 swVerString . . . 1260
8.1279.2.7 Tlvresult . . . 1260
8.1280 unpack_dms_SLQSSwiGetOSInfo_t Struct Reference . . . 1260
8.1280.1 Detailed Description . . . 1261
8.1280.2 Field Documentation . . . 1261
8.1280.2.1 nameString . . . 1261
8.1280.2.2 ParamPresenceMask . . . 1261
8.1280.2.3 Tlvresult . . . 1261
8.1280.2.4 versionString . . . 1261
8.1281 unpack_dms_SLQSSwiGetSerialNoExt_t Struct Reference . . . 1261
8.1281.1 Detailed Description . . . 1261
8.1281.2 Field Documentation . . . 1262
8.1281.2.1 meidString . . . 1262
8.1281.2.2 ParamPresenceMask . . . 1262
8.1281.2.3 Tlvresult . . . 1262

8.1282 Unpack_dms_SLQSSwiSetDyingGaspCfg_t Struct Reference . . . 1262
8.1282.1 Detailed Description . . . 1262
8.1282.2 Field Documentation . . . 1262
8.1282.2.1 ParamPresenceMask . . . 1262
8.1282.2.2 Tlvresult . . . 1262
8.1283 Unpack_dms_SLQSSwiSetHostDevInfo_t Struct Reference . . . 1262
8.1283.1 Detailed Description . . . 1262
8.1283.2 Field Documentation . . . 1263
8.1283.2.1 ParamPresenceMask . . . 1263
8.1283.2.2 Tlvresult . . . 1263
8.1284 Unpack_dms_SLQSSwiSetOSInfo_t Struct Reference . . . 1263
8.1284.1 Detailed Description . . . 1263
8.1284.2 Field Documentation . . . 1263
8.1284.2.1 ParamPresenceMask . . . 1263
8.1284.2.2 Tlvresult . . . 1263
8.1285 Unpack_dms_SLQSUIMGetState_t Struct Reference . . . 1263
8.1285.1 Detailed Description . . . 1263
8.1285.2 Field Documentation . . . 1264
8.1285.2.1 ParamPresenceMask . . . 1264
8.1285.2.2 state . . . 1264
8.1285.2.3 Tlvresult . . . 1264
8.1286 Unpack_dms_SwiEventReportCallBack_ind_t Struct Reference . . . 1264
8.1286.1 Detailed Description . . . 1264
8.1286.2 Field Documentation . . . 1265
8.1286.2.1 ParamPresenceMask . . . 1265
8.1286.2.2 TempTlv . . . 1265
8.1286.2.3 UimStatusTlv . . . 1265
8.1286.2.4 VoltTlv . . . 1265
8.1287 Unpack_dms_SwiSetEventReport_t Struct Reference . . . 1265
8.1287.1 Detailed Description . . . 1265
8.1287.2 Field Documentation . . . 1265
8.1287.2.1 ParamPresenceMask . . . 1265
8.1287.2.2 Tlvresult . . . 1265
8.1288 Unpack_dms_SwiUimSelect_t Struct Reference . . . 1265
8.1288.1 Detailed Description . . . 1265
8.1288.2 Field Documentation . . . 1266
8.1288.2.1 ParamPresenceMask . . . 1266
8.1288.2.2 Tlvresult . . . 1266
8.1289 Unpack_dms_UIMGetControlKeyStatus_t Struct Reference . . . 1266
8.1289.1 Detailed Description . . . 1266

8.1289.2 Field Documentation . . . 1267
8.1289.2.1 facilityState . . . 1267
8.1289.2.2 ParamPresenceMask . . . 1267
8.1289.2.3 Tlvresult . . . 1267
8.1289.2.4 unblockRetriesLeft . . . 1267
8.1289.2.5 verifyRetriesLeft . . . 1267
8.1290 unpack_dms_UIMGetICCID_t Struct Reference . . . 1267
8.1290.1 Detailed Description . . . 1267
8.1290.2 Field Documentation . . . 1267
8.1290.2.1 ParamPresenceMask . . . 1267
8.1290.2.2 String . . . 1267
8.1290.2.3 stringSize . . . 1267
8.1290.2.4 Tlvresult . . . 1267
8.1291 unpack_dms_UIMGetPINStatus_t Struct Reference . . . 1268
8.1291.1 Detailed Description . . . 1268
8.1291.2 Field Documentation . . . 1269
8.1291.2.1 p1Status . . . 1269
8.1291.2.2 p1UnblockRetriesLeft . . . 1269
8.1291.2.3 p1VerifyRetriesLeft . . . 1269
8.1291.2.4 p2Status . . . 1269
8.1291.2.5 p2UnblockRetriesLeft . . . 1269
8.1291.2.6 p2VerifyRetriesLeft . . . 1269
8.1291.2.7 ParamPresenceMask . . . 1269
8.1291.2.8 Tlvresult . . . 1269
8.1292 unpack_dms_UIMSetControlKeyProtection_t Struct Reference . . . 1269
8.1292.1 Detailed Description . . . 1269
8.1292.2 Field Documentation . . . 1270
8.1292.2.1 ParamPresenceMask . . . 1270
8.1292.2.2 Tlvresult . . . 1270
8.1292.2.3 verifyRetriesLeft . . . 1270
8.1293 unpack_dms_UIMSetPINProtection_t Struct Reference . . . 1270
8.1293.1 Detailed Description . . . 1270
8.1293.2 Field Documentation . . . 1271
8.1293.2.1 ParamPresenceMask . . . 1271
8.1293.2.2 Tlvresult . . . 1271
8.1293.2.3 unblockRetriesLeft . . . 1271
8.1293.2.4 verifyRetriesLeft . . . 1271
8.1294 unpack_dms_UIMUnblockControlKey_t Struct Reference . . . 1271
8.1294.1 Detailed Description . . . 1271
8.1294.2 Field Documentation . . . 1271

8.1294.2.1 ParamPresenceMask . . . 1271
8.1294.2.2 Tlvresult . . . 1271
8.1294.2.3 unblockRetriesLeft . . . 1271
8.1295 unpack_fms_GetImagesPreference_t Struct Reference . . . 1271
8.1295.1 Detailed Description . . . 1272
8.1295.2 Field Documentation . . . 1272
8.1295.2.1 ImageListSize . . . 1272
8.1295.2.2 ParamPresenceMask . . . 1272
8.1295.2.3 pImageList . . . 1272
8.1295.2.4 Tlvresult . . . 1272
8.1296 unpack_fms_GetStoredImages_t Struct Reference . . . 1272
8.1296.1 Detailed Description . . . 1272
8.1296.2 Field Documentation . . . 1273
8.1296.2.1 imageList . . . 1273
8.1296.2.2 imagelistSize . . . 1273
8.1296.2.3 ParamPresenceMask . . . 1273
8.1296.2.4 Tlvresult . . . 1273
8.1297 unpack_fms_SetImagesPreference_t Struct Reference . . . 1273
8.1297.1 Detailed Description . . . 1273
8.1297.2 Field Documentation . . . 1273
8.1297.2.1 ImageTypes . . . 1273
8.1297.2.2 imageTypesSize . . . 1273
8.1297.2.3 ParamPresenceMask . . . 1273
8.1297.2.4 Tlvresult . . . 1273
8.1298 unpack_loc_BestAvailPos_Ind_t Struct Reference . . . 1273
8.1298.1 Detailed Description . . . 1274
8.1298.2 Field Documentation . . . 1279
8.1298.2.1 pAltitudeWrtEllipsoid . . . 1279
8.1298.2.2 pAltitudeWrtMeanSeaLevel . . . 1279
8.1298.2.3 ParamPresenceMask . . . 1279
8.1298.2.4 pGpsTime . . . 1279
8.1298.2.5 pHeading . . . 1279
8.1298.2.6 pHeadingUnc . . . 1279
8.1298.2.7 pHorCirConf . . . 1279
8.1298.2.8 pHorEllpConf . . . 1279
8.1298.2.9 pHorReliability . . . 1279
8.1298.2.10 pHorUncCircular . . . 1280
8.1298.2.11 pHorUncEllipseOrientAzimuth . . . 1280
8.1298.2.12 pHorUncEllipseSemiMajor . . . 1280
8.1298.2.13 pHorUncEllipseSemiMinor . . . 1280

8.1298.2.14 Latitude . . . 1280
8.1298.2.15 Longitude . . . 1280
8.1298.2.16 MagneticDeviation . . . 1280
8.1298.2.17 PrecisionDilution . . . 1280
8.1298.2.18 SensorDataUsage . . . 1280
8.1298.2.19 SpeedHorizontal . . . 1280
8.1298.2.20 SpeedUnc . . . 1280
8.1298.2.21 SpeedVertical . . . 1280
8.1298.2.22 SpeedVerticalUnc . . . 1280
8.1298.2.23 SvUsedforFix . . . 1280
8.1298.2.24 TechnologyMask . . . 1280
8.1298.2.25 TimeSrc . . . 1280
8.1298.2.26 TimestampUtc . . . 1280
8.1298.2.27 TimeUnc . . . 1280
8.1298.2.28 VertConfidence . . . 1280
8.1298.2.29 VertReliability . . . 1280
8.1298.2.30 VertUnc . . . 1280
8.1298.2.31 Xid . . . 1280
8.1298.2.32 status . . . 1280
8.1298.2.33 Tlvresult . . . 1280
8.1299 unpack_loc_CradleMountCallback_Ind_t Struct Reference . . . 1280
8.1299.1 Detailed Description . . . 1281
8.1299.2 Field Documentation . . . 1281
8.1299.2.1 cradleMountConfigStatus . . . 1281
8.1299.2.2 ParamPresenceMask . . . 1281
8.1300 unpack_loc_Delete_Assist_Data_t Struct Reference . . . 1281
8.1300.1 Detailed Description . . . 1281
8.1300.2 Field Documentation . . . 1281
8.1300.2.1 ParamPresenceMask . . . 1281
8.1300.2.2 Tlvresult . . . 1281
8.1301 unpack_loc_DeleteAssistData_Ind_t Struct Reference . . . 1282
8.1301.1 Detailed Description . . . 1282
8.1301.2 Field Documentation . . . 1282
8.1301.2.1 ParamPresenceMask . . . 1282
8.1301.2.2 status . . . 1282
8.1301.2.3 Tlvresult . . . 1282
8.1302 unpack_loc_EngineState_Ind_t Struct Reference . . . 1282
8.1302.1 Detailed Description . . . 1283
8.1302.2 Field Documentation . . . 1283
8.1302.2.1 engineState . . . 1283

8.1302.2.2 ParamPresenceMask . . . 1283
8.1302.2.3 Tlvresult . . . 1283
8.1303 unpack_loc_EventNMEA_Ind_t Struct Reference . . . 1283
8.1303.1 Detailed Description . . . 1283
8.1303.2 Field Documentation . . . 1284
8.1303.2.1 NMEAData . . . 1284
8.1303.2.2 ParamPresenceMask . . . 1284
8.1303.2.3 Tlvresult . . . 1284
8.1304 unpack_loc_EventRegister_t Struct Reference . . . 1284
8.1304.1 Detailed Description . . . 1284
8.1304.2 Field Documentation . . . 1284
8.1304.2.1 ParamPresenceMask . . . 1284
8.1304.2.2 Tlvresult . . . 1284
8.1305 unpack_loc_EventTimeSyncCallback_Ind_t Struct Reference . . . 1284
8.1305.1 Detailed Description . . . 1284
8.1305.2 Field Documentation . . . 1284
8.1305.2.1 ParamPresenceMask . . . 1285
8.1305.2.2 timeSyncRefCounter . . . 1285
8.1306 unpack_loc_GetOpMode_Ind_t Struct Reference . . . 1285
8.1306.1 Detailed Description . . . 1285
8.1306.2 Field Documentation . . . 1286
8.1306.2.1 ParamPresenceMask . . . 1286
8.1306.2.2 pMode . . . 1286
8.1306.2.3 Status . . . 1286
8.1307 unpack_loc_GetServer_Ind_t Struct Reference . . . 1286
8.1307.1 Detailed Description . . . 1286
8.1307.2 Field Documentation . . . 1287
8.1307.2.1 ParamPresenceMask . . . 1287
8.1307.2.2 pIPv4AddrInfo . . . 1287
8.1307.2.3 pIPv6AddrInfo . . . 1287
8.1307.2.4 pURL . . . 1288
8.1307.2.5 serverStatus . . . 1288
8.1307.2.6 serverType . . . 1288
8.1307.2.7 Tlvresult . . . 1288
8.1308 unpack_loc_GnssSvInfo_Ind_t Struct Reference . . . 1288
8.1308.1 Detailed Description . . . 1288
8.1308.2 Field Documentation . . . 1288
8.1308.2.1 altitudeAssumed . . . 1288
8.1308.2.2 ParamPresenceMask . . . 1288
8.1308.2.3 pSatelliteInfo . . . 1288

8.1308.2.4 Tlvresult . . . 1288
8.1309 unpack_loc_InjectPositionCallback_Ind_t Struct Reference . . . 1288
8.1309.1 Detailed Description . . . 1289
8.1309.2 Field Documentation . . . 1289
8.1309.2.1 ParamPresenceMask . . . 1289
8.1309.2.2 status . . . 1289
8.1310 unpack_loc_InjectSensorDataCallback_Ind_t Struct Reference . . . 1289
8.1310.1 Detailed Description . . . 1289
8.1310.2 Field Documentation . . . 1290
8.1310.2.1 injectSensorDataStatus . . . 1290
8.1310.2.2 pAccelSamplesAccepted . . . 1290
8.1310.2.3 pAccelTempSamplesAccepted . . . 1291
8.1310.2.4 ParamPresenceMask . . . 1291
8.1310.2.5 pGyroSamplesAccepted . . . 1291
8.1310.2.6 pGyroTempSamplesAccepted . . . 1291
8.1310.2.7 pOpaqueIdentifier . . . 1291
8.1311 unpack_loc_InjectTimeSyncDataCallback_Ind_t Struct Reference . . . 1291
8.1311.1 Detailed Description . . . 1291
8.1311.2 Field Documentation . . . 1291
8.1311.2.1 injectTimeSyncStatus . . . 1291
8.1311.2.2 ParamPresenceMask . . . 1291
8.1312 unpack_loc_InjectUTCTimeCallback_Ind_t Struct Reference . . . 1291
8.1312.1 Detailed Description . . . 1292
8.1312.2 Field Documentation . . . 1292
8.1312.2.1 ParamPresenceMask . . . 1292
8.1312.2.2 status . . . 1292
8.1313 unpack_loc_PositionRpt_Ind_t Struct Reference . . . 1292
8.1313.1 Detailed Description . . . 1293
8.1313.2 Field Documentation . . . 1298
8.1313.2.1 pAltitudeAssumed . . . 1298
8.1313.2.2 pAltitudeWrtEllipsoid . . . 1298
8.1313.2.3 pAltitudeWrtMeanSeaLevel . . . 1298
8.1313.2.4 ParamPresenceMask . . . 1298
8.1313.2.5 pFixId . . . 1298
8.1313.2.6 pGpsTime . . . 1298
8.1313.2.7 pHeading . . . 1298
8.1313.2.8 pHeadingUnc . . . 1298
8.1313.2.9 pHorConfidence . . . 1298
8.1313.2.10 pHorReliability . . . 1298
8.1313.2.11 pHorUncCircular . . . 1298

8.1313.2.12 pHorUncEllipseOrientAzimuth . . . 1298
8.1313.2.13 pHorUncEllipseSemiMajor . . . 1298
8.1313.2.14 pHorUncEllipseSemiMinor . . . 1298
8.1313.2.15 pLatitude . . . 1298
8.1313.2.16 pLeapSeconds . . . 1298
8.1313.2.17 pLongitude . . . 1298
8.1313.2.18 pMagneticDeviation . . . 1298
8.1313.2.19 pPrecisionDilution . . . 1298
8.1313.2.20 pSensorDataUsage . . . 1298
8.1313.2.21 pSpeedHorizontal . . . 1298
8.1313.2.22 pSpeedUnc . . . 1298
8.1313.2.23 pSpeedVertical . . . 1298
8.1313.2.24 pSvUsedforFix . . . 1298
8.1313.2.25 pTechnologyMask . . . 1298
8.1313.2.26 pTimeSrc . . . 1298
8.1313.2.27 pTimestampUtc . . . 1298
8.1313.2.28 pTimeUnc . . . 1299
8.1313.2.29 pVertConfidence . . . 1299
8.1313.2.30 pVertReliability . . . 1299
8.1313.2.31 pVertUnc . . . 1299
8.1313.2.32 sessionId . . . 1299
8.1313.2.33 sessionStatus . . . 1299
8.1313.2.34 Tlvresult . . . 1299
8.1314 unpack_loc_SensorStreamingCallback_Ind_t Struct Reference . . . 1299
8.1314.1 Detailed Description . . . 1299
8.1314.2 Field Documentation . . . 1299
8.1314.2.1 pAccelAcceptReady . . . 1299
8.1314.2.2 pAccelTempAcceptReady . . . 1299
8.1314.2.3 ParamPresenceMask . . . 1300
8.1314.2.4 pGyroAcceptReady . . . 1300
8.1314.2.5 pGyroTempAcceptReady . . . 1300
8.1315 unpack_loc_SetExtPowerConfig_Ind_t Struct Reference . . . 1300
8.1315.1 Detailed Description . . . 1300
8.1315.2 Field Documentation . . . 1300
8.1315.2.1 ParamPresenceMask . . . 1300
8.1315.2.2 status . . . 1300
8.1315.2.3 Tlvresult . . . 1300
8.1316 unpack_loc_SetExtPowerState_t Struct Reference . . . 1300
8.1316.1 Detailed Description . . . 1301
8.1316.2 Field Documentation . . . 1301

8.1316.2.1 ParamPresenceMask . . . 1301
8.1316.2.2 Tlvresult . . . 1301
8.1317 unpack_loc_SetOperationMode_Ind_t Struct Reference . . . 1301
8.1317.1 Detailed Description . . . 1301
8.1317.2 Field Documentation . . . 1302
8.1317.2.1 ParamPresenceMask . . . 1302
8.1317.2.2 status . . . 1302
8.1317.2.3 Tlvresult . . . 1302
8.1318 unpack_loc_SetOperationMode_t Struct Reference . . . 1302
8.1318.1 Detailed Description . . . 1302
8.1318.2 Field Documentation . . . 1302
8.1318.2.1 ParamPresenceMask . . . 1302
8.1318.2.2 Tlvresult . . . 1302
8.1319 unpack_loc_SetServer_Ind_t Struct Reference . . . 1302
8.1319.1 Detailed Description . . . 1302
8.1319.2 Field Documentation . . . 1303
8.1319.2.1 ParamPresenceMask . . . 1303
8.1319.2.2 serverStatus . . . 1303
8.1319.2.3 Tlvresult . . . 1303
8.1320 unpack_loc_SLQSLOCGetBestAvailPos_t Struct Reference . . . 1303
8.1320.1 Detailed Description . . . 1303
8.1320.2 Field Documentation . . . 1304
8.1320.2.1 ParamPresenceMask . . . 1304
8.1320.2.2 Tlvresult . . . 1304
8.1321 unpack_loc_SLQSLOCGetOpMode_t Struct Reference . . . 1304
8.1321.1 Detailed Description . . . 1304
8.1321.2 Field Documentation . . . 1304
8.1321.2.1 ParamPresenceMask . . . 1304
8.1321.2.2 Tlvresult . . . 1304
8.1322 unpack_loc_Start_t Struct Reference . . . 1304
8.1322.1 Detailed Description . . . 1304
8.1322.2 Field Documentation . . . 1305
8.1322.2.1 ParamPresenceMask . . . 1305
8.1322.2.2 Tlvresult . . . 1305
8.1323 unpack_loc_Stop_t Struct Reference . . . 1305
8.1323.1 Detailed Description . . . 1305
8.1323.2 Field Documentation . . . 1305
8.1323.2.1 ParamPresenceMask . . . 1305
8.1323.2.2 Tlvresult . . . 1305
8.1324 unpack_nas_GetACCOLC_t Struct Reference . . . 1305

8.1324.1 Detailed Description . . . 1305
8.1324.2 Field Documentation . . . 1306
8.1324.2.1 pAccolc . . . 1306
8.1324.2.2 ParamPresenceMask . . . 1306
8.1325 unpack_nas_GetANAAAAuthenticationStatus_t Struct Reference . . . 1306
8.1325.1 Detailed Description . . . 1306
8.1325.2 Field Documentation . . . 1306
8.1325.2.1 ParamPresenceMask . . . 1306
8.1325.2.2 pAuthStatus . . . 1306
8.1326 unpack_nas_GetCDMANetworkParameters_t Struct Reference . . . 1306
8.1326.1 Detailed Description . . . 1307
8.1326.2 Field Documentation . . . 1308
8.1326.2.1 Application . . . 1308
8.1326.2.2 Broadcast . . . 1308
8.1326.2.3 CustomSCP . . . 1308
8.1326.2.4 ForceRev0 . . . 1308
8.1326.2.5 ParamPresenceMask . . . 1308
8.1326.2.6 Protocol . . . 1308
8.1326.2.7 RegForeignNID . . . 1308
8.1326.2.8 RegForeignSID . . . 1309
8.1326.2.9 RegHomeSID . . . 1309
8.1326.2.10 Roaming . . . 1309
8.1326.2.11 SCI . . . 1309
8.1326.2.12 SCM . . . 1309
8.1327 unpack_nas_GetHomeNetwork3GPP2_t Struct Reference . . . 1309
8.1327.1 Detailed Description . . . 1309
8.1327.2 Field Documentation . . . 1311
8.1327.2.1 nameSize . . . 1311
8.1327.2.2 ParamPresenceMask . . . 1311
8.1327.2.3 pMCC . . . 1311
8.1327.2.4 pMNC . . . 1311
8.1327.2.5 pName . . . 1311
8.1327.2.6 pNID . . . 1311
8.1327.2.7 pNw2DescDisp . . . 1311
8.1327.2.8 pNw2DescEnc . . . 1311
8.1327.2.9 pNw2DescLen . . . 1311
8.1327.2.10 pNw2MCC . . . 1311
8.1327.2.11 pNw2MNC . . . 1311
8.1327.2.12 pNw2Name . . . 1311
8.1327.2.13 pSID . . . 1311

8.1328 unpack_nas_GetHomeNetwork_t Struct Reference . . . 1311
8.1328.1 Detailed Description . . . 1311
8.1328.2 Field Documentation . . . 1312
8.1328.2.1 mcc . . . 1312
8.1328.2.2 mnc . . . 1312
8.1328.2.3 name . . . 1312
8.1328.2.4 nid . . . 1312
8.1328.2.5 ParamPresenceMask . . . 1312
8.1328.2.6 sid . . . 1312
8.1329 unpack_nas_GetNetworkPreference_t Struct Reference . . . 1312
8.1329.1 Detailed Description . . . 1312
8.1329.2 Field Documentation . . . 1313
8.1329.2.1 ActiveTechPref . . . 1313
8.1329.2.2 Duration . . . 1313
8.1329.2.3 ParamPresenceMask . . . 1313
8.1329.2.4 PersistentTechPref . . . 1313
8.1329.2.5 Tlvresult . . . 1313
8.1330 unpack_nas_GetRFInfo_t Struct Reference . . . 1313
8.1330.1 Detailed Description . . . 1314
8.1330.2 Field Documentation . . . 1314
8.1330.2.1 instancesSize . . . 1314
8.1330.2.2 ParamPresenceMask . . . 1314
8.1330.2.3 RFBandInfoElements . . . 1314
8.1331 unpack_nas_GetServingNetwork_t Struct Reference . . . 1314
8.1331.1 Detailed Description . . . 1315
8.1331.2 Field Documentation . . . 1316
8.1331.2.1 CSDomain . . . 1316
8.1331.2.2 DataCaps . . . 1316
8.1331.2.3 DataCapsLen . . . 1316
8.1331.2.4 MCC . . . 1316
8.1331.2.5 MNC . . . 1316
8.1331.2.6 Name . . . 1317
8.1331.2.7 nameSize . . . 1317
8.1331.2.8 ParamPresenceMask . . . 1317
8.1331.2.9 PSDomain . . . 1317
8.1331.2.10 RadioIfaces . . . 1317
8.1331.2.11 RadioIfacesSize . . . 1317
8.1331.2.12 RAN . . . 1317
8.1331.2.13 RegistrationState . . . 1317
8.1331.2.14 Roaming . . . 1317

8.1332 nnpack_nas_GetServingNetworkCapabilities_t Struct Reference . . . 1317
8.1332.1 Detailed Description . . . 1317
8.1332.2 Field Documentation . . . 1318
8.1332.2.1 DataCaps . . . 1318
8.1332.2.2 DataCapsLen . . . 1318
8.1332.2.3 ParamPresenceMask . . . 1318
8.1333 nnpack_nas_GetSignalStrengths_t Struct Reference . . . 1318
8.1333.1 Detailed Description . . . 1318
8.1333.2 Field Documentation . . . 1318
8.1333.2.1 len . . . 1318
8.1333.2.2 ParamPresenceMask . . . 1318
8.1333.2.3 radio . . . 1318
8.1333.2.4 rssi . . . 1318
8.1334 nnpack_nas_PerformNetworkScan_t Struct Reference . . . 1319
8.1334.1 Detailed Description . . . 1319
8.1334.2 Field Documentation . . . 1320
8.1334.2.1 p3GppNetworkInfoInstances . . . 1320
8.1334.2.2 p3GppNetworkInstanceSize . . . 1320
8.1334.2.3 ParamPresenceMask . . . 1320
8.1334.2.4 pLteOpModeTlv . . . 1320
8.1334.2.5 pPCIInfo . . . 1320
8.1334.2.6 pPCSInstance . . . 1320
8.1334.2.7 pPCSInstanceSize . . . 1320
8.1334.2.8 pRATINstance . . . 1320
8.1334.2.9 pRATInstanceSize . . . 1320
8.1334.2.10 pScanResult . . . 1320
8.1335 nnpack_nas_SetDataCapabilitiesCallback_ind_t Struct Reference . . . 1320
8.1335.1 Detailed Description . . . 1321
8.1335.2 Field Documentation . . . 1321
8.1335.2.1 dataCaps . . . 1321
8.1335.2.2 dataCapsSize . . . 1321
8.1335.2.3 ParamPresenceMask . . . 1321
8.1336 nnpack_nas_SetEventReportInd_t Struct Reference . . . 1321
8.1336.1 Detailed Description . . . 1321
8.1336.2 Field Documentation . . . 1322
8.1336.2.1 ParamPresenceMask . . . 1322
8.1336.2.2 RFTlv . . . 1322
8.1336.2.3 RRTlv . . . 1322
8.1336.2.4 SLQSSSTlv . . . 1322
8.1336.2.5 SSTlv . . . 1322

8.1337 unpack_nas_SetNasLTECphyCaIndCallback_ind_t Struct Reference . . . 1322
8.1337.1 Detailed Description . . . 1322
8.1337.2 Field Documentation . . . 1323
8.1337.2.1 ParamPresenceMask . . . 1323
8.1337.2.2 sPhyCaAggPcellInfo . . . 1323
8.1337.2.3 sPhyCaAggScellDlBw . . . 1323
8.1337.2.4 sPhyCaAggScellIndex . . . 1323
8.1337.2.5 sPhyCaAggScellIndType . . . 1323
8.1337.2.6 sPhyCaAggScellInfo . . . 1323
8.1338 unpack_nas_SetNetworkPreference_t Struct Reference . . . 1323
8.1338.1 Detailed Description . . . 1323
8.1338.2 Field Documentation . . . 1323
8.1338.2.1 ParamPresenceMask . . . 1324
8.1338.2.2 Tlvresult . . . 1324
8.1339 unpack_nas_SetRoamingIndicatorCallback_ind_t Struct Reference . . . 1324
8.1339.1 Detailed Description . . . 1324
8.1339.2 Field Documentation . . . 1324
8.1339.2.1 ParamPresenceMask . . . 1324
8.1339.2.2 roaming . . . 1324
8.1340 unpack_nas_SetServingSystemCallback_ind_t Struct Reference . . . 1324
8.1340.1 Detailed Description . . . 1324
8.1340.2 Field Documentation . . . 1325
8.1340.2.1 ParamPresenceMask . . . 1325
8.1340.2.2 SSInfo . . . 1325
8.1340.2.3 Tlvresult . . . 1325
8.1341 unpack_nas_SLQSGetErrorRate_t Struct Reference . . . 1325
8.1341.1 Detailed Description . . . 1325
8.1341.2 Field Documentation . . . 1326
8.1341.2.1 ParamPresenceMask . . . 1326
8.1341.2.2 pCDMAFrameErrRate . . . 1326
8.1341.2.3 pGSMBER . . . 1326
8.1341.2.4 pHDRPackErrRate . . . 1326
8.1341.2.5 pWCDMABER . . . 1326
8.1342 unpack_nas_SlqsGetLTECphyCAInfo_t Struct Reference . . . 1326
8.1342.1 Detailed Description . . . 1326
8.1342.2 Field Documentation . . . 1327
8.1342.2.1 LTECphyCaInfo . . . 1327
8.1342.2.2 ParamPresenceMask . . . 1327
8.1342.2.3 Tlvresult . . . 1327
8.1343 unpack_nas_SLQSGetNetworkTime_t Struct Reference . . . 1327

8.1343.1 Detailed Description . . . 1327
8.1343.2 Field Documentation . . . 1327
8.1343.2.1 p3GPP2TimeInfo . . . 1327
8.1343.2.2 p3GPPTimeInfo . . . 1327
8.1343.2.3 ParamPresenceMask . . . 1327
8.1344 unpack_nas_SLQSGetOperatorNameData_t Struct Reference . . . 1327
8.1344.1 Detailed Description . . . 1328
8.1344.2 Field Documentation . . . 1328
8.1344.2.1 ParamPresenceMask . . . 1328
8.1344.2.2 pNITZInformation . . . 1328
8.1344.2.3 pOperatorNameString . . . 1328
8.1344.2.4 pOperatorPLMNList . . . 1328
8.1344.2.5 pPLMNNetworkName . . . 1328
8.1344.2.6 pSrvcProviderName . . . 1328
8.1345 unpack_nas_SLQSGetPLMNName_t Struct Reference . . . 1329
8.1345.1 Detailed Description . . . 1329
8.1345.2 Field Documentation . . . 1331
8.1345.2.1 longName . . . 1331
8.1345.2.2 longNameCI . . . 1331
8.1345.2.3 longNameEn . . . 1331
8.1345.2.4 longNameLen . . . 1331
8.1345.2.5 longNameSB . . . 1331
8.1345.2.6 ParamPresenceMask . . . 1331
8.1345.2.7 shortName . . . 1331
8.1345.2.8 shortNameCI . . . 1331
8.1345.2.9 shortNameEn . . . 1331
8.1345.2.10 shortNameLen . . . 1331
8.1345.2.11 shortNameSB . . . 1331
8.1345.2.12 spn . . . 1331
8.1345.2.13 spnEncoding . . . 1332
8.1345.2.14 spnLength . . . 1332
8.1346 unpack_nas_SLQSGetServingSystem_t Struct Reference . . . 1332
8.1346.1 Detailed Description . . . 1332
8.1346.2 Field Documentation . . . 1335
8.1346.2.1 BasestationID . . . 1335
8.1346.2.2 BasestationLatitude . . . 1335
8.1346.2.3 BasestationLongitude . . . 1335
8.1346.2.4 CallBarStatus . . . 1335
8.1346.2.5 CDMA_P_Rev . . . 1335
8.1346.2.6 CDMASystemInfoExt . . . 1335

8.1346.2.7 CellID . . . 1336
8.1346.2.8 ConcSvcInfo . . . 1336
8.1346.2.9 CurrentPLMN . . . 1336
8.1346.2.10 DataSrvCapabilities . . . 1336
8.1346.2.11 DefaultRoamInd . . . 1336
8.1346.2.12 DetailedSvcInfo . . . 1336
8.1346.2.13 DTMInd . . . 1336
8.1346.2.14 Gpp2TimeZone . . . 1336
8.1346.2.15 GppNetworkDSTAdjustment . . . 1336
8.1346.2.16 GppTimeZone . . . 1336
8.1346.2.17 HdrPersonality . . . 1336
8.1346.2.18 lac . . . 1336
8.1346.2.19 NetworkID . . . 1336
8.1346.2.20 ParamPresenceMask . . . 1336
8.1346.2.21 PRLInd . . . 1336
8.1346.2.22 RoamIndicatorVal . . . 1336
8.1346.2.23 RoamingIndicatorList . . . 1336
8.1346.2.24 ServingSystem . . . 1336
8.1346.2.25 SystemID . . . 1336
8.1346.2.26 TrackAreaCode . . . 1336
8.1347 unpack_nas_SLQSGetSignalStrength_t Struct Reference . . . 1336
8.1347.1 Detailed Description . . . 1337
8.1347.2 Field Documentation . . . 1338
8.1347.2.1 ecioList . . . 1338
8.1347.2.2 ecioListLen . . . 1338
8.1347.2.3 errorRateList . . . 1338
8.1347.2.4 errorRateListLen . . . 1338
8.1347.2.5 io . . . 1339
8.1347.2.6 ltersrp . . . 1339
8.1347.2.7 ltesnr . . . 1339
8.1347.2.8 ParamPresenceMask . . . 1339
8.1347.2.9 rsrqInfo . . . 1339
8.1347.2.10 rxSignalStrengthList . . . 1339
8.1347.2.11 rxSignalStrengthListLen . . . 1339
8.1347.2.12 SignalStrengthReqMask . . . 1339
8.1347.2.13 Snr . . . 1339
8.1348 unpack_nas_SLQSGetSysInfo_t Struct Reference . . . 1339
8.1348.1 Detailed Description . . . 1339
8.1348.2 Field Documentation . . . 1342
8.1348.2.1 pAddCDMASysInfo . . . 1342

8.1348.2.2 pAddGSMSysInfo . . . 1342
8.1348.2.3 pAddHDRSysInfo . . . 1342
8.1348.2.4 pAddLTESysInfo . . . 1342
8.1348.2.5 pAddWCDMASysInfo . . . 1342
8.1348.2.6 ParamPresenceMask . . . 1342
8.1348.2.7 pCampedCiotLteOpMode . . . 1342
8.1348.2.8 pCDMASrvStatusInfo . . . 1342
8.1348.2.9 pCDMASysInfo . . . 1342
8.1348.2.10 pGSMCallBarringSysInfo . . . 1342
8.1348.2.11 pGSMCipherDomainSysInfo . . . 1342
8.1348.2.12 pGSMSrvStatusInfo . . . 1342
8.1348.2.13 pGSMSysInfo . . . 1342
8.1348.2.14 pHDRSrvStatusInfo . . . 1342
8.1348.2.15 pHDRSysInfo . . . 1342
8.1348.2.16 pLTESrvStatusInfo . . . 1342
8.1348.2.17 pLTESysInfo . . . 1342
8.1348.2.18 pLTEVoiceSupportSysInfo . . . 1342
8.1348.2.19 pWCDMACallBarringSysInfo . . . 1342
8.1348.2.20 pWCDMACipherDomainSysInfo . . . 1343
8.1348.2.21 pWCDMASrvStatusInfo . . . 1343
8.1348.2.22 pWCDMASysInfo . . . 1343
8.1349 unpack_nas_SLQSGetSysSelectionPref_t Struct Reference . . . 1343
8.1349.1 Detailed Description . . . 1343
8.1349.2 Field Documentation . . . 1347
8.1349.2.1 ParamPresenceMask . . . 1347
8.1349.2.2 pBandPref . . . 1347
8.1349.2.3 pEmerMode . . . 1347
8.1349.2.4 pGWAcqOrderPref . . . 1347
8.1349.2.5 pLTEBandPref . . . 1347
8.1349.2.6 pModePref . . . 1347
8.1349.2.7 pNetSelPref . . . 1347
8.1349.2.8 pPRLPref . . . 1347
8.1349.2.9 pRoamPref . . . 1347
8.1349.2.10 pSrvDomainPref . . . 1347
8.1350 unpack_nas_SLQSGetSysSelectionPrefExt_t Struct Reference . . . 1347
8.1350.1 Detailed Description . . . 1348
8.1350.2 Field Documentation . . . 1349
8.1350.2.1 pAcqOrderPref . . . 1349
8.1350.2.2 pBandPref . . . 1349
8.1350.2.3 pCiotAcqOrderPref . . . 1349

8.1350.2.4 pCiotLteOpModePref . . . 1350
8.1350.2.5 pEmerMode . . . 1350
8.1350.2.6 pGWAcqOrderPref . . . 1350
8.1350.2.7 pLTEBandPref . . . 1350
8.1350.2.8 pLTEBandPrefExt . . . 1350
8.1350.2.9 pLteM1BandPref . . . 1350
8.1350.2.10 pLteNb1BandPref . . . 1350
8.1350.2.11 pMode Pref . . . 1350
8.1350.2.12 pNetSelPref . . . 1350
8.1350.2.13 pNr5gBandPref . . . 1350
8.1350.2.14 pPRLPref . . . 1350
8.1350.2.15 pRatDisabledMask . . . 1350
8.1350.2.16 pRoamPref . . . 1350
8.1350.2.17 pSrvDomainPref . . . 1350
8.1351 unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t Struct Reference . . . 1350
8.1351.1 Detailed Description . . . 1350
8.1351.2 Field Documentation . . . 1351
8.1351.2.1 edrxCiotLteModeTlv . . . 1351
8.1351.2.2 edrxCycleLengthTlv . . . 1351
8.1351.2.3 edrxEnableTypeTlv . . . 1351
8.1351.2.4 edrxPagingTimeWindowTlv . . . 1351
8.1351.2.5 edrxRatTypeTlv . . . 1351
8.1351.2.6 ParamPresenceMask . . . 1351
8.1352 unpack_nas_SLQSNasGet3GPP2Subscription_t Struct Reference . . . 1351
8.1352.1 Detailed Description . . . 1351
8.1352.2 Field Documentation . . . 1352
8.1352.2.1 ParamPresenceMask . . . 1352
8.1352.2.2 pCDMAChannel . . . 1352
8.1352.2.3 pDirNum . . . 1352
8.1352.2.4 pHomeSIDNID . . . 1352
8.1352.2.5 pMinBasedIMSI . . . 1352
8.1352.2.6 pNAMNameInfo . . . 1352
8.1352.2.7 pTrueIMSI . . . 1352
8.1353 unpack_nas_SLQSNasGetCellLocationInfo_t Struct Reference . . . 1352
8.1353.1 Detailed Description . . . 1353
8.1353.2 Field Documentation . . . 1353
8.1353.2.1 ParamPresenceMask . . . 1354
8.1353.2.2 pCDMAInfo . . . 1354
8.1353.2.3 pGERANInfo . . . 1354
8.1353.2.4 pLTEInfoInterfreq . . . 1354

8.1353.2.5 pLTEInfoIntrafreq . . . 1354
8.1353.2.6 pLTEInfoNeighboringGSM . . . 1354
8.1353.2.7 pLTEInfoNeighboringWCDMA . . . 1354
8.1353.2.8 pUMTSCellID . . . 1354
8.1353.2.9 pUMTSInfo . . . 1354
8.1353.2.10 pWCDMAInfoLTENeighborCell . . . 1354
8.1354 unpack_nas_SLQSNASGeteDRXParams_t Struct Reference . . . 1354
8.1354.1 Detailed Description . . . 1354
8.1354.2 Field Documentation . . . 1355
8.1354.2.1 ParamPresenceMask . . . 1355
8.1354.2.2 pCycleLen . . . 1355
8.1354.2.3 pEdrxEnable . . . 1355
8.1354.2.4 pPagingTimeWindow . . . 1355
8.1355 unpack_nas_SLQSNASGeteDRXParamsExt_t Struct Reference . . . 1355
8.1355.1 Detailed Description . . . 1355
8.1355.2 Field Documentation . . . 1356
8.1355.2.1 ParamPresenceMask . . . 1356
8.1355.2.2 pCycleLen . . . 1356
8.1355.2.3 pEdrxEnable . . . 1356
8.1355.2.4 pEdrxRAT . . . 1356
8.1355.2.5 pLteOpMode . . . 1356
8.1355.2.6 pPagingTimeWindow . . . 1356
8.1356 unpack_nas_SLQSNASGetForbiddenNetworks_t Struct Reference . . . 1356
8.1356.1 Detailed Description . . . 1357
8.1356.2 Field Documentation . . . 1357
8.1356.2.1 ParamPresenceMask . . . 1357
8.1356.2.2 pForbiddenNetworks3GPP . . . 1357
8.1357 unpack_nas_SLQSNasGetHDRColorCode_t Struct Reference . . . 1357
8.1357.1 Detailed Description . . . 1357
8.1357.2 Field Documentation . . . 1357
8.1357.2.1 ParamPresenceMask . . . 1357
8.1357.2.2 pColorCode . . . 1357
8.1358 unpack_nas_SLQSNasGetRFInfo_t Struct Reference . . . 1357
8.1358.1 Detailed Description . . . 1358
8.1358.2 Field Documentation . . . 1358
8.1358.2.1 pLTEOperationMode . . . 1358
8.1358.2.2 pRfBandInfoExtFormat . . . 1358
8.1358.2.3 pRfBandwidthInfo . . . 1358
8.1358.2.4 pRfDedicatedBandInfo . . . 1358
8.1358.2.5 rfbandInfoList . . . 1358

8.1358.2.6 Tlvresult . . . 1358
8.1359 unpack_nas_SLQSNasGetSigInfo_t Struct Reference . . . 1358
8.1359.1 Detailed Description . . . 1359
8.1359.2 Field Documentation . . . 1359
8.1359.2.1 CDMASSInfo . . . 1359
8.1359.2.2 GSMSSInfo . . . 1359
8.1359.2.3 HDRSSInfo . . . 1359
8.1359.2.4 LTESSInfo . . . 1359
8.1359.2.5 ParamPresenceMask . . . 1359
8.1359.2.6 WCDMASSInfo . . . 1359
8.1360 unpack_nas_SLQSNasGetTxRxInfo_t Struct Reference . . . 1359
8.1360.1 Detailed Description . . . 1360
8.1360.2 Field Documentation . . . 1360
8.1360.2.1 ParamPresenceMask . . . 1360
8.1360.2.2 pRXChain0Info . . . 1360
8.1360.2.3 pRXChain1Info . . . 1360
8.1360.2.4 pTXInfo . . . 1360
8.1361 unpack_nas_SLQSNasNetworkRejectCallback_Ind_t Struct Reference . . . 1360
8.1361.1 Detailed Description . . . 1360
8.1361.2 Field Documentation . . . 1363
8.1361.2.1 ParamPresenceMask . . . 1363
8.1361.2.2 pCsgId . . . 1363
8.1361.2.3 pLteOpMode . . . 1363
8.1361.2.4 pPlmnId . . . 1363
8.1361.2.5 radioIf . . . 1363
8.1361.2.6 rejectCause . . . 1363
8.1361.2.7 serviceDomain . . . 1363
8.1362 unpack_nas_SLQSNasNetworkTimeCallBack_ind_t Struct Reference . . . 1363
8.1362.1 Detailed Description . . . 1363
8.1362.2 Field Documentation . . . 1364
8.1362.2.1 ParamPresenceMask . . . 1364
8.1362.2.2 pDayltSavAdj . . . 1364
8.1362.2.3 pRadioInterface . . . 1364
8.1362.2.4 pTimeZone . . . 1364
8.1362.2.5 universalTime . . . 1364
8.1363 unpack_nas_SLQSNasSigInfoCallback_ind_t Struct Reference . . . 1364
8.1363.1 Detailed Description . . . 1365
8.1363.2 Field Documentation . . . 1365
8.1363.2.1 ParamPresenceMask . . . 1365
8.1363.2.2 pCDMASigInfo . . . 1365

8.1363.2.3 pGSMSigInfo . . . 1365
8.1363.2.4 pHDRSigInfo . . . 1365
8.1363.2.5 pLTESigInfo . . . 1365
8.1363.2.6 pRscp . . . 1365
8.1363.2.7 pTDSCDMASigInfoExt . . . 1366
8.1363.2.8 pWCDMASigInfo . . . 1366
8.1364 nnpack_nas_SLQSNASSwiGetChannelLock_t Struct Reference . . . 1366
8.1364.1 Detailed Description . . . 1366
8.1364.2 Field Documentation . . . 1366
8.1364.2.1 ParamPresenceMask . . . 1366
8.1364.2.2 pLteEARFCN . . . 1366
8.1364.2.3 pLtePCI . . . 1366
8.1364.2.4 pWcdmaUARFCN . . . 1366
8.1365 nnpack_nas_SLQSNasSwiModemStatus_t Struct Reference . . . 1366
8.1365.1 Detailed Description . . . 1367
8.1365.2 Field Documentation . . . 1367
8.1365.2.1 commonInfo . . . 1367
8.1365.2.2 ParamPresenceMask . . . 1367
8.1365.2.3 pLTEInfo . . . 1367
8.1366 nnpack_nas_SLQSNasSwiOTAMessageCallback_ind_t Struct Reference . . . 1367
8.1366.1 Detailed Description . . . 1367
8.1366.2 Field Documentation . . . 1368
8.1366.2.1 Info . . . 1368
8.1366.2.2 ParamPresenceMask . . . 1368
8.1366.2.3 Tlvresult . . . 1368
8.1367 nnpack_nas_SLQSNasTimerCallback_ind_t Struct Reference . . . 1368
8.1367.1 Detailed Description . . . 1368
8.1367.2 Field Documentation . . . 1368
8.1367.2.1 ParamPresenceMask . . . 1368
8.1367.2.2 3396_apn . . . 1368
8.1367.2.3 3396_plmn_id . . . 1368
8.1367.2.4 3396_val . . . 1368
8.1368 nnpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t Struct Reference . . . 1368
8.1368.1 Detailed Description . . . 1369
8.1368.2 Field Documentation . . . 1369
8.1368.2.1 Info . . . 1369
8.1368.2.2 ParamPresenceMask . . . 1369
8.1368.2.3 Tlvresult . . . 1369
8.1369 nnpack_nas_SLQSSwiGetHDRPersonality_t Struct Reference . . . 1369
8.1369.1 Detailed Description . . . 1369

8.1369.2 Field Documentation . . . 1370
8.1369.2.1 ParamPresenceMask . . . 1370
8.1369.2.2 pCurrentPersonality . . . 1370
8.1369.2.3 pPersonalityListLength . . . 1370
8.1369.2.4 pProtocolSubtypeElement . . . 1370
8.1370 unpack_nas_SLQSSwiGetHDRProtSubtype_t Struct Reference . . . 1370
8.1370.1 Detailed Description . . . 1370
8.1370.2 Field Documentation . . . 1371
8.1370.2.1 pAppSubType . . . 1371
8.1370.2.2 ParamPresenceMask . . . 1371
8.1370.2.3 pCurrentPrsnlty . . . 1371
8.1370.2.4 pPersonalityListLength . . . 1371
8.1370.2.5 pProtoSubTypElmnt . . . 1371
8.1371 unpack_nas_SLQSSwiGetHRPDStats_t Struct Reference . . . 1371
8.1371.1 Detailed Description . . . 1371
8.1371.2 Field Documentation . . . 1372
8.1371.2.1 ParamPresenceMask . . . 1372
8.1371.2.2 pDRCParams . . . 1372
8.1371.2.3 pPilotSetData . . . 1372
8.1371.2.4 pUATI . . . 1372
8.1372 unpack_nas_SLQSSwiGetLteCQI_t Struct Reference . . . 1372
8.1372.1 Detailed Description . . . 1372
8.1372.2 Field Documentation . . . 1373
8.1372.2.1 CQIValueCW0 . . . 1373
8.1372.2.2 CQIValueCW1 . . . 1373
8.1372.2.3 ParamPresenceMask . . . 1373
8.1372.2.4 ValidityCW0 . . . 1373
8.1372.2.5 ValidityCW1 . . . 1373
8.1373 unpack_nas_SLQSSwiGetLteSccRxInfo_t Struct Reference . . . 1373
8.1373.1 Detailed Description . . . 1373
8.1373.2 Field Documentation . . . 1373
8.1373.2.1 ParamPresenceMask . . . 1373
8.1373.2.2 pSccRxInfo . . . 1373
8.1374 unpack_nas_SLQSSwiHDRPersonalityCallback_Ind_t Struct Reference . . . 1373
8.1374.1 Detailed Description . . . 1373
8.1374.2 Field Documentation . . . 1374
8.1374.2.1 ParamPresenceMask . . . 1374
8.1374.2.2 pHDRPersInd . . . 1374
8.1375 unpack_nas_SLQSSwiNetworkDebug_t Struct Reference . . . 1374
8.1375.1 Detailed Description . . . 1374

8.1375.2 Field Documentation . . . 1375
8.1375.2.1 ParamPresenceMask . . . 1375
8.1375.2.2 pDataStatusDetail . . . 1375
8.1375.2.3 pDeviceConfigDetail . . . 1375
8.1375.2.4 pNetworkStat1x . . . 1375
8.1375.2.5 pNetworkStatEVDO . . . 1375
8.1375.2.6 pObjectVer . . . 1375
8.1376 unpack_nas_SLQSSwiRandIndicatorCallback_Ind_t Struct Reference . . . 1375
8.1376.1 Detailed Description . . . 1375
8.1376.2 Field Documentation . . . 1375
8.1376.2.1 ParamPresenceMask . . . 1375
8.1376.2.2 rankIndicatorTlv . . . 1375
8.1377 unpack_nas_SLQSSysInfoCallback_ind_t Struct Reference . . . 1375
8.1377.1 Detailed Description . . . 1376
8.1377.2 Field Documentation . . . 1378
8.1377.2.1 pAddCDMASysInfo . . . 1379
8.1377.2.2 pAddGSMSysInfo . . . 1379
8.1377.2.3 pAddHDRSysInfo . . . 1379
8.1377.2.4 pAddLTESysInfo . . . 1379
8.1377.2.5 pAddWCDMASysInfo . . . 1379
8.1377.2.6 ParamPresenceMask . . . 1379
8.1377.2.7 pCDMASrvStatusInfo . . . 1379
8.1377.2.8 pCDMASysInfo . . . 1379
8.1377.2.9 pGSMCallBarringSysInfo . . . 1379
8.1377.2.10 pGSMCipherDomainSysInfo . . . 1379
8.1377.2.11 pGSMSrvStatusInfo . . . 1379
8.1377.2.12 pGSMSysInfo . . . 1379
8.1377.2.13 pHDRSrvStatusInfo . . . 1379
8.1377.2.14 pHDRSysInfo . . . 1379
8.1377.2.15 pLteCiotOpModeTlv . . . 1379
8.1377.2.16 pLTESrvStatusInfo . . . 1379
8.1377.2.17 pLTESysInfo . . . 1379
8.1377.2.18 pLTEVoiceSupportSysInfo . . . 1379
8.1377.2.19 pNR5GCellStatus . . . 1379
8.1377.2.20 pNR5GSerStatTlv . . . 1379
8.1377.2.21 pNR5GSystemInfoTlv . . . 1379
8.1377.2.22 pSysInfoNoChange . . . 1379
8.1377.2.23 pWCDMACallBarringSysInfo . . . 1379
8.1377.2.24 pWCDMACipherDomainSysInfo . . . 1379
8.1377.2.25 pWCDMASrvStatusInfo . . . 1379

8.1377.2.26 pWCDMASysInfo . . . 1379
8.1378 unpack_omaDmConfigTlv_t Struct Reference . . . 1379
8.1378.1 Detailed Description . . . 1380
8.1378.2 Field Documentation . . . 1380
8.1378.2.1 alertmsg . . . 1380
8.1378.2.2 alertmsglength . . . 1380
8.1378.2.3 state . . . 1380
8.1378.2.4 userInputReq . . . 1380
8.1378.2.5 userInputTimeout . . . 1380
8.1379 unpack_omaDmFotaTlv_t Struct Reference . . . 1380
8.1379.1 Detailed Description . . . 1381
8.1379.2 Field Documentation . . . 1382
8.1379.2.1 description . . . 1382
8.1379.2.2 descriptionlength . . . 1382
8.1379.2.3 fwdloadsize . . . 1382
8.1379.2.4 fwloadComplete . . . 1382
8.1379.2.5 namelength . . . 1382
8.1379.2.6 package_name . . . 1382
8.1379.2.7 sessionType . . . 1382
8.1379.2.8 severity . . . 1382
8.1379.2.9 state . . . 1382
8.1379.2.10 updateCompleteStatus . . . 1382
8.1379.2.11 userInputReq . . . 1382
8.1379.2.12 userInputTimeout . . . 1382
8.1379.2.13 version . . . 1382
8.1379.2.14 versionlength . . . 1382
8.1380 unpack_omaDmNotificationsTlv_t Struct Reference . . . 1382
8.1380.1 Detailed Description . . . 1383
8.1380.2 Field Documentation . . . 1383
8.1380.2.1 notification . . . 1383
8.1380.2.2 sessionStatus . . . 1383
8.1381 unpack_pds_GetPDSDefaults_t Struct Reference . . . 1383
8.1381.1 Detailed Description . . . 1383
8.1381.2 Field Documentation . . . 1384
8.1381.2.1 pAccuracy . . . 1384
8.1381.2.2 ParamPresenceMask . . . 1384
8.1381.2.3 pInterval . . . 1384
8.1381.2.4 pOperation . . . 1384
8.1381.2.5 pTimeout . . . 1384
8.1382 unpack_pds_GetPDSState_t Struct Reference . . . 1384

8.1382.1 Detailed Description . . . 1384
8.1382.2 Field Documentation . . . 1385
8.1382.2.1 ParamPresenceMask . . . 1385
8.1382.2.2 pEnabledStatus . . . 1385
8.1382.2.3 pTrackingStatus . . . 1385
8.1383 qmnpack_pds_GetPortAutomaticTracking_t Struct Reference . . . 1385
8.1383.1 Detailed Description . . . 1385
8.1383.2 Field Documentation . . . 1385
8.1383.2.1 ParamPresenceMask . . . 1386
8.1383.2.2 pbAuto . . . 1386
8.1384 qmnpack_pds_GetServiceAutomaticTracking_t Struct Reference . . . 1386
8.1384.1 Detailed Description . . . 1386
8.1384.2 Field Documentation . . . 1386
8.1384.2.1 ParamPresenceMask . . . 1386
8.1384.2.2 pbAuto . . . 1386
8.1385 qmnpack_pds_GetXTRAAutomaticDownload_t Struct Reference . . . 1386
8.1385.1 Detailed Description . . . 1386
8.1385.2 Field Documentation . . . 1387
8.1385.2.1 ParamPresenceMask . . . 1387
8.1385.2.2 pbEnabled . . . 1387
8.1385.2.3 pInterval . . . 1387
8.1386 qmnpack_pds_GetXTRANetwork_t Struct Reference . . . 1387
8.1386.1 Detailed Description . . . 1387
8.1386.2 Field Documentation . . . 1387
8.1386.2.1 ParamPresenceMask . . . 1387
8.1386.2.2 pPreference . . . 1387
8.1387 qmnpack_pds_GetXTRAValidity_t Struct Reference . . . 1387
8.1387.1 Detailed Description . . . 1388
8.1387.2 Field Documentation . . . 1388
8.1387.2.1 ParamPresenceMask . . . 1388
8.1387.2.2 pDuration . . . 1388
8.1387.2.3 pGPSWeek . . . 1388
8.1387.2.4 pGPSWeekOffset . . . 1388
8.1388 qmnpack_pds_SetEventReport_Ind_t Struct Reference . . . 1388
8.1388.1 Detailed Description . . . 1389
8.1388.2 Field Documentation . . . 1390
8.1388.2.1 dLatitude . . . 1390
8.1388.2.2 dLongitude . . . 1390
8.1388.2.3 has_dLatitude . . . 1390
8.1388.2.4 has_dLongitude . . . 1390

8.1388.2.5 has_PositionDataNMEA . . . 1390
8.1388.2.6 has_posSrc . . . 1390
8.1388.2.7 has_SessionStatus . . . 1390
8.1388.2.8 ParamPresenceMask . . . 1390
8.1388.2.9 PositionDataNMEA . . . 1390
8.1388.2.10 posSrc . . . 1390
8.1388.2.11 SessionStatus . . . 1390
8.1389 unpack_pds_SetPdsState_Ind_t Struct Reference . . . 1390
8.1389.1 Detailed Description . . . 1390
8.1389.2 Field Documentation . . . 1391
8.1389.2.1 EnabledStatus . . . 1391
8.1389.2.2 ParamPresenceMask . . . 1391
8.1389.2.3 TlvPresent . . . 1391
8.1389.2.4 TrackingStatus . . . 1391
8.1390 unpack_pds_SLQSGetAGPSConfig_t Struct Reference . . . 1391
8.1390.1 Detailed Description . . . 1391
8.1390.2 Field Documentation . . . 1392
8.1390.2.1 ParamPresenceMask . . . 1392
8.1390.2.2 pServerAddress . . . 1392
8.1390.2.3 pServerPort . . . 1392
8.1390.2.4 pServerURL . . . 1392
8.1390.2.5 pServerURLLength . . . 1392
8.1391 unpack_pds_SLQSGetGPSStateInfo_t Struct Reference . . . 1392
8.1391.1 Detailed Description . . . 1393
8.1391.2 Field Documentation . . . 1396
8.1391.2.1 Altitude . . . 1396
8.1391.2.2 EngineState . . . 1396
8.1391.2.3 glo_almanac_sv_msk . . . 1396
8.1391.2.4 glo_ephemeris_sv_msk . . . 1396
8.1391.2.5 glo_health_sv_msk . . . 1396
8.1391.2.6 glo_visible_sv_msk . . . 1396
8.1391.2.7 gps_almanac_sv_msk . . . 1396
8.1391.2.8 gps_ephemeris_sv_msk . . . 1396
8.1391.2.9 gps_health_sv_msk . . . 1396
8.1391.2.10 gps_visible_sv_msk . . . 1396
8.1391.2.11 HorizontalUncertainty . . . 1396
8.1391.2.12 no_valid . . . 1396
8.1391.2.13 latitude . . . 1396
8.1391.2.14 longitude . . . 1396
8.1391.2.15 ParamPresenceMask . . . 1396

8.1391.2.16 sbas_almanac_sv_msk . . . 1396
8.1391.2.17 sbas_ephemeris_sv_msk . . . 1396
8.1391.2.18 sbas_health_sv_msk . . . 1396
8.1391.2.19 sbas_visible_sv_msk . . . 1396
8.1391.2.20 time_uncert_ms . . . 1396
8.1391.2.21 timeStmp_gps_week . . . 1396
8.1391.2.22 timeStmp_tow_ms . . . 1396
8.1391.2.23 validMask . . . 1396
8.1391.2.24 verticalUncertainty . . . 1396
8.1391.2.25 xtra_start_gps_minutes . . . 1397
8.1391.2.26 xtra_start_gps_week . . . 1397
8.1391.2.27 xtra_valid_duration_hours . . . 1397
8.1392 unpack_qmi_t Struct Reference . . . 1397
8.1392.1 Detailed Description . . . 1397
8.1392.2 Field Documentation . . . 1397
8.1392.2.1 msgid . . . 1397
8.1392.2.2 type . . . 1397
8.1392.2.3 xid . . . 1397
8.1393 unpack_qos_BindDataPort_t Struct Reference . . . 1397
8.1393.1 Detailed Description . . . 1397
8.1393.2 Field Documentation . . . 1397
8.1393.2.1 ParamPresenceMask . . . 1397
8.1394 unpack_qos_dataRate_t Struct Reference . . . 1398
8.1394.1 Detailed Description . . . 1398
8.1394.2 Field Documentation . . . 1398
8.1394.2.1 dataRateMax . . . 1398
8.1394.2.2 guaranteedRate . . . 1398
8.1395 unpack_qos_IPv4Addr_t Struct Reference . . . 1398
8.1395.1 Detailed Description . . . 1398
8.1395.2 Field Documentation . . . 1398
8.1395.2.1 addr . . . 1398
8.1395.2.2 subnetMask . . . 1398
8.1396 unpack_qos_IPv6Addr_t Struct Reference . . . 1398
8.1396.1 Detailed Description . . . 1399
8.1396.2 Field Documentation . . . 1399
8.1396.2.1 addr . . . 1399
8.1396.2.2 prefixLen . . . 1399
8.1397 unpack_qos_IPv6TrafCls_t Struct Reference . . . 1399
8.1397.1 Detailed Description . . . 1399
8.1397.2 Field Documentation . . . 1399

8.1397.2.1 mask . . . 1399
8.1397.2.2 val . . . 1399
8.1398 unpack_qos_pktErrRate_t Struct Reference . . . 1399
8.1398.1 Detailed Description . . . 1400
8.1398.2 Field Documentation . . . 1400
8.1398.2.1 exponent . . . 1400
8.1398.2.2 multiplier . . . 1400
8.1399 unpack_qos_Port_t Struct Reference . . . 1400
8.1399.1 Detailed Description . . . 1400
8.1399.2 Field Documentation . . . 1400
8.1399.2.1 port . . . 1400
8.1399.2.2 range . . . 1400
8.1400 unpack_qos_QosFlowInfo_t Struct Reference . . . 1400
8.1400.1 Detailed Description . . . 1401
8.1400.2 Field Documentation . . . 1401
8.1400.2.1 BearerID . . . 1401
8.1400.2.2 is_RxQFlowGranted_Available . . . 1401
8.1400.2.3 is_TxQFlowGranted_Available . . . 1401
8.1400.2.4 NumRxFilters . . . 1402
8.1400.2.5 NumTxFilters . . . 1402
8.1400.2.6 QFlowState . . . 1402
8.1400.2.7 RxQFilter . . . 1402
8.1400.2.8 RxQFlowGranted . . . 1402
8.1400.2.9 TxQFilter . . . 1402
8.1400.2.10 TxQFlowGranted . . . 1402
8.1401 unpack_qos_QosFlowInfoState_t Struct Reference . . . 1402
8.1401.1 Detailed Description . . . 1402
8.1401.2 Field Documentation . . . 1402
8.1401.2.1 id . . . 1402
8.1401.2.2 isNewFlow . . . 1402
8.1401.2.3 state . . . 1402
8.1402 unpack_qos_SLQSQosGetNetworkStatus_t Struct Reference . . . 1402
8.1402.1 Detailed Description . . . 1403
8.1402.2 Field Documentation . . . 1403
8.1402.2.1 NWQoSStatus . . . 1403
8.1402.2.2 ParamPresenceMask . . . 1403
8.1403 unpack_qos_SLQSQosSwiReadApnExtraParams_t Struct Reference . . . 1403
8.1403.1 Detailed Description . . . 1403
8.1403.2 Field Documentation . . . 1404
8.1403.2.1 ambr_dl . . . 1404

8.1403.2.2 ambr_dl_ext . . . 1404
8.1403.2.3 ambr_dl_ext2 . . . 1404
8.1403.2.4 ambr_ul . . . 1404
8.1403.2.5 ambr_ul_ext . . . 1404
8.1403.2.6 ambr_ul_ext2 . . . 1404
8.1403.2.7 apnId . . . 1404
8.1403.2.8 ParamPresenceMask . . . 1404
8.1404 unpack_qos_SLQSQosSwiReadDataStats_t Struct Reference . . . 1405
8.1404.1 Detailed Description . . . 1405
8.1404.2 Field Documentation . . . 1406
8.1404.2.1 apnId . . . 1406
8.1404.2.2 numQosFlow . . . 1406
8.1404.2.3 ParamPresenceMask . . . 1406
8.1404.2.4 qosFlow . . . 1406
8.1404.2.5 total_rx_bytes . . . 1406
8.1404.2.6 total_rx_pkt . . . 1406
8.1404.2.7 total_tx_bytes . . . 1406
8.1404.2.8 total_tx_bytes_drp . . . 1406
8.1404.2.9 total_tx_pkt . . . 1406
8.1404.2.10 total_tx_pkt_drp . . . 1406
8.1405 unpack_qos_SLQSSetQosEventCallback_ind_t Struct Reference . . . 1406
8.1405.1 Detailed Description . . . 1406
8.1405.2 Field Documentation . . . 1407
8.1405.2.1 NumFlows . . . 1407
8.1405.2.2 ParamPresenceMask . . . 1407
8.1405.2.3 QosFlowInfo . . . 1407
8.1406 unpack_qos_SLQSSetQosEventCallback_t Struct Reference . . . 1407
8.1406.1 Detailed Description . . . 1407
8.1406.2 Field Documentation . . . 1407
8.1406.2.1 ParamPresenceMask . . . 1407
8.1407 unpack_qos_SLQSSetQosNWStatusCallback_ind_t Struct Reference . . . 1407
8.1407.1 Detailed Description . . . 1407
8.1407.2 Field Documentation . . . 1408
8.1407.2.1 ParamPresenceMask . . . 1408
8.1407.2.2 status . . . 1408
8.1408 unpack_qos_SLQSSetQosPriEventCallback_ind_t Struct Reference . . . 1408
8.1408.1 Detailed Description . . . 1408
8.1408.2 Field Documentation . . . 1408
8.1408.2.1 event . . . 1408
8.1408.2.2 ParamPresenceMask . . . 1408

8.1409 unpack_qos_SLQSSetQosStatusCallback_ind_t Struct Reference . . . 1408
8.1409.1 Detailed Description . . . 1409
8.1409.2 Field Documentation . . . 1410
8.1409.2.1 event . . . 1410
8.1409.2.2 id . . . 1410
8.1409.2.3 ParamPresenceMask . . . 1410
8.1409.2.4 reason . . . 1410
8.1409.2.5 status . . . 1410
8.1410 unpack_qos_swiQosFilter_t Struct Reference . . . 1410
8.1410.1 Detailed Description . . . 1411
8.1410.2 Field Documentation . . . 1412
8.1410.2.1 EspSpi . . . 1412
8.1410.2.2 Id . . . 1412
8.1410.2.3 Index . . . 1412
8.1410.2.4 IPv4DstAddr . . . 1412
8.1410.2.5 IPv4SrcAddr . . . 1412
8.1410.2.6 IPv4Tos . . . 1412
8.1410.2.7 IPv6DstAddr . . . 1412
8.1410.2.8 IPv6Label . . . 1412
8.1410.2.9 IPv6SrcAddr . . . 1412
8.1410.2.10 IPv6TrafCls . . . 1412
8.1410.2.11 is_EspSpi_Available . . . 1412
8.1410.2.12 is_Id_Available . . . 1412
8.1410.2.13 is_IPv4DstAddr_Available . . . 1412
8.1410.2.14 is_IPv4SrcAddr_Available . . . 1412
8.1410.2.15 is_IPv4Tos_Available . . . 1412
8.1410.2.16 is_IPv6DstAddr_Available . . . 1412
8.1410.2.17 is_IPv6Label_Available . . . 1412
8.1410.2.18 is_IPv6SrcAddr_Available . . . 1412
8.1410.2.19 is_IPv6TrafCls_Available . . . 1413
8.1410.2.20 is_NxtHdrProto_Available . . . 1413
8.1410.2.21 is_Precedence_Available . . . 1413
8.1410.2.22 is_TCPDstPort_Available . . . 1413
8.1410.2.23 is_TCPSrcPort_Available . . . 1413
8.1410.2.24 is_TranDstPort_Available . . . 1413
8.1410.2.25 is_TranSrcPort_Available . . . 1413
8.1410.2.26 is_UDPDstPort_Available . . . 1413
8.1410.2.27 is_UDPSrcPort_Available . . . 1413
8.1410.2.28 NxtHdrProto . . . 1413
8.1410.2.29 Precedence . . . 1413

8.1410.2.30 TCPDstPort . . . 1413
8.1410.2.31 TCPSrcPort . . . 1413
8.1410.2.32 TranDstPort . . . 1413
8.1410.2.33 TranSrcPort . . . 1413
8.1410.2.34 UDPDstPort . . . 1413
8.1410.2.35 UDPSrcPort . . . 1413
8.1410.2.36 Version . . . 1413
8.1411 unpack_qos_swiQosFlow_t Struct Reference . . . 1413
8.1411.1 Detailed Description . . . 1414
8.1411.2 Field Documentation . . . 1416
8.1411.2.1 DataRate . . . 1416
8.1411.2.2 Index . . . 1416
8.1411.2.3 is_DataRate_Available . . . 1416
8.1411.2.4 is_Jitter_Available . . . 1416
8.1411.2.5 is_Latency_Available . . . 1416
8.1411.2.6 is_LteQci_Available . . . 1416
8.1411.2.7 is_MaxAllowedPktSz_Available . . . 1416
8.1411.2.8 is_MinPolicedPktSz_Available . . . 1416
8.1411.2.9 is_PktErrRate_Available . . . 1416
8.1411.2.10 is_ProfileId3GPP2_Available . . . 1416
8.1411.2.11 is_TokenBucket_Available . . . 1416
8.1411.2.12 is_TrafficClass_Available . . . 1416
8.1411.2.13 is_val_3GPP2Pri_Available . . . 1416
8.1411.2.14 is_val_3GPPImCn_Available . . . 1416
8.1411.2.15 is_val_3GPPResResidualBER_Available . . . 1417
8.1411.2.16 is_val_3GPPSigInd_Available . . . 1417
8.1411.2.17 is_val_3GPPTraHdlPri_Available . . . 1417
8.1411.2.18 Jitter . . . 1417
8.1411.2.19 Latency . . . 1417
8.1411.2.20 LteQci . . . 1417
8.1411.2.21 MaxAllowedPktSz . . . 1417
8.1411.2.22 MinPolicedPktSz . . . 1417
8.1411.2.23 PktErrRate . . . 1417
8.1411.2.24 ProfileId3GPP2 . . . 1417
8.1411.2.25 TokenBucket . . . 1417
8.1411.2.26 TrafficClass . . . 1417
8.1411.2.27 val_3GPP2Pri . . . 1417
8.1411.2.28 val_3GPPImCn . . . 1417
8.1411.2.29 val_3GPPResResidualBER . . . 1417
8.1411.2.30 val_3GPPSigInd . . . 1417

8.1411.2.3val_3GPPTraHdlPri . . . 1417
8.1412 qmpack_qos_tokenBucket_t Struct Reference . . . 1417
8.1412.1 Detailed Description . . . 1417
8.1412.2 Field Documentation . . . 1418
8.1412.2.1 bucketSz . . . 1418
8.1412.2.2 peakRate . . . 1418
8.1412.2.3 tokenRate . . . 1418
8.1413 qmpack_qos_Tos_t Struct Reference . . . 1418
8.1413.1 Detailed Description . . . 1418
8.1413.2 Field Documentation . . . 1418
8.1413.2.1 mask . . . 1418
8.1413.2.2 val . . . 1418
8.1414 qmpack_QosFlowStat_t Struct Reference . . . 1418
8.1414.1 Detailed Description . . . 1418
8.1414.2 Field Documentation . . . 1419
8.1414.2.1 bearerId . . . 1419
8.1414.2.2 tx_bytes . . . 1419
8.1414.2.3 tx_bytes_drp . . . 1419
8.1414.2.4 tx_pkt . . . 1419
8.1414.2.5 tx_pkt_drp . . . 1419
8.1415 qmpack_result_t Struct Reference . . . 1419
8.1415.1 Detailed Description . . . 1419
8.1415.2 Field Documentation . . . 1419
8.1415.2.1 ParamPresenceMask . . . 1419
8.1415.2.2 Tlvresult . . . 1419
8.1416 qmpack_rms_GetSMSWake_t Struct Reference . . . 1420
8.1416.1 Detailed Description . . . 1420
8.1416.2 Field Documentation . . . 1420
8.1416.2.1 enabled . . . 1420
8.1416.2.2 ParamPresenceMask . . . 1420
8.1416.2.3 wake_mask . . . 1420
8.1417 qmpack_rms_SetSMSWake_t Struct Reference . . . 1420
8.1417.1 Detailed Description . . . 1420
8.1417.2 Field Documentation . . . 1421
8.1417.2.1 ParamPresenceMask . . . 1421
8.1418 qmpack_RMTransferStatistics_ind_t Struct Reference . . . 1421
8.1418.1 Detailed Description . . . 1421
8.1418.2 Field Documentation . . . 1421
8.1418.2.1 ParamPresenceMask . . . 1421
8.1418.2.2 RxDropConutTlv . . . 1421

8.1418.2.3 RxOkByteCountTlv . . . 1422
8.1418.2.4 RxOkConutTlv . . . 1422
8.1418.2.5 TxDropConutTlv . . . 1422
8.1418.2.6 TxOkByteCountTlv . . . 1422
8.1418.2.7 TxOkConutTlv . . . 1422
8.1419 unpack_sar_SLQSGetRfSarState_t Struct Reference . . . 1422
8.1419.1 Detailed Description . . . 1422
8.1419.2 Field Documentation . . . 1422
8.1419.2.1 ParamPresenceMask . . . 1422
8.1419.2.2 pSarRFState . . . 1422
8.1420 unpack_sms_GetSMSCAddress_t Struct Reference . . . 1422
8.1420.1 Detailed Description . . . 1423
8.1420.2 Field Documentation . . . 1423
8.1420.2.1 addressSize . . . 1423
8.1420.2.2 ParamPresenceMask . . . 1423
8.1420.2.3 pSMSCAddress . . . 1423
8.1420.2.4 pSMSCType . . . 1423
8.1420.2.5 typeSize . . . 1423
8.1421 unpack_sms_SaveSMS_t Struct Reference . . . 1423
8.1421.1 Detailed Description . . . 1424
8.1421.2 Field Documentation . . . 1424
8.1421.2.1 ParamPresenceMask . . . 1424
8.1421.2.2 pMessageIndex . . . 1424
8.1422 unpack_sms_SendSMS_t Struct Reference . . . 1424
8.1422.1 Detailed Description . . . 1424
8.1422.2 Field Documentation . . . 1424
8.1422.2.1 messageFailureCode . . . 1424
8.1422.2.2 messageID . . . 1424
8.1422.2.3 ParamPresenceMask . . . 1424
8.1423 unpack_sms_SetNewSMSCallback_ind_t Struct Reference . . . 1425
8.1423.1 Detailed Description . . . 1425
8.1423.2 Field Documentation . . . 1426
8.1423.2.1 ETWSPLMNTlv . . . 1426
8.1423.2.2 ETWSTlv . . . 1426
8.1423.2.3 IMSTlv . . . 1426
8.1423.2.4 MMTlv . . . 1426
8.1423.2.5 NewMMTlv . . . 1426
8.1423.2.6 ParamPresenceMask . . . 1426
8.1423.2.7 SMSCTlv . . . 1426
8.1423.2.8 TRMessageTlv . . . 1426

8.1424 unpack_sms_SetNewSMSCallback_t Struct Reference . . . 1426
8.1424.1 Detailed Description . . . 1426
8.1424.2 Field Documentation . . . 1426
8.1424.2.1 ParamPresenceMask . . . 1426
8.1425 unpack_sms_SetSMSCAddress_t Struct Reference . . . 1426
8.1425.1 Detailed Description . . . 1426
8.1425.2 Field Documentation . . . 1427
8.1425.2.1 ParamPresenceMask . . . 1427
8.1426 unpack_sms_SLQSDeleteSMS_t Struct Reference . . . 1427
8.1426.1 Detailed Description . . . 1427
8.1426.2 Field Documentation . . . 1427
8.1426.2.1 ParamPresenceMask . . . 1427
8.1427 unpack_sms_SLQSGetIndicationRegister_t Struct Reference . . . 1427
8.1427.1 Detailed Description . . . 1427
8.1427.2 Field Documentation . . . 1428
8.1427.2.1 ParamPresenceMask . . . 1428
8.1427.2.2 pGetIndicationRegInfo . . . 1428
8.1428 unpack_sms_SLQSGetMessageWaiting_t Struct Reference . . . 1428
8.1428.1 Detailed Description . . . 1428
8.1428.2 Field Documentation . . . 1428
8.1428.2.1 ParamPresenceMask . . . 1428
8.1428.2.2 pGetMsgWaitingInfoResp . . . 1428
8.1429 unpack_sms_SLQSGetSMS_t Struct Reference . . . 1428
8.1429.1 Detailed Description . . . 1428
8.1429.2 Field Documentation . . . 1429
8.1429.2.1 message . . . 1429
8.1429.2.2 messageFormat . . . 1429
8.1429.2.3 messageSize . . . 1429
8.1429.2.4 messageTag . . . 1429
8.1429.2.5 ParamPresenceMask . . . 1429
8.1430 unpack_sms_SLQSGetSmsBroadcastConfig_t Struct Reference . . . 1429
8.1430.1 Detailed Description . . . 1430
8.1430.2 Field Documentation . . . 1430
8.1430.2.1 ParamPresenceMask . . . 1430
8.1430.2.2 pBroadcastConfig . . . 1430
8.1430.2.3 pCDMABroadcastConfig . . . 1430
8.1431 unpack_sms_SLQSGetSMSList_t Struct Reference . . . 1430
8.1431.1 Detailed Description . . . 1430
8.1431.2 Field Documentation . . . 1431
8.1431.2.1 messageList . . . 1431

8.1431.2.2 messageListSize . . . 1431
8.1431.2.3 ParamPresenceMask . . . 1431
8.1432 qmpack_sms_SLQSGetTransLayerInfo_t Struct Reference . . . 1431
8.1432.1 Detailed Description . . . 1431
8.1432.2 Field Documentation . . . 1431
8.1432.2.1 ParamPresenceMask . . . 1431
8.1432.2.2 pGetTransLayerInfo . . . 1431
8.1433 qmpack_sms_SLQSGetTransNWRegInfo_t Struct Reference . . . 1431
8.1433.1 Detailed Description . . . 1432
8.1433.2 Field Documentation . . . 1432
8.1433.2.1 ParamPresenceMask . . . 1432
8.1433.2.2 pGetTransNWRegInfo . . . 1432
8.1434 qmpack_sms_SLQSModifySMSStatus_t Struct Reference . . . 1432
8.1434.1 Detailed Description . . . 1432
8.1434.2 Field Documentation . . . 1432
8.1434.2.1 ParamPresenceMask . . . 1432
8.1435 qmpack_sms_SLQSNWRegInfoCallback_ind_t Struct Reference . . . 1432
8.1435.1 Detailed Description . . . 1433
8.1435.2 Field Documentation . . . 1433
8.1435.2.1 NWRegStat . . . 1433
8.1435.2.2 ParamPresenceMask . . . 1433
8.1436 qmpack_sms_SLQSSendAsyncSMS_t Struct Reference . . . 1433
8.1436.1 Detailed Description . . . 1433
8.1436.2 Field Documentation . . . 1433
8.1436.2.1 ParamPresenceMask . . . 1433
8.1437 qmpack_sms_SLQSSetIndicationRegister_t Struct Reference . . . 1433
8.1437.1 Detailed Description . . . 1434
8.1437.2 Field Documentation . . . 1434
8.1437.2.1 ParamPresenceMask . . . 1434
8.1438 qmpack_sms_SLQSSetSmsBroadcastActivation_t Struct Reference . . . 1434
8.1438.1 Detailed Description . . . 1434
8.1438.2 Field Documentation . . . 1434
8.1438.2.1 ParamPresenceMask . . . 1434
8.1439 qmpack_sms_SLQSSetSmsBroadcastConfig_t Struct Reference . . . 1434
8.1439.1 Detailed Description . . . 1434
8.1439.2 Field Documentation . . . 1435
8.1439.2.1 ParamPresenceMask . . . 1435
8.1440 qmpack_sms_SLQSSetSmsStorage_t Struct Reference . . . 1435
8.1440.1 Detailed Description . . . 1435
8.1440.2 Field Documentation . . . 1435

8.1440.2.1 ParamPresenceMask . . . 1435
8.1441 unpack_sms_SLQSSmsGetMaxStorageSize_t Struct Reference . . . 1435
8.1441.1 Detailed Description . . . 1435
8.1441.2 Field Documentation . . . 1435
8.1441.2.1 ParamPresenceMask . . . 1436
8.1441.2.2 pMaxStorageSizeResp . . . 1436
8.1442 unpack_sms_SLQSSmsGetMessageProtocol_t Struct Reference . . . 1436
8.1442.1 Detailed Description . . . 1436
8.1442.2 Field Documentation . . . 1436
8.1442.2.1 ParamPresenceMask . . . 1436
8.1442.2.2 pMessageProtocol . . . 1436
8.1443 unpack_sms_SLQSSmsSetRoutes_t Struct Reference . . . 1436
8.1443.1 Detailed Description . . . 1436
8.1443.2 Field Documentation . . . 1436
8.1443.2.1 ParamPresenceMask . . . 1436
8.1444 unpack_sms_SLQSSwiGetSMSStorage_t Struct Reference . . . 1437
8.1444.1 Detailed Description . . . 1437
8.1444.2 Field Documentation . . . 1437
8.1444.2.1 ParamPresenceMask . . . 1437
8.1444.2.2 pSmsStorage . . . 1437
8.1445 unpack_sms_SLQSTransLayerInfoCallback_ind_t Struct Reference . . . 1437
8.1445.1 Detailed Description . . . 1437
8.1445.2 Field Documentation . . . 1438
8.1445.2.1 ParamPresenceMask . . . 1438
8.1445.2.2 pTransLayerInfo . . . 1438
8.1445.2.3 regInd . . . 1438
8.1446 unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t Struct Reference . . . 1438
8.1446.1 Detailed Description . . . 1438
8.1446.2 Field Documentation . . . 1440
8.1446.2.1 alphaIDLen . . . 1440
8.1446.2.2 causeCode . . . 1440
8.1446.2.3 errorClass . . . 1440
8.1446.2.4 messageID . . . 1440
8.1446.2.5 msgDelFailureCause . . . 1440
8.1446.2.6 msgDelFailureType . . . 1440
8.1446.2.7 pAlphaID . . . 1440
8.1446.2.8 ParamPresenceMask . . . 1440
8.1446.2.9 RPCause . . . 1440
8.1446.2.10 sendStatus . . . 1440
8.1446.2.11 TPCause . . . 1440

8.1446.2.12 userData . . . 1440
8.1447 unpack_sms_SLQSWmsMemoryFullCallBack_ind_t Struct Reference . . . 1440
8.1447.1 Detailed Description . . . 1440
8.1447.2 Field Documentation . . . 1441
8.1447.2.1 messageMode . . . 1441
8.1447.2.2 ParamPresenceMask . . . 1441
8.1447.2.3 storageType . . . 1441
8.1448 unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t Struct Reference . . . 1441
8.1448.1 Detailed Description . . . 1441
8.1448.2 Field Documentation . . . 1441
8.1448.2.1 msgWaitInfo . . . 1441
8.1448.2.2 numInstances . . . 1441
8.1448.2.3 ParamPresenceMask . . . 1441
8.1449 unpack_swidms_SLQSSwiDmsGetHWWatchdog_t Struct Reference . . . 1441
8.1449.1 Detailed Description . . . 1442
8.1449.2 Field Documentation . . . 1442
8.1449.2.1 ParamPresenceMask . . . 1442
8.1449.2.2 pHWWatchdog . . . 1442
8.1450 unpack_swidms_SLQSSwiDmsGetMTU_t Struct Reference . . . 1442
8.1450.1 Detailed Description . . . 1442
8.1450.2 Field Documentation . . . 1443
8.1450.2.1 ParamPresenceMask . . . 1443
8.1450.2.2 pEhrpdMTUSize . . . 1443
8.1450.2.3 pHrpdMTUSize . . . 1443
8.1450.2.4 pMTUSize3gpp . . . 1443
8.1450.2.5 pUsbMTUSize . . . 1443
8.1451 unpack_swidms_SLQSSwiDmsGetSecureInfo_t Struct Reference . . . 1443
8.1451.1 Detailed Description . . . 1443
8.1451.2 Field Documentation . . . 1443
8.1451.2.1 jtagAccessAllowed . . . 1443
8.1451.2.2 memoryDumpAllowed . . . 1443
8.1451.2.3 ParamPresenceMask . . . 1444
8.1451.2.4 secureBootEnabled . . . 1444
8.1451.2.5 TlvResult . . . 1444
8.1452 unpack_swidms_SLQSSwiDmsGetUsbComp_t Struct Reference . . . 1444
8.1452.1 Detailed Description . . . 1444
8.1452.2 Field Documentation . . . 1444
8.1452.2.1 ParamPresenceMask . . . 1444
8.1452.2.2 pInterfaceCfg . . . 1444
8.1452.2.3 pSupportedBitmasks . . . 1444

8.1453 unpack_swidms_SLQSSwiDmsGetUsbNetNum_t Struct Reference . . . 1444
8.1453.1 Detailed Description . . . 1444
8.1453.2 Field Documentation . . . 1445
8.1453.2.1 ParamPresenceMask . . . 1445
8.1453.2.2 usbNetNum . . . 1445
8.1454 unpack_swidms_SLQSSwiDmsSetHWWatchdog_t Struct Reference . . . 1445
8.1454.1 Detailed Description . . . 1445
8.1454.2 Field Documentation . . . 1445
8.1454.2.1 ParamPresenceMask . . . 1445
8.1454.2.2 Tlvresult . . . 1445
8.1455 unpack_swidms_SLQSSwiDmsSetMTU_t Struct Reference . . . 1445
8.1455.1 Detailed Description . . . 1446
8.1455.2 Field Documentation . . . 1446
8.1455.2.1 ParamPresenceMask . . . 1446
8.1455.2.2 Tlvresult . . . 1446
8.1456 unpack_swidms_SLQSSwiDmsSetUsbComp_t Struct Reference . . . 1446
8.1456.1 Detailed Description . . . 1446
8.1456.2 Field Documentation . . . 1446
8.1456.2.1 ParamPresenceMask . . . 1446
8.1456.2.2 Tlvresult . . . 1446
8.1457 unpack_swiloc_SwiLocGetAutoStart_t Struct Reference . . . 1446
8.1457.1 Detailed Description . . . 1447
8.1457.2 Field Documentation . . . 1448
8.1457.2.1 fix_rate . . . 1448
8.1457.2.2 fix_rate_reported . . . 1448
8.1457.2.3 fix_type . . . 1448
8.1457.2.4 fix_type_reported . . . 1448
8.1457.2.5 function . . . 1448
8.1457.2.6 function_reported . . . 1448
8.1457.2.7 max_dist . . . 1448
8.1457.2.8 max_dist_reported . . . 1448
8.1457.2.9 max_time . . . 1448
8.1457.2.10 max_time_reported . . . 1448
8.1457.2.11 ParamPresenceMask . . . 1448
8.1458 unpack_swioma_SLQSOMADMAlertCallback_ind_t Struct Reference . . . 1448
8.1458.1 Detailed Description . . . 1448
8.1458.2 Field Documentation . . . 1449
8.1458.2.1 eventType . . . 1449
8.1458.2.2 ParamPresenceMask . . . 1449
8.1458.2.3 SessionInfoConfig . . . 1449

8.1458.2.4 SessionInfoFota . . . 1449
8.1458.2.5 SessionInfoNotification . . . 1449
8.1459 unpack_swioma_SLQSOMADMGetSessionInfo_t Struct Reference . . . 1449
8.1459.1 Detailed Description . . . 1450
8.1459.2 Field Documentation . . . 1452
8.1459.2.1 Date . . . 1452
8.1459.2.2 DateLength . . . 1452
8.1459.2.3 ParamPresenceMask . . . 1452
8.1459.2.4 PkgDescLength . . . 1452
8.1459.2.5 PkgDescription . . . 1452
8.1459.2.6 PkgName . . . 1452
8.1459.2.7 PkgNameLength . . . 1452
8.1459.2.8 RetryCount . . . 1452
8.1459.2.9 SessionState . . . 1452
8.1459.2.10 SessionType . . . 1452
8.1459.2.11 Severity . . . 1452
8.1459.2.12 Source . . . 1452
8.1459.2.13 SourceLength . . . 1452
8.1459.2.14 Status . . . 1452
8.1459.2.15 Time . . . 1452
8.1459.2.16 TimeLength . . . 1452
8.1459.2.17 UpdateCompleteStatus . . . 1452
8.1460 unpack_swioma_SLQSOMADMGetSettings_t Struct Reference . . . 1452
8.1460.1 Detailed Description . . . 1453
8.1460.2 Field Documentation . . . 1453
8.1460.2.1 Autosdm . . . 1453
8.1460.2.2 FOTAdownload . . . 1454
8.1460.2.3 FOTAUpdate . . . 1454
8.1460.2.4 FwAutoCheck . . . 1454
8.1460.2.5 OMADMEnabled . . . 1454
8.1460.2.6 ParamPresenceMask . . . 1454
8.1461 unpack_swioma_SLQSOMADMStartSession_t Struct Reference . . . 1454
8.1461.1 Detailed Description . . . 1454
8.1461.2 Field Documentation . . . 1454
8.1461.2.1 FwAvailability . . . 1454
8.1461.2.2 ParamPresenceMask . . . 1454
8.1462 unpack_uim_ChangePin_t Struct Reference . . . 1454
8.1462.1 Detailed Description . . . 1455
8.1462.2 Field Documentation . . . 1455
8.1462.2.1 ParamPresenceMask . . . 1455

8.1462.2.2 pEncryptedPIN1 . . . 1455
8.1462.2.3 pIndicationToken . . . 1455
8.1462.2.4 pRemainingRetries . . . 1455
8.1462.2.5 Tlvresult . . . 1455
8.1463 unpack_uim_GetCardStatus_t Struct Reference . . . 1455
8.1463.1 Detailed Description . . . 1455
8.1463.2 Field Documentation . . . 1456
8.1463.2.1 ParamPresenceMask . . . 1456
8.1463.2.2 pCardStatus . . . 1456
8.1463.2.3 pHotSwapStatus . . . 1456
8.1463.2.4 Tlvresult . . . 1456
8.1464 unpack_uim_GetCardStatusV2_t Struct Reference . . . 1456
8.1464.1 Detailed Description . . . 1456
8.1464.2 Field Documentation . . . 1457
8.1464.2.1 ParamPresenceMask . . . 1457
8.1464.2.2 pCardStatus . . . 1457
8.1464.2.3 pHotSwapStatus . . . 1457
8.1464.2.4 pSimBusyStatus . . . 1457
8.1464.2.5 pValidCardStatus . . . 1457
8.1464.2.6 Tlvresult . . . 1457
8.1465 unpack_uim_ReadTransparent_t Struct Reference . . . 1457
8.1465.1 Detailed Description . . . 1457
8.1465.2 Field Documentation . . . 1458
8.1465.2.1 ParamPresenceMask . . . 1458
8.1465.2.2 pCardResult . . . 1458
8.1465.2.3 pEncryptedData . . . 1458
8.1465.2.4 pIndicationToken . . . 1458
8.1465.2.5 pReadResult . . . 1458
8.1465.2.6 Tlvresult . . . 1458
8.1466 unpack_uim_SetPinProtection_t Struct Reference . . . 1458
8.1466.1 Detailed Description . . . 1458
8.1466.2 Field Documentation . . . 1459
8.1466.2.1 ParamPresenceMask . . . 1459
8.1466.2.2 pEncryptedPIN1 . . . 1459
8.1466.2.3 pIndicationToken . . . 1459
8.1466.2.4 pRemainingRetries . . . 1459
8.1466.2.5 Tlvresult . . . 1459
8.1467 unpack_uim_SetUimSlotStatusChangeCallback_ind_t Struct Reference . . . 1459
8.1467.1 Detailed Description . . . 1459
8.1467.2 Field Documentation . . . 1459

8.1467.2.1 bNumberOfPhySlots . . . 1459
8.1467.2.2 ParamPresenceMask . . . 1459
8.1467.2.3 slotsstatusChange . . . 1459
8.1468 unpack_uim_SLQSUIMAuthenticate_t Struct Reference . . . 1459
8.1468.1 Detailed Description . . . 1460
8.1468.2 Field Documentation . . . 1460
8.1468.2.1 ParamPresenceMask . . . 1460
8.1468.2.2 pAuthenticateResult . . . 1460
8.1468.2.3 pCardResult . . . 1460
8.1468.2.4 pIndicationToken . . . 1460
8.1469 unpack_uim_SLQSUIMDepersonalization_t Struct Reference . . . 1460
8.1469.1 Detailed Description . . . 1460
8.1469.2 Field Documentation . . . 1461
8.1469.2.1 ParamPresenceMask . . . 1461
8.1469.2.2 pRemainingRetries . . . 1461
8.1470 unpack_uim_SLQSUIMEventRegister_t Struct Reference . . . 1461
8.1470.1 Detailed Description . . . 1461
8.1470.2 Field Documentation . . . 1461
8.1470.2.1 eventMask . . . 1461
8.1470.2.2 ParamPresenceMask . . . 1461
8.1471 unpack_uim_SLQSUIMGetConfiguration_t Struct Reference . . . 1461
8.1471.1 Detailed Description . . . 1462
8.1471.2 Field Documentation . . . 1462
8.1471.2.1 ParamPresenceMask . . . 1462
8.1471.2.2 pAutoSelection . . . 1462
8.1471.2.3 pHaltSubscription . . . 1462
8.1471.2.4 pPersonalizationStatus . . . 1462
8.1472 unpack_uim_SLQSUIMGetFileAttributes_t Struct Reference . . . 1462
8.1472.1 Detailed Description . . . 1462
8.1472.2 Field Documentation . . . 1463
8.1472.2.1 ParamPresenceMask . . . 1463
8.1472.2.2 pCardResult . . . 1463
8.1472.2.3 pFileAttributes . . . 1463
8.1472.2.4 pIndicationToken . . . 1463
8.1473 unpack_uim_SLQSUIMGetSlotsStatus_t Struct Reference . . . 1463
8.1473.1 Detailed Description . . . 1463
8.1473.2 Field Documentation . . . 1464
8.1473.2.1 ParamPresenceMask . . . 1464
8.1473.2.2 pNumberOfPhySlot . . . 1464
8.1473.2.3 pUimSlotsStatus . . . 1464

8.1474 unpack_uim_SLQSUIMRefreshCallback_Ind_t Struct Reference . . . 1464
8.1474.1 Detailed Description . . . 1464
8.1474.2 Field Documentation . . . 1464
8.1474.2.1 ParamPresenceMask . . . 1464
8.1474.2.2 refreshEvent . . . 1464
8.1474.2.3 TlvPresent . . . 1464
8.1475 unpack_uim_SLQSUIMRefreshGetLastEvent_t Struct Reference . . . 1464
8.1475.1 Detailed Description . . . 1464
8.1475.2 Field Documentation . . . 1465
8.1475.2.1 ParamPresenceMask . . . 1465
8.1475.2.2 pRefreshEvent . . . 1465
8.1476 unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t Struct Reference . . . 1465
8.1476.1 Detailed Description . . . 1465
8.1476.2 Field Documentation . . . 1465
8.1476.2.1 ParamPresenceMask . . . 1465
8.1476.2.2 pCardStatus . . . 1465
8.1477 unpack_uim_UnblockPin_t Struct Reference . . . 1465
8.1477.1 Detailed Description . . . 1466
8.1477.2 Field Documentation . . . 1466
8.1477.2.1 ParamPresenceMask . . . 1466
8.1477.2.2 pEncryptedPIN1 . . . 1466
8.1477.2.3 pIndicationToken . . . 1466
8.1477.2.4 pRemainingRetries . . . 1466
8.1477.2.5 Tlvresult . . . 1466
8.1478 unpack_uim_UnblockPinV2_t Struct Reference . . . 1466
8.1478.1 Detailed Description . . . 1466
8.1478.2 Field Documentation . . . 1467
8.1478.2.1 ParamPresenceMask . . . 1467
8.1478.2.2 pCardResult . . . 1467
8.1478.2.3 pEncryptedPIN1 . . . 1467
8.1478.2.4 pIndicationToken . . . 1467
8.1478.2.5 pRemainingRetries . . . 1467
8.1478.2.6 Tlvresult . . . 1467
8.1479 unpack_uim_VerifyPin_t Struct Reference . . . 1467
8.1479.1 Detailed Description . . . 1467
8.1479.2 Field Documentation . . . 1468
8.1479.2.1 ParamPresenceMask . . . 1468
8.1479.2.2 pEncryptedPIN1 . . . 1468
8.1479.2.3 pIndicationToken . . . 1468
8.1479.2.4 pRemainingRetries . . . 1468

8.1479.2.5 Tlvresult . . . 1468
8.1480 unpack_voice_allCallStatusCallback_ind_t Struct Reference . . . 1468
8.1480.1 Detailed Description . . . 1468
8.1480.2 Field Documentation . . . 1470
8.1480.2.1 arrCallInfomation . . . 1470
8.1480.2.2 ParamPresenceMask . . . 1470
8.1480.2.3 pArrAlertingPattern . . . 1470
8.1480.2.4 pArrAlertingType . . . 1470
8.1480.2.5 pArrAlphaID . . . 1470
8.1480.2.6 pArrCalledPartyNum . . . 1470
8.1480.2.7 pArrCallEndReason . . . 1470
8.1480.2.8 pArrConnectPartyNum . . . 1470
8.1480.2.9 pArrDiagInfo . . . 1470
8.1480.2.10 pArrRedirPartyNum . . . 1470
8.1480.2.11 pArrRemotePartyName . . . 1470
8.1480.2.12 pArrRemotePartyNum . . . 1470
8.1480.2.13 pArrSvcOption . . . 1470
8.1481 unpack_voice_DTMFEventCallback_ind_t Struct Reference . . . 1470
8.1481.1 Detailed Description . . . 1470
8.1481.2 Field Documentation . . . 1471
8.1481.2.1 DTMFInformation . . . 1471
8.1481.2.2 ParamPresenceMask . . . 1471
8.1481.2.3 pOffLength . . . 1471
8.1481.2.4 pOnLength . . . 1471
8.1482 unpack_voice_OTASPStatusCallback_ind_t Struct Reference . . . 1471
8.1482.1 Detailed Description . . . 1471
8.1482.2 Field Documentation . . . 1472
8.1482.2.1 callID . . . 1472
8.1482.2.2 OTASPStatus . . . 1472
8.1482.2.3 ParamPresenceMask . . . 1472
8.1483 unpack_voice_SLQSOriginateUSSD_t Struct Reference . . . 1472
8.1483.1 Detailed Description . . . 1473
8.1483.2 Field Documentation . . . 1475
8.1483.2.1 pAlphaIDInfo . . . 1475
8.1483.2.2 ParamPresenceMask . . . 1475
8.1483.2.3 pCallId . . . 1475
8.1483.2.4 pCcResultType . . . 1475
8.1483.2.5 pCCSuppsType . . . 1475
8.1483.2.6 pfailureCause . . . 1475
8.1483.2.7 pUSSDInfo . . . 1475

8.1484 unpack_voice_SLQSVoiceAnswerCall_t Struct Reference . . . 1475
8.1484.1 Detailed Description . . . 1475
8.1484.2 Field Documentation . . . 1476
8.1484.2.1 ParamPresenceMask . . . 1476
8.1484.2.2 pCallId . . . 1476
8.1485 unpack_voice_SLQSVoiceBurstDTMF_t Struct Reference . . . 1476
8.1485.1 Detailed Description . . . 1476
8.1485.2 Field Documentation . . . 1476
8.1485.2.1 ParamPresenceMask . . . 1476
8.1485.2.2 pCallID . . . 1476
8.1486 unpack_voice_SLQSVoiceDialCall_t Struct Reference . . . 1476
8.1486.1 Detailed Description . . . 1477
8.1486.2 Field Documentation . . . 1477
8.1486.2.1 pAlphaIDInfo . . . 1477
8.1486.2.2 ParamPresenceMask . . . 1477
8.1486.2.3 pCallID . . . 1477
8.1486.2.4 pCCResultType . . . 1477
8.1486.2.5 pCCSUPSType . . . 1477
8.1487 unpack_voice_SLQSVoiceEndCall_t Struct Reference . . . 1477
8.1487.1 Detailed Description . . . 1478
8.1487.2 Field Documentation . . . 1478
8.1487.2.1 ParamPresenceMask . . . 1478
8.1487.2.2 pCallId . . . 1478
8.1488 unpack_voice_SLQSVoiceGetAllCallInfo_t Struct Reference . . . 1478
8.1488.1 Detailed Description . . . 1478
8.1488.2 Field Documentation . . . 1481
8.1488.2.1 ParamPresenceMask . . . 1481
8.1488.2.2 pArrAlertingPattern . . . 1481
8.1488.2.3 pArrAlertingType . . . 1481
8.1488.2.4 pArrAlphaID . . . 1481
8.1488.2.5 pArrCalledPartyNum . . . 1481
8.1488.2.6 pArrCallEndReason . . . 1481
8.1488.2.7 pArrCallInfo . . . 1481
8.1488.2.8 pArrConnectPartyNum . . . 1481
8.1488.2.9 pArrDiagInfo . . . 1481
8.1488.2.10 pArrRedirPartyNum . . . 1481
8.1488.2.11 pArrRemotePartyName . . . 1481
8.1488.2.12 pArrRemotePartyNum . . . 1481
8.1488.2.13 pArrSvcOption . . . 1481
8.1488.2.14 pArrUUSInfo . . . 1481

8.1488.2.15 pOTASPStatus . . . 1481
8.1488.2.16 pVoicePrivacy . . . 1481
8.1489 unpack_voice_SLQSVoiceGetCallBarring_t Struct Reference . . . 1482
8.1489.1 Detailed Description . . . 1482
8.1489.2 Field Documentation . . . 1483
8.1489.2.1 pAlphaIDInfo . . . 1483
8.1489.2.2 ParamPresenceMask . . . 1483
8.1489.2.3 pCallID . . . 1483
8.1489.2.4 pCCResType . . . 1483
8.1489.2.5 pCCSUPSType . . . 1483
8.1489.2.6 pFailCause . . . 1483
8.1489.2.7 pSvcClass . . . 1483
8.1490 unpack_voice_SLQSVoiceGetCallForwardingStatus_t Struct Reference . . . 1483
8.1490.1 Detailed Description . . . 1483
8.1490.2 Field Documentation . . . 1484
8.1490.2.1 pAlphaIDInfo . . . 1484
8.1490.2.2 ParamPresenceMask . . . 1484
8.1490.2.3 pCallID . . . 1484
8.1490.2.4 pCCResType . . . 1484
8.1490.2.5 pCCSUPSType . . . 1484
8.1490.2.6 pFailCause . . . 1485
8.1490.2.7 pGetCallFWExtInfo . . . 1485
8.1490.2.8 pGetCallFWInfo . . . 1485
8.1491 unpack_voice_SLQSVoiceGetCallInfo_t Struct Reference . . . 1485
8.1491.1 Detailed Description . . . 1485
8.1491.2 Field Documentation . . . 1487
8.1491.2.1 pAlertingPattern . . . 1487
8.1491.2.2 pAlertType . . . 1487
8.1491.2.3 pAlphaIDInfo . . . 1487
8.1491.2.4 ParamPresenceMask . . . 1487
8.1491.2.5 pCallInfo . . . 1487
8.1491.2.6 pConnectNumInfo . . . 1487
8.1491.2.7 pDiagInfo . . . 1487
8.1491.2.8 pOTASPStatus . . . 1487
8.1491.2.9 pRemotePartyName . . . 1487
8.1491.2.10 pRemotePartyNum . . . 1487
8.1491.2.11 pSrvOpt . . . 1488
8.1491.2.12 pUUSInfo . . . 1488
8.1491.2.13 pVoicePrivacy . . . 1488
8.1492 unpack_voice_SLQSVoiceGetCallWaiting_t Struct Reference . . . 1488

8.1492.1 Detailed Description . . . 1488
8.1492.2 Field Documentation . . . 1489
8.1492.2.1 pAlphaIDInfo . . . 1489
8.1492.2.2 ParamPresenceMask . . . 1489
8.1492.2.3 pCallID . . . 1489
8.1492.2.4 pCCResType . . . 1489
8.1492.2.5 pCCSUPSType . . . 1489
8.1492.2.6 pFailCause . . . 1489
8.1492.2.7 pSvcClass . . . 1489
8.1493 unpack_voice_SLQSVoiceGetCLIP_t Struct Reference . . . 1489
8.1493.1 Detailed Description . . . 1489
8.1493.2 Field Documentation . . . 1490
8.1493.2.1 pAlphaIDInfo . . . 1490
8.1493.2.2 ParamPresenceMask . . . 1490
8.1493.2.3 pCallID . . . 1490
8.1493.2.4 pCCResType . . . 1490
8.1493.2.5 pCCSUPSType . . . 1490
8.1493.2.6 pCLIPResp . . . 1491
8.1493.2.7 pFailCause . . . 1491
8.1494 unpack_voice_SLQSVoiceGetCLIR_t Struct Reference . . . 1491
8.1494.1 Detailed Description . . . 1491
8.1494.2 Field Documentation . . . 1492
8.1494.2.1 pAlphaIDInfo . . . 1492
8.1494.2.2 ParamPresenceMask . . . 1492
8.1494.2.3 pCallID . . . 1492
8.1494.2.4 pCCResType . . . 1492
8.1494.2.5 pCCSUPSType . . . 1492
8.1494.2.6 pCLIRResp . . . 1492
8.1494.2.7 pFailCause . . . 1492
8.1495 unpack_voice_SLQSVoiceGetCNAP_t Struct Reference . . . 1492
8.1495.1 Detailed Description . . . 1492
8.1495.2 Field Documentation . . . 1493
8.1495.2.1 pAlphaIDInfo . . . 1493
8.1495.2.2 ParamPresenceMask . . . 1493
8.1495.2.3 pCallID . . . 1493
8.1495.2.4 pCCResType . . . 1493
8.1495.2.5 pCCSUPSType . . . 1493
8.1495.2.6 pCNAPResp . . . 1493
8.1495.2.7 pFailCause . . . 1493
8.1496 unpack_voice_SLQSVoiceGetCOLP_t Struct Reference . . . 1494

8.1496.1 Detailed Description . . . 1494
8.1496.2 Field Documentation . . . 1495
8.1496.2.1 pAlphaIDInfo . . . 1495
8.1496.2.2 ParamPresenceMask . . . 1495
8.1496.2.3 pCallID . . . 1495
8.1496.2.4 pCCResType . . . 1495
8.1496.2.5 pCCSUPSType . . . 1495
8.1496.2.6 pCOLPResp . . . 1495
8.1496.2.7 pFailCause . . . 1495
8.1497 unpack_voice_SLQSVoiceGetCOLR_t Struct Reference . . . 1495
8.1497.1 Detailed Description . . . 1495
8.1497.2 Field Documentation . . . 1496
8.1497.2.1 pAlphaIDInfo . . . 1496
8.1497.2.2 ParamPresenceMask . . . 1496
8.1497.2.3 pCallID . . . 1496
8.1497.2.4 pCCResType . . . 1496
8.1497.2.5 pCCSUPSType . . . 1496
8.1497.2.6 pCOLRResp . . . 1496
8.1497.2.7 pFailCause . . . 1496
8.1498 unpack_voice_SLQSVoiceGetConfig_t Struct Reference . . . 1496
8.1498.1 Detailed Description . . . 1497
8.1498.2 Field Documentation . . . 1498
8.1498.2.1 pAirTimerCnt . . . 1498
8.1498.2.2 ParamPresenceMask . . . 1498
8.1498.2.3 pAutoAnswerStat . . . 1498
8.1498.2.4 pCurAMRConfig . . . 1498
8.1498.2.5 pCurPrefVoiceSO . . . 1498
8.1498.2.6 pCurrTTYMode . . . 1498
8.1498.2.7 pCurVoiceDomainPref . . . 1498
8.1498.2.8 pCurVoicePrivacyPref . . . 1498
8.1498.2.9 pRoamTimerCnt . . . 1498
8.1499 unpack_voice_SLQSVoiceManageCalls_t Struct Reference . . . 1498
8.1499.1 Detailed Description . . . 1499
8.1499.2 Field Documentation . . . 1499
8.1499.2.1 ParamPresenceMask . . . 1499
8.1499.2.2 pFailCause . . . 1499
8.1500 unpack_voice_SLQSVoiceSendFlash_t Struct Reference . . . 1499
8.1500.1 Detailed Description . . . 1499
8.1500.2 Field Documentation . . . 1499
8.1500.2.1 ParamPresenceMask . . . 1499

8.1500.2.2 pCallID . . . 1500
8.1501 unpack_voice_SLQSVoiceSetCallBarringPassword_t Struct Reference . . . 1500
8.1501.1 Detailed Description . . . 1500
8.1501.2 Field Documentation . . . 1501
8.1501.2.1 pAlphaIDInfo . . . 1501
8.1501.2.2 ParamPresenceMask . . . 1501
8.1501.2.3 pCallID . . . 1501
8.1501.2.4 pCCResType . . . 1501
8.1501.2.5 pCCSUPSType . . . 1501
8.1501.2.6 pFailCause . . . 1501
8.1502 unpack_voice_SLQSVoiceSetConfig_t Struct Reference . . . 1501
8.1502.1 Detailed Description . . . 1501
8.1502.2 Field Documentation . . . 1502
8.1502.2.1 pAirTimerStatus . . . 1502
8.1502.2.2 ParamPresenceMask . . . 1502
8.1502.2.3 pAutoAnsStatus . . . 1502
8.1502.2.4 pPrefVoiceSOStatus . . . 1502
8.1502.2.5 pRoamTimerStatus . . . 1502
8.1502.2.6 pTTYConfigStatus . . . 1502
8.1502.2.7 pVoiceDomainPrefStatus . . . 1502
8.1503 unpack_voice_SLQSVoiceSetSUPSService_t Struct Reference . . . 1503
8.1503.1 Detailed Description . . . 1503
8.1503.2 Field Documentation . . . 1504
8.1503.2.1 pAlphaIDInfo . . . 1504
8.1503.2.2 ParamPresenceMask . . . 1504
8.1503.2.3 pCallID . . . 1504
8.1503.2.4 pCCResultType . . . 1504
8.1503.2.5 pCCSUPSType . . . 1504
8.1503.2.6 pFailCause . . . 1504
8.1504 unpack_voice_SLQSVoiceStartContDTMF_t Struct Reference . . . 1504
8.1504.1 Detailed Description . . . 1504
8.1504.2 Field Documentation . . . 1504
8.1504.2.1 ParamPresenceMask . . . 1504
8.1504.2.2 pCallID . . . 1504
8.1505 unpack_voice_SLQSVoiceStopContDTMF_t Struct Reference . . . 1504
8.1505.1 Detailed Description . . . 1505
8.1505.2 Field Documentation . . . 1505
8.1505.2.1 callID . . . 1505
8.1505.2.2 ParamPresenceMask . . . 1505
8.1506 unpack_voice_SLQSVoiceSUPSCallback_ind_t Struct Reference . . . 1505

8.1506.1 Detailed Description . . . 1505
8.1506.2 Field Documentation . . . 1507
8.1506.2.1 pAlphaIDInfo . . . 1507
8.1506.2.2 ParamPresenceMask . . . 1507
8.1506.2.3 pCallBarPasswd . . . 1507
8.1506.2.4 pCallFwdInfo . . . 1508
8.1506.2.5 pCallFWNum . . . 1508
8.1506.2.6 pCallFWTimerVal . . . 1508
8.1506.2.7 pCallID . . . 1508
8.1506.2.8 pCLIPstatus . . . 1508
8.1506.2.9 pCLIRstatus . . . 1508
8.1506.2.10 pCNAPstatus . . . 1508
8.1506.2.11 pCOLPstatus . . . 1508
8.1506.2.12 pCOLRstatus . . . 1508
8.1506.2.13 pDataSrc . . . 1508
8.1506.2.14 pFailCause . . . 1508
8.1506.2.15 pNewPwdData . . . 1508
8.1506.2.16 pReason . . . 1508
8.1506.2.17 pSvcClass . . . 1508
8.1506.2.18 pUSSInfo . . . 1508
8.1506.2.19 pUPSInformation . . . 1508
8.1507 unpack_voice_SUPSNotificationCallback_ind_t Struct Reference . . . 1508
8.1507.1 Detailed Description . . . 1508
8.1507.2 Field Documentation . . . 1510
8.1507.2.1 callID . . . 1510
8.1507.2.2 notifType . . . 1510
8.1507.2.3 ParamPresenceMask . . . 1510
8.1507.2.4 pCUGIndex . . . 1510
8.1507.2.5 pECTNum . . . 1510
8.1508 unpack_voice_USSDNotificationCallback_ind_t Struct Reference . . . 1510
8.1508.1 Detailed Description . . . 1510
8.1508.2 Field Documentation . . . 1510
8.1508.2.1 notification_Type . . . 1510
8.1508.2.2 ParamPresenceMask . . . 1510
8.1508.2.3 USSDNotificationNetworkInfo . . . 1510
8.1509 unpack_voice_VoiceInfoRecCallback_ind_t Struct Reference . . . 1510
8.1509.1 Detailed Description . . . 1511
8.1509.2 Field Documentation . . . 1513
8.1509.2.1 callID . . . 1513
8.1509.2.2 ParamPresenceMask . . . 1513

8.1509.2.3 pCalledPartyInfo . . . 1513
8.1509.2.4 pCallerIDInfo . . . 1513
8.1509.2.5 pCallerNameInfo . . . 1513
8.1509.2.6 pCallingPartyInfo . . . 1513
8.1509.2.7 pCallWaitInd . . . 1513
8.1509.2.8 pCLIRCause . . . 1513
8.1509.2.9 pConnectNumInfo . . . 1513
8.1509.2.10 pDispInfo . . . 1513
8.1509.2.11 pExtDispInfo . . . 1513
8.1509.2.12 pExtDispRecInfo . . . 1513
8.1509.2.13 pLineCtrlInfo . . . 1513
8.1509.2.14 pNSSAudioCtrl . . . 1513
8.1509.2.15 pNSSRelease . . . 1513
8.1509.2.16 pRedirNumInfo . . . 1513
8.1509.2.17 pSignalInfo . . . 1513
8.1510 unpack_voice_voicePrivacyChangeCallback_ind_t Struct Reference . . . 1513
8.1510.1 Detailed Description . . . 1513
8.1510.2 Field Documentation . . . 1514
8.1510.2.1 callID . . . 1514
8.1510.2.2 ParamPresenceMask . . . 1514
8.1510.2.3 voicePrivacy . . . 1514
8.1511 unpack_wds_DHCPv4ClientLease_ind_t Struct Reference . . . 1514
8.1511.1 Detailed Description . . . 1514
8.1511.2 Field Documentation . . . 1515
8.1511.2.1 DHCPv4LeaseOptTlv . . . 1515
8.1511.2.2 DHCPv4LeaseStateTlv . . . 1515
8.1511.2.3 IPv4AddrTlv . . . 1515
8.1511.2.4 ParamPresenceMask . . . 1515
8.1511.2.5 ProfileIdTlv . . . 1515
8.1512 unpack_wds_GetAutoconnect_t Struct Reference . . . 1515
8.1512.1 Detailed Description . . . 1515
8.1512.2 Field Documentation . . . 1515
8.1512.2.1 ParamPresenceMask . . . 1515
8.1512.2.2 psetting . . . 1515
8.1513 unpack_wds_GetByteTotals_t Struct Reference . . . 1515
8.1513.1 Detailed Description . . . 1515
8.1513.2 Field Documentation . . . 1516
8.1513.2.1 ParamPresenceMask . . . 1516
8.1513.2.2 pRXTotalBytes . . . 1516
8.1513.2.3 pTXTotalBytes . . . 1516

8.1514 unpack_wds_GetConnectionRate_t Struct Reference . . . 1516
8.1514.1 Detailed Description . . . 1516
8.1514.2 Field Documentation . . . 1517
8.1514.2.1 currentChannelRXRate . . . 1517
8.1514.2.2 currentChannelTXRate . . . 1517
8.1514.2.3 maxChannelRXRate . . . 1517
8.1514.2.4 maxChannelTXRate . . . 1517
8.1514.2.5 ParamPresenceMask . . . 1517
8.1515 unpack_wds_GetDataBearerTechnology_t Struct Reference . . . 1517
8.1515.1 Detailed Description . . . 1517
8.1515.2 Field Documentation . . . 1518
8.1515.2.1 ParamPresenceMask . . . 1518
8.1515.2.2 pDataBearer . . . 1518
8.1516 unpack_wds_GetDefaultProfile_t Struct Reference . . . 1518
8.1516.1 Detailed Description . . . 1519
8.1516.2 Field Documentation . . . 1520
8.1516.2.1 apnname . . . 1520
8.1516.2.2 apnsize . . . 1520
8.1516.2.3 auth . . . 1520
8.1516.2.4 ipaddr . . . 1521
8.1516.2.5 ipaddrv6 . . . 1521
8.1516.2.6 name . . . 1521
8.1516.2.7 namesize . . . 1521
8.1516.2.8 ParamPresenceMask . . . 1521
8.1516.2.9 pdptype . . . 1521
8.1516.2.10 pridns . . . 1521
8.1516.2.11 pridnsv6 . . . 1521
8.1516.2.12 secdns . . . 1521
8.1516.2.13 secdnsv6 . . . 1521
8.1516.2.14 username . . . 1521
8.1516.2.15 usersize . . . 1521
8.1517 unpack_wds_GetDefaultProfileNum_t Struct Reference . . . 1521
8.1517.1 Detailed Description . . . 1521
8.1517.2 Field Documentation . . . 1521
8.1517.2.1 index . . . 1521
8.1517.2.2 ParamPresenceMask . . . 1521
8.1518 unpack_wds_GetDormancyState_t Struct Reference . . . 1521
8.1518.1 Detailed Description . . . 1522
8.1518.2 Field Documentation . . . 1522
8.1518.2.1 dormancyState . . . 1522

8.1518.2.2 ParamPresenceMask . . . 1522
8.1519 unpack_wds_GetLastMobileIPError_t Struct Reference . . . 1522
8.1519.1 Detailed Description . . . 1522
8.1519.2 Field Documentation . . . 1522
8.1519.2.1 error . . . 1523
8.1519.2.2 ParamPresenceMask . . . 1523
8.1520 unpack_wds_GetMobileIP_t Struct Reference . . . 1523
8.1520.1 Detailed Description . . . 1523
8.1520.2 Field Documentation . . . 1523
8.1520.2.1 mipMode . . . 1523
8.1520.2.2 ParamPresenceMask . . . 1523
8.1521 unpack_wds_GetMobileIPProfile_t Struct Reference . . . 1523
8.1521.1 Detailed Description . . . 1524
8.1521.2 Field Documentation . . . 1525
8.1521.2.1 AAASPI . . . 1525
8.1521.2.2 AAAState . . . 1525
8.1521.2.3 address . . . 1525
8.1521.2.4 enabled . . . 1525
8.1521.2.5 HASPI . . . 1525
8.1521.2.6 HAState . . . 1525
8.1521.2.7 NAI . . . 1525
8.1521.2.8 naiSize . . . 1525
8.1521.2.9 ParamPresenceMask . . . 1525
8.1521.2.10 primaryHA . . . 1525
8.1521.2.11 revTunneling . . . 1525
8.1521.2.12 secondaryHA . . . 1525
8.1522 unpack_wds_GetPacketStatistics_t Struct Reference . . . 1525
8.1522.1 Detailed Description . . . 1526
8.1522.2 Field Documentation . . . 1527
8.1522.2.1 ParamPresenceMask . . . 1527
8.1522.2.2 pRXDroppedCount . . . 1527
8.1522.2.3 pRXOkBytesCount . . . 1527
8.1522.2.4 pRXOKBytesLastCall . . . 1527
8.1522.2.5 pRXPacketErrors . . . 1527
8.1522.2.6 pRXPacketOverflows . . . 1527
8.1522.2.7 pRXPacketSuccesses . . . 1527
8.1522.2.8 pTXDroppedCount . . . 1527
8.1522.2.9 pTXOkBytesCount . . . 1527
8.1522.2.10 pTXOKBytesLastCall . . . 1527
8.1522.2.11 pTXPacketErrors . . . 1527

8.1522.2.12 pTXPacketOverflows . . . 1527
8.1522.2.13 pTXPacketSuccesses . . . 1527
8.1523 qmpack_wds_GetPacketStatus_t Struct Reference . . . 1527
8.1523.1 Detailed Description . . . 1528
8.1523.2 Field Documentation . . . 1529
8.1523.2.1 ParamPresenceMask . . . 1529
8.1523.2.2 rXDroppedCount . . . 1529
8.1523.2.3 rXOkBytesCount . . . 1529
8.1523.2.4 rXOKBytesLastCall . . . 1529
8.1523.2.5 rXPacketErrors . . . 1529
8.1523.2.6 rXPacketOverflows . . . 1529
8.1523.2.7 rXPacketSuccesses . . . 1529
8.1523.2.8 tXDroppedCount . . . 1529
8.1523.2.9 tXOkBytesCount . . . 1529
8.1523.2.10 tXOKBytesLastCall . . . 1529
8.1523.2.11 tXPacketErrors . . . 1529
8.1523.2.12 tXPacketOverflows . . . 1529
8.1523.2.13 tXPacketSuccesses . . . 1529
8.1524 qmpack_wds_GetSessionDuration_t Struct Reference . . . 1529
8.1524.1 Detailed Description . . . 1529
8.1524.2 Field Documentation . . . 1530
8.1524.2.1 callDuration . . . 1530
8.1524.2.2 ParamPresenceMask . . . 1530
8.1525 qmpack_wds_GetSessionState_t Struct Reference . . . 1530
8.1525.1 Detailed Description . . . 1530
8.1525.2 Field Documentation . . . 1530
8.1525.2.1 connectionStatus . . . 1530
8.1525.2.2 ParamPresenceMask . . . 1530
8.1526 qmpack_wds_RMSetTransferStatistics_t Struct Reference . . . 1530
8.1526.1 Detailed Description . . . 1531
8.1526.2 Field Documentation . . . 1531
8.1526.2.1 ParamPresenceMask . . . 1531
8.1527 qmpack_wds_SetMobileIPProfile_t Struct Reference . . . 1531
8.1527.1 Detailed Description . . . 1531
8.1527.2 Field Documentation . . . 1531
8.1527.2.1 ParamPresenceMask . . . 1531
8.1528 qmpack_wds_SLQSCreateProfile_t Struct Reference . . . 1531
8.1528.1 Detailed Description . . . 1531
8.1528.2 Field Documentation . . . 1532
8.1528.2.1 ParamPresenceMask . . . 1532

8.1528.2.2 pCreateProfileOut . . . 1532
8.1528.2.3 pProfileID . . . 1532
8.1528.2.4 Tlvresult . . . 1532
8.1529 unpack_wds_SLQSDeleteProfile_t Struct Reference . . . 1532
8.1529.1 Detailed Description . . . 1532
8.1529.2 Field Documentation . . . 1532
8.1529.2.1 extendedErrorCode . . . 1532
8.1529.2.2 ParamPresenceMask . . . 1532
8.1530 unpack_wds_SLQSDUNCallInfoCallBack_ind_t Struct Reference . . . 1533
8.1530.1 Detailed Description . . . 1533
8.1530.2 Field Documentation . . . 1534
8.1530.2.1 CRTlv . . . 1534
8.1530.2.2 CSTlv . . . 1534
8.1530.2.3 DBTTlv . . . 1534
8.1530.2.4 DSTlv . . . 1534
8.1530.2.5 LMCERTlv . . . 1534
8.1530.2.6 ParamPresenceMask . . . 1534
8.1530.2.7 RXBOTlv . . . 1534
8.1530.2.8 TXBOTlv . . . 1534
8.1531 unpack_wds_SLQSGet3GPPConfigItem_t Struct Reference . . . 1534
8.1531.1 Detailed Description . . . 1534
8.1531.2 Field Documentation . . . 1535
8.1531.2.1 _3gppRelease . . . 1535
8.1531.2.2 defaultPDNEnabled . . . 1535
8.1531.2.3 LTEAttachProfile . . . 1536
8.1531.2.4 LTEAttachProfileList . . . 1536
8.1531.2.5 LTEAttachProfileListLen . . . 1536
8.1531.2.6 ParamPresenceMask . . . 1536
8.1531.2.7 profileList . . . 1536
8.1532 unpack_wds_SLQSGetCurrDataSystemStat_t Struct Reference . . . 1536
8.1532.1 Detailed Description . . . 1536
8.1532.2 Field Documentation . . . 1536
8.1532.2.1 currNetworkInfo . . . 1536
8.1532.2.2 networkInfoLen . . . 1536
8.1532.2.3 ParamPresenceMask . . . 1537
8.1532.2.4 prefNetwork . . . 1537
8.1533 unpack_wds_SLQSGetCurrentChannelRate_t Struct Reference . . . 1537
8.1533.1 Detailed Description . . . 1537
8.1533.2 Field Documentation . . . 1538
8.1533.2.1 current_channel_rx_rate . . . 1538

8.1533.2.2 current_channel_tx_rate . . . 1538
8.1533.2.3 max_channel_rx_rate . . . 1538
8.1533.2.4 max_channel_tx_rate . . . 1538
8.1533.2.5 ParamPresenceMask . . . 1538
8.1534 unpack_wds_SLQSGetDataBearerTechnology_t Struct Reference . . . 1538
8.1534.1 Detailed Description . . . 1538
8.1534.2 Field Documentation . . . 1538
8.1534.2.1 curDataBearerTechnology . . . 1538
8.1534.2.2 dataBearerMask . . . 1539
8.1534.2.3 lastCallDataBearerTechnology . . . 1539
8.1534.2.4 ParamPresenceMask . . . 1539
8.1535 unpack_wds_SLQSGetDUNCallInfo_t Struct Reference . . . 1539
8.1535.1 Detailed Description . . . 1539
8.1535.2 Field Documentation . . . 1541
8.1535.2.1 callEndReason . . . 1541
8.1535.2.2 channelRate . . . 1541
8.1535.2.3 connectionStatus . . . 1541
8.1535.2.4 dataBearerTech . . . 1541
8.1535.2.5 dormancyStatus . . . 1541
8.1535.2.6 lastCallDataBearerTech . . . 1541
8.1535.2.7 lastCallRXOKBytesCnt . . . 1541
8.1535.2.8 lastCallTXOKBytesCnt . . . 1542
8.1535.2.9 mdmCallDurationActive . . . 1542
8.1535.2.10 ParamPresenceMask . . . 1542
8.1535.2.11 rxOKBytesCount . . . 1542
8.1535.2.12 txOKBytesCount . . . 1542
8.1536 unpack_wds_SLQSGetProfileSettings_t Struct Reference . . . 1542
8.1536.1 Detailed Description . . . 1542
8.1536.2 Field Documentation . . . 1542
8.1536.2.1 ParamPresenceMask . . . 1542
8.1536.2.2 pProfileSettings . . . 1542
8.1536.2.3 ProfileType . . . 1542
8.1536.2.4 Tlvresult . . . 1542
8.1537 unpack_wds_SLQSGetRuntimeSettings_t Struct Reference . . . 1542
8.1537.1 Detailed Description . . . 1543
8.1537.2 Field Documentation . . . 1545
8.1537.2.1 APNName . . . 1545
8.1537.2.2 Authentication . . . 1545
8.1537.2.3 DomainList . . . 1545
8.1537.2.4 GPRSGrantedQoS . . . 1545

8.1537.2.5 GWAddressV4 . . . 1545
8.1537.2.6 IMCNflag . . . 1545
8.1537.2.7 IPFamilyPreference . . . 1545
8.1537.2.8 IPv4 . . . 1545
8.1537.2.9 IPV6AddrInfo . . . 1545
8.1537.2.10 IPV6GWAddrInfo . . . 1545
8.1537.2.11 Mtu . . . 1545
8.1537.2.12 ParamPresenceMask . . . 1545
8.1537.2.13 PCSCFAddrPCO . . . 1545
8.1537.2.14 PCSCFFQDNAddrList . . . 1545
8.1537.2.15 PDPType . . . 1545
8.1537.2.16 PrimaryDNSV4 . . . 1545
8.1537.2.17 PrimaryDNSV6 . . . 1545
8.1537.2.18 ProfileID . . . 1545
8.1537.2.19 ProfileName . . . 1545
8.1537.2.20 SecondaryDNSV4 . . . 1545
8.1537.2.21 SecondaryDNSV6 . . . 1545
8.1537.2.22 ServerAddrList . . . 1545
8.1537.2.23 SubnetMaskV4 . . . 1545
8.1537.2.24 Technology . . . 1546
8.1537.2.25 UMTSGrantedQoS . . . 1546
8.1537.2.26 Username . . . 1546
8.1538 Unpack_wds_SLQSModifyProfile_t Struct Reference . . . 1546
8.1538.1 Detailed Description . . . 1546
8.1538.2 Field Documentation . . . 1546
8.1538.2.1 ParamPresenceMask . . . 1546
8.1538.2.2 pExtErrorCode . . . 1546
8.1539 Unpack_wds_SLQSSetIPFamilyPreference_t Struct Reference . . . 1546
8.1539.1 Detailed Description . . . 1546
8.1539.2 Field Documentation . . . 1547
8.1539.2.1 ParamPresenceMask . . . 1547
8.1539.2.2 Tlvresult . . . 1547
8.1540 Unpack_wds_SLQSSetPacketSrvStatusCallback_t Struct Reference . . . 1547
8.1540.1 Detailed Description . . . 1547
8.1540.2 Field Documentation . . . 1548
8.1540.2.1 bearerID . . . 1548
8.1540.2.2 conn_status . . . 1549
8.1540.2.3 ipFamily . . . 1549
8.1540.2.4 ParamPresenceMask . . . 1549
8.1540.2.5 reconfigReqd . . . 1549

8.1540.2.6 sessionEndReason . . . 1549
8.1540.2.7 techName . . . 1549
8.1540.2.8 verboseSessnEndReason . . . 1549
8.1540.2.9 verboseSessnEndReasonType . . . 1549
8.1541 unpack_wds_SLQSSetWdsEventCallback_ind_t Struct Reference . . . 1549
8.1541.1 Detailed Description . . . 1549
8.1541.2 Field Documentation . . . 1553
8.1541.2.1 currDBTechAvail . . . 1553
8.1541.2.2 currNWInfo . . . 1553
8.1541.2.3 dataSysStatAvail . . . 1553
8.1541.2.4 dBTechAvail . . . 1553
8.1541.2.5 dBtechExtAvail . . . 1554
8.1541.2.6 dBTechExtRatValue . . . 1554
8.1541.2.7 dBTechExtSoMask . . . 1554
8.1541.2.8 dBTechnology . . . 1554
8.1541.2.9 dBtechnologyExt . . . 1554
8.1541.2.10 dormancyStatAvail . . . 1554
8.1541.2.11 dormancyStatus . . . 1554
8.1541.2.12 ipstatAvail . . . 1554
8.1541.2.13 ipStatus . . . 1554
8.1541.2.14 netInfoLen . . . 1554
8.1541.2.15 ParamPresenceMask . . . 1554
8.1541.2.16 prefNetwork . . . 1554
8.1541.2.17 ratMask . . . 1554
8.1541.2.18 rx_bytes . . . 1554
8.1541.2.19 rx_pkts . . . 1554
8.1541.2.20 soMask . . . 1554
8.1541.2.21 tx_bytes . . . 1554
8.1541.2.22 tx_pkts . . . 1554
8.1541.2.23 xferStatAvail . . . 1554
8.1542 unpack_wds_SLQSSGetDHCPv4ClientConfig_t Struct Reference . . . 1554
8.1542.1 Detailed Description . . . 1554
8.1542.2 Field Documentation . . . 1555
8.1542.2.1 ParamPresenceMask . . . 1555
8.1542.2.2 pHwConfig . . . 1555
8.1542.2.3 pRequestOptionList . . . 1555
8.1543 unpack_wds_SLQSSGetLoopback_t Struct Reference . . . 1555
8.1543.1 Detailed Description . . . 1555
8.1543.2 Field Documentation . . . 1556
8.1543.2.1 ByteLoopbackMode . . . 1556

8.1543.2.2 ByteLoopbackMultiplier . . . 1556
8.1543.2.3 ParamPresenceMask . . . 1556
8.1544 unpack_wds_SLQSStartDataSession_t Struct Reference . . . 1556
8.1544.1 Detailed Description . . . 1556
8.1544.2 Field Documentation . . . 1556
8.1544.2.1 ParamPresenceMask . . . 1556
8.1544.2.2 pFailureReason . . . 1556
8.1544.2.3 psid . . . 1557
8.1544.2.4 pVerboseFailReasonType . . . 1557
8.1544.2.5 pVerboseFailureReason . . . 1557
8.1545 unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t Struct Reference . . . 1557
8.1545.1 Detailed Description . . . 1557
8.1545.2 Field Documentation . . . 1559
8.1545.2.1 apnName . . . 1559
8.1545.2.2 bearerId . . . 1559
8.1545.2.3 contextId . . . 1559
8.1545.2.4 ipv4Address . . . 1559
8.1545.2.5 ipv4GWAddress . . . 1559
8.1545.2.6 ipv6Address . . . 1559
8.1545.2.7 ipv6GWAddress . . . 1559
8.1545.2.8 ParamPresenceMask . . . 1559
8.1545.2.9 prDNSIPv4Address . . . 1559
8.1545.2.10 prDNSIPv6Address . . . 1559
8.1545.2.11 prPCSCFIPv4Address . . . 1559
8.1545.2.12 prPCSCFIPv6Address . . . 1559
8.1545.2.13 seDNSIPv4Address . . . 1559
8.1545.2.14 seDNSIPv6Address . . . 1559
8.1545.2.15 sePCSCFIPv4Address . . . 1559
8.1545.2.16 sePCSCFIPv6Address . . . 1559
8.1546 UnPackGetProfileSettingOut Struct Reference . . . 1559
8.1546.1 Detailed Description . . . 1559
8.1546.2 Field Documentation . . . 1560
8.1546.2.1 curProfile . . . 1560
8.1546.2.2 pExtErrCode . . . 1560
8.1547 unpackWdsProfileParam Union Reference . . . 1560
8.1547.1 Detailed Description . . . 1560
8.1547.2 Field Documentation . . . 1560
8.1547.2.1 SlqsProfile3GPP . . . 1560
8.1547.2.2 SlqsProfile3GPP2 . . . 1560
8.1548 urlAddr Struct Reference . . . 1560

8.1548.1 Detailed Description . . . 1560
8.1548.2 Field Documentation . . . 1561
8.1548.2.1 address . . . 1561
8.1548.2.2 TlvPresent . . . 1561
8.1549 URLAddrInfo Struct Reference . . . 1561
8.1549.1 Detailed Description . . . 1561
8.1549.2 Field Documentation . . . 1561
8.1549.2.1 urlAddr . . . 1561
8.1550 USBCompConfig Struct Reference . . . 1561
8.1550.1 Detailed Description . . . 1561
8.1550.2 Field Documentation . . . 1562
8.1550.2.1 pUSBComp . . . 1562
8.1551 USBCompParams Struct Reference . . . 1562
8.1551.1 Detailed Description . . . 1562
8.1551.2 Field Documentation . . . 1564
8.1551.2.1 pNumSupUSBComps . . . 1564
8.1551.2.2 pSupUSBComps . . . 1564
8.1551.2.3 pUSBComp . . . 1564
8.1552 usbMTUSizeTlv Struct Reference . . . 1564
8.1552.1 Detailed Description . . . 1564
8.1552.2 Field Documentation . . . 1565
8.1552.2.1 TlvPresent . . . 1565
8.1552.2.2 UsbMTUSize . . . 1565
8.1553 USSDNoWaitIndicationInfo Struct Reference . . . 1565
8.1553.1 Detailed Description . . . 1565
8.1553.2 Field Documentation . . . 1565
8.1553.2.1 pAlphaIdentifier . . . 1565
8.1553.2.2 pError . . . 1565
8.1553.2.3 pFailureCause . . . 1565
8.1553.2.4 pUSSDData . . . 1565
8.1554 USSDRespFNetwork Struct Reference . . . 1565
8.1554.1 Detailed Description . . . 1566
8.1554.2 Field Documentation . . . 1566
8.1554.2.1 pRespData . . . 1566
8.1554.2.2 pTypeCode . . . 1566
8.1555 USSInfo Struct Reference . . . 1566
8.1555.1 Detailed Description . . . 1566
8.1555.2 Field Documentation . . . 1566
8.1555.2.1 ussData . . . 1566
8.1555.2.2 ussDCS . . . 1566

8.1555.2.3 ussLen . . . 1567
8.1556 USSResp Struct Reference . . . 1567
8.1556.1 Field Documentation . . . 1567
8.1556.1.1 pAlphaIDInfo . . . 1567
8.1556.1.2 pCallId . . . 1567
8.1556.1.3 pCcResultType . . . 1567
8.1556.1.4 pCCSuppsType . . . 1567
8.1556.1.5 pfailureCause . . . 1567
8.1556.1.6 pUSSDInfo . . . 1567
8.1557 UUSInfo Struct Reference . . . 1567
8.1557.1 Detailed Description . . . 1567
8.1557.2 Field Documentation . . . 1568
8.1557.2.1 UUSData . . . 1568
8.1557.2.2 UUSDatalen . . . 1568
8.1557.2.3 UUSDcs . . . 1568
8.1557.2.4 UUSType . . . 1568
8.1558 validCardStatus Struct Reference . . . 1568
8.1558.1 Detailed Description . . . 1568
8.1558.2 Field Documentation . . . 1569
8.1558.2.1 validCard . . . 1569
8.1558.2.2 validCardLength . . . 1569
8.1559 verifyUIMPIN Struct Reference . . . 1569
8.1559.1 Detailed Description . . . 1569
8.1559.2 Field Documentation . . . 1569
8.1559.2.1 pinID . . . 1569
8.1559.2.2 pinLen . . . 1569
8.1559.2.3 pinVal . . . 1569
8.1560 voice_airTimer Struct Reference . . . 1569
8.1560.1 Detailed Description . . . 1570
8.1560.2 Field Documentation . . . 1570
8.1560.2.1 airTimerValue . . . 1570
8.1560.2.2 namID . . . 1570
8.1561 voice_allCallsAlphaIDInfo Struct Reference . . . 1570
8.1561.1 Detailed Description . . . 1570
8.1561.2 Field Documentation . . . 1570
8.1561.2.1 AlphaIDInfo . . . 1570
8.1561.2.2 callID . . . 1570
8.1562 voice_allCallsDiagInfo Struct Reference . . . 1570
8.1562.1 Detailed Description . . . 1571
8.1562.2 Field Documentation . . . 1571

8.1562.2.1 callID . . . 1571
8.1562.2.2 DiagInfo . . . 1571
8.1563 voice_allCallsUUSInfo Struct Reference . . . 1571
8.1563.1 Detailed Description . . . 1571
8.1563.2 Field Documentation . . . 1571
8.1563.2.1 callID . . . 1571
8.1563.2.2 uusInfo . . . 1571
8.1564 voice_alphaIDInfo Struct Reference . . . 1571
8.1564.1 Detailed Description . . . 1572
8.1564.2 Field Documentation . . . 1572
8.1564.2.1 alphaDcs . . . 1572
8.1564.2.2 alphaLen . . . 1572
8.1564.2.3 alphaText . . . 1572
8.1565 voice_arrAlertingPattern Struct Reference . . . 1572
8.1565.1 Detailed Description . . . 1572
8.1565.2 Field Documentation . . . 1573
8.1565.2.1 alertingPattern . . . 1573
8.1565.2.2 callID . . . 1573
8.1565.2.3 numInstances . . . 1573
8.1566 voice_arrAlertingType Struct Reference . . . 1573
8.1566.1 Detailed Description . . . 1573
8.1566.2 Field Documentation . . . 1574
8.1566.2.1 AlertingType . . . 1574
8.1566.2.2 callID . . . 1574
8.1566.2.3 numInstances . . . 1574
8.1567 voice_arrAlphaID Struct Reference . . . 1574
8.1567.1 Detailed Description . . . 1574
8.1567.2 Field Documentation . . . 1574
8.1567.2.1 allCallsAlphaIDInfoArr . . . 1574
8.1567.2.2 numInstances . . . 1574
8.1568 voice_arrCalledPartyNum Struct Reference . . . 1574
8.1568.1 Detailed Description . . . 1574
8.1568.2 Field Documentation . . . 1575
8.1568.2.1 CalledPartyNum . . . 1575
8.1568.2.2 numInstances . . . 1575
8.1569 voice_arrCallEndReason Struct Reference . . . 1575
8.1569.1 Detailed Description . . . 1575
8.1569.2 Field Documentation . . . 1575
8.1569.2.1 callEndReason . . . 1575
8.1569.2.2 callID . . . 1575

8.1569.2.3 numInstances . . . 1575
8.1570 voice_arrCallInfo Struct Reference . . . 1575
8.1570.1 Detailed Description . . . 1576
8.1570.2 Field Documentation . . . 1576
8.1570.2.1 getAllCallInfo . . . 1576
8.1570.2.2 numInstances . . . 1576
8.1571 voice_arrConnectPartyNum Struct Reference . . . 1576
8.1571.1 Detailed Description . . . 1576
8.1571.2 Field Documentation . . . 1576
8.1571.2.1 ConnectedPartyNum . . . 1576
8.1571.2.2 numInstances . . . 1576
8.1572 voice_arrDiagInfo Struct Reference . . . 1577
8.1572.1 Detailed Description . . . 1577
8.1572.2 Field Documentation . . . 1577
8.1572.2.1 DiagInfo . . . 1577
8.1572.2.2 numInstances . . . 1577
8.1573 voice_arrRedirPartyNum Struct Reference . . . 1577
8.1573.1 Detailed Description . . . 1577
8.1573.2 Field Documentation . . . 1577
8.1573.2.1 numInstances . . . 1578
8.1573.2.2 RedirPartyNum . . . 1578
8.1574 voice_arrRemotePartyName Struct Reference . . . 1578
8.1574.1 Detailed Description . . . 1578
8.1574.2 Field Documentation . . . 1578
8.1574.2.1 GetAllCallRmtPtyName . . . 1578
8.1574.2.2 numInstances . . . 1578
8.1575 voice_arrRemotePartyNum Struct Reference . . . 1578
8.1575.1 Detailed Description . . . 1578
8.1575.2 Field Documentation . . . 1579
8.1575.2.1 numInstances . . . 1579
8.1575.2.2 RmtPtyNum . . . 1579
8.1576 voice_arrSvcOption Struct Reference . . . 1579
8.1576.1 Detailed Description . . . 1579
8.1576.2 Field Documentation . . . 1579
8.1576.2.1 callID . . . 1579
8.1576.2.2 numInstances . . . 1579
8.1576.2.3 srvOption . . . 1579
8.1577 voice_arrUUSInfo Struct Reference . . . 1579
8.1577.1 Detailed Description . . . 1579
8.1577.2 Field Documentation . . . 1580

8.1577.2.1 AllCallsUUSInfo . . . 1580
8.1577.2.2 numInstances . . . 1580
8.1578 voice_burstDTMFInfo Struct Reference . . . 1580
8.1578.1 Detailed Description . . . 1580
8.1578.2 Field Documentation . . . 1580
8.1578.2.1 digitCnt . . . 1580
8.1578.2.2 pCallID . . . 1580
8.1578.2.3 pDigitBuff . . . 1581
8.1579 voice_calledPartyInfo Struct Reference . . . 1581
8.1579.1 Detailed Description . . . 1581
8.1579.2 Field Documentation . . . 1582
8.1579.2.1 number . . . 1582
8.1579.2.2 numLen . . . 1582
8.1579.2.3 numPlan . . . 1582
8.1579.2.4 numType . . . 1582
8.1579.2.5 PI . . . 1582
8.1579.2.6 SI . . . 1582
8.1580 voice_calledPartySubAddr Struct Reference . . . 1582
8.1580.1 Detailed Description . . . 1582
8.1580.2 Field Documentation . . . 1583
8.1580.2.1 extBit . . . 1583
8.1580.2.2 oddEvenInd . . . 1583
8.1580.2.3 subAddr . . . 1583
8.1580.2.4 subAddrLen . . . 1583
8.1580.2.5 subAddrType . . . 1583
8.1581 voice_callerIDInfo Struct Reference . . . 1583
8.1581.1 Detailed Description . . . 1583
8.1581.2 Field Documentation . . . 1584
8.1581.2.1 callerID . . . 1584
8.1581.2.2 callerIDLen . . . 1584
8.1581.2.3 PI . . . 1584
8.1582 voice_callFwdTypeAndPlan Struct Reference . . . 1584
8.1582.1 Detailed Description . . . 1584
8.1582.2 Field Documentation . . . 1585
8.1582.2.1 numberPlan . . . 1585
8.1582.2.2 numberType . . . 1585
8.1583 voice_callFWExtInfo Struct Reference . . . 1585
8.1583.1 Detailed Description . . . 1585
8.1583.2 Field Documentation . . . 1586
8.1583.2.1 noReplyTimer . . . 1586

8.1583.2.2 number . . . 1586
8.1583.2.3 numLen . . . 1586
8.1583.2.4 numPlan . . . 1586
8.1583.2.5 numType . . . 1586
8.1583.2.6 PI . . . 1586
8.1583.2.7 SI . . . 1586
8.1583.2.8 SvcClass . . . 1586
8.1583.2.9 SvcStatus . . . 1586
8.1584 voice_callFWInfo Struct Reference . . . 1587
8.1584.1 Detailed Description . . . 1587
8.1584.2 Field Documentation . . . 1587
8.1584.2.1 noReplyTimer . . . 1587
8.1584.2.2 number . . . 1587
8.1584.2.3 numLen . . . 1587
8.1584.2.4 SvcClass . . . 1587
8.1584.2.5 SvcStatus . . . 1587
8.1585 voice_callInfo Struct Reference . . . 1587
8.1585.1 Detailed Description . . . 1588
8.1585.2 Field Documentation . . . 1589
8.1585.2.1 callID . . . 1589
8.1585.2.2 callState . . . 1589
8.1585.2.3 callType . . . 1589
8.1585.2.4 direction . . . 1589
8.1585.2.5 mode . . . 1589
8.1586 voice_callingPartyInfo Struct Reference . . . 1589
8.1586.1 Detailed Description . . . 1589
8.1586.2 Field Documentation . . . 1590
8.1586.2.1 number . . . 1590
8.1586.2.2 numLen . . . 1590
8.1586.2.3 numPlan . . . 1590
8.1586.2.4 numType . . . 1591
8.1586.2.5 PI . . . 1591
8.1586.2.6 SI . . . 1591
8.1587 voice_ccSUPSType Struct Reference . . . 1591
8.1587.1 Detailed Description . . . 1591
8.1587.2 Field Documentation . . . 1591
8.1587.2.1 reason . . . 1591
8.1587.2.2 svcType . . . 1591
8.1588 voice_CLIPResp Struct Reference . . . 1591
8.1588.1 Detailed Description . . . 1592

8.1588.2 Field Documentation . . . 1592
8.1588.2.1 ActiveStatus . . . 1592
8.1588.2.2 ProvisionStatus . . . 1592
8.1589 voice_CLIRResp Struct Reference . . . 1592
8.1589.1 Detailed Description . . . 1592
8.1589.2 Field Documentation . . . 1593
8.1589.2.1 ActiveStatus . . . 1593
8.1589.2.2 ProvisionStatus . . . 1593
8.1590 voice_CNAPResp Struct Reference . . . 1593
8.1590.1 Detailed Description . . . 1593
8.1590.2 Field Documentation . . . 1593
8.1590.2.1 ActiveStatus . . . 1593
8.1590.2.2 ProvisionStatus . . . 1593
8.1591 voice_COLPResp Struct Reference . . . 1594
8.1591.1 Detailed Description . . . 1594
8.1591.2 Field Documentation . . . 1594
8.1591.2.1 ActiveStatus . . . 1594
8.1591.2.2 ProvisionStatus . . . 1594
8.1592 voice_COLRResp Struct Reference . . . 1594
8.1592.1 Detailed Description . . . 1594
8.1592.2 Field Documentation . . . 1595
8.1592.2.1 ActiveStatus . . . 1595
8.1592.2.2 ProvisionStatus . . . 1595
8.1593 voice_connectNumInfo Struct Reference . . . 1595
8.1593.1 Detailed Description . . . 1595
8.1593.2 Field Documentation . . . 1596
8.1593.2.1 callerID . . . 1596
8.1593.2.2 callerIDLen . . . 1596
8.1593.2.3 numPlan . . . 1596
8.1593.2.4 numPresInd . . . 1597
8.1593.2.5 numType . . . 1597
8.1593.2.6 screeningInd . . . 1597
8.1594 voice_CUGInfo Struct Reference . . . 1597
8.1594.1 Detailed Description . . . 1597
8.1594.2 Field Documentation . . . 1597
8.1594.2.1 CUGIndex . . . 1597
8.1594.2.2 SuppOA . . . 1597
8.1594.2.3 SuppPrefCUG . . . 1597
8.1595 voice_curAMRConfig Struct Reference . . . 1597
8.1595.1 Detailed Description . . . 1597

8.1595.2 Field Documentation . . . 1598
8.1595.2.1 gsmAmrStat . . . 1598
8.1595.2.2 wcdmaAmrStat . . . 1598
8.1596 voice_diagInfo Struct Reference . . . 1598
8.1596.1 Detailed Description . . . 1598
8.1596.2 Field Documentation . . . 1598
8.1596.2.1 diagInfoLen . . . 1598
8.1596.2.2 diagnosticInfo . . . 1598
8.1597 voice_DTMFInfo Struct Reference . . . 1599
8.1597.1 Detailed Description . . . 1599
8.1597.2 Field Documentation . . . 1599
8.1597.2.1 callID . . . 1599
8.1597.2.2 digitBuff . . . 1599
8.1597.2.3 digitCnt . . . 1599
8.1597.2.4 DTMFEvent . . . 1599
8.1598 voice_DTMFLengths Struct Reference . . . 1599
8.1598.1 Detailed Description . . . 1600
8.1598.2 Field Documentation . . . 1600
8.1598.2.1 DTMFInterdigitInterval . . . 1600
8.1598.2.2 DTMFPulseWidth . . . 1600
8.1599 voice_ECTNum Struct Reference . . . 1600
8.1599.1 Detailed Description . . . 1600
8.1599.2 Field Documentation . . . 1601
8.1599.2.1 ECTCallState . . . 1601
8.1599.2.2 number . . . 1601
8.1599.2.3 presentationInd . . . 1601
8.1600 voice_extDispRecInfo Struct Reference . . . 1601
8.1600.1 Detailed Description . . . 1601
8.1600.2 Field Documentation . . . 1601
8.1600.2.1 dispType . . . 1601
8.1600.2.2 extDispInfo . . . 1601
8.1600.2.3 extDispInfoLen . . . 1602
8.1601 voice_getAllCallInformation Struct Reference . . . 1602
8.1601.1 Detailed Description . . . 1602
8.1601.2 Field Documentation . . . 1602
8.1601.2.1 ALS . . . 1602
8.1601.2.2 Callinfo . . . 1602
8.1601.2.3 isEmpty . . . 1602
8.1602 voice_getAllCallRmtPtyName Struct Reference . . . 1602
8.1602.1 Detailed Description . . . 1602

8.1602.2 Field Documentation . . . 1603
8.1602.2.1 callID . . . 1603
8.1602.2.2 RemotePartyName . . . 1603
8.1603 voice_getAllCallRmtPtyNum Struct Reference . . . 1603
8.1603.1 Detailed Description . . . 1603
8.1603.2 Field Documentation . . . 1603
8.1603.2.1 callID . . . 1603
8.1603.2.2 RemotePartyNum . . . 1603
8.1604 voice_getCallFWExtInfo Struct Reference . . . 1603
8.1604.1 Detailed Description . . . 1603
8.1604.2 Field Documentation . . . 1604
8.1604.2.1 CallFWExtInfo . . . 1604
8.1604.2.2 numInstances . . . 1604
8.1605 voice_getCallFWInfo Struct Reference . . . 1604
8.1605.1 Detailed Description . . . 1604
8.1605.2 Field Documentation . . . 1604
8.1605.2.1 CallFWInfo . . . 1604
8.1605.2.2 numInstances . . . 1604
8.1606 voice_lineCtrlInfo Struct Reference . . . 1604
8.1606.1 Detailed Description . . . 1605
8.1606.2 Field Documentation . . . 1605
8.1606.2.1 polarityIncluded . . . 1605
8.1606.2.2 pwrDenialTime . . . 1605
8.1606.2.3 revPolarity . . . 1605
8.1606.2.4 toggleMode . . . 1605
8.1607 voice_newPwdData Struct Reference . . . 1605
8.1607.1 Detailed Description . . . 1605
8.1607.2 Field Documentation . . . 1606
8.1607.2.1 newPwd . . . 1606
8.1607.2.2 newPwdAgain . . . 1606
8.1608 voice_NSSAudioCtrl Struct Reference . . . 1606
8.1608.1 Detailed Description . . . 1606
8.1608.2 Field Documentation . . . 1606
8.1608.2.1 downLink . . . 1606
8.1608.2.2 upLink . . . 1606
8.1609 voice_peerNumberInfo Struct Reference . . . 1606
8.1609.1 Detailed Description . . . 1606
8.1609.2 Field Documentation . . . 1607
8.1609.2.1 callID . . . 1608
8.1609.2.2 number . . . 1608

8.1609.2.3 numLen . . . 1608
8.1609.2.4 numPI . . . 1608
8.1609.2.5 numPlan . . . 1608
8.1609.2.6 numSI . . . 1608
8.1609.2.7 numType . . . 1608
8.1610 voice_pref VoiceSO Struct Reference . . . 1608
8.1610.1 Detailed Description . . . 1608
8.1610.2 Field Documentation . . . 1610
8.1610.2.1 evrcCapability . . . 1610
8.1610.2.2 homeOrigVoiceSO . . . 1610
8.1610.2.3 homePageVoiceSO . . . 1610
8.1610.2.4 namID . . . 1610
8.1610.2.5 roamOrigVoiceSO . . . 1610
8.1611 voice_redirNumInfo Struct Reference . . . 1610
8.1611.1 Detailed Description . . . 1610
8.1611.2 Field Documentation . . . 1611
8.1611.2.1 number . . . 1611
8.1611.2.2 numLen . . . 1611
8.1611.2.3 numPlan . . . 1611
8.1611.2.4 numType . . . 1611
8.1611.2.5 PI . . . 1611
8.1611.2.6 reason . . . 1611
8.1611.2.7 SI . . . 1611
8.1612 voice_remotePartyName Struct Reference . . . 1612
8.1612.1 Detailed Description . . . 1612
8.1612.2 Field Documentation . . . 1612
8.1612.2.1 callerName . . . 1612
8.1612.2.2 codingScheme . . . 1612
8.1612.2.3 nameLen . . . 1612
8.1612.2.4 namePI . . . 1612
8.1613 voice_remotePartyNum Struct Reference . . . 1612
8.1613.1 Detailed Description . . . 1613
8.1613.2 Field Documentation . . . 1613
8.1613.2.1 numLen . . . 1613
8.1613.2.2 presentationInd . . . 1613
8.1613.2.3 remPartyNumber . . . 1613
8.1614 voice_roamTimer Struct Reference . . . 1613
8.1614.1 Detailed Description . . . 1613
8.1614.2 Field Documentation . . . 1614
8.1614.2.1 namID . . . 1614

8.1614.2.2 roamTimerValue . . . 1614
8.1615 voice_signalInfo Struct Reference . . . 1614
8.1615.1 Detailed Description . . . 1614
8.1615.2 Field Documentation . . . 1614
8.1615.2.1 alertPitch . . . 1614
8.1615.2.2 signal . . . 1614
8.1615.2.3 signalType . . . 1614
8.1616 voice_SUPSInfo Struct Reference . . . 1615
8.1616.1 Detailed Description . . . 1615
8.1616.2 Field Documentation . . . 1615
8.1616.2.1 isModByCC . . . 1615
8.1616.2.2 svcType . . . 1615
8.1617 voice_USSDNotificationNetworkInfo Struct Reference . . . 1615
8.1617.1 Detailed Description . . . 1615
8.1617.2 Field Documentation . . . 1616
8.1617.2.1 networkInfo . . . 1616
8.1617.2.2 tlvPresent . . . 1616
8.1618 voice_USSInfo Struct Reference . . . 1616
8.1618.1 Detailed Description . . . 1616
8.1618.2 Field Documentation . . . 1616
8.1618.2.1 ussData . . . 1616
8.1618.2.2 ussDCS . . . 1616
8.1618.2.3 ussLen . . . 1616
8.1619 voice_UUSInfo Struct Reference . . . 1616
8.1619.1 Detailed Description . . . 1617
8.1619.2 Field Documentation . . . 1617
8.1619.2.1 UUSData . . . 1617
8.1619.2.2 UUSDatalen . . . 1617
8.1619.2.3 UUSDcs . . . 1617
8.1619.2.4 UUSType . . . 1617
8.1620 voiceALSSelectLineInfo Struct Reference . . . 1618
8.1620.1 Detailed Description . . . 1618
8.1620.2 Field Documentation . . . 1618
8.1620.2.1 lineValue . . . 1618
8.1621 voiceALSSetLineSwitchInfo Struct Reference . . . 1618
8.1621.1 Detailed Description . . . 1618
8.1621.2 Field Documentation . . . 1618
8.1621.2.1 switchOption . . . 1618
8.1622 voiceAnswerCall Struct Reference . . . 1618
8.1622.1 Detailed Description . . . 1619

8.1622.2 Field Documentation . . . 1619
8.1622.2.1 pCallId . . . 1619
8.1623 VoiceBindSubscriptionInfo Struct Reference . . . 1619
8.1623.1 Detailed Description . . . 1619
8.1623.2 Field Documentation . . . 1619
8.1623.2.1 subsType . . . 1619
8.1624 VoiceBurstDTMFInfo Struct Reference . . . 1619
8.1624.1 Detailed Description . . . 1619
8.1624.2 Field Documentation . . . 1620
8.1624.2.1 BurstDTMFInfo . . . 1620
8.1624.2.2 pBurstDTMFLengths . . . 1620
8.1625 VoiceCallInfoReq Struct Reference . . . 1620
8.1625.1 Detailed Description . . . 1620
8.1625.2 Field Documentation . . . 1620
8.1625.2.1 callID . . . 1620
8.1626 VoiceCallInfoResp Struct Reference . . . 1620
8.1626.1 Detailed Description . . . 1620
8.1626.2 Field Documentation . . . 1622
8.1626.2.1 pAlertingPattern . . . 1622
8.1626.2.2 pAlertType . . . 1622
8.1626.2.3 pAlphaIDInfo . . . 1622
8.1626.2.4 pCallInfo . . . 1622
8.1626.2.5 pConnectNumInfo . . . 1622
8.1626.2.6 pDiagInfo . . . 1622
8.1626.2.7 pOTASPStatus . . . 1622
8.1626.2.8 pRemotePartyName . . . 1622
8.1626.2.9 pRemotePartyNum . . . 1623
8.1626.2.10 pSrvOpt . . . 1623
8.1626.2.11 pUUSInfo . . . 1623
8.1626.2.12 pVoicePrivacy . . . 1623
8.1627 VoiceCallRequestParams Struct Reference . . . 1623
8.1627.1 Detailed Description . . . 1623
8.1627.2 Field Documentation . . . 1624
8.1627.2.1 callNumber . . . 1624
8.1627.2.2 pCallPartySubAdd . . . 1624
8.1627.2.3 pCallType . . . 1624
8.1627.2.4 pCLIRType . . . 1624
8.1627.2.5 pCUGInfo . . . 1624
8.1627.2.6 pEmergencyCategory . . . 1624
8.1627.2.7 pSvcType . . . 1624

8.1627.2.8 pUUSInFo . . . 1624
8.1628 VoiceCallResponseParams Struct Reference . . . 1624
8.1628.1 Detailed Description . . . 1625
8.1628.2 Field Documentation . . . 1625
8.1628.2.1 pAlphaIDInfo . . . 1625
8.1628.2.2 pCallID . . . 1625
8.1628.2.3 pCCResultType . . . 1625
8.1628.2.4 pCCSUPSType . . . 1625
8.1629 VoiceContDTMFinfo Struct Reference . . . 1625
8.1629.1 Detailed Description . . . 1625
8.1629.2 Field Documentation . . . 1626
8.1629.2.1 DTMFdigit . . . 1626
8.1629.2.2 pCallID . . . 1626
8.1630 VoiceDTMFEventInfo Struct Reference . . . 1626
8.1630.1 Detailed Description . . . 1626
8.1630.2 Field Documentation . . . 1627
8.1630.2.1 DTMFInformation . . . 1627
8.1630.2.2 pOffLength . . . 1627
8.1630.2.3 pOnLength . . . 1627
8.1630.2.4 results . . . 1627
8.1631 VoiceFlashInfo Struct Reference . . . 1627
8.1631.1 Detailed Description . . . 1627
8.1631.2 Field Documentation . . . 1627
8.1631.2.1 pCallID . . . 1628
8.1631.2.2 pFlashPayLd . . . 1628
8.1631.2.3 pFlashType . . . 1628
8.1632 VoiceGetAllCallInfo Struct Reference . . . 1628
8.1632.1 Detailed Description . . . 1628
8.1632.2 Field Documentation . . . 1630
8.1632.2.1 pArrAlertingPattern . . . 1630
8.1632.2.2 pArrAlertingType . . . 1630
8.1632.2.3 pArrAlphaID . . . 1630
8.1632.2.4 pArrCalledPartyNum . . . 1630
8.1632.2.5 pArrCallEndReason . . . 1630
8.1632.2.6 pArrCallInfo . . . 1630
8.1632.2.7 pArrConnectPartyNum . . . 1630
8.1632.2.8 pArrDiagInfo . . . 1630
8.1632.2.9 pArrRedirPartyNum . . . 1630
8.1632.2.10 pArrRemotePartyName . . . 1630
8.1632.2.11 pArrRemotePartyNum . . . 1630

8.1632.2.12 pArrSvcOption . . . 1630
8.1632.2.13 pArrUUSInfo . . . 1630
8.1632.2.14 pOTASPStatus . . . 1630
8.1632.2.15 pVoicePrivacy . . . 1630
8.1633 VoiceGetCallBarringReq Struct Reference . . . 1630
8.1633.1 Detailed Description . . . 1630
8.1633.2 Field Documentation . . . 1631
8.1633.2.1 pSvcClass . . . 1631
8.1633.2.2 reason . . . 1631
8.1634 VoiceGetCallBarringResp Struct Reference . . . 1631
8.1634.1 Detailed Description . . . 1631
8.1634.2 Field Documentation . . . 1632
8.1634.2.1 pAlphaIDInfo . . . 1632
8.1634.2.2 pCallID . . . 1632
8.1634.2.3 pCCResType . . . 1632
8.1634.2.4 pCCSUPSType . . . 1632
8.1634.2.5 pFailCause . . . 1632
8.1634.2.6 pSvcClass . . . 1632
8.1635 VoiceGetCallFWReq Struct Reference . . . 1632
8.1635.1 Detailed Description . . . 1633
8.1635.2 Field Documentation . . . 1633
8.1635.2.1 pSvcClass . . . 1633
8.1635.2.2 Reason . . . 1633
8.1636 VoiceGetCallFWResp Struct Reference . . . 1633
8.1636.1 Detailed Description . . . 1633
8.1636.2 Field Documentation . . . 1634
8.1636.2.1 pAlphaIDInfo . . . 1634
8.1636.2.2 pCallID . . . 1634
8.1636.2.3 pCCResType . . . 1634
8.1636.2.4 pCCSUPSType . . . 1634
8.1636.2.5 pFailCause . . . 1634
8.1636.2.6 pGetCallFWExtInfo . . . 1634
8.1636.2.7 pGetCallFWInfo . . . 1634
8.1637 VoiceGetCallWaitInfo Struct Reference . . . 1634
8.1637.1 Detailed Description . . . 1635
8.1637.2 Field Documentation . . . 1635
8.1637.2.1 pAlphaIDInfo . . . 1636
8.1637.2.2 pCallID . . . 1636
8.1637.2.3 pCCResType . . . 1636
8.1637.2.4 pCCSUPSType . . . 1636

8.1637.2.5 pFailCause . . . 1636
8.1637.2.6 pSvcClass . . . 1636
8.1638 VoiceGetCLIPResp Struct Reference . . . 1636
8.1638.1 Detailed Description . . . 1636
8.1638.2 Field Documentation . . . 1637
8.1638.2.1 pAlphaIDInfo . . . 1637
8.1638.2.2 pCallID . . . 1637
8.1638.2.3 pCCResType . . . 1637
8.1638.2.4 pCCSUPSType . . . 1637
8.1638.2.5 pCLIPResp . . . 1637
8.1638.2.6 pFailCause . . . 1637
8.1639 VoiceGetCLIRResp Struct Reference . . . 1637
8.1639.1 Detailed Description . . . 1637
8.1639.2 Field Documentation . . . 1638
8.1639.2.1 pAlphaIDInfo . . . 1638
8.1639.2.2 pCallID . . . 1638
8.1639.2.3 pCCResType . . . 1638
8.1639.2.4 pCCSUPSType . . . 1638
8.1639.2.5 pCLIRResp . . . 1638
8.1639.2.6 pFailCause . . . 1638
8.1640 VoiceGetCNAPResp Struct Reference . . . 1638
8.1640.1 Detailed Description . . . 1638
8.1640.2 Field Documentation . . . 1639
8.1640.2.1 pAlphaIDInfo . . . 1639
8.1640.2.2 pCallID . . . 1639
8.1640.2.3 pCCResType . . . 1639
8.1640.2.4 pCCSUPSType . . . 1639
8.1640.2.5 pCNAPResp . . . 1639
8.1640.2.6 pFailCause . . . 1639
8.1641 VoiceGetCOLPResp Struct Reference . . . 1639
8.1641.1 Detailed Description . . . 1640
8.1641.2 Field Documentation . . . 1640
8.1641.2.1 pAlphaIDInfo . . . 1640
8.1641.2.2 pCallID . . . 1641
8.1641.2.3 pCCResType . . . 1641
8.1641.2.4 pCCSUPSType . . . 1641
8.1641.2.5 pCOLPResp . . . 1641
8.1641.2.6 pFailCause . . . 1641
8.1642 VoiceGetCOLRResp Struct Reference . . . 1641
8.1642.1 Detailed Description . . . 1641

8.1642.2 Field Documentation . . . 1642
8.1642.2.1 pAlphaIDInfo . . . 1642
8.1642.2.2 pCallID . . . 1642
8.1642.2.3 pCCResType . . . 1642
8.1642.2.4 pCCSUPSType . . . 1642
8.1642.2.5 pCOLRResp . . . 1642
8.1642.2.6 pFailCause . . . 1642
8.1643 VoiceGetConfigReq Struct Reference . . . 1642
8.1643.1 Detailed Description . . . 1642
8.1643.2 Field Documentation . . . 1643
8.1643.2.1 pAirTimer . . . 1643
8.1643.2.2 pAMRStatus . . . 1643
8.1643.2.3 pAutoAnswer . . . 1643
8.1643.2.4 pNamID . . . 1643
8.1643.2.5 pPrefVoicePrivacy . . . 1643
8.1643.2.6 pPrefVoiceSO . . . 1643
8.1643.2.7 pRoamTimer . . . 1644
8.1643.2.8 pTTYMode . . . 1644
8.1643.2.9 pVoiceDomainPref . . . 1644
8.1644 VoiceGetConfigResp Struct Reference . . . 1644
8.1644.1 Detailed Description . . . 1644
8.1644.2 Field Documentation . . . 1645
8.1644.2.1 pAirTimerCnt . . . 1645
8.1644.2.2 pAutoAnswerStat . . . 1645
8.1644.2.3 pCurAMRConfig . . . 1645
8.1644.2.4 pCurPrefVoiceSO . . . 1645
8.1644.2.5 pCurrTTYMode . . . 1645
8.1644.2.6 pCurVoiceDomainPref . . . 1645
8.1644.2.7 pCurVoicePrivacyPref . . . 1645
8.1644.2.8 pRoamTimerCnt . . . 1645
8.1645 VoiceIndicationRegisterInfo Struct Reference . . . 1645
8.1645.1 Detailed Description . . . 1646
8.1645.2 Field Documentation . . . 1646
8.1645.2.1 pRegDTMFEvents . . . 1646
8.1645.2.2 pRegVoicePrivacyEvents . . . 1646
8.1645.2.3 pSuppsNotifEvents . . . 1646
8.1646 VoiceInfoRec Struct Reference . . . 1646
8.1646.1 Detailed Description . . . 1647
8.1646.2 Field Documentation . . . 1648
8.1646.2.1 callID . . . 1648

8.1646.2.2 pCalledPartyInfo . . . 1648
8.1646.2.3 pCallerIDInfo . . . 1648
8.1646.2.4 pCallerNameInfo . . . 1648
8.1646.2.5 pCallingPartyInfo . . . 1648
8.1646.2.6 pCallWaitInd . . . 1648
8.1646.2.7 pCLIRCause . . . 1648
8.1646.2.8 pConnectNumInfo . . . 1648
8.1646.2.9 pDispInfo . . . 1648
8.1646.2.10 pExtDispInfo . . . 1648
8.1646.2.11 pExtDispRecInfo . . . 1648
8.1646.2.12 pLineCtrlInfo . . . 1648
8.1646.2.13 pNSSAudioCtrl . . . 1649
8.1646.2.14 pNSSRelease . . . 1649
8.1646.2.15 pRedirNumInfo . . . 1649
8.1646.2.16 pSignalInfo . . . 1649
8.1646.2.17 results . . . 1649
8.1647 VoiceManageCallsReq Struct Reference . . . 1649
8.1647.1 Detailed Description . . . 1649
8.1647.2 Field Documentation . . . 1649
8.1647.2.1 pCallID . . . 1649
8.1647.2.2 SUPSType . . . 1650
8.1648 VoiceManageCallsResp Struct Reference . . . 1650
8.1648.1 Detailed Description . . . 1650
8.1648.2 Field Documentation . . . 1650
8.1648.2.1 pFailCause . . . 1650
8.1649 VoiceOrigUSSDNoWaitInfo Struct Reference . . . 1650
8.1649.1 Detailed Description . . . 1650
8.1649.2 Field Documentation . . . 1650
8.1649.2.1 USSInformation . . . 1650
8.1650 VoiceOTASPStatusInfo Struct Reference . . . 1650
8.1650.1 Detailed Description . . . 1651
8.1650.2 Field Documentation . . . 1651
8.1650.2.1 callID . . . 1651
8.1650.2.2 OTASPStatus . . . 1651
8.1650.2.3 results . . . 1651
8.1651 VoicePrivacyInfo Struct Reference . . . 1651
8.1651.1 Detailed Description . . . 1652
8.1651.2 Field Documentation . . . 1652
8.1651.2.1 callID . . . 1652
8.1651.2.2 results . . . 1652

8.1651.2.3 voicePrivacy . . . 1652
8.1652 VoiceSetAllCallStatusCbkInfo Struct Reference . . . 1652
8.1652.1 Detailed Description . . . 1652
8.1652.2 Field Documentation . . . 1654
8.1652.2.1 arrCallInfomation . . . 1654
8.1652.2.2 pArrAlertingPattern . . . 1654
8.1652.2.3 pArrAlertingType . . . 1654
8.1652.2.4 pArrAlphaID . . . 1654
8.1652.2.5 pArrCalledPartyNum . . . 1654
8.1652.2.6 pArrCallEndReason . . . 1654
8.1652.2.7 pArrConnectPartyNum . . . 1654
8.1652.2.8 pArrDiagInfo . . . 1654
8.1652.2.9 pArrRedirPartyNum . . . 1654
8.1652.2.10 pArrRemotePartyName . . . 1654
8.1652.2.11 pArrRemotePartyNum . . . 1654
8.1652.2.12 pArrSvcOption . . . 1654
8.1652.2.13 results . . . 1654
8.1653 VoiceSetCallBarringPwdInfo Struct Reference . . . 1654
8.1653.1 Detailed Description . . . 1655
8.1653.2 Field Documentation . . . 1655
8.1653.2.1 newPasswd . . . 1655
8.1653.2.2 newPasswdAgain . . . 1655
8.1653.2.3 oldPasswd . . . 1655
8.1653.2.4 Reason . . . 1655
8.1654 VoiceSetCallBarringPwdResp Struct Reference . . . 1655
8.1654.1 Detailed Description . . . 1656
8.1654.2 Field Documentation . . . 1656
8.1654.2.1 pAlphaIDInfo . . . 1656
8.1654.2.2 pCallID . . . 1656
8.1654.2.3 pCCResType . . . 1656
8.1654.2.4 pCCSUPSType . . . 1656
8.1654.2.5 pFailCause . . . 1656
8.1655 VoiceSetConfigReq Struct Reference . . . 1657
8.1655.1 Detailed Description . . . 1657
8.1655.2 Field Documentation . . . 1658
8.1655.2.1 pAirTimerConfig . . . 1658
8.1655.2.2 pAutoAnswer . . . 1658
8.1655.2.3 pPrefVoiceDomain . . . 1658
8.1655.2.4 pPrefVoiceSO . . . 1658
8.1655.2.5 pRoamTimerConfig . . . 1658

8.1655.2.6 pTTYMode . . . 1658
8.1656 VoiceSetConfigResp Struct Reference . . . 1658
8.1656.1 Detailed Description . . . 1658
8.1656.2 Field Documentation . . . 1659
8.1656.2.1 pAirTimerStatus . . . 1659
8.1656.2.2 pAutoAnsStatus . . . 1659
8.1656.2.3 pPrefVoiceSOStatus . . . 1659
8.1656.2.4 pRoamTimerStatus . . . 1659
8.1656.2.5 pTTYConfigStatus . . . 1659
8.1656.2.6 pVoiceDomainPrefStatus . . . 1659
8.1657 VoiceSetPrefPrivacy Struct Reference . . . 1659
8.1657.1 Detailed Description . . . 1660
8.1657.2 Field Documentation . . . 1660
8.1657.2.1 privacyPref . . . 1660
8.1658 VoiceSetSUPSServiceReq Struct Reference . . . 1660
8.1658.1 Detailed Description . . . 1660
8.1658.2 Field Documentation . . . 1662
8.1658.2.1 pCallBarringPasswd . . . 1662
8.1658.2.2 pCallForwardingNumber . . . 1662
8.1658.2.3 pCallFwdTypeAndPlan . . . 1662
8.1658.2.4 pServiceClass . . . 1662
8.1658.2.5 pTimerVal . . . 1662
8.1658.2.6 reason . . . 1662
8.1658.2.7 voiceSvc . . . 1662
8.1659 VoiceSetSUPSServiceResp Struct Reference . . . 1662
8.1659.1 Detailed Description . . . 1662
8.1659.2 Field Documentation . . . 1663
8.1659.2.1 pAlphaIDInfo . . . 1663
8.1659.2.2 pCallID . . . 1663
8.1659.2.3 pCCResultType . . . 1663
8.1659.2.4 pCCSUPSType . . . 1663
8.1659.2.5 pFailCause . . . 1663
8.1660 VoiceStopContDTMFinfo Struct Reference . . . 1663
8.1660.1 Detailed Description . . . 1663
8.1660.2 Field Documentation . . . 1664
8.1660.2.1 callID . . . 1664
8.1661 VoiceSUPSInfo Struct Reference . . . 1664
8.1661.1 Detailed Description . . . 1664
8.1661.2 Field Documentation . . . 1666
8.1661.2.1 pAlphaIDInfo . . . 1666

8.1661.2.2 pCallBarPasswd . . . 1666
8.1661.2.3 pCallFwdInfo . . . 1666
8.1661.2.4 pCallFWNum . . . 1666
8.1661.2.5 pCallFWTimerVal . . . 1666
8.1661.2.6 pCallID . . . 1666
8.1661.2.7 pCLIPstatus . . . 1666
8.1661.2.8 pCLIRstatus . . . 1666
8.1661.2.9 pCNAPstatus . . . 1666
8.1661.2.10 pCOLPstatus . . . 1666
8.1661.2.11 pCOLRstatus . . . 1666
8.1661.2.12 pDataSrc . . . 1666
8.1661.2.13 pFailCause . . . 1666
8.1661.2.14 pNewPwdData . . . 1666
8.1661.2.15 pReason . . . 1666
8.1661.2.16 pSvcClass . . . 1666
8.1661.2.17 pUSSInfo . . . 1666
8.1661.2.18 results . . . 1666
8.1661.2.19 pUPSInformation . . . 1666
8.1662 VoiceSUPSNotification Struct Reference . . . 1666
8.1662.1 Detailed Description . . . 1667
8.1662.2 Field Documentation . . . 1668
8.1662.2.1 callID . . . 1668
8.1662.2.2 notifType . . . 1668
8.1662.2.3 pCUGIndex . . . 1668
8.1662.2.4 pECTNum . . . 1668
8.1662.2.5 results . . . 1668
8.1663 WcdmaCellInfo Struct Reference . . . 1668
8.1663.1 Detailed Description . . . 1668
8.1663.2 Field Documentation . . . 1669
8.1663.2.1 cpich_ecno . . . 1669
8.1663.2.2 cpich_rscp . . . 1669
8.1663.2.3 psc . . . 1669
8.1663.2.4 srxlev . . . 1669
8.1664 WCDMAECIOThresh Struct Reference . . . 1669
8.1664.1 Detailed Description . . . 1669
8.1664.2 Field Documentation . . . 1669
8.1664.2.1 pWCDMAECIOThreshList . . . 1669
8.1664.2.2 WCDMAECIOThreshListLen . . . 1669
8.1665 WCDMAInfoLTENeighborCell Struct Reference . . . 1669
8.1665.1 Detailed Description . . . 1670

8.1665.2 Field Documentation . . . 1670
8.1665.2.1 UMTSLTENbrCell . . . 1670
8.1665.2.2 umtsLTENbrCellLen . . . 1670
8.1665.2.3 wcdmaRRCState . . . 1670
8.1666 wcdmaLongMsgDecodingParams Struct Reference . . . 1670
8.1666.1 Detailed Description . . . 1671
8.1666.2 Field Documentation . . . 1672
8.1666.2.1 Date . . . 1672
8.1666.2.2 MessageLen . . . 1672
8.1666.2.3 pIsUDHPresent . . . 1672
8.1666.2.4 pMessage . . . 1672
8.1666.2.5 pPartNum . . . 1672
8.1666.2.6 pReferenceNum . . . 1672
8.1666.2.7 pScAddr . . . 1672
8.1666.2.8 pScAddrLength . . . 1672
8.1666.2.9 pSenderAddr . . . 1672
8.1666.2.10 pSenderAddrLength . . . 1672
8.1666.2.11 pTextMsg . . . 1672
8.1666.2.12 pTextMsgLength . . . 1672
8.1666.2.13 pTotalNum . . . 1672
8.1666.2.14 time . . . 1672
8.1667 wcdmaMsgDecodingParams Struct Reference . . . 1672
8.1667.1 Detailed Description . . . 1672
8.1667.2 Field Documentation . . . 1673
8.1667.2.1 date . . . 1673
8.1667.2.2 MessageLen . . . 1673
8.1667.2.3 pMessage . . . 1673
8.1667.2.4 pScAddrLength . . . 1673
8.1667.2.5 pSenderAddrLength . . . 1673
8.1667.2.6 pTextMsgLength . . . 1674
8.1667.2.7 scAddr . . . 1674
8.1667.2.8 senderAddr . . . 1674
8.1667.2.9 textMsg . . . 1674
8.1667.2.10 time . . . 1674
8.1668 wcdmaMsgEncodingParams Struct Reference . . . 1674
8.1668.1 Detailed Description . . . 1674
8.1668.2 Field Documentation . . . 1674
8.1668.2.1 alphabet . . . 1674
8.1668.2.2 messageSize . . . 1674
8.1668.2.3 pDestAddr . . . 1674

8.1668.2.4 PDUMessage . . . 1675
8.1668.2.5 pTextMsg . . . 1675
8.1669 WCDMARSSIThresh Struct Reference . . . 1675
8.1669.1 Detailed Description . . . 1675
8.1669.2 Field Documentation . . . 1675
8.1669.2.1 pWCDMARSSIThreshList . . . 1675
8.1669.2.2 WCDMARSSIThreshListLen . . . 1675
8.1670 WCDMASysInfo Struct Reference . . . 1675
8.1670.1 Detailed Description . . . 1676
8.1670.2 Field Documentation . . . 1678
8.1670.2.1 cellId . . . 1678
8.1670.2.2 cellIdValid . . . 1678
8.1670.2.3 hsCallStatus . . . 1678
8.1670.2.4 hsCallStatusValid . . . 1678
8.1670.2.5 hsInd . . . 1678
8.1670.2.6 hsIndValid . . . 1678
8.1670.2.7 lac . . . 1678
8.1670.2.8 lacValid . . . 1678
8.1670.2.9 MCC . . . 1678
8.1670.2.10 MNC . . . 1678
8.1670.2.11 networkIdValid . . . 1678
8.1670.2.12 psc . . . 1678
8.1670.2.13 pscValid . . . 1678
8.1670.2.14 regRejectInfoValid . . . 1679
8.1670.2.15 rejCause . . . 1679
8.1670.2.16 rejectSrvDomain . . . 1679
8.1670.2.17 sysInfoWCDMA . . . 1679
8.1671 wcdmaUARFCN Struct Reference . . . 1679
8.1671.1 Detailed Description . . . 1679
8.1671.2 Field Documentation . . . 1679
8.1671.2.1 status . . . 1679
8.1671.2.2 uarfcn . . . 1679
8.1672 wds_channelRate Struct Reference . . . 1679
8.1672.1 Detailed Description . . . 1679
8.1672.2 Field Documentation . . . 1680
8.1672.2.1 CurrChanRxRate . . . 1680
8.1672.2.2 CurrChanTxRate . . . 1680
8.1673 wds_ChannelRateTlv Struct Reference . . . 1680
8.1673.1 Detailed Description . . . 1680
8.1673.2 Field Documentation . . . 1680

8.1673.2.1 ChannelRate . . . 1680
8.1673.2.2 TlvPresent . . . 1680
8.1674 wds_ConnStatusTlv Struct Reference . . . 1680
8.1674.1 Detailed Description . . . 1680
8.1674.2 Field Documentation . . . 1681
8.1674.2.1 MDMConnStatus . . . 1681
8.1674.2.2 TlvPresent . . . 1681
8.1675 wds_currNetworkInfo Struct Reference . . . 1681
8.1675.1 Detailed Description . . . 1681
8.1675.2 Field Documentation . . . 1682
8.1675.2.1 NetworkType . . . 1682
8.1675.2.2 RATMask . . . 1682
8.1675.2.3 SOMask . . . 1682
8.1676 wds_DataBearTechTlv Struct Reference . . . 1682
8.1676.1 Detailed Description . . . 1682
8.1676.2 Field Documentation . . . 1682
8.1676.2.1 DataBearerTech . . . 1682
8.1676.2.2 TlvPresent . . . 1683
8.1677 wds_DataULongLongTlv Struct Reference . . . 1683
8.1677.1 Detailed Description . . . 1683
8.1677.2 Field Documentation . . . 1683
8.1677.2.1 TlvPresent . . . 1683
8.1677.2.2 ullData . . . 1683
8.1678 wds_DataULongTlv Struct Reference . . . 1683
8.1678.1 Detailed Description . . . 1683
8.1678.2 Field Documentation . . . 1683
8.1678.2.1 TlvPresent . . . 1683
8.1678.2.2 ulData . . . 1683
8.1679 wds_DHCPLeaseOptTlv Struct Reference . . . 1683
8.1679.1 Detailed Description . . . 1684
8.1679.2 Field Documentation . . . 1684
8.1679.2.1 numOpt . . . 1684
8.1679.2.2 optList . . . 1684
8.1679.2.3 optListData . . . 1684
8.1679.2.4 TlvPresent . . . 1684
8.1680 wds_DHCPLeaseStateTlv Struct Reference . . . 1684
8.1680.1 Detailed Description . . . 1684
8.1680.2 Field Documentation . . . 1684
8.1680.2.1 leaseState . . . 1684
8.1680.2.2 TlvPresent . . . 1685

8.1681 wds_DHCPOpt Struct Reference . . . 1685
8.1681.1 Detailed Description . . . 1685
8.1681.2 Field Documentation . . . 1685
8.1681.2.1 optCode . . . 1685
8.1681.2.2 optValLen . . . 1685
8.1681.2.3 pOptVal . . . 1685
8.1682 wds_DHCPProfileIdTlv Struct Reference . . . 1685
8.1682.1 Detailed Description . . . 1685
8.1682.2 Field Documentation . . . 1686
8.1682.2.1 profileId . . . 1686
8.1682.2.2 profileType . . . 1686
8.1682.2.3 TlvPresent . . . 1686
8.1683 wds_DHCPv4HWConfig Struct Reference . . . 1686
8.1683.1 Detailed Description . . . 1686
8.1683.2 Field Documentation . . . 1686
8.1683.2.1 chaddr . . . 1686
8.1683.2.2 chaddrLen . . . 1686
8.1683.2.3 hwType . . . 1686
8.1684 wds_DHCPv4Option Struct Reference . . . 1686
8.1684.1 Detailed Description . . . 1687
8.1684.2 Field Documentation . . . 1687
8.1684.2.1 optCode . . . 1687
8.1684.2.2 optVal . . . 1687
8.1684.2.3 optValLen . . . 1687
8.1685 wds_DHCPv4OptionList Struct Reference . . . 1687
8.1685.1 Detailed Description . . . 1687
8.1685.2 Field Documentation . . . 1687
8.1685.2.1 numOpt . . . 1687
8.1685.2.2 pOptList . . . 1687
8.1686 wds_DHCPv4ProfileId Struct Reference . . . 1688
8.1686.1 Detailed Description . . . 1688
8.1686.2 Field Documentation . . . 1688
8.1686.2.1 profileId . . . 1688
8.1686.2.2 profileType . . . 1688
8.1687 wds_Domain Struct Reference . . . 1688
8.1687.1 Detailed Description . . . 1688
8.1687.2 Field Documentation . . . 1688
8.1687.2.1 domainLen . . . 1688
8.1687.2.2 domainName . . . 1688
8.1688 wds_DomainNameList Struct Reference . . . 1689

8.1688.1 Detailed Description . . . 1689
8.1688.2 Field Documentation . . . 1689
8.1688.2.1 domain . . . 1689
8.1688.2.2 numInstances . . . 1689
8.1689 wds_DormStatTlv Struct Reference . . . 1689
8.1689.1 Detailed Description . . . 1689
8.1689.2 Field Documentation . . . 1689
8.1689.2.1 DormancyStat . . . 1690
8.1689.2.2 TlvPresent . . . 1690
8.1690 wds_GPRSQoS Struct Reference . . . 1690
8.1690.1 Detailed Description . . . 1690
8.1690.2 Field Documentation . . . 1690
8.1690.2.1 delayClass . . . 1690
8.1690.2.2 meanThroughputClass . . . 1690
8.1690.2.3 peakThroughputClass . . . 1690
8.1690.2.4 precedenceClass . . . 1690
8.1690.2.5 reliabilityClass . . . 1690
8.1691 wds_IPv4AdTlv Struct Reference . . . 1690
8.1691.1 Detailed Description . . . 1691
8.1691.2 Field Documentation . . . 1691
8.1691.2.1 IPv4Addr . . . 1691
8.1691.2.2 TlvPresent . . . 1691
8.1692 wds_IPV6AddressInfo Struct Reference . . . 1691
8.1692.1 Detailed Description . . . 1691
8.1692.2 Field Documentation . . . 1691
8.1692.2.1 IPAddressV6 . . . 1691
8.1692.2.2 IPV6PrefixLen . . . 1691
8.1693 wds_IPV6GWAddressInfo Struct Reference . . . 1691
8.1693.1 Detailed Description . . . 1692
8.1693.2 Field Documentation . . . 1692
8.1693.2.1 gwAddressV6 . . . 1692
8.1693.2.2 gwV6PrefixLen . . . 1692
8.1694 wds_LastMdmCallEndRsnTlv Struct Reference . . . 1692
8.1694.1 Detailed Description . . . 1692
8.1694.2 Field Documentation . . . 1692
8.1694.2.1 CallEndReason . . . 1692
8.1694.2.2 TlvPresent . . . 1692
8.1695 wds_PCSCFFQDNAddress Struct Reference . . . 1693
8.1695.1 Detailed Description . . . 1693
8.1695.2 Field Documentation . . . 1693

8.1695.2.1 fqdnAddr . . . 1693
8.1695.2.2 fqdnLen . . . 1693
8.1696 wds_PCSCFFQDNAddressList Struct Reference . . . 1693
8.1696.1 Detailed Description . . . 1693
8.1696.2 Field Documentation . . . 1693
8.1696.2.1 numInstances . . . 1693
8.1696.2.2 pcsfFQDNAddress . . . 1694
8.1697 wds_PCSCFIPv4ServerAddressList Struct Reference . . . 1694
8.1697.1 Detailed Description . . . 1694
8.1697.2 Field Documentation . . . 1694
8.1697.2.1 numInstances . . . 1694
8.1697.2.2 pscsfIPv4Addr . . . 1694
8.1698 wds_ProfileIdentifier Struct Reference . . . 1694
8.1698.1 Detailed Description . . . 1694
8.1698.2 Field Documentation . . . 1695
8.1698.2.1 profileIndex . . . 1695
8.1698.2.2 profileType . . . 1695
8.1699 wds_profileInfo Union Reference . . . 1695
8.1699.1 Detailed Description . . . 1695
8.1699.2 Field Documentation . . . 1695
8.1699.2.1 SlqsProfile3GPP . . . 1695
8.1699.2.2 SlqsProfile3GPP2 . . . 1695
8.1700 wds_RXBytesOKTlv Struct Reference . . . 1695
8.1700.1 Detailed Description . . . 1695
8.1700.2 Field Documentation . . . 1695
8.1700.2.1 RxByteOKCnt . . . 1696
8.1700.2.2 TlvPresent . . . 1696
8.1701 wds_transferStatInd Struct Reference . . . 1696
8.1701.1 Detailed Description . . . 1696
8.1701.2 Field Documentation . . . 1696
8.1701.2.1 StatsMask . . . 1696
8.1701.2.2 StatsPeriod . . . 1696
8.1702 wds_TrStatInd Struct Reference . . . 1696
8.1702.1 Detailed Description . . . 1696
8.1702.2 Field Documentation . . . 1697
8.1702.2.1 statsMask . . . 1697
8.1702.2.2 statsPeriod . . . 1697
8.1703 wds_TXBytesOKTlv Struct Reference . . . 1697
8.1703.1 Detailed Description . . . 1697
8.1703.2 Field Documentation . . . 1697

8.1703.2.1 TlvPresent . . . 1697
8.1703.2.2 TxByteOKCnt . . . 1697
8.1704 wds_UMTSMinQoS Struct Reference . . . 1697
8.1704.1 Detailed Description . . . 1698
8.1704.2 Field Documentation . . . 1699
8.1704.2.1 deliveryErrSDU . . . 1699
8.1704.2.2 grntDownlinkBitrate . . . 1700
8.1704.2.3 grntUplinkBitrate . . . 1700
8.1704.2.4 maxDownlinkBitrate . . . 1700
8.1704.2.5 maxSDUSize . . . 1700
8.1704.2.6 maxUplinkBitrate . . . 1700
8.1704.2.7 qosDeliveryOrder . . . 1700
8.1704.2.8 resBerRatio . . . 1700
8.1704.2.9 sduErrorRatio . . . 1700
8.1704.2.10 trafficClass . . . 1700
8.1704.2.11 trafficPriority . . . 1700
8.1704.2.12 transferDelay . . . 1700
8.1705 WdsByteTotals Struct Reference . . . 1700
8.1705.1 Detailed Description . . . 1700
8.1705.2 Field Documentation . . . 1701
8.1705.2.1 ByteTotalsElmntsV4 . . . 1701
8.1705.2.2 ByteTotalsElmntsV6 . . . 1701
8.1705.2.3 pV4sessionId . . . 1701
8.1705.2.4 pV6sessionId . . . 1701
8.1706 WdsByteTotalsElmnts Struct Reference . . . 1701
8.1706.1 Detailed Description . . . 1701
8.1706.2 Field Documentation . . . 1701
8.1706.2.1 pRXTotalBytes . . . 1701
8.1706.2.2 pTXTotalBytes . . . 1701
8.1707 WdsClientLeaseChange Struct Reference . . . 1701
8.1707.1 Detailed Description . . . 1701
8.1707.2 Field Documentation . . . 1702
8.1707.2.1 pEnableNotification . . . 1702
8.1708 WdsConnectionRate Struct Reference . . . 1702
8.1708.1 Detailed Description . . . 1702
8.1708.2 Field Documentation . . . 1702
8.1708.2.1 ConnRateElmntsV4 . . . 1702
8.1708.2.2 ConnRateElmntsV6 . . . 1702
8.1708.2.3 pV4sessionId . . . 1702
8.1708.2.4 pV6sessionId . . . 1702

8.1709 WdsConnectionRateElmnts Struct Reference . . . 1703
8.1709.1 Detailed Description . . . 1703
8.1709.2 Field Documentation . . . 1703
8.1709.2.1 pCurrentChannelRXRate . . . 1703
8.1709.2.2 pCurrentChannelTXRate . . . 1703
8.1709.2.3 pMaxChannelRXRate . . . 1703
8.1709.2.4 pMaxChannelTXRate . . . 1703
8.1710 WdsDHCPv4ClientLeaseInd Struct Reference . . . 1703
8.1710.1 Detailed Description . . . 1703
8.1710.2 Field Documentation . . . 1704
8.1710.2.1 pIPv4Addr . . . 1704
8.1710.2.2 pLeaseState . . . 1704
8.1710.2.3 pOptList . . . 1704
8.1710.2.4 pProfileId . . . 1704
8.1711 WdsDHCPv4Config Struct Reference . . . 1704
8.1711.1 Detailed Description . . . 1704
8.1711.2 Field Documentation . . . 1705
8.1711.2.1 pHwConfig . . . 1705
8.1711.2.2 pProfileId . . . 1705
8.1711.2.3 pRequestOptionList . . . 1705
8.1712 WdsDHCPv4HWConfig Struct Reference . . . 1705
8.1712.1 Detailed Description . . . 1705
8.1712.2 Field Documentation . . . 1705
8.1712.2.1 chaddr . . . 1705
8.1712.2.2 chaddrLen . . . 1705
8.1712.2.3 hwType . . . 1705
8.1713 WdsDhcpv4HwConfig Struct Reference . . . 1705
8.1713.1 Detailed Description . . . 1706
8.1713.2 Field Documentation . . . 1706
8.1713.2.1 chaddr . . . 1706
8.1713.2.2 chaddrLen . . . 1706
8.1713.2.3 hwType . . . 1706
8.1714 WdsDHCPv4Option Struct Reference . . . 1706
8.1714.1 Detailed Description . . . 1706
8.1714.2 Field Documentation . . . 1706
8.1714.2.1 optCode . . . 1706
8.1714.2.2 optVal . . . 1707
8.1714.2.3 optValLen . . . 1707
8.1715 WdsDhcpv4Option Struct Reference . . . 1707
8.1715.1 Detailed Description . . . 1707

8.1715.2 Field Documentation . . . 1707
8.1715.2.1 optCode . . . 1707
8.1715.2.2 optVal . . . 1707
8.1715.2.3 optValLen . . . 1707
8.1716 WdsDHCPv4OptionList Struct Reference . . . 1707
8.1716.1 Detailed Description . . . 1707
8.1716.2 Field Documentation . . . 1708
8.1716.2.1 numOpt . . . 1708
8.1716.2.2 pOptList . . . 1708
8.1717 WdsDhcpv4OptionList Struct Reference . . . 1708
8.1717.1 Detailed Description . . . 1708
8.1717.2 Field Documentation . . . 1708
8.1717.2.1 numOpt . . . 1708
8.1717.2.2 pOptList . . . 1708
8.1718 WdsDhcpv4ProfileId Struct Reference . . . 1708
8.1718.1 Detailed Description . . . 1708
8.1718.2 Field Documentation . . . 1709
8.1718.2.1 profileId . . . 1709
8.1718.2.2 profileType . . . 1709
8.1719 WdsDHCPv4ProfileId Struct Reference . . . 1709
8.1719.1 Detailed Description . . . 1709
8.1719.2 Field Documentation . . . 1709
8.1719.2.1 profileId . . . 1709
8.1719.2.2 profileType . . . 1709
8.1720 WDSGetLoopbackData Struct Reference . . . 1709
8.1720.1 Detailed Description . . . 1709
8.1720.2 Field Documentation . . . 1710
8.1720.2.1 ByteLoopbackMode . . . 1710
8.1720.2.2 ByteLoopbackMultiplier . . . 1710
8.1721 WdsIpAddressInfoReq Struct Reference . . . 1710
8.1721.1 Detailed Description . . . 1710
8.1721.2 Field Documentation . . . 1710
8.1721.2.1 ip . . . 1710
8.1721.2.2 pv4sessionId . . . 1710
8.1721.2.3 pv6sessionId . . . 1710
8.1722 WdsPktStatisticsElmnts Struct Reference . . . 1711
8.1722.1 Detailed Description . . . 1711
8.1722.2 Field Documentation . . . 1712
8.1722.2.1 pRXDroppedCount . . . 1712
8.1722.2.2 pRXOkBytesCount . . . 1712

8.1722.2.3 pRXOKBytesLastCall . . . 1712
8.1722.2.4 pRXPacketErrors . . . 1712
8.1722.2.5 pRXPacketOverflows . . . 1712
8.1722.2.6 pRXPacketSuccesses . . . 1712
8.1722.2.7 pTXDroppedCount . . . 1712
8.1722.2.8 pTXOkBytesCount . . . 1712
8.1722.2.9 pTXOKBytesLastCall . . . 1712
8.1722.2.10 pTXPacketErrors . . . 1712
8.1722.2.11 pTXPacketOverflows . . . 1712
8.1722.2.12 pTXPacketSuccesses . . . 1712
8.1723 WdsPktStatisticsReq Struct Reference . . . 1712
8.1723.1 Detailed Description . . . 1712
8.1723.2 Field Documentation . . . 1713
8.1723.2.1 pStatMask . . . 1713
8.1724 WdsPktStatisticsResp Struct Reference . . . 1713
8.1724.1 Detailed Description . . . 1713
8.1724.2 Field Documentation . . . 1713
8.1724.2.1 PktStatElmntsV4 . . . 1713
8.1724.2.2 PktStatElmntsV6 . . . 1713
8.1724.2.3 pV4sessionId . . . 1713
8.1724.2.4 pV6sessionId . . . 1714
8.1725 WdsProfileParam Union Reference . . . 1714
8.1725.1 Detailed Description . . . 1714
8.1725.2 Field Documentation . . . 1714
8.1725.2.1 SlqsProfile3GPP . . . 1714
8.1725.2.2 SlqsProfile3GPP2 . . . 1714
8.1726 WdsRunTimeSettings Struct Reference . . . 1714
8.1726.1 Detailed Description . . . 1714
8.1726.2 Field Documentation . . . 1715
8.1726.2.1 rts . . . 1715
8.1726.2.2 v4sessionId . . . 1715
8.1726.2.3 v6sessionId . . . 1715
8.1727 WdsSetEventReportReq Struct Reference . . . 1715
8.1727.1 Detailed Description . . . 1715
8.1727.2 Field Documentation . . . 1716
8.1727.2.1 pCurrChannelRateInd . . . 1716
8.1727.2.2 pCurrDataBearerTechInd . . . 1716
8.1727.2.3 pCurrPrefDataSysInd . . . 1716
8.1727.2.4 pDataBearerTechInd . . . 1716
8.1727.2.5 pDataCallStatusChangeInd . . . 1716

8.1727.2.6 pDataSystemStatusChangeInd . . . 1716
8.1727.2.7 pDormancyStatusInd . . . 1716
8.1727.2.8 pEVDOPageMonPerChangeInd . . . 1716
8.1727.2.9 pMIPStatusInd . . . 1717
8.1727.2.10 pTransferStatInd . . . 1717
8.1728 WDSSetLoopbackData Struct Reference . . . 1717
8.1728.1 Detailed Description . . . 1717
8.1728.2 Field Documentation . . . 1717
8.1728.2.1 pLoopbackMode . . . 1717
8.1728.2.2 pLoopbackMultiplier . . . 1717
8.1729 WDSSWICurrentChannelRates Struct Reference . . . 1717
8.1729.1 Detailed Description . . . 1717
8.1729.2 Field Documentation . . . 1718
8.1729.2.1 current_channel_rx_rate . . . 1718
8.1729.2.2 current_channel_tx_rate . . . 1718
8.1729.2.3 max_channel_rx_rate . . . 1718
8.1729.2.4 max_channel_tx_rate . . . 1718

9 File Documentation **1719**
9.1 apdoxypages.c File Reference . . . 1719
9.1.1 Detailed Description . . . 1719
9.2 common.h File Reference . . . 1719
9.2.1 Macro Definition Documentation . . . 1721
9.2.1.1 DEAULT_LOC_TIMEOUT_IN_SEC . . . 1721
9.2.1.2 MINREQBKLEN . . . 1721
9.2.1.3 MSGID_AND_LEN . . . 1721
9.2.1.4 MSGID_DONT_CARE . . . 1721
9.2.1.5 SDK_VALIDATE_INPUT_PACK_PARAM . . . 1721
9.2.1.6 SDK_VALIDATE_INPUT_PACK_PARAM_AND_FILL_XID . . . 1721
9.2.1.7 SDK_VALIDATE_INPUT_UNPACK_PARAM . . . 1722
9.2.1.8 SDU_HDR_LEN . . . 1722
9.2.1.9 SWI_INIT_UNPACK_RESULT_VALUE . . . 1722
9.2.1.10 UNUSEDPARAM . . . 1722
9.2.2 Typedef Documentation . . . 1722
9.2.2.1 logger . . . 1722
9.2.3 Enumeration Type Documentation . . . 1722
9.2.3.1 eLOG_LEVEL . . . 1722
9.2.3.2 eQMI_SVC . . . 1722
9.2.3.3 eTimeout . . . 1723
9.2.3.4 msgtype . . . 1723

9.2.4 Function Documentation . . . 1723
9.2.4.1 fill_pack_ctx . . . 1723
9.2.4.2 fill_sdu_hdr . . . 1723
9.2.4.3 get_version . . . 1723
9.2.4.4 helper_get_error_code . . . 1724
9.2.4.5 helper_get_error_reason . . . 1724
9.2.4.6 helper_get_req_str . . . 1724
9.2.4.7 helper_get_resp_ctx . . . 1724
9.2.4.8 helper_get_xid . . . 1724
9.2.4.9 helper_isBootLoader_DebugEnabled . . . 1724
9.2.4.10 helper_set_log_func . . . 1725
9.2.4.11 helper_set_log_lvl . . . 1725
9.2.4.12 liteqmi_GetVersion . . . 1725
9.2.4.13 liteqmi_helper_decode7bitAsciiEncString . . . 1725
9.2.4.14 liteqmi_log . . . 1725
9.2.4.15 unpack_result_code_only . . . 1725
9.2.5 Variable Documentation . . . 1725
9.2.5.1 glog . . . 1725
9.2.5.2 gloglvl . . . 1725
9.3 dms.h File Reference . . . 1725
9.3.1 Macro Definition Documentation . . . 1733
9.3.1.1 ACT_CODE_MAX_SIZE . . . 1733
9.3.1.2 CK_MAX_SIZE . . . 1733
9.3.1.3 DMS_IMGDETAILS_LEN . . . 1733
9.3.1.4 DMS_MAX_CUST_ID_LEN . . . 1733
9.3.1.5 DMS_MAX_CUST_VALUE_LEN . . . 1733
9.3.1.6 DMS_MAX_FWUPDATE_LOG_STR_SZ . . . 1733
9.3.1.7 DMS_MAX_FWUPDATE_REF_STR_SZ . . . 1733
9.3.1.8 DMS_MAX_RADIO_IFCS_SIZE . . . 1733
9.3.1.9 DMS_PM_FACTORY . . . 1733
9.3.1.10 DMS_PM_LOW . . . 1733
9.3.1.11 DMS_PM_OFFLINE . . . 1733
9.3.1.12 DMS_PM_ONLINE . . . 1733
9.3.1.13 DMS_PM_PERSISTENT_LOW . . . 1733
9.3.1.14 DMS_PM_RESET . . . 1733
9.3.1.15 DMS_PM_SHUT_DOWN . . . 1733
9.3.1.16 DMS_SET_REG_IND_DISABLE . . . 1733
9.3.1.17 DMS_SET_REG_IND_ENABLE . . . 1733
9.3.1.18 DMS_SET_REG_IND_NO_CHANGE . . . 1733
9.3.1.19 DMS_SET_REPORT_DISABLE . . . 1733

9.3.1.20 DMS_SET_REPORT_ENABLE . . . 1733
9.3.1.21 DMS_SLQSFWINFO_APPVERSION_SZ . . . 1733
9.3.1.22 DMS_SLQSFWINFO_BOOTVERSION_SZ . . . 1733
9.3.1.23 DMS_SLQSFWINFO_CARRIER_SZ . . . 1733
9.3.1.24 DMS_SLQSFWINFO_CUR_CARR_NAME . . . 1733
9.3.1.25 DMS_SLQSFWINFO_CUR_CARR_REV . . . 1733
9.3.1.26 DMS_SLQSFWINFO_MODELID_SZ . . . 1733
9.3.1.27 DMS_SLQSFWINFO_PACKAGEID_SZ . . . 1733
9.3.1.28 DMS_SLQSFWINFO_PRIVERSION_SZ . . . 1734
9.3.1.29 DMS_SLQSFWINFO_SKU_SZ . . . 1734
9.3.1.30 DMS_SWI_SET_IND_DISABLE . . . 1734
9.3.1.31 DMS_SWI_SET_IND_ENABLE . . . 1734
9.3.1.32 DMS_UINT8_MAX_STRING_SZ . . . 1734
9.3.1.33 DMS_VALID_FSN_LEN . . . 1734
9.3.1.34 ERI_DATA_MAX_SIZE . . . 1734
9.3.1.35 MAX_BUILD_ID_LEN . . . 1734
9.3.1.36 MEID_MAX_SIZE . . . 1734
9.3.1.37 SLQS_MAX_DYING_GASP_CFG_SMS_CONTENT_LENGTH . . . 1734
9.3.1.38 SLQS_MAX_DYING_GASP_CFG_SMS_NUMBER_LENGTH . . . 1734
9.3.1.39 SPC_SIZE . . . 1734
9.3.1.40 UNIQUE_ID_LEN . . . 1734
9.3.2 Function Documentation . . . 1734
9.3.2.1 pack_dms_ActivateAutomatic . . . 1734
9.3.2.2 pack_dms_GetActivationState . . . 1734
9.3.2.3 pack_dms_GetBandCapability . . . 1735
9.3.2.4 pack_dms_GetCrashAction . . . 1735
9.3.2.5 pack_dms_GetCustFeature . . . 1735
9.3.2.6 pack_dms_GetCustFeaturesV2 . . . 1736
9.3.2.7 pack_dms_GetDeviceCap . . . 1736
9.3.2.8 pack_dms_GetDeviceCapabilities . . . 1737
9.3.2.9 pack_dms_GetDeviceHardwareRev . . . 1737
9.3.2.10 pack_dms_GetDeviceMfr . . . 1737
9.3.2.11 pack_dms_GetDeviceSerialNumbers . . . 1738
9.3.2.12 pack_dms_GetFirmwareInfo . . . 1738
9.3.2.13 pack_dms_GetFirmwareRevision . . . 1738
9.3.2.14 pack_dms_GetFirmwareRevisions . . . 1739
9.3.2.15 pack_dms_GetFSN . . . 1739
9.3.2.16 pack_dms_GetHardwareRevision . . . 1739
9.3.2.17 pack_dms_GetIMSI . . . 1740
9.3.2.18 pack_dms_GetManufacturer . . . 1740

9.3.2.19 pack_dms_GetModelID . . . 1740
9.3.2.20 pack_dms_GetNetworkTime . . . 1741
9.3.2.21 pack_dms_GetOfflineReason . . . 1741
9.3.2.22 pack_dms_GetPower . . . 1741
9.3.2.23 pack_dms_GetPRLVersion . . . 1742
9.3.2.24 pack_dms_GetSerialNumbers . . . 1742
9.3.2.25 pack_dms_GetUSBComp . . . 1743
9.3.2.26 pack_dms_GetVoiceNumber . . . 1743
9.3.2.27 pack_dms_ResetToFactoryDefaults . . . 1743
9.3.2.28 pack_dms_SetActivationStatusCallback . . . 1744
9.3.2.29 pack_dms_SetCrashAction . . . 1744
9.3.2.30 pack_dms_SetCustFeature . . . 1744
9.3.2.31 pack_dms_SetCustFeaturesV2 . . . 1745
9.3.2.32 pack_dms_SetEventReport . . . 1745
9.3.2.33 pack_dms_SetFirmwarePreference . . . 1745
9.3.2.34 pack_dms_SetIndicationRegister . . . 1746
9.3.2.35 pack_dms_SetPower . . . 1746
9.3.2.36 pack_dms_SetUSBComp . . . 1747
9.3.2.37 pack_dms_SLQSDmsSwiGetPCInfo . . . 1747
9.3.2.38 pack_dms_SLQSDmsSwiGetResetInfo . . . 1747
9.3.2.39 pack_dms_SLQSDmsSwiGetUimSelection . . . 1748
9.3.2.40 pack_dms_SLQSDmsSwiIndicationRegister . . . 1748
9.3.2.41 pack_dms_SLQSGetBandCapability . . . 1748
9.3.2.42 pack_dms_SLQSGetERIFile . . . 1749
9.3.2.43 pack_dms_SLQSGetPowerSaveModeConfig . . . 1749
9.3.2.44 pack_dms_SLQSSetPowerSaveModeConfig . . . 1750
9.3.2.45 pack_dms_SLQSSwiClearDyingGaspStatistics . . . 1750
9.3.2.46 pack_dms_SLQSSwiGetCrashInfo . . . 1750
9.3.2.47 pack_dms_SLQSSwiGetDyingGaspCfg . . . 1751
9.3.2.48 pack_dms_SLQSSwiGetDyingGaspStatistics . . . 1751
9.3.2.49 pack_dms_SLQSSwiGetFirmwareCurr . . . 1751
9.3.2.50 pack_dms_SLQSSwiGetFwUpdateStatus . . . 1752
9.3.2.51 pack_dms_SLQSSwiGetHostDevInfo . . . 1752
9.3.2.52 pack_dms_SLQSSwiGetOSInfo . . . 1752
9.3.2.53 pack_dms_SLQSSwiGetSerialNoExt . . . 1753
9.3.2.54 pack_dms_SLQSSwiSetDyingGaspCfg . . . 1753
9.3.2.55 pack_dms_SLQSSwiSetHostDevInfo . . . 1753
9.3.2.56 pack_dms_SLQSSwiSetOSInfo . . . 1754
9.3.2.57 pack_dms_SLQSUIMGetState . . . 1754
9.3.2.58 pack_dms_SwiSetEventReport . . . 1754

9.3.2.59 pack_dms_SwiUimSelect . . . 1755
9.3.2.60 pack_dms_UIMChangePIN . . . 1755
9.3.2.61 pack_dms_UIMGetControlKeyStatus . . . 1756
9.3.2.62 pack_dms_UIMGetICCID . . . 1756
9.3.2.63 pack_dms_UIMGetPINStatus . . . 1756
9.3.2.64 pack_dms_UIMSetControlKeyProtection . . . 1757
9.3.2.65 pack_dms_UIMSetPINProtection . . . 1757
9.3.2.66 pack_dms_UIMUnblockControlKey . . . 1757
9.3.2.67 pack_dms_UIMUnblockPIN . . . 1758
9.3.2.68 pack_dms_UIMVerifyPIN . . . 1758
9.3.2.69 pack_dms_ValidateSPC . . . 1759
9.3.2.70 unpack_dms_ActivateAutomatic . . . 1759
9.3.2.71 unpack_dms_GetActivationState . . . 1759
9.3.2.72 unpack_dms_GetBandCapability . . . 1760
9.3.2.73 unpack_dms_GetCrashAction . . . 1760
9.3.2.74 unpack_dms_GetCustFeature . . . 1760
9.3.2.75 unpack_dms_GetCustFeaturesV2 . . . 1761
9.3.2.76 unpack_dms_GetDeviceCap . . . 1761
9.3.2.77 unpack_dms_GetDeviceCapabilities . . . 1761
9.3.2.78 unpack_dms_GetDeviceHardwareRev . . . 1762
9.3.2.79 unpack_dms_GetDeviceMfr . . . 1762
9.3.2.80 unpack_dms_GetDeviceSerialNumbers . . . 1762
9.3.2.81 unpack_dms_GetFirmwareInfo . . . 1763
9.3.2.82 unpack_dms_GetFirmwareRevision . . . 1763
9.3.2.83 unpack_dms_GetFirmwareRevisions . . . 1764
9.3.2.84 unpack_dms_GetFSN . . . 1764
9.3.2.85 unpack_dms_GetHardwareRevision . . . 1764
9.3.2.86 unpack_dms_GetIMSI . . . 1765
9.3.2.87 unpack_dms_GetManufacturer . . . 1765
9.3.2.88 unpack_dms_GetModelID . . . 1765
9.3.2.89 unpack_dms_GetNetworkTime . . . 1766
9.3.2.90 unpack_dms_GetOfflineReason . . . 1766
9.3.2.91 unpack_dms_GetPower . . . 1766
9.3.2.92 unpack_dms_GetPRLVersion . . . 1767
9.3.2.93 unpack_dms_GetSerialNumbers . . . 1767
9.3.2.94 unpack_dms_GetUSBComp . . . 1767
9.3.2.95 unpack_dms_GetVoiceNumber . . . 1768
9.3.2.96 unpack_dms_PSMCfgChange_ind . . . 1768
9.3.2.97 unpack_dms_ResetToFactoryDefaults . . . 1768
9.3.2.98 unpack_dms_SetActivationStatusCallback . . . 1769

9.3.2.99 unpack_dms_SetCrashAction . . . 1769
9.3.2.100 unpack_dms_SetCustFeature . . . 1769
9.3.2.101 unpack_dms_SetCustFeaturesV2 . . . 1770
9.3.2.102 unpack_dms_SetEventReport . . . 1770
9.3.2.103 unpack_dms_SetEventReport_ind . . . 1771
9.3.2.104 unpack_dms_SetFirmwarePreference . . . 1771
9.3.2.105 unpack_dms_SetIndicationRegister . . . 1771
9.3.2.106 unpack_dms_SetPower . . . 1772
9.3.2.107 unpack_dms_SetUSBComp . . . 1772
9.3.2.108 unpack_dms_SLQSDmsSwiGetPCInfo . . . 1772
9.3.2.109 unpack_dms_SLQSDmsSwiGetResetInfo . . . 1773
9.3.2.110 unpack_dms_SLQSDmsSwiGetResetInfo_Ind . . . 1773
9.3.2.111 unpack_dms_SLQSDmsSwiGetUimSelection . . . 1773
9.3.2.112 unpack_dms_SLQSDmsSwiIndicationRegister . . . 1774
9.3.2.113 unpack_dms_SLQSGetBandCapability . . . 1774
9.3.2.114 unpack_dms_SLQSGetERIFile . . . 1775
9.3.2.115 unpack_dms_SLQSGetPowerSaveModeConfig . . . 1775
9.3.2.116 unpack_dms_SLQSSetPowerSaveModeConfig . . . 1775
9.3.2.117 unpack_dms_SLQSSwiClearDyingGaspStatistics . . . 1776
9.3.2.118 unpack_dms_SLQSSwiGetCrashInfo . . . 1776
9.3.2.119 unpack_dms_SLQSSwiGetDyingGaspCfg . . . 1776
9.3.2.120 unpack_dms_SLQSSwiGetDyingGaspStatistics . . . 1777
9.3.2.121 unpack_dms_SLQSSwiGetFirmwareCurr . . . 1777
9.3.2.122 unpack_dms_SLQSSwiGetFwUpdateStatus . . . 1777
9.3.2.123 unpack_dms_SLQSSwiGetHostDevInfo . . . 1778
9.3.2.124 unpack_dms_SLQSSwiGetOSInfo . . . 1778
9.3.2.125 unpack_dms_SLQSSwiGetSerialNoExt . . . 1778
9.3.2.126 unpack_dms_SLQSSwiSetDyingGaspCfg . . . 1779
9.3.2.127 unpack_dms_SLQSSwiSetHostDevInfo . . . 1779
9.3.2.128 unpack_dms_SLQSSwiSetOSInfo . . . 1779
9.3.2.129 unpack_dms_SLQSUIMGetState . . . 1780
9.3.2.130 unpack_dms_SwiEventReportCallBack_ind . . . 1780
9.3.2.131 unpack_dms_SwiSetEventReport . . . 1780
9.3.2.132 unpack_dms_SwiUimSelect . . . 1781
9.3.2.133 unpack_dms_UIMChangePIN . . . 1781
9.3.2.134 unpack_dms_UIMGetControlKeyStatus . . . 1781
9.3.2.135 unpack_dms_UIMGetICCID . . . 1782
9.3.2.136 unpack_dms_UIMGetPINStatus . . . 1782
9.3.2.137 unpack_dms_UIMSetControlKeyProtection . . . 1782
9.3.2.138 unpack_dms_UIMSetPINProtection . . . 1783

9.3.2.139 unpack_dms_UIMUnblockControlKey . . . 1783
9.3.2.140 unpack_dms_UIMUnblockPIN . . . 1784
9.3.2.141 unpack_dms_UIMVerifyPIN . . . 1784
9.3.2.142 unpack_dms_ValidateSPC . . . 1784
9.4 fms.h File Reference . . . 1785
9.4.1 Macro Definition Documentation . . . 1786
9.4.1.1 FMS_FW_PRI_BUILD_MATCH_LEN . . . 1786
9.4.1.2 FMS_GOBI_LISTENTRIES_MAX . . . 1786
9.4.1.3 FMS_GOBI_MBN_BUILD_ID_STR_LEN . . . 1786
9.4.1.4 FMS_GOBI_MBN_IMG_ID_SIZE . . . 1786
9.4.1.5 FMS_GOBI_MBN_IMG_ID_STR_LEN . . . 1786
9.4.1.6 FMS_IMAGE_ID_BUILD_ID_LEN . . . 1786
9.4.1.7 FMS_IMAGE_ID_IMG_ID_LEN . . . 1786
9.4.1.8 FMS_IMAGE_ID_MAX_ENTRIES . . . 1786
9.4.1.9 FMS_IMAGE_ID_PRI_IMGTYPE . . . 1786
9.4.1.10 FMS_MAX_IMAGE_ID_ELEMENT . . . 1786
9.4.1.11 FMS_MAX_IMAGE_PREFERENCE_IMAGE_SIZE . . . 1786
9.4.1.12 LITE_TOTAL_IMAGE_ID_STRING_SIZE . . . 1786
9.4.2 Function Documentation . . . 1786
9.4.2.1 GetValidFwPriCombinations . . . 1786
9.4.2.2 pack_fms_GetImagesPreference . . . 1787
9.4.2.3 pack_fms_GetStoredImages . . . 1787
9.4.2.4 pack_fms_SetImagesPreference . . . 1787
9.4.2.5 unpack_fms_GetImagesPreference . . . 1787
9.4.2.6 unpack_fms_GetStoredImages . . . 1787
9.4.2.7 unpack_fms_SetImagesPreference . . . 1788
9.5 loc.h File Reference . . . 1788
9.5.1 Macro Definition Documentation . . . 1792
9.5.1.1 LOC_UINT8_MAX_STRING_SZ . . . 1792
9.5.1.2 LOCEVENTMASKBATCHFULLNOTIFICATION . . . 1792
9.5.1.3 LOCEVENTMASKENGINESTATE . . . 1792
9.5.1.4 LOCEVENTMASKFIXSESSIONSTATE . . . 1792
9.5.1.5 LOCEVENTMASKGEOFENCEBATCHBREACHNOTIFICATION . . . 1792
9.5.1.6 LOCEVENTMASKGEOFENCEBREACHNOTIFICATION . . . 1792
9.5.1.7 LOCEVENTMASKGEOFENCEGENALERT . . . 1792
9.5.1.8 LOCEVENTMASKGNSSMEASUREMENTREPORT . . . 1792
9.5.1.9 LOCEVENTMASKGNSSSVINFO . . . 1792
9.5.1.10 LOCEVENTMASKINJECTPOSITIONREQ . . . 1793
9.5.1.11 LOCEVENTMASKINJECTPREDICTEDORBITSREQ . . . 1793
9.5.1.12 LOCEVENTMASKINJECTTIMEREQ . . . 1793

9.5.1.13 LOCEVENTMASKINJECTWIFIAPDATAREQ . . . 1793
9.5.1.14 LOCEVENTMASKINVALIDVALUE . . . 1793
9.5.1.15 LOCEVENTMASKLIVEBATCHEDPOSITIONREPORT . . . 1793
9.5.1.16 LOCEVENTMASKLOCATIONSERVERCONNECTIONREQ . . . 1793
9.5.1.17 LOCEVENTMASKMOTIONDATACONTROL . . . 1793
9.5.1.18 LOCEVENTMASKNIGEOFENCENOTIFICATION . . . 1793
9.5.1.19 LOCEVENTMASKNINOTIFYVERIFYREQ . . . 1793
9.5.1.20 LOCEVENTMASKNMEA . . . 1793
9.5.1.21 LOCEVENTMASKPEDOMETERCONTROL . . . 1794
9.5.1.22 LOCEVENTMASKPOSITIONREPORT . . . 1794
9.5.1.23 LOCEVENTMASKSENSORSTREAMINGREADYSTATUS . . . 1794
9.5.1.24 LOCEVENTMASKSETSPISTREAMINGREPORT . . . 1794
9.5.1.25 LOCEVENTMASKTIMESYNCREQ . . . 1794
9.5.1.26 LOCEVENTMASKVEHICLEDATAREADYSTATUS . . . 1794
9.5.1.27 LOCEVENTMASKWIFIREQ . . . 1794
9.5.1.28 MAX_LOC_NMEA_STR_LEN . . . 1794
9.5.1.29 MAX_SENSOR_DATA_LEN . . . 1794
9.5.1.30 MAX_TEMP_DATA_LEN . . . 1794
9.5.2 Typedef Documentation . . . 1794
9.5.2.1 unpack_loc_DeleteAssistData_t . . . 1794
9.5.2.2 unpack_loc_SLQSLOCGetServer_t . . . 1794
9.5.2.3 unpack_loc_SLQSLOCInjectPosition_t . . . 1794
9.5.2.4 unpack_loc_SLQSLOCInjectSensorData_t . . . 1794
9.5.2.5 unpack_loc_SLQSLOCInjectUTCTime_t . . . 1794
9.5.2.6 unpack_loc_SLQSLOCSetCradleMountConfig_t . . . 1794
9.5.3 Enumeration Type Documentation . . . 1795
9.5.3.1 anonymous enum . . . 1795
9.5.4 Function Documentation . . . 1795
9.5.4.1 pack_loc_DeleteAssistData . . . 1795
9.5.4.2 pack_loc_EventRegister . . . 1795
9.5.4.3 pack_loc_SetExtPowerState . . . 1796
9.5.4.4 pack_loc_SetOperationMode . . . 1796
9.5.4.5 pack_loc_SLQSLOCGetBestAvailPos . . . 1796
9.5.4.6 pack_loc_SLQSLOCGetOpMode . . . 1797
9.5.4.7 pack_loc_SLQSLOCGetServer . . . 1797
9.5.4.8 pack_loc_SLQSLOCInjectPosition . . . 1798
9.5.4.9 pack_loc_SLQSLOCInjectSensorData . . . 1798
9.5.4.10 pack_loc_SLQSLOCInjectUTCTime . . . 1798
9.5.4.11 pack_loc_SLQSLOCSetCradleMountConfig . . . 1799
9.5.4.12 pack_loc_SLQSLOCSetServer . . . 1799

9.5.4.13 pack_loc_Start . . . 1800
9.5.4.14 pack_loc_Stop . . . 1800
9.5.4.15 unpack_loc_BestAvailPos_Ind . . . 1800
9.5.4.16 unpack_loc_CradleMountCallback_Ind . . . 1801
9.5.4.17 unpack_loc_DeleteAssistData . . . 1801
9.5.4.18 unpack_loc_DeleteAssistData_Ind . . . 1801
9.5.4.19 unpack_loc_EngineState_Ind . . . 1802
9.5.4.20 unpack_loc_EventNMEA_Ind . . . 1802
9.5.4.21 unpack_loc_EventRegister . . . 1802
9.5.4.22 unpack_loc_EventTimeSyncCallback_Ind . . . 1803
9.5.4.23 unpack_loc_GetOpMode_Ind . . . 1803
9.5.4.24 unpack_loc_GetServer_Ind . . . 1803
9.5.4.25 unpack_loc_GnssSvInfo_Ind . . . 1804
9.5.4.26 unpack_loc_InjectPositionCallback_Ind . . . 1804
9.5.4.27 unpack_loc_InjectSensorDataCallback_Ind . . . 1804
9.5.4.28 unpack_loc_InjectTimeSyncDataCallback_Ind . . . 1805
9.5.4.29 unpack_loc_InjectUTCTimeCallback_Ind . . . 1805
9.5.4.30 unpack_loc_PositionRpt_Ind . . . 1805
9.5.4.31 unpack_loc_SensorStreamingCallback_Ind . . . 1806
9.5.4.32 unpack_loc_SetExtPowerConfig_Ind . . . 1806
9.5.4.33 unpack_loc_SetExtPowerState . . . 1806
9.5.4.34 unpack_loc_SetOperationMode . . . 1807
9.5.4.35 unpack_loc_SetOperationMode_Ind . . . 1807
9.5.4.36 unpack_loc_SetServer_Ind . . . 1807
9.5.4.37 unpack_loc_SLQSLOCGetBestAvailPos . . . 1808
9.5.4.38 unpack_loc_SLQSLOCGetOpMode . . . 1808
9.5.4.39 unpack_loc_SLQSLOCGetServer . . . 1808
9.5.4.40 unpack_loc_SLQSLOCInjectPosition . . . 1809
9.5.4.41 unpack_loc_SLQSLOCInjectSensorData . . . 1809
9.5.4.42 unpack_loc_SLQSLOCInjectUTCTime . . . 1809
9.5.4.43 unpack_loc_SLQSLOCSetCradleMountConfig . . . 1810
9.5.4.44 unpack_loc_SLQSLOCSetServer . . . 1810
9.5.4.45 unpack_loc_Start . . . 1810
9.5.4.46 unpack_loc_Stop . . . 1811
9.6 nas.h File Reference . . . 1811
9.6.1 Macro Definition Documentation . . . 1823
9.6.1.1 LITE_NW_SCAN_LTE_OP_MODE_MAX_LENGTH . . . 1823
9.6.1.2 NAS_IMSI_M_S1_LENGTH . . . 1823
9.6.1.3 NAS_IMSI_M_S2_LENGTH . . . 1823
9.6.1.4 NAS_MAX_DESCRIPTION_LENGTH . . . 1823

9.6.1.5 NAS_MAX_NUM_NETWORKS . . . 1823
9.6.1.6 NAS_MAX_PHY_CA_AGG_SCELL_ARRRY_SIZE . . . 1823
9.6.1.7 NAS_MAX_SCC_RX_INFO_INSTANCES . . . 1823
9.6.1.8 NAS_MAX_SLQS_NAS_PCI_INFO_LENGTH . . . 1823
9.6.1.9 NAS_MAX_SLQS_NAS_PCI_INFO_PLMN_LENGTH . . . 1823
9.6.1.10 NAS_MCC_MNC_INST_LENGTH . . . 1823
9.6.1.11 NAS_NAM_NAME_LENGTH . . . 1823
9.6.1.12 NAS_OTA_MESSAGE_MAX_BUF_SIZE . . . 1823
9.6.1.13 NAS_PLMN_LENGTH . . . 1823
9.6.1.14 NAS_SERVING_SYSTEM_INFO_MAX_RADIO_INTERFACE_LIST . . . 1823
9.6.2 Typedef Documentation . . . 1823
9.6.2.1 nas_LTEBandPrefExtTlv . . . 1823
9.6.2.2 nas_NR5gBandPrefTlv . . . 1823
9.6.2.3 unpack_nas_InitiateDomainAttach_t . . . 1824
9.6.2.4 unpack_nas_SetACCOLC_t . . . 1824
9.6.2.5 unpack_nas_SetCDMANetworkParameters_t . . . 1824
9.6.2.6 unpack_nas_SetLURejectCallback_t . . . 1824
9.6.2.7 unpack_nas_SetRFInfoCallback_t . . . 1824
9.6.2.8 unpack_nas_SLQSConfigSigInfo_t . . . 1824
9.6.2.9 unpack_nas_SLQSInitiateNetworkRegistration_t . . . 1824
9.6.2.10 unpack_nas_SLQSNasConfigSigInfo2_t . . . 1824
9.6.2.11 unpack_nas_SLQSNasIndicationRegisterExt_t . . . 1824
9.6.2.12 unpack_nas_SLQSNASSeteDRXParams_t . . . 1824
9.6.2.13 unpack_nas_SLQSNasSwiIndicationRegister_t . . . 1824
9.6.2.14 unpack_nas_SLQSNASSwiSetChannelLock_t . . . 1824
9.6.2.15 unpack_nas_SLQSSetBandPreference_t . . . 1824
9.6.2.16 unpack_nas_SLQSSetSignalStrengthsCallback_t . . . 1824
9.6.2.17 unpack_nas_SLQSSetSysSelectionPref_t . . . 1824
9.6.2.18 unpack_nas_SLQSSetSysSelectionPrefExt_t . . . 1824
9.6.2.19 unpack_nas_SLQSSwiPSDetach_t . . . 1824
9.6.3 Enumeration Type Documentation . . . 1824
9.6.3.1 LITE_TYPE_OF_SERVICE_DOMAIN . . . 1824
9.6.3.2 LITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND . . . 1824
9.6.3.3 LITEQMI_NAS_LTE_CPHY_CA_BW_NRB . . . 1826
9.6.3.4 LITEQMI_NAS_LTE_CPHY_SCELL_STATE . . . 1826
9.6.3.5 NAS_LTE_CPHY_CA_BW_NRB_LITE . . . 1826
9.6.3.6 NAS_LTE_CPHY_SCELL_STATE_LITE . . . 1826
9.6.4 Function Documentation . . . 1826
9.6.4.1 pack_nas_GetACCOLC . . . 1826
9.6.4.2 pack_nas_GetANAAAAuthenticationStatus . . . 1827

9.6.4.3 pack_nas_GetCDMANetworkParameters . . . 1827
9.6.4.4 pack_nas_GetHomeNetwork . . . 1827
9.6.4.5 pack_nas_GetHomeNetwork3GPP2 . . . 1828
9.6.4.6 pack_nas_GetNetworkPreference . . . 1828
9.6.4.7 pack_nas_GetRFInfo . . . 1828
9.6.4.8 pack_nas_GetServingNetwork . . . 1829
9.6.4.9 pack_nas_GetServingNetworkCapabilities . . . 1829
9.6.4.10 pack_nas_GetSignalStrengths . . . 1829
9.6.4.11 pack_nas_InitiateDomainAttach . . . 1830
9.6.4.12 pack_nas_PerformNetworkScan . . . 1830
9.6.4.13 pack_nas_PerformNetworkScanPCI . . . 1830
9.6.4.14 pack_nas_SetACCOLC . . . 1831
9.6.4.15 pack_nas_SetCDMANetworkParameters . . . 1831
9.6.4.16 pack_nas_SetLURejectCallback . . . 1831
9.6.4.17 pack_nas_SetNetworkPreference . . . 1832
9.6.4.18 pack_nas_SetRFInfoCallback . . . 1832
9.6.4.19 pack_nas_SLQSConfigSigInfo . . . 1832
9.6.4.20 pack_nas_SLQSGetErrorRate . . . 1833
9.6.4.21 pack_nas_SlqsGetLTECphyCAInfo . . . 1833
9.6.4.22 pack_nas_SLQSGetNetworkTime . . . 1833
9.6.4.23 pack_nas_SLQSGetOperatorNameData . . . 1834
9.6.4.24 pack_nas_SLQSGetPLMNName . . . 1834
9.6.4.25 pack_nas_SLQSGetServingSystem . . . 1834
9.6.4.26 pack_nas_SLQSGetSignalStrength . . . 1835
9.6.4.27 pack_nas_SLQSGetSysInfo . . . 1835
9.6.4.28 pack_nas_SLQSGetSysSelectionPref . . . 1835
9.6.4.29 pack_nas_SLQSGetSysSelectionPrefExt . . . 1836
9.6.4.30 pack_nas_SLQSInitiateNetworkRegistration . . . 1836
9.6.4.31 pack_nas_SLQSNasConfigSigInfo2 . . . 1836
9.6.4.32 pack_nas_SLQSNasGet3GPP2Subscription . . . 1837
9.6.4.33 pack_nas_SLQSNasGetCellLocationInfo . . . 1837
9.6.4.34 pack_nas_SLQSNASGeteDRXParams . . . 1838
9.6.4.35 pack_nas_SLQSNASGeteDRXParamsExt . . . 1838
9.6.4.36 pack_nas_SLQSNASGetForbiddenNetworks . . . 1838
9.6.4.37 pack_nas_SLQSNasGetHDRColorCode . . . 1839
9.6.4.38 pack_nas_SLQSNasGetRFInfo . . . 1839
9.6.4.39 pack_nas_SLQSNasGetSigInfo . . . 1839
9.6.4.40 pack_nas_SLQSNasGetTxRxInfo . . . 1840
9.6.4.41 pack_nas_SLQSNasIndicationRegisterExt . . . 1840
9.6.4.42 pack_nas_SLQSNASSeteDRXParams . . . 1840

9.6.4.43 pack_nas_SLQSNASSwiGetChannelLock . . . 1841
9.6.4.44 pack_nas_SLQSNasSwiIndicationRegister . . . 1841
9.6.4.45 pack_nas_SLQSNasSwiModemStatus . . . 1841
9.6.4.46 pack_nas_SLQSNASSwiSetChannelLock . . . 1842
9.6.4.47 pack_nas_SLQSSetBandPreference . . . 1842
9.6.4.48 pack_nas_SLQSSetSignalStrengthsCallback . . . 1842
9.6.4.49 pack_nas_SLQSSetSysSelectionPref . . . 1843
9.6.4.50 pack_nas_SLQSSetSysSelectionPrefExt . . . 1843
9.6.4.51 pack_nas_SLQSSwiGetHDRPersonality . . . 1844
9.6.4.52 pack_nas_SLQSSwiGetHDRProtSubtype . . . 1844
9.6.4.53 pack_nas_SLQSSwiGetHRPDStats . . . 1844
9.6.4.54 pack_nas_SLQSSwiGetLteCQI . . . 1845
9.6.4.55 pack_nas_SLQSSwiGetLteSccRxInfo . . . 1845
9.6.4.56 pack_nas_SLQSSwiNetworkDebug . . . 1845
9.6.4.57 pack_nas_SLQSSwiPSDetach . . . 1846
9.6.4.58 unpack_nas_GetACCOLC . . . 1846
9.6.4.59 unpack_nas_GetANAAAAuthenticationStatus . . . 1846
9.6.4.60 unpack_nas_GetCDMANetworkParameters . . . 1847
9.6.4.61 unpack_nas_GetHomeNetwork . . . 1847
9.6.4.62 unpack_nas_GetHomeNetwork3GPP2 . . . 1847
9.6.4.63 unpack_nas_GetNetworkPreference . . . 1848
9.6.4.64 unpack_nas_GetRFInfo . . . 1848
9.6.4.65 unpack_nas_GetServingNetwork . . . 1848
9.6.4.66 unpack_nas_GetServingNetworkCapabilities . . . 1849
9.6.4.67 unpack_nas_GetSignalStrengths . . . 1849
9.6.4.68 unpack_nas_InitiateDomainAttach . . . 1850
9.6.4.69 unpack_nas_PerformNetworkScan . . . 1850
9.6.4.70 unpack_nas_SetACCOLC . . . 1850
9.6.4.71 unpack_nas_SetCDMANetworkParameters . . . 1851
9.6.4.72 unpack_nas_SetDataCapabilitiesCallback_ind . . . 1851
9.6.4.73 unpack_nas_SetEventReportInd . . . 1851
9.6.4.74 unpack_nas_SetLURejectCallback . . . 1852
9.6.4.75 unpack_nas_SetNasLTECphyCaIndCallback_ind . . . 1852
9.6.4.76 unpack_nas_SetNetworkPreference . . . 1852
9.6.4.77 unpack_nas_SetRFInfoCallback . . . 1853
9.6.4.78 unpack_nas_SetRoamingIndicatorCallback_ind . . . 1853
9.6.4.79 unpack_nas_SetServingSystemCallback_ind . . . 1853
9.6.4.80 unpack_nas_SLQSConfigSigInfo . . . 1854
9.6.4.81 unpack_nas_SLQSGetErrorRate . . . 1854
9.6.4.82 unpack_nas_SlqsGetLTECphyCAInfo . . . 1854

9.6.4.83 unpack_nas_SLQSGetNetworkTime . . . 1855
9.6.4.84 unpack_nas_SLQSGetOperatorNameData . . . 1855
9.6.4.85 unpack_nas_SLQSGetPLMNName . . . 1855
9.6.4.86 unpack_nas_SLQSGetServingSystem . . . 1856
9.6.4.87 unpack_nas_SLQSGetSignalStrength . . . 1856
9.6.4.88 unpack_nas_SLQSGetSysInfo . . . 1856
9.6.4.89 unpack_nas_SLQSGetSysSelectionPref . . . 1857
9.6.4.90 unpack_nas_SLQSGetSysSelectionPrefExt . . . 1857
9.6.4.91 unpack_nas_SLQSInitiateNetworkRegistration . . . 1858
9.6.4.92 unpack_nas_SLQSNasConfigSigInfo2 . . . 1858
9.6.4.93 unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind . . . 1858
9.6.4.94 unpack_nas_SLQSNasGet3GPP2Subscription . . . 1859
9.6.4.95 unpack_nas_SLQSNasGetCellLocationInfo . . . 1859
9.6.4.96 unpack_nas_SLQSNASGeteDRXParams . . . 1859
9.6.4.97 unpack_nas_SLQSNASGeteDRXParamsExt . . . 1860
9.6.4.98 unpack_nas_SLQSNASGetForbiddenNetworks . . . 1860
9.6.4.99 unpack_nas_SLQSNasGetHDRColorCode . . . 1860
9.6.4.100 unpack_nas_SLQSNasGetRFInfo . . . 1861
9.6.4.101 unpack_nas_SLQSNasGetSigInfo . . . 1861
9.6.4.102 unpack_nas_SLQSNasGetTxRxInfo . . . 1861
9.6.4.103 unpack_nas_SLQSNasIndicationRegisterExt . . . 1862
9.6.4.104 unpack_nas_SLQSNasNetworkRejectCallback_Ind . . . 1862
9.6.4.105 unpack_nas_SLQSNasNetworkTimeCallBack_ind . . . 1863
9.6.4.106 unpack_nas_SLQSNASSeteDRXParams . . . 1863
9.6.4.107 unpack_nas_SLQSNasSigInfoCallback_ind . . . 1863
9.6.4.108 unpack_nas_SLQSNASSwiGetChannelLock . . . 1864
9.6.4.109 unpack_nas_SLQSNasSwiIndicationRegister . . . 1864
9.6.4.110 unpack_nas_SLQSNasSwiModemStatus . . . 1864
9.6.4.111 unpack_nas_SLQSNasSwiOTAMessageCallback_ind . . . 1865
9.6.4.112 unpack_nas_SLQSNASSwiSetChannelLock . . . 1865
9.6.4.113 unpack_nas_SLQSNasSysInfoCallback_ind . . . 1865
9.6.4.114 unpack_nas_SLQSNasTimerCallback_ind . . . 1866
9.6.4.115 unpack_nas_SLQSSetBandPreference . . . 1866
9.6.4.116 unpack_nas_SLQSSetSignalStrengthsCallback . . . 1866
9.6.4.117 unpack_nas_SLQSSetSysSelectionPref . . . 1867
9.6.4.118 unpack_nas_SLQSSetSysSelectionPrefCallBack_ind . . . 1867
9.6.4.119 unpack_nas_SLQSSetSysSelectionPrefExt . . . 1867
9.6.4.120 unpack_nas_SLQSSwiGetHDRPersonality . . . 1868
9.6.4.121 unpack_nas_SLQSSwiGetHDRProtSubtype . . . 1868
9.6.4.122 unpack_nas_SLQSSwiGetHRPDStats . . . 1868

9.6.4.123 unpack_nas_SLQSSwiGetLteCQI . . . 1869
9.6.4.124 unpack_nas_SLQSSwiGetLteSccRxInfo . . . 1869
9.6.4.125 unpack_nas_SLQSSwiHDRPersonalityCallback_Ind . . . 1869
9.6.4.126 unpack_nas_SLQSSwiNetworkDebug . . . 1870
9.6.4.127 unpack_nas_SLQSSwiPSDetach . . . 1870
9.6.4.128 unpack_nas_SLQSSwiRandIndicatorCallback_Ind . . . 1870
9.6.4.129 unpack_valid_nas_GetCDMANetworkParameters . . . 1871
9.6.4.130 unpack_valid_nas_SLQSGetServingSystem . . . 1871
9.6.4.131 unpack_valid_nas_SLQSGetSignalStrength . . . 1872
9.6.4.132 unpack_valid_nas_SLQSNasGetSigInfo . . . 1873
9.7 pds.h File Reference . . . 1873
9.7.1 Typedef Documentation . . . 1876
9.7.1.1 unpack_pds_ForceXTRADownload_t . . . 1876
9.7.1.2 unpack_pds_PDSInjectTimeReference_t . . . 1876
9.7.1.3 unpack_pds_ResetPDSData_t . . . 1876
9.7.1.4 unpack_pds_SetEventReportCallback_t . . . 1876
9.7.1.5 unpack_pds_SetPDSDefaults_t . . . 1876
9.7.1.6 unpack_pds_SetPDSState_t . . . 1876
9.7.1.7 unpack_pds_SetPortAutomaticTracking_t . . . 1876
9.7.1.8 unpack_pds_SetServiceAutomaticTracking_t . . . 1876
9.7.1.9 unpack_pds_SetXTRAAutomaticDownload_t . . . 1876
9.7.1.10 unpack_pds_SetXTRANetwork_t . . . 1876
9.7.1.11 unpack_pds_SLQSPDSDeterminePosition_t . . . 1876
9.7.1.12 unpack_pds_SLQSPDSInjectAbsoluteTimeReference_t . . . 1876
9.7.1.13 unpack_pds_SLQSPDSInjectPositionData_t . . . 1876
9.7.1.14 unpack_pds_SLQSSetAGPSConfig_t . . . 1876
9.7.1.15 unpack_pds_SLQSSetPositionMethodState_t . . . 1876
9.7.1.16 unpack_pds_StartPDSTrackingSessionExt_t . . . 1876
9.7.1.17 unpack_pds_StopPDSTrackingSession_t . . . 1876
9.7.2 Function Documentation . . . 1876
9.7.2.1 pack_pds_ForceXTRADownload . . . 1877
9.7.2.2 pack_pds_GetPDSDefaults . . . 1877
9.7.2.3 pack_pds_GetPDSState . . . 1877
9.7.2.4 pack_pds_GetPortAutomaticTracking . . . 1878
9.7.2.5 pack_pds_GetServiceAutomaticTracking . . . 1878
9.7.2.6 pack_pds_GetXTRAAutomaticDownload . . . 1878
9.7.2.7 pack_pds_GetXTRANetwork . . . 1879
9.7.2.8 pack_pds_GetXTRAValidity . . . 1879
9.7.2.9 pack_pds_PDSInjectTimeReference . . . 1879
9.7.2.10 pack_pds_ResetPDSData . . . 1880

9.7.2.11 pack_pds_SetEventReportCallback . . . 1880
9.7.2.12 pack_pds_SetPDSDefaults . . . 1880
9.7.2.13 pack_pds_SetPDSState . . . 1881
9.7.2.14 pack_pds_SetPortAutomaticTracking . . . 1881
9.7.2.15 pack_pds_SetServiceAutomaticTracking . . . 1881
9.7.2.16 pack_pds_SetXTRAAutomaticDownload . . . 1882
9.7.2.17 pack_pds_SetXTRANetwork . . . 1882
9.7.2.18 pack_pds_SLQSGetAGPSConfig . . . 1883
9.7.2.19 pack_pds_SLQSGetGPSStateInfo . . . 1883
9.7.2.20 pack_pds_SLQSPDSDeterminePosition . . . 1883
9.7.2.21 pack_pds_SLQSPDSInjectAbsoluteTimeReference . . . 1884
9.7.2.22 pack_pds_SLQSPDSInjectPositionData . . . 1884
9.7.2.23 pack_pds_SLQSSetAGPSConfig . . . 1884
9.7.2.24 pack_pds_SLQSSetPositionMethodState . . . 1885
9.7.2.25 pack_pds_StartPDSTrackingSessionExt . . . 1885
9.7.2.26 pack_pds_StopPDSTrackingSession . . . 1885
9.7.2.27 unpack_pds_ForceXTRADownload . . . 1886
9.7.2.28 unpack_pds_GetPDSDefaults . . . 1886
9.7.2.29 unpack_pds_GetPDSState . . . 1886
9.7.2.30 unpack_pds_GetPortAutomaticTracking . . . 1887
9.7.2.31 unpack_pds_GetServiceAutomaticTracking . . . 1887
9.7.2.32 unpack_pds_GetXTRAAutomaticDownload . . . 1888
9.7.2.33 unpack_pds_GetXTRANetwork . . . 1888
9.7.2.34 unpack_pds_GetXTRAValidity . . . 1888
9.7.2.35 unpack_pds_PDSInjectTimeReference . . . 1889
9.7.2.36 unpack_pds_ResetPDSData . . . 1889
9.7.2.37 unpack_pds_SetEventReport_Ind . . . 1889
9.7.2.38 unpack_pds_SetEventReportCallback . . . 1890
9.7.2.39 unpack_pds_SetPDSDefaults . . . 1890
9.7.2.40 unpack_pds_SetPDSState . . . 1890
9.7.2.41 unpack_pds_SetPdsState_Ind . . . 1891
9.7.2.42 unpack_pds_SetPortAutomaticTracking . . . 1891
9.7.2.43 unpack_pds_SetServiceAutomaticTracking . . . 1891
9.7.2.44 unpack_pds_SetXTRAAutomaticDownload . . . 1892
9.7.2.45 unpack_pds_SetXTRANetwork . . . 1892
9.7.2.46 unpack_pds_SLQSGetAGPSConfig . . . 1892
9.7.2.47 unpack_pds_SLQSGetGPSStateInfo . . . 1893
9.7.2.48 unpack_pds_SLQSPDSDeterminePosition . . . 1893
9.7.2.49 unpack_pds_SLQSPDSInjectAbsoluteTimeReference . . . 1893
9.7.2.50 unpack_pds_SLQSPDSInjectPositionData . . . 1894

9.7.2.51 unpack_pds_SLQSSetAGPSConfig . . . 1894
9.7.2.52 unpack_pds_SLQSSetPositionMethodState . . . 1894
9.7.2.53 unpack_pds_StartPDSTrackingSessionExt . . . 1895
9.7.2.54 unpack_pds_StopPDSTrackingSession . . . 1895
9.8 qaCbkCatEventReportInd.h File Reference . . . 1895
9.8.1 Macro Definition Documentation . . . 1896
9.8.1.1 QMI_CAN_COMMON_EVENT_TLV_NUMBER . . . 1896
9.8.1.2 QMI_MAX_CAT_EVENT_DATA_LENGTH . . . 1896
9.8.2 Enumeration Type Documentation . . . 1896
9.8.2.1 eQMI_CAT_EVENT_REPORT_IND_TLV . . . 1896
9.8.2.2 eQMI_CAT_EVENT_REPORT_IND_TLV_LENGTH . . . 1897
9.8.3 Function Documentation . . . 1897
9.8.3.1 UpkQmiCbkCatEventReportInd . . . 1897
9.9 qaCbkSwiOmaDmEventReportInd.h File Reference . . . 1897
9.9.1 Macro Definition Documentation . . . 1898
9.9.1.1 QMI_SWIOMA_DM_CONFIG . . . 1898
9.9.1.2 QMI_SWIOMA_DM_FOTA . . . 1898
9.9.1.3 QMI_SWIOMA_DM_NOT . . . 1898
9.9.2 Enumeration Type Documentation . . . 1898
9.9.2.1 eQMI_SWIOMA_DM_EVENT_REPORT_IND . . . 1898
9.9.3 Function Documentation . . . 1898
9.9.3.1 UpkQmiCbkSwiOmaDmEventReportInd . . . 1898
9.9.3.2 UpkQmiCbkSwiOmaDmEventReportIndExt . . . 1898
9.10 qaGobiApiAudio.h File Reference . . . 1898
9.10.1 Detailed Description . . . 1899
9.10.2 Function Documentation . . . 1899
9.10.2.1 SLQSGetAudioPathConfig . . . 1899
9.10.2.2 SLQSGetAudioProfile . . . 1899
9.10.2.3 SLQSGetAudioVolTLBConfig . . . 1900
9.10.2.4 SLQSSetAudioPathConfig . . . 1900
9.10.2.5 SLQSSetAudioProfile . . . 1901
9.10.2.6 SLQSSetAudioVolTLBConfig . . . 1901
9.11 qaGobiApiCat.h File Reference . . . 1902
9.11.1 Detailed Description . . . 1902
9.11.2 Function Documentation . . . 1902
9.11.2.1 CATSendEnvelopeCommand . . . 1902
9.11.2.2 CATSendTerminalResponse . . . 1903
9.12 qaGobiApiCbk.h File Reference . . . 1903
9.12.1 Detailed Description . . . 1912
9.12.2 Macro Definition Documentation . . . 1912

9.12.2.1 CBK_DISABLE_EVENT . . . 1912
9.12.2.2 CBK_ENABLE_EVENT . . . 1912
9.12.2.3 CBK_NOCHANGE . . . 1912
9.12.2.4 DEREGISTER_EVENT . . . 1912
9.12.2.5 DEREGISTER_SRV . . . 1912
9.12.2.6 DHCP_MAX_NUM_OPTIONS . . . 1912
9.12.2.7 DHCP_OPTION_DATA_BUF_SIZE . . . 1912
9.12.2.8 EVENT_MASK_CARD . . . 1912
9.12.2.9 EVENT_MASK_DEREGISTER_ALL . . . 1912
9.12.2.10 EVENT_MASK_PHY_SLOT_STATUS . . . 1912
9.12.2.11 FIRST_INSTANCE . . . 1912
9.12.2.12 INVALID_INSTACNE . . . 1912
9.12.2.13 IPV4 . . . 1912
9.12.2.14 IPV4V6 . . . 1912
9.12.2.15 IPV6 . . . 1913
9.12.2.16 LOC_EVENT_MASK_ENG_STATE . . . 1913
9.12.2.17 LOC_EVENT_MASK_GNSS_SV_INFO . . . 1913
9.12.2.18 LOC_EVENT_MASK_INJECT_TIME . . . 1913
9.12.2.19 LOC_EVENT_MASK_NMEA . . . 1913
9.12.2.20 LOC_EVENT_MASK_SENSOR_STREAM . . . 1913
9.12.2.21 LOC_EVENT_MASK_TIME_SYNC . . . 1913
9.12.2.22 LOC_EVENT_POSITION_REPORT . . . 1913
9.12.2.23 MAX_MITIGATION_DEV_ID_LEN . . . 1913
9.12.2.24 MAX_NMEA_STR_LEN . . . 1913
9.12.2.25 MAX_NO_OF_APPLICATIONS . . . 1913
9.12.2.26 MAX_NO_OF_CALLS . . . 1913
9.12.2.27 MAX_NO_OF_FILES . . . 1913
9.12.2.28 MAX_NO_OF_SLOTS . . . 1913
9.12.2.29 MAX_NO_OF_UUSINFO . . . 1913
9.12.2.30 MAX_PATH_LENGTH . . . 1913
9.12.2.31 MAX_RADIO_INTERFACE_LIST . . . 1913
9.12.2.32 MAX_URL_ADDR_STR_LEN . . . 1913
9.12.2.33 MAXUSSDLENGTH . . . 1913
9.12.2.34 NAS_SRV . . . 1913
9.12.2.35 NUM_OF_SET . . . 1913
9.12.2.36 PDS_SRV . . . 1913
9.12.2.37 QMI_ETWS_MAX_PAYLOAD_LENGTH . . . 1913
9.12.2.38 QMI_MAX_VOICE_NUMBER_LENGTH . . . 1913
9.12.2.39 QMI_WMS_MAX_PAYLOAD_LENGTH . . . 1913
9.12.2.40 REGISTER_EVENT . . . 1913

9.12.2.41 REGISTER_SRV . . . 1913
9.12.2.42 SECOND_INSTANCE . . . 1913
9.12.2.43 SIGSTRENGTH_THRESHOLD_ARR_SZ . . . 1914
9.12.2.44 THIRD_INSTANCE . . . 1914
9.12.2.45 USSD_DCS_8BIT . . . 1914
9.12.2.46 USSD_DCS_ASCII . . . 1914
9.12.2.47 USSD_DCS_UCS2 . . . 1914
9.12.2.48 VOICE_SRV . . . 1914
9.12.2.49 WDS_SRV . . . 1914
9.12.3 Typedef Documentation . . . 1914
9.12.3.1 accelAcceptReady . . . 1914
9.12.3.2 accelTempAcceptReady . . . 1914
9.12.3.3 eDevState . . . 1915
9.12.3.4 eSMSEventType . . . 1915
9.12.3.5 gpsTime . . . 1915
9.12.3.6 gyroAcceptReady . . . 1915
9.12.3.7 gyroTempAcceptReady . . . 1916
9.12.3.8 LteNasReleaseInfo . . . 1916
9.12.3.9 modemTempNotification . . . 1917
9.12.3.10 modemUIMStatusNotification . . . 1917
9.12.3.11 packetSrvStatus . . . 1918
9.12.3.12 precisionDilution . . . 1919
9.12.3.13 ResetInfoNotification . . . 1919
9.12.3.14 sensorDataUsage . . . 1920
9.12.3.15 sessionInformation . . . 1920
9.12.3.16 sessionInformationExt . . . 1921
9.12.3.17 SMSAsyncRawSend . . . 1921
9.12.3.18 SMSCAddressInfo . . . 1922
9.12.3.19 SMSEtwsMessageInfo . . . 1922
9.12.3.20 SMSEtwsPlmnInfo . . . 1922
9.12.3.21 SMSEventInfo . . . 1922
9.12.3.22 SMSMessageModeInfo . . . 1923
9.12.3.23 SMSMTMessageInfo . . . 1923
9.12.3.24 SMSOnIMSInfo . . . 1924
9.12.3.25 SMSTransferRouteMTMessageInfo . . . 1924
9.12.3.26 svUsedforFix . . . 1924
9.12.3.27 SwiAvmsEventInd . . . 1925
9.12.3.28 SwiOTAMsg . . . 1925
9.12.3.29 tFNActivationStatus . . . 1925
9.12.3.30 tFNAllCallStatus . . . 1926

9.12.3.31 tFNASwiLTECphyCallInfo . . . 1926
9.12.3.32 tFNASwiOTAMsg . . . 1926
9.12.3.33 tFNAsyncRawSend . . . 1926
9.12.3.34 tFNBandPreference . . . 1927
9.12.3.35 tFNBestAvailPos . . . 1929
9.12.3.36 tFNCATEvent . . . 1929
9.12.3.37 tFNCbkUimSlotStatusChangeInd . . . 1929
9.12.3.38 tFNDataCapabilities . . . 1930
9.12.3.39 tFNDataSysStatus . . . 1930
9.12.3.40 tFNDelAssistData . . . 1930
9.12.3.41 tFNDeviceStateChange . . . 1930
9.12.3.42 tFNDHCPv4ClientLeaseStatus . . . 1931
9.12.3.43 tFNDTMFEvent . . . 1931
9.12.3.44 tFNDUNCallInfo . . . 1931
9.12.3.45 tFNEventNmea . . . 1931
9.12.3.46 tFNEventPosition . . . 1932
9.12.3.47 tFNFwDldCompletion . . . 1932
9.12.3.48 tFNGetOpMode . . . 1932
9.12.3.49 tFNGetServer . . . 1932
9.12.3.50 tFNGnssSvInfo . . . 1933
9.12.3.51 tFNHDRPersonaity . . . 1933
9.12.3.52 tFNImsaPdpStatus . . . 1933
9.12.3.53 tFNImsaRatStatus . . . 1933
9.12.3.54 tFNImsaRegStatus . . . 1933
9.12.3.55 tFNImsaSvcStatus . . . 1934
9.12.3.56 tFNImsRegMgrConfig . . . 1934
9.12.3.57 tFNImsSIPConfig . . . 1934
9.12.3.58 tFNImsSMSConfig . . . 1934
9.12.3.59 tFNImsUserConfig . . . 1934
9.12.3.60 tFNImsVoIPConfig . . . 1935
9.12.3.61 tFNInfoRec . . . 1935
9.12.3.62 tFNInjectPosition . . . 1935
9.12.3.63 tFNInjectSensorData . . . 1935
9.12.3.64 tFNInjectTimeStatus . . . 1935
9.12.3.65 tFNInjectUTCTime . . . 1936
9.12.3.66 tFNLUReject . . . 1936
9.12.3.67 tFNMemoryFull . . . 1938
9.12.3.68 tFNMessageWaiting . . . 1938
9.12.3.69 tFNMitiLvlRpt . . . 1938
9.12.3.70 tFNMobileIPStatus . . . 1938

9.12.3.71 tFNModemTempInfo . . . 1938
9.12.3.72 tFNNasEdrxChangeInfo . . . 1939
9.12.3.73 tFNNasTimer . . . 1939
9.12.3.74 tFNNet . . . 1939
9.12.3.75 tFNNetworkReject . . . 1939
9.12.3.76 tFNNetworkTime . . . 1940
9.12.3.77 tFNNewGPS . . . 1940
9.12.3.78 tFNNewNMEA . . . 1941
9.12.3.79 tFNNewRMTransferStatistics . . . 1941
9.12.3.80 tFNNewSMS . . . 1941
9.12.3.81 tFNOMADMState . . . 1941
9.12.3.82 tFNOpMode . . . 1942
9.12.3.83 tFNOTASPStatus . . . 1942
9.12.3.84 tFNPacketSrvState . . . 1943
9.12.3.85 tFNPDSState . . . 1943
9.12.3.86 tFNPower . . . 1943
9.12.3.87 tFNPrivacyChange . . . 1943
9.12.3.88 tFNPSMCfgParamChange . . . 1944
9.12.3.89 tFNQosNWStatus . . . 1944
9.12.3.90 tFNQosPriEvent . . . 1944
9.12.3.91 tFNQosStatus . . . 1944
9.12.3.92 tFNRankIndicator . . . 1945
9.12.3.93 tFNResetInfo . . . 1946
9.12.3.94 tFNRFInfo . . . 1946
9.12.3.95 tFNRoamingIndicator . . . 1946
9.12.3.96 tFNSDKTerminated . . . 1946
9.12.3.97 tFNSensorStreaming . . . 1947
9.12.3.98 tFNServingSystem . . . 1947
9.12.3.99 tFNSetCradleMount . . . 1947
9.12.3.100 tFNSetEngineState . . . 1947
9.12.3.101 tFNSetEventTimeSync . . . 1947
9.12.3.102 tFNSetExtPowerConfig . . . 1948
9.12.3.103 tFNSetServer . . . 1948
9.12.3.104 tFNSigInfo . . . 1948
9.12.3.105 tFNSignalStrength . . . 1948
9.12.3.106 tFNSLQSOMADMAlert . . . 1949
9.12.3.107 tFNSLQSQOSEvent . . . 1949
9.12.3.108 tFNSLQSSessionState . . . 1949
9.12.3.109 tFNSLQSSignalStrengths . . . 1949
9.12.3.110 tFNSLQSWDSEvent . . . 1949

9.12.3.111 tFNSMSEvents . . . 1950
9.12.3.112 tFNSUPSInfo . . . 1950
9.12.3.113 tFNSUPSNotification . . . 1950
9.12.3.114 tFNSwiAvmEventReport . . . 1950
9.12.3.115 tFNSysInfo . . . 1951
9.12.3.116 tFNSysSelectionPref . . . 1951
9.12.3.117 tFNtransLayerInfo . . . 1951
9.12.3.118 tFNtransNWRegInfo . . . 1951
9.12.3.119 tFNUIMRefresh . . . 1951
9.12.3.120 tFNUIMStatusChangeInfo . . . 1952
9.12.3.121 tFNUIMStatusInfo . . . 1952
9.12.3.122 tFNUSSDNotification . . . 1952
9.12.3.123 tFNUSSDNoWaitIndication . . . 1952
9.12.3.124 tFNUSSDRelease . . . 1953
9.12.3.125 transLayerNotification . . . 1953
9.12.3.126 transNWRegInfoNotification . . . 1953
9.12.4 Enumeration Type Documentation . . . 1954
9.12.4.1 device_state_enum . . . 1954
9.12.4.2 eQaQMIService . . . 1954
9.12.4.3 SMSEventType . . . 1954
9.12.4.4 TYPE_OF_SERVICE_DOMAIN . . . 1954
9.12.5 Function Documentation . . . 1955
9.12.5.1 iSetCATEventCallback . . . 1955
9.12.5.2 iSetSignalStrengthCallback . . . 1955
9.12.5.3 iSLQSSetDUNCallInfoCallback . . . 1955
9.12.5.4 iSLQSSetSignalStrengthsCallback . . . 1955
9.12.5.5 iSLQSSetWdsFirstInstEventCallback . . . 1955
9.12.5.6 iSLQSSetWdsSecondInstEventCallback . . . 1955
9.12.5.7 iSLQSSetWdsThirdInstEventCallback . . . 1955
9.12.5.8 iSLQSSetWdsXferStatsFirstInstCallback . . . 1955
9.12.5.9 iSLQSSetWdsXferStatsSecondInstCallback . . . 1955
9.12.5.10 SetActivationStatusCallback . . . 1955
9.12.5.11 SetCATEventCallback . . . 1955
9.12.5.12 SetCfgParamChangeCallback . . . 1956
9.12.5.13 SetDataCapabilitiesCallback . . . 1957
9.12.5.14 SetDeviceStateChangeCbk . . . 1957
9.12.5.15 SetFwDldCompletionCbk . . . 1957
9.12.5.16 SetGPSCallback . . . 1958
9.12.5.17 SetLocBestAvailPosCallback . . . 1958
9.12.5.18 SetLocCradleMountCallback . . . 1959

9.12.5.19 SetLocDeleteAssistDataCallback . . . 1959
9.12.5.20 SetLocEngineStateCallback . . . 1959
9.12.5.21 SetLocEventMaskNMEACallback . . . 1959
9.12.5.22 SetLocEventPositionCallback . . . 1960
9.12.5.23 SetLocEventTimeSyncCallback . . . 1960
9.12.5.24 SetLocGetOpModeCallback . . . 1960
9.12.5.25 SetLocGetServerCallback . . . 1960
9.12.5.26 SetLocGnssSvInfoCallback . . . 1961
9.12.5.27 SetLocInjectSensorDataCallback . . . 1961
9.12.5.28 SetLocInjectTimeCallback . . . 1961
9.12.5.29 SetLocOpModeCallback . . . 1962
9.12.5.30 SetLocSensorStreamingCallback . . . 1962
9.12.5.31 SetLocSetExtPowerConfigCallback . . . 1962
9.12.5.32 SetLocSetServerCallback . . . 1962
9.12.5.33 SetLURejectCallback . . . 1963
9.12.5.34 SetMobileIPStatusCallback . . . 1963
9.12.5.35 SetNasLTECphyCaIndCallback . . . 1964
9.12.5.36 SetNetChangeCbk . . . 1964
9.12.5.37 SetNewSMSCallback . . . 1965
9.12.5.38 SetNMEACallback . . . 1965
9.12.5.39 SetOMADMStateCallback . . . 1965
9.12.5.40 SetPDSStateCallback . . . 1966
9.12.5.41 SetPowerCallback . . . 1966
9.12.5.42 SetRankIndicatorCallback . . . 1966
9.12.5.43 SetRFInfoCallback . . . 1966
9.12.5.44 SetRMTransferStatisticsCallback . . . 1967
9.12.5.45 SetRoamingIndicatorCallback . . . 1967
9.12.5.46 SetSignalStrengthCallback . . . 1968
9.12.5.47 SetSLQSOMADMAlertCallback . . . 1968
9.12.5.48 SetSLQSOMADMAlertCallbackExt . . . 1969
9.12.5.49 SetUimSlotStatusChangeCallback . . . 1969
9.12.5.50 SetUSSDNotificationCallback . . . 1969
9.12.5.51 SetUSSDNoWaitIndicationCallback . . . 1970
9.12.5.52 SetUSSDReleaseCallback . . . 1970
9.12.5.53 SLQSNasEdrxChangeInfoCallBack . . . 1970
9.12.5.54 SLQSNasNetworkRejectCallback . . . 1971
9.12.5.55 SLQSNasNetworkTimeCallBack . . . 1971
9.12.5.56 SLQSNasSigInfo2CallBack . . . 1971
9.12.5.57 SLQSNasSigInfoCallBack . . . 1972
9.12.5.58 SLQSNasSwiOTAMessageCallback . . . 1972

9.12.5.59 SLQSNasSysInfoCallBack 1973
9.12.5.60 SLQSNasTimerCallback 1973
9.12.5.61 SLQSSetBandPreferenceCbk 1974
9.12.5.62 SLQSSetDataSystemStatusCallback 1974
9.12.5.63 SLQSSetDHCPv4ClientLeaseStatusCallback 1974
9.12.5.64 SLQSSetDUNCallInfoCallback 1975
9.12.5.65 SLQSSetIMSAPdpStatusCallback 1975
9.12.5.66 SLQSSetIMSARatStatusCallback 1976
9.12.5.67 SLQSSetIMSARegStatusCallback 1976
9.12.5.68 SLQSSetIMSASvcStatusCallback 1976
9.12.5.69 SLQSSetIMSSMSConfigCallback 1977
9.12.5.70 SLQSSetIMSUserConfigCallback 1977
9.12.5.71 SLQSSetIMSVoIPConfigCallback 1978
9.12.5.72 SLQSSetLocInjectPositionCallback 1978
9.12.5.73 SLQSSetLocInjectUTCTimeCallback 1978
9.12.5.74 SLQSSetModemTempCallback 1978
9.12.5.75 SLQSSetPacketSrvStatusCallback 1979
9.12.5.76 SLQSSetQosEventCallback 1979
9.12.5.77 SLQSSetQosNWStatusCallback 1980
9.12.5.78 SLQSSetQosPriEventCallback 1980
9.12.5.79 SLQSSetQosStatusCallback 1981
9.12.5.80 SLQSSetRegMgrConfigCallback 1981
9.12.5.81 SLQSSetSDKTerminatedCallback 1981
9.12.5.82 SLQSSetServingSystemCallback 1982
9.12.5.83 SLQSSetSessionStateCallback 1982
9.12.5.84 SLQSSetSignalStrengthsCallback 1983
9.12.5.85 SLQSSetSIPConfigCallback 1983
9.12.5.86 SLQSSetSMSEventCallback 1984
9.12.5.87 SLQSSetSwiGetResetInfoCallback 1984
9.12.5.88 SLQSSetSwiHDRPersCallback 1984
9.12.5.89 SLQSSetSysSelectionPrefCallBack 1985
9.12.5.90 SLQSSetTransLayerInfoCallback 1985
9.12.5.91 SLQSSetTransNWRegInfoCallback 1986
9.12.5.92 SLQSSetUIMStatusCallback 1986
9.12.5.93 SLQSSetWdsEventCallback 1986
9.12.5.94 SLQSSetWdsTransferStatisticCallback 1987
9.12.5.95 SLQSSwiAVMSEventReportCallback 1988
9.12.5.96 SLQSTmdMitigationLvlRptCallback 1988
9.12.5.97 SLQSUIMSetRefreshCallBack 1988
9.12.5.98 SLQSUIMSetStatusChangeCallBack 1988

9.12.5.99 SLQSVoiceInfoRecCallback . . . 1989
9.12.5.100 SLQSVoiceSetAllCallStatusCallBack . . . 1989
9.12.5.101 SLQSVoiceSetDTMFEventCallBack . . . 1990
9.12.5.102 SLQSVoiceSetOTASPStatusCallBack . . . 1990
9.12.5.103 SLQSVoiceSetPrivacyChangeCallBack . . . 1991
9.12.5.104 SLQSVoiceSetSUPSCallBack . . . 1991
9.12.5.105 SLQSVoiceSetSUPSNotificationCallback . . . 1991
9.12.5.106 SLQSWmsAsyncRawSendCallBack . . . 1992
9.12.5.107 SLQSWmsMemoryFullCallBack . . . 1992
9.12.5.108 SLQSWmsMessageWaitingCallBack . . . 1993
9.13 qaGobiApiDcs.h File Reference . . . 1993
9.13.1 Detailed Description . . . 1994
9.13.2 Macro Definition Documentation . . . 1994
9.13.2.1 LEN . . . 1994
9.13.2.2 PORTNAM_LEN . . . 1994
9.13.3 Function Documentation . . . 1994
9.13.3.1 GetQmapIsSupported . . . 1994
9.13.3.2 QCWWAN2kConnect . . . 1995
9.13.3.3 QCWWAN2kEnumerateDevices . . . 1995
9.13.3.4 QCWWAN2kGetConnectedDeviceID . . . 1996
9.13.3.5 QCWWANConnect . . . 1996
9.13.3.6 QCWWANDisconnect . . . 1996
9.13.3.7 QCWWANEnumerateDevices . . . 1997
9.13.3.8 SetQmapIPTable . . . 1997
9.13.3.9 SetQmapIPv6Table . . . 1998
9.13.3.10 SetSDKImagePath . . . 1998
9.13.3.11 SLQSGetDeviceMode . . . 1998
9.13.3.12 SLQSGetNetStatistic . . . 1999
9.13.3.13 SLQSGetUsbPortNames . . . 1999
9.13.3.14 SLQSKillSDKProcess . . . 1999
9.13.3.15 SLQSSetLoggingMask . . . 2000
9.13.3.16 SLQSStart . . . 2000
9.13.3.17 SLQSStart_AVAgent . . . 2001
9.13.3.18 SLQSStartSrv . . . 2001
9.14 qaGobiApiDms.h File Reference . . . 2002
9.14.1 Detailed Description . . . 2004
9.14.2 Macro Definition Documentation . . . 2005
9.14.2.1 MAX_CUST_ID_LEN . . . 2005
9.14.2.2 MAX_CUST_VALUE_LEN . . . 2005
9.14.2.3 MAX_DYING_GASP_CFG_SMS_CONTENT_LENGTH . . . 2005

9.14.2.4 MAX_DYING_GASP_CFG_SMS_NUMBER_LENGTH . . . 2005
9.14.2.5 MAX_FSN_LENGTH . . . 2005
9.14.3 Typedef Documentation . . . 2005
9.14.3.1 custFeaturesInfo . . . 2005
9.14.3.2 custFeaturesSetting . . . 2006
9.14.3.3 dmsCurrentPRLInfo . . . 2008
9.14.3.4 ERIFileparams . . . 2008
9.14.3.5 serialNumbersInfo . . . 2008
9.14.3.6 SLQSSwiGetHostDevInfoParams . . . 2009
9.14.3.7 SLQSSwiGetOSInfoParams . . . 2009
9.14.3.8 SLQSSwiGetSerialNoExtParams . . . 2010
9.14.3.9 SLQSSwiSetHostDevInfoParams . . . 2010
9.14.3.10 SLQSSwiSetOSInfoParams . . . 2011
9.14.4 Function Documentation . . . 2011
9.14.4.1 ActivateAutomatic . . . 2011
9.14.4.2 GetActivationState . . . 2012
9.14.4.3 GetDeviceCapabilities . . . 2012
9.14.4.4 GetFirmwareRevision . . . 2013
9.14.4.5 GetFirmwareRevisions . . . 2014
9.14.4.6 GetHardwareRevision . . . 2014
9.14.4.7 GetIMSI . . . 2015
9.14.4.8 GetManufacturer . . . 2015
9.14.4.9 GetModelID . . . 2016
9.14.4.10 GetNetworkTime . . . 2016
9.14.4.11 GetOfflineReason . . . 2017
9.14.4.12 GetPower . . . 2018
9.14.4.13 GetPRLVersion . . . 2018
9.14.4.14 GetSerialNumbers . . . 2019
9.14.4.15 GetVoiceNumber . . . 2019
9.14.4.16 ResetToFactoryDefaults . . . 2020
9.14.4.17 SetPower . . . 2020
9.14.4.18 SLQSDmsSwiGetPCInfo . . . 2021
9.14.4.19 SLQSDmsSwiGetResetInfo . . . 2021
9.14.4.20 SLQSDmsSwiGetUimSelection . . . 2021
9.14.4.21 SLQSDmsSwiIndicationRegister . . . 2021
9.14.4.22 SLQSGetBandCapabilities . . . 2022
9.14.4.23 SLQSGetBandCapability . . . 2022
9.14.4.24 SLQSGetCurrentPRLInfo . . . 2024
9.14.4.25 SLQSGetCustFeatures . . . 2024
9.14.4.26 SLQSGetCustFeaturesV2 . . . 2025

9.14.4.27 SLQSGetERIFile . . . 2025
9.14.4.28 SLQSGetPowerSaveModeConfig . . . 2026
9.14.4.29 SLQSGetSerialNumbers . . . 2026
9.14.4.30 SLQSSetCustFeatures . . . 2026
9.14.4.31 SLQSSetCustFeaturesV2 . . . 2027
9.14.4.32 SLQSSetPowerSaveModeConfig . . . 2027
9.14.4.33 SLQSSwiClearDyingGaspStatistics . . . 2028
9.14.4.34 SLQSSwiDmsUimSelect . . . 2028
9.14.4.35 SLQSSwiGetCrashAction . . . 2028
9.14.4.36 SLQSSwiGetCrashInfo . . . 2029
9.14.4.37 SLQSSwiGetDyingGaspCfg . . . 2029
9.14.4.38 SLQSSwiGetDyingGaspStatistics . . . 2030
9.14.4.39 SLQSSwiGetFSN . . . 2030
9.14.4.40 SLQSSwiGetFwUpdateStatus . . . 2030
9.14.4.41 SLQSSwiGetHostDevInfo . . . 2031
9.14.4.42 SLQSSwiGetOSInfo . . . 2031
9.14.4.43 SLQSSwiGetSerialNoExt . . . 2032
9.14.4.44 SLQSSwiGetUSBComp . . . 2032
9.14.4.45 SLQSSwiSetCrashAction . . . 2032
9.14.4.46 SLQSSwiSetDyingGaspCfg . . . 2033
9.14.4.47 SLQSSwiSetHostDevInfo . . . 2033
9.14.4.48 SLQSSwiSetOSInfo . . . 2034
9.14.4.49 SLQSSwiSetUSBComp . . . 2034
9.14.4.50 SLQSUIMGetState . . . 2035
9.14.4.51 UIMChangePIN . . . 2035
9.14.4.52 UIMGetControlKeyStatus . . . 2036
9.14.4.53 UIMGetICCID . . . 2037
9.14.4.54 UIMGetPINStatus . . . 2037
9.14.4.55 UIMSetControlKeyProtection . . . 2038
9.14.4.56 UIMSetPINProtection . . . 2039
9.14.4.57 UIMUnblockControlKey . . . 2040
9.14.4.58 UIMUnblockPIN . . . 2040
9.14.4.59 UIMVerifyPIN . . . 2041
9.14.4.60 ValidateSPC . . . 2042
9.15 qaGobiApiFms.h File Reference . . . 2042
9.15.1 Detailed Description . . . 2046
9.15.2 Macro Definition Documentation . . . 2046
9.15.2.1 BUILD_ID_LEN . . . 2046
9.15.2.2 BUILD_ID_MAX_LEN . . . 2046
9.15.2.3 DEVICE_OFFLINE . . . 2046

9.15.2.4 DEVICE_RESET . . . 2046
9.15.2.5 DEVICE_SHUTDOWN . . . 2046
9.15.2.6 FIRMWARE_UPDATE_FAIL . . . 2046
9.15.2.7 FIRMWARE_UPDATE_SUCCESS . . . 2046
9.15.2.8 FIRMWARE_UPGRADE_SUCCESS . . . 2046
9.15.2.9 G3K_FIRMWARE_DOWNLOAD . . . 2046
9.15.2.10 GOBI_LISTENTRIES_MAX . . . 2046
9.15.2.11 GOBI_MBN_BUILD_ID_STR_LEN . . . 2046
9.15.2.12 GOBI_MBN_IMG_ID_SIZE . . . 2046
9.15.2.13 GOBI_MBN_IMG_ID_STR_LEN . . . 2046
9.15.2.14 GOBI_SET_IMG_PREF_RSPLEN . . . 2046
9.15.2.15 IMG_ID_LEN . . . 2046
9.15.2.16 IMGDETAILS_LEN . . . 2046
9.15.2.17 MAX_IMAGE_IDE_ELEMENTS . . . 2046
9.15.2.18 PRI_UPDATE_FAIL . . . 2046
9.15.2.19 SLQSFWINFO_APPVERSION_SZ . . . 2046
9.15.2.20 SLQSFWINFO_BOOTVERSION_SZ . . . 2046
9.15.2.21 SLQSFWINFO_CARRIER_SZ . . . 2046
9.15.2.22 SLQSFWINFO_CUR_CARR_NAME . . . 2046
9.15.2.23 SLQSFWINFO_CUR_CARR_REV . . . 2046
9.15.2.24 SLQSFWINFO_MODELID_SZ . . . 2046
9.15.2.25 SLQSFWINFO_PACKAGEID_SZ . . . 2046
9.15.2.26 SLQSFWINFO_PART_NO_SZ . . . 2047
9.15.2.27 SLQSFWINFO_PRIVERSION_SZ . . . 2047
9.15.2.28 SLQSFWINFO_SKU_SZ . . . 2047
9.15.2.29 SPKG_FIRMWARE_DOWNLOAD . . . 2047
9.15.2.30 TOTAL_IMAGE_ID_STRING_SIZE . . . 2047
9.15.2.31 UNIQUE_ID_LEN . . . 2047
9.15.3 Enumeration Type Documentation . . . 2047
9.15.3.1 eGobiDeviceSeries . . . 2047
9.15.3.2 eGobiImageCarrier . . . 2047
9.15.3.3 eGobiImageGPS . . . 2048
9.15.3.4 eGobiImageRegion . . . 2049
9.15.3.5 eGobiImageTech . . . 2049
9.15.4 Function Documentation . . . 2049
9.15.4.1 DeleteStoredImage . . . 2049
9.15.4.2 DownloadToSlot . . . 2050
9.15.4.3 eGetDeviceSeries . . . 2050
9.15.4.4 GetImagesPreference . . . 2050
9.15.4.5 GetImageStore . . . 2051

9.15.4.6 GetStoredImages . . . 2051
9.15.4.7 SetImagePath . . . 2052
9.15.4.8 SetImagesPreference . . . 2053
9.15.4.9 SLQSDownloadFirmwareToSlot . . . 2053
9.15.4.10 SLQSGetBootVersionNumber . . . 2054
9.15.4.11 SLQSGetFirmwareInfo . . . 2055
9.15.4.12 SLQSGetImageInfo . . . 2055
9.15.4.13 SLQSGetImageInfo_9x15 . . . 2056
9.15.4.14 SLQSGetImageInfoMC77xx . . . 2056
9.15.4.15 SLQSGetImageInfoMC83xx . . . 2057
9.15.4.16 SLQSGetImagePartNumber . . . 2058
9.15.4.17 SLQSGetValidFwPriCombinations . . . 2058
9.15.4.18 SLQSIsBootloaderDebugEnabled . . . 2059
9.15.4.19 SLQSIsSpkgFormatRequired . . . 2059
9.15.4.20 SLQSSetCrashStateCheckIgnore . . . 2059
9.15.4.21 SLQSSetSIMBasedImageSwitching . . . 2060
9.15.4.22 SLQSSetSpkgFormatRequired . . . 2060
9.15.4.23 SLQSSwiGetAllCarrierImages . . . 2060
9.15.4.24 SLQSSwiGetFirmwareCurr . . . 2061
9.15.4.25 SLQSUpgradeFirmware9x07 . . . 2061
9.15.4.26 SLQSUpgradeFirmware9x15 . . . 2062
9.15.4.27 upgrade_9x07_9x50_fw . . . 2063
9.15.4.28 upgrade_mc77xx_fw . . . 2063
9.15.4.29 UpgradeFirmware2k . . . 2063
9.16 qaGobiApiIms.h File Reference . . . 2064
9.16.1 Detailed Description . . . 2065
9.16.2 Function Documentation . . . 2065
9.16.2.1 SLQSGetIMSSMSConfig . . . 2065
9.16.2.2 SLQSGetIMSUserConfig . . . 2065
9.16.2.3 SLQSGetIMSVoIPConfig . . . 2066
9.16.2.4 SLQSGetRegMgrConfig . . . 2066
9.16.2.5 SLQSGetSIPConfig . . . 2067
9.16.2.6 SLQSImsConfigIndicationRegister . . . 2067
9.16.2.7 SLQSSetIMSSMSConfig . . . 2068
9.16.2.8 SLQSSetIMSUserConfig . . . 2068
9.16.2.9 SLQSSetIMSVoIPConfig . . . 2069
9.16.2.10 SLQSSetRegMgrConfig . . . 2069
9.16.2.11 SLQSSetSIPConfig . . . 2070
9.17 qaGobiApiImsa.h File Reference . . . 2070
9.17.1 Detailed Description . . . 2071

9.17.2 Function Documentation . . . 2071
9.17.2.1 SLQSGetIMSARegStatus . . . 2071
9.17.2.2 SLQSGetIMSAServiceStatus . . . 2071
9.17.2.3 SLQSGetIMSASupportedFields . . . 2072
9.17.2.4 SLQSGetIMSASupportedMsg . . . 2072
9.17.2.5 SLQSRegisterIMSAIndication . . . 2073
9.18 qaGobiApiLoc.h File Reference . . . 2073
9.18.1 Detailed Description . . . 2074
9.18.2 Macro Definition Documentation . . . 2075
9.18.2.1 MAX_SENSOR_DATA_LEN . . . 2075
9.18.2.2 MAX_TEMP_DATA_LEN . . . 2075
9.18.3 Function Documentation . . . 2075
9.18.3.1 SLQSLOCDelAssData . . . 2075
9.18.3.2 SLQSLOCEventRegister . . . 2075
9.18.3.3 SLQSLOCGetBestAvailPos . . . 2076
9.18.3.4 SLQSLOCGetOpMode . . . 2076
9.18.3.5 SLQSLOCGetServer . . . 2076
9.18.3.6 SLQSLOCInjectPosition . . . 2077
9.18.3.7 SLQSLOCInjectSensorData . . . 2077
9.18.3.8 SLQSLOCInjectUTCTime . . . 2078
9.18.3.9 SLQSLOCSetCradleMountConfig . . . 2078
9.18.3.10 SLQSLOCSetExtPowerState . . . 2078
9.18.3.11 SLQSLOCSetOpMode . . . 2079
9.18.3.12 SLQSLOCSetServer . . . 2079
9.18.3.13 SLQSLOCStart . . . 2080
9.18.3.14 SLQSLOCStop . . . 2080
9.18.3.15 SwiLocGetAutoStart . . . 2081
9.18.3.16 SwiLocSetAutoStart . . . 2081
9.19 qaGobiApiNas.h File Reference . . . 2081
9.19.1 Detailed Description . . . 2089
9.19.2 Macro Definition Documentation . . . 2089
9.19.2.1 IMSI_M_S1_LENGTH . . . 2089
9.19.2.2 IMSI_M_S2_LENGTH . . . 2089
9.19.2.3 MAX_DATA_SRV_CAPABILITIES . . . 2089
9.19.2.4 MAX_DESCRIPTION_LENGTH . . . 2089
9.19.2.5 MAX_PHY_CA_AGG_SCELL_ARRRY_SIZE . . . 2089
9.19.2.6 MAX_PILOT_SETS . . . 2089
9.19.2.7 MAX_SERV_SYSTEM_RADIO_INTERFACES . . . 2089
9.19.2.8 NAM_NAME_LENGTH . . . 2089
9.19.2.9 NAS_MAX_SCC_RX_INFO_INSTANCES . . . 2089

9.19.2.10 NAS_MAX_SLQS_NAS_PCI_INFO_LENGTH . . . 2089
9.19.2.11 NAS_MAX_SLQS_NAS_PCI_INFO_PLMN_LENGTH . . . 2089
9.19.2.12 NAS_SIG_INFO_MAX_TDSCDMA_THRESHOLDS_LIST_SIZE . . . 2089
9.19.2.13 NAS_SIG_INFO_MIN_dB_FLOAT_VALUE . . . 2089
9.19.2.14 NAS_SIG_INFO_MIN_dBm_FLOAT_VALUE . . . 2089
9.19.2.15 PLMN_LENGTH . . . 2090
9.19.2.16 SLQS_NAS_MCC_MNC_INST_LENGTH . . . 2090
9.19.2.17 SLQS_NAS_NW_SCAN_LTE_OP_MODE_MAX_LENGTH . . . 2090
9.19.2.18 SLQS_SS_INFO_LIST_MAX_ELEMENTS . . . 2090
9.19.2.19 SLQS_SYSTEM_ID_SIZE . . . 2090
9.19.2.20 UATISIZE . . . 2090
9.19.3 Typedef Documentation . . . 2090
9.19.3.1 LTEBandPrefExtTlv . . . 2090
9.19.3.2 NR5gBandPrefTlv . . . 2090
9.19.3.3 SlqsNas3GppNetworkRAT . . . 2090
9.19.3.4 slqsNetworkScanInfo . . . 2090
9.19.3.5 slqsNetworkScanInfoReq . . . 2091
9.19.3.6 sysSelectPrefExtInfo . . . 2094
9.19.3.7 sysSelectPrefInfo . . . 2095
9.19.3.8 sysSelectPrefParams . . . 2100
9.19.4 Enumeration Type Documentation . . . 2106
9.19.4.1 _NAMS_RADIO_IF_TECHNOLOGY_ . . . 2106
9.19.4.2 eSYS_SRV_DOMAIN . . . 2106
9.19.4.3 LTE_BAND_CLASS_E_UTRA_OPERATING_BAND . . . 2107
9.19.4.4 NAS_LTE_CPHY_CA_BW_NRB . . . 2108
9.19.4.5 NAS_LTE_CPHY_SCELL_STATE . . . 2108
9.19.5 Function Documentation . . . 2108
9.19.5.1 GetACCOLC . . . 2108
9.19.5.2 GetANAAAAuthenticationStatus . . . 2109
9.19.5.3 GetCDMANetworkParameters . . . 2109
9.19.5.4 GetHomeNetwork . . . 2111
9.19.5.5 GetHomeNetwork3GPP2 . . . 2112
9.19.5.6 GetNetworkPreference . . . 2113
9.19.5.7 GetRFInfo . . . 2114
9.19.5.8 GetServingNetwork . . . 2115
9.19.5.9 GetServingNetworkCapabilities . . . 2116
9.19.5.10 GetSignalStrengths . . . 2117
9.19.5.11 InitiateDomainAttach . . . 2117
9.19.5.12 InitiateNetworkRegistration . . . 2118
9.19.5.13 PerformNetworkScan . . . 2118

9.19.5.14 SetACCOLC . . . 2119
9.19.5.15 SetCDMANetworkParameters . . . 2119
9.19.5.16 SetNetworkPreference . . . 2121
9.19.5.17 SLQSConfigSigInfo . . . 2121
9.19.5.18 SLQSGetErrorRate . . . 2122
9.19.5.19 SLQSGetNetworkTime . . . 2122
9.19.5.20 SLQSGetOperatorNameData . . . 2123
9.19.5.21 SLQSGetPLMNName . . . 2123
9.19.5.22 SLQSGetServingSystem . . . 2124
9.19.5.23 SLQSGetSignalStrength . . . 2124
9.19.5.24 SLQSGetSysSelectionPref . . . 2125
9.19.5.25 SLQSGetSysSelectionPrefExt . . . 2125
9.19.5.26 SLQSInitiateNetworkRegistration . . . 2125
9.19.5.27 SLQSNasConfigSigInfo2 . . . 2126
9.19.5.28 SLQSNasGet3GPP2Subscription . . . 2126
9.19.5.29 SLQSNasGetCellLocationInfo . . . 2127
9.19.5.30 SLQSNASGeteDRXParams . . . 2127
9.19.5.31 SLQSNASGeteDRXParamsExt . . . 2128
9.19.5.32 SLQSNASGetForbiddenNetworks . . . 2128
9.19.5.33 SLQSNasGetHDRColorCode . . . 2128
9.19.5.34 SLQSNASGetLTECPHYCaInfo . . . 2129
9.19.5.35 SLQSNasGetRFInfo . . . 2129
9.19.5.36 SLQSNasGetSigInfo . . . 2129
9.19.5.37 SLQSNasGetSysInfo . . . 2130
9.19.5.38 SLQSNasGetTxRxInfo . . . 2130
9.19.5.39 SLQSNasIndicationRegister . . . 2131
9.19.5.40 SLQSNasIndicationRegisterExt . . . 2132
9.19.5.41 SLQSNasIndicationRegisterLTECphyCa . . . 2132
9.19.5.42 SLQSNASSeteDRXParams . . . 2133
9.19.5.43 SLQSNASSwiGetChannelLock . . . 2133
9.19.5.44 SLQSNasSwiIndicationRegister . . . 2133
9.19.5.45 SLQSNasSwiModemStatus . . . 2134
9.19.5.46 SLQSNASSwiSetChannelLock . . . 2134
9.19.5.47 SLQSPerformNetworkScan . . . 2135
9.19.5.48 SLQSPerformNetworkScanPCI . . . 2135
9.19.5.49 SLQSSetBandPreference . . . 2136
9.19.5.50 SLQSSetSysSelectionPref . . . 2137
9.19.5.51 SLQSSetSysSelectionPrefExt . . . 2137
9.19.5.52 SLQSSwiGetHDRPersonality . . . 2138
9.19.5.53 SLQSSwiGetHDRProtSubtype . . . 2138

9.19.5.54 SLQSSwiGetHRPDStats . . . 2138
9.19.5.55 SLQSSwiGetLteCQI . . . 2139
9.19.5.56 SLQSSwiGetLteSccRxInfo . . . 2139
9.19.5.57 SLQSSwiNetworkDebug . . . 2140
9.19.5.58 SLQSSwiPSDetach . . . 2140
9.20 qaGobiApiOmadm.h File Reference . . . 2140
9.20.1 Detailed Description . . . 2141
9.20.2 Function Documentation . . . 2141
9.20.2.1 OMADMCancelSession . . . 2141
9.20.2.2 OMADMGetPendingNIA . . . 2141
9.20.2.3 OMADMGetSessionInfo . . . 2142
9.20.2.4 OMADMStartSession . . . 2143
9.21 qaGobiApiPds.h File Reference . . . 2143
9.21.1 Detailed Description . . . 2144
9.21.2 Macro Definition Documentation . . . 2145
9.21.2.1 DEFAULTBYTEVALUE . . . 2145
9.21.2.2 DEFAULTLONGVALUE . . . 2145
9.21.2.3 DEFAULTWORDVALUE . . . 2145
9.21.3 Enumeration Type Documentation . . . 2145
9.21.3.1 anonymous enum . . . 2145
9.21.4 Function Documentation . . . 2145
9.21.4.1 ForceXTRADownload . . . 2145
9.21.4.2 GetPDSDefaults . . . 2145
9.21.4.3 GetPDSState . . . 2146
9.21.4.4 GetPortAutomaticTracking . . . 2147
9.21.4.5 GetServiceAutomaticTracking . . . 2147
9.21.4.6 GetXTRAAutomaticDownload . . . 2147
9.21.4.7 GetXTRANetwork . . . 2148
9.21.4.8 GetXTRAValidity . . . 2148
9.21.4.9 PDSInjectTimeReference . . . 2149
9.21.4.10 ResetPDSData . . . 2149
9.21.4.11 SetPDSDefaults . . . 2150
9.21.4.12 SetPDSState . . . 2151
9.21.4.13 SetPortAutomaticTracking . . . 2152
9.21.4.14 SetServiceAutomaticTracking . . . 2152
9.21.4.15 SetXTRAAutomaticDownload . . . 2152
9.21.4.16 SetXTRANetwork . . . 2153
9.21.4.17 SLQSGetAGPSConfig . . . 2153
9.21.4.18 SLQSGetGPSStateInfo . . . 2154
9.21.4.19 SLQSPDSDeterminePosition . . . 2155

9.21.4.20 SLQSPDSInjectAbsoluteTimeReference . . . 2155
9.21.4.21 SLQSPDSInjectPositionData . . . 2155
9.21.4.22 SLQSSetAGPSConfig . . . 2156
9.21.4.23 SLQSSetPositionMethodState . . . 2157
9.21.4.24 StartPDSTrackingSessionExt . . . 2157
9.21.4.25 StopPDSTrackingSession . . . 2158
9.22 qaGobiApiQos.h File Reference . . . 2158
9.22.1 Detailed Description . . . 2159
9.22.2 Macro Definition Documentation . . . 2159
9.22.2.1 MAX_QOS_FILTER_TLV . . . 2159
9.22.2.2 MAX_QOS_SPEC_PER_APN . . . 2159
9.22.3 Function Documentation . . . 2159
9.22.3.1 SetQosMuxID . . . 2159
9.22.3.2 SLQSQosGetFlowStatus . . . 2160
9.22.3.3 SLQSQosGetGranted . . . 2160
9.22.3.4 SLQSQosGetNetworkStatus . . . 2160
9.22.3.5 SLQSQosGetNWProf . . . 2161
9.22.3.6 SLQSQosModify . . . 2161
9.22.3.7 SLQSQosRel . . . 2162
9.22.3.8 SLQSQosReq . . . 2162
9.22.3.9 SLQSQosReset . . . 2163
9.22.3.10 SLQSQosResume . . . 2163
9.22.3.11 SLQSQosSuspend . . . 2164
9.22.3.12 SLQSQosSwiReadApnExtraParams . . . 2164
9.22.3.13 SLQSQosSwiReadDataStats . . . 2165
9.23 qaGobiApiRms.h File Reference . . . 2165
9.23.1 Detailed Description . . . 2165
9.23.2 Function Documentation . . . 2165
9.23.2.1 GetSMSWake . . . 2165
9.23.2.2 SetSMSWake . . . 2166
9.24 qaGobiApiSar.h File Reference . . . 2166
9.24.1 Detailed Description . . . 2167
9.24.2 Enumeration Type Documentation . . . 2167
9.24.2.1 eQMISARRFState . . . 2167
9.24.3 Function Documentation . . . 2168
9.24.3.1 SLQSGetRfSarState . . . 2168
9.24.3.2 SLQSSetRfSarState . . . 2168
9.25 qaGobiApiSms.h File Reference . . . 2169
9.25.1 Detailed Description . . . 2171
9.25.2 Macro Definition Documentation . . . 2171

9.25.2.1 ABSOLUTE_VALIDITY . . . 2171
9.25.2.2 CONFIG_LEN . . . 2171
9.25.2.3 MAX_SMS_ROUTES . . . 2171
9.25.2.4 MAX_SMSC_LENGTH . . . 2171
9.25.2.5 MAXIMUM_SMS_MSG_LEN . . . 2171
9.25.2.6 NUM_OF_SET . . . 2171
9.25.2.7 SMS_ASCII_STRING_ARRAY_SIZE . . . 2171
9.25.2.8 SMS_ASCII_STRING_SIZE . . . 2171
9.25.2.9 SMS_DEFAULT_TIME_ZONE . . . 2171
9.25.2.10 SMS_INVALID_TIME_STAMP_VALUE . . . 2172
9.25.2.11 SMS_MESSAGE_TIMESTEMP_SIZE . . . 2172
9.25.2.12 TIME_DATE_BUF . . . 2172
9.25.2.13 TIME_STAMP_BUF . . . 2172
9.25.3 Typedef Documentation . . . 2172
9.25.3.1 getIndicationRegResp . . . 2172
9.25.3.2 getTransLayerInfoResp . . . 2172
9.25.3.3 getTransNWRegInfoResp . . . 2173
9.25.3.4 qaQmi3GPP2BroadcastCfgInfo . . . 2173
9.25.3.5 qaQmi3GPPBroadcastCfgInfo . . . 2174
9.25.3.6 setIndicationRegReq . . . 2174
9.25.3.7 transLayerInfo . . . 2175
9.25.4 Enumeration Type Documentation . . . 2175
9.25.4.1 sEnumTimeStampenum . . . 2175
9.25.5 Function Documentation . . . 2175
9.25.5.1 GetSMSCAddress . . . 2175
9.25.5.2 SaveSMS . . . 2176
9.25.5.3 SendSMS . . . 2177
9.25.5.4 SetSMSCAddress . . . 2178
9.25.5.5 SLQSCDMADecodeMTTextMsg . . . 2178
9.25.5.6 SLQSCDMADecodeMTTextMsgExt . . . 2178
9.25.5.7 SLQSCDMAEncodeMOTextMsg . . . 2179
9.25.5.8 SLQSDeleteSMS . . . 2179
9.25.5.9 SLQSGetIndicationRegister . . . 2180
9.25.5.10 SLQSGetMessageWaiting . . . 2181
9.25.5.11 SLQSGetSMS . . . 2181
9.25.5.12 SLQSGetSmsBroadcastConfig . . . 2182
9.25.5.13 SLQSGetSMSList . . . 2183
9.25.5.14 SLQSGetTransLayerInfo . . . 2184
9.25.5.15 SLQSGetTransNWRegInfo . . . 2184
9.25.5.16 SLQSModifySMSStatus . . . 2184

9.25.5.17 SLQSSendAsyncSMS . . . 2185
9.25.5.18 SLQSSendLongSMS . . . 2186
9.25.5.19 SLQSSendSMS . . . 2186
9.25.5.20 SLQSSetIndicationRegister . . . 2187
9.25.5.21 SLQSSetSmsBroadcastActivation . . . 2187
9.25.5.22 SLQSSetSmsBroadcastConfig . . . 2188
9.25.5.23 SLQSSetSmsStorage . . . 2188
9.25.5.24 SLQSSmsGetMaxStorageSize . . . 2189
9.25.5.25 SLQSSmsGetMessageProtocol . . . 2189
9.25.5.26 SLQSSmsSetRoutes . . . 2190
9.25.5.27 SLQSSwiGetSMSStorage . . . 2190
9.25.5.28 SLQSWCDMADecodeLongTextMsg . . . 2191
9.25.5.29 SLQSWCDMADecodeMTEncoding . . . 2191
9.25.5.30 SLQSWCDMADecodeMTTextMsg . . . 2192
9.25.5.31 SLQSWCDMAEncodeMOTextMsg . . . 2192
9.26 qaGobiApiSwi.h File Reference . . . 2192
9.26.1 Detailed Description . . . 2193
9.26.2 Function Documentation . . . 2193
9.26.2.1 SLQSGetPidof . . . 2193
9.26.2.2 SLQSGetSdkVersion . . . 2193
9.26.2.3 SLQSSendRawQMI . . . 2194
9.27 qaGobiApiSwiAudio.h File Reference . . . 2194
9.27.1 Detailed Description . . . 2194
9.27.2 Macro Definition Documentation . . . 2195
9.27.2.1 MAX_LEN_IFACE_TABLE . . . 2195
9.27.3 Function Documentation . . . 2195
9.27.3.1 SLQSGetM2MAudioProfile . . . 2195
9.27.3.2 SLQSGetM2MAudioVolume . . . 2195
9.27.3.3 SLQSGetM2MAVMute . . . 2196
9.27.3.4 SLQSGetM2MSpkrGain . . . 2196
9.27.3.5 SLQSSetM2MAudioAVCFG . . . 2197
9.27.3.6 SLQSSetM2MAudioLPBK . . . 2197
9.27.3.7 SLQSSetM2MAudioNVDef . . . 2197
9.27.3.8 SLQSSetM2MAudioProfile . . . 2198
9.27.3.9 SLQSSetM2MAudioVolume . . . 2198
9.27.3.10 SLQSSetM2MAVMute . . . 2198
9.27.3.11 SLQSSetM2MSpkrGain . . . 2199
9.28 qaGobiApiSwiAvms.h File Reference . . . 2199
9.28.1 Detailed Description . . . 2201
9.28.2 Macro Definition Documentation . . . 2201

9.28.2.1 MAX_AVMS_RETRY_TIMER_NUMBER . . . 2201
9.28.2.2 MAX_GET_SETTINGS_AVMS_APN_STRING_LENGTH . . . 2201
9.28.2.3 MAX_GET_SETTINGS_AVMS_PWD_STRING_LENGTH . . . 2201
9.28.2.4 MAX_GET_SETTINGS_AVMS_UNAME_STRING_LENGTH . . . 2201
9.28.2.5 MAX_SWI_AVMS_SET_SETTING_APN_LENGTH . . . 2201
9.28.2.6 MAX_SWI_AVMS_SET_SETTING_CONNECTION_RETRY_TIMMERS . . . 2201
9.28.2.7 MAX_SWI_AVMS_SET_SETTING_PWD_LENGTH . . . 2201
9.28.2.8 MAX_SWI_AVMS_SET_SETTING_UNAME_LENGTH . . . 2202
9.28.2.9 QMISWIAVMSSESSIONGETINFO_BINARYUPDATESESSIONINFO_DESC_LENGTH . . . 2202
9.28.2.10 QMISWIAVMSSESSIONGETINFO_BINARYUPDATESESSIONINFO_NAME_LENGTH . . . 2202
9.28.2.11 QMISWIAVMSSESSIONGETINFO_BINARYUPDATESESSIONINFO_VERSION_LENGTH . . . 2202
9.28.2.12 QMISWIAVMSSESSIONGETINFO_CONFIG_ALERT_MSG_LENGTH . . . 2202
9.28.3 Typedef Documentation . . . 2202
9.28.3.1 QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp . . . 2202
9.28.3.2 QmiSwiAvmsEventReportConfigResp . . . 2203
9.28.3.3 QmiSwiAvmsEventReportConnectionRequestResp . . . 2203
9.28.3.4 QmiSwiAvmsEventReportDataSessionStatusResp . . . 2203
9.28.3.5 QmiSwiAvmsEventReportHTTPStatusResp . . . 2203
9.28.3.6 QmiSwiAvmsEventReportNotificationResp . . . 2204
9.28.3.7 QmiSwiAvmsEventReportPackageIDResp . . . 2205
9.28.3.8 QmiSwiAvmsEventReportRegStatusResp . . . 2205
9.28.3.9 QmiSwiAvmsEventReportSessionTypeResp . . . 2206
9.28.3.10 QmiSwiAvmsEventReportWAMSParamChangeResp . . . 2206
9.28.3.11 QmiSwiAvmsSetSettingsAPNInfo . . . 2206
9.28.3.12 QmiSwiAvmsSetSettingsConnectionRetryTimers . . . 2206
9.28.3.13 QmiSwiAvmsSetSettingsPeriodInfo . . . 2206
9.28.3.14 SLQSAVMSSetSettingsReq . . . 2206
9.28.3.15 SLQSAVMSSetSettingsReq_v2 . . . 2207
9.28.3.16 SLQSAVMSSettings . . . 2209
9.28.3.17 SLQSAVMSSettings_v2 . . . 2209
9.28.3.18 SLQSAVMSSettingsAPNInfo . . . 2209
9.28.3.19 SLQSAVMSSettingsConnectionRetryTimers . . . 2209
9.28.3.20 SLQSAVMSSettingsPeriodsInfo . . . 2209
9.28.4 Function Documentation . . . 2209
9.28.4.1 SLQSAVMSGetSessionInfo . . . 2209
9.28.4.2 SLQSAVMSGetSettings . . . 2209
9.28.4.3 SLQSAVMSGetSettings_v2 . . . 2210
9.28.4.4 SLQSAVMSSelection . . . 2210

9.28.4.5 SLQSAVMSSetEventReport . . . 2210
9.28.4.6 SLQSAVMSSetSettings . . . 2211
9.28.4.7 SLQSAVMSSetSettings_v2 . . . 2211
9.28.4.8 SLQSAVMSSetSettingsIgnoreAutoReboot . . . 2212
9.28.4.9 SLQSAVMSStartSession . . . 2212
9.28.4.10 SLQSAVMSStopSession . . . 2213
9.29 qaGobiApiSwiDms.h File Reference . . . 2213
9.29.1 Detailed Description . . . 2214
9.29.2 Function Documentation . . . 2214
9.29.2.1 SLQSSwiDmsGetHWWatchdog . . . 2214
9.29.2.2 SLQSSwiDmsGetMTU . . . 2214
9.29.2.3 SLQSSwiDmsGetSecureInfo . . . 2215
9.29.2.4 SLQSSwiDmsGetUsbComp . . . 2215
9.29.2.5 SLQSSwiDmsGetUsbNetNum . . . 2215
9.29.2.6 SLQSSwiDmsSetHWWatchdog . . . 2216
9.29.2.7 SLQSSwiDmsSetMTU . . . 2216
9.29.2.8 SLQSSwiDmsSetUsbComp . . . 2217
9.29.2.9 SLQSSwiDmsSetUsbNetNum . . . 2217
9.30 qaGobiApiSwiOmadms.h File Reference . . . 2217
9.30.1 Detailed Description . . . 2218
9.30.2 Typedef Documentation . . . 2218
9.30.2.1 SLQSOMADMSessionInfo . . . 2218
9.30.2.2 SLQSOMADMSettings . . . 2220
9.30.2.3 SLQSOMADMSettingsReqParams . . . 2221
9.30.2.4 SLQSOMADMSettingsReqParams3 . . . 2222
9.30.3 Function Documentation . . . 2222
9.30.3.1 SLQSOMADMCancelSession . . . 2222
9.30.3.2 SLQSOMADMGetSessionInfo . . . 2223
9.30.3.3 SLQSOMADMGetSettings . . . 2223
9.30.3.4 SLQSOMADMGetSettings2 . . . 2224
9.30.3.5 SLQSOMADMSendSelection . . . 2224
9.30.3.6 SLQSOMADMSendSelection2 . . . 2225
9.30.3.7 SLQSOMADMSetSettings . . . 2226
9.30.3.8 SLQSOMADMSetSettings2 . . . 2226
9.30.3.9 SLQSOMADMSetSettings3 . . . 2226
9.30.3.10 SLQSOMADMStartSession . . . 2227
9.30.3.11 SLQSOMADMStartSession2 . . . 2227
9.31 qaGobiApiTableBandClasses.h File Reference . . . 2228
9.31.1 Detailed Description . . . 2228
9.31.2 Band Classes (Value - Description) . . . 2228

9.31.2.1 LTE Bands . . . 2230
9.32 qaGobiApiTableCallControlReturnReasons.h File Reference . . . 2231
9.32.1 Detailed Description . . . 2231
9.32.2 S1 . . . 2232
9.33 qaGobiApiTableCallEndReasons.h File Reference . . . 2232
9.33.1 Detailed Description . . . 2232
9.33.2 Call end reason codes (Code - Reason) . . . 2233
9.33.2.1 Technology-agnostic call end reasons . . . 2233
9.33.2.2 EVDO CDMA 1xEV-DO . . . 2233
9.33.2.3 WCDMA/GSM call end reasons . . . 2234
9.33.2.4 EVDO CDMA 1xEV-DO . . . 2236
9.33.2.5 call end reason type . . . 2236
9.33.2.6 Mobile IP call end reasons (Type=1) . . . 2236
9.33.2.7 Internal call end reasons (Type=2) . . . 2238
9.33.2.8 Call Manager defined call end reasons (Type=3) . . . 2241
9.33.2.9 3GPP specification defined call end reasons (Type=6) . . . 2245
9.33.2.10 PPP call end reasons (Type=7) . . . 2247
9.33.2.11 EHRPD call end reasons (Type=8) . . . 2248
9.33.2.12 IPV6 call end reasons (Type=9) . . . 2249
9.34 qaGobiApiTableCarrierCodes.h File Reference . . . 2249
9.34.1 Detailed Description . . . 2249
9.34.2 Carrier Codes (Number - Carrier) . . . 2249
9.35 qaGobiApiTableCodingScheme.h File Reference . . . 2251
9.35.1 Detailed Description . . . 2251
9.35.2 S1 . . . 2251
9.35.2.1 Use of bits 3..0\n\n . . . 2251
9.35.3 Coding Group Bits 7..4(0001) . . . 2251
9.35.3.1 use of bits 3..0 . . . 2251
9.35.4 Coding Group Bits 7..4(0010) . . . 2252
9.35.4.1 use of bits 3..0 . . . 2252
9.35.5 Coding Group Bits 7..4(0011) . . . 2252
9.35.5.1 use of bits 3..0 . . . 2252
9.35.6 Coding Group Bits 7..4(01xx) . . . 2252
9.35.6.1 use of bits 3..0 . . . 2252
9.35.7 Coding Group Bits 7..4(1001) . . . 2253
9.35.7.1 Reserved coding groups . . . 2253
9.35.8 Coding Group Bits 7..4(1010..1101) . . . 2253
9.35.8.1 Reserved coding groups . . . 2253
9.35.9 Coding Group Bits 7..4(1110) . . . 2253
9.35.9.1 Defined by the WAP Forum . . . 2253

9.35.10 Coding Group Bits 7..4 (1111) . . . 2253
9.35.10.1 Data coding / message handling . . . 2253
9.35.11 Macro Definition Documentation . . . 2253
9.35.11.1 __GOBI_API_CODING_SCHEME_H__ . . . 2253
9.36 qaGobiApiTableGpsCapabilityCodes.h File Reference . . . 2253
9.36.1 Detailed Description . . . 2254
9.36.2 GPS capability (Value - Capability) . . . 2254
9.37 qaGobiApiTablePowerModes.h File Reference . . . 2254
9.37.1 Detailed Description . . . 2254
9.37.2 Power Modes (Value - Description) . . . 2254
9.38 qaGobiApiTableRadioInterfaces.h File Reference . . . 2255
9.38.1 Detailed Description . . . 2255
9.38.2 Radio interface . . . 2255
9.38.2.1 Technology (Value - Radio Interface Technology) . . . 2255
9.39 qaGobiApiTableRegionCodes.h File Reference . . . 2255
9.39.1 Detailed Description . . . 2255
9.39.2 Region Codes (Code - Region) . . . 2255
9.40 qaGobiApiTableServiceOptions.h File Reference . . . 2256
9.40.1 Detailed Description . . . 2256
9.40.2 Service Option codes (Code - Reason) . . . 2256
9.40.2.1 Description . . . 2256
9.41 qaGobiApiTableSupServiceInfoClasses.h File Reference . . . 2258
9.41.1 Detailed Description . . . 2258
9.41.2 Supplementary Service Information Classes (Value - Service Class) . . . 2258
9.42 qaGobiApiTableSwiAudio.h File Reference . . . 2258
9.42.1 Detailed Description . . . 2259
9.42.2 ACDB Device (Device ID - description) . . . 2259
9.42.3 Physical Interface (Device ID - description - Interface parameters) . . . 2259
9.43 qaGobiApiTableSwiOMADMSessionStatus.h File Reference . . . 2259
9.43.1 Detailed Description . . . 2259
9.43.2 OMA DM Session Status (Session Status - Meaning - Usage) . . . 2259
9.44 qaGobiApiTableSwiOMADMUpdateCompleteStatus.h File Reference . . . 2260
9.44.1 Detailed Description . . . 2260
9.44.2 OMA DM Update Complete Status (Update Complete Status - Meaning - Usage) . . . 2260
9.45 qaGobiApiTableVoiceCallEndReasons.h File Reference . . . 2261
9.45.1 Detailed Description . . . 2261
9.45.2 Voice Call and supplementary services end reason codes (Code - Reason) . . . 2262
9.45.2.1 General . . . 2262
9.45.2.2 service Errors . . . 2263
9.45.2.3 control cause values . . . 2264

9.45.2.4 reject causes . . . 2266
9.45.2.5 reject causes . . . 2266
9.45.2.6 reject causes . . . 2267
9.45.2.7 stratum reject causes . . . 2267
9.45.2.8 reject causes . . . 2267
9.45.2.9 IP end reasons . . . 2267
9.46 qaGobiApiTmd.h File Reference . . . 2268
9.46.1 Detailed Description . . . 2268
9.46.2 Macro Definition Documentation . . . 2268
9.46.2.1 MAX_MITIGATION_DEV_ID_LEN . . . 2268
9.46.2.2 MAX_MITIGATION_DEV_LIST_LEN . . . 2268
9.46.3 Function Documentation . . . 2268
9.46.3.1 SLQSTmdDeRegNotMitigationLvl . . . 2268
9.46.3.2 SLQSTmdGetMitigationDevList . . . 2269
9.46.3.3 SLQSTmdGetMitigationLvl . . . 2269
9.46.3.4 SLQSTmdRegNotMitigationLvl . . . 2269
9.47 qaGobiApiUim.h File Reference . . . 2270
9.47.1 Detailed Description . . . 2272
9.47.2 Macro Definition Documentation . . . 2272
9.47.2.1 MAX_ACTIVE_PERS_FEATURES . . . 2272
9.47.2.2 MAX_CONTENT_LENGTH . . . 2272
9.47.2.3 MAX_DESCRIPTION_LENGTH . . . 2272
9.47.2.4 MAX_ICCID_LENGTH . . . 2272
9.47.2.5 MAX_NO_OF_APPLICATIONS . . . 2272
9.47.2.6 MAX_NO_OF_SLOTS . . . 2272
9.47.2.7 MAX_PATH_LENGTH . . . 2272
9.47.2.8 MAX_PUK_LENGTH . . . 2272
9.47.2.9 MAX_SLOTS_STATUS . . . 2272
9.47.3 Function Documentation . . . 2272
9.47.3.1 SLQSUIMAuthenticate . . . 2272
9.47.3.2 SLQSUIMChangePin . . . 2273
9.47.3.3 SLQSUIMDepersonalization . . . 2273
9.47.3.4 SLQSUIMEventRegister . . . 2274
9.47.3.5 SLQSUIMGetCardStatus . . . 2274
9.47.3.6 SLQSUIMGetCardStatusV2 . . . 2275
9.47.3.7 SLQSUIMGetConfiguration . . . 2276
9.47.3.8 SLQSUIMGetFileAttributes . . . 2276
9.47.3.9 SLQSUIMGetSlotsStatus . . . 2277
9.47.3.10 SLQSUIMPowerDown . . . 2277
9.47.3.11 SLQSUIMPowerUp . . . 2277

9.47.3.12 SLQSUIMReadTransparent . . . 2278
9.47.3.13 SLQSUIMRefreshComplete . . . 2278
9.47.3.14 SLQSUIMRefreshGetLastEvent . . . 2279
9.47.3.15 SLQSUIMRefreshOK . . . 2280
9.47.3.16 SLQSUIMRefreshRegister . . . 2280
9.47.3.17 SLQSUIMReset . . . 2281
9.47.3.18 SLQSUIMSetPinProtection . . . 2281
9.47.3.19 SLQSUIMSwitchSlot . . . 2282
9.47.3.20 SLQSUIMUnblockPin . . . 2282
9.47.3.21 SLQSUIMUnblockPinV2 . . . 2283
9.47.3.22 SLQSUIMVerifyPin . . . 2283
9.48 qaGobiApiVoice.h File Reference . . . 2284
9.48.1 Detailed Description . . . 2287
9.48.2 Macro Definition Documentation . . . 2287
9.48.2.1 MAX_CALL_NO_LEN . . . 2287
9.48.2.2 MAX_DESCRIPTION_LENGTH . . . 2287
9.48.2.3 MAX_NO_OF_CALLS . . . 2287
9.48.2.4 MAXUSSDLENGTH . . . 2287
9.48.2.5 PASSWORD_LENGTH . . . 2287
9.48.3 Enumeration Type Documentation . . . 2287
9.48.3.1 serviceClassInformation . . . 2287
9.48.4 Function Documentation . . . 2287
9.48.4.1 AnswerUSSD . . . 2287
9.48.4.2 CancelUSSD . . . 2288
9.48.4.3 OriginateUSSD . . . 2288
9.48.4.4 SLQSOriginateUSSD . . . 2289
9.48.4.5 SLQSVoiceALSSelectLine . . . 2289
9.48.4.6 SLQSVoiceALSSetLineSwitching . . . 2290
9.48.4.7 SLQSVoiceAnswerCall . . . 2290
9.48.4.8 SLQSVoiceBindSubscription . . . 2291
9.48.4.9 SLQSVoiceBurstDTMF . . . 2291
9.48.4.10 SLQSVoiceDialCall . . . 2292
9.48.4.11 SLQSVoiceEndCall . . . 2292
9.48.4.12 SLQSVoiceGetAllCallInfo . . . 2293
9.48.4.13 SLQSVoiceGetCallBarring . . . 2293
9.48.4.14 SLQSVoiceGetCallForwardingStatus . . . 2294
9.48.4.15 SLQSVoiceGetCallInfo . . . 2294
9.48.4.16 SLQSVoiceGetCallWaiting . . . 2295
9.48.4.17 SLQSVoiceGetCLIP . . . 2295
9.48.4.18 SLQSVoiceGetCLIR . . . 2296

9.48.4.19 SLQSVoiceGetCNAP . . . 2297
9.48.4.20 SLQSVoiceGetCOLP . . . 2297
9.48.4.21 SLQSVoiceGetCOLR . . . 2298
9.48.4.22 SLQSVoiceGetConfig . . . 2298
9.48.4.23 SLQSVoiceIndicationRegister . . . 2299
9.48.4.24 SLQSVoiceManageCalls . . . 2299
9.48.4.25 SLQSVoiceOrigUSSDNoWait . . . 2300
9.48.4.26 SLQSVoiceSendFlash . . . 2300
9.48.4.27 SLQSVoiceSetCallBarringPassword . . . 2301
9.48.4.28 SLQSVoiceSetConfig . . . 2301
9.48.4.29 SLQSVoiceSetPreferredPrivacy . . . 2302
9.48.4.30 SLQSVoiceSetSUPSService . . . 2302
9.48.4.31 SLQSVoiceStartContDTMF . . . 2303
9.48.4.32 SLQSVoiceStopContDTMF . . . 2303
9.49 qaGobiApiWds.h File Reference . . . 2304
9.49.1 Detailed Description . . . 2308
9.49.2 Macro Definition Documentation . . . 2308
9.49.2.1 IPV6_ADDRESS_ARRAY_SIZE . . . 2308
9.49.3 Typedef Documentation . . . 2308
9.49.3.1 GetProfileSettingIn . . . 2308
9.49.3.2 GetProfileSettingOut . . . 2308
9.49.3.3 QmiProfileInfo . . . 2308
9.49.3.4 QmiWDSDataBearers . . . 2309
9.49.3.5 QmiWDSDataBearerTechnology . . . 2309
9.49.3.6 slqs3GPPConfigItem . . . 2311
9.49.4 Enumeration Type Documentation . . . 2312
9.49.4.1 pdpidx . . . 2312
9.49.4.2 qmiDataBearerMasks . . . 2312
9.49.5 Function Documentation . . . 2312
9.49.5.1 GetAutoconnect . . . 2312
9.49.5.2 GetByteTotals . . . 2313
9.49.5.3 GetConnectionRate . . . 2313
9.49.5.4 GetDataBearerTechnology . . . 2314
9.49.5.5 GetDefaultProfile . . . 2315
9.49.5.6 GetDefaultProfileLTE . . . 2316
9.49.5.7 GetDefaultProfileNum . . . 2318
9.49.5.8 GetDormancyState . . . 2319
9.49.5.9 GetIPAddressLTE . . . 2319
9.49.5.10 GetLastMobileIPError . . . 2320
9.49.5.11 GetMobileIP . . . 2320

9.49.5.12 GetMobileIPProfile . . . 2321
9.49.5.13 GetPacketStatistics . . . 2322
9.49.5.14 GetPacketStatus . . . 2323
9.49.5.15 GetSessionDuration . . . 2323
9.49.5.16 GetSessionState . . . 2324
9.49.5.17 iGetByteTotals . . . 2324
9.49.5.18 iGetConnectionRate . . . 2324
9.49.5.19 iGetPacketStatistics . . . 2324
9.49.5.20 iSLQSMISetIPFamilyPreference . . . 2324
9.49.5.21 RMSetTransferStatistics . . . 2325
9.49.5.22 SetActiveMobileIPProfile . . . 2325
9.49.5.23 SetAutoconnect . . . 2325
9.49.5.24 SetDefaultProfile . . . 2326
9.49.5.25 SetDefaultProfileLTE . . . 2327
9.49.5.26 SetDefaultProfileLTEV2 . . . 2329
9.49.5.27 SetDefaultProfileNum . . . 2330
9.49.5.28 SetMobileIP . . . 2331
9.49.5.29 SetMobileIPParameters . . . 2331
9.49.5.30 SetMobileIPProfile . . . 2332
9.49.5.31 SetMuxID . . . 2333
9.49.5.32 SLQSAutoConnect . . . 2333
9.49.5.33 SLQSCreateProfile . . . 2334
9.49.5.34 SLQSDeleteProfile . . . 2334
9.49.5.35 SLQSGet3GPPConfigItem . . . 2335
9.49.5.36 SLQSGetByteTotals . . . 2335
9.49.5.37 SLQSGetConnectionRate . . . 2336
9.49.5.38 SLQSGetCurrDataSystemStat . . . 2336
9.49.5.39 SLQSGetCurrentChannelRate . . . 2337
9.49.5.40 SLQSGetDataBearerTechnology . . . 2337
9.49.5.41 SLQSGetDataBearerTechnologyExt . . . 2338
9.49.5.42 SLQSGetDUNCallInfo . . . 2338
9.49.5.43 SLQSGetPacketStatistics . . . 2339
9.49.5.44 SLQSGetProfile . . . 2339
9.49.5.45 SLQSGetProfileSettings . . . 2341
9.49.5.46 SLQSGetRuntimeSettings . . . 2341
9.49.5.47 SLQSGetSessionState . . . 2342
9.49.5.48 SLQSModifyProfile . . . 2342
9.49.5.49 SLQSResetPacketStatics . . . 2343
9.49.5.50 SLQSSet3GPPConfigItem . . . 2343
9.49.5.51 SLQSSetProfile . . . 2343

9.49.5.52 SLQSSGetDHCPv4ClientConfig . . . 2345
9.49.5.53 SLQSSGetLoopback . . . 2345
9.49.5.54 SLQSSSetDHCPv4ClientConfig . . . 2346
9.49.5.55 SLQSSSetLoopback . . . 2346
9.49.5.56 SLQSStartStopDataSession . . . 2346
9.49.5.57 SLQSWdsGoActive . . . 2347
9.49.5.58 SLQSWdsGoDormant . . . 2347
9.49.5.59 SLQSWdsSetEventReport . . . 2348
9.49.5.60 SLQSWdsSwiPDPRuntimeSettings . . . 2348
9.49.5.61 WDS_IsGobiDevice . . . 2349
9.50 qaNasGetRFBandInfo.h File Reference . . . 2349
9.50.1 Enumeration Type Documentation . . . 2349
9.50.1.1 eQMI_NAS_GET_RF_INFO_RESP . . . 2349
9.50.2 Function Documentation . . . 2349
9.50.2.1 PkQmiNasGetRFBandInfo . . . 2349
9.50.2.2 UpkQmiNasGetRFBandInfo . . . 2349
9.51 qaNasPerformNetworkScan.h File Reference . . . 2350
9.51.1 Macro Definition Documentation . . . 2350
9.51.1.1 FORBIDDEN_INDEX . . . 2350
9.51.1.2 INDEX_ZERO . . . 2350
9.51.1.3 MAX_DESCRIPTION_LENGTH . . . 2350
9.51.1.4 PREFERRED_INDEX . . . 2350
9.51.1.5 QMI_NAS_MAX_INSTANCES . . . 2350
9.51.1.6 QMI_NAS_NETSTATUS_MASK . . . 2350
9.51.1.7 ROAMING_INDEX . . . 2350
9.51.2 Enumeration Type Documentation . . . 2350
9.51.2.1 eQMI_NAS_PERFORM_NETWORK_SCAN_RESP . . . 2350
9.51.3 Function Documentation . . . 2351
9.51.3.1 PkQmiNasPerformNetworkScan . . . 2351
9.51.3.2 UpkQmiNasPerformNetworkScan . . . 2351
9.52 qmerrno.h File Reference . . . 2351
9.52.1 Enumeration Type Documentation . . . 2353
9.52.1.1 eQCWWANError . . . 2353
9.52.1.2 qm_wds_ds_profile_extended_err_codes . . . 2358
9.53 qos.h File Reference . . . 2358
9.53.1 Macro Definition Documentation . . . 2360
9.53.1.1 LITEQMI_MAX_QOS_FILTERS . . . 2360
9.53.1.2 LITEQMI_MAX_QOS_FLOW_PER_APN_STATS . . . 2360
9.53.1.3 LITEQMI_MAX_QOS_FLOWS . . . 2360
9.53.2 Function Documentation . . . 2360

9.53.2.1 pack_qos_BindDataPort . . . 2360
9.53.2.2 pack_qos_SLQSQosGetNetworkStatus . . . 2360
9.53.2.3 pack_qos_SLQSQosSwiReadApnExtraParams . . . 2361
9.53.2.4 pack_qos_SLQSQosSwiReadDataStats . . . 2362
9.53.2.5 pack_qos_SLQSSetQosEventCallback . . . 2362
9.53.2.6 unpack_qos_BindDataPort . . . 2363
9.53.2.7 unpack_qos_SLQSQosGetNetworkStatus . . . 2363
9.53.2.8 unpack_qos_SLQSQosSwiReadApnExtraParams . . . 2364
9.53.2.9 unpack_qos_SLQSQosSwiReadDataStats . . . 2364
9.53.2.10 unpack_qos_SLQSSetQosEventCallback . . . 2365
9.53.2.11 unpack_qos_SLQSSetQosEventCallback_ind . . . 2365
9.53.2.12 unpack_qos_SLQSSetQosNWStatusCallback_ind . . . 2366
9.53.2.13 unpack_qos_SLQSSetQosPriEventCallback_ind . . . 2367
9.53.2.14 unpack_qos_SLQSSetQosStatusCallback_ind . . . 2367
9.54 rms.h File Reference . . . 2368
9.54.1 Macro Definition Documentation . . . 2368
9.54.1.1 __LITEQMI_RMS_H__ . . . 2368
9.54.2 Function Documentation . . . 2368
9.54.2.1 pack_rms_GetSMSWake . . . 2368
9.54.2.2 pack_rms_SetSMSWake . . . 2369
9.54.2.3 unpack_rms_GetSMSWake . . . 2369
9.54.2.4 unpack_rms_SetSMSWake . . . 2369
9.55 sar.h File Reference . . . 2370
9.55.1 Typedef Documentation . . . 2370
9.55.1.1 unpack_sar_SLQSSetRfSarState_t . . . 2370
9.55.2 Function Documentation . . . 2370
9.55.2.1 pack_sar_SLQSGetRfSarState . . . 2370
9.55.2.2 pack_sar_SLQSSetRfSarState . . . 2371
9.55.2.3 unpack_sar_SLQSGetRfSarState . . . 2371
9.55.2.4 unpack_sar_SLQSSetRfSarState . . . 2371
9.56 sms.h File Reference . . . 2372
9.56.1 Macro Definition Documentation . . . 2375
9.56.1.1 MAX_CDMA_ENC_MO_TXT_MSG_SIZE . . . 2375
9.56.1.2 MAX_MS_TRANSFER_ROUTE_MSG . . . 2375
9.56.1.3 MAX_MSC_ADDRESS_SIZE . . . 2375
9.56.1.4 MAX_MSE_TWS_MSG . . . 2375
9.56.1.5 MAX_SMS_LIST_SIZE . . . 2375
9.56.1.6 MAX_SMS_MESSAGE_SIZE . . . 2375
9.56.1.7 SMS_CONFIG_LEN . . . 2376
9.56.1.8 SMS_MAX_SMS_ROUTES . . . 2376

9.56.1.9 SMS_NUM_OF_SET . . . 2376
9.56.1.10 SMSC_TYPE_LEN . . . 2376
9.56.2 Enumeration Type Documentation . . . 2376
9.56.2.1 eqmiCbkSetStatus . . . 2376
9.56.3 Function Documentation . . . 2376
9.56.3.1 pack_sms_GetSMSCAddress . . . 2376
9.56.3.2 pack_sms_SaveSMS . . . 2376
9.56.3.3 pack_sms_SendSMS . . . 2377
9.56.3.4 pack_sms_SetNewSMSCallback . . . 2377
9.56.3.5 pack_sms_SetSMSCAddress . . . 2377
9.56.3.6 pack_sms_SLQSDeleteSMS . . . 2378
9.56.3.7 pack_sms_SLQSGetIndicationRegister . . . 2378
9.56.3.8 pack_sms_SLQSGetMessageWaiting . . . 2378
9.56.3.9 pack_sms_SLQSGetSMS . . . 2379
9.56.3.10 pack_sms_SLQSGetSmsBroadcastConfig . . . 2379
9.56.3.11 pack_sms_SLQSGetSMSList . . . 2379
9.56.3.12 pack_sms_SLQSGetTransLayerInfo . . . 2380
9.56.3.13 pack_sms_SLQSGetTransNWRegInfo . . . 2380
9.56.3.14 pack_sms_SLQSModifySMSStatus . . . 2380
9.56.3.15 pack_sms_SLQSSendAsyncSMS . . . 2381
9.56.3.16 pack_sms_SLQSSetIndicationRegister . . . 2381
9.56.3.17 pack_sms_SLQSSetSmsBroadcastActivation . . . 2382
9.56.3.18 pack_sms_SLQSSetSmsBroadcastConfig . . . 2382
9.56.3.19 pack_sms_SLQSSetSmsStorage . . . 2382
9.56.3.20 pack_sms_SLQSSmsGetMaxStorageSize . . . 2383
9.56.3.21 pack_sms_SLQSSmsGetMessageProtocol . . . 2383
9.56.3.22 pack_sms_SLQSSmsSetRoutes . . . 2383
9.56.3.23 pack_sms_SLQSSwiGetSMSStorage . . . 2384
9.56.3.24 unpack_sms_GetSMSCAddress . . . 2384
9.56.3.25 unpack_sms_SaveSMS . . . 2384
9.56.3.26 unpack_sms_SendSMS . . . 2385
9.56.3.27 unpack_sms_SetNewSMSCallback . . . 2385
9.56.3.28 unpack_sms_SetNewSMSCallback_ind . . . 2385
9.56.3.29 unpack_sms_SetSMSCAddress . . . 2386
9.56.3.30 unpack_sms_SLQSDeleteSMS . . . 2386
9.56.3.31 unpack_sms_SLQSGetIndicationRegister . . . 2387
9.56.3.32 unpack_sms_SLQSGetMessageWaiting . . . 2387
9.56.3.33 unpack_sms_SLQSGetSMS . . . 2387
9.56.3.34 unpack_sms_SLQSGetSmsBroadcastConfig . . . 2388
9.56.3.35 unpack_sms_SLQSGetSMSList . . . 2388

9.56.3.36 unpack_sms_SLQSGetTransLayerInfo . . . 2388
9.56.3.37 unpack_sms_SLQSGetTransNWRegInfo . . . 2389
9.56.3.38 unpack_sms_SLQSModifySMSStatus . . . 2389
9.56.3.39 unpack_sms_SLQSNWRegInfoCallback_ind . . . 2389
9.56.3.40 unpack_sms_SLQSSendAsyncSMS . . . 2390
9.56.3.41 unpack_sms_SLQSSetIndicationRegister . . . 2390
9.56.3.42 unpack_sms_SLQSSetSmsBroadcastActivation . . . 2390
9.56.3.43 unpack_sms_SLQSSetSmsBroadcastConfig . . . 2391
9.56.3.44 unpack_sms_SLQSSetSmsStorage . . . 2391
9.56.3.45 unpack_sms_SLQSSmsGetMaxStorageSize . . . 2391
9.56.3.46 unpack_sms_SLQSSmsGetMessageProtocol . . . 2392
9.56.3.47 unpack_sms_SLQSSmsSetRoutes . . . 2392
9.56.3.48 unpack_sms_SLQSSwiGetSMSStorage . . . 2393
9.56.3.49 unpack_sms_SLQSTransLayerInfoCallback_ind . . . 2393
9.56.3.50 unpack_sms_SLQSWmsAsyncRawSendCallBack_ind . . . 2393
9.56.3.51 unpack_sms_SLQSWmsMemoryFullCallBack_ind . . . 2394
9.56.3.52 unpack_sms_SLQSWmsMessageWaitingCallBack_ind . . . 2394
9.57 SwiDataTypes.h File Reference . . . 2394
9.57.1 Detailed Description . . . 2395
9.57.2 Macro Definition Documentation . . . 2395
9.57.2.1 MEMSET_STATIC_OUTPUT_STRUCT . . . 2395
9.57.2.2 QMI_NO_LTE_FW_SUPPORT . . . 2395
9.57.2.3 QMI_TLV_PLACEHOLDER . . . 2395
9.57.2.4 SWI_API . . . 2395
9.57.2.5 UNUSEDPARAM . . . 2395
9.57.3 Typedef Documentation . . . 2395
9.57.3.1 BOOL . . . 2395
9.57.3.2 BYTE . . . 2395
9.57.3.3 CHAR . . . 2395
9.57.3.4 FLOAT . . . 2396
9.57.3.5 INT32 . . . 2396
9.57.3.6 INT8 . . . 2396
9.57.3.7 LPCSTR . . . 2396
9.57.3.8 qmuint16 . . . 2396
9.57.3.9 qmulong . . . 2396
9.57.3.10 SHORT . . . 2396
9.57.3.11 ULONG . . . 2396
9.57.3.12 ULONGLONG . . . 2396
9.57.3.13 USHORT . . . 2396
9.57.3.14 WORD . . . 2396

9.58 swidms.h File Reference . . . 2396
9.58.1 Typedef Documentation . . . 2397
9.58.1.1 unpack_swidms_SLQSSwiDmsSetUsbNetNum_t . . . 2397
9.58.2 Function Documentation . . . 2397
9.58.2.1 pack_swidms_SLQSSwiDmsGetHWWatchdog . . . 2397
9.58.2.2 pack_swidms_SLQSSwiDmsGetMTU . . . 2398
9.58.2.3 pack_swidms_SLQSSwiDmsGetSecureInfo . . . 2398
9.58.2.4 pack_swidms_SLQSSwiDmsGetUsbComp . . . 2398
9.58.2.5 pack_swidms_SLQSSwiDmsGetUsbNetNum . . . 2399
9.58.2.6 pack_swidms_SLQSSwiDmsSetHWWatchdog . . . 2399
9.58.2.7 pack_swidms_SLQSSwiDmsSetMTU . . . 2399
9.58.2.8 pack_swidms_SLQSSwiDmsSetUsbComp . . . 2400
9.58.2.9 pack_swidms_SLQSSwiDmsSetUsbNetNum . . . 2400
9.58.2.10 unpack_swidms_SLQSSwiDmsGetHWWatchdog . . . 2400
9.58.2.11 unpack_swidms_SLQSSwiDmsGetMTU . . . 2401
9.58.2.12 unpack_swidms_SLQSSwiDmsGetSecureInfo . . . 2401
9.58.2.13 unpack_swidms_SLQSSwiDmsGetUsbComp . . . 2402
9.58.2.14 unpack_swidms_SLQSSwiDmsGetUsbNetNum . . . 2402
9.58.2.15 unpack_swidms_SLQSSwiDmsSetHWWatchdog . . . 2402
9.58.2.16 unpack_swidms_SLQSSwiDmsSetMTU . . . 2403
9.58.2.17 unpack_swidms_SLQSSwiDmsSetUsbComp . . . 2403
9.58.2.18 unpack_swidms_SLQSSwiDmsSetUsbNetNum . . . 2403
9.59 swiloc.h File Reference . . . 2404
9.59.1 Typedef Documentation . . . 2404
9.59.1.1 unpack_swiloc_SwiLocSetAutoStart_t . . . 2404
9.59.2 Function Documentation . . . 2404
9.59.2.1 pack_swiloc_SwiLocGetAutoStart . . . 2404
9.59.2.2 pack_swiloc_SwiLocSetAutoStart . . . 2405
9.59.2.3 unpack_swiloc_SwiLocGetAutoStart . . . 2405
9.59.2.4 unpack_swiloc_SwiLocSetAutoStart . . . 2405
9.60 swioma.h File Reference . . . 2406
9.60.1 Macro Definition Documentation . . . 2407
9.60.1.1 LITEQMI_MAX_SWIOMA_STR_LEN . . . 2407
9.60.2 Typedef Documentation . . . 2407
9.60.2.1 unpack_swioma_SLQSOMADMAlertCallback_t . . . 2407
9.60.2.2 unpack_swioma_SLQSOMADMCancelSession_t . . . 2407
9.60.2.3 unpack_swioma_SLQSOMADMSendSelection_t . . . 2407
9.60.2.4 unpack_swioma_SLQSOMADMSetSettings_t . . . 2407
9.60.3 Function Documentation . . . 2407
9.60.3.1 pack_swioma_SLQSOMADMAlertCallback . . . 2407

9.60.3.2 pack_swioma_SLQSOMADMCancelSession . . . 2408
9.60.3.3 pack_swioma_SLQSOMADMGetSessionInfo . . . 2408
9.60.3.4 pack_swioma_SLQSOMADMGetSettings . . . 2409
9.60.3.5 pack_swioma_SLQSOMADMSendSelection . . . 2409
9.60.3.6 pack_swioma_SLQSOMADMSetSettings . . . 2410
9.60.3.7 pack_swioma_SLQSOMADMStartSession . . . 2411
9.60.3.8 unpack_swioma_SLQSOMADMAlertCallback . . . 2411
9.60.3.9 unpack_swioma_SLQSOMADMAlertCallback_ind . . . 2412
9.60.3.10 unpack_swioma_SLQSOMADMCancelSession . . . 2412
9.60.3.11 unpack_swioma_SLQSOMADMGetSessionInfo . . . 2413
9.60.3.12 unpack_swioma_SLQSOMADMGetSettings . . . 2413
9.60.3.13 unpack_swioma_SLQSOMADMSendSelection . . . 2414
9.60.3.14 unpack_swioma_SLQSOMADMSetSettings . . . 2414
9.60.3.15 unpack_swioma_SLQSOMADMStartSession . . . 2415
9.61 switype_256bit.h File Reference . . . 2415
9.61.1 Macro Definition Documentation . . . 2415
9.61.1.1 SWI_UINT256_BIT_OFFSET . . . 2415
9.61.1.2 SWI_UINT256_BITS_PER_WORD . . . 2415
9.61.1.3 SWI_UINT256_INT_VALUE . . . 2416
9.61.1.4 SWI_UINT256_WORD_COUNT . . . 2416
9.61.1.5 SWI_UINT256_WORD_OFFSET . . . 2416
9.61.2 Function Documentation . . . 2416
9.61.2.1 swi_uint256_clear_bit . . . 2416
9.61.2.2 swi_uint256_get_bit . . . 2416
9.61.2.3 swi_uint256_print_mask . . . 2416
9.61.2.4 swi_uint256_set_bit . . . 2416
9.62 SWIWWANCMAPI.h File Reference . . . 2416
9.63 uim.h File Reference . . . 2417
9.63.1 Macro Definition Documentation . . . 2420
9.63.1.1 MAX_DESCRIPTION_LENGTH . . . 2420
9.63.1.2 MAX_ICCID_LENGTH . . . 2420
9.63.1.3 MAX_NO_OF_APPLICATIONS . . . 2420
9.63.1.4 MAX_NO_OF_SLOTS . . . 2420
9.63.1.5 MAX_SLOTS_STATUS . . . 2420
9.63.1.6 UIM_MAX_ACTIVE_PERS_FEATURES . . . 2420
9.63.1.7 UIM_MAX_CONTENT_LENGTH . . . 2420
9.63.1.8 UIM_MAX_DESCRIPTION_LENGTH . . . 2420
9.63.1.9 UIM_MAX_NO_OF_APPLICATIONS . . . 2420
9.63.1.10 UIM_MAX_NO_OF_SLOTS . . . 2420
9.63.1.11 UIM_UINT8_MAX_STRING_SZ . . . 2420

9.63.2 Typedef Documentation . . . 2420
9.63.2.1 unpack_uim_SLQSUIMPowerDown_t . . . 2420
9.63.2.2 unpack_uim_SLQSUIMPowerUp_t . . . 2420
9.63.2.3 unpack_uim_SLQSUIMRefreshComplete_t . . . 2420
9.63.2.4 unpack_uim_SLQSUIMRefreshOK_t . . . 2420
9.63.2.5 unpack_uim_SLQSUIMRefreshRegister_t . . . 2420
9.63.2.6 unpack_uim_SLQSUIMReset_t . . . 2420
9.63.2.7 unpack_uim_SLQSUIMSwitchSlot_t . . . 2420
9.63.3 Function Documentation . . . 2421
9.63.3.1 pack_uim_ChangePin . . . 2421
9.63.3.2 pack_uim_GetCardStatus . . . 2421
9.63.3.3 pack_uim_ReadTransparent . . . 2421
9.63.3.4 pack_uim_SetPinProtection . . . 2422
9.63.3.5 pack_uim_SLQSUIMAuthenticate . . . 2422
9.63.3.6 pack_uim_SLQSUIMDepersonalization . . . 2422
9.63.3.7 pack_uim_SLQSUIMEventRegister . . . 2423
9.63.3.8 pack_uim_SLQSUIMGetConfiguration . . . 2423
9.63.3.9 pack_uim_SLQSUIMGetFileAttributes . . . 2424
9.63.3.10 pack_uim_SLQSUIMGetSlotsStatus . . . 2424
9.63.3.11 pack_uim_SLQSUIMPowerDown . . . 2424
9.63.3.12 pack_uim_SLQSUIMPowerUp . . . 2425
9.63.3.13 pack_uim_SLQSUIMRefreshComplete . . . 2425
9.63.3.14 pack_uim_SLQSUIMRefreshGetLastEvent . . . 2425
9.63.3.15 pack_uim_SLQSUIMRefreshOK . . . 2426
9.63.3.16 pack_uim_SLQSUIMRefreshRegister . . . 2426
9.63.3.17 pack_uim_SLQSUIMReset . . . 2426
9.63.3.18 pack_uim_SLQSUIMSwitchSlot . . . 2427
9.63.3.19 pack_uim_UnblockPin . . . 2427
9.63.3.20 pack_uim_VerifyPin . . . 2428
9.63.3.21 unpack_uim_ChangePin . . . 2428
9.63.3.22 unpack_uim_GetCardStatus . . . 2428
9.63.3.23 unpack_uim_GetCardStatusV2 . . . 2429
9.63.3.24 unpack_uim_ReadTransparent . . . 2429
9.63.3.25 unpack_uim_SetPinProtection . . . 2429
9.63.3.26 unpack_uim_SetUimSlotStatusChangeCallback_ind . . . 2430
9.63.3.27 unpack_uim_SLQSUIMAuthenticate . . . 2430
9.63.3.28 unpack_uim_SLQSUIMDepersonalization . . . 2430
9.63.3.29 unpack_uim_SLQSUIMEventRegister . . . 2431
9.63.3.30 unpack_uim_SLQSUIMGetConfiguration . . . 2431
9.63.3.31 unpack_uim_SLQSUIMGetFileAttributes . . . 2432

9.63.3.32 unpack_uim_SLQSUIMGetSlotsStatus . . . 2432
9.63.3.33 unpack_uim_SLQSUIMPowerDown . . . 2432
9.63.3.34 unpack_uim_SLQSUIMPowerUp . . . 2433
9.63.3.35 unpack_uim_SLQSUIMRefreshCallback_Ind . . . 2433
9.63.3.36 unpack_uim_SLQSUIMRefreshComplete . . . 2433
9.63.3.37 unpack_uim_SLQSUIMRefreshGetLastEvent . . . 2434
9.63.3.38 unpack_uim_SLQSUIMRefreshOK . . . 2434
9.63.3.39 unpack_uim_SLQSUIMRefreshRegister . . . 2434
9.63.3.40 unpack_uim_SLQSUIMReset . . . 2435
9.63.3.41 unpack_uim_SLQSUIMSetStatusChangeCallBack_ind . . . 2435
9.63.3.42 unpack_uim_SLQSUIMSwitchSlot . . . 2435
9.63.3.43 unpack_uim_UnblockPin . . . 2436
9.63.3.44 unpack_uim_UnblockPinV2 . . . 2436
9.63.3.45 unpack_uim_VerifyPin . . . 2436
9.64 voice.h File Reference . . . 2437
9.64.1 Detailed Description . . . 2442
9.64.2 S1 . . . 2442
9.64.3 Macro Definition Documentation . . . 2442
9.64.3.1 BARRING_PASSWORD_LENGTH . . . 2442
9.64.3.2 MAX_VOICE_CALL_NO_LEN . . . 2442
9.64.3.3 MAX_VOICE_DESCRIPTION_LENGTH . . . 2442
9.64.3.4 MAXVOICEUSSDLENGTH . . . 2442
9.64.3.5 VOICE_MAX_NO_OF_CALLS . . . 2443
9.64.4 Typedef Documentation . . . 2443
9.64.4.1 unpack_voice_AnswerUSSD_t . . . 2443
9.64.4.2 unpack_voice_CancelUSSD_t . . . 2443
9.64.4.3 unpack_voice_OriginateUSSD_t . . . 2443
9.64.4.4 unpack_voice_SLQSVoiceALSSelectLine_t . . . 2443
9.64.4.5 unpack_voice_SLQSVoiceALSSetLineSwitching_t . . . 2443
9.64.4.6 unpack_voice_SLQSVoiceBindSubscription_t . . . 2443
9.64.4.7 unpack_voice_SLQSVoiceIndicationRegister_t . . . 2443
9.64.4.8 unpack_voice_SLQSVoiceOrigUSSDNoWait_t . . . 2443
9.64.4.9 unpack_voice_SLQSVoiceSetPreferredPrivacy_t . . . 2443
9.64.5 Enumeration Type Documentation . . . 2443
9.64.5.1 liteServiceClassInformation . . . 2443
9.64.6 Function Documentation . . . 2443
9.64.6.1 pack_voice_AnswerUSSD . . . 2443
9.64.6.2 pack_voice_CancelUSSD . . . 2444
9.64.6.3 pack_voice_OriginateUSSD . . . 2444
9.64.6.4 pack_voice_SLQSOriginateUSSD . . . 2444

9.64.6.5 pack_voice_SLQSVoiceALSSelectLine . . . 2445
9.64.6.6 pack_voice_SLQSVoiceALSSetLineSwitching . . . 2445
9.64.6.7 pack_voice_SLQSVoiceAnswerCall . . . 2446
9.64.6.8 pack_voice_SLQSVoiceBindSubscription . . . 2446
9.64.6.9 pack_voice_SLQSVoiceBurstDTMF . . . 2446
9.64.6.10 pack_voice_SLQSVoiceDialCall . . . 2447
9.64.6.11 pack_voice_SLQSVoiceEndCall . . . 2447
9.64.6.12 pack_voice_SLQSVoiceGetAllCallInfo . . . 2447
9.64.6.13 pack_voice_SLQSVoiceGetCallBarring . . . 2448
9.64.6.14 pack_voice_SLQSVoiceGetCallForwardingStatus . . . 2448
9.64.6.15 pack_voice_SLQSVoiceGetCallInfo . . . 2449
9.64.6.16 pack_voice_SLQSVoiceGetCallWaiting . . . 2449
9.64.6.17 pack_voice_SLQSVoiceGetCLIP . . . 2449
9.64.6.18 pack_voice_SLQSVoiceGetCLIR . . . 2450
9.64.6.19 pack_voice_SLQSVoiceGetCNAP . . . 2450
9.64.6.20 pack_voice_SLQSVoiceGetCOLP . . . 2450
9.64.6.21 pack_voice_SLQSVoiceGetCOLR . . . 2451
9.64.6.22 pack_voice_SLQSVoiceGetConfig . . . 2451
9.64.6.23 pack_voice_SLQSVoiceIndicationRegister . . . 2451
9.64.6.24 pack_voice_SLQSVoiceManageCalls . . . 2452
9.64.6.25 pack_voice_SLQSVoiceOrigUSSDNoWait . . . 2452
9.64.6.26 pack_voice_SLQSVoiceSendFlash . . . 2452
9.64.6.27 pack_voice_SLQSVoiceSetCallBarringPassword . . . 2453
9.64.6.28 pack_voice_SLQSVoiceSetConfig . . . 2453
9.64.6.29 pack_voice_SLQSVoiceSetPreferredPrivacy . . . 2454
9.64.6.30 pack_voice_SLQSVoiceSetSUPSService . . . 2454
9.64.6.31 pack_voice_SLQSVoiceStartContDTMF . . . 2454
9.64.6.32 pack_voice_SLQSVoiceStopContDTMF . . . 2455
9.64.6.33 unpack_voice_allCallStatusCallback_ind . . . 2455
9.64.6.34 unpack_voice_AnswerUSSD . . . 2455
9.64.6.35 unpack_voice_CancelUSSD . . . 2456
9.64.6.36 unpack_voice_DTMFEventCallback_ind . . . 2456
9.64.6.37 unpack_voice_OriginateUSSD . . . 2456
9.64.6.38 unpack_voice_OTASPStatusCallback_ind . . . 2457
9.64.6.39 unpack_voice_SLQSOriginateUSSD . . . 2457
9.64.6.40 unpack_voice_SLQSVoiceALSSelectLine . . . 2458
9.64.6.41 unpack_voice_SLQSVoiceALSSetLineSwitching . . . 2458
9.64.6.42 unpack_voice_SLQSVoiceAnswerCall . . . 2458
9.64.6.43 unpack_voice_SLQSVoiceBindSubscription . . . 2459
9.64.6.44 unpack_voice_SLQSVoiceBurstDTMF . . . 2459

9.64.6.45 unpack_voice_SLQSVoiceDialCall . . . 2459
9.64.6.46 unpack_voice_SLQSVoiceEndCall . . . 2460
9.64.6.47 unpack_voice_SLQSVoiceGetAllCallInfo . . . 2460
9.64.6.48 unpack_voice_SLQSVoiceGetCallBarring . . . 2460
9.64.6.49 unpack_voice_SLQSVoiceGetCallForwardingStatus . . . 2461
9.64.6.50 unpack_voice_SLQSVoiceGetCallInfo . . . 2461
9.64.6.51 unpack_voice_SLQSVoiceGetCallWaiting . . . 2461
9.64.6.52 unpack_voice_SLQSVoiceGetCLIP . . . 2462
9.64.6.53 unpack_voice_SLQSVoiceGetCLIR . . . 2462
9.64.6.54 unpack_voice_SLQSVoiceGetCNAP . . . 2462
9.64.6.55 unpack_voice_SLQSVoiceGetCOLP . . . 2463
9.64.6.56 unpack_voice_SLQSVoiceGetCOLR . . . 2463
9.64.6.57 unpack_voice_SLQSVoiceGetConfig . . . 2463
9.64.6.58 unpack_voice_SLQSVoiceIndicationRegister . . . 2464
9.64.6.59 unpack_voice_SLQSVoiceManageCalls . . . 2464
9.64.6.60 unpack_voice_SLQSVoiceOrigUSSDNoWait . . . 2464
9.64.6.61 unpack_voice_SLQSVoiceSendFlash . . . 2465
9.64.6.62 unpack_voice_SLQSVoiceSetCallBarringPassword . . . 2465
9.64.6.63 unpack_voice_SLQSVoiceSetConfig . . . 2465
9.64.6.64 unpack_voice_SLQSVoiceSetPreferredPrivacy . . . 2466
9.64.6.65 unpack_voice_SLQSVoiceSetSUPSService . . . 2466
9.64.6.66 unpack_voice_SLQSVoiceStartContDTMF . . . 2466
9.64.6.67 unpack_voice_SLQSVoiceStopContDTMF . . . 2467
9.64.6.68 unpack_voice_SLQSVoiceSUPSCallback_ind . . . 2467
9.64.6.69 unpack_voice_SUPSNotificationCallback_ind . . . 2467
9.64.6.70 unpack_voice_USSDNotificationCallback_ind . . . 2468
9.64.6.71 unpack_voice_VoiceInfoRecCallback_ind . . . 2468
9.64.6.72 unpack_voice_voicePrivacyChangeCallback_ind . . . 2469
9.65 wds.h File Reference . . . 2469
9.65.1 Detailed Description . . . 2475
9.65.2 SO Mask . . . 2475
9.65.3 RAT Mask . . . 2476
9.65.4 Macro Definition Documentation . . . 2477
9.65.4.1 BYT_STAT_STAT_MASK . . . 2477
9.65.4.2 IPV6_ADDRESS_ARRAY_SIZE . . . 2477
9.65.4.3 MAX_WDS_3GPP_CONF_LTE_ATTACH_PROFILE_LIST_SIZE . . . 2477
9.65.4.4 PACK_WDS_IPV4 . . . 2477
9.65.4.5 PACK_WDS_IPV6 . . . 2477
9.65.4.6 WDS_DHCP_MAX_NUM_OPTIONS . . . 2477
9.65.4.7 WDS_DHCP_OPTION_DATA_BUF_SIZE . . . 2477

9.65.4.8 WDS_PROFILE_3GPP . . . 2477
9.65.4.9 WDS_PROFILE_3GPP2 . . . 2477
9.65.4.10 WDS_TFTID_SOURCE_IP_SIZE . . . 2477
9.65.5 Typedef Documentation . . . 2477
9.65.5.1 unpack_wds_DHCPv4ClientLeaseChange_t . . . 2477
9.65.5.2 unpack_wds_RMTransferStatistics_ind_t . . . 2477
9.65.5.3 unpack_wds_SetAutoconnect_t . . . 2477
9.65.5.4 unpack_wds_SetDefaultProfile_t . . . 2477
9.65.5.5 unpack_wds_SetDefaultProfileNum_t . . . 2477
9.65.5.6 unpack_wds_SetMobileIP_t . . . 2477
9.65.5.7 unpack_wds_SetMobileIPParameters_t . . . 2477
9.65.5.8 unpack_wds_SetMuxID_t . . . 2477
9.65.5.9 unpack_wds_SLQSResetPacketStatics_t . . . 2477
9.65.5.10 unpack_wds_SLQSSet3GPPConfigItem_t . . . 2477
9.65.5.11 unpack_wds_SLQSSetWdsEventCallback_t . . . 2477
9.65.5.12 unpack_wds_SLQSSSetDHCPv4ClientConfig_t . . . 2477
9.65.5.13 unpack_wds_SLQSSSetLoopback_t . . . 2477
9.65.5.14 unpack_wds_SLQSStopDataSession_t . . . 2477
9.65.5.15 unpack_wds_SLQSWdsGoActive_t . . . 2477
9.65.5.16 unpack_wds_SLQSWdsGoDormant_t . . . 2477
9.65.5.17 unpack_wds_SLQSWdsSetEventReport_t . . . 2478
9.65.5.18 UnpackQmiProfileInfo . . . 2478
9.65.6 Enumeration Type Documentation . . . 2478
9.65.6.1 liteQmiDataBearerMasks . . . 2478
9.65.7 Function Documentation . . . 2478
9.65.7.1 pack_wds_DHCPv4ClientLeaseChange . . . 2478
9.65.7.2 pack_wds_GetAutoconnect . . . 2478
9.65.7.3 pack_wds_GetByteTotals . . . 2479
9.65.7.4 pack_wds_GetConnectionRate . . . 2479
9.65.7.5 pack_wds_GetDataBearerTechnology . . . 2480
9.65.7.6 pack_wds_GetDefaultProfile . . . 2480
9.65.7.7 pack_wds_GetDefaultProfileNum . . . 2481
9.65.7.8 pack_wds_GetDormancyState . . . 2481
9.65.7.9 pack_wds_GetLastMobileIPError . . . 2481
9.65.7.10 pack_wds_GetMobileIP . . . 2482
9.65.7.11 pack_wds_GetMobileIPProfile . . . 2482
9.65.7.12 pack_wds_GetPacketStatistics . . . 2483
9.65.7.13 pack_wds_GetPacketStatus . . . 2483
9.65.7.14 pack_wds_GetSessionDuration . . . 2484
9.65.7.15 pack_wds_GetSessionState . . . 2484

9.65.7.16 pack_wds_RMSetTransferStatistics . . . 2484
9.65.7.17 pack_wds_SetAutoconnect . . . 2485
9.65.7.18 pack_wds_SetDefaultProfile . . . 2485
9.65.7.19 pack_wds_SetDefaultProfileNum . . . 2486
9.65.7.20 pack_wds_SetMobileIP . . . 2486
9.65.7.21 pack_wds_SetMobileIPParameters . . . 2486
9.65.7.22 pack_wds_SetMobileIPProfile . . . 2487
9.65.7.23 pack_wds_SetMuxID . . . 2487
9.65.7.24 pack_wds_SLQSCreateProfile . . . 2488
9.65.7.25 pack_wds_SLQSDeleteProfile . . . 2488
9.65.7.26 pack_wds_SLQSGet3GPPConfigItem . . . 2488
9.65.7.27 pack_wds_SLQSGetCurrDataSystemStat . . . 2489
9.65.7.28 pack_wds_SLQSGetCurrentChannelRate . . . 2489
9.65.7.29 pack_wds_SLQSGetDataBearerTechnology . . . 2490
9.65.7.30 pack_wds_SLQSGetDUNCallInfo . . . 2490
9.65.7.31 pack_wds_SLQSGetProfileSettings . . . 2491
9.65.7.32 pack_wds_SLQSGetRuntimeSettings . . . 2491
9.65.7.33 pack_wds_SLQSModifyProfile . . . 2492
9.65.7.34 pack_wds_SLQSResetPacketStatics . . . 2492
9.65.7.35 pack_wds_SLQSSet3GPPConfigItem . . . 2492
9.65.7.36 pack_wds_SLQSSetIPFamilyPreference . . . 2493
9.65.7.37 pack_wds_SLQSSetWdsEventCallback . . . 2493
9.65.7.38 pack_wds_SLQSSGetDHCPv4ClientConfig . . . 2494
9.65.7.39 pack_wds_SLQSSGetLoopback . . . 2494
9.65.7.40 pack_wds_SLQSSSetDHCPv4ClientConfig . . . 2494
9.65.7.41 pack_wds_SLQSSSetLoopback . . . 2495
9.65.7.42 pack_wds_SLQSStartDataSession . . . 2495
9.65.7.43 pack_wds_SLQSStopDataSession . . . 2496
9.65.7.44 pack_wds_SLQSWdsGoActive . . . 2496
9.65.7.45 pack_wds_SLQSWdsGoDormant . . . 2496
9.65.7.46 pack_wds_SLQSWdsSetEventReport . . . 2497
9.65.7.47 pack_wds_SLQSWdsSwiPDPRuntimeSettings . . . 2497
9.65.7.48 unpack_wds_DHCPv4ClientLease_ind . . . 2498
9.65.7.49 unpack_wds_DHCPv4ClientLeaseChange . . . 2498
9.65.7.50 unpack_wds_GetAutoconnect . . . 2498
9.65.7.51 unpack_wds_GetByteTotals . . . 2499
9.65.7.52 unpack_wds_GetConnectionRate . . . 2499
9.65.7.53 unpack_wds_GetDataBearerTechnology . . . 2499
9.65.7.54 unpack_wds_GetDefaultProfile . . . 2500
9.65.7.55 unpack_wds_GetDefaultProfileNum . . . 2500

9.65.7.56 unpack_wds_GetDormancyState . . . 2500
9.65.7.57 unpack_wds_GetLastMobileIPError . . . 2501
9.65.7.58 unpack_wds_GetMobileIP . . . 2501
9.65.7.59 unpack_wds_GetMobileIPProfile . . . 2501
9.65.7.60 unpack_wds_GetPacketStatistics . . . 2502
9.65.7.61 unpack_wds_GetPacketStatus . . . 2502
9.65.7.62 unpack_wds_GetSessionDuration . . . 2502
9.65.7.63 unpack_wds_GetSessionState . . . 2503
9.65.7.64 unpack_wds_RMSetTransferStatistics . . . 2503
9.65.7.65 unpack_wds_RMTransferStatistics_ind . . . 2503
9.65.7.66 unpack_wds_SetAutoconnect . . . 2504
9.65.7.67 unpack_wds_SetDefaultProfile . . . 2504
9.65.7.68 unpack_wds_SetDefaultProfileNum . . . 2504
9.65.7.69 unpack_wds_SetMobileIP . . . 2505
9.65.7.70 unpack_wds_SetMobileIPParameters . . . 2505
9.65.7.71 unpack_wds_SetMobileIPProfile . . . 2505
9.65.7.72 unpack_wds_SetMuxID . . . 2506
9.65.7.73 unpack_wds_SLQSCreateProfile . . . 2506
9.65.7.74 unpack_wds_SLQSDeleteProfile . . . 2506
9.65.7.75 unpack_wds_SLQSDUNCallInfoCallBack_ind . . . 2507
9.65.7.76 unpack_wds_SLQSGet3GPPConfigItem . . . 2507
9.65.7.77 unpack_wds_SLQSGetCurrDataSystemStat . . . 2507
9.65.7.78 unpack_wds_SLQSGetCurrentChannelRate . . . 2508
9.65.7.79 unpack_wds_SLQSGetDataBearerTechnology . . . 2508
9.65.7.80 unpack_wds_SLQSGetDUNCallInfo . . . 2508
9.65.7.81 unpack_wds_SLQSGetProfileSettings . . . 2509
9.65.7.82 unpack_wds_SLQSGetRuntimeSettings . . . 2509
9.65.7.83 unpack_wds_SLQSModifyProfile . . . 2509
9.65.7.84 unpack_wds_SLQSResetPacketStatics . . . 2510
9.65.7.85 unpack_wds_SLQSSet3GPPConfigItem . . . 2510
9.65.7.86 unpack_wds_SLQSSetIPFamilyPreference . . . 2510
9.65.7.87 unpack_wds_SLQSSetPacketSrvStatusCallback . . . 2511
9.65.7.88 unpack_wds_SLQSSetWdsEventCallback . . . 2511
9.65.7.89 unpack_wds_SLQSSetWdsEventCallback_ind . . . 2511
9.65.7.90 unpack_wds_SLQSSGetDHCPv4ClientConfig . . . 2512
9.65.7.91 unpack_wds_SLQSSGetLoopback . . . 2512
9.65.7.92 unpack_wds_SLQSSSetDHCPv4ClientConfig . . . 2512
9.65.7.93 unpack_wds_SLQSSSetLoopback . . . 2513
9.65.7.94 unpack_wds_SLQSStartDataSession . . . 2513
9.65.7.95 unpack_wds_SLQSStopDataSession . . . 2513

9.65.7.96 unpack_wds_SLQSWdsGoActive 2514
9.65.7.97 unpack_wds_SLQSWdsGoDormant 2514
9.65.7.98 unpack_wds_SLQSWdsSetEventReport 2514
9.65.7.99 unpack_wds_SLQSWdsSwiPDPRuntimeSettings 2515

Index **2516**

Chapter 1

Welcome to the Sierra Wireless Linux QMI SDK API Reference Guide

This API reference guide contains information about all the modules, in the Sierra Wireless Linux QMI SDK (SLQS). Use the tabs at the top of the page to navigate the reference guide.

- Modules tab – lists all the service modules and provides a link to the API header file in each module.
- References tab – links to reference material.

1.1 Important Notice

Due to the nature of wireless communications, transmission and reception of data can never be guaranteed. Data may be delayed, corrupted (i.e., have errors) or be totally lost. Although significant delays or losses of data are rare when wireless devices such as the Sierra Wireless modem are used in a normal manner with a well-constructed network, the Sierra Wireless modem should not be used in situations where failure to transmit or receive data could result in damage of any kind to the user or any other party, including but not limited to personal injury, death, or loss of property. Sierra Wireless accepts no responsibility for damages of any kind resulting from delays or errors in data transmitted or received using the Sierra Wireless modem, or for failure of the Sierra Wireless modem to transmit or receive such data.

1.2 Limitation of Liability

The information in this manual is subject to change without notice and does not represent a commitment on the part of Sierra Wireless. SIERRA WIRELESS AND ITS AFFILIATES SPECIFICALLY DISCLAIM LIABILITY FOR ANY AND ALL DIRECT, INDIRECT, SPECIAL, GENERAL, INCIDENTAL, CONSEQUENTIAL, PUNITIVE OR EXEMPLARY DAMAGES INCLUDING, BUT NOT LIMITED TO, LOSS OF PROFITS OR REVENUE OR ANTICIPATED PROFITS OR REVENUE ARISING OUT OF THE USE OR INABILITY TO USE ANY SIERRA WIRELESS PRODUCT, EVEN IF SIERRA WIRELESS AND/OR ITS AFFILIATES HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES OR THEY ARE FORESEEABLE OR FOR CLAIMS BY ANY THIRD PARTY.

Notwithstanding the foregoing, in no event shall Sierra Wireless and/or its affiliates aggregate liability arising under or in connection with the Sierra Wireless product, regardless of the number of events, occurrences, or claims giving rise to liability, be in excess of the price paid by the purchaser for the Sierra Wireless product.

1.3 Patents

Patents This product may contain technology developed by or for Sierra Wireless Inc. This product includes technology licensed from QUALCOMM® 3G. This product is manufactured or sold by Sierra Wireless Inc. or its affiliates

under one or more patents licensed from InterDigital Group.

1.4 Copyright

© 2011-2015 Sierra Wireless. All rights reserved.

1.5 Trademarks

AirCard® and Heart of the Wireless Machine® are registered trademarks of Sierra Wireless. Watcher® is a trademark of Sierra Wireless, registered in the European Community. Sierra Wireless, the Sierra Wireless logo, the red wave design, and the red-tipped antenna are trademarks of Sierra Wireless. Windows® is a registered trademark of Microsoft Corporation. QUALCOMM® is a registered trademark of QUALCOMM Incorporated. Used under license. Linux is a registered trademark of Linus Torvalds. Other trademarks are the property of the respective owners.

1.6 Contact Information

If you have any questions about the Sierra Wireless Linux SDK, contact your Sierra Wireless account manager.

Consult our website for up-to-date product descriptions, documentation, application notes, firmware upgrades, troubleshooting tips, and press releases: http://www.sierrawireless.com.

Chapter 2

Module Index

2.1 Modules

Here is a list of all modules:

Device Connectivity Service (DCS) 43
Wireless Data Service (WDS) 44
Device Management Service (DMS) 45
Network Access Service (NAS) 46
CallBacK registration (CBK) 47
Short Message Service (SMS) 48
Position Determination Service (PDS) 49
Card Application Toolkit (CAT) 50
Remote Management Service (RMS) 51
Firmware Management Service (FMS) 52
Open Mobile Alliance Service (OMA) 53
Specific Absorption Rate (SAR) 54
SWI Open Mobile Alliance Service (SWIOMA) 55
Voice Service (VOICE) 56
Non-service specific APIs (SWI) 57
User Identity Module Service (UIM) 58
Audio Service (AUDIO) 59
Quality of Service (QOS) 60
IMS Service (IMS) 61
SWI Audio Service(SWIAUDIO) 62
Location Service(LOC) 63
Thermal Mitigation Device(TMD) 64
AVMS (SWIAVMS) 65
SWIDMS 66

Chapter 3

Namespace Index

3.1 Namespace List

Here is a list of all namespaces with brief descriptions:

Tables 67

Chapter 4

Data Structure Index

4.1 Data Structures

Here are the data structures with brief descriptions:

_getIndicationRegResp . . . 69
_GetProfileSettingIn . . . 70
_GetProfileSettingOut . . . 70
_getResetInfoNotification . . . 71
_getTransLayerInfoResp . . . 72
_getTransNWRegInfoResp . . . 72
_MitigationDevInfo . . . 73
_modemTempNotification . . . 73
_modemUIMStatusNotification . . . 74
_packetSrvStatus . . . 75
_qaQmi3GPP2BroadcastCfgInfo . . . 77
_qaQmi3GPPBroadcastCfgInfo . . . 77
_QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp . . . 78
_QmiSwiAvmsEventReportConfigResp . . . 80
_QmiSwiAvmsEventReportConnectionRequestResp . . . 81
_QmiSwiAvmsEventReportDataSessionStatusResp . . . 81
_QmiSwiAvmsEventReportHTTPStatusResp . . . 82
_QmiSwiAvmsEventReportNotificationResp . . . 84
_QmiSwiAvmsEventReportPackageIDResp . . . 85
_QmiSwiAvmsEventReportRegStatusResp . . . 85
_QmiSwiAvmsEventReportSessionTypeResp . . . 85
_QmiSwiAvmsEventReportWAMSParamChangeResp . . . 86
_QmiSwiAvmsSetSettingsAPNInfo . . . 86
_QmiSwiAvmsSetSettingsConnectionRetryTimers . . . 87
_QmiSwiAvmsSetSettingsPeriodInfo . . . 87
_setIndicationRegReq . . . 87
_slqs3GPPConfigItem . . . 88
_SLQSAVMSSetSettingsReqPara . . . 90
_SLQSAVMSSetSettingsReqPara_v2 . . . 92
_SLQSAVMSSettings . . . 94
_SLQSAVMSSettings_v2 . . . 95
_SLQSAVMSSettingsAPNInfo . . . 95
_SLQSAVMSSettingsConnectionRetryTimers . . . 96
_SLQSAVMSSettingsPeriodsInfo . . . 96
SlqsNas3GppNetworkRAT . . . 96
_slqsNetworkScanInfo . . . 97
_slqsNetworkScanInfoReq . . . 99
_SLQSOMADMSessionInfo . . . 102

_SLQSOMADMSettings . . . 104
_SLQSOMADMSettingsReqParams . . . 106
_SLQSOMADMSettingsReqParams3 . . . 107
_SLQSSwiGetHostDevInfoParams . . . 108
_SLQSSwiGetOSInfoParams . . . 109
_SLQSSwiGetSerialNoExtParams . . . 110
_SLQSSwiSetHostDevInfoParams . . . 110
_SLQSSwiSetOSInfoParams . . . 112
_SwiAvmsEventInd . . . 112
_sysSelectPrefExtInfo . . . 113
_sysSelectPrefInfo . . . 115
_sysSelectPrefParams . . . 120
_transLayerinfo . . . 126
_transLayerInfoNotification . . . 126
_transNWRegInfoNotification . . . 127
accelAcceptReady_s . . . 128
accelTempAcceptReady_s . . . 128
acqOrderPref . . . 129
AcqOrderPrefTlv . . . 130
ActPilotPNElement . . . 131
AddCDMASysInfo . . . 131
AddSysInfo . . . 132
airTimer . . . 132
allCallsAlphaIDInfo . . . 133
allCallsDiagInfo . . . 133
allCallsUUSInfo . . . 134
alphaIDInfo . . . 134
altitudeSrcInfo . . . 135
altSrcInfo_t . . . 136
appStats . . . 137
appStatus . . . 140
arrAlertingPattern . . . 143
arrAlertingType . . . 144
arrAlphaID . . . 145
arrCalledPartyNum . . . 145
arrCallEndReason . . . 146
arrCallInfo . . . 147
arrConnectPartyNum . . . 147
arrDiagInfo . . . 148
arrRedirPartyNum . . . 148
arrRemotePartyName . . . 149
arrRemotePartyNum . . . 149
arrSvcOption . . . 150
arrUUSInfo . . . 151
authenticateResult . . . 151
authenticationData . . . 152
BandCapabilityResp . . . 153
BandPrefTlv . . . 156
BdsSV . . . 157
BdsSVInfo . . . 157
BroadcastConfig . . . 158
burstDTMFInfo . . . 158
CallBarringSysInfo . . . 159
callBarStatus . . . 160
calledPartyInfo . . . 161
calledPartySubAdd . . . 162
callerIDInfo . . . 163
callFwdTypeAndPlan . . . 164

callFWExtInfo . . . 165
callFWInfo . . . 167
callInfo . . . 168
callingPartyInfo . . . 169
cardResult . . . 171
cardStatus . . . 171
CarrierImage_t . . . 173
CatAlPhaIdentifierTlv . . . 174
CatCommonEventTlv . . . 174
CatEndProactiveSessionTlv . . . 175
CATEventDataType . . . 175
CatEventIDDataTlv . . . 175
CatEventListTlv . . . 176
CatRefreshTlv . . . 176
ccSUPSType . . . 177
CDMABroadcastConfig . . . 177
CDMAChannel . . . 178
CDMAECIOThresh . . . 179
CDMAInfo . . . 179
cdmaMsgDecodingParams . . . 180
cdmaMsgDecodingParamsExt . . . 183
cdmaMsgEncodingParams . . . 187
CDMARSSIThresh . . . 188
cdmaSSInfo . . . 189
CDMASSInfo . . . 189
CDMASysInfo . . . 190
CDMASysInfoExt . . . 194
CellDb . . . 194
cellParams . . . 195
changeUIMPIN . . . 196
ChannelRate . . . 197
channelRate . . . 198
ciotAcqOrderPref . . . 198
CiotAcqOrderPrefTlv . . . 199
CiotLteOpModePrefTlv . . . 200
CLIPResp . . . 200
CLIRResp . . . 201
ClkInfo . . . 202
CNAPResp . . . 203
COLPResp . . . 204
COLRResp . . . 205
CommInfo . . . 205
connectionStatus . . . 207
ConnectionStatus . . . 208
connectNumInfo . . . 208
CrashInfo . . . 210
CrashInfoParams . . . 211
crashInfoParams . . . 212
crashInformation . . . 212
CreateProfileIn . . . 213
CreateProfileOut . . . 214
CsgId . . . 215
CSGID . . . 215
CUGInfo . . . 216
curAMRConfig . . . 217
CurrDataSysStat . . . 218
currentCatEvent . . . 219
CurrentImgList . . . 219

currentPLMN . . . 220
CurrImageInfo . . . 221
CurrNetworkInfo . . . 222
currNetworkInfo . . . 224
custFeaturesInfo . . . 224
custFeaturesSetting . . . 227
custSettingInfo . . . 228
custSettingList . . . 229
dataBearers . . . 230
DataBearerTech . . . 230
DataBearerTechExt . . . 232
dataBearerTechnology . . . 233
dataRate . . . 235
dataSrvCapabilities . . . 235
DataStatusDetail . . . 236
DataULongLongTlv . . . 238
DataULongTlv . . . 238
DcsUsbPortNames . . . 238
delAssistDataStatus . . . 238
depersonalizationInformation . . . 239
detailSvcInfo . . . 240
DeviceConfigDetail . . . 242
DHCPOption . . . 243
DHCPOptionList . . . 243
diagInfo . . . 244
dirNum . . . 244
dms_ActivationStatusTlv . . . 245
dms_OperatingModeTlv . . . 246
dms_PSMActiveTimerIndTlv . . . 246
dms_PSMActiveTimerTlv . . . 247
dms_PSMDurationDueToOOSTlv . . . 247
dms_PSMDurationThresholdTlv . . . 248
dms_PSMEarlyWakeupTimeTlv . . . 248
dms_PSMEnableStateIndTlv . . . 249
dms_PSMEnableStateTlv . . . 249
dms_PSMPeriodicUpdateTimerIndTlv . . . 250
dms_PSMPeriodicUpdateTimerTlv . . . 250
dms_PSMRandomizationWindowTlv . . . 251
dms_TemperatureTlv . . . 251
dms_UimAutoSwitchActSlotTlv . . . 252
dms_UimStatusTlv . . . 253
dms_VoltageTlv . . . 253
dmsCurrentPRLInfo . . . 254
DMScustSettingInfo . . . 255
DMScustSettingList . . . 256
DMSgetCustomFeatureV2 . . . 256
DMSgetCustomInput . . . 257
dmsIndicationRegisterReq . . . 257
dmsPsmCfgParamChange . . . 258
dmsSwiGetPCInfo . . . 259
dmsSwiGetResetInfo . . . 260
dmsSwiGetUIMSelection . . . 261
Domain . . . 262
DomainNameList . . . 262
DRCParams . . . 263
DTMFInfo . . . 263
DTMFLengths . . . 264
DUNCallInfoInd . . . 265

dunchannelRate . . . 265
ecioListElement . . . 266
ECIOThresh . . . 267
ECTNum . . . 267
EdrxCiotLteMode . . . 268
EdrxCycleLength . . . 269
EdrxEnableType . . . 269
EdrxPagingTimeWindow . . . 270
EdrxRatType . . . 270
ehrpdMTUSizeTlv . . . 271
encryptedPIN1 . . . 272
eriDataparams . . . 272
ERIFileparams . . . 273
errorRateListElement . . . 273
eTWSPLMNInfoTlv . . . 274
extDispRecInfo . . . 275
FactorySequenceNumber . . . 275
fileAttributes . . . 276
fileInfo . . . 279
FirmwareUpdatStat . . . 280
FMSImageElement . . . 282
FMSImageIdElement . . . 282
FMSImageIDEntries . . . 283
FMSImageList . . . 284
FMSPrefImageList . . . 285
ForbiddenNetworks3GPP . . . 285
fwinfo_s . . . 286
GERANInfo . . . 287
geranInstInfo . . . 289
getAllCallInformation . . . 289
getAllCallRmtPtyName . . . 290
getAllCallRmtPtyNum . . . 291
GetAudioPathConfigReq . . . 291
GetAudioPathConfigResp . . . 292
GetAudioProfileReq . . . 294
GetAudioProfileResp . . . 294
GetAudioVolTLBConfigReq . . . 296
GetAudioVolTLBConfigResp . . . 296
getCallFWExtInfo . . . 297
getCallFWInfo . . . 297
getCustomFeatureV2 . . . 298
getCustomInput . . . 299
getDUNCallInfoReq . . . 299
getDUNCallInfoResp . . . 301
getDyingGaspCfg . . . 303
getDyingGaspStatistics . . . 304
GetErrRateResp . . . 305
GetHRPDStatsResp . . . 306
GetIMSSMSConfigParams . . . 306
GetIMSUserConfigParams . . . 307
GetIMSVoIPConfigResp . . . 308
GetInstIDResp . . . 310
GetM2MAudioProfileReq . . . 311
GetM2MAudioProfileResp . . . 311
GetM2MAudioVolumeReq . . . 312
GetM2MAudioVolumeResp . . . 313
GetM2MAVMuteReq . . . 313
GetM2MAVMuteResp . . . 314

GetM2MSpkrGainReq . . . 314
GetM2MSpkrGainResp . . . 315
getMsgWaitingInfo . . . 315
GetNetworkTimeResp . . . 316
GetRegMgrConfigParams . . . 316
GetSessionIDResp . . . 317
GetSIPConfigResp . . . 317
GnssData . . . 319
gnssSvInfoNotification . . . 320
GPRSQoS . . . 321
GPRSRequestedQoS . . . 322
GPSStateInfo . . . 323
gpsTime_s . . . 327
gsmCellInfo . . . 327
GSMRSSIThresh . . . 329
GSMSrvStatusInfo . . . 329
GSMSysInfo . . . 330
gyroAcceptReady_s . . . 333
gyroTempAcceptReady_s . . . 334
HDRECIOThresh . . . 334
HDRIOThresh . . . 335
HDRPersonalityInd . . . 335
HDRPersonalityResp . . . 336
HDRProtSubtypResp . . . 336
HDRRSSIThresh . . . 337
HDRSINRThresh . . . 338
HDRSINRThreshold . . . 338
hdrSSInfo . . . 339
HDRSSInfo . . . 340
HDRSysInfo . . . 341
homeSIDNID . . . 343
hotSwapStatus . . . 344
hrpdMTUSizeTlv . . . 344
image_info_t . . . 345
ImageElement . . . 346
ImageIdElement . . . 346
ImageIDEntries . . . 347
ImageList . . . 348
IMSAIndRegisterInfo . . . 349
imsaPdpStatusInfo . . . 350
imsaRatStatusInfo . . . 350
IMSARegistrationStatus . . . 351
imsaRegStatusInfo . . . 352
IMSAServiceStatus . . . 352
IMSASupportedFieldsResp . . . 355
IMSASupportedMsgInfo . . . 355
imsaSvcStatusInfo . . . 356
imsCfgIndRegisterInfo . . . 357
imsRegMgrConfigInfo . . . 358
imsSIPConfigInfo . . . 359
imsSMSConfigInfo . . . 360
imsUserConfigInfo . . . 361
imsVoIPConfigInfo . . . 361
IndFieldsList . . . 363
infoInterFreq . . . 364
intfaceCfgTlv . . . 365
IOThresh . . . 366
IPv4Addr . . . 367

IPv4Config . . . 367
IPv4Info . . . 368
IPv6Addr . . . 368
ipv6AddressInfo . . . 369
IPV6AddressInfo . . . 369
IPv6Config . . . 370
IPV6GWAddressInfo . . . 370
IPv6Info . . . 371
IPv6TrafCls . . . 372
LibPackGPRSRequestedQoS . . . 372
LibpackProfile3GPP . . . 373
LibpackProfile3GPP2 . . . 380
LibPackprofile_3GPP . . . 386
LibPackprofile_3GPP2 . . . 392
LibPackQosClassID . . . 397
LibPackTFTIDParams . . . 398
LibPackUMTSQoS . . . 400
LibPackUMTSReqQoSSigInd . . . 403
lineCtrlInfo . . . 403
loc_accelAcceptReady . . . 404
loc_accelTempAcceptReady . . . 405
loc_BdsSV . . . 405
loc_BdsSVInfo . . . 406
loc_CellDb . . . 406
loc_ClkInfo . . . 407
loc_GnssData . . . 408
loc_gpsTime . . . 410
loc_gyroAcceptReady . . . 410
loc_gyroTempAcceptReady . . . 411
loc_IPv4Config . . . 412
loc_IPv4Info . . . 412
loc_IPv6Config . . . 413
loc_IPv6Info . . . 413
loc_LocApplicationInfo . . . 414
loc_precisionDilution . . . 415
loc_satelliteInfo . . . 416
loc_sensorDataUsage . . . 418
loc_SV . . . 419
loc_SVInfo . . . 420
loc_svUsedforFix . . . 420
loc_urlAddr . . . 421
loc_URLAddrInfo . . . 421
LocApplicationInfo . . . 422
LocDelAssDataReq . . . 423
LOCEventRegisterReqResp . . . 424
LOCExtPowerStateReqResp . . . 426
LocGetServerReq . . . 426
LocInjectPositionReq . . . 427
LocInjectSensorDataReq . . . 431
LocSetCradleMountReq . . . 432
LocSetServerReq . . . 433
LOCStartReq . . . 434
LOCStopReq . . . 436
lteBandPrefExt . . . 436
LteCiotOpModeTlv . . . 437
LteCQIParm . . . 437
lteEARFCN . . . 438
lteGsmCellInfo . . . 439

LTEInfo . . . 440
LTEInfoInterfreq . . . 443
LTEInfoIntrafreq . . . 443
LTEInfoNeighboringGSM . . . 445
LTEInfoNeighboringWCDMA . . . 446
LteM1BandPrefTlv . . . 447
LteNasReleaseInfo_s . . . 449
LteNb1BandPrefTlv . . . 449
LTEOperationMode . . . 451
LteOpMode . . . 451
lteOpModeTlv . . . 452
ltePCI . . . 453
lteRsrpinformation . . . 454
LTERSRPThresh . . . 454
LTERSRQThresh . . . 455
LTERSSIThresh . . . 455
LteSccRxInfoResp . . . 456
LTESigRptCfg . . . 456
LTESigRptConfig . . . 457
lteSnrinformation . . . 458
LTESNRThresh . . . 458
LTESNRThreshold . . . 459
lteSSInfo . . . 460
LTESSInfo . . . 460
LTESysInfo . . . 461
lteWcdmaCellInfo . . . 464
messageModeTlv . . . 465
messageWaitingInfoContent . . . 465
minBasedIMSI . . . 466
mitigationDevList . . . 467
MNRInfo . . . 467
ModifyProfileIn . . . 468
ModifyProfileOut . . . 469
msgWaitingInfo . . . 469
mtuSize3gppTlv . . . 470
MTUSizeReq . . . 470
namName . . . 471
nas_acqOrderPref . . . 471
nas_AcqOrderPrefTlv . . . 472
nas_ActPilotPNElement . . . 473
nas_AddCDMASysInfo . . . 473
nas_AddSysInfo . . . 474
nas_BandPrefInfoTlv . . . 474
nas_BandPrefTlv . . . 475
nas_CallBarringSysInfo . . . 477
nas_callBarStatus . . . 477
nas_CDMAChannel . . . 478
nas_CDMAECIOThresh . . . 479
nas_CDMAInfo . . . 480
nas_CDMARSSIThresh . . . 481
nas_CDMASysInfo . . . 481
nas_CDMASysInfoExt . . . 485
nas_cellParams . . . 485
nas_ciotAcqOrderPref . . . 486
nas_CiotAcqOrderPrefTlv . . . 487
nas_CiotLteOpModePrefTlv . . . 488
nas_CommInfo . . . 488
nas_CsgId . . . 490

nas_CSGID . . . 490
nas_currentPLMN . . . 491
nas_dataSrvCapabilities . . . 492
nas_DataStatusDetail . . . 493
nas_detailSvcInfo . . . 495
nas_DeviceConfigDetail . . . 496
nas_dirNum . . . 497
nas_DRCParams . . . 497
nas_ecioListElement . . . 498
nas_ECIOThresh . . . 499
nas_EdrxCiotLteMode . . . 499
nas_EdrxCycleLength . . . 500
nas_EdrxEnableType . . . 500
nas_EdrxPagingTimeWindow . . . 501
nas_EdrxRatType . . . 501
nas_EmerModeTlv . . . 502
nas_errorRateListElement . . . 503
nas_ForbiddenNetworks3GPP . . . 504
nas_GERANInfo . . . 505
nas_geranInstInfo . . . 506
nas_gsmCellInfo . . . 507
nas_GSMRSSIThresh . . . 508
nas_GSMSrvStatusInfo . . . 509
nas_GSMSysInfo . . . 510
nas_GWAcqOrderPrefTlv . . . 513
nas_HDRECIOThresh . . . 513
nas_HDRIOThresh . . . 514
nas_HDRPersonality_Ind_Data . . . 514
nas_HDRRSSIThresh . . . 515
nas_HDRSINRThresh . . . 516
nas_HDRSINRThreshold . . . 516
nas_HDRSysInfo . . . 517
nas_homeSIDNID . . . 519
nas_infoInterFreq . . . 519
nas_IOThresh . . . 521
nas_lteBandPrefExt . . . 521
nas_LTEBandPrefTlv . . . 522
nas_LteCiotOpModeTlv . . . 524
nas_lteEARFCN . . . 524
nas_lteGsmCellInfo . . . 525
nas_LTEInfo . . . 526
nas_LTEInfoInterfreq . . . 529
nas_LTEInfoIntrafreq . . . 529
nas_LTEInfoNeighboringGSM . . . 531
nas_LTEInfoNeighboringWCDMA . . . 532
nas_LteM1BandPrefTlv . . . 533
nas_LteNb1BandPrefTlv . . . 535
nas_LTEOperationMode . . . 537
nas_LteOpMode . . . 537
nas_lteOpModeTlv . . . 538
nas_ltePCI . . . 539
nas_lteRsrpinformation . . . 539
nas_LTERSRPThresh . . . 540
nas_LTERSRQThresh . . . 540
nas_LTERSSIThresh . . . 541
nas_LTESigRptCfg . . . 542
nas_LTESigRptConfig . . . 542
nas_lteSnrinformation . . . 543

nas_LTESNRThresh . . . 544
nas_LTESNRThreshold . . . 544
nas_LTESysInfo . . . 545
nas_lteWcdmaCellInfo . . . 547
nas_minBasedIMSI . . . 548
nas_MNRInfo . . . 549
nas_ModePrefTlv . . . 550
nas_namName . . . 550
nas_netSelectionPref . . . 551
nas_NetSelPrefTlv . . . 552
nas_NetworkStat1x . . . 552
nas_NetworkStatEVDO . . . 554
nas_nmrCellInfo . . . 556
nas_nr5gBandPref . . . 557
nas_NR5GCellStatusTlv . . . 558
nas_NR5GSerStatTlv . . . 559
nas_NR5GSystemInfoTlv . . . 560
nas_operatorNameString . . . 563
nas_OperatorPLMNData . . . 563
nas_operatorPLMNList . . . 564
nas_PhyCaAggPcellInfo . . . 565
nas_PhyCaAggScellDlBw . . . 566
nas_PhyCaAggScellIndex . . . 566
nas_PhyCaAggScellIndType . . . 567
nas_PhyCaAggScellInfo . . . 568
nas_PilotSetData . . . 570
nas_PilotSetParams . . . 571
nas_PlmnID . . . 571
nas_PLMNNetworkName . . . 572
nas_PLMNNetworkNameData . . . 572
nas_PRLPrefTlv . . . 574
nas_protocolSubtypeElement . . . 575
nas_qaQmi3Gpp2TimeZone . . . 576
nas_QmiNas3GppNetworkInfo . . . 577
nas_QmiNas3GppNetworkRAT . . . 578
nas_QmisNasPcsDigit . . . 579
nas_QmisNasSlqsNasPCICellInfo . . . 580
nas_QmisNasSlqsNasPCIInfo . . . 581
nas_RankIndicatorTlv . . . 582
nas_RatDisabledMaskTlv . . . 582
nas_RejectReasonTlv . . . 583
nas_RFBandInfoElements . . . 583
nas_RfBandInfoExtFormat . . . 584
nas_RfBandInfoExtFormatElements . . . 585
nas_RfBandInfoList . . . 586
nas_RfBandwidthInfo . . . 586
nas_RfBandwidthInfoElements . . . 587
nas_RfDedicatedBandInfo . . . 588
nas_RfDedicatedBandInfoElements . . . 588
nas_RFInfoTlv . . . 589
nas_roamIndList . . . 590
nas_RoamPrefTlv . . . 591
nas_RSRPThresh . . . 591
nas_rsrqInformation . . . 592
nas_RSRQThresh . . . 592
nas_RSSIThresh . . . 593
nas_rxInfo . . . 594
nas_RxSigInfo . . . 595

nas_rxSignalStrengthListElement . . . 596
nas_SccRxInfo . . . 597
nas_serviceProviderName . . . 598
nas_servSystem . . . 599
nas_sidNid . . . 600
nas_SignalStrengthTlv . . . 601
nas_SLQSSignalStrengthsIndReq . . . 601
nas_SLQSSignalStrengthsInformation . . . 603
nas_SLQSSignalStrengthsTlv . . . 604
nas_SrvDomainPrefTlv . . . 605
nas_SrvStatusInfo . . . 605
nas_sysInfoCommon . . . 606
nas_TDSCDMAECIOThresh . . . 609
nas_TDSCDMARSCPThresh . . . 609
nas_TDSCDMARSSIThresh . . . 610
nas_TDSCDMASINRCONFThresh . . . 610
nas_TDSCDMASINRThresh . . . 611
nas_timeInfo . . . 611
nas_trueIMSI . . . 613
nas_txInfo . . . 614
nas_UMTSInfo . . . 614
nas_UMTSinstInfo . . . 616
nas_umtsLTENbrCell . . . 617
nas_UniversalTime . . . 618
nas_wcdmaCellInfo . . . 619
nas_WCDMAECIOThresh . . . 620
nas_WCDMAInfoLTENeighborCell . . . 620
nas_WCDMARSSIThresh . . . 621
nas_WCDMASysInfo . . . 622
nas_wcdmaUARFCN . . . 625
NASAcqOrderPrefTlv . . . 626
NASBandPreferenceTlv . . . 626
nasCellLocationInfoResp . . . 627
NASCiotAcqOrderPrefTlv . . . 628
NASCiotLteOpModePrefTlv . . . 628
NASEmergencyModeTlv . . . 629
nasGet3GPP2SubscriptionInfoReq . . . 629
nasGet3GPP2SubscriptionInfoResp . . . 630
nasGeteDRXParamsReq . . . 631
nasGeteDRXParamsResp . . . 631
nasGetForbiddenNetworksResp . . . 634
nasGetHDRColorCodeResp . . . 634
nasGetLTECphyCa . . . 634
NasGetLTECphyCaInfo . . . 635
nasGetLTECphyCaResp . . . 636
NasGetRFInfoResp . . . 637
nasGetSigInfoResp . . . 637
nasGetSysInfoResp . . . 638
nasGetTxRxInfoReq . . . 642
nasGetTxRxInfoResp . . . 642
NASGWAcqOrderPrefTlv . . . 643
nasIndicationRegisterReq . . . 643
nasInitNetworkReg . . . 646
NASLTEBandPreferenceTlv . . . 647
NASLteM1BandPrefTlv . . . 648
NASLteNasReleaseInfoTlv . . . 648
NASLteNB1BandPrefTlv . . . 649
NASModePreferenceTlv . . . 649

NASNetSelPreferenceTlv . . . 650
nasNetworkReject . . . 650
nasNetworkTime . . . 653
NASNr5gBandPrefTlv . . . 654
nasOperatorNameResp . . . 655
NASOTAMessageTlv . . . 655
NASPhyCaAggPcellInfo . . . 656
NASPhyCaAggScellArray . . . 657
NASPhyCaAggScellDlBw . . . 659
NASPhyCaAggScellIndex . . . 659
NASPhyCaAggScellIndType . . . 660
NASPhyCaAggScellInfo . . . 660
nasPLMNNameReq . . . 661
nasPLMNNameResp . . . 662
NASPRLPreferenceTlv . . . 665
NASQmiCbkNasSwiOTAMessageInd . . . 665
NASQmiCbkNasSystemSelPrefInd . . . 666
NASRatDisabledMaskTlv . . . 668
NASRoamPreferenceTlv . . . 668
NASServDomainPrefTlv . . . 669
NASServingSystemInfo . . . 669
nasSeteDRXParamsReq . . . 671
nasSigInfo . . . 672
nasSwiGetChannelLockResp . . . 673
NasSwiIndReg . . . 674
nasSwiSetChannelLockReq . . . 675
nasSysInfo . . . 676
NASTimeInfoTlv . . . 679
nasTimers . . . 680
netSelectionPref . . . 681
NetStats . . . 681
NetworkDebugResp . . . 682
NetworkStat1x . . . 683
NetworkStatEVDO . . . 685
newMTMessageTlv . . . 687
newPwdData . . . 687
nmrCellInfo . . . 688
nr5gBandPref . . . 689
NR5GCellStatusTlv . . . 690
NR5GSerStatTlv . . . 691
NR5GSystemInfoTlv . . . 692
NSSAudioCtrl . . . 695
NWProfile . . . 696
omaDmConfigTlv . . . 696
omaDmConfigTlvExt . . . 697
omaDmFotaTlv . . . 699
omaDmFotaTlvExt . . . 701
omaDmNotificationsTlv . . . 703
operatorNameString . . . 704
OperatorPLMNData . . . 705
operatorPLMNList . . . 705
pack_dms_ActivateAutomatic_t . . . 706
pack_dms_GetCustFeaturesV2_t . . . 706
pack_dms_ResetToFactoryDefaults_t . . . 707
pack_dms_SetActivationStatusCallback_t . . . 707
pack_dms_SetCrashAction_t . . . 708
pack_dms_SetCustFeature_t . . . 708
pack_dms_SetCustFeaturesV2_t . . . 710

pack_dms_SetEventReport_t . . . 711
pack_dms_SetIndicationRegister_t . . . 712
pack_dms_SetPower_t . . . 712
pack_dms_SetUSBComp_t . . . 713
pack_dms_SLQSDmsSwiIndicationRegister_t . . . 714
pack_dms_SLQSSetPowerSaveModeConfig_t . . . 715
pack_dms_SLQSSwiGetCrashInfo_t . . . 715
pack_dms_SLQSSwiSetDyingGaspCfg_t . . . 716
pack_dms_SLQSSwiSetHostDevInfo_t . . . 716
pack_dms_SLQSSwiSetOSInfo_t . . . 717
pack_dms_SwiSetEventReport_t . . . 718
pack_dms_SwiUimSelect_t . . . 719
pack_dms_UIMChangePIN_t . . . 719
pack_dms_UIMGetControlKeyStatus_t . . . 720
pack_dms_UIMGetICCID_t . . . 720
pack_dms_UIMSetControlKeyProtection_t . . . 721
pack_dms_UIMSetPINProtection_t . . . 721
pack_dms_UIMUnblockControlKey_t . . . 722
pack_dms_UIMUnblockPIN_t . . . 723
pack_dms_UIMVerifyPIN_t . . . 723
pack_fms_GetImagesPreference_t . . . 724
pack_fms_GetStoredImages_t . . . 724
pack_fms_SetImagesPreference_t . . . 725
pack_loc_Delete_Assist_Data_t . . . 725
pack_loc_EventRegister_t . . . 726
pack_loc_SetExtPowerState_t . . . 729
pack_loc_SetOperationMode_t . . . 729
pack_loc_SLQSLOCGetBestAvailPos_t . . . 730
pack_loc_SLQSLOCGetServer_t . . . 731
pack_loc_SLQSLOCInjectPosition_t . . . 731
pack_loc_SLQSLOCInjectSensorData_t . . . 736
pack_loc_SLQSLOCInjectUTCTime_t . . . 738
pack_loc_SLQSLOCSetCradleMountConfig_t . . . 738
pack_loc_SLQSLOCSetServer_t . . . 739
pack_loc_Start_t . . . 740
pack_loc_Stop_t . . . 742
pack_nas_InitiateDomainAttach_t . . . 742
pack_nas_PerformNetworkScanPCI_t . . . 743
pack_nas_SetACCOLC_t . . . 743
pack_nas_SetCDMANetworkParameters_t . . . 743
pack_nas_SetNetworkPreference_t . . . 745
pack_nas_SLQSConfigSigInfo_t . . . 746
pack_nas_SLQSGetPLMNName_t . . . 747
pack_nas_SLQSInitiateNetworkRegistration_t . . . 748
pack_nas_SLQSNasConfigSigInfo2_t . . . 749
pack_nas_SLQSNasGet3GPP2Subscription_t . . . 754
pack_nas_SLQSNASGeteDRXParamsExt_t . . . 754
pack_nas_SLQSNasGetTxRxInfo_t . . . 755
pack_nas_SLQSNasIndicationRegisterExt_t . . . 756
pack_nas_SLQSNASSeteDRXParams_t . . . 759
pack_nas_SLQSNasSwiIndicationRegister_t . . . 760
pack_nas_SLQSNASSwiSetChannelLock_t . . . 762
pack_nas_SLQSSetBandPreference_t . . . 762
pack_nas_SLQSSetSignalStrengthsCallback_t . . . 764
pack_nas_SLQSSetSysSelectionPref_t . . . 764
pack_nas_SLQSSetSysSelectionPrefExt_t . . . 770
pack_nas_SLQSSwiPSDetach_t . . . 780
pack_pds_PDSInjectTimeReference_t . . . 780

pack_pds_ResetPDSData_t . . . 781
pack_pds_SetEventReportCallback_t . . . 782
pack_pds_SetPDSDefaults_t . . . 782
pack_pds_SetPDSState_t . . . 783
pack_pds_SetPortAutomaticTracking_t . . . 783
pack_pds_SetServiceAutomaticTracking_t . . . 784
pack_pds_SetXTRAAutomaticDownload_t . . . 784
pack_pds_SetXTRANetwork_t . . . 785
pack_pds_SLQSGetAGPSConfig_t . . . 785
pack_pds_SLQSPDSInjectAbsoluteTimeReference_t . . . 786
pack_pds_SLQSPDSInjectPositionData_t . . . 787
pack_pds_SLQSSetAGPSConfig_t . . . 789
pack_pds_SLQSSetPositionMethodState_t . . . 789
pack_pds_StartPDSTrackingSessionExt_t . . . 790
pack_qmi_t . . . 791
pack_qos_BindDataPort_t . . . 792
pack_qos_SLQSQosSwiReadApnExtraParams_t . . . 793
pack_qos_SLQSQosSwiReadDataStats_t . . . 793
pack_qos_SLQSSetQosEventCallback_t . . . 793
pack_rms_SetSMSWake_t . . . 794
pack_sar_SLQSSetRfSarState_t . . . 794
pack_sms_SaveSMS_t . . . 795
pack_sms_SendSMS_t . . . 796
pack_sms_SetNewSMSCallback_t . . . 797
pack_sms_SetSMSCAddress_t . . . 797
pack_sms_SLQSDeleteSMS_t . . . 797
pack_sms_SLQSGetSMS_t . . . 798
pack_sms_SLQSGetSmsBroadcastConfig_t . . . 799
pack_sms_SLQSGetSMSList_t . . . 799
pack_sms_SLQSModifySMSStatus_t . . . 800
pack_sms_SLQSSendAsyncSMS_t . . . 801
pack_sms_SLQSSetIndicationRegister_t . . . 801
pack_sms_SLQSSetSmsBroadcastActivation_t . . . 802
pack_sms_SLQSSetSmsBroadcastConfig_t . . . 802
pack_sms_SLQSSetSmsStorage_t . . . 803
pack_sms_SLQSSmsGetMaxStorageSize_t . . . 804
pack_sms_SLQSSmsSetRoutes_t . . . 804
pack_swidms_SLQSSwiDmsSetHWWatchdog_t . . . 804
pack_swidms_SLQSSwiDmsSetMTU_t . . . 805
pack_swidms_SLQSSwiDmsSetUsbComp_t . . . 805
pack_swidms_SLQSSwiDmsSetUsbNetNum_t . . . 806
pack_swiloc_SwiLocSetAutoStart_t . . . 807
pack_swioma_SLQSOMADMCancelSession_t . . . 808
pack_swioma_SLQSOMADMGetSessionInfo_t . . . 809
pack_swioma_SLQSOMADMSendSelection_t . . . 809
pack_swioma_SLQSOMADMSetSettings_t . . . 810
pack_swioma_SLQSOMADMStartSession_t . . . 811
pack_uim_ChangePin_t . . . 811
pack_uim_ReadTransparent_t . . . 812
pack_uim_SetPinProtection_t . . . 814
pack_uim_SLQSUIMAuthenticate_t . . . 815
pack_uim_SLQSUIMDepersonalization_t . . . 815
pack_uim_SLQSUIMEventRegister_t . . . 816
pack_uim_SLQSUIMGetConfiguration_t . . . 816
pack_uim_SLQSUIMGetFileAttributes_t . . . 817
pack_uim_SLQSUIMPowerDown_t . . . 817
pack_uim_SLQSUIMPowerUp_t . . . 818
pack_uim_SLQSUIMRefreshComplete_t . . . 818

pack_uim_SLQSUIMRefreshGetLastEvent_t . . . 819
pack_uim_SLQSUIMRefreshOK_t . . . 819
pack_uim_SLQSUIMRefreshRegister_t . . . 820
pack_uim_SLQSUIMSwitchSlot_t . . . 820
pack_uim_UnblockPin_t . . . 821
pack_uim_VerifyPin_t . . . 822
pack_voice_AnswerUSSD_t . . . 823
pack_voice_OriginateUSSD_t . . . 824
pack_voice_SLQSOriginateUSSD_t . . . 824
pack_voice_SLQSVoiceALSSelectLine_t . . . 825
pack_voice_SLQSVoiceALSSetLineSwitching_t . . . 825
pack_voice_SLQSVoiceAnswerCall_t . . . 826
pack_voice_SLQSVoiceBindSubscription_t . . . 826
pack_voice_SLQSVoiceBurstDTMF_t . . . 826
pack_voice_SLQSVoiceDialCall_t . . . 827
pack_voice_SLQSVoiceEndCall_t . . . 829
pack_voice_SLQSVoiceGetCallBarring_t . . . 829
pack_voice_SLQSVoiceGetCallForwardingStatus_t . . . 830
pack_voice_SLQSVoiceGetCallInfo_t . . . 831
pack_voice_SLQSVoiceGetCallWaiting_t . . . 831
pack_voice_SLQSVoiceGetConfig_t . . . 832
pack_voice_SLQSVoiceIndicationRegister_t . . . 834
pack_voice_SLQSVoiceManageCalls_t . . . 834
pack_voice_SLQSVoiceOrigUSSDNoWait_t . . . 835
pack_voice_SLQSVoiceSendFlash_t . . . 836
pack_voice_SLQSVoiceSetCallBarringPassword_t . . . 836
pack_voice_SLQSVoiceSetConfig_t . . . 837
pack_voice_SLQSVoiceSetPreferredPrivacy_t . . . 839
pack_voice_SLQSVoiceSetSUPSService_t . . . 839
pack_voice_SLQSVoiceStartContDTMF_t . . . 841
pack_voice_SLQSVoiceStopContDTMF_t . . . 842
pack_wds_DHCPv4ClientLeaseChange_t . . . 842
pack_wds_GetDefaultProfile_t . . . 843
pack_wds_GetDefaultProfileNum_t . . . 843
pack_wds_GetDormancyState_t . . . 844
pack_wds_GetLastMobileIPError_t . . . 844
pack_wds_GetMobileIP_t . . . 844
pack_wds_GetMobileIPProfile_t . . . 844
pack_wds_GetPacketStatistics_t . . . 845
pack_wds_GetPacketStatus_t . . . 845
pack_wds_GetSessionDuration_t . . . 846
pack_wds_RMSetTransferStatistics_t . . . 846
pack_wds_SetAutoconnect_t . . . 847
pack_wds_SetDefaultProfile_t . . . 847
pack_wds_SetDefaultProfileNum_t . . . 849
pack_wds_SetMobileIP_t . . . 850
pack_wds_SetMobileIPParameters_t . . . 850
pack_wds_SetMobileIPProfile_t . . . 851
pack_wds_SLQSCreateProfile_t . . . 853
pack_wds_SLQSDeleteProfile_t . . . 854
pack_wds_SLQSGetCurrDataSystemStat_t . . . 854
pack_wds_SLQSGetDataBearerTechnology_t . . . 855
pack_wds_SLQSGetDUNCallInfo_t . . . 855
pack_wds_SLQSGetProfileSettings_t . . . 856
pack_wds_SLQSGetRuntimeSettings_t . . . 857
pack_wds_SLQSModifyProfile_t . . . 858
pack_wds_SLQSSet3GPPConfigItem_t . . . 859
pack_wds_SLQSSetIPFamilyPreference_t . . . 861

pack_wds_SLQSSetWdsEventCallback_t . . . 861
pack_wds_SLQSSGetDHCPv4ClientConfig_t . . . 862
pack_wds_SLQSSSetDHCPv4ClientConfig_t . . . 862
pack_wds_SLQSSSetLoopback_t . . . 863
pack_wds_SLQSStartDataSession_t . . . 863
pack_wds_SLQSStopDataSession_t . . . 865
pack_wds_SLQSWdsSetEventReport_t . . . 865
pack_wds_SLQSWdsSwiPDPRuntimeSettings_t . . . 867
PackCreateProfileOut . . . 867
packgetDyingGaspCfg . . . 868
packgetDyingGaspStatistics . . . 868
PCMparams . . . 869
PCSCFFQDNAddress . . . 870
PCSCFFQDNAddressList . . . 870
PCSCFIPv4ServerAddressList . . . 871
PDSPositionData . . . 871
PDSPosMethodStateReq . . . 873
peerNumberInfo . . . 874
personalizationStatus . . . 876
PhyCaAggPcellInfo . . . 877
PhyCaAggScellArray . . . 877
PhyCaAggScellDlBw . . . 879
PhyCaAggScellIndex . . . 879
PhyCaAggScellIndType . . . 880
PhyCaAggScellInfo . . . 881
PilotSetData . . . 883
PilotSetParams . . . 884
pktErrRate . . . 884
PlmnID . . . 885
PLMNNetworkName . . . 885
PLMNNetworkNameData . . . 886
Port . . . 888
PowerSaveModeConfigReq . . . 888
PowerSaveModeConfigResp . . . 889
precisionDilution_s . . . 890
PrefImageList . . . 891
prefVoiceSO . . . 891
Profile3GPP . . . 893
Profile3GPP2 . . . 899
ProfileIdentifier . . . 904
protocolSubtypeElement . . . 905
PSDetachReq . . . 907
PSMActiveTimerTlv . . . 907
PSMDurationDueToOOSTlv . . . 908
PSMDurationThresholdTlv . . . 908
PSMEarlyWakeupTimeTlv . . . 909
PSMEnableStateTlv . . . 909
PSMPeriodicUpdateTimerTlv . . . 910
PSMRandomizationWindowTlv . . . 910
qaQmi3Gpp2TimeZone . . . 911
qaQmiInterfaceInfo . . . 911
qaQmiServingSystemParam . . . 912
QmiCbkCatEventStatusReportInd . . . 916
QmiCbkLocBestAvailPosInd . . . 916
QmiCbkLocCradleMountInd . . . 922
QmiCbkLocEngineStateInd . . . 922
QmiCbkLocEventNMEAInd . . . 923
QmiCbkLocEventTimeSyncInd . . . 923

QmiCbkLocGetOpModeInd . . . 924
QmiCbkLocGetServerInd . . . 925
QmiCbkLocInjectPositionInd . . . 927
QmiCbkLocInjectSensorDataInd . . . 927
QmiCbkLocInjectTimeInd . . . 929
QmiCbkLocInjectUTCTimeInd . . . 929
QmiCbkLocOpModeInd . . . 930
QmiCbkLocPositionReportInd . . . 931
QmiCbkLocSensorStreamingInd . . . 937
QmiCbkLocSetExtPowerConfigInd . . . 938
QmiCbkLocSetServerInd . . . 938
QmiCbkNasEdrxChangeInfo . . . 939
QmiCbkNasLTECphyCaInfo . . . 940
QmiCbkSwiOmaDmEventStatusReportInd . . . 941
QmiCbkSwiOmaDmEventStatusReportIndExt . . . 941
QmiCbkTmdMitiLvlRptInd . . . 941
QmiCbkWdsStatisticsIndState . . . 942
qmifwinfo_s . . . 943
QmiNas3GppNetworkInfo . . . 944
QmiNasGetRFBandInfoResp . . . 945
QmiNasPerformNetworkScanResp . . . 946
qmiSmsMessageList . . . 946
qmiWDSDataBearerTechnology . . . 947
QmiWdsIpAddressInfo . . . 947
qmiWdsRunTimeSettings . . . 948
qmTlvResult . . . 952
qos_BindDataPortMuxID_t . . . 952
qos_BindDataPortPeripheralEndPointID_t . . . 953
qos_BindDataPortSIODataPort_t . . . 953
QosClassID . . . 953
QosEventInfo . . . 954
QosFlowInfo . . . 956
QosFlowInfoState . . . 957
QosMap . . . 957
RankIndicatorInd . . . 958
RatDisabledMaskTlv . . . 958
readResult . . . 959
readTransparentInfo . . . 960
redirNumInfo . . . 960
registerRefresh . . . 962
remainingRetries . . . 963
remotePartyName . . . 963
remotePartyNum . . . 964
ReqFieldsList . . . 965
RespFieldsList . . . 966
RFBandInfoElements . . . 966
RfBandInfoExtFormat . . . 967
RfBandInfoExtFormatElements . . . 968
RfBandInfoList . . . 969
RfBandwidthInfo . . . 969
RfBandwidthInfoElements . . . 970
RfDedicatedBandInfo . . . 970
RfDedicatedBandInfoElements . . . 971
rmTrasnferStaticsReq . . . 972
roamIndList . . . 972
RoamingInfo . . . 973
roamTimer . . . 973
RSRPThresh . . . 974

rsrqInformation . . . 975
RSRQThresh . . . 975
RSSIThresh . . . 976
RXAGCList . . . 977
RXAVCList . . . 978
rxInfo . . . 978
RXPCMIIRFltr . . . 980
RxSigInfo . . . 981
rxSignalStrengthListElement . . . 982
sApnExtraParams . . . 983
satelliteInfo . . . 984
SccRxInfo . . . 987
sensorData . . . 987
sensorData_t . . . 989
sensorDataUsage_s . . . 991
serialNumbersInfo . . . 991
serviceProviderName . . . 993
ServingSystemInfo . . . 993
servSystem . . . 995
sessionInfo . . . 996
sessionInfoExt . . . 997
sessionInfoTlv . . . 997
sessionInfoTlvExt . . . 998
SetAudioPathConfigReq . . . 998
SetAudioProfileReq . . . 1000
SetAudioVolTLBConfigReq . . . 1001
SetAudioVolTLBConfigResp . . . 1002
setCustomSettingV2 . . . 1003
setDyingGaspCfg . . . 1003
SetIMSSMSConfigReq . . . 1004
SetIMSSMSConfigResp . . . 1004
SetIMSUserConfigReq . . . 1005
SetIMSUserConfigResp . . . 1005
SetIMSVoIPConfigReq . . . 1006
SetIMSVoIPConfigResp . . . 1008
setIntfaceCfgTlv . . . 1009
SetLocGetServerCallbackPara . . . 1010
SetLocSetServerCallbackParam . . . 1010
SetM2MAudioAVCFGReq . . . 1011
SetM2MAudioLPBKReq . . . 1011
SetM2MAudioProfileReq . . . 1012
SetM2MAudioVolumeReq . . . 1013
SetM2MAVMuteReq . . . 1014
SetM2MSpkrGainReq . . . 1014
setPINProtection . . . 1015
SetRegMgrConfigReq . . . 1016
SetRegMgrConfigResp . . . 1017
setSignalStrengthInfo . . . 1017
SetSIPConfigReq . . . 1022
SetSIPConfigResp . . . 1023
sGetDeviceSeriesResult . . . 1023
sidNid . . . 1024
sigInfo . . . 1024
signalInfo . . . 1026
SignalStrengthDataType . . . 1026
simBusyStatus . . . 1027
slot_t . . . 1027
slotInf . . . 1028

slotInfo . . . 1030
slots_t . . . 1031
slqsautoconnect . . . 1032
SLQSDeleteProfileParams . . . 1033
slqsfwinfo_s . . . 1033
slqsfwpartno_s . . . 1034
SlqsNas3GppNetworkInfo . . . 1035
SlqsNasPCICellInfo . . . 1036
SlqsNasPCIInfo . . . 1037
SlqsNasPcsDigit . . . 1038
slqssendasyncsmsparams_s . . . 1039
slqssendsmsparams_s . . . 1041
slqsSessionStateInfo . . . 1042
SLQSSetDHCPv4ClientLeaseStatusCallbackParam . . . 1043
slqsSignalStrengthInfo . . . 1044
SLQSSignalStrengthsIndReq . . . 1046
SLQSSignalStrengthsInformation . . . 1048
SLQSTmdMitigationLvlRptCallbackParam . . . 1049
slqsWdsEventInfo . . . 1049
sms_BroadcastConfig . . . 1051
sms_CDMABroadcastConfig . . . 1051
sms_DateTime . . . 1052
sms_getIndicationReg . . . 1052
sms_getMsgWaitingInfo . . . 1053
sms_getTransLayerInfo . . . 1054
sms_getTransNWRegInfo . . . 1054
sms_maxStorageSizeReq . . . 1055
sms_maxStorageSizeResp . . . 1055
sms_messageWaitingInfoContent . . . 1056
sms_msgProtocolResp . . . 1057
sms_qaQmi3GPP2BroadcastCfgInfo . . . 1057
sms_qaQmi3GPPBroadcastCfgInfo . . . 1058
sms_routeEntry . . . 1059
sms_sendAsyncsmsParams . . . 1060
sms_setIndicationReg . . . 1062
sms_setRoutesReq . . . 1063
sms_timestemp . . . 1063
sms_transLayerInfo . . . 1064
SMSAsyncRawSend_s . . . 1064
SMSCAddress . . . 1066
sMSCAddressInfo . . . 1067
sMSCAddressTlv . . . 1067
SMSEtwsMessage . . . 1068
sMSEtwsMessageInfo . . . 1068
sMSEtwsMessageTlv . . . 1069
SMSEtwsPlmn . . . 1069
sMSEtwsPlmnInfo . . . 1070
SMSEventInfo_s . . . 1070
smsMaxStorageSizeReq . . . 1072
smsMaxStorageSizeResp . . . 1072
SMSMemoryInfo . . . 1073
SMSMessageMode . . . 1073
sMSMessageModeInfo . . . 1074
smsMsgprotocolResp . . . 1074
SMSMTMessage . . . 1075
sMSMTMessageInfo . . . 1075
SMSOnIMS . . . 1076
sMSOnIMSInfo . . . 1076

sMSOnIMSTlv . . . 1077
smsRouteEntry . . . 1077
smsSetRoutesReq . . . 1078
SMSTransferRouteMTMessage . . . 1079
sMSTransferRouteMTMessageInfo . . . 1080
sQosFlowStat . . . 1081
sQosStat . . . 1082
SrvStatusInfo . . . 1083
ssdatasession_params . . . 1084
supportedIntBitmaskTlv . . . 1086
SupportedMsgList . . . 1087
SUPSInfo . . . 1087
SV . . . 1088
SVInfo . . . 1089
svUsedforFix_s . . . 1090
SWI_STRUCT_CarrierImage . . . 1090
swi_uint256_t . . . 1091
swidms_ehrpdMTUSizeTlv . . . 1092
swidms_hrpdMTUSizeTlv . . . 1092
swidms_intfaceCfgTlv . . . 1093
swidms_mtuSize3gppTlv . . . 1094
swidms_supportedIntBitmaskTlv . . . 1095
swidms_SwiDmsGetHWWatchdog . . . 1095
swidms_usbMTUSizeTlv . . . 1096
SwiDmsGetHWWatchdog . . . 1097
SwiDmsGetMTUResp . . . 1097
SwiDmsGetSecureInfoResp . . . 1098
SwiDmsGetUsbCompResp . . . 1099
SwiDmsSetHWWatchdog . . . 1099
SwiDmsSLQSGetUsbNetNum . . . 1100
SwiDmsUIMSelectReq . . . 1100
SwiLocGetAutoStartResp . . . 1101
SwiLocSetAutoStartReq . . . 1102
swiModemStatusResp . . . 1104
SwiOTAMsg_s . . . 1104
swiPDPRuntimeSettingsReq . . . 1105
swiPDPRuntimeSettingsResp . . . 1106
swiQosFilter . . . 1108
swiQosFlow . . . 1111
swiQosGranted . . . 1114
swiQosIds . . . 1114
swiQosModifyReq . . . 1115
swiQosReq . . . 1115
swiRMTrasnferStaticsReq . . . 1116
sysInfoCommon . . . 1117
sysSelectPrefParamsExt . . . 1119
t_gpsTime . . . 1123
t_sensor . . . 1123
t_Sv . . . 1124
TDSCDMAECIOThresh . . . 1124
TDSCDMARSCPThresh . . . 1125
TDSCDMARSSIThresh . . . 1125
tdscdmaSigInfoExt . . . 1126
TDSCDMASigInfoExt . . . 1126
TDSCDMASINRCONFThresh . . . 1127
TDSCDMASINRThresh . . . 1128
tempData_t . . . 1128
tempratureData . . . 1129

TFTIDParams . . . 1130
timeInfo . . . 1132
TmdDeRegNotMitigationLvlReq . . . 1134
TmdGetMitigationDevListResp . . . 1134
TmdGetMitigationLvlReq . . . 1135
TmdGetMitigationLvlResp . . . 1136
TmdMitigationLvlIndReq . . . 1136
TmdRegNotMitigationLvlReq . . . 1137
tokenBucket . . . 1137
Tos . . . 1138
transferRouteMessageTlv . . . 1138
TransferStatInd . . . 1139
TransferStatsDataType . . . 1139
TrStatInd . . . 1140
trueIMSI . . . 1140
TXAGCList . . . 1141
txInfo . . . 1142
TXPCMIIRFltr . . . 1143
uim_appStatus . . . 1144
uim_authenticateResult . . . 1147
uim_authenticationData . . . 1148
uim_cardResult . . . 1149
uim_cardStatus . . . 1150
uim_changeUIMPIN . . . 1151
uim_depersonalizationInformation . . . 1152
uim_encryptedPIN1 . . . 1153
uim_fileAttributes . . . 1154
uim_fileInfo . . . 1157
uim_hotSwapStatus . . . 1158
uim_personalizationStatus . . . 1158
uim_readResult . . . 1159
uim_readTransparentInfo . . . 1160
uim_refreshevent . . . 1160
uim_registerRefresh . . . 1162
uim_remainingRetries . . . 1163
uim_sessionInformation . . . 1164
uim_setPINProtection . . . 1164
uim_simBusyStatus . . . 1165
uim_slotInfo . . . 1166
uim_UIMSessionInformation . . . 1167
uim_unblockUIMPIN . . . 1168
uim_validCardStatus . . . 1169
uim_verifyUIMPIN . . . 1170
UIMAuthenticateReq . . . 1171
UIMAuthenticateResp . . . 1171
UimAutoSwitchActSlotTlv . . . 1172
UIMChangePinReq . . . 1173
UIMDepersonalizationReq . . . 1173
UIMDepersonalizationResp . . . 1174
UIMEventRegisterReqResp . . . 1174
UIMGetCardStatusResp . . . 1175
UIMGetCardStatusRespV2 . . . 1175
UIMGetConfigurationReq . . . 1176
UIMGetConfigurationResp . . . 1177
UIMGetFileAttributesReq . . . 1177
UIMGetFileAttributesResp . . . 1178
UIMGetSlotsStatusResp . . . 1179
UIMPinResp . . . 1179

UIMPinRespV2 . . . 1180
UIMPowerDownReq . . . 1181
UIMPowerUpReq . . . 1181
UIMReadTransparentReq . . . 1182
UIMReadTransparentResp . . . 1183
UIMRefreshCompleteReq . . . 1184
UIMRefreshEvent . . . 1184
UIMRefreshGetLastEventReq . . . 1186
UIMRefreshGetLastEventResp . . . 1186
UIMRefreshOKReq . . . 1186
UIMRefreshRegisterReq . . . 1187
UIMSessionInformation . . . 1188
UIMSetPinProtectionReq . . . 1188
UIMSlotsStatus . . . 1189
UIMSlotStatus . . . 1190
UIMSlotStatusChangeInfo . . . 1191
UIMStatusChangeInfo . . . 1191
UIMSwitchSlotReq . . . 1192
UIMUnblockPinReq . . . 1192
UIMVerifyPinReq . . . 1193
UMTSInfo . . . 1194
UMTSinstInfo . . . 1196
umtsLTENbrCell . . . 1197
UMTSMinQoS . . . 1198
UMTSQoS . . . 1200
UMTSReqQoSSigInd . . . 1202
unblockUIMPIN . . . 1203
UniversalTime . . . 1204
unpack_dms_GetActivationState_t . . . 1205
unpack_dms_GetBandCapability_t . . . 1206
unpack_dms_GetCrashAction_t . . . 1208
unpack_dms_GetCustFeature_t . . . 1209
unpack_dms_GetCustFeaturesV2_t . . . 1211
unpack_dms_GetDeviceCap_t . . . 1212
unpack_dms_GetDeviceCapabilities_t . . . 1213
unpack_dms_GetDeviceHardwareRev_t . . . 1215
unpack_dms_GetDeviceMfr_t . . . 1216
unpack_dms_GetDeviceSerialNumbers_t . . . 1216
unpack_dms_GetFirmwareInfo_t . . . 1218
unpack_dms_GetFirmwareRevision_t . . . 1220
unpack_dms_GetFirmwareRevisions_t . . . 1221
unpack_dms_GetFSN_t . . . 1222
unpack_dms_GetHardwareRevision_t . . . 1223
unpack_dms_GetIMSI_t . . . 1223
unpack_dms_GetManufacturer_t . . . 1224
unpack_dms_GetModelID_t . . . 1225
unpack_dms_GetNetworkTime_t . . . 1225
unpack_dms_GetOfflineReason_t . . . 1226
unpack_dms_GetPower_t . . . 1227
unpack_dms_GetPRLVersion_t . . . 1228
unpack_dms_GetSerialNumbers_t . . . 1229
unpack_dms_GetUSBComp_t . . . 1230
unpack_dms_GetVoiceNumber_t . . . 1232
unpack_dms_PSMCfgChange_ind_t . . . 1234
unpack_dms_ResetToFactoryDefaults_t . . . 1234
unpack_dms_SetActivationStatusCallback_t . . . 1235
unpack_dms_SetCrashAction_t . . . 1235
unpack_dms_SetCustFeature_t . . . 1236

unpack_dms_SetCustFeaturesV2_t . . . 1236
unpack_dms_SetEventReport_ind_t . . . 1237
unpack_dms_SetEventReport_t . . . 1238
unpack_dms_SetFirmwarePreference_t . . . 1238
unpack_dms_SetIndicationRegister_t . . . 1239
unpack_dms_SetPower_t . . . 1239
unpack_dms_SetUSBComp_t . . . 1240
unpack_dms_SLQSDmsSwiGetPCInfo_t . . . 1240
unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t . . . 1243
unpack_dms_SLQSDmsSwiGetResetInfo_t . . . 1244
unpack_dms_SLQSDmsSwiGetUimSelection_t . . . 1245
unpack_dms_SLQSDmsSwiIndicationRegister_t . . . 1246
unpack_dms_SLQSGetBandCapability_t . . . 1247
unpack_dms_SLQSGetERIFile_t . . . 1251
unpack_dms_SLQSGetPowerSaveModeConfig_t . . . 1252
unpack_dms_SLQSSetPowerSaveModeConfig_t . . . 1253
unpack_dms_SLQSSwiClearDyingGaspStatistics_t . . . 1254
unpack_dms_SLQSSwiGetCrashInfo_t . . . 1254
unpack_dms_SLQSSwiGetDyingGaspCfg_t . . . 1255
unpack_dms_SLQSSwiGetDyingGaspStatistics_t . . . 1256
unpack_dms_SLQSSwiGetFirmwareCurr_t . . . 1256
unpack_dms_SLQSSwiGetFwUpdateStatus_t . . . 1257
unpack_dms_SLQSSwiGetHostDevInfo_t . . . 1259
unpack_dms_SLQSSwiGetOSInfo_t . . . 1260
unpack_dms_SLQSSwiGetSerialNoExt_t . . . 1261
unpack_dms_SLQSSwiSetDyingGaspCfg_t . . . 1262
unpack_dms_SLQSSwiSetHostDevInfo_t . . . 1262
unpack_dms_SLQSSwiSetOSInfo_t . . . 1263
unpack_dms_SLQSUIMGetState_t . . . 1263
unpack_dms_SwiEventReportCallBack_ind_t . . . 1264
unpack_dms_SwiSetEventReport_t . . . 1265
unpack_dms_SwiUimSelect_t . . . 1265
unpack_dms_UIMGetControlKeyStatus_t . . . 1266
unpack_dms_UIMGetICCID_t . . . 1267
unpack_dms_UIMGetPINStatus_t . . . 1268
unpack_dms_UIMSetControlKeyProtection_t . . . 1269
unpack_dms_UIMSetPINProtection_t . . . 1270
unpack_dms_UIMUnblockControlKey_t . . . 1271
unpack_fms_GetImagesPreference_t . . . 1271
unpack_fms_GetStoredImages_t . . . 1272
unpack_fms_SetImagesPreference_t . . . 1273
unpack_loc_BestAvailPos_Ind_t . . . 1273
unpack_loc_CradleMountCallback_Ind_t . . . 1280
unpack_loc_Delete_Assist_Data_t . . . 1281
unpack_loc_DeleteAssistData_Ind_t . . . 1282
unpack_loc_EngineState_Ind_t . . . 1282
unpack_loc_EventNMEA_Ind_t . . . 1283
unpack_loc_EventRegister_t . . . 1284
unpack_loc_EventTimeSyncCallback_Ind_t . . . 1284
unpack_loc_GetOpMode_Ind_t . . . 1285
unpack_loc_GetServer_Ind_t . . . 1286
unpack_loc_GnssSvInfo_Ind_t . . . 1288
unpack_loc_InjectPositionCallback_Ind_t . . . 1288
unpack_loc_InjectSensorDataCallback_Ind_t . . . 1289
unpack_loc_InjectTimeSyncDataCallback_Ind_t . . . 1291
unpack_loc_InjectUTCTimeCallback_Ind_t . . . 1291
unpack_loc_PositionRpt_Ind_t . . . 1292
unpack_loc_SensorStreamingCallback_Ind_t . . . 1299

unpack_loc_SetExtPowerConfig_Ind_t . . . 1300
unpack_loc_SetExtPowerState_t . . . 1300
unpack_loc_SetOperationMode_Ind_t . . . 1301
unpack_loc_SetOperationMode_t . . . 1302
unpack_loc_SetServer_Ind_t . . . 1302
unpack_loc_SLQSLOCGetBestAvailPos_t . . . 1303
unpack_loc_SLQSLOCGetOpMode_t . . . 1304
unpack_loc_Start_t . . . 1304
unpack_loc_Stop_t . . . 1305
unpack_nas_GetACCOLC_t . . . 1305
unpack_nas_GetANAAAAuthenticationStatus_t . . . 1306
unpack_nas_GetCDMANetworkParameters_t . . . 1306
unpack_nas_GetHomeNetwork3GPP2_t . . . 1309
unpack_nas_GetHomeNetwork_t . . . 1311
unpack_nas_GetNetworkPreference_t . . . 1312
unpack_nas_GetRFInfo_t . . . 1313
unpack_nas_GetServingNetwork_t . . . 1314
unpack_nas_GetServingNetworkCapabilities_t . . . 1317
unpack_nas_GetSignalStrengths_t . . . 1318
unpack_nas_PerformNetworkScan_t . . . 1319
unpack_nas_SetDataCapabilitiesCallback_ind_t . . . 1320
unpack_nas_SetEventReportInd_t . . . 1321
unpack_nas_SetNasLTECphyCaIndCallback_ind_t . . . 1322
unpack_nas_SetNetworkPreference_t . . . 1323
unpack_nas_SetRoamingIndicatorCallback_ind_t . . . 1324
unpack_nas_SetServingSystemCallback_ind_t . . . 1324
unpack_nas_SLQSGetErrorRate_t . . . 1325
unpack_nas_SlqsGetLTECphyCAInfo_t . . . 1326
unpack_nas_SLQSGetNetworkTime_t . . . 1327
unpack_nas_SLQSGetOperatorNameData_t . . . 1327
unpack_nas_SLQSGetPLMNName_t . . . 1329
unpack_nas_SLQSGetServingSystem_t . . . 1332
unpack_nas_SLQSGetSignalStrength_t . . . 1336
unpack_nas_SLQSGetSysInfo_t . . . 1339
unpack_nas_SLQSGetSysSelectionPref_t . . . 1343
unpack_nas_SLQSGetSysSelectionPrefExt_t . . . 1347
unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t . . . 1350
unpack_nas_SLQSNasGet3GPP2Subscription_t . . . 1351
unpack_nas_SLQSNasGetCellLocationInfo_t . . . 1352
unpack_nas_SLQSNASGeteDRXParams_t . . . 1354
unpack_nas_SLQSNASGeteDRXParamsExt_t . . . 1355
unpack_nas_SLQSNASGetForbiddenNetworks_t . . . 1356
unpack_nas_SLQSNasGetHDRColorCode_t . . . 1357
unpack_nas_SLQSNasGetRFInfo_t . . . 1357
unpack_nas_SLQSNasGetSigInfo_t . . . 1358
unpack_nas_SLQSNasGetTxRxInfo_t . . . 1359
unpack_nas_SLQSNasNetworkRejectCallback_Ind_t . . . 1360
unpack_nas_SLQSNasNetworkTimeCallBack_ind_t . . . 1363
unpack_nas_SLQSNasSigInfoCallback_ind_t . . . 1364
unpack_nas_SLQSNASSwiGetChannelLock_t . . . 1366
unpack_nas_SLQSNasSwiModemStatus_t . . . 1366
unpack_nas_SLQSNasSwiOTAMessageCallback_ind_t . . . 1367
unpack_nas_SLQSNasTimerCallback_ind_t . . . 1368
unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t . . . 1368
unpack_nas_SLQSSwiGetHDRPersonality_t . . . 1369
unpack_nas_SLQSSwiGetHDRProtSubtype_t . . . 1370
unpack_nas_SLQSSwiGetHRPDStats_t . . . 1371
unpack_nas_SLQSSwiGetLteCQI_t . . . 1372

unpack_nas_SLQSSwiGetLteSccRxInfo_t . . . 1373
unpack_nas_SLQSSwiHDRPersonalityCallback_Ind_t . . . 1373
unpack_nas_SLQSSwiNetworkDebug_t . . . 1374
unpack_nas_SLQSSwiRandIndicatorCallback_Ind_t . . . 1375
unpack_nas_SLQSSysInfoCallback_ind_t . . . 1375
unpack_omaDmConfigTlv_t . . . 1379
unpack_omaDmFotaTlv_t . . . 1380
unpack_omaDmNotificationsTlv_t . . . 1382
unpack_pds_GetPDSDefaults_t . . . 1383
unpack_pds_GetPDSState_t . . . 1384
unpack_pds_GetPortAutomaticTracking_t . . . 1385
unpack_pds_GetServiceAutomaticTracking_t . . . 1386
unpack_pds_GetXTRAAutomaticDownload_t . . . 1386
unpack_pds_GetXTRANetwork_t . . . 1387
unpack_pds_GetXTRAValidity_t . . . 1387
unpack_pds_SetEventReport_Ind_t . . . 1388
unpack_pds_SetPdsState_Ind_t . . . 1390
unpack_pds_SLQSGetAGPSConfig_t . . . 1391
unpack_pds_SLQSGetGPSStateInfo_t . . . 1392
unpack_qmi_t . . . 1397
unpack_qos_BindDataPort_t . . . 1397
unpack_qos_dataRate_t . . . 1398
unpack_qos_IPv4Addr_t . . . 1398
unpack_qos_IPv6Addr_t . . . 1398
unpack_qos_IPv6TrafCls_t . . . 1399
unpack_qos_pktErrRate_t . . . 1399
unpack_qos_Port_t . . . 1400
unpack_qos_QosFlowInfo_t . . . 1400
unpack_qos_QosFlowInfoState_t . . . 1402
unpack_qos_SLQSQosGetNetworkStatus_t . . . 1402
unpack_qos_SLQSQosSwiReadApnExtraParams_t . . . 1403
unpack_qos_SLQSQosSwiReadDataStats_t . . . 1405
unpack_qos_SLQSSetQosEventCallback_ind_t . . . 1406
unpack_qos_SLQSSetQosEventCallback_t . . . 1407
unpack_qos_SLQSSetQosNWStatusCallback_ind_t . . . 1407
unpack_qos_SLQSSetQosPriEventCallback_ind_t . . . 1408
unpack_qos_SLQSSetQosStatusCallback_ind_t . . . 1408
unpack_qos_swiQosFilter_t . . . 1410
unpack_qos_swiQosFlow_t . . . 1413
unpack_qos_tokenBucket_t . . . 1417
unpack_qos_Tos_t . . . 1418
unpack_QosFlowStat_t . . . 1418
unpack_result_t . . . 1419
unpack_rms_GetSMSWake_t . . . 1420
unpack_rms_SetSMSWake_t . . . 1420
unpack_RMTransferStatistics_ind_t . . . 1421
unpack_sar_SLQSGetRfSarState_t . . . 1422
unpack_sms_GetSMSCAddress_t . . . 1422
unpack_sms_SaveSMS_t . . . 1423
unpack_sms_SendSMS_t . . . 1424
unpack_sms_SetNewSMSCallback_ind_t . . . 1425
unpack_sms_SetNewSMSCallback_t . . . 1426
unpack_sms_SetSMSCAddress_t . . . 1426
unpack_sms_SLQSDeleteSMS_t . . . 1427
unpack_sms_SLQSGetIndicationRegister_t . . . 1427
unpack_sms_SLQSGetMessageWaiting_t . . . 1428
unpack_sms_SLQSGetSMS_t . . . 1428
unpack_sms_SLQSGetSmsBroadcastConfig_t . . . 1429

unpack_sms_SLQSGetSMSList_t . . . 1430
unpack_sms_SLQSGetTransLayerInfo_t . . . 1431
unpack_sms_SLQSGetTransNWRegInfo_t . . . 1431
unpack_sms_SLQSModifySMSStatus_t . . . 1432
unpack_sms_SLQSNWRegInfoCallback_ind_t . . . 1432
unpack_sms_SLQSSendAsyncSMS_t . . . 1433
unpack_sms_SLQSSetIndicationRegister_t . . . 1433
unpack_sms_SLQSSetSmsBroadcastActivation_t . . . 1434
unpack_sms_SLQSSetSmsBroadcastConfig_t . . . 1434
unpack_sms_SLQSSetSmsStorage_t . . . 1435
unpack_sms_SLQSSmsGetMaxStorageSize_t . . . 1435
unpack_sms_SLQSSmsGetMessageProtocol_t . . . 1436
unpack_sms_SLQSSmsSetRoutes_t . . . 1436
unpack_sms_SLQSSwiGetSMSStorage_t . . . 1437
unpack_sms_SLQSTransLayerInfoCallback_ind_t . . . 1437
unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t . . . 1438
unpack_sms_SLQSWmsMemoryFullCallBack_ind_t . . . 1440
unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t . . . 1441
unpack_swidms_SLQSSwiDmsGetHWWatchdog_t . . . 1441
unpack_swidms_SLQSSwiDmsGetMTU_t . . . 1442
unpack_swidms_SLQSSwiDmsGetSecureInfo_t . . . 1443
unpack_swidms_SLQSSwiDmsGetUsbComp_t . . . 1444
unpack_swidms_SLQSSwiDmsGetUsbNetNum_t . . . 1444
unpack_swidms_SLQSSwiDmsSetHWWatchdog_t . . . 1445
unpack_swidms_SLQSSwiDmsSetMTU_t . . . 1445
unpack_swidms_SLQSSwiDmsSetUsbComp_t . . . 1446
unpack_swiloc_SwiLocGetAutoStart_t . . . 1446
unpack_swioma_SLQSOMADMAlertCallback_ind_t . . . 1448
unpack_swioma_SLQSOMADMGetSessionInfo_t . . . 1449
unpack_swioma_SLQSOMADMGetSettings_t . . . 1452
unpack_swioma_SLQSOMADMStartSession_t . . . 1454
unpack_uim_ChangePin_t . . . 1454
unpack_uim_GetCardStatus_t . . . 1455
unpack_uim_GetCardStatusV2_t . . . 1456
unpack_uim_ReadTransparent_t . . . 1457
unpack_uim_SetPinProtection_t . . . 1458
unpack_uim_SetUimSlotStatusChangeCallback_ind_t . . . 1459
unpack_uim_SLQSUIMAuthenticate_t . . . 1459
unpack_uim_SLQSUIMDepersonalization_t . . . 1460
unpack_uim_SLQSUIMEventRegister_t . . . 1461
unpack_uim_SLQSUIMGetConfiguration_t . . . 1461
unpack_uim_SLQSUIMGetFileAttributes_t . . . 1462
unpack_uim_SLQSUIMGetSlotsStatus_t . . . 1463
unpack_uim_SLQSUIMRefreshCallback_Ind_t . . . 1464
unpack_uim_SLQSUIMRefreshGetLastEvent_t . . . 1464
unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t . . . 1465
unpack_uim_UnblockPin_t . . . 1465
unpack_uim_UnblockPinV2_t . . . 1466
unpack_uim_VerifyPin_t . . . 1467
unpack_voice_allCallStatusCallback_ind_t . . . 1468
unpack_voice_DTMFEventCallback_ind_t . . . 1470
unpack_voice_OTASPStatusCallback_ind_t . . . 1471
unpack_voice_SLQSOriginateUSSD_t . . . 1472
unpack_voice_SLQSVoiceAnswerCall_t . . . 1475
unpack_voice_SLQSVoiceBurstDTMF_t . . . 1476
unpack_voice_SLQSVoiceDialCall_t . . . 1476
unpack_voice_SLQSVoiceEndCall_t . . . 1477
unpack_voice_SLQSVoiceGetAllCallInfo_t . . . 1478

unpack_voice_SLQSVoiceGetCallBarring_t . . . 1482
unpack_voice_SLQSVoiceGetCallForwardingStatus_t . . . 1483
unpack_voice_SLQSVoiceGetCallInfo_t . . . 1485
unpack_voice_SLQSVoiceGetCallWaiting_t . . . 1488
unpack_voice_SLQSVoiceGetCLIP_t . . . 1489
unpack_voice_SLQSVoiceGetCLIR_t . . . 1491
unpack_voice_SLQSVoiceGetCNAP_t . . . 1492
unpack_voice_SLQSVoiceGetCOLP_t . . . 1494
unpack_voice_SLQSVoiceGetCOLR_t . . . 1495
unpack_voice_SLQSVoiceGetConfig_t . . . 1496
unpack_voice_SLQSVoiceManageCalls_t . . . 1498
unpack_voice_SLQSVoiceSendFlash_t . . . 1499
unpack_voice_SLQSVoiceSetCallBarringPassword_t . . . 1500
unpack_voice_SLQSVoiceSetConfig_t . . . 1501
unpack_voice_SLQSVoiceSetSUPSService_t . . . 1503
unpack_voice_SLQSVoiceStartContDTMF_t . . . 1504
unpack_voice_SLQSVoiceStopContDTMF_t . . . 1504
unpack_voice_SLQSVoiceSUPSCallback_ind_t . . . 1505
unpack_voice_SUPSNotificationCallback_ind_t . . . 1508
unpack_voice_USSDNotificationCallback_ind_t . . . 1510
unpack_voice_VoiceInfoRecCallback_ind_t . . . 1510
unpack_voice_voicePrivacyChangeCallback_ind_t . . . 1513
unpack_wds_DHCPv4ClientLease_ind_t . . . 1514
unpack_wds_GetAutoconnect_t . . . 1515
unpack_wds_GetByteTotals_t . . . 1515
unpack_wds_GetConnectionRate_t . . . 1516
unpack_wds_GetDataBearerTechnology_t . . . 1517
unpack_wds_GetDefaultProfile_t . . . 1518
unpack_wds_GetDefaultProfileNum_t . . . 1521
unpack_wds_GetDormancyState_t . . . 1521
unpack_wds_GetLastMobileIPError_t . . . 1522
unpack_wds_GetMobileIP_t . . . 1523
unpack_wds_GetMobileIPProfile_t . . . 1523
unpack_wds_GetPacketStatistics_t . . . 1525
unpack_wds_GetPacketStatus_t . . . 1527
unpack_wds_GetSessionDuration_t . . . 1529
unpack_wds_GetSessionState_t . . . 1530
unpack_wds_RMSetTransferStatistics_t . . . 1530
unpack_wds_SetMobileIPProfile_t . . . 1531
unpack_wds_SLQSCreateProfile_t . . . 1531
unpack_wds_SLQSDeleteProfile_t . . . 1532
unpack_wds_SLQSDUNCallInfoCallBack_ind_t . . . 1533
unpack_wds_SLQSGet3GPPConfigItem_t . . . 1534
unpack_wds_SLQSGetCurrDataSystemStat_t . . . 1536
unpack_wds_SLQSGetCurrentChannelRate_t . . . 1537
unpack_wds_SLQSGetDataBearerTechnology_t . . . 1538
unpack_wds_SLQSGetDUNCallInfo_t . . . 1539
unpack_wds_SLQSGetProfileSettings_t . . . 1542
unpack_wds_SLQSGetRuntimeSettings_t . . . 1542
unpack_wds_SLQSModifyProfile_t . . . 1546
unpack_wds_SLQSSetIPFamilyPreference_t . . . 1546
unpack_wds_SLQSSetPacketSrvStatusCallback_t . . . 1547
unpack_wds_SLQSSetWdsEventCallback_ind_t . . . 1549
unpack_wds_SLQSSGetDHCPv4ClientConfig_t . . . 1554
unpack_wds_SLQSSGetLoopback_t . . . 1555
unpack_wds_SLQSStartDataSession_t . . . 1556
unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t . . . 1557
UnPackGetProfileSettingOut . . . 1559

unpackWdsProfileParam . . . 1560
urlAddr . . . 1560
URLAddrInfo . . . 1561
USBCompConfig . . . 1561
USBCompParams . . . 1562
usbMTUSizeTlv . . . 1564
USSDNoWaitIndicationInfo . . . 1565
USSDRespFNetwork . . . 1565
USSInfo . . . 1566
USSResp . . . 1567
UUSInfo . . . 1567
validCardStatus . . . 1568
verifyUIMPIN . . . 1569
voice_airTimer . . . 1569
voice_allCallsAlphaIDInfo . . . 1570
voice_allCallsDiagInfo . . . 1570
voice_allCallsUUSInfo . . . 1571
voice_alphaIDInfo . . . 1571
voice_arrAlertingPattern . . . 1572
voice_arrAlertingType . . . 1573
voice_arrAlphaID . . . 1574
voice_arrCalledPartyNum . . . 1574
voice_arrCallEndReason . . . 1575
voice_arrCallInfo . . . 1575
voice_arrConnectPartyNum . . . 1576
voice_arrDiagInfo . . . 1577
voice_arrRedirPartyNum . . . 1577
voice_arrRemotePartyName . . . 1578
voice_arrRemotePartyNum . . . 1578
voice_arrSvcOption . . . 1579
voice_arrUUSInfo . . . 1579
voice_burstDTMFInfo . . . 1580
voice_calledPartyInfo . . . 1581
voice_calledPartySubAdd . . . 1582
voice_callerIDInfo . . . 1583
voice_callFwdTypeAndPlan . . . 1584
voice_callFWExtInfo . . . 1585
voice_callFWInfo . . . 1587
voice_callInfo . . . 1587
voice_callingPartyInfo . . . 1589
voice_ccSUPSType . . . 1591
voice_CLIPResp . . . 1591
voice_CLIRResp . . . 1592
voice_CNAPResp . . . 1593
voice_COLPResp . . . 1594
voice_COLRResp . . . 1594
voice_connectNumInfo . . . 1595
voice_CUGInfo . . . 1597
voice_curAMRConfig . . . 1597
voice_diagInfo . . . 1598
voice_DTMFInfo . . . 1599
voice_DTMFLengths . . . 1599
voice_ECTNum . . . 1600
voice_extDispRecInfo . . . 1601
voice_getAllCallInformation . . . 1602
voice_getAllCallRmtPtyName . . . 1602
voice_getAllCallRmtPtyNum . . . 1603
voice_getCallFWExtInfo . . . 1603

voice_getCallFWInfo . . . 1604
voice_lineCtrlInfo . . . 1604
voice_newPwdData . . . 1605
voice_NSSAudioCtrl . . . 1606
voice_peerNumberInfo . . . 1606
voice_prefVoiceSO . . . 1608
voice_redirNumInfo . . . 1610
voice_remotePartyName . . . 1612
voice_remotePartyNum . . . 1612
voice_roamTimer . . . 1613
voice_signalInfo . . . 1614
voice_SUPSInfo . . . 1615
voice_USSDNotificationNetworkInfo . . . 1615
voice_USSInfo . . . 1616
voice_UUSInfo . . . 1616
voiceALSSelectLineInfo . . . 1618
voiceALSSetLineSwitchInfo . . . 1618
voiceAnswerCall . . . 1618
voiceBindSubscriptionInfo . . . 1619
voiceBurstDTMFInfo . . . 1619
voiceCallInfoReq . . . 1620
voiceCallInfoResp . . . 1620
voiceCallRequestParams . . . 1623
voiceCallResponseParams . . . 1624
voiceContDTMFinfo . . . 1625
voiceDTMFEventInfo . . . 1626
voiceFlashInfo . . . 1627
voiceGetAllCallInfo . . . 1628
voiceGetCallBarringReq . . . 1630
voiceGetCallBarringResp . . . 1631
voiceGetCallFWReq . . . 1632
voiceGetCallFWResp . . . 1633
voiceGetCallWaitInfo . . . 1634
voiceGetCLIPResp . . . 1636
voiceGetCLIRResp . . . 1637
voiceGetCNAPResp . . . 1638
voiceGetCOLPResp . . . 1639
voiceGetCOLRResp . . . 1641
voiceGetConfigReq . . . 1642
voiceGetConfigResp . . . 1644
voiceIndicationRegisterInfo . . . 1645
voiceInfoRec . . . 1646
voiceManageCallsReq . . . 1649
voiceManageCallsResp . . . 1650
voiceOrigUSSDNoWaitInfo . . . 1650
voiceOTASPStatusInfo . . . 1650
voicePrivacyInfo . . . 1651
voiceSetAllCallStatusCbkInfo . . . 1652
voiceSetCallBarringPwdInfo . . . 1654
voiceSetCallBarringPwdResp . . . 1655
voiceSetConfigReq . . . 1657
voiceSetConfigResp . . . 1658
voiceSetPrefPrivacy . . . 1659
voiceSetSUPSServiceReq . . . 1660
voiceSetSUPSServiceResp . . . 1662
voiceStopContDTMFinfo . . . 1663
voiceSUPSInfo . . . 1664
voiceSUPSNotification . . . 1666

wcdmaCellInfo . . . 1668
WCDMAECIOThresh . . . 1669
WCDMAInfoLTENeighborCell . . . 1669
wcdmaLongMsgDecodingParams . . . 1670
wcdmaMsgDecodingParams . . . 1672
wcdmaMsgEncodingParams . . . 1674
WCDMARSSIThresh . . . 1675
WCDMASysInfo . . . 1675
wcdmaUARFCN . . . 1679
wds_channelRate . . . 1679
wds_ChannelRateTlv . . . 1680
wds_ConnStatusTlv . . . 1680
wds_currNetworkInfo . . . 1681
wds_DataBearTechTlv . . . 1682
wds_DataULongLongTlv . . . 1683
wds_DataULongTlv . . . 1683
wds_DHCPLeaseOptTlv . . . 1683
wds_DHCPLeaseStateTlv . . . 1684
wds_DHCPOpt . . . 1685
wds_DHCPProfileIdTlv . . . 1685
wds_DHCPv4HWConfig . . . 1686
wds_DHCPv4Option . . . 1686
wds_DHCPv4OptionList . . . 1687
wds_DHCPv4ProfileId . . . 1688
wds_Domain . . . 1688
wds_DomainNameList . . . 1689
wds_DormStatTlv . . . 1689
wds_GPRSQoS . . . 1690
wds_IPv4AdTlv . . . 1690
wds_IPV6AddressInfo . . . 1691
wds_IPV6GWAddressInfo . . . 1691
wds_LastMdmCallEndRsnTlv . . . 1692
wds_PCSCFFQDNAddress . . . 1693
wds_PCSCFFQDNAddressList . . . 1693
wds_PCSCFIPv4ServerAddressList . . . 1694
wds_ProfileIdentifier . . . 1694
wds_profileInfo . . . 1695
wds_RXBytesOKTlv . . . 1695
wds_transferStatInd . . . 1696
wds_TrStatInd . . . 1696
wds_TXBytesOKTlv . . . 1697
wds_UMTSMinQoS . . . 1697
WdsByteTotals . . . 1700
WdsByteTotalsElmnts . . . 1701
WdsClientLeaseChange . . . 1701
WdsConnectionRate . . . 1702
WdsConnectionRateElmnts . . . 1703
WdsDHCPv4ClientLeaseInd . . . 1703
WdsDHCPv4Config . . . 1704
WdsDHCPv4HWConfig . . . 1705
wdsDhcpv4HwConfig . . . 1705
WdsDHCPv4Option . . . 1706
wdsDhcpv4Option . . . 1707
WdsDHCPv4OptionList . . . 1707
wdsDhcpv4OptionList . . . 1708
wdsDhcpv4ProfileId . . . 1708
WdsDHCPv4ProfileId . . . 1709
WDSGetLoopbackData . . . 1709

WdsIpAddressInfoReq 1710
WdsPktStatisticsElmnts 1711
WdsPktStatisticsReq 1712
WdsPktStatisticsResp 1713
WdsProfileParam 1714
WdsRunTimeSettings 1714
wdsSetEventReportReq 1715
WDSSetLoopbackData 1717
WDSSWICurrentChannelRates 1717

Chapter 5

File Index

5.1 File List

Here is a list of all files with brief descriptions:

apdoxypages.c
Contains the module declaration for the Doxygen output. Also contains the content of the main page and related pages . . . 1719
common.h . . . 1719
dms.h . . . 1725
fms.h . . . 1785
loc.h . . . 1788
nas.h . . . 1811
pds.h . . . 1873
qaCbkCatEventReportInd.h . . . 1895
qaCbkSwiOmaDmEventReportInd.h . . . 1897
qaGobiApiAudio.h
Audio Service API function prototypes . . . 1898
qaGobiApiCat.h
Card Application Toolkit API function headers . . . 1902
qaGobiApiCbk.h
Callback Service API function prototypes . . . 1903
qaGobiApiDcs.h
Device Connectivity Service API function prototypes . . . 1993
qaGobiApiDms.h
Device Management Service API function prototypes . . . 2002
qaGobiApiFms.h
Firmware Management Service API function prototypes . . . 2042
qaGobiApiIms.h
IMS Service API function prototypes . . . 2064
qaGobiApiImsa.h
IMSA Service API function prototypes . . . 2070
qaGobiApiLoc.h
Location API function prototypes . . . 2073
qaGobiApiNas.h
Network Access Service API function prototypes . . . 2081
qaGobiApiOmadm.h
Open Mobile Alliance Device Management Service API function prototypes . . . 2140
qaGobiApiPds.h
Position Determination Service API function prototypes . . . 2143
qaGobiApiQos.h
Quality of Service API function prototypes . . . 2158

qaGobiApiRms.h
Remote Management Service API function prototypes . . . 2165
qaGobiApiSar.h
Specific Absorption Rate API function prototypes . . . 2166
qaGobiApiSms.h
Short Message Service API function prototypes . . . 2169
qaGobiApiSwi.h
SWI API function prototypes . . . 2192
qaGobiApiSwiAudio.h
M2M Audio Service API function prototypes . . . 2194
qaGobiApiSwiAvms.h
SWI Open Mobile Alliance Device Management Service API function prototypes SWI AVMS QMI Service revision 1.14 . . . 2199
qaGobiApiSwiDms.h
SWI DMS API function prototypes . . . 2213
qaGobiApiSwiOmadms.h
SWI Open Mobile Alliance Device Management Service API function prototypes SWI OMA-DM QMI Service revision 1.6 . . . 2217
qaGobiApiTableBandClasses.h
Network Access Service API Band Classes table . . . 2228
qaGobiApiTableCallControlReturnReasons.h
Call Control Return Reasons table . . . 2231
qaGobiApiTableCallEndReasons.h
Wireless Data Service Call End Reasons . . . 2232
qaGobiApiTableCarrierCodes.h
Carrier Codes table . . . 2249
qaGobiApiTableCodingScheme.h
Data Coding Scheme . . . 2251
qaGobiApiTableGpsCapabilityCodes.h
Position Determination Service API GPS Capability Codes . . . 2253
qaGobiApiTablePowerModes.h
Device Management Service API Power Modes table . . . 2254
qaGobiApiTableRadioInterfaces.h
Network Access Service API Radio Interfaces table . . . 2255
qaGobiApiTableRegionCodes.h
Region Codes table . . . 2255
qaGobiApiTableServiceOptions.h
Voice Service Options . . . 2256
qaGobiApiTableSupServiceInfoClasses.h
Voice Supplementary Service Information Classes . . . 2258
qaGobiApiTableSwiAudio.h
Swi Audio related tables . . . 2258
qaGobiApiTableSwiOMADMSessionStatus.h
Session Status table . . . 2259
qaGobiApiTableSwiOMADMUpdateCompleteStatus.h
Update Complete Status table . . . 2260
qaGobiApiTableVoiceCallEndReasons.h
Voice Service Call and supplementary services end reasons . . . 2261
qaGobiApiTmd.h
Thermal Mitigation Device API function prototypes . . . 2268
qaGobiApiUim.h
Uim Service API function prototypes . . . 2270
qaGobiApiVoice.h
Voice Service API function prototypes . . . 2284
qaGobiApiWds.h
Wireless Data Service API function prototypes . . . 2304
qaNasGetRFBandInfo.h . . . 2349
qaNasPerformNetworkScan.h . . . 2350

qmerrno.h 2351
qos.h 2358
rms.h 2368
sar.h 2370
sms.h 2372
SwiDataTypes.h
SWI data types 2394
swidms.h 2396
swiloc.h 2404
swioma.h 2406
switype_256bit.h 2415
SWIWWANCMAPI.h 2416
uim.h 2417
voice.h 2437
wds.h 2469

Chapter 6

Module Documentation

6.1 Device Connectivity Service (DCS)

Files

- file qaGobiApiDcs.h

  Device Connectivity Service API function prototypes.

6.1.1 Detailed Description

6.2 Wireless Data Service (WDS)

Files

- file qaGobiApiTableCallEndReasons.h

  Wireless Data Service Call End Reasons.
- file qaGobiApiTableCarrierCodes.h

  Carrier Codes table.
- file qaGobiApiTableRegionCodes.h

  Region Codes table.
- file qaGobiApiWds.h

  Wireless Data Service API function prototypes.

6.2.1 Detailed Description

6.3 Device Management Service (DMS)

Files

- file qaGobiApiTablePowerModes.h

  Device Management Service API Power Modes table.
- file qaGobiApiDms.h

  Device Management Service API function prototypes.

6.3.1 Detailed Description

6.4 Network Access Service (NAS)

Files

- file qaGobiApiTableRadioInterfaces.h

  Network Access Service API Radio Interfaces table.
- file qaGobiApiTableBandClasses.h

  Network Access Service API Band Classes table.
- file qaGobiApiNas.h

  Network Access Service API function prototypes.

6.4.1 Detailed Description

6.5 CallBacK registration (CBK)

Files

- file qaGobiApiCbk.h

  Callback Service API function prototypes.

6.5.1 Detailed Description

6.6 Short Message Service (SMS)

Files

- file qaGobiApiSms.h

  Short Message Service API function prototypes.

6.6.1 Detailed Description

6.7 Position Determination Service (PDS)

Files

- file qaGobiApiTableGpsCapabilityCodes.h

  Position Determination Service API GPS Capability Codes.
- file qaGobiApiPds.h

  Position Determination Service API function prototypes.

6.7.1 Detailed Description

6.8 Card Application Toolkit (CAT)

Files

- file qaGobiApiCat.h

  Card Application Toolkit API function headers.

6.8.1 Detailed Description

6.9 Remote Management Service (RMS)

Files

- file qaGobiApiRms.h

  Remote Management Service API function prototypes.

6.9.1 Detailed Description

6.10 Firmware Management Service (FMS)

Files

- file qaGobiApiFms.h

  Firmware Management Service API function prototypes.

6.10.1 Detailed Description

6.11 Open Mobile Alliance Service (OMA)

Files

- file qaGobiApiOmadm.h

  Open Mobile Alliance Device Management Service API function prototypes.

6.11.1 Detailed Description

6.12 Specific Absorption Rate (SAR)

Files

- file qaGobiApiSar.h

  Specific Absorption Rate API function prototypes.

6.12.1 Detailed Description

6.13 SWI Open Mobile Alliance Service (SWIOMA)

Files

- file qaGobiApiTableSwiOMADMUpdateCompleteStatus.h

  Update Complete Status table.
- file qaGobiApiTableSwiOMADMSessionStatus.h

  Session Status table.
- file qaGobiApiSwiOmadms.h

  SWI Open Mobile Alliance Device Management Service API function prototypes SWI OMA-DM QMI Service revision 1.6.

6.13.1 Detailed Description

6.14 Voice Service (VOICE)

Files

- file qaGobiApiTableServiceOptions.h

  Voice Service Options.
- file qaGobiApiTableVoiceCallEndReasons.h

  Voice Service Call and supplementary services end reasons.
- file qaGobiApiTableCodingScheme.h

  Data Coding Scheme.
- file qaGobiApiTableCallControlReturnReasons.h

  Call Control Return Reasons table.
- file qaGobiApiTableSupServiceInfoClasses.h

  Voice Supplementary Service Information Classes.
- file qaGobiApiVoice.h

  Voice Service API function prototypes.

6.14.1 Detailed Description

6.15 Non-service specific APIs (SWI)

Files

- file qaGobiApiSwi.h

  SWI API function prototypes.

6.15.1 Detailed Description

6.16 User Identity Module Service (UIM)

Files

- file qaGobiApiUim.h

  Uim Service API function prototypes.

6.16.1 Detailed Description

6.17 Audio Service (AUDIO)

Files

- file qaGobiApiAudio.h

  Audio Service API function prototypes.

6.17.1 Detailed Description

6.18 Quality of Service (QOS)

Files

- file qaGobiApiQos.h

  Quality of Service API function prototypes.

6.18.1 Detailed Description

6.19 IMS Service (IMS)

Files

- file qaGobiApiIms.h

  IMS Service API function prototypes.
- file qaGobiApiImsa.h

  IMSA Service API function prototypes.

6.19.1 Detailed Description

6.20 SWI Audio Service(SWIAUDIO)

Files

- file qaGobiApiTableSwiAudio.h

  Swi Audio related tables.
- file qaGobiApiSwiAudio.h

  M2M Audio Service API function prototypes.

6.20.1 Detailed Description

6.21 Location Service(LOC)

Files

- file qaGobiApiLoc.h

  Location API function prototypes.

6.21.1 Detailed Description

6.22 Thermal Mitigation Device(TMD)

Files

- file qaGobiApiTmd.h

  Thermal Mitigation Device API function prototypes.

6.22.1 Detailed Description

6.23 AVMS (SWIAVMS)

Files

- file qaGobiApiSwiAvms.h

  SWI Open Mobile Alliance Device Management Service API function prototypes SWI AVMS QMI Service revision 1.14.

6.23.1 Detailed Description

6.24 SWIDMS

Files

- file qaGobiApiSwiDms.h

  SWI DMS API function prototypes.

6.24.1 Detailed Description

Chapter 7

Namespace Documentation

7.1 Tables Namespace Reference

7.1.1 Detailed Description

Tables referenced in the API function headers:

- Table 1 - Call End Reason Codes The reason a call (either in process or connected) was ended. qaGobiApiTableCallEndReasons.h
- Table 2 - Carrier codes List of carrier identification codes. qaGobiApiTableCarrierCodes.h
- Table 3 - Region codes List of region identification codes. qaGobiApiTableRegionCodes.h
- Table 4 - GPS capability codes List of GPS capability codes. qaGobiApiTableGpsCapabilityCodes.h
- Table 5 - Radio Interfaces List of radio interface technologies. qaGobiApiTableRadioInterfaces.h
- Table 6 - Band classes List of band classes. qaGobiApiTableBandClasses.h
- Table 7 - Power modes List of operating modes. qaGobiApiTablePowerModes.h
- Table 8 - Service Options List of Service Options. qaGobiApiTableServiceOptions.h
- Table 9 - Voice Call End Reason List of Voice Call End Reason. qaGobiApiTableVoiceCallEndReasons.h
- Table 10 - Data Coding Scheme List of Data Coding Scheme. qaGobiApiTableCodingScheme.h
- Table 11 - Call Control Return Reasons List of Voice Call Control Return Reasons. qaGobiApiTableCallControlReturnReasons.h
- Table 12 - Supplementary Service Information Classes List of Voice Supplementary Service Information Classes. qaGobiApiTableSupServiceInfoClasses.h
- Table 13 - Audio Calibration Data Base(ACDB) Device List of ACDB devices. qaGobiApiTableSwiAudio.h
- Table 14 - PIFACE List of physical interfaces. qaGobiApiTableSwiAudio.h

Chapter 8

Data Structure Documentation

8.1 _getIndicationRegResp Struct Reference

Data Fields

- BYTE * pRegTransLayerInfoEvt
- BYTE * pRegTransNWRegInfoEvt
- BYTE * pRegCallStatInfoEvt

8.1.1 Detailed Description

This structure contains Get Indication Register Response parameters

Parameters

pRegTrans-LayerInfoEvt	- • Optional 1 BYTE parameter indicating registration status of transport layer information events • Values: – 0x00 - Disabled – 0x01 - Enabled • function SLQSGetIndicationRegister() returns a default value 0xFF if this parameter is allocated memory in the structure and no response is received from the device.
pRegTransNW-RegInfoEvt	- • Optional 1 BYTEparameter indicating registration status of transport network registration information events • Values: – 0x00 - Disabled – 0x01 - Enabled • function SLQSGetIndicationRegister() returns a default value 0xFF if this parameter is allocated memory in the structure and no response is received from the device.
pRegCallStat-InfoEvt	- • Optional 1 BYTE parameter indicating registration status of call status information events • Values: – 0x00 - Disabled – 0x01 - Enabled • function SLQSGetIndicationRegister() returns a default value 0xFF if this parameter is allocated memory in the structure and no response is received from the device.

8.1.2 Field Documentation

8.1.2.1 BYTE* _getIndicationRegResp::pRegCallStatInfoEvt

8.1.2.2 BYTE* _getIndicationRegResp::pRegTransLayerInfoEvt

8.1.2.3 BYTE* _getIndicationRegResp::pRegTransNWRegInfoEvt

8.2 _GetProfileSettingIn Struct Reference

Data Fields

- BYTE ProfileType
- BYTE ProfileID

8.2.1 Detailed Description

This structure contains the input parameters for SLQSGetProfileSettings

Parameters

ProfileType	• Identifies the technology type of the profile – 0x00 - 3GPP – 0x01 - 3GPP2
ProfileID	• index identifying the profile

8.2.2 Field Documentation

8.2.2.1 BYTE _GetProfileSettingIn::ProfileID

8.2.2.2 BYTE _GetProfileSettingIn::ProfileType

8.3 _GetProfileSettingOut Struct Reference

Data Fields

- QmiProfileInfo curProfile
- WORD * pExtErrCode

8.3.1 Detailed Description

This structure contains the profile settings retrieved by the API SLQSGetProfileSettings

Parameters

curProfile	• Structure containing details of the profile • See QmiProfileInfo for more details

pExtErrCode	• pointer to a 2 byte extended error code • Error code will only will be present if error code eQCWWAN_ERR_QMI_EXTENDED_INTERNAL is returned by device. • See qm_wds_ds_profile_extended_err_codes enum in qmerrno.h for received error description.

8.3.2 Field Documentation

8.3.2.1 QmiProfileInfo _GetProfileSettingOut::curProfile

8.3.2.2 WORD* _GetProfileSettingOut::pExtErrCode

8.4 _getResetInfoNotification Struct Reference

Data Fields

- BYTE type
- BYTE source

8.4.1 Detailed Description

Contains the parameters passed for SLQSSetSwiGetResetInfoCallback by the device.

Parameters

type	• type of reset or power down, possible values listed below: – 0 - unknown – 1 - warm – 2 - hard – 3 - crash – 4 - power down
source	• entity which initiated the reset or power down, possible values listed below: – 0 - unknown – 1 - user requested – 2 - hardware switch – 3 - temperature critical – 4 - voltage critical – 5 - configuration update – 6 - LWM2M – 7 - OMA-DM – 8 - FOTA

Note

None

8.4.2 Field Documentation

8.4.2.1 BYTE _getResetInfoNotification::source

8.4.2.2 BYTE _getResetInfoNotification::type

8.5 _getTransLayerInfoResp Struct Reference

Data Fields

- BYTE * pRegInd
- transLayerInfo * pTransLayerInfo

8.5.1 Detailed Description

This structure contains Get Transport Layer Info Response parameters

Parameters

pRegInd	- • Optional parameter indicating if transport layer is registered • Values: – 0x00 - Transport layer is not registered – 0x01 - Transport layer is registered • function SLQSGetTransLayerInfo() returns a default value 0xFF if no response is received from the device.
pTransLayerInfo	• Pointer to structure of transLayerInfo. – Optional parameter – See transLayerInfo for more information • function SLQSGetTransLayerInfo() returns a default value 0xFF for parameter values if no response is received from the device.

8.5.2 Field Documentation

8.5.2.1 BYTE* _getTransLayerInfoResp::pRegInd

8.5.2.2 transLayerInfo* _getTransLayerInfoResp::pTransLayerInfo

8.6 _getTransNWRegInfoResp Struct Reference

Data Fields

- BYTE * pRegStatus

8.6.1 Detailed Description

This structure contains transport network registration info parameter

Parameters

pRegStatus	- • Optional 1 BYTE parameter indicating transport layer network registration status • Values: – 0x00 - No service – 0x01 - In progress – 0x02 - Failed – 0x03 - Limited Service – 0x04 - Full Service • function SLQSGetTransNWRegInfo() returns a default value 0xFF if no response is received from the device.

8.6.2 Field Documentation

8.6.2.1 BYTE* _getTransNWRegInfoResp::pRegStatus

8.7 _MitigationDevInfo Struct Reference

Data Fields

- BYTE deviceIdLen
- CHAR deviceID [255]

8.7.1 Detailed Description

This structure contains mitigation Level Indication request parameters

Parameters

deviceIdLen	• Number of sets of the following elements – deviceID
deviceID	• Mitigation device ID

8.7.2 Field Documentation

8.7.2.1 CHAR _MitigationDevInfo::deviceID[255]

8.7.2.2 BYTE _MitigationDevInfo::deviceIdLen

8.8 _modemTempNotification Struct Reference

Data Fields

- BYTE ModemTempState
- WORD ModemTemperature

8.8.1 Detailed Description

Contains the parameters passed for SLQSSetModemTempCallback by the device.

Parameters

ModemTemp-State	• provides the temperature state of the modem • Values: – 0 - unknown – 1 - normal – 2 - high(warning) – 3 - high(critical) – 4 - low(critical)
Modem-Temperature	• provides the temperature of the modem

Note

None

8.8.2 Field Documentation

8.8.2.1 WORD _modemTempNotification::ModemTemperature

8.8.2.2 BYTE _modemTempNotification::ModemTempState

8.9 _modemUIMStatusNotification Struct Reference

Data Fields

- BYTE ModemUIMStatusInterface
- BYTE ModemUIMStatusEvent

8.9.1 Detailed Description

Contains the parameters passed for SLQSSetUIMStatusCallback by the device.

Parameters

ModemUIM-StatusInterface	• provides the temperature state of the modem • Values: – 0 - External UIM. – 1 - Embedded UIM. – 2 - Remote UIM.
ModemUIM-StatusEvent	• Values: – 0 - UIM card removed. – 1 - UIM card inserted.

Note

None

8.9.2 Field Documentation

8.9.2.1 BYTE _modemUIMStatusNotification::ModemUIMStatusEvent

8.9.2.2 BYTE _modemUIMStatusNotification::ModemUIMStatusInterface

8.10 _packetSrvStatus Struct Reference

Data Fields

- qaQmiInterfaceInfo * pQmiInterfaceInfo
- BYTE connStatus
- BYTE reconfigReqd
- WORD sessionEndReason
- WORD verboseSessnEndReasonType
- WORD verboseSessnEndReason
- BYTE ipFamily
- WORD techName
- BYTE bearerID

8.10.1 Detailed Description

Contains the parameters passed for SLQSSetPacketSrvStatusCallback by the device.

Parameters

pQmiInterface-Info	• See qaQmiInterfaceInfo for more information
connStatus	• Current Link Status – 1 - Disconnected – 2 - Connected – 3 - Suspended – 4 - Authenticating
reconfigReqd	• Indicates if the network interface on the host needs to be reconfigured – 0 - No need to reconfigure – 1 - Reconfiguration required
sessionEnd-Reason	• See qaGobiApiTableCallEndReasons.h for Call End Reason, 0xFFFF means invalid value

verboseSessnEndReasonType	• Call End Reason Type – 0 - Unspecified – 1 - Mobile IP – 2 - Internal – 3 - Call Manager defined – 6 - 3GPP Specification defined – 7 - PPP – 8 - EHRPD – 9 - IPv6 – 0xFFFF - invalid value
verboseSessnEndReason	• See qaGobiApiTableCallEndReasons.h for verbose Call End Reason. The values depend on verboseSessnEndReasonType parameter 0xFFFF means invalid value
ipFamily	• IP Family of the packet data connection – 4 - IPv4 – 6 - IPv6 – 0xFF - invalid value
techName	• Technology name of the packet data connection. – 32767 - CDMA – 32764 - UMTS – 30592 - EPC – 30590 - EMBMS – 30584 - Modem Link Local – 0xFFFF - invalid value EPC is a logical interface to support LTE/eHRPD handoff. Modem Link is an interface for transferring data between entities on the AP and modem.
bearerID	• Bearer ID (3GPP) or RLP ID (3GPP2) of the packet data connection 0xFF means invalid value

Note

Any parameter not returned by the device is returned as its maximum unsigned value by the callback.

8.10.2 Field Documentation

8.10.2.1 BYTE _packetSrvStatus::bearerID

8.10.2.2 BYTE _packetSrvStatus::connStatus

8.10.2.3 BYTE _packetSrvStatus::ipFamily

8.10.2.4 qaQmiInterfaceInfo* _packetSrvStatus::pQmiInterfaceInfo

8.10.2.5 BYTE _packetSrvStatus::reconfigReqd

8.10.2.6 WORD _packetSrvStatus::sessionEndReason

8.10.2.7 WORD _packetSrvStatus::techName

8.10.2.8 WORD _packetSrvStatus::verboseSessnEndReason

8.10.2.9 WORD _packetSrvStatus::verboseSessnEndReasonType

8.11 _qaQmi3GPP2BroadcastCfgInfo Struct Reference

Data Fields

- BYTE activated_ind
- WORD num_instances
- struct CDMABroadcastConfig CDMABroadcastConfig [0x05]

8.11.1 Detailed Description

This structure contains the 3GPP2 Broadcast Configuration Information parameters

Parameters

activated_ind	• Broadcast SMS – 0x00 - Deactivated – 0x01 - Activated
num_instances	• Number of sets (N) of parameters Following each set describes one entry in the broadcast configuration table. – serviceCategory – language – selected
broadcastConfig	• A CDMABroadcastConfig structure array. • Further defined by the structure CDMABroadcastConfig

8.11.2 Field Documentation

8.11.2.1 BYTE _qaQmi3GPP2BroadcastCfgInfo::activated_ind

8.11.2.2 struct CDMABroadcastConfig _qaQmi3GPP2BroadcastCfgInfo::CDMABroadcastConfig[0x05]

8.11.2.3 WORD _qaQmi3GPP2BroadcastCfgInfo::num_instances

8.12 _qaQmi3GPPBroadcastCfgInfo Struct Reference

Data Fields

- BYTE activated_ind
- WORD num_instances

- struct BroadcastConfig broadcastConfig [0x05]

8.12.1 Detailed Description

This structure contains the 3GPP Broadcast Configuration Information parameters

Parameters

activated_ind	• Broadcast SMS – 0x00 - Deactivated – 0x01 - Activated
num_instances	• Number of sets (N) of parameters Following each set describes one entry in the broadcast configuration table. – fromServiceId – toServiceId – selected
broadcastConfig	• A BroadcastConfig structure array. • Further defined by the structure BroadcastConfig

8.12.2 Field Documentation

8.12.2.1 BYTE _qaQmi3GPPBroadcastCfgInfo::activated_ind

8.12.2.2 struct BroadcastConfig _qaQmi3GPPBroadcastCfgInfo::broadcastConfig[0x05]

8.12.2.3 WORD _qaQmi3GPPBroadcastCfgInfo::num_instances

8.13 _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp Struct Reference

Data Fields

- BYTE bBinaryType
- BYTE bState
- BYTE bUserInputRequest
- WORD wUserInputTimeout
- ULONG ulPkgDownloadSize
- ULONG ulPkgDownloadComplete
- WORD wUpdateCompeteStatus
- BYTE bSerity
- WORD wVersionLength
- CHAR szVersion [128]
- WORD wNameLength
- CHAR szName [128]
- WORD wDescriptionLength
- CHAR szDescription [1024]
- BYTE TlvPresent

8.13.1 Detailed Description

Parameters

bBinaryType	: Type • 1 - Firmware. • 2 - User App. • 3 - Legato Framework.
bStat	: State • 0x01 - No binary update available. • 0x02 - Query binary Download. • 0x03 - Binary Downloading. • 0x04 - Binary downloaded. • 0x05 -Query Binary Update. • 0x06 - Binary updating. • 0x07 - Binary updated.
bUserInput-Request	Bit mask of available user inputs. • 0x00 - No user input required. Informational indication. • 0x01 - Accept. • 0x02 - Reject.
wUserInput-Timeout	Timeout for user input in minutes. A value of 0 means no time-out.
ulPkgDownload-Size	The size (in bytes) of the update package
ulPkgDownload-Complete	The number of bytes being downloaded. For downloading state, this value shall be $>$ 0 and incremented toward the pkg_dload_size. For other states, the value shall be 0 as it is meaningless.
wUpdate-CompeteStatus	Result code.This field should be looked at only when the AVMS session is complete.
bSerity	Serity. • 0x01 - Mandatory. • 0x02 - Optional.
wVersionLength	Length of FW Version string in bytes.
szVersion	FW Version string in ASCII.
wNameLength	Length Package Name string in bytes.
szName	Package Name in UCS2.
wDescription-Length	Length of description in bytes.
szDescription	Description of Update Package in USC2.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.13.2 Field Documentation

8.13.2.1 BYTE _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::bBinaryType

8.13.2.2 BYTE _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::bSerity

8.13.2.3 BYTE _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::bState

8.13.2.4 BYTE _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::bUserInputRequest

8.13.2.5 CHAR _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::szDescription[1024]

8.13.2.6 CHAR _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::szName[128]

8.13.2.7 CHAR _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::szVersion[128]

8.13.2.8 BYTE _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::TlvPresent

8.13.2.9 ULONG _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::ulPkgDownloadComplete

8.13.2.10 ULONG _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::ulPkgDownloadSize

8.13.2.11 WORD _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::wDescriptionLength

8.13.2.12 WORD _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::wNameLength

8.13.2.13 WORD _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::wUpdateCompeteStatus

8.13.2.14 WORD _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::wUserInputTimeout

8.13.2.15 WORD _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp::wVersionLength

8.14 _QmiSwiAvmsEventReportConfigResp Struct Reference

Data Fields

- BYTE bState
- BYTE bUserInputRequest
- WORD wUserInputTimeout
- WORD wAlertMsgLength
- CHAR szAlertMsg [200]
- BYTE TlvPresent

8.14.1 Detailed Description

Parameters

bState	State. • 0x01 - AVMS Read Request. • 0x02 - AVMS Change Request. • 0x03 - AVMS Config Complete.
bUserInput-Request	Bit mask of available user inputs. • 0x00 - No user input required. Informational indication. • 0x01 - Accept. • 0x02 - Reject.
wUserInput-Timeout	Timeout for user input in seconds. A value of 0 means no time-out
wAlertMsg-Length	Length of Alert message string in bytes.
szAlertMsg	Alert message in UCS2.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.14.2 Field Documentation

8.14.2.1 BYTE _QmiSwiAvmsEventReportConfigResp::bState

8.14.2.2 BYTE _QmiSwiAvmsEventReportConfigResp::bUserInputRequest

8.14.2.3 CHAR _QmiSwiAvmsEventReportConfigResp::szAlertMsg[200]

8.14.2.4 BYTE _QmiSwiAvmsEventReportConfigResp::TlvPresent

8.14.2.5 WORD _QmiSwiAvmsEventReportConfigResp::wAlertMsgLength

8.14.2.6 WORD _QmiSwiAvmsEventReportConfigResp::wUserInputTimeout

8.15 _QmiSwiAvmsEventReportConnectionRequestResp Struct Reference

Data Fields

- BYTE bUserInputRequest
- WORD wUserInputTimeout
- BYTE TlvPresent

8.15.1 Detailed Description

Parameters

bUserInput-Request	Bit mask of available user inputs. • 0x00 - No user input required. Informational indication. • 0x01 - Accept. • 0x02 - Reject.
bUserInput-Request	Timeout for user input in minutes. A value of 0 means no time-out.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.15.2 Field Documentation

8.15.2.1 BYTE _QmiSwiAvmsEventReportConnectionRequestResp::bUserInputRequest

8.15.2.2 BYTE _QmiSwiAvmsEventReportConnectionRequestResp::TlvPresent

8.15.2.3 WORD _QmiSwiAvmsEventReportConnectionRequestResp::wUserInputTimeout

8.16 _QmiSwiAvmsEventReportDataSessionStatusResp Struct Reference

Data Fields

- BYTE bType
- WORD wErrorCode
- BYTE TlvPresent

8.16.1 Detailed Description

Parameters

bType	Notification type. • 0: Data session closed. • 1: Data session activated. • 2: Register made. -3: Data session error.
wErrorCode	LWM2M Session error code. • 0x0000: none
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.16.2 Field Documentation

8.16.2.1 BYTE _QmiSwiAvmsEventReportDataSessionStatusResp::bType

8.16.2.2 BYTE _QmiSwiAvmsEventReportDataSessionStatusResp::TlvPresent

8.16.2.3 WORD _QmiSwiAvmsEventReportDataSessionStatusResp::wErrorCode

8.17 _QmiSwiAvmsEventReportHTTPStatusResp Struct Reference

Data Fields

- WORD wHTTPStatus
- BYTE TlvPresent

8.17.1 Detailed Description

Parameters

wHTTPStatus	See RFC 7231. • 100 - Continue • 101 - Switching Protocols • 200 - OK • 201 - Created • 202 - Accepted • 203 - Non-Authoritative Information • 204 - No Content • 205 - Reset Content • 206 - Partial Content • 300 - Multiple Choices • 301 - Moved Permanently • 302 - Found • 303 - See Other • 304 - Not Modified • 305 - Use Proxy • 307 - Temporary Redirect • 400 - Bad Request • 401 - Unauthorized • 402 - Payment Required • 403 - Forbidden • 404 - Not Found • 405 - Method Not Allowed • 406 - Not Acceptable • 407 - Proxy Authentication Required • 408 - Request Timeout • 409 - Conflict • 410 - Gone • 411 - Length Required • 412 - Precondition Failed • 413 - Payload Too Large • 414 - URI Too Long • 415 - Unsupported Media Type • 416 - Range Not Satisfiable • 417 - Expectation Failed • 426 - Upgrade Required • 500 - Internal Server Error • 501 - Not Implemented • 502 - Bad Gateway • 503 - Service Unavailable • 504 - Gateway Timeout • 505 - HTTP Version Not Supported
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.17.2 Field Documentation

8.17.2.1 BYTE _QmiSwiAvmsEventReportHTTPStatusResp::TlvPresent

8.17.2.2 WORD _QmiSwiAvmsEventReportHTTPStatusResp::wHTTPStatus

8.18 _QmiSwiAvmsEventReportNotificationResp Struct Reference

Data Fields

- BYTE bNotification
- WORD wSessionStatus
- BYTE TlvPresent

8.18.1 Detailed Description

Parameters

bNotification	Notification. • 0x14 - Module starts sending data to server. • 0x15 - Authentication with the server. • 0x16 - session with the server is ended.
wSessionStatus	This field will set to the session status for notifications that occur at the end of a session, zero for all other notifications. • 0x0000: Successful: Session succeeded • 0x0001: Break: Session succeeded • 0x0002: Large Object Handled: Session succeeded • 0x0003: No status: Session succeeded • 0x0004: No more commands: Session succeeded • 0x0005: User cancel: Session cancelled • 0x0100-0x01FF: General errors • 0x0200-0x02FF: Syncml errors • 0x0300-0x03FF: Authentication errors • 0x0400-0x04FF: Protocol errors • 0x0500-0x05FF: Tree errors (DM Only) • 0x0600-0x06FF: Not applicable • 0x0700-0x07FF: Trigger errors • 0x0800-0x08FF: FUMO errors • 0x0900-0x09FF: Communication errors • 0x0A00-0x0AFF: Parsing errors • 0x0B00-0x0CFF: Not applicable • 0x7F00-0x7F12:Insignia errors • 0x7F13: Illegal text: Text received contains illegal characters • 0x7F14: Download failure: Failed to download FOTA image • 0x7F15: Empty session: Session ran successfully, but no information wasa updated • 0x7F16: Factory reset successful: Factory reset succeeded • 0x7F17: Factory reset fail: Factory reset failed
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.18.2 Field Documentation

8.18.2.1 BYTE _QmiSwiAvmsEventReportNotificationResp::bNotification

8.18.2.2 BYTE _QmiSwiAvmsEventReportNotificationResp::TlvPresent

8.18.2.3 WORD _QmiSwiAvmsEventReportNotificationResp::wSessionStatus

8.19 _QmiSwiAvmsEventReportPackageIDResp Struct Reference

Data Fields

- BYTE bPackageID
- BYTE TlvPresent

8.19.1 Detailed Description

Parameters

bPackageID	Package ID of the application binary that this AVMS_EVENT_ID notification is for.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.19.2 Field Documentation

8.19.2.1 BYTE _QmiSwiAvmsEventReportPackageIDResp::bPackageID

8.19.2.2 BYTE _QmiSwiAvmsEventReportPackageIDResp::TlvPresent

8.20 _QmiSwiAvmsEventReportRegStatusResp Struct Reference

Data Fields

- BYTE bRegStatus
- BYTE TlvPresent

8.20.1 Detailed Description

Parameters

bRegStatus	LWM2M Registration status. • 0: Need Bootstrap. • 1: Bootstrap made. • 2: Register made. -3: Update made.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.20.2 Field Documentation

8.20.2.1 BYTE _QmiSwiAvmsEventReportRegStatusResp::bRegStatus

8.20.2.2 BYTE _QmiSwiAvmsEventReportRegStatusResp::TlvPresent

8.21 _QmiSwiAvmsEventReportSessionTypeResp Struct Reference

Data Fields

- BYTE bType
- BYTE TlvPresent

8.21.1 Detailed Description

Parameters

bType	Session Type. • 0: Bootstrap session. • 1. DM session
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.21.2 Field Documentation

8.21.2.1 BYTE _QmiSwiAvmsEventReportSessionTypeResp::bType

8.21.2.2 BYTE _QmiSwiAvmsEventReportSessionTypeResp::TlvPresent

8.22 _QmiSwiAvmsEventReportWAMSParamChangeResp Struct Reference

Data Fields

- WORD wWamsChangeMask
- BYTE TlvPresent

8.22.1 Detailed Description

Parameters

wWamsChange-Mask	Mask of WAMS parameters changed. • By default set to 0xFF for all changes. • 0x01 - device_login • 0x02 - device_MD5_key • 0x04 - server_login • 0x08 - server_MD5_key • 0x10 - server_URL • 0x20 - Nonce • 0x40 - Application key
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

8.22.2 Field Documentation

8.22.2.1 BYTE _QmiSwiAvmsEventReportWAMSParamChangeResp::TlvPresent

8.22.2.2 WORD _QmiSwiAvmsEventReportWAMSParamChangeResp::wWamsChangeMask

8.23 _QmiSwiAvmsSetSettingsAPNInfo Struct Reference

Data Fields

- BYTE bAPNLength
- CHAR szAPN [49]
- BYTE bUnameLength
- CHAR szUname [29]
- BYTE bPWDLength
- CHAR szPWD [29]

8.23.1 Field Documentation

8.23.1.1 BYTE _QmiSwiAvmsSetSettingsAPNInfo::bAPNLength

8.23.1.2 BYTE _QmiSwiAvmsSetSettingsAPNInfo::bPWDLength

8.23.1.3 BYTE _QmiSwiAvmsSetSettingsAPNInfo::bUnameLength

8.23.1.4 CHAR _QmiSwiAvmsSetSettingsAPNInfo::szAPN[49]

8.23.1.5 CHAR _QmiSwiAvmsSetSettingsAPNInfo::szPWD[29]

8.23.1.6 CHAR _QmiSwiAvmsSetSettingsAPNInfo::szUname[29]

8.24 _QmiSwiAvmsSetSettingsConnectionRetryTimers Struct Reference

Data Fields

- WORD Timers [8]

8.24.1 Field Documentation

8.24.1.1 WORD _QmiSwiAvmsSetSettingsConnectionRetryTimers::Timers[8]

8.25 _QmiSwiAvmsSetSettingsPeriodInfo Struct Reference

Data Fields

- ULONG ulMin
- ULONG ulMax

8.25.1 Field Documentation

8.25.1.1 ULONG _QmiSwiAvmsSetSettingsPeriodInfo::ulMax

8.25.1.2 ULONG _QmiSwiAvmsSetSettingsPeriodInfo::ulMin

8.26 _setIndicationRegReq Struct Reference

Data Fields

- BYTE * pRegTransLayerInfoEvt
- BYTE * pRegTransNWRegInfoEvt

- BYTE * pRegCallStatInfoEvt

8.26.1 Detailed Description

This structure contains Indication Register request parameters

Parameters

pRegTrans-LayerInfoEvt	- • Optional 1 BYTE parameter indicating registration status of transport layer information events • Values: – 0x00 - Disabled – 0x01 - Enabled – NULL - No change - specifying NULL indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device
pRegTransNW-RegInfoEvt	- • Optional 1 BYTE parameter indicating registration status of transport network registration information events • Values: – 0x00 - Disabled – 0x01 - Enabled – NULL - No change - specifying NULL indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device
pRegCallStat-InfoEvt	- • Optional 1 BYTE parameter indicating registration status of call status information events • Values: – 0x00 - Disabled – 0x01 - Enabled – NULL - No change - specifying NULL indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device

8.26.2 Field Documentation

8.26.2.1 BYTE* _setIndicationRegReq::pRegCallStatInfoEvt

8.26.2.2 BYTE* _setIndicationRegReq::pRegTransLayerInfoEvt

8.26.2.3 BYTE* _setIndicationRegReq::pRegTransNWRegInfoEvt

8.27 _slqs3GPPConfigItem Struct Reference

Data Fields

- WORD * pLTEAttachProfile
- WORD * pProfileList
- BYTE * pDefaultPDNEnabled
- BYTE * p3gppRelease
- WORD LTEAttachProfileListLen
- WORD * pLTEAttachProfileList

8.27.1 Detailed Description

This structure contains the 3gpp Configuration Item information.

Parameters

pLTEAttach-Profile	• LTE Attach Profile – points to a single WORD Value indicating the attached LTE Profile – Optional parameter with possible values 1-16 (EM/MC73xx or earlier) – function SLQSGet3GPPConfigItem() returns a default value 255 if no LTE Attach Profile is configured • This setting is deprecated on MC/EM74xx
pProfileList	• Profile List – an array of 4 profile configurations – Each element points to a single WORD value indicating profile – Optional parameter with possible values * 1 - 16 (MC/EM73xx and before) * 1 - 24 (MC/EM74xx and onwards) – function SLQSGet3GPPConfigItem() returns a default value 255 if no 3gpp configuration is present
pDefaultPDN-Enabled	• Always Connect Default PDN – A single BYTE value indicating the status of Always connect default PDN * 0 - disabled * 1 - enabled – Optional parameter – function SLQSGet3GPPConfigItem() returns a default value 255 if no 3gpp configuration is present
p3gppRelease	• 3gpp release – A single BYTE value indicating the 3gpp release * 0 - Release 99 * 1 - Release 5 * 2 - Release 6 * 3 - Release 7 * 4 - Release 8 – In 9x30 and onwards * 5 - Release 9 * 6 - Release 10 * 7 - Release 11 – Optional parameter – function SLQSGet3GPPConfigItem() returns a default value 255 if no 3gpp configuration is present

pLTEAttach-ProfileList	• pointer to WORD array indicating LTE Attach Profile List – Optional parameter – possible values: 1-24 – This setting is only supported for MC/EM74xx onwards – The new equivalent option for "pLTEAttachProfile" on 74xx modems is "pLTEAttachProfile-List". Please provide attach profiles in order of decreasing priority in this list.
LTEAttach-ProfileListLen	• Number of element in pLTEAttachProfileList – valid range: 1-24 * This setting is only supported for MC/EM74xx onwards

8.27.2 Field Documentation

8.27.2.1 WORD _slqs3GPPConfigItem::LTEAttachProfileListLen

8.27.2.2 BYTE* _slqs3GPPConfigItem::p3gppRelease

8.27.2.3 BYTE* _slqs3GPPConfigItem::pDefaultPDNEnabled

8.27.2.4 WORD* _slqs3GPPConfigItem::pLTEAttachProfile

8.27.2.5 WORD* _slqs3GPPConfigItem::pLTEAttachProfileList

8.27.2.6 WORD* _slqs3GPPConfigItem::pProfileList

8.28 _SLQSAVMSSetSettingsReqPara Struct Reference

Data Fields

- BYTE * pAutoConnect
- BYTE * pAutoReboot
- BYTE * pFwPromptdownload
- BYTE * pFwPromptUpdate
- BYTE * pFwAutoSDM
- ULONG * pPollingTimer
- QmiSwiAvmsSetSettingsConnectionRetryTimers * pConnectionRetryTimers
- QmiSwiAvmsSetSettingsAPNInfo * pAPNInfo
- BYTE * pNotifStore
- QmiSwiAvmsSetSettingsPeriodInfo * pPeroidInfo

8.28.1 Detailed Description

Sets the AVMS settings requested (For AVC1 service).

Parameters

bAutoConnect[IN]	• Auto Connect to AirVantage server – 0x00 - FALSE – 0x01 - TRUE
bAutoReboot[IN]	• Automatic device reboot when the request is received from AirVantage server – 0x00 - FALSE – 0x01 - TRUE
bFwPromptdownload[IN]	• Start Firmware Download promptly/automatically – 0x00 - FALSE – 0x01 - TRUE
bFwPromptUpdate[IN]	• Start Firmware Download promptly/automatically – 0x00 - FALSE – 0x01 - TRUE
FwAutoSDM[Optional]	- OMA Automatic UI Alert Response • 0x00 - DISABLED • 0x01 - ENABLED ACCEPT • 0x02 - ENABLED REJECT
PollingTimer[Optional]	• 0-525600 (min) • 0:disabled
ConnectionRetryTimers[Optional]	• See QmiSwiAvmsSetSettingsConnectionRetryTimers for more information
APNInfo[Optional]	• See QmiSwiAvmsSetSettingsAPNInfo for more information
NotifStore[Optional]	• 0 : Disabled. • 1 : Enabeld.
PeroidInfo[Optional]	• See QmiSwiAvmsSetSettingsPeriodInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

8.28.2 Field Documentation

8.28.2.1 QmiSwiAvmsSetSettingsAPNInfo* _SLQSAVMSSetSettingsReqPara::pAPNInfo

8.28.2.2 BYTE* _SLQSAVMSSetSettingsReqPara::pAutoConnect

8.28.2.3 BYTE* _SLQSAVMSSetSettingsReqPara::pAutoReboot

8.28.2.4 QmiSwiAvmsSetSettingsConnectionRetryTimers* _SLQSAVMSSetSettingsReqPara::pConnectionRetry-Timers

8.28.2.5 BYTE* _SLQSAVMSSetSettingsReqPara::pFwAutoSDM

8.28.2.6 BYTE* _SLQSAVMSSetSettingsReqPara::pFwPromptdownload

8.28.2.7 BYTE* _SLQSAVMSSetSettingsReqPara::pFwPromptUpdate

8.28.2.8 BYTE* _SLQSAVMSSetSettingsReqPara::pNotifStore

8.28.2.9 QmiSwiAvmsSetSettingsPeriodInfo* _SLQSAVMSSetSettingsReqPara::pPeroidInfo

8.28.2.10 ULONG* _SLQSAVMSSetSettingsReqPara::pPollingTimer

8.29 _SLQSAVMSSetSettingsReqPara_v2 Struct Reference

Data Fields

- BYTE * pAutoConnect
- BYTE * pFwPromptdownload
- BYTE * pFwPromptUpdate
- BYTE * pFwAutoSDM
- ULONG * pPollingTimer
- QmiSwiAvmsSetSettingsConnectionRetryTimers * pConnectionRetryTimers
- QmiSwiAvmsSetSettingsAPNInfo * pAPNInfo
- BYTE * pNotifStore
- QmiSwiAvmsSetSettingsPeriodInfo * pPeroidInfo
- BYTE * pAutoReboot

8.29.1 Detailed Description

Sets the AVMS settings requested (For AVC2 service).

Parameters

bAutoConnect[IN]	• Auto Connect to AirVantage server – 0x00 - FALSE – 0x01 - TRUE
bFwPromptdownload[IN]	• Start Firmware Download promptly/automatically – 0x00 - FALSE – 0x01 - TRUE

bFwPrompt-Update[IN]	• Start Firmware Download promptly/automatically – 0x00 - FALSE – 0x01 - TRUE
FwAutoSDM[-Optional]	- OMA Automatic UI Alert Response • 0x00 - DISABLED • 0x01 - ENABLED ACCEPT • 0x02 - ENABLED REJECT
PollingTimer[-Optional]	• 0-525600 (min) • 0:disabled
Connection-RetryTimers[-Optional]	• See QmiSwiAvmsSetSettingsConnectionRetryTimers for more information
APNInfo[-Optional]	• See QmiSwiAvmsSetSettingsAPNInfo for more information
NotifStore[-Optional]	• 0 : Disabled. • 1 : Enabeld.
PeroidInfo[-Optional]	• See QmiSwiAvmsSetSettingsPeriodInfo for more information
bAutoReboot[-Optional]	• Automatic device reboot when the request is received from AirVantage server – 0x00 - FALSE – 0x01 - TRUE

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Setting PromptFwDownload/PromptFwUpdate as TRUE implies AutoConnect to be also TRUE even if AutoConnect was set FALSE initially. Automatic firmware download/update selection trumps the connection setting flag.

8.29.2 Field Documentation

8.29.2.1 QmiSwiAvmsSetSettingsAPNInfo* _SLQSAVMSSetSettingsReqPara_v2::pAPNInfo

8.29.2.2 BYTE* _SLQSAVMSSetSettingsReqPara_v2::pAutoConnect

8.29.2.3 BYTE* _SLQSAVMSSetSettingsReqPara_v2::pAutoReboot

8.29.2.4 QmiSwiAvmsSetSettingsConnectionRetryTimers* _SLQSAVMSSetSettingsReqPara_v2::pConnectionRetry-Timers

8.29.2.5 BYTE* _SLQSAVMSSetSettingsReqPara_v2::pFwAutoSDM

8.29.2.6 BYTE* _SLQSAVMSSetSettingsReqPara_v2::pFwPromptdownload

8.29.2.7 BYTE* _SLQSAVMSSetSettingsReqPara_v2::pFwPromptUpdate

8.29.2.8 BYTE* _SLQSAVMSSetSettingsReqPara_v2::pNotifStore

8.29.2.9 QmiSwiAvmsSetSettingsPeriodInfo* _SLQSAVMSSetSettingsReqPara_v2::pPeroidInfo

8.29.2.10 ULONG* _SLQSAVMSSetSettingsReqPara_v2::pPollingTimer

8.30 _SLQSAVMSSettings Struct Reference

Data Fields

- ULONG * pOMADMEnabled
- BYTE * pAutoConnect
- BYTE * pAutoReboot
- BYTE * pFwPromptdownload
- BYTE * pFwPromptUpdate
- BYTE * pFwAutoSDM
- ULONG * pPollingTimer
- SLQSAVMSSettingsConnectionRetryTimers * pConnectionRetryTimers
- SLQSAVMSSettingsAPNInfo * pAPNInfo
- BYTE * pNotificationStore
- SLQSAVMSSettingsPeriodsInfo * pPeroidsInfo

8.30.1 Field Documentation

8.30.1.1 SLQSAVMSSettingsAPNInfo* _SLQSAVMSSettings::pAPNInfo

8.30.1.2 BYTE* _SLQSAVMSSettings::pAutoConnect

8.30.1.3 BYTE* _SLQSAVMSSettings::pAutoReboot

8.30.1.4 SLQSAVMSSettingsConnectionRetryTimers* _SLQSAVMSSettings::pConnectionRetryTimers

8.30.1.5 BYTE* _SLQSAVMSSettings::pFwAutoSDM

8.30.1.6 BYTE* _SLQSAVMSSettings::pFwPromptdownload

8.30.1.7 BYTE* _SLQSAVMSSettings::pFwPromptUpdate

8.30.1.8 BYTE* _SLQSAVMSSettings::pNotificationStore

8.30.1.9 ULONG* _SLQSAVMSSettings::pOMADMEnabled

8.30.1.10 SLQSAVMSSettingsPeriodsInfo* _SLQSAVMSSettings::pPeroidsInfo

8.30.1.11 ULONG* _SLQSAVMSSettings::pPollingTimer

8.31 _SLQSAVMSSettings_v2 Struct Reference

Data Fields

- ULONG * pOMADMEnabled
- BYTE * pAutoConnect
- BYTE * pFwPromptdownload
- BYTE * pFwPromptUpdate
- BYTE * pFwAutoSDM
- ULONG * pPollingTimer
- SLQSAVMSSettingsConnectionRetryTimers * pConnectionRetryTimers
- SLQSAVMSSettingsAPNInfo * pAPNInfo
- BYTE * pNotificationStore
- SLQSAVMSSettingsPeriodsInfo * pPeroidsInfo
- BYTE * pAutoReboot

8.31.1 Field Documentation

8.31.1.1 SLQSAVMSSettingsAPNInfo* _SLQSAVMSSettings_v2::pAPNInfo

8.31.1.2 BYTE* _SLQSAVMSSettings_v2::pAutoConnect

8.31.1.3 BYTE* _SLQSAVMSSettings_v2::pAutoReboot

8.31.1.4 SLQSAVMSSettingsConnectionRetryTimers* _SLQSAVMSSettings_v2::pConnectionRetryTimers

8.31.1.5 BYTE* _SLQSAVMSSettings_v2::pFwAutoSDM

8.31.1.6 BYTE* _SLQSAVMSSettings_v2::pFwPromptdownload

8.31.1.7 BYTE* _SLQSAVMSSettings_v2::pFwPromptUpdate

8.31.1.8 BYTE* _SLQSAVMSSettings_v2::pNotificationStore

8.31.1.9 ULONG* _SLQSAVMSSettings_v2::pOMADMEnabled

8.31.1.10 SLQSAVMSSettingsPeriodsInfo* _SLQSAVMSSettings_v2::pPeroidsInfo

8.31.1.11 ULONG* _SLQSAVMSSettings_v2::pPollingTimer

8.32 _SLQSAVMSSettingsAPNInfo Struct Reference

Data Fields

- BYTE bAPNLength
- CHAR * pAPN
- BYTE bUnameLength
- CHAR * pUname
- BYTE bPWDLength
- CHAR * pPWD

8.32.1 Field Documentation

8.32.1.1 BYTE _SLQSAVMSSettingsAPNInfo::bAPNLength

8.32.1.2 BYTE _SLQSAVMSSettingsAPNInfo::bPWDLength

8.32.1.3 BYTE _SLQSAVMSSettingsAPNInfo::bUnameLength

8.32.1.4 CHAR* _SLQSAVMSSettingsAPNInfo::pAPN

8.32.1.5 CHAR* _SLQSAVMSSettingsAPNInfo::pPWD

8.32.1.6 CHAR* _SLQSAVMSSettingsAPNInfo::pUname

8.33 _SLQSAVMSSettingsConnectionRetryTimers Struct Reference

Data Fields

- WORD Timers [8]

8.33.1 Field Documentation

8.33.1.1 WORD _SLQSAVMSSettingsConnectionRetryTimers::Timers[8]

8.34 _SLQSAVMSSettingsPeriodsInfo Struct Reference

Data Fields

- ULONG min
- ULONG max

8.34.1 Field Documentation

8.34.1.1 ULONG _SLQSAVMSSettingsPeriodsInfo::max

8.34.1.2 ULONG _SLQSAVMSSettingsPeriodsInfo::min

8.35 _SlqsNas3GppNetworkRAT_ Struct Reference

Data Fields

- WORD MCC
- WORD MNC
- BYTE RAT

8.35.1 Detailed Description

Contain the 3GPP radio access technology information.

Parameters

MCC	• Mobile Country Code
MNC	• Mobile Network Code
RAT	• Radio Access Technology – 0x04 - GERAN – 0x05 - UMTS – 0x08 - LTE – 0x09 - TD-SCDMA

8.35.2 Field Documentation

8.35.2.1 WORD _SlqsNas3GppNetworkRAT_::MCC

8.35.2.2 WORD _SlqsNas3GppNetworkRAT_::MNC

8.35.2.3 BYTE _SlqsNas3GppNetworkRAT_::RAT

8.36 _slqsNetworkScanInfo Struct Reference

Data Fields

- BYTE ∗ pNetworkInfoInstances
- struct SlqsNas3GppNetworkInfo ∗ pNetworkInfo
- BYTE ∗ pRATInstances
- SlqsNas3GppNetworkRAT ∗ pRATInfo
- BYTE ∗ pPCSDigitInstances
- struct SlqsNasPcsDigit ∗ pPCSDigitInfo
- ULONG ∗ pScanResult
- struct SlqsNasPCIInfo ∗ pPCIInfo
- BYTE has_PCIInfo
- lteOpModeTlv ∗ pLteOpModeTlv

8.36.1 Detailed Description

Contain the network scan information.

Parameters

pNetworkInfoInstances[IN/OUT]	• Upon input, maximum number of elements that the network info instance array can contain. • Upon successful output, the actual number of elements in the network info instance array.
pNetworkInfo[OUT]	• Network info instance array – See SlqsNas3GppNetworkInfo for more information

pRATInstances[-IN/OUT]	• Upon input, maximum number of elements that the RAT info instance array can contain. • Upon successful output, the actual number of elements in the RAT info instance array.
pRATInfo[OUT]	• RAT info instance array – See SlqsNas3GppNetworkRAT for more information
pPCSDigit-Instances[IN/O-UT]	• Upon input, maximum number of elements that the PCS Digit info instance array can contain. • Upon successful output, the actual number of elements in the PCS Digit info instance array.
pPCSDigitInfo[-OUT]	• PCS Digit info instance array – See SlqsNasPcsDigit for more information
pScanResult[O-UT]	• status of network scan • 0x00 - scan successful • 0x01 - scan was aborted • 0x02 - scan did not complete due to a radio link failure recovery in progress
pPCIInfo[OUT]	• PCI Information. • See SlqsNasPCIInfo for more information.
has_PCIInfo[-Out]	• PCI Information Availability. – false : Unavailable. – true : Available.
pLteOpMode-Tlv[OUT]	• LTE Operational Mode. • See lteOpModeTlv for more information.

8.36.2 Field Documentation

8.36.2.1 BYTE _slqsNetworkScanInfo::has_PCIInfo

8.36.2.2 lteOpModeTlv* _slqsNetworkScanInfo::pLteOpModeTlv

8.36.2.3 struct SlqsNas3GppNetworkInfo* _slqsNetworkScanInfo::pNetworkInfo

8.36.2.4 BYTE* _slqsNetworkScanInfo::pNetworkInfoInstances

8.36.2.5 struct SlqsNasPCIInfo* _slqsNetworkScanInfo::pPCIInfo

8.36.2.6 struct SlqsNasPcsDigit* _slqsNetworkScanInfo::pPCSDigitInfo

8.36.2.7 BYTE* _slqsNetworkScanInfo::pPCSDigitInstances

8.36.2.8 SIqsNas3GppNetworkRAT* _sIqsNetworkScanInfo::pRATInfo

8.36.2.9 BYTE* _sIqsNetworkScanInfo::pRATInstances

8.36.2.10 ULONG* _sIqsNetworkScanInfo::pScanResult

8.37 _sIqsNetworkScanInfoReq Struct Reference

Data Fields

- BYTE * pNetworkType
- ULONG * pScanType
- ULONGLONG * pCiotOpModePref
- ULONGLONG * pLteM1BandPref
- ULONGLONG * pLteNB1BandPref

8.37.1 Detailed Description

Contain the network scan request information.

Parameters

pNetworkType	• Optional parameter NetworkType. • Bit 0 - GSM • Bit 1 - UMTS • Bit 2 - LTE • Bit 3 - TD-SCDMA
pScanType[IN]	• Optional parameter Scan Type. • 0x00 - PLMN (default) • 0x01 - Closed subscriber group • 0x02 - Mode preference • 0x03 - Physical cell ID
pCiotOpMode-Pref[IN]	• CIOT LTE Operational Mode Preference • Bitmask representing the Cellular Internet of Things (CIoT) LTE operational mode preference. • Values: – Bit 0 (0x01) - QMI_NAS_CIOT_LTE_OP_MODE_PREF_WB - LTE wideband (legacy LTE) – Bit 1 (0x02) - QMI_NAS_CIOT_LTE_OP_MODE_PREF_M1 - LTE M1 – Bit 2 (0x04) - QMI_NAS_CIOT_LTE_OP_MODE_PREF_NB1 - LTE NB1 – All unlisted bits are reserved for future use and the service point ignores them if used.

pLteM1Band-Pref[IN]	• Bitmask representing the LTE M1 band preferencet. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127

pLteNb1Band-Pref[IN]	• Bitmask representing the LTE NB1 band preference. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127

8.37.2 Field Documentation

8.37.2.1 ULONGLONG* _slqsNetworkScanInfoReq::pCiotOpModePref

8.37.2.2 ULONGLONG* _slqsNetworkScanInfoReq::pLteM1BandPref

8.37.2.3 ULONGLONG* _slqsNetworkScanInfoReq::pLteNB1BandPref

8.37.2.4 BYTE* _slqsNetworkScanInfoReq::pNetworkType

8.37.2.5 ULONG* _slqsNetworkScanInfoReq::pScanType

8.38 _SLQSOMADMSessionInfo Struct Reference

Data Fields

- BYTE * pStatus
- WORD * pUpdateCompleteStatus
- BYTE * pSeverity
- WORD * pSourceLength
- BYTE * pSource
- WORD * pPkgNameLength
- BYTE * pPkgName
- WORD * pPkgDescLength
- BYTE * pPkgDescription
- WORD * pDateLength
- BYTE * pDate
- WORD * pTimeLength
- BYTE * pTime
- BYTE * pSessionType
- BYTE * pSessionState
- WORD * pRetryCount

8.38.1 Detailed Description

Structure containing the OMA DM Session Info returned by the device. Also used as input parameter to specify the size of variable parameters. (ref. notes)

Parameters

pStatus	• 1 Byte parameter indicating status(optional) – 0x01 - No Firmware available – 0x02 - Query Firmware Download – 0x03 - Firmware Downloading – 0x04 - Firmware Downloaded – 0x05 - Query Firmware Update – 0x06 - Firmware Updating – 0x07 - Firmware Updated
pUpdate-CompleteStatus	• 2 byte parameter indicating Update Complete Status(optional) – See qaGobiApiTableSwiOMADMUpdateCompleteStatus.h Update Complete Status
pSeverity	• 1 byte parameter indicating severity(optional) – 0x01 - Mandatory – 0x02 - Optional

pSourceLength	• 2 byte parameter indicating Length of Vendor Name String in Bytes.(optional)
pSource	• Variable length parameter indicating Vendor Name in ASCII(optional)
pPkgName-Length	• 2 byte parameter indicating Length of Package Name String in Bytes.(optional)
pPkgName	• Variable length parameter indicating Package Name in ASCII(optional)
pPkgDesc-Length	• 2 byte parameter indicating Length of Package Description String in Bytes.(optional)
pPkgDescription	• Variable length parameter indicating Package Description in ASCII(optional)
pDateLength	• 2 byte parameter indicating Length of Package Description String in Bytes.(optional)
pDate	• Variable length parameter indicating Package Description in ASCII
pTimeLength	• 2 byte parameter indicating Length of Time String in Bytes.(optional)
pTime	• Variable length parameter indicating Time String in ASCII(optional)
pSessionType	• 1 byte parameter reflects the last session started for Sprint(optional) – 0x00 - No session since boot – 0x01 - Sprint CI-DC Session – 0x02 - Sprint CI-PRL Session – 0x03 - Sprint CI-FUMO Session – 0x04 - Sprint HFA-DC Session – 0x05 - Sprint HFA-PRL Session – 0x06 - Sprint HFA-FUMO Session – 0x07 - Sprint NI Session
pSessionState	• 1 byte parameter indicating session state(optional) – 0x01 - idle – 0x02 - active – 0x03 - pending
pRetryCount	• 1 byte parameter indicating retries left count(optional) – valid values 0 to 6

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

As input parameter the members pSourceLength, pPkgNameLength pPkgDescLength, pDateLength, pTimeLength have to be specified. These should contain the initialized size of pSource, pPkgName, pPkgDescription, pDate, pTime respectively.

8.38.2 Field Documentation

8.38.2.1 BYTE* _SLQSOMADMSessionInfo::pDate

8.38.2.2 WORD* _SLQSOMADMSessionInfo::pDateLength

8.38.2.3 WORD* _SLQSOMADMSessionInfo::pPkgDescLength

8.38.2.4 BYTE* _SLQSOMADMSessionInfo::pPkgDescription

8.38.2.5 BYTE* _SLQSOMADMSessionInfo::pPkgName

8.38.2.6 WORD* _SLQSOMADMSessionInfo::pPkgNameLength

8.38.2.7 WORD* _SLQSOMADMSessionInfo::pRetryCount

8.38.2.8 BYTE* _SLQSOMADMSessionInfo::pSessionState

8.38.2.9 BYTE* _SLQSOMADMSessionInfo::pSessionType

8.38.2.10 BYTE* _SLQSOMADMSessionInfo::pSeverity

8.38.2.11 BYTE* _SLQSOMADMSessionInfo::pSource

8.38.2.12 WORD* _SLQSOMADMSessionInfo::pSourceLength

8.38.2.13 BYTE* _SLQSOMADMSessionInfo::pStatus

8.38.2.14 BYTE* _SLQSOMADMSessionInfo::pTime

8.38.2.15 WORD* _SLQSOMADMSessionInfo::pTimeLength

8.38.2.16 WORD* _SLQSOMADMSessionInfo::pUpdateCompleteStatus

8.39 _SLQSOMADMSettings Struct Reference

Data Fields

- ULONG * pOMADMEnabled
- BYTE * pFOTAdownload
- BYTE * pFOTAUpdate
- BYTE * pAutosdm
- BYTE * pFwAutoCheck

8.39.1 Detailed Description

Structure containing the OMA DM settings retrieved from the device

Parameters

pOMADM-Enabled[OUT]	• 4 byte parameter indicating OMADM service enabled – 0x00000001 - Client-initiated device configuration – 0x00000002 - Network-initiated device configuration – 0x00000010 - Client-initiated FUMO – 0x00000020 - Network-initiated FUMO • function SLQSOMADMGetSettings2() returns a default value 0xFFFFFFFF in case this parameter is not returned by the modem.
pFOT-Adownload[OUT]	• 1 Byte parameter indicating support for FOTA Automatic download – 0x00 - Host permission required before downloading – 0x01 - Automatically start downloading, no host permission required – 0x02 - Automatically start downloading, while not roaming – 0x03 - Automatically reject download – 0x04 - Automatically reject download with “Enterprise Reject Policy” • function SLQSOMADMGetSettings2() returns a default value 0xFF in case this parameter is not returned by the modem.
pFOTAUpdate[-OUT]	• 1 byte parameter indicating FOTA Automatic update – 0x00 - User permission required before updating firmware – 0x01 - No user permission required before updating firmware – 0x02 - User permission required, auto update on power up • function SLQSOMADMGetSettings2() returns a default value 0xFF in case this parameter is not returned by the modem.
pAutosdm[OUT]	• 1 byte parameter indicating OMA Automatic UI Alert Response – 0x00 - Disabled – 0x01 - Enabled Accept – 0x02 - Enabled Reject • function SLQSOMADMGetSettings2() returns a default value 0xFF in case this parameter is not returned by the modem.
pFwAutoCheck[-OUT]	• Optional 1 byte parameter indicating OMA Automatic Check for Firmware Update on Power-Up Response – 0x00 - Disabled – 0x01 - Enabled • function SLQSOMADMGetSettings2() returns a default value 0xFF in case this parameter is not returned by the modem.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

8.39.2 Field Documentation

8.39.2.1 BYTE* _SLQSOMADMSettings::pAutosdm

8.39.2.2 BYTE* _SLQSOMADMSettings::pFOTAdownload

8.39.2.3 BYTE* _SLQSOMADMSettings::pFOTAUpdate

8.39.2.4 BYTE* _SLQSOMADMSettings::pFwAutoCheck

8.39.2.5 ULONG* _SLQSOMADMSettings::pOMADMEnabled

8.40 _SLQSOMADMSettingsReqParams Struct Reference

Data Fields

- BYTE FOTAdownload
- BYTE FOTAUpdate
- BYTE * pAutosdm

8.40.1 Detailed Description

Structure containing the OMA DM settings to be set on the device

Parameters

FOTAdownload	• 1 Byte parameter indicating support for FOTA Automatic download – 0x00 - Firmware auto download FALSE – 0x01 - Firmware auto download TRUE
FOTAUpdate	• 1 byte parameter indicating FOTA Automatic update – 0x00 - Firmware auto update FALSE – 0x01 - Firmware auto update TRUE
pAutosdm[IN]	• Optional 1 byte parameter indicating OMA Automatic UI Alert Response – 0x00 - Disabled – 0x01 - Enabled Accept – 0x02 - Enabled Reject

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

8.40.2 Field Documentation

8.40.2.1 BYTE _SLQSOMADMSettingsReqParams::FOTAdownload

8.40.2.2 BYTE _SLQSOMADMSettingsReqParams::FOTAUpdate

8.40.2.3 BYTE* _SLQSOMADMSettingsReqParams::pAutosdm

8.41 _SLQSOMADMSettingsReqParams3 Struct Reference

Data Fields

- BYTE FOTAdownload
- BYTE FOTAUpdate
- BYTE * pAutosdm
- BYTE * pFwAutoCheck

8.41.1 Detailed Description

Structure containing the OMA DM settings to be set on the device

Parameters

FOTAdownload	• 1 Byte parameter indicating support for FOTA Automatic download – 0x00 - Firmware auto download FALSE – 0x01 - Firmware auto download TRUE
FOTAUpdate	• 1 byte parameter indicating FOTA Automatic update – 0x00 - Firmware auto update FALSE – 0x01 - Firmware auto update TRUE
pAutosdm[IN]	• Optional 1 byte parameter indicating OMA Automatic UI Alert Response – 0x00 - Disabled – 0x01 - Enabled Accept – 0x02 - Enabled Reject
pFwAutoCheck[IN]	• Optional 1 byte parameter indicating OMA Automatic Check for Firmware Update on Power-Up Response – 0x00 - Disabled – 0x01 - Enabled

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

8.41.2 Field Documentation

8.41.2.1 BYTE _SLQSOMADMSettingsReqParams3::FOTAdownload

8.41.2.2 BYTE _SLQSOMADMSettingsReqParams3::FOTAUpdate

8.41.2.3 BYTE* _SLQSOMADMSettingsReqParams3::pAutosdm

8.41.2.4 BYTE* _SLQSOMADMSettingsReqParams3::pFwAutoCheck

8.42 _SLQSSwiGetHostDevInfoParams Struct Reference

Data Fields

- BYTE bManSize
- CHAR * pManString
- BYTE bModelSize
- CHAR * pModelString
- BYTE bSWVerSize
- CHAR * pSWVerString
- BYTE bPlasmaIDSize
- CHAR * pPlasmaIDString
- BYTE bHostIDSize
- CHAR * pHostID

8.42.1 Detailed Description

This structure is used to Get Host Device Information

Parameters

bManSize[IN/OUT]	• Host Device Manufacturer String Size
pManString[OUT]	• Host Device Manufacturer Name(Optional parameter) • Null terminated ASCII String
bModelSize[IN/OUT]	• Host Device Model String Size
pModelString[OUT]	• Host Device Model String(Optional parameter) • Null terminated ASCII string.
bSWVerSize[IN/OUT]	• Host Device Software Version String Size
pSWVerString[OUT]	• Host Device Software Version String(Optional parameter) • Null terminated ASCII string
bPlasmaIDSize[IN/OUT]	• Host Device Plasma ID String Size

pPlasmaID-String[OUT]	• Host Device Plasma ID String(Optional parameter) • Null terminated alphanumeric ASCII String.

8.42.2 Field Documentation

8.42.2.1 BYTE _SLQSSwiGetHostDevInfoParams::bHostIDSize

8.42.2.2 BYTE _SLQSSwiGetHostDevInfoParams::bManSize

8.42.2.3 BYTE _SLQSSwiGetHostDevInfoParams::bModelSize

8.42.2.4 BYTE _SLQSSwiGetHostDevInfoParams::bPlasmaIDSize

8.42.2.5 BYTE _SLQSSwiGetHostDevInfoParams::bSWVerSize

8.42.2.6 CHAR* _SLQSSwiGetHostDevInfoParams::pHostID

8.42.2.7 CHAR* _SLQSSwiGetHostDevInfoParams::pManString

8.42.2.8 CHAR* _SLQSSwiGetHostDevInfoParams::pModelString

8.42.2.9 CHAR* _SLQSSwiGetHostDevInfoParams::pPlasmaIDString

8.42.2.10 CHAR* _SLQSSwiGetHostDevInfoParams::pSWVerString

8.43 _SLQSSwiGetOSInfoParams Struct Reference

Data Fields

- BYTE bNameSize
- CHAR * pNameString
- BYTE bVersionSize
- CHAR * pVersionString

8.43.1 Detailed Description

This structure is used to Get OS Information

Parameters

bNameSize[IN/-OUT]	• Size of Operating System Name
pNameString[O-UT]	• Operating System Name(Optional parameter) • Null terminated ASCII string
bVersionSize[I-N/OUT]	• Operating System Version Size

pVersionString[-OUT]	• Operating System Version String(Optional parameter) • Null terminated ASCII string.

8.43.2 Field Documentation

8.43.2.1 BYTE _SLQSSwiGetOSInfoParams::bNameSize

8.43.2.2 BYTE _SLQSSwiGetOSInfoParams::bVersionSize

8.43.2.3 CHAR* _SLQSSwiGetOSInfoParams::pNameString

8.43.2.4 CHAR* _SLQSSwiGetOSInfoParams::pVersionString

8.44 _SLQSSwiGetSerialNoExtParams Struct Reference

Data Fields

- BYTE meidLength
- CHAR * pMeidString

8.44.1 Detailed Description

This structure is used to store MEID Information

Parameters

meidLength[OUT]	• String length of the of MEID received
pMeidString[OUT]	• Optional parameter • Pointer to receive String containing the Mobile Equipment Identifier(MEID) of the device.

8.44.2 Field Documentation

8.44.2.1 BYTE _SLQSSwiGetSerialNoExtParams::meidLength

8.44.2.2 CHAR* _SLQSSwiGetSerialNoExtParams::pMeidString

8.45 _SLQSSwiSetHostDevInfoParams Struct Reference

Data Fields

- BYTE bManSize
- CHAR * pManString
- BYTE bModelSize
- CHAR * pModelString
- BYTE bSWVerSize

- CHAR * pSWVerString
- BYTE bPlasmaIDSize
- CHAR * pPlasmaIDString
- BYTE bHostIDSize
- CHAR * pHostID

8.45.1 Detailed Description

This structure is used to Set Host Device Information

Parameters

bManSize[IN]	• Host Device Manufacturer String Size
pManString[IN]	• Host Device Manufacturer Name(Optional parameter) • Null terminated ASCII String
bModelSize[IN]	• Host Device Model String Size
pModelString[IN]	• Host Device Model String(Optional parameter) • Null terminated ASCII string.
bSWVerSize[IN]	• Host Device Software Version String Size
pSWVerString[IN]	• Host Device Software Version String(Optional parameter) • Null terminated ASCII string
bPlasmaIDSize[IN]	• Host Device Plasma ID String Size
pPlasmaIDString[IN]	• Host Device Plasma ID String(Optional parameter) • Null terminated alphanumeric ASCII String.

8.45.2 Field Documentation

8.45.2.1 BYTE _SLQSSwiSetHostDevInfoParams::bHostIDSize

8.45.2.2 BYTE _SLQSSwiSetHostDevInfoParams::bManSize

8.45.2.3 BYTE _SLQSSwiSetHostDevInfoParams::bModelSize

8.45.2.4 BYTE _SLQSSwiSetHostDevInfoParams::bPlasmaIDSize

8.45.2.5 BYTE _SLQSSwiSetHostDevInfoParams::bSWVerSize

8.45.2.6 CHAR* _SLQSSwiSetHostDevInfoParams::pHostID

8.45.2.7 CHAR* _SLQSSwiSetHostDevInfoParams::pManString

8.45.2.8 CHAR* _SLQSSwiSetHostDevInfoParams::pModelString

8.45.2.9 CHAR* _SLQSSwiSetHostDevInfoParams::pPlasmaIDString

8.45.2.10 CHAR* _SLQSSwiSetHostDevInfoParams::pSWVerString

8.46 _SLQSSwiSetOSInfoParams Struct Reference

Data Fields

- BYTE bNameSize
- CHAR * pNameString
- BYTE bVersionSize
- CHAR * pVersionString

8.46.1 Detailed Description

This structure is used to Set OS Information

Parameters

bNameSize[IN]	• Size of Operating System Name
pNameString[IN]	• Operating System Name(Optional parameter) • Null terminated ASCII string
bVersionSize[IN]	• Operating System Version Size
pVersionString[IN]	• Operating System Version String(Optional parameter) • Null terminated ASCII string.

8.46.2 Field Documentation

8.46.2.1 BYTE _SLQSSwiSetOSInfoParams::bNameSize

8.46.2.2 BYTE _SLQSSwiSetOSInfoParams::bVersionSize

8.46.2.3 CHAR* _SLQSSwiSetOSInfoParams::pNameString

8.46.2.4 CHAR* _SLQSSwiSetOSInfoParams::pVersionString

8.47 _SwiAvmsEventInd Struct Reference

Data Fields

- QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp BinaryUpdateSessionInfo
- QmiSwiAvmsEventReportConfigResp Config
- QmiSwiAvmsEventReportNotificationResp Notification
- QmiSwiAvmsEventReportConnectionRequestResp ConnectionRequest
- QmiSwiAvmsEventReportWAMSParamChangeResp WAMSParaChanged
- QmiSwiAvmsEventReportPackageIDResp PackageID
- QmiSwiAvmsEventReportDataSessionStatusResp DataSessionStatus
- QmiSwiAvmsEventReportSessionTypeResp SessionType
- QmiSwiAvmsEventReportHTTPStatusResp HTTPStatus
- QmiSwiAvmsEventReportRegStatusResp RegStatus

8.47.1 Field Documentation

8.47.1.1 QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp _SwiAvmsEventInd::BinaryUpdateSessionInfo

8.47.1.2 QmiSwiAvmsEventReportConfigResp _SwiAvmsEventInd::Config

8.47.1.3 QmiSwiAvmsEventReportConnectionRequestResp _SwiAvmsEventInd::ConnectionRequest

8.47.1.4 QmiSwiAvmsEventReportDataSessionStatusResp _SwiAvmsEventInd::DataSessionStatus

8.47.1.5 QmiSwiAvmsEventReportHTTPStatusResp _SwiAvmsEventInd::HTTPStatus

8.47.1.6 QmiSwiAvmsEventReportNotificationResp _SwiAvmsEventInd::Notification

8.47.1.7 QmiSwiAvmsEventReportPackageIDResp _SwiAvmsEventInd::PackageID

8.47.1.8 QmiSwiAvmsEventReportRegStatusResp _SwiAvmsEventInd::RegStatus

8.47.1.9 QmiSwiAvmsEventReportSessionTypeResp _SwiAvmsEventInd::SessionType

8.47.1.10 QmiSwiAvmsEventReportWAMSParamChangeResp _SwiAvmsEventInd::WAMSParaChanged

8.48 _sysSelectPrefExtInfo Struct Reference

Data Fields

- sysSelectPrefInfo * pSysSelectPrefInfo
- AcqOrderPrefTlv * pAcqOrderPref
- RatDisabledMaskTlv * pRatDisabledMask
- CiotLteOpModePrefTlv * pCiotLteOpModePref
- LteM1BandPrefTlv * pLteM1BandPref
- LteNb1BandPrefTlv * pLteNb1BandPref
- CiotAcqOrderPrefTlv * pCiotAcqOrderPref
- NR5gBandPrefTlv * pNr5gBandPref
- LTEBandPrefExtTlv * pLTEBandPrefExt

8.48.1 Detailed Description

Structure for storing the current preferred system selection settings for the device.

Parameters

pSysSelectPrefInfo	• See sysSelectPrefInfo for more information
pAcqOrderPref	• Optional parameter • Acquisition Order Preference • See AcqOrderPrefTlv for more information
pRatDisabledMask	• Optional parameter • See RatDisabledMaskTlv for more information
pCiotLteOpModePref	• Optional parameter • See CiotLteOpModePrefTlv for more information
pLteM1BandPref	• Optional parameter • See LteM1BandPrefTlv for more information
pLteNb1BandPref	• Optional parameter • See LteNb1BandPrefTlv for more information
pCiotAcqOrderPref	• Optional parameter indicating CIOT Acquisition Order Preference • See CiotAcqOrderPrefTlv for more information
pNr5gBandPref	• Optional parameter indicating NR5G Band Preference • See NR5gBandPrefTlv for more information
pLTEBandPrefExt	• Optional parameter indicating LTE Band Preference Extended • See LTEBandPrefExtTlv for more information

Note

None

8.48.2 Field Documentation

8.48.2.1 AcqOrderPrefTlv* _sysSelectPrefExtInfo::pAcqOrderPref

8.48.2.2 CiotAcqOrderPrefTlv* _sysSelectPrefExtInfo::pCiotAcqOrderPref

8.48.2.3 CiotLteOpModePrefTlv* _sysSelectPrefExtInfo::pCiotLteOpModePref

8.48.2.4 LTEBandPrefExtTlv* _sysSelectPrefExtInfo::pLTEBandPrefExt

8.48.2.5 LteM1BandPrefTlv* _sysSelectPrefExtInfo::pLteM1BandPref

8.48.2.6 LteNb1BandPrefTlv∗ _sysSelectPrefExtInfo::pLteNb1BandPref

8.48.2.7 NR5gBandPrefTlv∗ _sysSelectPrefExtInfo::pNr5gBandPref

8.48.2.8 RatDisabledMaskTlv∗ _sysSelectPrefExtInfo::pRatDisabledMask

8.48.2.9 sysSelectPrefInfo∗ _sysSelectPrefExtInfo::pSysSelectPrefInfo

8.49 _sysSelectPrefInfo Struct Reference

Data Fields

- BYTE ∗ pEmerMode
- WORD ∗ pModePref
- ULONGLONG ∗ pBandPref
- WORD ∗ pPRLPref
- WORD ∗ pRoamPref
- ULONGLONG ∗ pLTEBandPref
- BYTE ∗ pNetSelPref
- ULONG ∗ pSrvDomainPref
- ULONG ∗ pGWAcqOrderPref

8.49.1 Detailed Description

Structure for storing the current preferred system selection settings for the device.

Parameters

pEmerMode	• Optional parameter specifying the emergency Mode • Values: – 0 - OFF (normal) – 1 - ON (Emergency) • function SLQSGetSysSelectionPref() returns a default value FF if no value is returned by the device.
pModePref	• Optional parameter • Bit Mask indicating the radio technology mode preference • Bit values: – Bit 0 - cdma2000 1x – Bit 1 - cdma2000 HRPD(1xEV-DO) – Bit 2 - GSM – Bit 3 - UMTS – Bit 4 - LTE – Bit 5 - TD-SCDMA – Bit 6 - NR5G • function SLQSGetSysSelectionPref() returns a default value FF if no value is returned by the device.

pBandPref	• Optional parameter • Bit mask representing the band preference • Bit values: – Bit 0 - Band Class 0, A-System – Bit 1 - Band Class 0, B-System, Band Class 0 AB, GSM 850 Band – Bit 2 - Band Class 1, all blocks – Bit 3 - Band Class 2 place holder – Bit 4 - Band Class 3, A-System – Bit 5 - Band Class 4, all blocks – Bit 6 - Band Class 5, all blocks – Bit 7 - GSM_DCS_1800 band – Bit 8 - GSM Extended GSM (E-GSM) 900 band – Bit 9 - GSM Primary GSM (P-GSM) 900 band – Bit 10 - Band Class 6 – Bit 11 - Band Class 7 – Bit 12 - Band Class 8 – Bit 13 - Band Class 9 – Bit 14 - Band Class 10 – Bit 15 - Band Class 11 – Bit 16 - GSM 450 band – Bit 17 - GSM 480 band – Bit 18 - GSM 750 band – Bit 19 - GSM 850 band – Bit 20 - GSM Railways GSM 900 Band – Bit 21 - GSM PCS 1900 band – Bit 22 - WCDMA Europe, Japan, and China IMT 2100 band – Bit 23 - WCDMA U.S. PCS 1900 band – Bit 24 - WCDMA Europe and China DCS 1800 band – Bit 25 - WCDMA U.S. 1700 band – Bit 26 - WCDMA U.S. 850 band – Bit 27 - WCDMA Japan 800 band – Bit 28 - Band Class 12 – Bit 29 - Band Class 14 – Bit 30 - Reserved – Bit 31 - Band Class 15 – Bit 32 to 47 - Reserved – Bit 48 - WCDMA Europe 2600 band – Bit 49 - WCDMA Europe and Japan 900 band – Bit 50 - WCDMA Japan 1700 band – Bit 51 to 55 - Reserved – Bit 56 - Band Class 16 – Bit 57 - Band Class 17 – Bit 58 - Band Class 18 – Bit 59 - Band Class 19 – Bit 60 to 64 - Reserved • function SLQSGetSysSelectionPref() returns a default value FFFFFFFFFFFFFFFF if no value is returned by the device.

pPRLPref	• Optional parameter indicating the CDMA PRL Preference • Values: – 0x0001 - Acquire available system only on the A side – 0x0002 - Acquire available system only on the B side – 0x3FFF - Acquire any available systems • function SLQSGetSysSelectionPref() returns a default value FFFF if no value is returned by the device.
pRoamPref	• Optional parameter indicating the roaming Preference • Values: – 0x01 - Acquire only systems for which the roaming indicator is off – 0x02 - Acquire a system as long as its roaming indicator is not off – 0x03 - Acquire only systems for which the roaming indicator is off or solid on, i.e. not flashing; CDMA only – 0xFF - Acquire systems, regardless of their roaming indicator • function SLQSGetSysSelectionPref() returns a default value FFFF if no value is returned by the device.

pLTEBandPref	• Optional parameter • Bit mask representing the LTE band preference • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – All other bits are reserved • function SLQSGetSysSelectionPref() returns a default value FFFFFFFFFFFFFFFF if no value is returned by the device.

pNetSelPref	• Optional parameter indicating network selection preference • Values: – 0x00 - Automatic network selection – 0x01 - Manual network selection • function SLQSGetSysSelectionPref() returns a default value FF if no value is returned by the device.
pSrvDomainPref	• Optional parameter indicating Service domain preference • Values: – 0x00 - Circuit switched only – 0x01 - Packet switched only – 0x02 - Circuit switched and packet switched – 0x03 - Packet switched attach – 0x04 - Packet switched detach • function SLQSGetSysSelectionPref() returns a default value FFFFFFFF if no value is returned by the device.
pGWAcqOrder-Pref	• Optional parameter indicating GSM/WCDMA Acquisition order Preference • Values: – 0x00 - Automatic – 0x01 - GSM then WCDMA – 0x02 - WCDMA then GSM • function SLQSGetSysSelectionPref() returns a default value FFFFFFFF if no value is returned by the device.

Note

None

8.49.2 Field Documentation

8.49.2.1 ULONGLONG* _sysSelectPrefInfo::pBandPref

8.49.2.2 BYTE* _sysSelectPrefInfo::pEmerMode

8.49.2.3 ULONG* _sysSelectPrefInfo::pGWAcqOrderPref

8.49.2.4 ULONGLONG* _sysSelectPrefInfo::pLTEBandPref

8.49.2.5 WORD* _sysSelectPrefInfo::pModePref

8.49.2.6 BYTE* _sysSelectPrefInfo::pNetSelPref

8.49.2.7 WORD* _sysSelectPrefInfo::pPRLPref

8.49.2.8 WORD* _sysSelectPrefInfo::pRoamPref

8.49.2.9 ULONG* _sysSelectPrefInfo::pSrvDomainPref

8.50 _sysSelectPrefParams Struct Reference

Data Fields

- BYTE * pEmerMode
- WORD * pModePref
- ULONGLONG * pBandPref
- WORD * pPRLPref
- WORD * pRoamPref
- ULONGLONG * pLTEBandPref
- struct netSelectionPref * pNetSelPref
- BYTE * pChgDuration
- BYTE * pMNCIncPCSDigStat
- ULONG * pSrvDomainPref
- ULONG * pGWAcqOrderPref
- ULONGLONG * pTdscdmaBandPref
- struct acqOrderPref * pAcqOrderPref
- ULONG * pSrvRegRestriction
- struct CSGID * pCSGID
- BYTE * pRAT

8.50.1 Detailed Description

Contain the system selection preferences.

Parameters

pEmerMode	• Optional parameter specifying the emergency Mode • Values: – 0 - OFF (normal) – 1 - ON (Emergency)
pModePref	• Optional parameter • Bit Mask indicating the radio technology mode preference • Bit values: – Bit 0 - cdma2000 1x – Bit 1 - cdma2000 HRPD(1xEV-DO) – Bit 2 - GSM – Bit 3 - UMTS – Bit 4 - LTE – Bit 5 - TD-SCDMA – Bit 6 - NR5G

pBandPref	• Optional parameter • Bit mask representing the band preference • Bit values: – Bit 0 - Band Class 0, A-System – Bit 1 - Band Class 0, B-System, Band Class 0 AB, GSM 850 Band – Bit 2 - Band Class 1, all blocks – Bit 3 - Band Class 2 place holder – Bit 4 - Band Class 3, A-System – Bit 5 - Band Class 4, all blocks – Bit 6 - Band Class 5, all blocks – Bit 7 - GSM_DCS_1800 band – Bit 8 - GSM Extended GSM (E-GSM) 900 band – Bit 9 - GSM Primary GSM (P-GSM) 900 band – Bit 10 - Band Class 6 – Bit 11 - Band Class 7 – Bit 12 - Band Class 8 – Bit 13 - Band Class 9 – Bit 14 - Band Class 10 – Bit 15 - Band Class 11 – Bit 16 - GSM 450 band – Bit 17 - GSM 480 band – Bit 18 - GSM 750 band – Bit 19 - GSM 850 band – Bit 20 - GSM Railways GSM 900 Band – Bit 21 - GSM PCS 1900 band – Bit 22 - WCDMA Europe, Japan, and China IMT 2100 band – Bit 23 - WCDMA U.S. PCS 1900 band – Bit 24 - WCDMA Europe and China DCS 1800 band – Bit 25 - WCDMA U.S. 1700 band – Bit 26 - WCDMA U.S. 850 band – Bit 27 - WCDMA Japan 800 band – Bit 28 - Band Class 12 – Bit 29 - Band Class 14 – Bit 30 - Reserved – Bit 31 - Band Class 15 – Bit 32 to 47 - Reserved – Bit 48 - WCDMA Europe 2600 band – Bit 49 - WCDMA Europe and Japan 900 band – Bit 50 - WCDMA Japan 1700 band – Bit 51 to 55 - Reserved – Bit 56 - Band Class 16 – Bit 57 - Band Class 17 – Bit 58 - Band Class 18 – Bit 59 - Band Class 19 – Bit 60 to 64 - Reserved

pPRLPref	• Optional parameter indicating the CDMA PRL Preference • Values: – 0x0001 - Acquire available system only on the A side – 0x0002 - Acquire available system only on the B side – 0x3FFF - Acquire any available systems
pRoamPref	• Optional parameter indicating the roaming Preference • Values: – 0x01 - Acquire only systems for which the roaming indicator is off – 0x02 - Acquire a system as long as its roaming indicator is not off – 0x03 - Acquire only systems for which the roaming indicator is off or solid on, i.e. not flashing; CDMA only – 0xFF - Acquire systems, regardless of their roaming indicator

pLTEBandPref	• Optional parameter • Bit mask representing the LTE band preference • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – All other bits are reserved

pNetSelPref	- netSelectionPref • Optional parameter for specifying Network Selection Preference • Modem selects networks based on this parameter(if present). • Either of pNetSelPref or pCSGID can be set. • see netSelectionPref for more information
pChgDuration	• Optional parameter specifying the duration of the change • At least one system selection setting to be set if pChgDuration is populated. • Values: – 0x00 - Power cycle - Remains active until the next device power cycle – 0x01 - Permanent - Remains active through power cycles until changed by client – Device will use "0x01 - permanent" as default if this parameter is omitted
pMNCIncPCS-DigStat	• Optional parameter indicating if MNC includes PCS digit • pNetSelPref is expected if MNC includes PCS digit is set to 1. • Values: – TRUE - MNC is a 3 digit value; e.g., a reported value of 90 corresponds to an MNC value of 090 – FALSE - MNC is a 2-digit value; e.g., a reported value of 90 corresponds to an MNC value of 90
pSrvDomainPref	• Optional parameter indicating Service domain preference • Values: – 0x00 - Circuit switched only – 0x01 - Packet switched only – 0x02 - Circuit switched and packet switched – 0x03 - Packet switched attach – 0x04 - Packet switched detach
pGWAcqOrder-Pref	• Optional parameter indicating GSM/WCDMA Acquisition order Preference • Values: – 0x00 - Automatic – 0x01 - GSM then WCDMA – 0x02 - WCDMA then GSM
pTdscdmaBand-Pref	• Optional parameter indicating bitmask representing the TD-SCDMA band preference to be set. • Values: – 0x01 - TD-SCDMA Band A – 0x02 - TD-SCDMA Band B – 0x04 - TD-SCDMA Band C – 0x08 - TD-SCDMA Band D – 0x10 - TD-SCDMA Band E – 0x20 - TD-SCDMA Band F – All other bits are reserved

pAcqOrderPref	- acqOrderPref • Optional parameter for specifying Acquisition Order Preference • see acqOrderPref for more information
pSrvReg-Restriction	• Optional parameter indicating Network Selection Registration Restriction Preference • Values: – 0x00 - Device follows the normal registration process – 0x01 - Device camps on the network according to its provisioning, but does not register – 0x02 - Device selects the network for limited service – All other values are reserved.
pCSGID	- CSGID • Optional parameter for specifying CSG ID • Either of pNetSelPref or pCSGID can be set. • see CSGID for more information
pRAT	• Optional parameter Radio Access Technology order Preference • Values: – 0x04 - GSM – 0x05 - UMTS – 0x08 - LTE – 0x09 - TDSCDMA – 0x0A - LTE-M1 – 0x0B - LTE-NB1 – 0x0C - NR5G

8.50.2 Field Documentation

8.50.2.1 struct acqOrderPref* _sysSelectPrefParams::pAcqOrderPref

8.50.2.2 ULONGLONG* _sysSelectPrefParams::pBandPref

8.50.2.3 BYTE* _sysSelectPrefParams::pChgDuration

8.50.2.4 struct CSGID* _sysSelectPrefParams::pCSGID

8.50.2.5 BYTE* _sysSelectPrefParams::pEmerMode

8.50.2.6 ULONG* _sysSelectPrefParams::pGWAcqOrderPref

8.50.2.7 ULONGLONG* _sysSelectPrefParams::pLTEBandPref

8.50.2.8 BYTE* _sysSelectPrefParams::pMNCIncPCSDigStat

8.50.2.9 WORD* _sysSelectPrefParams::pModePref

8.50.2.10 struct netSelectionPref* _sysSelectPrefParams::pNetSelPref

8.50.2.11 WORD* _sysSelectPrefParams::pPRLPref

8.50.2.12 BYTE* _sysSelectPrefParams::pRAT

8.50.2.13 WORD* _sysSelectPrefParams::pRoamPref

8.50.2.14 ULONG* _sysSelectPrefParams::pSrvDomainPref

8.50.2.15 ULONG* _sysSelectPrefParams::pSrvRegRestriction

8.50.2.16 ULONGLONG* _sysSelectPrefParams::pTdscdmaBandPref

8.51 _transLayerinfo Struct Reference

Data Fields

- BYTE TransType
- BYTE TransCap

8.51.1 Detailed Description

This structure contains Transport Layer Information

Parameters

TransType	• Transport Type – 0x00 - IMS
TransCap	• Transport Capability • Values: – 0x00 - CDMA – 0x01 - GW

8.51.2 Field Documentation

8.51.2.1 BYTE _transLayerinfo::TransCap

8.51.2.2 BYTE _transLayerinfo::TransType

8.52 _transLayerInfoNotification Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE regInd
- transLayerInfo * pTransLayerInfo

8.52.1 Detailed Description

Contains the parameters passed for SLQSSetTransLayerInfoCallback by the device.

Parameters

regInd	• Indicates whether the transport layer is registered or not • Values: – 0x00 - Transport layer is not registered – 0x01 - Transport layer is registered
pTransLayerInfo	• Optional parameter • See transLayerInfo for more information

Note

None

8.52.2 Field Documentation

8.52.2.1 transLayerInfo* _transLayerInfoNotification::pTransLayerInfo

8.52.2.2 BYTE _transLayerInfoNotification::regInd

8.52.2.3 struct qmTlvResult _transLayerInfoNotification::results

8.53 _transNWRegInfoNotification Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE NWRegStat

8.53.1 Detailed Description

Contains the parameters passed for SLQSSetTransNWRegInfoCallback by the device.

Parameters

NWRegStat	• provides the transport network registration information • Values: – 0x00 - No Service – 0x01 - In Progress – 0x02 - Failed – 0x03 - Limited Service – 0x04 - Full Service

Note

None

8.53.2 Field Documentation

8.53.2.1 BYTE _transNWRegInfoNotification::NWRegStat

8.53.2.2 struct qmTlvResult _transNWRegInfoNotification::results

8.54 accelAcceptReady_s Struct Reference

Data Fields

- BYTE injectEnable
- WORD samplesPerBatch
- WORD batchPerSec

8.54.1 Detailed Description

This structure contains Accelerometer Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPerBatch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

8.54.2 Field Documentation

8.54.2.1 WORD accelAcceptReady_s::batchPerSec

8.54.2.2 BYTE accelAcceptReady_s::injectEnable

8.54.2.3 WORD accelAcceptReady_s::samplesPerBatch

8.55 accelTempAcceptReady_s Struct Reference

Data Fields

- BYTE injectEnable
- WORD samplesPerBatch
- WORD batchPerSec

8.55.1 Detailed Description

This structure contains Accelerometer Temperature Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

8.55.2 Field Documentation

8.55.2.1 WORD accelTempAcceptReady_s::batchPerSec

8.55.2.2 BYTE accelTempAcceptReady_s::injectEnable

8.55.2.3 WORD accelTempAcceptReady_s::samplesPerBatch

8.56 acqOrderPref Struct Reference

Data Fields

- BYTE acqOrdeLen
- BYTE ∗ pAcqOrder

8.56.1 Detailed Description

Contain the Acquisition Order Preference.

Parameters

acqOrdeLen	• Number of sets of the following elements.

pAcqOrder	• Acquisition order preference to be set. Values: – 0x01 - NAS_RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE – 0x09 - NAS_RADIO_IF_TDSCDMA - TD-SCDMA – 0x0C - NAS_RADIO_IF_NR5G - NR5G

8.56.2 Field Documentation

8.56.2.1 BYTE acqOrderPref::acqOrdeLen

8.56.2.2 BYTE* acqOrderPref::pAcqOrder

8.57 AcqOrderPrefTlv Struct Reference

Data Fields

- BYTE acqOrdeLen
- BYTE * pAcqOrder
- BYTE TlvPresent

8.57.1 Detailed Description

Contain the Acquisition Order Preference.

Parameters

acqOrdeLen	• Number of sets of the following elements.
pAcqOrder	• Acquisition order preference to be set. Values: – 0x01 - NAS_RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE – 0x09 - NAS_RADIO_IF_TDSCDMA - TD-SCDMA – 0x0C - NAS_RADIO_IF_NR5G - NR5G
TlvPresent	• Tlv Present

8.57.2 Field Documentation

8.57.2.1 BYTE AcqOrderPrefTlv::acqOrdeLen

8.57.2.2 BYTE* AcqOrderPrefTlv::pAcqOrder

8.57.2.3 BYTE AcqOrderPrefTlv::TlvPresent

8.58 ActPilotPNElement Struct Reference

Data Fields

- WORD ActSetPilotPN
- BYTE ActSetPilotPNStrength

8.58.1 Detailed Description

This structure describes Active Pilot PN elements

Parameters

ActSetPilotPN	• Active Pilot PN
ActSetPilotPN-Strength	• Active Pilot PN strength

8.58.2 Field Documentation

8.58.2.1 WORD ActPilotPNElement::ActSetPilotPN

8.58.2.2 BYTE ActPilotPNElement::ActSetPilotPNStrength

8.59 AddCDMASysInfo Struct Reference

Data Fields

- WORD geoSysIdx
- WORD regPrd

8.59.1 Detailed Description

Structure for storing the Additional CDMA System Information.

Parameters

geoSysIdx	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used.
regPrd	• Registration period after the CDMA system is acquired. • When the CDMA registration period is not valid, 0xFFFF is used.

8.59.2 Field Documentation

8.59.2.1 WORD AddCDMASysInfo::geoSysIdx

8.59.2.2 WORD AddCDMASysInfo::regPrd

8.60 AddSysInfo Struct Reference

Data Fields

- WORD geoSysIdx
- ULONG cellBroadcastCap

8.60.1 Detailed Description

Structure for storing the Additional GSM and WCDMA System Information.

Parameters

geoSysIdx	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used.
cellBroadcast-Cap	• Cell broadcast capability of the serving system. • When the CDMA registration period is not valid, 0xFFFF is used. – NAS_CELL_BROADCAST_CAP_UNKNOWN - Cell broadcast support is unknown – NAS_CELL_BROADCAST_CAP_OFF - Cell broadcast is not supported – NAS_CELL_BROADCAST_CAP_ON - Cell broadcast is supported

8.60.2 Field Documentation

8.60.2.1 ULONG AddSysInfo::cellBroadcastCap

8.60.2.2 WORD AddSysInfo::geoSysIdx

8.61 airTimer Struct Reference

Data Fields

- BYTE namID
- ULONG airTimerValue

8.61.1 Detailed Description

This structure contains information about the Air Timer.

Parameters

namID	• Index of the NAM(Number Assignment Module) to be configured. • Range 0 to 3. • Some modems support only 1 or 2 NAMs. • 0xFF,if not available.
airTimerValue	• Time in minutes. • Cumulative air time is slammed. • 0xFFFFFFFF,if not available.

8.61.2 Field Documentation

8.61.2.1 ULONG airTimer::airTimerValue

8.61.2.2 BYTE airTimer::namID

8.62 allCallsAlphaIDInfo Struct Reference

Data Fields

- BYTE callID
- alphaIDInfo AlphaIDInfo

8.62.1 Detailed Description

This structure contains information for Alpha Identifier for All Calls

Parameters

callID	• Unique call identifier for the call.
AlphaIDInfo	• See alphaIDInfo for more information.

8.62.2 Field Documentation

8.62.2.1 alphaIDInfo allCallsAlphaIDInfo::AlphaIDInfo

8.62.2.2 BYTE allCallsAlphaIDInfo::callID

8.63 allCallsDiagInfo Struct Reference

Data Fields

- BYTE callID
- diagInfo DiagInfo

8.63.1 Detailed Description

This structure contains Diagnostic Information for All Calls

Parameters

callID	• Unique call identifier for the call.
DiagInfo	• See diagInfo for more information.

8.63.2 Field Documentation

8.63.2.1 BYTE allCallsDiagInfo::callID

8.63.2.2 diagInfo allCallsDiagInfo::DiagInfo

8.64 allCallsUUSInfo Struct Reference

Data Fields

- BYTE callID
- UUSInfo uusInfo

8.64.1 Detailed Description

This structure contains information for User to User Signaling Service for All Calls.

Parameters

callID	• Unique call identifier for the call.
uusInfo	• See UUSInfo for more information.

8.64.2 Field Documentation

8.64.2.1 BYTE allCallsUUSInfo::callID

8.64.2.2 UUSInfo allCallsUUSInfo::uusInfo

8.65 alphaIDInfo Struct Reference

Data Fields

- BYTE alphaDcs
- BYTE alphaLen
- BYTE alphaText [255]

8.65.1 Detailed Description

This structure contains information about the Alpha Identifier.

Parameters

alphaDcs	• Alpha coding scheme – 0x01 - GSM Default_Char – 0x02 - UCS2 – 0xFF - Not Available
alphaLen	• Number of sets of the following elements: – pAlpha_text • If zero(0) then no further information exists.
alphaText[MAX_-DESCRIPTION-_LENGTH]	• Data encoded as per the alpha_dcs

8.65.2 Field Documentation

8.65.2.1 BYTE alphaIDInfo::alphaDcs

8.65.2.2 BYTE alphaIDInfo::alphaLen

8.65.2.3 BYTE alphaIDInfo::alphaText[255]

8.66 altitudeSrcInfo Struct Reference

Data Fields

- ULONG source
- ULONG linkage
- ULONG coverage

8.66.1 Detailed Description

This structure specifies information regarding the altitude source

Parameters

source	• Specifies the source of the altitude • Valid values – 0 - Source is unknown – 1 - GPS is the source – 2 - Cell ID provided the source – 3 - Source is enhanced cell ID – 4 - Wi-Fi is the source – 5 - Terrestrial source – 6 - Hybrid terrestrial source – 7 - Altitude database is the source – 8 - Barometric altimeter is the source – 9 - Other sources
linkage	• Specifies the dependency between the horizontal and altitude position components • Valid values – 0 - Not specified – 1 - Fully interdependent – 2 - Depends on latitude and longitude – 3 - Fully independent
coverage	• Specifies the region of uncertainty. • Valid values – 0 - Not specified – 1 - Altitude uncertainty is valid at the injected horizontal position coordinates only – 2 - Altitude uncertainty applies to the position of the device regardless of horizontal position

8.66.2 Field Documentation

8.66.2.1 ULONG altitudeSrcInfo::coverage

8.66.2.2 ULONG altitudeSrcInfo::linkage

8.66.2.3 ULONG altitudeSrcInfo::source

8.67 altSrcInfo_t Struct Reference

Data Fields

- uint32_t source
- uint32_t linkage
- uint32_t coverage

8.67.1 Detailed Description

This structure specifies information regarding the altitude source

Parameters

source	• Specifies the source of the altitude • Valid values – 0 - Source is unknown – 1 - GPS is the source – 2 - Cell ID provided the source – 3 - Source is enhanced cell ID – 4 - Wi-Fi is the source – 5 - Terrestrial source – 6 - Hybrid terrestrial source – 7 - Altitude database is the source – 8 - Barometric altimeter is the source – 9 - Other sources
linkage	• Specifies the dependency between the horizontal and altitude position components • Valid values – 0 - Not specified – 1 - Fully interdependent – 2 - Depends on latitude and longitude – 3 - Fully independent
coverage	• Specifies the region of uncertainty. • Valid values – 0 - Not specified – 1 - Altitude uncertainty is valid at the injected horizontal position coordinates only – 2 - Altitude uncertainty applies to the position of the device regardless of horizontal position

8.67.2 Field Documentation

8.67.2.1 uint32_t altSrcInfo_t::coverage

8.67.2.2 uint32_t altSrcInfo_t::linkage

8.67.2.3 uint32_t altSrcInfo_t::source

8.68 appStats Struct Reference

Data Fields

- uint8_t appType
- uint8_t appState
- uint8_t persoState
- uint8_t persoFeature
- uint8_t persoRetries
- uint8_t persoUnblockRetries
- uint8_t aidLength
- uint8_t aidVal [255]
- uint8_t univPin

- uint8_t pin1State
- uint8_t pin1Retries
- uint8_t puk1Retries
- uint8_t pin2State
- uint8_t pin2Retries
- uint8_t puk2Retries

8.68.1 Detailed Description

This structure contains Application Status Information loaded on the card.

Parameters

appType	• Indicates the type of the application. – 0 - Unknown – 1 - SIM card – 2 - USIM application – 3 - RUIM card – 4 - CSIM application – 5 - ISIM application • Other values are reserved for the future and are to be handled as "Unknown".
appState	• Indicates the state of the application. – 0 - Unknown – 1 - Detected – 2 - PIN1 or UPIN is required – 3 - PUK1 or PUK for UPIN is required – 4 - Personalization state must be checked – 5 - PIN1 is blocked – 6 - Illegal – 7 - Ready
persoState	• Indicates the state of the personalization for the application. – 0 - Unknown – 1 - Personalization operation is in progress – 2 - Ready – 3 - Personalization code is required – 4 - PUK for personalization code is required – 5 - Permanently blocked

persoFeature	• Indicates the personalization feature. • This applies only when a personalization code is required to deactivate or unblock personalization. – 0 - GW network personalization – 1 - GW network subset personalization – 2 - GW service provider personalization – 3 - GW corporate personalization – 4 - GW UIM personalization – 5 - 1X network type 1 personalization – 6 - 1X network type 2 personalization – 7 - 1X HRPD personalization – 8 - 1X service provider personalization – 9 - 1X corporate personalization – 10 - 1X RUIM personalization – 11 - Unknown
persoRetries	• Indicates the number of retries remaining to disable the personalization.
persoUnblockRetries	• Indicates the number of retries remaining to unblock the personalization.
aidLength	• Number of sets of the following elements. i.e. aidVal • If zero(0) then no aidVal information exists.
aidVal[MAX_DESCRIPTION_LENGTH]	• Application identifier value.
univPin	• Indicates whether UPIN replaces PIN1. – 0 - PIN1 is used – 1 - UPIN replaces PIN1
pin1State	• Indicates the state of PIN1. – 0 - Unknown – 1 - Enabled and not verified – 2 - Enabled and verified – 3 - Disabled – 4 - Blocked – 5 - Permanently blocked
pin1Retries	• Indicates the number of retries remaining to verify PIN1.
puk1Retries	• Indicates the number of retries remaining to unblock PIN1.

pin2State	• Indicates the state of PIN2. – 0 - Unknown – 1 - Enabled and not verified – 2 - Enabled and verified – 3 - Disabled – 4 - Blocked – 5 - Permanently blocked
pin2Retries	• Indicates the number of retries remaining to verify PIN2.
puk2Retries	• Indicates the number of retries remaining to unblock PIN2.

8.68.2 Field Documentation

8.68.2.1 uint8_t appStats::aidLength

8.68.2.2 uint8_t appStats::aidVal[255]

8.68.2.3 uint8_t appStats::appState

8.68.2.4 uint8_t appStats::appType

8.68.2.5 uint8_t appStats::persoFeature

8.68.2.6 uint8_t appStats::persoRetries

8.68.2.7 uint8_t appStats::persoState

8.68.2.8 uint8_t appStats::persoUnblockRetries

8.68.2.9 uint8_t appStats::pin1Retries

8.68.2.10 uint8_t appStats::pin1State

8.68.2.11 uint8_t appStats::pin2Retries

8.68.2.12 uint8_t appStats::pin2State

8.68.2.13 uint8_t appStats::puk1Retries

8.68.2.14 uint8_t appStats::puk2Retries

8.68.2.15 uint8_t appStats::univPin

8.69 appStatus Struct Reference

Data Fields

- BYTE appType

- BYTE appState
- BYTE persoState
- BYTE persoFeature
- BYTE persoRetries
- BYTE persoUnblockRetries
- BYTE aidLength
- BYTE aidVal [255]
- BYTE univPin
- BYTE pin1State
- BYTE pin1Retries
- BYTE puk1Retries
- BYTE pin2State
- BYTE pin2Retries
- BYTE puk2Retries

8.69.1 Detailed Description

This structure contains Application Status Information loaded on the card.

Parameters

appType	• Indicates the type of the application. – 0 - Unknown – 1 - SIM card – 2 - USIM application – 3 - RUIM card – 4 - CSIM application – 5 - ISIM application • Other values are reserved for the future and are to be handled as "Unknown".
appState	• Indicates the state of the application. – 0 - Unknown – 1 - Detected – 2 - PIN1 or UPIN is required – 3 - PUK1 or PUK for UPIN is required – 4 - Personalization state must be checked – 5 - PIN1 is blocked – 6 - Illegal – 7 - Ready
persoState	• Indicates the state of the personalization for the application. – 0 - Unknown – 1 - Personalization operation is in progress – 2 - Ready – 3 - Personalization code is required – 4 - PUK for personalization code is required – 5 - Permanently blocked

persoFeature	• Indicates the personalization feature. • This applies only when a personalization code is required to deactivate or unblock personalization. – 0 - GW network personalization – 1 - GW network subset personalization – 2 - GW service provider personalization – 3 - GW corporate personalization – 4 - GW UIM personalization – 5 - 1X network type 1 personalization – 6 - 1X network type 2 personalization – 7 - 1X HRPD personalization – 8 - 1X service provider personalization – 9 - 1X corporate personalization – 10 - 1X RUIM personalization – 11 - Unknown
persoRetries	• Indicates the number of retries remaining to disable the personalization.
persoUnblockRetries	• Indicates the number of retries remaining to unblock the personalization.
aidLength	• Number of sets of the following elements. i.e. aidVal • If zero(0) then no aidVal information exists.
aidVal[MAX_DESCRIPTION_LENGTH]	• Application identifier value.
univPin	• Indicates whether UPIN replaces PIN1. – 0 - PIN1 is used – 1 - UPIN replaces PIN1
pin1State	• Indicates the state of PIN1. – 0 - Unknown – 1 - Enabled and not verified – 2 - Enabled and verified – 3 - Disabled – 4 - Blocked – 5 - Permanently blocked
pin1Retries	• Indicates the number of retries remaining to verify PIN1.
puk1Retries	• Indicates the number of retries remaining to unblock PIN1.

pin2State	• Indicates the state of PIN2. – 0 - Unknown – 1 - Enabled and not verified – 2 - Enabled and verified – 3 - Disabled – 4 - Blocked – 5 - Permanently blocked
pin2Retries	• Indicates the number of retries remaining to verify PIN2.
puk2Retries	• Indicates the number of retries remaining to unblock PIN2.

8.69.2 Field Documentation

8.69.2.1 BYTE appStatus::aidLength

8.69.2.2 BYTE appStatus::aidVal[255]

8.69.2.3 BYTE appStatus::appState

8.69.2.4 BYTE appStatus::appType

8.69.2.5 BYTE appStatus::persoFeature

8.69.2.6 BYTE appStatus::persoRetries

8.69.2.7 BYTE appStatus::persoState

8.69.2.8 BYTE appStatus::persoUnblockRetries

8.69.2.9 BYTE appStatus::pin1Retries

8.69.2.10 BYTE appStatus::pin1State

8.69.2.11 BYTE appStatus::pin2Retries

8.69.2.12 BYTE appStatus::pin2State

8.69.2.13 BYTE appStatus::puk1Retries

8.69.2.14 BYTE appStatus::puk2Retries

8.69.2.15 BYTE appStatus::univPin

8.70 arrAlertingPattern Struct Reference

Data Fields

- BYTE numInstances

- BYTE callID [20]
- ULONG alertingPattern [20]

8.70.1 Detailed Description

This structure contains an array of Alerting Pattern.

Parameters

numInstances	• Number of callID, alertingPattern that follow. • If zero(0) then no further information exists.
callID[MAX_NO_OF_CALLS]	• Array of Unique call identifier for the call.
alertingPattern[MAX_NO_OF_CALLS]	• Array of Alerting pattern. – 0x00 - QMI_VOICE_ALERTING_PATTERN_1 - Pattern 1 – 0x01 - QMI_VOICE_ALERTING_PATTERN_2 - Pattern 2 – 0x02 - QMI_VOICE_ALERTING_PATTERN_3 - Pattern 3 – 0x04 - QMI_VOICE_ALERTING_PATTERN_5 - Pattern 5 – 0x05 - QMI_VOICE_ALERTING_PATTERN_6 - Pattern 6 – 0x06 - QMI_VOICE_ALERTING_PATTERN_7 - Pattern 7 – 0x07 - QMI_VOICE_ALERTING_PATTERN_8 - Pattern 8 – 0x08 - QMI_VOICE_ALERTING_PATTERN_9 - Pattern 9

8.70.2 Field Documentation

8.70.2.1 ULONG arrAlertingPattern::alertingPattern[20]

8.70.2.2 BYTE arrAlertingPattern::callID[20]

8.70.2.3 BYTE arrAlertingPattern::numInstances

8.71 arrAlertingType Struct Reference

Data Fields

- BYTE numInstances
- BYTE callID [20]
- BYTE AlertingType [20]

8.71.1 Detailed Description

This structure contains an array of Alerting Type.

Parameters

numInstances	• Number of callID, AlertingType that follow. • If zero(0) then no further information exists.
callID[MAX_NO_OF_CALLS]	• Array of Unique call identifier for the call.
AlertingType[MAX_NO_OF_CALLS]	• Array of Alerting type. – 0x00 - ALERTING_LOCAL - Local – 0x01 - ALERTING_REMOTE - Remote

8.71.2 Field Documentation

8.71.2.1 BYTE arrAlertingType::AlertingType[20]

8.71.2.2 BYTE arrAlertingType::callID[20]

8.71.2.3 BYTE arrAlertingType::numInstances

8.72 arrAlphaID Struct Reference

Data Fields

- BYTE numInstances
- allCallsAlphaIDInfo allCallsAlphaIDInfoArr [20]

8.72.1 Detailed Description

This structure contains an array of Alpha ID Info

Parameters

numInstances	• Number of allCallsAlphaIDInfo that follow. • If zero(0) then no further information exists.
allCallsAlphaIDInfo[MAX_NO_OF_CALLS]	• Array of allCallsAlphaIDInfo. • See allCallsAlphaIDInfo for more information.

8.72.2 Field Documentation

8.72.2.1 allCallsAlphaIDInfo arrAlphaID::allCallsAlphaIDInfoArr[20]

8.72.2.2 BYTE arrAlphaID::numInstances

8.73 arrCalledPartyNum Struct Reference

Data Fields

- BYTE numInstances
- peerNumberInfo CalledPartyNum [20]

8.73.1 Detailed Description

This structure contains an array of Called Party Numbers consisting of information of all the numbers which have been called from the device.

Parameters

numInstances	• Number of calledPartyNum that follow. • If zero(0) then no further information exists.
CalledPartyNum[MAX_NO_OF_CALLS]	• Array of CalledPartyNum. • See peerNumberInfo for more information.

8.73.2 Field Documentation

8.73.2.1 peerNumberInfo arrCalledPartyNum::CalledPartyNum[20]

8.73.2.2 BYTE arrCalledPartyNum::numInstances

8.74 arrCallEndReason Struct Reference

Data Fields

- BYTE numInstances
- BYTE callID [20]
- WORD callEndReason [20]

8.74.1 Detailed Description

This structure contains an array of Call End Reasons.

Parameters

numInstances	• Number of callID, callEndReason that follow. • If zero(0) then no further information exists.
callID[MAX_NO_OF_CALLS]	• Array of Unique call identifier for the call.
callEndReason[MAX_NO_OF_CALLS]	• Array of Call End Reason . • See Table9 qaGobiApiTableVoiceCallEndReasons.h for a list of valid voice-related call end reasons

8.74.2 Field Documentation

8.74.2.1 WORD arrCallEndReason::callEndReason[20]

8.74.2.2 BYTE arrCallEndReason::callID[20]

8.74.2.3 BYTE arrCallEndReason::numInstances

8.75 arrCallInfo Struct Reference

Data Fields

- BYTE numInstances
- getAllCallInformation getAllCallInfo [20]

8.75.1 Detailed Description

This structure contains an array of Call Info

Parameters

numInstances	• Number of getAllCallInfo that follow. • If zero(0) then no further information exists.
getAllCallInfo[MAX_NO_OF_CALLS]	• Array of CallInfo. • See getAllCallInfo for more information.

8.75.2 Field Documentation

8.75.2.1 getAllCallInformation arrCallInfo::getAllCallInfo[20]

8.75.2.2 BYTE arrCallInfo::numInstances

8.76 arrConnectPartyNum Struct Reference

Data Fields

- BYTE numInstances
- peerNumberInfo ConnectedPartyNum [20]

8.76.1 Detailed Description

This structure contains an array of Connected Party Numbers consisting of information regarding all the devices connected.

Parameters

numInstances	• Number of ConnectedPartyNum that follow. • If zero(0) then no further information exists.

ConnectedParty-Num[MAX_NO_-OF_CALLS]	• Array of ConnectedPartyNum. • See peerNumberInfo for more information.

8.76.2 Field Documentation

8.76.2.1 peerNumberInfo arrConnectPartyNum::ConnectedPartyNum[20]

8.76.2.2 BYTE arrConnectPartyNum::numInstances

8.77 arrDiagInfo Struct Reference

Data Fields

- BYTE numInstances
- allCallsDiagInfo DiagInfo [20]

8.77.1 Detailed Description

This structure contains an array of Diagnostic Information.

Parameters

numInstances	• Number of DiagInfo that follow. • If zero(0) then no further information exists.
DiagInfo[MAX_-NO_OF_CALLS]	• Array of DiagInfo. • See allCallsDiagInfo for more information.

8.77.2 Field Documentation

8.77.2.1 allCallsDiagInfo arrDiagInfo::DiagInfo[20]

8.77.2.2 BYTE arrDiagInfo::numInstances

8.78 arrRedirPartyNum Struct Reference

Data Fields

- BYTE numInstances
- peerNumberInfo RedirPartyNum [20]

8.78.1 Detailed Description

This structure contains an array of Redirecting Party Numbers consisting of information of all the numbers which have been redirected from the device.

Parameters

numInstances	• Number of redirPartyNum that follow. • If zero(0) then no further information exists.
RedirPartyNum[MAX_NO_OF_CALLS]	• Array of RedirPartyNum. • See peerNumberInfo for more information.

8.78.2 Field Documentation

8.78.2.1 BYTE arrRedirPartyNum::numInstances

8.78.2.2 peerNumberInfo arrRedirPartyNum::RedirPartyNum[20]

8.79 arrRemotePartyName Struct Reference

Data Fields

- BYTE numInstances
- getAllCallRmtPtyName GetAllCallRmtPtyName [20]

8.79.1 Detailed Description

This structure contains an array of Remote Party Names

Parameters

numInstances	• Number of remotePartyName that follow. • If zero(0) then no further information exists.
GetAllCallRmtPtyName[MAX_NO_OF_CALLS]	• Array of remotePartyName. • See getAllCallRmtPtyName for more information.

8.79.2 Field Documentation

8.79.2.1 getAllCallRmtPtyName arrRemotePartyName::GetAllCallRmtPtyName[20]

8.79.2.2 BYTE arrRemotePartyName::numInstances

8.80 arrRemotePartyNum Struct Reference

Data Fields

- BYTE numInstances
- getAllCallRmtPtyNum RmtPtyNum [20]

8.80.1 Detailed Description

This structure contains an array of Remote Party Numbers

Parameters

numInstances	• Number of remotePartyNum that follow. • If zero(0) then no further information exists.
RmtPtyNum[MAX_NO_OF_CALLS]	• Array of remotePartyNum. • See getAllCallRmtPtyNum for more information.

8.80.2 Field Documentation

8.80.2.1 BYTE arrRemotePartyNum::numInstances

8.80.2.2 getAllCallRmtPtyNum arrRemotePartyNum::RmtPtyNum[20]

8.81 arrSvcOption Struct Reference

Data Fields

- BYTE numInstances
- BYTE callID [20]
- WORD srvOption [20]

8.81.1 Detailed Description

This structure contains array an of Servicing option.

Parameters

numInstances	• Number of callID, srvOption that follow. • If zero(0) then no further information exists.
callID[MAX_NO_OF_CALLS]	• Array of Unique call identifier for the call.
srvOption[MAX_NO_OF_CALLS]	• Array of Service option. • See Table9 qaGobiApiTableServiceOptions.h for standard service option number assignments.

8.81.2 Field Documentation

8.81.2.1 BYTE arrSvcOption::callID[20]

8.81.2.2 BYTE arrSvcOption::numInstances

8.81.2.3 WORD arrSvcOption::srvOption[20]

8.82 arrUUSInfo Struct Reference

Data Fields

- BYTE numInstances
- allCallsUUSInfo AllCallsUUSInfo [20]

8.82.1 Detailed Description

This structure contains an array of User to User Signaling Service Information

Parameters

numInstances	• Number of allCallsUUSInfo that follow. • If zero(0) then no further information exists.
AllCallsUUSInfo[MAX_NO_OF_CALLS]	• Array of allCallsUUSInfo. • See allCallsUUSInfo for more information.

8.82.2 Field Documentation

8.82.2.1 allCallsUUSInfo arrUUSInfo::AllCallsUUSInfo[20]

8.82.2.2 BYTE arrUUSInfo::numInstances

8.83 authenticateResult Struct Reference

Data Fields

- WORD contentLen
- BYTE content [1024]

8.83.1 Detailed Description

This structure contains the information about the authenticate result.

Parameters

contentLen	• Length of the following elements i.e. content.
content[MAX_CONTENT_LENGTH]	• Authenticate data. • This value is a sequence of bytes returned from the card.

8.83.2 Field Documentation

8.83.2.1 BYTE authenticateResult::content[1024]

8.83.2.2 WORD authenticateResult::contentLen

8.84 authenticationData Struct Reference

Data Fields

- BYTE context
- WORD dataLen
- BYTE data [1024]

8.84.1 Detailed Description

This structure contains the Session Information.

Parameters

context	• Authenticate context. – 0 - Runs the GSM algorithm (valid only on a 2GSIM card) – 1 - Runs the CAVE algorithm (valid only on a RUIM card) – 2 - GSM security context (valid only on a USIM application) – 3 - 3G security context (valid only on a USIM application) – 4 - VGCS/VBS security context (valid only on aUSIM application) – 5 - GBA security context, Bootstrapping mode (valid only on a USIM or ISIM application) – 6 - GBA security context, NAF Derivation mode (valid only on a USIM or ISIM application) – 7 - MBMS security context, MSK Update mode (valid only on a USIM application) – 8 - MBMS security context, MTK Generation mode (valid only on a USIM application) – 9 - MBMS security context, MSK Deletion mode (valid only on a USIM application) – 10 - MBMS security context, MUK Deletion mode (valid only on a USIM application) – 11 - IMS AKA security context (valid only on aISIM application) – 12 - HTTP-digest security context (valid only onan ISIM application) – 13 - Compute IP authentication, CHAP (valid onlyon RUIM or CSIM) – 14 - Compute IP authentication, MN-HA authenticator (valid only on RUIM or CSIM) – 15 - Compute IP authentication, MIP-RRQ hash (valid only on RUIM or CSIM) – 16 - Compute IP authentication, MN-AAA authenticator (valid only on RUIM or CSIM) – 17 - Compute IP authentication, HRPD access authenticator (valid only on RUIM or CSIM) • Other values are possible and reserved for future use.
dataLen	• Length of the following elements i.e. data.
data[MAX_DESCRIPTION_LENGTH]	• Authenticate Data.

8.84.2 Field Documentation

8.84.2.1 BYTE authenticationData::context

8.84.2.2 BYTE authenticationData::data[1024]

8.84.2.3 WORD authenticationData::dataLen

8.85 BandCapabilityResp Struct Reference

Data Fields

- ULONGLONG bandCapability
- ULONGLONG * pLteBandCapability
- ULONGLONG * pTdsBandCapability

8.85.1 Detailed Description

This structure contains the TLV required to Get Band Capability.

Parameters

bandCapability[-OUT]	Bitmask of bands supported by the device • Bit 0 - Band class 0, A-system • Bit 1 - Band class 0, B-system • Bit 2 - Band class 1, all blocks • Bit 3 - Band class 2 • Bit 4 - Band class 3, A-system • Bit 5 - Band class 4, all blocks • Bit 6 - Band class 5, all blocks • Bit 7 - GSM DCS band (1800) • Bit 8 - GSM Extended GSM (E-GSM) band (900) • Bit 9 - GSM Primary GSM (P-GSM) band (900) • Bit 10 - Band class 6 • Bit 11 - Band class 7 • Bit 12 - Band class 8 • Bit 13 - Band class 9 • Bit 14 - Band class 10 • Bit 15 - Band class 11 • Bit 16 - GSM 450 band • Bit 17 - GSM 480 band • Bit 18 - GSM 750 band • Bit 19 - GSM 850 band • Bit 20 - GSM railways GSM band (900) • Bit 21 - GSM PCS band (1900) • Bit 22 - WCDMA (Europe, Japan, and China) 2100 band • Bit 23 - WCDMA US PCS 1900 band • Bit 24 - WCDMA (Europe and China) DCS 1800 band • Bit 25 - WCDMA US 1700 band • Bit 26 - WCDMA US 850 band • Bit 27 - WCDMA Japan 800 band • Bit 28 - Band class 12 • Bit 29 - Band class 14 • Bit 30 - Reserved • Bit 31 - Band class 15 • Bits 32 through 47 - Reserved • Bit 48 - WCDMA Europe 2600 band • Bit 49 - WCDMA Europe and Japan 900 band • Bit 50 - WCDMA Japan 1700 band • Bits 51 through 55 - Reserved • Bit 56 - Band class 16 • Bit 57 - Band class 17 • Bit 58 - Band class 18 • Bit 59 - Band class 19 • Bit 60 - WCDMA Japan 850 band • Bit 61 - WCDMA 1500 band • Bits 62 and 63 - Reserved

OUT]	pLteBandCapability[OUT] Bitmask of LTE bands supported by the device • Bit 0 - LTE EUTRAN Band 1 UL:1920-1980; DL: 2110-2170 • Bit 1 - LTE EUTRAN Band 2 UL:1850-1910; DL: 1930-1990 • Bit 2 - LTE EUTRAN Band 3 UL:1710-1785; DL: 1805-1880 • Bit 3 - LTE EUTRAN Band 4 UL:1710-1755; DL: 2110-2155 • Bit 4 - LTE EUTRAN Band 5 UL: 824-849; DL: 869-894 • Bit 5 - LTE EUTRAN Band 6 UL: 830-840; DL: 875-885 • Bit 6 - LTE EUTRAN Band 7 UL:2500-2570; DL: 2620-2690 • Bit 7 - LTE EUTRAN Band 8 UL: 880-915; DL: 925-960 • Bit 8 - LTE EUTRAN Band 9 UL:1749.9-1784.9; DL: 1844.9-1879.9 • Bit 9 - LTE EUTRAN Band 10 UL:1710-1770; DL: 2110-2170 • Bit 10 - LTE EUTRAN Band 11 UL:1427.9-1452.9; DL: 1475.9-1500.9 • Bit 11 - LTE EUTRAN Band 12 UL:698-716; DL: 728-746 • Bit 12 - LTE EUTRAN Band 13 UL: 777-787; DL: 746-756 • Bit 13 - LTE EUTRAN Band 14 UL: 788-798; DL: 758-768 • Bits 14 and 15 - Reserved • Bit 16 - LTE EUTRAN Band 17 UL: 704-716; DL: 734-746 • Bit 17 - LTE EUTRAN Band 18 UL: 815-830; DL: 860-875 • Bit 18 - LTE EUTRAN Band 19 UL: 830-845; DL: 875-890 • Bit 19 - LTE EUTRAN Band 20 UL: 832-862; DL: 791-821 • Bit 20 - LTE EUTRAN Band 21 UL: 1447.9-1462.9; DL: 1495.9-1510.9 • Bit 21 - Reserved • Bit 22 - LTE EUTRAN Band 23 UL: 2000-2020; DL: 2180-2200 • Bit 23 - LTE EUTRAN Band 24 UL: 1626.5-1660.5; DL: 1525-1559 • Bit 24 - LTE EUTRAN Band 25 UL: 1850-1915; DL: 1930-1995 • Bit 25 - LTE EUTRAN Band 26 UL: 814-849; DL: 859-894 • Bit 26 - Reserved • Bit 27 - LTE EUTRAN Band 28 UL: 703-748; DL: 758-803 • Bit 28 - LTE EUTRAN Band 29 UL: 1850-1910 or 1710-1755; DL: 716-728 • Bit 29 - LTE EUTRAN Band 30 UL: 2350-2360; DL: 2305-2315 • Bit 30 - Reserved • Bit 31 - LTE EUTRAN Band 32 DL: 9920-10359 • Bit 32 - LTE EUTRAN Band 33 UL: 1900-1920; DL: 1900-1920 • Bit 33 - LTE EUTRAN Band 34 UL: 2010-2025; DL: 2010-2025 • Bit 34 - LTE EUTRAN Band 35 UL: 1850-1910; DL: 1850-1910 • Bit 35 - LTE EUTRAN Band 36 UL: 1930-1990; DL: 1930-1990 • Bit 36 - LTE EUTRAN Band 37 UL: 1910-1930; DL: 1910-1930 • Bit 37 - LTE EUTRAN Band 38 UL: 2570-2620; DL: 2570-2620 • Bit 38 - LTE EUTRAN Band 39 UL: 1880-1920; DL: 1880-1920 • Bit 39 - LTE EUTRAN Band 40 UL: 2300-2400; DL: 2300-2400 • Bit 40 - LTE EUTRAN Band 41 UL: 2496-2690; DL: 2496-2690 • Bit 41 - LTE EUTRAN Band 42 UL: 3400-3600; DL: 3400-3600 • Bit 42 - LTE EUTRAN Band 43 UL: 3600-3800; DL: 3600-3800 • Bits 43 through 64 - Reserved

OUT]	pTdsBandCapability[OUT] Bitmask of TDS bands supported by the device. • Bit 0 - TDS Band A 1900 to 1920 MHz, 2010 to 2020 MHz • Bit 1 - TDS Band B 1850 to 1910 MHz, 1930 to 1990 MHz • Bit 2 - TDS Band C 1910 to 1930 MHz • Bit 3 - TDS Band D 2570 to 2620 MHz • Bit 4 - TDS Band E 2300 to 2400 MHz • Bit 5 - TDS Band F 1880 to 1920 MHz

8.85.2 Field Documentation

8.85.2.1 ULONGLONG BandCapabilityResp::bandCapability

8.85.2.2 ULONGLONG* BandCapabilityResp::pLteBandCapability

8.85.2.3 ULONGLONG* BandCapabilityResp::pTdsBandCapability

8.86 BandPrefTlv Struct Reference

Data Fields

- ULONGLONG bits_1_64
- ULONGLONG bits_65_128
- ULONGLONG bits_129_192
- ULONGLONG bits_193_256
- BYTE TlvPresent

8.86.1 Detailed Description

Contain the Band Preference.

Parameters

bits_1_64	• Bits 1 to 64 of the 256-bit Operating Band bitmask.
bits_65_128	• Bits 65 to 128 of the 256-bit Operating Band bitmask.
bits_129_192	• Bits 129 to 192 of the 256-bit Operating Band bitmask.
bits_193_256	• Bits 193 to 256 of the 256-bit Operating Band bitmask.
TlvPresent	• Tlv Present

8.86.2 Field Documentation

8.86.2.1 ULONGLONG BandPrefTlv::bits_129_192

8.86.2.2 ULONGLONG BandPrefTlv::bits_193_256

8.86.2.3 ULONGLONG BandPrefTlv::bits_1_64

8.86.2.4 ULONGLONG BandPrefTlv::bits_65_128

8.86.2.5 BYTE BandPrefTlv::TlvPresent

8.87 BdsSV Struct Reference

Data Fields

- WORD id
- BYTE mask

8.87.1 Detailed Description

This structure contains the BDS SV Info

Parameters

id	• SV ID of the satellite whose data is to be deleted. – Range for BDS: 201 to 237
mask	• Indicates if the ephemeris or almanac for a satellite is to be deleted • Valid values: – QMI_LOC_MASK_DELETE_EPHEMERIS (0x01) - Delete ephemeris for the satellite – QMI_LOC_MASK_DELETE_ALMANAC (0x02) - Delete almanac for the satellite

8.87.2 Field Documentation

8.87.2.1 WORD BdsSV::id

8.87.2.2 BYTE BdsSV::mask

8.88 BdsSVInfo Struct Reference

Data Fields

- BYTE len
- BdsSV * pSV

8.88.1 Detailed Description

This structure contains the number of sets of the BDS SVN Info

Parameters

len	• Number of sets of the following elements: – gnssSvId – deleteSvInfoMask
pSV	• Pointer to struct BdsSV. See BdsSV for more information

8.88.2 Field Documentation

8.88.2.1 BYTE BdsSVInfo::len

8.88.2.2 BdsSV* BdsSVInfo::pSV

8.89 BroadcastConfig Struct Reference

Data Fields

- WORD fromServiceId
- WORD toServiceId
- BYTE selected

8.89.1 Detailed Description

This structure contains BroadcastConfig parameters

Parameters

fromServiceId	• Starting point of range of CBM message identifiers
toServiceId	• Ending point of range of CBM message identifiers
selected	• Range of CBM message identifiers indicated by from_service_id and to_service_id – 0x00 - Not selected – 0x01 - Selected

8.89.2 Field Documentation

8.89.2.1 WORD BroadcastConfig::fromServiceId

8.89.2.2 BYTE BroadcastConfig::selected

8.89.2.3 WORD BroadcastConfig::toServiceId

8.90 burstDTMFInfo Struct Reference

Data Fields

- BYTE * pCallID
- BYTE digitCnt
- BYTE pDigitBuff [255]

8.90.1 Detailed Description

This structure contains Voice Burst DTMF Information

Parameters

pCallID[IN/OUT]	• Call ID associated with call on which the DTMF information has to be sent. A burst DTMF request is sent to the current active/alerting call when pCallId is set to 0xFF. • This is IN/OUT parameter, value passed by user will be packed in request and value received from the device would be returned to the user. • If the call ID value received is 0, no value has been returned by the device
digitCnt	• Length of DTMF digit buffer which follows
pDigitBuff[MAX_DESCRIPTION_LENGTH]	• DTMF digit buffer in ASCII, NULL terminated

8.90.2 Field Documentation

8.90.2.1 BYTE burstDTMFInfo::digitCnt

8.90.2.2 BYTE* burstDTMFInfo::pCallID

8.90.2.3 BYTE burstDTMFInfo::pDigitBuff[255]

8.91 CallBarringSysInfo Struct Reference

Data Fields

- ULONG csBarStatus
- ULONG psBarStatus

8.91.1 Detailed Description

Structure for storing the GSM and WCDMA Call Barring System Information.

Parameters

csBarStatus	• Call barring status for circuit-switched calls. – NAS_CELL_ACCESS_NORMAL_ONLY - Cell access is allowed for normal calls only – NAS_CELL_ACCESS_EMERGENCY_ONLY - Cell access is allowed for emergency calls only – NAS_CELL_ACCESS_NO_CALLS - Cell access is not allowed for any call type – NAS_CELL_ACCESS_ALL_CALLS - Cell access is allowed for all call types – NAS_CELL_ACCESS_UNKNOWN - Cell access type is unknown
psBarStatus	• Call barring status for packet-switched calls. – NAS_CELL_ACCESS_NORMAL_ONLY - Cell access is allowed for normal calls only – NAS_CELL_ACCESS_EMERGENCY_ONLY - Cell access is allowed for emergency calls only – NAS_CELL_ACCESS_NO_CALLS - Cell access is not allowed for any call type – NAS_CELL_ACCESS_ALL_CALLS - Cell access is allowed for all call types – NAS_CELL_ACCESS_UNKNOWN - Cell access type is unknown

8.91.2 Field Documentation

8.91.2.1 ULONG CallBarringSysInfo::csBarStatus

8.91.2.2 ULONG CallBarringSysInfo::psBarStatus

8.92 callBarStatus Struct Reference

Data Fields

- ULONG csBarStatus
- ULONG psBarStatus

8.92.1 Detailed Description

This structure contains Call Barring Status.

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

csBarStatus	• Call Barring Status for circuit-switched calls. • Values: • NAS_CELL_ACCESS_NORMAL_ONLY - Cell access is allowed for normal calls only • NAS_CELL_ACCESS_EMERGENCY_ONLY - Cell access is allowed for emergency calls only • NAS_CELL_ACCESS_NO_CALLS - Cell access is not allowed for any call type • NAS_CELL_ACCESS_ALL_CALLS - Cell access is allowed for all call types • NAS_CELL_ACCESS_UNKNOWN - Cell access type is unknown

psBarStatus	• Call Barring Status for packet-switched calls. • Values: – NAS_CELL_ACCESS_NORMAL_ONLY - Cell access is allowed for normal calls only – NAS_CELL_ACCESS_EMERGENCY_ONLY - Cell access is allowed for emergency calls only – NAS_CELL_ACCESS_NO_CALLS - Cell access is not allowed for any call type – NAS_CELL_ACCESS_ALL_CALLS - Cell access is allowed for all call types – NAS_CELL_ACCESS_UNKNOWN - Cell access type is unknown

8.92.2 Field Documentation

8.92.2.1 ULONG callBarStatus::csBarStatus

8.92.2.2 ULONG callBarStatus::psBarStatus

8.93 calledPartyInfo Struct Reference

Data Fields

- BYTE PI
- BYTE SI
- BYTE numType
- BYTE numPlan
- BYTE numLen
- BYTE number [255]

8.93.1 Detailed Description

This structure contains Called party Number Information

Parameters

PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.
SI	• Number of sets of following elements – Caller Id
SI	• Number screening indicator. • Values: – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network

numType	• Number type. • Values: – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension
numPlan	• Number plan. • Values: – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
numLen	• Provides the length of number which follow.
number[255]	• number of numLen length, NULL terminated.

8.93.2 Field Documentation

8.93.2.1 BYTE calledPartyInfo::number[255]

8.93.2.2 BYTE calledPartyInfo::numLen

8.93.2.3 BYTE calledPartyInfo::numPlan

8.93.2.4 BYTE calledPartyInfo::numType

8.93.2.5 BYTE calledPartyInfo::PI

8.93.2.6 BYTE calledPartyInfo::SI

8.94 calledPartySubAdd Struct Reference

Data Fields

- BYTE extBit

- BYTE subAddrType
- BYTE oddEvenInd
- BYTE subAddrLen
- BYTE subAddr [255]

8.94.1 Detailed Description

This structure contains information about the Called Sub Party Addresses.

Parameters

extBit	• Extension bit.
subAddrType	• Subaddress type. – 0x00 - NSAP – 0x01 - USER
oddEvenInd	• Even/odd indicator. – 0x00 - Even number of address signals – 0x01 - Odd number of address signals
subAddrLen	• Number of sets of the following elements: – SubAddress
subAddr[MAX_-DESCRIPTION-_LENGTH]	• Array of the SubAddress in BCD number format.

8.94.2 Field Documentation

8.94.2.1 BYTE calledPartySubAdd::extBit

8.94.2.2 BYTE calledPartySubAdd::oddEvenInd

8.94.2.3 BYTE calledPartySubAdd::subAddr[255]

8.94.2.4 BYTE calledPartySubAdd::subAddrLen

8.94.2.5 BYTE calledPartySubAdd::subAddrType

8.95 callerIDInfo Struct Reference

Data Fields

- BYTE PI
- BYTE callerIDLen
- BYTE callerID [255]

8.95.1 Detailed Description

This structure contains Caller ID Information

Parameters

PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.
callerIDLen	• Number of sets of following elements – Caller Id
pCallerID	• Caller ID in ASCII string.

8.95.2 Field Documentation

8.95.2.1 BYTE callerIDInfo::callerID[255]

8.95.2.2 BYTE callerIDInfo::callerIDLen

8.95.2.3 BYTE callerIDInfo::PI

8.96 callFwdTypeAndPlan Struct Reference

Data Fields

- BYTE numberType
- BYTE numberPlan

8.96.1 Detailed Description

This structure contains Supplementary Service request parameters related to different features and their activation, deactivation, registration and erasure (applicable only for 3GPP)

Parameters

numberType	• Call forwarding number type – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION Reserved extension

numberPlan	• Call forwarding number plan – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION Reserved extension

8.96.2 Field Documentation

8.96.2.1 BYTE callFwdTypeAndPlan::numberPlan

8.96.2.2 BYTE callFwdTypeAndPlan::numberType

8.97 callFWExtInfo Struct Reference

Data Fields

- BYTE SvcStatus
- BYTE SvcClass
- BYTE noReplyTimer
- BYTE PI
- BYTE SI
- BYTE numType
- BYTE numPlan
- BYTE numLen
- BYTE number [255]

8.97.1 Detailed Description

This structure contains information for Get Call Forwarding Extended Information.

Parameters

SvcStatus	• Service status. Values: – 0x00 - SERVICE_STATUS_INACTIVE - Inactive – 0x01 - SERVICE_STATUS_ACTIVE - Active
SvcClass	• Service Class is a combination (sum) of information class constants • See qaGobiApiTableSupServiceInfoClasses.h for service classes.
noReplyTimer	• No reply timer value in seconds • A value of 0 indicates that no_reply_timer is ignored.

PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.
SI	• Number screening indicator. • Values: – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network
numType	• Number type. • Values: – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension
numPlan	• Number plan. • Values: – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
numLen	• Provides the length of number which follow.
number[255]	• number of numLen length, NULL terminated.

8.97.2 Field Documentation

8.97.2.1 BYTE callFWExtInfo::noReplyTimer

8.97.2.2 BYTE callFWExtInfo::number[255]

8.97.2.3 BYTE callFWExtInfo::numLen

8.97.2.4 BYTE callFWExtInfo::numPlan

8.97.2.5 BYTE callFWExtInfo::numType

8.97.2.6 BYTE callFWExtInfo::PI

8.97.2.7 BYTE callFWExtInfo::SI

8.97.2.8 BYTE callFWExtInfo::SvcClass

8.97.2.9 BYTE callFWExtInfo::SvcStatus

8.98 callFWInfo Struct Reference

Data Fields

- BYTE SvcStatus
- BYTE SvcClass
- BYTE numLen
- BYTE number [255]
- BYTE noReplyTimer

8.98.1 Detailed Description

This structure contains information for Get Call Forwarding Information.

Parameters

SvcStatus	• Service status. Values: – 0x00 - SERVICE_STATUS_INACTIVE - Inactive – 0x01 - SERVICE_STATUS_ACTIVE - Active
SvcClass	• Service Class is a combination (sum) of information class constants • See qaGobiApiTableSupServiceInfoClasses.h for service classes.
numLen	• Provides the length of number which follow.
number[255]	• number of numLen length, NULL terminated.
noReplyTimer	• No reply timer value in seconds • A value of 0 indicates that noReplyTimer is ignored.

8.98.2 Field Documentation

8.98.2.1 BYTE callFWInfo::noReplyTimer

8.98.2.2 BYTE callFWInfo::number[255]

8.98.2.3 BYTE callFWInfo::numLen

8.98.2.4 BYTE callFWInfo::SvcClass

8.98.2.5 BYTE callFWInfo::SvcStatus

8.99 callInfo Struct Reference

Data Fields

- BYTE callID
- BYTE callState
- BYTE callType
- BYTE direction
- BYTE mode

8.99.1 Detailed Description

This structure contains Information about call state changes. For example, when an incoming call is received, this structure is populated and indicate the incoming call information. When this incoming call is answered, the call status changes from INCOMING to CONVERSATION, which means a change in the call information and this structure is populated again with the changes and notified to/retrived by the user.

Parameters

callID	• Call identifier for the call queried for information. • If zero(0) then invalid.
callState	• Call state. – 0x01 - CALL_STATE_ORIGINATION - Origination – 0x02 - CALL_STATE_INCOMING - Incoming – 0x03 - CALL_STATE_CONVERSATION - Conversation – 0x04 - CALL_STATE_CC_IN_PROGRESS - Call is originating but waiting for call control to complete – 0x05 - CALL_STATE_ALERTING - Alerting – 0x06 - CALL_STATE_HOLD - Hold – 0x07 - CALL_STATE_WAITING - Waiting – 0x08 - CALL_STATE_DISCONNECTING - Disconnecting – 0x09 - CALL_STATE_END - End – 0x0A - CALL_STATE_SETUP - MT call is in Setup state in 3GPP – 0xFF - Not Available

callType	• Call type. – 0x00 - CALL_TYPE_VOICE - Voice – 0x02 - CALL_TYPE_VOICE_IP - Voice over IP – 0x06 - CALL_TYPE_OTAPA - OTAPA – 0x07 - CALL_TYPE_STD_OTASP - Standard OTASP – 0x08 - CALL_TYPE_NON_STD_OTASP - Nonstandard OTASP – 0x09 - CALL_TYPE_EMERGENCY - Emergency – 0xFF - Not Available
direction	• Direction. – 0x01 - CALL_DIRECTION_MO - MO call – 0x02 - CALL_DIRECTION_MT - MT call – 0xFF - Not Available
mode	• Mode. • If the mode field is "0x01 - CDMA",the optional Service Option, Voice Privacy, and OTASP Status (only for OTASP calls) TLVs are included in the response. – 0x01 - CALL_MODE_CDMA - CDMA – 0x02 - CALL_MODE_GSM - GSM – 0x03 - CALL_MODE_UMTS - UMTS – 0x04 - CALL_MODE_LTE - LTE – 0x05 - CALL_MODE_TDS - TD-SCDMA – 0xFF - Not Available

8.99.2 Field Documentation

8.99.2.1 BYTE callInfo::callID

8.99.2.2 BYTE callInfo::callState

8.99.2.3 BYTE callInfo::callType

8.99.2.4 BYTE callInfo::direction

8.99.2.5 BYTE callInfo::mode

8.100 callingPartyInfo Struct Reference

Data Fields

- BYTE PI
- BYTE SI
- BYTE numType
- BYTE numPlan
- BYTE numLen
- BYTE number [255]

8.100.1 Detailed Description

This structure contains Calling party Number Information

Parameters

PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.
SI	• Number of sets of following elements – Caller Id
SI	• Number screening indicator. • Values: – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network
numType	• Number type. • Values: – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension
numPlan	• Number plan. • Values: – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
numLen	• Provides the length of number which follow.

number[255]	• number of numLen length, NULL terminated.

8.100.2 Field Documentation

8.100.2.1 BYTE callingPartyInfo::number[255]

8.100.2.2 BYTE callingPartyInfo::numLen

8.100.2.3 BYTE callingPartyInfo::numPlan

8.100.2.4 BYTE callingPartyInfo::numType

8.100.2.5 BYTE callingPartyInfo::PI

8.100.2.6 BYTE callingPartyInfo::SI

8.101 cardResult Struct Reference

Data Fields

- BYTE sw1
- BYTE sw2

8.101.1 Detailed Description

This structure contains the information about the card result.

Parameters

sw1	• SW1 received from the card.
sw2	• SW2 received from the card.

8.101.2 Field Documentation

8.101.2.1 BYTE cardResult::sw1

8.101.2.2 BYTE cardResult::sw2

8.102 cardStatus Struct Reference

Data Fields

- WORD indexGwPri
- WORD index1xPri
- WORD indexGwSec
- WORD index1xSec

- BYTE numSlot
- slotInfo SlotInfo [5]

8.102.1 Detailed Description

This structure contains Card Status Information.

Parameters

indexGwPri	• Index of the primary GW provisioning application. • The most significant byte indicates the slot (starting from 0), while the least significant byte indicates the application for that slot (starting from 0). • The value 0xFFFF identifies when the session does not exist.
index1xPri	• Index of the primary 1X provisioning application. • The most significant byte indicates the slot (starting from 0), while the least significant byte indicates the application for that slot (starting from 0). • The value 0xFFFF identifies when the session does not exist.
indexGwSec	• Index of the secondary GW provisioning application. • The most significant byte indicates the slot (starting from 0), while the least significant byte indicates the application for that slot (starting from 0). • The value 0xFFFF identifies when the session does not exist.
index1xSec	• Index of the secondary GW provisioning application. • The most significant byte indicates the slot (starting from 0), while the least significant byte indicates the application for that slot (starting from 0). • The value 0xFFFF identifies when the session does not exist.
numSlot	• Indicates the number of slots available on the device. • The following block is repeated for each slot. i.e. cardState • If zero(0) then no cardState information exists.
SlotInfo[MAX_NO_OF_SLOTS]	• See slotInfo for more information.

8.102.2 Field Documentation

8.102.2.1 WORD cardStatus::index1xPri

8.102.2.2 WORD cardStatus::index1xSec

8.102.2.3 WORD cardStatus::indexGwPri

8.102.2.4 WORD cardStatus::indexGwSec

8.102.2.5 BYTE cardStatus::numSlot

8.102.2.6 slotInfo cardStatus::SlotInfo[5]

8.103 CarrierImage_t Struct Reference

Data Fields

- uint32_t m_nCarrierId
- uint32_t m_nFolderId
- uint32_t m_nStorage
- uint8_t m_FwImageId [100]
- uint8_t m_FwBuildId [100]
- uint8_t m_PriImageId [100]
- uint8_t m_PriBuildId [100]

8.103.1 Detailed Description

This structure contains the Carrier Image parameters.

Parameters

m_nCarrierId	• Unique numeric carrier ID indicating the carrier that the following images belong to
m_nFolderId	• Unique numeric folder ID indicating the folder where the images should reside on the host storage.
m_nStorage	• Information of storage type • Values – 0 - Device – 1 - Host
m_FwImageId	• Firmware image ID
m_FwBuildId	• Firmware build ID
m_PriImageId	• PRI image ID
m_PriBuildId	• PRI build ID

8.103.2 Field Documentation

8.103.2.1 uint8_t CarrierImage_t::m_FwBuildId[100]

8.103.2.2 uint8_t CarrierImage_t::m_FwImageId[100]

8.103.2.3 uint32_t CarrierImage_t::m_nCarrierId

8.103.2.4 uint32_t CarrierImage_t::m_nFolderId

8.103.2.5 uint32_t CarrierImage_t::m_nStorage

8.103.2.6 uint8_t CarrierImage_t::m_PriBuildId[100]

8.103.2.7 uint8_t CarrierImage_t::m_PriImageId[100]

8.104 CatAlPhaIdentifierTlv Struct Reference

Data Fields

- BYTE ReferenceID
- USHORT AlphaIDLength
- BYTE AlphaID [255]

8.104.1 Detailed Description

structure used to store all Alpha Identifier parameters.

Parameters

ReferenceID	- proactive command type that included the alpha identifier - 0x01; sends SMS proactive command
AlphaIDLength	- length of AlphaID (in bytes)
AlphaID	- alpha identifier, encoded as in ETSI TS 102 223 [Section 8.2]

8.104.2 Field Documentation

8.104.2.1 BYTE CatAlPhaIdentifierTlv::AlphaID[255]

8.104.2.2 USHORT CatAlPhaIdentifierTlv::AlphaIDLength

8.104.2.3 BYTE CatAlPhaIdentifierTlv::ReferenceID

8.105 CatCommonEventTlv Struct Reference

Data Fields

- BYTE TlvPresent
- BYTE EventID
- WORD EventLength
- union currentCatEvent CatEvent

8.105.1 Field Documentation

8.105.1.1 union currentCatEvent CatCommonEventTlv::CatEvent

8.105.1.2 BYTE CatCommonEventTlv::EventID

8.105.1.3 WORD CatCommonEventTlv::EventLength

8.105.1.4 BYTE CatCommonEventTlv::TlvPresent

8.106 CatEndProactiveSessionTlv Struct Reference

Data Fields

- BYTE EndProactiveSession

8.106.1 Detailed Description

structure used to store End Proactive Session event parameters.

Parameters

EndProactive-Session	- The proactive session end type values are: • 0x01 - End proactive session command type received from the card • 0x02 - End proactive session internal to ME

8.106.2 Field Documentation

8.106.2.1 BYTE CatEndProactiveSessionTlv::EndProactiveSession

8.107 CATEventDataType Struct Reference

Data Fields

- ULONG eventMask
- ULONG * pErrorMask

8.107.1 Field Documentation

8.107.1.1 ULONG CATEventDataType::eventMask

8.107.1.2 ULONG* CATEventDataType::pErrorMask

8.108 CatEventIDDataTlv Struct Reference

Data Fields

- ULONG ReferenceID
- USHORT DataLength
- BYTE Data [255]

8.108.1 Detailed Description

structure used to store all Common CAT Event parameters.

Parameters

ReferenceID	- proactive command reference ID.
DataLength	- length of pData (in Bytes)
Data	- command specific to the CAT event ID, encoded as in ETSI TS 102 223 [Section 6.6.X]

8.108.2 Field Documentation

8.108.2.1 BYTE CatEventIDDataTlv::Data[255]

8.108.2.2 USHORT CatEventIDDataTlv::DataLength

8.108.2.3 ULONG CatEventIDDataTlv::ReferenceID

8.109 CatEventListTlv Struct Reference

Data Fields

- ULONG SetupEventList

8.109.1 Detailed Description

structure used to store all Event List parameters.

Parameters

SetupEventList	- Setup event list bit mask • 0x00000001 - User Activity Notify • 0x00000002 - Idle Screen Available • 0x00000004 - Lang Selection Notify Each set bit indicates the availability of the corresponding event in Setup Event list proactive command; all unlisted bits are reserved for future use and will be ignored

8.109.2 Field Documentation

8.109.2.1 ULONG CatEventListTlv::SetupEventList

8.110 CatRefreshTlv Struct Reference

Data Fields

- USHORT RefreshMode
- BYTE RefreshStage

8.110.1 Detailed Description

structure used to store all Refresh Event parameters.

Parameters

RefreshMode	- The Refresh Event as in ETSI TS 102 223 [Section 8.6]
RefreshStage	- Stage of a refresh procedure • 0x01 - Refresh start • 0x02 - Refresh success • 0x03 - Refresh failed

8.110.2 Field Documentation

8.110.2.1 USHORT CatRefreshTlv::RefreshMode

8.110.2.2 BYTE CatRefreshTlv::RefreshStage

8.111 ccSUPSType Struct Reference

Data Fields

- BYTE svcType
- BYTE reason

8.111.1 Detailed Description

This structure contains information about the Call Control Supplementary Service Types

Parameters

svcType	• Service type. – 0x01 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_ACTIVATE - Activate – 0x02 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_DEACTIVATE - Deactivate – 0x03 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_REGISTER - Register – 0x04 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_ERASE - Erase – 0x05 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_INTERROGATE - Interrogate – 0x06 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_REGISTER_PASSWORD - Register password – 0x07 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_USSD - USSD – 0xFF - Not Available
reason	• Call control supplementary service result reason • Values: – See qaGobiApiTableCallControlReturnReasons.h for return reasons.

8.111.2 Field Documentation

8.111.2.1 BYTE ccSUPSType::reason

8.111.2.2 BYTE ccSUPSType::svcType

8.112 CDMABroadcastConfig Struct Reference

Data Fields

- WORD serviceCategory
- WORD language
- BYTE selected

8.112.1 Detailed Description

This structure contains CDMABroadcastConfig parameters

Parameters

serviceCategory	• Service category
language	• Language
selected	• Specified service_category and language – 0x00 - Not selected – 0x01 - Selected

8.112.2 Field Documentation

8.112.2.1 WORD CDMABroadcastConfig::language

8.112.2.2 BYTE CDMABroadcastConfig::selected

8.112.2.3 WORD CDMABroadcastConfig::serviceCategory

8.113 CDMAChannel Struct Reference

Data Fields

- WORD priChA
- WORD priChB
- WORD secChA
- WORD secChB

8.113.1 Detailed Description

This structure contains the parameters for CDMA Channel Information

Parameters

priChA	• A Channel number for the primary carrier. – 0xFFFF - Not Available
priChB	• B Channel number for the primary carrier. – 0xFFFF - Not Available
secChA	• A Channel number for the secondary carrier. – 0xFFFF - Not Available

secChB	• B Channel number for the secondary carrier. – 0xFFFF - Not Available

8.113.2 Field Documentation

8.113.2.1 WORD CDMAChannel::priChA

8.113.2.2 WORD CDMAChannel::priChB

8.113.2.3 WORD CDMAChannel::secChA

8.113.2.4 WORD CDMAChannel::secChB

8.114 CDMAECIOThresh Struct Reference

Data Fields

- BYTE CDMAECIOThreshListLen
- WORD * pCDMAECIOThreshList

8.114.1 Detailed Description

This structure contains CDMA ECIO threshold related parameters.

Parameters

CDMAECIO-ThreshListLen	• Length of the CDMA ECIO threshold list parameter to follow
pCDMAECIO-ThreshList	• Array of ECIO thresholds (in units of 0.1 dB) • Maximum of 32 values. Range for ECIO values: -31.5 to 0 (in dB)

8.114.2 Field Documentation

8.114.2.1 BYTE CDMAECIOThresh::CDMAECIOThreshListLen

8.114.2.2 WORD* CDMAECIOThresh::pCDMAECIOThreshList

8.115 CDMAInfo Struct Reference

Data Fields

- WORD sid
- WORD nid
- WORD baseId
- WORD refpn
- ULONG baseLat

- ULONG baseLong

8.115.1 Detailed Description

This structure contains information about the CDMA Network.

Parameters

sid	• System ID. – 0xFFFF - Not Available
nid	• Network ID. – 0xFFFF - Not Available
baseId	• Base station ID. – 0xFFFF - Not Available
refpn	• Reference PN. – 0xFFFF - Not Available
baseLat	• Latitude of the current base station in units of 0.25 sec. – 0xFFFFFFFF - Not Available
baseLong	• Longitude of the current base station in units of 0.25 sec. – 0xFFFFFFFF - Not Available

8.115.2 Field Documentation

8.115.2.1 WORD CDMAInfo::baseId

8.115.2.2 ULONG CDMAInfo::baseLat

8.115.2.3 ULONG CDMAInfo::baseLong

8.115.2.4 WORD CDMAInfo::nid

8.115.2.5 WORD CDMAInfo::refpn

8.115.2.6 WORD CDMAInfo::sid

8.116 cdmaMsgDecodingParams Struct Reference

Data Fields

- ULONG messageLength
- BYTE * pMessage

- ULONG * pMessageID
- BYTE * pSenderAddrLength
- CHAR senderAddr [24+1]
- BYTE * pTextMsgLength
- USHORT textMsg [160+2]
- BYTE * pPriority
- BYTE * pPrivacy
- BYTE * pLanguage
- sms_timestemp mcTimeStamp
- sms_timestemp absoluteValidity
- BYTE * pRelativeValidity
- BYTE * pDisplayMode
- BOOL * pUserAcknowledgementReq
- BOOL * pReadAcknowledgementReq
- BYTE * pAlertPriority
- BYTE * pCallbkAddrLength
- CHAR * pCallbkAddr

8.116.1 Detailed Description

Structure contains parameters which need to be decoded from message

Parameters

messageLength[IN]	• Length of the message to be decoded in bytes
pMessage[IN]	• Message read off the device via GetSMS
pSenderAddrLength[IN/OUT]	• Upon input, indicates the maximum number of ASCII characters (including NULL termination) that the pSenderAddr buffer can accommodate. Note that a length of 14 is reasonable.Upon successful output, returns the length of originating address string (including the NULL termination)
pSenderAddr[OUT]	• Returns NULL-terminated ASCII String containing the originating address.International number will be prepended with a '+'character
pTextMsgLength[IN/OUT]	• Upon input, specifies the number of UCS2 characters the given text message buffer can accommodate.Upon successful output, returns the number of UCS2 characters returns in the given text messagebuffer(including NULL-terminator)
pTextMsg[OUT]	• Returns the text message as NULL-terminated UCS2 string
pPriority[OUT]	(optional parameter) • Returns the priority setting of the message 0x00 - normal 0x01 - interactive 0x02 - urgent 0x03 - emergency 0xFF - unavailable setting
pPrivacy[OUT](optional	parameter) • Returns the privacy setting of the message 0x00 - not restricted 0x01 - restricted 0x02 - confidential 0x03 - secret 0xFF - unavailable setting

pLanguage[OUT]	(optional parameter) • Returns the language setting of the message 0x00 - unspecified 0x01 - english 0x02 - french 0x03 - spanish 0x04 - japanese 0x05 - korean 0x06 - chinese 0x07 - hebrew 0xFF - unavailable setting
mcTimeStamp[8][OUT]	(optional parameter) • Returns the message center timestamp which takes the form: YYMMDDHHMMSSTZ where YY - year MM - month DD - day HH - hour MM - minute SS - second TZ - timezone All values are in decimal. Timezone is in relation to GMT, one unit is equal to 15 minutes and MSB indicates a negative value.If this information is unavailable for message then this field will be filled with 0xFF
absoluteValidity[8][OUT]	(optional parameter) • Returns the absolute validity period setting for this message.This field takes the same form as mcTimeStamp
pRelativeValidity[OUT]	(optional parameter) • Returns the relative validity period.Values have the following meanings: 0 to 143: validity period =(value + 1)∗ 5 minutes 144 to 167: validity period =12 hours+(value - 143)∗30 minutes 168 to 196: validity period = (value - 166) ∗ 1 day 197 to 244: validity period = (value - 192) ∗ 1 week 245: validity period = indefinite 246: validity period = immediate 247: validity period = valid until mobile becomes inactive 248: validity period = valid until registration area changes 249 to 254: reserved 255: unavailable information
pDisplayMode[OUT]	(optional parameter) • Returns the display mode parameter 0x00 - immediate display 0x01 - mobile default setting 0x02 - user invoked 0x03 - reserved 0xFF - unavailable parameter
pUserAcknowledgementReq[OUT]	(optional parameter) • Returns the user (manual) acknowledgment request parameter TRUE - means the user is requested to manually acknowledge the delivery of the message. FALSE - means no such user acknowledgement is requested
pReadAcknowledgementReq[OUT]	(optional parameter) • Returns the read acknowledgement request parameter TRUE - means acknowledgment of the message being viewed is requested. FALSE - means no such read acknowledgement is requested
pAlertPriority[OUT]	(optional parameter) • Returns the alerting parameter setting 0x00 - use default alert 0x01 - use low priority alert 0x02 - use medium priority alert 0x03 - use high priority alert 0xFF - unavailable parameter
pCallbkAddrLength[OUT]	(optional parameter) • returns the length of Callback address string (including the NULL termination)
pCallbkAddr[OUT]	(optional parameter) • returns NULL-terminated ASCII String containing callback address String containing the Call Back number with a 32 maximum characters.

8.116.2 Field Documentation

8.116.2.1 sms_timestemp cdmaMsgDecodingParams::absoluteValidity

8.116.2.2 sms_timestemp cdmaMsgDecodingParams::mcTimeStamp

8.116.2.3 ULONG cdmaMsgDecodingParams::messageLength

8.116.2.4 BYTE* cdmaMsgDecodingParams::pAlertPriority

8.116.2.5 CHAR* cdmaMsgDecodingParams::pCallbkAddr

8.116.2.6 BYTE* cdmaMsgDecodingParams::pCallbkAddrLength

8.116.2.7 BYTE* cdmaMsgDecodingParams::pDisplayMode

8.116.2.8 BYTE* cdmaMsgDecodingParams::pLanguage

8.116.2.9 BYTE* cdmaMsgDecodingParams::pMessage

8.116.2.10 ULONG* cdmaMsgDecodingParams::pMessageID

8.116.2.11 BYTE* cdmaMsgDecodingParams::pPriority

8.116.2.12 BYTE* cdmaMsgDecodingParams::pPrivacy

8.116.2.13 BOOL* cdmaMsgDecodingParams::pReadAcknowledgementReq

8.116.2.14 BYTE* cdmaMsgDecodingParams::pRelativeValidity

8.116.2.15 BYTE* cdmaMsgDecodingParams::pSenderAddrLength

8.116.2.16 BYTE* cdmaMsgDecodingParams::pTextMsgLength

8.116.2.17 BOOL* cdmaMsgDecodingParams::pUserAcknowledgementReq

8.116.2.18 CHAR cdmaMsgDecodingParams::senderAddr[24+1]

8.116.2.19 USHORT cdmaMsgDecodingParams::textMsg[160+2]

8.117 cdmaMsgDecodingParamsExt Struct Reference

Data Fields

- ULONG messageLength
- BYTE * pMessage
- ULONG * pMessageID
- BYTE * pSenderAddrLength
- CHAR * pSenderAddr
- BYTE * pTextMsgLength
- WORD * pTextMsg
- BYTE * pPriority
- BYTE * pPrivacy
- BYTE * pLanguage
- sms_timestemp mcTimeStamp
- sms_timestemp absoluteValidity
- BYTE * pRelativeValidity
- BYTE * pDisplayMode
- BOOL * pUserAcknowledgementReq

- BOOL * pReadAcknowledgementReq
- BYTE * pAlertPriority
- BYTE * pCallbkAddrLength
- CHAR * pCallbkAddr
- USHORT * pReferenceNum
- BYTE * pTotalNum
- BYTE * pPartNum
- BOOL * pIsUDHPresent

8.117.1 Detailed Description

Structure contains parameters which need to be decoded from message

Parameters

messageLength[IN]	• Length of the message to be decoded in bytes
pMessage[IN]	• Message read off the device via GetSMS
pSenderAddrLength[IN/OUT]	• Upon input, indicates the maximum number of ASCII characters (including NULL termination) that the pSenderAddr buffer can accommodate. Note that a length of 14 is reasonable.Upon successful output, returns the length of originating address string (including the NULL termination)
pSenderAddr[OUT]	• Returns NULL-terminated ASCII String containing the originating address.International number will be prepended with a '+'character
pTextMsgLength[IN/OUT]	• Upon input, specifies the number of UCS2 characters the given text message buffer can accommodate.Upon successful output, returns the number of UCS2 characters returns in the given text messagebuffer(including NULL-terminator)
pTextMsg[OUT]	• Returns the text message as NULL-terminated UCS2 string
pPriority[OUT]	(optional parameter) • Returns the priority setting of the message 0x00 - normal 0x01 - interactive 0x02 - urgent 0x03 - emergency 0xFF - unavailable setting
pPrivacy[OUT](optional	parameter) • Returns the privacy setting of the message 0x00 - not restricted 0x01 - restricted 0x02 - confidential 0x03 - secret 0xFF - unavailable setting
pLanguage[OUT]	(optional parameter) • Returns the language setting of the message 0x00 - unspecified 0x01 - english 0x02 - french 0x03 - spanish 0x04 - japanese 0x05 - korean 0x06 - chinese 0x07 - hebrew 0xFF - unavailable setting

mcTimeStamp[8][OUT]	(optional parameter) • Returns the message center timestamp which takes the form: YYMMDDHHMMSSTZ where YY - year MM - month DD - day HH - hour MM - minute SS - second TZ - timezone All values are in decimal. Timezone is in relation to GMT, one unit is equal to 15 minutes and MSB indicates a negative value.If this information is unavailable for message then this field will be filled with 0xFF
absoluteValidity[8][OUT]	(optional parameter) • Returns the absolute validity period setting for this message.This field takes the same form as mcTimeStamp
pRelativeValidity[OUT]	(optional parameter) • Returns the relative validity period.Values have the following meanings: 0 to 143: validity period =(value + 1)∗ 5 minutes 144 to 167: validity period =12 hours+(value - 143)∗30 minutes 168 to 196: validity period = (value - 166) ∗ 1 day 197 to 244: validity period = (value - 192) ∗ 1 week 245: validity period = indefinite 246: validity period = immediate 247: validity period = valid until mobile becomes inactive 248: validity period = valid until registration area changes 249 to 254: reserved 255: unavailable information
pDisplayMode[OUT]	(optional parameter) • Returns the display mode parameter 0x00 - immediate display 0x01 - mobile default setting 0x02 - user invoked 0x03 - reserved 0xFF - unavailable parameter
pUserAcknowledgementReq[OUT]	(optional parameter) • Returns the user (manual) acknowledgment request parameter TRUE - means the user is requested to manually acknowledge the delivery of the message. FALSE - means no such user acknowledgement is requested
pReadAcknowledgementReq[OUT]	(optional parameter) • Returns the read acknowledgement request parameter TRUE - means acknowledgment of the message being viewed is requested. FALSE - means no such read acknowledgement is requested
pAlertPriority[OUT]	(optional parameter) • Returns the alerting parameter setting 0x00 - use default alert 0x01 - use low priority alert 0x02 - use medium priority alert 0x03 - use high priority alert 0xFF - unavailable parameter
pCallbkAddrLength[OUT]	(optional parameter) • returns the length of Callback address string (including the NULL termination)
pCallbkAddr[OUT]	(optional parameter) • returns NULL-terminated ASCII String containing callback address String containing the Call Back number with a 32 maximum characters.
pReferenceNum[OUT]	• Reference number of the sms
pTotalNum[OUT]	• Total number of the concatenated message
pPartNum[OUT]	• Sequence number of the current message

pIsUDHPresent	• Is User Data Header Present in the PDU? If yes, it means it is a • concatenated SMS.

8.117.2 Field Documentation

8.117.2.1 sms_timestemp cdmaMsgDecodingParamsExt::absoluteValidity

8.117.2.2 sms_timestemp cdmaMsgDecodingParamsExt::mcTimeStamp

8.117.2.3 ULONG cdmaMsgDecodingParamsExt::messageLength

8.117.2.4 BYTE* cdmaMsgDecodingParamsExt::pAlertPriority

8.117.2.5 CHAR* cdmaMsgDecodingParamsExt::pCallbkAddr

8.117.2.6 BYTE* cdmaMsgDecodingParamsExt::pCallbkAddrLength

8.117.2.7 BYTE* cdmaMsgDecodingParamsExt::pDisplayMode

8.117.2.8 BOOL* cdmaMsgDecodingParamsExt::pIsUDHPresent

8.117.2.9 BYTE* cdmaMsgDecodingParamsExt::pLanguage

8.117.2.10 BYTE* cdmaMsgDecodingParamsExt::pMessage

8.117.2.11 ULONG* cdmaMsgDecodingParamsExt::pMessageID

8.117.2.12 BYTE* cdmaMsgDecodingParamsExt::pPartNum

8.117.2.13 BYTE* cdmaMsgDecodingParamsExt::pPriority

8.117.2.14 BYTE* cdmaMsgDecodingParamsExt::pPrivacy

8.117.2.15 BOOL* cdmaMsgDecodingParamsExt::pReadAcknowledgementReq

8.117.2.16 USHORT* cdmaMsgDecodingParamsExt::pReferenceNum

8.117.2.17 BYTE* cdmaMsgDecodingParamsExt::pRelativeValidity

8.117.2.18 CHAR* cdmaMsgDecodingParamsExt::pSenderAddr

8.117.2.19 BYTE* cdmaMsgDecodingParamsExt::pSenderAddrLength

8.117.2.20 WORD* cdmaMsgDecodingParamsExt::pTextMsg

8.117.2.21 BYTE* cdmaMsgDecodingParamsExt::pTextMsgLength

8.117.2.22 BYTE* cdmaMsgDecodingParamsExt::pTotalNum

8.117.2.23 BOOL* cdmaMsgDecodingParamsExt::pUserAcknowledgementReq

8.118 cdmaMsgEncodingParams Struct Reference

Data Fields

- BYTE * pMessageSize
- BYTE * pMessage
- BYTE messageId
- CHAR * pDestAddr
- CHAR * pCallbackAddr
- ULONG textMsgLength
- WORD * pTextMsg
- BYTE * pPriority
- BYTE * pEncodingAlphabet
- BYTE * pRelValidity

8.118.1 Detailed Description

Structure contains parameters for message to be encoded

Parameters

pMessageSize[IN/OUT]	• Upon input, specifies the total number of bytes that the given pMessage buffer can hold (a buffer of length 240 is recommended).Upon successful output, specifies the length of the constructed message placed in the pMessage buffer (in bytes)
pMessage[OUT]	- The constructed raw message
messageId[IN]	• The message reference number for this message. This value should be incremented for every message the host application sends
pDestAddr[IN]	• Gives NULL-terminated ASCII String containing a destination address.International number will be prepended with a '+' character
pCallbackAddr[IN]	• Gives NULL-terminated ASCII String containing a callback address.International number will be prepended with a '+' character
textMsgLength[IN]	• Number of UCS2 characters in the text message(excluding NULL)
pTextMsg[IN]	• Text message to be encoded
pPriority[IN](optional	parameter) • Gives the priority of the outgoing message: 0 - normal (default if NULL pointer is given) 1 - interactive 2 - urgent 3 - emergency 64 - 64 is decoded value for URGENT VZAM Support interactive. 128 - 128 is decoded value for URGENT VZAM Support urgent. 192 - 128 is decoded value for URGENT VZAM Support emergency.

pEncoding-Alphabet[IN/OU-T](optional	parameter) • Upon input, specifies the alphabet the text message should be encoded in 0 - 8bit ASCII (not supported at this time) 1 - IS91EP (not supported at this time) 2 - 7bit ASCII (default if NULL pointer is given) 3 - IA5 (not supported at this time) 4 - unicode (not supported at this time) 5 - shift JIS (not supported at this time) 6 - korean (not supported at this time) 7 - latin hebrew (not supported at this time) 8 - latin (not supported at this time) 9 - GSM 7 bit default Upon successful output, specifies the alphabet used to encode the message.
pRelValidity[I-N](optional	parameter) • Gives the relative validity period of the outgoing message 0 - Set Relative validity to 11 1 - Set Relative validity to 71 2 - Set Relative validity to 167 3 - Set Relative validity to 169 4 - Set Relative validity to 171 Values have the following meanings: 0 to 143: validity period = (value + 1)∗ 5 minutes 144 to 167: validity period = 12 hours + (value - 143)∗30 minutes 168 to 196: validity period = (value - 166) ∗ 1 day 197 to 244: validity period = (value - 192) ∗ 1 week 245: validity period = indefinite

Currently only encoding of 7bit ASCII messages is supported.

8.118.2 Field Documentation

8.118.2.1 BYTE cdmaMsgEncodingParams::messageId

8.118.2.2 CHAR∗ cdmaMsgEncodingParams::pCallbackAddr

8.118.2.3 CHAR∗ cdmaMsgEncodingParams::pDestAddr

8.118.2.4 BYTE∗ cdmaMsgEncodingParams::pEncodingAlphabet

8.118.2.5 BYTE∗ cdmaMsgEncodingParams::pMessage

8.118.2.6 BYTE∗ cdmaMsgEncodingParams::pMessageSize

8.118.2.7 BYTE∗ cdmaMsgEncodingParams::pPriority

8.118.2.8 BYTE∗ cdmaMsgEncodingParams::pRelValidity

8.118.2.9 WORD∗ cdmaMsgEncodingParams::pTextMsg

8.118.2.10 ULONG cdmaMsgEncodingParams::textMsgLength

8.119 CDMARSSIThresh Struct Reference

Data Fields

- BYTE CDMARSSIThreshListLen
- WORD ∗ pCDMARSSIThreshList

8.119.1 Detailed Description

This structure contains CDMA RSSI threshold related parameters.

Parameters

CDMARSSI-ThreshListLen	• Length of the CDMARSSI threshold list parameter to follow
pCDMARSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • maximum of 32 values. • Range for RSSI values:-105 to -21 (in dBm).

8.119.2 Field Documentation

8.119.2.1 BYTE CDMARSSIThresh::CDMARSSIThreshListLen

8.119.2.2 WORD* CDMARSSIThresh::pCDMARSSIThreshList

8.120 cdmaSSInfo Struct Reference

Data Fields

- int8_t rssi
- int16_t ecio

8.120.1 Detailed Description

This structure contains the parameters for CDMA/WCDMA Signal Strength Information

Parameters

rssi	• RSSI in dBm (signed value). • A value of -125 dBm or lower is used to indicate No Signal.
ecio	• ECIO value representing negative 0.5 dBm increments, i.e., 2 means -1 dBm (14 means -7 dBm, 63 means -31.5 dBm).

8.120.2 Field Documentation

8.120.2.1 int16_t cdmaSSInfo::ecio

8.120.2.2 int8_t cdmaSSInfo::rssi

8.121 CDMASSInfo Struct Reference

Data Fields

- INT8 rssi
- SHORT ecio

8.121.1 Detailed Description

This structure contains the parameters for CDMA/WCDMA Signal Strength Information

Parameters

rssi	• RSSI in dBm (signed value). • A value of -125 dBm or lower is used to indicate No Signal.
ecio	• ECIO value representing negative 0.5 dBm increments, i.e., 2 means -1 dBm (14 means -7 dBm, 63 means -31.5 dBm).

8.121.2 Field Documentation

8.121.2.1 SHORT CDMASSInfo::ecio

8.121.2.2 INT8 CDMASSInfo::rssi

8.122 CDMASysInfo Struct Reference

Data Fields

- sysInfoCommon sysInfoCDMA
- BYTE isSysPrlMatchValid
- BYTE isSysPrlMatch
- BYTE pRevInUseValid
- BYTE pRevInUse
- BYTE bsPRevValid
- BYTE bsPRev
- BYTE ccsSupportedValid
- BYTE ccsSupported
- BYTE cdmaSysIdValid
- WORD systemID
- WORD networkID
- BYTE bsInfoValid
- WORD baseId
- ULONG baseLat
- ULONG baseLong
- BYTE packetZoneValid
- WORD packetZone
- BYTE networkIdValid
- BYTE MCC [3]
- BYTE MNC [3]

8.122.1 Detailed Description

Structure for storing the CDMA System Information.

Parameters

sysInfoCDMA	• See sysInfoCommon for more information.
isSysPrlMatch-Valid	• Indicates whether the system PRL match is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
isSysPrlMatch	• Indicates whether the system is in a PRL. • Only applies to CDMA/HDR. – 0x00 - System is not in a PRL – 0x01 - System is in a PRL – 0xFF - Not Available • If the system is not in a PRL, roam_status carries the value from the default roaming indicator in the PRL. • If the system is in a PRL, roam_status is set to the value based on the standard specification.
pRevInUseValid	• Indicates whether the P_Rev in use is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
pRevInUse	• The lesser of the base station P_Rev and mobile P_Rev • Only applicable for CDMA. – 0xFF - Not Available
bsPRevValid	• Indicates whether the base station P_Rev is valid – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
bsPRev	• Base station P_Rev. • Only applicable for CDMA. – 0xFF - Not Available
ccsSupported-Valid	• Indicates whether the supported concurrent service is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

ccsSupported	• Whether concurrent service is supported. • Only applicable for CDMA. – 0x00 - Not supported – 0x01 - Supported – 0xFF - Not Available
cdmaSysIdValid	• Indicates whether the CDMA system ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
systemID	• System ID. – 0xFFFF - Not Available
networkID	• Network ID. – 0xFFFF - Not Available
bsInfoValid	• Indicates whether the base station information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
baseLat	• Base station latitude in units of 0.25 sec. • Expressed as a two's complement signed number with positive numbers signifying North latitudes. – 0xFFFFFFFF - Not Available
baseLong	• Base station longitude in units of 0.25 sec. • Expressed as a two's complement signed number with positive numbers signifying East latitudes. – 0xFFFFFFFF - Not Available
packetZoneValid	• Indicates whether the packet zone is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
packetZone	• Packet zone (8-bit). – 0xFFFF indicates no packet zone. • Only applicable for CDMA.

networkIdValid	• Indicates whether the network ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
MCC[PLMN_LENGTH]	• Mobile Country Code. • MCC digits in ASCII characters • MCC wildcard value is returned as {'3', 0xFF, 0xFF}.
MNC[PLMN_LENGTH]	• Mobile Network Code. • MNC digits in ASCII characters • An unused byte is set to 0xFF. • MNC wildcard value is returned as {'7', 0xFF, 0xFF}.

8.122.2 Field Documentation

8.122.2.1 WORD CDMASysInfo::baseId

8.122.2.2 ULONG CDMASysInfo::baseLat

8.122.2.3 ULONG CDMASysInfo::baseLong

8.122.2.4 BYTE CDMASysInfo::bsInfoValid

8.122.2.5 BYTE CDMASysInfo::bsPRev

8.122.2.6 BYTE CDMASysInfo::bsPRevValid

8.122.2.7 BYTE CDMASysInfo::ccsSupported

8.122.2.8 BYTE CDMASysInfo::ccsSupportedValid

8.122.2.9 BYTE CDMASysInfo::cdmaSysIdValid

8.122.2.10 BYTE CDMASysInfo::isSysPrlMatch

8.122.2.11 BYTE CDMASysInfo::isSysPrlMatchValid

8.122.2.12 BYTE CDMASysInfo::MCC[3]

8.122.2.13 BYTE CDMASysInfo::MNC[3]

8.122.2.14 WORD CDMASysInfo::networkID

8.122.2.15 BYTE CDMASysInfo::networkIdValid

8.122.2.16 WORD CDMASysInfo::packetZone

8.122.2.17 BYTE CDMASysInfo::packetZoneValid

8.122.2.18 BYTE CDMASysInfo::pRevInUse

8.122.2.19 BYTE CDMASysInfo::pRevInUseValid

8.122.2.20 sysInfoCommon CDMASysInfo::sysInfoCDMA

8.122.2.21 WORD CDMASysInfo::systemID

8.123 CDMASysInfoExt Struct Reference

Data Fields

- WORD MCC
- BYTE imsi_11_12

8.123.1 Detailed Description

This structure contains CDMA system information extension

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

MCC	• Mobile Country Code
imsi_11_12	• IMSI_11_12

8.123.2 Field Documentation

8.123.2.1 BYTE CDMASysInfoExt::imsi_11_12

8.123.2.2 WORD CDMASysInfoExt::MCC

8.124 CellDb Struct Reference

Data Fields

- ULONG mask

8.124.1 Detailed Description

This structure contains the cell database

Parameters

mask	• Mask for the cell database assistance data that is to be deleted • Valid values: – 0x00000001 - DELETE_CELLDB_POS – 0x00000002 - DELETE_CELLDB_LATEST_GPS_POS – 0x00000004 - DELETE_CELLDB_OTA_POS – 0x00000008 - DELETE_CELLDB_EXT_REF_POS – 0x00000010 - DELETE_CELLDB_TIMETAG – 0x00000020 - DELETE_CELLDB_CELLID – 0x00000040 - DELETE_CELLDB_CACHED_CELLID – 0x00000080 - DELETE_CELLDB_LAST_SRV_CELL – 0x00000100 - DELETE_CELLDB_CUR_SRV_CELL – 0x00000200 - DELETE_CELLDB_NEIGHBOR_INFO

8.124.2 Field Documentation

8.124.2.1 ULONG CellDb::mask

8.125 cellParams Struct Reference

Data Fields

- WORD pci
- SHORT rsrq
- SHORT rsrp
- SHORT rssi
- SHORT srxlev

8.125.1 Detailed Description

This structure contains information about the Cell parameters.

Parameters

pci	• Physical cell ID. • Range: 0 to 503.
rsrq	• Current RSRQ in 1/10 dB as measured by L1. • Range: -20.0 dB to -3.0 dB.
rsrp	• Current RSRP in 1/10 dBm as measured by L1. • Range: -140.0 dBm to -44.0 dBm.
rssi	• Current RSSI in 1/10 dBm as measured by L1. • Range: -120.0 dBm to 0.

srxlev	• Cell selection Rx level (Srxlev) value. • Range: -128 to 128. • This field is only valid when ue_in_idle is TRUE.

8.125.2 Field Documentation

8.125.2.1 WORD cellParams::pci

8.125.2.2 SHORT cellParams::rsrp

8.125.2.3 SHORT cellParams::rsrq

8.125.2.4 SHORT cellParams::rssi

8.125.2.5 SHORT cellParams::srxlev

8.126 changeUIMPIN Struct Reference

Data Fields

- BYTE pinID
- BYTE oldPINLen
- BYTE oldPINVal [255]
- BYTE pinLen
- BYTE pinVal [255]

8.126.1 Detailed Description

This structure contains the information about the pin parameters that need to be verified.

Parameters

pinID	• Indicates the PIN ID to be changed. – 1 - PIN1 (also called PIN) – 2 - PIN2 – 3 - Universal PIN – 4 - Hidden key
oldPINLen	• Length of the following elements i.e. old pin value.
oldPINVal[MAX_DESCRIPTION_LENGTH]	• Old PIN value. • This value is a sequence of ASCII characters.
pinLen	• Length of the following elements i.e. new pin value.

pinVal[MAX_DESCRIPTION_LENGTH]	• New PIN value. • This value is a sequence of ASCII characters.

8.126.2 Field Documentation

8.126.2.1 BYTE changeUIMPIN::oldPINLen

8.126.2.2 BYTE changeUIMPIN::oldPINVal[255]

8.126.2.3 BYTE changeUIMPIN::pinID

8.126.2.4 BYTE changeUIMPIN::pinLen

8.126.2.5 BYTE changeUIMPIN::pinVal[255]

8.127 ChannelRate Struct Reference

Data Fields

- ULONG CurrChanTxRate
- ULONG CurrChanRxRate
- ULONG MaxChanTxRate
- ULONG MaxChanRxRate

8.127.1 Detailed Description

This structure contains Channel Rate

Parameters

CurrChanTxRate	• Instantaneous channel Tx rate in bits per second
CurrChanRxRate	• Instantaneous channel Rx rate in bits per second
MaxChanTxRate	• maximum Tx rate that can be assigned to the device by the serving system in bits per second
MaxChanRxRate	• maximum Rx rate that can be assigned to the device by the serving system in bits per second

8.127.2 Field Documentation

8.127.2.1 ULONG ChannelRate::CurrChanRxRate

8.127.2.2 ULONG ChannelRate::CurrChanTxRate

8.127.2.3 ULONG ChannelRate::MaxChanRxRate

8.127.2.4 ULONG ChannelRate::MaxChanTxRate

8.128 channelRate Struct Reference

Data Fields

- ULONG CurrChanTxRate
- ULONG CurrChanRxRate

8.128.1 Detailed Description

This structure contains Channel Rate

Parameters

CurrChanTxRate	• Max channel Tx rate in bits per second
CurrChanRx-Rate	• Max channel Rx rate in bits per second

8.128.2 Field Documentation

8.128.2.1 ULONG channelRate::CurrChanRxRate

8.128.2.2 ULONG channelRate::CurrChanTxRate

8.129 ciotAcqOrderPref Struct Reference

Data Fields

- BYTE ciotAcqOrderLen
- ULONG * pCiotAcqOrder

8.129.1 Detailed Description

Contain the CIOT Acquisition Order Preference.

Parameters

ciotAcqOrderLen	• Number of sets of the following elements.
pCiotAcqOrder	• CIOT Acquisition order preference to be set. • Values – 0x01 - cdma2000 ®1X – 0x02 - cdma2000 ® HRPD (1xEV-DO) – 0x04 - GSM – 0x05 - UMTS – 0x08 - LTE – 0x09 - TD-SCDMA – 0x0a - LTE_M1 – 0x0b - LTE_NB1

8.129.2 Field Documentation

8.129.2.1 BYTE ciotAcqOrderPref::ciotAcqOrderLen

8.129.2.2 ULONG* ciotAcqOrderPref::pCiotAcqOrder

8.130 CiotAcqOrderPrefTlv Struct Reference

Data Fields

- BYTE ciotAcqOrderLen
- ULONG * pCiotAcqOrder
- BYTE TlvPresent

8.130.1 Detailed Description

Contain the CIOT Acquisition Order Preference.

Parameters

ciotAcqOrderLen	• Number of sets of the following elements.
pCiotAcqOrder	• CIOT Acquisition order preference to be set. • Values – 0x01 - cdma2000 ®1X – 0x02 - cdma2000 ® HRPD (1xEV-DO) – 0x04 - GSM – 0x05 - UMTS – 0x08 - LTE – 0x09 - TD-SCDMA – 0x0a - LTE_M1 – 0x0b - LTE_NB1

TlvPresent	• Tlv Present

8.130.2 Field Documentation

8.130.2.1 BYTE CiotAcqOrderPrefTlv::ciotAcqOrderLen

8.130.2.2 ULONG* CiotAcqOrderPrefTlv::pCiotAcqOrder

8.130.2.3 BYTE CiotAcqOrderPrefTlv::TlvPresent

8.131 CiotLteOpModePrefTlv Struct Reference

Data Fields

- ULONGLONG ciotLteOpModePref
- BYTE TlvPresent

8.131.1 Detailed Description

Contain the CIOT LTE Operational Mode Preference.

Parameters

ciotLteOpMode-Pref	• CIOT LTE Operational Mode Preference • Values: – Bit 0 (0x01) - LTE wideband – Bit 1 (0x02) - LTE M1 – Bit 2 (0x04) - LTE NB1 All unlisted bits are reserved for future use and the service point ignores them if used.
TlvPresent	• Tlv Present

8.131.2 Field Documentation

8.131.2.1 ULONGLONG CiotLteOpModePrefTlv::ciotLteOpModePref

8.131.2.2 BYTE CiotLteOpModePrefTlv::TlvPresent

8.132 CLIPResp Struct Reference

Data Fields

- BYTE ActiveStatus
- BYTE ProvisionStatus

8.132.1 Detailed Description

This structure contains information about the Calling Line Identification Presentation (CLIP) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available
ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED - Provisioned – 0xFF - Not Available

8.132.2 Field Documentation

8.132.2.1 BYTE CLIPResp::ActiveStatus

8.132.2.2 BYTE CLIPResp::ProvisionStatus

8.133 CLIRResp Struct Reference

Data Fields

- BYTE ActiveStatus
- BYTE ProvisionStatus

8.133.1 Detailed Description

This structure contains information about the Calling Line Identification Restriction (CLIR) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available

ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED_PERMANENT - Permanently provisioned – 0x02 - PROVISION_STATUS_PRESENTATION_RESTRICTED - Restricted presentation – 0x03 - PROVISION_STATUS_PRESENTATION_ALLOWED - Allowed presentation – 0xFF - Not Available

8.133.2 Field Documentation

8.133.2.1 BYTE CLIRResp::ActiveStatus

8.133.2.2 BYTE CLIRResp::ProvisionStatus

8.134 ClkInfo Struct Reference

Data Fields

- ULONG mask

8.134.1 Detailed Description

This structure contains the clock Info

Parameters

mask	• Mask for the clock information assistance data that is to be deleted • Valid bitmasks: – QMI_LOC_MASK_DELETE_CLOCK_INFO_TIME_EST (0x00000001) - Mask to delete time estimate from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_FREQ_EST (0x00000002) - Mask to delete frequency estimate from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_WEEK_NUMBER (0x00000004) - Mask to delete week number from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_RTC_TIME (0x00000008) - Mask to delete RTC time from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_TIME_TRANSFER (0x00000010) - Mask to delete time transfer from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GPSTIME_EST (0x00000020) - Mask to delete GPS time estimate from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GLOTIME_EST (0x00000040) - Mask to delete GLONASS time estimate from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GLODAY_NUMBER (0x00000080) - Mask to delete GLONASS day number from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GLO4YEAR_NUMBER (0x00000100) - Mask to delete GLONASS four year number from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GLO_RF_GRP_DELAY (0x00000200) - Mask to delete GLONASS RF GRP delay from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_DISABLE_TT (0x00000400) - Mask to delete disable TT from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GG_LEAPSEC (0x00000800) - Mask to delete a BDS time estimate from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GG_GGTB (0x00001000) - Mask to delete a BDS time estimate from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_BDSTIME_EST (0x00002000) - Mask to delete a BDS time estimate from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GB_GBTB (0x00004000) - Mask to delete Glonass-to-BDS time bias-related information from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_BG_BGTB (0x00008000) - Mask to delete BDS-to-GLONASS time bias-related information from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_BDSWEEK_NUMBER (0x00010000) - Mask to delete the BDS week number from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_BDS_RF_GRP_DELAY (0x00020000) - Mask to delete the BDS RF GRP delay from the clock information

8.134.2 Field Documentation

8.134.2.1 ULONG ClkInfo::mask

8.135 CNAPResp Struct Reference

Data Fields

- BYTE ActiveStatus
- BYTE ProvisionStatus

8.135.1 Detailed Description

This structure contains information about the Calling Name Presentation (CNAP) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available
ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED - Provisioned – 0xFF - Not Available

8.135.2 Field Documentation

8.135.2.1 BYTE CNAPResp::ActiveStatus

8.135.2.2 BYTE CNAPResp::ProvisionStatus

8.136 COLPResp Struct Reference

Data Fields

- BYTE ActiveStatus
- BYTE ProvisionStatus

8.136.1 Detailed Description

This structure contains information about the Connected Line Identification Presentation (COLP) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available

ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED - Provisioned – 0xFF - Not Available

8.136.2 Field Documentation

8.136.2.1 BYTE COLPResp::ActiveStatus

8.136.2.2 BYTE COLPResp::ProvisionStatus

8.137 COLRResp Struct Reference

Data Fields

- BYTE ActiveStatus
- BYTE ProvisionStatus

8.137.1 Detailed Description

This structure contains information about the Connected Line Identification Restriction (COLR) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available
ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED - Provisioned – 0xFF - Not Available

8.137.2 Field Documentation

8.137.2.1 BYTE COLRResp::ActiveStatus

8.137.2.2 BYTE COLRResp::ProvisionStatus

8.138 CommInfo Struct Reference

Data Fields

- INT8 temperature
- BYTE modemMode
- BYTE systemMode
- BYTE imsRegState
- BYTE psState

8.138.1 Detailed Description

Structure for storing the common information for the device.

Parameters

temperature	• Temperature. – 8-bit signed integer – 0xFF - Not Available.
modemMode	• Modem Operating Mode. – 0x00 - POWERING OFF – 0x01 - FACTORY TEST – 0x02 - OFFLINE – 0x03 - OFFLINE_AMPS – 0x04 - OFFLINE_CDMA – 0x05 - ONLINE – 0x06 - LOW POWER MODE – 0x07 - RESETTING – 0x08 - NETWORK TEST – 0x09 - OFFLINE REQUEST – 0x0A - PSEUDO ONLINE – 0x0B - RESETTING MODEM – 0xFF - Unknown
systemMode	• System Acquisition Mode. – 0x00 - No service – 0x01 - AMPS – 0x02 - CDMA – 0x03 - GSM – 0x04 - HDR – 0x05 - WCDMA – 0x06 - GPS – 0x08 - WLAN – 0x09 - LTE – 0xFF - Unknown

imsRegState	• IMS Registration State. – 0x00 - NO SRV – 0x01 - IN PROG – 0x02 - FAILED – 0x03 - LIMITED – 0x04 - FULL SRV – 0xFF - Unknown
psState	• PS Attach State. – 0x00 - Attached – 0x01 - Detached – 0xFF - Unknown

8.138.2 Field Documentation

8.138.2.1 BYTE CommInfo::imsRegState

8.138.2.2 BYTE CommInfo::modemMode

8.138.2.3 BYTE CommInfo::psState

8.138.2.4 BYTE CommInfo::systemMode

8.138.2.5 INT8 CommInfo::temperature

8.139 connectionStatus Struct Reference

Data Fields

- uint8_t MDMConnStatus
- uint64_t MDMCallDuration

8.139.1 Detailed Description

This structure contains modem connection status

Parameters

MDMConn-Status	• Current link status – 0x01 - DISCONNECTED – 0x02 - CONNECTED – 0xff - Invalid data.

MDMCall-Duration	• Call duration in milliseconds. • If the modem connection status is connected, this represent the duration of the current DUN call. • If the modem connection status is disconnected, this represents the duration of the last DUN call since the device was powered up (zero, if no call has been made or if the last call was not DUN). – 0xffffffffffffffff - Invalid data.

8.139.2 Field Documentation

8.139.2.1 uint64_t connectionStatus::MDMCallDuration

8.139.2.2 uint8_t connectionStatus::MDMConnStatus

8.140 ConnectionStatus Struct Reference

Data Fields

- BYTE MDMConnStatus
- ULONGLONG MDMCallDuration

8.140.1 Detailed Description

This structure contains modem connection status

Parameters

MDMConn-Status	• Current link status – 0x01 - DISCONNECTED – 0x02 - CONNECTED
MDMCall-Duration	• Call duration in milliseconds. • If the modem connection status is connected, this represent the duration of the current DUN call. • If the modem connection status is disconnected, this represents the duration of the last DUN call since the device was powered up (zero, if no call has been made or if the last call was not DUN).

8.140.2 Field Documentation

8.140.2.1 ULONGLONG ConnectionStatus::MDMCallDuration

8.140.2.2 BYTE ConnectionStatus::MDMConnStatus

8.141 connectNumInfo Struct Reference

Data Fields

- BYTE numPresInd
- BYTE screeningInd
- BYTE numType
- BYTE numPlan
- BYTE callerIDLen
- BYTE callerID [81]

8.141.1 Detailed Description

This structure contains information about the numbers connected to a device. It contains information such as number type, eg International or Local.

Parameters

numPresInd	• Presentation indicator – 0x00 - PRESENTATION_ALLOWED - Allowed presentation – 0x01 - PRESENTATION_RESTRICTED - Restricted presentation – 0x02 - PRESENTATION_NUM_UNAVAILABLE - Unavailable presentation – 0x04 - PRESENTATION_PAYPHONE - Payphone presentation (GSM/UMTS specific) – 0xFF - Not Available
screeningInd	• Screening indicator. – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network – 0xFF - Not Available
numType	• Number type. – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension – 0xFF - Not Available

numPlan	• Number plan. – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension – 0xFF - Not Available
callerIDLen	• Provides the length of caller ID which follow. • If zero(0) then no further information exists.
callerID[MAX_CALL_NO_LEN]	• callerID of numLen length, NULL terminated.

8.141.2 Field Documentation

8.141.2.1 BYTE connectNumInfo::callerID[81]

8.141.2.2 BYTE connectNumInfo::callerIDLen

8.141.2.3 BYTE connectNumInfo::numPlan

8.141.2.4 BYTE connectNumInfo::numPresInd

8.141.2.5 BYTE connectNumInfo::numType

8.141.2.6 BYTE connectNumInfo::screeningInd

8.142 CrashInfo Struct Reference

Data Fields

- WORD numCrashes
- ULONG crashId
- ULONG crashData
- WORD crashStrLen
- CHAR * pCrashString
- WORD gcDumpStrLen
- CHAR * pGCDumpString

8.142.1 Detailed Description

This structure is used to store Crash Information

Parameters

numCrashes[OUT]	• Number of instances of the remaining fields
crashId[OUT]	• Random crash id assigned at crash
crashData[OUT]	• Crash Data
crashStrLen[IN/OUT]	• Length of pCrashString as an INPUT, length of the pCrashString field returned by API as an OUTPUT
pCrashString[OUT]	• Pointer to store crash string
gcDumpStrLen[IN/OUT]	• Length of pGCDumpString as an INPUT, Length of the pGCDumpString field returned by API as an OUTPUT
pGCDumpString[OUT]	• gcdump string for the crash

8.142.2 Field Documentation

8.142.2.1 ULONG CrashInfo::crashData

8.142.2.2 ULONG CrashInfo::crashId

8.142.2.3 WORD CrashInfo::crashStrLen

8.142.2.4 WORD CrashInfo::gcDumpStrLen

8.142.2.5 WORD CrashInfo::numCrashes

8.142.2.6 CHAR* CrashInfo::pCrashString

8.142.2.7 CHAR* CrashInfo::pGCDumpString

8.143 CrashInfoParams Struct Reference

Data Fields

- BYTE * pDevCrashStatus
- CrashInfo * pCrashInfo

8.143.1 Detailed Description

This structure is used to store Crash Information

Parameters

pDevCrashStatus[OUT]	• Device Crash Status • 0 - no crash • 1 - crash has occurred
pCrashInfo[OUT]	• Pointer to structure CrashInfo (Optional parameter) • See CrashInfo for more information

8.143.2 Field Documentation

8.143.2.1 CrashInfo* CrashInfoParams::pCrashInfo

8.143.2.2 BYTE* CrashInfoParams::pDevCrashStatus

8.144 crashInfoParams Struct Reference

Data Fields

- uint8_t crashStatus
- crashInformation crashInfo

8.144.1 Detailed Description

This structure contains crash information parameters

Parameters

crashStatus[OUT]	• Device Crash Status • 0 - no crash • 1 - crash has occurred
crashInfo[OUT]	• See crashInformation

8.144.2 Field Documentation

8.144.2.1 crashInformation crashInfoParams::crashInfo

8.144.2.2 uint8_t crashInfoParams::crashStatus

8.145 crashInformation Struct Reference

Data Fields

- uint16_t numCrashes
- uint32_t crashId
- uint32_t crashData

- uint16_t crashStrlen
- char crashString [255]
- uint16_t gcdumpStrlen
- char gcdumpString [1024]

8.145.1 Detailed Description

This structure contains crash information

Parameters

numCrashes[OUT]	• number of instances of the remaining fields
crashId[OUT]	• ramdom crash id assigned at crash
crashData	• crash data[OUT]
crashStrlen[IN/OUT]	• length of the crashString field as an input, length of the crashString field returned by API as an OUTPUT
crashString	• crash string
gcdumpStrlen[OUT]	• length of the gcdumpString field as an input, length of the gcdumpString field returned by API as an OUTPUT
gcdumpString[OUT]	• gcdump string for the crash

8.145.2 Field Documentation

8.145.2.1 uint32_t crashInformation::crashData

8.145.2.2 uint32_t crashInformation::crashId

8.145.2.3 char crashInformation::crashString[255]

8.145.2.4 uint16_t crashInformation::crashStrlen

8.145.2.5 char crashInformation::gcdumpString[1024]

8.145.2.6 uint16_t crashInformation::gcdumpStrlen

8.145.2.7 uint16_t crashInformation::numCrashes

8.146 CreateProfileIn Struct Reference

Data Fields

- BYTE * pProfileID
- BYTE * pProfileType
- QmiProfileInfo curProfile

8.146.1 Detailed Description

This structure contains the input parameters for SLQSCreateProfile

Parameters

ProfileID	• 1 to 16 for 3GPP profile (EM/MC73xx or earlier) • 1 to 24 for 3GPP profile (EM/MC74xx onwards) • 101 to 106 for 3GPP2 profile
ProfileType	• Identifies the technology type of the profile – 0x00 - 3GPP – 0x01 - 3GPP2 – NULL is not allowed
curProfile	• union of Profile3GPP and Profile3GPP2

Note

- If profileID is NULL, 3GPP profile will be created and index will be assigned based on availability in device.
- If profileID is not NULL depending on pProfileType 3GPP/3GPP2 relevant profile will be created

8.146.2 Field Documentation

8.146.2.1 QmiProfileInfo CreateProfileIn::curProfile

8.146.2.2 BYTE* CreateProfileIn::pProfileID

8.146.2.3 BYTE* CreateProfileIn::pProfileType

8.147 CreateProfileOut Struct Reference

Data Fields

- BYTE * pProfileType
- BYTE * pProfileIndex
- USHORT * pExtErrorCode

8.147.1 Detailed Description

structure contains out parameter Information

Parameters

profileType	• Identifies the type of profile 0x00 = 3GPP 0x01 = 3GPP2
profileIndex	• Index identifying the profile that was created
pExtErrorCode	• The extended error code received from DS Profile subsystem

8.147.2 Field Documentation

8.147.2.1 USHORT* CreateProfileOut::pExtErrorCode

8.147.2.2 BYTE* CreateProfileOut::pProfileIndex

8.147.2.3 BYTE* CreateProfileOut::pProfileType

8.148 CsgId Struct Reference

Data Fields

- ULONG csgId
- BYTE TlvPresent

8.148.1 Detailed Description

This structure contains csg ID.

Parameters

csgId	• Closed subscriber group identifier.
TlvPresent	• Tlv Present or not

8.148.2 Field Documentation

8.148.2.1 ULONG CsgId::csgId

8.148.2.2 BYTE CsgId::TlvPresent

8.149 CSGID Struct Reference

Data Fields

- WORD mcc
- WORD mnc
- BYTE mncPcsDigits

- ULONG id
- BYTE rat

8.149.1 Detailed Description

Contain the CSGID.

Parameters

mcc	• MCC value. Range 0 to 999
mnc	• MNC value. Range 0 to 999
mncPcsDigits	• TRUE - MNC is a three-digit value; e.g., a reported value of 90 corresponds to an MNC value of 090 • FALSE - MNC is a two-digit value; e.g., a reported value of 90 corresponds to an MNC value of 90
id	• Closed subscriber group identifier.
rat	• Radio interface technology of the CSG network. Values: – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS – 0x08 - RADIO_IF_LTE - LTE – 0x09 - RADIO_IF_TDSCDMA - TDS

8.149.2 Field Documentation

8.149.2.1 ULONG CSGID::id

8.149.2.2 WORD CSGID::mcc

8.149.2.3 WORD CSGID::mnc

8.149.2.4 BYTE CSGID::mncPcsDigits

8.149.2.5 BYTE CSGID::rat

8.150 CUGInfo Struct Reference

Data Fields

- WORD CUGIndex
- BYTE SuppPrefCUG
- BYTE SuppOA

8.150.1 Detailed Description

This structure contains Closed User Group Information

Parameters

CUGIndex	• Range 0x00... 0x7FFF
SuppPrefCUG	• Suppress preferential CUG – 0x00 - FALSE – 0x01 - TRUE
SuppOA	• Suppress OA subscription option – 0x00 - FALSE – 0x01 - TRUE

8.150.2 Field Documentation

8.150.2.1 WORD CUGInfo::CUGIndex

8.150.2.2 BYTE CUGInfo::SuppOA

8.150.2.3 BYTE CUGInfo::SuppPrefCUG

8.151 curAMRConfig Struct Reference

Data Fields

- BYTE gsmAmrStat
- BYTE wcdmaAmrStat

8.151.1 Detailed Description

This structure contains the Current Adaptive Multi Rate Configuration Information.

Parameters

gsmAmrStat	• GSM AMR Status – 0x00 - Disable – 0x01 - Enable – 0xFF - Not Available
wcdmaAmrStat	• WCDMA AMR Status • One or a combination of the following bitmask values: – Bit 0 - AMR codec advertised is not supported – Bit 1 - Controls WCDMA AMR wideband – Bit 2 - Controls GSM half rate AMR – Bit 3 - Controls GSM AMR wideband – Bit 4 - Controls GSM AMR narrowband • 0xFF, if not available

8.151.2 Field Documentation

8.151.2.1 BYTE curAMRConfig::gsmAmrStat

8.151.2.2 BYTE curAMRConfig::wcdmaAmrStat

8.152 CurrDataSysStat Struct Reference

Data Fields

- BYTE * pPrefNetwork
- BYTE * pNetworkInfoLen
- CurrNetworkInfo * pCurrNetworkInfo

8.152.1 Detailed Description

Data System Status

Parameters

pPrefNetwork	[OUT] • Preferred Network • Values: – 0 - 3GPP – 1 - 3GPP2
pNetworkInfoLen	[IN/OUT] • As input parameter size assigned to next parameter i.e. network information • As output the actual number of network information elements returned by the device
pCurrNetwork-Info	[OUT] • Network information • See CurrNetworkInfo for more details

8.152.2 Field Documentation

8.152.2.1 CurrNetworkInfo* CurrDataSysStat::pCurrNetworkInfo

8.152.2.2 BYTE* CurrDataSysStat::pNetworkInfoLen

8.152.2.3 BYTE* CurrDataSysStat::pPrefNetwork

8.153 currentCatEvent Union Reference

Data Fields

- struct CatEventIDDataTlv CatEvIDData
- struct CatAlPhaIdentifierTlv CatAlphaIdtfr
- struct CatEventListTlv CatEventLst
- struct CatRefreshTlv CatRefresh
- struct CatEndProactiveSessionTlv CatEndPS

8.153.1 Detailed Description

Union used to represent the current CAT Event Data. Choose the structure based on the EventID received.

- Use CatEventIDDataTlv if the Event ID is any of the below.
  - 16
  - 17
  - 18
  - 19
  - 20
  - 23
  - 24
- Use CatAlPhaIdentifierTlv if the Event ID is 21
- Use CatEventListTlv if the Event ID is 22
- Use CatRefreshTlv if the Event ID is 25
- Use CatEndProactiveSessionTlv if the Event ID is 26

8.153.2 Field Documentation

8.153.2.1 struct CatAlPhaIdentifierTlv currentCatEvent::CatAlphaIdtfr

8.153.2.2 struct CatEndProactiveSessionTlv currentCatEvent::CatEndPS

8.153.2.3 struct CatEventListTlv currentCatEvent::CatEventLst

8.153.2.4 struct CatEventIDDataTlv currentCatEvent::CatEvIDData

8.153.2.5 struct CatRefreshTlv currentCatEvent::CatRefresh

8.154 CurrentImgList Struct Reference

Data Fields

- BYTE numEntries
- CurrImageInfo * pCurrImgInfo
- CHAR priver [16]
- CHAR pkgver [16]
- CHAR fwvers [16]
- CHAR carrier [16]

8.154.1 Detailed Description

This structure is used to store image list

Parameters

numEntries[IN/-OUT]	• Number of entries in the image list to follow • The size of the list pCurrImgInfo must be specified when calling the API
pCurrImgInfo[O-UT]	• Currently Active Image List
priver[OUT]	• PRI version of the currently running firmware
pkgver[OUT]	• Package version of the currently running firmware
fwvers[OUT]	• firmware version of the currently running firmware
carrier[OUT]	• Carrier string of the currently running firmware

8.154.2 Field Documentation

8.154.2.1 CHAR CurrentImgList::carrier[16]

8.154.2.2 CHAR CurrentImgList::fwvers[16]

8.154.2.3 BYTE CurrentImgList::numEntries

8.154.2.4 CurrImageInfo* CurrentImgList::pCurrImgInfo

8.154.2.5 CHAR CurrentImgList::pkgver[16]

8.154.2.6 CHAR CurrentImgList::priver[16]

8.155 currentPLMN Struct Reference

Data Fields

- WORD MCC

- WORD MNC
- BYTE netDescrLength
- BYTE netDescr [255]

8.155.1 Detailed Description

This structure contains the current PLMN parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

MCC	• mobile country code – A 16 bit representation of MCC – Range 0 to 999
MNC	• mobile network code – A 16 bit representation of MNC – Range 0 to 999
netDescrLength	• Length of Network description field • Defaults to zero
netDescr	• Network Description – optional string containing network name or description

8.155.2 Field Documentation

8.155.2.1 WORD currentPLMN::MCC

8.155.2.2 WORD currentPLMN::MNC

8.155.2.3 BYTE currentPLMN::netDescr[255]

8.155.2.4 BYTE currentPLMN::netDescrLength

8.156 CurrImageInfo Struct Reference

Data Fields

- BYTE imageType
- BYTE uniqueID [16]
- BYTE buildIDLen
- BYTE buildID [255]

8.156.1 Detailed Description

This structure is used to store image information

Parameters

imageType[OUT]	• Image Type • Values: – 0 - FW – 1 - configuration
uniqueID[OUT]	• Image Unique Identifier (ASCII characters)
buildIDLen[OUT]	• Length of build ID string to follow • If set to zero, build ID string will be blank
buildID[OUT]	• String containing image information(ASCII characters) • Maximum length of this string is 255 chars

8.156.2 Field Documentation

8.156.2.1 BYTE CurrImageInfo::buildID[255]

8.156.2.2 BYTE CurrImageInfo::buildIDLen

8.156.2.3 BYTE CurrImageInfo::imageType

8.156.2.4 BYTE CurrImageInfo::uniqueID[16]

8.157 CurrNetworkInfo Struct Reference

Data Fields

- BYTE NetworkType
- ULONG RATMask
- ULONG SOMask

8.157.1 Detailed Description

Network information structure

Parameters

NetworkType	• Values: – 0 - 3GPP – 1 - 3GPP2

RATMask	• Radio Access Technology (RAT) mask to indicate the type of technology. • Values: – 0 - Don't Care – 0x8000 - NULL Bearer • CDMA RAT mask values: – 0x01 - CDMA_1x – 0x02 - EVDO_REV0 – 0x04 - EVDO_REVA – 0x08 - EVDO_REVB – 0x10 - EHRPD – 0x20 - FMC • UMTS RAT mask values: – 0x01 - WCDMA – 0x02 - GPRS – 0x04 - HSDPA – 0x08 - HSUPA – 0x10 - EDGE – 0x20 - LTE – 0x40 - HSDPA+ – 0x80 - DC_HSDPA+ – 0x100 - 64_QAM – 0x200 - TDSCDMA
SOMask	• Service Option (SO) mask to indicate the service option or type of application. • Values: – 0 - Don't Care • CDMA 1x SO mask values: – 0x01 - CDMA_1X_IS95 – 0x02 - CDMA_1X_IS2000 – 0x04 - CDMA_1X_IS2000_REL_A • CDMA EV-DO Rev 0 SO mask values: – 0x01 - DPA • CDMA EV-DO Rev A SO mask values: – 0x01 - DPA – 0x02 - MFPA – 0x04 - EMPA – 0x08 - EMPA_EHRPD • CDMA EV-DO Rev B SO mask values: – 0x01 - DPA – 0x02 - MFPA – 0x04 - EMPA – 0x08 - EMPA_EHRPD – 0x10 - MMPA – 0x20 - MMPA_EHRPD

8.157.2 Field Documentation

8.157.2.1 BYTE CurrNetworkInfo::NetworkType

8.157.2.2 ULONG CurrNetworkInfo::RATMask

8.157.2.3 ULONG CurrNetworkInfo::SOMask

8.158 currNetworkInfo Struct Reference

Data Fields

- uint8_t NetworkType
- uint32_t RATMask
- uint32_t SOMask

8.158.1 Detailed Description

Network information structure

Parameters

NetworkType	• Values: – 0 - 3GPP – 1 - 3GPP2
RATMask	RAT Mask
SOMask	SO Mask

8.158.2 Field Documentation

8.158.2.1 uint8_t currNetworkInfo::NetworkType

8.158.2.2 uint32_t currNetworkInfo::RATMask

8.158.2.3 uint32_t currNetworkInfo::SOMask

8.159 custFeaturesInfo Struct Reference

Data Fields

- ULONG GpsEnable
- BYTE * pDisableIMSI
- WORD * pIPFamSupport
- BYTE * pRMAutoConnect
- BYTE * pGPSSel
- BYTE * pSMSSupport
- BYTE * pIsVoiceEnabled
- BYTE * pDHCPRelayEnabled
- BYTE * pGPSLPM

8.159.1 Detailed Description

This structure contains current settings of custom features

Parameters

GpsEnable[OUT]	• describes if GPS is enabled or disabled • values: – 0x00 - GPS is disabled – 0x01 - GPS is enabled • function SLQSGetCustFeatures() returns a default value FFFFFFFF if no value is returned by the modem
pDisableIMSI[OUT]	• optional 1 byte parameter • describes if IMSI display is enabled or disabled • values: – 0x00 - Allow display of IMSI – 0x01 - Do not display IMSI • function SLQSGetCustFeatures() returns a default value FF if no value is returned by the modem
pIPFamSupport[OUT]	• optional 2 byte BitMask • bitmask representing the IP families supported • values: – 0x01 - IPv4 – 0x02 - IPv6 – 0x04 - IPv4v6 • function SLQSGetCustFeatures() returns a default value FFFF if no value is returned by the modem
pRMAutoConnect[OUT]	• optional 1 byte parameter • QMI Mode RM Net Auto Connect Support • values: – 0x00 - Not Supported – 0x01 - Supported • function SLQSGetCustFeatures() returns a default value FF if no value is returned by the modem
pGPSSel[OUT]	• optional 1 byte parameter • GPS Antenna Select • values: – 0x00 - Dedicated GPS Port – 0x01 - GPS Rx over AUX Port – 0x02 - GPS Rx over dedicated GPS port with no bias voltage applied • function SLQSGetCustFeatures() returns a default value FF if no value is returned by the modem

pSMSSupport[-OUT]	• optional 1 byte parameter • SMS support • values: – 0x00 - Not supported – 0x01 - supported • Used to determine whether or not to hide SMS from user • function SLQSGetCustFeatures() returns a default value FF if no value is returned by the modem. In this case assume, SMS is supported.
pIsVoice-Enabled[OUT]	• optional 1 byte parameter • Voice support • values: – 0x00 - Enable voice on both AT and QMI interface (default) – 0x01 - Reserved – 0x02 - Disable voice on both AT and QMI interface
pDHCPRelay-Enabled[OUT]	• optional 1 byte parameter • DHCP Relay support • values: – 0x00 - Disable DHCP relay – 0x01 - Enable DHCP relay
pGPSLPM[OUT]	• optional 1 byte parameter • GPSLPM support • values: – 0x00 - Enable GPS in Low Power Mode – 0x01 - Disable GPS in Low Power Mode

8.159.2 Field Documentation

8.159.2.1 ULONG custFeaturesInfo::GpsEnable

8.159.2.2 BYTE* custFeaturesInfo::pDHCPRelayEnabled

8.159.2.3 BYTE* custFeaturesInfo::pDisableIMSI

8.159.2.4 BYTE* custFeaturesInfo::pGPSLPM

8.159.2.5 BYTE* custFeaturesInfo::pGPSSel

8.159.2.6 WORD* custFeaturesInfo::pIPFamSupport

8.159.2.7 BYTE* custFeaturesInfo::pIsVoiceEnabled

8.159.2.8 BYTE* custFeaturesInfo::pRMAutoConnect

8.159.2.9 BYTE∗ custFeaturesInfo::pSMSSupport

8.160 custFeaturesSetting Struct Reference

Data Fields

- BYTE ∗ pGPSSel
- ULONG ∗ pGPSEnable
- BYTE ∗ pIsVoiceEnabled
- BYTE ∗ pDHCPRelayEnabled
- BYTE ∗ pGPSLPM

8.160.1 Detailed Description

This structure contains settings to be used for custom features

Parameters

pGPSSel	• optional 1 byte parameter • GPS Antenna Select • values: – 0x00 - Dedicated GPS Port – 0x01 - GPS Rx over AUX Port – 0x02 - GPS Rx over dedicated GPS port with no bias voltage applied
pGPSEnable	• optional 4 byte parameter • GPS Enable/Disable • values: The value of 7 least significant bits: – 0 - Disabled – 1 - MT & MO enabled – 2 - MO enabled – 3 - MT enabled – 4 - MT & MO enabled if GPS_DISABLE pin is not asserted – 5 - MO GPS enabled if GPS_DISABLE pin is not asserted – 6 - MT GPS enabled if GPS_DISABLE pin is not asserted

Note

Only MC7750 3.5.x firmware supports above 0x04, 0x05 and 0x06 settings. To disable GLONASS, set the most significant bit - 0x80. This setting is only applicable if GPS is not Disabled.

Parameters

pIsVoiceEnabled	• optional 1 byte parameter • voice enabled/disabled • values: – 0 - Enable voice on both AT and QMI interface (default) – 1 - Reserved – 2 - Disable voice on both AT and QMI interface

pDHCPRelay-Enabled	• optional 1 byte parameter • DHCPRELAYENABLE support • values: – 0 - Disable DHCP relay – 1 - Enable DHCP relay
pGPSLPM	• optional 1 byte parameter • GPSLPM support • values: – 0 - Enable GPS in Low Power Mode – 1 - Disable GPS in Low Power Mode

8.160.2 Field Documentation

8.160.2.1 BYTE* custFeaturesSetting::pDHCPRelayEnabled

8.160.2.2 ULONG* custFeaturesSetting::pGPSEnable

8.160.2.3 BYTE* custFeaturesSetting::pGPSLPM

8.160.2.4 BYTE* custFeaturesSetting::pGPSSel

8.160.2.5 BYTE* custFeaturesSetting::pIsVoiceEnabled

8.161 custSettingInfo Struct Reference

Data Fields

- WORD id_length
- CHAR cust_id [64+1]
- WORD value_length
- BYTE cust_value [8+1]
- WORD cust_attr

8.161.1 Detailed Description

This structure contains information about Customization Setting. This TLV is only applicable for 9x30 modules so far

Parameters

id_length	• length of cust_id field
cust_id	• Customization ID (Maximum 64 bytes)
value_length	• length of cust_value field

cust_value	• Customization Setting Value (Maximum 8 bytes)
cust_attr	• Customization Setting attribute through QMI – bit 0: Values: * 0 - read only * 1 - read/write

8.161.2 Field Documentation

8.161.2.1 WORD custSettingInfo::cust_attr

8.161.2.2 CHAR custSettingInfo::cust_id[64+1]

8.161.2.3 BYTE custSettingInfo::cust_value[8+1]

8.161.2.4 WORD custSettingInfo::id_length

8.161.2.5 WORD custSettingInfo::value_length

8.162 custSettingList Struct Reference

Data Fields

- BYTE list_type
- WORD num_instances
- custSettingInfo custSetting [256]

8.162.1 Detailed Description

This structure contains the fields of TLV Customization Setting List. This TLV is only applicable for 9x30 modules so far

Parameters

list_type	• list type requested
num_instances	• number of instances of customization setting
custSetting	• See custSettingInfo for more information

8.162.2 Field Documentation

8.162.2.1 custSettingInfo custSettingList::custSetting[256]

8.162.2.2 BYTE custSettingList::list_type

8.162.2.3 WORD custSettingList::num_instances

8.163 dataBearers Struct Reference

Data Fields

- BYTE dataBearerMask
- QmiWDSDataBearerTechnology * pCurDataBearerTechnology
- QmiWDSDataBearerTechnology * pLastCallDataBearerTechnology

8.163.1 Detailed Description

Structure to hold the data bearer technology values

Parameters

dataBearerMask[OUT]	• This bit mask indicates if data bearer information for the current and/or last call has been received from the device. If a bit is set, then the information is available in the corresponding structure i.e. the one provided by the caller. Refer to qmiDataBearerMasks for bit-mask positions.
pCurDataBearerTechnology[OUT]	• current data bearer technology value. – NULL if the parameter is not required
pLastCallDataBearerTechnology[OUT]	• last call data bearer technology value. – NULL if the parameter is not required

8.163.2 Field Documentation

8.163.2.1 BYTE dataBearers::dataBearerMask

8.163.2.2 QmiWDSDataBearerTechnology* dataBearers::pCurDataBearerTechnology

8.163.2.3 QmiWDSDataBearerTechnology* dataBearers::pLastCallDataBearerTechnology

8.164 DataBearerTech Struct Reference

Data Fields

- ULONG techType
- ULONG ratValue
- ULONGLONG soMask

8.164.1 Detailed Description

Network information structure

Parameters

TechType	• Technology type • Values: – 0 - WDS_BEARER_TECH_NETWORK_3GPP - 3GPP – 1 - WDS_BEARER_TECH_NETWORK_3GPP2 - 3GPP2
ratValue	• Radio Access Technology (RAT) value • Values: – 0x00 - WDS_BEARER_TECH_RAT_EX_NULL_BEARER - NULL bearer – 0x01 - WDS_BEARER_TECH_RAT_EX_3GPP_WCDMA - 3GPP WCDMA – 0x02 - WDS_BEARER_TECH_RAT_EX_3GPP_GERAN - 3GPP GERAN – 0x03 - WDS_BEARER_TECH_RAT_EX_3GPP_LTE - 3GPP LTE – 0x04 - WDS_BEARER_TECH_RAT_EX_3GPP_TDSCDMA - 3GPP TDSCDMA – 0x05 - WDS_BEARER_TECH_RAT_EX_3GPP_WLAN - 3GPP WLAN – 0x64 - WDS_BEARER_TECH_RAT_EX_3GPP_MAX - 3GPP maximum – 0x65 - WDS_BEARER_TECH_RAT_EX_3GPP2_1X - 3GPP2 1X – 0x66 - WDS_BEARER_TECH_RAT_EX_3GPP2_HRPD - 3GPP2 HRPD – 0x67 - WDS_BEARER_TECH_RAT_EX_3GPP2_EHRPD - 3GPP2 EHRPD – 0x68 - WDS_BEARER_TECH_RAT_EX_3GPP2_WLAN - 3GPP2 WLAN – 0xC8 - WDS_BEARER_TECH_RAT_EX_3GPP2_MAX - 3GPP2 maximum

SOMask	• Service Option (SO) mask to indicate the service option or type of application. An SO mask value of zero indicates that this field is ignored. • Values: – 0x00 - SO mask unspecified • 3GPP SO mask: – 0x01 - WCDMA – 0x02 - HSDPA – 0x04 - HSUPA – 0x08 - HSDPAPLUS – 0x10 - DC HSDPAPLUS – 0x20 - 64 QAM – 0x40 - HSPA – 0x80 - GPRS – 0x100 - EDGE – 0x200 - GSM – 0x400 - S2B – 0x800 - LTE limited service – 0x1000 - LTE FDD – 0x2000 - LTE TDD • 3GPP2 SO mask: – 0x01000000 - 1X IS95 – 0x02000000 - 1X IS2000 – 0x04000000 - 1X IS2000 REL A – 0x08000000 - HDR REV0 DPA – 0x10000000 - HDR REVA DPA – 0x20000000 - HDR REVB DPA – 0x40000000 - HDR REVA MPA – 0x80000000 - HDR REVB MPA – 0x100000000 - HDR REVA EMPA – 0x200000000 - HDR REVB EMPA – 0x400000000 - HDR REVB MMPA – 0x800000000 - HDR EVDO FMC

8.164.2 Field Documentation

8.164.2.1 ULONG DataBearerTech::ratValue

8.164.2.2 ULONGLONG DataBearerTech::soMask

8.164.2.3 ULONG DataBearerTech::techType

8.165 DataBearerTechExt Struct Reference

Data Fields

- DataBearerTech * pBearerTech
- DataBearerTech * pLastBearerTech

8.165.1 Detailed Description

Data Bearer Technology Ext

Parameters

pBearerTech	[OUT] • See DataBearerTech for more information
pLastBearerTech	[OUT] • See DataBearerTech for more information

8.165.2 Field Documentation

8.165.2.1 DataBearerTech* DataBearerTechExt::pBearerTech

8.165.2.2 DataBearerTech* DataBearerTechExt::pLastBearerTech

8.166 dataBearerTechnology Struct Reference

Data Fields

- BYTE currentNetwork
- ULONG ratMask
- ULONG soMask

8.166.1 Detailed Description

Structure to hold the current data bearer technology values

Parameters

pCurrent-Network[OUT]	• current selected network – 0 - UNKNOWN – 1 - 3GPP2 – 2 - 3GPP

pRatMask[OUT]	• Radio Access Technology (RAT) mask to indicate the type of technology (RAT mask value of zero indicates that this field is ignored) – 0x8000 - NULL Bearer – 0x0000 - DO_NOT_CARE – CDMA RAT mask * 0x01 - CDMA_1X * 0x02 - EVDO_REV0 * 0x04 - EVDO_REVA * 0x08 - EVDO_REVB * 0x10 - EHRPD * 0x20 - FMC – UMTS RAT mask * 0x01 - WCDMA * 0x02 - GPRS * 0x04 - HSDPA * 0x08 - HSUPA * 0x10 - EDGE * 0x20 - LTE * 0x40 - HSDPA+ * 0x80 - DC_HSDPA+ * 0x100 - 64_QAM * 0x200 - TDSCDMA
pSoMask[OUT]	• Service Option (SO) mask to indicate the SO or type of application (SO mask value of zero indicates that this field is ignored) – 0x00 - DO_NOT_CARE – CDMA 1X SO mask * 0x01 - CDMA_1X_IS95 * 0x02 - CDMA_1X_IS2000 * 0x04 - CDMA_1X_IS2000_REL_A – CDMA EV-DO Rev 0 SO mask * 0x01 - DPA – CDMA EV-DO Rev A SO mask * 0x01 - EVDO_REVA_DPA * 0x02 - EVDO_REVA_MFPA * 0x04 - EVDO_REVA_EMPA * 0x08 - EVDO_REVA_EMPA_EHRPD – CDMA EV-DO Rev B SO mask * 0x01 - DPA * 0x02 - MFPA * 0x04 - EMPA * 0x08 - EMPA_EHRPD * 0x10 - MMPA * 0x20 - MMPA_EHRPD

8.166.2 Field Documentation

8.166.2.1 BYTE dataBearerTechnology::currentNetwork

8.166.2.2 ULONG dataBearerTechnology::ratMask

8.166.2.3 ULONG dataBearerTechnology::soMask

8.167 dataRate Struct Reference

Data Fields

- ULONG dataRateMax
- ULONG guaranteedRate

8.167.1 Detailed Description

This structure contains the IP flow data rate min max

Parameters

dataRateMax	Maximum required data rate (bits per second)
guaranteedRate	Minimum guaranteed data rate (bits per second)

8.167.2 Field Documentation

8.167.2.1 ULONG dataRate::dataRateMax

8.167.2.2 ULONG dataRate::guaranteedRate

8.168 dataSrvCapabilities Struct Reference

Data Fields

- BYTE dataCapabilitiesLen
- BYTE dataCapabilities [0x20]

8.168.1 Detailed Description

This structure contains the data services capability

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

dataCapabilities-Len	• Length of data capabilities list • Defaults to zero
dataCapabilities	• List of data capabilities • Values: – 0x01 - GPRS – 0x02 - EDGE – 0x03 - HSDPA – 0x04 - HSUPA – 0x05 - WCDMA – 0x06 - CDMA – 0x07 - EV-DO Rev0 – 0x08 - EV-DO RevA – 0x09 - GSM – 0x0A - EV-DO Rev B – 0x0B - LTE – 0x0C - HSDPA+ – 0x0D - DC-HSDPA+

8.168.2 Field Documentation

8.168.2.1 BYTE dataSrvCapabilities::dataCapabilities[0x20]

8.168.2.2 BYTE dataSrvCapabilities::dataCapabilitiesLen

8.169 DataStatusDetail Struct Reference

Data Fields

- ULONG IPAddress
- BYTE LastErrCode

8.169.1 Detailed Description

This structure contains Data Status Details

Parameters

IPAddress	• IP Address • 0xABCDEFGH - AB.CD.EF.GH • Example: – 0x12345678 - 18.52.86.120 0x12=18 0x34=52 0x56=86 0x78=120 • 0xFFFFFFFF - NA

LastErrCode	• MIP Error code – 0x00 - MIP_RRP_CODE_SUCCESS – 0x01 - MIP_RRP_CODE_SUCCESS_NO_SIM_BINDINGS – 0x40 - MIP_RRP_CODE_FAILURE_FA_REASON_UNSPECIFIED – 0x41 - MIP_RRP_CODE_FAILURE_FA_ADMIN_PROHIBITED – 0x42 - MIP_RRP_CODE_FAILURE_FA_INSUFFICIENT_RESOURCES – 0x43 - MIP_RRP_CODE_FAILURE_FA_MOBILE_NODE_FAILED_AUTH – 0x44 - MIP_RRP_CODE_FAILURE_FA_HA_FAILED_AUTH – 0x45 - MIP_RRP_CODE_FAILURE_FA_REQUESTED_LIFETIME_TOO_LONG – 0x46 - MIP_RRP_CODE_FAILURE_FA_MALFORMED_REQUEST – 0x47 - MIP_RRP_CODE_FAILURE_FA_MALFORMED_REPLY – 0x48 - MIP_RRP_CODE_FAILURE_FA_ENCAPSULATION_UNAVAILABLE – 0x49 - MIP_RRP_CODE_FAILURE_FA_VJHC_UNAVAILABLE – 0x4A - MIP_RRP_CODE_FAILURE_FA_CANT_REV_TUN – 0x4B - MIP_RRP_CODE_FAILURE_FA_MUST_REV_TUN – 0x4C - MIP_RRP_CODE_FAILURE_FA_BAD_TTL – 0x4D - MIP_RRP_CODE_FAILURE_INVALID_COA – 0x4F - MIP_RRP_CODE_FAILURE_FA_DELIVERY_STYLE_NOT_SUPPORTED – 0x59 - MIP_RRP_CODE_FAILURE_FA_VS_REASON – 0x61 - MIP_RRP_CODE_FAILURE_MISSING_NAI – 0x62 - MIP_RRP_CODE_FAILURE_MISSING_HA_ADDR – 0x63 - MIP_RRP_CODE_FAILURE_MISSING_HOMEADDR – 0x68 - MIP_RRP_CODE_FAILURE_UNKNOWN_CHALLENGE – 0x69 - MIP_RRP_CODE_FAILURE_MISSING_CHALLENGE – 0x6A - MIP_RRP_CODE_FAILURE_STALE_CHALLENGE – 0x6B - MIP_RRP_CODE_FAILURE_MISSING_MN_FA – 0x80 - MIP_RRP_CODE_FAILURE_HA_REASON_UNSPECIFIED – 0x81 - MIP_RRP_CODE_FAILURE_HA_ADMIN_PROHIBITED – 0x82 - MIP_RRP_CODE_FAILURE_HA_INSUFFICIENT_RESOURCES – 0x83 - MIP_RRP_CODE_FAILURE_HA_MOBILE_NODE_FAILED_AUTH – 0x84 - MIP_RRP_CODE_FAILURE_HA_FA_FAILED_AUTH – 0x85 - MIP_RRP_CODE_FAILURE_HA_REG_ID_MISMATCH – 0x86 - MIP_RRP_CODE_FAILURE_HA_MALFORMED_REQUEST – 0x88 - MIP_RRP_CODE_FAILURE_UNKNOWN_HA – 0x89 - MIP_RRP_CODE_FAILURE_HA_CANT_REV_TUN – 0x8A - MIP_RRP_CODE_FAILURE_HA_MUST_REV_TUN – 0x8B - MIP_RRP_CODE_FAILURE_HA_ENCAPSULATION_UNAVAILABLE – 0x8F - MIP_RRP_CODE_FAILURE_REDIRECTED_HA – 0x90 - MIP_RRP_CODE_FAILURE_HA_BAD_AAA_AUTH – 0xFF - NA

8.169.2 Field Documentation

8.169.2.1 ULONG DataStatusDetail::IPAddress

8.169.2.2 BYTE DataStatusDetail::LastErrCode

8.170 DataULongLongTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONGLONG ullData

8.170.1 Field Documentation

8.170.1.1 BYTE DataULongLongTlv::TlvPresent

8.170.1.2 ULONGLONG DataULongLongTlv::ullData

8.171 DataULongTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG ulData

8.171.1 Field Documentation

8.171.1.1 BYTE DataULongTlv::TlvPresent

8.171.1.2 ULONG DataULongTlv::ulData

8.172 DcsUsbPortNames Struct Reference

Data Fields

- CHAR AtCmdPort [32]
- CHAR NmeaPort [32]
- CHAR DmPort [32]

8.172.1 Field Documentation

8.172.1.1 CHAR DcsUsbPortNames::AtCmdPort[32]

8.172.1.2 CHAR DcsUsbPortNames::DmPort[32]

8.172.1.3 CHAR DcsUsbPortNames::NmeaPort[32]

8.173 delAssistDataStatus Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG status

8.173.1 Detailed Description

Contain the parameters passed for SetLocDeleteAssistDataCallback by the device.

Parameters

status	• Status of the Delete Assist Data request • Valid values: – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure

Note

None

8.173.2 Field Documentation

8.173.2.1 struct qmTlvResult delAssistDataStatus::results

8.173.2.2 ULONG delAssistDataStatus::status

8.174 depersonalizationInformation Struct Reference

Data Fields

- BYTE feature
- BYTE operation
- BYTE ckLen
- BYTE ckVal [255]

8.174.1 Detailed Description

This structure contains the Depersonalization Information.

Parameters

feature	• Indicates the personalization feature to de-activate or unblock. – 0 - GW network personalization – 1 - GW network subset personalization – 2 - GW service provider personalization – 3 - GW corporate personalization – 4 - GW UIM personalization – 5 - 1X network type 1 personalization – 6 - 1X network type 2 personalization – 7 - 1X HRPD personalization – 8 - 1X service provider personalization – 9 - 1X corporate personalization – 10 - 1X RUIM personalization
operation	• Indicates the operation to perform. – 0 - Deactivate personalization. – 1 - Unblock personalization.
ckLen	• Length of the following elements i.e. control key value.
ckVal[MAX_DESCRIPTION_LENGTH]	• Control key value. • This value is a sequence of ASCII characters.

8.174.2 Field Documentation

8.174.2.1 BYTE depersonalizationInformation::ckLen

8.174.2.2 BYTE depersonalizationInformation::ckVal[255]

8.174.2.3 BYTE depersonalizationInformation::feature

8.174.2.4 BYTE depersonalizationInformation::operation

8.175 detailSvcInfo Struct Reference

Data Fields

- BYTE srvStatus
- BYTE srvCapability
- BYTE hdrSrvStatus
- BYTE hdrHybrid
- BYTE isSysForbidden

8.175.1 Detailed Description

This structure contains Detailed Service information

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

srvStatus	• Service status • Values: – 0x00 - No service – 0x01 - Limited service – 0x02 - Service available – 0x03 - Limited regional service – 0x04 - MS in power save or deep sleep
srvCapability	• System's service capability • Values: – 0x00 - No Service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - MS found the right system but not yet registered/attached
hdrSrvStatus	• HDR service status • Values: – 0x00 - No service – 0x01 - Limited service – 0x02 - Service available – 0x03 - Limited regional service – 0x04 - MS in power save or deep sleep
hdrHybrid	• HDR hybrid information • Values: – 0x00 - System is not hybrid – 0x01 - System is hybrid
isSysForbidden	• Forbidden system information • Values: – 0x00 - System is not a forbidden system – 0x01 - System is a forbidden system

8.175.2 Field Documentation

8.175.2.1 BYTE detailSvcInfo::hdrHybrid

8.175.2.2 BYTE detailSvcInfo::hdrSrvStatus

8.175.2.3 BYTE detailSvcInfo::isSysForbidden

8.175.2.4 BYTE detailSvcInfo::srvCapability

8.175.2.5 BYTE detailSvcInfo::srvStatus

8.176 DeviceConfigDetail Struct Reference

Data Fields

- BYTE Technology
- BYTE QLIC
- BYTE Chipset
- BYTE HWVersion

8.176.1 Detailed Description

This structure contains Device Configuration Details

Parameters

Technology	• Current technology in use – 0x00 - 1x RTT – 0x01 - EVDO Rev 0 – 0x02 - EVDO Rev A – 0xFF - NA
QLIC	• Quasi Linear Interference Cancellation – 0x00 - Not supported – 0x01 - Supported
Chipset	• Qualcomm platform – 0x4E - MDM6200 – 0x4F - MDM6600 – 0xFF - NA
HWVersion	• Hardware version – 0x00 - BSHWREV0 – 0x01 - BSHWREV1 – 0x02 - BSHWREV2 – 0x03 - BSHWREV3 – 0x04 - BSHWREVMAX – 0xFF - BSHWREVUNKNOWN

8.176.2 Field Documentation

8.176.2.1 BYTE DeviceConfigDetail::Chipset

8.176.2.2 BYTE DeviceConfigDetail::HWVersion

8.176.2.3 BYTE DeviceConfigDetail::QLIC

8.176.2.4 BYTE DeviceConfigDetail::Technology

8.177 DHCPOption Struct Reference

Data Fields

- BYTE optCode
- BYTE optValLen
- BYTE * pOptVal

8.177.1 Detailed Description

This structure contains DHCPv4 lease option values

Parameters

optCode	• Values – Option code
optValLen	• Values – Option value length
pOptValue	• Val – Option value

8.177.2 Field Documentation

8.177.2.1 BYTE DHCPOption::optCode

8.177.2.2 BYTE DHCPOption::optValLen

8.177.2.3 BYTE* DHCPOption::pOptVal

8.178 DHCPOptionList Struct Reference

Data Fields

- BYTE numOpt
- DHCPOption * pOptions

8.178.1 Detailed Description

This structure contains DHCPv4 lease option list

Parameters

optListSize	• Values – Size of Option List
pOptions	• Values – Options

8.178.2 Field Documentation

8.178.2.1 BYTE DHCPOptionList::numOpt

8.178.2.2 DHCPOption* DHCPOptionList::pOptions

8.179 diagInfo Struct Reference

Data Fields

- BYTE diagInfoLen
- BYTE diagnosticInfo [255]

8.179.1 Detailed Description

This structure contains Diagnostic Information

Parameters

diagInfoLen	• Provides the length of information which follow. • If zero(0) then no further information exists.
diagnosticInfo[MAX_DESCRIPTION_LENGTH]	• Diagnostic information.

8.179.2 Field Documentation

8.179.2.1 BYTE diagInfo::diagInfoLen

8.179.2.2 BYTE diagInfo::diagnosticInfo[255]

8.180 dirNum Struct Reference

Data Fields

- BYTE dirNumLen
- BYTE dirNum [255]

8.180.1 Detailed Description

This structure contains the parameters for Directory Number Information

Parameters

dirNumLen	• Number of sets of the following elements: – dir_num • If zero(0), then no information follows.
dirNum	• Directory number in ASCII characters.

8.180.2 Field Documentation

8.180.2.1 BYTE dirNum::dirNum[255]

8.180.2.2 BYTE dirNum::dirNumLen

8.181 dms_ActivationStatusTlv Struct Reference

Data Fields

- uint16_t TlvPresent
- uint32_t activationStatus

8.181.1 Detailed Description

Activation Status Tlv

Parameters

TlvPresent	• Tlv Present
activationStatus	• Service Activation Code – 0 - Service not activated – 1 - Service activated – 2 - Activation connecting – 3 - Activation connected – 4 - OTASP security authenticated – 5 - OTASP NAM downloaded – 6 - OTASP MDN downloaded – 7 - OTASP IMSI downloaded – 8 - OTASP PRL downloaded – 9 - OTASP SPC downloaded – 10 - OTASP settings committed

8.181.2 Field Documentation

8.181.2.1 uint32_t dms_ActivationStatusTlv::activationStatus

8.181.2.2 uint16_t dms_ActivationStatusTlv::TlvPresent

8.182 dms_OperatingModeTlv Struct Reference

Data Fields

- uint16_t TlvPresent
- uint32_t operatingMode

8.182.1 Detailed Description

Operating Mode Tlv

Parameters

TlvPresent	• Tlv Present
operatingMode	• 0 - Online • 1 - Low power • 2 - Factory test mode • 3 - Offline • 4 - Resetting • 5 - Shutting down • 6 - Persistent low power • 7 - Mode-only low power

8.182.2 Field Documentation

8.182.2.1 uint32_t dms_OperatingModeTlv::operatingMode

8.182.2.2 uint16_t dms_OperatingModeTlv::TlvPresent

8.183 dms_PSMActiveTimerIndTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t ActiveTimerInd

8.183.1 Detailed Description

This Structure used to store DMS PSM Active Timer TLV Value.

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response
ActiveTimerInd	• Active Timer • PSM active timer value (in seconds).

8.183.2 Field Documentation

8.183.2.1 uint32_t dms_PSMActiveTimerIndTlv::ActiveTimerInd

8.183.2.2 uint8_t dms_PSMActiveTimerIndTlv::TlvPresent

8.184 dms_PSMActiveTimerTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t activeTimer

8.184.1 Detailed Description

This structure contains the parameters for Power Save Mode active timer.

Parameters

TlvPresent	• Tlv Present.
activeTimer	Active Timer • Power Save mode active timer value (in seconds).

8.184.2 Field Documentation

8.184.2.1 uint32_t dms_PSMActiveTimerTlv::activeTimer

8.184.2.2 uint8_t dms_PSMActiveTimerTlv::TlvPresent

8.185 dms_PSMDurationDueToOOSTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t durationDueToOOS

8.185.1 Detailed Description

This structure contains the parameters for Power Save Mode Duration due to an outage.

Parameters

TlvPresent	• Tlv Present.
durationDueTo-OOS	Duration Due to OOS • Power Save mode duration due to an outage (in seconds).

8.185.2 Field Documentation

8.185.2.1 uint32_t dms_PSMDurationDueToOOSTlv::durationDueToOOS

8.185.2.2 uint8_t dms_PSMDurationDueToOOSTlv::TlvPresent

8.186 dms_PSMDurationThresholdTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t durationThreshold

8.186.1 Detailed Description

This structure contains the parameters for Power Save Mode Duration Threshold.

Parameters

TlvPresent	• Tlv Present.
duration-Threshold	Duration Threshold • Minimum duration for the device to benefit by entering PSM (in seconds).

8.186.2 Field Documentation

8.186.2.1 uint32_t dms_PSMDurationThresholdTlv::durationThreshold

8.186.2.2 uint8_t dms_PSMDurationThresholdTlv::TlvPresent

8.187 dms_PSMEarlyWakeupTimeTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t earlyWakeupTime

8.187.1 Detailed Description

This structure contains the parameters for Power Save Mode early wakeup time.

Parameters

TlvPresent	• Tlv Present.
earlyWakeup-Time	• Early Wakeup Time • Power Save mode early wakeup time (in seconds) indicating how early the device should exit PSM to offset for bootup and acquisition delay.

8.187.2 Field Documentation

8.187.2.1 uint32_t dms_PSMEarlyWakeupTimeTlv::earlyWakeupTime

8.187.2.2 uint8_t dms_PSMEarlyWakeupTimeTlv::TlvPresent

8.188 dms_PSMEnableStateIndTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t EnableStateInd

8.188.1 Detailed Description

This Structure used to store DMS PSM Enable state TLV Value.

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response

EnableStateInd	• PSM Enable State
	• Values
	  – 0 - PSM is not enabled
	  – 1 - PSM is enabled

8.188.2 Field Documentation

8.188.2.1 uint8_t dms_PSMEnableStateIndTlv::EnableStateInd

8.188.2.2 uint8_t dms_PSMEnableStateIndTlv::TlvPresent

8.189 dms_PSMEnableStateTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t enableState

8.189.1 Detailed Description

This structure contains the parameters for Power Save Mode Enable State.

Parameters

TlvPresent	• Tlv Present.
enableState	Power Save Mode Enable State Values • 0 - PSM is not enabled • 1 - PSM is enabled

8.189.2 Field Documentation

8.189.2.1 uint8_t dms_PSMEnableStateTlv::enableState

8.189.2.2 uint8_t dms_PSMEnableStateTlv::TlvPresent

8.190 dms_PSMPeriodicUpdateTimerIndTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t PeriodicUpdateTimerInd

8.190.1 Detailed Description

This Structure used to store DMS PSM Periodic Update Timer TLV Value.

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response
PeriodicUpdate-TimerInd	• Periodic Update Timer • PSM periodic update timer value (in seconds).

8.190.2 Field Documentation

8.190.2.1 uint32_t dms_PSMPeriodicUpdateTimerIndTlv::PeriodicUpdateTimerInd

8.190.2.2 uint8_t dms_PSMPeriodicUpdateTimerIndTlv::TlvPresent

8.191 dms_PSMPeriodicUpdateTimerTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t periodicUpdateTimer

8.191.1 Detailed Description

This structure contains the parameters for Power Save Mode periodic update timer.

Parameters

TlvPresent	• Tlv Present.
periodicUpdateTimer	Periodic Update Timer • Power Save mode periodic update timer value (in seconds).

8.191.2 Field Documentation

8.191.2.1 uint32_t dms_PSMPeriodicUpdateTimerTlv::periodicUpdateTimer

8.191.2.2 uint8_t dms_PSMPeriodicUpdateTimerTlv::TlvPresent

8.192 dms_PSMRandomizationWindowTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t randomizationWindow

8.192.1 Detailed Description

This structure contains the parameters for Power Save Mode wakeup randomization window.

Parameters

TlvPresent	• Tlv Present.
randomizationWindow	Randomization Window • Power Save mode wakeup randomization window (in seconds)

8.192.2 Field Documentation

8.192.2.1 uint32_t dms_PSMRandomizationWindowTlv::randomizationWindow

8.192.2.2 uint8_t dms_PSMRandomizationWindowTlv::TlvPresent

8.193 dms_TemperatureTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t TempStat
- uint16_t Temperature

8.193.1 Detailed Description

This structure stores information about temperature TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
TempStat	• Temperature state – 0 - unknown – 1 - normal – 2 - high (warning) – 3 - high (critical) – 4 - low (critical)
Temperature	• temperature in degree celsius

8.193.2 Field Documentation

8.193.2.1 uint16_t dms_TemperatureTlv::Temperature

8.193.2.2 uint8_t dms_TemperatureTlv::TempStat

8.193.2.3 uint8_t dms_TemperatureTlv::TlvPresent

8.194 dms_UimAutoSwitchActSlotTlv Struct Reference

Data Fields

- uint8_t uimAutoSwitchActSlot
- uint8_t TlvPresent

8.194.1 Detailed Description

This structure contains the TLV required to Get UIM auto active slot Tlv.

Parameters

uimAutoSwitch-ActSlot[Optional]	• When UIMAUTOSWITCH feature enabled and SIM auto-switch is activated, indicates currently active UIM slot. • Values – 0 - slot 1 (e.g. external SIM) – 1 - slot 2 (e.g. embedded SIM)
TlvPresent	• Tlv Present.

8.194.2 Field Documentation

8.194.2.1 uint8_t dms_UimAutoSwitchActSlotTlv::TlvPresent

8.194.2.2 uint8_t dms_UimAutoSwitchActSlotTlv::uimAutoSwitchActSlot

8.195 dms_UimStatusTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t intf
- uint8_t event

8.195.1 Detailed Description

This structure stores information about UIM status TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
intf	• interface type – 0 - External UIM. – 1 - Embedded UIM. – 2 - Remote UIM.
event	• event type – 0 - UIM card removed. – 1 - UIM card inserted.

8.195.2 Field Documentation

8.195.2.1 uint8_t dms_UimStatusTlv::event

8.195.2.2 uint8_t dms_UimStatusTlv::intf

8.195.2.3 uint8_t dms_UimStatusTlv::TlvPresent

8.196 dms_VoltageTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t VoltStat
- uint16_t Voltage

8.196.1 Detailed Description

This structure stores information about voltage TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
VoltStat	• Voltage state – 0 - unknown – 1 - normal – 2 - low (warning) – 3 - low (critical) – 4 - high (critical)
Voltage	• Voltage in mV

8.196.2 Field Documentation

8.196.2.1 uint8_t dms_VoltageTlv::TlvPresent

8.196.2.2 uint16_t dms_VoltageTlv::Voltage

8.196.2.3 uint8_t dms_VoltageTlv::VoltStat

8.197 dmsCurrentPRLInfo Struct Reference

Data Fields

- WORD * pPRLVersion
- BYTE * pPRLPreference

8.197.1 Detailed Description

This structure contains GetCurrentPRLInfo response parameter

Parameters

pPRLVersion[OUT]	- Optional • PRL version of device.
pPRLPreference	[OUT]- Optional • PRL Preference – 0 - Unset – 1 - Set

8.197.2 Field Documentation

8.197.2.1 BYTE* dmsCurrentPRLInfo::pPRLPreference

8.197.2.2 WORD* dmsCurrentPRLInfo::pPRLVersion

8.198 DMScustSettingInfo Struct Reference

Data Fields

- uint16_t id_length
- uint8_t cust_id [64+1]
- uint16_t value_length
- uint8_t cust_value [8+1]
- uint16_t cust_attr

8.198.1 Detailed Description

This structure contains information about Customization Setting. This TLV is only applicable for 9x30 modules so far

Parameters

id_length	• length of cust_id field
cust_id	• Customization ID (Maximum 64 bytes) • NULL terminated ASCII string.
value_length	• length of cust_value field
cust_value	• Customization Setting Value (Maximum 8 bytes)

cust_attr	• Customization Setting attribute through QMI
	  – bit 0: Values:
	  * 0 - read only
	  * 1 - read/write

8.198.2 Field Documentation

8.198.2.1 uint16_t DMScustSettingInfo::cust_attr

8.198.2.2 uint8_t DMScustSettingInfo::cust_id[64+1]

8.198.2.3 uint8_t DMScustSettingInfo::cust_value[8+1]

8.198.2.4 uint16_t DMScustSettingInfo::id_length

8.198.2.5 uint16_t DMScustSettingInfo::value_length

8.199 DMScustSettingList Struct Reference

Data Fields

- uint8_t list_type
- uint16_t num_instances
- DMScustSettingInfo custSetting [255+1]

8.199.1 Detailed Description

This structure contains the fields of TLV Customization Setting List. This TLV is only applicable for 9x30 modules so far

Parameters

list_type	• list type requested
num_instances	• number of instances of customization setting
custSetting	• See DMScustSettingInfo for more information

8.199.2 Field Documentation

8.199.2.1 DMScustSettingInfo DMScustSettingList::custSetting[255+1]

8.199.2.2 uint8_t DMScustSettingList::list_type

8.199.2.3 uint16_t DMScustSettingList::num_instances

8.200 DMSgetCustomFeatureV2 Struct Reference

Data Fields

- DMSgetCustomInput * pGetCustomInput
- DMScustSettingInfo * pCustSettingInfo
- DMScustSettingList * pCustSettingList

8.200.1 Detailed Description

This struture contains the TLV required to get the Customization Info and customization list.

Parameters

pGetCustom-Input[IN]	• See DMSgetCustomInput for more information
pCustSetting-Info[OUT]	• See DMScustSettingInfo for more information

pCustSetting-List[OUT]	• See DMScustSettingList for more information

8.200.2 Field Documentation

8.200.2.1 DMScustSettingInfo∗ DMSgetCustomFeatureV2::pCustSettingInfo

8.200.2.2 DMScustSettingList∗ DMSgetCustomFeatureV2::pCustSettingList

8.200.2.3 DMSgetCustomInput∗ DMSgetCustomFeatureV2::pGetCustomInput

8.201 DMSgetCustomInput Struct Reference

Data Fields

- uint8_t cust_id [64+1]
- uint8_t list_type

8.201.1 Detailed Description

This structure contains which customization id or the list type want to retrieve from modem. This TLV is only applicable for 9x30 modules so far

Parameters

cust_id	• Customization ID (Maximum 64 bytes) • NULL terminated ASCII string.
list_type	• list type requested

8.201.2 Field Documentation

8.201.2.1 uint8_t DMSgetCustomInput::cust_id[64+1]

8.201.2.2 uint8_t DMSgetCustomInput::list_type

8.202 dmsIndicationRegisterReq Struct Reference

Data Fields

- BYTE ∗ pSwiGetResetInd

8.202.1 Detailed Description

This structure contains the SLQSDmsSwiIndicationRegister request parameters.

Parameters

pGetResetInd	[IN,Optional] • Get Reset Info indication registration. The following callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable

Note

'NULL' value confirms that the indication value is not sent.

8.202.2 Field Documentation

8.202.2.1 BYTE∗ dmsIndicationRegisterReq::pSwiGetResetInd

8.203 dmsPsmCfgParamChange Struct Reference

Data Fields

- BYTE ∗ pEnableState
- ULONG ∗ pActiveTimer
- ULONG ∗ pPeriodicUpdateTimer

8.203.1 Detailed Description

Contains the parameters passed for SLQSSetIMSARegStatusCallback by the device.

Parameters

pEnableState	• PSM Enable State • Values – 0 - PSM is not enabled – 1 - PSM is enabled
pActiveTimer	• Active Timer • PSM active timer value (in seconds).
pPeriodic-UpdateTimer	• Periodic Update Timer • PSM periodic update timer value (in seconds).

8.203.2 Field Documentation

8.203.2.1 ULONG∗ dmsPsmCfgParamChange::pActiveTimer

8.203.2.2 BYTE∗ dmsPsmCfgParamChange::pEnableState

8.203.2.3 ULONG* dmsPsmCfgParamChange::pPeriodicUpdateTimer

8.204 dmsSwiGetPCInfo Struct Reference

Data Fields

- BYTE opMode
- ULONG * pLpmFlag
- BYTE * pWdisable
- BYTE * pPowerOffMode
- BYTE * pPersistentLpm

8.204.1 Detailed Description

This structure contains the TLV required to Get device power control status information.

Parameters

[OUT]	opMode • Selected operating mode. • Values – 0 - Online – 1 - Low power – 2 - Factory Test mode – 3 - Offline – 4 - Resetting – 5 - Shutting down – 6 - Persistent low power – 8 - Conducting network test for GSM/WCDMA
[OUT]	pLpmFlag[Optional] • LPM Force Flags • Bitmask – bit0 - Tracks the state of W_DISABLE TLV, indicating state of the W_DISABLE switch. – bit1 - Set if LPM is requested by a host request, such as AT command, QMI or MBIM request. Cleared by a host request to return to online mode. Also set when the device is cold or warm booted in persistent LPM. – bit2 - Set when the device temperature is outside the valid operating range. Cleared if the temperature returns to the normal range. – bit3 - Set when the device voltage is outside the valid operating range. Cleared if the voltage returns to the normal range. – bit4 - Set on power up when BIOS locking is enabled. Cleared when the host has disabled the BIOS lock. – bit5 - Set if the current device configuration does not match the GOBI image preference. – bit6-31 - Additional LPM causes may be added to future products.
[OUT]	pWdisable[Optional] • W_DISABLE • Values – 0 - Switch set to ON position – 1 - Switch set to OFF position

[OUT]	pPowerOffMode[Optional] • Power-off Mode • Action taken when W_DISABLE is switched to the OFF position – 0 - LPM – 1 - Shutdown – 2 - Ignore
[OUT]	pPersistentLpm[Optional] • LPM Persistence • Values – 0 - Non-persistent LPM – 1 - Persistent LPM

8.204.2 Field Documentation

8.204.2.1 BYTE dmsSwiGetPCInfo::opMode

8.204.2.2 ULONG* dmsSwiGetPCInfo::pLpmFlag

8.204.2.3 BYTE* dmsSwiGetPCInfo::pPersistentLpm

8.204.2.4 BYTE* dmsSwiGetPCInfo::pPowerOffMode

8.204.2.5 BYTE* dmsSwiGetPCInfo::pWdisable

8.205 dmsSwiGetResetInfo Struct Reference

Data Fields

- BYTE type
- BYTE source

8.205.1 Detailed Description

This structure contains the TLV required to Get Reset Info.

Parameters

OUT]	type[OUT] • type of reset or power down, possible values listed below: – 0 - unknown – 1 - warm – 2 - hard – 3 - crash – 4 - power down

OUT]	source[OUT] • entity which initiated the reset or power down, possible values listed below: – 0 - unknown – 1 - user requested – 2 - hardware switch – 3 - temperature critical – 4 - voltage critical – 5 - configuration update – 6 - LWM2M – 7 - OMA-DM – 8 - FOTA

8.205.2 Field Documentation

8.205.2.1 BYTE dmsSwiGetResetInfo::source

8.205.2.2 BYTE dmsSwiGetResetInfo::type

8.206 dmsSwiGetUIMSelection Struct Reference

Data Fields

- BYTE uimSelect
- UimAutoSwitchActSlotTlv * pUimAutoSwitchActSlot

8.206.1 Detailed Description

This structure contains the TLV required to Get currently selected active UIM slot.

Parameters

[OUT]	uimSelect • Active selected UIM slot • Values – 0 - slot 1 (e.g. external SIM) – 1 - slot 2 (e.g. embedded SIM) – 2 - remote SIM (if supported) – 3 - SIM auto-switch activated
[OUT]	pUimAutoSwitchActSlot[Optional] • See UimAutoSwitchActSlotTlv for more information of the input structure

8.206.2 Field Documentation

8.206.2.1 UimAutoSwitchActSlotTlv* dmsSwiGetUIMSelection::pUimAutoSwitchActSlot

8.206.2.2 BYTE dmsSwiGetUIMSelection::uimSelect

8.207 Domain Struct Reference

Data Fields

- WORD domainLen
- CHAR domainName [256]

8.207.1 Detailed Description

This structure contains the DomainName Information

Parameters

domainLen	• length of the received Domain name
domainName	• Domain name(Max 256 characters)

8.207.2 Field Documentation

8.207.2.1 WORD Domain::domainLen

8.207.2.2 CHAR Domain::domainName[256]

8.208 DomainNameList Struct Reference

Data Fields

- BYTE numInstances
- struct Domain domain [10]

8.208.1 Detailed Description

This structure contains the DomainNameList Information

Parameters

numInstances	• Number of Domain name received
domain	• Domain name information(Max 10 Domain names)

8.208.2 Field Documentation

8.208.2.1 struct Domain DomainNameList::domain[10]

8.208.2.2 BYTE DomainNameList::numInstances

8.209 DRCParams Struct Reference

Data Fields

- BYTE DRCValue
- BYTE DRCCover

8.209.1 Detailed Description

This structure contains Data Rate Channel parameters

Parameters

DRCValue	• Current Data Rate Channel
DRCCover	• Current Data Rate Channel cover

8.209.2 Field Documentation

8.209.2.1 BYTE DRCParams::DRCCover

8.209.2.2 BYTE DRCParams::DRCValue

8.210 DTMFInfo Struct Reference

Data Fields

- BYTE callID
- BYTE DTMFEvent
- BYTE digitCnt
- BYTE digitBuff [255]

8.210.1 Detailed Description

This structure contains information about the DTMF (Dual Tone Multi-Frequency).

Parameters

callID	• Call identifier for the current call.
DTMFEvent	• DTMF event – 0x00 - DTMF_EVENT_REV_BURST - Sends a CDMA-burst DTMF – 0x01 - DTMF_EVENT_REV_START_CONT - Starts a continuous DTMF tone – 0x03 - DTMF_EVENT_REV_STOP_CONT - Stops a continuous DTMF tone – 0x05 - DTMF_EVENT_FWD_BURST - Received a CDMA-burst DTMF message – 0x06 - DTMF_EVENT_FWD_START_CONT - Received a start-continuous DTMF tone order – 0x07 - DTMF_EVENT_FWD_STOP_CONT - Received a stop-continuous DTMF tone order

digitCnt	• Number of set of following element i.e. digitBuff.
digitBuff[MAX_-DESCRIPTION-_LENGTH]	• DTMF digit buffer in ASCII string which is NULL terminated

8.210.2 Field Documentation

8.210.2.1 BYTE DTMFInfo::callID

8.210.2.2 BYTE DTMFInfo::digitBuff[255]

8.210.2.3 BYTE DTMFInfo::digitCnt

8.210.2.4 BYTE DTMFInfo::DTMFEvent

8.211 DTMFLengths Struct Reference

Data Fields

- BYTE DTMFPulseWidth
- BYTE DTMFInterdigitInterval

8.211.1 Detailed Description

This structure contains Voice Burst DTMF pulse length information

Parameters

DTMFPulse-Width	• DTMF pulse width. Values: – 0x00 - DTMF_ONLENGTH_95MS - 95 ms – 0x01 - DTMF_ONLENGTH_150MS - 150 ms – 0x02 - DTMF_ONLENGTH_200MS - 200 ms – 0x03 - DTMF_ONLENGTH_250MS - 250 ms – 0x04 - DTMF_ONLENGTH_300MS - 300 ms – 0x05 - DTMF_ONLENGTH_350MS - 350 ms – 0x06 - DTMF_ONLENGTH_SMS SMS Tx special pulse width
DTMFInterdigit-Interval	• DTMF interdigit interval Values: – 0x00 - DTMF_OFFLENGTH_60MS - 60 ms – 0x01 - DTMF_OFFLENGTH_100MS - 100 ms – 0x02 - DTMF_OFFLENGTH_150MS - 150 ms – 0x03 - DTMF_OFFLENGTH_200MS - 200 ms

8.211.2 Field Documentation

8.211.2.1 BYTE DTMFLengths::DTMFInterdigitInterval

8.211.2.2 BYTE DTMFLengths::DTMFPulseWidth

8.212 DUNCallInfoInd Struct Reference

Data Fields

- BYTE MdmConnStatus
- WORD CallEndReason
- ULONGLONG TXOKBytesCount
- ULONGLONG RXOKBytesCount
- BYTE DormancyStatus
- BYTE DataBearerTech
- channelRate ChannelRate

8.212.1 Field Documentation

8.212.1.1 WORD DUNCallInfoInd::CallEndReason

8.212.1.2 channelRate DUNCallInfoInd::ChannelRate

8.212.1.3 BYTE DUNCallInfoInd::DataBearerTech

8.212.1.4 BYTE DUNCallInfoInd::DormancyStatus

8.212.1.5 BYTE DUNCallInfoInd::MdmConnStatus

8.212.1.6 ULONGLONG DUNCallInfoInd::RXOKBytesCount

8.212.1.7 ULONGLONG DUNCallInfoInd::TXOKBytesCount

8.213 dunchannelRate Struct Reference

Data Fields

- uint32_t CurrChanTxRate
- uint32_t CurrChanRxRate
- uint32_t MaxChanTxRate
- uint32_t MaxChanRxRate

8.213.1 Detailed Description

This structure contains Channel Rate

Parameters

CurrChanTxRate	• Instantaneous channel Tx rate in bits per second • 0xffffffff - Invalid data.

CurrChanRx-Rate	• Instantaneous channel Rx rate in bits per second • 0xffffffff - Invalid data.
MaxChanTxRate	• maximum Tx rate that can be assigned to the device by the serving system in bits per second • 0xffffffff - Invalid data.
MaxChanRx-Rate	• maximum Rx rate that can be assigned to the device by the serving system in bits per second • 0xffffffff - Invalid data.

8.213.2 Field Documentation

8.213.2.1 uint32_t dunchannelRate::CurrChanRxRate

8.213.2.2 uint32_t dunchannelRate::CurrChanTxRate

8.213.2.3 uint32_t dunchannelRate::MaxChanRxRate

8.213.2.4 uint32_t dunchannelRate::MaxChanTxRate

8.214 ecioListElement Struct Reference

Data Fields

- SHORT ecio
- BYTE radioIf

8.214.1 Detailed Description

This structure contains the ECIO Information

Parameters

ecio	• ECIO value in dBm
radioIf	• Radio interface technology of the signal being measured – 0x00 - RADIO_IF_NO_SVC - None (no service) – 0x01 - RADIO_IF_CDMA_1X - cdma2000® 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS

8.214.2 Field Documentation

8.214.2.1 SHORT ecioListElement::ecio

8.214.2.2 BYTE ecioListElement::radioIf

8.215 ECIOThresh Struct Reference

Data Fields

- BYTE ECIOThresListLen
- SHORT * pECIOThresList

8.215.1 Detailed Description

This structure contains ECIO threshold related parameters.

Parameters

ECIOThresList-Len	• Length of the ECIO threshold list parameter to follow
pECIOThresList	• Sequence of thresholds delimiting ECIO event reporting bands • Every time a new ECIO value crosses a threshold value, an event report indication message with the new ECIO value is sent to the requesting control point. For this field – Each ECIO threshold value is a signed 2 byte value – Each ECIO threshold value increments in negative 0.5 dB, e.g., an ECIO threshold value of 2 means -1dB – Maximum number of threshold values is 16 – At least one value must be specified – Threshold values specified above are used for all RATs

8.215.2 Field Documentation

8.215.2.1 BYTE ECIOThresh::ECIOThresListLen

8.215.2.2 SHORT* ECIOThresh::pECIOThresList

8.216 ECTNum Struct Reference

Data Fields

- BYTE ECTCallState
- BYTE presentationInd
- BYTE number [81]

8.216.1 Detailed Description

Contains the parameters passed for Explicit Communication Transfer by the device.

Parameters

ECTCallState	• ECT call state: – 0x00 - ECT_CALL_STATE_NONE - None – 0x01 - ECT_CALL_STATE_ALERTING - Alerting – 0x02 - ECT_CALL_STATE_ACTIVE - Active
presentationInd	• Presentation indicator – 0x00 - presentationAllowedAddress – 0x01 - presentationRestricted – 0x02 - numberNotAvailable – 0x04 - presentationRestrictedAddress
number	• Number in ASCII characters terminated by NULL

8.216.2 Field Documentation

8.216.2.1 BYTE ECTNum::ECTCallState

8.216.2.2 BYTE ECTNum::number[81]

8.216.2.3 BYTE ECTNum::presentationInd

8.217 EdrxCiotLteMode Struct Reference

Data Fields

- ULONG lteOpMode
- BYTE TlvPresent

8.217.1 Detailed Description

This structure contains the parameters for LTE Operational Mode Indicator Type.

Parameters

lteOpMode	• CIOT LTE mode. • Values – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_NB1 (0x03) - Camped on LTE NB1
TlvPresent	• Tlv Present.

8.217.2 Field Documentation

8.217.2.1 ULONG EdrxCiotLteMode::IteOpMode

8.217.2.2 BYTE EdrxCiotLteMode::TlvPresent

8.218 EdrxCycleLength Struct Reference

Data Fields

- BYTE cycleLength
- BYTE TlvPresent

8.218.1 Detailed Description

This structure contains the parameters for eDRX Cycle Length Indicator Type.

Parameters

cycleLength	• eDRX cycle length. Value is per 3GPP TS 24.008 Rel-13 Section 10.5.5.32.
TlvPresent	• Tlv Present.

8.218.2 Field Documentation

8.218.2.1 BYTE EdrxCycleLength::cycleLength

8.218.2.2 BYTE EdrxCycleLength::TlvPresent

8.219 EdrxEnableType Struct Reference

Data Fields

- BYTE edrxEnabled
- BYTE TlvPresent

8.219.1 Detailed Description

This structure contains the parameters for eDRX Enabled Indicator Type.

Parameters

edrxEnabled	• Values – 0x00 - Disabled – 0x01 - Enabled
TlvPresent	• Tlv Present.

8.219.2 Field Documentation

8.219.2.1 BYTE EdrxEnableType::edrxEnabled

8.219.2.2 BYTE EdrxEnableType::TlvPresent

8.220 EdrxPagingTimeWindow Struct Reference

Data Fields

- BYTE edrxPtw
- BYTE TlvPresent

8.220.1 Detailed Description

This structure contains the parameters for eDRX Paging Time Window Indicator Type.

Parameters

edrxPtw	• eDRX paging time window. Value is per 3GPP TS 24.008 Rel-13 Section 10.5.5.32
TlvPresent	• Tlv Present.

8.220.2 Field Documentation

8.220.2.1 BYTE EdrxPagingTimeWindow::edrxPtw

8.220.2.2 BYTE EdrxPagingTimeWindow::TlvPresent

8.221 EdrxRatType Struct Reference

Data Fields

- BYTE edrxRatType
- BYTE TlvPresent

8.221.1 Detailed Description

This structure contains the parameters for eDRX RAT type Indicator Type.

Parameters

edrxRatType	• Radio access technology • Values – NAS_RADIO_IF_NO_SVC (0x00) - None (no service) – NAS_RADIO_IF_CDMA_1X (0x01) - cdma2000 ® 1X – NAS_RADIO_IF_CDMA_1XEVDO (0x02) - cdma2000 ® HRPD (1xEV-DO) – NAS_RADIO_IF_AMPS (0x03) - AMPS – NAS_RADIO_IF_GSM (0x04) - GSM – NAS_RADIO_IF_UMTS (0x05) - UMTS – NAS_RADIO_IF_WLAN (0x06) - WLAN – NAS_RADIO_IF_GPS (0x07) - GPS – NAS_RADIO_IF_LTE (0x08) - LTE – NAS_RADIO_IF_TDSCDMA (0x09) - TD-SCDMA – NAS_RADIO_IF_LTE_M1 (0x0a) - LTE-M1 – NAS_RADIO_IF_LTE_NB1 (0x0b) - LTE-NB1 – NAS_RADIO_IF_NO_CHANGE (-1) - No change
TlvPresent	• Tlv Present.

8.221.2 Field Documentation

8.221.2.1 BYTE EdrxRatType::edrxRatType

8.221.2.2 BYTE EdrxRatType::TlvPresent

8.222 ehrpdMTUSizeTlv Struct Reference

Data Fields

- BYTE TlvPresent
- WORD ehrpdMTUSize

8.222.1 Detailed Description

This structure contains the parameters for EHRPD MTU Size.

Parameters

TlvPresent	• Tlv Present.
ehrpdMTUSize	EHRPD size • Size of EHRPD MTU

8.222.2 Field Documentation

8.222.2.1 WORD ehrpdMTUSizeTlv::ehrpdMTUSize

8.222.2.2 BYTE ehrpdMTUSizeTlv::TlvPresent

8.223 encryptedPIN1 Struct Reference

Data Fields

- BYTE pin1Len
- BYTE pin1Val [255]

8.223.1 Detailed Description

This structure contains the encrypted PIN1 Information.

Parameters

pin1Len	• Number of sets of the following elements ie encrypted PIN1 value. • If zero(0), no information follows.
pin1Val	• Encrypted PIN1 value.

Note

This value is returned only when PIN1 is enabled successfully and the feature is supported.

8.223.2 Field Documentation

8.223.2.1 BYTE encryptedPIN1::pin1Len

8.223.2.2 BYTE encryptedPIN1::pin1Val[255]

8.224 eriDataparams Struct Reference

Data Fields

- uint16_t eriDataLen
- uint8_t eriData [1024]

8.224.1 Detailed Description

This structure contains Extended Roaming Indicator(ERI) file parameters

Parameters

eriDataLen	• Upon input, the maximum number of bytes that file contents array can contain. • Upon successful output, actual number of bytes written to file contents array
eriData	• ERI data read from persistent storage(Max size is 1024)

8.224.2 Field Documentation

8.224.2.1 uint8_t eriDataparams::eriData[1024]

8.224.2.2 uint16_t eriDataparams::eriDataLen

8.225 ERIFileparams Struct Reference

Data Fields

- WORD * pFileSize
- BYTE * pFile

8.225.1 Detailed Description

This structure contains Extended Roaming Indicator(ERI) file parameters

Parameters

pFileSize[IN/OUT]	• Upon input, the maximum number of bytes that file contents array can contain. • Upon successful output, actual number of bytes written to file contents array
pFile[OUT]	• ERI data read from persistent storage(Max size is 1024)

8.225.2 Field Documentation

8.225.2.1 BYTE* ERIFileparams::pFile

8.225.2.2 WORD* ERIFileparams::pFileSize

8.226 errorRateListElement Struct Reference

Data Fields

- USHORT errorRate
- BYTE radioIf

8.226.1 Detailed Description

This structure contains the Error Rate Information

Parameters

errorRate	• Error rate value corresponds to the RAT that is currently registered. – For CDMA, the error rate reported is Frame Error Rate: * Valid error rate values between 1 and 10000 are returned to indicate percentage, e.g., a value of 300 means the error rate is 3% * A value of 0xFFFF indicates that the error rate is unknown or unavailable – For HDR, the error rate reported is Packet Error Rate: * Valid error rate values between 1 and 10000 are returned to indicate percentage, e.g., a value of 300 means the error rate is 3% * A value of 0xFFFF indicates that the error rate is unknown or unavailable – For GSM, the error rate reported is Bit Error Rate: * Valid values are 0, 100, 200, 300, 400, 500, 600, and 700 The reported value divided by 100 gives the error rate as an RxQual value, e.g.,a value of 300 represents an RxQual value of 3. * A value of 25500 indicates No Data – For WCDMA, the error rate reported is Block Error Rate (BLER): * Valid values are 1 to 10000 * The reported value divided by 100 provides the error rate in percentages, e.g., a value of 300 represents a BLER of 3%. * A value of 0 indicates No Data
radioIf	• Radio interface technology of the signal being measured – 0x00 - RADIO_IF_NO_SVC - None (no service) – 0x01 - RADIO_IF_CDMA_1X - cdma2000® 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS

8.226.2 Field Documentation

8.226.2.1 USHORT errorRateListElement::errorRate

8.226.2.2 BYTE errorRateListElement::radioIf

8.227 eTWSPLMNInfoTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- sMSEtwsPlmnInfo ETWSPLMNInfo

8.227.1 Detailed Description

This structure contains ETWS PLMN TLV information

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response
ETWSPLMNInfo	• ETWS PLMN Information • See sMSEtwsPlmnInfo for more information

8.227.2 Field Documentation

8.227.2.1 sMSEtwsPlmnInfo eTWSPLMNInfoTlv::ETWSPLMNInfo

8.227.2.2 uint8_t eTWSPLMNInfoTlv::TlvPresent

8.228 extDispRecInfo Struct Reference

Data Fields

- BYTE dispType
- BYTE extDispInfoLen
- BYTE extDispInfo [255]

8.228.1 Detailed Description

This structure contains Line Control Information

Parameters

dispType	• Values are per [S1, Table 3.7.5.16-1].
extDispInfoLen	• Number of sets of the following elements: – ext_display_info
extDispInfo	• Extended display information buffer containing the display record; refer to [S1, Section 3.7.5.16] for the format information of the buffer contents.

8.228.2 Field Documentation

8.228.2.1 BYTE extDispRecInfo::dispType

8.228.2.2 BYTE extDispRecInfo::extDispInfo[255]

8.228.2.3 BYTE extDispRecInfo::extDispInfoLen

8.229 FactorySequenceNumber Struct Reference

Data Fields

- BYTE FSNumber [255]

8.229.1 Detailed Description

This structure used to store Factory Sequence Number parameter

Parameters

FSNumber[OUT]	• Facorty Sequence Number • Maximum Length is 255 Bytes

8.229.2 Field Documentation

8.229.2.1 BYTE FactorySequenceNumber::FSNumber[255]

8.230 fileAttributes Struct Reference

Data Fields

- WORD fileSize
- WORD fileID
- BYTE fileType
- WORD recordSize
- WORD recordCount
- BYTE secRead
- WORD secReadMask
- BYTE secWrite
- WORD secWriteMask
- BYTE secIncrease
- WORD secIncreaseMask
- BYTE secDeactivate
- WORD secDeactivateMask
- BYTE secActivate
- WORD secActivateMask
- WORD rawLen
- BYTE rawValue [255]

8.230.1 Detailed Description

This structure contains the information about the File Attributes.

Parameters

fileSize	• Indicates the size of the file.
fileID	• Indicates the ID of the file.

fileType	• Indicates the type of the file. – 0 - Transparent – 1 - Cyclic – 2 - Linear fixed – 3 - Dedicated file – 4 - Master file
recordSize	• Indicates the size of the records. • Only for cyclic and linear fixed files
recordCount	• Indicates the total no. of the records. • Only for linear fixed files
secRead	• Read security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secReadMask	• Mask with read security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM
secWrite	• Write security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secWriteMask	• Mask with write security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM

secIncrease	• Increase security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secIncrease-Mask	• Mask with increase security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM
secDeactivate	• Deactivate security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secDeactivate-Mask	• Mask with deactivate security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM
secActivate	• Activate security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secActivateMask	• Mask with activate security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM
rawLen	• Length of the following elements i.e. raw value.

rawValue[MAX_-DESCRIPTION-_LENGTH]	• Raw value of file attributes.

8.230.2 Field Documentation

8.230.2.1 WORD fileAttributes::fileID

8.230.2.2 WORD fileAttributes::fileSize

8.230.2.3 BYTE fileAttributes::fileType

8.230.2.4 WORD fileAttributes::rawLen

8.230.2.5 BYTE fileAttributes::rawValue[255]

8.230.2.6 WORD fileAttributes::recordCount

8.230.2.7 WORD fileAttributes::recordSize

8.230.2.8 BYTE fileAttributes::secActivate

8.230.2.9 WORD fileAttributes::secActivateMask

8.230.2.10 BYTE fileAttributes::secDeactivate

8.230.2.11 WORD fileAttributes::secDeactivateMask

8.230.2.12 BYTE fileAttributes::secIncrease

8.230.2.13 WORD fileAttributes::secIncreaseMask

8.230.2.14 BYTE fileAttributes::secRead

8.230.2.15 WORD fileAttributes::secReadMask

8.230.2.16 BYTE fileAttributes::secWrite

8.230.2.17 WORD fileAttributes::secWriteMask

8.231 fileInfo Struct Reference

Data Fields

- WORD fileID
- BYTE pathLen
- WORD path [255]

8.231.1 Detailed Description

This structure contains paramaters for file Information

Parameters

fileID	• This is Identifier to SIM files; e.g. in UIM "6F07" is Identifier of IMSI File
pathLen	• Length of file Path
path	• Path value. This value must be the complete path of the file, which is a sequence block of 2 bytes (e.g., 0x3F00 0x7FFF)is for LTE and (0x3F00 ,0x7F20) is for GSM.

8.231.2 Field Documentation

8.231.2.1 WORD fileInfo::fileID

8.231.2.2 WORD fileInfo::path[255]

8.231.2.3 BYTE fileInfo::pathLen

8.232 FirmwareUpdatStat Struct Reference

Data Fields

- ULONG ResCode
- BYTE * pImgType
- ULONG * pRefData
- BYTE * pRefStringLen
- BYTE * pRefString
- BYTE * pLogStringLen
- BYTE * pLogString

8.232.1 Detailed Description

This structure is used to store Firmware Update Status

Parameters

ResCode[OUT]	• FW Update Result Code • Values: – 0x00000001 - Successful – 0xFFFFFFFF - Unknown (due to power off reset after firmware update) – 0x100000nn - File update errors while nn will be the exact error number: * 00 - General error – 0x200000nn - NVUP update errors while nn will be the exact error number: * 00 - General error – 0x40000nnn - FOTA update agent errors while nnn will be the exact error number: * 000 ∼ 0FF - Insignia defined error code * 100 ∼ 1FF - Sierra defined error code * See qaGobiApiTableFwDldErrorCodes.h for more detailed information – 0x800000nn - FDT/SSDP reported errors while nn will be the exact error number * See qaGobiApiTableFwDldErrorCodes.h for more detailed information
pImgType[OUT]	• Optional parameter • Firmware image type that failed the update
pRefData[OUT]	• Optional parameter • Failed image reference data • This is normally the offset of the image that caused the failure
pRefStringLen[IN/OUT]	• Length of Reference String parameter to follow • As input parameter specifies length assigned to pRefString parameter • As output parameter specifies length of actual value retrieved from the device
pRefString[OUT]	• Optional parameter • Failed image reference string. This is normally the partition name of the image that caused the failure if applicable.
pLogStringLen[IN/OUT]	• Length of Reference String parameter to follow • As input parameter specifies length assigned to pRefString parameter • As output parameter specifies length of actual value retrieved from the device
pLogString[OUT]	• Optional parameter • Failed image reference string. This is normally the partition name of the image that caused the failure if applicable.

8.232.2 Field Documentation

8.232.2.1 BYTE* FirmwareUpdatStat::pImgType

8.232.2.2 BYTE* FirmwareUpdatStat::pLogString

8.232.2.3 BYTE* FirmwareUpdatStat::pLogStringLen

8.232.2.4 ULONG* FirmwareUpdatStat::pRefData

8.232.2.5 BYTE* FirmwareUpdatStat::pRefString

8.232.2.6 BYTE* FirmwareUpdatStat::pRefStringLen

8.232.2.7 ULONG FirmwareUpdatStat::ResCode

8.233 FMSImageElement Struct Reference

Data Fields

- uint8_t imageType
- uint8_t imageId [100]
- uint8_t buildIdLength
- uint8_t buildId [100]

8.233.1 Detailed Description

This structure contains the Image Element information

Parameters

imageType	• Type of image 0 - Modem 1 - PRI
imageId	• Unique image identifier
buildIdLength	• Length of the build ID string (may be zero)
pBuildId	• Build ID ANSI string with length provided by the previous field

8.233.2 Field Documentation

8.233.2.1 uint8_t FMSImageElement::buildId[100]

8.233.2.2 uint8_t FMSImageElement::buildIdLength

8.233.2.3 uint8_t FMSImageElement::imageId[100]

8.233.2.4 uint8_t FMSImageElement::imageType

8.234 FMSImageIdElement Struct Reference

Data Fields

- uint8_t storageIndex
- uint8_t failureCount
- uint8_t imageID [100]
- uint8_t buildIDLength
- uint8_t buildID [100]

8.234.1 Detailed Description

This structure contains the Image ID list element Information

Parameters

storageIndex	• Index in storage where the image is located(a value of 0xFF indicates that the storage for this type of image is not relevant)
failureCount	• Number of consecutive write attempts to this storage index that have failed(a value of 0xFF indicates unspecified)
imageID	• Image unique identifier(max 16 chars.)
buildIDLength	• Length of the build ID string. If there is no build ID, this field will be 0 and no data will follow.
buildID	• String containing image build information(Max 100 characters)

8.234.2 Field Documentation

8.234.2.1 uint8_t FMSImageIdElement::buildID[100]

8.234.2.2 uint8_t FMSImageIdElement::buildIDLength

8.234.2.3 uint8_t FMSImageIdElement::failureCount

8.234.2.4 uint8_t FMSImageIdElement::imageID[100]

8.234.2.5 uint8_t FMSImageIdElement::storageIndex

8.235 FMSImageIDEntries Struct Reference

Data Fields

- uint8_t imageType
- uint8_t maxImages
- uint8_t executingImage
- uint8_t imageIDSize
- FMSImageIdElement imageIDElement [50]

8.235.1 Detailed Description

This structure contains the list entry Information

Parameters

imageType	• Type of image – 0 - Modem – 1 - PRI
maxImages	• Maximum number of images of this type that may be stored concurrently on the device
executingImage	• Index (into the next array) of image that is currently executing
imageIDSize	• The number of elements in the image ID list
imageIDElement	• Array of ImageIDElement Structure (Max 50 elements) • See FMSImageIdElement

8.235.2 Field Documentation

8.235.2.1 uint8_t FMSImageIDEntries::executingImage

8.235.2.2 FMSImageIdElement FMSImageIDEntries::imageIDElement[50]

8.235.2.3 uint8_t FMSImageIDEntries::imageIDSize

8.235.2.4 uint8_t FMSImageIDEntries::imageType

8.235.2.5 uint8_t FMSImageIDEntries::maxImages

8.236 FMSImageList Struct Reference

Data Fields

- uint8_t listSize
- FMSImageIDEntries imageIDEntries [2]

8.236.1 Detailed Description

This structure contains the Get Stored Images List

Parameters

listSize	• The number of elements in the image list

imageIDEntries	• Array of ImageIDEntries Structure (Max 2 entries)

8.236.2 Field Documentation

8.236.2.1 FMSImageIDEntries FMSImageList::imageIDEntries[2]

8.236.2.2 uint8_t FMSImageList::listSize

8.237 FMSPrefImageList Struct Reference

Data Fields

- uint8_t listSize
- FMSImageElement listEntries [2]

8.237.1 Detailed Description

This structure contains the Preference Image List information

Parameters

listSize	• The number of elements in the image list
pListEntries	• Array of Image entries with size provided by previous field • See FMSImageElement

8.237.2 Field Documentation

8.237.2.1 FMSImageElement FMSPrefImageList::listEntries[2]

8.237.2.2 uint8_t FMSPrefImageList::listSize

8.238 ForbiddenNetworks3GPP Struct Reference

Data Fields

- WORD forbiddenNwInstLen
- WORD MCC [255]
- WORD MNC [255]
- BYTE TlvPresent

8.238.1 Detailed Description

This structure contains the ForbiddenNetworks3GPP response parameters.

Parameters

forbiddenNwInst-Len	• Number of sets of the following elements – MCC – MNC
MCC	• Mobile Country Code • A 16-bit integer representation of MCC • Range: 0 to 999
MNC	• Mobile Network Code • A 16-bit integer representation of MNC • Range: 0 to 999
TlvPresent	• Tlv Present

8.238.2 Field Documentation

8.238.2.1 WORD ForbiddenNetworks3GPP::forbiddenNwInstLen

8.238.2.2 WORD ForbiddenNetworks3GPP::MCC[255]

8.238.2.3 WORD ForbiddenNetworks3GPP::MNC[255]

8.238.2.4 BYTE ForbiddenNetworks3GPP::TlvPresent

8.239 fwinfo_s Struct Reference

Data Fields

- ULONG FirmwareID
- ULONG Technology
- ULONG Carrier
- ULONG Region
- ULONG GPSCapability

8.239.1 Detailed Description

Gobi firmware image info structure

Parameters

FirmwareID	• Firmware ID obtained from the firmware image
Technology	• Technology (0xFFFFFFFF if unknown)

Carrier	• Carrier (0xFFFFFFFF if unknown)
Region	• Region (0xFFFFFFFF if unknown)
GPSCapability	• GPS capability (0xFFFFFFFF if unknown)

8.239.2 Field Documentation

8.239.2.1 ULONG fwinfo_s::Carrier

8.239.2.2 ULONG fwinfo_s::FirmwareID

8.239.2.3 ULONG fwinfo_s::GPSCapability

8.239.2.4 ULONG fwinfo_s::Region

8.239.2.5 ULONG fwinfo_s::Technology

8.240 GERANInfo Struct Reference

Data Fields

- ULONG cellID
- BYTE plmn [3]
- WORD lac
- WORD arfcn
- BYTE bsic
- ULONG timingAdvance
- WORD rxLev
- BYTE nmrInst
- nmrCellInfo insNmrCellInfo [255]

8.240.1 Detailed Description

This structure contains information about the GERAN Network.

Parameters

cellID	• Cell ID. • 0xFFFFFFFF indicates cell ID information is not present.
plmn[PLMN_LENGTH]	• MCC/MNC information coded as octet 3, 4, and 5. • This field is ignored when nmrCellID is not present.

lac	• Location area code. • This field is ignored when nmrCellID is not present. – 0xFFFF - Not Available
arfcn	• Absolute RF channel number. – 0xFFFF - Not Available
bsic	• Base station identity code. – 0xFF - Not Available
timingAdvance	• Measured delay (in bit periods; 1 bit period = 48/13 microsecond) of access burst transmission on RACH or PRACH to the expected signal from an MS at zero distance under static channel conditions. – 0xFFFFFFFF - Not Available
rxLev	• Serving Cell Rx measurement. • Values range between 0 and 63. • Mapped to a measured signal level: – Rxlev 0 is a signal strength less than -110 dBm – Rxlev 1 is -110 dBm to -109 dBm – Rxlev 2 is -109 dBm to -108 dBm – ... – Rxlev 62 is -49 dBm to -48 dBm – Rxlev 63 is greater than -48 dBm – 0xFFFF - Not Available
nmrInst	• Provides the number of set of instances which follow. • If 0(zero), then no information follows it.
insNmrCellInfo[-MAX_DESCRIP-TION_LENGTH]	• See nmrCellInfo for more information.

8.240.2 Field Documentation

8.240.2.1 WORD GERANInfo::arfcn

8.240.2.2 BYTE GERANInfo::bsic

8.240.2.3 ULONG GERANInfo::cellID

8.240.2.4 nmrCellInfo GERANInfo::insNmrCellInfo[255]

8.240.2.5 WORD GERANInfo::lac

8.240.2.6 BYTE GERANInfo::nmrInst

8.240.2.7 BYTE GERANInfo::plmn[3]

8.240.2.8 WORD GERANInfo::rxLev

8.240.2.9 ULONG GERANInfo::timingAdvance

8.241 geranInstInfo Struct Reference

Data Fields

- WORD geranArfcn
- BYTE geranBsicNcc
- BYTE geranBsicBcc
- SHORT geranRssi

8.241.1 Detailed Description

This structure contains information about the GERAN Instances in UMTS Network.

Parameters

geranArfcn	• Absolute RF channel number.
geranBsicNcc	• Base station identity code network color code. • 0xFF indicates information is not present.
geranBsicBcc	• Base station identity code base station color code. • 0xFF indicates information is not present.
geranRssi	• Received signal strength indicator.

8.241.2 Field Documentation

8.241.2.1 WORD geranInstInfo::geranArfcn

8.241.2.2 BYTE geranInstInfo::geranBsicBcc

8.241.2.3 BYTE geranInstInfo::geranBsicNcc

8.241.2.4 SHORT geranInstInfo::geranRssi

8.242 getAllCallInformation Struct Reference

Data Fields

- callInfo CallInfo
- BYTE isEmpty
- BYTE ALS

8.242.1 Detailed Description

This structure contains information related to call state change.

Parameters

CallInfo	• See callInfo for more information.
isEmpty	• Multiparty indicator. – 0x00 - False – 0x01 - True
ALS	• Alternate Line Service line indicator. • Feature for supporting two different phone numbers on the same mobile device. – 0x00 - ALS_LINE1 - Line 1 (default) – 0x01 - ALS_LINE2 - Line 2

8.242.2 Field Documentation

8.242.2.1 BYTE getAllCallInformation::ALS

8.242.2.2 callInfo getAllCallInformation::CallInfo

8.242.2.3 BYTE getAllCallInformation::isEmpty

8.243 getAllCallRmtPtyName Struct Reference

Data Fields

- BYTE callID
- remotePartyName RemotePartyName

8.243.1 Detailed Description

This structure contains information for All Call Remote Party Names

Parameters

callID	• Unique call identifier for the call.
RemoteParty-Name	• See remotePartyName for more information.

8.243.2 Field Documentation

8.243.2.1 BYTE getAllCallRmtPtyName::callID

8.243.2.2 remotePartyName getAllCallRmtPtyName::RemotePartyName

8.244 getAllCallRmtPtyNum Struct Reference

Data Fields

- BYTE callID
- remotePartyNum RemotePartyNum

8.244.1 Detailed Description

This structure contains information for All Call Remote Party Numbers

Parameters

callID	• Unique call identifier for the call.
RemoteParty-Num	• See remotePartyNum for more information.

8.244.2 Field Documentation

8.244.2.1 BYTE getAllCallRmtPtyNum::callID

8.244.2.2 remotePartyNum getAllCallRmtPtyNum::RemotePartyNum

8.245 GetAudioPathConfigReq Struct Reference

Data Fields

- BYTE Profile
- BYTE Item

8.245.1 Detailed Description

This structure contains the SLQSGetAudioPathConfig request parameters

Parameters

Profile	• Audio Profile – 0-9
Item	• Item – 0 - AV_EC – 1 - AV_NS – 2 - AV_TXVOL – 3 - AV_DTMFTXG – 4 - AV_CODECSTG – 5 - AV_TXPCMIIRFLTR – 6 - AV_RXPCMIIRFLTR – 7 - AV_MICGAIN – 8 - AV_RXAGC – 9 - AV_TXAGC – 10 - AV_RXAGCLIST – 11 - AV_RXAVCLIST – 12 - AV_TXAGCLIST

8.245.2 Field Documentation

8.245.2.1 BYTE GetAudioPathConfigReq::Item

8.245.2.2 BYTE GetAudioPathConfigReq::Profile

8.246 GetAudioPathConfigResp Struct Reference

Data Fields

- BYTE * pECMode
- BYTE * pNSEnable
- WORD * pTXGain
- WORD * pDTMFTXGain
- WORD * pCodecSTGain
- TXPCMIIRFltr * pTXPCMIIRFltr
- RXPCMIIRFltr * pRXPCMIIRFltr
- BYTE * pMICGainSelect
- BYTE * pRXAVCAGCSwitch
- BYTE * pTXAVCSwitch
- RXAGCList * pRXAGCList
- RXAVCList * pRXAVCList
- TXAGCList * pTXAGCList

8.246.1 Detailed Description

This structure contains the SLQSGetAudioPathConfig response parameters.

Parameters

pECMode	[Optional] • AV_EC – 0 - Echo cancellation off – 1 - Handset mode – 2 - Headset mode – 3 - Car kit mode – 4 - Speaker Mode
pNSEnable	[Optional] • AV_NS – 0 - Noise suppression off – 1 - Noise suppression on
pTXGain	[Optional] • AV_TXVOL – 0x0000 - 0xffff
pDTMFTXGain	[Optional] • AV_DTMFTXG – 0x0000 - 0xffff
pCodecSTGain	[Optional] • AV_CODECSTG – 0x0000 - 0xffff
pTXPCMIIRFltr	[Optional] • See TXPCMIIRFltr for more information
pRXPCMIIRFltr	[Optional] • See RXPCMIIRFltr for more information
pMICGainSelect	[Optional] • AV_MICGAIN
pRXAVCAGC-Switch	[Optional] • RX AVC/AGC Switch
pTXAVCSwitch	[Optional] • TX AVC Switch
pRXAGCList	[Optional] • See RXAGCList for more information
pRXAVCList	[Optional] • See RXAVCList for more information
pTXAGCList	[Optional] • See TXAGCList for more information

8.246.2 Field Documentation

8.246.2.1 WORD* GetAudioPathConfigResp::pCodecSTGain

8.246.2.2 WORD* GetAudioPathConfigResp::pDTMFTXGain

8.246.2.3 BYTE* GetAudioPathConfigResp::pECMode

8.246.2.4 BYTE* GetAudioPathConfigResp::pMICGainSelect

8.246.2.5 BYTE* GetAudioPathConfigResp::pNSEnable

8.246.2.6 RXAGCList* GetAudioPathConfigResp::pRXAGCList

8.246.2.7 BYTE* GetAudioPathConfigResp::pRXAVCAGCSwitch

8.246.2.8 RXAVCList* GetAudioPathConfigResp::pRXAVCList

8.246.2.9 RXPCMIIRFltr* GetAudioPathConfigResp::pRXPCMIIRFltr

8.246.2.10 TXAGCList* GetAudioPathConfigResp::pTXAGCList

8.246.2.11 BYTE* GetAudioPathConfigResp::pTXAVCSwitch

8.246.2.12 WORD* GetAudioPathConfigResp::pTXGain

8.246.2.13 TXPCMIIRFltr* GetAudioPathConfigResp::pTXPCMIIRFltr

8.247 GetAudioProfileReq Struct Reference

Data Fields

- BYTE Generator

8.247.1 Detailed Description

This structure contains the SLQSGetAudioProfile request parameters

Parameters

Generator	• Audio Generator – 0 - Voice – 1 - Key Beep – 2 - MIDI

8.247.2 Field Documentation

8.247.2.1 BYTE GetAudioProfileReq::Generator

8.248 GetAudioProfileResp Struct Reference

Data Fields

- BYTE Profile
- BYTE EarMute
- BYTE MicMute
- BYTE Volume

8.248.1 Detailed Description

This structure contains the SLQSGetAudioProfile response parameters.

Parameters

Profile	• Audio Profile – 0 - Handset – 1 - Headset – 2 - Car Kit – 3 - Speaker phone – 4 - Auxiliary – 5 - TTY – 6 - Auxiliary external PCM – 7 - Primary external PCM – 8 - External slave PCM – 9 - I2S
EarMute	• Ear Mute Setting – 0 - unmuted – 1 - muted
MicMute	• MIC Mute Setting – 0 - unmuted – 1 - muted
Volume	• Audio Volume Level – 0 to 7

8.248.2 Field Documentation

8.248.2.1 BYTE GetAudioProfileResp::EarMute

8.248.2.2 BYTE GetAudioProfileResp::MicMute

8.248.2.3 BYTE GetAudioProfileResp::Profile

8.248.2.4 BYTE GetAudioProfileResp::Volume

8.249 GetAudioVolTLBConfigReq Struct Reference

Data Fields

- BYTE Profile
- BYTE Generator
- BYTE Volume
- BYTE Item

8.249.1 Detailed Description

This structure contains the SLQSGetAudioVolTLBConfig request parameters

Parameters

Profile	• Audio Profile – 0-9
Generator	• Audio Generator – 0-2
Volume	• Audio Volume Level – 0-7
Item	• Item – 13 - AV_RXVOLDB – 14 - AV_DTMFVOLDB – 15 - AV_PAD

8.249.2 Field Documentation

8.249.2.1 BYTE GetAudioVolTLBConfigReq::Generator

8.249.2.2 BYTE GetAudioVolTLBConfigReq::Item

8.249.2.3 BYTE GetAudioVolTLBConfigReq::Profile

8.249.2.4 BYTE GetAudioVolTLBConfigReq::Volume

8.250 GetAudioVolTLBConfigResp Struct Reference

Data Fields

- WORD ResCode

8.250.1 Detailed Description

This structure contains the SLQSGetAudioVolTLBConfig response parameters.

Parameters

ResCode	• Result of requested item

8.250.2 Field Documentation

8.250.2.1 WORD GetAudioVolTLBConfigResp::ResCode

8.251 getCallFWExtInfo Struct Reference

Data Fields

- BYTE numInstances
- callFWExtInfo CallFWExtInfo [20]

8.251.1 Detailed Description

This structure contains an array of Call Forwarded Extended Information.

Parameters

numInstances	• Number of callFWExtInfo that follow. • If zero(0) then no further information exists.
CallFWExtInfo[-MAX_NO_OF_-CALLS]	• Array of CallFWExtInfo. – See CallFWExtInfo for more information.

8.251.2 Field Documentation

8.251.2.1 callFWExtInfo getCallFWExtInfo::CallFWExtInfo[20]

8.251.2.2 BYTE getCallFWExtInfo::numInstances

8.252 getCallFWInfo Struct Reference

Data Fields

- BYTE numInstances
- callFWInfo CallFWInfo [20]

8.252.1 Detailed Description

This structure contains an array of Call Forwarded Information.

Parameters

numInstances	• Number of callFWInfo that follow. • If zero(0) then no further information exists.
CallFWInfo[MAX_NO_OF_CALLS]	• Array of callFWInfo. – See callFWInfo for more information.

8.252.2 Field Documentation

8.252.2.1 callFWInfo getCallFWInfo::CallFWInfo[20]

8.252.2.2 BYTE getCallFWInfo::numInstances

8.253 getCustomFeatureV2 Struct Reference

Data Fields

- getCustomInput ∗ pGetCustomInput
- custSettingInfo ∗ pCustSettingInfo
- custSettingList ∗ pCustSettingList

8.253.1 Detailed Description

This struture contains the TLV required to get the Customization Info and customization list.

Parameters

pGetCustomInput[IN]	• Optional parameter • See getCustomInput for more information
pCustSettingInfo[OUT]	• Optional parameter • See custSettingInfo for more information
pCustSettingList[OUT]	• Optional parameter • See custSettingList for more information

8.253.2 Field Documentation

8.253.2.1 custSettingInfo∗ getCustomFeatureV2::pCustSettingInfo

8.253.2.2 custSettingList∗ getCustomFeatureV2::pCustSettingList

8.253.2.3 getCustomInput∗ getCustomFeatureV2::pGetCustomInput

8.254 getCustomInput Struct Reference

Data Fields

- CHAR cust_id [64+1]
- BYTE list_type

8.254.1 Detailed Description

This structure contains which customization id or the list type want to retrieve from modem. This TLV is only applicable for 9x30 modules so far

Parameters

cust_id	• Customization ID (Maximum 64 bytes)
list_type	• list type requested

8.254.2 Field Documentation

8.254.2.1 CHAR getCustomInput::cust_id[64+1]

8.254.2.2 BYTE getCustomInput::list_type

8.255 getDUNCallInfoReq Struct Reference

Data Fields

- ULONG Mask
- BYTE * pReportConnStatus
- TransferStatInd * pTransferStatInd
- BYTE * pReportDormStatus
- BYTE * pReportDataBearerTech
- BYTE * pReportChannelRate

8.255.1 Detailed Description

This structure contains the DUN Call Info Request parameters.

Parameters

Mask	• Mandatory parameter • Set the bits corresponding to the information requested to 1 • All other bits must be set to 0. • If any values are not available or applicable, the corresponding TLVs are not returned in the response. – Bit 0 - Connection Status – Bit 1 - Last call end reason – Bit 2 - Tx/Rx bytes OK – Bit 3 - Dormancy status – Bit 4 - Data bearer – Bit 5 - Channel rate – Bit 6 - Call active duration
pReportConnStatus	• Connect Status Indicator – 0 - Do not report – 1 - Report connection status and call end reason
pTransferStatInd	• See TransferStatInd for more information
pReportDormStatus	• Dormancy Status Indicator – 0 - Do not report – 1 - Report traffic channel state of interface used for data connection
pReportDataBearerTech	• Current Data Bearer Technology Indicator – 0 - Do not report – 1 - Report radio interface used for data transfer when it changes
pReportChannelRate	• Channel Rate Indicator – 0 - Do not report – 1 - Report channel rate

8.255.2 Field Documentation

8.255.2.1 ULONG getDUNCallInfoReq::Mask

8.255.2.2 BYTE* getDUNCallInfoReq::pReportChannelRate

8.255.2.3 BYTE* getDUNCallInfoReq::pReportConnStatus

8.255.2.4 BYTE* getDUNCallInfoReq::pReportDataBearerTech

8.255.2.5 BYTE* getDUNCallInfoReq::pReportDormStatus

8.255.2.6 TransferStatInd* getDUNCallInfoReq::pTransferStatInd

8.256 getDUNCallInfoResp Struct Reference

Data Fields

- ConnectionStatus * pConnectionStatus
- WORD * pCallEndReason
- ULONGLONG * pTXOKBytesCount
- ULONGLONG * pRXOKBytesCount
- BYTE * pDormancyStatus
- BYTE * pDataBearerTech
- ChannelRate * pChannelRate
- ULONGLONG * pLastCallTXOKBytesCnt
- ULONGLONG * pLastCallRXOKBytesCnt
- ULONGLONG * pMdmCallDurationActive
- BYTE * pLastCallDataBearerTech

8.256.1 Detailed Description

This structure contains the DUN Call Info response parameters

Parameters

pConnection-Status	• See ConnectionStatus for more information
pCallEndReason	• Last modem call end reason • See qaGobiApiTableCallEndReasons.h for Call End Reason • Only valid if the last call made was DUN, else zero is returned
pTXOKBytes-Count	• Number of bytes transmitted without error • Returned only if a data call is up
pRXOKBytes-Count	• Number of bytes received without error • Returned only if a data call is up
pDormancy-Status	• Current traffic channel status • Returned if a data call is up – 0x01 - Traffic channel dormant – 0x02 - Traffic channel active

pDataBearer-Tech	• Current data bearer technology • Returned only if a data call is up – 0x01 - cdma2000 1X – 0x02 - cdma2000 HRPD (1xEV-DO) – 0x03 - GSM – 0x04 - UMTS – 0x05 - cdma200 HRPD (1xEV-DO RevA) – 0x06 - EDGE – 0x07 - HSDPA and WCDMA – 0x08 - WCDMA and HSUPA – 0x09 - HSDPA and HSUPA – 0x0A - LTE – 0x0B - cdma2000 EHRPD – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA – 0x10 - HSDPA+ and 64QAM – 0x11 - HSDPA+, 64QAM and HSUPA – 0x12 - TDSCDMA – 0x13 - TDSCDMA and HSDPA – 0xFF - Unknown
pChannelRate	• See ChannelRate for more information
pLastCallTXOK-BytesCnt	• Number of bytes transmitted without error during the last data call (0 if no call was made). • Return only if not in a call and the previous call was made using DUN.
pLastCallRXOK-BytesCnt	• Number of bytes transmitted without error during the last data call (0 if no call was made). • Return only if not in a call and the previous call was made using DUN.
pMdmCall-DurationActive	• Duration that the call is active in milliseconds • If the modem connection status is connected, this represents the active duration of the current DUN call • If the modem connection status is disconnected, this represents the duration of the last DUN call since the device was powered up (0 if no call has been made or if the last call was not DUN)

pLastCallData-BearerTech	• Last Call Data Bearer Technology • Returned only if not in a call and when the previous call was made using DUN – 0x01 - cdma2000 1X – 0x02 - cdma2000 HRPD (1xEV-DO) – 0x03 - GSM – 0x04 - UMTS – 0x05 - cdma200 HRPD (1xEV-DO Rev A) – 0x06 - EDGE – 0x07 - HSDPA and WCDMA – 0x08 - WCDMA and HSUPA – 0x09 - HSDPA and HSUPA – 0x0A - LTE – 0x0B - cdma2000 EHRPD – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA – 0x10 - HSDPA+ and 64QAM – 0x11 - HSDPA+, 64QAM and HSUPA – 0x12 - TDSCDMA – 0x13 - TDSCDMA and HSDPA – 0xFF - Unknown

8.256.2 Field Documentation

8.256.2.1 WORD* getDUNCallInfoResp::pCallEndReason

8.256.2.2 ChannelRate* getDUNCallInfoResp::pChannelRate

8.256.2.3 ConnectionStatus* getDUNCallInfoResp::pConnectionStatus

8.256.2.4 BYTE* getDUNCallInfoResp::pDataBearerTech

8.256.2.5 BYTE* getDUNCallInfoResp::pDormancyStatus

8.256.2.6 BYTE* getDUNCallInfoResp::pLastCallDataBearerTech

8.256.2.7 ULONGLONG* getDUNCallInfoResp::pLastCallRXOKBytesCnt

8.256.2.8 ULONGLONG* getDUNCallInfoResp::pLastCallTXOKBytesCnt

8.256.2.9 ULONGLONG* getDUNCallInfoResp::pMdmCallDurationActive

8.256.2.10 ULONGLONG* getDUNCallInfoResp::pRXOKBytesCount

8.256.2.11 ULONGLONG* getDUNCallInfoResp::pTXOKBytesCount

8.257 getDyingGaspCfg Struct Reference

Data Fields

- BYTE * pDestSMSNum
- BYTE * pDestSMSContent

8.257.1 Detailed Description

This struture contains the TLV required to get the Dysing GASP Config.

Parameters

pDestSMSNum[-OUT]	• SMS Destination Number as string of 8 bit ASCII Characters Max 20 chars. • Optional parameter.
pDestSMS-Content[OUT]	• SMS COntent as a string of 8 bit ASCII text characters Max 160 chars. • Optional parameter.

8.257.2 Field Documentation

8.257.2.1 BYTE* getDyingGaspCfg::pDestSMSContent

8.257.2.2 BYTE* getDyingGaspCfg::pDestSMSNum

8.258 getDyingGaspStatistics Struct Reference

Data Fields

- ULONG * pTimeStamp
- BYTE * pSMSAttemptedFlag

8.258.1 Detailed Description

This struture contains the TLV required to get the Dysing GASP Statistics.

Parameters

pTimeStamp[O-UT]	• Timestamp of the last time power loss was detected and Dying Gasp feature was triggered. • UTC time in seconds since Jan 06, 1980 (GPS Epoch).
pSMS-AttemptedFlag[-OUT]	• Indicates whether device attempted to send SMS in the last power loss event. • 0 - SMS not attempted • 1 - SMS attempted • This only indicates device sent the SMS but does not guarantee network delivery.

8.258.2 Field Documentation

8.258.2.1 BYTE∗ getDyingGaspStatistics::pSMSAttemptedFlag

8.258.2.2 ULONG∗ getDyingGaspStatistics::pTimeStamp

8.259 GetErrRateResp Struct Reference

Data Fields

- WORD ∗ pCDMAFrameErrRate
- WORD ∗ pHDRPackErrRate
- BYTE ∗ pGSMBER
- BYTE ∗ pWCDMABER

8.259.1 Detailed Description

This structure contains information about the SLQSGetErrorRate response parameters.

Parameters

pCDMAFrame-ErrRate[Out]	• CDMA Frame Error Rate • Valid error rate values between 1 and 10000 are returned to indicate the percentage, e.g., a value of 300 means the error rate is 3%. • A value of 0xFFFF indicates that the error rate is unknown/unavailable.
pHDRPackErr-Rate[Out]	• HDR Packet Error Rate • Valid error rate values between 1 and 10000 are returned to indicate the percentage, e.g., a value of 300 means the error rate is 3%. • A value of 0xFFFF indicates that the error rate is unknown/unavailable.
pGSMBER[Out]	• GSM Bit Error Rate • Valid error rate values between 1 and 100 are returned to indicate the percentage value. • A 0% block error rate (BLER) indicates No Data.
pWCDMABER[-Out]	• WCDMA Block Error Rate • Valid error rate values between 1 and 100 are returned to indicate the percentage value. • A value of 0xFF indicates that the error rate is unknown/unavailable.

8.259.2 Field Documentation

8.259.2.1 WORD∗ GetErrRateResp::pCDMAFrameErrRate

8.259.2.2 BYTE∗ GetErrRateResp::pGSMBER

8.259.2.3 WORD∗ GetErrRateResp::pHDRPackErrRate

8.259.2.4 BYTE∗ GetErrRateResp::pWCDMABER

8.260 GetHRPDStatsResp Struct Reference

Data Fields

- DRCParams * pDRCParams
- BYTE * pUATI
- PilotSetData * pPilotSetData

8.260.1 Detailed Description

This structure contains information about the SLQSSwiGetHRPDStats response parameters.

Parameters

pDRCParams[-Out]	• See DRCParams for more information.
pUATI[Out]	• A 128-bit address that includes the access terminal identifier and subnet ID • Size must be 16 bytes
pPilotSetData[-Out]	• See PilotSetData for more information.

8.260.2 Field Documentation

8.260.2.1 DRCParams* GetHRPDStatsResp::pDRCParams

8.260.2.2 PilotSetData* GetHRPDStatsResp::pPilotSetData

8.260.2.3 BYTE* GetHRPDStatsResp::pUATI

8.261 GetIMSSMSConfigParams Struct Reference

Data Fields

- BYTE * pSettingResp
- BYTE * pSMSFormat
- BYTE * pSMSOverIPNwInd
- BYTE * pPhoneCtxtURILen
- BYTE * pPhoneCtxtURI

8.261.1 Detailed Description

This structure contains the SLQSGetIMSSMSConfig response parameters.

Parameters

pSettingResp	• Settings Response

pSMSFormat	• SMS format – 0 - 3GPP – 1 - 3GPP2
pSMSOverIPNw-Ind	• SMS over IP Network Indication Flag – TRUE - Turn on mobile-originated SMS – FALSE - Turn off mobile-originated SMS
pPhoneCtxtURI-Len[IN/OUT]	• Size in bytes assigned to the Phone context Universal Resource Identifier to follow
pPhoneCtxtURI	• Phone context universal resource identifier • Length of this string must be specified in pPhoneCtxtURILen parameter

8.261.2 Field Documentation

8.261.2.1 BYTE∗ GetIMSSMSConfigParams::pPhoneCtxtURI

8.261.2.2 BYTE∗ GetIMSSMSConfigParams::pPhoneCtxtURILen

8.261.2.3 BYTE∗ GetIMSSMSConfigParams::pSettingResp

8.261.2.4 BYTE∗ GetIMSSMSConfigParams::pSMSFormat

8.261.2.5 BYTE∗ GetIMSSMSConfigParams::pSMSOverIPNwInd

8.262 GetIMSUserConfigParams Struct Reference

Data Fields

- BYTE ∗ pSettingResp
- BYTE ∗ pIMSDomainLen
- BYTE ∗ pIMSDomain

8.262.1 Detailed Description

This structure contains the SLQSGetIMSUserConfig response parameters.

Parameters

pSettingResp	• Settings Response
pIMSDomain-Len[IN/OUT]	• Length of IMS Domain Name to follow

pIMSDomain	• IMS domain name • Length of this string must be specified in pIMSDomainLen parameter

8.262.2 Field Documentation

8.262.2.1 BYTE* GetIMSUserConfigParams::pIMSDomain

8.262.2.2 BYTE* GetIMSUserConfigParams::pIMSDomainLen

8.262.2.3 BYTE* GetIMSUserConfigParams::pSettingResp

8.263 GetIMSVoIPConfigResp Struct Reference

Data Fields

- BYTE * pSettingResp
- WORD * pSessionExpiryTimer
- WORD * pMinSessionExpiryTimer
- BYTE * pAmrWbEnable
- BYTE * pScrAmrEnable
- BYTE * pScrAmrWbEnable
- BYTE * pAmrMode
- WORD * pAmrWBMode
- BYTE * pAmrOctetAligned
- BYTE * pAmrWBOctetAligned
- WORD * pRingingTimer
- WORD * pRingBackTimer
- WORD * pRTPRTCPInactTimer

8.263.1 Detailed Description

This structure contains the SLQSGetIMSVoIPConfig request parameters.

Parameters

pSettingResp	• Settings Response. A settings specific error code is returned when the standard response error type is QMI_ERR_CAUSE_CODE
pSessionExpiry-Timer	• Session duration, in seconds
pMinSession-ExpiryTimer	• Minimum allowed value for session expiry timer, in seconds
pAmrWbEnable	• Flag to enable/disable Adaptive Multirate Codec(AMR) WideBand(WB) audio • Values: – True - Enable – False - Disable

pScrAmrEnable	• Flag to enable/disable Source Control Rate(SCR) for AMR NarrowBand (NB) • Values: – True - Enable – False - Disable
pScrAmrWb-Enable	• Flag to enable/disable SCR for AMR WB Audio • Values: – True - Enable – False - Disable
pAmrMode	• BitMask for AMR NB modes allowed • Values: – 0x1 - 4.75 kbps – 0x2 - 5.15 kbps – 0x4 - 5.9 kbps – 0x8 - 6.17 kbps – 0x10 - 7.4 kbps – 0x20 - 7.95 kbps – 0x40 - 10.2 kbps – 0x80 - 12.2 kbps
pAmrWBMode	• BitMask for AMR WB modes allowed • Values: – 0x1 - 6.60 kbps – 0x2 - 8.85 kbps – 0x4 - 12.65 kbps – 0x8 - 14.25 kbps – 0x10 - 15.85 kbps – 0x20 - 18.25 kbps – 0x40 - 19.85 kbps – 0x80 - 23.05 kbps – 0x100 - 23.85 kbps
pAmrOctet-Aligned	• Flag to indicate if the octet is aligned for AMR NB Audio • Values: – True - Aligned – False - Not aligned, Bandwidth Efficient mode
pAmrWBOctet-Aligned	• Flag to indicate if the octet is aligned for AMR WB Audio • Values: – True - Aligned – False - Not aligned, Bandwidth Efficient mode

pRingingTimer	• Duration of ringing timer, in seconds. The ringing timer starts on the ringing event. If the call is not answered within the duration of this timer, the call is disconnected.
pRingBackTimer	• Duration of ringback timer, in seconds. The ringback timer starts on the ringback event. If the call is not answered within the duration of this timer, the call is disconnected.
pRTPRTCP-InactTimer	• Duration of RTP/RTCP inactivity timer, in seconds. If no RTP/RTCP packet is received prior to the expiry of this timer, the call is disconnected.

8.263.2 Field Documentation

8.263.2.1 BYTE* GetIMSVoIPConfigResp::pAmrMode

8.263.2.2 BYTE* GetIMSVoIPConfigResp::pAmrOctetAligned

8.263.2.3 BYTE* GetIMSVoIPConfigResp::pAmrWbEnable

8.263.2.4 WORD* GetIMSVoIPConfigResp::pAmrWBMode

8.263.2.5 BYTE* GetIMSVoIPConfigResp::pAmrWBOctetAligned

8.263.2.6 WORD* GetIMSVoIPConfigResp::pMinSessionExpiryTimer

8.263.2.7 WORD* GetIMSVoIPConfigResp::pRingBackTimer

8.263.2.8 WORD* GetIMSVoIPConfigResp::pRingingTimer

8.263.2.9 WORD* GetIMSVoIPConfigResp::pRTPRTCPInactTimer

8.263.2.10 BYTE* GetIMSVoIPConfigResp::pScrAmrEnable

8.263.2.11 BYTE* GetIMSVoIPConfigResp::pScrAmrWbEnable

8.263.2.12 WORD* GetIMSVoIPConfigResp::pSessionExpiryTimer

8.263.2.13 BYTE* GetIMSVoIPConfigResp::pSettingResp

8.264 GetInstIDResp Struct Reference

Data Fields

- BYTE * pInstanceID
- BYTE * pIPFamily

8.264.1 Field Documentation

8.264.1.1 BYTE* GetInstIDResp::pInstanceID

8.264.1.2 BYTE* GetInstIDResp::pIPFamily

8.265 GetM2MAudioProfileReq Struct Reference

Data Fields

- BYTE * pGenerator

8.265.1 Detailed Description

This structure contains the SLQSGetM2MAudioProfile request parameters.

Parameters

pGenerator[optional]	• Generator – 0 - Voice

8.265.2 Field Documentation

8.265.2.1 BYTE* GetM2MAudioProfileReq::pGenerator

8.266 GetM2MAudioProfileResp Struct Reference

Data Fields

- BYTE Profile
- BYTE EarMute
- BYTE MicMute
- BYTE Generator
- BYTE Volume
- BYTE CwtMute

8.266.1 Detailed Description

This structure contains the SLQSGetM2MAudioProfile response parameters.

Parameters

Profile	• Audio Profile – 0-5
EarMute	• Ear Mute – 0 - Mute – 1 - Unmute

MicMute	• MIC Mute – 0 - Mute – 1 - Unmute
Generator	• Generator – 0 - Voice
Volume	• RX volume level – 0-5
CwtMute	• Call waiting tone Mute – 0 - Mute – 1 - Unmute

8.266.2 Field Documentation

8.266.2.1 BYTE GetM2MAudioProfileResp::CwtMute

8.266.2.2 BYTE GetM2MAudioProfileResp::EarMute

8.266.2.3 BYTE GetM2MAudioProfileResp::Generator

8.266.2.4 BYTE GetM2MAudioProfileResp::MicMute

8.266.2.5 BYTE GetM2MAudioProfileResp::Profile

8.266.2.6 BYTE GetM2MAudioProfileResp::Volume

8.267 GetM2MAudioVolumeReq Struct Reference

Data Fields

- BYTE Profile
- BYTE Generator

8.267.1 Detailed Description

This structure contains the SLQSGetM2MAudioVolume request parameters.

Parameters

Profile	• Audio Profile – 0-5

Generator	• Generator – 0 - Voice

8.267.2 Field Documentation

8.267.2.1 BYTE GetM2MAudioVolumeReq::Generator

8.267.2.2 BYTE GetM2MAudioVolumeReq::Profile

8.268 GetM2MAudioVolumeResp Struct Reference

Data Fields

- BYTE Level

8.268.1 Detailed Description

This structure contains the SLQSGetM2MAudioVolume response parameters.

Parameters

Level	• The RX Volume Level – 0-5

8.268.2 Field Documentation

8.268.2.1 BYTE GetM2MAudioVolumeResp::Level

8.269 GetM2MAVMuteReq Struct Reference

Data Fields

- BYTE Profile

8.269.1 Detailed Description

This structure contains the SLQSGetM2MAVMute request parameters.

Parameters

Profile	• Audio Profile Number – 0-5

8.269.2 Field Documentation

8.269.2.1 BYTE GetM2MAVMuteReq::Profile

8.270 GetM2MAVMuteResp Struct Reference

Data Fields

- BYTE EarMute
- BYTE MicMute
- BYTE CwtMute

8.270.1 Detailed Description

This structure contains the SLQSGetM2MAVMute response parameters.

Parameters

pEarMute	• Ear Mute – 0-Mute – 1-UnMute
pMicMute	• Mic Mute – 0-Mute – 1-unmute
CwtMute	• Waiting tone Mute – 0-5

8.270.2 Field Documentation

8.270.2.1 BYTE GetM2MAVMuteResp::CwtMute

8.270.2.2 BYTE GetM2MAVMuteResp::EarMute

8.270.2.3 BYTE GetM2MAVMuteResp::MicMute

8.271 GetM2MSpkrGainReq Struct Reference

Data Fields

- BYTE Profile

8.271.1 Detailed Description

This structure contains the SLQSGetM2MSpkrGain request parameters.

Parameters

pProfile	• Audio Profile Number – 0-5

8.271.2 Field Documentation

8.271.2.1 BYTE GetM2MSpkrGainReq::Profile

8.272 GetM2MSpkrGainResp Struct Reference

Data Fields

- WORD Value

8.272.1 Detailed Description

This structure contains the SLQSGetM2MSpkrGain response parameters.

Parameters

Value	• RX speakerphone gain – 0x0 - 0x7fff

8.272.2 Field Documentation

8.272.2.1 WORD GetM2MSpkrGainResp::Value

8.273 getMsgWaitingInfo Struct Reference

Data Fields

- BYTE numInstances
- messageWaitingInfoContent msgWaitInfo [0xFF]

8.273.1 Detailed Description

This structure contains Get Message Waiting Info Response parameters

Parameters

numInstances	• Number of sets of the elements in structure messageWaitingInfoContent
pMsgWaitInfo	• Pointer to structure of messageWaitingInfoContent. – See messageWaitingInfoContent for more information.

8.273.2 Field Documentation

8.273.2.1 messageWaitingInfoContent getMsgWaitingInfo::msgWaitInfo[0xFF]

8.273.2.2 BYTE getMsgWaitingInfo::numInstances

8.274 GetNetworkTimeResp Struct Reference

Data Fields

- timeInfo * p3GPP2TimeInfo
- timeInfo * p3GPPTimeInfo

8.274.1 Detailed Description

This structure contains information about the GetNetworkTime response parameters.

Parameters

p3GPP2TimeInfo	[Optional] • See timeInfo for more information
p3GPPTimeInfo	[Optional] • See timeInfo for more information

8.274.2 Field Documentation

8.274.2.1 timeInfo* GetNetworkTimeResp::p3GPP2TimeInfo

8.274.2.2 timeInfo* GetNetworkTimeResp::p3GPPTimeInfo

8.275 GetRegMgrConfigParams Struct Reference

Data Fields

- BYTE * pSettingResp
- WORD * pPCSCFPort
- BYTE * pPriCSCFPortNameLen
- BYTE * pPriCSCFPortName
- BYTE * pIMSTestMode

8.275.1 Detailed Description

This structure contains the SLQSGetRegMgrConfig response parameters.

Parameters

pSettingResp	• Settings Response
pPCSCFPort	• Proxy call session control function port

pPriCSCFPortNameLen(IN/OUT)	• Size in bytes assigned to the primary CSCF Port name parameter to follow
pPriCSCFPortName	• Call Session control port, fully qualified domain name • Length of this string must be specified in pPriCSCFPortNameLen parameter
pIMSTestMode	• IMS Test mode Enabled. – TRUE - Enabled – FALSE - Disabled

Note

pPriCSCFPortNameLen must be set to a valid value during API call to retrieve pPriCSCFPortName.

8.275.2 Field Documentation

8.275.2.1 BYTE* GetRegMgrConfigParams::pIMSTestMode

8.275.2.2 WORD* GetRegMgrConfigParams::pPCSCFPort

8.275.2.3 BYTE* GetRegMgrConfigParams::pPriCSCFPortName

8.275.2.4 BYTE* GetRegMgrConfigParams::pPriCSCFPortNameLen

8.275.2.5 BYTE* GetRegMgrConfigParams::pSettingResp

8.276 GetSessionIDResp Struct Reference

Data Fields

- ULONG * pSessionIDv4
- ULONG * pSessionIDv6

8.276.1 Field Documentation

8.276.1.1 ULONG* GetSessionIDResp::pSessionIDv4

8.276.1.2 ULONG* GetSessionIDResp::pSessionIDv6

8.277 GetSIPConfigResp Struct Reference

Data Fields

- BYTE * pSettingResp
- WORD * pSIPLocalPort
- ULONG * pTimerSIPReg
- ULONG * pSubscribeTimer
- ULONG * pTimerT1

- ULONG * pTimerT2
- ULONG * pTimerTf
- BYTE * pSigCompEnabled

8.277.1 Detailed Description

This structure contains the SLQSGetSIPConfig response parameters.

Parameters

pSettingResp	• Settings Response
pSIPLocalPort	• Primary call session control function SIP port number
pTimerSIPReg	• Initial SIP registration duration from the User equipment, in seconds
pSubscribeTimer	• Duration of the subscription by the UE for IMS registration notifications, in seconds
pTimerT1	• RTT estimate, in milliseconds
pTimerT2	• The maximum retransmit interval for non-invite requests and invite responses, in milliseconds
pTimerTf	• Non-invite transaction timeout timer, in milliseconds
pSigComp-Enabled	• Sig Comp Status – TRUE - Sig Comp Enabled – FALSE - Sig Comp Disabled

8.277.2 Field Documentation

8.277.2.1 BYTE* GetSIPConfigResp::pSettingResp

8.277.2.2 BYTE* GetSIPConfigResp::pSigCompEnabled

8.277.2.3 WORD* GetSIPConfigResp::pSIPLocalPort

8.277.2.4 ULONG* GetSIPConfigResp::pSubscribeTimer

8.277.2.5 ULONG* GetSIPConfigResp::pTimerSIPReg

8.277.2.6 ULONG* GetSIPConfigResp::pTimerT1

8.277.2.7 ULONG* GetSIPConfigResp::pTimerT2

8.277.2.8 ULONG* GetSIPConfigResp::pTimerTf

8.278 GnssData Struct Reference

Data Fields

- ULONGLONG mask

8.278.1 Detailed Description

This structure contains the GNSS data

Parameters

mask	• Mask for the GNSS data that is to be deleted • Valid values: – QMI_LOC_MASK_DELETE_GPS_SVDIR (0x00000001) - Mask to delete GPS SVDIR – QMI_LOC_MASK_DELETE_GPS_SVSTEER (0x00000002) - Mask to delete GPS SVSTEER – QMI_LOC_MASK_DELETE_GPS_TIME (0x00000004) - Mask to delete GPS time – QMI_LOC_MASK_DELETE_GPS_ALM_CORR (0x00000008) - Mask to delete almanac correlation – QMI_LOC_MASK_DELETE_GLO_SVDIR (0x00000010) - Mask to delete GLONASS SVDIR – QMI_LOC_MASK_DELETE_GLO_SVSTEER (0x00000020) - Mask to delete GLONASS SVSTEER – QMI_LOC_MASK_DELETE_GLO_TIME (0x00000040) - Mask to delete GLONASS time – QMI_LOC_MASK_DELETE_GLO_ALM_CORR (0x00000080) - Mask to delete GLONASS almanac correlation – QMI_LOC_MASK_DELETE_SBAS_SVDIR (0x00000100) - Mask to delete SBAS SVDIR – QMI_LOC_MASK_DELETE_SBAS_SVSTEER (0x00000200) - Mask to delete SBAS SVSTEER – QMI_LOC_MASK_DELETE_POSITION (0x00000400) - Mask to delete position estimate – QMI_LOC_MASK_DELETE_TIME (0x00000800) - Mask to delete time estimate – QMI_LOC_MASK_DELETE_IONO (0x00001000) - Mask to delete IONO – QMI_LOC_MASK_DELETE_UTC (0x00002000) - Mask to delete UTC estimate – QMI_LOC_MASK_DELETE_HEALTH (0x00004000) - Mask to delete SV health record – QMI_LOC_MASK_DELETE_SADATA (0x00008000) - Mask to delete SADATA – QMI_LOC_MASK_DELETE_RTI (0x00010000) - Mask to delete RTI – QMI_LOC_MASK_DELETE_SV_NO_EXIST (0x00020000) - Mask to delete SV_NO_EXIST – QMI_LOC_MASK_DELETE_FREQ_BIAS_EST (0x00040000) - Mask to delete frequency bias estimate – QMI_LOC_MASK_DELETE_BDS_SVDIR (0x00080000) - Mask to delete BDS SVDIR – QMI_LOC_MASK_DELETE_BDS_SVSTEER (0x00100000) - Mask to delete BDS SVSTEER – QMI_LOC_MASK_DELETE_BDS_TIME (0x00200000) - Mask to delete BDS time – QMI_LOC_MASK_DELETE_BDS_ALM_CORR (0x00400000) - Mask to delete BDS almanac correlation – QMI_LOC_MASK_DELETE_GNSS_SV_BLACKLIST_GPS (0x00800000) - Mask to delete GNSS SV blacklist GPS – QMI_LOC_MASK_DELETE_GNSS_SV_BLACKLIST_GLO (0x01000000) - Mask to delete GNSS SV blacklist GLO – QMI_LOC_MASK_DELETE_GNSS_SV_BLACKLIST_BDS (0x02000000) - Mask to delete GNSS SV blacklist BDS

8.278.2 Field Documentation

8.278.2.1 ULONGLONG GnssData::mask

8.279 gnssSvInfoNotification Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE bAltitudeAssumed
- satelliteInfo * pSatelliteInfo

8.279.1 Detailed Description

Contain the parameters passed for SetLocGnssSvInfoCallback by the device.

Parameters

bAltitude-Assumed	• Indicates whether altitude is assumed or calculated – 0x00 (FALSE) - Valid altitude is calculated – 0x01 (TRUE) - Valid altitude is assumed; there may not be enough satellites to determine precise altitude
pSatelliteInfo	• See satelliteInfo for more information.

Note

None

8.279.2 Field Documentation

8.279.2.1 BYTE gnssSvInfoNotification::bAltitudeAssumed

8.279.2.2 satelliteInfo* gnssSvInfoNotification::pSatelliteInfo

8.279.2.3 struct qmTlvResult gnssSvInfoNotification::results

8.280 GPRSQoS Struct Reference

Data Fields

- ULONG precedenceClass
- ULONG delayClass
- ULONG reliabilityClass
- ULONG peakThroughputClass
- ULONG meanThroughputClass

8.280.1 Detailed Description

This structure contains the GPRS Quality Of Service Information

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

precedence-Class	• Precedence class
delayClass	• Delay class
reliabilityClass	• Reliability class
peak-Throughput-Class	• Peak throughput class
mean-Throughput-Class	• Mean throughput class

8.280.2 Field Documentation

8.280.2.1 ULONG GPRSQoS::delayClass

8.280.2.2 ULONG GPRSQoS::meanThroughputClass

8.280.2.3 ULONG GPRSQoS::peakThroughputClass

8.280.2.4 ULONG GPRSQoS::precedenceClass

8.280.2.5 ULONG GPRSQoS::reliabilityClass

8.281 GPRSRequestedQoS Struct Reference

Data Fields

- ULONG precedenceClass
- ULONG delayClass
- ULONG reliabilityClass
- ULONG peakThroughputClass
- ULONG meanThroughputClass

8.281.1 Detailed Description

This structure contains the GPRS Quality Of Service Information

Parameters

precedence-Class	• Precedence class
delayClass	• Delay class
reliabilityClass	• Reliability class

peakThroughputClass	• Peak throughput class
meanThroughputClass	• Mean throughput class

8.281.2 Field Documentation

8.281.2.1 ULONG GPRSRequestedQoS::delayClass

8.281.2.2 ULONG GPRSRequestedQoS::meanThroughputClass

8.281.2.3 ULONG GPRSRequestedQoS::peakThroughputClass

8.281.2.4 ULONG GPRSRequestedQoS::precedenceClass

8.281.2.5 ULONG GPRSRequestedQoS::reliabilityClass

8.282 GPSStateInfo Struct Reference

Data Fields

- BYTE EngineState
- ULONG ValidMask
- ULONGLONG Latitude
- ULONGLONG Longitude
- ULONG HorizontalUncertainty
- ULONG Altitude
- ULONG VerticalUncertainty
- ULONG TimeStmp_tow_ms
- WORD TimeStmp_gps_week
- ULONG Time_uncert_ms
- BYTE Iono_valid
- ULONG gps_ephemeris_sv_msk
- ULONG gps_almanac_sv_msk
- ULONG gps_health_sv_msk
- ULONG gps_visible_sv_msk
- ULONG glo_ephemeris_sv_msk
- ULONG glo_almanac_sv_msk
- ULONG glo_health_sv_msk
- ULONG glo_visible_sv_msk
- ULONG sbas_ephemeris_sv_msk
- ULONG sbas_almanac_sv_msk
- ULONG sbas_health_sv_msk
- ULONG sbas_visible_sv_msk
- WORD xtra_start_gps_week
- WORD xtra_start_gps_minutes
- WORD xtra_valid_duration_hours

8.282.1 Detailed Description

GPS state Info.

Parameters

EngineState	• Values: – 0 - OFF – 1 - ON • This field is always valid
ValidMask	• Mask of valid state information data. • Values: – 0x00000001 - Position(latitude/longitude/horizontal uncertainty) – 0x00000002 - Altitude and vertical uncertainty – 0x00000004 - Time ms – 0x00000008 - Time week number – 0x00000010 - Time uncertainty – 0x00000020 - Iono validity – 0x00000040 - GPS ephemeris – 0x00000080 - GPS almanac – 0x00000100 - GPS health – 0x00000200 - GPS visible SVs – 0x00000400 - GLONASS ephemeris – 0x00000800 - GLONASS almanac – 0x00001000 - GLONASS health – 0x00002000 - GLONASS visible SVs – 0x00004000 - SBAS ephemeris – 0x00008000 - SBAS almanac – 0x00010000 - SBAS health – 0x00020000 - SBAS visible SVs – 0x00040000 - XTRA information
Latitude	• Latitude position referenced to the WGS-84 reference ellipsoid, counting positive angles north of the equator and negative angles south of the equator. • Units: Decimal degrees • Range: -90 to +90 degrees. • Value is in double float format (refer to IEEE Std 754-1985)
Longitude	• Longitude position referenced to the WGS-84 reference ellipsoid, counting positive angles east of the Greenwich Meridian and negative angles west of Greenwich meridian. • Units: Decimal degrees • Range: -180 to +180 degrees • Value is in double float format (refer to IEEE Std 754-1985)
Horizontal-Uncertainty	• Circular horizontal uncertainty (in meters). The uncertainty is provided at 63 percent confidence. • Value is in single float format (refer to IEEE Std 754-1985)

Altitude	• Height above the WGS-84 reference ellipsoid. Value conveys height (in meters) plus 500 m • Range -500 to 15883 • Value in single float format (refer to IEEE Std 754-1985)
Vertical-Uncertainty	• Vertical uncertainty (in meters). The uncertainty is provided at 68 percent confidence. • Value in single float format (refer to IEEE Std 754-1985)
TimeStmp_tow_-ms	• Time stamp in GPS time of week(in milliseconds)
TimeStmp_gps-_week	• GPS week number
Time_uncert_ms	• Time uncertainty (in milliseconds). The uncertainty is provided at 99 percent confidence.
Iono_valid	• Iono validity. • Values: – 0 - Invalid – 1 - Valid
gps_ephemeris-_sv_msk	• GPS SV mask for ephemeris; if the bit is set, ephemeris for that SV is available.
gps_almanac_-sv_msk	• GPS SV mask for almanac; if the bit is set, almanac for that SV is available.
gps_health_sv_-msk	• GPS SV mask for health; if the bit is set, health for that SV is available.
gps_visible_sv_-msk	• GPS SV mask for visible Svs; if the bit is set, the SV is available.
glo_ephemeris_-sv_msk	• GLONASS SV mask for ephemeris; if the bit is set, ephemeris for that SV is available.
glo_almanac_sv-_msk	• GLONASS SV mask for almanac; if the bit is set, almanac for that SV is available.
glo_health_sv_-msk	• GLONASS SV mask for health; if the bit is set, health for that SV is available.
glo_visible_sv_-msk	• GLONASS SV mask for visible SVs; if the bit is set, the SV is available.
sbas_-ephemeris_sv_-msk	• SBAS SV mask for ephemeris; if the bit is set, ephemeris for that SV is available.

sbas_almanac_sv_msk	• SBAS SV mask for almanac; if the bit is set, almanac for that SV is available.
sbas_health_sv_msk	• SBAS SV mask for health; if the bit is set, health for that SV is available.
sbas_visible_sv_msk	• SBAS SV mask for visible SVs; if the bit is set, the SV is available.
xtra_start_gps_week	• Current XTRA information is valid starting from this GPS week number
xtra_start_gps_minutes	• Current XTRA information is valid starting from the GPS minutes with the GPS week
xtra_valid_duration_hours	• XTRA information is valid for this many hours starting from the specified GPS week/minutes

8.282.2 Field Documentation

8.282.2.1 ULONG GPSStateInfo::Altitude

8.282.2.2 BYTE GPSStateInfo::EngineState

8.282.2.3 ULONG GPSStateInfo::glo_almanac_sv_msk

8.282.2.4 ULONG GPSStateInfo::glo_ephemeris_sv_msk

8.282.2.5 ULONG GPSStateInfo::glo_health_sv_msk

8.282.2.6 ULONG GPSStateInfo::glo_visible_sv_msk

8.282.2.7 ULONG GPSStateInfo::gps_almanac_sv_msk

8.282.2.8 ULONG GPSStateInfo::gps_ephemeris_sv_msk

8.282.2.9 ULONG GPSStateInfo::gps_health_sv_msk

8.282.2.10 ULONG GPSStateInfo::gps_visible_sv_msk

8.282.2.11 ULONG GPSStateInfo::HorizontalUncertainty

8.282.2.12 BYTE GPSStateInfo::Iono_valid

8.282.2.13 ULONGLONG GPSStateInfo::Latitude

8.282.2.14 ULONGLONG GPSStateInfo::Longitude

8.282.2.15 ULONG GPSStateInfo::sbas_almanac_sv_msk

8.282.2.16 ULONG GPSStateInfo::sbas_ephemeris_sv_msk

8.282.2.17 ULONG GPSStateInfo::sbas_health_sv_msk

8.282.2.18 ULONG GPSStateInfo::sbas_visible_sv_msk

8.282.2.19 ULONG GPSStateInfo::Time_uncert_ms

8.282.2.20 WORD GPSStateInfo::TimeStmp_gps_week

8.282.2.21 ULONG GPSStateInfo::TimeStmp_tow_ms

8.282.2.22 ULONG GPSStateInfo::ValidMask

8.282.2.23 ULONG GPSStateInfo::VerticalUncertainty

8.282.2.24 WORD GPSStateInfo::xtra_start_gps_minutes

8.282.2.25 WORD GPSStateInfo::xtra_start_gps_week

8.282.2.26 WORD GPSStateInfo::xtra_valid_duration_hours

8.283 gpsTime_s Struct Reference

Data Fields

- WORD gpsWeek
- ULONG gpsTimeOfWeekMs

8.283.1 Detailed Description

This structure contains GPS Time info.

Parameters

gpsWeek	• Current GPS week as calculated from midnight, Jan. 6, 1980. • Units - Weeks
gpsTimeOf-WeekMs	• Amount of time into the current GPS week. • Units - Milliseconds

8.283.2 Field Documentation

8.283.2.1 ULONG gpsTime_s::gpsTimeOfWeekMs

8.283.2.2 WORD gpsTime_s::gpsWeek

8.284 gsmCellInfo Struct Reference

Data Fields

- WORD arfcn
- BYTE band1900

- BYTE cellIdValid
- BYTE bsicId
- SHORT rssi
- SHORT srxlev

8.284.1 Detailed Description

This structure contains information about the GSM Cell.

Parameters

arfcn	• GSM frequency being reported. • Range: 0 to 1023.
band1900	• Band indicator for the GSM ARFCN • This field is only valid if arfcn is in the overlapping region. • If TRUE and the cell is in the overlapping region, the ARFCN is on the 1900 band. • If FALSE, it is on the 1800 band.
cellIdValid	• Flag indicating whether the base station identity code ID is valid.
bsicId	• Base station identity code ID, including base station color code and network color code. • The lower 6 bits can be set to any value.
rssi	• Measured RSSI value in 1/10 dB. • Range: -200.0 dB to 0
srxlev	• Cell selection Rx level (Srxlev) value. • Range: -128 to 128. • This field is only valid when ue_in_idle is TRUE.

8.284.2 Field Documentation

8.284.2.1 WORD gsmCellInfo::arfcn

8.284.2.2 BYTE gsmCellInfo::band1900

8.284.2.3 BYTE gsmCellInfo::bsicId

8.284.2.4 BYTE gsmCellInfo::cellIdValid

8.284.2.5 SHORT gsmCellInfo::rssi

8.284.2.6 SHORT gsmCellInfo::srxlev

8.285 GSMRSSIThresh Struct Reference

Data Fields

- BYTE GSMRSSIThreshListLen
- WORD * pGSMRSSIThreshList

8.285.1 Detailed Description

This structure contains GSM RSSI threshold related parameters.

Parameters

GSMRSSI-ThreshListLen	• Length of the GSM RSSI threshold list parameter to follow
pGSMRSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • Maximum of 32 values • Range for RSSI values: -111 to -48 (in dBm)

8.285.2 Field Documentation

8.285.2.1 BYTE GSMRSSIThresh::GSMRSSIThreshListLen

8.285.2.2 WORD* GSMRSSIThresh::pGSMRSSIThreshList

8.286 GSMSrvStatusInfo Struct Reference

Data Fields

- BYTE srvStatus
- BYTE trueSrvStatus
- BYTE isPrefDataPath

8.286.1 Detailed Description

Structure for storing the service status information for GSM, WCDMA and LTE networks.

Parameters

srvStatus	• Service status of the system. – 0x00 - No service – 0x01 - Limited service – 0x02 - Service – 0x03 - Limited regional service – 0x04 - Power save – 0xFF - Not Available

trueSrvStatus	• True service status of the system. • Not applicable to CDMA/HDR. – 0x00 - No service – 0x01 - Limited service – 0x02 - Service – 0x03 - Limited regional service – 0x04 - Power save – 0xFF - Not Available
isPrefDataPath	• Whether the RAT is the preferred data path. – 0x00 - Not preferred – 0x01 - Preferred – 0xFF - Not Available

8.286.2 Field Documentation

8.286.2.1 BYTE GSMSrvStatusInfo::isPrefDataPath

8.286.2.2 BYTE GSMSrvStatusInfo::srvStatus

8.286.2.3 BYTE GSMSrvStatusInfo::trueSrvStatus

8.287 GSMSysInfo Struct Reference

Data Fields

- sysInfoCommon sysInfoGSM
- BYTE lacValid
- WORD lac
- BYTE cellIdValid
- ULONG cellId
- BYTE regRejectInfoValid
- BYTE rejectSrvDomain
- BYTE rejCause
- BYTE networkIdValid
- BYTE MCC [3]
- BYTE MNC [3]
- BYTE egprsSuppValid
- BYTE egprsSupp
- BYTE dtmSuppValid
- BYTE dtmSupp

8.287.1 Detailed Description

Structure for storing the GSM System Information.

Parameters

sysInfoGSM	• See sysInfoCommon for more information.
lacValid	• Indicates whether the location area code is valid.. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
lac	• Location area code. • Only applies to 3GPP. – 0xFFFF - Not Available
cellIdValid	• Indicates whether the cell ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
cellId	• Cell ID. – 0xFFFFFFFF - Not Available
regRejectInfo-Valid	• Indicates whether the registration reject information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
rejectSrvDomain	• Type of service domain in which the registration is rejected. – 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available
rejCause	• Reject cause values sent are specified in [3GPP TS 24.008, Section 10.5.3.6]. – 0xFF - Not Available
networkIdValid	• Indicates whether the network ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

MCC[PLMN_LENGTH]	• Mobile Country Code. • MCC digits in ASCII characters
MNC[PLMN_LENGTH]	• Mobile Network Code. • MNC digits in ASCII characters • An unused byte is set to 0xFF. • In case of two-digit MNC values, the third (unused) digit is set to 0xFF. For example, 15 (a two-digit MNC) is reported using the byte stream 0x31 0x35 0xFF.
egprsSuppValid	• Indicates whether the EGPRS support is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
egprsSupp	• EGPRS support indication. • Only applicable for GSM. – 0x00 - Not available – 0x01 - Available – 0xFF - Not Available
dtmSuppValid	• Indicates whether Dual Transfer mode support is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
dtmSupp	• Dual Transfer mode support indication. • Only applicable for GSM. – 0x00 - Not available – 0x01 - Available – 0xFF - Not Available

8.287.2 Field Documentation

8.287.2.1 ULONG GSMSysInfo::cellId

8.287.2.2 BYTE GSMSysInfo::cellIdValid

8.287.2.3 BYTE GSMSysInfo::dtmSupp

8.287.2.4 BYTE GSMSysInfo::dtmSuppValid

8.287.2.5 BYTE GSMSysInfo::egprsSupp

8.287.2.6 BYTE GSMSysInfo::egprsSuppValid

8.287.2.7 WORD GSMSysInfo::lac

8.287.2.8 BYTE GSMSysInfo::lacValid

8.287.2.9 BYTE GSMSysInfo::MCC[3]

8.287.2.10 BYTE GSMSysInfo::MNC[3]

8.287.2.11 BYTE GSMSysInfo::networkIdValid

8.287.2.12 BYTE GSMSysInfo::regRejectInfoValid

8.287.2.13 BYTE GSMSysInfo::rejCause

8.287.2.14 BYTE GSMSysInfo::rejectSrvDomain

8.287.2.15 sysInfoCommon GSMSysInfo::sysInfoGSM

8.288 gyroAcceptReady_s Struct Reference

Data Fields

- BYTE injectEnable
- WORD samplesPerBatch
- WORD batchPerSec

8.288.1 Detailed Description

This structure contains Gyroscope Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

8.288.2 Field Documentation

8.288.2.1 WORD gyroAcceptReady_s::batchPerSec

8.288.2.2 BYTE gyroAcceptReady_s::injectEnable

8.288.2.3 WORD gyroAcceptReady_s::samplesPerBatch

8.289 gyroTempAcceptReady_s Struct Reference

Data Fields

- BYTE injectEnable
- WORD samplesPerBatch
- WORD batchPerSec

8.289.1 Detailed Description

This structure contains Gyroscope Temperature Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

8.289.2 Field Documentation

8.289.2.1 WORD gyroTempAcceptReady_s::batchPerSec

8.289.2.2 BYTE gyroTempAcceptReady_s::injectEnable

8.289.2.3 WORD gyroTempAcceptReady_s::samplesPerBatch

8.290 HDRECIOThresh Struct Reference

Data Fields

- BYTE HDRECIOThreshListLen
- WORD ∗ pHDRECIOThreshList

8.290.1 Detailed Description

This structure contains HDR ECIO threshold related parameters.

Parameters

HDRECIO-ThreshListLen	• Length of the HDR ECIO threshold list parameter to follow
pHDRECIO-ThreshList	• Array of ECIO thresholds (in units of 0.1 dB) • Maximum of 32 values • Range for ECIO values: -31.5 to 0 (in dB).

8.290.2 Field Documentation

8.290.2.1 BYTE HDRECIOThresh::HDRECIOThreshListLen

8.290.2.2 WORD* HDRECIOThresh::pHDRECIOThreshList

8.291 HDRIOThresh Struct Reference

Data Fields

- BYTE HDRIOThreshListLen
- WORD * pHDRIOThreshList

8.291.1 Detailed Description

This structure contains HDR IO threshold related parameters.

Parameters

HDRIOThresh-ListLen	• Length of the HDR IO threshold list parameter to follow
pHDRIOThresh-List	• Array of IO thresholds (in units of 0.1 dBm) • Maximum of 32 values • Range for IO values: -128 to -13 (in dBm).

8.291.2 Field Documentation

8.291.2.1 BYTE HDRIOThresh::HDRIOThreshListLen

8.291.2.2 WORD* HDRIOThresh::pHDRIOThreshList

8.292 HDRPersonalityInd Struct Reference

Data Fields

- WORD * pCurrentPersonality
- BYTE * pPersonalityListLength
- protocolSubtypeElement * pProtocolSubtypeElement

8.292.1 Field Documentation

8.292.1.1 WORD* HDRPersonalityInd::pCurrentPersonality

8.292.1.2 BYTE* HDRPersonalityInd::pPersonalityListLength

8.292.1.3 protocolSubtypeElement* HDRPersonalityInd::pProtocolSubtypeElement

8.293 HDRPersonalityResp Struct Reference

Data Fields

- WORD * pCurrentPersonality
- BYTE * pPersonalityListLength
- protocolSubtypeElement * pProtocolSubtypeElement

8.293.1 Detailed Description

This structure contains information about the SLQSSwiGetHDRPersonality response parameters.

Parameters

pCurrentPersonality[Out]	• Current active personality index.
pPersonalityListLength[In/Out]	• Number of Personality Protocol Subtype contains in this response. • maximum input value is 3
pProtocolSubtypeElement[Out]	• See protocolSubtypeElement for more information.

8.293.2 Field Documentation

8.293.2.1 WORD* HDRPersonalityResp::pCurrentPersonality

8.293.2.2 BYTE* HDRPersonalityResp::pPersonalityListLength

8.293.2.3 protocolSubtypeElement* HDRPersonalityResp::pProtocolSubtypeElement

8.294 HDRProtSubtypResp Struct Reference

Data Fields

- WORD * pCurrentPrsnlty
- BYTE * pPersonalityListLength

- protocolSubtypeElement * pProtoSubTypElmnt
- ULONGLONG * pAppSubType

8.294.1 Detailed Description

This structure contains information about the SLQSSwiGetHDRProtSubtype response parameters.

Parameters

pCurrent-Personality[Out]	• Current active personality index.
pPersonalityList-Length[In/Out]	• Number of Personality Protocol Subtype contains in this response. • maximum input value is 4
pProtocol-Subtype-Element[Out]	• See protocolSubtypeElement for more information.
pAppSubType[-Out]	• Stream application subtype • Application subtype for each stream,

8.294.2 Field Documentation

8.294.2.1 ULONGLONG* HDRProtSubtypResp::pAppSubType

8.294.2.2 WORD* HDRProtSubtypResp::pCurrentPrsnlty

8.294.2.3 BYTE* HDRProtSubtypResp::pPersonalityListLength

8.294.2.4 protocolSubtypeElement* HDRProtSubtypResp::pProtoSubTypElmnt

8.295 HDRRSSIThresh Struct Reference

Data Fields

- BYTE HDRRSSIThreshListLen
- WORD * pHDRRSSIThreshList

8.295.1 Detailed Description

This structure contains HDR RSSI threshold related parameters.

Parameters

HDRRSSI-ThreshListLen	• Length of the HDR RSSI threshold list parameter to follow
pHDRRSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • Maximum of 32 values. • Range for RSSI values: -118 to -13 (in dBm).

8.295.2 Field Documentation

8.295.2.1 BYTE HDRRSSIThresh::HDRRSSIThreshListLen

8.295.2.2 WORD* HDRRSSIThresh::pHDRRSSIThreshList

8.296 HDRSINRThresh Struct Reference

Data Fields

- BYTE HDRSINRThresListLen
- BYTE * pHDRSINRThresList

8.296.1 Detailed Description

This structure contains HDR SINR threshold related parameters.

Parameters

HDRSINRThres-ListLen	• Length of the HDR SINR threshold list parameter to follow
pHDRSINR-ThresList	• Sequence of thresholds delimiting SINR event reporting bands • Every time a new SINR value crosses a threshold value, an event report indication message with the new SINR value is sent to the requesting control point. For this field – SINR is reported only for HDR – Each SINR threshold value is an unsigned 1 byte value – Maximum number of threshold values is 16 – At least one value must be specified

8.296.2 Field Documentation

8.296.2.1 BYTE HDRSINRThresh::HDRSINRThresListLen

8.296.2.2 BYTE* HDRSINRThresh::pHDRSINRThresList

8.297 HDRSINRThreshold Struct Reference

Data Fields

- BYTE HDRSINRThreshListLen
- WORD * pHDRSINRThreshList

8.297.1 Detailed Description

This structure contains HDR SINR threshold related parameters.

Parameters

HDRSINR-ThreshListLen	• Length of the HDR ECIO threshold list parameter to follow
pHDRSINR-ThreshList	• Array of SINR level thresholds (in units of 1) • maximum of 32 values. • Valid levels are 0 to 8 – 0x00 - SINR_LEVEL_0 is -9 dB – 0x01 - SINR_LEVEL_1 is -6 dB – 0x02 - SINR_LEVEL_2 is -4.5 dB – 0x03 - SINR_LEVEL_3 is -3 dB – 0x04 - SINR_LEVEL_4 is -2 dB – 0x05 - SINR_LEVEL_5 is +1 dB – 0x06 - SINR_LEVEL_6 is +3 dB – 0x07 - SINR_LEVEL_7 is +6 dB – 0x08 - SINR_LEVEL_8 is +9 dB

8.297.2 Field Documentation

8.297.2.1 BYTE HDRSINRThreshold::HDRSINRThreshListLen

8.297.2.2 WORD* HDRSINRThreshold::pHDRSINRThreshList

8.298 hdrSSInfo Struct Reference

Data Fields

- int8_t rssi
- int16_t ecio
- uint8_t sinr
- int32_t io

8.298.1 Detailed Description

This structure contains the parameters for HDR Signal Strength Information

Parameters

rssi	• RSSI in dBm (signed value). • A value of -125 dBm or lower is used to indicate No Signal.
ecio	• ECIO value representing negative 0.5 dBm increments, i.e., 2 means -1 dBm (14 means -7 dBm, 63 means -31.5 dBm).
sinr	• SINR level. • SINR is only applicable for 1xEV-DO. • Valid levels are 0 to 8, where the maximum value for: – 0 - SINR_LEVEL_0 is -9 dB – 1 - SINR_LEVEL_1 is -6 dB – 2 - SINR_LEVEL_2 is -4.5 dB – 3 - SINR_LEVEL_3 is -3 dB – 4 - SINR_LEVEL_4 is -2 dB – 5 - SINR_LEVEL_5 is +1 dB – 6 - SINR_LEVEL_6 is +3 dB – 7 - SINR_LEVEL_7 is +6 dB – 8 - SINR_LEVEL_8 is +9 dB – 0xFF - Not Available
io	• Received IO in dBm. • IO is only applicable for 1xEV-DO.

8.298.2 Field Documentation

8.298.2.1 int16_t hdrSSInfo::ecio

8.298.2.2 int32_t hdrSSInfo::io

8.298.2.3 int8_t hdrSSInfo::rssi

8.298.2.4 uint8_t hdrSSInfo::sinr

8.299 HDRSSInfo Struct Reference

Data Fields

- INT8 rssi
- SHORT ecio
- BYTE sinr
- INT32 io

8.299.1 Detailed Description

This structure contains the parameters for HDR Signal Strength Information

Parameters

rssi	• RSSI in dBm (signed value). • A value of -125 dBm or lower is used to indicate No Signal.
ecio	• ECIO value representing negative 0.5 dBm increments, i.e., 2 means -1 dBm (14 means -7 dBm, 63 means -31.5 dBm).
sinr	• SINR level. • SINR is only applicable for 1xEV-DO. • Valid levels are 0 to 8, where the maximum value for: – 0 - SINR_LEVEL_0 is -9 dB – 1 - SINR_LEVEL_1 is -6 dB – 2 - SINR_LEVEL_2 is -4.5 dB – 3 - SINR_LEVEL_3 is -3 dB – 4 - SINR_LEVEL_4 is -2 dB – 5 - SINR_LEVEL_5 is +1 dB – 6 - SINR_LEVEL_6 is +3 dB – 7 - SINR_LEVEL_7 is +6 dB – 8 - SINR_LEVEL_8 is +9 dB – 0xFF - Not Available
io	• Received IO in dBm. • IO is only applicable for 1xEV-DO.

8.299.2 Field Documentation

8.299.2.1 SHORT HDRSSInfo::ecio

8.299.2.2 INT32 HDRSSInfo::io

8.299.2.3 INT8 HDRSSInfo::rssi

8.299.2.4 BYTE HDRSSInfo::sinr

8.300 HDRSysInfo Struct Reference

Data Fields

- sysInfoCommon sysInfoHDR
- BYTE isSysPrlMatchValid
- BYTE isSysPrlMatch
- BYTE hdrPersonalityValid
- BYTE hdrPersonality
- BYTE hdrActiveProtValid
- BYTE hdrActiveProt
- BYTE is856SysIdValid
- BYTE is856SysId [16]

8.300.1 Detailed Description

Structure for storing the HDR System Information.

Parameters

sysInfoHDR	• See sysInfoCommon for more information.
isSysPrlMatch-Valid	• Indicates whether the system PRL match is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
isSysPrlMatch	• Indicates whether the system is in a PRL. • Only applies to CDMA/HDR. – 0x00 - System is not in a PRL – 0x01 - System is in a PRL – 0xFF - Not Available • If the system is not in a PRL, roam_status carries the value from the default roaming indicator in the PRL. • If the system is in a PRL, roam_status is set to the value based on the standard specification.
hdrPersonality-Valid	• Indicates whether the HDR personality is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
hdrPersonality	• HDR personality information. • Only applicable for HDR. – 0x00 - None – 0x02 - HRPD – 0x03 - eHRPD – 0xFF - Not Available
hdrActiveProt-Valid	• Indicates whether the HDR active protocol revision information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
hdrActiveProt	• HDR active protocol revision information . • Only applicable for HDR. – 0x00 - None – 0x02 - HDR Rel 0 – 0x03 - HDR Rel A – 0x04 - HDR Rel B – 0xFF - Not Available

is856SysIdValid	• Indicates whether the IS-856 system ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
is856SysId[SLQS_SYSTEM_IDSIZE]	• IS-856 system ID. • Only applicable for HDR.

8.300.2 Field Documentation

8.300.2.1 BYTE HDRSysInfo::hdrActiveProt

8.300.2.2 BYTE HDRSysInfo::hdrActiveProtValid

8.300.2.3 BYTE HDRSysInfo::hdrPersonality

8.300.2.4 BYTE HDRSysInfo::hdrPersonalityValid

8.300.2.5 BYTE HDRSysInfo::is856SysId[16]

8.300.2.6 BYTE HDRSysInfo::is856SysIdValid

8.300.2.7 BYTE HDRSysInfo::isSysPrlMatch

8.300.2.8 BYTE HDRSysInfo::isSysPrlMatchValid

8.300.2.9 sysInfoCommon HDRSysInfo::sysInfoHDR

8.301 homeSIDNID Struct Reference

Data Fields

- BYTE numInstances
- sidNid SidNid [255]

8.301.1 Detailed Description

This structure contains the parameters for Home SID/NID Information

Parameters

numInstances	• Number of sets of the following elements: – sid – nid • If zero(0), then no information follows.
SidNid	• See sidNid for more information

8.301.2 Field Documentation

8.301.2.1 BYTE homeSIDNID::numInstances

8.301.2.2 sidNid homeSIDNID::SidNid[255]

8.302 hotSwapStatus Struct Reference

Data Fields

- BYTE hotSwapLength
- BYTE hotSwap [255]

8.302.1 Detailed Description

This structure contains Hot Swap Status Information.

Parameters

hotSwapLength	• Number of sets of the following elements. i.e. hot_swap
hotSwap[MAX_-DESCRIPTION-_LENGTH]	• Indicates the status of the hot-swap switch. – 0 - Hot-swap is not supported – 1 - Hot-swap is supported, but the status of the switch is not supported – 2 - Switch indicates that the card is present – 3 - Switch indicates that the card is not present

8.302.2 Field Documentation

8.302.2.1 BYTE hotSwapStatus::hotSwap[255]

8.302.2.2 BYTE hotSwapStatus::hotSwapLength

8.303 hrpdMTUSizeTlv Struct Reference

Data Fields

- BYTE TlvPresent
- WORD hrpdMTUSize

8.303.1 Detailed Description

This structure contains the parameters for HRPD MTU Size.

Parameters

TlvPresent	• Tlv Present.

hrpdMTUSize	HRPD size • Size of HRPD MTU

8.303.2 Field Documentation

8.303.2.1 WORD hrpdMTUSizeTlv::hrpdMTUSize

8.303.2.2 BYTE hrpdMTUSizeTlv::TlvPresent

8.304 image_info_t Struct Reference

Data Fields

- uint8_t imageType
- uint8_t uniqueID [16]
- uint8_t buildIDLen
- uint8_t buildID [255]

8.304.1 Detailed Description

This structure is used to store image information

Parameters

imageType	• Image Type
	• Values:
	  – 0 - FW
	  – 1 - configuration

uniqueID	• Image Unique Identifier (ASCII characters)
buildIDLen	• Length of build ID string to follow • If set to zero, build ID string will be blank
buildID	• String containing image information(ASCII characters) • Maximum length of this string is 255 chars

8.304.2 Field Documentation

8.304.2.1 uint8_t image_info_t::buildID[255]

8.304.2.2 uint8_t image_info_t::buildIDLen

8.304.2.3 uint8_t image_info_t::imageType

8.304.2.4 uint8_t image_info_t::uniqueID[16]

8.305 ImageElement Struct Reference

Data Fields

- BYTE imageType
- BYTE imageId [100]
- BYTE buildIdLength
- CHAR buildId [100]

8.305.1 Detailed Description

push current alignment to stack set alignment to 1 byte boundary This structure contains the Image Element information

Parameters

imageType	• Type of image 0 - Modem 1 - PRI
imageId	• Unique image identifier
buildIdLength	• Length of the build ID string (may be zero)
buildId	• Build ID ANSI string(Max 100 characters)

8.305.2 Field Documentation

8.305.2.1 CHAR ImageElement::buildId[100]

8.305.2.2 BYTE ImageElement::buildIdLength

8.305.2.3 BYTE ImageElement::imageId[100]

8.305.2.4 BYTE ImageElement::imageType

8.306 ImageIdElement Struct Reference

Data Fields

- BYTE storageIndex
- BYTE failureCount
- BYTE imageID [100]
- BYTE buildIDLength
- CHAR buildID [100]

8.306.1 Detailed Description

push current alignment to stack set alignment to 1 byte boundary This structure contains the Image ID list element Information

Parameters

storageIndex	• Index in storage where the image is located(a value of 0xFF indicates that the storage for this type of image is not relevant)
failureCount	• Number of consecutive write attempts to this storage index that have failed(a value of 0xFF indicates unspecified)
imageID	• Image unique identifier(max 16 chars.)
buildIDLength	• Length of the build ID string. If there is no build ID, this field will be 0 and no data will follow.
buildID	• String containing image build information(Max 100 characters)

8.306.2 Field Documentation

8.306.2.1 CHAR ImageIdElement::buildID[100]

8.306.2.2 BYTE ImageIdElement::buildIDLength

8.306.2.3 BYTE ImageIdElement::failureCount

8.306.2.4 BYTE ImageIdElement::imageID[100]

8.306.2.5 BYTE ImageIdElement::storageIndex

8.307 ImageIDEntries Struct Reference

Data Fields

- BYTE imageType
- BYTE maxImages
- BYTE executingImage
- BYTE imageIDSize
- struct ImageIdElement imageIDElement [50]

8.307.1 Detailed Description

This structure contains the list entry Information

Parameters

imageType	• Type of image – 0 - Modem – 1 - PRI
maxImages	• Maximum number of images of this type that may be stored concurrently on the device
executingImage	• Index (into the next array) of image that is currently executing
imageIDSize	• The number of elements in the image ID list
imageIDElement	• Array of ImageIDElement Structure (Max 50 elements)

8.307.2 Field Documentation

8.307.2.1 BYTE ImageIDEntries::executingImage

8.307.2.2 struct ImageIdElement ImageIDEntries::imageIDElement[50]

8.307.2.3 BYTE ImageIDEntries::imageIDSize

8.307.2.4 BYTE ImageIDEntries::imageType

8.307.2.5 BYTE ImageIDEntries::maxImages

8.308 ImageList Struct Reference

Data Fields

- BYTE listSize
- struct ImageIDEntries imageIDEntries [2]

8.308.1 Detailed Description

This structure contains the Get Stored Images List

Parameters

listSize	• The number of elements in the image list
imageIDEntries	• Array of ImageIDEntries Structure (Max 2 entries)

8.308.2 Field Documentation

8.308.2.1 struct ImageIDEntries ImageList::imageIDEntries[2]

8.308.2.2 BYTE ImageList::listSize

8.309 IMSAIndRegisterInfo Struct Reference

Data Fields

- BYTE * pRegStatusConfig
- BYTE * pServiceStatusConfig
- BYTE * pRatHandoverStatusConfig
- BYTE * pPdpStatusConfig

8.309.1 Detailed Description

This structure contains parameters of IMSA Config Indication Register

Parameters

pRegStatusConfig(optional)	• Register Indication For Registration status. • When this registration is enabled, the device learns of Registration status via the QMI_IMSA_REGISTRATION_STATUS_IND indication. – 0x00 - Disable – 0x01 - Enable
pServiceStatusConfig(optional)	• Register Indication For Service status Events. • When this registration is enabled, the device learns of Service status via the QMI_IMSA_SERVICE_STATUS_IND indication. – 0x00 - Disable – 0x01 - Enable
pRatHandoverStatusConfig(optional)	• Registration Indication For RAT handover status. • When this registration is enabled, the device learns of RAT handover status via the QMI_IMSA_RAT_HANDOVER_STATUS_IND indication. – 0x00 - Disable – 0x01 - Enable
pPdpStatusConfig(optional)	• PDP Status Configuration. – 0x00 - Disable – 0x01 - Enable

Note

One of the optional parameter is mandatory to be present in the request.

8.309.2 Field Documentation

8.309.2.1 BYTE* IMSAIndRegisterInfo::pPdpStatusConfig

8.309.2.2 BYTE* IMSAIndRegisterInfo::pRatHandoverStatusConfig

8.309.2.3 BYTE* IMSAIndRegisterInfo::pRegStatusConfig

8.309.2.4 BYTE* IMSAIndRegisterInfo::pServiceStatusConfig

8.310 imsaPdpStatusInfo Struct Reference

Data Fields

- BYTE connetionState
- ULONG * pFailErrorCode

8.310.1 Detailed Description

Contains the parameters passed for SLQSSetIMSAPdpStatusCallback by the device.

Parameters

connetionState	IMS PDP connection state information. • TRUE - IMS PDP is connected. • FALSE - IMS PDP is not connected.
pFailErrorCode	IMS PDP connection failure error reason code when the IMS PDP Connection State TLV is FALSE. • 0 - Generic failure reason for other than specified • 1 - Option is unsubscribed. • 2 - PDP status was unknown.

8.310.2 Field Documentation

8.310.2.1 BYTE imsaPdpStatusInfo::connetionState

8.310.2.2 ULONG* imsaPdpStatusInfo::pFailErrorCode

8.311 imsaRatStatusInfo Struct Reference

Data Fields

- ULONG * pRATStatus
- ULONG * pSrcRAT
- ULONG * pTgtRAT
- BYTE * pErrorCodeStr

8.311.1 Detailed Description

Contains the parameters passed for SLQSSetIMSARatStatusCallback by the device.

Parameters

pRATStatus	• RAT handover Status

pSrcRAT	• Source RAT
pTgtRAT	• Target RAT
pErrorCodeStr	• Error Code String

8.311.2 Field Documentation

8.311.2.1 BYTE∗ imsaRatStatusInfo::pErrorCodeStr

8.311.2.2 ULONG∗ imsaRatStatusInfo::pRATStatus

8.311.2.3 ULONG∗ imsaRatStatusInfo::pSrcRAT

8.311.2.4 ULONG∗ imsaRatStatusInfo::pTgtRAT

8.312 IMSARegistrationStatus Struct Reference

Data Fields

- BYTE ∗ pImsRegStatus
- WORD ∗ pImsRegErrCode
- ULONG ∗ pNewImsRegStatus

8.312.1 Detailed Description

This structure contains response parameters of registration status.

Parameters

pImsRegStatus	• IMS Registration Status (Deprecated). • Values – TRUE - UE is registered on the IMS network – FALSE - UE is not registered on the IMS network
pImsRegErr-Code	• IMS Registration Error Code. • An error code is returned when the IMS registration status is IMSA_STATUS_NOT_REGISTE-RED. -Values – 3xx - Redirection responses – 4xx - Client failure responses – 5xx - Server failure responses – 6xx - Global failure responses

pNewImsRegStatus	• New IMS Registration Status • Values – 0 - Not registered for IMS – 1 - Registering for IMS – 2 - Registered for IMS

8.312.2 Field Documentation

8.312.2.1 WORD* IMSARegistrationStatus::pImsRegErrCode

8.312.2.2 BYTE* IMSARegistrationStatus::pImsRegStatus

8.312.2.3 ULONG* IMSARegistrationStatus::pNewImsRegStatus

8.313 imsaRegStatusInfo Struct Reference

Data Fields

- BYTE * pbIMSRegistered
- WORD * pRegStatusErrorCode
- ULONG * pImsRegStatus

8.313.1 Detailed Description

Contains the parameters passed for SLQSSetIMSARegStatusCallback by the device.

Parameters

pbIMSRegistered	• TRUE/FALSE
pRegStatusErrorCode	• if IMSA_STATUS_NOT_REGISTERED. Values: 3xx - Redirection responses 4xx - Client failure responses 5xx - Server failure responses 6xx - Global failure responses
pImsRegStatus	IMS registration status. Values: IMSA_STATUS_NOT_REGISTERED - 0 IMSA_STATUS_REGISTERING - 1 IMSA_STATUS_REGISTERED -2

8.313.2 Field Documentation

8.313.2.1 BYTE* imsaRegStatusInfo::pbIMSRegistered

8.313.2.2 ULONG* imsaRegStatusInfo::pImsRegStatus

8.313.2.3 WORD* imsaRegStatusInfo::pRegStatusErrorCode

8.314 IMSAServiceStatus Struct Reference

Data Fields

- ULONG * pSmsServiceStatus
- ULONG * pVoipServiceStatus
- ULONG * pVtServiceStatus
- ULONG * pSmsServiceRat
- ULONG * pVoipServiceRat
- ULONG * pVtServiceRat
- ULONG * pUtServiceStatus
- ULONG * pUtServiceRat
- ULONG * pVsServiceStatus
- ULONG * pVsServiceRat

8.314.1 Detailed Description

This structure contains response parameters of service status for various IMS services.

Parameters

pSmsService-Status	• SMS Service Status. • Values – 0 - IMS SMS service is not available – 1 - IMS SMS is in limited service – 2 - IMS SMS is in full service
pVoipSerive-Status	• VoIP Service Status. -Values – 0 - IMS VoIP service is not available – 2 - IMS VoIP is in full service
pVtService-Status	• VT Service Status • Values – 0 - IMS VT service is not available – 2 - IMS VT is in full service
pSmsServiceRat	• SMS service RAT • Values – 0 - IMS service is registered on WLAN – 1 - IMS service is registered on WWAN – 2 - IMS service is registered on interworking WLAN
pVoipServiceRat	• VoIP service RAT. • Values – 0 - IMS service is registered on WLAN – 1 - IMS service is registered on WWAN – 2 - IMS service is registered on interworking WLAN

pVtServiceRat	• VT service RAT. • Values – 0 - IMS service is registered on WLAN – 1 - IMS service is registered on WWAN – 2 - IMS service is registered on interworking WLAN
pUtService-Status	• UT service Status. • Values – 0 - IMS UT service is not available – 2 - IMS UT is in full service
pUtServiceRat	• UT service RAT. • Values – 0 - IMS service is registered on WLAN – 1 - IMS service is registered on WWAN – 2 - IMS service is registered on interworking WLAN
pVsService-Status	• VS service Status. • Values – 0 - IMS UT service is not available – 2 - IMS UT is in full service
pVsServiceRat	• VS service RAT. • Values – 0 - IMS service is registered on WLAN – 1 - IMS service is registered on WWAN – 2 - IMS service is registered on interworking WLAN

8.314.2 Field Documentation

8.314.2.1 ULONG* IMSAServiceStatus::pSmsServiceRat

8.314.2.2 ULONG* IMSAServiceStatus::pSmsServiceStatus

8.314.2.3 ULONG* IMSAServiceStatus::pUtServiceRat

8.314.2.4 ULONG* IMSAServiceStatus::pUtServiceStatus

8.314.2.5 ULONG* IMSAServiceStatus::pVoipServiceRat

8.314.2.6 ULONG* IMSAServiceStatus::pVoipServiceStatus

8.314.2.7 ULONG* IMSAServiceStatus::pVsServiceRat

8.314.2.8 ULONG* IMSAServiceStatus::pVsServiceStatus

8.314.2.9 ULONG* IMSAServiceStatus::pVtServiceRat

8.314.2.10 ULONG* IMSAServiceStatus::pVtServiceStatus

8.315 IMSASupportedFieldsResp Struct Reference

Data Fields

- struct ReqFieldsList * pReqFieldsList
- struct RespFieldsList * pRespFieldsList
- struct IndFieldsList * pIndFieldsList

8.315.1 Detailed Description

This structure contains response of supported fields by the currently running software.

Parameters

pReqFieldsList	• List of Supported Request Fields. • See ReqFieldsList for more information
pRespFieldsList	• List of Supported Request Fields. • See RespFieldsList for more information
pIndFieldsList	• List of Supported Request Fields. • See IndFieldsList for more information

8.315.2 Field Documentation

8.315.2.1 struct IndFieldsList* IMSASupportedFieldsResp::pIndFieldsList

8.315.2.2 struct ReqFieldsList* IMSASupportedFieldsResp::pReqFieldsList

8.315.2.3 struct RespFieldsList* IMSASupportedFieldsResp::pRespFieldsList

8.316 IMSASupportedMsgInfo Struct Reference

Data Fields

- struct SupportedMsgList * pSupportedMsgList

8.316.1 Detailed Description

This structure contains Queries the set of messages implemented by the currently running software.

Parameters

pSupportedMsg-List	• List of Supported Messages. • See SupportedMsgList for more information

8.316.2 Field Documentation

8.316.2.1 struct SupportedMsgList* IMSASupportedMsgInfo::pSupportedMsgList

8.317 imsaSvcStatusInfo Struct Reference

Data Fields

- ULONG * pSMSSvcStatus
- ULONG * pVOIPSvcStatus
- ULONG * pVTSvcStatus
- ULONG * pSMSSvcRAT
- ULONG * pVOIPSvcRAT
- ULONG * pVTSvcRAT
- ULONG * pUTSvcStatus
- ULONG * pUTSvcRAT

8.317.1 Detailed Description

Contains the parameters passed for SLQSSetIMSASvcStatusCallback by the device.

Parameters

pSMSSvcStatus	IMS SMS NOT AVAILABLE - 0 IMS SMS LIMITED SERVICE - 1 IMS SMS FULL SERVICE - 2
pVOIPSvcStatus	IMS VOIP NOT AVAILABLE - 0 IMS SMS FULL SERVICE -2
pVTSvcStatus	IMS VT NOT AVAILABLE - 0 IMS VT FULL SERVICE - 2
pSMSSvcRAT	IMS service is registered on WLAN - 0 IMS service is registered on WWAN - 1 IMS service is registered on interworking WLAN -2
pVOIPSvcRAT	IMS service is registered on WLAN - 0 IMS service is registered on WWAN - 1 IMS service is registered on interworking WLAN -2 *
pVTSvcRAT	IMS service is registered on WLAN - 0 IMS service is registered on WWAN - 1 IMS service is registered on interworking WLAN -2
pUTSvcStatus	IMS VOIP NOT AVAILABLE - 0 IMS SMS FULL SERVICE -2
pUTSvcRAT	IMS service is registered on WLAN - 0 IMS service is registered on WWAN - 1 IMS service is registered on interworking WLAN -2

8.317.2 Field Documentation

8.317.2.1 ULONG* imsaSvcStatusInfo::pSMSSvcRAT

8.317.2.2 ULONG* imsaSvcStatusInfo::pSMSSvcStatus

8.317.2.3 ULONG* imsaSvcStatusInfo::pUTSvcRAT

8.317.2.4 ULONG* imsaSvcStatusInfo::pUTSvcStatus

8.317.2.5 ULONG* imsaSvcStatusInfo::pVOIPSvcRAT

8.317.2.6 ULONG* imsaSvcStatusInfo::pVOIPSvcStatus

8.317.2.7 ULONG* imsaSvcStatusInfo::pVTSvcRAT

8.317.2.8 ULONG* imsaSvcStatusInfo::pVTSvcStatus

8.318 imsCfgIndRegisterInfo Struct Reference

Data Fields

- BYTE * pSIPConfigEvents
- BYTE * pRegMgrConfigEvents
- BYTE * pSMSConfigEvents
- BYTE * pUserConfigEvents
- BYTE * pVoIPConfigEvents

8.318.1 Detailed Description

This structure contains parameters of IMS Config Indication Register

Parameters

pSIPConfigEvents(optional)	• Registration Indication For SIP Configuration Events. • When this registration is enabled, the device learns of SIP config events via the QMI_IMS_SIP_CONFIG_IND indication. – 0x00 - Disable – 0x01 - Enable
pRegMgrConfigEvents(optional)	• Registration Indication For Registration Manager Configuration Events. • When this registration is enabled, the device learns of Reg Mgr config events via the QMI_IMS_REG_MGR_CONFIG_IND indication. – 0x00 - Disable – 0x01 - Enable
pSMSConfigEvents(optional)	• Registration Indication For SMS Configuration Events. • When this registration is enabled, the device learns of SMS config events via the QMI_IMS_SMS_CONFIG_IND indication. – 0x00 - Disable – 0x01 - Enable
pUserConfigEvents(optional)	• Registration Indication For User Configuration Events. • When this registration is enabled, the device learns of user config events via the QMI_IMS_USER_CONFIG_IND indication. – 0x00 - Disable – 0x01 - Enable

pVoIPConfig-Events(optional)	• Registration Indication For VoIP Configuration Events. • When this registration is enabled, the device learns of VOIP config events via the QMI_IMS_VOIP_CONFIG_IND indication. – 0x00 - Disable – 0x01 - Enable

Note

One of the optional parameter is mandatory to be present in the request.

8.318.2 Field Documentation

8.318.2.1 BYTE∗ imsCfgIndRegisterInfo::pRegMgrConfigEvents

8.318.2.2 BYTE∗ imsCfgIndRegisterInfo::pSIPConfigEvents

8.318.2.3 BYTE∗ imsCfgIndRegisterInfo::pSMSConfigEvents

8.318.2.4 BYTE∗ imsCfgIndRegisterInfo::pUserConfigEvents

8.318.2.5 BYTE∗ imsCfgIndRegisterInfo::pVoIPConfigEvents

8.319 imsRegMgrConfigInfo Struct Reference

Data Fields

- WORD ∗ pPriCSCFPort
- BYTE ∗ pCSCFPortName
- BYTE ∗ pIMSTestMode

8.319.1 Detailed Description

Contains the parameters passed for SLQSSetRegMgrConfigCallback by the device.

Parameters

pPriCSCFPort	• Primary call session control function port
pCSCFPort-Name	• Call Session control port, fully qualified domain name • Length of this string can be of maximum 255 bytes
pIMSTestMode	• IMS Test mode Enabled. – TRUE - Enable, no IMS registration – FALSE - Disable, IMS registration is initiated

8.319.2 Field Documentation

8.319.2.1 BYTE∗ imsRegMgrConfigInfo::pCSCFPortName

8.319.2.2 BYTE∗ imsRegMgrConfigInfo::pIMSTestMode

8.319.2.3 WORD∗ imsRegMgrConfigInfo::pPriCSCFPort

8.320 imsSIPConfigInfo Struct Reference

Data Fields

- WORD ∗ pSIPLocalPort
- ULONG ∗ pTimerSIPReg
- ULONG ∗ pSubscribeTimer
- ULONG ∗ pTimerT1
- ULONG ∗ pTimerT2
- ULONG ∗ pTimerTf
- BYTE ∗ pSigCompEnabled

8.320.1 Detailed Description

Contains the parameters passed for SLQSSetSIPConfigCallback by the device.

Parameters

pSIPLocalPort	• Primary call session control function SIP port number
pTimerSIPReg	• Initial SIP registration duration from the User equipment, in seconds
pSubscribeTimer	• Duration of the subscription by the UE for IMS registration notifications, in seconds
pTimerT1	• RTT estimate, in milliseconds
pTimerT2	• The maximum retransmit interval for non-invite requests and invite responses, in milliseconds
pTimerTf	• Non-invite transaction timeout timer, in milliseconds
pSigComp-Enabled	• Sig Comp Status – TRUE - Enable – FALSE - Disable

Note

None

8.320.2 Field Documentation

8.320.2.1 BYTE* imsSIPConfigInfo::pSigCompEnabled

8.320.2.2 WORD* imsSIPConfigInfo::pSIPLocalPort

8.320.2.3 ULONG* imsSIPConfigInfo::pSubscribeTimer

8.320.2.4 ULONG* imsSIPConfigInfo::pTimerSIPReg

8.320.2.5 ULONG* imsSIPConfigInfo::pTimerT1

8.320.2.6 ULONG* imsSIPConfigInfo::pTimerT2

8.320.2.7 ULONG* imsSIPConfigInfo::pTimerTf

8.321 imsSMSConfigInfo Struct Reference

Data Fields

- BYTE * pSMSFormat
- BYTE * pSMSOverIPNwInd
- BYTE * pPhoneCtxtURI

8.321.1 Detailed Description

Contains the parameters passed for SLQSSetIMSSMSConfigCallback by the device.

Parameters

pSMSFormat	• SMS format – 0 - 3GPP – 1 - 3GPP2
pSMSOverIPNw-Ind	• SMS over IP Network Indication Flag – TRUE - Mobile-Originated(MO) SMS turned on – FALSE - MO SMS turned off
pPhoneCtxtURI	• Phone context universal resource identifier • Length of this string can be of maximum 255 bytes

8.321.2 Field Documentation

8.321.2.1 BYTE* imsSMSConfigInfo::pPhoneCtxtURI

8.321.2.2 BYTE* imsSMSConfigInfo::pSMSFormat

8.321.2.3 BYTE* imsSMSConfigInfo::pSMSOverIPNwInd

8.322 imsUserConfigInfo Struct Reference

Data Fields

- BYTE * pIMSDomain

8.322.1 Detailed Description

Contains the parameters passed for SLQSSetIMSUserConfigCallback by the device.

Parameters

pIMSDomain	• IMS domain name • Length of this string can be of maximum 255 bytes

8.322.2 Field Documentation

8.322.2.1 BYTE* imsUserConfigInfo::pIMSDomain

8.323 imsVoIPConfigInfo Struct Reference

Data Fields

- WORD * pSessionExpiryTimer
- WORD * pMinSessionExpiryTimer
- BYTE * pAmrWbEnable
- BYTE * pScrAmrEnable
- BYTE * pScrAmrWbEnable
- BYTE * pAmrMode
- WORD * pAmrWBMode
- BYTE * pAmrOctetAligned
- BYTE * pAmrWBOctetAligned
- WORD * pRingingTimer
- WORD * pRingBackTimer
- WORD * pRTPRTCPInactTimer

8.323.1 Detailed Description

Contains the parameters passed for SLQSSetIMSVoIPConfigCallback by the device.

Parameters

pSessionExpiry-Timer	• Session duration, in seconds
pMinSession-ExpiryTimer	• Minimum allowed value for session expiry timer, in seconds

pAmrWbEnable	• Flag to enable/disable Adaptive Multirate Codec(AMR) WideBand(WB) audio • Values: – True - Enabled – False - Disabled
pScrAmrEnable	• Flag to enable/disable Source Control Rate(SCR) for AMR NarrowBand (NB) • Values: – True - Enabled – False - Disabled
pScrAmrWb-Enable	• Flag to enable/disable SCR for AMR WB Audio • Values: – True - Enabled – False - Disabled
pAmrMode	• BitMask for AMR NB modes allowed • Values: – 0x1 - 4.75 kbps – 0x2 - 5.15 kbps – 0x4 - 5.9 kbps – 0x8 - 6.17 kbps – 0x10 - 7.4 kbps – 0x20 - 7.95 kbps – 0x40 - 10.2 kbps – 0x80 - 12.2 kbps
pAmrWBMode	• BitMask for AMR WB modes allowed • Values: – 0x1 - 6.60 kbps – 0x2 - 8.85 kbps – 0x4 - 12.65 kbps – 0x8 - 14.25 kbps – 0x10 - 15.85 kbps – 0x20 - 18.25 kbps – 0x40 - 19.85 kbps – 0x80 - 23.05 kbps – 0x100 - 23.85 kbps
pAmrOctet-Aligned	• Flag to indicate if the octet is aligned for AMR NB Audio • Values: – True - Aligned – False - Not aligned, Bandwidth Efficient mode

pAmrWBOctet-Aligned	• Flag to indicate if the octet is aligned for AMR WB Audio • Values: – True - Aligned – False - Not aligned, Bandwidth Efficient mode
pRingingTimer	• Duration of ringing timer, in seconds. The ringing timer starts on the ringing event. If the call is not answered within the duration of this timer, the call is disconnected.
pRingBackTimer	• Duration of ringback timer, in seconds. The ringback timer starts on the ringback event. If the call is not answered within the duration of this timer, the call is disconnected.
pRTPRTCP-InactTimer	• Duration of RTP/RTCP inactivity timer, in seconds. If no RTP/RTCP packet is received prior to the expiry of this timer, the call is disconnected.

8.323.2 Field Documentation

8.323.2.1 BYTE* imsVoIPConfigInfo::pAmrMode

8.323.2.2 BYTE* imsVoIPConfigInfo::pAmrOctetAligned

8.323.2.3 BYTE* imsVoIPConfigInfo::pAmrWbEnable

8.323.2.4 WORD* imsVoIPConfigInfo::pAmrWBMode

8.323.2.5 BYTE* imsVoIPConfigInfo::pAmrWBOctetAligned

8.323.2.6 WORD* imsVoIPConfigInfo::pMinSessionExpiryTimer

8.323.2.7 WORD* imsVoIPConfigInfo::pRingBackTimer

8.323.2.8 WORD* imsVoIPConfigInfo::pRingingTimer

8.323.2.9 WORD* imsVoIPConfigInfo::pRTPRTCPInactTimer

8.323.2.10 BYTE* imsVoIPConfigInfo::pScrAmrEnable

8.323.2.11 BYTE* imsVoIPConfigInfo::pScrAmrWbEnable

8.323.2.12 WORD* imsVoIPConfigInfo::pSessionExpiryTimer

8.324 IndFieldsList Struct Reference

Data Fields

- BYTE indicationFieldsLen
- BYTE indicationFields [256]

8.324.1 Detailed Description

This structure contains the Supported Indication Fields List Information

Parameters

indicationFields-Len	• Number of sets of the indication fields.
indicationFields	• Describes which optional field IDs are supported in QMI indication. • Format is same as request field.

8.324.2 Field Documentation

8.324.2.1 BYTE IndFieldsList::indicationFields[256]

8.324.2.2 BYTE IndFieldsList::indicationFieldsLen

8.325 infoInterFreq Struct Reference

Data Fields

- WORD earfcn
- BYTE threshXLow
- BYTE threshXHigh
- BYTE cell_resel_priority
- BYTE cells_len
- cellParams cellInterFreqParams [255]

8.325.1 Detailed Description

This structure contains information about the inter-frequency.

Parameters

earfcn	• E-UTRA absolute radio frequency channel number of the serving cell. • Range: 0 to 65535.
threshXLow	• Cell Srxlev low threshold. • Range: 0 to 31. • When the serving cell does not exceed thresh_serving_low, the value of an evaluated cell must be smaller than this value to be considered for re-selection.
threshXHigh	• Cell Srxlev high threshold. • Range: 0 to 31. • When the serving cell exceeds thresh_serving_low, the value of an evaluated cell must be greater than this value to be considered for re-selection.

cell_resel_-priority	• Cell re-selection priority • Range: 0 to 7. • This field is only valid when ue_in_idle is TRUE.
cells_len	• Provides the number of set of cell params.
cellInterFreq-Params[MAX_D-ESCRIPTION_L-ENGTH]	• See cellParams for more information.

8.325.2 Field Documentation

8.325.2.1 BYTE infoInterFreq::cell_resel_priority

8.325.2.2 cellParams infoInterFreq::cellInterFreqParams[255]

8.325.2.3 BYTE infoInterFreq::cells_len

8.325.2.4 WORD infoInterFreq::earfcn

8.325.2.5 BYTE infoInterFreq::threshXHigh

8.325.2.6 BYTE infoInterFreq::threshXLow

8.326 intfaceCfgTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG CurrentCfgType
- ULONG CfgValue

8.326.1 Detailed Description

This structure contains the parameters for host usb interface composition

Parameters

TlvPresent	• Tlv Present.
CurrentCfgType	• Current configure type, see values below: – 1 - MBIM – 2 - USBIF + PCIE – 3 - RMNET – 4 - RNDIS – 5 - PCIE only

CfgValue	• Host composition bit mask, see supported USB interface bitmasks, not supported by QMI object setting for 9x50 modules – 0x00000001 - DIAG interface – 0x00000002 - ADB interface – 0x00000004 - NMEA interface – 0x00000008 - MODEM interface – 0x00000010 - RESERVED5 – 0x00000020 - RESERVED6 – 0x00000040 - RESERVED7 – 0x00000080 - RESERVED8 – 0x00000100 - RMENT0 interface – 0x00000200 - RESERVED10 – 0x00000400 - RMENT1 interface – 0x00000800 - RESERVED12 – 0x00001000 - MBIM interface – 0x00002000 - RESERVED14 – 0x00004000 - RNDIS interface – 0x00008000 - RESERVED16 – 0x00010000 - AUDIO interface – 0x00020000 - RESERVED18 – 0x00080000 - ECM interface – 0x00100000 - RESERVED21 – 0x00200000 - RESERVED22 – 0xFFC00000 - RESERVED

8.326.2 Field Documentation

8.326.2.1 ULONG intfaceCfgTlv::CfgValue

8.326.2.2 ULONG intfaceCfgTlv::CurrentCfgType

8.326.2.3 BYTE intfaceCfgTlv::TlvPresent

8.327 IOThresh Struct Reference

Data Fields

- BYTE IOThresListLen
- INT32 * pIOThresList

8.327.1 Detailed Description

This structure contains IO threshold related parameters.

Parameters

IOThresListLen	• Length of the LTE SNR threshold list parameter to follow

pIOThresList	• Sequence of thresholds delimiting IO event reporting bands • Every time a new IO value crosses a threshold value, an event report indication message with the new IO value is sent to the requesting control point. For this field – IO is applicable only for HDR – Each IO threshold value is a signed 4 byte value – Maximum number of threshold values is 16 – At least one value must be specified

8.327.2 Field Documentation

8.327.2.1 BYTE IOThresh::IOThresListLen

8.327.2.2 INT32* IOThresh::pIOThresList

8.328 IPv4Addr Struct Reference

Data Fields

- ULONG addr
- ULONG subnetMask

8.328.1 Detailed Description

This structure contains the IPv4 filter address

Parameters

addr	IPv4 address
subnetMask	A packet matches if: • (addr and subnetMask) == (IP pkt addr & subnetMask) Callers to set up a filter with a range of source addresses, if needed; subnet mask of all 1s (255.255.255.255) specifies a single address value

8.328.2 Field Documentation

8.328.2.1 ULONG IPv4Addr::addr

8.328.2.2 ULONG IPv4Addr::subnetMask

8.329 IPv4Config Struct Reference

Data Fields

- ULONG IPv4Addr
- WORD IPv4Port

8.329.1 Detailed Description

This structure specifies information regarding the IPv4 address and port.

Parameters

IPv4Addr	• IPv4 address.
IPv4Port	• IPv4 port.

8.329.2 Field Documentation

8.329.2.1 ULONG IPv4Config::IPv4Addr

8.329.2.2 WORD IPv4Config::IPv4Port

8.330 IPv4Info Struct Reference

Data Fields

- ULONG address
- WORD port
- BYTE TlvPresent

8.330.1 Detailed Description

This structure contains LOC Server IPV4 info field.

Parameters

address	• IPv4 address.
port	• IPv4 port.
TlvPresent	• Tlv Present or not

8.330.2 Field Documentation

8.330.2.1 ULONG IPv4Info::address

8.330.2.2 WORD IPv4Info::port

8.330.2.3 BYTE IPv4Info::TlvPresent

8.331 IPv6Addr Struct Reference

Data Fields

- BYTE addr [16]
- BYTE prefixLen

8.331.1 Detailed Description

This structure contains the IPv6 filter address

Parameters

addr	IPv6 address (in network byte order); this is a 16-byte byte array (in Big-endian format)
prefixLen	IPv6 filter prefix length; can take a value between 0 and 128 Note: A packet matches if the IPv6 source address bytes until the prefix lengths are equal. Therefore prefix length can be used to set a filter with a range of source addresses. A prefix length of 128 specifies a single address value.

8.331.2 Field Documentation

8.331.2.1 BYTE IPv6Addr::addr[16]

8.331.2.2 BYTE IPv6Addr::prefixLen

8.332 ipv6AddressInfo Struct Reference

Data Fields

- uint8_t IPV6PrefixLen
- uint16_t IPAddressV6 [8]

8.332.1 Detailed Description

This structure contains the IPv6 address information

Parameters

IPV6PrefixLen	Length of the received IPv6 address • 0xff - Invalid IPv6 address information.
IPAddressV6	IPv6 address(in network byte order)

8.332.2 Field Documentation

8.332.2.1 uint16_t ipv6AddressInfo::IPAddressV6[8]

8.332.2.2 uint8_t ipv6AddressInfo::IPV6PrefixLen

8.333 IPV6AddressInfo Struct Reference

Data Fields

- BYTE IPV6PrefixLen
- USHORT IPAddressV6 [8]

8.333.1 Detailed Description

This structure contains the IPV6 Address Information

Parameters

IPV6PrefixLen	• Length of the received IPv6 address in no. of bits; can take value between 0 and 128 – 0xFF - Not Available
IPAddressV6	• IPv6 address(in network byte order); This is an 8-element array of 16 bit numbers, each of which is in big endian format.

8.333.2 Field Documentation

8.333.2.1 USHORT IPV6AddressInfo::IPAddressV6[8]

8.333.2.2 BYTE IPV6AddressInfo::IPV6PrefixLen

8.334 IPv6Config Struct Reference

Data Fields

- WORD IPv6Addr [8]
- ULONG IPv6Port

8.334.1 Detailed Description

This structure specifies information regarding the IPv6 address and port.

Parameters

IPv6Addr	• IPv6 address. • Type - Array of unsigned integers • Maximum length of the array: 8
IPv6Port	• IPv6 port.

8.334.2 Field Documentation

8.334.2.1 WORD IPv6Config::IPv6Addr[8]

8.334.2.2 ULONG IPv6Config::IPv6Port

8.335 IPV6GWAddressInfo Struct Reference

Data Fields

- BYTE gwV6PrefixLen
- USHORT gwAddressV6 [8]

8.335.1 Detailed Description

This structure contains the IPV6 Gateway Address Information

Parameters

gwV6PrefixLen	• Length of the received IPv6 Gateway address in no. of bits; can take value between 0 and 128
IPAddressV6	• IPv6 Gateway address(in network byte order); This is an 8-element array of 16 bit numbers, each of which is in big endian format.

8.335.2 Field Documentation

8.335.2.1 USHORT IPV6GWAddressInfo::gwAddressV6[8]

8.335.2.2 BYTE IPV6GWAddressInfo::gwV6PrefixLen

8.336 IPv6Info Struct Reference

Data Fields

- WORD address [8]
- ULONG port
- BYTE TlvPresent

8.336.1 Detailed Description

This structure contains LOC Get Server IPV6 info field.

Parameters

address	• IPv6 address. • Type - Array of unsigned integers • Maximum length of the array - 8
port	• IPv6 port.
TlvPresent	• Tlv Present or not

8.336.2 Field Documentation

8.336.2.1 WORD IPv6Info::address[8]

8.336.2.2 ULONG IPv6Info::port

8.336.2.3 BYTE IPv6Info::TlvPresent

8.337 IPv6TrafCls Struct Reference

Data Fields

- BYTE val
- BYTE mask

8.337.1 Detailed Description

This structure contains the IPv6 filter traffic class

Parameters

val	The traffic class value
mask	The packet matches the traffic class filter if: (IPv6_filter_traffic_class_val and IPv6_filter_traffic_class_mask) == (Traffic class value in the IP packet & IPv6_filter_traffic_class_mask) Example: • IPv6_filter_tc_val = 00101000 • IPv6_filter_tc_mask = 11111100 Filter will compare only the first 6 bits in IPv6_filter_traffic_class with the first 6 bits in the traffic class field of the IP packet; first 6 bits in the traffic class field of the IP packet must be 001010 to match filter; last 2 bits can be anything, since they are ignored by filtering

8.337.2 Field Documentation

8.337.2.1 BYTE IPv6TrafCls::mask

8.337.2.2 BYTE IPv6TrafCls::val

8.338 LibPackGPRSRequestedQoS Struct Reference

Data Fields

- uint32_t precedenceClass
- uint32_t delayClass
- uint32_t reliabilityClass
- uint32_t peakThroughputClass
- uint32_t meanThroughputClass

8.338.1 Detailed Description

This structure contains the GPRS Quality Of Service Information

Parameters

precedence-Class	• Precedence class

delayClass	• Delay class
reliabilityClass	• Reliability class
peak-Throughput-Class	• Peak throughput class
mean-Throughput-Class	• Mean throughput class

8.338.2 Field Documentation

8.338.2.1 uint32_t LibPackGPRSRequestedQoS::delayClass

8.338.2.2 uint32_t LibPackGPRSRequestedQoS::meanThroughputClass

8.338.2.3 uint32_t LibPackGPRSRequestedQoS::peakThroughputClass

8.338.2.4 uint32_t LibPackGPRSRequestedQoS::precedenceClass

8.338.2.5 uint32_t LibPackGPRSRequestedQoS::reliabilityClass

8.339 LibpackProfile3GPP Struct Reference

Data Fields

- uint8_t * pProfilename
- uint16_t * pProfilenameSize
- uint8_t * pPDPtype
- uint8_t * pPdpHdrCompType
- uint8_t * pPdpDataCompType
- uint8_t * pAPNName
- uint16_t * pAPNnameSize
- uint32_t * pPriDNSIPv4AddPref
- uint32_t * pSecDNSIPv4AddPref
- LibPackUMTSQoS * pUMTSReqQoS
- LibPackUMTSQoS * pUMTSMinQoS
- LibPackGPRSRequestedQoS * pGPRSRequestedQos
- LibPackGPRSRequestedQoS * pGPRSMinimumQoS
- uint8_t * pUsername
- uint16_t * pUsernameSize
- uint8_t * pPassword
- uint16_t * pPasswordSize
- uint8_t * pAuthenticationPref
- uint32_t * pIPv4AddrPref
- uint8_t * pPcscfAddrUsingPCO
- uint8_t * pPdpAccessConFlag
- uint8_t * pPcscfAddrUsingDhcp
- uint8_t * pImCnFlag
- LibPackTFTIDParams * pTFTID1Params

- LibPackTFTIDParams * pTFTID2Params
- uint8_t * pPdpContext
- uint8_t * pSecondaryFlag
- uint8_t * pPrimaryID
- uint16_t * pIPv6AddPref
- LibPackUMTSReqQoSSigInd * pUMTSReqQoSSigInd
- LibPackUMTSReqQoSSigInd * pUMTSMinQosSigInd
- uint16_t * pPriDNSIPv6addpref
- uint16_t * pSecDNSIPv6addpref
- uint8_t * pAddrAllocPref
- LibPackQosClassID * pQosClassID
- uint8_t * pAPNDisabledFlag
- uint32_t * pPDNInactivTimeout
- uint8_t * pAPNClass
- uint8_t * pSupportEmergencyCalls

8.339.1 Detailed Description

This structure contains Input parameters of unpack_wds_SLQSGetProfileSettings_t Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

pProfileName	• One or more uint8_ts describing the profile • NULL pointer - Invalid data. • Bit to check in ParamPresenceMask - **16**
pProfilename-Size;	• This parameter is an input parameter and should be initialised to the size of pProfileName field. Size of this parameter is 2 uint8_ts. • Bit to check in ParamPresenceMask - **16**
pPDPType	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile – 0x00 - PDP-IP (IPv4) – 0x01 - PDP-PPP – 0x02 - PDP-IPV6 – 0x03 - PDP-IPV4V6 • Bit to check in ParamPresenceMask - **17**
pPdpHdrComp-Type	• PDP header compression type – 0 - PDP header compression is OFF – 1 - Manufacturer preferred compression – 2 - PDP header compression based on RFC 1144 – 3 - PDP header compression based on RFC 25074 PDP header compression based on RFC 3095 • Bit to check in ParamPresenceMask - **18**

pPdpDataCompType	• PDP data compression type – 0 - PDP data compression is OFF – 1 - Manufacturer preferred compression – 2 - V.42BIS data compression – 3 - V.44 data compression • Bit to check in ParamPresenceMask - **19**
pAPNName	• Access point name • Bit to check in ParamPresenceMask - **20**
pAPNnameSize;	• This parameter is an input parameter and should be initialised to the size of pAPNName field. Size of this parameter is 2 uint8_ts. • Bit to check in ParamPresenceMask - **20**
pPriDNSIPv4AddPref	• Primary DNS IPv4 Address Preference • Bit to check in ParamPresenceMask - **21**
pSecDNSIPv4AddPref	• Secondary DNS IPv4 Address Preference • Bit to check in ParamPresenceMask - **22**
pUMTSReqQoS	• UMTS Requested QoS • Bit to check in ParamPresenceMask - **23**
pUMTSMinQoS	• UMTS Minimum QoS • Bit to check in ParamPresenceMask - **24**
pGPRSRequestedQoS	• GPRS Requested QoS • Bit to check in ParamPresenceMask - **25**
pGPRSMinimumQoS	• GPRS Minimum QoS • Bit to check in ParamPresenceMask - **26**
pUsername	• User name • Bit to check in ParamPresenceMask - **27**
pUsernameSize;	• This parameter is an input parameter and should be initialised to the size of pUsername field. Size of this parameter is 2 uint8_ts. • Bit to check in ParamPresenceMask - **27**

pPassword	• Password • Bit to check in ParamPresenceMask - **28**
pPasswordSize;	• This parameter is an input parameter and should be initialised to the size of pPassword field. Size of this parameter is 2 uint8_ts. • Bit to check in ParamPresenceMask - **28**
pAuthentication-Pref	• Authentication Preference – Bit map that indicates the authentication algorithm preference * Bit 0 - PAP preference · 0 - PAP is never performed · 1 - PAP may be performed * Bit 1 - CHAP preference · 0 - CHAP is never performed · 1 - CHAP may be performed * If more than one bit is set, then the device decides which authentication procedure is performed while setting up the data session. For example, the device may have a policy to select the most secure authentication mechanism. • Bit to check in ParamPresenceMask - **29**
pIPv4AddrPref	• IPv4 Address Preference • Bit to check in ParamPresenceMask - **30**
pPcscfAddr-UsingPCO	• P-CSCF Address using PCO Flag – 1 - (TRUE) implies request PCSCF address using PCO – 0 - (FALSE) implies do not request By default, this value is 0 • Bit to check in ParamPresenceMask - **31**
pPdpAccess-ConFlag	• PDP access control flag – 0 - PDP access control none – 1 - PDP access control reject – 2 - PDP access control permission • Bit to check in ParamPresenceMask - **32**
pPcscfAddr-UsingDhcp	• P-CSCF address using DHCP – 1 - (TRUE) implies Request PCSCF address using DHCP – 0 - (FALSE) implies do not request By default, value is 0 • Bit to check in ParamPresenceMask - **33**

pImCnFlag	• IM CN flag – 1 - (TRUE) implies request IM CN flag for this profile – 0 - (FALSE) implies do not request IM CN flag for this profile • Bit to check in ParamPresenceMask - **34**
pTFTID1Params	• Traffic Flow Template • Bit to check in ParamPresenceMask - **35**
pTFTID2Params	• Traffic Flow Template • Bit to check in ParamPresenceMask - **36**
pPdpContext	• PDP context number • Bit to check in ParamPresenceMask - **37**
pSecondaryFlag	• PDP context secondary flag – 1 - (TRUE) implies this is secondary profile – 0 - (FALSE) implies this is not secondary profile • Bit to check in ParamPresenceMask - **38**
pPrimaryID	• PDP context primary ID • function SLQSGetProfileSettings() returns a default value 0xFF if this parameter is not returned by the device • Bit to check in ParamPresenceMask - **39**
pIPv6AddPref	• IPv6 address preference Preferred IPv6 address to be assigned to the TE; actual assigned address is negotiated with the network and may differ from this value; if not specified, the IPv6 address is obtained automatically from the network • Bit to check in ParamPresenceMask - **40**
pUMTSReqQoS-SigInd	• UMTS requested QoS with Signalling Indication flag • Bit to check in ParamPresenceMask - **41**
pUMTSMinQoS-SigInd	• UMTS minimum QoS with Signalling Indication flag • Bit to check in ParamPresenceMask - **42**
pPrimaryDNSI-Pv6addpref	• Primary DNS IPv6 address preference – The value may be used as a preference during negotiation with the network; if not specified, the wireless device will attempt to obtain the DNS address automatically from the network; the negotiated value is provided to the host via DHCP • Bit to check in ParamPresenceMask - **43**

pSecondaryDNSIPv6addpref	• Secondary DNS IPv6 address preference • Bit to check in ParamPresenceMask - **44**
paddrAllocationPref	• DHCP/NAS preference – This enumerated value may be used to indicate the address allocation preference * 0 - NAS signaling is used for address allocation * 1 - DHCP is used for address allocation • Bit to check in ParamPresenceMask - **45**
pQosClassID	• 3GPP LTE QoS parameters • Bit to check in ParamPresenceMask - **46**
pAPNDisabledFlag	• Optional 1 uint8_t Flag indicating if the APN is disabled/enabled • If set, the profile can not be used for making data calls • Any data call is failed locally • Values: – 0 - FALSE(default) – 1 - True • This parameter is currently read only and can be read by using the function SLQSGetProfileSettings(). • Bit to check in ParamPresenceMask - **47**
pPDNInactivTimeout	• Optional 4 uint8_ts indicating the duration of inactivity timer in seconds • If the PDP context/PDN connection is inactive for this duration i.e. No data Tx/Rx occurs, the PDP context/PDN connection is disconnected • Default value of zero indicates infinite value • This parameter is currently read only and can be read by using the function SLQSGetProfileSettings(). • Bit to check in ParamPresenceMask - **48**
pAPNClass	• Optional 1 uint8_t numeric identifier representing the APN in profile • Can be set and queried but is not used by the modem • This parameter is currently read only and can be read by using the function SLQSGetProfileSettings(). • Bit to check in ParamPresenceMask - **49**
pSupportEmergencyCalls	• Optional 1 Byte Flag indicating if the emergency call support is disabled/enabled • Can be queried to get current status • Values: – 0 - FALSE(default) – 1 - TRUE • Bit to check in ParamPresenceMask - **54**

8.339.2 Field Documentation

8.339.2.1 uint8_t* LibpackProfile3GPP::pAddrAllocPref

8.339.2.2 uint8_t* LibpackProfile3GPP::pAPNClass

8.339.2.3 uint8_t* LibpackProfile3GPP::pAPNDisabledFlag

8.339.2.4 uint8_t* LibpackProfile3GPP::pAPNName

8.339.2.5 uint16_t* LibpackProfile3GPP::pAPNnameSize

8.339.2.6 uint8_t* LibpackProfile3GPP::pAuthenticationPref

8.339.2.7 LibPackGPRSRequestedQoS* LibpackProfile3GPP::pGPRSMinimumQoS

8.339.2.8 LibPackGPRSRequestedQoS* LibpackProfile3GPP::pGPRSRequestedQos

8.339.2.9 uint8_t* LibpackProfile3GPP::pImCnFlag

8.339.2.10 uint32_t* LibpackProfile3GPP::pIPv4AddrPref

8.339.2.11 uint16_t* LibpackProfile3GPP::pIPv6AddPref

8.339.2.12 uint8_t* LibpackProfile3GPP::pPassword

8.339.2.13 uint16_t* LibpackProfile3GPP::pPasswordSize

8.339.2.14 uint8_t* LibpackProfile3GPP::pPcscfAddrUsingDhcp

8.339.2.15 uint8_t* LibpackProfile3GPP::pPcscfAddrUsingPCO

8.339.2.16 uint32_t* LibpackProfile3GPP::pPDNInactivTimeout

8.339.2.17 uint8_t* LibpackProfile3GPP::pPdpAccessConFlag

8.339.2.18 uint8_t* LibpackProfile3GPP::pPdpContext

8.339.2.19 uint8_t* LibpackProfile3GPP::pPdpDataCompType

8.339.2.20 uint8_t* LibpackProfile3GPP::pPdpHdrCompType

8.339.2.21 uint8_t* LibpackProfile3GPP::pPDPtype

8.339.2.22 uint32_t* LibpackProfile3GPP::pPriDNSIPv4AddPref

8.339.2.23 uint16_t* LibpackProfile3GPP::pPriDNSIPv6addpref

8.339.2.24 uint8_t* LibpackProfile3GPP::pPrimaryID

8.339.2.25 uint8_t* LibpackProfile3GPP::pProfilename

8.339.2.26 uint16_t* LibpackProfile3GPP::pProfilenameSize

8.339.2.27 LibPackQosClassID* LibpackProfile3GPP::pQosClassID

8.339.2.28 uint32_t* LibpackProfile3GPP::pSecDNSIPv4AddPref

8.339.2.29 uint16_t* LibpackProfile3GPP::pSecDNSIPv6addpref

8.339.2.30 uint8_t* LibpackProfile3GPP::pSecondaryFlag

8.339.2.31 uint8_t* LibpackProfile3GPP::pSupportEmergencyCalls

8.339.2.32 LibPackTFTIDParams* LibpackProfile3GPP::pTFTID1Params

8.339.2.33 LibPackTFTIDParams* LibpackProfile3GPP::pTFTID2Params

8.339.2.34 LibPackUMTSQoS* LibpackProfile3GPP::pUMTSMinQoS

8.339.2.35 LibPackUMTSReqQoSSigInd* LibpackProfile3GPP::pUMTSMinQosSigInd

8.339.2.36 LibPackUMTSQoS* LibpackProfile3GPP::pUMTSReqQoS

8.339.2.37 LibPackUMTSReqQoSSigInd* LibpackProfile3GPP::pUMTSReqQoSSigInd

8.339.2.38 uint8_t* LibpackProfile3GPP::pUsername

8.339.2.39 uint16_t* LibpackProfile3GPP::pUsernameSize

8.340 LibpackProfile3GPP2 Struct Reference

Data Fields

- uint8_t * pNegoDnsSrvrPref
- uint32_t * pPppSessCloseTimerDO
- uint32_t * pPppSessCloseTimer1x
- uint8_t * pAllowLinger
- uint16_t * pLcpAckTimeout
- uint16_t * pIpcpAckTimeout
- uint16_t * pAuthTimeout
- uint8_t * pLcpCreqRetryCount
- uint8_t * pIpcpCreqRetryCount
- uint8_t * pAuthRetryCount
- uint8_t * pAuthProtocol
- uint8_t * pUserId
- uint16_t * pUserIdSize
- uint8_t * pAuthPassword
- uint16_t * pAuthPasswordSize
- uint8_t * pDataRate
- uint32_t * pAppType
- uint8_t * pDataMode
- uint8_t * pAppPriority
- uint8_t * pApnString
- uint16_t * pApnStringSize
- uint8_t * pPdnType
- uint8_t * pIsPcscfAddressNedded
- uint32_t * pPrimaryV4DnsAddress
- uint32_t * pSecondaryV4DnsAddress
- uint16_t * pPriV6DnsAddress
- uint16_t * pSecV6DnsAddress

- uint8_t * pRATType
- uint8_t * pAPNEnabled3GPP2
- uint32_t * pPDNInactivTimeout3GPP2
- uint8_t * pAPNClass3GPP2

8.340.1 Detailed Description

This structure contains the 3GPP2 profile parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

pNegoDnsSrvr-Pref	• Negotiate DNS Server Preference – 1 - (TRUE)implies request DNS addresses from the PDSN – 0 - (FALSE)implies do not request DNS addresses from the PDSN – Default value is 1 (TRUE) • Bit to check in ParamPresenceMask - **144**
pPppSessClose-TimerDO	• PPP Session Close Timer for DO – Timer value (in seconds) on DO indicating how long the PPP Session should linger before closing down • Bit to check in ParamPresenceMask - **145**
pPppSessClose-Timer1x	• PPP Session Close Timer for 1X – Timer value (in seconds) on 1X indicating how long the PPP session should linger before closing down • Bit to check in ParamPresenceMask - **146**
pAllowLinger	• Allow/disallow lingering of interface – 1 -(TRUE) implies allow lingering – 0 -(FALSE) implies do not allow lingering • Bit to check in ParamPresenceMask - **147**
pLcpAckTimeout	• LCP ACK Timeout – Value of LCP ACK Timeout in milliseconds • Bit to check in ParamPresenceMask - **148**
pIpcpAck-Timeout	• IPCP ACK Timeout – Value of IPCP ACK Timeout in milliseconds • Bit to check in ParamPresenceMask - **149**
pAuthTimeout	• AUTH Timeout – Value of Authentication Timeout in milliseconds • Bit to check in ParamPresenceMask - **150**

pLcpCreqRetry-Count	• LCP Configuration Request Retry Count • Bit to check in ParamPresenceMask - **151**
pIpcpCreqRetry-Count	• IPCP Configuration Request Retry Count • Bit to check in ParamPresenceMask - **152**
pAuthRetry-Count	• Authentication Retry Count value • Bit to check in ParamPresenceMask - **153**
pAuthProtocol	• Authentication Protocol – 1 - PAP – 2 - CHAP – 3 - PAP or CHAP • Bit to check in ParamPresenceMask - **154**
pUserId	• User ID to be used during data network authentication • maximum length allowed is 127 uint8_ts; • QMI_ERR_ARG_TOO_LONG will be returned if the storage on the wireless device is insufficient in size to hold the value. • Bit to check in ParamPresenceMask - **155**
pUserIdSize;	• This parameter is an input parameter and should be initialised to the size of pUserId field. Size of this parameter is 2 uint8_ts. • Bit to check in ParamPresenceMask - **155**
pAuthPassword	• Password to be used during data network authentication; • maximum length allowed is 127 uint8_ts • QMI_ERR_ARG_TOO_LONG will be returned if the storage on the wireless device is insufficient in size to hold the value. • Bit to check in ParamPresenceMask - **156**
pAuthPassword-Size;	• This parameter is an input parameter and should be initialised to the size of pAuthPassword field. Size of this parameter is 2 uint8_ts. • Bit to check in ParamPresenceMask - **156**
pDataRate	• Data Rate Requested – 0 - Low (Low speed Service Options (SO15) only) – 1 - Medium (SO33 + low R-SCH) – 2 - High (SO33 + high R-SCH) – Default is 2 • Bit to check in ParamPresenceMask - **157**

pAppType	• Application Type: – 0x00000001 - Default Application Type – 0x00000020 - LBS Application Type – 0x00000040 - Tethered Application Type – This parameter is not used while creating/modifying a profile • Bit to check in ParamPresenceMask - **158**
pDataMode	• Data Mode to use: – 0 - CDMA or HDR (Hybrid 1X/1xEV-DO) – 1 - CDMA Only (1X only) – 2 - HDR Only (1xEV-DO only) – Default is 0 • Bit to check in ParamPresenceMask - **159**
pAppPriority	• Application Priority – Numerical 1 uint8_t value defining the application priority; higher value implies higher priority – This parameter is not used while creating/modifying a profile • Bit to check in ParamPresenceMask - **160**
pApnString	• String representing the Access Point Name • maximum length allowed is 100 uint8_ts • QMI_ERR_ARG_TOO_LONG will be returned if the APN name is too long. • Bit to check in ParamPresenceMask - **161**
pApnStringSize;	• This parameter is an input parameter and should be initialised to the size of pApnString field. Size of this parameter is 2 uint8_ts. • Bit to check in ParamPresenceMask - **161**
pPdnType	• Packed Data Network Type Requested: – 0 - IPv4 PDN Type – 1 - IPv6 PDN Type – 2 - IPv4 or IPv6 PDN Type – 3 - Unspecified PDN Type (implying no preference) • Bit to check in ParamPresenceMask - **162**
pIsPcscf-AddressNedded	• This boolean value is used to control if PCSCF address is requested from PDSN – 1 -(TRUE) implies request for PCSCF value from the PDSN – 0 -(FALSE) implies do not request for PCSCF value from the PDSN • Bit to check in ParamPresenceMask - **163**

pPrimaryV4Dns-Address	• IPv4 Primary DNS address – The Primary IPv4 DNS address that can be statically assigned to the UE • Bit to check in ParamPresenceMask - **164**
pSecondaryV4-DnsAddress	• IPv4 Secondary DNS address – The Secondary IPv4 DNS address that can be statically assigned to the UE • Bit to check in ParamPresenceMask - **165**
pPriV6Dns-Address	• Primary IPv6 DNS address – The Primary IPv6 DNS address that can be statically assigned to the UE • Bit to check in ParamPresenceMask - **166**
pSecV6Dns-Address	• Secondary IPv6 DNS address – The Secondary IPv6 DNS address that can be statically assigned to the UE • Bit to check in ParamPresenceMask - **167**
pRATType	• Optional 1 uint8_t Flag indicating RAT Type • Values: – 1 - HRPD – 2 - EHRPD – 3 - HRPD_EHRPD • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings(). • Bit to check in ParamPresenceMask - **168**
pAPNEnabled3-GPP2	• Optional 1 uint8_t Flag indicating if the APN is disabled/enabled • If disabled, the profile can not be used for making data calls • Values: – 0 - Disabled – 1 - Enabled(default value) • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings(). • Bit to check in ParamPresenceMask - **169**
pPDNInactiv-Timeout3GPP2	• Optional 4 uint8_ts indicating the duration of inactivity timer in seconds • If the PDP context/PDN connection is inactive for this duration i.e. No data Tx/Rx occurs, the PDP context/PDN connection is disconnected • Default value of zero indicates infinite value • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings(). • Bit to check in ParamPresenceMask - **170**

pAPNClass3GPP2	• Optional 1 uint8_t numeric identifier representing the APN in profile • Can be set and queried but is not used by the modem • This parameter is currently read only and can be read by using the function SLQSGetProfileSettings(). • Bit to check in ParamPresenceMask - **171**

8.340.2 Field Documentation

8.340.2.1 uint8_t* LibpackProfile3GPP2::pAllowLinger

8.340.2.2 uint8_t* LibpackProfile3GPP2::pAPNClass3GPP2

8.340.2.3 uint8_t* LibpackProfile3GPP2::pAPNEnabled3GPP2

8.340.2.4 uint8_t* LibpackProfile3GPP2::pApnString

8.340.2.5 uint16_t* LibpackProfile3GPP2::pApnStringSize

8.340.2.6 uint8_t* LibpackProfile3GPP2::pAppPriority

8.340.2.7 uint32_t* LibpackProfile3GPP2::pAppType

8.340.2.8 uint8_t* LibpackProfile3GPP2::pAuthPassword

8.340.2.9 uint16_t* LibpackProfile3GPP2::pAuthPasswordSize

8.340.2.10 uint8_t* LibpackProfile3GPP2::pAuthProtocol

8.340.2.11 uint8_t* LibpackProfile3GPP2::pAuthRetryCount

8.340.2.12 uint16_t* LibpackProfile3GPP2::pAuthTimeout

8.340.2.13 uint8_t* LibpackProfile3GPP2::pDataMode

8.340.2.14 uint8_t* LibpackProfile3GPP2::pDataRate

8.340.2.15 uint16_t* LibpackProfile3GPP2::pIpcpAckTimeout

8.340.2.16 uint8_t* LibpackProfile3GPP2::pIpcpCreqRetryCount

8.340.2.17 uint8_t* LibpackProfile3GPP2::pIsPcscfAddressNedded

8.340.2.18 uint16_t* LibpackProfile3GPP2::pLcpAckTimeout

8.340.2.19 uint8_t* LibpackProfile3GPP2::pLcpCreqRetryCount

8.340.2.20 uint8_t* LibpackProfile3GPP2::pNegoDnsSrvrPref

8.340.2.21 uint32_t* LibpackProfile3GPP2::pPDNInactivTimeout3GPP2

8.340.2.22 uint8_t* LibpackProfile3GPP2::pPdnType

8.340.2.23 uint32_t* LibpackProfile3GPP2::pPppSessCloseTimer1x

8.340.2.24 uint32_t* LibpackProfile3GPP2::pPppSessCloseTimerDO

8.340.2.25 uint32_t* LibpackProfile3GPP2::pPrimaryV4DnsAddress

8.340.2.26 uint16_t* LibpackProfile3GPP2::pPriV6DnsAddress

8.340.2.27 uint8_t* LibpackProfile3GPP2::pRATType

8.340.2.28 uint32_t* LibpackProfile3GPP2::pSecondaryV4DnsAddress

8.340.2.29 uint16_t* LibpackProfile3GPP2::pSecV6DnsAddress

8.340.2.30 uint8_t* LibpackProfile3GPP2::pUserId

8.340.2.31 uint16_t* LibpackProfile3GPP2::pUserIdSize

8.341 LibPackprofile_3GPP Struct Reference

Data Fields

- uint8_t * pProfilename
- uint16_t * pProfilenameSize
- uint8_t * pPDPtype
- uint8_t * pPdpHdrCompType
- uint8_t * pPdpDataCompType
- uint8_t * pAPNName
- uint16_t * pAPNnameSize
- uint32_t * pPriDNSIPv4AddPref
- uint32_t * pSecDNSIPv4AddPref
- LibPackUMTSQoS * pUMTSReqQoS
- LibPackUMTSQoS * pUMTSMinQoS
- LibPackGPRSRequestedQoS * pGPRSRequestedQos
- LibPackGPRSRequestedQoS * pGPRSMinimumQoS
- uint8_t * pUsername
- uint16_t * pUsernameSize
- uint8_t * pPassword
- uint16_t * pPasswordSize
- uint8_t * pAuthenticationPref
- uint32_t * pIPv4AddrPref
- uint8_t * pPcscfAddrUsingPCO
- uint8_t * pPdpAccessConFlag
- uint8_t * pPcscfAddrUsingDhcp
- uint8_t * pImCnFlag
- LibPackTFTIDParams * pTFTID1Params
- LibPackTFTIDParams * pTFTID2Params
- uint8_t * pPdpContext
- uint8_t * pSecondaryFlag
- uint8_t * pPrimaryID
- uint16_t * pIPv6AddPref
- LibPackUMTSReqQoSSigInd * pUMTSReqQoSSigInd
- LibPackUMTSReqQoSSigInd * pUMTSMinQosSigInd
- uint16_t * pPriDNSIPv6addpref
- uint16_t * pSecDNSIPv6addpref

- uint8_t * pAddrAllocPref
- LibPackQosClassID * pQosClassID
- uint8_t * pAPNDisabledFlag
- uint32_t * pPDNInactivTimeout
- uint8_t * pAPNClass
- uint8_t * pSupportEmergencyCalls

8.341.1 Detailed Description

This structure contains Input/Output parameters of pack_wds_SLQSCreateProfile

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

pProfileName	• One or more bytes describing the profile
pProfilenameSize;	• This parameter is an input parameter and should be initialised to the size of pProfileName field. Size of this parameter is 2 bytes.
pPDPType	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile – 0x00 - PDP-IP (IPv4) – 0x01 - PDP-PPP – 0x02 - PDP-IPV6 – 0x03 - PDP-IPV4V6
pPdpHdrCompType	• PDP header compression type – 0 - PDP header compression is OFF – 1 - Manufacturer preferred compression – 2 - PDP header compression based on RFC 1144 – 3 - PDP header compression based on RFC 25074 PDP header compression based on RFC 3095
pPdpDataCompType	• PDP data compression type – 0 - PDP data compression is OFF – 1 - Manufacturer preferred compression – 2 - V.42BIS data compression – 3 - V.44 data compression
pAPNName	• Access point name
pAPNnameSize;	• This parameter is an input parameter and should be initialised to the size of pAPNName field. Size of this parameter is 2 bytes.

pPriDNSIPv4-AddPref	• Primary DNS IPv4 Address Preference
pSecDNSIPv4-AddPref	• Secondary DNS IPv4 Address Preference
pUMTSReqQoS	• UMTS Requested QoS
pUMTSMinQoS	• UMTS Minimum QoS
pGPRS-RequestedQoS	• GPRS Minimum QoS
pUsername	• User name
pUsernameSize;	• This parameter is an input parameter and should be initialised to the size of pUsername field. Size of this parameter is 2 bytes.
pPassword	• Password
pPasswordSize;	• This parameter is an input parameter and should be initialised to the size of pPassword field. Size of this parameter is 2 bytes.
pAuthentication-Pref	• Authentication Preference – Bit map that indicates the authentication algorithm preference * Bit 0 - PAP preference · 0 - PAP is never performed · 1 - PAP may be performed * Bit 1 - CHAP preference · 0 - CHAP is never performed · 1 - CHAP may be performed * If more than one bit is set, then the device decides which authentication procedure is performed while setting up the data session. For example, the device may have a policy to select the most secure authentication mechanism.
pIPv4AddrPref	• IPv4 Address Preference
pPcscfAddr-UsingPCO	• P-CSCF Address using PCO Flag – 1 - (TRUE) implies request PCSCF address using PCO – 0 - (FALSE) implies do not request By default, this value is 0

pPdpAccess-ConFlag	• PDP access control flag – 0 - PDP access control none – 1 - PDP access control reject – 2 - PDP access control permission
pPcscfAddr-UsingDhcp	• P-CSCF address using DHCP – 1 - (TRUE) implies Request PCSCF address using DHCP – 0 - (FALSE) implies do not request By default, value is 0
pImCnFlag	• IM CN flag – 1 - (TRUE) implies request IM CN flag for this profile – 0 - (FALSE) implies do not request IM CN flag for this profile
pTFTID1Params	• Traffic Flow Template
pTFTID2Params	• Traffic Flow Template
pPdpContext	• PDP context number
pSecondaryFlag	• PDP context secondary flag – 1 - (TRUE) implies this is secondary profile – 0 - (FALSE) implies this is not secondary profile
pPrimaryID	• PDP context primary ID • function SLQSGetProfileSettings() returns a default value 0xFF if this parameter is not returned by the device
pIPv6AddPref	• IPv6 address preference Preferred IPv6 address to be assigned to the TE; actual assigned address is negotiated with the network and may differ from this value; if not specified, the IPv6 address is obtained automatically from the network
pUMTSReqQoS-SigInd	• UMTS requested QoS with Signalling Indication flag
pUMTSMinQoS-SigInd	• UMTS minimum QoS with Signalling Indication flag
pPrimaryDNSI-Pv6addpref	• Primary DNS IPv6 address preference – The value may be used as a preference during negotiation with the network; if not specified, the wireless device will attempt to obtain the DNS address automatically from the network; the negotiated value is provided to the host via DHCP

pSecondaryDNSIPv6addpref	• Secondary DNS IPv6 address preference
paddrAllocationPref	• DHCP/NAS preference – This enumerated value may be used to indicate the address allocation preference * 0 - NAS signaling is used for address allocation * 1 - DHCP is used for address allocation
pQosClassID	• 3GPP LTE QoS parameters
pAPNDisabledFlag	• Optional 1 uint8_t Flag indicating if the APN is disabled/enabled • If set, the profile can not be used for making data calls • Any data call is failed locally • Values: – 0 - FALSE(default) – 1 - True • This parameter is currently read only and can be read by using the function SLQSGetProfileSettings().
pPDNInactivTimeout	• Optional 4 Bytes indicating the duration of inactivity timer in seconds • If the PDP context/PDN connection is inactive for this duration i.e. No data Tx/Rx occurs, the PDP context/PDN connection is disconnected • Default value of zero indicates infinite value • This parameter is currently read only and can be read by using the function SLQSGetProfileSettings().
pAPNClass	• Optional 1 uint8_t numeric identifier representing the APN in profile • Can be set and queried but is not used by the modem • This parameter is currently read only and can be read by using the function SLQSGetProfileSettings().
pSupportEmergencyCalls	• Optional 1 Byte Flag indicating if the emergency call support is disabled/enabled • If set, the profile can be used for making emergency calls • Values: – 0 - FALSE(default) – 1 - TRUE

8.341.2 Field Documentation

8.341.2.1 uint8_t* LibPackprofile_3GPP::pAddrAllocPref

8.341.2.2 uint8_t* LibPackprofile_3GPP::pAPNClass

8.341.2.3 uint8_t* LibPackprofile_3GPP::pAPNDisabledFlag

8.341.2.4 uint8_t* LibPackprofile_3GPP::pAPNName

8.341.2.5 uint16_t* LibPackprofile_3GPP::pAPNnameSize

8.341.2.6 uint8_t* LibPackprofile_3GPP::pAuthenticationPref

8.341.2.7 LibPackGPRSRequestedQoS* LibPackprofile_3GPP::pGPRSMinimumQoS

8.341.2.8 LibPackGPRSRequestedQoS* LibPackprofile_3GPP::pGPRSRequestedQos

8.341.2.9 uint8_t* LibPackprofile_3GPP::pImCnFlag

8.341.2.10 uint32_t* LibPackprofile_3GPP::pIPv4AddrPref

8.341.2.11 uint16_t* LibPackprofile_3GPP::pIPv6AddPref

8.341.2.12 uint8_t* LibPackprofile_3GPP::pPassword

8.341.2.13 uint16_t* LibPackprofile_3GPP::pPasswordSize

8.341.2.14 uint8_t* LibPackprofile_3GPP::pPcscfAddrUsingDhcp

8.341.2.15 uint8_t* LibPackprofile_3GPP::pPcscfAddrUsingPCO

8.341.2.16 uint32_t* LibPackprofile_3GPP::pPDNInactivTimeout

8.341.2.17 uint8_t* LibPackprofile_3GPP::pPdpAccessConFlag

8.341.2.18 uint8_t* LibPackprofile_3GPP::pPdpContext

8.341.2.19 uint8_t* LibPackprofile_3GPP::pPdpDataCompType

8.341.2.20 uint8_t* LibPackprofile_3GPP::pPdpHdrCompType

8.341.2.21 uint8_t* LibPackprofile_3GPP::pPDPtype

8.341.2.22 uint32_t* LibPackprofile_3GPP::pPriDNSIPv4AddPref

8.341.2.23 uint16_t* LibPackprofile_3GPP::pPriDNSIPv6addpref

8.341.2.24 uint8_t* LibPackprofile_3GPP::pPrimaryID

8.341.2.25 uint8_t* LibPackprofile_3GPP::pProfilename

8.341.2.26 uint16_t* LibPackprofile_3GPP::pProfilenameSize

8.341.2.27 LibPackQosClassID* LibPackprofile_3GPP::pQosClassID

8.341.2.28 uint32_t* LibPackprofile_3GPP::pSecDNSIPv4AddPref

8.341.2.29 uint16_t* LibPackprofile_3GPP::pSecDNSIPv6addpref

8.341.2.30 uint8_t* LibPackprofile_3GPP::pSecondaryFlag

8.341.2.31 uint8_t* LibPackprofile_3GPP::pSupportEmergencyCalls

8.341.2.32 LibPackTFTIDParams* LibPackprofile_3GPP::pTFTID1Params

8.341.2.33 LibPackTFTIDParams* LibPackprofile_3GPP::pTFTID2Params

8.341.2.34 LibPackUMTSQoS* LibPackprofile_3GPP::pUMTSMinQoS

8.341.2.35 LibPackUMTSReqQoSSigInd* LibPackprofile_3GPP::pUMTSMinQosSigInd

8.341.2.36 LibPackUMTSQoS* LibPackprofile_3GPP::pUMTSReqQoS

8.341.2.37 LibPackUMTSReqQoSSigInd* LibPackprofile_3GPP::pUMTSReqQoSSigInd

8.341.2.38 uint8_t* LibPackprofile_3GPP::pUsername

8.341.2.39 uint16_t* LibPackprofile_3GPP::pUsernameSize

8.342 LibPackprofile_3GPP2 Struct Reference

Data Fields

- uint8_t * pNegoDnsSrvrPref
- uint32_t * pPppSessCloseTimerDO
- uint32_t * pPppSessCloseTimer1x
- uint8_t * pAllowLinger
- uint16_t * pLcpAckTimeout
- uint16_t * pIpcpAckTimeout
- uint16_t * pAuthTimeout
- uint8_t * pLcpCreqRetryCount
- uint8_t * pIpcpCreqRetryCount
- uint8_t * pAuthRetryCount
- uint8_t * pAuthProtocol
- uint8_t * pUserId
- uint16_t * pUserIdSize
- uint8_t * pAuthPassword
- uint16_t * pAuthPassword_tSize
- uint8_t * pDataRate
- uint32_t * pAppType
- uint8_t * pDataMode
- uint8_t * pAppPriority
- uint8_t * pApnString
- uint16_t * pApnStringSize
- uint8_t * pPdnType
- uint8_t * pIsPcscfAddressNedded
- uint32_t * pPrimaryV4DnsAddress
- uint32_t * pSecondaryV4DnsAddress
- uint16_t * pPriV6DnsAddress
- uint16_t * pSecV6DnsAddress
- uint8_t * pRATType
- uint8_t * pAPNEnabled3GPP2
- uint32_t * pPDNInactivTimeout3GPP2
- uint8_t * pAPNClass3GPP2

8.342.1 Detailed Description

This structure contains the 3GPP2 profile parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

pNegoDnsSrvr-Pref	• Negotiate DNS Server Preference – 1 - (TRUE)implies request DNS addresses from the PDSN – 0 - (FALSE)implies do not request DNS addresses from the PDSN – Default value is 1 (TRUE)
pPppSessClose-TimerDO	• PPP Session Close Timer for DO – Timer value (in seconds) on DO indicating how long the PPP Session should linger before closing down
pPppSessClose-Timer1x	• PPP Session Close Timer for 1X – Timer value (in seconds) on 1X indicating how long the PPP session should linger before closing down
pAllowLinger	• Allow/disallow lingering of interface – 1 -(TRUE) implies allow lingering – 0 -(FALSE) implies do not allow lingering
pLcpAckTimeout	• LCP ACK Timeout – Value of LCP ACK Timeout in milliseconds
pIpcpAck-Timeout	• IPCP ACK Timeout – Value of IPCP ACK Timeout in milliseconds
pAuthTimeout	• AUTH Timeout – Value of Authentication Timeout in milliseconds
pLcpCreqRetry-Count	• LCP Configuration Request Retry Count
pIpcpCreqRetry-Count	• IPCP Configuration Request Retry Count
pAuthRetry-Count	• Authentication Retry Count value

pAuthProtocol	• Authentication Protocol – 1 - PAP – 2 - CHAP – 3 - PAP or CHAP
pUserId	• User ID to be used during data network authentication • maximum length allowed is 127 bytes; • QMI_ERR_ARG_TOO_LONG will be returned if the storage on the wireless device is insufficient in size to hold the value.
pUserIdSize;	• This parameter is an input parameter and should be initialised to the size of pUserId field. Size of this parameter is 2 bytes.
pAuthPassword	• Password to be used during data network authentication; • maximum length allowed is 127 bytes • QMI_ERR_ARG_TOO_LONG will be returned if the storage on the wireless device is insufficient in size to hold the value.
pAuthPassword-Size;	• This parameter is an input parameter and should be initialised to the size of pAuthPassword field. Size of this parameter is 2 bytes.
pDataRate	• Data Rate Requested – 0 - Low (Low speed Service Options (SO15) only) – 1 - Medium (SO33 + low R-SCH) – 2 - High (SO33 + high R-SCH) – Default is 2
pAppType	• Application Type: – 0x00000001 - Default Application Type – 0x00000020 - LBS Application Type – 0x00000040 - Tethered Application Type – This parameter is not used while creating/modifying a profile
pDataMode	• Data Mode to use: – 0 - CDMA or HDR (Hybrid 1X/1xEV-DO) – 1 - CDMA Only (1X only) – 2 - HDR Only (1xEV-DO only) – Default is 0

pAppPriority	• Application Priority – Numerical 1 uint8_t value defining the application priority; higher value implies higher priority – This parameter is not used while creating/modifying a profile
pApnString	• String representing the Access Point Name • maximum length allowed is 100 bytes • QMI_ERR_ARG_TOO_LONG will be returned if the APN name is too long.
pApnStringSize;	• This parameter is an input parameter and should be initialised to the size of pApnString field. Size of this parameter is 2 bytes.
pPdnType	• Packed Data Network Type Requested: – 0 - IPv4 PDN Type – 1 - IPv6 PDN Type – 2 - IPv4 or IPv6 PDN Type – 3 - Unspecified PDN Type (implying no preference)
pIsPcscf-AddressNedded	• This boolean value is used to control if PCSCF address is requested from PDSN – 1 -(TRUE) implies request for PCSCF value from the PDSN – 0 -(FALSE) implies do not request for PCSCF value from the PDSN
pPrimaryV4Dns-Address	• IPv4 Primary DNS address – The Primary IPv4 DNS address that can be statically assigned to the UE
pSecondaryV4-DnsAddress	• IPv4 Secondary DNS address – The Secondary IPv4 DNS address that can be statically assigned to the UE
pPriV6Dns-Address	• Primary IPv6 DNS address – The Primary IPv6 DNS address that can be statically assigned to the UE
pSecV6Dns-Address	• Secondary IPv6 DNS address – The Secondary IPv6 DNS address that can be statically assigned to the UE
pRATType	• Optional 1 uint8_t Flag indicating RAT Type • Values: – 1 - HRPD – 2 - EHRPD – 3 - HRPD_EHRPD • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().

pAPNEnabled3-GPP2	• Optional 1 uint8_t Flag indicating if the APN is disabled/enabled • If disabled, the profile can not be used for making data calls • Values: – 0 - Disabled – 1 - Enabled(default value) • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().
pPDNInactiv-Timeout3GPP2	• Optional 4 Bytes indicating the duration of inactivity timer in seconds • If the PDP context/PDN connection is inactive for this duration i.e. No data Tx/Rx occurs, the PDP context/PDN connection is disconnected • Default value of zero indicates infinite value • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().
pAPNClass3GP-P2	• Optional 1 uint8_t numeric identifier representing the APN in profile • Can be set and queried but is not used by the modem • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().

8.342.2 Field Documentation

8.342.2.1 uint8_t* LibPackprofile_3GPP2::pAllowLinger

8.342.2.2 uint8_t* LibPackprofile_3GPP2::pAPNClass3GPP2

8.342.2.3 uint8_t* LibPackprofile_3GPP2::pAPNEnabled3GPP2

8.342.2.4 uint8_t* LibPackprofile_3GPP2::pApnString

8.342.2.5 uint16_t* LibPackprofile_3GPP2::pApnStringSize

8.342.2.6 uint8_t* LibPackprofile_3GPP2::pAppPriority

8.342.2.7 uint32_t* LibPackprofile_3GPP2::pAppType

8.342.2.8 uint8_t* LibPackprofile_3GPP2::pAuthPassword

8.342.2.9 uint16_t* LibPackprofile_3GPP2::pAuthPassword_tSize

8.342.2.10 uint8_t* LibPackprofile_3GPP2::pAuthProtocol

8.342.2.11 uint8_t* LibPackprofile_3GPP2::pAuthRetryCount

8.342.2.12 uint16_t* LibPackprofile_3GPP2::pAuthTimeout

8.342.2.13 uint8_t* LibPackprofile_3GPP2::pDataMode

8.342.2.14 uint8_t* LibPackprofile_3GPP2::pDataRate

8.342.2.15 uint16_t* LibPackprofile_3GPP2::pIpcpAckTimeout

8.342.2.16 uint8_t* LibPackprofile_3GPP2::pIpcpCreqRetryCount

8.342.2.17 uint8_t* LibPackprofile_3GPP2::pIsPcscfAddressNedded

8.342.2.18 uint16_t* LibPackprofile_3GPP2::pLcpAckTimeout

8.342.2.19 uint8_t* LibPackprofile_3GPP2::pLcpCreqRetryCount

8.342.2.20 uint8_t* LibPackprofile_3GPP2::pNegoDnsSrvrPref

8.342.2.21 uint32_t* LibPackprofile_3GPP2::pPDNInactivTimeout3GPP2

8.342.2.22 uint8_t* LibPackprofile_3GPP2::pPdnType

8.342.2.23 uint32_t* LibPackprofile_3GPP2::pPppSessCloseTimer1x

8.342.2.24 uint32_t* LibPackprofile_3GPP2::pPppSessCloseTimerDO

8.342.2.25 uint32_t* LibPackprofile_3GPP2::pPrimaryV4DnsAddress

8.342.2.26 uint16_t* LibPackprofile_3GPP2::pPriV6DnsAddress

8.342.2.27 uint8_t* LibPackprofile_3GPP2::pRATType

8.342.2.28 uint32_t* LibPackprofile_3GPP2::pSecondaryV4DnsAddress

8.342.2.29 uint16_t* LibPackprofile_3GPP2::pSecV6DnsAddress

8.342.2.30 uint8_t* LibPackprofile_3GPP2::pUserId

8.342.2.31 uint16_t* LibPackprofile_3GPP2::pUserIdSize

8.343 LibPackQosClassID Struct Reference

Data Fields

- uint8_t QCI
- uint32_t gDlBitRate
- uint32_t maxDlBitRate
- uint32_t gUlBitRate
- uint32_t maxUlBitRate

8.343.1 Detailed Description

This structure contains 3GPP LTE QoS parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

QCI	• QOS specified using the QOS Class Identifier (QOS) values QCI value 0 - Requests the network to assign the appropriate QCI value QCI values 1-4 - Associated with guaranteed bit rates QCI values 5-9 - Associated with non-guaranteed bit rates
gDlBitRate	• Guaranteed DL bit rate
maxDlBitRate	• Maximum DL bit rate
gUlBitRate	• Guaranteed UL bit rate
maxUlBitRate	• Maximum UL bit rate

8.343.2 Field Documentation

8.343.2.1 uint32_t LibPackQosClassID::gDlBitRate

8.343.2.2 uint32_t LibPackQosClassID::gUlBitRate

8.343.2.3 uint32_t LibPackQosClassID::maxDlBitRate

8.343.2.4 uint32_t LibPackQosClassID::maxUlBitRate

8.343.2.5 uint8_t LibPackQosClassID::QCI

8.344 LibPackTFTIDParams Struct Reference

Data Fields

- uint8_t filterId
- uint8_t eValid
- uint8_t ipVersion
- uint16_t * pSourceIP
- uint8_t sourceIPMask
- uint8_t nextHeader
- uint16_t destPortRangeStart
- uint16_t destPortRangeEnd
- uint16_t srcPortRangeStart
- uint16_t srcPortRangeEnd
- uint32_t IPSECSPI
- uint16_t tosMask
- uint32_t flowLabel

8.344.1 Detailed Description

This structure contains traffic flow template parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

filterId	• Filter identifier
eValid	• Evaluation precedence index
ipVersion	• IP version number – 4 - IPv4 – 6 - IPv6
pSourceIP	• Source IP address – IPv4 - Fill the first 4 uint8_ts – IPv6 - Fill all the 16 uint8_ts
sourceIPMask	• Mask value for the source address
nextHeader	• Next header/protocol value
destPortRange-Start	• Start value of the destination port range
destPortRange-End	• End value of the destination port range
srcPortRange-Start	• Start value of the source port range
srcPortRange-End	• End value of the source port range
IPSECSPI	• IPSEC security parameter index
tosMask	• TOS mask (Traffic class for IPv6)
flowLabel	• Flow label

8.344.2 Field Documentation

8.344.2.1 uint16_t LibPackTFTIDParams::destPortRangeEnd

8.344.2.2 uint16_t LibPackTFTIDParams::destPortRangeStart

8.344.2.3 uint8_t LibPackTFTIDParams::eValid

8.344.2.4 uint8_t LibPackTFTIDParams::filterId

8.344.2.5 uint32_t LibPackTFTIDParams::flowLabel

8.344.2.6 uint32_t LibPackTFTIDParams::IPSECSPI

8.344.2.7 uint8_t LibPackTFTIDParams::ipVersion

8.344.2.8 uint8_t LibPackTFTIDParams::nextHeader

8.344.2.9 uint16_t* LibPackTFTIDParams::pSourceIP

8.344.2.10 uint8_t LibPackTFTIDParams::sourceIPMask

8.344.2.11 uint16_t LibPackTFTIDParams::srcPortRangeEnd

8.344.2.12 uint16_t LibPackTFTIDParams::srcPortRangeStart

8.344.2.13 uint16_t LibPackTFTIDParams::tosMask

8.345 LibPackUMTSQoS Struct Reference

Data Fields

- uint8_t trafficClass
- uint32_t maxUplinkBitrate
- uint32_t maxDownlinkBitrate
- uint32_t grntUplinkBitrate
- uint32_t grntDownlinkBitrate
- uint8_t qosDeliveryOrder
- uint32_t maxSDUSize
- uint8_t sduErrorRatio
- uint8_t resBerRatio
- uint8_t deliveryErrSDU
- uint32_t transferDelay
- uint32_t trafficPriority

8.345.1 Detailed Description

This structure contains the UMTS Quality Of Service Information

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

trafficClass	• 0x00 - Subscribed • 0x01 - Conversational • 0x02 - Streaming • 0x03 - Interactive • 0x04 - Background • 0xff - Invalid UMTS Quality Of Service Information.

maxUplinkBitrate	• Maximum uplink bit rate in bits/sec
maxDownlink-Bitrate	• Maximum downlink bit rate in bits/sec
grntUplinkBitrate	• Guaranteed uplink bit rate in bits/sec
grntDownlink-Bitrate	• Guranteed downlink bit rate in bits/sec
qosDelivery-Order	- Qos delivery order • 0x00 - Subscribe • 0x01 - delivery order on • 0x02 - delivery order off
maxSDUSize	• Maximum SDU size
sduErrorRatio	- SDU error ratio • Target value for fraction of SDUs lost or detected as erroneous. • 0x00 - Subscribe • 0x01 - 1∗10^(-2) • 0x02 - 7∗10^(-3) • 0x03 - 1∗10^(-3) • 0x04 - 1∗10^(-4) • 0x05 - 1∗10^(-5) • 0x06 - 1∗10^(-6) • 0x07 - 1∗10^(-1)
resBerRatio	- Residual bit error ratio • Target value for undetected bit error ratio in in the delivered SDUs. • 0x00 - Subscribe • 0x01 - 5∗10^(-2) • 0x02 - 1∗10^(-2) • 0x03 - 5∗10^(-3) • 0x04 - 4∗10^(-3) • 0x05 - 1∗10^(-3) • 0x06 - 1∗10^(-4) • 0x07 - 1∗10^(-5) • 0x08 - 1∗10^(-6) • 0x09 - 1∗10^(-8)

deliveryErrSDU	- Delivery of erroneous SDUs • Indicates whether SDUs detected as erroneous shall be delivered or not. • 0x00 - Subscribe • 0x01 - 5∗10^(-2) • 0x02 - 1∗10^(-2) • 0x03 - 5∗10^(-3) • 0x04 - 4∗10^(-3) • 0x05 - 1∗10^(-3) • 0x06 - 1∗10^(-4) • 0x07 - 1∗10^(-5) • 0x08 - 1∗10^(-6) • 0x09 - 1∗10^(-8)
transferDelay	- Transfer delay (ms) • Indicates the targeted time between a request to transfer an SDU at one SAP to its delivery at the other SAP in milliseconds.
trafficPriority	- Transfer handling priority • Specifies the relative importance for handling of SDUs that belong to the UMTS bearer, compared to the SDUs of other bearers.

Note

Check trafficClass before use.

8.345.2 Field Documentation

8.345.2.1 uint8_t LibPackUMTSQoS::deliveryErrSDU

8.345.2.2 uint32_t LibPackUMTSQoS::grntDownlinkBitrate

8.345.2.3 uint32_t LibPackUMTSQoS::grntUplinkBitrate

8.345.2.4 uint32_t LibPackUMTSQoS::maxDownlinkBitrate

8.345.2.5 uint32_t LibPackUMTSQoS::maxSDUSize

8.345.2.6 uint32_t LibPackUMTSQoS::maxUplinkBitrate

8.345.2.7 uint8_t LibPackUMTSQoS::qosDeliveryOrder

8.345.2.8 uint8_t LibPackUMTSQoS::resBerRatio

8.345.2.9 uint8_t LibPackUMTSQoS::sduErrorRatio

8.345.2.10 uint8_t LibPackUMTSQoS::trafficClass

8.345.2.11 uint32_t LibPackUMTSQoS::trafficPriority

8.345.2.12 uint32_t LibPackUMTSQoS::transferDelay

8.346 LibPackUMTSReqQoSSigInd Struct Reference

Data Fields

- LibPackUMTSQoS UMTSReqQoS
- uint8_t SigInd

8.346.1 Detailed Description

This structure contains UMTS requested QoS with Signaling Indication flag

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

UMTSReqQoS	• Contains the UMTS Quality Of Service Information • See LibPackUMTSQoS
SigInd	- Signaling Indication flag • TRUE - Signaling indication ON • FALSE - Signaling indication OFF

8.346.2 Field Documentation

8.346.2.1 uint8_t LibPackUMTSReqQoSSigInd::SigInd

8.346.2.2 LibPackUMTSQoS LibPackUMTSReqQoSSigInd::UMTSReqQoS

8.347 lineCtrlInfo Struct Reference

Data Fields

- BYTE polarityIncluded
- BYTE toggleMode
- BYTE revPolarity
- BYTE pwrDenialTime

8.347.1 Detailed Description

This structure contains Line Control Information

Parameters

polarityIncluded	• Included Polarity; Boolean Value
toggleMode	• Toggle mode; Boolean Value

revPolarity	• Reverse Polarity; Boolean Value
pwrDenialTime	• Power denial time; refer to [S1, Section 3.7.5.15 Line Control] for valid values

8.347.2 Field Documentation

8.347.2.1 BYTE lineCtrlInfo::polarityIncluded

8.347.2.2 BYTE lineCtrlInfo::pwrDenialTime

8.347.2.3 BYTE lineCtrlInfo::revPolarity

8.347.2.4 BYTE lineCtrlInfo::toggleMode

8.348 loc_accelAcceptReady Struct Reference

Data Fields

- uint8_t injectEnable
- uint16_t samplesPerBatch
- uint16_t batchPerSec

8.348.1 Detailed Description

This structure contains Accelerometer Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch $*$ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

8.348.2 Field Documentation

8.348.2.1 uint16_t loc_accelAcceptReady::batchPerSec

8.348.2.2 uint8_t loc_accelAcceptReady::injectEnable

8.348.2.3 uint16_t loc_accelAcceptReady::samplesPerBatch

8.349 loc_accelTempAcceptReady Struct Reference

Data Fields

- uint8_t injectEnable
- uint16_t samplesPerBatch
- uint16_t batchPerSec

8.349.1 Detailed Description

This structure contains Accelerometer Temperature Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

8.349.2 Field Documentation

8.349.2.1 uint16_t loc_accelTempAcceptReady::batchPerSec

8.349.2.2 uint8_t loc_accelTempAcceptReady::injectEnable

8.349.2.3 uint16_t loc_accelTempAcceptReady::samplesPerBatch

8.350 loc_BdsSV Struct Reference

Data Fields

- uint16_t id
- uint8_t mask

8.350.1 Detailed Description

This structure contains the BDS SV Info

Parameters

id	• SV ID of the satellite whose data is to be deleted. – Range for BDS: 201 to 237
mask	• Indicates if the ephemeris or almanac for a satellite is to be deleted • Valid values: – QMI_LOC_MASK_DELETE_EPHEMERIS (0x01) - Delete ephemeris for the satellite – QMI_LOC_MASK_DELETE_ALMANAC (0x02) - Delete almanac for the satellite

8.350.2 Field Documentation

8.350.2.1 uint16_t loc_BdsSV::id

8.350.2.2 uint8_t loc_BdsSV::mask

8.351 loc_BdsSVInfo Struct Reference

Data Fields

- uint8_t len
- loc_BdsSV * pSV

8.351.1 Detailed Description

This structure contains the number of sets of the BDS SVN Info

Parameters

len	• Number of sets of the following elements: – gnssSvId – deleteSvInfoMask
pSV	• Pointer to struct loc_BdsSV. See loc_BdsSV for more information

8.351.2 Field Documentation

8.351.2.1 uint8_t loc_BdsSVInfo::len

8.351.2.2 loc_BdsSV* loc_BdsSVInfo::pSV

8.352 loc_CellDb Struct Reference

Data Fields

- uint32_t mask

8.352.1 Detailed Description

This structure contains the cell database

Parameters

mask	• Mask for the cell database assistance data that is to be deleted • Valid values: – 0x00000001 - DELETE_CELLDB_POS – 0x00000002 - DELETE_CELLDB_LATEST_GPS_POS – 0x00000004 - DELETE_CELLDB_OTA_POS – 0x00000008 - DELETE_CELLDB_EXT_REF_POS – 0x00000010 - DELETE_CELLDB_TIMETAG – 0x00000020 - DELETE_CELLDB_CELLID – 0x00000040 - DELETE_CELLDB_CACHED_CELLID – 0x00000080 - DELETE_CELLDB_LAST_SRV_CELL – 0x00000100 - DELETE_CELLDB_CUR_SRV_CELL – 0x00000200 - DELETE_CELLDB_NEIGHBOR_INFO

8.352.2 Field Documentation

8.352.2.1 uint32_t loc_CellDb::mask

8.353 loc_ClkInfo Struct Reference

Data Fields

- uint32_t mask

8.353.1 Detailed Description

This structure contains the clock Info

Parameters

mask	• Mask for the clock information assistance data that is to be deleted • Valid bitmasks: – QMI_LOC_MASK_DELETE_CLOCK_INFO_TIME_EST (0x00000001) - Mask to delete time estimate from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_FREQ_EST (0x00000002) - Mask to delete frequency estimate from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_WEEK_NUMBER (0x00000004) - Mask to delete week number from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_RTC_TIME (0x00000008) - Mask to delete RTC time from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_TIME_TRANSFER (0x00000010) - Mask to delete time transfer from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GPSTIME_EST (0x00000020) - Mask to delete GPS time estimate from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GLOTIME_EST (0x00000040) - Mask to delete GLONASS time estimate from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GLODAY_NUMBER (0x00000080) - Mask to delete GLONASS day number from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GLO4YEAR_NUMBER (0x00000100) - Mask to delete GLONASS four year number from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GLO_RF_GRP_DELAY (0x00000200) - Mask to delete GLONASS RF GRP delay from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_DISABLE_TT (0x00000400) - Mask to delete disable TT from clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GG_LEAPSEC (0x00000800) - Mask to delete a BDS time estimate from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GG_GGTB (0x00001000) - Mask to delete a BDS time estimate from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_BDSTIME_EST (0x00002000) - Mask to delete a BDS time estimate from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_GB_GBTB (0x00004000) - Mask to delete Glonass-to-BDS time bias-related information from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_BG_BGTB (0x00008000) - Mask to delete BDS-to-GLONASS time bias-related information from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_BDSWEEK_NUMBER (0x00010000) - Mask to delete the BDS week number from the clock information – QMI_LOC_MASK_DELETE_CLOCK_INFO_BDS_RF_GRP_DELAY (0x00020000) - Mask to delete the BDS RF GRP delay from the clock information

8.353.2 Field Documentation

8.353.2.1 uint32_t loc_ClkInfo::mask

8.354 loc_GnssData Struct Reference

Data Fields

- uint64_t mask

8.354.1 Detailed Description

This structure contains the GNSS data

Parameters

mask	• Mask for the GNSS data that is to be deleted • Valid values: – QMI_LOC_MASK_DELETE_GPS_SVDIR (0x00000001) - Mask to delete GPS SVDIR – QMI_LOC_MASK_DELETE_GPS_SVSTEER (0x00000002) - Mask to delete GPS SVSTEER – QMI_LOC_MASK_DELETE_GPS_TIME (0x00000004) - Mask to delete GPS time – QMI_LOC_MASK_DELETE_GPS_ALM_CORR (0x00000008) - Mask to delete almanac correlation – QMI_LOC_MASK_DELETE_GLO_SVDIR (0x00000010) - Mask to delete GLONASS SVDIR – QMI_LOC_MASK_DELETE_GLO_SVSTEER (0x00000020) - Mask to delete GLONASS SVSTEER – QMI_LOC_MASK_DELETE_GLO_TIME (0x00000040) - Mask to delete GLONASS time – QMI_LOC_MASK_DELETE_GLO_ALM_CORR (0x00000080) - Mask to delete GLONASS almanac correlation – QMI_LOC_MASK_DELETE_SBAS_SVDIR (0x00000100) - Mask to delete SBAS SVDIR – QMI_LOC_MASK_DELETE_SBAS_SVSTEER (0x00000200) - Mask to delete SBAS SVSTEER – QMI_LOC_MASK_DELETE_POSITION (0x00000400) - Mask to delete position estimate – QMI_LOC_MASK_DELETE_TIME (0x00000800) - Mask to delete time estimate – QMI_LOC_MASK_DELETE_IONO (0x00001000) - Mask to delete IONO – QMI_LOC_MASK_DELETE_UTC (0x00002000) - Mask to delete UTC estimate – QMI_LOC_MASK_DELETE_HEALTH (0x00004000) - Mask to delete SV health record – QMI_LOC_MASK_DELETE_SADATA (0x00008000) - Mask to delete SADATA – QMI_LOC_MASK_DELETE_RTI (0x00010000) - Mask to delete RTI – QMI_LOC_MASK_DELETE_SV_NO_EXIST (0x00020000) - Mask to delete SV_NO_EXIST – QMI_LOC_MASK_DELETE_FREQ_BIAS_EST (0x00040000) - Mask to delete frequency bias estimate – QMI_LOC_MASK_DELETE_BDS_SVDIR (0x00080000) - Mask to delete BDS SVDIR – QMI_LOC_MASK_DELETE_BDS_SVSTEER (0x00100000) - Mask to delete BDS SVSTEER – QMI_LOC_MASK_DELETE_BDS_TIME (0x00200000) - Mask to delete BDS time – QMI_LOC_MASK_DELETE_BDS_ALM_CORR (0x00400000) - Mask to delete BDS almanac correlation – QMI_LOC_MASK_DELETE_GNSS_SV_BLACKLIST_GPS (0x00800000) - Mask to delete GNSS SV blacklist GPS – QMI_LOC_MASK_DELETE_GNSS_SV_BLACKLIST_GLO (0x01000000) - Mask to delete GNSS SV blacklist GLO – QMI_LOC_MASK_DELETE_GNSS_SV_BLACKLIST_BDS (0x02000000) - Mask to delete GNSS SV blacklist BDS

8.354.2 Field Documentation

8.354.2.1 uint64_t loc_GnssData::mask

8.355 loc_gpsTime Struct Reference

Data Fields

- uint16_t gpsWeek
- uint32_t gpsTimeOfWeekMs

8.355.1 Detailed Description

This structure contains GPS Time info.

Parameters

gpsWeek	• Current GPS week as calculated from midnight, Jan. 6, 1980. • Units - Weeks
gpsTimeOf-WeekMs	• Amount of time into the current GPS week. • Units - Milliseconds

8.355.2 Field Documentation

8.355.2.1 uint32_t loc_gpsTime::gpsTimeOfWeekMs

8.355.2.2 uint16_t loc_gpsTime::gpsWeek

8.356 loc_gyroAcceptReady Struct Reference

Data Fields

- uint8_t injectEnable
- uint16_t samplesPerBatch
- uint16_t batchPerSec

8.356.1 Detailed Description

This structure contains Gyroscope Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data

samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

8.356.2 Field Documentation

8.356.2.1 uint16_t loc_gyroAcceptReady::batchPerSec

8.356.2.2 uint8_t loc_gyroAcceptReady::injectEnable

8.356.2.3 uint16_t loc_gyroAcceptReady::samplesPerBatch

8.357 loc_gyroTempAcceptReady Struct Reference

Data Fields

- uint8_t injectEnable
- uint16_t samplesPerBatch
- uint16_t batchPerSec

8.357.1 Detailed Description

This structure contains Gyroscope Temperature Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

8.357.2 Field Documentation

8.357.2.1 uint16_t loc_gyroTempAcceptReady::batchPerSec

8.357.2.2 uint8_t loc_gyroTempAcceptReady::injectEnable

8.357.2.3 uint16_t loc_gyroTempAcceptReady::samplesPerBatch

8.358 loc_IPv4Config Struct Reference

Data Fields

- uint32_t IPv4Addr
- uint16_t IPv4Port

8.358.1 Detailed Description

This structure specifies information regarding the IPv4 address and port.

Parameters

IPv4Addr	• IPv4 address.
IPv4Port	• IPv4 port.

8.358.2 Field Documentation

8.358.2.1 uint32_t loc_IPv4Config::IPv4Addr

8.358.2.2 uint16_t loc_IPv4Config::IPv4Port

8.359 loc_IPv4Info Struct Reference

Data Fields

- uint32_t address
- uint16_t port
- uint8_t TlvPresent

8.359.1 Detailed Description

This structure contains LOC Server IPV4 info field.

Parameters

address	• IPv4 address.
port	• IPv4 port.

TlvPresent	• Tlv Present or not

8.359.2 Field Documentation

8.359.2.1 uint32_t loc_IPv4Info::address

8.359.2.2 uint16_t loc_IPv4Info::port

8.359.2.3 uint8_t loc_IPv4Info::TlvPresent

8.360 loc_IPv6Config Struct Reference

Data Fields

- uint16_t IPv6Addr [8]
- uint32_t IPv6Port

8.360.1 Detailed Description

This structure specifies information regarding the IPv6 address and port.

Parameters

IPv6Addr	• IPv6 address. • Type - Array of unsigned integers • Maximum length of the array: 8
IPv6Port	• IPv6 port.

8.360.2 Field Documentation

8.360.2.1 uint16_t loc_IPv6Config::IPv6Addr[8]

8.360.2.2 uint32_t loc_IPv6Config::IPv6Port

8.361 loc_IPv6Info Struct Reference

Data Fields

- uint16_t address [8]
- uint32_t port
- uint8_t TlvPresent

8.361.1 Detailed Description

This structure contains LOC Get Server IPV6 info field.

Parameters

address	• IPv6 address. • Type - Array of unsigned integers • Maximum length of the array - 8
port	• IPv6 port.
TlvPresent	• Tlv Present or not

8.361.2 Field Documentation

8.361.2.1 uint16_t loc_IPv6Info::address[8]

8.361.2.2 uint32_t loc_IPv6Info::port

8.361.2.3 uint8_t loc_IPv6Info::TlvPresent

8.362 loc_LocApplicationInfo Struct Reference

Data Fields

- uint8_t appProviderLength
- uint8_t * pAppProvider
- uint8_t appNameLength
- uint8_t * pAppName
- uint8_t appVersionValid
- uint8_t appVersionLength
- uint8_t * pAppVersion

8.362.1 Detailed Description

This structure contains the Application Information

Parameters

appProvider-Length	• Length of the Application Provider
pAppProvider	• Application Provider • Depends upon the Length of application Provider
appNameLength	• Length of Application Name
pAppName	• Application Name • Depends upon the Length of application Name

appVersionValid	• Specifies whether the application version string contains a valid value • 0x00 (FALSE) Application version string is invalid • 0x01 (TRUE) Application version string is valid
appVersion-Length	• Length of Application Version
pAppVersion	• Application Version • Depends upon the Length of application Version

8.362.2 Field Documentation

8.362.2.1 uint8_t loc_LocApplicationInfo::appNameLength

8.362.2.2 uint8_t loc_LocApplicationInfo::appProviderLength

8.362.2.3 uint8_t loc_LocApplicationInfo::appVersionLength

8.362.2.4 uint8_t loc_LocApplicationInfo::appVersionValid

8.362.2.5 uint8_t* loc_LocApplicationInfo::pAppName

8.362.2.6 uint8_t* loc_LocApplicationInfo::pAppProvider

8.362.2.7 uint8_t* loc_LocApplicationInfo::pAppVersion

8.363 loc_precisionDilution Struct Reference

Data Fields

- uint32_t PDOP
- uint32_t HDOP
- uint32_t VDOP

8.363.1 Detailed Description

This structure contains Dilution of precision associated with this position.

Parameters

PDOP	• Position dilution of precision. • Range - 1 (highest accuracy) to 50 (lowest accuracy) • PDOP = square root of (Square of HDOP + Square of VDOP2)
HDOP	• Horizontal dilution of precision. • Range - 1 (highest accuracy) to 50 (lowest accuracy)

VDOP	• Vertical dilution of precision. • Range- 1 (highest accuracy) to 50 (lowest accuracy)

8.363.2 Field Documentation

8.363.2.1 uint32_t loc_precisionDilution::HDOP

8.363.2.2 uint32_t loc_precisionDilution::PDOP

8.363.2.3 uint32_t loc_precisionDilution::VDOP

8.364 loc_satelliteInfo Struct Reference

Data Fields

- uint8_t svListLen
- uint32_t validMask
- uint32_t system
- uint16_t gnssSvId
- uint8_t healthStatus
- uint32_t svStatus
- uint8_t svInfoMask
- float elevation
- float azimuth
- float snr

8.364.1 Detailed Description

Contain fields in struct loc_satelliteInfo

Parameters

svListLen	• number of sets of the following elements: – validMask – system – gnssSvid – healthStatus – svStatus – svInfoMask – elevation – azimuth – snr

validMask	• Bitmask indicating which of the fields in this TLV are valid. Valid bitmasks: – 0x00000001 - VALID_SYSTEM – 0x00000002 - VALID_GNSS_SVID – 0x00000004 - VALID_HEALTH_STATUS – 0x00000008 - VALID_PROCESS_STATUS – 0x00000010 - VALID_SVINFO_MASK – 0x00000020 - VALID_ELEVATION – 0x00000040 - VALID_AZIMUTH – 0x00000080 - VALID_SNR
system	• Indicates to which constellation this SV belongs. Valid values: – eQMI_LOC_SV_SYSTEM_GPS (1) - GPS satellite – eQMI_LOC_SV_SYSTEM_GALILEO (2) - GALILEO satellite – eQMI_LOC_SV_SYSTEM_SBAS (3) - SBAS satellite – eQMI_LOC_SV_SYSTEM_COMPASS (4) - COMPASS satellite – eQMI_LOC_SV_SYSTEM_GLONASS (5) - GLONASS satellite – eQMI_LOC_SV_SYSTEM_BDS (6) - BDS satellite
gnssSvId	• GNSS SV ID. The GPS and GLONASS SVs can be disambiguated using the system field. Range: – FOR GPS: 1 to 32 – FOR GLONASS: 1 to 32 – FOR SBAS: 120 to 151 – for BDS: 201 to 237
healthStatus	• health status. Range: 0 - 1 – 0 - unhealthy – 1 - healthy
svStatus	• SV process status. Valid values: – eQMI_LOC_SV_STATUS_IDLE (1) - SV is not being actively processed – eQMI_LOC_SV_STATUS_SEARCH (2) - The system is searching for this SV – eQMI_LOC_SV_STATUS_TRACK (3) - SV is being tracked
svInfoMask	• Indicates whether almanac and ephemeris information is available. Valid bitmasks: – 0x01 - SVINFO_HAS_EPHEMERIS – 0x02 - SVINFO_HAS_ALMANAC
elevation	• SV elevation angle. – Units: Degrees – Range: 0 to 90

azimuth	• SV azimuth angle. – Units: Degrees – Range: 0 to 360
snr	• SV signal-to-noise ratio – Units: dB-Hz

8.364.2 Field Documentation

8.364.2.1 float loc_satelliteInfo::azimuth

8.364.2.2 float loc_satelliteInfo::elevation

8.364.2.3 uint16_t loc_satelliteInfo::gnssSvId

8.364.2.4 uint8_t loc_satelliteInfo::healthStatus

8.364.2.5 float loc_satelliteInfo::snr

8.364.2.6 uint8_t loc_satelliteInfo::svInfoMask

8.364.2.7 uint8_t loc_satelliteInfo::svListLen

8.364.2.8 uint32_t loc_satelliteInfo::svStatus

8.364.2.9 uint32_t loc_satelliteInfo::system

8.364.2.10 uint32_t loc_satelliteInfo::validMask

8.365 loc_sensorDataUsage Struct Reference

Data Fields

- uint32_t usageMask
- uint32_t aidingIndicatorMask

8.365.1 Detailed Description

This structure contains Sensor Data Usage info.

Parameters

usageMask	• Specifies which sensors were used in calculating the position in the position report. – Value * 0x00000001 - Accelerometer used * 0x00000002 - Gyroscope used

aidingIndicator-Mask	• Specifies which results were aided by sensors. – Value * 0x00000001 - AIDED_HEADING * 0x00000002 - AIDED_SPEED * 0x00000004 - AIDED_POSITION * 0x00000008 - AIDED_VELOCITY

8.365.2 Field Documentation

8.365.2.1 uint32_t loc_sensorDataUsage::aidingIndicatorMask

8.365.2.2 uint32_t loc_sensorDataUsage::usageMask

8.366 loc_SV Struct Reference

Data Fields

- uint16_t id
- uint32_t system
- uint8_t mask

8.366.1 Detailed Description

This structure contains the Delete LOC SV Info

Parameters

id	• LOC SV ID of the satellite whose data is to be deleted • Range: – For GPS: 1 to 32 – For SBAS: 33 to 64 – For GLONASS: 65 to 96
system	• Indicates to which constellation this loc_SV belongs • Valid values: – eQMI_LOC_SV_SYSTEM_GPS (1) - GPS satellite – eQMI_LOC_SV_SYSTEM_GALILEO (2) - GALILEO satellite – eQMI_LOC_SV_SYSTEM_SBAS (3) - SBAS satellite – eQMI_LOC_SV_SYSTEM_COMPASS (4) - COMPASS satellite – eQMI_LOC_SV_SYSTEM_GLONASS (5) - GLONASS satellite – eQMI_LOC_SV_SYSTEM_BDS (6) - BDS satellite
mask	• Indicates if the ephemeris or almanac for a satellite is to be deleted • Valid values: – 0x01 - DELETE_EPHEMERIS – 0x02 - DELETE_ALMANAC

8.366.2 Field Documentation

8.366.2.1 uint16_t loc_SV::id

8.366.2.2 uint8_t loc_SV::mask

8.366.2.3 uint32_t loc_SV::system

8.367 loc_SVInfo Struct Reference

Data Fields

- uint8_t len
- loc_SV * pSV

8.367.1 Detailed Description

This structure contains the elements of Delete LOC SV Info

Parameters

len	• Number of sets of the following elements in struct loc_SV: – gnssSvId – system – deleteSvInfoMask
pSV	• Pointer to struct loc_SV. See loc_SV for more information

8.367.2 Field Documentation

8.367.2.1 uint8_t loc_SVInfo::len

8.367.2.2 loc_SV* loc_SVInfo::pSV

8.368 loc_svUsedforFix Struct Reference

Data Fields

- uint8_t gnssSvUsedList_len
- uint16_t gnssSvUsedList [255]

8.368.1 Detailed Description

This structure contains SVs Used to Calculate the Fix.

Parameters

gnssSvUsedList_len	• Number of sets of gnssSvUsedList

pGnssSvUsed-List	• Entry in the list contains the SV ID of a satellite used for calculating this position report. • Following information is associated with each SV ID: – GPS - 1 to 32 – SBAS - 33 to 64 – GLONASS - 65 to 96 – QZSS - 193 to 197 – BDS - 201 to 237

8.368.2 Field Documentation

8.368.2.1 uint16_t loc_svUsedforFix::gnssSvUsedList[255]

8.368.2.2 uint8_t loc_svUsedforFix::gnssSvUsedList_len

8.369 loc_urlAddr Struct Reference

Data Fields

- char address [256]
- uint8_t TlvPresent

8.369.1 Detailed Description

This structure contains LOC Get Server URL address field.

Parameters

address	• Uniform Resource Locator • Type - NULL terminated string • Maximum string length (including NULL terminator) 256
TlvPresent	• Tlv Present or not

8.369.2 Field Documentation

8.369.2.1 char loc_urlAddr::address[256]

8.369.2.2 uint8_t loc_urlAddr::TlvPresent

8.370 loc_URLAddrInfo Struct Reference

Data Fields

- char urlAddr [256]

8.370.1 Detailed Description

This structure specifies information regarding the URL.

Parameters

urlAddr	• URL address. • Type - NULL-terminated string • Maximum string length (including NULL terminator) - 256

8.370.2 Field Documentation

8.370.2.1 char loc_URLAddrInfo::urlAddr[256]

8.371 LocApplicationInfo Struct Reference

Data Fields

- BYTE appProviderLength
- CHAR * pAppProvider
- BYTE appNameLength
- CHAR * pAppName
- BYTE appVersionValid
- CHAR appVersionLength
- CHAR * pAppVersion

8.371.1 Detailed Description

This structure contains the Application Information

Parameters

appProvider-Length	• Length of the Application Provider
pAppProvider	• Application Provider • Depends upon the Length of application Provider
appNameLength	• Length of Application Name
pAppName	• Application Name • Depends upon the Length of application Name
appVersionValid	• Specifies whether the application version string contains a valid value • 0x00 (FALSE) - Application version string is invalid • 0x01 (TRUE) - Application version string is valid

appVersion-Length	• Length of Application Version
pAppVersion	• Application Version • Depends upon the Length of application Version

8.371.2 Field Documentation

8.371.2.1 BYTE LocApplicationInfo::appNameLength

8.371.2.2 BYTE LocApplicationInfo::appProviderLength

8.371.2.3 CHAR LocApplicationInfo::appVersionLength

8.371.2.4 BYTE LocApplicationInfo::appVersionValid

8.371.2.5 CHAR* LocApplicationInfo::pAppName

8.371.2.6 CHAR* LocApplicationInfo::pAppProvider

8.371.2.7 CHAR* LocApplicationInfo::pAppVersion

8.372 LocDelAssDataReq Struct Reference

Data Fields

- SVInfo * pSVInfo
- GnssData * pGnssData
- CellDb * pCellDb
- ClkInfo * pClkInfo
- BdsSVInfo * pBdsSVInfo

8.372.1 Detailed Description

This structure contains LOC delete assist data request

Parameters

pSVInfo[IN]	• Optional parameter • Pointer to struct SVInfo. See SVInfo for more information
pGnssData[IN]	• Optional parameter • Pointer to struct GnssData. See GnssData for more information
pCellDb[IN]	• Optional parameter • Pointer to struct CellDb. See CellDb for more information

pClkInfo[IN]	• Optional parameter • Pointer to struct ClkInfo. See ClkInfo for more information
pBdsSVInfo[IN]	• Optional parameter • Pointer to struct BdsSVInfo. See BdsSVInfo for more information

8.372.2 Field Documentation

8.372.2.1 BdsSVInfo* LocDelAssDataReq::pBdsSVInfo

8.372.2.2 CellDb* LocDelAssDataReq::pCellDb

8.372.2.3 ClkInfo* LocDelAssDataReq::pClkInfo

8.372.2.4 GnssData* LocDelAssDataReq::pGnssData

8.372.2.5 SVInfo* LocDelAssDataReq::pSVInfo

8.373 LOCEventRegisterReqResp Struct Reference

Data Fields

- ULONGLONG eventRegister

8.373.1 Detailed Description

This structure contains the Parameter for RegisterEvents

Parameters

pEventRegMask	• Specifies the events that the control point is interested in receiving. -Values – 0x00000001 - to receive position report event indications – 0x00000002 - to receive satellite report event indications.These reports are sent at a 1 Hz rate. – 0x00000004 - to receive NMEA reports for position and satellites in view.The report is at a 1 Hz rate. – 0x00000008 - to receive NI Notify/Verify request event indications – 0x00000010 - to receive time injection request event indications. – 0x00000020 - to receive predicted orbits request event indications. – 0x00000040 - to receive position injection request event indications. – 0x00000080 - to receive engine state report event indications. – 0x00000100 - to receive fix session status report event indications. – 0x00000200 - to receive Wi-Fi position request event indications. – 0x00000400 - to receive notifications from the location engine indicating its readiness to accept data from the sensors(accelerometer, gyroscope, etc.). – 0x00000800 - to receive time sync requests from the GPS engine. Time sync enables the GPS engine to synchronize its clock with the sensor processor's clock. – 0x00001000 - to receive Stationary Position Indicator (SPI) streaming report indications. – 0x00002000 - to receive location server requests. These requests are generated when the service wishes to establish a connection with a location server. – 0x00004000 - to receive notifications related to network-initiated Geofences. These events notify the client when a network-initiated Geofence is added, deleted, or edited. – 0x00008000 - to receive Geofence alerts. These alerts are generated to inform the client of the changes that may affect a Geofence, e.g., if GPS is turned off or if the network is unavailable. – 0x00010000 - to receive notifications when a Geofence is breached. These events are generated when a UE enters or leaves the perimeter of a Geofence. This breach report is for a single Geofence. – 0x00020000 - to register for pedometer control requests from the location engine. The location engine sends this event to control the injection of pedometer reports. – 0x00040000 - to register for motion data control requests from the location engine. The location engine sends this event to control the injection of motion data. – 0x00080000 - to receive notification when a batch is full. The location engine sends this event to notify of Batch Full for ongoing batching session. – 0x00100000 - to receive position report indications along with an ongoing batching session. The location engine sends this event to notify the batched position report while a batching session is ongoing. – 0x00200000 - to receive Wi-Fi Access Point (AP) data inject request event indications. – 0x00400000 - to receive notifications when a Geofence is breached. These events are generated when a UE enters or leaves the perimeter of a Geofence. This breach notification is for multiple Geofences. Breaches from multiple Geofences are all batched and sent in the same notification. – 0x00800000 - to receive notifications from the location engine indicating its readiness to accept vehicle data (vehicle accelerometer, vehicle angular rate, vehicle odometry, etc.). – 0x01000000 - to receive system clock and satellite measurement report events (system clock, SV time, Doppler, etc.). – 0x02000000 - to receive satellite position reports as polynomials.Reports are generated only for the GNSS satellite constellations that are enabled using QMI_LOC_SET_GNSS_-CONSTELL_REPORT_CONFIG.

Note

Multiple events can be registered by OR the individual masks and sending them in this TLV. All unused bits in this mask must be set to 0.

8.373.2 Field Documentation

8.373.2.1 ULONGLONG LOCEventRegisterReqResp::eventRegister

8.374 LOCExtPowerStateReqResp Struct Reference

Data Fields

- ULONG extPowerState

8.374.1 Detailed Description

This structure contains the Parameter External Power Source State.

Parameters

pLOCEvent-RegisterReq-Resp	• Specifies the Power state; injected by the control point. • Values – 0 - Device is not connected to an external power source – 1 - Device is connected to an external power source – 2 - Unknown external power state

8.374.2 Field Documentation

8.374.2.1 ULONG LOCExtPowerStateReqResp::extPowerState

8.375 LocGetServerReq Struct Reference

Data Fields

- ULONG serverType
- BYTE * pServerAddrTypeMask

8.375.1 Detailed Description

This structure contains parameters to gets the location server from the location engine.

Parameters

serverType	• Type of server. • Valid values – eQMI_LOC_SERVER_TYPE_CDMA_PDE (1) - Server type is CDMA PDE – eQMI_LOC_SERVER_TYPE_CDMA_MPC (2) - Server type is CDMA MPC – eQMI_LOC_SERVER_TYPE_UMTS_SLP (3) - Server type is UMTS SLP – eQMI_LOC_SERVER_TYPE_CUSTOM_PDE (4)- Server type is custom PDE
pServerAddr-TypeMask	• Optional parameter • Type of address the client wants. If unspecified, the indication will contain all the types of addresses it has for the specified server type. • Valid bitmasks – 0x01 - IPv4 – 0x02 - IPv6 – 0x04 - URL

8.375.2 Field Documentation

8.375.2.1 BYTE* LocGetServerReq::pServerAddrTypeMask

8.375.2.2 ULONG LocGetServerReq::serverType

8.376 LocInjectPositionReq Struct Reference

Data Fields

- ULONGLONG * pLatitude
- ULONGLONG * pLongitude
- ULONG * pHorUncCircular
- BYTE * pHorConfidence
- ULONG * pHorReliability
- ULONG * pAltitudeWrtEllipsoid
- ULONG * pAltitudeWrtMeanSeaLevel
- ULONG * pVertUnc
- BYTE * pVertConfidence
- ULONG * pVertReliability
- altitudeSrcInfo * pAltitudeSrcInfo
- ULONGLONG * pTimestampUtc
- ULONG * pTimestampAge
- ULONG * pPositionSrc
- ULONG * pRawHorUncCircular
- BYTE * pRawHorConfidence

8.376.1 Detailed Description

This structure contains LOC Inject Position parameters

Parameters

pLatitude	• Optional parameter • Type - Floating point • Units - Degrees • Range - -90.0 to 90.0 • Positive values indicate northern latitude • Negative values indicate southern latitude • Note - This field must be specified together with pLongitude and pHorUncCircular.
pLongitude	• Optional parameter • Type - Floating point • Units - Degrees • Range - -180.0 to 180.0 • Positive values indicate eastern latitude • Negative values indicate western latitude • Note - This field must be specified together with pLatitude and pHorUncCircular.
pHorUncCircular	• Optional parameter • Horizontal position uncertainty. • Units - Meters • Note - This field must be specified together with pLatitude and pLongitude.

pHorConfidence	• Optional parameter
	• Horizontal confidence.
	• Units - Percent
	• Values
	  – Valid Values - 1 to 99
	  – Invalid Values - 0, 101 to 255
	  – If 100 is received, reinterpret to 99
	• Note - This field must be specified together with horizontal uncertainty. If not specified when pHorUncCircular is set, the default value is 50.

pHorReliability	• Optional parameter

- Values
  - 0 - Location reliability is not set.
  - 1 - Location reliability is very low; use it at your own risk
  - 2 - Location reliability is low; little or no cross-checking is possible.
  - 3 - Location reliability is medium; limited cross-check passed
  - 4 - Location reliability is high; strong cross-check passed

Parameters

pAltitudeWrt-Ellipsoid	• Optional parameter • Altitude With Respect to Ellipsoid. • Units - Meters • Values – Positive - height – Negative = depth
pAltitudeWrt-MeanSeaLevel	• Optional parameter • Altitude With Respect to Sea Level. • Units - Meters
pVertUnc	• Optional parameter • Vertical uncertainty. • Units - Meters • Note - This is mandatory if either pAltitudeWrtEllipsoid or pAltitudeWrtMeanSeaLevel is specified.
pVertConfidence	• Optional parameter • Vertical confidence. • Units - Percentage • Values – Valid Values - 0 to 99 – Invalid Values - 0, 100-256 – If 100 is received, reinterpret to 99 • Note - This field must be specified together with the vertical uncertainty. If not specified, the default value will be 50.
pVertReliability	• Optional parameter

- Values
  - 0 - Location reliability is not set.
  - 1 - Location reliability is very low; use it at your own risk.
  - 2 - Location reliability is low; little or no cross-checking is possible
  - 3 - Location reliability is medium; limited cross-check passed
  - 4 - Location reliability is high; strong cross-check passed

Parameters

pAltitudeSrcInfo	• Optional parameter

- Pointer to struct altitudeSrcInfo. See altitudeSrcInfo for more information

Parameters

pTimestampUtc	• Optional parameter • UTC timestamp • Units - Milliseconds since Jan. 1, 1970
pTimestampAge	• Optional parameter • Position age, which is an estimate of how long ago this fix was made. • Units - Milliseconds

pPositionSrc	• Optional parameter
	• Source from which this position was obtained
	• Valid values
	  – 0 - Position source is GNSS
	  – 1 - Position source is Cell ID
	  – 2 - Position source is Enhanced Cell ID
	  – 3 - Position source is Wi-Fi
	  – 4 - Position source is Terrestrial
	  – 5 - Position source is GNSS Terrestrial Hybrid
	  – 6 - Other sources
	• Note - If altitude is specified and the altitude source is not specified, the engine assumes that the altitude was obtained using the specified position source.
	  – If both altitude and altitude source are specified, the engine assumes that only latitude and longitude were obtained using the specified position source.

pRawHorUnc-Circular	• Optional parameter • Horizontal position uncertainty (circular) without any optimization. • Units - Meters

pRawHor-Confidence	• Optional parameter
	• Horizontal confidence associated with raw horizontal uncertainty
	• Units: Percent
	• Values
	  – Valid values - 1 to 99
	  – Invalid values - 0, 101 to 255
	  – If 100 is received, reinterpret to 99
	• Note - This field must be specified together with raw horizontal uncertainty. If not specified when rawHorUncCircular is set, the default value is 50.

8.376.2 Field Documentation

8.376.2.1 altitudeSrcInfo* LocInjectPositionReq::pAltitudeSrcInfo

8.376.2.2 ULONG* LocInjectPositionReq::pAltitudeWrtEllipsoid

8.376.2.3 ULONG* LocInjectPositionReq::pAltitudeWrtMeanSeaLevel

8.376.2.4 BYTE* LocInjectPositionReq::pHorConfidence

8.376.2.5 ULONG* LocInjectPositionReq::pHorReliability

8.376.2.6 ULONG* LocInjectPositionReq::pHorUncCircular

8.376.2.7 ULONGLONG* LocInjectPositionReq::pLatitude

8.376.2.8 ULONGLONG* LocInjectPositionReq::pLongitude

8.376.2.9 ULONG* LocInjectPositionReq::pPositionSrc

8.376.2.10 BYTE* LocInjectPositionReq::pRawHorConfidence

8.376.2.11 ULONG* LocInjectPositionReq::pRawHorUncCircular

8.376.2.12 ULONG* LocInjectPositionReq::pTimestampAge

8.376.2.13 ULONGLONG* LocInjectPositionReq::pTimestampUtc

8.376.2.14 BYTE* LocInjectPositionReq::pVertConfidence

8.376.2.15 ULONG* LocInjectPositionReq::pVertReliability

8.376.2.16 ULONG* LocInjectPositionReq::pVertUnc

8.377 LocInjectSensorDataReq Struct Reference

Data Fields

- ULONG * pOpaqueIdentifier
- sensorData * pAcceleroData
- sensorData * pGyroData
- ULONG * pAcceleroTimeSrc
- ULONG * pGyroTimeSrc
- tempratureData * pAcceleroTempData
- tempratureData * pGyroTempData

8.377.1 Detailed Description

This structure contains parameters to inject sensor data into the GNSS location engine

Parameters

pOpaque-Identifier	• Opaque Identifier (Optional parameter) • An opaque identifier that is sent in by the client that will be echoed in the indication so the client can relate the indication to the request.
pAcceleroData	• Optional parameter • Pointer to struct sensorData. See sensorData for more information

pGyroData	• Optional parameter • Pointer to struct sensorData. See sensorData for more information
pAcceleroTime-Src	• 3-Axis Accelerometer Data Time Source (Optional parameter) • The location service uses this field to identify the time reference used in the accelerometer data time stamps. • If not specified, the location service assumes that the time source for the accelerometer data is unknown. • Valid values – 0 - Sensor time source is unspecified – 1 - Time source is common between the sensors and the location engine
pGyroTimeSrc	• 3-Axis Gyroscope Data Time Source (Optional) • The location service uses this field to identify the time reference used in the gyroscope data time stamps. • If not specified, the location service assumes that the time source for the gyroscope data is unknown. • Valid values – 0 - Sensor time source is unspecified – 1 - Time source is common between the sensors and the location engine
pAcceleroTemp-Data	• Optional parameter • Pointer to struct temprature Data. See temprature Data for more information
pGyroTempData	• Optional parameter • Pointer to struct temprature Data. See temprature Data for more information

8.377.2 Field Documentation

8.377.2.1 sensorData* LocInjectSensorDataReq::pAcceleroData

8.377.2.2 temprature Data* LocInjectSensorDataReq::pAcceleroTempData

8.377.2.3 ULONG* LocInjectSensorDataReq::pAcceleroTimeSrc

8.377.2.4 sensorData* LocInjectSensorDataReq::pGyroData

8.377.2.5 temprature Data* LocInjectSensorDataReq::pGyroTempData

8.377.2.6 ULONG* LocInjectSensorDataReq::pGyroTimeSrc

8.377.2.7 ULONG* LocInjectSensorDataReq::pOpaqueIdentifier

8.378 LocSetCradleMountReq Struct Reference

Data Fields

- ULONG state
- BYTE * pConfidence

8.378.1 Detailed Description

This structure contains parameters to set current cradle mount configuration

Parameters

state	• Cradle Mount State • Valid values: – 0 - Device is mounted on the cradle – 1 - Device is not mounted on the cradle – 2 - Unknown cradle mount state
pConfidence	• Cradle Mount Confidence (Optional) • Confidence in the Cradle Mount state expressed as a percentage. • Range - 0 to 100

8.378.2 Field Documentation

8.378.2.1 BYTE* LocSetCradleMountReq::pConfidence

8.378.2.2 ULONG LocSetCradleMountReq::state

8.379 LocSetServerReq Struct Reference

Data Fields

- ULONG serverType
- IPv4Config * pIPv4Config
- IPv6Config * pIPv6Config
- URLAddrInfo * pURLAddr

8.379.1 Detailed Description

This structure contains parameters to set A-GPS Server

Parameters

serverType	• Type of server • Valid values: – 1 - Server type is CDMA PDE – 2 - Server type is CDMA MPC – 3 - Server type is UMTS SLP – 4 - Server type is custom PDE

pIPv4Config	• IPv4 address and port (Optional) • See IPv4Config for more information
pIPv6Config	• IPv6 address and port (Optional) • See IPv6Config for more information
pURLAddr	• Uniform Resource Locator (Optional) • See URLAddrInfo for more information

8.379.2 Field Documentation

8.379.2.1 IPv4Config∗ LocSetServerReq::pIPv4Config

8.379.2.2 IPv6Config∗ LocSetServerReq::pIPv6Config

8.379.2.3 URLAddrInfo∗ LocSetServerReq::pURLAddr

8.379.2.4 ULONG LocSetServerReq::serverType

8.380 LOCStartReq Struct Reference

Data Fields

- BYTE SessionId
- ULONG ∗ pRecurrenceType
- ULONG ∗ pHorizontalAccuracyLvl
- ULONG ∗ pIntermediateReportState
- ULONG ∗ pMinIntervalTime
- struct LocApplicationInfo ∗ pApplicationInfo
- ULONG ∗ pConfigAltitudeAssumed

8.380.1 Detailed Description

This structure contains the LOC Start Request

Parameters

SessionId[IN]	• ID of the session as identified by the control point. • Range: 0 to 255
pRecurrence-Type[IN]	• Optional Parameter • Specifies the type of session in which the control point is interested. • Defaults to SINGLE. -Values – 1 - Request periodic position fixes – 2 - Request a single position fix

pHorizontal-AccuracyLvl[IN]	• Optional Parameter • Specifies the horizontal accuracy level required by the control point. • Defaults to LOW • Values – 1 - Low accuracy – 2 - Medium accuracy – 3 - High accuracy
pIntermediate-ReportState[IN]	• Optional Parameter • Specifies if the control point is interested in receiving intermediate reports. • ON by default. • Values – 1 - Intermediate reports are turned on – 2 - Intermediate reports are turned off
pMinInterval-Time[IN]	• Optional Parameter • Minimum time interval, specified by the control point, that must elapse between position reports. • Units - Milliseconds • Default - 1000 ms
LocApplication-Info[IN]	• Optional Parameter • LOC Application Parameters • See LocApplicationInfo for more information
pConfigAltitude-Assumed[IN]	• Optional Parameter • Configuration for Altitude Assumed Info in GNSS SV Info Event • Defaults to ENABLED. • Values – 1 - Enable Altitude Assumed information in GNSS SV Info Event – 2 - Disable Altitude Assumed information in GNSS SV Info Event

8.380.2 Field Documentation

8.380.2.1 struct LocApplicationInfo* LOCStartReq::pApplicationInfo

8.380.2.2 ULONG* LOCStartReq::pConfigAltitudeAssumed

8.380.2.3 ULONG* LOCStartReq::pHorizontalAccuracyLvl

8.380.2.4 ULONG* LOCStartReq::pIntermediateReportState

8.380.2.5 ULONG* LOCStartReq::pMinIntervalTime

8.380.2.6 ULONG* LOCStartReq::pRecurrenceType

8.380.2.7 BYTE LOCStartReq::SessionId

8.381 LOCStopReq Struct Reference

Data Fields

- BYTE sessionId

8.381.1 Detailed Description

This structure contains the LOC Stop Request

Parameters

sessionId	• ID of the session as identified by the control point. • Range: 0 to 255

8.381.2 Field Documentation

8.381.2.1 BYTE LOCStopReq::sessionId

8.382 lteBandPrefExt Struct Reference

Data Fields

- ULONGLONG bits_1_64
- ULONGLONG bits_65_128
- ULONGLONG bits_129_192
- ULONGLONG bits_193_256

8.382.1 Detailed Description

Contain the LTE Band Preference Extended parameters

Parameters

bits_1_64	• Bits 1 to 64 of the 256-bit LTE E-UTRA Operating Band bitmask.
bits_65_128	• Bits 65 to 128 of the 256-bit LTE E-UTRA Operating Band bitmask.
bits_129_192	• Bits 129 to 192 of the 256-bit LTE E-UTRA Operating Band bitmask.
bits_193_256	• Bits 193 to 256 of the 256-bit LTE E-UTRA Operating Band bitmask.

8.382.2 Field Documentation

8.382.2.1 ULONGLONG lteBandPrefExt::bits_129_192

8.382.2.2 ULONGLONG lteBandPrefExt::bits_193_256

8.382.2.3 ULONGLONG lteBandPrefExt::bits_1_64

8.382.2.4 ULONGLONG lteBandPrefExt::bits_65_128

8.383 LteCiotOpModeTlv Struct Reference

Data Fields

- ULONG campedCiotLteOpMode
- BYTE TlvPresent

8.383.1 Detailed Description

This structure contains Camped CIOT LTE Operational Mode parameters.

Parameters

campedCiotLte-OpMode	• Indicates the camped CIoT LTE mode of operation. • Values: – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_ NB1 (0x03) - Camped on LTE NB1
TlvPresent	• Tlv Present or not

8.383.2 Field Documentation

8.383.2.1 ULONG LteCiotOpModeTlv::campedCiotLteOpMode

8.383.2.2 BYTE LteCiotOpModeTlv::TlvPresent

8.384 LteCQIParm Struct Reference

Data Fields

- BYTE ValidityCW0
- BYTE CQIValueCW0
- BYTE ValidityCW1
- BYTE CQIValueCW1

8.384.1 Detailed Description

This structure contains information about the SLQSSwiGetLteCQI response parameters.

Parameters

pValidityCW0[OUT]	• Values – 0- Invalid. – 1- Valid.
pCQIValueCW0[OUT]	• Values – Range 0∼15
pValidityCW1[OUT]	• Values – 0- Invalid. – 1- Valid.
pCQIValueCW1[OUT]	• Values – Range 0∼15

8.384.2 Field Documentation

8.384.2.1 BYTE LteCQIParm::CQIValueCW0

8.384.2.2 BYTE LteCQIParm::CQIValueCW1

8.384.2.3 BYTE LteCQIParm::ValidityCW0

8.384.2.4 BYTE LteCQIParm::ValidityCW1

8.385 lteEARFCN Struct Reference

Data Fields

- BYTE status
- ULONG earfcn0
- ULONG earfcn1

8.385.1 Detailed Description

This structure contains the parameters for WCDMA UARCFN.

Parameters

status	• 0 - Disable • 1 - Enable

earfcn0	• Primary DL EARFCN to which the UE is locked
earfcn1	• Secondary DL EARFCN to which the UE is locked • Note : Make earfcn1 value equal to earfcn0 if only one EARFCN is desired.

8.385.2 Field Documentation

8.385.2.1 ULONG IteEARFCN::earfcn0

8.385.2.2 ULONG IteEARFCN::earfcn1

8.385.2.3 BYTE IteEARFCN::status

8.386 IteGsmCellInfo Struct Reference

Data Fields

- BYTE cellReselPriority
- BYTE threshGsmHigh
- BYTE threshGsmLow
- BYTE nccPermitted
- BYTE cells_len
- gsmCellInfo GsmCellInfo [255]

8.386.1 Detailed Description

This structure contains information about the LTE GSM Cell.

Parameters

cellReselPriority	• Priority of this frequency group. • Range: 0 to 7. • This field is only valid when ue_in_idle is TRUE.
threshGsmHigh	• Reselection threshold for high priority layers. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE.
threshGsmLow	• Reselection threshold for low priority layers. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE.

nccPermitted	• Bitmask specifying whether a neighbor with a specific network color code is to be reported. • Range: 0 to 255. • Bit n set to 1 means a neighbor with NCC n must be included in the report. This flag is synonymous with a blacklist in other RATs. • This field is only valid when ue_in_idle is TRUE.
cells_len	• Provides the number of set of gsm cells.
GsmCellInfo[MAX_DESCRIPTION_LENGTH]	• See gsmCellInfo for more information.

8.386.2 Field Documentation

8.386.2.1 BYTE lteGsmCellInfo::cellReselPriority

8.386.2.2 BYTE lteGsmCellInfo::cells_len

8.386.2.3 gsmCellInfo lteGsmCellInfo::GsmCellInfo[255]

8.386.2.4 BYTE lteGsmCellInfo::nccPermitted

8.386.2.5 BYTE lteGsmCellInfo::threshGsmHigh

8.386.2.6 BYTE lteGsmCellInfo::threshGsmLow

8.387 LTEInfo Struct Reference

Data Fields

- BYTE band
- BYTE bandwidth
- WORD RXChan
- WORD TXChan
- BYTE emmState
- BYTE emmSubState
- BYTE emmConnState

8.387.1 Detailed Description

Structure for storing the LTE information for the device.

Parameters

band	• LTE Band – 1 ∼ 41 (Band in decimal) – 0xFF - Invalid

bandwidth	• BandWidth. – 0x00 - 1.4 MHz – 0x01 - 3 MHz – 0x02 - 5 MHz – 0x03 - 10 MHz – 0x04 - 15 MHz – 0x05 - 20 MHz – 0x06 - Invalid – 0xFF - Unknown
RXChan	• RX channel number in decimal – 0xFFFF - Not Available
TXChan	• TX channel number in decimal – 0xFFFF - Not Available
emmState	• EMM State. – 0x00 - Deregistered – 0x01 - Reg Initiated – 0x02 - Registered – 0x03 - TAU Initiated – 0x04 - SR Initiated – 0x05 - Dereg Initiated – 0x06 - Invalid – 0xFF - Unknown

emmSubState	• EMM Sub State. – 0xFF - NOT Applicable • When EMM_state is 0x00: – 0x00 - No IMSI – 0x01 - PLMN Search – 0x02 - Attach Needed – 0x03 - No Cell – 0x04 - Attaching – 0x05 - Normal Service – 0x06 - Limited Service – 0x07 - Waiting for PDN • When EMM_state is 0x01: – 0x00 - Waiting for NW – 0x01 - Waiting for ESM • When EMM_state is 0x02: – 0x00 - Normal Service – 0x01 - Update Needed – 0x02 - Attempt Update – 0x03 - No Cell – 0x04 - PLMN Search – 0x05 - Limited Service – 0x06 - MM Update – 0x07 - IMSI Detach – 0x08 - Waiting for ESM
emmConnState	• EMM Connected Mode State. – 0x00 - RRC Idle – 0x01 - Waiting RRC Cfm – 0x02 - RRC Connected – 0x03 - RRC Releasing – 0xFF - Unknown

8.387.2 Field Documentation

8.387.2.1 BYTE LTEInfo::band

8.387.2.2 BYTE LTEInfo::bandwidth

8.387.2.3 BYTE LTEInfo::emmConnState

8.387.2.4 BYTE LTEInfo::emmState

8.387.2.5 BYTE LTEInfo::emmSubState

8.387.2.6 WORD LTEInfo::RXChan

8.387.2.7 WORD LTEInfo::TXChan

8.388 LTEInfoInterfreq Struct Reference

Data Fields

- BYTE ueInIdle
- BYTE freqsLen
- infoInterFreq InfoInterfreq [255]

8.388.1 Detailed Description

This structure contains information about the LTE Inter-Frequency Network.

Parameters

ueInIdle	• TRUE if the UE is in Idle mode, otherwise FALSE. – 0xFF - Not Available
freqsLen	• Provides the number of set of inter frequency information. • If 0(zero), then no information follows it.
InfoInterfreq[MAX_DESCRIPTION_LENGTH]	• See infoInterFreq for more information.

8.388.2 Field Documentation

8.388.2.1 BYTE LTEInfoInterfreq::freqsLen

8.388.2.2 infoInterFreq LTEInfoInterfreq::InfoInterfreq[255]

8.388.2.3 BYTE LTEInfoInterfreq::ueInIdle

8.389 LTEInfoIntrafreq Struct Reference

Data Fields

- BYTE ueInIdle
- BYTE plmn [3]
- WORD tac
- ULONG globalCellId
- WORD earfcn
- WORD servingCellId
- BYTE cellReselPriority
- BYTE sNonIntraSearch
- BYTE threshServingLow
- BYTE sIntraSearch
- BYTE cellsLen
- cellParams CellParams [255]

8.389.1 Detailed Description

This structure contains information about the LTE Intra-Frequency Network.

Parameters

ueInIdle	• TRUE if the UE is in Idle mode, otherwise FALSE. – 0xFF - Not Available
plmn[PLMN_LENGTH]	• PLMN ID coded as octet 3, 4, and 5.
tac	• Tracking area code. – 0xFFFF - Not Available
globalCellId	• Global cell ID in the system information block. – 0xFFFFFFFF - Not Available
earfcn	• E-UTRA absolute radio frequency channel number of the serving cell. • Range: 0 to 65535. – 0xFFFF - Not Available
servingCellId	• LTE serving cell ID. • Range: 0 to 503. • This is the cell ID of the serving cell and can be found in the cell list. – 0xFFFF - Not Available
cellReselPriority	• Priority for serving frequency. • Range: 0 to 7. • This field is only valid when ue_in_idle is TRUE. – 0xFF - Not Available
sNonIntraSearch	• S non-intra search threshold to control non-intrafrequency searches. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE. – 0xFF - Not Available
threshServingLow	• Serving cell low threshold. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE. – 0xFF - Not Available

sIntraSearch	• S Intra search threshold. • Range: 0 to 31. • The current cell measurement must fall below this threshold to consider intrafrequency for reselection. • This field is only valid when ue_in_idle is TRUE. – 0xFF - Not Available
cellsLen	• Provides the number of set of cell params. • If 0(zero), then no information follows it.
CellParams[MAX_DESCRIPTION_LENGTH]	• See cellParams for more information.

8.389.2 Field Documentation

8.389.2.1 cellParams LTEInfoIntrafreq::CellParams[255]

8.389.2.2 BYTE LTEInfoIntrafreq::cellReselPriority

8.389.2.3 BYTE LTEInfoIntrafreq::cellsLen

8.389.2.4 WORD LTEInfoIntrafreq::earfcn

8.389.2.5 ULONG LTEInfoIntrafreq::globalCellId

8.389.2.6 BYTE LTEInfoIntrafreq::plmn[3]

8.389.2.7 WORD LTEInfoIntrafreq::servingCellId

8.389.2.8 BYTE LTEInfoIntrafreq::sIntraSearch

8.389.2.9 BYTE LTEInfoIntrafreq::sNonIntraSearch

8.389.2.10 WORD LTEInfoIntrafreq::tac

8.389.2.11 BYTE LTEInfoIntrafreq::threshServingLow

8.389.2.12 BYTE LTEInfoIntrafreq::ueInIdle

8.390 LTEInfoNeighboringGSM Struct Reference

Data Fields

- BYTE ueInIdle
- BYTE freqsLen
- lteGsmCellInfo LteGsmCellInfo [255]

8.390.1 Detailed Description

This structure contains information about the LTE Neighboring GSM Network.

Parameters

ueInIdle	• TRUE if the UE is in Idle mode, otherwise FALSE. – 0xFF - Not Available
freqsLen	• Provides the number of set of LTE GSM cell information. • If 0(zero), then no information follows it.
LteGsmCellInfo[MAX_DESCRIPTION_LENGTH]	• See lteGsmCellInfo for more information.

8.390.2 Field Documentation

8.390.2.1 BYTE LTEInfoNeighboringGSM::freqsLen

8.390.2.2 lteGsmCellInfo LTEInfoNeighboringGSM::LteGsmCellInfo[255]

8.390.2.3 BYTE LTEInfoNeighboringGSM::ueInIdle

8.391 LTEInfoNeighboringWCDMA Struct Reference

Data Fields

- BYTE ueInIdle
- BYTE freqsLen
- lteWcdmaCellInfo LTEWCDMACellInfo [255]

8.391.1 Detailed Description

This structure contains information about the LTE Neighboring WCDMA Network.

Parameters

ueInIdle	• TRUE if the UE is in Idle mode, otherwise FALSE. – 0xFF - Not Available
freqsLen	• Provides the number of set of LTE WCDMA cell information. • If 0(zero), then no information follows it.
LTEWCDMACellInfo[MAX_DESCRIPTION_LENGTH]	• See lteWcdmaCellInfo for more information.

8.391.2 Field Documentation

8.391.2.1 BYTE LTEInfoNeighboringWCDMA::freqsLen

8.391.2.2 lteWcdmaCellInfo LTEInfoNeighboringWCDMA::LTEWCDMACellInfo[255]

8.391.2.3 BYTE LTEInfoNeighboringWCDMA::ueInIdle

8.392 LteM1BandPrefTlv Struct Reference

Data Fields

- ULONGLONG lteM1BandPref
- BYTE TlvPresent

8.392.1 Detailed Description

Contain the LTE M1 band Preference.

Parameters

lteM1BandPref	• Bitmask representing the LTE M1 band preference • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127
TlvPresent	• Tlv Present

8.392.2 Field Documentation

8.392.2.1 ULONGLONG LteM1BandPrefTlv::lteM1BandPref

8.392.2.2 BYTE LteM1BandPrefTlv::TlvPresent

8.393 LteNasReleaseInfo_s Struct Reference

Data Fields

- BYTE nas_release
- BYTE nas_major
- BYTE nas_minor

8.393.1 Detailed Description

This structure contains LTE Nas Release Infomation

Parameters

nas_release	• LTE NAS release
nas_major	• LTE NAS version major
nas_minor	• LTE NAS version minor

8.393.2 Field Documentation

8.393.2.1 BYTE LteNasReleaseInfo_s::nas_major

8.393.2.2 BYTE LteNasReleaseInfo_s::nas_minor

8.393.2.3 BYTE LteNasReleaseInfo_s::nas_release

8.394 LteNb1BandPrefTlv Struct Reference

Data Fields

- ULONGLONG lteNb1BandPref
- BYTE TlvPresent

8.394.1 Detailed Description

Contain the LTE NB1 band Preference.

Parameters

lteNb1BandPref	• Bitmask representing the LTE NB1 band preference. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127
TlvPresent	• Tlv Present

8.394.2 Field Documentation

8.394.2.1 ULONGLONG LteNb1BandPrefTlv::lteNb1BandPref

8.394.2.2 BYTE LteNb1BandPrefTlv::TlvPresent

8.395 LTEOperationMode Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG * pLTEOperationMode

8.395.1 Detailed Description

This structure contains the LTEOperationMode response parameters.

Parameters

TlvPresent	• Tlv Present
pLTEOperation-Mode	• LTE Operational Mode

8.395.2 Field Documentation

8.395.2.1 ULONG* LTEOperationMode::pLTEOperationMode

8.395.2.2 BYTE LTEOperationMode::TlvPresent

8.396 LteOpMode Struct Reference

Data Fields

- ULONG lteOpMode
- BYTE TlvPresent

8.396.1 Detailed Description

This structure contains LTE Operational Mode

Parameters

lteOpMode	• LTE Operational Mode • CIOT LTE mode on which reject indication is received. • Values – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_NB1 (0x03) - Camped on LTE NB1
TlvPresent	• Tlv Present or not

8.396.2 Field Documentation

8.396.2.1 ULONG LteOpMode::lteOpMode

8.396.2.2 BYTE LteOpMode::TlvPresent

8.397 lteOpModeTlv Struct Reference

Data Fields

- BYTE lteOpModeLen
- WORD MCC [255]
- WORD MNC [255]
- ULONG lteOpMode [255]
- BYTE TlvPresent

8.397.1 Detailed Description

This structure contains the LTE Operational Mode response parameters.

Parameters

lteOpModeLen	• Number of sets of the following elements – MCC – MNC – lteOpMode
MCC	• Mobile Country Code • A 16-bit integer representation of MCC • Range: 0 to 999
MNC	• Mobile Network Code • A 16-bit integer representation of MNC • Range: 0 to 999

IteOpMode	• Indicates the LTE mode of operation. • Values: – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_NB1 (0x03) - Camped on LTE NB1
TlvPresent	• Tlv Present

8.397.2 Field Documentation

8.397.2.1 ULONG IteOpModeTlv::IteOpMode[255]

8.397.2.2 BYTE IteOpModeTlv::IteOpModeLen

8.397.2.3 WORD IteOpModeTlv::MCC[255]

8.397.2.4 WORD IteOpModeTlv::MNC[255]

8.397.2.5 BYTE IteOpModeTlv::TlvPresent

8.398 ItePCI Struct Reference

Data Fields

- BYTE status
- ULONG earfcn
- ULONG pci

8.398.1 Detailed Description

This structure contains the parameters for WCDMA UARCFN.

Parameters

status	• 0 - Disable • 1 - Enable
earfcn	• UARFCN to which UE is locked
pci	• PCI to which the UE is locked

8.398.2 Field Documentation

8.398.2.1 ULONG ltePCI::earfcn

8.398.2.2 ULONG ltePCI::pci

8.398.2.3 BYTE ltePCI::status

8.399 lteRsrpinformation Struct Reference

Data Fields

- SHORT rsrplevel

8.399.1 Detailed Description

This structure contains the LTE RSRP Information

Parameters

rsrplevel	• LTE RSRP in dBm as a mesaured by L1. Range: -44 to -140(-44 means -44dBm, -140 means -140dBm).

8.399.2 Field Documentation

8.399.2.1 SHORT lteRsrpinformation::rsrplevel

8.400 LTERSRPThresh Struct Reference

Data Fields

- BYTE LTERSRPThreshListLen
- WORD * pLTERSRPThreshList

8.400.1 Detailed Description

This structure contains LTE RSRP threshold related parameters.

Parameters

LTERSRP-ThreshListLen	• Length of the LTE RSRP threshold list parameter to follow
pLTERSRP-ThreshList	• Array of RSRP thresholds (in units of 0.1 dBm) • Maximum of 32 values • Range for RSRP values: -140 to -44 (in dBm).

8.400.2 Field Documentation

8.400.2.1 BYTE LTERSRPThresh::LTERSRPThreshListLen

8.400.2.2 WORD* LTERSRPThresh::pLTERSRPThreshList

8.401 LTERSRQThresh Struct Reference

Data Fields

- BYTE LTERSRQThreshListLen
- WORD * pLTERSRQThreshList

8.401.1 Detailed Description

This structure contains LTE RSRQ threshold related parameters.

Parameters

LTERSRQ-ThreshListLen	• Length of the LTE RSRQ threshold list parameter to follow
pLTERSRQ-ThreshList	• Array of RSRQ thresholds (in units of 0.1 dBm) • Maximum of 32 values. • Range for RSRQ values: -20 to -3 (in dBm)

8.401.2 Field Documentation

8.401.2.1 BYTE LTERSRQThresh::LTERSRQThreshListLen

8.401.2.2 WORD* LTERSRQThresh::pLTERSRQThreshList

8.402 LTERSSIThresh Struct Reference

Data Fields

- BYTE LTERSSIThreshListLen
- WORD * pLTERSSIThreshList

8.402.1 Detailed Description

This structure contains LTE RSSI threshold related parameters.

Parameters

LTERSSI-ThreshListLen	• Length of the LTE RSSI threshold list parameter to follow
pLTERSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • Maximum of 32 values. • Range for RSSI values: -120 to 0 (in dBm)

8.402.2 Field Documentation

8.402.2.1 BYTE LTERSSIThresh::LTERSSIThreshListLen

8.402.2.2 WORD* LTERSSIThresh::pLTERSSIThreshList

8.403 LteSccRxInfoResp Struct Reference

Data Fields

- SccRxInfo * pSccRxInfo

8.403.1 Detailed Description

This structure contains information about the SLQSSwiGetLteSccRxInfo response parameters.

Parameters

pSccRxInfo	[Optional] • See SccRxInfo for more information

8.403.2 Field Documentation

8.403.2.1 SccRxInfo* LteSccRxInfoResp::pSccRxInfo

8.404 LTESigRptCfg Struct Reference

Data Fields

- BYTE rptRate
- BYTE avgPeriod

8.404.1 Detailed Description

This structure contains LTE Signal Report Config parameters.

Parameters

rptRate	• Rate on how often the LTE signal must be checked for reporting • Values: – 0 - Report using the default configuration – 1 - Report every 1 sec – 2 - Report every 2 sec – 3 - Report every 3 sec – 4 - Report every 4 sec – 5 - Report every 5 sec

avgPeriod	• Averaging period to be used for the LTE signal • Values: – 0 - Average using the default configuration – 1 - Average over 1 sec – 2 - Average over 2 sec – 3 - Average over 3 sec – 4 - Average over 4 sec – 5 - Average over 5 sec – 6 - Average over 6 sec – 7 - Average over 7 sec – 8 - Average over 8 sec – 9 - Average over 9 sec – 10 - Average over 10 sec

8.404.2 Field Documentation

8.404.2.1 BYTE LTESigRptCfg::avgPeriod

8.404.2.2 BYTE LTESigRptCfg::rptRate

8.405 LTESigRptConfig Struct Reference

Data Fields

- BYTE rptRate
- BYTE avgPeriod

8.405.1 Detailed Description

This structure contains LTE RSRP threshold related parameters.

Parameters

rptRate	• Rate on how often the LTE signal must be checked for reporting Values • 0 - Report using the default configuration • 1 - Report every 1 sec • 2 - Report every 2 sec • 3 - Report every 3 sec • 4 - Report every 4 sec • 5 - Report every 5 sec

avgPeriod	• Averaging period to be used for the LTE signal. • Values – 0 - Average using the default configuration – 1 - Average over 1 sec – 2 - Average over 2 sec – 3 - Average over 3 sec – 4 - Average over 4 sec – 5 - Average over 5 sec – 6 - Average over 6 sec – 7 - Average over 7 sec – 8 - Average over 8 sec – 9 - Average over 9 sec – 10 - Average over 10 sec

8.405.2 Field Documentation

8.405.2.1 BYTE LTESigRptConfig::avgPeriod

8.405.2.2 BYTE LTESigRptConfig::rptRate

8.406 IteSnrinformation Struct Reference

Data Fields

- SHORT snrlevel

8.406.1 Detailed Description

This structure contains the LTE SNR Information

Parameters

snrlevel	• LTE SNR level as a scaled integer in units of 0.1dB e.g. -16dB has a value of -160 and 24.6dB has value of 246.

8.406.2 Field Documentation

8.406.2.1 SHORT IteSnrinformation::snrlevel

8.407 LTESNRThresh Struct Reference

Data Fields

- BYTE LTESNRThresListLen
- SHORT * pLTESNRThresList

8.407.1 Detailed Description

This structure contains LTE SNR threshold related parameters.

Parameters

LTESNRThres-ListLen	• Length of the LTE SNR threshold list parameter to follow
pLTESNRThres-List	• Sequence of thresholds delimiting SNR event reporting bands • Every time a SNR value crosses a threshold value, an event report indication message with the new SNR value is sent to the requesting control point. For this field – For LTE, each SNR threshold value is a signed 2 Byte value – Maximum number of threshold values is 16 – At least one value must be specified – SNR level as a scaled integer in units of 0.1 dB; e.g., -16 dB has a value of -160 and 24.6 dB has a value of 246

8.407.2 Field Documentation

8.407.2.1 BYTE LTESNRThresh::LTESNRThresListLen

8.407.2.2 SHORT∗ LTESNRThresh::pLTESNRThresList

8.408 LTESNRThreshold Struct Reference

Data Fields

- BYTE LTESNRThreshListLen
- WORD ∗ pLTESNRThreshList

8.408.1 Detailed Description

This structure contains LTE SNR threshold related parameters.

Parameters

LTESNRThresh-ListLen	• Length of the LTE SNR threshold list parameter to follow
pLTESNR-ThreshList	• Array of SNR thresholds (in units of 0.1 dB) • Maximum of 32 values • Range for SNR values: -20 to 30 (in dB).

8.408.2 Field Documentation

8.408.2.1 BYTE LTESNRThreshold::LTESNRThreshListLen

8.408.2.2 WORD* LTESNRThreshold::pLTESNRThreshList

8.409 lteSSInfo Struct Reference

Data Fields

- int8_t rssi
- int8_t rsrq
- int16_t rsrp
- int16_t snr

8.409.1 Detailed Description

This structure contains the parameters for LTE Signal Strength Information

Parameters

rssi	• RSSI in dBm (signed value).
	• A value of -125 dBm or lower is used to indicate No Signal.
	  – For CDMA and UMTS, this indicates forward link pilot Ec
	  – For GSM, this indicates received signal strength

rsrq	• RSRQ value in dB (signed integer value) as measured by L1. • Range: -3 to -20 (-3 means -3 dB, -20 means -20 dB).
rsrp	• Current RSRP in dBm as measured by L1. • Range: -44 to -140 (-44 means -44 dBm, -140 means -140 dBm).
snr	• SNR level as a scaled integer in units of 0.1 dB. e.g., -16 dB has a value of -160 and 24.6 dB has a value of 246,

8.409.2 Field Documentation

8.409.2.1 int16_t lteSSInfo::rsrp

8.409.2.2 int8_t lteSSInfo::rsrq

8.409.2.3 int8_t lteSSInfo::rssi

8.409.2.4 int16_t lteSSInfo::snr

8.410 LTESSInfo Struct Reference

Data Fields

- INT8 rssi
- INT8 rsrq
- SHORT rsrp

- SHORT snr

8.410.1 Detailed Description

This structure contains the parameters for LTE Signal Strength Information

Parameters

rssi	• RSSI in dBm (signed value).
	• A value of -125 dBm or lower is used to indicate No Signal.
	  – For CDMA and UMTS, this indicates forward link pilot Ec
	  – For GSM, this indicates received signal strength

rsrq	• RSRQ value in dB (signed integer value) as measured by L1. • Range: -3 to -20 (-3 means -3 dB, -20 means -20 dB).
rsrp	• Current RSRP in dBm as measured by L1. • Range: -44 to -140 (-44 means -44 dBm, -140 means -140 dBm).
snr	• SNR level as a scaled integer in units of 0.1 dB. e.g., -16 dB has a value of -160 and 24.6 dB has a value of 246,

8.410.2 Field Documentation

8.410.2.1 SHORT LTESSInfo::rsrp

8.410.2.2 INT8 LTESSInfo::rsrq

8.410.2.3 INT8 LTESSInfo::rssi

8.410.2.4 SHORT LTESSInfo::snr

8.411 LTESysInfo Struct Reference

Data Fields

- sysInfoCommon sysInfoLTE
- BYTE lacValid
- WORD lac
- BYTE cellIdValid
- ULONG cellId
- BYTE regRejectInfoValid
- BYTE rejectSrvDomain
- BYTE rejCause
- BYTE networkIdValid
- BYTE MCC [3]
- BYTE MNC [3]
- BYTE tacValid
- WORD tac

8.411.1 Detailed Description

Structure for storing the LTE System Information.

Parameters

sysInfoLTE	• See sysInfoCommon for more information.
lacValid	• Indicates whether the location area code is valid.. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
lac	• Location area code. • Only applies to 3GPP. – 0xFFFF - Not Available
cellIdValid	• Indicates whether the cell ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
cellId	• Cell ID. – 0xFFFFFFFF - Not Available
regRejectInfo-Valid	• Indicates whether the registration reject information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
rejectSrvDomain	• Type of service domain in which the registration is rejected. – 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available
rejCause	• Reject cause values sent are specified in [3GPP TS 24.008, Section 10.5.3.6]. – 0xFF - Not Available

networkIdValid	• Indicates whether the network ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
MCC[PLMN_LENGTH]	• Mobile Country Code. • MCC digits in ASCII characters
MNC[PLMN_LENGTH]	• Mobile Network Code. • MNC digits in ASCII characters • An unused byte is set to 0xFF. • In case of two-digit MNC values, the third (unused) digit is set to 0xFF. For example, 15 (a two-digit MNC) is reported using the byte stream 0x31 0x35 0xFF.
tacValid	• Indicates whether tracking area code is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
tac	• Tracking area code. • Only applicable for LTE. – 0xFFFF - Not Available

8.411.2 Field Documentation

8.411.2.1 ULONG LTESysInfo::cellId

8.411.2.2 BYTE LTESysInfo::cellIdValid

8.411.2.3 WORD LTESysInfo::lac

8.411.2.4 BYTE LTESysInfo::lacValid

8.411.2.5 BYTE LTESysInfo::MCC[3]

8.411.2.6 BYTE LTESysInfo::MNC[3]

8.411.2.7 BYTE LTESysInfo::networkIdValid

8.411.2.8 BYTE LTESysInfo::regRejectInfoValid

8.411.2.9 BYTE LTESysInfo::rejCause

8.411.2.10 BYTE LTESysInfo::rejectSrvDomain

8.411.2.11 sysInfoCommon LTESysInfo::sysInfoLTE

8.411.2.12 WORD LTESysInfo::tac

8.411.2.13 BYTE LTESysInfo::tacValid

8.412 lteWcdmaCellInfo Struct Reference

Data Fields

- WORD uarfcn
- BYTE cellReselPriority
- WORD threshXhigh
- WORD threshXlow
- BYTE cellsLen
- wcdmaCellInfo WCDMACellInfo [255]

8.412.1 Detailed Description

This structure contains information about the LTE WCDMA Cell.

Parameters

uarfcn	• WCDMA layer frequency. • Range: 0 to 16383.
cellReselPriority	• Cell re-selection priority. • Range: 0 to 7. • This field is only valid when ue_in_idle is TRUE.
threshXhigh	• Re-selection low threshold. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE.
threshXlow	• Re-selection high threshold. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE.
cellsLen	• Provides the number of set of WCDMA cells.
WCDMACellInfo[MAX_DESCRIPTION_LENGTH]	• See wcdmaCellInfo for more information.

8.412.2 Field Documentation

8.412.2.1 BYTE lteWcdmaCellInfo::cellReselPriority

8.412.2.2 BYTE lteWcdmaCellInfo::cellsLen

8.412.2.3 WORD lteWcdmaCellInfo::threshXhigh

8.412.2.4 WORD lteWcdmaCellInfo::threshXlow

8.412.2.5 WORD lteWcdmaCellInfo::uarfcn

8.412.2.6 wcdmaCellInfo lteWcdmaCellInfo::WCDMACellInfo[255]

8.413 messageModeTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- sMSMessageModeInfo MessageModeInfo

8.413.1 Detailed Description

This structure contains message mode TLV information.

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response
MessageMode-Info	• Message Mode • See sMSMessageModeInfo for more information

8.413.2 Field Documentation

8.413.2.1 sMSMessageModeInfo messageModeTlv::MessageModeInfo

8.413.2.2 uint8_t messageModeTlv::TlvPresent

8.414 messageWaitingInfoContent Struct Reference

Data Fields

- BYTE msgType
- BYTE activeInd
- BYTE msgCount

8.414.1 Detailed Description

This structure contains message waiting information per instance

Parameters

msgType	• Message type – 0x00 - MWI_MESSAGE_TYPE_VOICMAIL - Voicemail – 0x01 - MWI_MESSAGE_TYPE_FAX - Fax – 0X02 - MWI_MESSAGE_TYPE_EMAIL - Email – 0x03 - MWI_MESSAGE_TYPE_OTHER - Other – 0x04 - MWI_MESSAGE_TYPE_VIDEOMAIL - Videomail
activeInd	• Indicates whether the indication is active – 0x00 - Inactive – 0x01 - Active
msgCount	• Number of messages

8.414.2 Field Documentation

8.414.2.1 BYTE messageWaitingInfoContent::activeInd

8.414.2.2 BYTE messageWaitingInfoContent::msgCount

8.414.2.3 BYTE messageWaitingInfoContent::msgType

8.415 minBasedIMSI Struct Reference

Data Fields

- BYTE mccM [3]
- WORD imsiM1112
- BYTE imsiMS1 [7]
- BYTE imsiMS2 [3]

8.415.1 Detailed Description

This structure contains the parameters for Min based IMSI Information

Parameters

mccM	• ASCII character representation of MCC_M
imsiM1112	• ASCII character representation of IMSI_M_11_12 value – 0xFFFF - Not Available
imsiMS1	• ASCII character representation of IMSI_M_S1 value
imsiMS2	• ASCII character representation of IMSI_M_S2 value

8.415.2 Field Documentation

8.415.2.1 WORD minBasedIMSI::imsiM1112

8.415.2.2 BYTE minBasedIMSI::imsiMS1[7]

8.415.2.3 BYTE minBasedIMSI::imsiMS2[3]

8.415.2.4 BYTE minBasedIMSI::mccM[3]

8.416 mitigationDevList Struct Reference

Data Fields

- BYTE mitigationDevIdLen
- CHAR mitigationDevId [255]
- BYTE maxMitigationLevel

8.416.1 Detailed Description

This structure contains mitigation devices list

Parameters

mitigationDevId-Len	• Number of sets of the following elements – mitigation_dev_id
mitigationDevId	• Mitigation device ID.
maxMitigation-Level	• Maximum valid mitigation level. • Valid range - 0 to max_mitigation_level.

8.416.2 Field Documentation

8.416.2.1 BYTE mitigationDevList::maxMitigationLevel

8.416.2.2 CHAR mitigationDevList::mitigationDevId[255]

8.416.2.3 BYTE mitigationDevList::mitigationDevIdLen

8.417 MNRInfo Struct Reference

Data Fields

- WORD mcc
- WORD mnc
- ULONG rat

8.417.1 Detailed Description

Structure contains Manual Network Register Information parameters

Parameters

mcc	• A 16-bit integer representation of Mobile Country Code. Range - 0 to 999.
mnc	• A 16-bit integer representation of Mobile Network Code. Range - 0 to 999.
rat	• Radio access technology for which to register. – 0x04 - RADIO_IF_GSM – 0x05 - RADIO_IF_UMTS – 0x08 - RADIO_IF_LTE

8.417.2 Field Documentation

8.417.2.1 WORD MNRInfo::mcc

8.417.2.2 WORD MNRInfo::mnc

8.417.2.3 ULONG MNRInfo::rat

8.418 ModifyProfileIn Struct Reference

Data Fields

- BYTE * pProfileID
- BYTE * pProfileType
- QmiProfileInfo curProfile

8.418.1 Detailed Description

This structure contains input parameters for SLQSModifyProfile

Parameters

ProfileID	• 1 to 16 for 3GPP profile (EM/MC73xx or earlier) • 1 to 24 for 3GPP profile (EM/MC74xx onwards) • 101 to 106 for 3GPP2 profile
ProfileType	• Identifies the technology type of the profile – 0x00 - 3GPP – 0x01 - 3GPP2 – NULL is not allowed

curProfile	• Contains Union of profile(3GPP/3GPP2) structures

8.418.2 Field Documentation

8.418.2.1 QmiProfileInfo ModifyProfileIn::curProfile

8.418.2.2 BYTE* ModifyProfileIn::pProfileID

8.418.2.3 BYTE* ModifyProfileIn::pProfileType

8.419 ModifyProfileOut Struct Reference

Data Fields

- USHORT * pExtErrorCode

8.419.1 Detailed Description

This structure contains out parameters for SLQSModifyProfile

Parameters

pExtErrorCode	• The extended error code received from DS Profile subsystem of type eWDS_ERR_PROFILE_-REG_xxx. • Error code will only will be present if error code eQCWWAN_ERR_QMI_EXTENDED_INTERN-AL is returned by device. • See qm_wds_ds_profile_extended_err_codes enum in qmerrno.h for received error description.

8.419.2 Field Documentation

8.419.2.1 USHORT* ModifyProfileOut::pExtErrorCode

8.420 msgWaitingInfo Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE numInstances
- messageWaitingInfoContent msgWaitInfo [0xFF]

8.420.1 Detailed Description

This structure holds information related to message waiting information

Parameters

numInstances	• Number of sets of the elements in structure messageWaitingInfoContent
msgWaitInfo	• Pointer to structure of messageWaitingInfoContent. – See messageWaitingInfoContent for more information.

8.420.2 Field Documentation

8.420.2.1 messageWaitingInfoContent msgWaitingInfo::msgWaitInfo[0xFF]

8.420.2.2 BYTE msgWaitingInfo::numInstances

8.420.2.3 struct qmTlvResult msgWaitingInfo::results

8.421 mtuSize3gppTlv Struct Reference

Data Fields

- BYTE TlvPresent
- WORD MTUSize3gpp

8.421.1 Detailed Description

This structure contains the parameters for 3GPP MTU Size.

Parameters

TlvPresent	• Tlv Present.
MTUSize3gpp	3GPP MTU size • Size of 3GPP MTU

8.421.2 Field Documentation

8.421.2.1 WORD mtuSize3gppTlv::MTUSize3gpp

8.421.2.2 BYTE mtuSize3gppTlv::TlvPresent

8.422 MTUSizeReq Struct Reference

Data Fields

- WORD MTUSize

8.422.1 Detailed Description

This structure contains the Set MTU request parameter.

Parameters

MTUSize	• Set MTU size • MTU Values – 0 - use default value – 576 to 2000 - other values required by carrier. – Set the same MTU for all RAT/interfaces.

8.422.2 Field Documentation

8.422.2.1 WORD MTUSizeReq::MTUSize

8.423 namName Struct Reference

Data Fields

- BYTE namNameLen
- BYTE namName [12]

8.423.1 Detailed Description

This structure contains the parameters for NAM Name Information

Parameters

namNameLen	• Number of sets of the following elements: – nam_name • If zero(0), then no information follows.
namName	• Name information in ASCII. The maximum length of nam_name is 12.

8.423.2 Field Documentation

8.423.2.1 BYTE namName::namName[12]

8.423.2.2 BYTE namName::namNameLen

8.424 nas_acqOrderPref Struct Reference

Data Fields

- uint8_t acqOrdeLen
- uint8_t * pAcqOrder

8.424.1 Detailed Description

Contain the Acquisition Order Preference.

Parameters

acqOrdeLen	• Number of sets of the following elements.
pAcqOrder	• Acquisition order preference to be set. Values: – 0x01 - NAS_RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE – 0x09 - NAS_RADIO_IF_TDSCDMA - TD-SCDMA

8.424.2 Field Documentation

8.424.2.1 uint8_t nas_acqOrderPref::acqOrdeLen

8.424.2.2 uint8_t∗ nas_acqOrderPref::pAcqOrder

8.425 nas_AcqOrderPrefTlv Struct Reference

Data Fields

- uint8_t acqOrdeLen
- uint8_t ∗ pAcqOrder
- uint8_t TlvPresent

8.425.1 Detailed Description

Contain the Acquisition Order Preference.

Parameters

acqOrdeLen	• Number of sets of the following elements.
pAcqOrder	• Acquisition order preference to be set. Values: – 0x01 - NAS_RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE – 0x09 - NAS_RADIO_IF_TDSCDMA - TD-SCDMA – 0x0C - NAS_RADIO_IF_NR5G - NR5G
TlvPresent	• Tlv Present

8.425.2 Field Documentation

8.425.2.1 uint8_t nas_AcqOrderPrefTlv::acqOrdeLen

8.425.2.2 uint8_t* nas_AcqOrderPrefTlv::pAcqOrder

8.425.2.3 uint8_t nas_AcqOrderPrefTlv::TlvPresent

8.426 nas_ActPilotPNElement Struct Reference

Data Fields

- uint16_t ActSetPilotPN
- uint8_t ActSetPilotPNStrength

8.426.1 Detailed Description

This structure contains pilot PN Element.

Parameters

ActSetPilotPN	• Active Pilot PN
ActSetPilotPN-Strength	• Active Pilot PN strength

8.426.2 Field Documentation

8.426.2.1 uint16_t nas_ActPilotPNElement::ActSetPilotPN

8.426.2.2 uint8_t nas_ActPilotPNElement::ActSetPilotPNStrength

8.427 nas_AddCDMASysInfo Struct Reference

Data Fields

- uint16_t geoSysIdx
- uint16_t regPrd

8.427.1 Detailed Description

Structure for storing the Additional CDMA System Information.

Parameters

geoSysIdx	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used.

regPrd	• Registration period after the CDMA system is acquired. • When the CDMA registration period is not valid, 0xFFFF is used.

8.427.2 Field Documentation

8.427.2.1 uint16_t nas_AddCDMASysInfo::geoSysIdx

8.427.2.2 uint16_t nas_AddCDMASysInfo::regPrd

8.428 nas_AddSysInfo Struct Reference

Data Fields

- uint16_t geoSysIdx
- uint32_t cellBroadcastCap

8.428.1 Detailed Description

Structure for storing the Additional GSM and WCDMA System Information.

Parameters

geoSysIdx	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used.
cellBroadcast-Cap	• Cell broadcast capability of the serving system. • When the CDMA registration period is not valid, 0xFFFF is used. – NAS_CELL_BROADCAST_CAP_UNKNOWN - Cell broadcast support is unknown – NAS_CELL_BROADCAST_CAP_OFF - Cell broadcast is not supported – NAS_CELL_BROADCAST_CAP_ON - Cell broadcast is supported

8.428.2 Field Documentation

8.428.2.1 uint32_t nas_AddSysInfo::cellBroadcastCap

8.428.2.2 uint16_t nas_AddSysInfo::geoSysIdx

8.429 nas_BandPrefInfoTlv Struct Reference

Data Fields

- uint64_t bits_1_64
- uint64_t bits_65_128
- uint64_t bits_129_192
- uint64_t bits_193_256

- uint8_t TlvPresent

8.429.1 Detailed Description

Contain the Band Preference.

Parameters

bits_1_64	• Bits 1 to 64 of the 256-bit Operating Band bitmask.
bits_65_128	• Bits 65 to 128 of the 256-bit Operating Band bitmask.
bits_129_192	• Bits 129 to 192 of the 256-bit Operating Band bitmask.
bits_193_256	• Bits 193 to 256 of the 256-bit Operating Band bitmask.
TlvPresent	• Tlv Present

8.429.2 Field Documentation

8.429.2.1 uint64_t nas_BandPrefInfoTlv::bits_129_192

8.429.2.2 uint64_t nas_BandPrefInfoTlv::bits_193_256

8.429.2.3 uint64_t nas_BandPrefInfoTlv::bits_1_64

8.429.2.4 uint64_t nas_BandPrefInfoTlv::bits_65_128

8.429.2.5 uint8_t nas_BandPrefInfoTlv::TlvPresent

8.430 nas_BandPrefTlv Struct Reference

Data Fields

- uint64_t BandPref
- uint8_t TlvPresent

8.430.1 Detailed Description

Contain the band preference for system selection preferences.

Parameters

BandPref	• Bitmask representing the radio technologies that are disabled. • Bit values: • Bit mask representing the band preference • Bit values: – Bit 0 - Band Class 0, A-System – Bit 1 - Band Class 0, B-System, Band Class 0 AB, GSM 850 Band – Bit 2 - Band Class 1, all blocks – Bit 3 - Band Class 2 place holder – Bit 4 - Band Class 3, A-System – Bit 5 - Band Class 4, all blocks – Bit 6 - Band Class 5, all blocks – Bit 7 - GSM_DCS_1800 band – Bit 8 - GSM Extended GSM (E-GSM) 900 band – Bit 9 - GSM Primary GSM (P-GSM) 900 band – Bit 10 - Band Class 6 – Bit 11 - Band Class 7 – Bit 12 - Band Class 8 – Bit 13 - Band Class 9 – Bit 14 - Band Class 10 – Bit 15 - Band Class 11 – Bit 16 - GSM 450 band – Bit 17 - GSM 480 band – Bit 18 - GSM 750 band – Bit 19 - GSM 850 band – Bit 20 - GSM Railways GSM 900 Band – Bit 21 - GSM PCS 1900 band – Bit 22 - WCDMA Europe, Japan, and China IMT 2100 band – Bit 23 - WCDMA U.S. PCS 1900 band – Bit 24 - WCDMA Europe and China DCS 1800 band – Bit 25 - WCDMA U.S. 1700 band – Bit 26 - WCDMA U.S. 850 band – Bit 27 - WCDMA Japan 800 band – Bit 28 - Band Class 12 – Bit 29 - Band Class 14 – Bit 30 - Reserved – Bit 31 - Band Class 15 – Bit 32 to 47 - Reserved – Bit 48 - WCDMA Europe 2600 band – Bit 49 - WCDMA Europe and Japan 900 band – Bit 50 - WCDMA Japan 1700 band – Bit 51 to 55 - Reserved – Bit 56 - Band Class 16 – Bit 57 - Band Class 17 – Bit 58 - Band Class 18 – Bit 59 - Band Class 19 – Bit 60 to 64 - Reserved

TlvPresent	• Tlv Present

8.430.2 Field Documentation

8.430.2.1 uint64_t nas_BandPrefTlv::BandPref

8.430.2.2 uint8_t nas_BandPrefTlv::TlvPresent

8.431 nas_CallBarringSysInfo Struct Reference

Data Fields

- uint32_t csBarStatus
- uint32_t psBarStatus

8.431.1 Detailed Description

Structure for storing the GSM and WCDMA Call Barring System Information.

Parameters

csBarStatus	• Call barring status for circuit-switched calls. – NAS_CELL_ACCESS_NORMAL_ONLY - Cell access is allowed for normal calls only – NAS_CELL_ACCESS_EMERGENCY_ONLY - Cell access is allowed for emergency calls only – NAS_CELL_ACCESS_NO_CALLS - Cell access is not allowed for any call type – NAS_CELL_ACCESS_ALL_CALLS - Cell access is allowed for all call types – NAS_CELL_ACCESS_UNKNOWN - Cell access type is unknown
psBarStatus	• Call barring status for packet-switched calls. – NAS_CELL_ACCESS_NORMAL_ONLY - Cell access is allowed for normal calls only – NAS_CELL_ACCESS_EMERGENCY_ONLY - Cell access is allowed for emergency calls only – NAS_CELL_ACCESS_NO_CALLS - Cell access is not allowed for any call type – NAS_CELL_ACCESS_ALL_CALLS - Cell access is allowed for all call types – NAS_CELL_ACCESS_UNKNOWN - Cell access type is unknown

8.431.2 Field Documentation

8.431.2.1 uint32_t nas_CallBarringSysInfo::csBarStatus

8.431.2.2 uint32_t nas_CallBarringSysInfo::psBarStatus

8.432 nas_callBarStatus Struct Reference

Data Fields

- uint32_t csBarStatus
- uint32_t psBarStatus

8.432.1 Detailed Description

This structure contains Call Barring Status.

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

csBarStatus	• Call Barring Status for circuit-switched calls. • Values: • NAS_CELL_ACCESS_NORMAL_ONLY - Cell access is allowed for normal calls only • NAS_CELL_ACCESS_EMERGENCY_ONLY - Cell access is allowed for emergency calls only • NAS_CELL_ACCESS_NO_CALLS - Cell access is not allowed for any call type • NAS_CELL_ACCESS_ALL_CALLS - Cell access is allowed for all call types • NAS_CELL_ACCESS_UNKNOWN - Cell access type is unknown
psBarStatus	• Call Barring Status for packet-switched calls. • Values: – NAS_CELL_ACCESS_NORMAL_ONLY - Cell access is allowed for normal calls only – NAS_CELL_ACCESS_EMERGENCY_ONLY - Cell access is allowed for emergency calls only – NAS_CELL_ACCESS_NO_CALLS - Cell access is not allowed for any call type – NAS_CELL_ACCESS_ALL_CALLS - Cell access is allowed for all call types – NAS_CELL_ACCESS_UNKNOWN - Cell access type is unknown

8.432.2 Field Documentation

8.432.2.1 uint32_t nas_callBarStatus::csBarStatus

8.432.2.2 uint32_t nas_callBarStatus::psBarStatus

8.433 nas_CDMAChannel Struct Reference

Data Fields

- uint16_t priChA
- uint16_t priChB
- uint16_t secChA
- uint16_t secChB

8.433.1 Detailed Description

This structure contains CDMA channel.

Parameters

priChA	• A Channel number for the primary carrier. – 0xFFFF - Not Available
priChB	• B Channel number for the primary carrier. – 0xFFFF - Not Available
secChA	• A Channel number for the secondary carrier. – 0xFFFF - Not Available
secChB	• B Channel number for the secondary carrier. – 0xFFFF - Not Available

8.433.2 Field Documentation

8.433.2.1 uint16_t nas_CDMAChannel::priChA

8.433.2.2 uint16_t nas_CDMAChannel::priChB

8.433.2.3 uint16_t nas_CDMAChannel::secChA

8.433.2.4 uint16_t nas_CDMAChannel::secChB

8.434 nas_CDMAECIOThresh Struct Reference

Data Fields

- uint8_t CDMAECIOThreshListLen
- int16_t * pCDMAECIOThreshList

8.434.1 Detailed Description

This structure contains CDMA ECIO threshold related parameters.

Parameters

CDMAECIO-ThreshListLen	• Length of the CDMA ECIO threshold list parameter to follow
pCDMAECIO-ThreshList	• Array of ECIO thresholds (in units of 0.1 dB) • Maximum of 32 values. Range for ECIO values: -31.5 to 0 (in dB)

8.434.2 Field Documentation

8.434.2.1 uint8_t nas_CDMAECIOThresh::CDMAECIOThreshListLen

8.434.2.2 int16_t* nas_CDMAECIOThresh::pCDMAECIOThreshList

8.435 nas_CDMAInfo Struct Reference

Data Fields

- uint16_t sid
- uint16_t nid
- uint16_t baseId
- uint16_t refpn
- uint32_t baseLat
- uint32_t baseLong

8.435.1 Detailed Description

This structure contains information about the CDMA Network.

Parameters

sid	• System ID. – 0xFFFF - Not Available
nid	• Network ID. – 0xFFFF - Not Available
baseId	• Base station ID. – 0xFFFF - Not Available
refpn	• Reference PN. – 0xFFFF - Not Available
baseLat	• Latitude of the current base station in units of 0.25 sec. – 0xFFFFFFFF - Not Available
baseLong	• Longitude of the current base station in units of 0.25 sec. – 0xFFFFFFFF - Not Available

8.435.2 Field Documentation

8.435.2.1 uint16_t nas_CDMAInfo::baseId

8.435.2.2 uint32_t nas_CDMAInfo::baseLat

8.435.2.3 uint32_t nas_CDMAInfo::baseLong

8.435.2.4 uint16_t nas_CDMAInfo::nid

8.435.2.5 uint16_t nas_CDMAInfo::refpn

8.435.2.6 uint16_t nas_CDMAInfo::sid

8.436 nas_CDMARSSIThresh Struct Reference

Data Fields

- uint8_t CDMARSSIThreshListLen
- int16_t * pCDMARSSIThreshList

8.436.1 Detailed Description

This structure contains CDMA RSSI threshold related parameters.

Parameters

CDMARSSI-ThreshListLen	• Length of the CDMARSSI threshold list parameter to follow
pCDMARSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • maximum of 32 values. • Range for RSSI values:-105 to -21 (in dBm).

8.436.2 Field Documentation

8.436.2.1 uint8_t nas_CDMARSSIThresh::CDMARSSIThreshListLen

8.436.2.2 int16_t* nas_CDMARSSIThresh::pCDMARSSIThreshList

8.437 nas_CDMASysInfo Struct Reference

Data Fields

- nas_sysInfoCommon sysInfoCDMA
- uint8_t isSysPrlMatchValid
- uint8_t isSysPrlMatch
- uint8_t pRevInUseValid
- uint8_t pRevInUse
- uint8_t bsPRevValid
- uint8_t bsPRev
- uint8_t ccsSupportedValid
- uint8_t ccsSupported
- uint8_t cdmaSysIdValid
- uint16_t systemID
- uint16_t networkID
- uint8_t bsInfoValid
- uint16_t baseId
- uint32_t baseLat

- uint32_t baseLong
- uint8_t packetZoneValid
- uint16_t packetZone
- uint8_t networkIdValid
- uint8_t MCC [3]
- uint8_t MNC [3]

8.437.1 Detailed Description

Structure for storing the CDMA System Information.

Parameters

sysInfoCDMA	• See nas_sysInfoCommon for more information.
isSysPrlMatch-Valid	• Indicates whether the system PRL match is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
isSysPrlMatch	• Indicates whether the system is in a PRL. • Only applies to CDMA/HDR. – 0x00 - System is not in a PRL – 0x01 - System is in a PRL – 0xFF - Not Available • If the system is not in a PRL, roam_status carries the value from the default roaming indicator in the PRL. • If the system is in a PRL, roam_status is set to the value based on the standard specification.
pRevInUseValid	• Indicates whether the P_Rev in use is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
pRevInUse	• The lesser of the base station P_Rev and mobile P_Rev • Only applicable for CDMA. – 0xFF - Not Available
bsPRevValid	• Indicates whether the base station P_Rev is valid – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
bsPRev	• Base station P_Rev. • Only applicable for CDMA. – 0xFF - Not Available

ccsSupported-Valid	• Indicates whether the supported concurrent service is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
ccsSupported	• Whether concurrent service is supported. • Only applicable for CDMA. – 0x00 - Not supported – 0x01 - Supported – 0xFF - Not Available
cdmaSysIdValid	• Indicates whether the CDMA system ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
systemID	• System ID. – 0xFFFF - Not Available
networkID	• Network ID. – 0xFFFF - Not Available
bsInfoValid	• Indicates whether the base station information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
baseLat	• Base station latitude in units of 0.25 sec. • Expressed as a two's complement signed number with positive numbers signifying North latitudes. – 0xFFFFFFFF - Not Available
baseLong	• Base station longitude in units of 0.25 sec. • Expressed as a two's complement signed number with positive numbers signifying East latitudes. – 0xFFFFFFFF - Not Available
packetZoneValid	• Indicates whether the packet zone is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

packetZone	• Packet zone (8-bit). – 0xFFFF indicates no packet zone. • Only applicable for CDMA.

networkIdValid	• Indicates whether the network ID is valid.
	  – 0x00 - Invalid
	  – 0x01 - Valid
	  – 0xFF - Not Available

MCC[NAS_PLMN_LENGTH]	• Mobile Country Code. • MCC digits in ASCII characters • MCC wildcard value is returned as {'3', 0xFF, 0xFF}.
MNC[NAS_PLMN_LENGTH]	• Mobile Network Code. • MNC digits in ASCII characters • An unused byte is set to 0xFF. • MNC wildcard value is returned as {'7', 0xFF, 0xFF}.

8.437.2 Field Documentation

8.437.2.1 uint16_t nas_CDMASysInfo::baseId

8.437.2.2 uint32_t nas_CDMASysInfo::baseLat

8.437.2.3 uint32_t nas_CDMASysInfo::baseLong

8.437.2.4 uint8_t nas_CDMASysInfo::bsInfoValid

8.437.2.5 uint8_t nas_CDMASysInfo::bsPRev

8.437.2.6 uint8_t nas_CDMASysInfo::bsPRevValid

8.437.2.7 uint8_t nas_CDMASysInfo::ccsSupported

8.437.2.8 uint8_t nas_CDMASysInfo::ccsSupportedValid

8.437.2.9 uint8_t nas_CDMASysInfo::cdmaSysIdValid

8.437.2.10 uint8_t nas_CDMASysInfo::isSysPrlMatch

8.437.2.11 uint8_t nas_CDMASysInfo::isSysPrlMatchValid

8.437.2.12 uint8_t nas_CDMASysInfo::MCC[3]

8.437.2.13 uint8_t nas_CDMASysInfo::MNC[3]

8.437.2.14 uint16_t nas_CDMASysInfo::networkID

8.437.2.15 uint8_t nas_CDMASysInfo::networkIdValid

8.437.2.16 uint16_t nas_CDMASysInfo::packetZone

8.437.2.17 uint8_t nas_CDMASysInfo::packetZoneValid

8.437.2.18 uint8_t nas_CDMASysInfo::pRevInUse

8.437.2.19 uint8_t nas_CDMASysInfo::pRevInUseValid

8.437.2.20 nas_sysInfoCommon nas_CDMASysInfo::sysInfoCDMA

8.437.2.21 uint16_t nas_CDMASysInfo::systemID

8.438 nas_CDMASysInfoExt Struct Reference

Data Fields

- uint16_t MCC
- uint8_t imsi_11_12

8.438.1 Detailed Description

This structure contains CDMA system information extension

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

MCC	• Mobile Country Code
imsi_11_12	• IMSI_11_12

8.438.2 Field Documentation

8.438.2.1 uint8_t nas_CDMASysInfoExt::imsi_11_12

8.438.2.2 uint16_t nas_CDMASysInfoExt::MCC

8.439 nas_cellParams Struct Reference

Data Fields

- uint16_t pci
- int16_t rsrq
- int16_t rsrp
- int16_t rssi
- int16_t srxlev

8.439.1 Detailed Description

This structure contains information about the Cell parameters.

Parameters

pci	• Physical cell ID. • Range: 0 to 503.
rsrq	• Current RSRQ in 1/10 dB as measured by L1. • Range: -20.0 dB to -3.0 dB.
rsrp	• Current RSRP in 1/10 dBm as measured by L1. • Range: -140.0 dBm to -44.0 dBm.
rssi	• Current RSSI in 1/10 dBm as measured by L1. • Range: -120.0 dBm to 0.
srxlev	• Cell selection Rx level (Srxlev) value. • Range: -128 to 128. • This field is only valid when ue_in_idle is TRUE.

8.439.2 Field Documentation

8.439.2.1 uint16_t nas_cellParams::pci

8.439.2.2 int16_t nas_cellParams::rsrp

8.439.2.3 int16_t nas_cellParams::rsrq

8.439.2.4 int16_t nas_cellParams::rssi

8.439.2.5 int16_t nas_cellParams::srxlev

8.440 nas_ciotAcqOrderPref Struct Reference

Data Fields

- uint8_t ciotAcqOrderLen
- uint32_t * pCiotAcqOrder

8.440.1 Detailed Description

Contain the CIOT Acquisition Order Preference.

Parameters

ciotAcqOrderLen	• Number of sets of the following elements.
pCiotAcqOrder	• CIOT Acquisition order preference to be set. • Values – 0x01 - cdma2000 ®1X – 0x02 - cdma2000 ® HRPD (1xEV-DO) – 0x04 - GSM – 0x05 - UMTS – 0x08 - LTE – 0x09 - TD-SCDMA – 0x0a - LTE_M1 – 0x0b - LTE_NB1

8.440.2 Field Documentation

8.440.2.1 uint8_t nas_ciotAcqOrderPref::ciotAcqOrderLen

8.440.2.2 uint32_t∗ nas_ciotAcqOrderPref::pCiotAcqOrder

8.441 nas_CiotAcqOrderPrefTlv Struct Reference

Data Fields

- uint8_t ciotAcqOrderLen
- uint32_t ∗ pCiotAcqOrder
- uint8_t TlvPresent

8.441.1 Detailed Description

Contain the CIOT Acquisition Order Preference.

Parameters

ciotAcqOrderLen	• Number of sets of the following elements.
pCiotAcqOrder	• CIOT Acquisition order preference to be set. • Values – 0x01 - cdma2000 ®1X – 0x02 - cdma2000 ® HRPD (1xEV-DO) – 0x04 - GSM – 0x05 - UMTS – 0x08 - LTE – 0x09 - TD-SCDMA – 0x0a - LTE_M1 – 0x0b - LTE_NB1

TlvPresent	• Tlv Present

8.441.2 Field Documentation

8.441.2.1 uint8_t nas_CiotAcqOrderPrefTlv::ciotAcqOrderLen

8.441.2.2 uint32_t* nas_CiotAcqOrderPrefTlv::pCiotAcqOrder

8.441.2.3 uint8_t nas_CiotAcqOrderPrefTlv::TlvPresent

8.442 nas_CiotLteOpModePrefTlv Struct Reference

Data Fields

- uint64_t ciotLteOpModePref
- uint8_t TlvPresent

8.442.1 Detailed Description

Contain the CIOT LTE Operational Mode Preference.

Parameters

ciotLteOpMode-Pref	• CIOT LTE Operational Mode Preference • Values: – Bit 0 (0x01) - LTE wideband – Bit 1 (0x02) - LTE M1 – Bit 2 (0x04) - LTE NB1 All unlisted bits are reserved for future use and the service point ignores them if used.
TlvPresent	• Tlv Present

8.442.2 Field Documentation

8.442.2.1 uint64_t nas_CiotLteOpModePrefTlv::ciotLteOpModePref

8.442.2.2 uint8_t nas_CiotLteOpModePrefTlv::TlvPresent

8.443 nas_CommInfo Struct Reference

Data Fields

- int8_t temperature
- uint8_t modemMode
- uint8_t systemMode
- uint8_t imsRegState

- uint8_t psState

8.443.1 Detailed Description

Structure for storing the common information for the device.

Parameters

temperature	• Temperature. – 8-bit signed integer – 0xFF - Not Available.
modemMode	• Modem Operating Mode. – 0x00 - POWERING OFF – 0x01 - FACTORY TEST – 0x02 - OFFLINE – 0x03 - OFFLINE_AMPS – 0x04 - OFFLINE_CDMA – 0x05 - ONLINE – 0x06 - LOW POWER MODE – 0x07 - RESETTING – 0x08 - NETWORK TEST – 0x09 - OFFLINE REQUEST – 0x0A - PSEUDO ONLINE – 0x0B - RESETTING MODEM – 0xFF - Unknown
systemMode	• System Acquisition Mode. – 0x00 - No service – 0x01 - AMPS – 0x02 - CDMA – 0x03 - GSM – 0x04 - HDR – 0x05 - WCDMA – 0x06 - GPS – 0x08 - WLAN – 0x09 - LTE – 0xFF - Unknown
imsRegState	• IMS Registration State. – 0x00 - NO SRV – 0x01 - IN PROG – 0x02 - FAILED – 0x03 - LIMITED – 0x04 - FULL SRV – 0xFF - Unknown

psState	• PS Attach State. – 0x00 - Attached – 0x01 - Detached – 0xFF - Unknown

8.443.2 Field Documentation

8.443.2.1 uint8_t nas_CommInfo::imsRegState

8.443.2.2 uint8_t nas_CommInfo::modemMode

8.443.2.3 uint8_t nas_CommInfo::psState

8.443.2.4 uint8_t nas_CommInfo::systemMode

8.443.2.5 int8_t nas_CommInfo::temperature

8.444 nas_CsgId Struct Reference

Data Fields

- uint32_t csgId
- uint8_t TlvPresent

8.444.1 Detailed Description

This structure contains csg ID.

Parameters

csgId	• Closed subscriber group identifier.
TlvPresent	• Tlv Present or not

8.444.2 Field Documentation

8.444.2.1 uint32_t nas_CsgId::csgId

8.444.2.2 uint8_t nas_CsgId::TlvPresent

8.445 nas_CSGID Struct Reference

Data Fields

- uint16_t mcc
- uint16_t mnc

- uint8_t mncPcsDigits
- uint32_t id
- uint8_t rat

8.445.1 Detailed Description

Contain the CSGID.

Parameters

mcc	• MCC value. Range 0 to 999
mnc	• MNC value. Range 0 to 999
mncPcsDigits	• TRUE - MNC is a three-digit value; e.g., a reported value of 90 corresponds to an MNC value of 090 • FALSE - MNC is a two-digit value; e.g., a reported value of 90 corresponds to an MNC value of 90
id	• Closed subscriber group identifier.
rat	• Radio interface technology of the CSG network. Values: – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS – 0x08 - RADIO_IF_LTE - LTE – 0x09 - RADIO_IF_TDSCDMA - TDS

8.445.2 Field Documentation

8.445.2.1 uint32_t nas_CSGID::id

8.445.2.2 uint16_t nas_CSGID::mcc

8.445.2.3 uint16_t nas_CSGID::mnc

8.445.2.4 uint8_t nas_CSGID::mncPcsDigits

8.445.2.5 uint8_t nas_CSGID::rat

8.446 nas_currentPLMN Struct Reference

Data Fields

- uint16_t MCC
- uint16_t MNC
- uint8_t netDescrLength
- uint8_t netDescr [255]

8.446.1 Detailed Description

This structure contains the current PLMN parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

MCC	• mobile country code – A 16 bit representation of MCC – Range 0 to 999
MNC	• mobile network code – A 16 bit representation of MNC – Range 0 to 999
netDescrLength	• Length of Network description field • Defaults to zero
netDescr	• Network Description – optional string containing network name or description

8.446.2 Field Documentation

8.446.2.1 uint16_t nas_currentPLMN::MCC

8.446.2.2 uint16_t nas_currentPLMN::MNC

8.446.2.3 uint8_t nas_currentPLMN::netDescr[255]

8.446.2.4 uint8_t nas_currentPLMN::netDescrLength

8.447 nas_dataSrvCapabilities Struct Reference

Data Fields

- uint8_t dataCapabilitiesLen
- uint8_t dataCapabilities [32]

8.447.1 Detailed Description

This structure contains the data services capability

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

dataCapabilities-Len	• Length of data capabilities list • Defaults to zero
dataCapabilities	• List of data capabilities • Values: – 0x01 - GPRS – 0x02 - EDGE – 0x03 - HSDPA – 0x04 - HSUPA – 0x05 - WCDMA – 0x06 - CDMA – 0x07 - EV-DO Rev0 – 0x08 - EV-DO RevA – 0x09 - GSM – 0x0A - EV-DO Rev B – 0x0B - LTE – 0x0C - HSDPA+ – 0x0D - DC-HSDPA+

8.447.2 Field Documentation

8.447.2.1 uint8_t nas_dataSrvCapabilities::dataCapabilities[32]

8.447.2.2 uint8_t nas_dataSrvCapabilities::dataCapabilitiesLen

8.448 nas_DataStatusDetail Struct Reference

Data Fields

- uint32_t IPAddress
- uint8_t LastErrCode

8.448.1 Detailed Description

This structure contains data status detail

Parameters

IPAddress	• IP Address • 0xABCDEFGH - AB.CD.EF.GH • Example: – 0x12345678 - 18.52.86.120 0x12=18 0x34=52 0x56=86 0x78=120 • 0xFFFFFFFF - NA

LastErrCode	• MIP Error code – 0x00 - MIP_RRP_CODE_SUCCESS – 0x01 - MIP_RRP_CODE_SUCCESS_NO_SIM_BINDINGS – 0x40 - MIP_RRP_CODE_FAILURE_FA_REASON_UNSPECIFIED – 0x41 - MIP_RRP_CODE_FAILURE_FA_ADMIN_PROHIBITED – 0x42 - MIP_RRP_CODE_FAILURE_FA_INSUFFICIENT_RESOURCES – 0x43 - MIP_RRP_CODE_FAILURE_FA_MOBILE_NODE_FAILED_AUTH – 0x44 - MIP_RRP_CODE_FAILURE_FA_HA_FAILED_AUTH – 0x45 - MIP_RRP_CODE_FAILURE_FA_REQUESTED_LIFETIME_TOO_LONG – 0x46 - MIP_RRP_CODE_FAILURE_FA_MALFORMED_REQUEST – 0x47 - MIP_RRP_CODE_FAILURE_FA_MALFORMED_REPLY – 0x48 - MIP_RRP_CODE_FAILURE_FA_ENCAPSULATION_UNAVAILABLE – 0x49 - MIP_RRP_CODE_FAILURE_FA_VJHC_UNAVAILABLE – 0x4A - MIP_RRP_CODE_FAILURE_FA_CANT_REV_TUN – 0x4B - MIP_RRP_CODE_FAILURE_FA_MUST_REV_TUN – 0x4C - MIP_RRP_CODE_FAILURE_FA_BAD_TTL – 0x4D - MIP_RRP_CODE_FAILURE_INVALID_COA – 0x4F - MIP_RRP_CODE_FAILURE_FA_DELIVERY_STYLE_NOT_SUPPORTED – 0x59 - MIP_RRP_CODE_FAILURE_FA_VS_REASON – 0x61 - MIP_RRP_CODE_FAILURE_MISSING_NAI – 0x62 - MIP_RRP_CODE_FAILURE_MISSING_HA_ADDR – 0x63 - MIP_RRP_CODE_FAILURE_MISSING_HOMEADDR – 0x68 - MIP_RRP_CODE_FAILURE_UNKNOWN_CHALLENGE – 0x69 - MIP_RRP_CODE_FAILURE_MISSING_CHALLENGE – 0x6A - MIP_RRP_CODE_FAILURE_STALE_CHALLENGE – 0x6B - MIP_RRP_CODE_FAILURE_MISSING_MN_FA – 0x80 - MIP_RRP_CODE_FAILURE_HA_REASON_UNSPECIFIED – 0x81 - MIP_RRP_CODE_FAILURE_HA_ADMIN_PROHIBITED – 0x82 - MIP_RRP_CODE_FAILURE_HA_INSUFFICIENT_RESOURCES – 0x83 - MIP_RRP_CODE_FAILURE_HA_MOBILE_NODE_FAILED_AUTH – 0x84 - MIP_RRP_CODE_FAILURE_HA_FA_FAILED_AUTH – 0x85 - MIP_RRP_CODE_FAILURE_HA_REG_ID_MISMATCH – 0x86 - MIP_RRP_CODE_FAILURE_HA_MALFORMED_REQUEST – 0x88 - MIP_RRP_CODE_FAILURE_UNKNOWN_HA – 0x89 - MIP_RRP_CODE_FAILURE_HA_CANT_REV_TUN – 0x8A - MIP_RRP_CODE_FAILURE_HA_MUST_REV_TUN – 0x8B - MIP_RRP_CODE_FAILURE_HA_ENCAPSULATION_UNAVAILABLE – 0x8F - MIP_RRP_CODE_FAILURE_REDIRECTED_HA – 0x90 - MIP_RRP_CODE_FAILURE_HA_BAD_AAA_AUTH – 0xFF - NA

8.448.2 Field Documentation

8.448.2.1 uint32_t nas_DataStatusDetail::IPAddress

8.448.2.2 uint8_t nas_DataStatusDetail::LastErrCode

8.449 nas_detailSvcInfo Struct Reference

Data Fields

- uint8_t srvStatus
- uint8_t srvCapability
- uint8_t hdrSrvStatus
- uint8_t hdrHybrid
- uint8_t isSysForbidden

8.449.1 Detailed Description

This structure contains Detailed Service information

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

srvStatus	• Service status • Values: – 0x00 - No service – 0x01 - Limited service – 0x02 - Service available – 0x03 - Limited regional service – 0x04 - MS in power save or deep sleep
srvCapability	• System's service capability • Values: – 0x00 - No Service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - MS found the right system but not yet registered/attached
hdrSrvStatus	• HDR service status • Values: – 0x00 - No service – 0x01 - Limited service – 0x02 - Service available – 0x03 - Limited regional service – 0x04 - MS in power save or deep sleep
hdrHybrid	• HDR hybrid information • Values: – 0x00 - System is not hybrid – 0x01 - System is hybrid

isSysForbidden	• Forbidden system information • Values: – 0x00 - System is not a forbidden system – 0x01 - System is a forbidden system

8.449.2 Field Documentation

8.449.2.1 uint8_t nas_detailSvcInfo::hdrHybrid

8.449.2.2 uint8_t nas_detailSvcInfo::hdrSrvStatus

8.449.2.3 uint8_t nas_detailSvcInfo::isSysForbidden

8.449.2.4 uint8_t nas_detailSvcInfo::srvCapability

8.449.2.5 uint8_t nas_detailSvcInfo::srvStatus

8.450 nas_DeviceConfigDetail Struct Reference

Data Fields

- uint8_t Technology
- uint8_t QLIC
- uint8_t Chipset
- uint8_t HWVersion

8.450.1 Detailed Description

This structure contains device configure detail.

Parameters

Technology	• Current technology in use – 0x00 - 1x RTT – 0x01 - EVDO Rev 0 – 0x02 - EVDO Rev A – 0xFF - NA
QLIC	• Quasi Linear Interference Cancellation – 0x00 - Not supported – 0x01 - Supported
Chipset	• Qualcomm platform – 0x4E - MDM6200 – 0x4F - MDM6600 – 0xFF - NA

HWVersion	• Hardware version – 0x00 - BSHWREV0 – 0x01 - BSHWREV1 – 0x02 - BSHWREV2 – 0x03 - BSHWREV3 – 0x04 - BSHWREVMAX – 0xFF - BSHWREVUNKNOWN

8.450.2 Field Documentation

8.450.2.1 uint8_t nas_DeviceConfigDetail::Chipset

8.450.2.2 uint8_t nas_DeviceConfigDetail::HWVersion

8.450.2.3 uint8_t nas_DeviceConfigDetail::QLIC

8.450.2.4 uint8_t nas_DeviceConfigDetail::Technology

8.451 nas_dirNum Struct Reference

Data Fields

- uint8_t dirNumLen
- uint8_t dirNum [255]

8.451.1 Detailed Description

This structure contains the parameters for Directory Number Information

Parameters

dirNumLen	• Number of sets of the following elements: – dir_num • If zero(0), then no information follows.
dirNum	• Directory number in ASCII characters.

8.451.2 Field Documentation

8.451.2.1 uint8_t nas_dirNum::dirNum[255]

8.451.2.2 uint8_t nas_dirNum::dirNumLen

8.452 nas_DRCParams Struct Reference

Data Fields

- uint8_t DRCValue
- uint8_t DRCCover

8.452.1 Detailed Description

This structure contains DRC information.

Parameters

DRCValue	• Current Data Rate Channel
DRCCover	• Current Data Rate Channel cover

8.452.2 Field Documentation

8.452.2.1 uint8_t nas_DRCParams::DRCCover

8.452.2.2 uint8_t nas_DRCParams::DRCValue

8.453 nas_ecioListElement Struct Reference

Data Fields

- int16_t ecio
- uint8_t radioIf

8.453.1 Detailed Description

This structure contains the ECIO Information

Parameters

ecio	• ECIO value in dBm
radioIf	• Radio interface technology of the signal being measured – 0x00 - RADIO_IF_NO_SVC - None (no service) – 0x01 - RADIO_IF_CDMA_1X - cdma2000® 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS

8.453.2 Field Documentation

8.453.2.1 int16_t nas_ecioListElement::ecio

8.453.2.2 uint8_t nas_ecioListElement::radioIf

8.454 nas_ECIOThresh Struct Reference

Data Fields

- uint8_t ECIOThresListLen
- int16_t * pECIOThresList

8.454.1 Detailed Description

This sturcture contain ECIO threshold list.

Parameters

ECIOThresList-Len	• Length of the ECIO threshold list parameter to follow
pECIOThresList	• Sequence of thresholds delimiting ECIO event reporting bands • Every time a new ECIO value crosses a threshold value, an event report indication message with the new ECIO value is sent to the requesting control point. For this field – Each ECIO threshold value is a signed 2 byte value – Each ECIO threshold value increments in negative 0.5 dB, e.g., an ECIO threshold value of 2 means -1dB – Maximum number of threshold values is 16 – At least one value must be specified – Threshold values specified above are used for all RATs

8.454.2 Field Documentation

8.454.2.1 uint8_t nas_ECIOThresh::ECIOThresListLen

8.454.2.2 int16_t* nas_ECIOThresh::pECIOThresList

8.455 nas_EdrxCiotLteMode Struct Reference

Data Fields

- uint32_t IteOpMode
- uint8_t TlvPresent

8.455.1 Detailed Description

This structure contains the parameters for LTE Operational Mode Indicator Type.

Parameters

lteOpMode	• CIOT LTE mode. • Values – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_NB1 (0x03) - Camped on LTE NB1
TlvPresent	• Tlv Present.

8.455.2 Field Documentation

8.455.2.1 uint32_t nas_EdrxCiotLteMode::lteOpMode

8.455.2.2 uint8_t nas_EdrxCiotLteMode::TlvPresent

8.456 nas_EdrxCycleLength Struct Reference

Data Fields

- uint8_t cycleLength
- uint8_t TlvPresent

8.456.1 Detailed Description

This structure contains the parameters for eDRX Cycle Length Indicator Type.

Parameters

cycleLength	• eDRX cycle length. Value is per 3GPP TS 24.008 Rel-13 Section 10.5.5.32.
TlvPresent	• Tlv Present.

8.456.2 Field Documentation

8.456.2.1 uint8_t nas_EdrxCycleLength::cycleLength

8.456.2.2 uint8_t nas_EdrxCycleLength::TlvPresent

8.457 nas_EdrxEnableType Struct Reference

Data Fields

- uint8_t edrxEnabled
- uint8_t TlvPresent

8.457.1 Detailed Description

This structure contains the parameters for eDRX Enabled Indicator Type.

Parameters

edrxEnabled	• Values – 0x00 - Disabled – 0x01 - Enabled
TlvPresent	• Tlv Present.

8.457.2 Field Documentation

8.457.2.1 uint8_t nas_EdrxEnableType::edrxEnabled

8.457.2.2 uint8_t nas_EdrxEnableType::TlvPresent

8.458 nas_EdrxPagingTimeWindow Struct Reference

Data Fields

- uint8_t edrxPtw
- uint8_t TlvPresent

8.458.1 Detailed Description

This structure contains the parameters for eDRX Paging Time Window Indicator Type.

Parameters

edrxPtw	• eDRX paging time window. Value is per 3GPP TS 24.008 Rel-13 Section 10.5.5.32
TlvPresent	• Tlv Present.

8.458.2 Field Documentation

8.458.2.1 uint8_t nas_EdrxPagingTimeWindow::edrxPtw

8.458.2.2 uint8_t nas_EdrxPagingTimeWindow::TlvPresent

8.459 nas_EdrxRatType Struct Reference

Data Fields

- uint8_t edrxRatType
- uint8_t TlvPresent

8.459.1 Detailed Description

This structure contains the parameters for eDRX RAT type Indicator Type.

Parameters

edrxRatType	• Radio access technology • Values – NAS_RADIO_IF_NO_SVC (0x00) - None (no service) – NAS_RADIO_IF_CDMA_1X (0x01) - cdma2000 ® 1X – NAS_RADIO_IF_CDMA_1XEVDO (0x02) - cdma2000 ® HRPD (1xEV-DO) – NAS_RADIO_IF_AMPS (0x03) - AMPS – NAS_RADIO_IF_GSM (0x04) - GSM – NAS_RADIO_IF_UMTS (0x05) - UMTS – NAS_RADIO_IF_WLAN (0x06) - WLAN – NAS_RADIO_IF_GPS (0x07) - GPS – NAS_RADIO_IF_LTE (0x08) - LTE – NAS_RADIO_IF_TDSCDMA (0x09) - TD-SCDMA – NAS_RADIO_IF_LTE_M1 (0x0a) - LTE-M1 – NAS_RADIO_IF_LTE_NB1 (0x0b) - LTE-NB1 – NAS_RADIO_IF_NO_CHANGE (-1) - No change
TlvPresent	• Tlv Present.

8.459.2 Field Documentation

8.459.2.1 uint8_t nas_EdrxRatType::edrxRatType

8.459.2.2 uint8_t nas_EdrxRatType::TlvPresent

8.460 nas_EmerModeTlv Struct Reference

Data Fields

- uint8_t EmerMode
- uint8_t TlvPresent

8.460.1 Detailed Description

Contain the emergency Mode parameters for system selection preferences.

Parameters

EmerMode	• Emergency Mode • Values: – 0 - OFF (normal) – 1 - ON (Emergency)

TlvPresent	• Tlv Present

8.460.2 Field Documentation

8.460.2.1 uint8_t nas_EmerModeTlv::EmerMode

8.460.2.2 uint8_t nas_EmerModeTlv::TlvPresent

8.461 nas_errorRateListElement Struct Reference

Data Fields

- uint16_t errorRate
- uint8_t radioIf

8.461.1 Detailed Description

This structure contains the Error Rate Information

Parameters

errorRate	• Error rate value corresponds to the RAT that is currently registered. – For CDMA, the error rate reported is Frame Error Rate: * Valid error rate values between 1 and 10000 are returned to indicate percentage, e.g., a value of 300 means the error rate is 3% * A value of 0xFFFF indicates that the error rate is unknown or unavailable – For HDR, the error rate reported is Packet Error Rate: * Valid error rate values between 1 and 10000 are returned to indicate percentage, e.g., a value of 300 means the error rate is 3% * A value of 0xFFFF indicates that the error rate is unknown or unavailable – For GSM, the error rate reported is Bit Error Rate: * Valid values are 0, 100, 200, 300, 400, 500, 600, and 700 The reported value divided by 100 gives the error rate as an RxQual value, e.g.,a value of 300 represents an RxQual value of 3. * A value of 25500 indicates No Data – For WCDMA, the error rate reported is Block Error Rate (BLER): * Valid values are 1 to 10000 * The reported value divided by 100 provides the error rate in percentages, e.g., a value of 300 represents a BLER of 3%. * A value of 0 indicates No Data

radioIf	• Radio interface technology of the signal being measured – 0x00 - RADIO_IF_NO_SVC - None (no service) – 0x01 - RADIO_IF_CDMA_1X - cdma2000® 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS

8.461.2 Field Documentation

8.461.2.1 uint16_t nas_errorRateListElement::errorRate

8.461.2.2 uint8_t nas_errorRateListElement::radioIf

8.462 nas_ForbiddenNetworks3GPP Struct Reference

Data Fields

- uint16_t forbiddenNwInstLen
- uint16_t MCC [255]
- uint16_t MNC [255]
- uint8_t TlvPresent

8.462.1 Detailed Description

This structure contains the ForbiddenNetworks3GPP response parameters.

Parameters

forbiddenNwInst-Len	• Number of sets of the following elements – MCC – MNC
MCC	• Mobile Country Code • A 16-bit integer representation of MCC • Range: 0 to 999
MNC	• Mobile Network Code • A 16-bit integer representation of MNC • Range: 0 to 999
TlvPresent	• Tlv Present

8.462.2 Field Documentation

8.462.2.1 uint16_t nas_ForbiddenNetworks3GPP::forbiddenNwInstLen

8.462.2.2 uint16_t nas_ForbiddenNetworks3GPP::MCC[255]

8.462.2.3 uint16_t nas_ForbiddenNetworks3GPP::MNC[255]

8.462.2.4 uint8_t nas_ForbiddenNetworks3GPP::TlvPresent

8.463 nas_GERANInfo Struct Reference

Data Fields

- uint32_t cellID
- uint8_t plmn [3]
- uint16_t lac
- uint16_t arfcn
- uint8_t bsic
- uint32_t timingAdvance
- uint16_t rxLev
- uint8_t nmrInst
- nas_nmrCellInfo insNmrCellInfo [255]

8.463.1 Detailed Description

This structure contains information about the GERAN Network.

Parameters

cellID	• Cell ID. • 0xFFFFFFFF indicates cell ID information is not present.
plmn[NAS_PLMN_LENGTH]	• MCC/MNC information coded as octet 3, 4, and 5. • This field is ignored when nmrCellID is not present.
lac	• Location area code. • This field is ignored when nmrCellID is not present. – 0xFFFF - Not Available
arfcn	• Absolute RF channel number. – 0xFFFF - Not Available
bsic	• Base station identity code. – 0xFF - Not Available

timingAdvance	• Measured delay (in bit periods; 1 bit period = 48/13 microsecond) of access burst transmission on RACH or PRACH to the expected signal from an MS at zero distance under static channel conditions. – 0xFFFFFFFF - Not Available
rxLev	• Serving Cell Rx measurement. • Values range between 0 and 63. • Mapped to a measured signal level: – Rxlev 0 is a signal strength less than -110 dBm – Rxlev 1 is -110 dBm to -109 dBm – Rxlev 2 is -109 dBm to -108 dBm – ... – Rxlev 62 is -49 dBm to -48 dBm – Rxlev 63 is greater than -48 dBm – 0xFFFF - Not Available
nmrInst	• Provides the number of set of instances which follow. • If 0(zero), then no information follows it.
insNmrCellInfo[NAS_MAX_DESCRIPTION_LENGTH]	• See nas_nmrCellInfo for more information.

8.463.2 Field Documentation

8.463.2.1 uint16_t nas_GERANInfo::arfcn

8.463.2.2 uint8_t nas_GERANInfo::bsic

8.463.2.3 uint32_t nas_GERANInfo::cellID

8.463.2.4 nas_nmrCellInfo nas_GERANInfo::insNmrCellInfo[255]

8.463.2.5 uint16_t nas_GERANInfo::lac

8.463.2.6 uint8_t nas_GERANInfo::nmrInst

8.463.2.7 uint8_t nas_GERANInfo::plmn[3]

8.463.2.8 uint16_t nas_GERANInfo::rxLev

8.463.2.9 uint32_t nas_GERANInfo::timingAdvance

8.464 nas_geranInstInfo Struct Reference

Data Fields

- uint16_t geranArfcn

- uint8_t geranBsicNcc
- uint8_t geranBsicBcc
- int16_t geranRssi

8.464.1 Detailed Description

This structure contains information about the GERAN Instances in UMTS Network.

Parameters

geranArfcn	• Absolute RF channel number.
geranBsicNcc	• Base station identity code network color code. • 0xFF indicates information is not present.
geranBsicBcc	• Base station identity code base station color code. • 0xFF indicates information is not present.
geranRssi	• Received signal strength indicator.

8.464.2 Field Documentation

8.464.2.1 uint16_t nas_geranInstInfo::geranArfcn

8.464.2.2 uint8_t nas_geranInstInfo::geranBsicBcc

8.464.2.3 uint8_t nas_geranInstInfo::geranBsicNcc

8.464.2.4 int16_t nas_geranInstInfo::geranRssi

8.465 nas_gsmCellInfo Struct Reference

Data Fields

- uint16_t arfcn
- uint8_t band1900
- uint8_t cellIdValid
- uint8_t bsicId
- int16_t rssi
- int16_t srxlev

8.465.1 Detailed Description

This structure contains information about the GSM Cell.

Parameters

arfcn	• GSM frequency being reported. • Range: 0 to 1023.
band1900	• Band indicator for the GSM ARFCN • This field is only valid if arfcn is in the overlapping region. • If TRUE and the cell is in the overlapping region, the ARFCN is on the 1900 band. • If FALSE, it is on the 1800 band.
cellIdValid	• Flag indicating whether the base station identity code ID is valid.
bsicId	• Base station identity code ID, including base station color code and network color code. • The lower 6 bits can be set to any value.
rssi	• Measured RSSI value in 1/10 dB. • Range: -200.0 dB to 0
srxlev	• Cell selection Rx level (Srxlev) value. • Range: -128 to 128. • This field is only valid when ue_in_idle is TRUE.

8.465.2 Field Documentation

8.465.2.1 uint16_t nas_gsmCellInfo::arfcn

8.465.2.2 uint8_t nas_gsmCellInfo::band1900

8.465.2.3 uint8_t nas_gsmCellInfo::bsicId

8.465.2.4 uint8_t nas_gsmCellInfo::cellIdValid

8.465.2.5 int16_t nas_gsmCellInfo::rssi

8.465.2.6 int16_t nas_gsmCellInfo::srxlev

8.466 nas_GSMRSSIThresh Struct Reference

Data Fields

- uint8_t GSMRSSIThreshListLen
- int16_t * pGSMRSSIThreshList

8.466.1 Detailed Description

This structure contains GSM RSSI threshold related parameters.

Parameters

GSMRSSI-ThreshListLen	• Length of the GSM RSSI threshold list parameter to follow
pGSMRSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • Maximum of 32 values • Range for RSSI values: -111 to -48 (in dBm)

8.466.2 Field Documentation

8.466.2.1 uint8_t nas_GSMRSSIThresh::GSMRSSIThreshListLen

8.466.2.2 int16_t* nas_GSMRSSIThresh::pGSMRSSIThreshList

8.467 nas_GSMSrvStatusInfo Struct Reference

Data Fields

- uint8_t srvStatus
- uint8_t trueSrvStatus
- uint8_t isPrefDataPath

8.467.1 Detailed Description

Structure for storing the service status information for GSM, WCDMA and LTE networks.

Parameters

srvStatus	• Service status of the system. – 0x00 - No service – 0x01 - Limited service – 0x02 - Service – 0x03 - Limited regional service – 0x04 - Power save – 0xFF - Not Available
trueSrvStatus	• True service status of the system. • Not applicable to CDMA/HDR. – 0x00 - No service – 0x01 - Limited service – 0x02 - Service – 0x03 - Limited regional service – 0x04 - Power save – 0xFF - Not Available

isPrefDataPath	• Whether the RAT is the preferred data path. – 0x00 - Not preferred – 0x01 - Preferred – 0xFF - Not Available

8.467.2 Field Documentation

8.467.2.1 uint8_t nas_GSMSrvStatusInfo::isPrefDataPath

8.467.2.2 uint8_t nas_GSMSrvStatusInfo::srvStatus

8.467.2.3 uint8_t nas_GSMSrvStatusInfo::trueSrvStatus

8.468 nas_GSMSysInfo Struct Reference

Data Fields

- nas_sysInfoCommon sysInfoGSM
- uint8_t lacValid
- uint16_t lac
- uint8_t cellIdValid
- uint32_t cellId
- uint8_t regRejectInfoValid
- uint8_t rejectSrvDomain
- uint8_t rejCause
- uint8_t networkIdValid
- uint8_t MCC [3]
- uint8_t MNC [3]
- uint8_t egprsSuppValid
- uint8_t egprsSupp
- uint8_t dtmSuppValid
- uint8_t dtmSupp

8.468.1 Detailed Description

Structure for storing the GSM System Information.

Parameters

sysInfoGSM	• See nas_sysInfoCommon for more information.
lacValid	• Indicates whether the location area code is valid.. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

lac	• Location area code. • Only applies to 3GPP. – 0xFFFF - Not Available
cellIdValid	• Indicates whether the cell ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
cellId	• Cell ID. – 0xFFFFFFFF - Not Available
regRejectInfo-Valid	• Indicates whether the registration reject information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
rejectSrvDomain	• Type of service domain in which the registration is rejected. – 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available
rejCause	• Reject cause values sent are specified in [3GPP TS 24.008, Section 10.5.3.6 and 10.5.5.14] – 0xFF - Not Available
networkIdValid	• Indicates whether the network ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
MCC[NAS_PLM-N_LENGTH]	• Mobile Country Code. • MCC digits in ASCII characters
MNC[NAS_PLM-N_LENGTH]	• Mobile Network Code. • MNC digits in ASCII characters • An unused byte is set to 0xFF. • In case of two-digit MNC values, the third (unused) digit is set to 0xFF. For example, 15 (a two-digit MNC) is reported using the byte stream 0x31 0x35 0xFF.

egprsSuppValid	• Indicates whether the EGPRS support is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
egprsSupp	• EGPRS support indication. • Only applicable for GSM. – 0x00 - Not available – 0x01 - Available – 0xFF - Not Available
dtmSuppValid	• Indicates whether Dual Transfer mode support is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
dtmSupp	• Dual Transfer mode support indication. • Only applicable for GSM. – 0x00 - Not available – 0x01 - Available – 0xFF - Not Available

8.468.2 Field Documentation

8.468.2.1 uint32_t nas_GSMSysInfo::cellId

8.468.2.2 uint8_t nas_GSMSysInfo::cellIdValid

8.468.2.3 uint8_t nas_GSMSysInfo::dtmSupp

8.468.2.4 uint8_t nas_GSMSysInfo::dtmSuppValid

8.468.2.5 uint8_t nas_GSMSysInfo::egprsSupp

8.468.2.6 uint8_t nas_GSMSysInfo::egprsSuppValid

8.468.2.7 uint16_t nas_GSMSysInfo::lac

8.468.2.8 uint8_t nas_GSMSysInfo::lacValid

8.468.2.9 uint8_t nas_GSMSysInfo::MCC[3]

8.468.2.10 uint8_t nas_GSMSysInfo::MNC[3]

8.468.2.11 uint8_t nas_GSMSysInfo::networkIdValid

8.468.2.12 uint8_t nas_GSMSysInfo::regRejectInfoValid

8.468.2.13 uint8_t nas_GSMSysInfo::rejCause

8.468.2.14 uint8_t nas_GSMSysInfo::rejectSrvDomain

8.468.2.15 nas_sysInfoCommon nas_GSMSysInfo::sysInfoGSM

8.469 nas_GWAcqOrderPrefTlv Struct Reference

Data Fields

- uint32_t GWAcqOrderPref
- uint8_t TlvPresent

8.469.1 Detailed Description

Contain the GSM/WCDMA Acquisition order preference for system selection preferences.

Parameters

GWAcqOrder-Pref	• Parameter indicating GSM/WCDMA Acquisition order Preference • Values: – 0x00 - Automatic – 0x01 - GSM then WCDMA – 0x02 - WCDMA then GSM
TlvPresent	• Tlv Present

8.469.2 Field Documentation

8.469.2.1 uint32_t nas_GWAcqOrderPrefTlv::GWAcqOrderPref

8.469.2.2 uint8_t nas_GWAcqOrderPrefTlv::TlvPresent

8.470 nas_HDRECIOThresh Struct Reference

Data Fields

- uint8_t HDRECIOThreshListLen
- int16_t * pHDRECIOThreshList

8.470.1 Detailed Description

This structure contains HDR ECIO threshold related parameters.

Parameters

HDRECIO-ThreshListLen	• Length of the HDR ECIO threshold list parameter to follow

pHDRECIO-ThreshList	• Array of ECIO thresholds (in units of 0.1 dB) • Maximum of 32 values • Range for ECIO values: -31.5 to 0 (in dB).

8.470.2 Field Documentation

8.470.2.1 uint8_t nas_HDRECIOThresh::HDRECIOThreshListLen

8.470.2.2 int16_t* nas_HDRECIOThresh::pHDRECIOThreshList

8.471 nas_HDRIOThresh Struct Reference

Data Fields

- uint8_t HDRIOThreshListLen
- int16_t * pHDRIOThreshList

8.471.1 Detailed Description

This structure contains HDR IO threshold related parameters.

Parameters

HDRIOThresh-ListLen	• Length of the HDR IO threshold list parameter to follow
pHDRIOThresh-List	• Array of IO thresholds (in units of 0.1 dBm) • Maximum of 32 values • Range for IO values: -128 to -13 (in dBm).

8.471.2 Field Documentation

8.471.2.1 uint8_t nas_HDRIOThresh::HDRIOThreshListLen

8.471.2.2 int16_t* nas_HDRIOThresh::pHDRIOThreshList

8.472 nas_HDRPersonality_Ind_Data Struct Reference

Data Fields

- uint16_t * pCurrentPersonality
- uint8_t * pPersonalityListLength
- nas_protocolSubtypeElement * pProtocolSubtypeElement

8.472.1 Detailed Description

Elements for HDR Personality indication.

Parameters

pCurrent-Personality	• Current active personality index. • Bit to check in ParamPresenceMask - **16**
pPersonalityList-Length	• Number of Personality Protocol Subtype contains in this response. • Bit to check in ParamPresenceMask - **17**
pProtocol-SubtypeElement	• See nas_protocolSubtypeElement for more information. • Bit to check in ParamPresenceMask - **17**

8.472.2 Field Documentation

8.472.2.1 uint16_t∗ nas_HDRPersonality_Ind_Data::pCurrentPersonality

8.472.2.2 uint8_t∗ nas_HDRPersonality_Ind_Data::pPersonalityListLength

8.472.2.3 nas_protocolSubtypeElement∗ nas_HDRPersonality_Ind_Data::pProtocolSubtypeElement

8.473 nas_HDRRSSIThresh Struct Reference

Data Fields

- uint8_t HDRRSSIThreshListLen
- int16_t ∗ pHDRRSSIThreshList

8.473.1 Detailed Description

This structure contains HDR RSSI threshold related parameters.

Parameters

HDRRSSI-ThreshListLen	• Length of the HDR RSSI threshold list parameter to follow
pHDRRSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • Maximum of 32 values. • Range for RSSI values: -118 to -13 (in dBm).

8.473.2 Field Documentation

8.473.2.1 uint8_t nas_HDRRSSIThresh::HDRRSSIThreshListLen

8.473.2.2 int16_t∗ nas_HDRRSSIThresh::pHDRRSSIThreshList

8.474 nas_HDRSINRThresh Struct Reference

Data Fields

- uint8_t HDRSINRThresListLen
- uint8_t ∗ pHDRSINRThresList

8.474.1 Detailed Description

This structure contains HDR SINR threshold list.

Parameters

HDRSINRThres-ListLen	• Length of the HDR SINR threshold list parameter to follow
pHDRSINR-ThresList	• Sequence of thresholds delimiting SINR event reporting bands • Every time a new SINR value crosses a threshold value, an event report indication message with the new SINR value is sent to the requesting control point. For this field – SINR is reported only for HDR – Each SINR threshold value is an unsigned 1 byte value – Maximum number of threshold values is 16 – At least one value must be specified

8.474.2 Field Documentation

8.474.2.1 uint8_t nas_HDRSINRThresh::HDRSINRThresListLen

8.474.2.2 uint8_t∗ nas_HDRSINRThresh::pHDRSINRThresList

8.475 nas_HDRSINRThreshold Struct Reference

Data Fields

- uint8_t HDRSINRThreshListLen
- uint16_t ∗ pHDRSINRThreshList

8.475.1 Detailed Description

This structure contains HDR SINR threshold related parameters.

Parameters

HDRSINR-ThreshListLen	• Length of the HDR ECIO threshold list parameter to follow

pHDRSINR-ThreshList	• Array of SINR level thresholds (in units of 1) • maximum of 32 values. • Valid levels are 0 to 8 – 0x00 - SINR_LEVEL_0 is -9 dB – 0x01 - SINR_LEVEL_1 is -6 dB – 0x02 - SINR_LEVEL_2 is -4.5 dB – 0x03 - SINR_LEVEL_3 is -3 dB – 0x04 - SINR_LEVEL_4 is -2 dB – 0x05 - SINR_LEVEL_5 is +1 dB – 0x06 - SINR_LEVEL_6 is +3 dB – 0x07 - SINR_LEVEL_7 is +6 dB – 0x08 - SINR_LEVEL_8 is +9 dB

8.475.2 Field Documentation

8.475.2.1 uint8_t nas_HDRSINRThreshold::HDRSINRThreshListLen

8.475.2.2 uint16_t* nas_HDRSINRThreshold::pHDRSINRThreshList

8.476 nas_HDRSysInfo Struct Reference

Data Fields

- nas_sysInfoCommon sysInfoHDR
- uint8_t isSysPrlMatchValid
- uint8_t isSysPrlMatch
- uint8_t hdrPersonalityValid
- uint8_t hdrPersonality
- uint8_t hdrActiveProtValid
- uint8_t hdrActiveProt
- uint8_t is856SysIdValid
- uint8_t is856SysId [16]

8.476.1 Detailed Description

Structure for storing the HDR System Information.

Parameters

sysInfoHDR	• See nas_sysInfoCommon for more information.
isSysPrlMatch-Valid	• Indicates whether the system PRL match is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

isSysPrlMatch	• Indicates whether the system is in a PRL. • Only applies to CDMA/HDR. – 0x00 - System is not in a PRL – 0x01 - System is in a PRL – 0xFF - Not Available • If the system is not in a PRL, roam_status carries the value from the default roaming indicator in the PRL. • If the system is in a PRL, roam_status is set to the value based on the standard specification.
hdrPersonality-Valid	• Indicates whether the HDR personality is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
hdrPersonality	• HDR personality information. • Only applicable for HDR. – 0x00 - None – 0x02 - HRPD – 0x03 - eHRPD – 0xFF - Not Available
hdrActiveProt-Valid	• Indicates whether the HDR active protocol revision information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
hdrActiveProt	• HDR active protocol revision information . • Only applicable for HDR. – 0x00 - None – 0x02 - HDR Rel 0 – 0x03 - HDR Rel A – 0x04 - HDR Rel B – 0xFF - Not Available
is856SysIdValid	• Indicates whether the IS-856 system ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
is856SysId[SLQ-S_SYSTEM_ID-_SIZE]	• IS-856 system ID. • Only applicable for HDR.

8.476.2 Field Documentation

8.476.2.1 uint8_t nas_HDRSysInfo::hdrActiveProt

8.476.2.2 uint8_t nas_HDRSysInfo::hdrActiveProtValid

8.476.2.3 uint8_t nas_HDRSysInfo::hdrPersonality

8.476.2.4 uint8_t nas_HDRSysInfo::hdrPersonalityValid

8.476.2.5 uint8_t nas_HDRSysInfo::is856SysId[16]

8.476.2.6 uint8_t nas_HDRSysInfo::is856SysIdValid

8.476.2.7 uint8_t nas_HDRSysInfo::isSysPrlMatch

8.476.2.8 uint8_t nas_HDRSysInfo::isSysPrlMatchValid

8.476.2.9 nas_sysInfoCommon nas_HDRSysInfo::sysInfoHDR

8.477 nas_homeSIDNID Struct Reference

Data Fields

- uint8_t numInstances
- nas_sidNid SidNid [255]

8.477.1 Detailed Description

This structure contains Home SID/NID

Parameters

numInstances	• Number of sets of the following elements: – sid – nid • If zero(0), then no information follows.
SidNid	• See nas_sidNid for more information

8.477.2 Field Documentation

8.477.2.1 uint8_t nas_homeSIDNID::numInstances

8.477.2.2 nas_sidNid nas_homeSIDNID::SidNid[255]

8.478 nas_infoInterFreq Struct Reference

Data Fields

- uint16_t earfcn
- uint8_t threshXLow
- uint8_t threshXHigh
- uint8_t cell_resel_priority
- uint8_t cells_len
- nas_cellParams cellInterFreqParams [255]

8.478.1 Detailed Description

This structure contains information about the inter-frequency.

Parameters

earfcn	• E-UTRA absolute radio frequency channel number of the serving cell. • Range: 0 to 65535.
threshXLow	• Cell Srxlev low threshold. • Range: 0 to 31. • When the serving cell does not exceed thresh_serving_low, the value of an evaluated cell must be smaller than this value to be considered for re-selection.
threshXHigh	• Cell Srxlev high threshold. • Range: 0 to 31. • When the serving cell exceeds thresh_serving_low, the value of an evaluated cell must be greater than this value to be considered for re-selection.
cell_resel_priority	• Cell re-selection priority • Range: 0 to 7. • This field is only valid when ue_in_idle is TRUE.
cells_len	• Provides the number of set of cell params.
cellInterFreqParams[NAS_MAX_DESCRIPTION_LENGTH]	• See nas_cellParams for more information.

8.478.2 Field Documentation

8.478.2.1 uint8_t nas_infoInterFreq::cell_resel_priority

8.478.2.2 nas_cellParams nas_infoInterFreq::cellInterFreqParams[255]

8.478.2.3 uint8_t nas_infoInterFreq::cells_len

8.478.2.4 uint16_t nas_infoInterFreq::earfcn

8.478.2.5 uint8_t nas_infoInterFreq::threshXHigh

8.478.2.6 uint8_t nas_infoInterFreq::threshXLow

8.479 nas_IOThresh Struct Reference

Data Fields

- uint8_t IOThresListLen
- int32_t * pIOThresList

8.479.1 Detailed Description

This structure contains IO threshold list.

Parameters

IOThresListLen	• Length of the IO threshold list parameter to follow
pIOThresList	• Sequence of thresholds delimiting IO event reporting bands • Every time a new IO value crosses a threshold value, an event report indication message with the new IO value is sent to the requesting control point. For this field – IO is applicable only for HDR – Each IO threshold value is a signed 4 byte value – Maximum number of threshold values is 16 – At least one value must be specified

8.479.2 Field Documentation

8.479.2.1 uint8_t nas_IOThresh::IOThresListLen

8.479.2.2 int32_t* nas_IOThresh::pIOThresList

8.480 nas_IteBandPrefExt Struct Reference

Data Fields

- uint64_t bits_1_64
- uint64_t bits_65_128
- uint64_t bits_129_192
- uint64_t bits_193_256

8.480.1 Detailed Description

Contain the LTE Band Preference Extended parameters

Parameters

bits_1_64	• Bits 1 to 64 of the 256-bit LTE E-UTRA Operating Band bitmask.
bits_65_128	• Bits 65 to 128 of the 256-bit LTE E-UTRA Operating Band bitmask.
bits_129_192	• Bits 129 to 192 of the 256-bit LTE E-UTRA Operating Band bitmask.
bits_193_256	• Bits 193 to 256 of the 256-bit LTE E-UTRA Operating Band bitmask.

8.480.2 Field Documentation

8.480.2.1 uint64_t nas_lteBandPrefExt::bits_129_192

8.480.2.2 uint64_t nas_lteBandPrefExt::bits_193_256

8.480.2.3 uint64_t nas_lteBandPrefExt::bits_1_64

8.480.2.4 uint64_t nas_lteBandPrefExt::bits_65_128

8.481 nas_LTEBandPrefTlv Struct Reference

Data Fields

- uint64_t LTEBandPref
- uint8_t TlvPresent

8.481.1 Detailed Description

Contain the LTE Band Preference for system selection preferences.

Parameters

LTEBandPref	• Bit mask representing the LTE band preference • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – All other bits are reserved
TlvPresent	• Tlv Present

8.481.2 Field Documentation

8.481.2.1 uint64_t nas_LTEBandPrefTlv::LTEBandPref

8.481.2.2 uint8_t nas_LTEBandPrefTlv::TlvPresent

8.482 nas_LteCiotOpModeTlv Struct Reference

Data Fields

- uint32_t campedCiotLteOpMode
- uint8_t TlvPresent

8.482.1 Detailed Description

This structure contains Camped CIOT LTE Operational Mode parameters.

Parameters

campedCiotLte-OpMode	• Indicates the camped CIoT LTE mode of operation. • Values: – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_ NB1 (0x03) - Camped on LTE NB1
TlvPresent	• Tlv Present or not

8.482.2 Field Documentation

8.482.2.1 uint32_t nas_LteCiotOpModeTlv::campedCiotLteOpMode

8.482.2.2 uint8_t nas_LteCiotOpModeTlv::TlvPresent

8.483 nas_lteEARFCN Struct Reference

Data Fields

- uint8_t status
- uint32_t earfcn0
- uint32_t earfcn1

8.483.1 Detailed Description

This structure contains LTE EARFCN infromation.

Parameters

status	• 0 - Disable • 1 - Enable

earfcn0	• Primary DL EARFCN to which the UE is locked
earfcn1	• Secondary DL EARFCN to which the UE is locked • Note : Make earfcn1 value equal to earfcn0 if only one EARFCN is desired.

8.483.2 Field Documentation

8.483.2.1 uint32_t nas_lteEARFCN::earfcn0

8.483.2.2 uint32_t nas_lteEARFCN::earfcn1

8.483.2.3 uint8_t nas_lteEARFCN::status

8.484 nas_lteGsmCellInfo Struct Reference

Data Fields

- uint8_t cellReselPriority
- uint8_t threshGsmHigh
- uint8_t threshGsmLow
- uint8_t nccPermitted
- uint8_t cells_len
- nas_gsmCellInfo GsmCellInfo [255]

8.484.1 Detailed Description

This structure contains information about the LTE GSM Cell.

Parameters

cellReselPriority	• Priority of this frequency group. • Range: 0 to 7. • This field is only valid when ue_in_idle is TRUE.
threshGsmHigh	• Reselection threshold for high priority layers. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE.
threshGsmLow	• Reselection threshold for low priority layers. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE.

nccPermitted	• Bitmask specifying whether a neighbor with a specific network color code is to be reported. • Range: 0 to 255. • Bit n set to 1 means a neighbor with NCC n must be included in the report. This flag is synonymous with a blacklist in other RATs. • This field is only valid when ue_in_idle is TRUE.
cells_len	• Provides the number of set of gsm cells.
GsmCellInfo[NAS_MAX_DESCRIPTION_LENGTH]	• See nas_gsmCellInfo for more information.

8.484.2 Field Documentation

8.484.2.1 uint8_t nas_lteGsmCellInfo::cellReselPriority

8.484.2.2 uint8_t nas_lteGsmCellInfo::cells_len

8.484.2.3 nas_gsmCellInfo nas_lteGsmCellInfo::GsmCellInfo[255]

8.484.2.4 uint8_t nas_lteGsmCellInfo::nccPermitted

8.484.2.5 uint8_t nas_lteGsmCellInfo::threshGsmHigh

8.484.2.6 uint8_t nas_lteGsmCellInfo::threshGsmLow

8.485 nas_LTEInfo Struct Reference

Data Fields

- uint8_t band
- uint8_t bandwidth
- uint16_t RXChan
- uint16_t TXChan
- uint8_t emmState
- uint8_t emmSubState
- uint8_t emmConnState

8.485.1 Detailed Description

Structure for storing the LTE information for the device.

Parameters

band	• LTE Band – 1 ∼ 40 (Band in decimal) – 0xFF - Invalid

bandwidth	• BandWidth. – 0x00 - 1.4 MHz – 0x01 - 3 MHz – 0x02 - 5 MHz – 0x03 - 10 MHz – 0x04 - 15 MHz – 0x05 - 20 MHz – 0x06 - Invalid – 0xFF - Unknown
RXChan	• RX channel number in decimal – 0xFFFF - Not Available
TXChan	• TX channel number in decimal – 0xFFFF - Not Available
emmState	• EMM State. – 0x00 - Deregistered – 0x01 - Reg Initiated – 0x02 - Registered – 0x03 - TAU Initiated – 0x04 - SR Initiated – 0x05 - Dereg Initiated – 0x06 - Invalid – 0xFF - Unknown

emmSubState	• EMM Sub State. – 0xFF - NOT Applicable • When EMM_state is 0x00: – 0x00 - No IMSI – 0x01 - PLMN Search – 0x02 - Attach Needed – 0x03 - No Cell – 0x04 - Attaching – 0x05 - Normal Service – 0x06 - Limited Service – 0x07 - Waiting for PDN • When EMM_state is 0x01: – 0x00 - Waiting for NW – 0x01 - Waiting for ESM • When EMM_state is 0x02: – 0x00 - Normal Service – 0x01 - Update Needed – 0x02 - Attempt Update – 0x03 - No Cell – 0x04 - PLMN Search – 0x05 - Limited Service – 0x06 - MM Update – 0x07 - IMSI Detach – 0x08 - Waiting for ESM
emmConnState	• EMM Connected Mode State. – 0x00 - RRC Idle – 0x01 - Waiting RRC Cfm – 0x02 - RRC Connected – 0x03 - RRC Releasing – 0xFF - Unknown

8.485.2 Field Documentation

8.485.2.1 uint8_t nas_LTEInfo::band

8.485.2.2 uint8_t nas_LTEInfo::bandwidth

8.485.2.3 uint8_t nas_LTEInfo::emmConnState

8.485.2.4 uint8_t nas_LTEInfo::emmState

8.485.2.5 uint8_t nas_LTEInfo::emmSubState

8.485.2.6 uint16_t nas_LTEInfo::RXChan

8.485.2.7 uint16_t nas_LTEInfo::TXChan

8.486 nas_LTEInfoInterfreq Struct Reference

Data Fields

- uint8_t ueInIdle
- uint8_t freqsLen
- nas_infoInterFreq InfoInterfreq [255]

8.486.1 Detailed Description

This structure contains information about the LTE Inter-Frequency Network.

Parameters

ueInIdle	• TRUE if the UE is in Idle mode, otherwise FALSE. – 0xFF - Not Available
freqsLen	• Provides the number of set of inter frequency information. • If 0(zero), then no information follows it.
InfoInterfreq[NAS_MAX_DESCRIPTION_LENGTH]	• See nas_infoInterFreq for more information.

8.486.2 Field Documentation

8.486.2.1 uint8_t nas_LTEInfoInterfreq::freqsLen

8.486.2.2 nas_infoInterFreq nas_LTEInfoInterfreq::InfoInterfreq[255]

8.486.2.3 uint8_t nas_LTEInfoInterfreq::ueInIdle

8.487 nas_LTEInfoIntrafreq Struct Reference

Data Fields

- uint8_t ueInIdle
- uint8_t plmn [3]
- uint16_t tac
- uint32_t globalCellId
- uint16_t earfcn
- uint16_t servingCellId
- uint8_t cellReselPriority
- uint8_t sNonIntraSearch
- uint8_t threshServingLow
- uint8_t sIntraSearch
- uint8_t cellsLen
- nas_cellParams CellParams [255]

8.487.1 Detailed Description

This structure contains information about the LTE Intra-Frequency Network.

Parameters

ueInIdle	• TRUE if the UE is in Idle mode, otherwise FALSE. – 0xFF - Not Available
plmn[NAS_PLMN_LENGTH]	• PLMN ID coded as octet 3, 4, and 5.
tac	• Tracking area code. – 0xFFFF - Not Available
globalCellId	• Global cell ID in the system information block. – 0xFFFFFFFF - Not Available
earfcn	• E-UTRA absolute radio frequency channel number of the serving cell. • Range: 0 to 65535. – 0xFFFF - Not Available
servingCellId	• LTE serving cell ID. • Range: 0 to 503. • This is the cell ID of the serving cell and can be found in the cell list. – 0xFFFF - Not Available
cellReselPriority	• Priority for serving frequency. • Range: 0 to 7. • This field is only valid when ue_in_idle is TRUE. – 0xFF - Not Available
sNonIntraSearch	• S non-intra search threshold to control non-intrafrequency searches. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE. – 0xFF - Not Available
threshServingLow	• Serving cell low threshold. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE. – 0xFF - Not Available

sIntraSearch	• S Intra search threshold. • Range: 0 to 31. • The current cell measurement must fall below this threshold to consider intrafrequency for reselection. • This field is only valid when ue_in_idle is TRUE. – 0xFF - Not Available
cellsLen	• Provides the number of set of cell params. • If 0(zero), then no information follows it.
CellParams[NAS_MAX_DESCRIPTION_LENGTH]	• See nas_cellParams for more information.

8.487.2 Field Documentation

8.487.2.1 nas_cellParams nas_LTEInfoIntrafreq::CellParams[255]

8.487.2.2 uint8_t nas_LTEInfoIntrafreq::cellReselPriority

8.487.2.3 uint8_t nas_LTEInfoIntrafreq::cellsLen

8.487.2.4 uint16_t nas_LTEInfoIntrafreq::earfcn

8.487.2.5 uint32_t nas_LTEInfoIntrafreq::globalCellId

8.487.2.6 uint8_t nas_LTEInfoIntrafreq::plmn[3]

8.487.2.7 uint16_t nas_LTEInfoIntrafreq::servingCellId

8.487.2.8 uint8_t nas_LTEInfoIntrafreq::sIntraSearch

8.487.2.9 uint8_t nas_LTEInfoIntrafreq::sNonIntraSearch

8.487.2.10 uint16_t nas_LTEInfoIntrafreq::tac

8.487.2.11 uint8_t nas_LTEInfoIntrafreq::threshServingLow

8.487.2.12 uint8_t nas_LTEInfoIntrafreq::ueInIdle

8.488 nas_LTEInfoNeighboringGSM Struct Reference

Data Fields

- uint8_t ueInIdle
- uint8_t freqsLen
- nas_lteGsmCellInfo LteGsmCellInfo [255]

8.488.1 Detailed Description

This structure contains information about the LTE Neighboring GSM Network.

Parameters

ueInIdle	• TRUE if the UE is in Idle mode, otherwise FALSE. – 0xFF - Not Available
freqsLen	• Provides the number of set of LTE GSM cell information. • If 0(zero), then no information follows it.
LteGsmCellInfo[NAS_MAX_DESCRIPTION_LENGTH]	• See nas_lteGsmCellInfo for more information.

8.488.2 Field Documentation

8.488.2.1 uint8_t nas_LTEInfoNeighboringGSM::freqsLen

8.488.2.2 nas_lteGsmCellInfo nas_LTEInfoNeighboringGSM::LteGsmCellInfo[255]

8.488.2.3 uint8_t nas_LTEInfoNeighboringGSM::ueInIdle

8.489 nas_LTEInfoNeighboringWCDMA Struct Reference

Data Fields

- uint8_t ueInIdle
- uint8_t freqsLen
- nas_lteWcdmaCellInfo LTEWCDMACellInfo [255]

8.489.1 Detailed Description

This structure contains information about the LTE Neighboring WCDMA Network.

Parameters

ueInIdle	• TRUE if the UE is in Idle mode, otherwise FALSE. – 0xFF - Not Available
freqsLen	• Provides the number of set of LTE WCDMA cell information. • If 0(zero), then no information follows it.
LTEWCDMACellInfo[NAS_MAX_DESCRIPTION_LENGTH]	• See nas_lteWcdmaCellInfo for more information.

8.489.2 Field Documentation

8.489.2.1 uint8_t nas_LTEInfoNeighboringWCDMA::freqsLen

8.489.2.2 nas_lteWcdmaCellInfo nas_LTEInfoNeighboringWCDMA::LTEWCDMACellInfo[255]

8.489.2.3 uint8_t nas_LTEInfoNeighboringWCDMA::ueInIdle

8.490 nas_LteM1BandPrefTlv Struct Reference

Data Fields

- uint64_t lteM1BandPref
- uint8_t TlvPresent

8.490.1 Detailed Description

Contain the LTE M1 band Preference.

Parameters

lteM1BandPref	• Bitmask representing the LTE M1 band preference • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127
TlvPresent	• Tlv Present

8.490.2 Field Documentation

8.490.2.1 uint64_t nas_LteM1BandPrefTlv::lteM1BandPref

8.490.2.2 uint8_t nas_LteM1BandPrefTlv::TlvPresent

8.491 nas_LteNb1BandPrefTlv Struct Reference

Data Fields

- uint64_t lteNb1BandPref
- uint8_t TlvPresent

8.491.1 Detailed Description

Contain the LTE NB1 band Preference.

Parameters

lteNb1BandPref	• Bitmask representing the LTE NB1 band preference. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127
TlvPresent	• Tlv Present

8.491.2 Field Documentation

8.491.2.1 uint64_t nas_LteNb1BandPrefTlv::lteNb1BandPref

8.491.2.2 uint8_t nas_LteNb1BandPrefTlv::TlvPresent

8.492 nas_LTEOperationMode Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t * pLTEOperationMode

8.492.1 Detailed Description

This structure contains the nas_LTEOperationMode response parameters.

Parameters

TlvPresent	• Tlv Present
pLTEOperation-Mode	• LTE Operational Mode

8.492.2 Field Documentation

8.492.2.1 uint32_t* nas_LTEOperationMode::pLTEOperationMode

8.492.2.2 uint8_t nas_LTEOperationMode::TlvPresent

8.493 nas_LteOpMode Struct Reference

Data Fields

- uint32_t lteOpMode
- uint8_t TlvPresent

8.493.1 Detailed Description

This structure contains LTE Operational Mode

Parameters

lteOpMode	• LTE Operational Mode • CIOT LTE mode on which reject indication is received. • Values – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_NB1 (0x03) - Camped on LTE NB1

TlvPresent	• Tlv Present or not

8.493.2 Field Documentation

8.493.2.1 uint32_t nas_LteOpMode::lteOpMode

8.493.2.2 uint8_t nas_LteOpMode::TlvPresent

8.494 nas_lteOpModeTlv Struct Reference

Data Fields

- uint8_t lteOpModeLen
- uint16_t MCC [255]
- uint16_t MNC [255]
- uint32_t lteOpMode [255]
- uint8_t TlvPresent

8.494.1 Detailed Description

This structure contains the LTE Operational Mode response parameters.

Parameters

lteOpModeLen	• Number of sets of the following elements – MCC – MNC – lteOpMode
MCC	• Mobile Country Code • A 16-bit integer representation of MCC • Range: 0 to 999
MNC	• Mobile Network Code • A 16-bit integer representation of MNC • Range: 0 to 999
lteOpMode	• Indicates the LTE mode of operation. • Values: – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_NB1 (0x03) - Camped on LTE NB1

TlvPresent	• Tlv Present

8.494.2 Field Documentation

8.494.2.1 uint32_t nas_IteOpModeTlv::IteOpMode[255]

8.494.2.2 uint8_t nas_IteOpModeTlv::IteOpModeLen

8.494.2.3 uint16_t nas_IteOpModeTlv::MCC[255]

8.494.2.4 uint16_t nas_IteOpModeTlv::MNC[255]

8.494.2.5 uint8_t nas_IteOpModeTlv::TlvPresent

8.495 nas_ItePCI Struct Reference

Data Fields

- uint8_t status
- uint32_t earfcn
- uint32_t pci

8.495.1 Detailed Description

This structure contains LTE PCI infromation.

Parameters

status	• 0 - Disable • 1 - Enable
earfcn	• UARFCN to which UE is locked
pci	• PCI to which the UE is locked

8.495.2 Field Documentation

8.495.2.1 uint32_t nas_ItePCI::earfcn

8.495.2.2 uint32_t nas_ItePCI::pci

8.495.2.3 uint8_t nas_ItePCI::status

8.496 nas_IteRsrpinformation Struct Reference

Data Fields

- int16_t rsrplevel

8.496.1 Detailed Description

This structure contains the LTE RSRP Information

Parameters

rsrplevel	• LTE RSRP in dBm as a mesaured by L1. Range: -44 to -140(-44 means -44dBm, -140 means -140dBm).

8.496.2 Field Documentation

8.496.2.1 int16_t nas_lteRsrpinformation::rsrplevel

8.497 nas_LTERSRPThresh Struct Reference

Data Fields

- uint8_t LTERSRPThreshListLen
- int16_t * pLTERSRPThreshList

8.497.1 Detailed Description

This structure contains LTE RSRP threshold related parameters.

Parameters

LTERSRP-ThreshListLen	• Length of the LTE RSRP threshold list parameter to follow
pLTERSRP-ThreshList	• Array of RSRP thresholds (in units of 0.1 dBm) • Maximum of 32 values • Range for RSRP values: -140 to -44 (in dBm).

8.497.2 Field Documentation

8.497.2.1 uint8_t nas_LTERSRPThresh::LTERSRPThreshListLen

8.497.2.2 int16_t* nas_LTERSRPThresh::pLTERSRPThreshList

8.498 nas_LTERSRQThresh Struct Reference

Data Fields

- uint8_t LTERSRQThreshListLen

- int16_t * pLTERSRQThreshList

8.498.1 Detailed Description

This structure contains LTE RSRQ threshold related parameters.

Parameters

LTERSRQ-ThreshListLen	• Length of the LTE RSRQ threshold list parameter to follow
pLTERSRQ-ThreshList	• Array of RSRQ thresholds (in units of 0.1 dBm) • Maximum of 32 values. • Range for RSRQ values: -20 to -3 (in dBm)

8.498.2 Field Documentation

8.498.2.1 uint8_t nas_LTERSRQThresh::LTERSRQThreshListLen

8.498.2.2 int16_t* nas_LTERSRQThresh::pLTERSRQThreshList

8.499 nas_LTERSSIThresh Struct Reference

Data Fields

- uint8_t LTERSSIThreshListLen
- int16_t * pLTERSSIThreshList

8.499.1 Detailed Description

This structure contains LTE RSSI threshold related parameters.

Parameters

LTERSSI-ThreshListLen	• Length of the LTE RSSI threshold list parameter to follow
pLTERSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • Maximum of 32 values. • Range for RSSI values: -120 to 0 (in dBm)

8.499.2 Field Documentation

8.499.2.1 uint8_t nas_LTERSSIThresh::LTERSSIThreshListLen

8.499.2.2 int16_t* nas_LTERSSIThresh::pLTERSSIThreshList

8.500 nas_LTESigRptCfg Struct Reference

Data Fields

- uint8_t rptRate
- uint8_t avgPeriod

8.500.1 Detailed Description

This structure contains LTE signal report config.

Parameters

rptRate	• Rate on how often the LTE signal must be checked for reporting • Values: – 0 - Report using the default configuration – 1 - Report every 1 sec – 2 - Report every 2 sec – 3 - Report every 3 sec – 4 - Report every 4 sec – 5 - Report every 5 sec
avgPeriod	• Averaging period to be used for the LTE signal • Values: – 0 - Average using the default configuration – 1 - Average over 1 sec – 2 - Average over 2 sec – 3 - Average over 3 sec – 4 - Average over 4 sec – 5 - Average over 5 sec – 6 - Average over 6 sec – 7 - Average over 7 sec – 8 - Average over 8 sec – 9 - Average over 9 sec – 10 - Average over 10 sec

8.500.2 Field Documentation

8.500.2.1 uint8_t nas_LTESigRptCfg::avgPeriod

8.500.2.2 uint8_t nas_LTESigRptCfg::rptRate

8.501 nas_LTESigRptConfig Struct Reference

Data Fields

- uint8_t rptRate
- uint8_t avgPeriod

8.501.1 Detailed Description

This structure contains LTE RSRP threshold related parameters.

Parameters

rptRate	• Rate on how often the LTE signal must be checked for reporting Values • 0 - Report using the default configuration • 1 - Report every 1 sec • 2 - Report every 2 sec • 3 - Report every 3 sec • 4 - Report every 4 sec • 5 - Report every 5 sec
avgPeriod	• Averaging period to be used for the LTE signal. • Values – 0 - Average using the default configuration – 1 - Average over 1 sec – 2 - Average over 2 sec – 3 - Average over 3 sec – 4 - Average over 4 sec – 5 - Average over 5 sec – 6 - Average over 6 sec – 7 - Average over 7 sec – 8 - Average over 8 sec – 9 - Average over 9 sec – 10 - Average over 10 sec

8.501.2 Field Documentation

8.501.2.1 uint8_t nas_LTESigRptConfig::avgPeriod

8.501.2.2 uint8_t nas_LTESigRptConfig::rptRate

8.502 nas_lteSnrinformation Struct Reference

Data Fields

- int16_t snrlevel

8.502.1 Detailed Description

This structure contains the LTE SNR Information

Parameters

snrlevel	• LTE SNR level as a scaled integer in units of 0.1dB e.g. -16dB has a value of -160 and 24.6dB has value of 246.

8.502.2 Field Documentation

8.502.2.1 int16_t nas_lteSnrinformation::snrlevel

8.503 nas_LTESNRThresh Struct Reference

Data Fields

- uint8_t LTESNRThresListLen
- int16_t * pLTESNRThresList

8.503.1 Detailed Description

This structure contains LTE SNR threshold list.

Parameters

LTESNRThres-ListLen	• Length of the LTE SNR threshold list parameter to follow
pLTESNRThres-List	• Sequence of thresholds delimiting SNR event reporting bands • Every time a SNR value crosses a threshold value, an event report indication message with the new SNR value is sent to the requesting control point. For this field – For LTE, each SNR threshold value is a signed 2 Byte value – Maximum number of threshold values is 16 – At least one value must be specified – SNR level as a scaled integer in units of 0.1 dB; e.g., -16 dB has a value of -160 and 24.6 dB has a value of 246

8.503.2 Field Documentation

8.503.2.1 uint8_t nas_LTESNRThresh::LTESNRThresListLen

8.503.2.2 int16_t* nas_LTESNRThresh::pLTESNRThresList

8.504 nas_LTESNRThreshold Struct Reference

Data Fields

- uint8_t LTESNRThreshListLen
- int16_t * pLTESNRThreshList

8.504.1 Detailed Description

This structure contains LTE SNR threshold related parameters.

Parameters

LTESNRThresh-ListLen	• Length of the LTE SNR threshold list parameter to follow

pLTESNR-ThreshList	• Array of SNR thresholds (in units of 0.1 dB) • Maximum of 32 values • Range for SNR values: -20 to 30 (in dB).

8.504.2 Field Documentation

8.504.2.1 uint8_t nas_LTESNRThreshold::LTESNRThreshListLen

8.504.2.2 int16_t* nas_LTESNRThreshold::pLTESNRThreshList

8.505 nas_LTESysInfo Struct Reference

Data Fields

- nas_sysInfoCommon sysInfoLTE
- uint8_t lacValid
- uint16_t lac
- uint8_t cellIdValid
- uint32_t cellId
- uint8_t regRejectInfoValid
- uint8_t rejectSrvDomain
- uint8_t rejCause
- uint8_t networkIdValid
- uint8_t MCC [3]
- uint8_t MNC [3]
- uint8_t tacValid
- uint16_t tac

8.505.1 Detailed Description

Structure for storing the LTE System Information.

Parameters

sysInfoLTE	• See nas_sysInfoCommon for more information.

lacValid	• Indicates whether the location area code is valid..
	  – 0x00 - Invalid
	  – 0x01 - Valid
	  – 0xFF - Not Available

lac	• Location area code. • Only applies to 3GPP. – 0xFFFF - Not Available

cellIdValid	• Indicates whether the cell ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
cellId	• Cell ID. – 0xFFFFFFFF - Not Available
regRejectInfo-Valid	• Indicates whether the registration reject information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
rejectSrvDomain	• Type of service domain in which the registration is rejected. – 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available
rejCause	• Reject cause values sent are specified in [3GPP TS 24.008, Section 10.5.3.6]. and [3GPP TS 24.301, Section 9.9.3.9] – 0xFF - Not Available
networkIdValid	• Indicates whether the network ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
MCC[NAS_PLM-N_LENGTH]	• Mobile Country Code. • MCC digits in ASCII characters
MNC[NAS_PLM-N_LENGTH]	• Mobile Network Code. • MNC digits in ASCII characters • An unused byte is set to 0xFF. • In case of two-digit MNC values, the third (unused) digit is set to 0xFF. For example, 15 (a two-digit MNC) is reported using the byte stream 0x31 0x35 0xFF.

tacValid	• Indicates whether tracking area code is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
tac	• Tracking area code. • Only applicable for LTE. – 0xFFFF - Not Available

8.505.2 Field Documentation

8.505.2.1 uint32_t nas_LTESysInfo::cellId

8.505.2.2 uint8_t nas_LTESysInfo::cellIdValid

8.505.2.3 uint16_t nas_LTESysInfo::lac

8.505.2.4 uint8_t nas_LTESysInfo::lacValid

8.505.2.5 uint8_t nas_LTESysInfo::MCC[3]

8.505.2.6 uint8_t nas_LTESysInfo::MNC[3]

8.505.2.7 uint8_t nas_LTESysInfo::networkIdValid

8.505.2.8 uint8_t nas_LTESysInfo::regRejectInfoValid

8.505.2.9 uint8_t nas_LTESysInfo::rejCause

8.505.2.10 uint8_t nas_LTESysInfo::rejectSrvDomain

8.505.2.11 nas_sysInfoCommon nas_LTESysInfo::sysInfoLTE

8.505.2.12 uint16_t nas_LTESysInfo::tac

8.505.2.13 uint8_t nas_LTESysInfo::tacValid

8.506 nas_IteWcdmaCellInfo Struct Reference

Data Fields

- uint16_t uarfcn
- uint8_t cellReselPriority
- uint16_t threshXhigh
- uint16_t threshXlow
- uint8_t cellsLen
- nas_wcdmaCellInfo WCDMACellInfo [255]

8.506.1 Detailed Description

This structure contains information about the LTE WCDMA Cell.

Parameters

uarfcn	• WCDMA layer frequency. • Range: 0 to 16383.
cellReselPriority	• Cell re-selection priority. • Range: 0 to 7. • This field is only valid when ue_in_idle is TRUE.
threshXhigh	• Re-selection low threshold. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE.
threshXlow	• Re-selection high threshold. • Range: 0 to 31. • This field is only valid when ue_in_idle is TRUE.
cellsLen	• Provides the number of set of WCDMA cells.
WCDMACell-Info[NAS_MAX_-DESCRIPTION-_LENGTH]	• See nas_wcdmaCellInfo for more information.

8.506.2 Field Documentation

8.506.2.1 uint8_t nas_lteWcdmaCellInfo::cellReselPriority

8.506.2.2 uint8_t nas_lteWcdmaCellInfo::cellsLen

8.506.2.3 uint16_t nas_lteWcdmaCellInfo::threshXhigh

8.506.2.4 uint16_t nas_lteWcdmaCellInfo::threshXlow

8.506.2.5 uint16_t nas_lteWcdmaCellInfo::uarfcn

8.506.2.6 nas_wcdmaCellInfo nas_lteWcdmaCellInfo::WCDMACellInfo[255]

8.507 nas_minBasedIMSI Struct Reference

Data Fields

- uint8_t mccM [3]
- uint16_t imsiM1112
- uint8_t imsiMS1 [7]

- uint8_t imsiMS2 [3]

8.507.1 Detailed Description

This structure contains MIN-based IMSI.

Parameters

mccM	• ASCII character representation of MCC_M
imsiM1112	• ASCII character representation of IMSI_M_11_12 value – 0xFFFF - Not Available
imsiMS1	• ASCII character representation of IMSI_M_S1 value
imsiMS2	• ASCII character representation of IMSI_M_S2 value

8.507.2 Field Documentation

8.507.2.1 uint16_t nas_minBasedIMSI::imsiM1112

8.507.2.2 uint8_t nas_minBasedIMSI::imsiMS1[7]

8.507.2.3 uint8_t nas_minBasedIMSI::imsiMS2[3]

8.507.2.4 uint8_t nas_minBasedIMSI::mccM[3]

8.508 nas_MNRInfo Struct Reference

Data Fields

- uint16_t mcc
- uint16_t mnc
- uint32_t rat

8.508.1 Detailed Description

Structure contains Manual Network Register Information parameters

Parameters

mcc	• A 16-bit integer representation of Mobile Country Code. Range - 0 to 999.
mnc	• A 16-bit integer representation of Mobile Network Code. Range - 0 to 999.

rat	• Radio access technology for which to register. – 0x04 - RADIO_IF_GSM – 0x05 - RADIO_IF_UMTS – 0x08 - RADIO_IF_LTE

8.508.2 Field Documentation

8.508.2.1 uint16_t nas_MNRInfo::mcc

8.508.2.2 uint16_t nas_MNRInfo::mnc

8.508.2.3 uint32_t nas_MNRInfo::rat

8.509 nas_ModePrefTlv Struct Reference

Data Fields

- uint16_t ModePref
- uint8_t TlvPresent

8.509.1 Detailed Description

Contain the radio technology mode preference

Parameters

ModePref	• Bit Mask indicating the radio technology mode preference • Bit values: – Bit 0 - cdma2000 1x – Bit 1 - cdma2000 HRPD(1xEV-DO) – Bit 2 - GSM – Bit 3 - UMTS – Bit 4 - LTE – Bit 5 - TD-SCDMA – Bit 6 - NR5G
TlvPresent	• Tlv Present

8.509.2 Field Documentation

8.509.2.1 uint16_t nas_ModePrefTlv::ModePref

8.509.2.2 uint8_t nas_ModePrefTlv::TlvPresent

8.510 nas_namName Struct Reference

Data Fields

- uint8_t namNameLen
- uint8_t namName [12]

8.510.1 Detailed Description

This structure contains NAM Name.

Parameters

namNameLen	• Number of sets of the following elements: – nam_name • If zero(0), then no information follows.
namName	• Name information in ASCII. The maximum length of nam_name is 12.

8.510.2 Field Documentation

8.510.2.1 uint8_t nas_namName::namName[12]

8.510.2.2 uint8_t nas_namName::namNameLen

8.511 nas_netSelectionPref Struct Reference

Data Fields

- uint8_t netReg
- uint16_t mcc
- uint16_t mnc

8.511.1 Detailed Description

Contain the network selection preference.

Parameters

netReg	• specifies one of the following actions: – 0x00 - Automatic registration * Device registers according to its provisioning; mcc and mnc fields are ignored – 0x01 - Manual Registration * Device registers to specified network; mcc and mnc must contain valid values
mcc	• MCC value. Range 0 to 999
mnc	• MNC value. Range 0 to 999

8.511.2 Field Documentation

8.511.2.1 uint16_t nas_netSelectionPref::mcc

8.511.2.2 uint16_t nas_netSelectionPref::mnc

8.511.2.3 uint8_t nas_netSelectionPref::netReg

8.512 nas_NetSelPrefTlv Struct Reference

Data Fields

- uint8_t NetSelPref
- uint8_t TlvPresent

8.512.1 Detailed Description

Contain the Network selection Preference for system selection preferences.

Parameters

NetSelPref	• Parameter indicating network selection preference • Values: – 0x00 - Automatic network selection – 0x01 - Manual network selection
TlvPresent	• Tlv Present

8.512.2 Field Documentation

8.512.2.1 uint8_t nas_NetSelPrefTlv::NetSelPref

8.512.2.2 uint8_t nas_NetSelPrefTlv::TlvPresent

8.513 nas_NetworkStat1x Struct Reference

Data Fields

- uint8_t State
- uint16_t SO
- uint32_t RX_PWR
- uint16_t RX_EC_IO
- uint32_t TX_PWR
- uint8_t ActSetCnt
- nas_ActPilotPNElement * pActPilotPNElements
- uint8_t NeighborSetCnt
- uint16_t * pNeighborSetPilotPN

8.513.1 Detailed Description

This structure contains network stat 1x.

Parameters

State	• CDMA current access state – 0x01 - Searching – 0x02 - Idle – 0x03 - Traffic – Others - NA
SO	• CDMA service option – 0xFFFF - Not in a call – 0x0001 - Basic Variable Rate Voice Service(8kbps) – 0x0002 - Mobile Station Loopback(8kbps) – 0x0003 - Enhanced Variable Rate Codec(EVRC) Voice Service(8kbps) – 0x0006 - Short message Services(Rate Set 1) – 0x0009 - Mobile Station Loopback(13kbps) – 0x000E - Short Message Service (Rate Set 2) – 0x0011 - High Rate Voice Service(13kbps) – 0x0020 - Test Data Service Option(TDSO) – 0x0021 - cdma2000 High Speed Packet Data Service, Internet or ISO Protocol Stack – 0x0044 - EVRC-B Voice Service(8 kbps) – 0x0046 - EVRC-WB Voice Service(8 kbps) – 0x0049 - Voice Echo mode supports smart blanking(EVRC-NW) – 0x004B - Enhanced loopback – 0x8000 - Proprietary Service Option (Qualcomm Inc.)
RX_PWR	• RX Pwr(dBm) – 0xABCD00EF - -ABCD.EF dBm – ABCD00EF should be transferred to decimal while displaying – Example: 0x12340056 - -4660.86dBm 0x1234 = 4660, 0x0056 = 86 – 0xFFFFFFFF - NA
RX_EC_IO	• RX EC/IO(dB) – 0xABCD - -AB.CD dB – ABCD should be transferred to decimal while displaying – Example: 0x1234 - -18.52dB 0x12 = 18, 0x34 = 52 – 0xFFFF - NA
TX_PWR	• TX PWR(dBm) – 0xFFFFFFFF - NA – Others - display actual value in decimal – Example: 0x1234 - -4660dBm 0x1234 = 4660

ActSetCnt	• Count of active pilot PN elements • As input specifies number of sets of parameter pActPilotElements for which memory has been assigned • As output specifies the actual number of sets of parameter pActPilotElements returned by device
pActPilotPN-Elements	• See nas_ActPilotPNElement for more information
NeighborSetCnt	• Count of neighbor pilot PN elements • As input specifies number of sets of parameter pNeighborSetPilotPN for which memory has been assigned • As output specifies the actual number of sets of parameter pNeighborSetPilotPN returned by device
pNeighborSet-PilotPN	• Neighbor pilot PN

8.513.2 Field Documentation

8.513.2.1 uint8_t nas_NetworkStat1x::ActSetCnt

8.513.2.2 uint8_t nas_NetworkStat1x::NeighborSetCnt

8.513.2.3 nas_ActPilotPNElement* nas_NetworkStat1x::pActPilotPNElements

8.513.2.4 uint16_t* nas_NetworkStat1x::pNeighborSetPilotPN

8.513.2.5 uint16_t nas_NetworkStat1x::RX_EC_IO

8.513.2.6 uint32_t nas_NetworkStat1x::RX_PWR

8.513.2.7 uint16_t nas_NetworkStat1x::SO

8.513.2.8 uint8_t nas_NetworkStat1x::State

8.513.2.9 uint32_t nas_NetworkStat1x::TX_PWR

8.514 nas_NetworkStatEVDO Struct Reference

Data Fields

- uint8_t State
- uint8_t MACIndex
- uint8_t SectorIDLen
- uint16_t * pSectorID
- uint16_t RX_PWR
- uint16_t PER
- uint16_t PilotEnergy
- uint8_t SNR

8.514.1 Detailed Description

This structure contains network stat EVDO.

Parameters

State	• EVDO network access state – 0x00 - Sleep – 0x01 - Searching – 0x02 - Idle – 0x03 - Active – 0xFF - NA
MACIndex	• HDR Mac index – 0xFF - NA – Others - Display the actual value in decimal – Example: 0x12 - 18 0x12 = 18
SectorIDLen	(IN/OUT) • Sector ID length • As input specifies length of parameter pSectorID for which memory has been assigned • As output specifies the actual length of parameter pSectorID returned by device
pSectorID	• Sector ID
RX_PWR	• TX PWR(dBm) – 0xABCD - -ABCD dBm – ABCD should be transferred to decimal while displaying – Example: 0x1234 - -4660dBm 0x1234 = 4660 – 0xFFFF - NA
PER	• HDR Packet Error Rate – 0xFFFF - Unknown – Others - display the actual value in decimal – Example: 0x1234 - -4660dBm 0x1234 = 4660
PilotEnergy	• Pilt Energy (dB) – 0xFFFF - NA – 0xABCD should be transferred to decimal while displaying – Example: 0x1234 - -4660dBm 0x1234 = 4660
SNR	• Signal to Noise ratio (dB)

8.514.2 Field Documentation

8.514.2.1 uint8_t nas_NetworkStatEVDO::MACIndex

8.514.2.2 uint16_t nas_NetworkStatEVDO::PER

8.514.2.3 uint16_t nas_NetworkStatEVDO::PilotEnergy

8.514.2.4 uint16_t* nas_NetworkStatEVDO::pSectorID

8.514.2.5 uint16_t nas_NetworkStatEVDO::RX_PWR

8.514.2.6 uint8_t nas_NetworkStatEVDO::SectorIDLen

8.514.2.7 uint8_t nas_NetworkStatEVDO::SNR

8.514.2.8 uint8_t nas_NetworkStatEVDO::State

8.515 nas_nmrCellInfo Struct Reference

Data Fields

- uint32_t nmrCellID
- uint8_t nmrPlmn [3]
- uint16_t nmrLac
- uint16_t nmrArfcn
- uint8_t nmrBsic
- uint16_t nmrRxLev

8.515.1 Detailed Description

This structure contains information about the Network Measurement Report (NMR) Cell Information.

Parameters

nmrCellID	• Cell ID. • 0xFFFFFFFF indicates cell ID information is not present.
nmrPlmn[NAS_PLMN_LENGTH]	• MCC/MNC information coded as octet 3, 4, and 5. • This field is ignored when nmrCellID is not present.
nmrLac	• Location area code. • This field is ignored when nmrCellID is not present. – 0xFFFF - Not Available
nmrArfcn	• Absolute RF channel number. – 0xFFFF - Not Available

nmrBsic	• Base station identity code. – 0xFF - Not Available
nmrRxLev	• Cell Rx measurement. • Values range between 0 and 63. • Mapped to a measured signal level: – Rxlev 0 is a signal strength less than -110 dBm – Rxlev 1 is -110 dBm to -109 dBm – Rxlev 2 is -109 dBm to -108 dBm – ... – Rxlev 62 is -49 dBm to -48 dBm – Rxlev 63 is greater than -48 dBm – 0xFFFF - Not Available

8.515.2 Field Documentation

8.515.2.1 uint16_t nas_nmrCellInfo::nmrArfcn

8.515.2.2 uint8_t nas_nmrCellInfo::nmrBsic

8.515.2.3 uint32_t nas_nmrCellInfo::nmrCellID

8.515.2.4 uint16_t nas_nmrCellInfo::nmrLac

8.515.2.5 uint8_t nas_nmrCellInfo::nmrPlmn[3]

8.515.2.6 uint16_t nas_nmrCellInfo::nmrRxLev

8.516 nas_nr5gBandPref Struct Reference

Data Fields

- uint64_t bits_1_64
- uint64_t bits_65_128
- uint64_t bits_129_192
- uint64_t bits_193_256

8.516.1 Detailed Description

Contain the NR5G Band Preference.

Parameters

bits_1_64	• Bits 1 to 64 of the 256-bit NR5G Operating Band bitmask.
bits_65_128	• Bits 65 to 128 of the 256-bit NR5G Operating Band bitmask.

bits_129_192	• Bits 129 to 192 of the 256-bit NR5G Operating Band bitmask.
bits_193_256	• Bits 193 to 256 of the 256-bit NR5G Operating Band bitmask.

8.516.2 Field Documentation

8.516.2.1 uint64_t nas_nr5gBandPref::bits_129_192

8.516.2.2 uint64_t nas_nr5gBandPref::bits_193_256

8.516.2.3 uint64_t nas_nr5gBandPref::bits_1_64

8.516.2.4 uint64_t nas_nr5gBandPref::bits_65_128

8.517 nas_NR5GCellStatusTlv Struct Reference

Data Fields

- uint32_t nr5gCellStatus
- uint8_t TlvPresent

8.517.1 Detailed Description

Structure for storing the NR5G Cell Access Status Info parameters

Parameters

nr5gCellStatus	• Cell access status for NR5G calls. – Values: * NAS_CELL_ACCESS_NORMAL_ ONLY (0x00) - Cell access is allowed for normal calls only * NAS_CELL_ACCESS_EMERGENCY_ ONLY (0x01) - Cell access is allowed for emergency calls only * NAS_CELL_ACCESS_NO_CALLS (0x02) - Cell access is not allowed for any call type * NAS_CELL_ACCESS_ALL_CALLS (0x03) - Cell access is allowed for all call types * NAS_CELL_ACCESS_UNKNOWN (-1) - Cell access type is unknown
TlvPresent	• Tlv Present or not

8.517.2 Field Documentation

8.517.2.1 uint32_t nas_NR5GCellStatusTlv::nr5gCellStatus

8.517.2.2 uint8_t nas_NR5GCellStatusTlv::TlvPresent

8.518 nas_NR5GSerStatTlv Struct Reference

Data Fields

- uint8_t srvStatus
- uint8_t trueSrvStatus
- uint8_t isPrefDataPath
- uint8_t TlvPresent

8.518.1 Detailed Description

This structure contains NR5G Service Status Info parameters.

Parameters

srvStatus	• Service status of the system. • Values: – 0x00 - SYS_SRV_STATUS_NO_SRV - No service – 0x01 - SYS_SRV_STATUS_LIMITED - Limited service – 0x02 - SYS_SRV_STATUS_SRV - Service – 0x03 - SYS_SRV_STATUS_LIMITED_REGIONAL - Limited regional service – 0x04 - SYS_SRV_STATUS_PWR_SAVE - Power save
trueSrvStatus	• True service status of the system (not applicable to CDMA/HDR). • Values: – 0x00 - SYS_SRV_STATUS_NO_SRV - No service – 0x01 - SYS_SRV_STATUS_LIMITED - Limited service – 0x02 - SYS_SRV_STATUS_SRV - Service – 0x03 - SYS_SRV_STATUS_LIMITED_REGIONAL - Limited regional service – 0x04 - SYS_SRV_STATUS_PWR_SAVE - Power save
isPrefDataPath	• Whether the RAT is the preferred data path: • Values – 0x00 - Not preferred – 0x01 - Preferred
TlvPresent	• Tlv Present or not

8.518.2 Field Documentation

8.518.2.1 uint8_t nas_NR5GSerStatTlv::isPrefDataPath

8.518.2.2 uint8_t nas_NR5GSerStatTlv::srvStatus

8.518.2.3 uint8_t nas_NR5GSerStatTlv::TlvPresent

8.518.2.4 uint8_t nas_NR5GSerStatTlv::trueSrvStatus

8.519 nas_NR5GSystemInfoTlv Struct Reference

Data Fields

- uint8_t srvDomainValid
- uint8_t srvDomain
- uint8_t srvCapValid
- uint8_t srvcapability
- uint8_t roamStatusValid
- uint8_t roamStatus
- uint8_t sysForbiddenValid
- uint8_t sysForbidden
- uint8_t lacValid
- uint16_t lac
- uint8_t cellIdValid
- uint32_t cellId
- uint8_t regRejectInfoValid
- uint8_t rejectSrvDomain
- uint8_t rejCause
- uint8_t nwIdValid
- int8_t MCC [3]
- int8_t MNC [3]
- uint8_t tacValid
- uint16_t tac
- uint8_t TlvPresent

8.519.1 Detailed Description

This structure contains NR5G System Info parameters.

Parameters

srvDomainValid	• Indicates whether the service domain is valid.
srvDomain	• Service domain registered on the system. – Values: * 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service * 0x01 - SYS_SRV_DOMAIN_CS_ONLY - Circuit-switched only * 0x02 - SYS_SRV_DOMAIN_PS_ONLY - Packet-switched only * 0x03 - SYS_SRV_DOMAIN_CS_PS - Circuit-switched and packet-switched * 0x04 - SYS_SRV_DOMAIN_CAMPED -Camped
srvCapValid	• Indicates whether the service capability is valid.

srvCapability	• Current system service capability. – Values: * 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service * 0x01 - SYS_SRV_DOMAIN_CS_ONLY - Circuit-switched only * 0x02 - SYS_SRV_DOMAIN_PS_ONLY - Packet-switched only * 0x03 - SYS_SRV_DOMAIN_CS_PS - Circuit-switched and packet-switched * 0x04 - SYS_SRV_DOMAIN_CAMPED - Camped
roamStatusValid	• Indicates whether the roaming status is valid.
roamStatus	• Current roaming status. – Values: * 0x00 - SYS_ROAM_STATUS_OFF - Off * 0x01 - SYS_ROAM_STATUS_ON - On * 0x02 - SYS_ROAM_STATUS_BLINK - Blinking * 0x03 - SYS_ROAM_STATUS_OUT_OF_NEIGHBORHOOD - Out of the neighborhood * 0x04 - SYS_ROAM_STATUS_OUT_OF_BLDG - Out of the building * 0x05 - SYS_ROAM_STATUS_PREF_SYS - Preferred system * 0x06 - SYS_ROAM_STATUS_AVAIL_SYS - Available system * 0x07 - SYS_ROAM_STATUS_ALLIANCE_PARTNER - Alliance partner * 0x08 - SYS_ROAM_STATUS_PREMIUM_PARTNER - Premium partner * 0x09 - SYS_ROAM_STATUS_FULL_SVC - Full service * 0x0A - SYS_ROAM_STATUS_PARTIAL_SVC -Partial service * 0x0B - SYS_ROAM_STATUS_BANNER_ON -Banner is on * 0x0C - SYS_ROAM_STATUS_BANNER_OFF -Banner is off Remainder of the values are per 3GPP2 C.R1001-F. Values from 0x02 onward are only applicable for 3GPP2.
sysForbidden-Valid	• Indicates whether the forbidden system is valid.
sysForbidden	• Whether the system is forbidden: • 0x00 Not forbidden • 0x01 Forbidden
lacValid	• Indicates whether the location area code is valid.
lac	• Location area code (only applicable for 3GPP).
cellIdValid	• Indicates whether the cell ID is valid.
cellId	• Cell ID.

rejectSrvDomain	• Type of service domain in which the registration is rejected. • Values: • 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service • 0x01 - SYS_SRV_DOMAIN_CS_ONLY - Circuit-switched only • 0x02 - SYS_SRV_DOMAIN_PS_ONLY - Packet-switched only • 0x03 - SYS_SRV_DOMAIN_CS_PS - Circuit-switched and packet-switched • 0x04 - SYS_SRV_DOMAIN_CAMPED - Camped
rejCause	• Reject cause values sent are specified in 3GPP TS • 24.008 Sections 10.5.3.6 and 10.5.5.14, and 3GPP • TS 24.301 Section 9.9.3.9.
nwIdValid	• Indicates whether the network ID is valid.
MCC	• MCC digits in ASCII characters.For CDMA, the MCC wildcard value is returned as{3, 0xFF, 0xFF}..
MNC	• MNC digits in ASCII characters. For this field: • Unused byte is set to 0xFF • In the case of two-digit MNC values, the third (unused) digit is set to 0xFF. For example, 15 (a two-digit MNC) is reported using thebyte stream 0x35 0x31 0xFF.For CDMA, the MNC wildcard value is returned as {7, 0xFF, 0xFF}.
tacValid	• Indicates whether the tracking area code is valid.
tac	• Tracking area code (only applicable for NR5G).
TlvPresent	• Tlv Present or not

8.519.2 Field Documentation

8.519.2.1 uint32_t nas_NR5GSystemInfoTlv::cellId

8.519.2.2 uint8_t nas_NR5GSystemInfoTlv::cellIdValid

8.519.2.3 uint16_t nas_NR5GSystemInfoTlv::lac

8.519.2.4 uint8_t nas_NR5GSystemInfoTlv::lacValid

8.519.2.5 int8_t nas_NR5GSystemInfoTlv::MCC[3]

8.519.2.6 int8_t nas_NR5GSystemInfoTlv::MNC[3]

8.519.2.7 uint8_t nas_NR5GSystemInfoTlv::nwIdValid

8.519.2.8 uint8_t nas_NR5GSystemInfoTlv::regRejectInfoValid

8.519.2.9 uint8_t nas_NR5GSystemInfoTlv::rejCause

8.519.2.10 uint8_t nas_NR5GSystemInfoTlv::rejectSrvDomain

8.519.2.11 uint8_t nas_NR5GSystemInfoTlv::roamStatus

8.519.2.12 uint8_t nas_NR5GSystemInfoTlv::roamStatusValid

8.519.2.13 uint8_t nas_NR5GSystemInfoTlv::srvcapability

8.519.2.14 uint8_t nas_NR5GSystemInfoTlv::srvCapValid

8.519.2.15 uint8_t nas_NR5GSystemInfoTlv::srvDomain

8.519.2.16 uint8_t nas_NR5GSystemInfoTlv::srvDomainValid

8.519.2.17 uint8_t nas_NR5GSystemInfoTlv::sysForbidden

8.519.2.18 uint8_t nas_NR5GSystemInfoTlv::sysForbiddenValid

8.519.2.19 uint16_t nas_NR5GSystemInfoTlv::tac

8.519.2.20 uint8_t nas_NR5GSystemInfoTlv::tacValid

8.519.2.21 uint8_t nas_NR5GSystemInfoTlv::TlvPresent

8.520 nas_operatorNameString Struct Reference

Data Fields

- uint8_t PLMNName [255]

8.520.1 Detailed Description

This structure contains PLMN name.

Parameters

PLMNName	• PLMN name must be coded in a default 7-bit alphabet with b8 set to 0.

8.520.2 Field Documentation

8.520.2.1 uint8_t nas_operatorNameString::PLMNName[255]

8.521 nas_OperatorPLMNData Struct Reference

Data Fields

- uint8_t mcc [3]
- uint8_t mnc [3]
- uint16_t lac1
- uint16_t lac2
- uint8_t PLMNRecID

8.521.1 Detailed Description

This structure contains Operator PLMN.

Parameters

mcc	• MCC in ASCII string (a value of D in any of the digits is to be used to indicate a "wild" value for that corresponding digit).
mnc	• MNC in ASCII string (a value of D in any of the digits is to be used to indicate a "wild" value for that corresponding digit; digit 3 in MNC is optional and when not present, will be set as ASCII F).
lac1	• Location area code 1.
lac2	• Location area code 1.
PLMNRecID	• PLMN network name record identifier.

8.521.2 Field Documentation

8.521.2.1 uint16_t nas_OperatorPLMNData::lac1

8.521.2.2 uint16_t nas_OperatorPLMNData::lac2

8.521.2.3 uint8_t nas_OperatorPLMNData::mcc[3]

8.521.2.4 uint8_t nas_OperatorPLMNData::mnc[3]

8.521.2.5 uint8_t nas_OperatorPLMNData::PLMNRecID

8.522 nas_operatorPLMNList Struct Reference

Data Fields

- uint16_t numInstance
- nas_OperatorPLMNData PLMNData [255]

8.522.1 Detailed Description

This structure contains Operator PLMN List.

Parameters

numInstance	• Number of sets of the elements.
PLMNData	• Refer OperatorPLMNLData for details (Optional).

8.522.2 Field Documentation

8.522.2.1 uint16_t nas_operatorPLMNList::numInstance

8.522.2.2 nas_OperatorPLMNData nas_operatorPLMNList::PLMNData[255]

8.523 nas_PhyCaAggPcellInfo Struct Reference

Data Fields

- int pci
- int freq
- NAS_LTE_CPHY_CA_BW_NRB_LITE dl_bw_value
- int iLTEbandValue
- uint8_t TlvPresent

8.523.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Pcell Information.

Parameters

pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
dl_bw_value	• Downlink Bandwidth Values. • See NAS_LTE_CPHY_CA_BW_NRB_LITE for more information.
scell_state	• Scell state Values. • See NAS_LTE_CPHY_SCELL_STATE_LITE for more information.
TlvPresent	• Tlv Present.

8.523.2 Field Documentation

8.523.2.1 NAS_LTE_CPHY_CA_BW_NRB_LITE nas_PhyCaAggPcellInfo::dl_bw_value

8.523.2.2 int nas_PhyCaAggPcellInfo::freq

8.523.2.3 int nas_PhyCaAggPcellInfo::iLTEbandValue

8.523.2.4 int nas_PhyCaAggPcellInfo::pci

8.523.2.5 uint8_t nas_PhyCaAggPcellInfo::TlvPresent

8.524 nas_PhyCaAggScellDlBw Struct Reference

Data Fields

- NAS_LTE_CPHY_CA_BW_NRB_LITE dl_bw_value
- uint8_t TlvPresent

8.524.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation Downlink Bandwidth of Scell.

Parameters

dl_bw_value	• Downlink Bandwidth Values. • See NAS_LTE_CPHY_CA_BW_NRB_LITE for more information.

8.524.2 Field Documentation

8.524.2.1 NAS_LTE_CPHY_CA_BW_NRB_LITE nas_PhyCaAggScellDlBw::dl_bw_value

8.524.2.2 uint8_t nas_PhyCaAggScellDlBw::TlvPresent

8.525 nas_PhyCaAggScellIndex Struct Reference

Data Fields

- uint8_t scell_idx
- uint8_t TlvPresent

8.525.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Index.

Parameters

scell_idx	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.

TlvPresent	• Tlv Present.

8.525.2 Field Documentation

8.525.2.1 uint8_t nas_PhyCaAggScellIndex::scell_idx

8.525.2.2 uint8_t nas_PhyCaAggScellIndex::TlvPresent

8.526 nas_PhyCaAggScellIndType Struct Reference

Data Fields

- int pci
- int freq
- NAS_LTE_CPHY_SCELL_STATE_LITE scell_state
- uint8_t TlvPresent

8.526.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Indicator Type.

Parameters

pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
scell_state	• Scell state Values. • See NAS_LTE_CPHY_SCELL_STATE_LITE for more information.
TlvPresent	• Tlv Present.

8.526.2 Field Documentation

8.526.2.1 int nas_PhyCaAggScellIndType::freq

8.526.2.2 int nas_PhyCaAggScellIndType::pci

8.526.2.3 NAS_LTE_CPHY_SCELL_STATE_LITE nas_PhyCaAggScellIndType::scell_state

8.526.2.4 uint8_t nas_PhyCaAggScellIndType::TlvPresent

8.527 nas_PhyCaAggScellInfo Struct Reference

Data Fields

- int pci
- int freq
- NAS_LTE_CPHY_CA_BW_NRB_LITE dl_bw_value
- uint16_t iLTEbandValue
- NAS_LTE_CPHY_SCELL_STATE_LITE scell_state
- uint8_t TlvPresent

8.527.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Information.

Parameters

pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
dl_bw_value	• Downlink Bandwidth Values. • See NAS_LTE_CPHY_CA_BW_NRB_LITE for more information.

iLTEbandValue	• Band value. • Range for LTE Band class 120 to 160. – 120 - LTE E-UTRA Operating Band 1 – 121 - LTE E-UTRA Operating Band 2 – 122 - LTE E-UTRA Operating Band 3 – 123 - LTE E-UTRA Operating Band 4 – 124 - LTE E-UTRA Operating Band 5 – 125 - LTE E-UTRA Operating Band 6 – 126 - LTE E-UTRA Operating Band 7 – 127 - LTE E-UTRA Operating Band 8 – 128 - LTE E-UTRA Operating Band 9 – 129 - LTE E-UTRA Operating Band 10 – 130 - LTE E-UTRA Operating Band 11 – 131 - LTE E-UTRA Operating Band 12 – 132 - LTE E-UTRA Operating Band 13 – 133 - LTE E-UTRA Operating Band 14 – 134 - LTE E-UTRA Operating Band 17 – 135 - LTE E-UTRA Operating Band 33 – 136 - LTE E-UTRA Operating Band 34 – 137 - LTE E-UTRA Operating Band 35 – 138 - LTE E-UTRA Operating Band 36 – 139 - LTE E-UTRA Operating Band 37 – 140 - LTE E-UTRA Operating Band 38 – 141 - LTE E-UTRA Operating Band 39 – 142 - LTE E-UTRA Operating Band 40 – 143 - LTE E-UTRA Operating Band 18 – 144 - LTE E-UTRA Operating Band 19 – 145 - LTE E-UTRA Operating Band 20 – 146 - LTE E-UTRA Operating Band 21 – 147 - LTE E-UTRA Operating Band 24 – 148 - LTE E-UTRA Operating Band 25 – 149 - LTE E-UTRA Operating Band 41 – 150 - LTE E-UTRA Operating Band 42 – 151 - LTE E-UTRA Operating Band 43 – 152 - LTE E-UTRA Operating Band 23 – 153 - LTE E-UTRA Operating Band 26 – 154 - LTE E-UTRA Operating Band 32 – 155 - LTE E-UTRA Operating Band 125 – 156 - LTE E-UTRA Operating Band 126 – 157 - LTE E-UTRA Operating Band 127 – 158 - LTE E-UTRA Operating Band 28 – 159 - LTE E-UTRA Operating Band 29 – 160 - LTE E-UTRA Operating Band 30
scell_state	• Scell state Values. • See NAS_LTE_CPHY_SCELL_STATE_LITE for more information.

TlvPresent	• Tlv Present.

8.527.2 Field Documentation

8.527.2.1 NAS_LTE_CPHY_CA_BW_NRB_LITE nas_PhyCaAggScellInfo::dl_bw_value

8.527.2.2 int nas_PhyCaAggScellInfo::freq

8.527.2.3 uint16_t nas_PhyCaAggScellInfo::iLTEbandValue

8.527.2.4 int nas_PhyCaAggScellInfo::pci

8.527.2.5 NAS_LTE_CPHY_SCELL_STATE_LITE nas_PhyCaAggScellInfo::scell_state

8.527.2.6 uint8_t nas_PhyCaAggScellInfo::TlvPresent

8.528 nas_PilotSetData Struct Reference

Data Fields

- uint8_t NumPilots
- nas_PilotSetParams ∗ pPilotSetInfo

8.528.1 Detailed Description

This structure contains pilot sets data.

Parameters

NumPilots	• Number of Pilot Sets • As input specifies number of sets of parameter pPilotSetInfo for which memory has been assigned • As output specifies the actual number of sets of parameter pPilotSetInfo returned by device
pPilotSetInfo	• Pilot Set Parameters • See nas_PilotSetParams for more information.

note A buffer under sized error is returned if the number of sets of pPilotSetInfo returned by the device is greater than the value in NumPilots input parameter.

8.528.2 Field Documentation

8.528.2.1 uint8_t nas_PilotSetData::NumPilots

8.528.2.2 nas_PilotSetParams∗ nas_PilotSetData::pPilotSetInfo

8.529 nas_PilotSetParams Struct Reference

Data Fields

- uint32_t PilotType
- uint16_t PilotPN
- uint16_t PilotStrength

8.529.1 Detailed Description

This structure contains pilot sets parameters.

Parameters

PilotType	• 0x00 - NAS_HRPD_PILOT_CURR_ACT_PLT Current Active Pilot • 0x01 - NAS_HRPD_PILOT_NEIGHBOR_PLT Neighbor pilot information
PilotPN	• Pilot PN sequence offset index
PilotStrength	• Strength of the pilot (in dB)

8.529.2 Field Documentation

8.529.2.1 uint16_t nas_PilotSetParams::PilotPN

8.529.2.2 uint16_t nas_PilotSetParams::PilotStrength

8.529.2.3 uint32_t nas_PilotSetParams::PilotType

8.530 nas_PlmnID Struct Reference

Data Fields

- uint16_t mcc
- uint16_t mnc
- uint8_t pcsDigit
- uint8_t TlvPresent

8.530.1 Detailed Description

This structure contains PLMN ID information

Parameters

mcc	• A 16-bit integer representation of MCC. Range: 0 to 999
mnc	• A 16-bit integer representation of MNC. Range: 0 to 999

pcsDigit	• This field is used to interpret the length of the corresponding MNC reported in the TLVs (in this table) with an mnc or mobile_network_code field. Values: – TRUE - MNC is a three-digit value; for example, a reported value of 90 corresponds to an MNC value of 090 – FALSE - MNC is a two-digit value; for example, a reported value of 90 corresponds to an MNC value of 90
TlvPresent	• Tlv Present or not

8.530.2 Field Documentation

8.530.2.1 uint16_t nas_PlmnID::mcc

8.530.2.2 uint16_t nas_PlmnID::mnc

8.530.2.3 uint8_t nas_PlmnID::pcsDigit

8.530.2.4 uint8_t nas_PlmnID::TlvPresent

8.531 nas_PLMNNetworkName Struct Reference

Data Fields

- uint8_t numInstance
- nas_PLMNNetworkNameData PLMNNetName [255]

8.531.1 Detailed Description

This structure contains NITZ Information list.

Parameters

numInstance	• Number of sets of the elements.
PLMNNetName	• Refer nas_PLMNNetworkNameData for details (Optional).

8.531.2 Field Documentation

8.531.2.1 uint8_t nas_PLMNNetworkName::numInstance

8.531.2.2 nas_PLMNNetworkNameData nas_PLMNNetworkName::PLMNNetName[255]

8.532 nas_PLMNNetworkNameData Struct Reference

Data Fields

- uint8_t codingScheme
- uint8_t countryInitials
- uint8_t longNameSpareBits
- uint8_t shortNameSpareBits
- uint8_t longNameLen
- uint8_t longName [255]
- uint8_t shortNameLen
- uint8_t shortName [255]

8.532.1 Detailed Description

This structure contains NITZ Information.

Parameters

codingScheme	• Coding scheme: – 0 - CODING_SCHEME_CELL_BROADCAST_GSM - Cell broadcast data coding scheme, GSM default alphabet, language unspecified;defined in 3GPP TS 23.038. – 1 - CODING_SCHEME_UCS2 - UCS2 (16 bit);defined in ISO/IEC 10646
countryInitials	• Country's initials: – 0 - COUNTRY_INITIALS_DO_NOT_ADD - MS should not add the letters for the country's initials to the text string. – 1 - COUNTRY_INITIALS_ADD - MS should add the letters for the country's initials and a separator, e.g., a space, to the text string.
longNameSpare-Bits	• Long Name Spare Bits: – 1 - SPARE_BITS_8 - Bit 8 is spare and set to 0 in octet n – 2 - SPARE_BITS_7_TO_8 - Bits 7 and 8 are spare and set to 0 in octet n. – 3 - SPARE_BITS_6_TO_8 - Bits 6 to 8 (inclusive) are spare and set to 0 in octet n. – 4 - SPARE_BITS_5_TO_8 - Bits 5 to 8 (inclusive) are spare and set to 0 in octet n. – 5 - SPARE_BITS_4_TO_8 - Bits 4 to 8 (inclusive) are spare and set to 0 in octet n. – 6 - SPARE_BITS_3_TO_8 - Bits 3 to 8 (inclusive) are spare and set to 0 in octet n. – 7 - SPARE_BITS_2_TO_8 - Bits 2 to 8 (inclusive) are spare and set to 0 in octet n. – 0 - SPARE_BITS_UNKNOWN - Carries no information about the number of spare bits in octet n.
shortName-SpareBits	• Short Name Spare Bits: – 1 - SPARE_BITS_8 - Bit 8 is spare and set to 0 in octet n. – 2 - SPARE_BITS_7_TO_8 - Bits 7 and 8 are spare and set to 0 in octet n. – 3 - SPARE_BITS_6_TO_8 - Bits 6 to 8 (inclusive) are spare and set to 0 in octet n. – 4 - SPARE_BITS_5_TO_8 - Bits 5 to 8 (inclusive) are spare and set to 0 in octet n. – 5 - SPARE_BITS_4_TO_8 - Bits 4 to 8 (inclusive) are spare and set to 0 in octet n. – 6 - SPARE_BITS_3_TO_8 - Bits 3 to 8 (inclusive) are spare and set to 0 in octet n. – 7 - SPARE_BITS_2_TO_8 - Bits 2 to 8 (inclusive) are spare and set to 0 in octet n. – 0 - SPARE_BITS_UNKNOWN - Carries no information about the number of spare bits in octet n.

longNameLen	• It provides the length of long name.
longName	• Long name string in coding_scheme.
shortNameLen	• It provides the length of short name.
shortName	• Short name string in coding_scheme.

8.532.2 Field Documentation

8.532.2.1 uint8_t nas_PLMNNetworkNameData::codingScheme

8.532.2.2 uint8_t nas_PLMNNetworkNameData::countryInitials

8.532.2.3 uint8_t nas_PLMNNetworkNameData::longName[255]

8.532.2.4 uint8_t nas_PLMNNetworkNameData::longNameLen

8.532.2.5 uint8_t nas_PLMNNetworkNameData::longNameSpareBits

8.532.2.6 uint8_t nas_PLMNNetworkNameData::shortName[255]

8.532.2.7 uint8_t nas_PLMNNetworkNameData::shortNameLen

8.532.2.8 uint8_t nas_PLMNNetworkNameData::shortNameSpareBits

8.533 nas_PRLPrefTlv Struct Reference

Data Fields

- uint16_t PRLPref
- uint8_t TlvPresent

8.533.1 Detailed Description

Contain the PRL preference for system selection preferences.

Parameters

PRLPref	• Parameter indicating the CDMA PRL Preference • Values: – 0x0001 - Acquire available system only on the A side – 0x0002 - Acquire available system only on the B side – 0x3FFF - Acquire any available systems

TlvPresent	• Tlv Present

8.533.2 Field Documentation

8.533.2.1 uint16_t nas_PRLPrefTlv::PRLPref

8.533.2.2 uint8_t nas_PRLPrefTlv::TlvPresent

8.534 nas_protocolSubtypeElement Struct Reference

Data Fields

- uint16_t PhysicalLayer
- uint16_t ControlMac
- uint16_t AccessMac
- uint16_t ForwardMac
- uint16_t ReverseMac
- uint16_t KeyExchange
- uint16_t AuthProt
- uint16_t EncryptProt
- uint16_t SecProt
- uint16_t IdleState
- uint16_t MultDisc
- uint16_t VirtStream

8.534.1 Detailed Description

This structure contains protocol subtype element.

Parameters

PhysicalLayer	• Specifies Physical Layer Protocol subtype
ControlMac	• Specifies Control Channel MAC Protocol subtype
AccessMac	• Specifies Access Channel MAC Protocol subtype
ForwardMac	• Specifies Forward Traffic Channel MAC Protocol subtype
ReverseMac	• Specifies Reverse Traffic Channel MAC Protocol subtype
KeyExchange	• Specifies Key exchange Protocol subtype

AuthProt	• Specifies Authentication Protocol subtype
EncryptProt	• Specifies Encryption Protocol subtype
SecProt	• Specifies Security Protocol subtype
IdleState	• Specifies Idle state Protocol subtype
MultDisc	• Specifies Generic multimode capability discovery Protocol subtype
VirtStream	• Specifies Generic Virtual Stream Protocol subtype

8.534.2 Field Documentation

8.534.2.1 uint16_t nas_protocolSubtypeElement::AccessMac

8.534.2.2 uint16_t nas_protocolSubtypeElement::AuthProt

8.534.2.3 uint16_t nas_protocolSubtypeElement::ControlMac

8.534.2.4 uint16_t nas_protocolSubtypeElement::EncryptProt

8.534.2.5 uint16_t nas_protocolSubtypeElement::ForwardMac

8.534.2.6 uint16_t nas_protocolSubtypeElement::IdleState

8.534.2.7 uint16_t nas_protocolSubtypeElement::KeyExchange

8.534.2.8 uint16_t nas_protocolSubtypeElement::MultDisc

8.534.2.9 uint16_t nas_protocolSubtypeElement::PhysicalLayer

8.534.2.10 uint16_t nas_protocolSubtypeElement::ReverseMac

8.534.2.11 uint16_t nas_protocolSubtypeElement::SecProt

8.534.2.12 uint16_t nas_protocolSubtypeElement::VirtStream

8.535 nas_qaQmi3Gpp2TimeZone Struct Reference

Data Fields

- uint8_t leapSeconds
- uint8_t localTimeOffset
- uint8_t daylightSavings

8.535.1 Detailed Description

This structure contains the 3GPP2TimeZone parameters

Parameters

leapSeconds	• leap seconds - Number of leap seconds since the start of CDMA system time.
localTimeOffset	• Local Time Offset - Offset of system time in units of 30 minutes; the value in this field conveys as 8 bit 2's compliment number.
daylightSavings	• Day Light Savings Indicator – 0x00 - OFF (daylight savings not in effect) – 0x01 - ON (daylight savings in effect)

8.535.2 Field Documentation

8.535.2.1 uint8_t nas_qaQmi3Gpp2TimeZone::daylightSavings

8.535.2.2 uint8_t nas_qaQmi3Gpp2TimeZone::leapSeconds

8.535.2.3 uint8_t nas_qaQmi3Gpp2TimeZone::localTimeOffset

8.536 nas_QmiNas3GppNetworkInfo Struct Reference

Data Fields

- uint16_t MCC
- uint16_t MNC
- uint32_t InUse
- uint32_t Roaming
- uint32_t Forbidden
- uint32_t Preferred
- char Desription [255]

8.536.1 Detailed Description

Contain the 3GPP network information.

Parameters

MCC	• Mobile Country Code
MNC	• Mobile Network Code

InUse	• Is the Network the current serving Network – 0 - Unknown – 1 - Current serving network – 2 - Not current serving network, available
Roaming	• Home/Roam Status of the Network – 0 - Unknown – 1 - Home – 2 - Roam
Forbidden	• Is the Network in the forbidden network list – 0 - Unknown – 1 - Forbidden – 2 - Not Forbidden
Preferred	• Is the Network in the Preferred network list – 0 - Unknown – 1 - Preferred – 2 - Not Preferred
Description	• Network Name/Description • This is a NULL terminated string.

8.536.2 Field Documentation

8.536.2.1 char nas_QmiNas3GppNetworkInfo::Desription[255]

8.536.2.2 uint32_t nas_QmiNas3GppNetworkInfo::Forbidden

8.536.2.3 uint32_t nas_QmiNas3GppNetworkInfo::InUse

8.536.2.4 uint16_t nas_QmiNas3GppNetworkInfo::MCC

8.536.2.5 uint16_t nas_QmiNas3GppNetworkInfo::MNC

8.536.2.6 uint32_t nas_QmiNas3GppNetworkInfo::Preferred

8.536.2.7 uint32_t nas_QmiNas3GppNetworkInfo::Roaming

8.537 nas_QmiNas3GppNetworkRAT Struct Reference

Data Fields

- uint16_t MCC
- uint16_t MNC
- uint8_t RAT

8.537.1 Detailed Description

Contain the 3GPP radio access technology information.

Parameters

MCC	• Mobile Country Code
MNC	• Mobile Network Code
RAT	• Radio Access Technology – 0x04 - GERAN – 0x05 - UMTS – 0x08 - LTE – 0x09 - TD-SCDMA

8.537.2 Field Documentation

8.537.2.1 uint16_t nas_QmiNas3GppNetworkRAT::MCC

8.537.2.2 uint16_t nas_QmiNas3GppNetworkRAT::MNC

8.537.2.3 uint8_t nas_QmiNas3GppNetworkRAT::RAT

8.538 nas_QmisNasPcsDigit Struct Reference

Data Fields

- uint16_t MCC
- uint16_t MNC
- uint8_t includes_pcs_digit

8.538.1 Detailed Description

Contain the PCS Digit information

Parameters

MCC	• Mobile Country Code
MNC	• Mobile Network Code
includes_pcs_digit	• this field is use to interpret the length of corresponding MNC reported • 0x01 - MNC is a three-digit value • 0x00 - MNC is a two-digit value

8.538.2 Field Documentation

8.538.2.1 uint8_t nas_QmisNasPcsDigit::includes_pcs_digit

8.538.2.2 uint16_t nas_QmisNasPcsDigit::MCC

8.538.2.3 uint16_t nas_QmisNasPcsDigit::MNC

8.539 nas_QmisNasSlqsNasPCICellInfo Struct Reference

Data Fields

- uint32_t freq
- uint16_t cellID
- uint32_t GlobalCellID
- uint8_t PlmnLen
- nas_QmisNasPcsDigit nasQmisNasPcsDigit [255]

8.539.1 Detailed Description

Contain the PCI Cell Info.

Parameters

freq	• Aboslute cell's frequency. Range 0 to 65535.
cellID	• Cell ID.
GlobalCellID	• Global Cell ID.
PlmnLen	• Number of Plmn(nasQmisNasPcsDigit) information sets.
nasQmisNas-PcsDigit	• See nas_QmisNasPcsDigit for more information.

8.539.2 Field Documentation

8.539.2.1 uint16_t nas_QmisNasSlqsNasPCICellInfo::cellID

8.539.2.2 uint32_t nas_QmisNasSlqsNasPCICellInfo::freq

8.539.2.3 uint32_t nas_QmisNasSlqsNasPCICellInfo::GlobalCellID

8.539.2.4 nas_QmisNasPcsDigit nas_QmisNasSlqsNasPCICellInfo::nasQmisNasPcsDigit[255]

8.539.2.5 uint8_t nas_QmisNasSlqsNasPCICellInfo::PlmnLen

8.540 nas_QmisNasSlqsNasPCIInfo Struct Reference

Data Fields

- uint8_t PCICellInfoLen
- nas_QmisNasSlqsNasPCICellInfo nasQmisNasSlqsNasPCICellInfo [255]
- uint16_t rsrp
- uint16_t rsrpRx0
- uint16_t rsrpRx1
- uint16_t rsrq
- uint16_t rsrqRx0
- uint16_t rsrqRx1

8.540.1 Detailed Description

Contain the NAS Perform network scan PCI information

Parameters

PCICellInfoLen	• Number of PCI Cell Info(PCICellInfo) information sets.
nasQmisNas-SlqsNasPCICell-Info	• See nas_QmisNasSlqsNasPCICellInfo for more information.
rsrp	• Combined RSRP.
rsrpRx0	• Rx0 RSRP.
rsrpRx1	• Rx1 RSRP.
rsrq	• Combined RSRQ.
rsrqRx0	• Rx0 RSRQ.
rsrpRx1	• Rx1 RSRQ.

8.540.2 Field Documentation

8.540.2.1 nas_QmisNasSlqsNasPCICellInfo nas_QmisNasSlqsNasPCIInfo::nasQmisNasSlqsNasPCICellInfo[255]

8.540.2.2 uint8_t nas_QmisNasSlqsNasPCIInfo::PCICellInfoLen

8.540.2.3 uint16_t nas_QmisNasSlqsNasPCIInfo::rsrp

8.540.2.4 uint16_t nas_QmisNasSlqsNasPCIInfo::rsrpRx0

8.540.2.5 uint16_t nas_QmisNasSlqsNasPCIInfo::rsrpRx1

8.540.2.6 uint16_t nas_QmisNasSlqsNasPCIInfo::rsrq

8.540.2.7 uint16_t nas_QmisNasSlqsNasPCIInfo::rsrqRx0

8.540.2.8 uint16_t nas_QmisNasSlqsNasPCIInfo::rsrqRx1

8.541 nas_RankIndicatorTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t count0
- uint32_t count1

8.541.1 Detailed Description

Elements for Rank indicator TLV.

Parameters

TlvPresent	• value is 1 if TLV is present, otherwise 0
count0	• count of Rank1
count1	• count of Rank2

8.541.2 Field Documentation

8.541.2.1 uint32_t nas_RankIndicatorTlv::count0

8.541.2.2 uint32_t nas_RankIndicatorTlv::count1

8.541.2.3 uint8_t nas_RankIndicatorTlv::TlvPresent

8.542 nas_RatDisabledMaskTlv Struct Reference

Data Fields

- uint16_t ratDisabledMask
- uint8_t TlvPresent

8.542.1 Detailed Description

Contain the RAT disabled mask

Parameters

ratDisabledMask	• Bitmask representing the radio technologies that are disabled. • Bit values: – Bit 0 (0x01) - cdma2000 ® 1X – Bit 1 (0x02) - cdma2000 ® HRPD(1xEV-DO) – Bit 2 (0x04) - GSM – Bit 3 (0x08) - UMTS – Bit 4 (0x10) - LTE – Bit 5 (0x20) - TD-SCDMA – Bit 6 (0x40) - NR5G All unlisted bits are reserved for future use and the service point ignores them if used.
TlvPresent	• Tlv Present

8.542.2 Field Documentation

8.542.2.1 uint16_t nas_RatDisabledMaskTlv::ratDisabledMask

8.542.2.2 uint8_t nas_RatDisabledMaskTlv::TlvPresent

8.543 nas_RejectReasonTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t serviceDomain
- uint32_t rejectCause

8.543.1 Detailed Description

This structure contains paramaters reject reason.

Parameters

TlvPresent	indicating the presence of the TLV in the QMI ind
serviceDomain	service domain
rejectCause	cause of reject

8.543.2 Field Documentation

8.543.2.1 uint32_t nas_RejectReasonTlv::rejectCause

8.543.2.2 uint32_t nas_RejectReasonTlv::serviceDomain

8.543.2.3 uint8_t nas_RejectReasonTlv::TlvPresent

8.544 nas_RFBandInfoElements Struct Reference

Data Fields

- uint8_t radioInterface
- uint16_t activeBandClass
- uint16_t activeChannel

8.544.1 Detailed Description

This structure contains the RFBandInfo response parameters.

Parameters

radioInterface	• Radio interface technology – See Tables for Radio Interface
activeBandClass	• Active Band Class – See Tables for Band Classes
activeChannel	• Active channel (0 if channel is not relevant to the reported technology)

8.544.2 Field Documentation

8.544.2.1 uint16_t nas_RFBandInfoElements::activeBandClass

8.544.2.2 uint16_t nas_RFBandInfoElements::activeChannel

8.544.2.3 uint8_t nas_RFBandInfoElements::radioInterface

8.545 nas_RfBandInfoExtFormat Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t * pInstancesSize
- struct nas_RfBandInfoExtFormatElements * pRfBandInfoExtFormatParam

8.545.1 Detailed Description

This structure contains the nas_RfBandInfoExtFormat response parameters.

Parameters

TlvPresent	• Tlv Present
pInstancesSize[-IN/OUT]	• Number of sets of the RFBandInfoElements • Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.
pRfBandInfoExt-FormatParam	• See nas_RfBandInfoExtFormatElements for more information

8.545.2 Field Documentation

8.545.2.1 uint8_t* nas_RfBandInfoExtFormat::pInstancesSize

8.545.2.2 struct nas_RfBandInfoExtFormatElements* nas_RfBandInfoExtFormat::pRfBandInfoExtFormatParam

8.545.2.3 uint8_t nas_RfBandInfoExtFormat::TlvPresent

8.546 nas_RfBandInfoExtFormatElements Struct Reference

Data Fields

- uint8_t radioInterface
- uint16_t activeBand
- uint32_t activeChannel

8.546.1 Detailed Description

This structure contains the RF Band Information, Extended Format.

Parameters

radioInterface	• Radio interface technology – See Tables for Radio Interface
activeBand	• Active Band Class – See Tables for Band Classes
activeChannel	• Active channel (0 if channel is not relevant to the reported technology)

8.546.2 Field Documentation

8.546.2.1 uint16_t nas_RfBandInfoExtFormatElements::activeBand

8.546.2.2 uint32_t nas_RfBandInfoExtFormatElements::activeChannel

8.546.2.3 uint8_t nas_RfBandInfoExtFormatElements::radioInterface

8.547 nas_RfBandInfoList Struct Reference

Data Fields

- uint8_t * pInstanceSize
- struct nas_RFBandInfoElements * pRFBandInfoParam

8.547.1 Detailed Description

This structure contains the RfBandInfoList response parameters.

Parameters

pInstanceSize[IN/OUT]	• Number of sets of the RFBandInfoElements • Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.
pRFBandInfoParam	• See nas_RFBandInfoElements for more information

8.547.2 Field Documentation

8.547.2.1 uint8_t* nas_RfBandInfoList::pInstanceSize

8.547.2.2 struct nas_RFBandInfoElements* nas_RfBandInfoList::pRFBandInfoParam

8.548 nas_RfBandwidthInfo Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t * pInstancesSize
- struct nas_RfBandwidthInfoElements * pRfBandwidthInfoParam

8.548.1 Detailed Description

This structure contains the nas_RfBandwidthInfo response parameters.

Parameters

TlvPresent	• Tlv Present
pInstancesSize[IN/OUT]	• Number of sets of the RFBandInfoElements • Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.

pRfBandwidth-InfoParam	• See nas_RfBandwidthInfoElements for more information

8.548.2 Field Documentation

8.548.2.1 uint8_t* nas_RfBandwidthInfo::pInstancesSize

8.548.2.2 struct nas_RfBandwidthInfoElements* nas_RfBandwidthInfo::pRfBandwidthInfoParam

8.548.2.3 uint8_t nas_RfBandwidthInfo::TlvPresent

8.549 nas_RfBandwidthInfoElements Struct Reference

Data Fields

- uint8_t radioInterface
- uint32_t bandwidth

8.549.1 Detailed Description

This structure contains the RF Bandwidth Information List parameters.

Parameters

radioInterface	• Radio interface technology – See Tables for Radio Interface
bandwidth	• Bandwidth – Values * NAS_LTE_BW_NRB_6 (0) - LTE 1.4 MHz bandwidth * NAS_LTE_BW_NRB_15 (1) - LTE 3 MHz bandwidth * NAS_LTE_BW_NRB_25 (2) - LTE 5 MHz bandwidth * NAS_LTE_BW_NRB_50 (3) - LTE 10 MHz bandwidth * NAS_LTE_BW_NRB_75 (4) - LTE 15 MHz bandwidth * NAS_LTE_BW_NRB_100 (5) - LTE 20 MHz bandwidth * NAS_NR5G_BW_NRB_6 (6) - NR5G 1.4 MHz bandwidth * NAS_NR5G_BW_NRB_15 (7) - NR5G 3 MHz bandwidth * NAS_NR5G_BW_NRB_25 (8) - NR5G 5 MHz bandwidth * NAS_NR5G_BW_NRB_50 (9) - NR5G 10 MHz bandwidth * NAS_NR5G_BW_NRB_75 (10) - NR5G 15 MHz bandwidth * NAS_NR5G_BW_NRB_100 (11) - NR5G 20 MHz bandwidth

8.549.2 Field Documentation

8.549.2.1 uint32_t nas_RfBandwidthInfoElements::bandwidth

8.549.2.2 uint8_t nas_RfBandwidthInfoElements::radioInterface

8.550 nas_RfDedicatedBandInfo Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t * pInstancesSize
- struct nas_RfDedicatedBandInfoElements * pRfDedicatedBandInfoParam

8.550.1 Detailed Description

This structure contains the nas_RfDedicatedBandInfo response parameters.

Parameters

TlvPresent	• Tlv Present
pInstancesSize[-IN/OUT]	• Number of sets of the RFBandInfoElements • Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.
pRfDedicated-BandInfoParam	• See nas_RfDedicatedBandInfoElements for more information

8.550.2 Field Documentation

8.550.2.1 uint8_t* nas_RfDedicatedBandInfo::pInstancesSize

8.550.2.2 struct nas_RfDedicatedBandInfoElements* nas_RfDedicatedBandInfo::pRfDedicatedBandInfoParam

8.550.2.3 uint8_t nas_RfDedicatedBandInfo::TlvPresent

8.551 nas_RfDedicatedBandInfoElements Struct Reference

Data Fields

- uint8_t radioInterface
- uint16_t dedicatedBand

8.551.1 Detailed Description

This structure contains the RF Dedicated Band Info.

Parameters

radioInterface	• Radio interface technology – See Tables for Radio Interface

dedicatedBand	• Dedicated Band Class – See Tables for Band Classes

8.551.2 Field Documentation

8.551.2.1 uint16_t nas_RfDedicatedBandInfoElements::dedicatedBand

8.551.2.2 uint8_t nas_RfDedicatedBandInfoElements::radioInterface

8.552 nas_RFInfoTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t radioInterfaceSize
- uint32_t radioInterface [255]
- uint32_t activeBandClass [255]
- uint32_t activeChannel [255]

8.552.1 Detailed Description

This structure contains paramaters RF Band Information List.

Parameters

TlvPresent	indicating the presence of the TLV in the QMI ind
radioInterface-Size	Number of sets of the following elements • radioInterface • activeBandClass • activeChannel
radioInterface	radio interface technology of the signal being measured • 0x01 - cdma2000 1X • 0x02 - cdma2000 HRPD (1xEV-DO) • 0x03 - AMPS • 0x04 - GSM • 0x05 - UMTS • 0x08 - LTE • 0x09 - TD-SCDMA
activeBandClass	active band class • 00 to 39 - CDMA band classes • 40 to 79 - GSM band classes • 80 to 91 - WCDMA band classes • 120 to 160 - LTE band classes • 200 to 205 - TD-SCDMA band classes
activeChannel	active channel • Active channel. If the channel is not relevant to the technology, a value of 0 is returned.

8.552.2 Field Documentation

8.552.2.1 uint32_t nas_RFInfoTlv::activeBandClass[255]

8.552.2.2 uint32_t nas_RFInfoTlv::activeChannel[255]

8.552.2.3 uint32_t nas_RFInfoTlv::radioInterface[255]

8.552.2.4 uint8_t nas_RFInfoTlv::radioInterfaceSize

8.552.2.5 uint8_t nas_RFInfoTlv::TlvPresent

8.553 nas_roamIndList Struct Reference

Data Fields

- uint8_t numInstances
- uint8_t radioInterface [32]
- uint8_t roamIndicator [32]

8.553.1 Detailed Description

This structure contains the Roaming Indicator List

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

numInstances	• number of sets of radio interface currently in use and roaming indicator – defaults to zero
radioInterface	• Radio Interface currently in use • Values: – 0x01 - RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS – 0x08 - RADIO_IF_LTE - LTE
roamIndicator	• Roaming Indicator • Values: – 0x00 - Roaming – 0x01 - Home

8.553.2 Field Documentation

8.553.2.1 uint8_t nas_roamIndList::numInstances

8.553.2.2 uint8_t nas_roamIndList::radioInterface[32]

8.553.2.3 uint8_t nas_roamIndList::roamIndicator[32]

8.554 nas_RoamPrefTlv Struct Reference

Data Fields

- uint16_t RoamPref
- uint8_t TlvPresent

8.554.1 Detailed Description

Contain the roaming preference for system selection preferences.

Parameters

RoamPref	• Parameter indicating the roaming Preference • Values: – 0x01 - Acquire only systems for which the roaming indicator is off – 0x02 - Acquire a system as long as its roaming indicator is not off – 0x03 - Acquire only systems for which the roaming indicator is off or solid on, i.e. not flashing; CDMA only – 0xFF - Acquire systems, regardless of their roaming indicator
TlvPresent	• Tlv Present

8.554.2 Field Documentation

8.554.2.1 uint16_t nas_RoamPrefTlv::RoamPref

8.554.2.2 uint8_t nas_RoamPrefTlv::TlvPresent

8.555 nas_RSRPThresh Struct Reference

Data Fields

- uint8_t RSRPThresListLen
- int16_t * pRSRPThresList

8.555.1 Detailed Description

This structure contains RSRP threshold list.

Parameters

RSRPThresList-Len	• Length of the RSRP threshold list parameter to follow
pRSRPThresList	• Sequence of thresholds delimiting current RSRP event reporting bands • Every time a new RSRP value crosses a specified threshold value, an event report indication message with the new RSRQ value is sent to the requesting control point. For this field – RSRP values are applicable only for LTE – RSRP values are measured in dBm, with a range of -44 dBm to -140 dBm – Each RSRP threshold value is a signed byte value – Maximum number of threshold values is 16 – At least one value must be specified

8.555.2 Field Documentation

8.555.2.1 int16_t∗ nas_RSRPThresh::pRSRPThresList

8.555.2.2 uint8_t nas_RSRPThresh::RSRPThresListLen

8.556 nas_rsrqInformation Struct Reference

Data Fields

- int8_t rsrq
- uint8_t radioIf

8.556.1 Detailed Description

This structure contains the RSRQ Information

Parameters

rsrq	• RSRQ value in dB (signed integer value); valid range is -3 to -20 (-3 means -3 dB, -20 means -20 dB)
radioIf	• Radio interface technology of the signal being measured – 0x08 - LTE

8.556.2 Field Documentation

8.556.2.1 uint8_t nas_rsrqInformation::radioIf

8.556.2.2 int8_t nas_rsrqInformation::rsrq

8.557 nas_RSRQThresh Struct Reference

Data Fields

- uint8_t RSRQThresListLen
- int8_t * pRSRQThresList

8.557.1 Detailed Description

This structure contains RSRQ threshold list.

Parameters

RSRQThresList-Len	• Length of the RSRQ threshold list parameter to follow
pRSRQThresList	• Sequence of thresholds delimiting current RSRQ event reporting bands • Every time a new RSRQ value crosses a threshold value, an event report indication message with the new RSRQ value is sent to the requesting control point. For this field – RSRQ values are applicable only for LTE – RSRQ values are measured in dBm, with a range of -20 dBm to -3 dBm – Each RSRQ threshold value is a signed byte value – Maximum number of threshold values is 16 – At least one value must be specified

8.557.2 Field Documentation

8.557.2.1 int8_t* nas_RSRQThresh::pRSRQThresList

8.557.2.2 uint8_t nas_RSRQThresh::RSRQThresListLen

8.558 nas_RSSIThresh Struct Reference

Data Fields

- uint8_t RSSIThresListLen
- int8_t * pRSSIThresList

8.558.1 Detailed Description

This sturcture contain RSSI threshold list.

Parameters

RSSIThresList-Len	• Length of the RSSI threshold list parameter to follow
pRSSIThresList	• RSSI in dBm(signed bytes) • A value of -125 dBm or lower is used to indicate No Signal • RSSI values have the following ranges (in dBm) – CDMA is -105 to -21 – HDR is -118 to -13 – GSM is -111 to -48 – WCDMA is -121 to 0 – LTE is -120 to 0 • Threshold values specified above are used for all RATs • The maximum number of threshold values is 16, each a signed byte value.

8.558.2 Field Documentation

8.558.2.1 int8_t∗ nas_RSSIThresh::pRSSIThresList

8.558.2.2 uint8_t nas_RSSIThresh::RSSIThresListLen

8.559 nas_rxInfo Struct Reference

Data Fields

- uint8_t isRadioTuned
- int32_t rxPower
- int32_t ecio
- int32_t rscp
- int32_t rsrp
- uint32_t phase

8.559.1 Detailed Description

This structure contains rx radio infomation.

Parameters

isRadioTuned	• Whether Rx is tuned to a channel: – 0x00 - Not tuned – 0x01 - Tuned – 0xFF - Not Available • If the radio is tuned, instantaneous values are set for the signal information fields below. • If the radio is not tuned, or is delayed or invalid, the values are set depending on each technology.
rx_pwr	• Rx power value in 1/10 dbm resolution.

ecio	• ECIO in 1/10 dB; valid for CDMA, HDR, GSM, WCDMA, and LTE.
rscp	• Received signal code power in 1/10 dbm. • Valid for WCDMA.
rsrp	• Current reference signal received power in 1/10 dbm valid for LTE.
phase	• Phase in 1/100 degrees; valid for LTE. • When the phase is unknown, 0xFFFFFFFF is used.

8.559.2 Field Documentation

8.559.2.1 int32_t nas_rxInfo::ecio

8.559.2.2 uint8_t nas_rxInfo::isRadioTuned

8.559.2.3 uint32_t nas_rxInfo::phase

8.559.2.4 int32_t nas_rxInfo::rscp

8.559.2.5 int32_t nas_rxInfo::rsrp

8.559.2.6 int32_t nas_rxInfo::rxPower

8.560 nas_RxSigInfo Struct Reference

Data Fields

- uint8_t rxChainIndex
- uint8_t isRadioTuned
- int32_t rxPower
- int32_t rsrp

8.560.1 Detailed Description

This structure contains the parameters for Rx Signal Info.

Parameters

rxChainIndex	• Rx antenna path
	• Valid Values
	  – 0 - Primary Rx
	  – 1 - Diversity Rx

isRadioTuned	• Rx path is tuned to a channel or Not • Values – 0x00 - Not tuned – 0x01 - Tuned

Note

If the radio is tuned, the instantaneous values are set for the fields below. If the radio is not tuned, the values set below may be invalid.

Parameters

rxPower	• Rx power value in 1/10 dBm resolution
rsrp	• Current reference signal received power in 1/10 dBm resolution

8.560.2 Field Documentation

8.560.2.1 uint8_t nas_RxSigInfo::isRadioTuned

8.560.2.2 int32_t nas_RxSigInfo::rsrp

8.560.2.3 uint8_t nas_RxSigInfo::rxChainIndex

8.560.2.4 int32_t nas_RxSigInfo::rxPower

8.561 nas_rxSignalStrengthListElement Struct Reference

Data Fields

- int16_t rxSignalStrength
- uint8_t radioIf

8.561.1 Detailed Description

This structure contains the Received Signal Strength Information

Parameters

rxSignalStrength	• Received signal strength in dBm – For CDMA and UMTS, this indicates forward link pilotEc. – For GSM, the received signal strength. – For LTE, this indicates the total received wideband power observed by UE.

radioIf	• Radio interface technology of the signal being radio_if measured – 0x00 - RADIO_IF_NO_SVC - None (no service) – 0x01 - RADIO_IF_CDMA_1X - cdma2000® 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS – 0x08 - RADIO_IF_LTE - LTE

Note

First elemnet of the RSSI list always contains the current Signal strength and Radio Interface.

8.561.2 Field Documentation

8.561.2.1 uint8_t nas_rxSignalStrengthListElement::radioIf

8.561.2.2 int16_t nas_rxSignalStrengthListElement::rxSignalStrength

8.562 nas_SccRxInfo Struct Reference

Data Fields

- int32_t rsrq
- int16_t snr
- uint8_t numInstances
- nas_RxSigInfo sigInfo [255]
- uint8_t TlvPresent

8.562.1 Detailed Description

This structure contains information about the SccRxInfo parameters.

Parameters

rsrq	• Current reference signal • Receive quality in 1/10 dB resolution
snr	• Reference signal signal-to-noise ratio in dB. • Range -10 to 30
numInstances	• Number of sets of the following – rxChainIndex – isRadioTuned – rxPower – rsrp

sigInfo	• See nas_RxSigInfo for more information
TlvPresent	• Tlv Present.

8.562.2 Field Documentation

8.562.2.1 uint8_t nas_SccRxInfo::numInstances

8.562.2.2 int32_t nas_SccRxInfo::rsrq

8.562.2.3 nas_RxSigInfo nas_SccRxInfo::sigInfo[255]

8.562.2.4 int16_t nas_SccRxInfo::snr

8.562.2.5 uint8_t nas_SccRxInfo::TlvPresent

8.563 nas_serviceProviderName Struct Reference

Data Fields

- uint8_t displayCondition
- uint8_t spnLength
- uint8_t spn [255]

8.563.1 Detailed Description

This structure contains service provider name.

Parameters

displayCondition	• Display condition.
spnLength	• It provides length of spn.
spn	• Service provider name string must use: The SMS default 7-bit coded alphabet as defined in 3GPP TS 23.038 with bit 8 set to 9.

8.563.2 Field Documentation

8.563.2.1 uint8_t nas_serviceProviderName::displayCondition

8.563.2.2 uint8_t nas_serviceProviderName::spn[255]

8.563.2.3 uint8_t nas_serviceProviderName::spnLength

8.564 nas_servSystem Struct Reference

Data Fields

- uint8_t regState
- uint8_t csAttachState
- uint8_t psAttachState
- uint8_t selNetwork
- uint8_t numRadioInterfaces
- uint8_t radioInterface [32]

8.564.1 Detailed Description

This structure contains the Serving System parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

regState	• Registration state - Registration state of the mobile • Values: – 0 - Not Registered; mobile is not currently searching for a new network to provide service – 1 - Registered with a network – 2 - Not registered, but mobile is currently searching for a new network to provide service – 3 - Registration denied by visible network – 4 - Registration state is unknown
csAttachState	• CS Attach State - Circuit-switched domain attach state of the mobile • Values: – 0 - Unknown or not applicable – 1 - Attached – 2 - Detached
psAttachState	• PS Attach State - Packet-switched domain attach state of the mobile • Values: – 0 - Unknown or not applicable – 1 - Attached – 2 - Detached
selNetwork	• Selected Network - Type of selected radio access network • Values: – 0 - Unknown – 1 - 3GPP2 network – 2 - 3GPP network
numRadio-Interfaces	• In Use Radio Interfaces Number – Number of radio interfaces currently in use – defaults to zero

radioInterface	• Radio Interface currently in use • Values: – 0x00 - RADIO_IF_NO_SVC - None(no service) – 0x01 - RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS – 0x08 - RADIO_IF_LTE - LTE

8.564.2 Field Documentation

8.564.2.1 uint8_t nas_servSystem::csAttachState

8.564.2.2 uint8_t nas_servSystem::numRadioInterfaces

8.564.2.3 uint8_t nas_servSystem::psAttachState

8.564.2.4 uint8_t nas_servSystem::radioInterface[32]

8.564.2.5 uint8_t nas_servSystem::regState

8.564.2.6 uint8_t nas_servSystem::selNetwork

8.565 nas_sidNid Struct Reference

Data Fields

- uint16_t nid
- uint16_t sid

8.565.1 Detailed Description

This structure contains the parameters for SidNid Information

Parameters

nid	• Network ID
sid	• System ID

8.565.2 Field Documentation

8.565.2.1 uint16_t nas_sidNid::nid

8.565.2.2 uint16_t nas_sidNid::sid

8.566 nas_SignalStrengthTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- int8_t signalStrength
- uint32_t radioInterface

8.566.1 Detailed Description

This structure contains paramaters Signal Strength.

Parameters

TlvPresent	indicating the presence of the TLV in the QMI ind
signalStrength	signal strength
radioInterface	radio interface technology of the signal being measured

8.566.2 Field Documentation

8.566.2.1 uint32_t nas_SignalStrengthTlv::radioInterface

8.566.2.2 int8_t nas_SignalStrengthTlv::signalStrength

8.566.2.3 uint8_t nas_SignalStrengthTlv::TlvPresent

8.567 nas_SLQSSignalStrengthsIndReq Struct Reference

Data Fields

- uint8_t rxSignalStrengthDelta
- uint8_t ecioDelta
- uint8_t ioDelta
- uint8_t sinrDelta
- uint8_t rsrqDelta
- uint8_t ecioThresholdListLen
- int16_t ecioThresholdList [10]
- uint8_t sinrThresholdListLen
- uint8_t sinrThresholdList [5]
- uint16_t lteSnrDelta
- uint8_t lteRsrpDelta

8.567.1 Detailed Description

Structure for storing the input parameters passed for SLQSSetSignalStrengthsCallback by the user.

Parameters

rxSignal-StrengthDelta	• RSSI delta(in dBm) at which an event report indication, including the current RSSI, will be sent to the requesting control point.

ecioDelta	• ECIO delta at which an event report indication, ecioDelta including the current ECIO, will be sent to the requesting control point. • ECIO delta is an unsigned 1 byte value that increments in negative 0.5 dBm, e.g., ecio_delta of 2 means a change of -1 dBm.
ioDelta	• IO delta (in dBm) at which an event report indication, ioDelta including the current IO, will be sent to the requesting control point.
sinrDelta	• SINR delta level at which an event report indication, sinrDelta including the current SINR, will be sent to the requesting control point.
rsrqDelta	• RSRQ delta level at which an event report indication, including the current RSRQ, will be sent to the requesting control point.
ecioThreshold-ListLen	• Number of elements in the ECIO threshold list.
ecioThreshold-List	• A sequence of thresholds delimiting Ecio event reporting bands. Every time a new Ecio value crosses a threshold value, an event report indication message with the new ECIO value is sent to the requesting control point. For this field: – Maximum number of threshold values is 10 – At least one value must be specified.
sinrThreshold-ListLen	• Number of elements in the SINR threshold list.
sinrThreshold-List	• A sequence of thresholds delimiting SINR event reporting bands. Every time a new SINR value crosses a threshold value, an event report indication message with the new sinr value is sent to the requesting control point. For this field: – Maximum number of threshold values is 5 – At least one value must be specified.
ltesnrdelta	• LTE SNR delta level at which an event report indication, including the current SNR, will be sent to the requesting control point. LTE SNR delta level is an unsigned 2 byte value, representing the delta in units of 0.1 dB, e.g., lte_snr_delta of 3 means a change 0.3dB.
ltersrpdelta	-LTE RSRP delta level at which an event report -indication, including the current RSRP, will be sent -to the requesting control point. LTE RSRP delta -level is an unsigned 1 byte value, representing the -delta in dB.

8.567.2 Field Documentation

8.567.2.1 uint8_t nas_SLQSSignalStrengthsIndReq::ecioDelta

8.567.2.2 int16_t nas_SLQSSignalStrengthsIndReq::ecioThresholdList[10]

8.567.2.3 uint8_t nas_SLQSSignalStrengthsIndReq::ecioThresholdListLen

8.567.2.4 uint8_t nas_SLQSSignalStrengthsIndReq::ioDelta

8.567.2.5 uint8_t nas_SLQSSignalStrengthsIndReq::lteRsrpDelta

8.567.2.6 uint16_t nas_SLQSSignalStrengthsIndReq::lteSnrDelta

8.567.2.7 uint8_t nas_SLQSSignalStrengthsIndReq::rsrqDelta

8.567.2.8 uint8_t nas_SLQSSignalStrengthsIndReq::rxSignalStrengthDelta

8.567.2.9 uint8_t nas_SLQSSignalStrengthsIndReq::sinrDelta

8.567.2.10 uint8_t nas_SLQSSignalStrengthsIndReq::sinrThresholdList[5]

8.567.2.11 uint8_t nas_SLQSSignalStrengthsIndReq::sinrThresholdListLen

8.568 nas_SLQSSignalStrengthsInformation Struct Reference

Data Fields

- nas_rxSignalStrengthListElement rxSignalStrengthInfo
- nas_ecioListElement ecioInfo
- uint32_t io
- uint8_t sinr
- nas_errorRateListElement errorRateInfo
- nas_rsrqInformation rsrqInfo
- nas_lteSnrinformation lteSnrinfo
- nas_lteRsrpinformation lteRsrpinfo

8.568.1 Detailed Description

This structure contains paramaters signal strengths information.

Parameters

rxSignal-StrengthInfo	• signal strength info list • Bit to check in ParamPresenceMask - **19**
ecioInfo	• ecio info list • Bit to check in ParamPresenceMask - **20**
io	• received IO in dBm; IO is only applicable for 1xEV-DO • Bit to check in ParamPresenceMask - **21**
sinr	• SINR level • Bit to check in ParamPresenceMask - **22**

errorRateInfo	• error rate info • Bit to check in ParamPresenceMask - **23**
rsrqInfo	• rsrq info • Bit to check in ParamPresenceMask - **24**
lteSnrinfo	• lte Snr information • Bit to check in ParamPresenceMask - **25**
lteRsrpinfo	• lte rsrp info • Bit to check in ParamPresenceMask - **26**

8.568.2 Field Documentation

8.568.2.1 nas_ecioListElement nas_SLQSSignalStrengthsInformation::ecioInfo

8.568.2.2 nas_errorRateListElement nas_SLQSSignalStrengthsInformation::errorRateInfo

8.568.2.3 uint32_t nas_SLQSSignalStrengthsInformation::io

8.568.2.4 nas_lteRsrpinformation nas_SLQSSignalStrengthsInformation::lteRsrpinfo

8.568.2.5 nas_lteSnrinformation nas_SLQSSignalStrengthsInformation::lteSnrinfo

8.568.2.6 nas_rsrqInformation nas_SLQSSignalStrengthsInformation::rsrqInfo

8.568.2.7 nas_rxSignalStrengthListElement nas_SLQSSignalStrengthsInformation::rxSignalStrengthInfo

8.568.2.8 uint8_t nas_SLQSSignalStrengthsInformation::sinr

8.569 nas_SLQSSignalStrengthsTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- nas_SLQSSignalStrengthsInformation sSLQSSignalStrengthsInfo

8.569.1 Detailed Description

This structure contains paramaters SLQS Signal Strength.

Parameters

TlvPresent	indicating the presence of the TLV in the QMI ind
sSLQSSignal-StrengthsInfo	signal strength info

8.569.2 Field Documentation

8.569.2.1 nas_SLQSSignalStrengthsInformation nas_SLQSSignalStrengthsTlv::sSLQSSignalStrengthsInfo

8.569.2.2 uint8_t nas_SLQSSignalStrengthsTlv::TlvPresent

8.570 nas_SrvDomainPrefTlv Struct Reference

Data Fields

- uint32_t SrvDomainPref
- uint8_t TlvPresent

8.570.1 Detailed Description

Contain the Service domain Preference for system selection preferences.

Parameters

SrvDomainPref	• Parameter indicating Service domain preference • Values: – 0x00 - Circuit switched only – 0x01 - Packet switched only – 0x02 - Circuit switched and packet switched – 0x03 - Packet switched attach – 0x04 - Packet switched detach
TlvPresent	• Tlv Present

8.570.2 Field Documentation

8.570.2.1 uint32_t nas_SrvDomainPrefTlv::SrvDomainPref

8.570.2.2 uint8_t nas_SrvDomainPrefTlv::TlvPresent

8.571 nas_SrvStatusInfo Struct Reference

Data Fields

- uint8_t srvStatus
- uint8_t isPrefDataPath

8.571.1 Detailed Description

Structure for storing the service status information for CDMA and HDR networks.

Parameters

srvStatus	• Service status of the system. – 0x00 - No service – 0x01 - Limited service – 0x02 - Service – 0x03 - Limited regional service – 0x04 - Power save – 0xFF - Not Available
isPrefDataPath	• Whether the RAT is the preferred data path. – 0x00 - Not preferred – 0x01 - Preferred – 0xFF - Not Available

8.571.2 Field Documentation

8.571.2.1 uint8_t nas_SrvStatusInfo::isPrefDataPath

8.571.2.2 uint8_t nas_SrvStatusInfo::srvStatus

8.572 nas_sysInfoCommon Struct Reference

Data Fields

- uint8_t srvDomainValid
- uint8_t srvDomain
- uint8_t srvCapabilityValid
- uint8_t srvCapability
- uint8_t roamStatusValid
- uint8_t roamStatus
- uint8_t isSysForbiddenValid
- uint8_t isSysForbidden

8.572.1 Detailed Description

Structure for storing the System Information common to CDMA, HDR, GSM, WCDMA and LTE networks.

Parameters

srvDomainValid	• Indicates whether the service domain is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

srvDomain	• Service domain registered on the system. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available
srvCapability-Valid	• Indicates whether the service capability is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
srvCapability	• Current system's service capability. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available
roamStatusValid	• Indicates whether the roaming status is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

roamStatus	• Current roaming status. – 0x00 - Off – 0x01 - On – 0x02 - Blinking – 0x03 - Out of the neighborhood – 0x04 - Out of the building – 0x05 - Preferred system – 0x06 - Available system – 0x07 - Alliance partner – 0x08 - Premium partner – 0x09 - Full service – 0x0A - Partial service – 0x0B - Banner is on – 0x0C - Banner is off – 0x0D to 0x3F - Reserved for Standard Enhanced Roaming Indicator Numbers – 0x40 to 0x7F - Reserved for Non-Standard Enhanced Roaming Indicator Numbers – 0x40 to 0xFF - Reserved. – 0xFF - Not Available • Values from 0x02 onward are only applicable for 3GPP2
isSysForbidden-Valid	• Indicates whether the forbidden system is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
isSysForbidden	• Whether the system is forbidden. – 0x00 - Not forbidden – 0x01 - Forbidden – 0xFF - Not Available

8.572.2 Field Documentation

8.572.2.1 uint8_t nas_sysInfoCommon::isSysForbidden

8.572.2.2 uint8_t nas_sysInfoCommon::isSysForbiddenValid

8.572.2.3 uint8_t nas_sysInfoCommon::roamStatus

8.572.2.4 uint8_t nas_sysInfoCommon::roamStatusValid

8.572.2.5 uint8_t nas_sysInfoCommon::srvCapability

8.572.2.6 uint8_t nas_sysInfoCommon::srvCapabilityValid

8.572.2.7 uint8_t nas_sysInfoCommon::srvDomain

8.572.2.8 uint8_t nas_sysInfoCommon::srvDomainValid

8.573 nas_TDSCDMAECIOThresh Struct Reference

Data Fields

- uint8_t TDSCDMAECIOThreshListLen
- float * pTDSCDMAECIOThreshList

8.573.1 Detailed Description

This structure contains TDSCDMA ECIO threshold related parameters.

Parameters

TDSCDMAECIOThreshListLen	• Length of the TDSCDMA ECIO threshold list parameter to follow
pTDSCDMAECIOThreshList	• Array of ECIO thresholds (in dB) used by TD-SCDMA • Maximum of 32 values.

8.573.2 Field Documentation

8.573.2.1 float* nas_TDSCDMAECIOThresh::pTDSCDMAECIOThreshList

8.573.2.2 uint8_t nas_TDSCDMAECIOThresh::TDSCDMAECIOThreshListLen

8.574 nas_TDSCDMARSCPThresh Struct Reference

Data Fields

- uint8_t TDSCDMARSCPThreshListLen
- int16_t * pTDSCDMARSCPThreshList

8.574.1 Detailed Description

This structure contains TDSCDMA RSCP threshold related parameters.

Parameters

TDSCDMARSCPThreshListLen	• Length of the TDSCDMA RSCP threshold list parameter to follow
pTDSCDMARSCPThreshList	• Array of RSCP thresholds (in units of 0.1 dBm) • Maximum of 32 values • Range for RSCP values: -120 to -25 (in dBm).

8.574.2 Field Documentation

8.574.2.1 int16_t* nas_TDSCDMARSCPThresh::pTDSCDMARSCPThreshList

8.574.2.2 uint8_t nas_TDSCDMARSCPThresh::TDSCDMARSCPThreshListLen

8.575 nas_TDSCDMARSSIThresh Struct Reference

Data Fields

- uint8_t TDSCDMARSSIThreshListLen
- float * pTDSCDMARSSIThreshList

8.575.1 Detailed Description

This structure contains TDSCDMA RSSI threshold related parameters.

Parameters

TDSCDMARSSIThreshListLen	• Length of the TDSCDMA RSSI threshold list parameter to follow
pTDSCDMARSSIThreshList	• Array of RSSI thresholds (in dBm) used by TD-SCDMA • Maximum of 32 values.

8.575.2 Field Documentation

8.575.2.1 float* nas_TDSCDMARSSIThresh::pTDSCDMARSSIThreshList

8.575.2.2 uint8_t nas_TDSCDMARSSIThresh::TDSCDMARSSIThreshListLen

8.576 nas_TDSCDMASINRCONFThresh Struct Reference

Data Fields

- uint8_t TDSCDMASINRCONFThreshListLen
- float * pTDSCDMASINRCONFThreshList

8.576.1 Detailed Description

This structure contains TDSCDMA SINR threshold list.

Parameters

TDSCDMASINRCONFThreshListLen	• Length of the TDSCDMA SINR threshold list parameter to follow
pTDSCDMASINRCONFThreshList	• Array of SINR thresholds (in dB) used by TD-SCDMA • Maximum of 32 values

8.576.2 Field Documentation

8.576.2.1 float∗ nas_TDSCDMASINRCONFThresh::pTDSCDMASINRCONFThreshList

8.576.2.2 uint8_t nas_TDSCDMASINRCONFThresh::TDSCDMASINRCONFThreshListLen

8.577 nas_TDSCDMASINRThresh Struct Reference

Data Fields

- uint8_t TDSCDMASINRThreshListLen
- float ∗ pTDSCDMASINRThreshList

8.577.1 Detailed Description

This structure contains TDSCDMA SINR threshold related parameters.

Parameters

TDSCDMASINRThreshListLen	• Length of the TDSCDMA SINR threshold list parameter to follow
pTDSCDMASINRThreshList	• Array of SINR thresholds (in dB) used by TD-SCDMA • Maximum of 32 values

8.577.2 Field Documentation

8.577.2.1 float∗ nas_TDSCDMASINRThresh::pTDSCDMASINRThreshList

8.577.2.2 uint8_t nas_TDSCDMASINRThresh::TDSCDMASINRThreshListLen

8.578 nas_timeInfo Struct Reference

Data Fields

- uint16_t year
- uint8_t month
- uint8_t day
- uint8_t hour
- uint8_t minute
- uint8_t second
- uint8_t dayOfWeek
- int8_t timeZone
- uint8_t dayLtSavingAdj
- uint8_t radioInterface
- uint8_t TlvPresent

8.578.1 Detailed Description

This structure contains the parameters for Network Time.

Parameters

year	• Year
month	• Month • 1 is January and 12 is December
day	• Day • Range - 1 to 31
hour	• Hour • Range - 0 to 59
minute	• Minute • Range - 0 to 59
second	• Second • Range - 0 to 59
dayOfWeek	• Day of the week • 0 is Monday and 6 is Sunday
timeZone	• Offset from Universal time • The difference between local time and Universal time, in increments of 15 min • Signed Value
dayLtSavingAdj	• Daylight saving adjustment in hours • Possible values - 0, 1, and 2. • This field is ignored if radio_if is NAS_RADIO_IF_CDMA_1XEVDO
radioInterface	• Radio interface from which the information comes • Values – 0x01 - NAS_RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE – 0x09 - NAS_RADIO_IF_TDSCDMA -TD-SCDMA
TlvPresent	• Tlv Present.

8.578.2 Field Documentation

8.578.2.1 uint8_t nas_timeInfo::day

8.578.2.2 uint8_t nas_timeInfo::dayLtSavingAdj

8.578.2.3 uint8_t nas_timeInfo::dayOfWeek

8.578.2.4 uint8_t nas_timeInfo::hour

8.578.2.5 uint8_t nas_timeInfo::minute

8.578.2.6 uint8_t nas_timeInfo::month

8.578.2.7 uint8_t nas_timeInfo::radioInterface

8.578.2.8 uint8_t nas_timeInfo::second

8.578.2.9 int8_t nas_timeInfo::timeZone

8.578.2.10 uint8_t nas_timeInfo::TlvPresent

8.578.2.11 uint16_t nas_timeInfo::year

8.579 nas_trueIMSI Struct Reference

Data Fields

- uint8_t mccT [3]
- uint16_t imsiT1112
- uint8_t imsiTS1 [7]
- uint8_t imsiTS2 [3]
- uint8_t imsiTaddrNum

8.579.1 Detailed Description

This structure contains True IMSI.

Parameters

mccT	• ASCII character representation of MCC_T
imsiT1112	• ASCII character representation of IMSI_T_11_12 value – 0xFFFF - Not Available
imsiTS1	• ASCII character representation of IMSI_T_S1 value
imsiTS2	• ASCII character representation of IMSI_T_S2 value

imsiTaddrNum	• Value of IMSI_T_ADDR_NUM – 0xFF - Not Available

8.579.2 Field Documentation

8.579.2.1 uint16_t nas_truelMSI::imsiT1112

8.579.2.2 uint8_t nas_truelMSI::imsiTaddrNum

8.579.2.3 uint8_t nas_truelMSI::imsiTS1[7]

8.579.2.4 uint8_t nas_truelMSI::imsiTS2[3]

8.579.2.5 uint8_t nas_truelMSI::mccT[3]

8.580 nas_txInfo Struct Reference

Data Fields

- uint8_t isInTraffic
- int32_t txPower

8.580.1 Detailed Description

This structure contains tx radio infomation.

Parameters

isInTraffic	• Whether the device is in traffic. – 0x00 - not in traffic – 0x01 - in traffic • The txPower field is only meaningful when in the device is in traffic.
txPower	• Tx power value in 1/10 dbm.

8.580.2 Field Documentation

8.580.2.1 uint8_t nas_txInfo::isInTraffic

8.580.2.2 int32_t nas_txInfo::txPower

8.581 nas_UMTSInfo Struct Reference

Data Fields

- uint16_t cellID

- uint8_t plmn [3]
- uint16_t lac
- uint16_t uarfcn
- uint16_t psc
- int16_t rscp
- int16_t ecio
- uint8_t umtsInst
- nas_UMTSinstInfo UMTSInstInfo [255]
- uint8_t geranInst
- nas_geranInstInfo GeranInstInfo [255]

8.581.1 Detailed Description

This structure contains information about the UMTS Network.

Parameters

cellID	• Cell ID. • 0xFFFFFFFF indicates cell ID information is not present.
plmn[NAS_PLMN_LENGTH]	• MCC/MNC information coded as octet 3, 4, and 5. • This field is ignored when nmrCellID is not present.
lac	• Location area code. • This field is ignored when nmrCellID is not present. – 0xFFFF - Not Available
uarfcn	• UTRA absolute RF channel number. – 0xFFFF - Not Available
psc	• Primary scrambling code. – 0xFFFF - Not Available
rscp	• Received signal code power. – 0xFFFF - Not Available
ecio	• ECIO(Signal-to-Interference-ratio). – 0xFFFF - Not Available
umtsInst	• Provides the number of set of UMTS info instances. • If 0(zero), then no information follows it.
UMTSInstInfo[NAS_MAX_DESCRIPTION_LENGTH]	• See nas_UMTSinstInfo for more information.

geranInst	• Provides the number of set of GERAN info instances. • If 0(zero), then no information follows it.
GeranInstInfo[NAS_MAX_DESCRIPTION_LENGTH]	• See nas_geranInstInfo for more information.

8.581.2 Field Documentation

8.581.2.1 uint16_t nas_UMTSInfo::cellID

8.581.2.2 int16_t nas_UMTSInfo::ecio

8.581.2.3 uint8_t nas_UMTSInfo::geranInst

8.581.2.4 nas_geranInstInfo nas_UMTSInfo::GeranInstInfo[255]

8.581.2.5 uint16_t nas_UMTSInfo::lac

8.581.2.6 uint8_t nas_UMTSInfo::plmn[3]

8.581.2.7 uint16_t nas_UMTSInfo::psc

8.581.2.8 int16_t nas_UMTSInfo::rscp

8.581.2.9 uint16_t nas_UMTSInfo::uarfcn

8.581.2.10 uint8_t nas_UMTSInfo::umtsInst

8.581.2.11 nas_UMTSinstInfo nas_UMTSInfo::UMTSInstInfo[255]

8.582 nas_UMTSinstInfo Struct Reference

Data Fields

- uint16_t umtsUarfcn
- uint16_t umtsPsc
- int16_t umtsRscp
- int16_t umtsEcio

8.582.1 Detailed Description

This structure contains information about the UMTS Instances in UMTS Network.

Parameters

umtsUarfcn	• UTRA absolute RF channel number.
umtsPsc	• Primary scrambling code.

umtsRscp	• Received signal code power.
umtsEcio	• ECIO(Signal-to-Interference-ratio).

8.582.2 Field Documentation

8.582.2.1 int16_t nas_UMTSinstInfo::umtsEcio

8.582.2.2 uint16_t nas_UMTSinstInfo::umtsPsc

8.582.2.3 int16_t nas_UMTSinstInfo::umtsRscp

8.582.2.4 uint16_t nas_UMTSinstInfo::umtsUarfcn

8.583 nas_umtsLTENbrCell Struct Reference

Data Fields

- uint16_t earfcn
- uint16_t pci
- uint32_t rsrp
- uint32_t rsrq
- int16_t srxlev
- uint8_t cellIsTDD

8.583.1 Detailed Description

This structure contains information about the UMTS LTE neighbour Cell.

Parameters

earfcn	• E-UTRA absolute RF channel number of the detected cell.
pci	• Physical cell ID of the detected cell. • Range is defined in 3GPP TS 36.211
rsrp	• Current received signal strength indication (in dBm) of the detected cell.
rsrq	• Current reference signal received quality (in dB) of the detected cell.
srxlev	• Cell selection Rx level (Srxlev) value of the detected cell in linear scale. • This field is only valid when wcdma_rrc_state is not NAS_WCDMA_RRC_STATE_CEL_FACH or NAS_WCDMA_RRC_STATE_CELL_DCH.

cellIsTDD	• TRUE if the cell is TDD; FALSE if the cell is FDD.

8.583.2 Field Documentation

8.583.2.1 uint8_t nas_umtsLTENbrCell::cellIsTDD

8.583.2.2 uint16_t nas_umtsLTENbrCell::earfcn

8.583.2.3 uint16_t nas_umtsLTENbrCell::pci

8.583.2.4 uint32_t nas_umtsLTENbrCell::rsrp

8.583.2.5 uint32_t nas_umtsLTENbrCell::rsrq

8.583.2.6 int16_t nas_umtsLTENbrCell::srxlev

8.584 nas_UniversalTime Struct Reference

Data Fields

- uint16_t year
- uint8_t month
- uint8_t day
- uint8_t hour
- uint8_t minute
- uint8_t second
- uint8_t dayOfWeek

8.584.1 Detailed Description

This structure contains the parameters for Universal Time Information.

Parameters

year	• Year.
month	• Month. – 1 is January and 12 is December.
day	• Day. – Range 1 to 31.
hour	• Hour. – Range 0 to 59.

minute	• Minute. – Range 0 to 59.
second	• Second. – Range 0 to 59.
dayOfWeek	• Day of the Week. – 0 is Monday and 6 is Sunday.

8.584.2 Field Documentation

8.584.2.1 uint8_t nas_UniversalTime::day

8.584.2.2 uint8_t nas_UniversalTime::dayOfWeek

8.584.2.3 uint8_t nas_UniversalTime::hour

8.584.2.4 uint8_t nas_UniversalTime::minute

8.584.2.5 uint8_t nas_UniversalTime::month

8.584.2.6 uint8_t nas_UniversalTime::second

8.584.2.7 uint16_t nas_UniversalTime::year

8.585 nas_wcdmaCellInfo Struct Reference

Data Fields

- uint16_t psc
- int16_t cpich_rscp
- int16_t cpich_ecno
- int16_t srxlev

8.585.1 Detailed Description

This structure contains information about the WCDMA Cell.

Parameters

psc	• Primary scrambling code. • Range: 0 to 511.
cpich_rscp	• Absolute power level (in 1/10 dBm) of the common pilot channel as received by the UE. • Range: -120.0 dBm to -25.0 dBm

cpich_ecno	• CPICH Ec/No; ratio (in 1/10 dB) of the received energy per PN chip for the CPICH to the total received power spectral density at the UE antenna connector. • Range: -50.0 dB to 0.
srxlev	• Cell selection Rx level (Srxlev) value. • Range: -128 to 128. • This field is only valid when ue_in_idle is TRUE.

8.585.2 Field Documentation

8.585.2.1 int16_t nas_wcdmaCellInfo::cpich_ecno

8.585.2.2 int16_t nas_wcdmaCellInfo::cpich_rscp

8.585.2.3 uint16_t nas_wcdmaCellInfo::psc

8.585.2.4 int16_t nas_wcdmaCellInfo::srxlev

8.586 nas_WCDMAECIOThresh Struct Reference

Data Fields

- uint8_t WCDMAECIOThreshListLen
- int16_t * pWCDMAECIOThreshList

8.586.1 Detailed Description

This structure contains WCDMA ECIO threshold related parameters.

Parameters

WCDMAECIO-ThreshListLen	• Length of the WCDMA ECIO threshold list parameter to follow
pWCDMAECIO-ThreshList	• Array of ECIO thresholds (in units of 0.1 dB) • Maximum of 32 values • Range for ECIO values: -31.5 to 0 (in dB)

8.586.2 Field Documentation

8.586.2.1 int16_t* nas_WCDMAECIOThresh::pWCDMAECIOThreshList

8.586.2.2 uint8_t nas_WCDMAECIOThresh::WCDMAECIOThreshListLen

8.587 nas_WCDMAInfoLTENeighborCell Struct Reference

Data Fields

- uint32_t wcdmaRRCState
- uint8_t umtsLTENbrCellLen
- nas_umtsLTENbrCell UMTSLTENbrCell [255]

8.587.1 Detailed Description

This structure contains information about the WCDMA - LTE Neighboring Cell Info Set.

Parameters

wcdmaRRC-State	• WCDMA RRC states. • Defined in 3GPP TS 25.331 • Values: – 0x00 - NAS_WCDMA_RRC_STATE_DISCONNECTED * WCDMA RRC State is IDLE – 0x01 - NAS_WCDMA_RRC_STATE_CELL_PCH * WCDMA RRC state is CELL_PCH – 0x02 - NAS_WCDMA_RRC_STATE_URA_PCH * WCDMA RRC state is URA_PCH – 0x03 - NAS_WCDMA_RRC_STATE_CELL_FACH * WCDMA RRC state is CELL_FACH – 0x04 - NAS_WCDMA_RRC_STATE_CELL_DCH * WCDMA RRC state is CELL_DCH
umtsLTENbr-CellLen	• Number of sets of UMTS LTE Neighbors.
UMTSLTENbr-Cell	• See nas_umtsLTENbrCell for more information.

8.587.2 Field Documentation

8.587.2.1 nas_umtsLTENbrCell nas_WCDMAInfoLTENeighborCell::UMTSLTENbrCell[255]

8.587.2.2 uint8_t nas_WCDMAInfoLTENeighborCell::umtsLTENbrCellLen

8.587.2.3 uint32_t nas_WCDMAInfoLTENeighborCell::wcdmaRRCState

8.588 nas_WCDMARSSIThresh Struct Reference

Data Fields

- uint8_t WCDMARSSIThreshListLen
- int16_t * pWCDMARSSIThreshList

8.588.1 Detailed Description

This structure contains WCDMA RSSI threshold related parameters.

Parameters

WCDMARSSI-ThreshListLen	• Length of the WCDMA RSSI threshold list parameter to follow
pWCDMARSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • Maximum of 32 values. • Range for RSSI values: -121 to 0 (in dBm)

8.588.2 Field Documentation

8.588.2.1 int16_t* nas_WCDMARSSIThresh::pWCDMARSSIThreshList

8.588.2.2 uint8_t nas_WCDMARSSIThresh::WCDMARSSIThreshListLen

8.589 nas_WCDMASysInfo Struct Reference

Data Fields

- nas_sysInfoCommon sysInfoWCDMA
- uint8_t lacValid
- uint16_t lac
- uint8_t cellIdValid
- uint32_t cellId
- uint8_t regRejectInfoValid
- uint8_t rejectSrvDomain
- uint8_t rejCause
- uint8_t networkIdValid
- uint8_t MCC [3]
- uint8_t MNC [3]
- uint8_t hsCallStatusValid
- uint8_t hsCallStatus
- uint8_t hsIndValid
- uint8_t hsInd
- uint8_t pscValid
- uint16_t psc

8.589.1 Detailed Description

Structure for storing the WCDMA System Information.

Parameters

sysInfoWCDMA	• See nas_sysInfoCommon for more information.
lacValid	• Indicates whether the location area code is valid.. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

lac	• Location area code. • Only applies to 3GPP. – 0xFFFF - Not Available
cellIdValid	• Indicates whether the cell ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
cellId	• Cell ID. – 0xFFFFFFFF - Not Available
regRejectInfo-Valid	• Indicates whether the registration reject information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
rejectSrvDomain	• Type of service domain in which the registration is rejected. – 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available
rejCause	• Reject cause values sent are specified in [3GPP TS 24.008, Section 10.5.3.6]. – 0xFF - Not Available
networkIdValid	• Indicates whether the network ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
MCC[NAS_PLM-N_LENGTH]	• Mobile Country Code. • MCC digits in ASCII characters
MNC[NAS_PLM-N_LENGTH]	• Mobile Network Code. • MNC digits in ASCII characters • An unused byte is set to 0xFF. • In case of two-digit MNC values, the third (unused) digit is set to 0xFF. For example, 15 (a two-digit MNC) is reported using the byte stream 0x31 0x35 0xFF.

hsCallStatus-Valid	• Indicates whether the high-speed call status is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
hsCallStatus	• Call status on high speed. • Only applicable for WCDMA. – 0x00 - HSDPA and HSUPA are unsupported – 0x01 - HSDPA is supported – 0x02 - HSUPA is supported – 0x03 - HSDPA and HSUPA are supported – 0x04 - HSDPA+ is supported – 0x05 - HSDPA+ and HSUPA are supported – 0x06 - Dual-cell HSDPA+ is supported – 0x07 - Dual-cell HSDPA+ and HSUPA are supported – 0xFF - Not Available
hsIndValid	• Indicates whether high-speed service indication is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
hsInd	• High-speed service indication • Only applicable for WCDMA. – 0x00 - HSDPA and HSUPA are unsupported – 0x01 - HSDPA is supported – 0x02 - HSUPA is supported – 0x03 - HSDPA and HSUPA are supported – 0x04 - HSDPA+ is supported – 0x05 - HSDPA+ and HSUPA are supported – 0x06 - Dual-cell HSDPA+ is supported – 0x07 - Dual-cell HSDPA+ and HSUPA are supported – 0xFF - Not Available
pscValid	• Indicates whether primary scrambling code is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
psc	• Primary scrambling code. – 0xFFFF - Not Available

8.589.2 Field Documentation

8.589.2.1 uint32_t nas_WCDMASysInfo::cellId

8.589.2.2 uint8_t nas_WCDMASysInfo::cellIdValid

8.589.2.3 uint8_t nas_WCDMASysInfo::hsCallStatus

8.589.2.4 uint8_t nas_WCDMASysInfo::hsCallStatusValid

8.589.2.5 uint8_t nas_WCDMASysInfo::hsInd

8.589.2.6 uint8_t nas_WCDMASysInfo::hsIndValid

8.589.2.7 uint16_t nas_WCDMASysInfo::lac

8.589.2.8 uint8_t nas_WCDMASysInfo::lacValid

8.589.2.9 uint8_t nas_WCDMASysInfo::MCC[3]

8.589.2.10 uint8_t nas_WCDMASysInfo::MNC[3]

8.589.2.11 uint8_t nas_WCDMASysInfo::networkIdValid

8.589.2.12 uint16_t nas_WCDMASysInfo::psc

8.589.2.13 uint8_t nas_WCDMASysInfo::pscValid

8.589.2.14 uint8_t nas_WCDMASysInfo::regRejectInfoValid

8.589.2.15 uint8_t nas_WCDMASysInfo::rejCause

8.589.2.16 uint8_t nas_WCDMASysInfo::rejectSrvDomain

8.589.2.17 nas_sysInfoCommon nas_WCDMASysInfo::sysInfoWCDMA

8.590 nas_wcdmaUARFCN Struct Reference

Data Fields

- uint8_t status
- uint32_t uarfcn

8.590.1 Detailed Description

This structure contains WCDMA UARFCN infromation.

Parameters

status	• 0 - Disable • 1 - Enable
uarfcn	• UARFCN to which UE is locked

8.590.2 Field Documentation

8.590.2.1 uint8_t nas_wcdmaUARFCN::status

8.590.2.2 uint32_t nas_wcdmaUARFCN::uarfcn

8.591 NASAcqOrderPrefTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t AcqOrderLen
- uint8_t AcqOrderPref [255]

8.591.1 Detailed Description

Structure used to store acquisition order preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
AcqOrderPref	- Acquisition order Preference Value

8.591.2 Field Documentation

8.591.2.1 uint8_t NASAcqOrderPrefTlv::AcqOrderLen

8.591.2.2 uint8_t NASAcqOrderPrefTlv::AcqOrderPref[255]

8.591.2.3 uint8_t NASAcqOrderPrefTlv::TlvPresent

8.592 NASBandPreferenceTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t band_pref

8.592.1 Detailed Description

Structure used to store all Band Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
band_pref	- Roaming Indication Value

8.592.2 Field Documentation

8.592.2.1 uint64_t NASBandPreferenceTlv::band_pref

8.592.2.2 uint8_t NASBandPreferenceTlv::TlvPresent

8.593 nasCellLocationInfoResp Struct Reference

Data Fields

- GERANInfo * pGERANInfo
- UMTSInfo * pUMTSInfo
- CDMAInfo * pCDMAInfo
- LTEInfoIntrafreq * pLTEInfoIntrafreq
- LTEInfoInterfreq * pLTEInfoInterfreq
- LTEInfoNeighboringGSM * pLTEInfoNeighboringGSM
- LTEInfoNeighboringWCDMA * pLTEInfoNeighboringWCDMA
- ULONG * pUMTSCellID
- WCDMAInfoLTENeighborCell * pWCDMAInfoLTENeighborCell

8.593.1 Detailed Description

This structure contains information about the Get Cell Location response parameters.

Parameters

pGERANInfo	• See GERANInfo for more information.
pUMTSInfo	• See UMTSInfo for more information.
pCDMAInfo	• See CDMAInfo for more information.
pLTEInfo-Intrafreq	• See LTEInfoIntrafreq for more information.
pLTEInfo-Interfreq	• See LTEInfoInterfreq for more information.
pLTEInfo-NeighboringGS-M	• See LTEInfoNeighboringGSM for more information.
pLTEInfo-NeighboringWC-DMA	• See LTEInfoNeighboringWCDMA for more information.
pUMTSCellID	• Cell ID. • 0xFFFFFFFF indicates cell ID information is not present.
pWCDMAInfoLT-ENeighborCell	• See WCDMAInfoLTENeighborCell for more information.

8.593.2 Field Documentation

8.593.2.1 CDMAInfo* nasCellLocationInfoResp::pCDMAInfo

8.593.2.2 GERANInfo* nasCellLocationInfoResp::pGERANInfo

8.593.2.3 LTEInfoInterfreq* nasCellLocationInfoResp::pLTEInfoInterfreq

8.593.2.4 LTEInfoIntrafreq* nasCellLocationInfoResp::pLTEInfoIntrafreq

8.593.2.5 LTEInfoNeighboringGSM* nasCellLocationInfoResp::pLTEInfoNeighboringGSM

8.593.2.6 LTEInfoNeighboringWCDMA* nasCellLocationInfoResp::pLTEInfoNeighboringWCDMA

8.593.2.7 ULONG* nasCellLocationInfoResp::pUMTSCellID

8.593.2.8 UMTSInfo* nasCellLocationInfoResp::pUMTSInfo

8.593.2.9 WCDMAInfoLTENeighborCell* nasCellLocationInfoResp::pWCDMAInfoLTENeighborCell

8.594 NASCiotAcqOrderPrefTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t CiotAcqOrderLen
- uint32_t CiotAcqOrderPref [255]

8.594.1 Detailed Description

Structure used to store CIOT acquisition order preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
CiotAcqOrder-Pref	- CIOT Acquisition order Preference Value

8.594.2 Field Documentation

8.594.2.1 uint8_t NASCiotAcqOrderPrefTlv::CiotAcqOrderLen

8.594.2.2 uint32_t NASCiotAcqOrderPrefTlv::CiotAcqOrderPref[255]

8.594.2.3 uint8_t NASCiotAcqOrderPrefTlv::TlvPresent

8.595 NASCiotLteOpModePrefTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t CiotLteOpModePref

8.595.1 Detailed Description

Structure used to store CIOT LTE Operational Mode Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
CiotLteOpMode-Pref	- Bitmask representing the CIoT LTE operational mode preference

8.595.2 Field Documentation

8.595.2.1 uint64_t NASCiotLteOpModePrefTlv::CiotLteOpModePref

8.595.2.2 uint8_t NASCiotLteOpModePrefTlv::TlvPresent

8.596 NASEmergencyModeTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t EmerMode

8.596.1 Detailed Description

Structure used to store Emergency Mode TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
EmerMode	- Emergency Mode Value

8.596.2 Field Documentation

8.596.2.1 uint8_t NASEmergencyModeTlv::EmerMode

8.596.2.2 uint8_t NASEmergencyModeTlv::TlvPresent

8.597 nasGet3GPP2SubscriptionInfoReq Struct Reference

Data Fields

- BYTE namID

8.597.1 Detailed Description

This structure contains the Get3GPP2SubscriptionInfo request parameters

Parameters

namID	[Mandatory] • NAM ID of the information to be retrieved. The index starts from 0. A nam_id of 0xFF is used to retrieve information of current NAM.

8.597.2 Field Documentation

8.597.2.1 BYTE nasGet3GPP2SubscriptionInfoReq::namID

8.598 nasGet3GPP2SubscriptionInfoResp Struct Reference

Data Fields

- namName * pNAMNameInfo
- dirNum * pDirNum
- homeSIDNID * pHomeSIDNID
- minBasedIMSI * pMinBasedIMSI
- trueIMSI * pTrueIMSI
- CDMAChannel * pCDMAChannel

8.598.1 Detailed Description

This structure contains the SLQSNasGet3GPP2Subscription response parameters.

Parameters

pNAMNameInfo	[Optional] • See namName for more information
pDirNum	[Optional] • See dirNum for more information
pHomeSIDNID	[Optional] • See homeSIDNID for more information
pMinBasedIMSI	[Optional] • See minBasedIMSI for more information
pTrueIMSI	[Optional] • See trueIMSI for more information
pCDMAChannel	[Optional] • See CDMAChannel for more information

8.598.2 Field Documentation

8.598.2.1 CDMAChannel* nasGet3GPP2SubscriptionInfoResp::pCDMAChannel

8.598.2.2 dirNum* nasGet3GPP2SubscriptionInfoResp::pDirNum

8.598.2.3 homeSIDNID* nasGet3GPP2SubscriptionInfoResp::pHomeSIDNID

8.598.2.4 minBasedIMSI* nasGet3GPP2SubscriptionInfoResp::pMinBasedIMSI

8.598.2.5 namName* nasGet3GPP2SubscriptionInfoResp::pNAMNameInfo

8.598.2.6 trueIMSI* nasGet3GPP2SubscriptionInfoResp::pTrueIMSI

8.599 nasGeteDRXParamsReq Struct Reference

Data Fields

- BYTE * pEdrxRAT
- ULONG * pLteOpMode

8.599.1 Detailed Description

This structure contains the SLQSNASGeteDRXParamsExt request parameters.

Parameters

pEdrxRAT	[Optional] • eDRX Radio Access Technology • Values – NAS_RADIO_IF_NO_SVC (0x00) - None (no service) – NAS_RADIO_IF_CDMA_1X (0x01) - cdma2000 ® 1X – NAS_RADIO_IF_CDMA_1XEVDO (0x02) - cdma2000 ® HRPD (1xEV-DO) – NAS_RADIO_IF_AMPS (0x03) - AMPS – NAS_RADIO_IF_GSM (0x04) - GSM – NAS_RADIO_IF_UMTS (0x05) - UMTS – NAS_RADIO_IF_WLAN (0x06) - WLAN – NAS_RADIO_IF_GPS (0x07) - GPS – NAS_RADIO_IF_LTE (0x08) - LTE – NAS_RADIO_IF_TDSCDMA (0x09) - TD-SCDMA – NAS_RADIO_IF_LTE_M1 (0x0a) - LTE-M1 – NAS_RADIO_IF_LTE_NB1 (0x0b) - LTE-NB1 – NAS_RADIO_IF_NO_CHANGE (-1) - No change Note: The device will use "0x08 - NAS_-RADIO_IF_LTE" as the default value if the TLV is omitted.
pLteOpMode	[Optional] • LTE Operational Mode • Values – NAS_CIOT_SYS_MODE_NO_ SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_ WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_ M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_ NB1 (0x03) - Camped on LTE NB1 Note: This TLV should be set when edrx_rat_type is LTE.

8.599.2 Field Documentation

8.599.2.1 BYTE* nasGeteDRXParamsReq::pEdrxRAT

8.599.2.2 ULONG* nasGeteDRXParamsReq::pLteOpMode

8.600 nasGeteDRXParamsResp Struct Reference

Data Fields

- BYTE * pCycleLen

- BYTE has_CycleLen
- BYTE * pPagingTimeWindow
- BYTE has_PagingTimeWindow
- BYTE * pEdrxEnable
- BYTE has_EdrxEnable
- BYTE * pEdrxRAT
- BYTE has_EdrxRAT
- ULONG * pLteOpMode
- BYTE has_LteOpMode

8.600.1 Detailed Description

This structure contains the SLQSNASGeteDRXParams request parameters.

Parameters

pCycleLen	[Optional] • eDRX cycle length • Value is per 3GPP TS 24.008 Rel-13 Section 10.5.5.32
has_CycleLen[-Out]	• eDRX cycle length Availability. – false : Unavailable. – true : Available.
pPagingTime-Window	[Optional] • eDRX paging time window • Value is per 3GPP TS 24.008 Rel-13 Section10.5.5.32
has_Paging-TimeWindow[-Out]	• eDRX paging time window Availability. – false : Unavailable. – true : Available.
pEdrxEnable	[Optional] • eDRX Enable • Values – 0x00 - Disable – 0x01 - Enable
has_Edrx-Enable[Out]	• eDRX Enable Availability. – false : Unavailable. – true : Available.

pEdrxRAT	[Optional] • eDRX Radio Access Technology • Values – NAS_RADIO_IF_NO_SVC (0x00) - None (no service) – NAS_RADIO_IF_CDMA_1X (0x01) - cdma2000 ® 1X – NAS_RADIO_IF_CDMA_1XEVDO (0x02) - cdma2000 ® HRPD (1xEV-DO) – NAS_RADIO_IF_AMPS (0x03) - AMPS – NAS_RADIO_IF_GSM (0x04) - GSM – NAS_RADIO_IF_UMTS (0x05) - UMTS – NAS_RADIO_IF_WLAN (0x06) - WLAN – NAS_RADIO_IF_GPS (0x07) - GPS – NAS_RADIO_IF_LTE (0x08) - LTE – NAS_RADIO_IF_TDSCDMA (0x09) - TD-SCDMA – NAS_RADIO_IF_LTE_M1 (0x0a) - LTE-M1 – NAS_RADIO_IF_LTE_NB1 (0x0b) - LTE-NB1 – NAS_RADIO_IF_NO_CHANGE (-1) - No change
has_EdrxRAT[-Out]	• eDRX Radio Access Technology Availability. – false : Unavailable. – true : Available.
pLteOpMode	[Optional] • LTE Operational Mode • Values – NAS_CIOT_SYS_MODE_NO_ SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_ WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_ M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_ NB1 (0x03) - Camped on LTE NB1
has_LteOpMode[Out]	• LTE Operational Mode Availability. – false : Unavailable. – true : Available.

8.600.2 Field Documentation

8.600.2.1 BYTE nasGeteDRXParamsResp::has_CycleLen

8.600.2.2 BYTE nasGeteDRXParamsResp::has_EdrxEnable

8.600.2.3 BYTE nasGeteDRXParamsResp::has_EdrxRAT

8.600.2.4 BYTE nasGeteDRXParamsResp::has_LteOpMode

8.600.2.5 BYTE nasGeteDRXParamsResp::has_PagingTimeWindow

8.600.2.6 BYTE* nasGeteDRXParamsResp::pCycleLen

8.600.2.7 BYTE* nasGeteDRXParamsResp::pEdrxEnable

8.600.2.8 BYTE∗ nasGeteDRXParamsResp::pEdrxRAT

8.600.2.9 ULONG∗ nasGeteDRXParamsResp::pLteOpMode

8.600.2.10 BYTE∗ nasGeteDRXParamsResp::pPagingTimeWindow

8.601 nasGetForbiddenNetworksResp Struct Reference

Data Fields

- ForbiddenNetworks3GPP ∗ pForbiddenNetworks3GPP

8.601.1 Detailed Description

This structure contains the SLQSNASGeteDRXParams request parameters.

Parameters

pForbidden-Networks3GPP	[Optional] • See ForbiddenNetworks3GPP for more information.

8.601.2 Field Documentation

8.601.2.1 ForbiddenNetworks3GPP∗ nasGetForbiddenNetworksResp::pForbiddenNetworks3GPP

8.602 nasGetHDRColorCodeResp Struct Reference

Data Fields

- BYTE ∗ pColorCode

8.602.1 Detailed Description

Structure for storing the current preferred system selection settings for the device.

Parameters

pColorCode	[Optional] • Color code value • Color code corresponding to the sector to which the AT is sending the access probe • See 3GPP2 C.S0024-B V3.0, Section 7.11.6.2.1 for more information. – 0xFF - Not Available

8.602.2 Field Documentation

8.602.2.1 BYTE∗ nasGetHDRColorCodeResp::pColorCode

8.603 nasGetLTECphyCa Struct Reference

Data Fields

- PhyCaAggScellIndType sPhyCaAggScellIndType
- PhyCaAggScellDlBw sPhyCaAggScellDlBw
- PhyCaAggScellInfo sPhyCaAggScellInfo
- PhyCaAggPcellInfo sPhyCaAggPcellInfo
- PhyCaAggScellIndex sPhyCaAggScellIndex
- PhyCaAggScellArray sPhyCaAggScellArray

8.603.1 Field Documentation

8.603.1.1 PhyCaAggPcellInfo nasGetLTECphyCa::sPhyCaAggPcellInfo

8.603.1.2 PhyCaAggScellArray nasGetLTECphyCa::sPhyCaAggScellArray

8.603.1.3 PhyCaAggScellDlBw nasGetLTECphyCa::sPhyCaAggScellDlBw

8.603.1.4 PhyCaAggScellIndex nasGetLTECphyCa::sPhyCaAggScellIndex

8.603.1.5 PhyCaAggScellIndType nasGetLTECphyCa::sPhyCaAggScellIndType

8.603.1.6 PhyCaAggScellInfo nasGetLTECphyCa::sPhyCaAggScellInfo

8.604 NasGetLTECphyCaInfo Struct Reference

Data Fields

- NASPhyCaAggScellIndType PhyCaAggScellIndType
- NASPhyCaAggScellDlBw PhyCaAggScellDlBw
- NASPhyCaAggScellInfo PhyCaAggScellInfo
- NASPhyCaAggPcellInfo PhyCaAggPcellInfo
- NASPhyCaAggScellIndex PhyCaAggScellIndex
- NASPhyCaAggScellArray PhyCaAggScellArray

8.604.1 Detailed Description

This structure contains the parameters for aggregation event information.

Parameters

PhyCaAggScell-IndType	• see NASPhyCaAggScellIndType • Bit to check in ParamPresenceMask - **16**
PhyCaAggScell-DlBw	• see NASPhyCaAggScellDlBw • Bit to check in ParamPresenceMask - **17**
PhyCaAggScell-Info	• see NASPhyCaAggScellInfo • Bit to check in ParamPresenceMask - **18**

PhyCaAggPcell-Info	• see NASPhyCaAggPcellInfo • Bit to check in ParamPresenceMask - **19**
PhyCaAggScell-Index	• see NASPhyCaAggScellIndex • Bit to check in ParamPresenceMask - **20**
PhyCaAggScell-Array	• see NASPhyCaAggScellArray • Bit to check in ParamPresenceMask - **21**

8.604.2 Field Documentation

8.604.2.1 NASPhyCaAggPcellInfo NasGetLTECphyCaInfo::PhyCaAggPcellInfo

8.604.2.2 NASPhyCaAggScellArray NasGetLTECphyCaInfo::PhyCaAggScellArray

8.604.2.3 NASPhyCaAggScellDlBw NasGetLTECphyCaInfo::PhyCaAggScellDlBw

8.604.2.4 NASPhyCaAggScellIndex NasGetLTECphyCaInfo::PhyCaAggScellIndex

8.604.2.5 NASPhyCaAggScellIndType NasGetLTECphyCaInfo::PhyCaAggScellIndType

8.604.2.6 NASPhyCaAggScellInfo NasGetLTECphyCaInfo::PhyCaAggScellInfo

8.605 nasGetLTECphyCaResp Struct Reference

Data Fields

- PhyCaAggScellIndType * pPhyCaAggScellIndType
- PhyCaAggScellDlBw * pPhyCaAggScellDlBw
- PhyCaAggScellInfo * pPhyCaAggScellInfo
- PhyCaAggPcellInfo * pPhyCaAggPcellInfo
- PhyCaAggScellIndex * pPhyCaAggScellIndex
- PhyCaAggScellArray * pPhyCaAggScellArray

8.605.1 Field Documentation

8.605.1.1 PhyCaAggPcellInfo* nasGetLTECphyCaResp::pPhyCaAggPcellInfo

8.605.1.2 PhyCaAggScellArray* nasGetLTECphyCaResp::pPhyCaAggScellArray

8.605.1.3 PhyCaAggScellDlBw* nasGetLTECphyCaResp::pPhyCaAggScellDlBw

8.605.1.4 PhyCaAggScellIndex* nasGetLTECphyCaResp::pPhyCaAggScellIndex

8.605.1.5 PhyCaAggScellIndType* nasGetLTECphyCaResp::pPhyCaAggScellIndType

8.605.1.6 PhyCaAggScellInfo* nasGetLTECphyCaResp::pPhyCaAggScellInfo

8.606 NasGetRFInfoResp Struct Reference

Data Fields

- RfBandInfoList rfbandInfoList
- RfDedicatedBandInfo * pRfDedicatedBandInfo
- RfBandInfoExtFormat * pRfBandInfoExtFormat
- RfBandwidthInfo * pRfBandwidthInfo
- LTEOperationMode * pLTEOperationMode

8.606.1 Detailed Description

This structure contains the SLQSNasGetRFInfo response parameters.

Parameters

rfbandInfoList	• See RfBandInfoList for more information
pRfDedicated-BandInfo	[Optional] • See RfDedicatedBandInfo for more information
pRfBandInfoExt-Format	[Optional] • See RfBandInfoExtFormat for more information
pRfBandwidth-Info	[Optional] • See RfBandwidthInfo for more information
pLTEOperation-Mode	[Optional] • See LTEOperationMode for more information

8.606.2 Field Documentation

8.606.2.1 LTEOperationMode* NasGetRFInfoResp::pLTEOperationMode

8.606.2.2 RfBandInfoExtFormat* NasGetRFInfoResp::pRfBandInfoExtFormat

8.606.2.3 RfBandwidthInfo* NasGetRFInfoResp::pRfBandwidthInfo

8.606.2.4 RfDedicatedBandInfo* NasGetRFInfoResp::pRfDedicatedBandInfo

8.606.2.5 RfBandInfoList NasGetRFInfoResp::rfbandInfoList

8.607 nasGetSigInfoResp Struct Reference

Data Fields

- CDMASSInfo * pCDMASSInfo
- HDRSSInfo * pHDRSSInfo
- INT8 * pGSMSSInfo
- CDMASSInfo * pWCDMASSInfo
- LTESSInfo * pLTESSInfo
- INT8 * pTDSCDMASigInfoRscp

- TDSCDMASigInfoExt * pTDSCDMASigInfoExt

8.607.1 Detailed Description

This structure contains the SLQSNasGetSigInfo response parameters.

Parameters

pCDMASSInfo	[Optional] • See CDMASSInfo for more information
pHDRSSInfo	[Optional] • See HDRSSInfo for more information
pGSMSSInfo	[Optional] • GSM signal strength is the RSSI in dBm (signed value). • A value of -125 dBm or lower is used to indicate No Signal.
pWCDMASSInfo	[Optional] • See CDMASSInfo for more information
pLTESSInfo	[Optional] • See LTESSInfo for more information
pTDSCDMASig-InfoRscp	[Optional] • RSCP of the Primary Common Control Physical Channel (PCCPCH) in dBm. • Measurement range: -120 dBm to -25 dBm.
pTDSCDMASig-InfoExt	[Optional] • See TDSCDMASigInfoExt for more information.

8.607.2 Field Documentation

8.607.2.1 CDMASSInfo* nasGetSigInfoResp::pCDMASSInfo

8.607.2.2 INT8* nasGetSigInfoResp::pGSMSSInfo

8.607.2.3 HDRSSInfo* nasGetSigInfoResp::pHDRSSInfo

8.607.2.4 LTESSInfo* nasGetSigInfoResp::pLTESSInfo

8.607.2.5 TDSCDMASigInfoExt* nasGetSigInfoResp::pTDSCDMASigInfoExt

8.607.2.6 INT8* nasGetSigInfoResp::pTDSCDMASigInfoRscp

8.607.2.7 CDMASSInfo* nasGetSigInfoResp::pWCDMASSInfo

8.608 nasGetSysInfoResp Struct Reference

Data Fields

- SrvStatusInfo * pCDMASrvStatusInfo
- SrvStatusInfo * pHDRSrvStatusInfo

- GSMSrvStatusInfo * pGSMSrvStatusInfo
- GSMSrvStatusInfo * pWCDMASrvStatusInfo
- GSMSrvStatusInfo * pLTESrvStatusInfo
- CDMASysInfo * pCDMASysInfo
- HDRSysInfo * pHDRSysInfo
- GSMSysInfo * pGSMSysInfo
- WCDMASysInfo * pWCDMASysInfo
- LTESysInfo * pLTESysInfo
- AddCDMASysInfo * pAddCDMASysInfo
- WORD * pAddHDRSysInfo
- AddSysInfo * pAddGSMSysInfo
- AddSysInfo * pAddWCDMASysInfo
- WORD * pAddLTESysInfo
- CallBarringSysInfo * pGSMCallBarringSysInfo
- CallBarringSysInfo * pWCDMACallBarringSysInfo
- BYTE * pLTEVoiceSupportSysInfo
- BYTE * pGSMCipherDomainSysInfo
- BYTE * pWCDMACipherDomainSysInfo
- ULONG * pCampedCiotLteOpMode

8.608.1 Detailed Description

Structure for storing the SLQSNasGetSysInfo response parameters.

Parameters

pCDMASrvStatusInfo	• See SrvStatusInfo for more information.
pHDRSrvStatusInfo	• See SrvStatusInfo for more information.
pGSMSrvStatusInfo	• See GSMSrvStatusInfo for more information.
pWCDMASrvStatusInfo	• See GSMSrvStatusInfo for more information.
pLTESrvStatusInfo	• See GSMSrvStatusInfo for more information.
pCDMASysInfo	• See CDMASysInfo for more information.
pHDRSysInfo	• See HDRSysInfo for more information.
pGSMSysInfo	• See GSMSysInfo for more information.
pWCDMASysInfo	• See WCDMASysInfo for more information.

pLTESysInfo	• See LTESysInfo for more information.
pAddCDMASysInfo	• See AddCDMASysInfo for more information.
pAddHDRSysInfo	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used.
pAddGSMSysInfo	• See AddSysInfo for more information.
pAddWCDMASysInfo	• See AddSysInfo for more information.
pAddLTESysInfo	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used.
pGSMCallBarringSysInfo	• See CallBarringSysInfo for more information.
pWCDMACallBarringSysInfo	• See CallBarringSysInfo for more information.
pLTEVoiceSupportSysInfo	• Indicates voice support status on LTE. – 0x00 - Voice is not supported – 0x01 - Voice is supported
pGSMCipherDomainSysInfo	• Ciphering on the service domain. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched
pWCDMACipherDomainSysInfo	• Ciphering on the service domain. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched

pCampedCiot-LteOpMode	• Camped CIOT LTE Operational Mode. • Values – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_NB1 (0x03) - Camped on LTE NB1 – 0xFFFFFFFF - Invalid Value

8.608.2 Field Documentation

8.608.2.1 AddCDMASysInfo* nasGetSysInfoResp::pAddCDMASysInfo

8.608.2.2 AddSysInfo* nasGetSysInfoResp::pAddGSMSysInfo

8.608.2.3 WORD* nasGetSysInfoResp::pAddHDRSysInfo

8.608.2.4 WORD* nasGetSysInfoResp::pAddLTESysInfo

8.608.2.5 AddSysInfo* nasGetSysInfoResp::pAddWCDMASysInfo

8.608.2.6 ULONG* nasGetSysInfoResp::pCampedCiotLteOpMode

8.608.2.7 SrvStatusInfo* nasGetSysInfoResp::pCDMASrvStatusInfo

8.608.2.8 CDMASysInfo* nasGetSysInfoResp::pCDMASysInfo

8.608.2.9 CallBarringSysInfo* nasGetSysInfoResp::pGSMCallBarringSysInfo

8.608.2.10 BYTE* nasGetSysInfoResp::pGSMCipherDomainSysInfo

8.608.2.11 GSMSrvStatusInfo* nasGetSysInfoResp::pGSMSrvStatusInfo

8.608.2.12 GSMSysInfo* nasGetSysInfoResp::pGSMSysInfo

8.608.2.13 SrvStatusInfo* nasGetSysInfoResp::pHDRSrvStatusInfo

8.608.2.14 HDRSysInfo* nasGetSysInfoResp::pHDRSysInfo

8.608.2.15 GSMSrvStatusInfo* nasGetSysInfoResp::pLTESrvStatusInfo

8.608.2.16 LTESysInfo* nasGetSysInfoResp::pLTESysInfo

8.608.2.17 BYTE* nasGetSysInfoResp::pLTEVoiceSupportSysInfo

8.608.2.18 CallBarringSysInfo* nasGetSysInfoResp::pWCDMACallBarringSysInfo

8.608.2.19 BYTE* nasGetSysInfoResp::pWCDMACipherDomainSysInfo

8.608.2.20 GSMSrvStatusInfo* nasGetSysInfoResp::pWCDMASrvStatusInfo

8.608.2.21 WCDMASysInfo* nasGetSysInfoResp::pWCDMASysInfo

8.609 nasGetTxRxInfoReq Struct Reference

Data Fields

- BYTE radio_if

8.609.1 Detailed Description

This structure contains the GetTxRxInfoReq request parameters

Parameters

radio_if	[Mandatory] • Radio interface technology of the signal being measured • Valid Values – 0x01 - NAS_RADIO_IF_CDMA_1X - CDMA – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - HDR – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE

8.609.2 Field Documentation

8.609.2.1 BYTE nasGetTxRxInfoReq::radio_if

8.610 nasGetTxRxInfoResp Struct Reference

Data Fields

- rxInfo * pRXChain0Info
- rxInfo * pRXChain1Info
- txInfo * pTXInfo

8.610.1 Detailed Description

This structure contains the GetTxRxInfoResp response parameters.

Parameters

pRXChain0Info	[Optional] • See rxInfo for more information.
pRXChain1Info	[Optional] • See rxInfo for more information.
pTXInfo	[Optional] • See txInfo for more information.

8.610.2 Field Documentation

8.610.2.1 rxInfo* nasGetTxRxInfoResp::pRXChain0Info

8.610.2.2 rxInfo* nasGetTxRxInfoResp::pRXChain1Info

8.610.2.3 txInfo* nasGetTxRxInfoResp::pTXInfo

8.611 NASGWAcqOrderPrefTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t GWAcqOrderPref

8.611.1 Detailed Description

Structure used to store GSM/WCDMA acquisition order preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
GWAcqOrder-Pref	- GSM/WCDMA acquisition order Preference Value

8.611.2 Field Documentation

8.611.2.1 uint32_t NASGWAcqOrderPrefTlv::GWAcqOrderPref

8.611.2.2 uint8_t NASGWAcqOrderPrefTlv::TlvPresent

8.612 nasIndicationRegisterReq Struct Reference

Data Fields

- BYTE * pSystemSelectionInd
- BYTE * pDDTMInd
- BYTE * pServingSystemInd
- BYTE * pDualStandByPrefInd
- BYTE * pSubscriptionInfoInd
- BYTE * pNetworkTimeInd
- BYTE * pSysInfoInd
- BYTE * pSignalStrengthInd
- BYTE * pErrorRateInd
- BYTE * pHDRNewUATIAssInd
- BYTE * pHDRSessionCloseInd
- BYTE * pManagedRoamingInd
- BYTE * pNetworkRejectInd
- BYTE * pSuppressSysInfoInd
- BYTE * pLTECphyCa
- BYTE * pEdrxChangeInfoInd

8.612.1 Detailed Description

This structure contains the SLQSNasIndicationRegisterExt request parameters.

Parameters

pSystem-SelectionInd	[Optional] • System Selection Preference indication registration. The following callbacks would not be invoked if the indication is disabled. tFNRoamingIndicator tFNDataCapabilities and tFNServingSystem – 0x00 - Disable – 0x01 - Enable
pDDTMInd	[Optional] • DDTM (Data Dedicated Transmission Mode) indication registration. The following callbacks would not be invoked if the indication is disabled. tFNDDTM – 0x00 - Disable – 0x01 - Enable
pServing-SystemInd	[Optional] • Serving System indication registration. The following callbacks would not be invoked if the indication is disabled. tFNBandPreference – 0x00 - Disable – 0x01 - Enable
pDualStandBy-PrefInd	[Optional] • Dual Standby Preference indication registration.The following callbacks would not be invoked if the indication is disabled. tFNDualStandByPref – 0x00 - Disable – 0x01 - Enable
pSubscription-InfoInd	[Optional] • Subscription Information indication registration.The following callbacks would not be invoked if the indication is disabled. tFNSubscriptionInfo – 0x00 - Disable – 0x01 - Enable
pNetworkTime-Ind	[Optional] • Network Time indication registration.The following callbacks would not be invoked if the indication is disabled. tFNNetworkTime – 0x00 - Disable – 0x01 - Enable
pSysInfoInd	[Optional] • System Information indication registration.The following callbacks would not be invoked if the indication is disabled. tFNSysInfo – 0x00 - Disable – 0x01 - Enable

pSignalStrength-Ind	[Optional] • Signal Strength indication registration.The following callbacks would not be invoked if the indication is disabled. tFNSigInfo – 0x00 - Disable – 0x01 - Enable
pErrorRateInd	[Optional] • Error Rate indication registration.The following callbacks would not be invoked if the indication is disabled. tFNErrRate – 0x00 - Disable – 0x01 - Enable
pHDRNewUATI-AssInd	[Optional] • HDR New UATI Assigned indication registration.The following callbacks would not be invoked if the indication is disabled. tFNHDRUATIUpdate – 0x00 - Disable – 0x01 - Enable
pHDRSession-CloseInd	[Optional] • HDR Session Closed indication registration.The following callbacks would not be invoked if the indication is disabled. tFNHDRSessionClose – 0x00 - Disable – 0x01 - Enable
pManaged-RoamingInd	[Optional] • Managed Roaming indication registration.The following callbacks would not be invoked if the indication is disabled. tFNManagedRoaming – 0x00 - Disable – 0x01 - Enable
pNetworkReject-Ind	[Optional] • Network reject information indication registration.The following callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pSuppressSys-InfoInd	[Optional] • Controls the reporting of QMI_NAS_SYS_INFO_IND when only the reject_cause field has changed. Values: – 0x00 - Disable – 0x01 - Enable
pLTECphyCa	[Optional] • LTE Physical Carrier Aggregation Information indication registration.The following callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable

pEdrxChange-InfoInd	[Optional] • EDRX Change Info indication registration.The following callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable

Note

Atleast one parameter must be provided as request. 'NULL' value confirms that the indication value is not sent.

8.612.2 Field Documentation

8.612.2.1 BYTE* nasIndicationRegisterReq::pDDTMInd

8.612.2.2 BYTE* nasIndicationRegisterReq::pDualStandByPrefInd

8.612.2.3 BYTE* nasIndicationRegisterReq::pEdrxChangeInfoInd

8.612.2.4 BYTE* nasIndicationRegisterReq::pErrorRateInd

8.612.2.5 BYTE* nasIndicationRegisterReq::pHDRNewUATIAssInd

8.612.2.6 BYTE* nasIndicationRegisterReq::pHDRSessionCloseInd

8.612.2.7 BYTE* nasIndicationRegisterReq::pLTECphyCa

8.612.2.8 BYTE* nasIndicationRegisterReq::pManagedRoamingInd

8.612.2.9 BYTE* nasIndicationRegisterReq::pNetworkRejectInd

8.612.2.10 BYTE* nasIndicationRegisterReq::pNetworkTimeInd

8.612.2.11 BYTE* nasIndicationRegisterReq::pServingSystemInd

8.612.2.12 BYTE* nasIndicationRegisterReq::pSignalStrengthInd

8.612.2.13 BYTE* nasIndicationRegisterReq::pSubscriptionInfoInd

8.612.2.14 BYTE* nasIndicationRegisterReq::pSuppressSysInfoInd

8.612.2.15 BYTE* nasIndicationRegisterReq::pSysInfoInd

8.612.2.16 BYTE* nasIndicationRegisterReq::pSystemSelectionInd

8.613 nasInitNetworkReg Struct Reference

Data Fields

- ULONG regAction
- MNRInfo * pMNRInfo
- ULONG * pChangeDuration
- BYTE * pMncPcsDigitStatus

8.613.1 Detailed Description

This structure contains Initiate Network Registration request parameters

Parameters

regAction	• Specifies one of the following register actions : – AUTO_REGISTER - Device registers according to its provisioning and optional parameters supplied with the command are ignored. – MANUAL_REGISTER - Device registers to a specified network and the optional Manual Network Register Information parameter pMNRInfo must also be included for the command to process successfully and supported only for 3GPP.
pMNRInfo	[Optional] • Pointer to structure MNRInfo – See MNRInfo for more information
pChange-Duration	[Optional] • Duration of the change. – 0x00 - Power cycle - Remains active until the next device power cycle – 0x01 - Permanent - Remains active through power cycles until changed by the client
pMncPcsDigit-Status	[Optional] • MNC PCS Digit Include Status – True - MNC is a 3-digit value. – False - MNC is a 2-digit value.

8.613.2 Field Documentation

8.613.2.1 ULONG* nasInitNetworkReg::pChangeDuration

8.613.2.2 BYTE* nasInitNetworkReg::pMncPcsDigitStatus

8.613.2.3 MNRInfo* nasInitNetworkReg::pMNRInfo

8.613.2.4 ULONG nasInitNetworkReg::regAction

8.614 NASLTEBandPreferenceTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t LTEBandPref

8.614.1 Detailed Description

Structure used to store LTE Band Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
LTEBandPref	- LTE Band Preference Value

8.614.2 Field Documentation

8.614.2.1 uint64_t NASLTEBandPreferenceTlv::LTEBandPref

8.614.2.2 uint8_t NASLTEBandPreferenceTlv::TlvPresent

8.615 NASLteM1BandPrefTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t LteM1BandPref

8.615.1 Detailed Description

Purpose: Structure used to store LTE M1 Band Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
LteM1BandPref	- Bitmask representing the LTE M1 band preference

8.615.2 Field Documentation

8.615.2.1 uint64_t NASLteM1BandPrefTlv::LteM1BandPref

8.615.2.2 uint8_t NASLteM1BandPrefTlv::TlvPresent

8.616 NASLteNasReleaseInfoTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t nas_release
- uint8_t nas_major
- uint8_t nas_minor

8.616.1 Detailed Description

This structure contains LTE Nas Release Infomation

Parameters

Tlvresult	• unpack result
nas_release	• LTE NAS release
nas_major	• LTE NAS version major

nas_minor	• LTE NAS version minor

8.616.2 Field Documentation

8.616.2.1 uint8_t NASLteNasReleaseInfoTlv::nas_major

8.616.2.2 uint8_t NASLteNasReleaseInfoTlv::nas_minor

8.616.2.3 uint8_t NASLteNasReleaseInfoTlv::nas_release

8.616.2.4 uint8_t NASLteNasReleaseInfoTlv::TlvPresent

8.617 NASLteNB1BandPrefTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t LteNB1BandPref

8.617.1 Detailed Description

Structure used to store LTE NB1 Band Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
LteNB1BandPref	- Bitmask representing the LTE NB1 band preference

8.617.2 Field Documentation

8.617.2.1 uint64_t NASLteNB1BandPrefTlv::LteNB1BandPref

8.617.2.2 uint8_t NASLteNB1BandPrefTlv::TlvPresent

8.618 NASModePreferenceTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint16_t ModePref

8.618.1 Detailed Description

Structure used to store Mode Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
ModePref	- Mode Preference Value

8.618.2 Field Documentation

8.618.2.1 uint16_t NASModePreferenceTlv::ModePref

8.618.2.2 uint8_t NASModePreferenceTlv::TlvPresent

8.619 NASNetSelPreferenceTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t NetSelPref

8.619.1 Detailed Description

Structure used to store Network Selection Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
NetSelPref	- Network Selection Preference Value

8.619.2 Field Documentation

8.619.2.1 uint8_t NASNetSelPreferenceTlv::NetSelPref

8.619.2.2 uint8_t NASNetSelPreferenceTlv::TlvPresent

8.620 nasNetworkReject Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE radioIf
- TYPE_OF_SERVICE_DOMAIN serviceDomain
- BYTE rejectCause
- PlmnID * pPlmnId
- CsgId * pCsgId
- LteOpMode * pLteOpMode

8.620.1 Detailed Description

Structure for storing the network reject indication parameters.

Parameters

radioIf	• Radio interface from which to get the information. Values: – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE – 0x09 - NAS_RADIO_IF_TDSCDMA - TDSCDMA

serviceDomain	• Type of service domain in which the registration is rejected. Values: – 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service – 0x01 - SYS_SRV_DOMAIN_CS_ONLY - Circuit-switched only – 0x02 - SYS_SRV_DOMAIN_PS_ONLY - Packet-switched only – 0x03 - SYS_SRV_DOMAIN_CS_PS - Circuit-switched and packet-switched – 0x04 - SYS_SRV_DOMAIN_CAMPED - Camped

rejectCause	• Reject cause values. – 2 - IMSI unknown in HLR – 3 - Illegal MS – 4 - IMSI unknown in VLR – 5 - IMEI not accepted – 6 - Illegal ME – 7 - EPS services not allowed – 8 - EPS services and non-EPS services not allowed – 9 - UE identity cannot be derived by the network – 10 - Implicitly detached – 11 - PLMN not allowed – 12 - Location Area not allowed – 13 - Roaming not allowed in this location area – 14 - EPS services not allowed in this PLMN – 15 - No Suitable Cells In Location Area – 16 - MSC temporarily not reachable – 17 - Network failure – 18 - CS domain not available – 19 - ESM failure – 20 - MAC failure – 21 - Synch failure – 22 - Congestion – 23 - GSM authentication unacceptable – 24 - Security mode rejected, unspecified – 25 - Not authorized for this CSG – 26 - Non-EPS authentication unacceptable – 32 - Service option not supported – 33 - Requested service option not subscribed – 34 - Service option temporarily out of order – 38 - Call cannot be identified – 48 to 63 - retry upon entry into a new cell – 95 - Semantically incorrect message – 96 - Invalid mandatory information – 97 - Message type non-existent or not implemented – 98 - Message type not compatible with the protocol state – 99 - Information element non-existent or not implemented – 100 - Conditional IE error – 101 - Message not compatible with the protocol state – 111 - Protocol error, unspecified – Note - Any other value received by the mobile station shall be treated as 34, 'Service option temporarily out of order'. * Any other value received by the network shall be treated as 111, 'Protocol error, unspecified'. See 3GPP TS 24.008, Section 4.4.4.7 and Section 10.5.3.6 See qaGobiApiTableCallEndReasons.h for Call End reasons
pPlmnId	(optional) • See PlmnID for more information

pCsgId	(optional) • See CsgId for more information.
pLteOpMode	(optional) • See LteOpMode for more information.

8.620.2 Field Documentation

8.620.2.1 CsgId* nasNetworkReject::pCsgId

8.620.2.2 LteOpMode* nasNetworkReject::pLteOpMode

8.620.2.3 PlmnID* nasNetworkReject::pPlmnId

8.620.2.4 BYTE nasNetworkReject::radioIf

8.620.2.5 BYTE nasNetworkReject::rejectCause

8.620.2.6 struct qmTlvResult nasNetworkReject::results

8.620.2.7 TYPE_OF_SERVICE_DOMAIN nasNetworkReject::serviceDomain

8.621 nasNetworkTime Struct Reference

Data Fields

- struct qmTlvResult results
- UniversalTime universalTime
- BYTE * pTimeZone
- BYTE * pDayltSavAdj
- BYTE * pRadioInterface

8.621.1 Detailed Description

Structure for storing the nasSysInfo indication parameters.

Parameters

universalTime	• See UniversalTime for more information.
pTimeZone	• Time Zone. • Offset from Universal time, i.e., the difference between local time and Universal time, in increments of 15 min (signed value).
pDayltSavAdj	• Daylight Saving Adjustment. • Daylight saving adjustment in hr. – Possible values: 0, 1, and 2.

pRadioInterface	• Radio interface from which the information comes • Values – 0x01 - NAS_RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE – 0x09 - NAS_RADIO_IF_TDSCDMA -TD-SCDMA

8.621.2 Field Documentation

8.621.2.1 BYTE* nasNetworkTime::pDayItSavAdj

8.621.2.2 BYTE* nasNetworkTime::pRadioInterface

8.621.2.3 BYTE* nasNetworkTime::pTimeZone

8.621.2.4 struct qmTlvResult nasNetworkTime::results

8.621.2.5 UniversalTime nasNetworkTime::universalTime

8.622 NASNr5gBandPrefTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t Nr5gBandPrefbits1_64
- uint64_t Nr5gBandPrefbits_65_128
- uint64_t Nr5gBandPrefbits_129_192
- uint64_t Nr5gBandPrefbits_193_256

8.622.1 Detailed Description

Structure used to store NR5G Band Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
Nr5gBandPref	- NR5G Band Preference

8.622.2 Field Documentation

8.622.2.1 uint64_t NASNr5gBandPrefTlv::Nr5gBandPrefbits1_64

8.622.2.2 uint64_t NASNr5gBandPrefTlv::Nr5gBandPrefbits_129_192

8.622.2.3 uint64_t NASNr5gBandPrefTlv::Nr5gBandPrefbits_193_256

8.622.2.4 uint64_t NASNr5gBandPrefTlv::Nr5gBandPrefbits_65_128

8.622.2.5 uint8_t NASNr5gBandPrefTlv::TlvPresent

8.623 nasOperatorNameResp Struct Reference

Data Fields

- serviceProviderName * pSrvcProviderName
- operatorPLMNList * pOperatorPLMNList
- PLMNNetworkName * pPLMNNetworkName
- operatorNameString * pOperatorNameString
- PLMNNetworkNameData * pNITZInformation

8.623.1 Detailed Description

This structure contains Operator Name Data related from multiple sources.

Parameters

pSrvcProvider-Name	• Refer serviceProviderName for details (Optional). • Can provide NULL if this parameter is not required.
pOperatorPLM-NList	• Refer operatorPLMNList for details (Optional). • Can provide NULL if this parameter is not required.
pPLMNNetwork-Name	• Refer PLMNNetworkName for details (Optional). • Can provide NULL if this parameter is not required.
pOperatorName-String	• Refer operatorNameString for details (Optional). • Can provide NULL if this parameter is not required.
pNITZ-Information	• Refer PLMNNetworkNameData for details (Optional). • Can provide NULL if this parameter is not required.

8.623.2 Field Documentation

8.623.2.1 PLMNNetworkNameData* nasOperatorNameResp::pNITZInformation

8.623.2.2 operatorNameString* nasOperatorNameResp::pOperatorNameString

8.623.2.3 operatorPLMNList* nasOperatorNameResp::pOperatorPLMNList

8.623.2.4 PLMNNetworkName* nasOperatorNameResp::pPLMNNetworkName

8.623.2.5 serviceProviderName* nasOperatorNameResp::pSrvcProviderName

8.624 NASOTAMessageTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t message_type
- uint16_t data_len
- uint8_t data_buf [2048]

8.624.1 Detailed Description

This structure contains OTA message

Parameters

Tlvresult	• unpack result
message_type	• message type – 0 - LTE ESM uplink – 1 - LTE ESM downlink – 2 - LTE EMM uplink – 3 - LTE EMM downlink – 4 - GSM/UMTS uplink – 5 - GSM/UMTS downlink
data_len	• OTA Message Content Length
data_buf	• OTA Message Content

8.624.2 Field Documentation

8.624.2.1 uint8_t NASOTAMessageTlv::data_buf[2048]

8.624.2.2 uint16_t NASOTAMessageTlv::data_len

8.624.2.3 uint32_t NASOTAMessageTlv::message_type

8.624.2.4 uint8_t NASOTAMessageTlv::TlvPresent

8.625 NASPhyCaAggPcellInfo Struct Reference

Data Fields

- uint32_t pci
- uint32_t freq
- LITEQMI_NAS_LTE_CPHY_CA_BW_NRB dl_bw_value
- uint32_t iLTEbandValue
- uint8_t TlvPresent

8.625.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Pcell Information.

Parameters

pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
dl_bw_value	• Downlink Bandwidth Values. • See LITEQMI_NAS_LTE_CPHY_CA_BW_NRB for more information.
scell_state	• Scell state Values. • See LITEQMI_NAS_LTE_CPHY_SCELL_STATE for more information.
TlvPresent	• Tlv Present.

8.625.2 Field Documentation

8.625.2.1 LITEQMI_NAS_LTE_CPHY_CA_BW_NRB NASPhyCaAggPcellInfo::dl_bw_value

8.625.2.2 uint32_t NASPhyCaAggPcellInfo::freq

8.625.2.3 uint32_t NASPhyCaAggPcellInfo::iLTEbandValue

8.625.2.4 uint32_t NASPhyCaAggPcellInfo::pci

8.625.2.5 uint8_t NASPhyCaAggPcellInfo::TlvPresent

8.626 NASPhyCaAggScellArray Struct Reference

Data Fields

- uint8_t cphy_scell_info_list_len
- uint16_t pci [255]
- uint16_t freq [255]
- LITEQMI_NAS_LTE_CPHY_CA_BW_NRB cphy_ca_dl_bandwidth [255]
- uint16_t band [255]
- LITEQMI_NAS_LTE_CPHY_SCELL_STATE scell_state [255]
- uint16_t scell_idx [255]
- uint8_t TlvPresent

8.626.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Index.

Parameters

cphy_scell_info-_list_len	• Number of sets of the following elements: – pci – freq – cphy_ca_dl_bandwidth – band – scell_state – scell_idx
pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
cphy_ca_dl_-bandwidth	• Downlink Bandwidth Values. • See LITEQMI_NAS_LTE_CPHY_CA_BW_NRB for more information.
band	• Band value. • See LITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND for more information.
scell_state	• Scell state Values. • See LITEQMI_NAS_LTE_CPHY_SCELL_STATE for more information.
scell_idx	• Scell index Values. • Range for index values: 0 to 7.
TlvPresent	• Tlv Present.

8.626.2 Field Documentation

8.626.2.1 uint16_t NASPhyCaAggScellArray::band[255]

8.626.2.2 LITEQMI_NAS_LTE_CPHY_CA_BW_NRB NASPhyCaAggScellArray::cphy_ca_dl_bandwidth[255]

8.626.2.3 uint8_t NASPhyCaAggScellArray::cphy_scell_info_list_len

8.626.2.4 uint16_t NASPhyCaAggScellArray::freq[255]

8.626.2.5 uint16_t NASPhyCaAggScellArray::pci[255]

8.626.2.6 uint16_t NASPhyCaAggScellArray::scell_idx[255]

8.626.2.7 LITEQMI_NAS_LTE_CPHY_SCELL_STATE NASPhyCaAggScellArray::scell_state[255]

8.626.2.8 uint8_t NASPhyCaAggScellArray::TlvPresent

8.627 NASPhyCaAggScellDlBw Struct Reference

Data Fields

- LITEQMI_NAS_LTE_CPHY_CA_BW_NRB dl_bw_value
- uint8_t TlvPresent

8.627.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation Downlink Bandwidth of Scell.

Parameters

dl_bw_value	• Downlink Bandwidth Values. • See LITEQMI_NAS_LTE_CPHY_CA_BW_NRB for more information.

8.627.2 Field Documentation

8.627.2.1 LITEQMI_NAS_LTE_CPHY_CA_BW_NRB NASPhyCaAggScellDlBw::dl_bw_value

8.627.2.2 uint8_t NASPhyCaAggScellDlBw::TlvPresent

8.628 NASPhyCaAggScellIndex Struct Reference

Data Fields

- uint8_t scell_idx
- uint8_t TlvPresent

8.628.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Index.

Parameters

scell_idx	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
TlvPresent	• Tlv Present.

8.628.2 Field Documentation

8.628.2.1 uint8_t NASPhyCaAggScellIndex::scell_idx

8.628.2.2 uint8_t NASPhyCaAggScellIndex::TlvPresent

8.629 NASPhyCaAggScellIndType Struct Reference

Data Fields

- uint32_t pci
- uint32_t freq
- LITEQMI_NAS_LTE_CPHY_SCELL_STATE scell_state
- uint8_t TlvPresent

8.629.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Indeicator Type.

Parameters

pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
scell_state	• Scell state Values. • See LITEQMI_NAS_LTE_CPHY_SCELL_STATE for more information.
TlvPresent	• Tlv Present.

8.629.2 Field Documentation

8.629.2.1 uint32_t NASPhyCaAggScellIndType::freq

8.629.2.2 uint32_t NASPhyCaAggScellIndType::pci

8.629.2.3 LITEQMI_NAS_LTE_CPHY_SCELL_STATE NASPhyCaAggScellIndType::scell_state

8.629.2.4 uint8_t NASPhyCaAggScellIndType::TlvPresent

8.630 NASPhyCaAggScellInfo Struct Reference

Data Fields

- uint32_t pci
- uint32_t freq
- LITEQMI_NAS_LTE_CPHY_CA_BW_NRB dl_bw_value
- uint32_t iLTEbandValue

- LITEQMI_NAS_LTE_CPHY_SCELL_STATE scell_state
- uint8_t TlvPresent

8.630.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Information.

Parameters

pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
dl_bw_value	• Downlink Bandwidth Values. • See LITEQMI_NAS_LTE_CPHY_CA_BW_NRB for more information.
iLTEbandValue	• Band value. • Range for LTE Band class 120 to 160.
scell_state	• Scell state Values. • See LITEQMI_NAS_LTE_CPHY_SCELL_STATE for more information.
TlvPresent	• Tlv Present.

8.630.2 Field Documentation

8.630.2.1 LITEQMI_NAS_LTE_CPHY_CA_BW_NRB NASPhyCaAggScellInfo::dl_bw_value

8.630.2.2 uint32_t NASPhyCaAggScellInfo::freq

8.630.2.3 uint32_t NASPhyCaAggScellInfo::iLTEbandValue

8.630.2.4 uint32_t NASPhyCaAggScellInfo::pci

8.630.2.5 LITEQMI_NAS_LTE_CPHY_SCELL_STATE NASPhyCaAggScellInfo::scell_state

8.630.2.6 uint8_t NASPhyCaAggScellInfo::TlvPresent

8.631 nasPLMNNameReq Struct Reference

Data Fields

- WORD mcc
- WORD mnc

- BYTE * pMncPcsStatus

8.631.1 Detailed Description

Structure for storing the PLMN Name request parameters

Parameters

mcc	• A 16-bit integer representation of MCC. Range: 0 to 999
mnc	• A 16-bit integer representation of MNC. Range: 0 to 999
pMncPcsStatus	• MNC PCS Digit Include Status • Used to interpret the length of the corresponding MNC reported in the PLMN TLV(0x01). • Values – TRUE - MNC is a three-digit value. e.g. a reported value of 90 corresponds to an MNC value of 090 – FALSE - MNC is a two-digit value. e.g. a reported value of 90 corresponds to an MNC value of 90

Note

If pMncPcsStatus is not present, an MNC smaller than 100 is assumed to be a two-digit value, and an MNC greater than or equal to 100 is assumed to be a three digit value.

8.631.2 Field Documentation

8.631.2.1 WORD nasPLMNNameReq::mcc

8.631.2.2 WORD nasPLMNNameReq::mnc

8.631.2.3 BYTE* nasPLMNNameReq::pMncPcsStatus

8.632 nasPLMNNameResp Struct Reference

Data Fields

- BYTE spnEncoding
- BYTE spnLength
- BYTE spn [255]
- BYTE shortNameEn
- BYTE shortNameCI
- BYTE shortNameSB
- BYTE shortNameLen
- BYTE shortName [255]
- BYTE longNameEn
- BYTE longNameCI
- BYTE longNameSB
- BYTE longNameLen
- BYTE longName [255]

8.632.1 Detailed Description

Structure for storing the PLMN Name response parameters

Parameters

spnEncoding	• Coding scheme used for service provider name. This value is ignored if spn_len is zero Values: – 0x00 - SMS default 7-bit coded alphabet as defined in 3GPP TS 23.038 with bit 8 set to 0 – 0x01 - UCS2 (16 bit, little-endian) 3GPP TS 23.038
spnLength	• Length of SPN which follows
spn	• Service Provider name string
shortNameEn	• Coding scheme used for PLMN short name. This value is ignored if PLMN short name length is zero Values: – 0x00 - SMS default 7-bit coded alphabet as defined in 3GPP TS 23.038 with bit 8 set to 0 – 0x01 - UCS2 (16 bit, little-endian) 3GPP TS 23.038
shortNameCI	• Indicates whether the country initials are to be added to the shortName. This value is ignored if shortNameLen is zero. Values: – 0x00 - Do not add the letters for the countrys initials to the name – 0x01 - Add the countrys initials and a text string to the name – 0xFF - Not specified
shortNameSB	• PLMN short name spare bits. This value is ignored if shortNameLen is zero. Values: – 0x01 - Bit 8 is spare and set to 0 in octet – 0x02 - Bits 7 and 8 are spare and set to 0 in octet n – 0x03 - Bits 6 to 8 (inclusive) are spare and set to 0 in octet n – 0x04 - Bits 5 to 8 (inclusive) are spare and set to 0 in octet n – 0x05 - Bits 4 to 8 (inclusive) are spare and set to 0 in octet n – 0x06 - Bits 3 to 8 (inclusive) are spare and set to 0 in octet n – 0x07 - Bits 2 to 8 (inclusive) are spare and set to 0 in octet n – 0x00 - Carries no information about the number of spare bits in octet n
shortNameLen	• Length of shortName which follows
shortName	• PLMN short name
longNameEn	• Coding scheme used for PLMN long name. This value is ignored if PLMN long name length is zero Values: – 0x00 - SMS default 7-bit coded alphabet as defined in 3GPP TS 23.038 with bit 8 set to 0 – 0x01 - UCS2 (16 bit, little-endian) 3GPP TS 23.038

longNameCI	• Indicates whether the country initials are to be added to the longName. This value is ignored if longNameLen is zero. Values: – 0x00 - Do not add the letters for the countrys initials to the name – 0x01 - Add the countrys initials and a text string to the name – 0xFF - Not specified
longNameSB	• PLMN long name spare bits. This value is ignored if longNameLen is zero. Values: – 0x01 - Bit 8 is spare and set to 0 in octet – 0x02 - Bits 7 and 8 are spare and set to 0 in octet n – 0x03 - Bits 6 to 8 (inclusive) are spare and set to 0 in octet n – 0x04 - Bits 5 to 8 (inclusive) are spare and set to 0 in octet n – 0x05 - Bits 4 to 8 (inclusive) are spare and set to 0 in octet n – 0x06 - Bits 3 to 8 (inclusive) are spare and set to 0 in octet n – 0x07 - Bits 2 to 8 (inclusive) are spare and set to 0 in octet n – 0x00 - Carries no information about the number of spare bits in octet n
longNameLen	• Length of longName which follows
longName	• PLMN long name

Note

None

8.632.2 Field Documentation

8.632.2.1 BYTE nasPLMNNameResp::longName[255]

8.632.2.2 BYTE nasPLMNNameResp::longNameCI

8.632.2.3 BYTE nasPLMNNameResp::longNameEn

8.632.2.4 BYTE nasPLMNNameResp::longNameLen

8.632.2.5 BYTE nasPLMNNameResp::longNameSB

8.632.2.6 BYTE nasPLMNNameResp::shortName[255]

8.632.2.7 BYTE nasPLMNNameResp::shortNameCI

8.632.2.8 BYTE nasPLMNNameResp::shortNameEn

8.632.2.9 BYTE nasPLMNNameResp::shortNameLen

8.632.2.10 BYTE nasPLMNNameResp::shortNameSB

8.632.2.11 BYTE nasPLMNNameResp::spn[255]

8.632.2.12 BYTE nasPLMNNameResp::spnEncoding

8.632.2.13 BYTE nasPLMNNameResp::spnLength

8.633 NASPRLPreferenceTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint16_t PRLPref

8.633.1 Detailed Description

Structure used to store CDMA PRL Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
PRLPref	- CDMA PRL Preference Value

8.633.2 Field Documentation

8.633.2.1 uint16_t NASPRLPreferenceTlv::PRLPref

8.633.2.2 uint8_t NASPRLPreferenceTlv::TlvPresent

8.634 NASQmiCbkNasSwiOTAMessageInd Struct Reference

Data Fields

- NASOTAMessageTlv otaMsgTlv
- NASLteNasReleaseInfoTlv nasRelInfoTlv
- NASTimeInfoTlv timeTlv

8.634.1 Detailed Description

This structure contains OTA message

Parameters

otaMsgTlv	• See NASOTAMessageTlv for more details • Bit to check in ParamPresenceMask - **1**
nasRelInfoTlv	• See NASLteNasReleaseInfoTlv for more details • Bit to check in ParamPresenceMask - **16**
timeTlv	• See NASTimeInfoTlv for more details • Bit to check in ParamPresenceMask - **17**

8.634.2 Field Documentation

8.634.2.1 NASLteNasReleaseInfoTlv NASQmiCbkNasSwiOTAMessageInd::nasRelInfoTlv

8.634.2.2 NASOTAMessageTlv NASQmiCbkNasSwiOTAMessageInd::otaMsgTlv

8.634.2.3 NASTimeInfoTlv NASQmiCbkNasSwiOTAMessageInd::timeTlv

8.635 NASQmiCbkNasSystemSelPrefInd Struct Reference

Data Fields

- NASEmergencyModeTlv EMTlv
- NASModePreferenceTlv MPTlv
- NASBandPreferenceTlv BPTlv
- NASPRLPreferenceTlv PRLPTlv
- NASRoamPreferenceTlv RPTlv
- NASLTEBandPreferenceTlv LBPTlv
- NASNetSelPreferenceTlv NSPTlv
- NASServDomainPrefTlv SDPTlv
- NASGWAcqOrderPrefTlv GWAOPTlv
- NASAcqOrderPrefTlv AOPTlv
- NASRatDisabledMaskTlv RatDMTlv
- NASCiotLteOpModePrefTlv CiotOpMPTlv
- NASLteM1BandPrefTlv M1BandPTlv
- NASLteNB1BandPrefTlv NB1BandPTlv
- NASCiotAcqOrderPrefTlv CiotAOPTlv
- NASNr5gBandPrefTlv NR5gBandPTlv

8.635.1 Detailed Description

Structure used to store all QMI Notification parameters.

Parameters

EMTlv	- Emergency mode Tlv • See NASEmergencyModeTlv for more details • Bit to check in ParamPresenceMask - **16**
MPTlv	- Mode preference Tlv • See NASModePreferenceTlv for more details • Bit to check in ParamPresenceMask - **17**
BPTlv	- Band preference Tlv • See NASBandPreferenceTlv for more details • Bit to check in ParamPresenceMask - **18**
PRLPTlv	- PRL preference Tlv • See NASPRLPreferenceTlv for more details • Bit to check in ParamPresenceMask - **19**
RPTlv	- Roaming preference Tlv • See NASRoamPreferenceTlv for more details • Bit to check in ParamPresenceMask - **20**

LBPTlv	- LTE band preference Tlv • See NASLTEBandPreferenceTlv for more details • Bit to check in ParamPresenceMask - **21**
NSPTlv	- Network selection preference Tlv • See NASNetSelPreferenceTlv for more details • Bit to check in ParamPresenceMask - **22**
SDPTlv	- Service domain preference Tlv • See NASServDomainPrefTlv for more details • Bit to check in ParamPresenceMask - **24**
GWAOPTlv	- GSM WCDMA Acquisition Order Preference Tlv • See NASGWAcqOrderPrefTlv for more details • Bit to check in ParamPresenceMask - **25**
AOPTlv	- Acquisition Order Preference Tlv • See NASAcqOrderPrefTlv for more details • Bit to check in ParamPresenceMask - **28**
RatDMTlv	- Disabled RAT Bitmask Tlv • See NASRatDisabledMaskTlv for more details • Bit to check in ParamPresenceMask - **34**
CiotOpMPTlv	- CIOT LTE Operational Mode Preference Tlv • See NASCiotLteOpModePrefTlv for more details • Bit to check in ParamPresenceMask - **36**
M1BandPTlv	- LTE M1 Band Preference Tlv • See NASLteM1BandPrefTlv for more details • Bit to check in ParamPresenceMask - **37**
NB1BandPTlv	- LTE NB1 Band Preference Tlv • See NASLteNB1BandPrefTlv for more details • Bit to check in ParamPresenceMask - **38**
CiotAOPTlv	- CIOT acquisition order preference Tlv • See NASCiotAcqOrderPrefTlv for more details • Bit to check in ParamPresenceMask - **39**
NR5gBandPTlv	- NR5G Band Preference Tlv • See NASNr5gBandPrefTlv for more details • Bit to check in ParamPresenceMask - **40**

Note: None

8.635.2 Field Documentation

8.635.2.1 NASAcqOrderPrefTlv NASQmiCbkNasSystemSelPrefInd::AOPTlv

8.635.2.2 NASBandPreferenceTlv NASQmiCbkNasSystemSelPrefInd::BPTlv

8.635.2.3 NASCiotAcqOrderPrefTlv NASQmiCbkNasSystemSelPrefInd::CiotAOPTlv

8.635.2.4 NASCiotLteOpModePrefTlv NASQmiCbkNasSystemSelPrefInd::CiotOpMPTlv

8.635.2.5 NASEmergencyModeTlv NASQmiCbkNasSystemSelPrefInd::EMTlv

8.635.2.6 NASGWAcqOrderPrefTlv NASQmiCbkNasSystemSelPrefInd::GWAOPTlv

8.635.2.7 NASLTEBandPreferenceTlv NASQmiCbkNasSystemSelPrefInd::LBPTlv

8.635.2.8 NASLteM1BandPrefTlv NASQmiCbkNasSystemSelPrefInd::M1BandPTlv

8.635.2.9 NASModePreferenceTlv NASQmiCbkNasSystemSelPrefInd::MPTlv

8.635.2.10 NASLteNB1BandPrefTlv NASQmiCbkNasSystemSelPrefInd::NB1BandPTlv

8.635.2.11 NASNr5gBandPrefTlv NASQmiCbkNasSystemSelPrefInd::NR5gBandPTlv

8.635.2.12 NASNetSelPreferenceTlv NASQmiCbkNasSystemSelPrefInd::NSPTlv

8.635.2.13 NASPRLPreferenceTlv NASQmiCbkNasSystemSelPrefInd::PRLPTlv

8.635.2.14 NASRatDisabledMaskTlv NASQmiCbkNasSystemSelPrefInd::RatDMTlv

8.635.2.15 NASRoamPreferenceTlv NASQmiCbkNasSystemSelPrefInd::RPTlv

8.635.2.16 NASServDomainPrefTlv NASQmiCbkNasSystemSelPrefInd::SDPTlv

8.636 NASRatDisabledMaskTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint16_t RatDisabledMask

8.636.1 Detailed Description

Structure used to store Disabled RAT Bitmask TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
RatDisabled-Mask	- Bitmask representing the radio technologies that are disabled

8.636.2 Field Documentation

8.636.2.1 uint16_t NASRatDisabledMaskTlv::RatDisabledMask

8.636.2.2 uint8_t NASRatDisabledMaskTlv::TlvPresent

8.637 NASRoamPreferenceTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint16_t RoamPref

8.637.1 Detailed Description

Structure used to store Roaming Preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
RoamPref	- Roaming Preference Value

8.637.2 Field Documentation

8.637.2.1 uint16_t NASRoamPreferenceTlv::RoamPref

8.637.2.2 uint8_t NASRoamPreferenceTlv::TlvPresent

8.638 NASServDomainPrefTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t SrvDomainPref

8.638.1 Detailed Description

Structure used to store Service domain preference TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
SrvDomainPref	- Service Domain Preference Value

8.638.2 Field Documentation

8.638.2.1 uint32_t NASServDomainPrefTlv::SrvDomainPref

8.638.2.2 uint8_t NASServDomainPrefTlv::TlvPresent

8.639 NASServingSystemInfo Struct Reference

Data Fields

- uint8_t registrationState
- uint8_t csAttachState
- uint8_t psAttachState
- uint8_t selectedNetwork
- uint8_t radioInterfaceNo
- uint8_t radioInterfaceList [255]
- uint8_t hdrPersonality

8.639.1 Detailed Description

This structure will hold the serving system parameters information

Parameters

registrationState	- Registration state of the mobile • 0 - QMI_NAS_NOT_REGISTERED Not registered;mobile is not currently searching for a new network to provide service • 1 - QMI_NAS_REGISTERED Registered with a network • 2 - QMI_NAS_NOT_REGISTERED_SEARCHING Not registered, but mobile is currently searching for a new network to provide service • 3 - QMI_NAS_REGISTRATION_DENIED Registration denied by the visible network • 4 - QMI_NAS_REGISTRATION_UNKNOWN Registration state is unknown
csAttachState	- Circuit Switch domain attach state of the mobile • 0 - Unknown or not applicable • 1 - Attached • 2 - Detached
psAttachState	- Packet domain attach state of the mobile • 0 - Unknown or not applicable • 1 - Attached • 2 - Detached
selectedNetwork	- Type of selected radio access network • 0x00 - Unknown • 0x01 - 3GPP2 network • 0x02 - 3GPP network
radioInterfaceNo	- Number of radio interfaces currently in use; this indicates how many radio_if identifiers follow this field
radioInterface-List	- Radio interface currently in use (each is 1 byte) • 0x00 - None (no service) • 0x01 - cdma2000 1X • 0x02 - cdma2000 HRPD (1xEV-DO) • 0x03 - AMPS • 0x04 - GSM • 0x05 - UMTS • 0x08 - LTE
hdrPersonality	- HDR personality information (valid only for EVDO) • 0x00 - Unknown • 0x01 - HRPD • 0x02 - eHRPD

Note: None

8.639.2 Field Documentation

8.639.2.1 uint8_t NASServingSystemInfo::csAttachState

8.639.2.2 uint8_t NASServingSystemInfo::hdrPersonality

8.639.2.3 uint8_t NASServingSystemInfo::psAttachState

8.639.2.4 uint8_t NASServingSystemInfo::radioInterfaceList[255]

8.639.2.5 uint8_t NASServingSystemInfo::radioInterfaceNo

8.639.2.6 uint8_t NASServingSystemInfo::registrationState

8.639.2.7 uint8_t NASServingSystemInfo::selectedNetwork

8.640 nasSeteDRXParamsReq Struct Reference

Data Fields

- BYTE * pEdrxEnable
- BYTE * pCycleLen
- BYTE * pPagingTimeWindow
- BYTE * pEdrxRatType
- ULONG * pEdrxCiotLteMode

8.640.1 Detailed Description

This structure contains the SLQSNASSeteDRXParams request parameters.

Parameters

pEdrxEnable	[Optional] • eDRX Enable • Values – 0x00 - Disable – 0x01 - Enable
pCycleLen	[Optional] • eDRX cycle length • Value to be set per 3GPP TS 24.008 Rel-13 Section 10.5.5.32
pPagingTime-Window	[Optional] • eDRX paging time window • Value to be set per 3GPP TS 24.008 Rel-13 Section 10.5.5.32

pEdrxRatType	[Optional] • Radio access technology • Values – NAS_RADIO_IF_NO_SVC (0x00) - None (no service) – NAS_RADIO_IF_CDMA_1X (0x01) - cdma2000 ® 1X – NAS_RADIO_IF_CDMA_1XEVDO (0x02) cdma2000 ® HRPD (1xEV-DO) – NAS_RADIO_IF_AMPS (0x03) - AMPS – NAS_RADIO_IF_GSM (0x04) - GSM – NAS_RADIO_IF_UMTS (0x05) - UMTS – NAS_RADIO_IF_WLAN (0x06) - WLAN – NAS_RADIO_IF_GPS (0x07) - GPS – NAS_RADIO_IF_LTE (0x08) - LTE – NAS_RADIO_IF_TDSCDMA (0x09)- TD-SCDMA – NAS_RADIO_IF_LTE_M1 (0x0a) - LTE-M1 – NAS_RADIO_IF_LTE_NB1 (0x0b) - LTE-NB1 – NAS_RADIO_IF_NO_CHANGE (-1)- No change Note: The device will use “0x08 - NAS_RADIO_IF_LTE” as the default value if the TLV is omitted.
pEdrxCiotLteMode	[Optional] • CIOT LTE mode • Values – NAS_CIOT_SYS_MODE_NO_ SRV(0x00) - No service – NAS_CIOT_SYS_MODE_LTE_ WB(0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_ M1(0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_ NB1(0x03) - Camped on LTE NB1 Note: This TLV should be set when pEdrxRatType is LTE.

8.640.2 Field Documentation

8.640.2.1 BYTE∗ nasSeteDRXParamsReq::pCycleLen

8.640.2.2 ULONG∗ nasSeteDRXParamsReq::pEdrxCiotLteMode

8.640.2.3 BYTE∗ nasSeteDRXParamsReq::pEdrxEnable

8.640.2.4 BYTE∗ nasSeteDRXParamsReq::pEdrxRatType

8.640.2.5 BYTE∗ nasSeteDRXParamsReq::pPagingTimeWindow

8.641 nasSigInfo Struct Reference

Data Fields

- struct qmTlvResult results
- CDMASSInfo ∗ pCDMASigInfo
- HDRSSInfo ∗ pHDRSigInfo
- INT8 ∗ pGSMSigInfo
- CDMASSInfo ∗ pWCDMASigInfo
- LTESSInfo ∗ pLTESigInfo
- INT8 ∗ pRscp

- TDSCDMASigInfoExt * pTDSCDMASigInfoExt

8.641.1 Detailed Description

Structure for storing the nasSigInfo indication parameters.

Parameters

pCDMASigInfo	• See CDMASSInfo for more information.
pHDRSigInfo	• See HDRSSInfo for more information.
pGSMSigInfo	• one byte value, GSM signal strength is the RSSI in dBm (signed value). A value of -125 dBm or lower is used to indicate No Signal
pWCDMASigInfo	• See CDMASSInfo for more information.
pLTESigInfo	• See LTESSInfo for more information.
pRscp	• RSCP of the Primary Common Control Physical Channel (PCCPCH) in dBm. Measurement range: -120 dBm to -25 dBm.
pTDSCDMASig-InfoExt	• See TDSCDMASigInfoExt for more information.

8.641.2 Field Documentation

8.641.2.1 CDMASSInfo* nasSigInfo::pCDMASigInfo

8.641.2.2 INT8* nasSigInfo::pGSMSigInfo

8.641.2.3 HDRSSInfo* nasSigInfo::pHDRSigInfo

8.641.2.4 LTESSInfo* nasSigInfo::pLTESigInfo

8.641.2.5 INT8* nasSigInfo::pRscp

8.641.2.6 TDSCDMASigInfoExt* nasSigInfo::pTDSCDMASigInfoExt

8.641.2.7 CDMASSInfo* nasSigInfo::pWCDMASigInfo

8.641.2.8 struct qmTlvResult nasSigInfo::results

8.642 nasSwiGetChannelLockResp Struct Reference

Data Fields

- wcdmaUARFCN ∗ pWcdmaUARFCN
- lteEARFCN ∗ pLteEARFCN
- ltePCI ∗ pLtePCI

8.642.1 Detailed Description

This structure contains the SLQSNASSwiGetChannelLock response parameters.

Parameters

pWcdmaUARFCN	[Optional] • See wcdmaUARFCN for more information
pLteEARFCN	[Optional] • See lteEARFCN for more information
pLtePCI	[Optional] • See ltePCI for more information

8.642.2 Field Documentation

8.642.2.1 lteEARFCN∗ nasSwiGetChannelLockResp::pLteEARFCN

8.642.2.2 ltePCI∗ nasSwiGetChannelLockResp::pLtePCI

8.642.2.3 wcdmaUARFCN∗ nasSwiGetChannelLockResp::pWcdmaUARFCN

8.643 NasSwiIndReg Struct Reference

Data Fields

- BYTE lteEsmUl
- BYTE lteEsmDl
- BYTE lteEmmUl
- BYTE lteEmmDl
- BYTE gsmUmtsUl
- BYTE gsmUmtsDl
- BYTE ∗ pRankIndicatorInd
- BYTE ∗ pTimer

8.643.1 Detailed Description

This structure contains the OTA message indication.

Parameters

lteEsmUl	• 0 - do not report • 1 - report LTE ESM uplink messages

lteEsmDl	• 0 - do not report • 1 - report LTE ESM downlink messages
lteEmmUl	• 0 - do not report • 1 - report LTE EMM uplink messages
lteEmmDl	• 0 - do not report • 1 - report GSM/UMTS uplink messages
gsmUmtsUl	• 0 - do not report • 1 - report GSM/UMTS uplink messages
gsmUmtsDl	• 0 - do not report • 1 - report GSM/UMTS downlink messages
pRankIndicator-Ind	• 0 - do not report • 1 - report Rank Indicator messages
pTimer	• 0 - do not report • 1 - report Timer Indicator messages

8.643.2 Field Documentation

8.643.2.1 BYTE NasSwiIndReg::gsmUmtsDl

8.643.2.2 BYTE NasSwiIndReg::gsmUmtsUl

8.643.2.3 BYTE NasSwiIndReg::lteEmmDl

8.643.2.4 BYTE NasSwiIndReg::lteEmmUl

8.643.2.5 BYTE NasSwiIndReg::lteEsmDl

8.643.2.6 BYTE NasSwiIndReg::lteEsmUl

8.643.2.7 BYTE* NasSwiIndReg::pRankIndicatorInd

8.643.2.8 BYTE* NasSwiIndReg::pTimer

8.644 nasSwiSetChannelLockReq Struct Reference

Data Fields

- wcdmaUARFCN * pWcdmaUARFCN

- lteEARFCN * pLteEARFCN
- ltePCI * pLtePCI

8.644.1 Detailed Description

This structure contains the SLQSNASSwiSetChannelLock response parameters.

Parameters

pWcdmaUARFCN	[Optional] • See wcdmaUARCFN for more information
pLteEARFCN	[Optional] • See lteEARCFN for more information
pLtePCI	[Optional] • See ltePCI for more information

8.644.2 Field Documentation

8.644.2.1 lteEARFCN* nasSwiSetChannelLockReq::pLteEARFCN

8.644.2.2 ltePCI* nasSwiSetChannelLockReq::pLtePCI

8.644.2.3 wcdmaUARFCN* nasSwiSetChannelLockReq::pWcdmaUARFCN

8.645 nasSysInfo Struct Reference

Data Fields

- struct qmTlvResult results
- SrvStatusInfo * pCDMASrvStatusInfo
- SrvStatusInfo * pHDRSrvStatusInfo
- GSMSrvStatusInfo * pGSMSrvStatusInfo
- GSMSrvStatusInfo * pWCDMASrvStatusInfo
- GSMSrvStatusInfo * pLTESrvStatusInfo
- CDMASysInfo * pCDMASysInfo
- HDRSysInfo * pHDRSysInfo
- GSMSysInfo * pGSMSysInfo
- WCDMASysInfo * pWCDMASysInfo
- LTESysInfo * pLTESysInfo
- AddCDMASysInfo * pAddCDMASysInfo
- WORD * pAddHDRSysInfo
- AddSysInfo * pAddGSMSysInfo
- AddSysInfo * pAddWCDMASysInfo
- WORD * pAddLTESysInfo
- CallBarringSysInfo * pGSMCallBarringSysInfo
- CallBarringSysInfo * pWCDMACallBarringSysInfo
- BYTE * pLTEVoiceSupportSysInfo
- BYTE * pGSMCipherDomainSysInfo
- BYTE * pWCDMACipherDomainSysInfo
- BYTE * pSysInfoNoChange

- LteCiotOpModeTlv * pLteCiotOpModeTlv
- NR5GSerStatTlv * pNR5GSerStatTlv
- NR5GSystemInfoTlv * pNR5GSystemInfoTlv
- NR5GCellStatusTlv * pNR5GCellStatus

8.645.1 Detailed Description

Structure for storing the nasSysInfo indication parameters.

Parameters

pCDMASrvStatusInfo	• See SrvStatusInfo for more information.
pHDRSrvStatusInfo	• See SrvStatusInfo for more information.
pGSMSrvStatusInfo	• See GSMSrvStatusInfo for more information.
pWCDMASrvStatusInfo	• See GSMSrvStatusInfo for more information.
pLTESrvStatusInfo	• See GSMSrvStatusInfo for more information.
pCDMASysInfo	• See CDMASysInfo for more information.
pHDRSysInfo	• See HDRSysInfo for more information.
pGSMSysInfo	• See GSMSysInfo for more information.
pWCDMASysInfo	• See WCDMASysInfo for more information.
pLTESysInfo	• See LTESysInfo for more information.
pAddCDMASysInfo	• See AddCDMASysInfo for more information.
pAddHDRSysInfo	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used.
pAddGSMSysInfo	• See AddSysInfo for more information.
pAddWCDMASysInfo	• See AddSysInfo for more information.

pAddLTESysInfo	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used.
pGSMCall-BarringSysInfo	• See CallBarringSysInfo for more information.
pWCDMACall-BarringSysInfo	• See CallBarringSysInfo for more information.
pLTEVoice-SupportSysInfo	• Indicates voice support status on LTE. – 0x00 - Voice is not supported – 0x01 - Voice is supported
pGSMCipher-DomainSysInfo	• Ciphering on the service domain. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched
pWCDMA-CipherDomain-SysInfo	• Ciphering on the service domain. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched
pSysInfoNo-Change	• System Info No Change. • Flag used to notify clients that a request to select a network ended with no change in the PLMN. – 0x01 - No change in system information
pLteCiotOp-ModeTlv	• See LteCiotOpModeTlv for more information.
pNR5GSerStat-Tlv	• See NR5GSerStatTlv for more information.
pNR5GSystem-InfoTlv	• See NR5GSystemInfoTlv for more information.
pNR5GCell-StatusTlv	• See NR5GCellStatusTlv for more information.

8.645.2 Field Documentation

8.645.2.1 AddCDMASysInfo* nasSysInfo::pAddCDMASysInfo

8.645.2.2 **AddSysInfo*** nasSysInfo::pAddGSMSysInfo

8.645.2.3 **WORD*** nasSysInfo::pAddHDRSysInfo

8.645.2.4 **WORD*** nasSysInfo::pAddLTESysInfo

8.645.2.5 **AddSysInfo*** nasSysInfo::pAddWCDMASysInfo

8.645.2.6 **SrvStatusInfo*** nasSysInfo::pCDMASrvStatusInfo

8.645.2.7 **CDMASysInfo*** nasSysInfo::pCDMASysInfo

8.645.2.8 **CallBarringSysInfo*** nasSysInfo::pGSMCallBarringSysInfo

8.645.2.9 **BYTE*** nasSysInfo::pGSMCipherDomainSysInfo

8.645.2.10 **GSMSrvStatusInfo*** nasSysInfo::pGSMSrvStatusInfo

8.645.2.11 **GSMSysInfo*** nasSysInfo::pGSMSysInfo

8.645.2.12 **SrvStatusInfo*** nasSysInfo::pHDRSrvStatusInfo

8.645.2.13 **HDRSysInfo*** nasSysInfo::pHDRSysInfo

8.645.2.14 **LteCiotOpModeTlv*** nasSysInfo::pLteCiotOpModeTlv

8.645.2.15 **GSMSrvStatusInfo*** nasSysInfo::pLTESrvStatusInfo

8.645.2.16 **LTESysInfo*** nasSysInfo::pLTESysInfo

8.645.2.17 **BYTE*** nasSysInfo::pLTEVoiceSupportSysInfo

8.645.2.18 **NR5GCellStatusTlv*** nasSysInfo::pNR5GCellStatus

8.645.2.19 **NR5GSerStatTlv*** nasSysInfo::pNR5GSerStatTlv

8.645.2.20 **NR5GSystemInfoTlv*** nasSysInfo::pNR5GSystemInfoTlv

8.645.2.21 **BYTE*** nasSysInfo::pSysInfoNoChange

8.645.2.22 **CallBarringSysInfo*** nasSysInfo::pWCDMACallBarringSysInfo

8.645.2.23 **BYTE*** nasSysInfo::pWCDMACipherDomainSysInfo

8.645.2.24 **GSMSrvStatusInfo*** nasSysInfo::pWCDMASrvStatusInfo

8.645.2.25 **WCDMASysInfo*** nasSysInfo::pWCDMASysInfo

8.645.2.26 struct **qmTlvResult** nasSysInfo::results

8.646 NASTimeInfoTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t time

8.646.1 Detailed Description

This structure contains LTE Nas time Infomation

Parameters

Tlvresult	• unpack result
time	• Seconds in local time since Jan. 6th 1980 00:00:00 UTC

8.646.2 Field Documentation

8.646.2.1 uint64_t NASTimeInfoTlv::time

8.646.2.2 uint8_t NASTimeInfoTlv::TlvPresent

8.647 nasTimers Struct Reference

Data Fields

- struct qmTlvResult results
- char t3396_apn [101]
- BYTE t3396_plmn_id [3]
- ULONG t3396_val

8.647.1 Detailed Description

This structure contains Network Timer

Parameters

t3396_apn	• APN name
t3396_plmn_id	• PLMN ID
t3396_val	• T3396 timer value

8.647.2 Field Documentation

8.647.2.1 struct qmTlvResult nasTimers::results

8.647.2.2 char nasTimers::t3396_apn[101]

8.647.2.3 BYTE nasTimers::t3396_plmn_id[3]

8.647.2.4 ULONG nasTimers::t3396_val

8.648 netSelectionPref Struct Reference

Data Fields

- BYTE netReg
- WORD mcc
- WORD mnc

8.648.1 Detailed Description

Contain the network selection preference.

Parameters

netReg	• specifies one of the following actions: – 0x00 - Automatic registration * Device registers according to its provisioning; mcc and mnc fields are ignored – 0x01 - Manual Registration * Device registers to specified network; mcc and mnc must contain valid values
mcc	• MCC value. Range 0 to 999
mnc	• MNC value. Range 0 to 999

8.648.2 Field Documentation

8.648.2.1 WORD netSelectionPref::mcc

8.648.2.2 WORD netSelectionPref::mnc

8.648.2.3 BYTE netSelectionPref::netReg

8.649 NetStats Struct Reference

Data Fields

- ULONG rx_packets
- ULONG tx_packets
- ULONGLONG rx_bytes
- ULONGLONG tx_bytes
- ULONG rx_errors
- ULONG tx_errors
- ULONG rx_overflows
- ULONG tx_overflows

8.649.1 Detailed Description

This structure contains the SLQSGetNetStatistic Information

Parameters

rx_packets	• Number of received Packets without error
tx_packets	• Number of transmitted Packets without error
rx_bytes	• Number of bytes recieved without error
tx_bytes	• NNumbero of bytes transmitted without error
rx_error	• Number of incoming packets with framing errors
tx_error	• Number of outgoing packets with framing errors
rx_overflows	• Number of packets dropped because Rx buffer overflowed
tx_overflows	• Number of packets dropped because Tx buffer overflowed

8.649.2 Field Documentation

8.649.2.1 ULONGLONG NetStats::rx_bytes

8.649.2.2 ULONG NetStats::rx_errors

8.649.2.3 ULONG NetStats::rx_overflows

8.649.2.4 ULONG NetStats::rx_packets

8.649.2.5 ULONGLONG NetStats::tx_bytes

8.649.2.6 ULONG NetStats::tx_errors

8.649.2.7 ULONG NetStats::tx_overflows

8.649.2.8 ULONG NetStats::tx_packets

8.650 NetworkDebugResp Struct Reference

Data Fields

- BYTE * pObjectVer
- NetworkStat1x * pNetworkStat1x
- NetworkStatEVDO * pNetworkStatEVDO
- DeviceConfigDetail * pDeviceConfigDetail
- DataStatusDetail * pDataStatusDetail

8.650.1 Detailed Description

This structure contains information about the SLQSSwiNetworkDebug response parameters.

Parameters

pObjectVer	• Object's version number for the host to handle – 0xFF - NA – Others - shows in decimal
pNetworkStat1x	• See NetworkStat1x for more information
pNetworkStatEVDO	• See NetworkStatEVDO for more information.
pDeviceConfigDetail	• See DeviceConfigDetail for more information.
pDataStatusDetail	• See DataStatusDetail for more information.

8.650.2 Field Documentation

8.650.2.1 DataStatusDetail∗ NetworkDebugResp::pDataStatusDetail

8.650.2.2 DeviceConfigDetail∗ NetworkDebugResp::pDeviceConfigDetail

8.650.2.3 NetworkStat1x∗ NetworkDebugResp::pNetworkStat1x

8.650.2.4 NetworkStatEVDO∗ NetworkDebugResp::pNetworkStatEVDO

8.650.2.5 BYTE∗ NetworkDebugResp::pObjectVer

8.651 NetworkStat1x Struct Reference

Data Fields

- BYTE State
- WORD SO
- ULONG RX_PWR
- WORD RX_EC_IO
- ULONG TX_PWR
- BYTE ActSetCnt
- ActPilotPNElement ∗ pActPilotPNElements
- BYTE NeighborSetCnt
- WORD ∗ pNeighborSetPilotPN

8.651.1 Detailed Description

This structure contains 1x network status details

Parameters

State	• CDMA current access state – 0x01 - Searching – 0x02 - Idle – 0x03 - Traffic – Others - NA
SO	• CDMA service option – 0xFFFF - Not in a call – 0x0001 - Basic Variable Rate Voice Service(8kbps) – 0x0002 - Mobile Station Loopback(8kbps) – 0x0003 - Enhanced Variable Rate Codec(EVRC) Voice Service(8kbps) – 0x0006 - Short message Services(Rate Set 1) – 0x0009 - Mobile Station Loopback(13kbps) – 0x000E - Short Message Service (Rate Set 2) – 0x0011 - High Rate Voice Service(13kbps) – 0x0020 - Test Data Service Option(TDSO) – 0x0021 - cdma2000 High Speed Packet Data Service, Internet or ISO Protocol Stack – 0x0044 - EVRC-B Voice Service(8 kbps) – 0x0046 - EVRC-WB Voice Service(8 kbps) – 0x0049 - Voice Echo mode supports smart blanking(EVRC-NW) – 0x004B - Enhanced loopback – 0x8000 - Proprietary Service Option (Qualcomm Inc.)
RX_PWR	• RX Pwr(dBm) – 0xABCD00EF - -ABCD.EF dBm – ABCD00EF should be transferred to decimal while displaying – Example: 0x12340056 - -4660.86dBm 0x1234 = 4660, 0x0056 = 86 – 0xFFFFFFFF - NA
RX_EC_IO	• RX EC/IO(dB) – 0xABCD - -AB.CD dB – ABCD should be transferred to decimal while displaying – Example: 0x1234 - -18.52dB 0x12 = 18, 0x34 = 52 – 0xFFFF - NA
TX_PWR	• TX PWR(dBm) – 0xFFFFFFFF - NA – Others - display actual value in decimal – Example: 0x1234 - -4660dBm 0x1234 = 4660

ActSetCnt(	IN/OUT) • Count of active pilot PN elements • As input specifies number of sets of parameter pActPilotElements for which memory has been assigned • As output specifies the actual number of sets of parameter pActPilotElements returned by device
pActPilotPN-Elements	• See ActPilotPNElement for more information
NeighborSetCnt(	IN/OUT) • Count of neighbor pilot PN elements • As input specifies number of sets of parameter pNeighborSetPilotPN for which memory has been assigned • As output specifies the actual number of sets of parameter pNeighborSetPilotPN returned by device
pNeighborSet-PilotPN	• Neighbor pilot PN

8.651.2 Field Documentation

8.651.2.1 BYTE NetworkStat1x::ActSetCnt

8.651.2.2 BYTE NetworkStat1x::NeighborSetCnt

8.651.2.3 ActPilotPNElement* NetworkStat1x::pActPilotPNElements

8.651.2.4 WORD* NetworkStat1x::pNeighborSetPilotPN

8.651.2.5 WORD NetworkStat1x::RX_EC_IO

8.651.2.6 ULONG NetworkStat1x::RX_PWR

8.651.2.7 WORD NetworkStat1x::SO

8.651.2.8 BYTE NetworkStat1x::State

8.651.2.9 ULONG NetworkStat1x::TX_PWR

8.652 NetworkStatEVDO Struct Reference

Data Fields

- BYTE State
- BYTE MACIndex
- BYTE SectorIDLen
- WORD * pSectorID
- WORD RX_PWR
- WORD PER
- WORD PilotEnergy
- BYTE SNR

8.652.1 Detailed Description

This structure contains EVDO network status details

Parameters

State	• EVDO network access state – 0x00 - Sleep – 0x01 - Searching – 0x02 - Idle – 0x03 - Active – 0xFF - NA
MACIndex	• HDR Mac index – 0xFF - NA – Others - Display the actual value in decimal – Example: 0x12 - 18 0x12 = 18
SectorIDLen	(IN/OUT) • Sector ID length • As input specifies length of parameter pSectorID for which memory has been assigned • As output specifies the actual length of parameter pSectorID returned by device
pSectorID	• Sector ID
RX_PWR	• TX PWR(dBm) – 0xABCD - -ABCD dBm – ABCD should be transferred to decimal while displaying – Example: 0x1234 - -4660dBm 0x1234 = 4660 – 0xFFFF - NA
PER	• HDR Packet Error Rate – 0xFFFF - Unknown – Others - display the actual value in decimal – Example: 0x1234 - -4660dBm 0x1234 = 4660
PilotEnergy	• Pilt Energy (dB) – 0xFFFF - NA – 0xABCD should be transferred to decimal while displaying – Example: 0x1234 - -4660dBm 0x1234 = 4660
SNR	• Signal to Noise ratio (dB)

8.652.2 Field Documentation

8.652.2.1 BYTE NetworkStatEVDO::MACIndex

8.652.2.2 WORD NetworkStatEVDO::PER

8.652.2.3 WORD NetworkStatEVDO::PilotEnergy

8.652.2.4 WORD* NetworkStatEVDO::pSectorID

8.652.2.5 WORD NetworkStatEVDO::RX_PWR

8.652.2.6 BYTE NetworkStatEVDO::SectorIDLen

8.652.2.7 BYTE NetworkStatEVDO::SNR

8.652.2.8 BYTE NetworkStatEVDO::State

8.653 newMTMessageTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- sMSMTMessageInfo MTMessageInfo

8.653.1 Detailed Description

This structure contains MT message TLV information.

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response
MTMessageInfo	• MT Message • See sMSMTMessageInfo for more information

8.653.2 Field Documentation

8.653.2.1 sMSMTMessageInfo newMTMessageTlv::MTMessageInfo

8.653.2.2 uint8_t newMTMessageTlv::TlvPresent

8.654 newPwdData Struct Reference

Data Fields

- BYTE newPwd [4]
- BYTE newPwdAgain [4]

8.654.1 Detailed Description

This structure contains New Password Data.

Parameters

newPwd[PASSWORD_LENGTH]	• New password. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.
newPwdAgain[PASSWORD_LENGTH]	• New password again. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.

8.654.2 Field Documentation

8.654.2.1 BYTE newPwdData::newPwd[4]

8.654.2.2 BYTE newPwdData::newPwdAgain[4]

8.655 nmrCellInfo Struct Reference

Data Fields

- ULONG nmrCellID
- BYTE nmrPlmn [3]
- WORD nmrLac
- WORD nmrArfcn
- BYTE nmrBsic
- WORD nmrRxLev

8.655.1 Detailed Description

This structure contains information about the Network Measurement Report (NMR) Cell Information.

Parameters

nmrCellID	• Cell ID. • 0xFFFFFFFF indicates cell ID information is not present.
nmrPlmn[PLMN_LENGTH]	• MCC/MNC information coded as octet 3, 4, and 5. • This field is ignored when nmrCellID is not present.
nmrLac	• Location area code. • This field is ignored when nmrCellID is not present. – 0xFFFF - Not Available

nmrArfcn	• Absolute RF channel number. – 0xFFFF - Not Available
nmrBsic	• Base station identity code. – 0xFF - Not Available
nmrRxLev	• Cell Rx measurement. • Values range between 0 and 63. • Mapped to a measured signal level: – Rxlev 0 is a signal strength less than -110 dBm – Rxlev 1 is -110 dBm to -109 dBm – Rxlev 2 is -109 dBm to -108 dBm – ... – Rxlev 62 is -49 dBm to -48 dBm – Rxlev 63 is greater than -48 dBm – 0xFFFF - Not Available

8.655.2 Field Documentation

8.655.2.1 WORD nmrCellInfo::nmrArfcn

8.655.2.2 BYTE nmrCellInfo::nmrBsic

8.655.2.3 ULONG nmrCellInfo::nmrCellID

8.655.2.4 WORD nmrCellInfo::nmrLac

8.655.2.5 BYTE nmrCellInfo::nmrPlmn[3]

8.655.2.6 WORD nmrCellInfo::nmrRxLev

8.656 nr5gBandPref Struct Reference

Data Fields

- ULONGLONG bits_1_64
- ULONGLONG bits_65_128
- ULONGLONG bits_129_192
- ULONGLONG bits_193_256

8.656.1 Detailed Description

Contain the NR5G Band Preference.

Parameters

bits_1_64	• Bits 1 to 64 of the 256-bit NR5G Operating Band bitmask.
bits_65_128	• Bits 65 to 128 of the 256-bit NR5G Operating Band bitmask.
bits_129_192	• Bits 129 to 192 of the 256-bit NR5G Operating Band bitmask.
bits_193_256	• Bits 193 to 256 of the 256-bit NR5G Operating Band bitmask.

8.656.2 Field Documentation

8.656.2.1 ULONGLONG nr5gBandPref::bits_129_192

8.656.2.2 ULONGLONG nr5gBandPref::bits_193_256

8.656.2.3 ULONGLONG nr5gBandPref::bits_1_64

8.656.2.4 ULONGLONG nr5gBandPref::bits_65_128

8.657 NR5GCellStatusTlv Struct Reference

Data Fields

- ULONG nr5gCellStatus
- BYTE TlvPresent

8.657.1 Detailed Description

Structure for storing the NR5G Cell Access Status Info parameters

Parameters

nr5gCellStatus	• Cell access status for NR5G calls. – Values: * NAS_CELL_ACCESS_NORMAL_ ONLY (0x00) - Cell access is allowed for normal calls only * NAS_CELL_ACCESS_EMERGENCY_ ONLY (0x01) - Cell access is allowed for emergency calls only * NAS_CELL_ACCESS_NO_CALLS (0x02) - Cell access is not allowed for any call type * NAS_CELL_ACCESS_ALL_CALLS (0x03) - Cell access is allowed for all call types * NAS_CELL_ACCESS_UNKNOWN (-1) - Cell access type is unknown
TlvPresent	• Tlv Present or not

8.657.2 Field Documentation

8.657.2.1 ULONG NR5GCellStatusTlv::nr5gCellStatus

8.657.2.2 BYTE NR5GCellStatusTlv::TlvPresent

8.658 NR5GSerStatTlv Struct Reference

Data Fields

- BYTE srvStatus
- BYTE trueSrvStatus
- BYTE isPrefDataPath
- BYTE TlvPresent

8.658.1 Detailed Description

This structure contains NR5G Service Status Info parameters.

Parameters

srvStatus	• Service status of the system. • Values: – 0x00 - SYS_SRV_STATUS_NO_SRV - No service – 0x01 - SYS_SRV_STATUS_LIMITED - Limited service – 0x02 - SYS_SRV_STATUS_SRV - Service – 0x03 - SYS_SRV_STATUS_LIMITED_REGIONAL - Limited regional service – 0x04 - SYS_SRV_STATUS_PWR_SAVE - Power save
trueSrvStatus	• True service status of the system (not applicable to CDMA/HDR). • Values: – 0x00 - SYS_SRV_STATUS_NO_SRV - No service – 0x01 - SYS_SRV_STATUS_LIMITED - Limited service – 0x02 - SYS_SRV_STATUS_SRV - Service – 0x03 - SYS_SRV_STATUS_LIMITED_REGIONAL - Limited regional service – 0x04 - SYS_SRV_STATUS_PWR_SAVE - Power save
isPrefDataPath	• Whether the RAT is the preferred data path: • Values – 0x00 - Not preferred – 0x01 - Preferred
TlvPresent	• Tlv Present or not

8.658.2 Field Documentation

8.658.2.1 BYTE NR5GSerStatTlv::isPrefDataPath

8.658.2.2 BYTE NR5GSerStatTlv::srvStatus

8.658.2.3 BYTE NR5GSerStatTlv::TlvPresent

8.658.2.4 BYTE NR5GSerStatTlv::trueSrvStatus

8.659 NR5GSystemInfoTlv Struct Reference

Data Fields

- BYTE srvDomainValid
- BYTE srvDomain
- BYTE srvCapValid
- BYTE srvcapability
- BYTE roamStatusValid
- BYTE roamStatus
- BYTE sysForbiddenValid
- BYTE sysForbidden
- BYTE lacValid
- WORD lac
- BYTE cellIdValid
- ULONG cellId
- BYTE regRejectInfoValid
- BYTE rejectSrvDomain
- BYTE rejCause
- BYTE nwIdValid
- CHAR MCC [PLMN_LENGTH]
- CHAR MNC [PLMN_LENGTH]
- BYTE tacValid
- WORD tac
- BYTE TlvPresent

8.659.1 Detailed Description

This structure contains NR5G System Info parameters.

Parameters

srvDomainValid	• Indicates whether the service domain is valid.
srvDomain	• Service domain registered on the system. – Values: * 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service * 0x01 - SYS_SRV_DOMAIN_CS_ONLY - Circuit-switched only * 0x02 - SYS_SRV_DOMAIN_PS_ONLY - Packet-switched only * 0x03 - SYS_SRV_DOMAIN_CS_PS - Circuit-switched and packet-switched * 0x04 - SYS_SRV_DOMAIN_CAMPED -Camped
srvCapValid	• Indicates whether the service capability is valid.

srvCapability	• Current system service capability. – Values: * 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service * 0x01 - SYS_SRV_DOMAIN_CS_ONLY - Circuit-switched only * 0x02 - SYS_SRV_DOMAIN_PS_ONLY - Packet-switched only * 0x03 - SYS_SRV_DOMAIN_CS_PS - Circuit-switched and packet-switched * 0x04 - SYS_SRV_DOMAIN_CAMPED - Camped
roamStatusValid	• Indicates whether the roaming status is valid.
roamStatus	• Current roaming status. – Values: * 0x00 - SYS_ROAM_STATUS_OFF - Off * 0x01 - SYS_ROAM_STATUS_ON - On * 0x02 - SYS_ROAM_STATUS_BLINK - Blinking * 0x03 - SYS_ROAM_STATUS_OUT_OF_NEIGHBORHOOD - Out of the neighborhood * 0x04 - SYS_ROAM_STATUS_OUT_OF_BLDG - Out of the building * 0x05 - SYS_ROAM_STATUS_PREF_SYS - Preferred system * 0x06 - SYS_ROAM_STATUS_AVAIL_SYS - Available system * 0x07 - SYS_ROAM_STATUS_ALLIANCE_PARTNER - Alliance partner * 0x08 - SYS_ROAM_STATUS_PREMIUM_PARTNER - Premium partner * 0x09 - SYS_ROAM_STATUS_FULL_SVC - Full service * 0x0A - SYS_ROAM_STATUS_PARTIAL_SVC -Partial service * 0x0B - SYS_ROAM_STATUS_BANNER_ON -Banner is on * 0x0C - SYS_ROAM_STATUS_BANNER_OFF -Banner is off Remainder of the values are per 3GPP2 C.R1001-F. Values from 0x02 onward are only applicable for 3GPP2.
sysForbidden-Valid	• Indicates whether the forbidden system is valid.
sysForbidden	• Whether the system is forbidden: • 0x00 Not forbidden • 0x01 Forbidden
lacValid	• Indicates whether the location area code is valid.
lac	• Location area code (only applicable for 3GPP).
cellIdValid	• Indicates whether the cell ID is valid.
cellId	• Cell ID.

rejectSrvDomain	• Type of service domain in which the registration is rejected. • Values: • 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service • 0x01 - SYS_SRV_DOMAIN_CS_ONLY - Circuit-switched only • 0x02 - SYS_SRV_DOMAIN_PS_ONLY - Packet-switched only • 0x03 - SYS_SRV_DOMAIN_CS_PS - Circuit-switched and packet-switched • 0x04 - SYS_SRV_DOMAIN_CAMPED - Camped
rejCause	• Reject cause values sent are specified in 3GPP TS • 24.008 Sections 10.5.3.6 and 10.5.5.14, and 3GPP • TS 24.301 Section 9.9.3.9.
nwIdValid	• Indicates whether the network ID is valid.
MCC	• MCC digits in ASCII characters.For CDMA, the MCC wildcard value is returned as{3, 0xFF, 0xFF}
MNC	• MNC digits in ASCII characters. For this field: • Unused byte is set to 0xFF • In the case of two-digit MNC values, the third (unused) digit is set to 0xFF. For example, 15 (a two-digit MNC) is reported using the byte stream 0x35 0x31 0xFF.For CDMA, the MNC wildcard value is returned as {7, 0xFF, 0xFF}.
tacValid	• Indicates whether the tracking area code is valid.
tac	• Tracking area code (only applicable for NR5G).
TlvPresent	• Tlv Present or not

8.659.2 Field Documentation

8.659.2.1 ULONG NR5GSystemInfoTlv::cellId

8.659.2.2 BYTE NR5GSystemInfoTlv::cellIdValid

8.659.2.3 WORD NR5GSystemInfoTlv::lac

8.659.2.4 BYTE NR5GSystemInfoTlv::lacValid

8.659.2.5 CHAR NR5GSystemInfoTlv::MCC[PLMN_LENGTH]

8.659.2.6 CHAR NR5GSystemInfoTlv::MNC[PLMN_LENGTH]

8.659.2.7 BYTE NR5GSystemInfoTlv::nwIdValid

8.659.2.8 BYTE NR5GSystemInfoTlv::regRejectInfoValid

8.659.2.9 BYTE NR5GSystemInfoTlv::rejCause

8.659.2.10 BYTE NR5GSystemInfoTlv::rejectSrvDomain

8.659.2.11 BYTE NR5GSystemInfoTlv::roamStatus

8.659.2.12 BYTE NR5GSystemInfoTlv::roamStatusValid

8.659.2.13 BYTE NR5GSystemInfoTlv::srvcapability

8.659.2.14 BYTE NR5GSystemInfoTlv::srvCapValid

8.659.2.15 BYTE NR5GSystemInfoTlv::srvDomain

8.659.2.16 BYTE NR5GSystemInfoTlv::srvDomainValid

8.659.2.17 BYTE NR5GSystemInfoTlv::sysForbidden

8.659.2.18 BYTE NR5GSystemInfoTlv::sysForbiddenValid

8.659.2.19 WORD NR5GSystemInfoTlv::tac

8.659.2.20 BYTE NR5GSystemInfoTlv::tacValid

8.659.2.21 BYTE NR5GSystemInfoTlv::TlvPresent

8.660 NSSAudioCtrl Struct Reference

Data Fields

- BYTE upLink
- BYTE downLink

8.660.1 Detailed Description

This structure contains National Supplementary Services - Audio Control Information

Parameters

upLink	• Values as per[S24, 4.10 Reservation response].
downLink	• Values as per[S24, 4.10 Reservation response].

8.660.2 Field Documentation

8.660.2.1 BYTE NSSAudioCtrl::downLink

8.660.2.2 BYTE NSSAudioCtrl::upLink

8.661 NWProfile Struct Reference

Data Fields

- WORD tech
- BYTE * pProfSz
- WORD * pProfValues

8.661.1 Detailed Description

This structure contains Network supported QoS profile

Parameters

tech	Technology on which the network supported QoS profiles are being returned: • CDMA - 0x8001
exponent	

8.661.2 Field Documentation

8.661.2.1 BYTE* NWProfile::pProfSz

8.661.2.2 WORD* NWProfile::pProfValues

8.661.2.3 WORD NWProfile::tech

8.662 omaDmConfigTlv Struct Reference

Data Fields

- BYTE state
- BYTE userInputReq
- USHORT userInputTimeout
- USHORT alertmsglength
- BYTE alertmsg [256]

8.662.1 Detailed Description

This structure will hold the SwiOmaDmConfig session parameters information.

Parameters

state	• 0x01 - OMA-DM Read Request • 0x02 - OMA-DM Change Request • 0x03 - OMA-DM Config Complete

userInputReq	- Bit mask of available user inputs • 0x00 - No user input required.Informational indication • 0x01 - Accept • 0x02 - Reject
userInput-Timeout	• Timeout for user input in minutes. A value of 0 means no time-out
alertmsglength	• Length of Alert message string in bytes
alertmsg	• Alert message in UCS2 (Max 256 characters)

8.662.2 Field Documentation

8.662.2.1 BYTE omaDmConfigTlv::alertmsg[256]

8.662.2.2 USHORT omaDmConfigTlv::alertmsglength

8.662.2.3 BYTE omaDmConfigTlv::state

8.662.2.4 BYTE omaDmConfigTlv::userInputReq

8.662.2.5 USHORT omaDmConfigTlv::userInputTimeout

8.663 omaDmConfigTlvExt Struct Reference

Data Fields

- BYTE state
- BYTE userInputReq
- USHORT userInputTimeout
- USHORT alertmsglength
- BYTE alertmsg [256]

8.663.1 Detailed Description

This structure will hold the SwiOmaDmConfig session parameters information.

Parameters

state	• 1 - reserved • 2 - reserved • 3 - reserved • 4 - CI DC Success • 5 - CI DC Failure • 6 - User/device initiated PRL update success. • 7 - User/device initiated PRL update failure. • 8 - HFA DC session start • 9 - HFA DC sucess. • 10 - HFA is cancelled. • 11 - HFA retry. UI Screen 13[1] with 0 percent progress bar should be shown. • 12 - HFA fail after 5 retries. UI Screen 2[1] should be displayed. • 13 - HFA retry down counter. Used to update the process bar of UI Screen 13[1]. • 14 - HFA PRL session start, UI screen 4[1] should be displayed. • 15 - HFA PRL update success. • 16 - Device is launching a NI session. UI Screen 1[1] should be displayed. • 17 - An empty session. UI Screen 2[1] should be displayed. • 18 - No network coverage. • 19 - HFA is not enabled. • 20 - CI DC Start, UI Screen 1[1] should be displayed. • 21 - CI PRL start, UI screen 4[1] should be displayed. • 22 - HFA PRL updates fail. • 23 - Device reboot. • 24 - CI DC is cancelled. • 25 - User/device initiated PRL update is cancelled. • 26 - NI session is cancelled. • 27 - Current NI session is not enabled. • 28 - NI DC success. • 29 - NI DC Fail. • 30 - NI PRL success • 31 - NI PRL fail. • 32 - Reserved • 33 - NI fumo fail • 34 - NI session fail, unable to point out the session type.
user_input_req	- OMA task stop to wait user's input if this field is valid. until user input selection or after "UI Timer out (next field). In the case of timeout, a default selection of "YES/OK" is accepted. Note that this option is valid when DM state is 4/6/12/28/30. 0 - user/host doesn't need to input anything, and OMA task doesn't blocked by UI. 1 - user/host must input "YES/OK/CANCEL". 2 - User/host must input "NO/CANCEL". 3 - user/host must input "YES/OK/NO/CANCEL.
user_input_-timeout	• Timeout for user input in seconds. This indicates how many seconds OMA task stop to wait for host/user's response.
alertmsglength	• Length of Alert message string in word(16-bit)

alertmsg	• Alert message in UCS2 (Max 256 characters) • This string is printed by host

8.663.2 Field Documentation

8.663.2.1 BYTE omaDmConfigTlvExt::alertmsg[256]

8.663.2.2 USHORT omaDmConfigTlvExt::alertmsglength

8.663.2.3 BYTE omaDmConfigTlvExt::state

8.663.2.4 BYTE omaDmConfigTlvExt::userInputReq

8.663.2.5 USHORT omaDmConfigTlvExt::userInputTimeout

8.664 omaDmFotaTlv Struct Reference

Data Fields

- BYTE state
- BYTE userInputReq
- USHORT userInputTimeout
- ULONG fwdloadsize
- ULONG fwloadComplete
- USHORT updateCompleteStatus
- BYTE severity
- USHORT versionlength
- BYTE version [256]
- USHORT namelength
- BYTE package_name [256]
- USHORT descriptionlength
- BYTE description [256]
- BYTE sessionType

8.664.1 Detailed Description

This structure will hold the SwiOmaDmFota session parameters information.

Parameters

state	• 0x01 - No Firmware available • 0x02 - Query Firmware Download • 0x03 - Firmware Downloading • 0x04 - Firmware downloaded • 0x05 - Query Firmware Update • 0x06 - Firmware updating • 0x07 - Firmware updated

userInputReq	- Bit mask of available user inputs • 0x00 - No user input required.Informational indication • 0x01 - Accept • 0x02 - Reject
userInput-Timeout	• Timeout for user input in minutes. A value of 0 means no time-out
fwdloadsize	• The size (in bytes) of the firmware update package
fwloadComplete	• The number of bytes downloaded. Need to determine how often to send this message for progress bar notification. Every 500ms or 5% increment.
update-CompleteStatus	• This field should be looked at only when the OMADM session is complete. • See qaGobiApiTableSwiOMADMUpdateCompleteStatus.h for update complete status.
severity	• 0x01 - Mandatory • 0x02 - Optional
versionlength	• Length of FW Version string in bytes
version	• FW Version string in ASCII (Max 256 characters)
namelength	• Length Package Name string in bytes
package_name	• Package Name in UCS2 (Max 256 characters)
descriptionlength	• Length of description in bytes
description	• Description of Update Package in USC2 (Max 256 characters)
sessionType	• 0x00 - Client initiated • 0x01 - Network initiated

8.664.2 Field Documentation

8.664.2.1 BYTE omaDmFotaTlv::description[256]

8.664.2.2 USHORT omaDmFotaTlv::descriptionlength

8.664.2.3 ULONG omaDmFotaTlv::fwdloadsize

8.664.2.4 ULONG omaDmFotaTlv::fwloadComplete

8.664.2.5 USHORT omaDmFotaTlv::namelength

8.664.2.6 BYTE omaDmFotaTlv::package_name[256]

8.664.2.7 BYTE omaDmFotaTlv::sessionType

8.664.2.8 BYTE omaDmFotaTlv::severity

8.664.2.9 BYTE omaDmFotaTlv::state

8.664.2.10 USHORT omaDmFotaTlv::updateCompleteStatus

8.664.2.11 BYTE omaDmFotaTlv::userInputReq

8.664.2.12 USHORT omaDmFotaTlv::userInputTimeout

8.664.2.13 BYTE omaDmFotaTlv::version[256]

8.664.2.14 USHORT omaDmFotaTlv::versionlength

8.665 omaDmFotaTlvExt Struct Reference

Data Fields

- BYTE state
- BYTE reserved
- USHORT userInputTimeout
- ULONG packageSize
- ULONG receivedBytes
- USHORT fumoResultCode
- USHORT versionlength
- BYTE version [256]
- USHORT namelength
- BYTE package_name [256]
- USHORT descriptionlength
- BYTE description [256]

8.665.1 Detailed Description

This structure will hold the SwiOmaDmFota session parameters information.

Parameters

state	• 0x01 - No Firmware available • 0x02 - reserved • 0x03 - Update progress bar, UI screen 7[1] should be displayed • 0x04 - reserved • 0x05 - FUMO image download success, UI screen 8[1] should be displayed • 0x06 - reserved • 0x07 - FUMO image installation result, used to return error code. • 0x08 - FUMO session start • 0x09 - UI Screen 7[1] with 0 percent bar should be displayed • 0x0A - FUMO image installation is cancelled by user. • 0x0B - FUMO session fail • 0x0C - Device is sending a report to OMA Server. • 0x0D - Report to server success. • 0x0E - Report to server fails. • 0x0F - reserved • 0x10 - FUMO session is cancelled before image download success. • 0x11 - UI Screen 16[1] should be displayed, FUMO delay option, OMA task is blocked until a valid response is recevied.
reserved	- For sprint reserved
user_input_timeout	• How many seconds OMA task stop to wait for user/host response.
packageSize	• The size (in bytes) of the firmware update package (only valid for states 3/5/7).
receivedBytes	• The number of bytes downloaded. Useful for FUMO state 3.
fumoResultCode	• Used when fumo state is 7/11. REsult code of FUMO image installation – 200 image install success • Others: image install fail
versionlength	• Length of FW Version string in bytes
version	• FW Version string in ASCII (Max 256 characters)
namelength	• Length Package Name string in bytes
package_name	• Package Name in UCS2 (Max 256 characters)
descriptionlength	• Length of description in bytes

description	• Description of Update Package in USC2 (Max 256 characters)

8.665.2 Field Documentation

8.665.2.1 BYTE omaDmFotaTlvExt::description[256]

8.665.2.2 USHORT omaDmFotaTlvExt::descriptionlength

8.665.2.3 USHORT omaDmFotaTlvExt::fumoResultCode

8.665.2.4 USHORT omaDmFotaTlvExt::namelength

8.665.2.5 BYTE omaDmFotaTlvExt::package_name[256]

8.665.2.6 ULONG omaDmFotaTlvExt::packageSize

8.665.2.7 ULONG omaDmFotaTlvExt::receivedBytes

8.665.2.8 BYTE omaDmFotaTlvExt::reserved

8.665.2.9 BYTE omaDmFotaTlvExt::state

8.665.2.10 USHORT omaDmFotaTlvExt::userInputTimeout

8.665.2.11 BYTE omaDmFotaTlvExt::version[256]

8.665.2.12 USHORT omaDmFotaTlvExt::versionlength

8.666 omaDmNotificationsTlv Struct Reference

Data Fields

- BYTE notification
- USHORT sessionStatus

8.666.1 Detailed Description

This structure will hold the SwiOmaDmConfig session parameters information.

Parameters

notification	• 0x01 - GPS settings change • 0x02 - Device reset • 0x03 - Device factory reset • 0x04 - CI-DC Session start • 0x05 - CI-DC Session end • 0x06 - CI-PRL Session start • 0x07 - CI-PRL Session end • 0x08 - CI-FUMO Session start • 0x09 - CI-FUMO session end • 0x0A - HFA-DC Session start • 0x0B - HFA-DC Session end • 0x0C - HFA-PRL Session start • 0x0D - HFA-PRL Session end • 0x0E - HFA-FUMO Session start • 0x0F - HFA-FUMO session end • 0x10 - NI Session start • 0x11 - NI session end
sessionStatus	• This field will set to the session status for notifications that occur at the end of a session, zero for all other notifications • See qaGobiApiTableSwiOMADMSessionStatus.h for session completion code.

8.666.2 Field Documentation

8.666.2.1 BYTE omaDmNotificationsTlv::notification

8.666.2.2 USHORT omaDmNotificationsTlv::sessionStatus

8.667 operatorNameString Struct Reference

Data Fields

- BYTE PLMNName [255]

8.667.1 Detailed Description

This structure contains Operator Name String as defined in CPHS4_2.WW6(Feb 27, 1997) (Section B.4.1.2)from multiple sources.

Parameters

PLMNName	• PLMN name must be coded in a default 7-bit alphabet with b8 set to 0.

8.667.2 Field Documentation

8.667.2.1 BYTE operatorNameString::PLMNName[255]

8.668 OperatorPLMNData Struct Reference

Data Fields

- BYTE mcc [3]
- BYTE mnc [3]
- WORD lac1
- WORD lac2
- BYTE PLMNRecID

8.668.1 Detailed Description

This structure contains Operator PLMN Data from multiple sources.

Parameters

mcc	• MCC in ASCII string (a value of D in any of the digits is to be used to indicate a "wild" value for that corresponding digit).
mnc	• MNC in ASCII string (a value of D in any of the digits is to be used to indicate a "wild" value for that corresponding digit; digit 3 in MNC is optional and when not present, will be set as ASCII F).
lac1	• Location area code 1.
lac2	• Location area code 1.
PLMNRecID	• PLMN network name record identifier.

8.668.2 Field Documentation

8.668.2.1 WORD OperatorPLMNData::lac1

8.668.2.2 WORD OperatorPLMNData::lac2

8.668.2.3 BYTE OperatorPLMNData::mcc[3]

8.668.2.4 BYTE OperatorPLMNData::mnc[3]

8.668.2.5 BYTE OperatorPLMNData::PLMNRecID

8.669 operatorPLMNList Struct Reference

Data Fields

- WORD numInstance
- OperatorPLMNData PLMNData [255]

8.669.1 Detailed Description

This structure contains Operator PLMN List as defined in 3GPP TS 31.102 (Section 4.2.59) from multiple sources.

Parameters

numInstance	• Number of sets of the elements.
PLMNData	• Refer OperatorPLMNLData for details (Optional).

8.669.2 Field Documentation

8.669.2.1 WORD operatorPLMNList::numInstance

8.669.2.2 OperatorPLMNData operatorPLMNList::PLMNData[255]

8.670 pack_dms_ActivateAutomatic_t Struct Reference

Data Fields

- uint8_t actCode [81]

8.670.1 Detailed Description

This structure contains UIM activate automation information

Parameters

actCode	• NULL-terminated string representing activation code (maximum string length of 12). • Specific carrier requirements may dictate actual activation code that is applicable, e.g., "∗22899"

8.670.2 Field Documentation

8.670.2.1 uint8_t pack_dms_ActivateAutomatic_t::actCode[81]

8.671 pack_dms_GetCustFeaturesV2_t Struct Reference

Data Fields

- uint8_t cust_id [64+1]
- uint8_t list_type
- uint16_t Tlvresult

8.671.1 Detailed Description

This structure contains which customization id or the list type want to retrieve from modem. This TLV is only applicable for 9x30 modules so far

Parameters

cust_id	• Customization ID (Maximum 64 bytes) • NULL terminated ASCII string.
list_type	• list type requested
Tlvresult	• Pack Result

8.671.2 Field Documentation

8.671.2.1 uint8_t pack_dms_GetCustFeaturesV2_t::cust_id[64+1]

8.671.2.2 uint8_t pack_dms_GetCustFeaturesV2_t::list_type

8.671.2.3 uint16_t pack_dms_GetCustFeaturesV2_t::Tlvresult

8.672 pack_dms_ResetToFactoryDefaults_t Struct Reference

Data Fields

- uint8_t spc [6]

8.672.1 Detailed Description

This structure contains UIM reset to factory default information

Parameters

spc[IN]	• Service programming code in ASCII format (digits 0 to 9 only)

8.672.2 Field Documentation

8.672.2.1 uint8_t pack_dms_ResetToFactoryDefaults_t::spc[6]

8.673 pack_dms_SetActivationStatusCallback_t Struct Reference

Data Fields

- uint8_t activationState

8.673.1 Detailed Description

This structure is used to store Set Service Activation Status callback parameter pack.

Parameters

activationState	• Service activation state. • Values – 0 - Do not report – 1 - Report activation state changes

8.673.2 Field Documentation

8.673.2.1 uint8_t pack_dms_SetActivationStatusCallback_t::activationState

8.674 pack_dms_SetCrashAction_t Struct Reference

Data Fields

- uint8_t crashAction

8.674.1 Detailed Description

This structure is used to store pack_dms_SetCrashAction parameters.

Parameters

crashAction	• 0 - USB Memory Download. Modem will reset after a crash and will stay in USB download mode with only DM port enumerated. • 1 - Reset. Modem will reset and come back in ONLINE mode. Minimal crash data will be available and can be extracted with at!gcdump? AT command • 2 - No Action

8.674.2 Field Documentation

8.674.2.1 uint8_t pack_dms_SetCrashAction_t::crashAction

8.675 pack_dms_SetCustFeature_t Struct Reference

Data Fields

- uint32_t GpsEnable
- uint8_t DisableIMSI
- uint16_t IPFamSupport
- uint8_t RMAutoConnect
- uint8_t GPSSel
- uint8_t SMSSupport
- uint8_t IsVoiceEnabled
- uint8_t DHCPRelayEnabled

- uint8_t GPSLPM

8.675.1 Detailed Description

This structure contains current settings of custom features pack parameters

Parameters

GpsEnable	• describes if GPS is enabled or disabled • values: – 0x00 - GPS is disabled – 0x01 - GPS is enabled
DisableIMSI	• optional 1 byte parameter • describes if IMSI display is enabled or disabled • values: – 0x00 - Allow display of IMSI – 0x01 - Do not display IMSI
IPFamSupport	• optional 2 byte BitMask • bitmask representing the IP families supported • values: – 0x01 - IPv4 – 0x02 - IPv6 – 0x04 - IPv4v6
RMAutoConnect	• optional 1 byte parameter • QMI Mode RM Net Auto Connect Support • values: – 0x00 - Not Supported – 0x01 - Supported
GPSSel	• optional 1 byte parameter • GPS Antenna Select • values: – 0x00 - Dedicated GPS Port – 0x01 - GPS Rx over AUX Port – 0x02 - GPS Rx over dedicated GPS port with no bias voltage applied
SMSSupport	• optional 1 byte parameter • SMS support • values: – 0x00 - Not supported – 0x01 - supported • Used to determine whether or not to hide SMS from user

IsVoiceEnabled	• optional 1 byte parameter • Voice support • values: – 0x00 - Enable voice on both AT and QMI interface (default) – 0x01 - Reserved – 0x02 - Disable voice on both AT and QMI interface
DHCPRelay-Enabled	• optional 1 byte parameter • DHCP Relay support • values: – 0x00 - Disable DHCP relay – 0x01 - Enable DHCP relay
GPSLPM	• optional 1 byte parameter • GPSLPM support • values: – 0x00 - Enable GPS in Low Power Mode – 0x01 - Disable GPS in Low Power Mode

8.675.2 Field Documentation

8.675.2.1 uint8_t pack_dms_SetCustFeature_t::DHCPRelayEnabled

8.675.2.2 uint8_t pack_dms_SetCustFeature_t::DisableIMSI

8.675.2.3 uint32_t pack_dms_SetCustFeature_t::GpsEnable

8.675.2.4 uint8_t pack_dms_SetCustFeature_t::GPSLPM

8.675.2.5 uint8_t pack_dms_SetCustFeature_t::GPSSel

8.675.2.6 uint16_t pack_dms_SetCustFeature_t::IPFamSupport

8.675.2.7 uint8_t pack_dms_SetCustFeature_t::IsVoiceEnabled

8.675.2.8 uint8_t pack_dms_SetCustFeature_t::RMAutoConnect

8.675.2.9 uint8_t pack_dms_SetCustFeature_t::SMSSupport

8.676 pack_dms_SetCustFeaturesV2_t Struct Reference

Data Fields

- uint8_t cust_id [64+1]
- uint16_t value_length
- uint8_t cust_value [8+1]
- uint16_t Tlvresult

8.676.1 Detailed Description

This structure contains customization settings set to modem pack

Parameters

cust_id	• Customization ID (Maximum 64 bytes) • NULL terminated ASCII string.
value_length	• length of cust_value field
cust_value	• Customization Setting Value (Maximum 8 bytes)
Tlvresult	• Pack Result

8.676.2 Field Documentation

8.676.2.1 uint8_t pack_dms_SetCustFeaturesV2_t::cust_id[64+1]

8.676.2.2 uint8_t pack_dms_SetCustFeaturesV2_t::cust_value[8+1]

8.676.2.3 uint16_t pack_dms_SetCustFeaturesV2_t::Tlvresult

8.676.2.4 uint16_t pack_dms_SetCustFeaturesV2_t::value_length

8.677 pack_dms_SetEventReport_t Struct Reference

Data Fields

- uint8_t mode

8.677.1 Detailed Description

This structure is used to store pack_dms_SetEventReport parameters.

Parameters

mode	• Operating Mode • 0 - reset • 1 - set • 2 - no change

8.677.2 Field Documentation

8.677.2.1 uint8_t pack_dms_SetEventReport_t::mode

8.678 pack_dms_SetIndicationRegister_t Struct Reference

Data Fields

- uint8_t PSMStatus
- uint8_t PSMCfgChangeInfo
- uint8_t RptIMSCapability

8.678.1 Detailed Description

This structure contains the DMS Register Indication request parameters

Parameters

PSMStatus	• Power Save Mode Status • Values – 0 - Do not report – 1 - Report PSM status – 2 - No Change
PSMCfgChange-Info	• Power Save Mode Configuration Change Information • Values – 0 - Do not report – 1 - Report Power Save Mode configuration changes – 2 - No Change
RptIMS-Capability	• Report IMS Capability • Values – 0 - Do not report – 1 - Report IMS capability – 2 - No Change

8.678.2 Field Documentation

8.678.2.1 uint8_t pack_dms_SetIndicationRegister_t::PSMCfgChangeInfo

8.678.2.2 uint8_t pack_dms_SetIndicationRegister_t::PSMStatus

8.678.2.3 uint8_t pack_dms_SetIndicationRegister_t::RptIMSCapability

8.679 pack_dms_SetPower_t Struct Reference

Data Fields

- uint32_t mode
- uint16_t Tlvresult

8.679.1 Detailed Description

Structure to store pack the operating mode of the device.

Parameters

mode	• Selected operating mode – See qaGobiApiTablePowerModes.h for power modes
Tlvresult	• pack Tlv Result.

8.679.2 Field Documentation

8.679.2.1 uint32_t pack_dms_SetPower_t::mode

8.679.2.2 uint16_t pack_dms_SetPower_t::Tlvresult

8.680 pack_dms_SetUSBComp_t Struct Reference

Data Fields

- uint8_t USBComp
- uint16_t Tlvresult

8.680.1 Detailed Description

This structure is used to store USB composition information pack paramters

Parameters

USBComp	• Current USB Composition • Values: – 0..5 - Reserved (non-QMI) – 6 - DM NMEA AT QMI – 7 - DM NMEA AT QMI1 QMI2 QMI3 – 8 - DM NMEA AT MBIM – 9 - MBIM – 10 - NMEA MBIM – 11 - DM MBIM – 12 - DM NMEA MBIM 13-22 are combined compositions. One is for Win8 MBIM interfaces, another is for legacy QMI interfaces – 13 - 6 for QMI, 8 for MBIM – 14 - 6 for QMI, 9 for MBIM – 15 - 6 for QMI, 10 for MBIM – 16 - 6 for QMI, 11 for MBIM – 17 - 6 for QMI, 12 for MBIM – 18 - 7 for QMI, 8 for MBIM – 19 - 7 for QMI, 9 for MBIM – 20 - 7 for QMI, 10 for MBIM – 21 - 7 for QMI, 11 for MBIM – 22 - 7 for QMI, 12 for MBIM
Tlvresult	• pack Tlv Result.

8.680.2 Field Documentation

8.680.2.1 uint16_t pack_dms_SetUSBComp_t::Tlvresult

8.680.2.2 uint8_t pack_dms_SetUSBComp_t::USBComp

8.681 pack_dms_SLQSDmsSwiIndicationRegister_t Struct Reference

Data Fields

- uint8_t resetInfoInd

8.681.1 Detailed Description

This structure contains set registration state for different indication pack

Parameters

resetInfoInd[IN]	• Values – 0 - Disable – 1 - Enable

8.681.2 Field Documentation

8.681.2.1 uint8_t pack_dms_SLQSDmsSwiIndicationRegister_t::resetInfoInd

8.682 pack_dms_SLQSSetPowerSaveModeConfig_t Struct Reference

Data Fields

- uint8_t * pPsmEnableState
- uint32_t * pActiveTimer
- uint32_t * pPeriodicUpdateTimer

8.682.1 Detailed Description

This structure contains the Power Save Mode (PSM) configuration parameter.

Parameters

pPsmEnable-State	[Optional] • PSM Enable State • Values – 0 - PSM is not enabled – 1 - PSM is enabled
pActiveTimer	[Optional] • Active Timer • PSM active timer value (in seconds). • ActiveTimer encoding is the GPRS timer 2 encoding specified in Table 10.5.172 of 3GPP TS 24.008.
pPeriodic-UpdateTimer	[Optional] • Periodic Update Timer • PSM periodic update timer value (in seconds) • Periodic Update Timer encoding is the GPRS timer 3 encoding specified in Table 10.5.163a of 3GPP TS 24.008.

8.682.2 Field Documentation

8.682.2.1 uint32_t* pack_dms_SLQSSetPowerSaveModeConfig_t::pActiveTimer

8.682.2.2 uint32_t* pack_dms_SLQSSetPowerSaveModeConfig_t::pPeriodicUpdateTimer

8.682.2.3 uint8_t* pack_dms_SLQSSetPowerSaveModeConfig_t::pPsmEnableState

8.683 pack_dms_SLQSSwiGetCrashInfo_t Struct Reference

Data Fields

- uint8_t clear

8.683.1 Detailed Description

This structure contains pack_dms_SLQSSwiGetCrashInfo parameters

Parameters

clear	• 0 - do not clear crash data after response • 1 - clear crash data after response

8.683.2 Field Documentation

8.683.2.1 uint8_t pack_dms_SLQSSwiGetCrashInfo_t::clear

8.684 pack_dms_SLQSSwiSetDyingGaspCfg_t Struct Reference

Data Fields

- uint8_t ∗ pDestSMSNum
- uint8_t ∗ pDestSMSContent

8.684.1 Detailed Description

This structure is used to store pack_dms_SLQSSwiSetDyingGaspCfg parameters

Parameters

pDestSMSNum[-IN]	• SMS Destination Number as string of 8 bit ASCII Characters Max 20 chars. • Optional parameter.
pDestSMS-Content[IN]	• SMS COntent as a string of 8 bit ASCII text characters Max 160 chars. • Optional parameter.

8.684.2 Field Documentation

8.684.2.1 uint8_t∗ pack_dms_SLQSSwiSetDyingGaspCfg_t::pDestSMSContent

8.684.2.2 uint8_t∗ pack_dms_SLQSSwiSetDyingGaspCfg_t::pDestSMSNum

8.685 pack_dms_SLQSSwiSetHostDevInfo_t Struct Reference

Data Fields

- char manString [255]
- char modelString [255]
- char swVerString [255]
- char plasmaIDString [255]
- char hostID [255]

8.685.1 Detailed Description

This structure contains SWI set host device info unpack information

Parameters

manString[IN]	• Host Device Manufacturer Name • Null terminated ASCII String
modelString[IN]	• Host Device Model String • Null terminated ASCII string.
swVerString[IN]	• Host Device Software Version String • Null terminated ASCII string
plasmaIDString[-IN]	• Host Device Plasma ID String • Null terminated alphanumeric ASCII string
HostID[IN]	• Device Host ID String • Null terminated alphanumeric ASCII string

8.685.2 Field Documentation

8.685.2.1 char pack_dms_SLQSSwiSetHostDevInfo_t::hostID[255]

8.685.2.2 char pack_dms_SLQSSwiSetHostDevInfo_t::manString[255]

8.685.2.3 char pack_dms_SLQSSwiSetHostDevInfo_t::modelString[255]

8.685.2.4 char pack_dms_SLQSSwiSetHostDevInfo_t::plasmaIDString[255]

8.685.2.5 char pack_dms_SLQSSwiSetHostDevInfo_t::swVerString[255]

8.686 pack_dms_SLQSSwiSetOSInfo_t Struct Reference

Data Fields

- char nameString [255]
- char versionString [255]

8.686.1 Detailed Description

This structure contains SWI set host OS info pack information

Parameters

nameString[IN]	Host device manufacture String • NULL terminated ASCII string.
VersionString[IN]	Host device model String • NULL terminated ASCII string.

8.686.2 Field Documentation

8.686.2.1 char pack_dms_SLQSSwiSetOSInfo_t::nameString[255]

8.686.2.2 char pack_dms_SLQSSwiSetOSInfo_t::versionString[255]

8.687 pack_dms_SwiSetEventReport_t Struct Reference

Data Fields

- uint8_t * pTempReport
- uint8_t * pVoltReport
- uint8_t * pUIMStatusReport

8.687.1 Detailed Description

This structure is used to store pack_dms_SwiSetEventReport parameters.

Parameters

pTempReport	(optional) • Temperature indicator. – 0 - Do not report – 1 - Report when state changes
pVoltReport	(optional) • Voltage Indicator. – 0 - Do not report – 1 - Report when state changes
pUIMStatus-Report	(optional) • UIM status Indicator. – 0 - Do not report – 1 - Report when state changes

8.687.2 Field Documentation

8.687.2.1 uint8_t* pack_dms_SwiSetEventReport_t::pTempReport

8.687.2.2 uint8_t* pack_dms_SwiSetEventReport_t::pUIMStatusReport

8.687.2.3 uint8_t* pack_dms_SwiSetEventReport_t::pVoltReport

8.688 pack_dms_SwiUimSelect_t Struct Reference

Data Fields

- uint8_t uim_select

8.688.1 Detailed Description

This structure is used to store pack_dms_SwiUimSelect parameters.

Parameters

uim_select	• Selection of UIM Card – 0 - External UIM Interface – 1 - Embedded UIM – 2 - Remote UIM – 3 - Auto switch

Note

Auto switch is applicable only if UIMAUTOSWITCH feature is enabled. This feature will activate the auto-switch mechanism if it is inactive.

8.688.2 Field Documentation

8.688.2.1 uint8_t pack_dms_SwiUimSelect_t::uim_select

8.689 pack_dms_UIMChangePIN_t Struct Reference

Data Fields

- uint8_t id
- uint8_t oldValue [255]
- uint8_t newValue [255]

8.689.1 Detailed Description

This structure contains UIM Unblock PIN Information

Parameters

id[IN]	• PIN ID – 1 (PIN1 / CHV1) – 2 (PIN2 / CHV2)
oldValue[IN]	• Old PIN value of PIN to change
newValue[IN]	• New PIN value of PIN to change

8.689.2 Field Documentation

8.689.2.1 uint8_t pack_dms_UIMChangePIN_t::id

8.689.2.2 uint8_t pack_dms_UIMChangePIN_t::newValue[255]

8.689.2.3 uint8_t pack_dms_UIMChangePIN_t::oldValue[255]

8.690 pack_dms_UIMGetControlKeyStatus_t Struct Reference

Data Fields

- uint8_t facility

8.690.1 Detailed Description

This structure contains UIM get control key status information

Parameters

facility[IN]	• MT or network facility – 0 - Network Personalization (PN) – 1 - Network Subset Personalization (PU) – 2 - Service Provider Personalization (PP) – 3 - Corporate Personalization (PC) – 4 - UIM Personalization (PF)

8.690.2 Field Documentation

8.690.2.1 uint8_t pack_dms_UIMGetControlKeyStatus_t::facility

8.691 pack_dms_UIMGetICCID_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.691.1 Detailed Description

This structure contains UIM Get ICCID pack

Parameters

Tlvresult	• Pack result.

8.691.2 Field Documentation

8.691.2.1 swi_uint256_t pack_dms_UIMGetICCID_t::ParamPresenceMask

8.691.2.2 uint16_t pack_dms_UIMGetICCID_t::Tlvresult

8.692 pack_dms_UIMSetControlKeyProtection_t Struct Reference

Data Fields

- uint8_t facility
- uint8_t facilityState
- uint8_t facilityCk [8]

8.692.1 Detailed Description

This structure contains UIM Set control key protection information

Parameters

facility[IN]	• MT or network facility – 0 - Network Personalization (PN) – 1 - Network Subset Personalization (PU) – 2 - Service Provider Personalization (PP) – 3 - Corporate Personalization (PC) – 4 - UIM Personalization (PF)
facilityState[IN]	• UIM facility state – 0 - Deactivated – 1 - Activated – 2 - Blocked
facilityCk[IN]	• Facility depersonalization control key, string in ASCII text (maximum 8 bytes)

8.692.2 Field Documentation

8.692.2.1 uint8_t pack_dms_UIMSetControlKeyProtection_t::facility

8.692.2.2 uint8_t pack_dms_UIMSetControlKeyProtection_t::facilityCk[8]

8.692.2.3 uint8_t pack_dms_UIMSetControlKeyProtection_t::facilityState

8.693 pack_dms_UIMSetPINProtection_t Struct Reference

Data Fields

- uint8_t id
- uint8_t bEnable
- uint8_t value [255]

8.693.1 Detailed Description

This structure contains PIN Protection Information

Parameters

id[IN]	• PIN ID – 1 (PIN1 / CHV1) – 2 (PIN2 / CHV2)
bEnable[IN]	• Enable/disable PIN protection, 0 = Disable
pValue[IN]	• PIN value of the PIN to be enabled/disabled

8.693.2 Field Documentation

8.693.2.1 uint8_t pack_dms_UIMSetPINProtection_t::bEnable

8.693.2.2 uint8_t pack_dms_UIMSetPINProtection_t::id

8.693.2.3 uint8_t pack_dms_UIMSetPINProtection_t::value[255]

8.694 pack_dms_UIMUnblockControlKey_t Struct Reference

Data Fields

- uint8_t facility
- uint8_t facilityCk [8]

8.694.1 Detailed Description

This structure contains UIM unblock Control Key information

Parameters

facility[IN]	• MT or network facility – 0 - Network Personalization (PN) – 1 - Network Subset Personalization (PU) – 2 - Service Provider Personalization (PP) – 3 - Corporate Personalization (PC) – 4 - UIM Personalization (PF)
facilityCk[IN]	• Facility depersonalization control key, string in ASCII text (maximum 8 bytes)

8.694.2 Field Documentation

8.694.2.1 uint8_t pack_dms_UIMUnblockControlKey_t::facility

8.694.2.2 uint8_t pack_dms_UIMUnblockControlKey_t::facilityCk[8]

8.695 pack_dms_UIMUnblockPIN_t Struct Reference

Data Fields

- uint8_t id
- uint8_t pukValue [255]
- uint8_t newPin [255]

8.695.1 Detailed Description

This structure contains UIM Unblock PIN Information

Parameters

id[IN]	• PIN ID – 1 (PIN1 / CHV1) – 2 (PIN2 / CHV2)
pukValue[IN]	• PUK value of PIN to be unblocked
newPin[IN]	• New PIN value for the PIN to be unblocked

8.695.2 Field Documentation

8.695.2.1 uint8_t pack_dms_UIMUnblockPIN_t::id

8.695.2.2 uint8_t pack_dms_UIMUnblockPIN_t::newPin[255]

8.695.2.3 uint8_t pack_dms_UIMUnblockPIN_t::pukValue[255]

8.696 pack_dms_UIMVerifyPIN_t Struct Reference

Data Fields

- uint8_t id
- uint8_t value [255]

8.696.1 Detailed Description

This structure contains PIN Value Information

Parameters

id[IN]	• PIN ID – 1 (PIN1 / CHV1) – 2 (PIN2 / CHV2)
value[IN]	• PIN value of the PIN to be enabled/disabled

8.696.2 Field Documentation

8.696.2.1 uint8_t pack_dms_UIMVerifyPIN_t::id

8.696.2.2 uint8_t pack_dms_UIMVerifyPIN_t::value[255]

8.697 pack_fms_GetImagesPreference_t Struct Reference

Data Fields

- uint16_t Tlvresult

8.697.1 Detailed Description

This structure contains the Get Image Preference information pack

Parameters

Tlvresult	• Pack result

8.697.2 Field Documentation

8.697.2.1 uint16_t pack_fms_GetImagesPreference_t::Tlvresult

8.698 pack_fms_GetStoredImages_t Struct Reference

Data Fields

- uint16_t Tlvresult

8.698.1 Detailed Description

This structure contains the Get Stored Images pack

Parameters

Tlvresult	• Pack result

8.698.2 Field Documentation

8.698.2.1 uint16_t pack_fms_GetStoredImages_t::Tlvresult

8.699 pack_fms_SetImagesPreference_t Struct Reference

Data Fields

- uint32_t imageListSize
- FMSPrefImageList * pImageList
- uint32_t bForceDownload
- uint8_t modemindex
- uint16_t Tlvresult

8.699.1 Detailed Description

This structure contains the Set Images Preference pack

Parameters

imageListSize	• Image List Size
pImageList	• Image List • See FMSPrefImageList
bForceDownload	• 0 - Not Force Donwload. • 1 - Focrce Download.
modemindex	• Modem Index.
Tlvresult	• Unpack result

8.699.2 Field Documentation

8.699.2.1 uint32_t pack_fms_SetImagesPreference_t::bForceDownload

8.699.2.2 uint32_t pack_fms_SetImagesPreference_t::imageListSize

8.699.2.3 uint8_t pack_fms_SetImagesPreference_t::modemindex

8.699.2.4 FMSPrefImageList* pack_fms_SetImagesPreference_t::pImageList

8.699.2.5 uint16_t pack_fms_SetImagesPreference_t::Tlvresult

8.700 pack_loc_Delete_Assist_Data_t Struct Reference

Data Fields

- loc_SVInfo * pSVInfo
- loc_GnssData * pGnssData
- loc_CellDb * pCellDb
- loc_ClkInfo * pClkInfo
- loc_BdsSVInfo * pBdsSVInfo
- uint16_t Tlvresult

8.700.1 Detailed Description

This structure contains LOC delete assist data pack

Parameters

pSVInfo	• Pointer to struct loc_SVInfo. See loc_SVInfo for more information
pGnssData	• Pointer to struct loc_GnssData. See loc_GnssData for more information
pCellDb	• Pointer to struct loc_CellDb. See loc_CellDb for more information
pClkInfo	• Pointer to struct loc_ClkInfo. See loc_ClkInfo for more information
pBdsSVInfo	• Pointer to struct loc_BdsSVInfo. See loc_BdsSVInfo for more information
Tlvresult	• Pack delete assist data request result.

8.700.2 Field Documentation

8.700.2.1 loc_BdsSVInfo* pack_loc_Delete_Assist_Data_t::pBdsSVInfo

8.700.2.2 loc_CellDb* pack_loc_Delete_Assist_Data_t::pCellDb

8.700.2.3 loc_ClkInfo* pack_loc_Delete_Assist_Data_t::pClkInfo

8.700.2.4 loc_GnssData* pack_loc_Delete_Assist_Data_t::pGnssData

8.700.2.5 loc_SVInfo* pack_loc_Delete_Assist_Data_t::pSVInfo

8.700.2.6 uint16_t pack_loc_Delete_Assist_Data_t::Tlvresult

8.701 pack_loc_EventRegister_t Struct Reference

Data Fields

- uint64_t eventRegister
- uint16_t Tlvresult

8.701.1 Detailed Description

This structure contains the Parameter for RegisterEvents

Parameters

eventRegister	• Specifies the events that the control point is interested in receiving. -Values – 0x00000001 - to receive position report event indications – 0x00000002 - to receive satellite report event indications.These reports are sent at a 1 Hz rate. – 0x00000004 - to receive NMEA reports for position and satellites in view.The report is at a 1 Hz rate. – 0x00000008 - to receive NI Notify/Verify request event indications – 0x00000010 - to receive time injection request event indications. – 0x00000020 - to receive predicted orbits request event indications. – 0x00000040 - to receive position injection request event indications. – 0x00000080 - to receive engine state report event indications. – 0x00000100 - to receive fix session status report event indications. – 0x00000200 - to receive Wi-Fi position request event indications. – 0x00000400 - to receive notifications from the location engine indicating its readiness to accept data from the sensors(accelerometer, gyroscope, etc.). – 0x00000800 - to receive time sync requests from the GPS engine. Time sync enables the GPS engine to synchronize its clock with the sensor processor's clock. – 0x00001000 - to receive Stationary Position Indicator (SPI) streaming report indications. – 0x00002000 - to receive location server requests. These requests are generated when the service wishes to establish a connection with a location server. – 0x00004000 - to receive notifications related to network-initiated Geofences. These events notify the client when a network-initiated Geofence is added, deleted, or edited. – 0x00008000 - to receive Geofence alerts. These alerts are generated to inform the client of the changes that may affect a Geofence, e.g., if GPS is turned off or if the network is unavailable. – 0x00010000 - to receive notifications when a Geofence is breached. These events are generated when a UE enters or leaves the perimeter of a Geofence. This breach report is for a single Geofence. – 0x00020000 - to register for pedometer control requests from the location engine. The location engine sends this event to control the injection of pedometer reports. – 0x00040000 - to register for motion data control requests from the location engine. The location engine sends this event to control the injection of motion data. – 0x00080000 - to receive notification when a batch is full. The location engine sends this event to notify of Batch Full for ongoing batching session. – 0x00100000 - to receive position report indications along with an ongoing batching session. The location engine sends this event to notify the batched position report while a batching session is ongoing. – 0x00200000 - to receive Wi-Fi Access Point (AP) data inject request event indications. – 0x00400000 - to receive notifications when a Geofence is breached. These events are generated when a UE enters or leaves the perimeter of a Geofence. This breach notification is for multiple Geofences. Breaches from multiple Geofences are all batched and sent in the same notification. – 0x00800000 - to receive notifications from the location engine indicating its readiness to accept vehicle data (vehicle accelerometer, vehicle angular rate, vehicle odometry, etc.). – 0x01000000 - to receive system clock and satellite measurement report events (system clock, SV time, Doppler, etc.). – 0x02000000 - to receive satellite position reports as polynomials.Reports are generated only for the GNSS satellite constellations that are enabled using QMI_LOC_SET_GNSS_-CONSTELL_REPORT_CONFIG.

Note

Multiple events can be registered by OR the individual masks and sending them in this TLV. All unused bits in this mask must be set to 0.

Parameters

Tlvresult	• Pack result.

8.701.2 Field Documentation

8.701.2.1 uint64_t pack_loc_EventRegister_t::eventRegister

8.701.2.2 uint16_t pack_loc_EventRegister_t::Tlvresult

8.702 pack_loc_SetExtPowerState_t Struct Reference

Data Fields

- uint32_t extPowerState
- uint16_t Tlvresult

8.702.1 Detailed Description

This structure contains the Parameter External Power Source State pack.

Parameters

extPowerState	• Specifies the Power state; injected by the control point. • Values – 0 - Device is not connected to an external power source – 1 - Device is connected to an external power source – 2 - Unknown external power state
Tlvresult	• Pack result.

8.702.2 Field Documentation

8.702.2.1 uint32_t pack_loc_SetExtPowerState_t::extPowerState

8.702.2.2 uint16_t pack_loc_SetExtPowerState_t::Tlvresult

8.703 pack_loc_SetOperationMode_t Struct Reference

Data Fields

- uint32_t mode
- uint16_t Tlvresult

8.703.1 Detailed Description

This structure contains Set Operation Mode pack

Parameters

mode	• Valid values: – eQMI_LOC_OPER_MODE_DEFAULT (1) - Use the default engine mode – eQMI_LOC_OPER_MODE_MSB (2) - Use the MS-based mode – eQMI_LOC_OPER_MODE_MSA (3) - Use the MS-assisted mode – eQMI_LOC_OPER_MODE_STANDALONE (4) - Use Standalone mode – eQMI_LOC_OPER_MODE_CELL_ID (5) - Use cell ID; this mode is only valid for GSM/UMTS networks – eQMI_LOC_OPER_MODE_WWAN (6) - Use WWAN measurements to calculate the position; if this mode is set, AFLT will be used for 1X networks and OTDOA will be used for LTE networks
Tlvresult	• Pack result.

8.703.2 Field Documentation

8.703.2.1 uint32_t pack_loc_SetOperationMode_t::mode

8.703.2.2 uint16_t pack_loc_SetOperationMode_t::Tlvresult

8.704 pack_loc_SLQSLOCGetBestAvailPos_t Struct Reference

Data Fields

- uint32_t xid
- uint16_t Tlvresult

8.704.1 Detailed Description

This structure contains Set Operation Mode pack

Parameters

xid	• Identifies the transaction. • The transaction ID is returned in the Get Best Available Position indication.
Tlvresult	• Pack result.

8.704.2 Field Documentation

8.704.2.1 uint16_t pack_loc_SLQSLOCGetBestAvailPos_t::Tlvresult

8.704.2.2 uint32_t pack_loc_SLQSLOCGetBestAvailPos_t::xid

8.705 pack_loc_SLQSLOCGetServer_t Struct Reference

Data Fields

- uint32_t serverType
- int has_serverAddrTypeMask
- uint8_t serverAddrTypeMask

8.705.1 Detailed Description

This structure contains parameters to Gets the location server. Please check has_<Param_Name> field for presence of optional parameters

Parameters

serverType	• Type of server. • Valid values – eQMI_LOC_SERVER_TYPE_CDMA_PDE (1) - Server type is CDMA PDE – eQMI_LOC_SERVER_TYPE_CDMA_MPC (2) - Server type is CDMA MPC – eQMI_LOC_SERVER_TYPE_UMTS_SLP (3) - Server type is UMTS SLP – eQMI_LOC_SERVER_TYPE_CUSTOM_PDE (4)- Server type is custom PDE
serverAddrTypeMask	• Optional parameter • Type of address the client wants. If unspecified, the indication will contain all the types of addresses it has for the specified server type. • Valid bitmasks – 0x01 - IPv4 – 0x02 - IPv6 – 0x04 - URL

8.705.2 Field Documentation

8.705.2.1 int pack_loc_SLQSLOCGetServer_t::has_serverAddrTypeMask

8.705.2.2 uint8_t pack_loc_SLQSLOCGetServer_t::serverAddrTypeMask

8.705.2.3 uint32_t pack_loc_SLQSLOCGetServer_t::serverType

8.706 pack_loc_SLQSLOCInjectPosition_t Struct Reference

Data Fields

- double latitude
- int has_latitude
- double longitude
- int has_longitude
- float horUncCircular

- int has_horUncCircular
- uint8_t horConfidence
- int has_horConfidence
- uint32_t horReliability
- int has_horReliability
- float altitudeWrtEllipsoid
- int has_altitudeWrtEllipsoid
- float altitudeWrtMeanSeaLevel
- int has_altitudeWrtMeanSeaLevel
- float vertUnc
- int has_vertUnc
- uint8_t vertConfidence
- int has_vertConfidence
- uint32_t vertReliability
- int has_vertRelicability
- altSrcInfo_t altitudeSrcInfo
- int has_altitudeSrcInfo
- uint64_t timestampUtc
- int has_timestampUtc
- uint32_t timestampAge
- int has_timestampAge
- uint32_t positionSrc
- int has_positionSrc
- float rawHorUncCircular
- int has_rawHorUncCircular
- uint8_t rawHorConfidence
- int has_rawHorConfidence

8.706.1 Detailed Description

This structure contains LOC Inject Position parameters Please check has_<Param_Name> field for presence of optional parameters

Parameters

latitude	• Optional parameter • Type - Floating point • Units - Degrees • Range - -90.0 to 90.0 • Positive values indicate northern latitude • Negative values indicate southern latitude • Note - This field must be specified together with pLongitude and pHorUncCircular.
longitude	• Optional parameter • Type - Floating point • Units - Degrees • Range - -180.0 to 180.0 • Positive values indicate eastern latitude • Negative values indicate western latitude • Note - This field must be specified together with pLatitude and pHorUncCircular.

horUncCircular	• Optional parameter • Horizontal position uncertainty. • Units - Meters • Note - This field must be specified together with pLatitude and pLongitude.

horConfidence	• Optional parameter
	• Horizontal confidence.
	• Units - Percent
	• Values
	  – Valid Values - 1 to 99
	  – Invalid Values - 0, 101 to 255
	  – If 100 is received, reinterpret to 99
	• Note - This field must be specified together with horizontal uncertainty. If not specified when pHorUncCircular is set, the default value is 50.

horReliability	• Optional parameter
	  – Values
	  * 0 - Location reliability is not set.
	  * 1 - Location reliability is very low; use it at your own risk
	  * 2 - Location reliability is low; little or no cross-checking is possible.
	  * 3 - Location reliability is medium; limited cross-check passed
	  * 4 - Location reliability is high; strong cross-check passed

altitudeWrt-Ellipsoid	• Optional parameter
	• Altitude With Respect to Ellipsoid.
	• Units - Meters
	• Values
	  – Positive - height
	  – Negative = depth

altitudeWrt-MeanSeaLevel	• Optional parameter • Altitude With Respect to Sea Level. • Units - Meters
vertUnc	• Optional parameter • Vertical uncertainty. • Units - Meters • Note - This is mandatory if either pAltitudeWrtEllipsoid or pAltitudeWrtMeanSeaLevel is specified.

vertConfidence	• Optional parameter
	• Vertical confidence.
	• Units - Percentage
	• Values
	  – Valid Values - 0 to 99
	  – Invalid Values - 0, 100-256
	  – If 100 is received, reinterpret to 99
	• Note - This field must be specified together with the vertical uncertainty. If not specified, the default value will be 50.

vertReliability	• Optional parameter
	  – Values
	  * 0 - Location reliability is not set.
	  * 1 - Location reliability is very low; use it at your own risk.
	  * 2 - Location reliability is low; little or no cross-checking is possible
	  * 3 - Location reliability is medium; limited cross-check passed
	  * 4 - Location reliability is high; strong cross-check passed

altitudeSrcInfo	• Optional parameter – Pointer to struct altitudeSrcInfo. See altitudeSrcInfo for more information
timestampUtc	• Optional parameter • UTC timestamp • Units - Milliseconds since Jan. 1, 1970
timestampAge	• Optional parameter • Position age, which is an estimate of how long ago this fix was made. • Units - Milliseconds

positionSrc	• Optional parameter
	• Source from which this position was obtained
	• Valid values
	  – 0 - Position source is GNSS
	  – 1 - Position source is Cell ID
	  – 2 - Position source is Enhanced Cell ID
	  – 3 - Position source is Wi-Fi
	  – 4 - Position source is Terrestrial
	  – 5 - Position source is GNSS Terrestrial Hybrid
	  – 6 - Other sources
	• Note - If altitude is specified and the altitude source is not specified, the engine assumes that the altitude was obtained using the specified position source.
	  – If both altitude and altitude source are specified, the engine assumes that only latitude and longitude were obtained using the specified position source.

rawHorUncCircular	• Optional parameter • Horizontal position uncertainty (circular) without any optimization. • Units - Meters
rawHorConfidence	• Optional parameter • Horizontal confidence associated with raw horizontal uncertainty • Units: Percent • Values – Valid values - 1 to 99 – Invalid values - 0, 101 to 255 – If 100 is received, reinterpret to 99 • Note - This field must be specified together with raw horizontal uncertainty. If not specified when rawHorUncCircular is set, the default value is 50.

8.706.2 Field Documentation

8.706.2.1 altSrcInfo_t pack_loc_SLQSLOCInjectPosition_t::altitudeSrcInfo

8.706.2.2 float pack_loc_SLQSLOCInjectPosition_t::altitudeWrtEllipsoid

8.706.2.3 float pack_loc_SLQSLOCInjectPosition_t::altitudeWrtMeanSeaLevel

8.706.2.4 int pack_loc_SLQSLOCInjectPosition_t::has_altitudeSrcInfo

8.706.2.5 int pack_loc_SLQSLOCInjectPosition_t::has_altitudeWrtEllipsoid

8.706.2.6 int pack_loc_SLQSLOCInjectPosition_t::has_altitudeWrtMeanSeaLevel

8.706.2.7 int pack_loc_SLQSLOCInjectPosition_t::has_horConfidence

8.706.2.8 int pack_loc_SLQSLOCInjectPosition_t::has_horReliability

8.706.2.9 int pack_loc_SLQSLOCInjectPosition_t::has_horUncCircular

8.706.2.10 int pack_loc_SLQSLOCInjectPosition_t::has_latitude

8.706.2.11 int pack_loc_SLQSLOCInjectPosition_t::has_longitude

8.706.2.12 int pack_loc_SLQSLOCInjectPosition_t::has_positionSrc

8.706.2.13 int pack_loc_SLQSLOCInjectPosition_t::has_rawHorConfidence

8.706.2.14 int pack_loc_SLQSLOCInjectPosition_t::has_rawHorUncCircular

8.706.2.15 int pack_loc_SLQSLOCInjectPosition_t::has_timestampAge

8.706.2.16 int pack_loc_SLQSLOCInjectPosition_t::has_timestampUtc

8.706.2.17 int pack_loc_SLQSLOCInjectPosition_t::has_vertConfidence

8.706.2.18 int pack_loc_SLQSLOCInjectPosition_t::has_vertRelicability

8.706.2.19 int pack_loc_SLQSLOCInjectPosition_t::has_vertUnc

8.706.2.20 uint8_t pack_loc_SLQSLOCInjectPosition_t::horConfidence

8.706.2.21 uint32_t pack_loc_SLQSLOCInjectPosition_t::horReliability

8.706.2.22 float pack_loc_SLQSLOCInjectPosition_t::horUncCircular

8.706.2.23 double pack_loc_SLQSLOCInjectPosition_t::latitude

8.706.2.24 double pack_loc_SLQSLOCInjectPosition_t::longitude

8.706.2.25 uint32_t pack_loc_SLQSLOCInjectPosition_t::positionSrc

8.706.2.26 uint8_t pack_loc_SLQSLOCInjectPosition_t::rawHorConfidence

8.706.2.27 float pack_loc_SLQSLOCInjectPosition_t::rawHorUncCircular

8.706.2.28 uint32_t pack_loc_SLQSLOCInjectPosition_t::timestampAge

8.706.2.29 uint64_t pack_loc_SLQSLOCInjectPosition_t::timestampUtc

8.706.2.30 uint8_t pack_loc_SLQSLOCInjectPosition_t::vertConfidence

8.706.2.31 uint32_t pack_loc_SLQSLOCInjectPosition_t::vertReliability

8.706.2.32 float pack_loc_SLQSLOCInjectPosition_t::vertUnc

8.707 pack_loc_SLQSLOCInjectSensorData_t Struct Reference

Data Fields

- int has_opaqueId
- uint32_t opaqueId
- int has_accleroData
- sensorData_t acceleroData
- int has_gyroData
- sensorData_t gyroData
- int has_acceleroTimeSrc
- uint32_t acceleroTimeSrc
- int has_gyroTimeSrc
- uint32_t gyroTimeSrc
- int has_accelTemp
- tempData_t accelTemp
- int has_gyroTemp
- tempData_t gyroTemp

8.707.1 Detailed Description

This structure contains parameters to inject sensor data into the GNSS location engine Please check has_<Param-_Name> field for presence of optional parameters

Parameters

opaqueId	• Opaque Identifier (Optional parameter) • An opaque identifier that is sent in by the client that will be echoed in the indication so the client can relate the indication to the request.
acceleroData	• 3-Axis Accelerometer Data (Optional parameter) • Pointer to struct sensorData. See sensorData_t for more information
gyroData	• 3-Axis Cyroscope Data (Optional parameter) • Pointer to struct sensorData. See sensorData_t for more information
acceleroTimeSrc	• 3-Axis Accelerometer Data Time Source (Optional parameter) • The location service uses this field to identify the time reference used in the accelerometer data time stamps. • If not specified, the location service assumes that the time source for the accelerometer data is unknown. • Valid values – 0 - Sensor time source is unspecified – 1 - Time source is common between the sensors and the location engine
gyroTimeSrc	• 3-Axis Gyroscope Data Time Source (Optional) • The location service uses this field to identify the time reference used in the gyroscope data time stamps. • If not specified, the location service assumes that the time source for the gyroscope data is unknown. • Valid values – 0 - Sensor time source is unspecified – 1 - Time source is common between the sensors and the location engine
accelTemp	• Accelerometer Temperature Data (Optional parameter) • Pointer to struct temprature Data. See tempData_t for more information
gyroTemp	• Gyroscope Temperature Data (Optional parameter) • Pointer to struct temprature Data. See tempData_t for more information

8.707.2 Field Documentation

8.707.2.1 sensorData_t pack_loc_SLQSLOCInjectSensorData_t::acceleroData

8.707.2.2 uint32_t pack_loc_SLQSLOCInjectSensorData_t::acceleroTimeSrc

8.707.2.3 tempData_t pack_loc_SLQSLOCInjectSensorData_t::accelTemp

8.707.2.4 sensorData_t pack_loc_SLQSLOCInjectSensorData_t::gyroData

8.707.2.5 tempData_t pack_loc_SLQSLOCInjectSensorData_t::gyroTemp

8.707.2.6 uint32_t pack_loc_SLQSLOCInjectSensorData_t::gyroTimeSrc

8.707.2.7 int pack_loc_SLQSLOCInjectSensorData_t::has_acceleroTimeSrc

8.707.2.8 int pack_loc_SLQSLOCInjectSensorData_t::has_accelTemp

8.707.2.9 int pack_loc_SLQSLOCInjectSensorData_t::has_accleroData

8.707.2.10 int pack_loc_SLQSLOCInjectSensorData_t::has_gyroData

8.707.2.11 int pack_loc_SLQSLOCInjectSensorData_t::has_gyroTemp

8.707.2.12 int pack_loc_SLQSLOCInjectSensorData_t::has_gyroTimeSrc

8.707.2.13 int pack_loc_SLQSLOCInjectSensorData_t::has_opaqueId

8.707.2.14 uint32_t pack_loc_SLQSLOCInjectSensorData_t::opaqueId

8.708 pack_loc_SLQSLOCInjectUTCTime_t Struct Reference

Data Fields

- uint64_t timeMsec
- uint32_t timeUncMsec

8.708.1 Detailed Description

This structure contains inject UTC time parameter.

Parameters

timeMsec	• The UTC time since Jan. 1, 1970
timeUncMsec	• The time Uncertainty

8.708.2 Field Documentation

8.708.2.1 uint64_t pack_loc_SLQSLOCInjectUTCTime_t::timeMsec

8.708.2.2 uint32_t pack_loc_SLQSLOCInjectUTCTime_t::timeUncMsec

8.709 pack_loc_SLQSLOCSetCradleMountConfig_t Struct Reference

Data Fields

- uint32_t state
- int has_confidence
- uint8_t confidence

8.709.1 Detailed Description

This structure contains parameters to set current cradle mount configuration Please check has_<Param_Name> field for presence of optional parameters

Parameters

state	• Cradle Mount State • Valid values: – 0 - Device is mounted on the cradle – 1 - Device is not mounted on the cradle – 2 - Unknown cradle mount state
confidence	• Cradle Mount Confidence (Optional) • Confidence in the Cradle Mount state expressed as a percentage. • Range - 0 to 100

8.709.2 Field Documentation

8.709.2.1 uint8_t pack_loc_SLQSLOCSetCradleMountConfig_t::confidence

8.709.2.2 int pack_loc_SLQSLOCSetCradleMountConfig_t::has_confidence

8.709.2.3 uint32_t pack_loc_SLQSLOCSetCradleMountConfig_t::state

8.710 pack_loc_SLQSLOCSetServer_t Struct Reference

Data Fields

- uint32_t serverType
- loc_IPv4Config * pIPv4Config
- loc_IPv6Config * pIPv6Config
- loc_URLAddrInfo * pURLAddr

8.710.1 Detailed Description

This structure contains parameters to set A-GPS Server

Parameters

serverType	• Type of server • Valid values: – 1 - Server type is CDMA PDE – 2 - Server type is CDMA MPC – 3 - Server type is UMTS SLP – 4 - Server type is custom PDE

pIPv4Config	• IPv4 address and port (Optional) • See loc_IPv4Config for more information
pIPv6Config	• IPv6 address and port (Optional) • See loc_IPv6Config for more information
pURLAddr	• Uniform Resource Locator (Optional) • See loc_URLAddrInfo for more information

8.710.2 Field Documentation

8.710.2.1 loc_IPv4Config* pack_loc_SLQSLOCSetServer_t::pIPv4Config

8.710.2.2 loc_IPv6Config* pack_loc_SLQSLOCSetServer_t::pIPv6Config

8.710.2.3 loc_URLAddrInfo* pack_loc_SLQSLOCSetServer_t::pURLAddr

8.710.2.4 uint32_t pack_loc_SLQSLOCSetServer_t::serverType

8.711 pack_loc_Start_t Struct Reference

Data Fields

- uint8_t SessionId
- uint32_t * pRecurrenceType
- uint32_t * pHorizontalAccuracyLvl
- uint32_t * pIntermediateReportState
- uint32_t * pMinIntervalTime
- loc_LocApplicationInfo * pApplicationInfo
- uint32_t * pConfigAltitudeAssumed
- uint16_t Tlvresult

8.711.1 Detailed Description

This structure contains the LOC Start pack

Parameters

SessionId	• ID of the session as identified by the control point. • Range: 0 to 255
pRecurrence-Type	• Optional Parameter • Specifies the type of session in which the control point is interested. • Defaults to SINGLE. -Values – 1 - Request periodic position fixes – 2 - Request a single position fix

pHorizontal-AccuracyLvl	• Optional Parameter • Specifies the horizontal accuracy level required by the control point. • Defaults to LOW • Values – 1 - Low accuracy – 2 - Medium accuracy – 3 - High accuracy
pIntermediate-ReportState	• Optional Parameter • Specifies if the control point is interested in receiving intermediate reports. • ON by default. • Values – 1 - Intermediate reports are turned on – 2 - Intermediate reports are turned off
pMinInterval-Time	• Optional Parameter • Minimum time interval, specified by the control point, that must elapse between position reports. • Units - Milliseconds • Default - 1000 ms
LocApplication-Info	• Optional Parameter • LOC Application Parameters • See loc_LocApplicationInfo for more information
pConfigAltitude-Assumed	• Optional Parameter • Configuration for Altitude Assumed Info in GNSS SV Info Event • Defaults to ENABLED. • Values – 1 - Enable Altitude Assumed information in GNSS SV Info Event – 2 - Disable Altitude Assumed information in GNSS SV Info Event
Tlvresult	• Unpack result.

8.711.2 Field Documentation

8.711.2.1 loc_LocApplicationInfo* pack_loc_Start_t::pApplicationInfo

8.711.2.2 uint32_t* pack_loc_Start_t::pConfigAltitudeAssumed

8.711.2.3 uint32_t* pack_loc_Start_t::pHorizontalAccuracyLvl

8.711.2.4 uint32_t* pack_loc_Start_t::pIntermediateReportState

8.711.2.5 uint32_t* pack_loc_Start_t::pMinIntervalTime

8.711.2.6 uint32_t* pack_loc_Start_t::pRecurrenceType

8.711.2.7 uint8_t pack_loc_Start_t::SessionId

8.711.2.8 uint16_t pack_loc_Start_t::Tlvresult

8.712 pack_loc_Stop_t Struct Reference

Data Fields

- uint8_t SessionId
- uint16_t Tlvresult

8.712.1 Detailed Description

This structure contains Stop LOC pack

Parameters

sessionId	• ID of the session as identified by the control point. • Range: 0 to 255
Tlvresult	• Unpack result.

8.712.2 Field Documentation

8.712.2.1 uint8_t pack_loc_Stop_t::SessionId

8.712.2.2 uint16_t pack_loc_Stop_t::Tlvresult

8.713 pack_nas_InitiateDomainAttach_t Struct Reference

Data Fields

- uint32_t action

8.713.1 Detailed Description

Pack structure for Initiates a domain attach/detach of the device.

Parameters

action	• Domain action to attempt 1 - Attach 2 - Detach

8.713.2 Field Documentation

8.713.2.1 uint32_t pack_nas_InitiateDomainAttach_t::action

8.714 pack_nas_PerformNetworkScanPCI_t Struct Reference

Data Fields

- uint8_t * pNetworkType
- uint32_t * pScanType
- uint64_t * pCiotOpModePref
- uint64_t * pLteM1BandPref
- uint64_t * pLteNB1BandPref

8.714.1 Field Documentation

8.714.1.1 uint64_t* pack_nas_PerformNetworkScanPCI_t::pCiotOpModePref

8.714.1.2 uint64_t* pack_nas_PerformNetworkScanPCI_t::pLteM1BandPref

8.714.1.3 uint64_t* pack_nas_PerformNetworkScanPCI_t::pLteNB1BandPref

8.714.1.4 uint8_t* pack_nas_PerformNetworkScanPCI_t::pNetworkType

8.714.1.5 uint32_t* pack_nas_PerformNetworkScanPCI_t::pScanType

8.715 pack_nas_SetACCOLC_t Struct Reference

Data Fields

- int8_t spc [6]
- uint8_t accolc

8.715.1 Detailed Description

Sets the access overload class (ACCOLC)

Parameters

spc	• service programming code NULL-terminated string of six digit
accolc	• ACCOLC : Valid range is 0 to 15

8.715.2 Field Documentation

8.715.2.1 uint8_t pack_nas_SetACCOLC_t::accolc

8.715.2.2 int8_t pack_nas_SetACCOLC_t::spc[6]

8.716 pack_nas_SetCDMANetworkParameters_t Struct Reference

Data Fields

- char * pSPC
- uint8_t * pForceRev0
- uint8_t * pCustomSCP
- uint32_t * pProtocol
- uint32_t * pBroadcast
- uint32_t * pApplication
- uint32_t * pRoaming

8.716.1 Detailed Description

Pack structure to set CDMA Network parameters.

Parameters

pSPC	• Six digit service programming code (not necessary when only the roaming field is being set)
pForceRev0	• (Optional)Force CDMA 1x-EV-DO Rev. 0 mode – 0 - Disabled – 1 - Enabled Note: Enabled can only be specified if pCustomSCP state is set to Disabled
pCustomSCP	• (Optional)Use a custom config for CDMA 1x-EV-DO SCP – 0 - Disabled – 1 - Enabled Note: Enabled can only be specified if pForceRev0 is set to Disabled
pProtocol	• Protocol mask for custom SCP config – 0x00000001 - Subtype 2 Physical Layer – 0x00000002 - Enhanced CCMAC – 0x00000004 - Enhanced ACMAC – 0x00000008 - Enhanced FTCMAC – 0x00000010 - Subtype 3 RTCMAC – 0x00000020 - Subsystem 1 RTCMAC – 0x00000040 - Enhanced Idle – 0x00000080 - Generic Multimode Capable Disc Port – 0xFFFFFFFF - Unknown
pBroadcast	• Broadcast mask for custom SCP config – 0x00000001 - Generic broadcast enabled – 0xFFFFFFFF - Unknown
pApplication	• Application mask for custom SCP config – 0x00000001 - SN Multiflow Packet Application – 0x00000002 - SN Enhanced Multiflow Packet Application – 0xFFFFFFFF - Unknown

pRoaming	• Roaming preference – 0 - Automatic – 1 - Home Only – 2 - Affiliated Roaming Only – 3 - Home and Affiliated Roaming – 0xFFFFFFFF - Unknown

8.716.2 Field Documentation

8.716.2.1 uint32_t* pack_nas_SetCDMANetworkParameters_t::pApplication

8.716.2.2 uint32_t* pack_nas_SetCDMANetworkParameters_t::pBroadcast

8.716.2.3 uint8_t* pack_nas_SetCDMANetworkParameters_t::pCustomSCP

8.716.2.4 uint8_t* pack_nas_SetCDMANetworkParameters_t::pForceRev0

8.716.2.5 uint32_t* pack_nas_SetCDMANetworkParameters_t::pProtocol

8.716.2.6 uint32_t* pack_nas_SetCDMANetworkParameters_t::pRoaming

8.716.2.7 char* pack_nas_SetCDMANetworkParameters_t::pSPC

8.717 pack_nas_SetNetworkPreference_t Struct Reference

Data Fields

- uint32_t TechnologyPref
- uint32_t Duration
- uint16_t Tlvresult

8.717.1 Detailed Description

This structure contains pack set network preference parameters.

Parameters

TechnologyPref[-IN]	• Bitmask representing the radio technology preference set. • No bits set indicates to the device to automatically determine the technology to use • Values: – Bit 0 - Technology is 3GPP2 – Bit 1 - Technology is 3GPP • Any combination of the following may be returned: – Bit 2 - Analog - AMPS if 3GPP2, GSM if 3GPP – Bit 3 - Digital - CDMA if 3GPP2, WCDMA if 3GPP – Bit 4 - HDR – Bit 5 - LTE – Bits 6 to 15 - Reserved

Duration[IN]	• Duration of active preference – 0 - Permanent – 1 - Power cycle – 2 - Until the end of the next call or a power cycle – 3 - Until the end of the next call, a specified time, or a power cycle – 4 to 6 - Until the end of the next call
Tlvresult	• pack result

8.717.2 Field Documentation

8.717.2.1 uint32_t pack_nas_SetNetworkPreference_t::Duration

8.717.2.2 uint32_t pack_nas_SetNetworkPreference_t::TechnologyPref

8.717.2.3 uint16_t pack_nas_SetNetworkPreference_t::Tlvresult

8.718 pack_nas_SLQSConfigSigInfo_t Struct Reference

Data Fields

- nas_RSSIThresh * pRSSIThresh
- nas_ECIOThresh * pECIOThresh
- nas_HDRSINRThresh * pHDRSINRThresh
- nas_LTESNRThresh * pLTESNRThresh
- nas_IOThresh * pIOThresh
- nas_RSRQThresh * pRSRQThresh
- nas_RSRPThresh * pRSRPThresh
- nas_LTESigRptCfg * pLTESigRptCfg
- nas_TDSCDMASINRCONFThresh * pTDSCDMASINRCONFThresh

8.718.1 Detailed Description

Structure for ConfigSigInfo pack.

Parameters

pRSSIThresh	• RSSI threshold List • See nas_RSSIThresh for more details
pECIOThresh	• ECIO Threshold List • See nas_ECIOThresh for more details
pHDRSINR-Thresh	• HDR SINR Threshold List • See nas_HDRSINRThresh for more details

pLTESNR-Thresh	• LTE SNR Threshold List • See nas_LTESNRThresh for more details
pIOThresh	• IO Threshold List • See nas_IOThresh for more details
pRSRQThresh	• RSRQ Threshold List • See nas_RSRQThresh for more details
pRSRPThresh	• RSRP Threshold List • See nas_RSRPThresh for more details
pLTESigRptCfg	• LTE signal report config • See nas_LTESigRptCfg for more details
pTDSCDMASIN-RCONFThresh	• TD-SCDMA SINR Threshold List • See nas_TDSCDMASINRCONFThresh for more details

8.718.2 Field Documentation

8.718.2.1 nas_ECIOThresh∗ pack_nas_SLQSConfigSigInfo_t::pECIOThresh

8.718.2.2 nas_HDRSINRThresh∗ pack_nas_SLQSConfigSigInfo_t::pHDRSINRThresh

8.718.2.3 nas_IOThresh∗ pack_nas_SLQSConfigSigInfo_t::pIOThresh

8.718.2.4 nas_LTESigRptCfg∗ pack_nas_SLQSConfigSigInfo_t::pLTESigRptCfg

8.718.2.5 nas_LTESNRThresh∗ pack_nas_SLQSConfigSigInfo_t::pLTESNRThresh

8.718.2.6 nas_RSRPThresh∗ pack_nas_SLQSConfigSigInfo_t::pRSRPThresh

8.718.2.7 nas_RSRQThresh∗ pack_nas_SLQSConfigSigInfo_t::pRSRQThresh

8.718.2.8 nas_RSSIThresh∗ pack_nas_SLQSConfigSigInfo_t::pRSSIThresh

8.718.2.9 nas_TDSCDMASINRCONFThresh∗ pack_nas_SLQSConfigSigInfo_t::pTDSCDMASINRCONFThresh

8.719 pack_nas_SLQSGetPLMNName_t Struct Reference

Data Fields

- uint16_t mcc
- uint16_t mnc
- uint8_t ∗ pMncPcsStatus

8.719.1 Detailed Description

This structure contains pack get operator name for specificed network parameters.

Parameters

mcc	• A 16-bit integer representation of MCC. Range: 0 to 999
mnc	• A 16-bit integer representation of MNC. Range: 0 to 999
pMncPcsStatus	• MNC PCS Digit Include Status • Used to interpret the length of the corresponding MNC reported in the PLMN TLV(0x01). • Values – TRUE - MNC is a three-digit value. e.g. a reported value of 90 corresponds to an MNC value of 090 – FALSE - MNC is a two-digit value. e.g. a reported value of 90 corresponds to an MNC value of 90

Note

If pMncPcsStatus is not present, an MNC smaller than 100 is assumed to be a two-digit value, and an MNC greater than or equal to 100 is assumed to be a three digit value.

8.719.2 Field Documentation

8.719.2.1 uint16_t pack_nas_SLQSGetPLMNName_t::mcc

8.719.2.2 uint16_t pack_nas_SLQSGetPLMNName_t::mnc

8.719.2.3 uint8_t∗ pack_nas_SLQSGetPLMNName_t::pMncPcsStatus

8.720 pack_nas_SLQSInitiateNetworkRegistration_t Struct Reference

Data Fields

- uint32_t regAction
- nas_MNRInfo ∗ pMNRInfo
- uint32_t ∗ pChangeDuration
- uint8_t ∗ pMncPcsDigitStatus

8.720.1 Detailed Description

This structure contains Initiate Network Registration request parameters

Parameters

regAction	• Specifies one of the following register actions : – AUTO_REGISTER - Device registers according to its provisioning and optional parameters supplied with the command are ignored. – MANUAL_REGISTER - Device registers to a specified network and the optional Manual Network Register Information parameter pMNRInfo must also be included for the command to process successfully and supported only for 3GPP.
pMNRInfo	[Optional] • Pointer to structure MNRInfo – See nas_MNRInfo for more information
pChange-Duration	[Optional] • Duration of the change. – 0x00 - Power cycle - Remains active until the next device power cycle – 0x01 - Permanent - Remains active through power cycles until changed by the client
pMncPcsDigit-Status	[Optional] • MNC PCS Digit Include Status – True - MNC is a 3-digit value. – False - MNC is a 2-digit value.

8.720.2 Field Documentation

8.720.2.1 uint32_t* pack_nas_SLQSInitiateNetworkRegistration_t::pChangeDuration

8.720.2.2 uint8_t* pack_nas_SLQSInitiateNetworkRegistration_t::pMncPcsDigitStatus

8.720.2.3 nas_MNRInfo* pack_nas_SLQSInitiateNetworkRegistration_t::pMNRInfo

8.720.2.4 uint32_t pack_nas_SLQSInitiateNetworkRegistration_t::regAction

8.721 pack_nas_SLQSNasConfigSigInfo2_t Struct Reference

Data Fields

- nas_CDMARSSIThresh * pCDMARSSIThresh
- uint16_t * pCDMARSSIDelta
- nas_CDMAECIOThresh * pCDMAECIOThresh
- uint16_t * pCDMAECIODelta
- nas_HDRRSSIThresh * pHDRRSSIThresh
- uint16_t * pHDRRSSIDelta
- nas_HDRECIOThresh * pHDRECIOThresh
- uint16_t * pHDRECIODelta
- nas_HDRSINRThreshold * pHDRSINRThresh
- uint16_t * pHDRSINRDelta
- nas_HDRIOThresh * pHDRIOThresh
- uint16_t * pHDRIODelta
- nas_GSMRSSIThresh * pGSMRSSIThresh
- uint16_t * pGSMRSSIDelta
- nas_WCDMARSSIThresh * pWCDMARSSIThresh

- uint16_t * pWCDMARSSIDelta
- nas_WCDMAECIOThresh * pWCDMAECIOThresh
- uint16_t * pWCDMAECIODelta
- nas_LTERSSIThresh * pLTERSSIThresh
- uint16_t * pLTERSSIDelta
- nas_LTESNRThreshold * pLTESNRThresh
- uint16_t * pLTESNRDelta
- nas_LTERSRQThresh * pLTERSRQThresh
- uint16_t * pLTERSRQDelta
- nas_LTERSRPThresh * pLTERSRPThresh
- uint16_t * pLTERSRPDelta
- nas_LTESigRptConfig * pLTESigRptConfig
- nas_TDSCDMARSCPThresh * pTDSCDMARSCPThresh
- uint16_t * pTDSCDMARSCPDelta
- nas_TDSCDMARSSIThresh * pTDSCDMARSSIThresh
- float * pTDSCDMARSSIDelta
- nas_TDSCDMAECIOThresh * pTDSCDMAECIOThresh
- float * pTDSCDMAECIODelta
- nas_TDSCDMASINRThresh * pTDSCDMASINRThresh
- float * pTDSCDMASINRDelta

8.721.1 Detailed Description

This structure contains pack set the signal strength reporting thresholds parameters.

Parameters

pCDMARSSI-Thresh	• CDMA RSSI threshold List
pCDMARSSI-Delta	• RSSI delta (in units of 0.1 dBm). • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pCDMAECIO-Thresh	• CDMA ECIO Threshold List
pCDMAECIO-Delta	• ECIO delta (in units of 0.1 dB). • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pHDRRSSI-Thresh	• HDR RSSI Threshold List
pHDRRSSIDelta	• RSSI delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pHDRECIO-Thresh	• HDR ECIO Threshold List
pHDRECIODelta	• ECIO delta (in units of 0.1 dB) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.

pHDRSINR-Thresh	• HDR SINR Threshold List
pHDRSINRDelta	• SINR delta (in units of 1 SINR level) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pHDRIOThresh	• HDR IO Threshold List
pHDRIODelta	• IO delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pGSMRSSI-Thresh	• GSM RSSI Threshold List • See nas_GSMRSSIThresh for more details
pGSMRSSIDelta	• RSSI delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pWCDMARSSI-Thresh	• WCDMA RSSI Threshold List • See nas_WCDMARSSIThresh for more details
pWCDMARSSI-Delta	• RSSI delta (in units of 0.1 dBm). • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pWCDMAECIO-Thresh	• WCDMA ECIO Threshold List
pWCDMAECIO-Delta	• ECIO delta (in units of 0.1 dB) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pLTERSSI-Thresh	• LTE RSSI Threshold List
pLTERSSIDelta	• RSSI delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pLTESNR-Thresh	• LTE SNR Threshold List
pLTESNRDelta	• SNR delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.

pLTERSRQ-Thresh	• LTE RSRQ Threshold List
pLTERSRQ-Delta	• RSRQ delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pLTERSRP-Thresh	• LTE RSRP Threshold List
pLTERSRPDelta	• RSRP delta (in units of 0.1 dBm). • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pLTESigRpt-Config	• LTE Signal Report Config
pTDSCDMARS-CPThresh	• TDSCDMA RSCP Threshold List
pTDSCDMARS-CPDelta	• RSCP delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pTDSCDMARS-SIThresh	• TDSCDMA RSSI Threshold List
pTDSCDMARS-SIDelta	• RSSI delta (in dBm) used by TD-SCDMA.
pTDSCDMAECI-OThresh	• TDSCDMA ECIO Threshold List
pTDSCDMAECI-ODelta	• ECIO delta (in dB) used by TD-SCDMA
pTDSCDMASIN-RThresh	• TDSCDMA SINR Threshold List
pTDSCDMASIN-RDelta	• SINR delta (in dB) used by TD-SCDMA.

Note

Mixture of threshold and delta values can be provided in the request. But for each type and RAT,only one of threshold list or delta value is to be provided.

8.721.2 Field Documentation

8.721.2.1 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pCDMAECIODelta

8.721.2.2 nas_CDMAECIOThresh* pack_nas_SLQSNasConfigSigInfo2_t::pCDMAECIOThresh

8.721.2.3 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pCDMARSSIDelta

8.721.2.4 nas_CDMARSSIThresh* pack_nas_SLQSNasConfigSigInfo2_t::pCDMARSSIThresh

8.721.2.5 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pGSMRSSIDelta

8.721.2.6 nas_GSMRSSIThresh* pack_nas_SLQSNasConfigSigInfo2_t::pGSMRSSIThresh

8.721.2.7 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pHDRECIODelta

8.721.2.8 nas_HDRECIOThresh* pack_nas_SLQSNasConfigSigInfo2_t::pHDRECIOThresh

8.721.2.9 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pHDRIODelta

8.721.2.10 nas_HDRIOThresh* pack_nas_SLQSNasConfigSigInfo2_t::pHDRIOThresh

8.721.2.11 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pHDRRSSIDelta

8.721.2.12 nas_HDRRSSIThresh* pack_nas_SLQSNasConfigSigInfo2_t::pHDRRSSIThresh

8.721.2.13 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pHDRSINRDelta

8.721.2.14 nas_HDRSINRThreshold* pack_nas_SLQSNasConfigSigInfo2_t::pHDRSINRThresh

8.721.2.15 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pLTERSRPDelta

8.721.2.16 nas_LTERSRPThresh* pack_nas_SLQSNasConfigSigInfo2_t::pLTERSRPThresh

8.721.2.17 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pLTERSRQDelta

8.721.2.18 nas_LTERSRQThresh* pack_nas_SLQSNasConfigSigInfo2_t::pLTERSRQThresh

8.721.2.19 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pLTERSSIDelta

8.721.2.20 nas_LTERSSIThresh* pack_nas_SLQSNasConfigSigInfo2_t::pLTERSSIThresh

8.721.2.21 nas_LTESigRptConfig* pack_nas_SLQSNasConfigSigInfo2_t::pLTESigRptConfig

8.721.2.22 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pLTESNRDelta

8.721.2.23 nas_LTESNRThreshold* pack_nas_SLQSNasConfigSigInfo2_t::pLTESNRThresh

8.721.2.24 float* pack_nas_SLQSNasConfigSigInfo2_t::pTDSCDMAECIODelta

8.721.2.25 nas_TDSCDMAECIOThresh* pack_nas_SLQSNasConfigSigInfo2_t::pTDSCDMAECIOThresh

8.721.2.26 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pTDSCDMARSCPDelta

8.721.2.27 nas_TDSCDMARSCPThresh* pack_nas_SLQSNasConfigSigInfo2_t::pTDSCDMARSCPThresh

8.721.2.28 float* pack_nas_SLQSNasConfigSigInfo2_t::pTDSCDMARSSIDelta

8.721.2.29 nas_TDSCDMARSSIThresh* pack_nas_SLQSNasConfigSigInfo2_t::pTDSCDMARSSIThresh

8.721.2.30 float* pack_nas_SLQSNasConfigSigInfo2_t::pTDSCDMASINRDelta

8.721.2.31 nas_TDSCDMASINRThresh* pack_nas_SLQSNasConfigSigInfo2_t::pTDSCDMASINRThresh

8.721.2.32 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pWCDMAECIODelta

8.721.2.33 nas_WCDMAECIOThresh* pack_nas_SLQSNasConfigSigInfo2_t::pWCDMAECIOThresh

8.721.2.34 uint16_t* pack_nas_SLQSNasConfigSigInfo2_t::pWCDMARSSIDelta

8.721.2.35 nas_WCDMARSSIThresh* pack_nas_SLQSNasConfigSigInfo2_t::pWCDMARSSIThresh

8.722 pack_nas_SLQSNasGet3GPP2Subscription_t Struct Reference

Data Fields

- uint8_t namID

8.722.1 Detailed Description

Structure for 3GPP2 Subscription pack.

Parameters

namID	[Mandatory] • NAM ID of the information to be retrieved. The index starts from 0. A nam_id of 0xFF is used to retrieve information of current NAM.

8.722.2 Field Documentation

8.722.2.1 uint8_t pack_nas_SLQSNasGet3GPP2Subscription_t::namID

8.723 pack_nas_SLQSNASGeteDRXParamsExt_t Struct Reference

Data Fields

- uint8_t * pEdrxRAT
- uint32_t * pLteOpMode

8.723.1 Detailed Description

This structure contains the SLQSNASGeteDRXParamsExt request parameters.

Parameters

pEdrxRAT	[Optional] • eDRX Radio Access Technology • Values – NAS_RADIO_IF_NO_SVC (0x00) - None (no service) – NAS_RADIO_IF_CDMA_1X (0x01) - cdma2000 ® 1X – NAS_RADIO_IF_CDMA_1XEVDO (0x02) - cdma2000 ® HRPD (1xEV-DO) – NAS_RADIO_IF_AMPS (0x03) - AMPS – NAS_RADIO_IF_GSM (0x04) - GSM – NAS_RADIO_IF_UMTS (0x05) - UMTS – NAS_RADIO_IF_WLAN (0x06) - WLAN – NAS_RADIO_IF_GPS (0x07) - GPS – NAS_RADIO_IF_LTE (0x08) - LTE – NAS_RADIO_IF_TDSCDMA (0x09) - TD-SCDMA – NAS_RADIO_IF_LTE_M1 (0x0a) - LTE-M1 – NAS_RADIO_IF_LTE_NB1 (0x0b) - LTE-NB1 – NAS_RADIO_IF_NO_CHANGE (-1) - No change Note: The device will use "0x08 - NAS_-RADIO_IF_LTE" as the default value if the TLV is omitted.
pLteOpMode	[Optional] • LTE Operational Mode • Values – NAS_CIOT_SYS_MODE_NO_ SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_ WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_ M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_ NB1 (0x03) - Camped on LTE NB1 Note: This TLV should be set when edrx_rat_type is LTE.

8.723.2 Field Documentation

8.723.2.1 uint8_t* pack_nas_SLQSNASGeteDRXParamsExt_t::pEdrxRAT

8.723.2.2 uint32_t* pack_nas_SLQSNASGeteDRXParamsExt_t::pLteOpMode

8.724 pack_nas_SLQSNasGetTxRxInfo_t Struct Reference

Data Fields

- uint8_t radio_if

8.724.1 Detailed Description

Structure for TxRx Info pack

Parameters

radio_if	[Mandatory] • Radio interface technology of the signal being measured • Valid Values – 0x01 - NAS_RADIO_IF_CDMA_1X - CDMA – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - HDR – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE

8.724.2 Field Documentation

8.724.2.1 uint8_t pack_nas_SLQSNasGetTxRxInfo_t::radio_if

8.725 pack_nas_SLQSNasIndicationRegisterExt_t Struct Reference

Data Fields

- uint8_t ∗ pSystemSelectionInd
- uint8_t ∗ pDDTMInd
- uint8_t ∗ pServingSystemInd
- uint8_t ∗ pDualStandByPrefInd
- uint8_t ∗ pSubscriptionInfoInd
- uint8_t ∗ pNetworkTimeInd
- uint8_t ∗ pSysInfoInd
- uint8_t ∗ pSignalStrengthInd
- uint8_t ∗ pErrorRateInd
- uint8_t ∗ pHDRNewUATIAssInd
- uint8_t ∗ pHDRSessionCloseInd
- uint8_t ∗ pManagedRoamingInd
- uint8_t ∗ pNetworkRejectInd
- uint8_t ∗ pSuppressSysInfoInd
- uint8_t ∗ pLTECphyCa
- uint8_t ∗ pEdrxChangeInfoInd

8.725.1 Detailed Description

This structure contains pack indication register parameters.

Parameters

pSystem-SelectionInd	[Optional] • System Selection Preference indication registration. The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pDDTMInd	[Optional] • DDTM (Data Dedicated Transmission Mode) indication registration. The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable

pServing-SystemInd	[Optional] • Serving System indication registration. The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pDualStandBy-PrefInd	[Optional] • Dual Standby Preference indication registration.The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pSubscription-InfoInd	[Optional] • Subscription Information indication registration.The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pNetworkTime-Ind	[Optional] • Network Time indication registration.The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pSysInfoInd	[Optional] • System Information indication registration.The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pSignalStrength-Ind	[Optional] • Signal Strength indication registration.The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pErrorRateInd	[Optional] • Error Rate indication registration.The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pHDRNewUATI-AssInd	[Optional] • HDR New UATI Assigned indication registration.The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable

pHDRSession-CloseInd	[Optional] • HDR Session Closed indication registration.The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pManaged-RoamingInd	[Optional] • Managed Roaming indication registration.The callbacks would not be invoked if the indication is disabled. – 0x00 - Disable
pNetworkReject-Ind	[Optional] • Network reject information indication registration.The following callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable
pSuppressSys-InfoInd	[Optional] • Controls the reporting of QMI_NAS_SYS_INFO_IND when only the reject_cause field has changed. Values: – 0x00 - Disable – 0x01 - Enable- 0x01 - Enable
pLTECphyCa	[Optional] • LTE Physical Carrier Aggregation Information.The following callbacks would not be invoked if the indication is disabled. – 0x00 - Disable (default value) – 0x01 - Enable
pEdrxChange-InfoInd	[Optional] • EDRX Change Info indication registration.The following callbacks would not be invoked if the indication is disabled. – 0x00 - Disable – 0x01 - Enable

8.725.2 Field Documentation

8.725.2.1 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pDDTMInd

8.725.2.2 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pDualStandByPrefInd

8.725.2.3 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pEdrxChangeInfoInd

8.725.2.4 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pErrorRateInd

8.725.2.5 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pHDRNewUATIAssInd

8.725.2.6 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pHDRSessionCloseInd

8.725.2.7 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pLTECphyCa

8.725.2.8 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pManagedRoamingInd

8.725.2.9 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pNetworkRejectInd

8.725.2.10 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pNetworkTimeInd

8.725.2.11 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pServingSystemInd

8.725.2.12 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pSignalStrengthInd

8.725.2.13 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pSubscriptionInfoInd

8.725.2.14 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pSuppressSysInfoInd

8.725.2.15 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pSysInfoInd

8.725.2.16 uint8_t* pack_nas_SLQSNasIndicationRegisterExt_t::pSystemSelectionInd

8.726 pack_nas_SLQSNASSeteDRXParams_t Struct Reference

Data Fields

- uint8_t * pEdrxEnable
- uint8_t * pCycleLen
- uint8_t * pPagingTimeWindow
- uint8_t * pEdrxRatType
- uint32_t * pEdrxCiotLteMode

8.726.1 Detailed Description

This structure contains the SLQSNASSeteDRXParams request parameters.

Parameters

pEdrxEnable	[Optional] • eDRX Enable • Values – 0x00 - Disable – 0x01 - Enable
pCycleLen	[Optional] • eDRX cycle length • Value to be set per 3GPP TS 24.008 Rel-13 Section 10.5.5.32
pPagingTime-Window	[Optional] • eDRX paging time window • Value to be set per 3GPP TS 24.008 Rel-13 Section 10.5.5.32

pEdrxRatType	[Optional] • Radio access technology • Values – NAS_RADIO_IF_NO_SVC (0x00) - None (no service) – NAS_RADIO_IF_CDMA_1X (0x01) - cdma2000 ® 1X – NAS_RADIO_IF_CDMA_1XEVDO (0x02) cdma2000 ® HRPD (1xEV-DO) – NAS_RADIO_IF_AMPS (0x03) - AMPS – NAS_RADIO_IF_GSM (0x04) - GSM – NAS_RADIO_IF_UMTS (0x05) - UMTS – NAS_RADIO_IF_WLAN (0x06) - WLAN – NAS_RADIO_IF_GPS (0x07) - GPS – NAS_RADIO_IF_LTE (0x08) - LTE – NAS_RADIO_IF_TDSCDMA (0x09)- TD-SCDMA – NAS_RADIO_IF_LTE_M1 (0x0a) - LTE-M1 – NAS_RADIO_IF_LTE_NB1 (0x0b) - LTE-NB1 – NAS_RADIO_IF_NO_CHANGE (-1)- No change Note: The device will use “0x08 - NAS_RADIO_IF_LTE” as the default value if the TLV is omitted.
pEdrxCiotLteMode	[Optional] • CIOT LTE mode • Values – NAS_CIOT_SYS_MODE_NO_ SRV(0x00) - No service – NAS_CIOT_SYS_MODE_LTE_ WB(0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_ M1(0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_ NB1(0x03) - Camped on LTE NB1 Note: This TLV should be set when pEdrxRatType is LTE.

8.726.2 Field Documentation

8.726.2.1 uint8_t∗ pack_nas_SLQSNASSeteDRXParams_t::pCycleLen

8.726.2.2 uint32_t∗ pack_nas_SLQSNASSeteDRXParams_t::pEdrxCiotLteMode

8.726.2.3 uint8_t∗ pack_nas_SLQSNASSeteDRXParams_t::pEdrxEnable

8.726.2.4 uint8_t∗ pack_nas_SLQSNASSeteDRXParams_t::pEdrxRatType

8.726.2.5 uint8_t∗ pack_nas_SLQSNASSeteDRXParams_t::pPagingTimeWindow

8.727 pack_nas_SLQSNasSwiIndicationRegister_t Struct Reference

Data Fields

- uint8_t lteEsmUl
- uint8_t lteEsmDl
- uint8_t lteEmmUl
- uint8_t lteEmmDl
- uint8_t gsmUmtsUl
- uint8_t gsmUmtsDl
- uint8_t ∗ pRankIndicatorInd

- uint8_t * pTimer

8.727.1 Detailed Description

This structure contains the OTA message indication.

Parameters

lteEsmUl	• 0 - do not report • 1 - report LTE ESM uplink messages
lteEsmDl	• 0 - do not report • 1 - report LTE ESM downlink messages
lteEmmUl	• 0 - do not report • 1 - report LTE EMM uplink messages
lteEmmDl	• 0 - do not report • 1 - report GSM/UMTS uplink messages
gsmUmtsUl	• 0 - do not report • 1 - report GSM/UMTS uplink messages
gsmUmtsDl	• 0 - do not report • 1 - report GSM/UMTS downlink messages
pRankIndicator-Ind	• 0 - do not report • 1 - report Rank Indicator messages
pTimer	• 0 - do not report • 1 - report Timer Indicator messages

8.727.2 Field Documentation

8.727.2.1 uint8_t pack_nas_SLQSNasSwiIndicationRegister_t::gsmUmtsDl

8.727.2.2 uint8_t pack_nas_SLQSNasSwiIndicationRegister_t::gsmUmtsUl

8.727.2.3 uint8_t pack_nas_SLQSNasSwiIndicationRegister_t::lteEmmDl

8.727.2.4 uint8_t pack_nas_SLQSNasSwiIndicationRegister_t::lteEmmUl

8.727.2.5 uint8_t pack_nas_SLQSNasSwiIndicationRegister_t::lteEsmDl

8.727.2.6 uint8_t pack_nas_SLQSNasSwiIndicationRegister_t::lteEsmUI

8.727.2.7 uint8_t* pack_nas_SLQSNasSwiIndicationRegister_t::pRankIndicatorInd

8.727.2.8 uint8_t* pack_nas_SLQSNasSwiIndicationRegister_t::pTimer

8.728 pack_nas_SLQSNASSwiSetChannelLock_t Struct Reference

Data Fields

- nas_wcdmaUARFCN * pWcdmaUARFCN
- nas_lteEARFCN * pLteEARFCN
- nas_ltePCI * pLtePCI

8.728.1 Detailed Description

Structure for ChannelLock pack.

Parameters

pWcdmaUARFCN	[Optional] • See nas_wcdmaUARFCN for more information
pLteEARFCN	[Optional] • See nas_lteEARFCN for more information
pLtePCI	[Optional] • See nas_ltePCI for more information

8.728.2 Field Documentation

8.728.2.1 nas_lteEARFCN* pack_nas_SLQSNASSwiSetChannelLock_t::pLteEARFCN

8.728.2.2 nas_ltePCI* pack_nas_SLQSNASSwiSetChannelLock_t::pLtePCI

8.728.2.3 nas_wcdmaUARFCN* pack_nas_SLQSNASSwiSetChannelLock_t::pWcdmaUARFCN

8.729 pack_nas_SLQSSetBandPreference_t Struct Reference

Data Fields

- uint64_t bandPref

8.729.1 Detailed Description

Provides information about the band preference.

Parameters

bandpreference	• Bit mask representing the band preference to be set. • Bit position meanings: – 0 - BC0_A - Band Class 0, A-System – 1 - BC0_B - Band Class 0, B-System, Band Class 0 AB , GSM 850 Band – 2 - BC1 - Band Class 1, all blocks – 3 - BC2 - Band Class 2 place holder – 4 - BC3 - Band Class 3, A-System – 5 - BC4 - Band Class 4, all blocks – 6 - BC5 - Band Class 5, all blocks – 7 - GSM_DCS_1800 - GSM DCS band – 8 - GSM_EGSM_900 - GSM Extended GSM (E-GSM) band – 9 - GSM_PGSM_900 - GSM Primary GSM (P-GSM) band – 10 - BC6 - Band Class 6 – 11 - BC7 - Band Class 7 – 12 - BC8 - Band Class 8 – 13 - BC9 - Band Class 9 – 14 - BC10 - Band Class 10 – 15 - BC11 - Band Class 11 – 16 - GSM_450 - GSM 450 band – 17 - GSM_480 - GSM 480 band – 18 - GSM_750 - GSM 750 band – 19 - GSM_850 - GSM 850 band – 20 - GSM_RGSM_900 - GSM Railways GSM Band – 21 - GSM_PCS_1900 - GSM PCS band – 22 - WCDMA_I_IMT_2000 - WCDMA EUROPE JAPAN and CHINA IMT 2100 band – 23 - WCDMA_II_PCS_1900 - WCDMA US PCS 1900 band – 24 - WCDMA_III_1700 - WCDMA EUROPE and CHINA DCS 1800 band – 25 - WCDMA_IV_1700 - WCDMA US 1700 band – 26 - WCDMA_V_850 - WCDMA US 850 band – 27 - WCDMA_VI_800 - WCDMA JAPAN 800 band – 28 - BC12 - Band Class 12 – 29 - BC14 - Band Class 14 – 30 - RESERVED_2 - Reserved 2 – 31 - BC15 - Band Class 15 – 32 - 47 - Reserved – 48 - WCDMA_VII_2600 - WCDMA EUROPE 2600 band – 49 - WCDMA_VIII_900 - WCDMA EUROPE and JAPAN 900 band – 50 - WCDMA_IX_1700 - WCDMA JAPAN 1700 band – 51 to 55 - Reserved – 56 - BBC16 - Band Class 16 – 57 - BC17 - Band Class 17 – 58 - BC18 - Band Class 18 – 59 - BC19 - Band Class 19 – 60 to 64 - Reserved

8.729.2 Field Documentation

8.729.2.1 uint64_t pack_nas_SLQSSetBandPreference_t::bandPref

8.730 pack_nas_SLQSSetSignalStrengthsCallback_t Struct Reference

Data Fields

- uint8_t bEnable
- nas_SLQSSignalStrengthsIndReq * pSigIndReq

8.730.1 Detailed Description

This structure contains paramaters pack set strength thresholds callback.

Parameters

bEnable	0/1 to disable/enable RSSI signal stregth indication
pSigIndReq	parameters to control signal strength indication

8.730.2 Field Documentation

8.730.2.1 uint8_t pack_nas_SLQSSetSignalStrengthsCallback_t::bEnable

8.730.2.2 nas_SLQSSignalStrengthsIndReq* pack_nas_SLQSSetSignalStrengthsCallback_t::pSigIndReq

8.731 pack_nas_SLQSSetSysSelectionPref_t Struct Reference

Data Fields

- uint8_t * pEmerMode
- uint16_t * pModePref
- uint64_t * pBandPref
- uint16_t * pPRLPref
- uint16_t * pRoamPref
- uint64_t * pLTEBandPref
- struct nas_netSelectionPref * pNetSelPref
- uint8_t * pChgDuration
- uint8_t * pMNCIncPCSDigStat
- uint32_t * pSrvDomainPref
- uint32_t * pGWAcqOrderPref
- uint64_t * pTdscdmaBandPref
- struct nas_acqOrderPref * pAcqOrderPref
- uint32_t * pSrvRegRestriction
- struct nas_CSGID * pCSGID
- unsigned char * pRAT

8.731.1 Detailed Description

Contain the system selection preferences.

Parameters

pEmerMode	• Optional parameter specifying the emergency Mode • Values: – 0 - OFF (normal) – 1 - ON (Emergency)
pModePref	• Optional parameter • Bit Mask indicating the radio technology mode preference • Bit values: – Bit 0 - cdma2000 1x – Bit 1 - cdma2000 HRPD(1xEV-DO) – Bit 2 - GSM – Bit 3 - UMTS – Bit 4 - LTE

pBandPref	• Optional parameter • Bit mask representing the band preference • Bit values: – Bit 0 - Band Class 0, A-System – Bit 1 - Band Class 0, B-System, Band Class 0 AB, GSM 850 Band – Bit 2 - Band Class 1, all blocks – Bit 3 - Band Class 2 place holder – Bit 4 - Band Class 3, A-System – Bit 5 - Band Class 4, all blocks – Bit 6 - Band Class 5, all blocks – Bit 7 - GSM_DCS_1800 band – Bit 8 - GSM Extended GSM (E-GSM) 900 band – Bit 9 - GSM Primary GSM (P-GSM) 900 band – Bit 10 - Band Class 6 – Bit 11 - Band Class 7 – Bit 12 - Band Class 8 – Bit 13 - Band Class 9 – Bit 14 - Band Class 10 – Bit 15 - Band Class 11 – Bit 16 - GSM 450 band – Bit 17 - GSM 480 band – Bit 18 - GSM 750 band – Bit 19 - GSM 850 band – Bit 20 - GSM Railways GSM 900 Band – Bit 21 - GSM PCS 1900 band – Bit 22 - WCDMA Europe, Japan, and China IMT 2100 band – Bit 23 - WCDMA U.S. PCS 1900 band – Bit 24 - WCDMA Europe and China DCS 1800 band – Bit 25 - WCDMA U.S. 1700 band – Bit 26 - WCDMA U.S. 850 band – Bit 27 - WCDMA Japan 800 band – Bit 28 - Band Class 12 – Bit 29 - Band Class 14 – Bit 30 - Reserved – Bit 31 - Band Class 15 – Bit 32 to 47 - Reserved – Bit 48 - WCDMA Europe 2600 band – Bit 49 - WCDMA Europe and Japan 900 band – Bit 50 - WCDMA Japan 1700 band – Bit 51 to 55 - Reserved – Bit 56 - Band Class 16 – Bit 57 - Band Class 17 – Bit 58 - Band Class 18 – Bit 59 - Band Class 19 – Bit 60 to 64 - Reserved

pPRLPref	• Optional parameter indicating the CDMA PRL Preference • Values: – 0x0001 - Acquire available system only on the A side – 0x0002 - Acquire available system only on the B side – 0x3FFF - Acquire any available systems
pRoamPref	• Optional parameter indicating the roaming Preference • Values: – 0x01 - Acquire only systems for which the roaming indicator is off – 0x02 - Acquire a system as long as its roaming indicator is not off – 0x03 - Acquire only systems for which the roaming indicator is off or solid on, i.e. not flashing; CDMA only – 0xFF - Acquire systems, regardless of their roaming indicator
pLTEBandPref	• Optional parameter • Bit mask representing the LTE band preference • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – All other bits are reserved

pNetSelPref	- netSelectionPref • Optional parameter for specifying Network Selection Preference • Modem selects networks based on this parameter(if present). • see nas_netSelectionPref for more information
pChgDuration	• Optional parameter specifying the duration of the change • Values: – 0x00 - Power cycle - Remains active until the next device power cycle – 0x01 - Permanent - Remains active through power cycles until changed by client – Device will use "0x01 - permanent" as default if this parameter is omitted
pMNCIncPCS-DigStat	• Optional parameter indicating if MNC includes PCS digit • Values: – TRUE - MNC is a 3 digit value; e.g., a reported value of 90 corresponds to an MNC value of 090 – FALSE - MNC is a 2-digit value; e.g., a reported value of 90 corresponds to an MNC value of 90
pSrvDomainPref	• Optional parameter indicating Service domain preference • Values: – 0x00 - Circuit switched only – 0x01 - Packet switched only – 0x02 - Circuit switched and packet switched – 0x03 - Packet switched attach – 0x04 - Packet switched detach
pGWAcqOrder-Pref	• Optional parameter indicating GSM/WCDMA Acquisition order Preference • Values: – 0x00 - Automatic – 0x01 - GSM then WCDMA – 0x02 - WCDMA then GSM
pTdscdmaBand-Pref	• Optional parameter indicating bitmask representing the TD-SCDMA band preference to be set. • Values: – 0x01 - TD-SCDMA Band A – 0x02 - TD-SCDMA Band B – 0x04 - TD-SCDMA Band C – 0x08 - TD-SCDMA Band D – 0x10 - TD-SCDMA Band E – 0x20 - TD-SCDMA Band F – All other bits are reserved
pAcqOrderPref	- acqOrderPref • Optional parameter for specifying Acquisition Order Preference • see nas_acqOrderPref for more information

pSrvReg-Restriction	• Optional parameter indicating Network Selection Registration Restriction Preference • Values: – 0x00 - Device follows the normal registration process – 0x01 - Device camps on the network according to its provisioning, but does not register – 0x02 - Device selects the network for limited service – All other values are reserved.
pCSGID	- CSGID • Optional parameter for specifying CSG ID • Either of pNetSelPref or pCSGID can be set. • see nas_CSGID for more information
pRAT	• Optional parameter Radio Access Technology order Preference • Values: – 0x04 - GSM – 0x05 - UMTS – 0x08 - LTE – 0x09 - TDSCDMA

8.731.2 Field Documentation

8.731.2.1 struct nas_acqOrderPref* pack_nas_SLQSSetSysSelectionPref_t::pAcqOrderPref

8.731.2.2 uint64_t* pack_nas_SLQSSetSysSelectionPref_t::pBandPref

8.731.2.3 uint8_t* pack_nas_SLQSSetSysSelectionPref_t::pChgDuration

8.731.2.4 struct nas_CSGID* pack_nas_SLQSSetSysSelectionPref_t::pCSGID

8.731.2.5 uint8_t* pack_nas_SLQSSetSysSelectionPref_t::pEmerMode

8.731.2.6 uint32_t* pack_nas_SLQSSetSysSelectionPref_t::pGWAcqOrderPref

8.731.2.7 uint64_t* pack_nas_SLQSSetSysSelectionPref_t::pLTEBandPref

8.731.2.8 uint8_t* pack_nas_SLQSSetSysSelectionPref_t::pMNCIncPCSDigStat

8.731.2.9 uint16_t* pack_nas_SLQSSetSysSelectionPref_t::pModePref

8.731.2.10 struct nas_netSelectionPref* pack_nas_SLQSSetSysSelectionPref_t::pNetSelPref

8.731.2.11 uint16_t* pack_nas_SLQSSetSysSelectionPref_t::pPRLPref

8.731.2.12 unsigned char* pack_nas_SLQSSetSysSelectionPref_t::pRAT

8.731.2.13 uint16_t* pack_nas_SLQSSetSysSelectionPref_t::pRoamPref

8.731.2.14 uint32_t* pack_nas_SLQSSetSysSelectionPref_t::pSrvDomainPref

8.731.2.15 uint32_t* pack_nas_SLQSSetSysSelectionPref_t::pSrvRegRestriction

8.731.2.16 uint64_t* pack_nas_SLQSSetSysSelectionPref_t::pTdscdmaBandPref

8.732 pack_nas_SLQSSetSysSelectionPrefExt_t Struct Reference

Data Fields

- uint8_t * pEmerMode
- uint16_t * pModePref
- uint64_t * pBandPref
- uint16_t * pPRLPref
- uint16_t * pRoamPref
- uint64_t * pLTEBandPref
- struct nas_netSelectionPref * pNetSelPref
- uint8_t * pChgDuration
- uint8_t * pMNCIncPCSDigStat
- uint32_t * pSrvDomainPref
- uint32_t * pGWAcqOrderPref
- uint64_t * pTdscdmaBandPref
- struct nas_acqOrderPref * pAcqOrderPref
- uint32_t * pSrvRegRestriction
- struct nas_CSGID * pCSGID
- unsigned char * pRAT
- struct nas_lteBandPrefExt * pLTEBandPrefExt
- uint64_t * pCiotLteOpModePref
- uint64_t * pLteM1BandPref
- uint64_t * pLteNb1BandPref
- uint32_t * pCiotLteOpMode
- struct nas_ciotAcqOrderPref * pCiotAcqOrderPref
- struct nas_nr5gBandPref * pNr5gBandPref

8.732.1 Detailed Description

Contain the system selection preferences.

Parameters

pEmerMode	• Optional parameter specifying the emergency Mode • Values: – 0 - OFF (normal) – 1 - ON (Emergency)

pModePref	• Optional parameter • Bit Mask indicating the radio technology mode preference • Bit values: – Bit 0 - cdma2000 1x – Bit 1 - cdma2000 HRPD(1xEV-DO) – Bit 2 - GSM – Bit 3 - UMTS – Bit 4 - LTE – Bit 5 - TD-SCDMA – Bit 6 - NR5G

pBandPref	• Optional parameter • Bit mask representing the band preference • Bit values: – Bit 0 - Band Class 0, A-System – Bit 1 - Band Class 0, B-System, Band Class 0 AB, GSM 850 Band – Bit 2 - Band Class 1, all blocks – Bit 3 - Band Class 2 place holder – Bit 4 - Band Class 3, A-System – Bit 5 - Band Class 4, all blocks – Bit 6 - Band Class 5, all blocks – Bit 7 - GSM_DCS_1800 band – Bit 8 - GSM Extended GSM (E-GSM) 900 band – Bit 9 - GSM Primary GSM (P-GSM) 900 band – Bit 10 - Band Class 6 – Bit 11 - Band Class 7 – Bit 12 - Band Class 8 – Bit 13 - Band Class 9 – Bit 14 - Band Class 10 – Bit 15 - Band Class 11 – Bit 16 - GSM 450 band – Bit 17 - GSM 480 band – Bit 18 - GSM 750 band – Bit 19 - GSM 850 band – Bit 20 - GSM Railways GSM 900 Band – Bit 21 - GSM PCS 1900 band – Bit 22 - WCDMA Europe, Japan, and China IMT 2100 band – Bit 23 - WCDMA U.S. PCS 1900 band – Bit 24 - WCDMA Europe and China DCS 1800 band – Bit 25 - WCDMA U.S. 1700 band – Bit 26 - WCDMA U.S. 850 band – Bit 27 - WCDMA Japan 800 band – Bit 28 - Band Class 12 – Bit 29 - Band Class 14 – Bit 30 - Reserved – Bit 31 - Band Class 15 – Bit 32 to 47 - Reserved – Bit 48 - WCDMA Europe 2600 band – Bit 49 - WCDMA Europe and Japan 900 band – Bit 50 - WCDMA Japan 1700 band – Bit 51 to 55 - Reserved – Bit 56 - Band Class 16 – Bit 57 - Band Class 17 – Bit 58 - Band Class 18 – Bit 59 - Band Class 19 – Bit 60 to 64 - Reserved

pPRLPref	• Optional parameter indicating the CDMA PRL Preference • Values: – 0x0001 - Acquire available system only on the A side – 0x0002 - Acquire available system only on the B side – 0x3FFF - Acquire any available systems
pRoamPref	• Optional parameter indicating the roaming Preference • Values: – 0x01 - Acquire only systems for which the roaming indicator is off – 0x02 - Acquire a system as long as its roaming indicator is not off – 0x03 - Acquire only systems for which the roaming indicator is off or solid on, i.e. not flashing; CDMA only – 0xFF - Acquire systems, regardless of their roaming indicator

pLTEBandPref	• Optional parameter • Bit mask representing the LTE band preference • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – All other bits are reserved

pNetSelPref	- netSelectionPref • Optional parameter for specifying Network Selection Preference • Modem selects networks based on this parameter(if present). • Either of pNetSelPref or pCSGID can be set. • see nas_netSelectionPref for more information
pChgDuration	• Optional parameter specifying the duration of the change • At least one system selection setting to be set if pChgDuration is populated. • Values: – 0x00 - Power cycle - Remains active until the next device power cycle – 0x01 - Permanent - Remains active through power cycles until changed by client – Device will use "0x01 - permanent" as default if this parameter is omitted
pMNCIncPCS-DigStat	• Optional parameter indicating if MNC includes PCS digit • pNetSelPref is expected if MNC includes PCS digit is set to 1. • Values: – TRUE - MNC is a 3 digit value; e.g., a reported value of 90 corresponds to an MNC value of 090 – FALSE - MNC is a 2-digit value; e.g., a reported value of 90 corresponds to an MNC value of 90
pSrvDomainPref	• Optional parameter indicating Service domain preference • Values: – 0x00 - Circuit switched only – 0x01 - Packet switched only – 0x02 - Circuit switched and packet switched – 0x03 - Packet switched attach – 0x04 - Packet switched detach
pGWAcqOrder-Pref	• Optional parameter indicating GSM/WCDMA Acquisition order Preference • Values: – 0x00 - Automatic – 0x01 - GSM then WCDMA – 0x02 - WCDMA then GSM
pTdscdmaBand-Pref	• Optional parameter indicating bitmask representing the TD-SCDMA band preference to be set. • Values: – 0x01 - TD-SCDMA Band A – 0x02 - TD-SCDMA Band B – 0x04 - TD-SCDMA Band C – 0x08 - TD-SCDMA Band D – 0x10 - TD-SCDMA Band E – 0x20 - TD-SCDMA Band F – All other bits are reserved

pAcqOrderPref	- acqOrderPref • Optional parameter for specifying Acquisition Order Preference • see nas_acqOrderPref for more information
pSrvReg-Restriction	• Optional parameter indicating Network Selection Registration Restriction Preference • Values: – 0x00 - Device follows the normal registration process – 0x01 - Device camps on the network according to its provisioning, but does not register – 0x02 - Device selects the network for limited service – All other values are reserved.
pCSGID	- CSGID • Optional parameter for specifying CSG ID • Either of pNetSelPref or pCSGID can be set. • see nas_CSGID for more information
pRAT	• Optional parameter Radio Access Technology order Preference • Values: – 0x04 - GSM – 0x05 - UMTS – 0x08 - LTE – 0x09 - TDSCDMA – 0x0A - LTE-M1 – 0x0B - LTE-NB1 – 0x0C - NR5G
pLTEBandPref-Ext[IN]	• LTE Band Preference Extended • see nas_lteBandPrefExt for more information
pCiotLteOp-ModePref[IN]	• CIOT LTE Operational Mode Preference • Bitmask representing the CIoT LTE operational mode preference to be set. • Values : – Bit 0 - LTE wideband – Bit 1 - LTE M1 – Bit 2 - LTE NB1 All unlisted bits are reserved for future use and the service point ignores them if used. If this TLV is not present, the modem will use the value read from the NV during bootup.

pLteM1Band-Pref[IN]	• Bitmask representing the LTE M1 band preference to be set. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127

- If this field is not present, the modem will use the M1 band preference value read from the NV.

Parameters

pLteNb1Band-Pref[IN]	• Bitmask representing the LTE NB1 band preference to be set. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127 • If this field is not present, the modem will use the NB1 band preference value read from the NV.

pCiotLteOpMode	• This TLV is used when the net_sel_pref is MANUAL and RAT TLV is LTE. • This TLV indicates the the operational mode to be used during the manual LTE PLMN selection. • Values : – 0x00 - No service – 0x01 - Camped on LTE wideband – 0x02 - Camped on LTE M1 – 0x03 - Camped on LTE NB1
pCiotAcqOrder-Pref[IN]	• CIOT Acquisition Order Preference • see nas_ciotAcqOrderPref for more information
pNr5gBandPref[-IN]	• NR5G Band Preference • see nas_nr5gBandPref for more information

8.732.2 Field Documentation

8.732.2.1 struct nas_acqOrderPref* pack_nas_SLQSSetSysSelectionPrefExt_t::pAcqOrderPref

8.732.2.2 uint64_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pBandPref

8.732.2.3 uint8_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pChgDuration

8.732.2.4 struct nas_ciotAcqOrderPref* pack_nas_SLQSSetSysSelectionPrefExt_t::pCiotAcqOrderPref

8.732.2.5 uint32_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pCiotLteOpMode

8.732.2.6 uint64_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pCiotLteOpModePref

8.732.2.7 struct nas_CSGID* pack_nas_SLQSSetSysSelectionPrefExt_t::pCSGID

8.732.2.8 uint8_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pEmerMode

8.732.2.9 uint32_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pGWAcqOrderPref

8.732.2.10 uint64_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pLTEBandPref

8.732.2.11 struct nas_lteBandPrefExt* pack_nas_SLQSSetSysSelectionPrefExt_t::pLTEBandPrefExt

8.732.2.12 uint64_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pLteM1BandPref

8.732.2.13 uint64_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pLteNb1BandPref

8.732.2.14 uint8_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pMNCIncPCSDigStat

8.732.2.15 uint16_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pModePref

8.732.2.16 struct nas_netSelectionPref* pack_nas_SLQSSetSysSelectionPrefExt_t::pNetSelPref

8.732.2.17 struct nas_nr5gBandPref* pack_nas_SLQSSetSysSelectionPrefExt_t::pNr5gBandPref

8.732.2.18 uint16_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pPRLPref

8.732.2.19 unsigned char* pack_nas_SLQSSetSysSelectionPrefExt_t::pRAT

8.732.2.20 uint16_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pRoamPref

8.732.2.21 uint32_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pSrvDomainPref

8.732.2.22 uint32_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pSrvRegRestriction

8.732.2.23 uint64_t* pack_nas_SLQSSetSysSelectionPrefExt_t::pTdscdmaBandPref

8.733 pack_nas_SLQSSwiPSDetach_t Struct Reference

Data Fields

- uint8_t * pDetachAction

8.733.1 Detailed Description

Structure for PS connection detach pack.

Parameters

pDetachAction[IN]	• Values – 2- Initiates an immediate packet domain detach.

8.733.2 Field Documentation

8.733.2.1 uint8_t* pack_nas_SLQSSwiPSDetach_t::pDetachAction

8.734 pack_pds_PDSInjectTimeReference_t Struct Reference

Data Fields

- uint64_t systemTime
- uint16_t systemDiscontinuities

8.734.1 Detailed Description

Structure contain the parameter for PDS Inject time.

Parameters

systemTime	• System time(milliseconds)
systemDiscontinuities	• Number of system time discontinuities

8.734.2 Field Documentation

8.734.2.1 uint16_t pack_pds_PDSInjectTimeReference_t::systemDiscontinuities

8.734.2.2 uint64_t pack_pds_PDSInjectTimeReference_t::systemTime

8.735 pack_pds_ResetPDSData_t Struct Reference

Data Fields

- uint32_t ∗ pGPSDataMask
- uint32_t ∗ pCellDataMask

8.735.1 Detailed Description

Structure contain the parameter to Resets the specified PDS data.

Parameters

pGPSDataMask	• Bitmask of GPS data to clear (optional) – 0x00000001 - EPH – 0x00000002 - ALM – 0x00000004 - POS – 0x00000008 - TIME – 0x00000010 - IONO – 0x00000020 - UTC – 0x00000040 - HEALTH – 0x00000080 - SVDIR – 0x00000100 - SVSTEER – 0x00000200 - SADATA – 0x00000400 - RTI – 0x00000800 - ALM_CORR – 0x00001000 - FREQ_BIAS_EST
pCellDataMask	• Bitmask of cell data to clear (optional) – 0x00000001 - POS – 0x00000002 - LATEST_GPS_POS – 0x00000004 - OTA_POS – 0x00000008 - EXT_REF_POS – 0x00000010 - TIMETAG – 0x00000020 - CELLID – 0x00000040 - CACHED_CELLID – 0x00000080 - LAST_SRV_CELL – 0x00000100 - CUR_SRV_CELL – 0x00000200 - NEIGHBOR_INFO

8.735.2 Field Documentation

8.735.2.1 uint32_t* pack_pds_ResetPDSData_t::pCellDataMask

8.735.2.2 uint32_t* pack_pds_ResetPDSData_t::pGPSDataMask

8.736 pack_pds_SetEventReportCallback_t Struct Reference

Data Fields

- uint8_t posDataNmea
- uint8_t rptPosData

8.736.1 Detailed Description

Structure contain the parameter for the automatic tracking configuration for the NMEA COM port.

Parameters

posDataNmea	• Report new position data in NMEA format. • Values – 0x00 - Disable – 0x01 - Enable
rptPosData	• Report new position data in raw format. • Values – 0x00 - Disable – 0x01 - Enable

8.736.2 Field Documentation

8.736.2.1 uint8_t pack_pds_SetEventReportCallback_t::posDataNmea

8.736.2.2 uint8_t pack_pds_SetEventReportCallback_t::rptPosData

8.737 pack_pds_SetPDSDefaults_t Struct Reference

Data Fields

- uint32_t operation
- uint8_t timeout
- uint32_t interval
- uint32_t accuracy

8.737.1 Detailed Description

Structure containing session configuration parameters.

Parameters

operation	• Current session operating mode – 0 - Standalone – 1 - MS based – 2 - MS assisted
timeout	• Maximum amount of time (seconds) to work on each fix, maximum is 255
interval	• Interval (seconds) between fix requests
accuracy	• Preferred accuracy threshold (meters)

8.737.2 Field Documentation

8.737.2.1 uint32_t pack_pds_SetPDSDefaults_t::accuracy

8.737.2.2 uint32_t pack_pds_SetPDSDefaults_t::interval

8.737.2.3 uint32_t pack_pds_SetPDSDefaults_t::operation

8.737.2.4 uint8_t pack_pds_SetPDSDefaults_t::timeout

8.738 pack_pds_SetPDSState_t Struct Reference

Data Fields

- uint32_t enable

8.738.1 Detailed Description

Structure contain PDS state parameters.

Parameters

enable	• Desired PDS state – Zero - disable – Non-Zero - enable

8.738.2 Field Documentation

8.738.2.1 uint32_t pack_pds_SetPDSState_t::enable

8.739 pack_pds_SetPortAutomaticTracking_t Struct Reference

Data Fields

- uint32_t bAuto

8.739.1 Detailed Description

Structure contain the parameter for the automatic tracking configuration for the NMEA COM port.

Parameters

bAuto	• Enable automatic tracking for NMEA COM port – 0x00 - Disabled – 0x01 - Enabled

8.739.2 Field Documentation

8.739.2.1 uint32_t pack_pds_SetPortAutomaticTracking_t::bAuto

8.740 pack_pds_SetServiceAutomaticTracking_t Struct Reference

Data Fields

- uint32_t bAuto

8.740.1 Detailed Description

Structure contain the parameter to Sets the automatic tracking state.

Parameters

bAuto	• Automatic tracking session started for service – 0x00 - Disabled – 0x01 - Enabled

8.740.2 Field Documentation

8.740.2.1 uint32_t pack_pds_SetServiceAutomaticTracking_t::bAuto

8.741 pack_pds_SetXTRAAutomaticDownload_t Struct Reference

Data Fields

- uint32_t bEnabled
- uint16_t interval

8.741.1 Detailed Description

Structure contain the parameter to set the XTRA automatic database download configuration.

Parameters

bEnabled	• Automatic XTRA download status – 0 - Disabled – 1 - Enabled
interval	• Interval (hours) between XTRA downloads

8.741.2 Field Documentation

8.741.2.1 uint32_t pack_pds_SetXTRAAutomaticDownload_t::bEnabled

8.741.2.2 uint16_t pack_pds_SetXTRAAutomaticDownload_t::interval

8.742 pack_pds_SetXTRANetwork_t Struct Reference

Data Fields

- uint32_t preference

8.742.1 Detailed Description

Structure contain the parameter to Sets the XTRA WWAN network preference

Parameters

preference	• XTRA WWAN network preference – 0x00 - None (any available network) – 0x01 - Home-only, only when on home systems – 0x02 - Roam-only, only when on non-home systems

8.742.2 Field Documentation

8.742.2.1 uint32_t pack_pds_SetXTRANetwork_t::preference

8.743 pack_pds_SLQSGetAGPSConfig_t Struct Reference

Data Fields

- uint8_t * pNetworkMode

8.743.1 Detailed Description

Structure contain the parameter to PDS AGPS (MS-based) configuration pack.

Parameters

pNetworkMode	• Network Mode of AGPS Server [optional - should be present in Multimode Systems] – 0x00 - UMTS – 0x01 - CDMA

8.743.2 Field Documentation

8.743.2.1 uint8_t* pack_pds_SLQSGetAGPSConfig_t::pNetworkMode

8.744 pack_pds_SLQSPDSInjectAbsoluteTimeReference_t Struct Reference

Data Fields

- uint64_t timeMsec
- uint32_t timeUncMsec
- uint8_t timeBase
- uint8_t forceFlag

8.744.1 Detailed Description

Structure contain the parameter to Injects a absolute time reference.

Parameters

timeMsec	• Represents the number of milliseconds elapsed since either a GPS or UTC time base. If the time base is UTC, this value should NOT include leap seconds
timeUncMsec	• Time uncertainty in milliseconds
timeBase	• Time base – 0x00 - GPS (midnight, Jan 6, 1980) – 0x01 - UTC (midnight, Jan 1, 1970)
forceFlag	• Force acceptance of data

8.744.2 Field Documentation

8.744.2.1 uint8_t pack_pds_SLQSPDSInjectAbsoluteTimeReference_t::forceFlag

8.744.2.2 uint8_t pack_pds_SLQSPDSInjectAbsoluteTimeReference_t::timeBase

8.744.2.3 uint64_t pack_pds_SLQSPDSInjectAbsoluteTimeReference_t::timeMsec

8.744.2.4 uint32_t pack_pds_SLQSPDSInjectAbsoluteTimeReference_t::timeUncMsec

8.745 pack_pds_SLQSPDSInjectPositionData_t Struct Reference

Data Fields

- uint64_t * pTimeStamp
- uint64_t * pLatitude
- uint64_t * pLongitude
- uint32_t * pAltitudeWrtEllipsoid
- uint32_t * pAltitudeWrtSealevel
- uint32_t * pHorizontalUncCircular
- uint32_t * pVerticalUnc
- uint8_t * pHorizontalConfidence
- uint8_t * pVerticalConfidence
- uint8_t * pPositionSource
- uint8_t * pTimeType

8.745.1 Detailed Description

Position Data Parameters from the external source to be injected to PDS engine.

Parameters

pTimeStamp	• Timestamp of the injected position in msec. The time can be of type UTC, GPS, or Age and is defined in the pTimeType parameter. If the pTimeType is not present, the timestamp shall be assumed to be UTC time
pLatitude	• Latitude position referenced to the WGS-84 reference ellipsoid, counting positive angles north of the equator and negative angles south of the equator. Value (in decimal degrees) in the range from -90 degrees to +90 degrees.Value in double float format (refer toIEEE Std 754-1985)
pLongitude	• Longitude position referenced to the WGS-84 reference ellipsoid, counting positive angles east of the Greenwich Meridian and negative angles west of Greenwich meridian. Value (in decimal degrees) in the range from -180 degrees to +180 degrees.
pAltitudeWrt-Ellipsoid	• Height above the WGS-84 reference ellipsoid. Value conveys height (in meters). When injecting altitude information, the control point should include either this parameter or the pAltitudeWrt-Sealevel parameter. Value in single float format (refer to IEEE Std 754-1985)
pAltitudeWrt-Sealevel	• Height of MS above the mean sea level in units (in meters). When injecting altitude information, the control point should include either this parameter or the pAltitudeWrtEllipsoid parameter. Value in single float format (refer to IEEE Std 754-1985)
pHorizontalUnc-Circular	• Circular horizontal uncertainty (in meters). This parameter must be included if the latitude and longitude parameters are specified. Value in single float format (refer to IEEE Std 754-1985)

pVerticalUnc	• Vertical uncertainty (in meters). This parameter must be included if one of the altitude parameter are specified.Value in single float format (refer to IEEE Std 754-1985)
pHorizontal-Confidence	• Confidence value of the location horizontal uncertainty, specified as percentage, 1 to 100. This parameter must be included if the latitude and longitude parameters are specified.
pVertical-Confidence	• Confidence value of the location vertical uncertainty, specified as percentage, 1 to 100. This parameter must be included if one of the altitude paramters are specified.
pPositionSource	• Source of injected position: – 0x00 - Unknown – 0x01 - GPS – 0x02 - Cell ID – 0x03 - Enhanced cell ID – 0x04 - WiFi – 0x05 - Terrestrial – 0x06 - Terrestrial hybrid – 0x07 - Other
pTimeType	• Defines the time value set in the pTimeStamp parameter. – 0x00 - UTC Time: starting Jan 1, 1970 – 0x01 - GPS Time: starting Jan 6, 1980 – 0x02 - Age: Age of position information

8.745.2 Field Documentation

8.745.2.1 uint32_t* pack_pds_SLQSPDSInjectPositionData_t::pAltitudeWrtEllipsoid

8.745.2.2 uint32_t* pack_pds_SLQSPDSInjectPositionData_t::pAltitudeWrtSealevel

8.745.2.3 uint8_t* pack_pds_SLQSPDSInjectPositionData_t::pHorizontalConfidence

8.745.2.4 uint32_t* pack_pds_SLQSPDSInjectPositionData_t::pHorizontalUncCircular

8.745.2.5 uint64_t* pack_pds_SLQSPDSInjectPositionData_t::pLatitude

8.745.2.6 uint64_t* pack_pds_SLQSPDSInjectPositionData_t::pLongitude

8.745.2.7 uint8_t* pack_pds_SLQSPDSInjectPositionData_t::pPositionSource

8.745.2.8 uint64_t* pack_pds_SLQSPDSInjectPositionData_t::pTimeStamp

8.745.2.9 uint8_t* pack_pds_SLQSPDSInjectPositionData_t::pTimeType

8.745.2.10 uint8_t* pack_pds_SLQSPDSInjectPositionData_t::pVerticalConfidence

8.745.2.11 uint32_t* pack_pds_SLQSPDSInjectPositionData_t::pVerticalUnc

8.746 pack_pds_SLQSSetAGPSConfig_t Struct Reference

Data Fields

- uint32_t * pServerAddress
- uint32_t * pServerPort
- uint8_t * pServerURL
- uint8_t * pServerURLLength
- uint8_t * pNetworkMode

8.746.1 Detailed Description

Structure contain the parameter to Sets the PDS AGPS (MS-based) configuration.

Parameters

pServerAddress	• IPv4 address of AGPS server [optional]
pServerPort	• Port number of AGPS server [optional - should be present when pServerAddress is present]
pServerURL	• URL of the AGPS server [optional]
pServerURL-Length	• URL length of AGPS server [optional - should be present when pServerURL is present]
pNetworkMode	• Network Mode of AGPS Server [optional - should be present in Multimode Systems] – 0x00 - UMTS – 0x01 - CDMA

8.746.2 Field Documentation

8.746.2.1 uint8_t* pack_pds_SLQSSetAGPSConfig_t::pNetworkMode

8.746.2.2 uint32_t* pack_pds_SLQSSetAGPSConfig_t::pServerAddress

8.746.2.3 uint32_t* pack_pds_SLQSSetAGPSConfig_t::pServerPort

8.746.2.4 uint8_t* pack_pds_SLQSSetAGPSConfig_t::pServerURL

8.746.2.5 uint8_t* pack_pds_SLQSSetAGPSConfig_t::pServerURLLength

8.747 pack_pds_SLQSSetPositionMethodState_t Struct Reference

Data Fields

- uint8_t * pXtraTimeState

- uint8_t * pXtraDataState
- uint8_t * pWifiState

8.747.1 Detailed Description

Parameters to Set state of positioning method for a device.

Parameters

pXtraTimeState	• XTRA Time Position Method State. • Values: – 0x00 - Disable – 0x01 - Enable
pXtraDataState	• XTRA Data Position Method State. • Values: – 0x00 - Disable – 0x01 - Enable
Latitude	• WiFi Position Method State • Values: – 0x00 - Disable – 0x01 - Enable

8.747.2 Field Documentation

8.747.2.1 uint8_t* pack_pds_SLQSSetPositionMethodState_t::pWifiState

8.747.2.2 uint8_t* pack_pds_SLQSSetPositionMethodState_t::pXtraDataState

8.747.2.3 uint8_t* pack_pds_SLQSSetPositionMethodState_t::pXtraTimeState

8.748 pack_pds_StartPDSTrackingSessionExt_t Struct Reference

Data Fields

- uint8_t sessionControl
- uint8_t sessionType
- uint8_t sessionOperation
- uint8_t sessionServerOption
- uint8_t fixTimeout
- uint32_t fixInterval
- uint32_t fixCount
- uint32_t fixAccuracy

8.748.1 Detailed Description

Structure contain the parameter for PDS tracking session.

Parameters

sessionControl	• Control method: – 0x0 - Manual
sessionType	• Type: – 0x0 - New
session-Operation	• Operating mode: – 0x00 - Standalone – 0x01 - MS-based
sessionServer-Option	• Location server option: – 0x0 - Default
fixTimeout	• Maximum time to work on each fix (in seconds, max 255)
fixCount	• Count of position fix requests for this session (must be at least 1)
fixInterval	• interval between position fix requests (in seconds)
fixAccuracy	• Preferred accuracy threshold(in meters)

8.748.2 Field Documentation

8.748.2.1 uint32_t pack_pds_StartPDSTrackingSessionExt_t::fixAccuracy

8.748.2.2 uint32_t pack_pds_StartPDSTrackingSessionExt_t::fixCount

8.748.2.3 uint32_t pack_pds_StartPDSTrackingSessionExt_t::fixInterval

8.748.2.4 uint8_t pack_pds_StartPDSTrackingSessionExt_t::fixTimeout

8.748.2.5 uint8_t pack_pds_StartPDSTrackingSessionExt_t::sessionControl

8.748.2.6 uint8_t pack_pds_StartPDSTrackingSessionExt_t::sessionOperation

8.748.2.7 uint8_t pack_pds_StartPDSTrackingSessionExt_t::sessionServerOption

8.748.2.8 uint8_t pack_pds_StartPDSTrackingSessionExt_t::sessionType

8.749 pack_qmi_t Struct Reference

Data Fields

- uint16_t xid
- int timeout
- uint16_t msgid
- uint8_t svc

8.749.1 Detailed Description

qmi request context

Parameters

in	*xid*	transaction id
out	*timeout*	timeout recommended in seconds
out	*msgid*	message id
out	*svc*	qmi service

8.749.2 Field Documentation

8.749.2.1 uint16_t pack_qmi_t::msgid

8.749.2.2 uint8_t pack_qmi_t::svc

8.749.2.3 int pack_qmi_t::timeout

8.749.2.4 uint16_t pack_qmi_t::xid

8.750 pack_qos_BindDataPort_t Struct Reference

Data Fields

- qos_BindDataPortPeripheralEndPointID_t * pPeripheralEndPointID
- qos_BindDataPortMuxID_t * pMuxID
- qos_BindDataPortSIODataPort_t * pSIODataPort

8.750.1 Detailed Description

Structure that contains the request Binds a control point to a data port.

Parameters

pPeripheralEndPointID	• See qos_BindDataPortPeripheralEndPointID_t for more information.
pMuxID	• See qos_BindDataPortMuxID_t for more information.
pSIODataPort	• See qos_BindDataPortSIODataPort_t for more information.

8.750.2 Field Documentation

8.750.2.1 qos_BindDataPortMuxID_t* pack_qos_BindDataPort_t::pMuxID

8.750.2.2 qos_BindDataPortPeripheralEndPointID_t* pack_qos_BindDataPort_t::pPeripheralEndPointID

8.750.2.3 qos_BindDataPortSIODataPort_t* pack_qos_BindDataPort_t::pSIODataPort

8.751 pack_qos_SLQSQosSwiReadApnExtraParams_t Struct Reference

Data Fields

- uint32_t apnId

8.751.1 Detailed Description

Structure that contains the APN ID to obtain extra APN parameters

Parameters

apnId[IN]	• APN id

8.751.2 Field Documentation

8.751.2.1 uint32_t pack_qos_SLQSQosSwiReadApnExtraParams_t::apnId

8.752 pack_qos_SLQSQosSwiReadDataStats_t Struct Reference

Data Fields

- uint32_t apnId

8.752.1 Detailed Description

Structure that contains the APN ID to obtain data statistics

Parameters

apnId[IN]	• APN id

8.752.2 Field Documentation

8.752.2.1 uint32_t pack_qos_SLQSQosSwiReadDataStats_t::apnId

8.753 pack_qos_SLQSSetQosEventCallback_t Struct Reference

Data Fields

- uint8_t enable

8.753.1 Detailed Description

Structure that contains the APN ID to obtain data statistics

Parameters

in	*enable*	• 1 - Enable QoS event reporting • 0 - Disable QoS event reporting

8.753.2 Field Documentation

8.753.2.1 uint8_t pack_qos_SLQSSetQosEventCallback_t::enable

8.754 pack_rms_SetSMSWake_t Struct Reference

Data Fields

- uint32_t enabled
- uint32_t wake_mask

8.754.1 Detailed Description

Pack set SMS wake parameters

Parameters

enabled	• SMS wake functionality enabled – 0 - Disabled – 1 - Enabled
wake_mask	• SMS wake mask to search for incoming messages (only relevant when enabled)

8.754.2 Field Documentation

8.754.2.1 uint32_t pack_rms_SetSMSWake_t::enabled

8.754.2.2 uint32_t pack_rms_SetSMSWake_t::wake_mask

8.755 pack_sar_SLQSSetRfSarState_t Struct Reference

Data Fields

- uint32_t RfSarState

8.755.1 Detailed Description

This sturcture contain sets the specified RF SAR state parameter.

Parameters

RfSarState	• SAR RF State – QMI_SAR_RF_STATE_DEFAULT – QMI_SAR_RF_STATE_1 – QMI_SAR_RF_STATE_2 – QMI_SAR_RF_STATE_3 – QMI_SAR_RF_STATE_4 – QMI_SAR_RF_STATE_5 – QMI_SAR_RF_STATE_6 – QMI_SAR_RF_STATE_7 – QMI_SAR_RF_STATE_8

8.755.2 Field Documentation

8.755.2.1 uint32_t pack_sar_SLQSSetRfSarState_t::RfSarState

8.756 pack_sms_SaveSMS_t Struct Reference

Data Fields

- uint32_t storageType
- uint32_t messageFormat
- uint32_t messageSize
- uint8_t ∗ pMessage

8.756.1 Detailed Description

Sutructure containing parameters to Save an SMS message to device memory

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
messageFormat	• Message format – 0 - CDMA (IS-637B) – 1 - 5 (Reserved) – 6 - GSM/WCDMA PP
messageSize	• The length of the message contents in bytes

pMessage	• The message contents

8.756.2 Field Documentation

8.756.2.1 uint32_t pack_sms_SaveSMS_t::messageFormat

8.756.2.2 uint32_t pack_sms_SaveSMS_t::messageSize

8.756.2.3 uint8_t∗ pack_sms_SaveSMS_t::pMessage

8.756.2.4 uint32_t pack_sms_SaveSMS_t::storageType

8.757 pack_sms_SendSMS_t Struct Reference

Data Fields

- uint32_t messageFormat
- uint32_t messageSize
- uint8_t ∗ pMessage
- uint8_t ∗ pLinktimer

8.757.1 Detailed Description

This structure contains pack send SMS parameters.

Parameters

messageFormat	• Message format – 0 - CDMA (IS-637B) – 1 - 5 (Reserved) – 6 - GSM/WCDMA PP
messageSize	• The length of the message contents in bytes
pLinktimer	• GW SMS link open for the specified number of second
pMessage	• The message contents in PDU format contains SMS header and payload message

8.757.2 Field Documentation

8.757.2.1 uint32_t pack_sms_SendSMS_t::messageFormat

8.757.2.2 uint32_t pack_sms_SendSMS_t::messageSize

8.757.2.3 uint8_t* pack_sms_SendSMS_t::pLinktimer

8.757.2.4 uint8_t* pack_sms_SendSMS_t::pMessage

8.758 pack_sms_SetNewSMSCallback_t Struct Reference

Data Fields

- enum eqmiCbkSetStatus status

8.758.1 Detailed Description

This strucure contains pack set new SMS callback parameters.

Parameters

status	callback parameter

8.758.2 Field Documentation

8.758.2.1 enum eqmiCbkSetStatus pack_sms_SetNewSMSCallback_t::status

8.759 pack_sms_SetSMSCAddress_t Struct Reference

Data Fields

- uint8_t * pSMSCAddress
- uint8_t * pSMSCType

8.759.1 Detailed Description

Structure to Set the SMS center address.

Parameters

SMSCAddress	• The SMS center address represented as a NULL terminated string
SMSCType	• The SMS center address type represented as a NULL terminated string (optional).

8.759.2 Field Documentation

8.759.2.1 uint8_t* pack_sms_SetSMSCAddress_t::pSMSCAddress

8.759.2.2 uint8_t* pack_sms_SetSMSCAddress_t::pSMSCType

8.760 pack_sms_SLQSDeleteSMS_t Struct Reference

Data Fields

- uint32_t storageType
- uint32_t * pMessageIndex
- uint32_t * pMessageTag
- uint8_t * pMessageMode

8.760.1 Detailed Description

This structure contains pack delete SMS parameters.

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
pMessageIndex	• (Optional) message index
pMessageTag	• (Optional) message tag – 0 - Read – 1 - Not read – 2 - Mobile originated and sent – 3 - Mobile originated but not yet sent
pMessageMode	• (Optional) message mode • this must be included if the device is capable of supporting more than one protocol • e.g. CDMA and GW – 0x00 - CDMA, LTE (if network type is CDMA) – 0x01 - GW, LTE (if network type is UMTS)

8.760.2 Field Documentation

8.760.2.1 uint32_t* pack_sms_SLQSDeleteSMS_t::pMessageIndex

8.760.2.2 uint8_t* pack_sms_SLQSDeleteSMS_t::pMessageMode

8.760.2.3 uint32_t* pack_sms_SLQSDeleteSMS_t::pMessageTag

8.760.2.4 uint32_t pack_sms_SLQSDeleteSMS_t::storageType

8.761 pack_sms_SLQSGetSMS_t Struct Reference

Data Fields

- uint32_t storageType
- uint32_t messageIndex
- uint8_t * pMessageMode

8.761.1 Detailed Description

This sturcture contains pack get SMS parameters.

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
messageIndex	• Message index
pMessageMode	• 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)

8.761.2 Field Documentation

8.761.2.1 uint32_t pack_sms_SLQSGetSMS_t::messageIndex

8.761.2.2 uint8_t∗ pack_sms_SLQSGetSMS_t::pMessageMode

8.761.2.3 uint32_t pack_sms_SLQSGetSMS_t::storageType

8.762 pack_sms_SLQSGetSmsBroadcastConfig_t Struct Reference

Data Fields

- uint8_t mode

8.762.1 Detailed Description

This structure contains get SMS boardcast configure parameter.

Parameters

mode	• Mode – 0x00 - CDMA, LTE (if network type is CDMA) – 0x01 - GW, LTE (if network type is UMTS)

8.762.2 Field Documentation

8.762.2.1 uint8_t pack_sms_SLQSGetSmsBroadcastConfig_t::mode

8.763 pack_sms_SLQSGetSMSList_t Struct Reference

Data Fields

- uint32_t storageType
- uint32_t * pRequestedTag
- uint8_t * pMessageMode

8.763.1 Detailed Description

This structure contains pack get SMS list parameters.

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
requestedTag	• (Optional) Message tag – 0 - Read – 1 - Not read – 2 - Mobile originated and sent – 3 - Mobile originated but not yet sent
messageMode	• 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)

8.763.2 Field Documentation

8.763.2.1 uint8_t* pack_sms_SLQSGetSMSList_t::pMessageMode

8.763.2.2 uint32_t* pack_sms_SLQSGetSMSList_t::pRequestedTag

8.763.2.3 uint32_t pack_sms_SLQSGetSMSList_t::storageType

8.764 pack_sms_SLQSModifySMSStatus_t Struct Reference

Data Fields

- uint32_t storageType
- uint32_t messageIndex
- uint32_t messageTag
- uint8_t * pMessageMode

8.764.1 Detailed Description

This structure contains pack modify SMS status parameters.

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
messageIndex	• Message index
messageTag	• Message tag – 0 - Read – 1 - Not read
pMessageMode	• 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)

8.764.2 Field Documentation

8.764.2.1 uint32_t pack_sms_SLQSModifySMSStatus_t::messageIndex

8.764.2.2 uint32_t pack_sms_SLQSModifySMSStatus_t::messageTag

8.764.2.3 uint8_t* pack_sms_SLQSModifySMSStatus_t::pMessageMode

8.764.2.4 uint32_t pack_sms_SLQSModifySMSStatus_t::storageType

8.765 pack_sms_SLQSSendAsyncSMS_t Struct Reference

Data Fields

- sms_sendAsyncsmsParams * pSendSmsParams

8.765.1 Detailed Description

Structure contain Parameter to Send an SMS message for immediate over-the-air transmission

Parameters

pSendSms-Params	• structure containing the SMS parameters. Refer sms_sendasyncsmsparams

8.765.2 Field Documentation

8.765.2.1 sms_sendAsyncsmsParams* pack_sms_SLQSSendAsyncSMS_t::pSendSmsParams

8.766 pack_sms_SLQSSetIndicationRegister_t Struct Reference

Data Fields

- sms_setIndicationReg * pSetIndicationRegReq

8.766.1 Detailed Description

Structure contain Parameter that sets the registration state of different WMS indications.

Parameters

pSetIndication-Reg	• Pointer to structure of indicationRegReqParams – See sms_setIndicationReg for more information

8.766.2 Field Documentation

8.766.2.1 sms_setIndicationReg* pack_sms_SLQSSetIndicationRegister_t::pSetIndicationRegReq

8.767 pack_sms_SLQSSetSmsBroadcastActivation_t Struct Reference

Data Fields

- uint8_t mode
- uint8_t broadcastActivate

8.767.1 Detailed Description

Structure contain parameters that Enables or disables the reception of broadcast SMS messages.

Parameters

Mode	• Mode • 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)
broadcast-Activate	• 0x00 - Disable broadcast • 0x01 - Activate broadcast

8.767.2 Field Documentation

8.767.2.1 uint8_t pack_sms_SLQSSetSmsBroadcastActivation_t::broadcastActivate

8.767.2.2 uint8_t pack_sms_SLQSSetSmsBroadcastActivation_t::mode

8.768 pack_sms_SLQSSetSmsBroadcastConfig_t Struct Reference

Data Fields

- uint8_t mode
- sms_qaQmi3GPPBroadcastCfgInfo * pBroadcastConfig
- sms_qaQmi3GPP2BroadcastCfgInfo * pCDMABroadcastConfig

8.768.1 Detailed Description

Structure containing parameters that provides the information about the SMS BroadcastConfiguration

Parameters

mode	• Mode – 0x00 - CDMA, LTE (if network type is CDMA) – 0x01 - GW, LTE (if network type is UMTS)
pBroadcast-Config	• The data for 3GPP Broadcast Information(Optional).
pCDMA-BroadcastConfig	• The data for 3GPP2 Broadcast Information(Optional).

8.768.2 Field Documentation

8.768.2.1 uint8_t pack_sms_SLQSSetSmsBroadcastConfig_t::mode

8.768.2.2 sms_qaQmi3GPPBroadcastCfgInfo* pack_sms_SLQSSetSmsBroadcastConfig_t::pBroadcastConfig

8.768.2.3 sms_qaQmi3GPP2BroadcastCfgInfo* pack_sms_SLQSSetSmsBroadcastConfig_t::pCDMABroadcastConfig

8.769 pack_sms_SLQSSetSmsStorage_t Struct Reference

Data Fields

- uint8_t smsStorage

8.769.1 Detailed Description

Structure contain Parameter to set the SMS Storage on the device

Parameters

smsStorage	• SMS Storage – 0x01 - device's permanent memory – 0x02 - UICC

8.769.2 Field Documentation

8.769.2.1 uint8_t pack_sms_SLQSSetSmsStorage_t::smsStorage

8.770 pack_sms_SLQSSmsGetMaxStorageSize_t Struct Reference

Data Fields

- sms_maxStorageSizeReq * pMaxStorageSizeReq

8.770.1 Detailed Description

This structure contains get maximum storage size.

Parameters

pMaxStorage-SizeReq	• Request parameters for SmsSLQSGetMaxStorageSize – See sms_maxStorageSizeReq for more information

8.770.2 Field Documentation

8.770.2.1 sms_maxStorageSizeReq* pack_sms_SLQSSmsGetMaxStorageSize_t::pMaxStorageSizeReq

8.771 pack_sms_SLQSSmsSetRoutes_t Struct Reference

Data Fields

- sms_setRoutesReq * pSetRoutesReq

8.771.1 Detailed Description

Structure contain parameter that Sets the action performed on SMS message receipt for specified message routes. It also specifies the action performed on SMS receipt of status reports.

Parameters

pSetRoutesReq	• Pointer to structure of smsSetRoutesReq – See sms_setRoutesReq for more information

8.771.2 Field Documentation

8.771.2.1 sms_setRoutesReq* pack_sms_SLQSSmsSetRoutes_t::pSetRoutesReq

8.772 pack_swidms_SLQSSwiDmsSetHWWatchdog_t Struct Reference

Data Fields

- uint32_t timeout
- uint32_t resetDelay
- uint8_t enable

8.772.1 Detailed Description

This structure contains the set hardware watchdong settings request parameter.

Parameters

timeout	• timeout value for HW watchdog (unit in second)
resetDelay	• delay before reset after watchdog timeout (unit in second)
enable	• 0 to disable watchdog; 1 to enable watchdog

8.772.2 Field Documentation

8.772.2.1 uint8_t pack_swidms_SLQSSwiDmsSetHWWatchdog_t::enable

8.772.2.2 uint32_t pack_swidms_SLQSSwiDmsSetHWWatchdog_t::resetDelay

8.772.2.3 uint32_t pack_swidms_SLQSSwiDmsSetHWWatchdog_t::timeout

8.773 pack_swidms_SLQSSwiDmsSetMTU_t Struct Reference

Data Fields

- uint16_t MTUSize

8.773.1 Detailed Description

This structure contains the Set MTU request parameter.

Parameters

MTUSize	• Set MTU size • MTU Values – 0 - use default value – 576 to 2000 - other values required by carrier. – Set the same MTU for all RAT/interfaces. – New MTU size effective after modem reboot.

8.773.2 Field Documentation

8.773.2.1 uint16_t pack_swidms_SLQSSwiDmsSetMTU_t::MTUSize

8.774 pack_swidms_SLQSSwiDmsSetUsbComp_t Struct Reference

Data Fields

- uint32_t CfgValue

8.774.1 Detailed Description

This structure contains the Set Usb Interface Config request parameter.

Parameters

CfgValue	• Host composition bit mask, see supported USB interface bitmasks, not supported by QMI object setting for 9x50 modules – 0x00000001 - DIAG interface – 0x00000002 - ADB interface – 0x00000004 - NMEA interface – 0x00000008 - MODEM interface – 0x00000010 - RESERVED5 – 0x00000020 - RESERVED6 – 0x00000040 - RESERVED7 – 0x00000080 - RESERVED8 – 0x00000100 - RMENT0 interface – 0x00000200 - RESERVED10 – 0x00000400 - RMENT1 interface – 0x00000800 - RESERVED12 – 0x00001000 - MBIM interface – 0x00002000 - RESERVED14 – 0x00004000 - RNDIS interface – 0x00008000 - RESERVED16 – 0x00010000 - AUDIO interface – 0x00020000 - RESERVED18 – 0x00080000 - ECM interface – 0x00100000 - RESERVED21 – 0x00200000 - RESERVED22 – 0xFFC00000 - RESERVED

8.774.2 Field Documentation

8.774.2.1 uint32_t pack_swidms_SLQSSwiDmsSetUsbComp_t::CfgValue

8.775 pack_swidms_SLQSSwiDmsSetUsbNetNum_t Struct Reference

Data Fields

- uint8_t nUsbNetNum

8.775.1 Detailed Description

This structure contains usb net number to set on remote endpoint for QMAP configuration

Parameters

nUsbNetNum	• value of usb net numbers to set for the device • range is 0-8

8.775.2 Field Documentation

8.775.2.1 uint8_t pack_swidms_SLQSSwiDmsSetUsbNetNum_t::nUsbNetNum

8.776 pack_swiloc_SwiLocSetAutoStart_t Struct Reference

Data Fields

- uint8_t function
- int set_function
- uint8_t fix_type
- int set_fix_type
- uint8_t max_time
- int set_max_time
- uint32_t max_dist
- int set_max_dist
- uint32_t fix_rate
- int set_fix_rate

8.776.1 Detailed Description

This structure contains SWI LOC Get Auto Start setting

Parameters

function	• Setting to indicate when modem should start an automatic GNSS fix – 0 - disabled – 1 - At bootup – 2 - When NMEA port is opened
set_function	• 0 - do not set to modem • I - set to modem
fix_type	• Type of GNSS fix: – 1 - Default Engine mode – 2 - MS-Based – 3 - MS-Assisted – 4 - Standalone
set_fix_type	• 0 - do not set to modem • I - set to modem

max_time	• Maximum time allowed for the receiver to get a fix in seconds • Valid range: 1-255
set_max_time	• 0 - do not set to modem • I - set to modem
max_dist	• Maximum uncertainty of a fix measured by distance in meters • Valid range: 1 - 4294967280
set_max_dist	• 0 - do not set to modem • I - set to modem
fix_rate	• Time between fixes in seconds • Valid range: 1–65535
set_fix_rate	• 0 - do not set to modem • I - set to modem

8.776.2 Field Documentation

8.776.2.1 uint32_t pack_swiloc_SwiLocSetAutoStart_t::fix_rate

8.776.2.2 uint8_t pack_swiloc_SwiLocSetAutoStart_t::fix_type

8.776.2.3 uint8_t pack_swiloc_SwiLocSetAutoStart_t::function

8.776.2.4 uint32_t pack_swiloc_SwiLocSetAutoStart_t::max_dist

8.776.2.5 uint8_t pack_swiloc_SwiLocSetAutoStart_t::max_time

8.776.2.6 int pack_swiloc_SwiLocSetAutoStart_t::set_fix_rate

8.776.2.7 int pack_swiloc_SwiLocSetAutoStart_t::set_fix_type

8.776.2.8 int pack_swiloc_SwiLocSetAutoStart_t::set_function

8.776.2.9 int pack_swiloc_SwiLocSetAutoStart_t::set_max_dist

8.776.2.10 int pack_swiloc_SwiLocSetAutoStart_t::set_max_time

8.777 pack_swioma_SLQSOMADMCancelSession_t Struct Reference

Data Fields

- uint32_t sessionType

8.777.1 Detailed Description

Structure that contains the session type for OMA cancel session command

Parameters

sessionType	[in] • Session type – 0x01 - FOTA, to check availability of FW Update – 0xFF - Cancel any active OMADM session

8.777.2 Field Documentation

8.777.2.1 uint32_t pack_swioma_SLQSOMADMCancelSession_t::sessionType

8.778 pack_swioma_SLQSOMADMGetSessionInfo_t Struct Reference

Data Fields

- uint32_t SessionType

8.778.1 Detailed Description

Structure that contains the session type for OMA get session info command

Parameters

SessionType	[in] • Session type – 0x01 - FOTA – 0xFF - Any active OMADM session. If no active sessions are available, then previous OMADM session info is returned

8.778.2 Field Documentation

8.778.2.1 uint32_t pack_swioma_SLQSOMADMGetSessionInfo_t::SessionType

8.779 pack_swioma_SLQSOMADMSendSelection_t Struct Reference

Data Fields

- uint32_t selection
- uint32_t * pDeferTime
- uint32_t * pRejectReason

8.779.1 Detailed Description

Structure containing the OMA DM selection

Parameters

selection	[in] • OMA-DM NIA Selection – 0x01 - Accept – 0x02 - Reject – 0x03 - Defer
pDeferTime	[in] • Defer time in minutes. A value of 0 will cause the prompt to be resent immediately. • This TLV is mandatory if selection is set to 0x03.
pRejectReason	[in] • Reject Reason • This TLV is processed if selection is set to 0x02. If it is not present, the reject reason 0 is used as default.

8.779.2 Field Documentation

8.779.2.1 uint32_t* pack_swioma_SLQSOMADMSendSelection_t::pDeferTime

8.779.2.2 uint32_t* pack_swioma_SLQSOMADMSendSelection_t::pRejectReason

8.779.2.3 uint32_t pack_swioma_SLQSOMADMSendSelection_t::selection

8.780 pack_swioma_SLQSOMADMSetSettings_t Struct Reference

Data Fields

- uint8_t FOTAdownload
- uint8_t FOTAUpdate
- uint8_t * pAutosdm
- uint8_t * pFwAutoCheck

8.780.1 Detailed Description

Structure containing the OMA DM settings to be set on the device This maps to structure SLQSOMADMSettings-ReqParams3

Parameters

FOTAdownload	• 1 Byte parameter indicating support for FOTA Automatic download – 0x00 - Firmware autodownload FALSE – 0x01 - Firmware autodownload TRUE
FOTAUpdate	• 1 byte parameter indicating FOTA Automatic update – 0x00 - Firmware autoupdate FALSE – 0x01 - Firmware autoupdate TRUE

pAutosdm	• Optional 1 byte parameter indicating OMA Automatic UI Alert Response – 0x00 - Disabled – 0x01 - Enabled Accept – 0x02 - Enabled Reject
pFwAutoCheck	• Optional 1 byte parameter indicating OMA Automatic Check for Firmware Update on Power-Up Response – 0x00 - Disabled – 0x01 - Enabled

8.780.2 Field Documentation

8.780.2.1 uint8_t pack_swioma_SLQSOMADMSetSettings_t::FOTAdownload

8.780.2.2 uint8_t pack_swioma_SLQSOMADMSetSettings_t::FOTAUpdate

8.780.2.3 uint8_t* pack_swioma_SLQSOMADMSetSettings_t::pAutosdm

8.780.2.4 uint8_t* pack_swioma_SLQSOMADMSetSettings_t::pFwAutoCheck

8.781 pack_swioma_SLQSOMADMStartSession_t Struct Reference

Data Fields

- uint32_t sessionType

8.781.1 Detailed Description

Structure that contains the session type for OMA start session command

Parameters

sessionType[IN]	• Session type – 0x01 - FOTA, to check availability of FW Update – 0x02 - DM, to check availability of DM Update – 0x03 - PRL, to check availability of PRL Update

8.781.2 Field Documentation

8.781.2.1 uint32_t pack_swioma_SLQSOMADMStartSession_t::sessionType

8.782 pack_uim_ChangePin_t Struct Reference

Data Fields

- uim_encryptedPIN1 EncryptedPIN1

- uint32_t * pIndicationToken
- uint8_t * pKeyReferenceID
- uim_sessionInformation sessionInfo
- uim_changeUIMPIN changePIN
- uint16_t TlvResult

8.782.1 Detailed Description

This structure contains information of the request parameters associated with a Change PIN API.

Parameters

sessionInfo	• See uim_sessionInformation for more information.
changePIN	• See uim_changeUIMPIN for more information.
pKeyReferenceID(optional)	• Indicates the PIN key reference ID. • Indicates the PIN key reference ID. Valid values are from 1 to 8, respectively, for application 1 to application 8. • This TLV is used only for PIN1 and PIN2 and is ignored in all other cases.
pIndicationToken(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication. • Valid Values – 0 - Result of operation in response. Indication will not be generated by the modem – Any other positive number - Result of operation in indication. Indication will have same token value set by this function

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.782.2 Field Documentation

8.782.2.1 uim_changeUIMPIN pack_uim_ChangePin_t::changePIN

8.782.2.2 uim_encryptedPIN1 pack_uim_ChangePin_t::EncryptedPIN1

8.782.2.3 uint32_t* pack_uim_ChangePin_t::pIndicationToken

8.782.2.4 uint8_t* pack_uim_ChangePin_t::pKeyReferenceID

8.782.2.5 uim_sessionInformation pack_uim_ChangePin_t::sessionInfo

8.782.2.6 uint16_t pack_uim_ChangePin_t::TlvResult

8.783 pack_uim_ReadTransparent_t Struct Reference

Data Fields

- uim_sessionInformation sessionInfo
- uim_fileInfo fileIndex
- uim_readTransparentInfo readTransparent
- uint32_t * pIndicationToken
- uint8_t * pEncryptData
- uint16_t Tlvresult

8.783.1 Detailed Description

This structure contains information of the request parameters associated with a Read Transparent API.

Parameters

sessionInfo	• See uim_sessionInformation for more information.
fileIndex	• See uim_fileInfo for more information.
readTransparent	• See uim_readTransparentInfo for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication. • Valid Values – 0 - Result of operation in response. Indication will not be generated by the modem – Any other positive number - Result of operation in indication. Indication will have same token value set by this function
pEncrypt-Data(optional)	• Encrypt Data. • Indicates whether the data read from the card is to be encrypted.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.783.2 Field Documentation

8.783.2.1 uim_fileInfo pack_uim_ReadTransparent_t::fileIndex

8.783.2.2 uint8_t* pack_uim_ReadTransparent_t::pEncryptData

8.783.2.3 uint32_t* pack_uim_ReadTransparent_t::pIndicationToken

8.783.2.4 uim_readTransparentInfo pack_uim_ReadTransparent_t::readTransparent

8.783.2.5 uim_sessionInformation pack_uim_ReadTransparent_t::sessionInfo

8.783.2.6 uint16_t pack_uim_ReadTransparent_t::Tlvresult

8.784 pack_uim_SetPinProtection_t Struct Reference

Data Fields

- uim_encryptedPIN1 EncryptedPIN1
- uint32_t * pIndicationToken
- uint8_t * pKeyReferenceID
- uim_sessionInformation sessionInfo
- uim_setPINProtection pinProtection
- uint16_t Tlvresult

8.784.1 Detailed Description

This structure contains information of the request parameters associated with a set pin protection API.

Parameters

sessionInfo	• See uim_sessionInformation for more information.
pinProtection	• See uim_setPINProtection for more information.
pKeyReferenceID(optional)	• Indicates the PIN key reference ID. • Indicates the PIN key reference ID. Valid values are from 1 to 8, respectively, for application 1 to application 8. • This TLV is used only for PIN1 and PIN2 and is ignored in all other cases.
pIndicationToken(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication. • Valid Values – 0 - Result of operation in response. Indication will not be generated by the modem – Any other positive number - Result of operation in indication. Indication will have same token value set by this function

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.784.2 Field Documentation

8.784.2.1 uim_encryptedPIN1 pack_uim_SetPinProtection_t::EncryptedPIN1

8.784.2.2 uint32_t* pack_uim_SetPinProtection_t::pIndicationToken

8.784.2.3 uim_setPINProtection pack_uim_SetPinProtection_t::pinProtection

8.784.2.4 uint8_t* pack_uim_SetPinProtection_t::pKeyReferenceID

8.784.2.5 uim_sessionInformation pack_uim_SetPinProtection_t::sessionInfo

8.784.2.6 uint16_t pack_uim_SetPinProtection_t::TIvresult

8.785 pack_uim_SLQSUIMAuthenticate_t Struct Reference

Data Fields

- uim_sessionInformation sessionInfo
- uim_authenticationData authData
- uint32_t * pIndicationToken

8.785.1 Detailed Description

This structure contains information of the request parameters associated with a SLQSUIMAuthenticate.

Parameters

sessionInfo	• See uim_sessionInformation for more information.
authData	• See uim_authenticationData for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.785.2 Field Documentation

8.785.2.1 uim_authenticationData pack_uim_SLQSUIMAuthenticate_t::authData

8.785.2.2 uint32_t* pack_uim_SLQSUIMAuthenticate_t::pIndicationToken

8.785.2.3 uim_sessionInformation pack_uim_SLQSUIMAuthenticate_t::sessionInfo

8.786 pack_uim_SLQSUIMDepersonalization_t Struct Reference

Data Fields

- uim_depersonalizationInformation depersonilisationInfo

8.786.1 Detailed Description

This structure contains information of the request parameters associated with a Depersonalization.

Parameters

depersonilisation-Info	• See uim_depersonalizationInformation for more information.

8.786.2 Field Documentation

8.786.2.1 uim_depersonalizationInformation pack_uim_SLQSUIMDepersonalization_t::depersonilisationInfo

8.787 pack_uim_SLQSUIMEventRegister_t Struct Reference

Data Fields

- uint32_t eventMask

8.787.1 Detailed Description

This structure contains pack event register parameter.

Parameters

eventMask	- bit 1 - card status • bit 4 - physical slot status

8.787.2 Field Documentation

8.787.2.1 uint32_t pack_uim_SLQSUIMEventRegister_t::eventMask

8.788 pack_uim_SLQSUIMGetConfiguration_t Struct Reference

Data Fields

- uint32_t * pConfigurationMask

8.788.1 Detailed Description

This structure contains information of the request parameters associated with Get Configuration to get the modem configuration for the UIM module

Parameters

pConfiguration-Mask(optional)	• Requested configurations – Bit 0 - Automatic selection – Bit 1 - Personalization status – Bit 2 - Halt subscription – All other bits are reserved for future use

Note

- if the TLV is missing, the service returns all configuration items in the response.

8.788.2 Field Documentation

8.788.2.1 uint32_t* pack_uim_SLQSUIMGetConfiguration_t::pConfigurationMask

8.789 pack_uim_SLQSUIMGetFileAttributes_t Struct Reference

Data Fields

- uim_sessionInformation sessionInfo
- uim_fileInfo fileIndex
- uint32_t * pIndicationToken

8.789.1 Detailed Description

This structure contains information of the request parameters associated with a Get File Attributes

Parameters

sessionInfo	• See uim_sessionInformation for more information.
fileIndex	• See uim_fileInfo for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.789.2 Field Documentation

8.789.2.1 uim_fileInfo pack_uim_SLQSUIMGetFileAttributes_t::fileIndex

8.789.2.2 uint32_t* pack_uim_SLQSUIMGetFileAttributes_t::pIndicationToken

8.789.2.3 uim_sessionInformation pack_uim_SLQSUIMGetFileAttributes_t::sessionInfo

8.790 pack_uim_SLQSUIMPowerDown_t Struct Reference

Data Fields

- uint8_t slot

8.790.1 Detailed Description

This structure contains information of the request parameters associated with a Power Down.

Parameters

slot	• Indicates the slot to be used. – 1 - Slot 1 – 2 - Slot 2

8.790.2 Field Documentation

8.790.2.1 uint8_t pack_uim_SLQSUIMPowerDown_t::slot

8.791 pack_uim_SLQSUIMPowerUp_t Struct Reference

Data Fields

- uint8_t slot
- uint8_t * pIgnoreHotSwapSwitch

8.791.1 Detailed Description

This structure contains information of the request parameters associated with a Power Down.

Parameters

slot	• Indicates the slot to be used. – 1 - Slot 1 – 2 - Slot 2
pIgnoreHot-Swap-Switch(optional)	• Hot-swap switch status. – 0 - Checks the hot-swap switch status – 1 - Ignores the hot-swap switch status

8.791.2 Field Documentation

8.791.2.1 uint8_t* pack_uim_SLQSUIMPowerUp_t::pIgnoreHotSwapSwitch

8.791.2.2 uint8_t pack_uim_SLQSUIMPowerUp_t::slot

8.792 pack_uim_SLQSUIMRefreshComplete_t Struct Reference

Data Fields

- uim_sessionInformation sessionInfo
- uint8_t refreshComplete

8.792.1 Detailed Description

This structure contains information of the request parameters associated with a Refresh Complete event.

Parameters

sessionInfo(-Mandatory)	• See uim_sessionInformation for more information.

refresh-Complete(-Mandatory)	• Indicates whether the refresh was successful. Valid values: – 0 - Refresh was not completed successfully – 1 - Refresh was completed successfully

8.792.2 Field Documentation

8.792.2.1 uint8_t pack_uim_SLQSUIMRefreshComplete_t::refreshComplete

8.792.2.2 uim_sessionInformation pack_uim_SLQSUIMRefreshComplete_t::sessionInfo

8.793 pack_uim_SLQSUIMRefreshGetLastEvent_t Struct Reference

Data Fields

- uim_sessionInformation sessionInfo

8.793.1 Detailed Description

This structure contains information of the request parameters associated with a Refresh Get Last Event.

Parameters

sessionInfo(-Mandatory)	• See uim_sessionInformation for more information.

8.793.2 Field Documentation

8.793.2.1 uim_sessionInformation pack_uim_SLQSUIMRefreshGetLastEvent_t::sessionInfo

8.794 pack_uim_SLQSUIMRefreshOK_t Struct Reference

Data Fields

- uim_sessionInformation sessionInfo
- uint8_t OKtoRefresh

8.794.1 Detailed Description

This structure contains Parameters of the Session Information

Parameters

sessionInfo	• Session Information • See uim_sessionInformation for more information

OKtoRefresh	• Indicates whether a refresh is OK. Valid values: – 0 - Not OK to refresh – 1 - OK to refresh

8.794.2 Field Documentation

8.794.2.1 uint8_t pack_uim_SLQSUIMRefreshOK_t::OKtoRefresh

8.794.2.2 uim_sessionInformation pack_uim_SLQSUIMRefreshOK_t::sessionInfo

8.795 pack_uim_SLQSUIMRefreshRegister_t Struct Reference

Data Fields

- uim_sessionInformation sessionInfo
- uim_registerRefresh regRefresh

8.795.1 Detailed Description

This structure contains information of the request parameters associated with a Refresh Register.

Parameters

sessionInfo	• Session Information params • See uim_sessionInformation for more information
regRefresh	• Register Refresh parameters • See uim_registerRefresh for more information

8.795.2 Field Documentation

8.795.2.1 uim_registerRefresh pack_uim_SLQSUIMRefreshRegister_t::regRefresh

8.795.2.2 uim_sessionInformation pack_uim_SLQSUIMRefreshRegister_t::sessionInfo

8.796 pack_uim_SLQSUIMSwitchSlot_t Struct Reference

Data Fields

- uint8_t bLogicalSlot
- uint32_t ulPhysicalSlot

8.796.1 Detailed Description

This structure contains information of the request parameters associated with a Switch Slot.

Parameters

bLogicalSlot	• Indicates the slot to be used. – 1 - Slot 1 – 2 - Slot 2 – 3 - Slot 3 – 4 - Slot 4 – 5 - Slot 5
ulPhysicalSlot	• 1 - Slot 1 • 2 - Slot 2 • 3 - Slot 3 • 4 - Slot 4 • 5 - Slot 5

8.796.2 Field Documentation

8.796.2.1 uint8_t pack_uim_SLQSUIMSwitchSlot_t::bLogicalSlot

8.796.2.2 uint32_t pack_uim_SLQSUIMSwitchSlot_t::ulPhysicalSlot

8.797 pack_uim_UnblockPin_t Struct Reference

Data Fields

- uim_encryptedPIN1 EncryptedPIN1
- uint32_t * pIndicationToken
- uint8_t * pKeyReferenceID
- uim_sessionInformation sessionInfo
- uim_unblockUIMPIN pinProtection
- uint16_t Tlvresult

8.797.1 Detailed Description

This structure contains information of the request parameters associated with a Unblock PIN API.

Parameters

EncryptedPIN1	• See uim_encryptedPIN1 for more information.
sessionInfo	• See uim_sessionInformation for more information.
pinProtection	• See uim_unblockUIMPIN for more information.

pKeyReferenceID(optional)	• Indicates the PIN key reference ID. • Indicates the PIN key reference ID. Valid values are from 1 to 8, respectively, for application 1 to application 8. • This TLV is used only for PIN1 and PIN2 and is ignored in all other cases.
pIndicationToken(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication. • Valid Values – 0 - Result of operation in response. Indication will not be generated by the modem – Any other positive number - Result of operation in indication. Indication will have same token value set by this function

8.797.2 Field Documentation

8.797.2.1 uim_encryptedPIN1 pack_uim_UnblockPin_t::EncryptedPIN1

8.797.2.2 uint32_t* pack_uim_UnblockPin_t::pIndicationToken

8.797.2.3 uim_unblockUIMPIN pack_uim_UnblockPin_t::pinProtection

8.797.2.4 uint8_t* pack_uim_UnblockPin_t::pKeyReferenceID

8.797.2.5 uim_sessionInformation pack_uim_UnblockPin_t::sessionInfo

8.797.2.6 uint16_t pack_uim_UnblockPin_t::Tlvresult

8.798 pack_uim_VerifyPin_t Struct Reference

Data Fields

- uim_encryptedPIN1 * pEncryptedPIN1
- uint32_t * pIndicationToken
- uint8_t * pKeyReferenceID
- uim_sessionInformation sessionInfo
- uim_verifyUIMPIN verifyPIN
- uint16_t Tlvresult

8.798.1 Detailed Description

This structure contains information of the request parameters associated with a verify PIN API.

Parameters

sessionInfo	• See uim_sessionInformation for more information.
verifyPIN	• See uim_verifyUIMPIN for more information.

pEncryptedPI-N1(optional)	• See uim_encryptedPIN1 for more information.
pKeyReferenceI-D(optional)	• Indicates the PIN key reference ID. • Indicates the PIN key reference ID. Valid values are from 1 to 8, respectively, for application 1 to application 8. • This TLV is used only for PIN1 and PIN2 and is ignored in all other cases.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication. • Valid Values – 0 - Result of operation in response. Indication will not be generated by the modem – Any other positive number - Result of operation in indication. Indication will have same token value set by this function

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.798.2 Field Documentation

8.798.2.1 uim_encryptedPIN1∗ pack_uim_VerifyPin_t::pEncryptedPIN1

8.798.2.2 uint32_t∗ pack_uim_VerifyPin_t::pIndicationToken

8.798.2.3 uint8_t∗ pack_uim_VerifyPin_t::pKeyReferenceID

8.798.2.4 uim_sessionInformation pack_uim_VerifyPin_t::sessionInfo

8.798.2.5 uint16_t pack_uim_VerifyPin_t::Tlvresult

8.798.2.6 uim_verifyUIMPIN pack_uim_VerifyPin_t::verifyPIN

8.799 pack_voice_AnswerUSSD_t Struct Reference

Data Fields

- uint8_t ∗ pInfo

8.799.1 Detailed Description

This structure contains pack anser USSD parameter.

Parameters

pInfo	• USS information • See voice_USSInfo for more details

8.799.2 Field Documentation

8.799.2.1 uint8_t* pack_voice_AnswerUSSD_t::pInfo

8.800 pack_voice_OriginateUSSD_t Struct Reference

Data Fields

- uint8_t * pInfo

8.800.1 Detailed Description

This structure contains pack orginate USSD parameter.

Parameters

pInfo	• USS information • See voice_USSInfo for more details

8.800.2 Field Documentation

8.800.2.1 uint8_t* pack_voice_OriginateUSSD_t::pInfo

8.801 pack_voice_SLQSOriginateUSSD_t Struct Reference

Data Fields

- uint8_t ussDCS
- uint8_t ussLen
- uint8_t ussData [182]

8.801.1 Detailed Description

This structure contains USS Information

Parameters

ussDCS	• 1 - ASCII coding scheme • 2 - 8-BIT coding scheme • 3 - UCS2
ussLen	• Range 1 to 182
ussData	• Data encoded as per the DCS

8.801.2 Field Documentation

8.801.2.1 uint8_t pack_voice_SLQSOriginateUSSD_t::ussData[182]

8.801.2.2 uint8_t pack_voice_SLQSOriginateUSSD_t::ussDCS

8.801.2.3 uint8_t pack_voice_SLQSOriginateUSSD_t::ussLen

8.802 pack_voice_SLQSVoiceALSSelectLine_t Struct Reference

Data Fields

- uint8_t lineValue

8.802.1 Detailed Description

This structure contains ALS Select Line Information Parameters.

Parameters

lineValue	• ALS Line Value. – 0x00 - ALS_LINE1 - Line 1 (default) – 0x01 - ALS_LINE2 - Line 2

8.802.2 Field Documentation

8.802.2.1 uint8_t pack_voice_SLQSVoiceALSSelectLine_t::lineValue

8.803 pack_voice_SLQSVoiceALSSetLineSwitching_t Struct Reference

Data Fields

- uint8_t switchOption

8.803.1 Detailed Description

This structure contains ALS Set Line Switching Information Parameters.

Parameters

switchOption	• Switch Option. – 0x00 - VOICE_LINE_SWITCHING_NOT_ALLOWED - Line switching is not allowed – 0x01 - VOICE_LINE_SWITCHING_ALLOWED - Line switching is allowed

8.803.2 Field Documentation

8.803.2.1 uint8_t pack_voice_SLQSVoiceALSSetLineSwitching_t::switchOption

8.804 pack_voice_SLQSVoiceAnswerCall_t Struct Reference

Data Fields

- uint8_t * pCallId

8.804.1 Detailed Description

Contains the parameters passed for pack voice Answer Call.

Parameters

pCallId	• Unique call identifier for the call that must be answered.

8.804.2 Field Documentation

8.804.2.1 uint8_t* pack_voice_SLQSVoiceAnswerCall_t::pCallId

8.805 pack_voice_SLQSVoiceBindSubscription_t Struct Reference

Data Fields

- uint8_t subsType

8.805.1 Detailed Description

This structure contains Bind Subscription Information Parameters.

Parameters

subsType	• Subscription Type. – 0x00 - VOICE_SUBS_TYPE_PRIMARY - Primary – 0x01 - VOICE_SUBS_TYPE_SECONDARY - Secondary

8.805.2 Field Documentation

8.805.2.1 uint8_t pack_voice_SLQSVoiceBindSubscription_t::subsType

8.806 pack_voice_SLQSVoiceBurstDTMF_t Struct Reference

Data Fields

- voice_burstDTMFInfo BurstDTMFInfo
- voice_DTMFLengths * pBurstDTMFLengths

8.806.1 Detailed Description

This structure contains parameters of burst Dual-Tone Multifrequency (DTMF)

Parameters

BurstDTMFInfo	• Burst DTMF Information – See voice_burstDTMFInfo for more information
pBurstDTMF-Lengths	[optional] • DTMF Lengths – See voice_DTMFLengths for more information • NULL pointer - Invalid data.

8.806.2 Field Documentation

8.806.2.1 voice_burstDTMFInfo pack_voice_SLQSVoiceBurstDTMF_t::BurstDTMFInfo

8.806.2.2 voice_DTMFLengths∗ pack_voice_SLQSVoiceBurstDTMF_t::pBurstDTMFLengths

8.807 pack_voice_SLQSVoiceDialCall_t Struct Reference

Data Fields

- uint8_t callNumber [81]
- uint8_t ∗ pCallType
- uint8_t ∗ pCLIRType
- voice_UUSInfo ∗ pUUSInFo
- voice_CUGInfo ∗ pCUGInfo
- uint8_t ∗ pEmergencyCategory
- voice_calledPartySubAdd ∗ pCallPartySubAdd
- uint8_t ∗ pSvcType

8.807.1 Detailed Description

This structure contains Voice Call Request Parameters

Parameters

callNumber[81]	• Number to be dialed in ASCII string, NULL terminated. • Length Range [1 to 81]
pCall-Type(optional)	• the type of call to be dialed. CALL_TYPE_VOICE is automatically selected if this parameter is not provided. When CALL_TYPE_NON_STD_OTASP is selected, the call is sent as a nonstandard OTASP call regardless of the digit string Call type values are: – 0x00 - CALL_TYPE_VOICE - Voice (automatic selection) – 0x01 - CALL_TYPE_VOICE_FORCED - Avoid modem call classification – 0x08 - CALL_TYPE_NON_STD_OTASP - Nonstandard OTASP∗ – 0x09 - CALL_TYPE_EMERGENCY - Emergency

pCLIR-Type(optional)	• CLIR type values are: – 0x01 - CLIR_SUPPRESSION - Suppression – 0x02 - CLIR_INVOCATION - Invocation
pUUSIn-Fo(optional)	• Pointer to structure of UUSInfo – See voice_UUSInfo for more information
pCUG-Info(optional)	• Pointer to structure of CUGInfo – See voice_CUGInfo for more information
pEmergency-Category(optional)	• Bit mask of emergency number categories. This is only applicable when the call type is set to Emergency. – Bit 0 - VOICE_EMER_CAT_POLICE_BIT - Police – Bit 1 - VOICE_EMER_CAT_AMBULANCE_BIT - Ambulance – Bit 2 - VOICE_EMER_CAT_FIRE_BRIGADE_BIT- Fire brigade – Bit 3 - VOICE_EMER_CAT_MARINE_GUARD_BIT - Marine guard – Bit 4 - VOICE_EMER_CAT_MOUNTAIN_RESCUE_BIT - Mountain rescue – Bit 5 - VOICE_EMER_CAT_MANUAL_ECALL_BIT - Manual emergency call – Bit 6 - VOICE_EMER_CAT_AUTO_ECALL_BIT - Automatic emergency call – Bit 7 - VOICE_EMER_CAT_SPARE_BIT - Spare bit
pCallPartySub-Add(optional)	• Pointer to structure of calledPartySubAdd – See voice_calledPartySubAdd for more information
pSvc-Type(optional)	• Service Type. – 0x01 - VOICE_DIAL_CALL_SRV_TYPE_AUTOMATIC - Automatic – 0x02 - VOICE_DIAL_CALL_SRV_TYPE_GSM - GSM – 0x03 - VOICE_DIAL_CALL_SRV_TYPE_WCDMA - WCDMA – 0x04 - VOICE_DIAL_CALL_SRV_TYPE_CDMA_AUTOMATIC - CDMA automatic – 0x05 - VOICE_DIAL_CALL_SRV_TYPE_GSM_WCDMA - GSM or WCDMA – 0x06 - VOICE_DIAL_CALL_SRV_TYPE_LTE -LTE

8.807.2 Field Documentation

8.807.2.1 uint8_t pack_voice_SLQSVoiceDialCall_t::callNumber[81]

8.807.2.2 voice_calledPartySubAdd* pack_voice_SLQSVoiceDialCall_t::pCallPartySubAdd

8.807.2.3 uint8_t* pack_voice_SLQSVoiceDialCall_t::pCallType

8.807.2.4 uint8_t* pack_voice_SLQSVoiceDialCall_t::pCLIRType

8.807.2.5 voice_CUGInfo* pack_voice_SLQSVoiceDialCall_t::pCUGInfo

8.807.2.6 uint8_t* pack_voice_SLQSVoiceDialCall_t::pEmergencyCategory

8.807.2.7 uint8_t* pack_voice_SLQSVoiceDialCall_t::pSvcType

8.807.2.8 voice_UUSInfo* pack_voice_SLQSVoiceDialCall_t::pUUSInFo

8.808 pack_voice_SLQSVoiceEndCall_t Struct Reference

Data Fields

- uint8_t * pCallId

8.808.1 Detailed Description

This structure contain pack voice end call parameter.

Parameters

pCallId	• Unique call identifier for the call that must be ended

8.808.2 Field Documentation

8.808.2.1 uint8_t* pack_voice_SLQSVoiceEndCall_t::pCallId

8.809 pack_voice_SLQSVoiceGetCallBarring_t Struct Reference

Data Fields

- uint8_t reason
- uint8_t * pSvcClass

8.809.1 Detailed Description

This structure contains Voice Get Call Barring Pack Parameters

Parameters

reason	• Call Barring Reason • Values: – 0x07 - QMI_VOICE_REASON_BARR_ALLOUTGOING - All outgoing – 0x08 - QMI_VOICE_REASON_BARR_OUTGOINGINT - Outgoing internal – 0x09 - QMI_VOICE_REASON_BARR_OUTGOINGINTEXTOHOME - Outgoing external to home – 0x0A - QMI_VOICE_REASON_BARR_ALLINCOMING - All incoming – 0x0B - QMI_VOICE_REASON_BARR_INCOMINGROAMING - Roaming incoming – 0x0C - QMI_VOICE_REASON_BARR_ALLBARRING - All calls are barred – 0x0D - QMI_VOICE_REASON_BARR_ALLOUTGOINGBARRING - All outgoing calls are barred – 0x0E - QMI_VOICE_REASON_BARR_ALLINCOMINGBARRING - All incoming calls are barred
pSvcClass	• Service class is a combination (sum) of information class constants (optional) • See qaGobiApiTableSupServiceInfoClasses.h for service classes. • Service Class is set to 0 if call waiting is not active for any of the information classes. • 0xFF,if Not Available

8.809.2 Field Documentation

8.809.2.1 uint8_t∗ pack_voice_SLQSVoiceGetCallBarring_t::pSvcClass

8.809.2.2 uint8_t pack_voice_SLQSVoiceGetCallBarring_t::reason

8.810 pack_voice_SLQSVoiceGetCallForwardingStatus_t Struct Reference

Data Fields

- uint8_t Reason
- uint8_t ∗ pSvcClass

8.810.1 Detailed Description

This structure contains Voice Get Call Forwarding Status Pack Parameters

Parameters

Reason	• Call Forwarding Reason • Values: – 0x01 - QMI_VOICE_REASON_FWDREASON_UNCONDITIONAL - Unconditional call forwarding – 0x02 - QMI_VOICE_REASON_FWDREASON_MOBILEBUSY - Forward when the mobile is busy – 0x03 - QMI_VOICE_REASON_FWDREASON_NOREPLY - Forward when there is no reply – 0x04 - QMI_VOICE_REASON_FWDREASON_UNREACHABLE - Forward when the call is unreachable – 0x05 - QMI_VOICE_REASON_FWDREASON_ALLFORWARDING - All forwarding – 0x06 - QMI_VOICE_REASON_FWDREASON_ALLCONDITIONAL - All conditional forwarding
pSvcClass(optional)	• Service Class is a combination (sum) of information class constants • See qaGobiApiTableSupServiceInfoClasses.h for service classes.

8.810.2 Field Documentation

8.810.2.1 uint8_t* pack_voice_SLQSVoiceGetCallForwardingStatus_t::pSvcClass

8.810.2.2 uint8_t pack_voice_SLQSVoiceGetCallForwardingStatus_t::Reason

8.811 pack_voice_SLQSVoiceGetCallInfo_t Struct Reference

Data Fields

- uint8_t callID

8.811.1 Detailed Description

This structure contains information of the request parameters associated with a call.

Parameters

callID	• Call identifier for the call queried for information.

8.811.2 Field Documentation

8.811.2.1 uint8_t pack_voice_SLQSVoiceGetCallInfo_t::callID

8.812 pack_voice_SLQSVoiceGetCallWaiting_t Struct Reference

Data Fields

- uint8_t * pSvcClass

8.812.1 Detailed Description

This structure contains Voice Get Call Waiting Response Parameters

Parameters

pSvcClass	• Service class is a combination (sum) of information class constants (optional) • See qaGobiApiTableSupServiceInfoClasses.h for service classes. • Service Class is set to 0 if call waiting is not active for any of the information classes. • 0xFF,if Not Available

8.812.2 Field Documentation

8.812.2.1 uint8_t∗ pack_voice_SLQSVoiceGetCallWaiting_t::pSvcClass

8.813 pack_voice_SLQSVoiceGetConfig_t Struct Reference

Data Fields

- uint8_t ∗ pAutoAnswer
- uint8_t ∗ pAirTimer
- uint8_t ∗ pRoamTimer
- uint8_t ∗ pTTYMode
- uint8_t ∗ pPrefVoiceSO
- uint8_t ∗ pAMRStatus
- uint8_t ∗ pPrefVoicePrivacy
- uint8_t ∗ pNamID
- uint8_t ∗ pVoiceDomainPref

8.813.1 Detailed Description

This structure contains Voice Get Configuration Request Parameters

Parameters

pAuto-Answer(optional)	• Indicator to retrieve the Auto Answer Information. – 0x01 - Include auto answer information
pAir-Timer(optional)	• Indicator to retrieve the Air Timer Information. – 0x01 - Include air calls timer count information • Currently Not Supported.
pRoam-Timer(optional)	• Indicator to retrieve the Roam Timer Information. – 0x01 - Include roam calls timer information • Currently Not Supported.

pTTY-Mode(optional)	• Indicator to retrieve the TTY Mode Information. – 0x01 - Include TTY configuration status information
pPrefVoiceS-O(optional)	• Indicator to retrieve the Preferred Voice SO Information. – 0x01 - Include preferred voice configuration status information • Currently Not Supported.
pAMR-Status(optional)	• Indicator to retrieve the AMR Status Information. – 0x01 - Include AMR status information
pPrefVoice-Privacy(optional)	• Indicator to retrieve the Preferred Voice Privacy Information. – 0x01 - Include preferred voice privacy status information
pNamI-D(optional)	• Index of the Number Assignment Module Index (CDMA subscription) to be configured • Range: 0 to 3. • Some modems support only 1 or 2 NAMs. • The NAM Index is valid only when the request contains at least one of Air Timer, Roam Timer, and Preferred Voice SO. • If no nam_id value is specified in the request,the default value is 0.
pVoiceDomain-Pref(optional)	• Indicator to retrieve the Preferred Voice Domain Information. – 0x01 - Include voice domain preference information

Note

Using NULL for the pointers would make sure that the parameter is not returned.

8.813.2 Field Documentation

8.813.2.1 uint8_t* pack_voice_SLQSVoiceGetConfig_t::pAirTimer

8.813.2.2 uint8_t* pack_voice_SLQSVoiceGetConfig_t::pAMRStatus

8.813.2.3 uint8_t* pack_voice_SLQSVoiceGetConfig_t::pAutoAnswer

8.813.2.4 uint8_t* pack_voice_SLQSVoiceGetConfig_t::pNamID

8.813.2.5 uint8_t* pack_voice_SLQSVoiceGetConfig_t::pPrefVoicePrivacy

8.813.2.6 uint8_t* pack_voice_SLQSVoiceGetConfig_t::pPrefVoiceSO

8.813.2.7 uint8_t* pack_voice_SLQSVoiceGetConfig_t::pRoamTimer

8.813.2.8 uint8_t* pack_voice_SLQSVoiceGetConfig_t::pTTYMode

8.813.2.9 uint8_t* pack_voice_SLQSVoiceGetConfig_t::pVoiceDomainPref

8.814 pack_voice_SLQSVoiceIndicationRegister_t Struct Reference

Data Fields

- uint8_t * pRegDTMFEvents
- uint8_t * pRegVoicePrivacyEvents
- uint8_t * pSuppsNotifEvents

8.814.1 Detailed Description

This structure contains parameters of Indication Register Information

Parameters

pRegDTMF-Events(optional)	• Registration Indication For DTMF Events. • When this registration is enabled, the device learns of DTMF events via the QMI_VOICE_DTMF_IND indication. – 0x00 - Disable – 0x01 - Enable
pRegVoice-Privacy-Events(optional)	• Registration Indication For Voice Privacy Events. • When this registration is enabled, the device learns of DTMF events via the QMI_VOICE_PRIVACY_IND indication. – 0x00 - Disable – 0x01 - Enable
pSuppsNotif-Events(optional)	• Registration Indication For Supplementary Service Notification Events. • When this registration is enabled, the device learns of DTMF events via the QMI_VOICE_SUPS_NOTIFICATION_IND indication. – 0x00 - Disable – 0x01 - Enable

Note

One of the optional parameter is mandatory to be present in the request.

8.814.2 Field Documentation

8.814.2.1 uint8_t* pack_voice_SLQSVoiceIndicationRegister_t::pRegDTMFEvents

8.814.2.2 uint8_t* pack_voice_SLQSVoiceIndicationRegister_t::pRegVoicePrivacyEvents

8.814.2.3 uint8_t* pack_voice_SLQSVoiceIndicationRegister_t::pSuppsNotifEvents

8.815 pack_voice_SLQSVoiceManageCalls_t Struct Reference

Data Fields

- uint8_t SUPSType

- uint8_t * pCallID

8.815.1 Detailed Description

This structure contains Manage Calls Information.

Parameters

SUPSType	• Supplementary service type during the call. – 0x01 - SUPS_TYPE_RELEASE_HELD_OR_WAITING * Release is held or waiting – 0x02 - SUPS_TYPE_RELEASE_ACTIVE_ACCEPT_HELD_OR_WAITING * Release is active and accepting held or waiting – 0x03 - SUPS_TYPE_HOLD_ACTIVE_ACCEPT_WAITING_OR_HELD * Hold is active and accepting waiting or held – 0x04 - SUPS_TYPE_HOLD_ALL_EXCEPT_SPECIFIED_CALL * Hold all calls except a specified one – 0x05 - SUPS_TYPE_MAKE_CONFERENCE_CALL * Make a conference call – 0x06 - SUPS_TYPE_EXPLICIT_CALL_TRANSFER * Explicit call transfer – 0x07 - SUPS_TYPE_CCBS_ACTIVATION * Activate completion of calls to busy subscriber – 0x08 - SUPS_TYPE_END_ALL_CALLS * End all calls – 0x09 - SUPS_TYPE_RELEASE_SPECIFIED_CALL * Release a specified call
pCallID[Optional]	• Applicable only for SUPSType 0x04, 0x07, and 0x09 • NULL pointer - Invalid data.

8.815.2 Field Documentation

8.815.2.1 uint8_t* pack_voice_SLQSVoiceManageCalls_t::pCallID

8.815.2.2 uint8_t pack_voice_SLQSVoiceManageCalls_t::SUPSType

8.816 pack_voice_SLQSVoiceOrigUSSDNoWait_t Struct Reference

Data Fields

- struct voice_USSInfo USSInformation

8.816.1 Detailed Description

This structure contains Orig USSD No Wait Information Parameters.

Parameters

USSInformation	• See voice_USSInfo for more information.

8.816.2 Field Documentation

8.816.2.1 struct voice_USSInfo pack_voice_SLQSVoiceOrigUSSDNoWait_t::USSInformation

8.817 pack_voice_SLQSVoiceSendFlash_t Struct Reference

Data Fields

- uint8_t ∗ pCallID
- uint8_t ∗ pFlashPayLd
- uint8_t ∗ pFlashType

8.817.1 Detailed Description

This structure contains the flash information associated with a call.

Parameters

pCallID	• Unique call identifier associated with the current call.
pFlashPayLd(optional)	• Payload in ASCII to be sent in Flash. • Variable Length, NULL terminated.
pFlashType(optional)	• Flash type. – 0 - Simple Flash (default) – 1 - Activate answer hold – 2 - Deactivate answer hold

8.817.2 Field Documentation

8.817.2.1 uint8_t∗ pack_voice_SLQSVoiceSendFlash_t::pCallID

8.817.2.2 uint8_t∗ pack_voice_SLQSVoiceSendFlash_t::pFlashPayLd

8.817.2.3 uint8_t∗ pack_voice_SLQSVoiceSendFlash_t::pFlashType

8.818 pack_voice_SLQSVoiceSetCallBarringPassword_t Struct Reference

Data Fields

- uint8_t Reason
- uint8_t oldPasswd [4]
- uint8_t newPasswd [4]

- uint8_t newPasswdAgain [4]

8.818.1 Detailed Description

This structure contains Voice Set Call Barring Password Pack Parameters

Parameters

Reason	• Call Barring Reason • Values: – 0x07 - QMI_VOICE_REASON_BARR_ALLOUTGOING - All outgoing – 0x08 - QMI_VOICE_REASON_BARR_OUTGOINGINT - Outgoing internal – 0x09 - QMI_VOICE_REASON_BARR_OUTGOINGINTEXTOHOME - Outgoing external to home – 0x0A - QMI_VOICE_REASON_BARR_ALLINCOMING - All incoming – 0x0B - QMI_VOICE_REASON_BARR_INCOMINGROAMING - Roaming incoming – 0x0C - QMI_VOICE_REASON_BARR_ALLBARRING - All calls are barred – 0x0D - QMI_VOICE_REASON_BARR_ALLOUTGOINGBARRING - All outgoing calls are barred – 0x0E - QMI_VOICE_REASON_BARR_ALLINCOMINGBARRING - All incoming calls are barred
oldPasswd[BARRING_PASSWORD_LENGTH]	• Old password. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.
newPasswd[BARRING_PASSWORD_LENGTH]	• New password. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.
newPasswdAgain[BARRING_PASSWORD_LENGTH]	• New password Again. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.

8.818.2 Field Documentation

8.818.2.1 uint8_t pack_voice_SLQSVoiceSetCallBarringPassword_t::newPasswd[4]

8.818.2.2 uint8_t pack_voice_SLQSVoiceSetCallBarringPassword_t::newPasswdAgain[4]

8.818.2.3 uint8_t pack_voice_SLQSVoiceSetCallBarringPassword_t::oldPasswd[4]

8.818.2.4 uint8_t pack_voice_SLQSVoiceSetCallBarringPassword_t::Reason

8.819 pack_voice_SLQSVoiceSetConfig_t Struct Reference

Data Fields

- uint8_t * pAutoAnswer
- voice_airTimer * pAirTimerConfig
- voice_roamTimer * pRoamTimerConfig
- uint8_t * pTTYMode
- voice_prefVoiceSO * pPrefVoiceSO
- uint8_t * pPrefVoiceDomain

8.819.1 Detailed Description

This structure contains information about the Set Configuration Request Parameters.

Parameters

pAutoAnswer	• Value specified is written to NV_AUTO_ANSWER_I. (optional) • Values: – 0x00 - Disable – 0x01 - Enable
pAirTimerConfig	• Value specified is written to NV_AIR_CNT_I. (optional) • See voice_airTimer for more information
pRoamTimer-Config	• Value specified is written to NV_ROAM_CNT_I. (optional) • See voice_roamTimer for more information
pTTYMode	• Value specified is written to NV_TTY_I. (optional) • Values: – 0x00 - TTY_MODE_FULL - Full – 0x01 - TTY_MODE_VCO - Voice carry over – 0x02 - TTY_MODE_HCO - Hearing carry over – 0x03 - TTY_MODE_OFF - Off
pPrefVoiceSO	• Value specified is written to NV_PREF_VOICE_SO_I. (optional) • See voice_prefVoiceSO for more information
pPrefVoice-Domain	• Preferred Voice-Domain. (optional) • Values: – 0x00 - VOICE_DOMAIN_PREF_CS_ONLY - Circuit-switched (CS) only – 0x01 - VOICE_DOMAIN_PREF_PS_ONLY - Packet-switched (PS) only – 0x02 - VOICE_DOMAIN_PREF_CS_PREF - CS is preferred, PS is secondary – 0x03 - VOICE_DOMAIN_PREF_PS_PREF - PS is preferred, CS is secondary

Note

One of the optional parameters must be present in the request.

8.819.2 Field Documentation

8.819.2.1 voice_airTimer* pack_voice_SLQSVoiceSetConfig_t::pAirTimerConfig

8.819.2.2 uint8_t* pack_voice_SLQSVoiceSetConfig_t::pAutoAnswer

8.819.2.3 uint8_t* pack_voice_SLQSVoiceSetConfig_t::pPrefVoiceDomain

8.819.2.4 voice_prefVoiceSO* pack_voice_SLQSVoiceSetConfig_t::pPrefVoiceSO

8.819.2.5 voice_roamTimer* pack_voice_SLQSVoiceSetConfig_t::pRoamTimerConfig

8.819.2.6 uint8_t* pack_voice_SLQSVoiceSetConfig_t::pTTYMode

8.820 pack_voice_SLQSVoiceSetPreferredPrivacy_t Struct Reference

Data Fields

- uint8_t privacyPref

8.820.1 Detailed Description

This structure contains the preferred voice privacy values.

Parameters

privacyPref	• Voice Privacy Preference – 0x00 - VOICE_PRIVACY_STANDARD - Standard privacy – 0x01 - VOICE_PRIVACY_ENHANCED - Enhanced privacy

8.820.2 Field Documentation

8.820.2.1 uint8_t pack_voice_SLQSVoiceSetPreferredPrivacy_t::privacyPref

8.821 pack_voice_SLQSVoiceSetSUPSService_t Struct Reference

Data Fields

- uint8_t voiceSvc
- uint8_t reason
- uint8_t * pServiceClass
- uint8_t * pCallBarringPasswd
- uint8_t * pCallForwardingNumber
- uint8_t * pTimerVal
- voice_callFwdTypeAndPlan * pCallFwdTypeAndPlan

8.821.1 Detailed Description

This structure contains Supplementary Service request parameters related to different features and their activation, deactivation, registration and erasure (applicable only for 3GPP)

Parameters

voiceSvc	• Manages all call-independent supplementary services, such as activation, deactivation, registration, and erasure (mandatory) – 0x01 - VOICE_SERVICE_ACTIVATE – 0x02 - VOICE_SERVICE_DEACTIVATE – 0x03 - VOICE_SERVICE_REGISTER – 0x04 - VOICE_SERVICE_ERASE
reason	• supplementary service reason values (mandatory) – 0x01 - QMI_VOICE_REASON_FWD_UNCONDITIONAL Unconditional call forwarding – 0x02 - QMI_VOICE_REASON_FWD_MOBILEBUSY Forward when the mobile is busy – 0x03 - QMI_VOICE_REASON_FWD_NOREPLY Forward when there is no reply – 0x04 - QMI_VOICE_REASON_FWD_UNREACHABLE Forward when the call is unreachable – 0x05 - QMI_VOICE_REASON_FWD_ALLFORWARDING All forwarding – 0x06 - QMI_VOICE_REASON_FWD_ALLCONDITIONAL All conditional forwarding – 0x07 - QMI_VOICE_REASON_BARR_ALLOUTGOING All outgoing calls are barred – 0x08 - QMI_VOICE_REASON_BARR_OUTGOINGINT Outgoing internal calls are barred – 0x09 - QMI_VOICE_REASON_BARR_OUTGOINGINTEXTOHOME Outgoing calls external to home are barred – 0x0A - QMI_VOICE_REASON_BARR_ALLINCOMING All incoming calls are barred – 0x0B - QMI_VOICE_REASON_BARR_INCOMINGROAMING Roaming incoming calls are barred – 0x0C - QMI_VOICE_REASON_BARR_ALLBARRING All calls are barred – 0x0D - QMI_VOICE_REASON_BARR_ALLOUTGOINGBARRING All outgoing calls are barred – 0x0E - QMI_VOICE_REASON_BARR_ALLINCOMINGBARRING All incoming calls are barred – 0x0F - QMI_VOICE_REASON_CALLWAITING Call waiting
pServiceClass	• Service class is a combination (sum) of information class constants (optional) – See liteServiceClassInformation for more information
pCallBarring-Passwd	• Password is required if call barring is provisioned using a password. Password consists of 4 ASCII digits. Range: 0000 to 9999 (optional)

pCallForwarding-Number	• Call forwarding number to be registered with the network. This has to be included in the request only when the service is set to VOICE_SERVICE_REGISTER. NULL terminated ASCII string. (optional)
pTimerVal	• Call forwarding no reply timer value in seconds. This has to be included in the request only when the service is set to VOICE_SERVICE_REGISTER and the reason is QMI_VOICE_REASON_FWD_NOREPLY. (optional) – Range: 5 to 30 in steps of 5
pCallFwdType-AndPlan	• Information about call forwarding type and plan. This parameter is ignored when the Call Forwarding Number is not included (optional) – See voice_callFwdTypeAndPlan for more information

8.821.2 Field Documentation

8.821.2.1 uint8_t∗ pack_voice_SLQSVoiceSetSUPSService_t::pCallBarringPasswd

8.821.2.2 uint8_t∗ pack_voice_SLQSVoiceSetSUPSService_t::pCallForwardingNumber

8.821.2.3 voice_callFwdTypeAndPlan∗ pack_voice_SLQSVoiceSetSUPSService_t::pCallFwdTypeAndPlan

8.821.2.4 uint8_t∗ pack_voice_SLQSVoiceSetSUPSService_t::pServiceClass

8.821.2.5 uint8_t∗ pack_voice_SLQSVoiceSetSUPSService_t::pTimerVal

8.821.2.6 uint8_t pack_voice_SLQSVoiceSetSUPSService_t::reason

8.821.2.7 uint8_t pack_voice_SLQSVoiceSetSUPSService_t::voiceSvc

8.822 pack_voice_SLQSVoiceStartContDTMF_t Struct Reference

Data Fields

- uint8_t ∗ pCallID
- uint8_t DTMFdigit

8.822.1 Detailed Description

This structure contains parameters of continuous DTMF

Parameters

pCallID	• Call ID associated with call on which the DTMF information has to be sent. Start continuous DTMF request is sent to the current active/alerting call when pCallId is set to 0xFF. • This is IN/OUT parameter, value passed by user will be packed in request and value received from the device would be returned to the user. • If the call ID value received is 0, no value has been returned by the device

DTMFdigit	• DTMF digit in ASCII.

8.822.2 Field Documentation

8.822.2.1 uint8_t pack_voice_SLQSVoiceStartContDTMF_t::DTMFdigit

8.822.2.2 uint8_t∗ pack_voice_SLQSVoiceStartContDTMF_t::pCallID

8.823 pack_voice_SLQSVoiceStopContDTMF_t Struct Reference

Data Fields

- uint8_t callID

8.823.1 Detailed Description

This structure contains parameters of stop continuous DTMF

Parameters

pCallID	• Call ID associated with call on which the DTMF information has to be sent. Stop continuous DTMF request is sent to the current active/alerting call when pCallId is set to 0xFF. • This is IN/OUT parameter, value passed by user will be packed in request and value received from the device would be returned to the user. • If the call ID value received is 0, no value has been returned by the device

8.823.2 Field Documentation

8.823.2.1 uint8_t pack_voice_SLQSVoiceStopContDTMF_t::callID

8.824 pack_wds_DHCPv4ClientLeaseChange_t Struct Reference

Data Fields

- uint8_t ∗ pEnableNotification

8.824.1 Detailed Description

WDS SWI DHCPv4 Client Lease Change Structure

Parameters

pEnable-Notification	• Enable Notification or not

8.824.2 Field Documentation

8.824.2.1 uint8_t* pack_wds_DHCPv4ClientLeaseChange_t::pEnableNotification

8.825 pack_wds_GetDefaultProfile_t Struct Reference

Data Fields

- uint32_t profiletype

8.825.1 Detailed Description

This structure contains pack get default profile information.

Parameters

profiletype	profile type • 0 - WDS_PROFILE_TYPE_3GPP (0x00) - 3GPP • 1 - WDS_PROFILE_TYPE_3GPP (0x01) - 3GPP2 • 2 - WDS_PROFILE_TYPE_EPC (0x02) - EPC

8.825.2 Field Documentation

8.825.2.1 uint32_t pack_wds_GetDefaultProfile_t::profiletype

8.826 pack_wds_GetDefaultProfileNum_t Struct Reference

Data Fields

- uint8_t type
- uint8_t family

8.826.1 Detailed Description

This structure contains pack Get Default Profile Number information.

Parameters

type	profile type • 0 - 3GPP • 1 - 3GPP2
family	profile family • 0 - Embedded • 1 - Tethered

8.826.2 Field Documentation

8.826.2.1 uint8_t pack_wds_GetDefaultProfileNum_t::family

8.826.2.2 uint8_t pack_wds_GetDefaultProfileNum_t::type

8.827 pack_wds_GetDormancyState_t Struct Reference

8.827.1 Detailed Description

This structure contains pack get dormancy state information.

Parameters

NULL	• this is a dummy structure

8.828 pack_wds_GetLastMobileIPError_t Struct Reference

8.828.1 Detailed Description

This structure contains pack get last mobile IP error information.

Parameters

NULL	• this is a dummy structure

8.829 pack_wds_GetMobileIP_t Struct Reference

8.829.1 Detailed Description

This structure contains pack get mobile IP information.

Parameters

NULL	• this is a dummy structure

8.830 pack_wds_GetMobileIPProfile_t Struct Reference

Data Fields

- uint8_t index

8.830.1 Detailed Description

This structure contains pack get mobile IP profile information.

Parameters

index	• Mobile IP profile ID

8.830.2 Field Documentation

8.830.2.1 uint8_t pack_wds_GetMobileIPProfile_t::index

8.831 pack_wds_GetPacketStatistics_t Struct Reference

Data Fields

- uint32_t ∗ pStatMask

8.831.1 Detailed Description

This structure contains pack get packet statistics information.

Parameters

pStatMask	• Packet Statistics Mask – 0x00000001 - Tx packets OK – 0x00000002 - Rx packets OK – 0x00000004 - Tx packet errors – 0x00000008 - Rx packet errors – 0x00000010 - Tx overflows – 0x00000020 - Rx overflows – 0x00000040 - Tx bytes OK – 0x00000080 - Rx bytes OK

8.831.2 Field Documentation

8.831.2.1 uint32_t∗ pack_wds_GetPacketStatistics_t::pStatMask

8.832 pack_wds_GetPacketStatus_t Struct Reference

Data Fields

- uint32_t statmask

8.832.1 Detailed Description

This structure contains pack get packet status information.

Parameters

statmask	packet statistics mask • 0x00000001 - Tx packets OK • 0x00000002 - Rx packets OK • 0x00000004 - Tx packet errors • 0x00000008 - Rx packet errors • 0x00000010 - Tx overflows • 0x00000020 - Rx overflows • 0x00000040 - Tx bytes OK • 0x00000080 - Rx bytes OK • 0x00000100 - Tx packets dropped • 0x00000200 - Rx packets dropped

8.832.2 Field Documentation

8.832.2.1 uint32_t pack_wds_GetPacketStatus_t::statmask

8.833 pack_wds_GetSessionDuration_t Struct Reference

8.833.1 Detailed Description

This structure contains pack get session duration information.

Parameters

NULL	• this is a dummy structure

8.834 pack_wds_RMSetTransferStatistics_t Struct Reference

Data Fields

- rmTrasnferStaticsReq RmTrasnferStaticsReq

8.834.1 Detailed Description

This structure contains pack fetch current data system transfer statistics information.

Parameters

RmTrasnfer-StaticsReq[IN]	• See rmTrasnferStaticsReq for more information

8.834.2 Field Documentation

8.834.2.1 rmTrasnferStaticsReq pack_wds_RMSetTransferStatistics_t::RmTrasnferStaticsReq

8.835 pack_wds_SetAutoconnect_t Struct Reference

Data Fields

- uint8_t acsetting
- uint8_t acroamsetting

8.835.1 Detailed Description

auto connect data session parameters.

Parameters

acsetting	• Current autoconnect setting: – 0x00 - Autoconnect disabled – 0x01 - Autoconnect enabled – 0x02 - Autoconnect paused (resume on powercycle)
acroamsetting	• Current autoconnect roaming status – 0x00 - Autoconnect always allowed – 0x01 - Autoconnect while in home service area only

8.835.2 Field Documentation

8.835.2.1 uint8_t pack_wds_SetAutoconnect_t::acroamsetting

8.835.2.2 uint8_t pack_wds_SetAutoconnect_t::acsetting

8.836 pack_wds_SetDefaultProfile_t Struct Reference

Data Fields

- uint32_t profileType
- uint32_t pdpType
- uint32_t ipAddress
- uint32_t primaryDNS
- uint32_t secondaryDNS
- uint32_t authentication
- uint8_t * pName
- uint8_t * pUsername
- uint8_t * pApnname
- uint8_t * pPassword

8.836.1 Detailed Description

Writes the default profile settings to the device. The default profile is used to establish an autoconnect data session.

Parameters

profileType	• Type of profile – 0 - 3GPP – 1 - 3GPP2
pdpType	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile (optional) – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6
ipAddress	• Preferred IPv4 addr to be assigned to device (optional)
primaryDNS	• Primary DNS Ipv4 address preference (optional)
secondaryDNS	• Secondary DNS Ipv4 address preference (optional)
authentication	• Bitmap that indicates authentication algorithm preference (optional) – 0x00000001 - PAP preference * 0 - Never performed * 1 - May be performed – 0x00000002 - CHAP preference * 0 - Never performed * 1 - May be performed – All other bits are reserved and must be set to 0 – If more than 1 bit is set, then device decides which authentication procedure is performed while setting up data session e.g. the device may have a policy to select the most secure authentication mechanism.
pName	• profile Name (optional)
pUsername	• Username used during network authentication (optional)
pAPNName	• Access point name. NULL-terminated string parameter that is a logical name used to select GGSN and external packet data network (optional) • If value is NULL or omitted, then subscription default value will be requested.
pPassword	• Password used during network authentication (optional)

8.836.2 Field Documentation

8.836.2.1 uint32_t pack_wds_SetDefaultProfile_t::authentication

8.836.2.2 uint32_t pack_wds_SetDefaultProfile_t::ipAddress

8.836.2.3 uint8_t* pack_wds_SetDefaultProfile_t::pApnname

8.836.2.4 uint32_t pack_wds_SetDefaultProfile_t::pdpType

8.836.2.5 uint8_t* pack_wds_SetDefaultProfile_t::pName

8.836.2.6 uint8_t* pack_wds_SetDefaultProfile_t::pPassword

8.836.2.7 uint32_t pack_wds_SetDefaultProfile_t::primaryDNS

8.836.2.8 uint32_t pack_wds_SetDefaultProfile_t::profileType

8.836.2.9 uint8_t* pack_wds_SetDefaultProfile_t::pUsername

8.836.2.10 uint32_t pack_wds_SetDefaultProfile_t::secondaryDNS

8.837 pack_wds_SetDefaultProfileNum_t Struct Reference

Data Fields

- uint8_t type
- uint8_t family
- uint8_t index

8.837.1 Detailed Description

This structure to hold Set default profile number

Parameters

type	Identifies the technology type of the profile • 0 - 3GPP • 1 - 3GPP2
family	Identifies the family of profile • 0 - Embedded • 1 - Tethered
index	Profile number to be set as default profile.

8.837.2 Field Documentation

8.837.2.1 uint8_t pack_wds_SetDefaultProfileNum_t::family

8.837.2.2 uint8_t pack_wds_SetDefaultProfileNum_t::index

8.837.2.3 uint8_t pack_wds_SetDefaultProfileNum_t::type

8.838 pack_wds_SetMobileIP_t Struct Reference

Data Fields

- uint32_t mode

8.838.1 Detailed Description

This structure contains set mobile IP pack information.

Parameters

mode	• Mobile IP setting – 0 - Mobile IP off (simple IP only) – 1 - Mobile IP preferred – 2 - Mobile IP only

8.838.2 Field Documentation

8.838.2.1 uint32_t pack_wds_SetMobileIP_t::mode

8.839 pack_wds_SetMobileIPParameters_t Struct Reference

Data Fields

- char * pSPC
- uint32_t * pMode
- uint8_t * pRetryLimit
- uint8_t * pRetryInterval
- uint8_t * pReRegPeriod
- uint8_t * pReRegTraffic
- uint8_t * pHAAuthenticator
- uint8_t * pHA2002bis

8.839.1 Detailed Description

Mobile IP parameters information.

Parameters

pSPC	• NULL-terminated string representing six digit service programming code.
pMode	• Mode to be set (optional) – 0 - Mobile IP off (simple IP only) – 1 - Mobile IP preferred – 2 - Mobile IP only

pRetryLimit	• Registration retry attempt limit (optional)
pRetryInterval	• Registration retry attempt interval used to determine the time between registration attempts (optional)
pReRegPeriod	• Period (in minutes) to attempt re-registration before current registration expires (optional)
pReRegTraffic	• Re-registration only if traffic since last attempt (optional) – Zero - Disabled – NonZero - Enabled
pHA-Authenticator	• MH-HA authenticator calculator (optional) – Zero - Disabled – NonZero - Enabled
pHA2002bis	• MH-HA RFC 2002bis authentication instead of RFC2002 (optional) – Zero - Disabled – NonZero - Enabled

8.839.2 Field Documentation

8.839.2.1 uint8_t∗ pack_wds_SetMobileIPParameters_t::pHA2002bis

8.839.2.2 uint8_t∗ pack_wds_SetMobileIPParameters_t::pHAAuthenticator

8.839.2.3 uint32_t∗ pack_wds_SetMobileIPParameters_t::pMode

8.839.2.4 uint8_t∗ pack_wds_SetMobileIPParameters_t::pReRegPeriod

8.839.2.5 uint8_t∗ pack_wds_SetMobileIPParameters_t::pReRegTraffic

8.839.2.6 uint8_t∗ pack_wds_SetMobileIPParameters_t::pRetryInterval

8.839.2.7 uint8_t∗ pack_wds_SetMobileIPParameters_t::pRetryLimit

8.839.2.8 char∗ pack_wds_SetMobileIPParameters_t::pSPC

8.840 pack_wds_SetMobileIPProfile_t Struct Reference

Data Fields

- int8_t spc [10]
- uint8_t index
- uint8_t ∗ pEnabled
- uint32_t ∗ pAddress

- uint32_t * pPrimaryHA
- uint32_t * pSecondaryHA
- uint8_t * pRevTunneling
- int8_t * pNAI
- uint32_t * pHASPI
- uint32_t * pAAASPI
- int8_t * pMNHA
- int8_t * pMNAAA

8.840.1 Detailed Description

Sets the mobile IP parameters.

Parameters

spc	• Six digit service programming code string
index	• Index of the profile to modify
pEnabled	• (Optional) Enable profile? 0 - Disabled Nonzero - Enabled
pAddress	• (Optional) Home IPv4 address
pPrimaryHA	• (Optional) Primary home agent IPv4 address
pSecondaryHA	• (Optional) Secondary home agent IPv4 address
pRevTunneling	• (Optional) Enable reverse tunneling? 0 - Disabled Nonzero - Enabled
pNAI	• (Optional) Network access identifier string
pHASPI	• (Optional) Home agent security parameter index
pAAASPI	• (Optional) AAA server security parameter index
pMNHA	• (Optional) MN-HA key string
pMNAAA	• (Optional) MN-AAA key string

8.840.2 Field Documentation

8.840.2.1 uint8_t pack_wds_SetMobileIPProfile_t::index

8.840.2.2 uint32_t* pack_wds_SetMobileIPProfile_t::pAAASPI

8.840.2.3 uint32_t* pack_wds_SetMobileIPProfile_t::pAddress

8.840.2.4 uint8_t* pack_wds_SetMobileIPProfile_t::pEnabled

8.840.2.5 uint32_t* pack_wds_SetMobileIPProfile_t::pHASPI

8.840.2.6 int8_t* pack_wds_SetMobileIPProfile_t::pMNAAA

8.840.2.7 int8_t* pack_wds_SetMobileIPProfile_t::pMNHA

8.840.2.8 int8_t* pack_wds_SetMobileIPProfile_t::pNAI

8.840.2.9 uint32_t* pack_wds_SetMobileIPProfile_t::pPrimaryHA

8.840.2.10 uint8_t* pack_wds_SetMobileIPProfile_t::pRevTunneling

8.840.2.11 uint32_t* pack_wds_SetMobileIPProfile_t::pSecondaryHA

8.840.2.12 int8_t pack_wds_SetMobileIPProfile_t::spc[10]

8.841 pack_wds_SLQSCreateProfile_t Struct Reference

Data Fields

- uint8_t * pProfileId
- uint8_t * pProfileType
- wds_profileInfo * pCurProfile

8.841.1 Detailed Description

This structure contains pack create profile.

Parameters

pProfileId	• 1 to 16 for 3GPP profile (EM/MC73xx or earlier) • 1 to 24 for 3GPP profile (EM/MC74xx onwards) • 101 to 106 for 3GPP2 profile
pProfileType	• Identifies the technology type of the profile – 0x00 - 3GPP – 0x01 - 3GPP2 – NULL is not allowed
pCurProfile	• union of 3GPP and 3GPP2 profile • See wds_profileInfo

Note

- If profileID is NULL, 3GPP profile will be created and index will be assigned based on availability in device.
- If profileID is not NULL depending on pProfileType 3GPP/3GPP2 relevant profile will be created

8.841.2 Field Documentation

8.841.2.1 wds_profileInfo* pack_wds_SLQSCreateProfile_t::pCurProfile

8.841.2.2 uint8_t* pack_wds_SLQSCreateProfile_t::pProfileId

8.841.2.3 uint8_t* pack_wds_SLQSCreateProfile_t::pProfileType

8.842 pack_wds_SLQSDeleteProfile_t Struct Reference

Data Fields

- uint8_t profileType
- uint8_t profileIndex

8.842.1 Detailed Description

This structure contains the information about the profile to be deleted.

Parameters

profileType	• Identifies the type of profile – 0x00 - 3GPP • Note: Deletion of 3GPP2 profiles is not supported.
profileIndex	• Index of the configured profile to be deleted – Value between 1 - 16 (EM/MC73xx or earlier) – Value between 1 - 24 (EM/MC74xx onwards)

8.842.2 Field Documentation

8.842.2.1 uint8_t pack_wds_SLQSDeleteProfile_t::profileIndex

8.842.2.2 uint8_t pack_wds_SLQSDeleteProfile_t::profileType

8.843 pack_wds_SLQSGetCurrDataSystemStat_t Struct Reference

8.843.1 Detailed Description

This structure contains pack get current data system state information.

Parameters

NULL	• this is a dummy structure

8.844 pack_wds_SLQSGetDataBearerTechnology_t Struct Reference

8.844.1 Detailed Description

This structure contains pack get data bearer technology information.

Parameters

NULL	• this is a dummy structure

8.845 pack_wds_SLQSGetDUNCallInfo_t Struct Reference

Data Fields

- uint32_t Mask
- uint8_t * pReportConnStatus
- wds_transferStatInd * pTransferStatInd
- uint8_t * pReportDormStatus
- uint8_t * pReportDataBearerTech
- uint8_t * pReportChannelRate

8.845.1 Detailed Description

This structure contains the DUN Call Info Request parameters.

Parameters

Mask	• Mandatory parameter • Set the bits corresponding to the information requested to 1 • All other bits must be set to 0. • If any values are not available or applicable, the corresponding TLVs are not returned in the response. – Bit 0 - Connection Status – Bit 1 - Last call end reason – Bit 2 - Tx/Rx bytes OK – Bit 3 - Dormancy status – Bit 4 - Data bearer – Bit 5 - Channel rate – Bit 6 - Call active duration
pReportConn-Status	• Connect Status Indicator – 0 - Do not report – 1 - Report connection status and call end reason
pTransferStatInd	• See wds_transferStatInd for more information

pReportDorm-Status	• Dormancy Status Indicator – 0 - Do not report – 1 - Report traffic channel state of interface used for data connection
pReportData-BearerTech	• Current Data Bearer Technology Indicator – 0 - Do not report – 1 - Report radio interface used for data transfer when it changes
pReport-ChannelRate	• Channel Rate Indicator – 0 - Do not report – 1 - Report channel rate

8.845.2 Field Documentation

8.845.2.1 uint32_t pack_wds_SLQSGetDUNCallInfo_t::Mask

8.845.2.2 uint8_t* pack_wds_SLQSGetDUNCallInfo_t::pReportChannelRate

8.845.2.3 uint8_t* pack_wds_SLQSGetDUNCallInfo_t::pReportConnStatus

8.845.2.4 uint8_t* pack_wds_SLQSGetDUNCallInfo_t::pReportDataBearerTech

8.845.2.5 uint8_t* pack_wds_SLQSGetDUNCallInfo_t::pReportDormStatus

8.845.2.6 wds_transferStatInd* pack_wds_SLQSGetDUNCallInfo_t::pTransferStatInd

8.846 pack_wds_SLQSGetProfileSettings_t Struct Reference

Data Fields

- uint8_t ProfileId
- uint8_t ProfileType

8.846.1 Detailed Description

This structure contains pack get profile settings information.

Parameters

ProfileID	• 1 to 16 for 3GPP profile (EM/MC73xx or earlier) • 1 to 24 for 3GPP profile (EM/MC74xx onwards) • 101 to 106 for 3GPP2 profile
ProfileType	• Identifies the technology type of the profile – 0x00 - 3GPP – 0x01 - 3GPP2

Note

- If profileID is NULL, 3GPP profile will be fetched and index will be assigned based on availability in device.
- If profileID is not NULL depending on pProfileType 3GPP/3GPP2 relevant profile will be fetched

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

8.846.2 Field Documentation

8.846.2.1 uint8_t pack_wds_SLQSGetProfileSettings_t::ProfileId

8.846.2.2 uint8_t pack_wds_SLQSGetProfileSettings_t::ProfileType

8.847 pack_wds_SLQSGetRuntimeSettings_t Struct Reference

Data Fields

- uint32_t * pReqSettings

8.847.1 Detailed Description

This structure contains pack get runtime settings information

Parameters

pReqSettings	Requested Settings (Optional Parameter) • Set bits to 1, corresponding to requested information. All other bits must be set to 0. • If the values are not available, the corresponding TLVs are not returned in the response. • Absence of this mask TLV results in the device returning all of the available information corresponding to bits 0 through 12. • In cases where the information from bit 13 or greater is required, this TLV with all the necessary bits set must be present in the request. • Values – Bit 0 - Profile identifier – Bit 1 - Profile name – Bit 2 - PDP type – Bit 3 - APN name – Bit 4 - DNS address – Bit 5 - UMTS/GPRS granted QoS – Bit 6 - Username – Bit 7 - Authentication Protocol – Bit 8 - IP address – Bit 9 - Gateway info (address and subnet mask) – Bit 10 - PCSCF address using PCO flag – Bit 11 - PCSCF server address list – Bit 12 - PCSCF domain name list – Bit 13 - MTU – Bit 14 - domain name list – Bit 15 - IP family – Bit 16 - IM_CM flag – Bit 17 - Technology name – Bit 18 - Operator reserved PCO (Not Supported on MC/EM73xx)

8.847.2 Field Documentation

8.847.2.1 uint32_t* pack_wds_SLQSGetRuntimeSettings_t::pReqSettings

8.848 pack_wds_SLQSModifyProfile_t Struct Reference

Data Fields

- uint8_t * pProfileId
- uint8_t * pProfileType
- wds_profileInfo curProfile

8.848.1 Detailed Description

This structure contains pack modify profile information.

Parameters

pProfileId	• 1 to 16 for 3GPP profile (EM/MC73xx or earlier) • 1 to 24 for 3GPP profile (EM/MC74xx onwards) • 101 to 106 for 3GPP2 profile
pProfileType	• Identifies the technology type of the profile – 0x00 - 3GPP – 0x01 - 3GPP2 – NULL is not allowed
curProfile	• union of 3GPP and 3GPP2 profile • See wds_profileInfo

Note

- If profileID is NULL, 3GPP profile will be created and index will be assigned based on availability in device.
- If profileID is not NULL depending on pProfileType 3GPP/3GPP2 relevant profile will be created

8.848.2 Field Documentation

8.848.2.1 wds_profileInfo pack_wds_SLQSModifyProfile_t::curProfile

8.848.2.2 uint8_t* pack_wds_SLQSModifyProfile_t::pProfileId

8.848.2.3 uint8_t* pack_wds_SLQSModifyProfile_t::pProfileType

8.849 pack_wds_SLQSSet3GPPConfigItem_t Struct Reference

Data Fields

- uint16_t * pLTEAttachProfile
- uint16_t * pProfileList
- uint8_t * pDefaultPDNEnabled
- uint8_t * p3gppRelease
- uint16_t * pLTEAttachProfileList
- uint16_t LTEAttachProfileListLen

8.849.1 Detailed Description

This structure contains pack set 3GPP configuration item information.

Parameters

pLTEAttach-Profile	• Optional parameter • LTE Attach Profile – points to a single WORD Value indicating the attached LTE Profile – Optional parameter with possible values 1-16 (EM/MC73xx or earlier) • This setting is deprecated on MC/EM74xx

ProfileList	Profile List • an array of 4 profile configurations • Each element points to a single WORD value indicating profile • Optional parameter with possible values – 1 - 16 (MC/EM73xx and before) – 1 - 24 (MC/EM74xx and onwards) • function SLQSGet3GPPConfigItem() returns a default value 255 if no 3gpp configuration is present
pDefaultPDN-Enabled	• Optional parameter – 0 - disabled – 1 - enabled
p3gppRelease	3GPP release • Optional parameter – 0 - Release_99 – 1 - Release_5 – 2 - Release_6 – 3 - Release_7 – 4 - Release_8 • In 9x30 and onwards – 5 - Release 9 – 6 - Release 10 – 7 - Release 11
pLTEAttach-ProfileList	• pointer to WORD array indicating LTE Attach Profile List – Optional parameter – possible values: 1-24 – This setting is only supported for MC/EM74xx onwards – Please provide attach profiles in order of decreasing priority in this list.
LTEAttach-ProfileListLen	• Number of element in pLTEAttachProfileList – valid range: 1-24 – This setting is only supported for MC/EM74xx onwards

8.849.2 Field Documentation

8.849.2.1 uint16_t pack_wds_SLQSSet3GPPConfigItem_t::LTEAttachProfileListLen

8.849.2.2 uint8_t* pack_wds_SLQSSet3GPPConfigItem_t::p3gppRelease

8.849.2.3 uint8_t* pack_wds_SLQSSet3GPPConfigItem_t::pDefaultPDNEnabled

8.849.2.4 uint16_t* pack_wds_SLQSSet3GPPConfigItem_t::pLTEAttachProfile

8.849.2.5 uint16_t* pack_wds_SLQSSet3GPPConfigItem_t::pLTEAttachProfileList

8.849.2.6 uint16_t* pack_wds_SLQSSet3GPPConfigItem_t::pProfileList

8.850 pack_wds_SLQSSetIPFamilyPreference_t Struct Reference

Data Fields

- uint8_t IPFamilyPreference

8.850.1 Detailed Description

This structure contains pack set IP family preference information

Parameters

IPFamily-Preference	IP Family preference • PACK_WDS_IPV4 IP Version 4 • PACK_WDS_IPV6 IP Version 6

8.850.2 Field Documentation

8.850.2.1 uint8_t pack_wds_SLQSSetIPFamilyPreference_t::IPFamilyPreference

8.851 pack_wds_SLQSSetWdsEventCallback_t Struct Reference

Data Fields

- uint8_t dataBearer
- uint8_t dormancyStatus
- uint8_t mobileIP
- uint8_t transferStats
- uint8_t currentDataBearer
- uint8_t dataSystemStatus
- uint8_t dataBearerTechExt
- uint8_t interval

8.851.1 Detailed Description

This structure contains set WDS event callback information.

Parameters

dataBearer	data bearer
dormancyStatus	dormancy status
mobileIP	mobile IP
currentData-Bearer	current data bearer
dataSystem-Status	data system status
dataBearerTech-Ext	data Bearer Technology Extended
interval	interval

8.851.2 Field Documentation

8.851.2.1 uint8_t pack_wds_SLQSSetWdsEventCallback_t::currentDataBearer

8.851.2.2 uint8_t pack_wds_SLQSSetWdsEventCallback_t::dataBearer

8.851.2.3 uint8_t pack_wds_SLQSSetWdsEventCallback_t::dataBearerTechExt

8.851.2.4 uint8_t pack_wds_SLQSSetWdsEventCallback_t::dataSystemStatus

8.851.2.5 uint8_t pack_wds_SLQSSetWdsEventCallback_t::dormancyStatus

8.851.2.6 uint8_t pack_wds_SLQSSetWdsEventCallback_t::interval

8.851.2.7 uint8_t pack_wds_SLQSSetWdsEventCallback_t::mobileIP

8.851.2.8 uint8_t pack_wds_SLQSSetWdsEventCallback_t::transferStats

8.852 pack_wds_SLQSSGetDHCPv4ClientConfig_t Struct Reference

Data Fields

- wdsDhcpv4ProfileId * pProfileId

8.852.1 Detailed Description

This structure contain get DHCPv4 client configure.

Parameters

pProfileId	pointer to Profile Id structure • See wdsDhcpv4ProfileId

8.852.2 Field Documentation

8.852.2.1 wdsDhcpv4ProfileId* pack_wds_SLQSSGetDHCPv4ClientConfig_t::pProfileId

8.853 pack_wds_SLQSSSetDHCPv4ClientConfig_t Struct Reference

Data Fields

- wds_DHCPv4ProfileId * pProfileId
- wds_DHCPv4HWConfig * pHwConfig
- wds_DHCPv4OptionList * pRequestOptionList

8.853.1 Detailed Description

WDS SWI DHCPv4 Config Structure

Parameters

pProfileId	• pointer to Profile Id structure
pHWConfig	• pointer to HW Config structure
pRequestOption-List	• pointer to Option List structure to be sent in DHCP request

8.853.2 Field Documentation

8.853.2.1 wds_DHCPv4HWConfig∗ pack_wds_SLQSSSetDHCPv4ClientConfig_t::pHwConfig

8.853.2.2 wds_DHCPv4ProfileId∗ pack_wds_SLQSSSetDHCPv4ClientConfig_t::pProfileId

8.853.2.3 wds_DHCPv4OptionList∗ pack_wds_SLQSSSetDHCPv4ClientConfig_t::pRequestOptionList

8.854 pack_wds_SLQSSSetLoopback_t Struct Reference

Data Fields

- uint8_t loopbackMode
- uint8_t loopbackMultiplier

8.854.1 Detailed Description

This structure contains pack set loopback information.

Parameters

loopbackMode	• Loopback Mode. – 0 - Disable – 1 - Enable
loopback-Multiplier	• Loopback multiplier. Number of downlink bytes to send for each uplink byte.

8.854.2 Field Documentation

8.854.2.1 uint8_t pack_wds_SLQSSSetLoopback_t::loopbackMode

8.854.2.2 uint8_t pack_wds_SLQSSSetLoopback_t::loopbackMultiplier

8.855 pack_wds_SLQSStartDataSession_t Struct Reference

Data Fields

- uint8_t ∗ pTech

- uint32_t * pprofileid3gpp
- uint32_t * pprofileid3gpp2
- uint32_t * pAuth
- char * pUser
- char * pPass

8.855.1 Detailed Description

This structure contains pack Start Data Session Information.

Parameters

pTech	• Indicates the technology preference – 1 - UMTS – 2 - CDMA – 3 - eMBMS – 4 - Modem Link Label. Modem Link is an interface for transferring data between entities on AP and modem. • optional
pprofileid3gpp	• pointer to 3GPP profile id • optional
pprofileid3gpp2	• pointer to 3GPP2 profile id • optional
pAuth	• Authentication type, it can be PAP or CHAP • optional
pUser	• username for authentication process • optional
pPass	• password for authentication process • optional

8.855.2 Field Documentation

8.855.2.1 uint32_t* pack_wds_SLQSStartDataSession_t::pAuth

8.855.2.2 char* pack_wds_SLQSStartDataSession_t::pPass

8.855.2.3 uint32_t* pack_wds_SLQSStartDataSession_t::pprofileid3gpp

8.855.2.4 uint32_t* pack_wds_SLQSStartDataSession_t::pprofileid3gpp2

8.855.2.5 uint8_t* pack_wds_SLQSStartDataSession_t::pTech

8.855.2.6 char* pack_wds_SLQSStartDataSession_t::pUser

8.856 pack_wds_SLQSStopDataSession_t Struct Reference

Data Fields

- uint32_t * psid

8.856.1 Detailed Description

This structure contains pack stop data session information.

Parameters

psid	session id

8.856.2 Field Documentation

8.856.2.1 uint32_t* pack_wds_SLQSStopDataSession_t::psid

8.857 pack_wds_SLQSWdsSetEventReport_t Struct Reference

Data Fields

- uint8_t * pCurrChannelRateInd
- wds_TrStatInd * pTransferStatInd
- uint8_t * pDataBearerTechInd
- uint8_t * pDormancyStatusInd
- uint8_t * pMIPStatusInd
- uint8_t * pCurrDataBearerTechInd
- uint8_t * pDataCallStatusChangeInd
- uint8_t * pCurrPrefDataSysInd
- uint8_t * pEVDOPageMonPerChangeInd
- uint8_t * pDataSystemStatusChangeInd

8.857.1 Detailed Description

This structure contains the information about the Set Event Report Request parameters.

Parameters

pCurrChannel-RateInd	(optional) • Current Channel Rate Indicator. – 0 - Do not report – 1 - Report channel rate when it changes
pTransferStatInd	(optional) • See wds_TrStatInd for more information.
pDataBearer-TechInd	(optional) • Data Bearer Technology Indicator. – 0 - Do not report – 1 - Report radio interface used for data transfer when it changes

pDormancy-StatusInd	(optional) • Dormancy Status indicator. – 0 - Do not report – 1 - Report traffic channel state of interface used for data connection
pMIPStatusInd	(optional) • MIP Status Indicator. – 0 - Do not report – 1 - Report MIP status
pCurrData-BearerTechInd	(optional) • Current Data Bearer Technology Indicator. – 0 - Do not report – 1 - Report current data bearer technology when it changes
pDataCallStatus-ChangeInd	(optional) • Data Call Status Change Indicator. – 0 - Do not report – 1 - Report data call status change when it changes
pCurrPrefData-SysInd	(optional) • Current Preferred Data System Indicator. – 0 - Do not report – 1 - Report preferred data system when it changes
pEVDOPage-MonPerChange-Ind	(optional) • EV-DO Page Monitor Period Change Indicator. – 0 - Do not report – 1 - Report EV-DO page monitor period change event
pDataSystem-StatusChange-Ind	(optional) • Data System Status Change Indicator. – 0 - Do not report – 1 - Report data system status change event

Note

At least one parameter should be present.

8.857.2 Field Documentation

8.857.2.1 uint8_t* pack_wds_SLQSWdsSetEventReport_t::pCurrChannelRateInd

8.857.2.2 uint8_t* pack_wds_SLQSWdsSetEventReport_t::pCurrDataBearerTechInd

8.857.2.3 uint8_t* pack_wds_SLQSWdsSetEventReport_t::pCurrPrefDataSysInd

8.857.2.4 uint8_t* pack_wds_SLQSWdsSetEventReport_t::pDataBearerTechInd

8.857.2.5 uint8_t* pack_wds_SLQSWdsSetEventReport_t::pDataCallStatusChangeInd

8.857.2.6 uint8_t* pack_wds_SLQSWdsSetEventReport_t::pDataSystemStatusChangeInd

8.857.2.7 uint8_t* pack_wds_SLQSWdsSetEventReport_t::pDormancyStatusInd

8.857.2.8 uint8_t* pack_wds_SLQSWdsSetEventReport_t::pEVDOPageMonPerChangeInd

8.857.2.9 uint8_t* pack_wds_SLQSWdsSetEventReport_t::pMIPStatusInd

8.857.2.10 wds_TrStatInd* pack_wds_SLQSWdsSetEventReport_t::pTransferStatInd

8.858 pack_wds_SLQSWdsSwiPDPRuntimeSettings_t Struct Reference

Data Fields

- uint8_t contextId
- uint8_t contextType

8.858.1 Detailed Description

This structure contains the PDP Runtime Settings Request parameters.

Parameters

contextId	• Context Identifier
contextType	• Identifies technology type – 0 - 3GPP – 1 - 3GPP2

8.858.2 Field Documentation

8.858.2.1 uint8_t pack_wds_SLQSWdsSwiPDPRuntimeSettings_t::contextId

8.858.2.2 uint8_t pack_wds_SLQSWdsSwiPDPRuntimeSettings_t::contextType

8.859 PackCreateProfileOut Struct Reference

Data Fields

- uint8_t ProfileType
- uint8_t ProfileIndex
- uint16_t ExtErrorCode

8.859.1 Detailed Description

This structure contains out parameter Information

Parameters

ProfileType	• Identifies the type of profile 0x00 = 3GPP 0x01 = 3GPP2 • Bit to check in ParamPresenceMask - **1**
ProfileIndex	• Index identifying the profile that was created • Bit to check in ParamPresenceMask - **1**
ExtErrorCode	• The extended error code received from DS Profile subsystem • Bit to check in ParamPresenceMask - **224**

8.859.2 Field Documentation

8.859.2.1 uint16_t PackCreateProfileOut::ExtErrorCode

8.859.2.2 uint8_t PackCreateProfileOut::ProfileIndex

8.859.2.3 uint8_t PackCreateProfileOut::ProfileType

8.860 packgetDyingGaspCfg Struct Reference

Data Fields

- uint8_t ∗ pDestSMSNum
- uint8_t ∗ pDestSMSContent

8.860.1 Detailed Description

This struture contains the TLV required to get the Dysing GASP Config.

Parameters

pDestSMSNum[IN]	• SMS Destination Number as string of 8 bit ASCII Characters Max 20 chars. • Optional parameter.
pDestSMSContent[IN]	• SMS COntent as a string of 8 bit ASCII text characters Max 160 chars. • Optional parameter.

8.860.2 Field Documentation

8.860.2.1 uint8_t∗ packgetDyingGaspCfg::pDestSMSContent

8.860.2.2 uint8_t∗ packgetDyingGaspCfg::pDestSMSNum

8.861 packgetDyingGaspStatistics Struct Reference

Data Fields

- uint32_t * pTimeStamp
- uint8_t * pSMSAttemptedFlag

8.861.1 Detailed Description

This structure contains Get Dysing GASP Statistics

Parameters

pTimeStamp[OUT]	• Timestamp of the last time power loss was detected and Dying Gasp feature was triggered. • UTC time in seconds since Jan 06, 1980 (GPS Epoch).
pSMSAttemptedFlag[OUT]	• Indicates whether device attempted to send SMS in the last power loss event. • 0 - SMS not attempted • 1 - SMS attempted • This only indicates device sent the SMS but does not guarantee network delivery.

8.861.2 Field Documentation

8.861.2.1 uint8_t* packgetDyingGaspStatistics::pSMSAttemptedFlag

8.861.2.2 uint32_t* packgetDyingGaspStatistics::pTimeStamp

8.862 PCMparams Struct Reference

Data Fields

- BYTE iFaceTabLen
- BYTE iFaceTab [255]

8.862.1 Detailed Description

This structure contains the PCM parameters.

Parameters

iFaceTabLen	• Number of sets of iface table
iFaceTab	• Physical Interface Parameters • See qaGobiApiTableSwiAudio.h for more information on physical interface parameters

8.862.2 Field Documentation

8.862.2.1 BYTE PCMparams::iFaceTab[255]

8.862.2.2 BYTE PCMparams::iFaceTabLen

8.863 PCSCFFQDNAddress Struct Reference

Data Fields

- WORD fqdnLen
- CHAR fqdnAddr [256]

8.863.1 Detailed Description

This structure contains the PCSCFFQDNAddress Information

Parameters

fqdnLen	• length of the received FQDN address
fqdnAddr	• FQDN address(Max 256 characters)

8.863.2 Field Documentation

8.863.2.1 CHAR PCSCFFQDNAddress::fqdnAddr[256]

8.863.2.2 WORD PCSCFFQDNAddress::fqdnLen

8.864 PCSCFFQDNAddressList Struct Reference

Data Fields

- BYTE numInstances
- struct PCSCFFQDNAddress pcsfFQDNAddress [10]

8.864.1 Detailed Description

This structure contains the PCSCFFQDNAddressList Information

Parameters

numInstances	• Number of FQDN addresses received
pcsfFQDN-Address	• FQDN address information(Max 10 addresses)

8.864.2 Field Documentation

8.864.2.1 BYTE PCSCFFQDNAddressList::numInstances

8.864.2.2 struct PCSCFFQDNAddress PCSCFFQDNAddressList::pcsfFQDNAddress[10]

8.865 PCSCFIPv4ServerAddressList Struct Reference

Data Fields

- BYTE numInstances
- ULONG pscsfIPv4Addr [64]

8.865.1 Detailed Description

This structure contains the PCSCFIPv4ServerAddressList Information

Parameters

numInstances	• number of address following
pscsfIPv4Addr	• P-CSCF IPv4 server addresses(Max 16 address, 4 bytes each)

8.865.2 Field Documentation

8.865.2.1 BYTE PCSCFIPv4ServerAddressList::numInstances

8.865.2.2 ULONG PCSCFIPv4ServerAddressList::pscsfIPv4Addr[64]

8.866 PDSPositionData Struct Reference

Data Fields

- ULONGLONG * pTimeStamp
- ULONGLONG * pLatitude
- ULONGLONG * pLongitude
- ULONG * pAltitudeWrtEllipsoid
- ULONG * pAltitudeWrtSealevel
- ULONG * pHorizontalUncCircular
- ULONG * pVerticalUnc
- BYTE * pHorizontalConfidence
- BYTE * pVerticalConfidence
- BYTE * pPositionSource
- BYTE * pTimeType

8.866.1 Detailed Description

Position Data Parameters from the external source to be injected to PDS engine.

Parameters

pTimeStamp	• Timestamp of the injected position in msec. The time can be of type UTC, GPS, or Age and is defined in the pTimeType parameter. If the pTimeType is not present, the timestamp shall be assumed to be UTC time
pLatitude	• Latitude position referenced to the WGS-84 reference ellipsoid, counting positive angles north of the equator and negative angles south of the equator. Value (in decimal degrees) in the range from -90 degrees to +90 degrees.Value in double float format (refer toIEEE Std 754-1985)
pLongitude	• Longitude position referenced to the WGS-84 reference ellipsoid, counting positive angles east of the Greenwich Meridian and negative angles west of Greenwich meridian. Value (in decimal degrees) in the range from -180 degrees to +180 degrees.
pAltitudeWrt-Ellipsoid	• Height above the WGS-84 reference ellipsoid. Value conveys height (in meters). When injecting altitude information, the control point should include either this parameter or the pAltitudeWrt-Sealevel parameter. Value in single float format (refer to IEEE Std 754-1985)
pAltitudeWrt-Sealevel	• Height of MS above the mean sea level in units (in meters). When injecting altitude information, the control point should include either this parameter or the pAltitudeWrtEllipsoid parameter. Value in single float format (refer to IEEE Std 754-1985)
pHorizontalUnc-Circular	• Circular horizontal uncertainty (in meters). This parameter must be included if the latitude and longitude parameters are specified. Value in single float format (refer to IEEE Std 754-1985)
pVerticalUnc	• Vertical uncertainty (in meters). This parameter must be included if one of the altitude parameter are specified.Value in single float format (refer to IEEE Std 754-1985)
pHorizontal-Confidence	• Confidence value of the location horizontal uncertainty, specified as percentage, 1 to 100. This parameter must be included if the latitude and longitude parameters are specified.
pVertical-Confidence	• Confidence value of the location vertical uncertainty, specified as percentage, 1 to 100. This parameter must be included if one of the altitude paramters are specified.
pPositionSource	• Source of injected position: – 0x00 - Unknown – 0x01 - GPS – 0x02 - Cell ID – 0x03 - Enhanced cell ID – 0x04 - WiFi – 0x05 - Terrestrial – 0x06 - Terrestrial hybrid – 0x07 - Other

pTimeType	• Defines the time value set in the pTimeStamp parameter. – 0x00 - UTC Time: starting Jan 1, 1970 – 0x01 - GPS Time: starting Jan 6, 1980 – 0x02 - Age: Age of position information

8.866.2 Field Documentation

8.866.2.1 ULONG∗ PDSPositionData::pAltitudeWrtEllipsoid

8.866.2.2 ULONG∗ PDSPositionData::pAltitudeWrtSealevel

8.866.2.3 BYTE∗ PDSPositionData::pHorizontalConfidence

8.866.2.4 ULONG∗ PDSPositionData::pHorizontalUncCircular

8.866.2.5 ULONGLONG∗ PDSPositionData::pLatitude

8.866.2.6 ULONGLONG∗ PDSPositionData::pLongitude

8.866.2.7 BYTE∗ PDSPositionData::pPositionSource

8.866.2.8 ULONGLONG∗ PDSPositionData::pTimeStamp

8.866.2.9 BYTE∗ PDSPositionData::pTimeType

8.866.2.10 BYTE∗ PDSPositionData::pVerticalConfidence

8.866.2.11 ULONG∗ PDSPositionData::pVerticalUnc

8.867 PDSPosMethodStateReq Struct Reference

Data Fields

- BYTE ∗ pXtraTimeState
- BYTE ∗ pXtraDataState
- BYTE ∗ pWifiState

8.867.1 Detailed Description

Parameters to Set state of positioning method for a device.

Parameters

pXtraTimeState	• XTRA Time Position Method State. • Values: – 0x00 - Disable – 0x01 - Enable

pXtraDataState	• XTRA Data Position Method State. • Values: – 0x00 - Disable – 0x01 - Enable
Latitude	• WiFi Position Method State • Values: – 0x00 - Disable – 0x01 - Enable

8.867.2 Field Documentation

8.867.2.1 BYTE* PDSPosMethodStateReq::pWifiState

8.867.2.2 BYTE* PDSPosMethodStateReq::pXtraDataState

8.867.2.3 BYTE* PDSPosMethodStateReq::pXtraTimeState

8.868 peerNumberInfo Struct Reference

Data Fields

- BYTE callID
- BYTE numPI
- BYTE numSI
- BYTE numType
- BYTE numPlan
- BYTE numLen
- BYTE number [81]

8.868.1 Detailed Description

This structure contains information for Connected Peer Numbers.

Parameters

callID	• Unique call identifier for the call.
numPI	• Number presentation indicator. – 0x00 - PRESENTATION_ALLOWED - Allowed presentation – 0x01 - PRESENTATION_RESTRICTED - Restricted presentation – 0x02 - PRESENTATION_NUM_UNAVAILABLE - Unavailable presentation – 0x04 - PRESENTATION_PAYPHONE - Payphone presentation (GSM/UMTS specific) – 0xFF - Not Available

numSI	• Number screening indicator. – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network
numType	• Number type. – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension
numPlan	• Number plan. – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
numLen	• Provides the length of number which follow.
number[MAX_CALL_NO_LEN]	• number of numLen length, NULL terminated.

8.868.2 Field Documentation

8.868.2.1 BYTE peerNumberInfo::callID

8.868.2.2 BYTE peerNumberInfo::number[81]

8.868.2.3 BYTE peerNumberInfo::numLen

8.868.2.4 BYTE peerNumberInfo::numPI

8.868.2.5 BYTE peerNumberInfo::numPlan

8.868.2.6 BYTE peerNumberInfo::numSI

8.868.2.7 BYTE peerNumberInfo::numType

8.869 personalizationStatus Struct Reference

Data Fields

- BYTE numFeatures
- BYTE feature [12]
- BYTE verifyLeft [12]
- BYTE unblockLeft [12]

8.869.1 Detailed Description

This structure contains the information about the card result.

Parameters

numFeatures	• Number of active personalization features. The following block is repeated for each feature.
feature	• Indicates the personalization feature to deactivate or unblock. Valid values: – 0 - GW network personalization – 1 - GW network subset personalization – 2 - GW service provider personalization – 3 - GW corporate personalization – 4 - GW UIM personalization – 5 - 1X network type 1 personalization – 6 - 1X network type 2 personalization – 7 - 1X HRPD personalization – 8 - 1X service provider personalization – 9 - 1X corporate personalization – 10 - 1X RUIM personalization
verifyLeft	• Number of the remaining attempts to verify the personalization feature.
unblockLeft	• Number of the remaining attempts to unblock the personalization feature.

8.869.2 Field Documentation

8.869.2.1 BYTE personalizationStatus::feature[12]

8.869.2.2 BYTE personalizationStatus::numFeatures

8.869.2.3 BYTE personalizationStatus::unblockLeft[12]

8.869.2.4 BYTE personalizationStatus::verifyLeft[12]

8.870 PhyCaAggPcellInfo Struct Reference

Data Fields

- int pci
- int freq
- NAS_LTE_CPHY_CA_BW_NRB dl_bw_value
- int iLTEbandValue
- BYTE TlvPresent

8.870.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Pcell Information.

Parameters

pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
dl_bw_value	• Downlink Bandwidth Values. • See NAS_LTE_CPHY_CA_BW_NRB for more information.
scell_state	• Scell state Values. • See NAS_LTE_CPHY_SCELL_STATE for more information.
TlvPresent	• Tlv Present.

8.870.2 Field Documentation

8.870.2.1 NAS_LTE_CPHY_CA_BW_NRB PhyCaAggPcellInfo::dl_bw_value

8.870.2.2 int PhyCaAggPcellInfo::freq

8.870.2.3 int PhyCaAggPcellInfo::iLTEbandValue

8.870.2.4 int PhyCaAggPcellInfo::pci

8.870.2.5 BYTE PhyCaAggPcellInfo::TlvPresent

8.871 PhyCaAggScellArray Struct Reference

Data Fields

- BYTE cphy_scell_info_list_len

- int pci [255]
- int freq [255]
- NAS_LTE_CPHY_CA_BW_NRB cphy_ca_dl_bandwidth [255]
- int band [255]
- NAS_LTE_CPHY_SCELL_STATE scell_state [255]
- int scell_idx [255]
- BYTE TlvPresent

8.871.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Index.

Parameters

cphy_scell_info-_list_len	• Number of sets of the following elements: – pci – freq – cphy_ca_dl_bandwidth – band – scell_state – scell_idx
pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
cphy_ca_dl_-bandwidth	• Downlink Bandwidth Values. • See NAS_LTE_CPHY_CA_BW_NRB for more information.
band	• Band value. • See LTE_BAND_CLASS_E_UTRA_OPERATING_BAND for more information.
scell_state	• Scell state Values. • See NAS_LTE_CPHY_SCELL_STATE for more information.
scell_idx	• Scell index Values. • Range for index values: 0 to 7.
TlvPresent	• Tlv Present.

8.871.2 Field Documentation

8.871.2.1 int PhyCaAggScellArray::band[255]

8.871.2.2 NAS_LTE_CPHY_CA_BW_NRB PhyCaAggScellArray::cphy_ca_dl_bandwidth[255]

8.871.2.3 BYTE PhyCaAggScellArray::cphy_scell_info_list_len

8.871.2.4 int PhyCaAggScellArray::freq[255]

8.871.2.5 int PhyCaAggScellArray::pci[255]

8.871.2.6 int PhyCaAggScellArray::scell_idx[255]

8.871.2.7 NAS_LTE_CPHY_SCELL_STATE PhyCaAggScellArray::scell_state[255]

8.871.2.8 BYTE PhyCaAggScellArray::TlvPresent

8.872 PhyCaAggScellDlBw Struct Reference

Data Fields

- NAS_LTE_CPHY_CA_BW_NRB dl_bw_value
- BYTE TlvPresent

8.872.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation Downlink Bandwidth of Scell.

Parameters

dl_bw_value	• Downlink Bandwidth Values. • See NAS_LTE_CPHY_CA_BW_NRB for more information.

8.872.2 Field Documentation

8.872.2.1 NAS_LTE_CPHY_CA_BW_NRB PhyCaAggScellDlBw::dl_bw_value

8.872.2.2 BYTE PhyCaAggScellDlBw::TlvPresent

8.873 PhyCaAggScellIndex Struct Reference

Data Fields

- BYTE scell_idx
- BYTE TlvPresent

8.873.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Index.

Parameters

scell_idx	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
TlvPresent	• Tlv Present.

8.873.2 Field Documentation

8.873.2.1 BYTE PhyCaAggScellIndex::scell_idx

8.873.2.2 BYTE PhyCaAggScellIndex::TlvPresent

8.874 PhyCaAggScellIndType Struct Reference

Data Fields

- int pci
- int freq
- NAS_LTE_CPHY_SCELL_STATE scell_state
- BYTE TlvPresent

8.874.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Indeicator Type.

Parameters

pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
scell_state	• Scell state Values. • See NAS_LTE_CPHY_SCELL_STATE for more information.
TlvPresent	• Tlv Present.

8.874.2 Field Documentation

8.874.2.1 int PhyCaAggScellIndType::freq

8.874.2.2 int PhyCaAggScellIndType::pci

8.874.2.3 NAS_LTE_CPHY_SCELL_STATE PhyCaAggScellIndType::scell_state

8.874.2.4 BYTE PhyCaAggScellIndType::TlvPresent

8.875 PhyCaAggScellInfo Struct Reference

Data Fields

- int pci
- int freq
- NAS_LTE_CPHY_CA_BW_NRB dl_bw_value
- int iLTEbandValue
- NAS_LTE_CPHY_SCELL_STATE scell_state
- BYTE TlvPresent

8.875.1 Detailed Description

This structure contains the parameters for Physical Carrier aggregation of Scell Information.

Parameters

pci	• Physical cell ID of the SCell Range. • Range for ID values: 0 to 503.
freq	• Frequency of the absolute cell Range. • Range for ID values: 0 to 65535.
dl_bw_value	• Downlink Bandwidth Values. • See NAS_LTE_CPHY_CA_BW_NRB for more information.

iLTEbandValue	• Band value. • Range for LTE Band class 120 to 160. – 120 - LTE E-UTRA Operating Band 1 – 121 - LTE E-UTRA Operating Band 2 – 122 - LTE E-UTRA Operating Band 3 – 123 - LTE E-UTRA Operating Band 4 – 124 - LTE E-UTRA Operating Band 5 – 125 - LTE E-UTRA Operating Band 6 – 126 - LTE E-UTRA Operating Band 7 – 127 - LTE E-UTRA Operating Band 8 – 128 - LTE E-UTRA Operating Band 9 – 129 - LTE E-UTRA Operating Band 10 – 130 - LTE E-UTRA Operating Band 11 – 131 - LTE E-UTRA Operating Band 12 – 132 - LTE E-UTRA Operating Band 13 – 133 - LTE E-UTRA Operating Band 14 – 134 - LTE E-UTRA Operating Band 17 – 135 - LTE E-UTRA Operating Band 33 – 136 - LTE E-UTRA Operating Band 34 – 137 - LTE E-UTRA Operating Band 35 – 138 - LTE E-UTRA Operating Band 36 – 139 - LTE E-UTRA Operating Band 37 – 140 - LTE E-UTRA Operating Band 38 – 141 - LTE E-UTRA Operating Band 39 – 142 - LTE E-UTRA Operating Band 40 – 143 - LTE E-UTRA Operating Band 18 – 144 - LTE E-UTRA Operating Band 19 – 145 - LTE E-UTRA Operating Band 20 – 146 - LTE E-UTRA Operating Band 21 – 147 - LTE E-UTRA Operating Band 24 – 148 - LTE E-UTRA Operating Band 25 – 149 - LTE E-UTRA Operating Band 41 – 150 - LTE E-UTRA Operating Band 42 – 151 - LTE E-UTRA Operating Band 43 – 152 - LTE E-UTRA Operating Band 23 – 153 - LTE E-UTRA Operating Band 26 – 154 - LTE E-UTRA Operating Band 32 – 155 - LTE E-UTRA Operating Band 125 – 156 - LTE E-UTRA Operating Band 126 – 157 - LTE E-UTRA Operating Band 127 – 158 - LTE E-UTRA Operating Band 28 – 159 - LTE E-UTRA Operating Band 29 – 160 - LTE E-UTRA Operating Band 30
scell_state	• Scell state Values. • See NAS_LTE_CPHY_SCELL_STATE for more information.

TlvPresent	• Tlv Present.

8.875.2 Field Documentation

8.875.2.1 NAS_LTE_CPHY_CA_BW_NRB PhyCaAggScellInfo::dl_bw_value

8.875.2.2 int PhyCaAggScellInfo::freq

8.875.2.3 int PhyCaAggScellInfo::iLTEbandValue

8.875.2.4 int PhyCaAggScellInfo::pci

8.875.2.5 NAS_LTE_CPHY_SCELL_STATE PhyCaAggScellInfo::scell_state

8.875.2.6 BYTE PhyCaAggScellInfo::TlvPresent

8.876 PilotSetData Struct Reference

Data Fields

- BYTE NumPilots
- PilotSetParams * pPilotSetInfo

8.876.1 Detailed Description

This structure contains Pilot Set Data

Parameters

NumPilots(IN/OUT)	• Number of Pilot Sets • As input specifies number of sets of parameter pPilotSetInfo for which memory has been assigned • As output specifies the actual number of sets of parameter pPilotSetInfo returned by device
pPilotSetInfo	• Pilot Set Parameters • See PilotSetParams for more information.

note A buffer under sized error is returned if the number of sets of pPilotSetInfo returned by the device is greater than the value in NumPilots input parameter.

8.876.2 Field Documentation

8.876.2.1 BYTE PilotSetData::NumPilots

8.876.2.2 PilotSetParams* PilotSetData::pPilotSetInfo

8.877 PilotSetParams Struct Reference

Data Fields

- ULONG PilotType
- WORD PilotPN
- WORD PilotStrength

8.877.1 Detailed Description

This structure contains Pilot Set parameters

Parameters

PilotType	• 0x00 - NAS_HRPD_PILOT_CURR_ACT_PLT Current Active Pilot • 0x01 - NAS_HRPD_PILOT_NEIGHBOR_PLT Neighbor pilot information
PilotPN	• Pilot PN sequence offset index
PilotStrength	• Strength of the pilot (in dB)

8.877.2 Field Documentation

8.877.2.1 WORD PilotSetParams::PilotPN

8.877.2.2 WORD PilotSetParams::PilotStrength

8.877.2.3 ULONG PilotSetParams::PilotType

8.878 pktErrRate Struct Reference

Data Fields

- WORD multiplier
- WORD exponent

8.878.1 Detailed Description

This structure contains the IP flow packet error rate

Parameters

multiplier	Factor m in calculating packet error rate: E = m∗10∗∗(-p)
exponent	Factor p in calculating packet error rate (see above)

8.878.2 Field Documentation

8.878.2.1 WORD pktErrRate::exponent

8.878.2.2 WORD pktErrRate::multiplier

8.879 PlmnID Struct Reference

Data Fields

- WORD mcc
- WORD mnc
- BOOL pcsDigit
- BYTE TlvPresent

8.879.1 Detailed Description

This structure contains PLMN ID information

Parameters

mcc	• A 16-bit integer representation of MCC. Range: 0 to 999
mnc	• A 16-bit integer representation of MNC. Range: 0 to 999
pcsDigit	• This field is used to interpret the length of the corresponding MNC reported in the TLVs (in this table) with an mnc or mobile_network_code field. Values: – TRUE - MNC is a three-digit value; for example, a reported value of 90 corresponds to an MNC value of 090 – FALSE - MNC is a two-digit value; for example, a reported value of 90 corresponds to an MNC value of 90
TlvPresent	• Tlv Present or not

8.879.2 Field Documentation

8.879.2.1 WORD PlmnID::mcc

8.879.2.2 WORD PlmnID::mnc

8.879.2.3 BOOL PlmnID::pcsDigit

8.879.2.4 BYTE PlmnID::TlvPresent

8.880 PLMNNetworkName Struct Reference

Data Fields

- BYTE numInstance
- PLMNNetworkNameData PLMNNetName [255]

8.880.1 Detailed Description

This structure contains PLMN Network Name as defined in 3GPP TS 24.008 (Section 10.5.3.5a) from multiple sources.

Parameters

numInstance	• Number of sets of the elements.
PLMNNetName	• Refer PLMNNetworkNameData for details (Optional).

8.880.2 Field Documentation

8.880.2.1 BYTE PLMNNetworkName::numInstance

8.880.2.2 PLMNNetworkNameData PLMNNetworkName::PLMNNetName[255]

8.881 PLMNNetworkNameData Struct Reference

Data Fields

- BYTE codingScheme
- BYTE countryInitials
- BYTE longNameSpareBits
- BYTE shortNameSpareBits
- BYTE longNameLen
- BYTE longName [255]
- BYTE shortNameLen
- BYTE shortName [255]

8.881.1 Detailed Description

This structure contains PLMN Network Name Data from multiple sources.

Parameters

codingScheme	• Coding scheme: – 0 - CODING_SCHEME_CELL_BROADCAST_GSM - Cell broadcast data coding scheme, GSM default alphabet, language unspecified;defined in 3GPP TS 23.038. – 1 - CODING_SCHEME_UCS2 - UCS2 (16 bit);defined in ISO/IEC 10646
countryInitials	• Country's initials: – 0 - COUNTRY_INITIALS_DO_NOT_ADD - MS should not add the letters for the country's initials to the text string. – 1 - COUNTRY_INITIALS_ADD - MS should add the letters for the country's initials and a separator, e.g., a space, to the text string.

longNameSpare-Bits	• Long Name Spare Bits: – 1 - SPARE_BITS_8 - Bit 8 is spare and set to 0 in octet n – 2 - SPARE_BITS_7_TO_8 - Bits 7 and 8 are spare and set to 0 in octet n. – 3 - SPARE_BITS_6_TO_8 - Bits 6 to 8 (inclusive) are spare and set to 0 in octet n. – 4 - SPARE_BITS_5_TO_8 - Bits 5 to 8 (inclusive) are spare and set to 0 in octet n. – 5 - SPARE_BITS_4_TO_8 - Bits 4 to 8 (inclusive) are spare and set to 0 in octet n. – 6 - SPARE_BITS_3_TO_8 - Bits 3 to 8 (inclusive) are spare and set to 0 in octet n. – 7 - SPARE_BITS_2_TO_8 - Bits 2 to 8 (inclusive) are spare and set to 0 in octet n. – 0 - SPARE_BITS_UNKNOWN - Carries no information about the number of spare bits in octet n.
shortName-SpareBits	• Short Name Spare Bits: – 1 - SPARE_BITS_8 - Bit 8 is spare and set to 0 in octet n. – 2 - SPARE_BITS_7_TO_8 - Bits 7 and 8 are spare and set to 0 in octet n. – 3 - SPARE_BITS_6_TO_8 - Bits 6 to 8 (inclusive) are spare and set to 0 in octet n. – 4 - SPARE_BITS_5_TO_8 - Bits 5 to 8 (inclusive) are spare and set to 0 in octet n. – 5 - SPARE_BITS_4_TO_8 - Bits 4 to 8 (inclusive) are spare and set to 0 in octet n. – 6 - SPARE_BITS_3_TO_8 - Bits 3 to 8 (inclusive) are spare and set to 0 in octet n. – 7 - SPARE_BITS_2_TO_8 - Bits 2 to 8 (inclusive) are spare and set to 0 in octet n. – 0 - SPARE_BITS_UNKNOWN - Carries no information about the number of spare bits in octet n.
longNameLen	• It provides the length of long name.
longName	• Long name string in coding_scheme.
shortNameLen	• It provides the length of short name.
shortName	• Short name string in coding_scheme.

8.881.2 Field Documentation

8.881.2.1 BYTE PLMNNetworkNameData::codingScheme

8.881.2.2 BYTE PLMNNetworkNameData::countryInitials

8.881.2.3 BYTE PLMNNetworkNameData::longName[255]

8.881.2.4 BYTE PLMNNetworkNameData::longNameLen

8.881.2.5 BYTE PLMNNetworkNameData::longNameSpareBits

8.881.2.6 BYTE PLMNNetworkNameData::shortName[255]

8.881.2.7 BYTE PLMNNetworkNameData::shortNameLen

8.881.2.8 BYTE PLMNNetworkNameData::shortNameSpareBits

8.882 Port Struct Reference

Data Fields

- WORD port
- WORD range

8.882.1 Detailed Description

This structure contains the Port Filter

Parameters

port	port value of the filter
range	range specifies the number of ports to be included in the filter starting from port; filter will match if port in the IP packet lies between port and (port + range) Range value of 0 implies that only one value of the port is valid, as specified by the port

8.882.2 Field Documentation

8.882.2.1 WORD Port::port

8.882.2.2 WORD Port::range

8.883 PowerSaveModeConfigReq Struct Reference

Data Fields

- BYTE * pPsmEnableState
- ULONG * pActiveTimer
- ULONG * pPeriodicUpdateTimer

8.883.1 Detailed Description

This structure contains the Power Save Mode (PSM) configuration parameter.

Parameters

pPsmEnable-State	[Optional] • PSM Enable State • Values – 0 - PSM is not enabled – 1 - PSM is enabled
pActiveTimer	[Optional] • Active Timer • PSM active timer value (in seconds). • ActiveTimer encoding is the GPRS timer 2 encoding specified in Table 10.5.172 of 3GPP TS 24.008.

pPeriodicUpdateTimer	[Optional] • Periodic Update Timer • PSM periodic update timer value (in seconds) • Periodic Update Timer encoding is the GPRS timer 3 encoding specified in Table 10.5.163a of 3GPP TS 24.008.

8.883.2 Field Documentation

8.883.2.1 ULONG∗ PowerSaveModeConfigReq::pActiveTimer

8.883.2.2 ULONG∗ PowerSaveModeConfigReq::pPeriodicUpdateTimer

8.883.2.3 BYTE∗ PowerSaveModeConfigReq::pPsmEnableState

8.884 PowerSaveModeConfigResp Struct Reference

Data Fields

- PSMEnableStateTlv ∗ pPsmEnableState
- PSMDurationThresholdTlv ∗ pDurationThreshold
- PSMDurationDueToOOSTlv ∗ pDurationDueToOOS
- PSMRandomizationWindowTlv ∗ pRandomizationWindow
- PSMActiveTimerTlv ∗ pActiveTimer
- PSMPeriodicUpdateTimerTlv ∗ pPeriodicUpdateTimer
- PSMEarlyWakeupTimeTlv ∗ pEarlyWakeupTime

8.884.1 Detailed Description

This structure contains the Power Save Mode (PSM) configuration parameter.

Parameters

pPsmEnableState	[Optional] • See PSMEnableStateTlv for more information
pDurationThreshold	[Optional] • See PSMDurationThresholdTlv for more information
pDurationDueToOOS	[Optional] • See PSMDurationDueToOOSTlv for more information
pRandomizationWindow	[Optional] • See PSMRandomizationWindowTlv for more information
pActiveTimer	[Optional] • See PSMActiveTimerTlv for more information
pPeriodicUpdateTimer	[Optional] • See PSMPeriodicUpdateTimerTlv for more information
pEarlyWakeupTime	[Optional] • See PSMEarlyWakeupTimeTlv for more information

8.884.2 Field Documentation

8.884.2.1 PSMActiveTimerTlv* PowerSaveModeConfigResp::pActiveTimer

8.884.2.2 PSMDurationDueToOOSTlv* PowerSaveModeConfigResp::pDurationDueToOOS

8.884.2.3 PSMDurationThresholdTlv* PowerSaveModeConfigResp::pDurationThreshold

8.884.2.4 PSMEarlyWakeupTimeTlv* PowerSaveModeConfigResp::pEarlyWakeupTime

8.884.2.5 PSMPeriodicUpdateTimerTlv* PowerSaveModeConfigResp::pPeriodicUpdateTimer

8.884.2.6 PSMEnableStateTlv* PowerSaveModeConfigResp::pPsmEnableState

8.884.2.7 PSMRandomizationWindowTlv* PowerSaveModeConfigResp::pRandomizationWindow

8.885 precisionDilution_s Struct Reference

Data Fields

- ULONG PDOP
- ULONG HDOP
- ULONG VDOP

8.885.1 Detailed Description

This structure contains Dilution of precision associated with this position.

Parameters

PDOP	• Position dilution of precision. • Range - 1 (highest accuracy) to 50 (lowest accuracy) • PDOP = square root of (Square of HDOP + Square of VDOP2)
HDOP	• Horizontal dilution of precision. • Range - 1 (highest accuracy) to 50 (lowest accuracy)
VDOP	• Vertical dilution of precision. • Range- 1 (highest accuracy) to 50 (lowest accuracy)

8.885.2 Field Documentation

8.885.2.1 ULONG precisionDilution_s::HDOP

8.885.2.2 ULONG precisionDilution_s::PDOP

8.885.2.3 ULONG precisionDilution_s::VDOP

8.886 PrefImageList Struct Reference

Data Fields

- BYTE listSize
- struct ImageElement listEntries [2]

8.886.1 Detailed Description

This structure contains the Preference Image List information

Parameters

listSize	• The number of elements in the image list
listEntries	• Array of Image entries(Max array size 2) • See ImageElement

8.886.2 Field Documentation

8.886.2.1 struct ImageElement PrefImageList::listEntries[2]

8.886.2.2 BYTE PrefImageList::listSize

8.887 prefVoiceSO Struct Reference

Data Fields

- BYTE namID
- BYTE evrcCapability
- WORD homePageVoiceSO
- WORD homeOrigVoiceSO
- WORD roamOrigVoiceSO

8.887.1 Detailed Description

This structure contains information about the Preferred Voice Service Options.

Parameters

namID	• Index of the NAM(Number Assignment Module) to be configured. • Range 0 to 3. • Some modems support only 1 or 2 NAMs. • 0xFF,if not available.

evrcCapability	• EVRC capability. • Values: – 0x00 - Disable – 0x01 - Enable – 0xFF - Not Available
homePageVoice-SO	• Home page voice SO; most preferred CDMA SO to be requested from the network when receiving an incoming (MT) voice call within the home network. • Values: – 0x0000 - VOICE_SO_WILD - Any service option – 0x0001 - VOICE_SO_IS_96A - IS-96A – 0x0003 - VOICE_SO_EVRC - EVRC – 0x0011 - VOICE_SO_13K_IS733 - 13K_IS733 – 0x0038 - VOICE_SO_SELECTABLE_MODE_VOCODER - Selectable mode vocoder – 0x0044 - VOICE_SO_4GV_NARR0W_BAND - 4GV narrowband – 0x0046 - VOICE_SO_4GV_WIDE_BAND - 4GV wideband – 0x8000 - VOICE_SO_13K - 13K – 0x8001 - VOICE_SO_IS_96 - IS-96 – 0x8023 - VOICE_SO_WVRC - WVRC – 0xFFFF - Not Available
homeOrigVoice-SO	• Home origination voice SO; most preferred CDMA SO to be requested from the network when receiving an incoming (MT) voice call within the home network. • Values: – 0x0000 - VOICE_SO_WILD - Any service option – 0x0001 - VOICE_SO_IS_96A - IS-96A – 0x0003 - VOICE_SO_EVRC - EVRC – 0x0011 - VOICE_SO_13K_IS733 - 13K_IS733 – 0x0038 - VOICE_SO_SELECTABLE_MODE_VOCODER - Selectable mode vocoder – 0x0044 - VOICE_SO_4GV_NARR0W_BAND - 4GV narrowband – 0x0046 - VOICE_SO_4GV_WIDE_BAND - 4GV wideband – 0x8000 - VOICE_SO_13K - 13K – 0x8001 - VOICE_SO_IS_96 - IS-96 – 0x8023 - VOICE_SO_WVRC - WVRC – 0xFFFF - Not Available

roamOrigVoiceSO	• Roaming origination voice SO; most preferred CDMA SO to be requested from the network when receiving an incoming (MT) voice call within the home network. • Values: – 0x0000 - VOICE_SO_WILD - Any service option – 0x0001 - VOICE_SO_IS_96A - IS-96A – 0x0003 - VOICE_SO_EVRC - EVRC – 0x0011 - VOICE_SO_13K_IS733 - 13K_IS733 – 0x0038 - VOICE_SO_SELECTABLE_MODE_VOCODER - Selectable mode vocoder – 0x0044 - VOICE_SO_4GV_NARR0W_BAND - 4GV narrowband – 0x0046 - VOICE_SO_4GV_WIDE_BAND - 4GV wideband – 0x8000 - VOICE_SO_13K - 13K – 0x8001 - VOICE_SO_IS_96 - IS-96 – 0x8023 - VOICE_SO_WVRC - WVRC – 0xFFFF - Not Available

8.887.2 Field Documentation

8.887.2.1 BYTE prefVoiceSO::evrcCapability

8.887.2.2 WORD prefVoiceSO::homeOrigVoiceSO

8.887.2.3 WORD prefVoiceSO::homePageVoiceSO

8.887.2.4 BYTE prefVoiceSO::namID

8.887.2.5 WORD prefVoiceSO::roamOrigVoiceSO

8.888 Profile3GPP Struct Reference

Data Fields

- CHAR * pProfilename
- WORD * pProfilenameSize
- BYTE * pPDPtype
- BYTE * pPdpHdrCompType
- BYTE * pPdpDataCompType
- CHAR * pAPNName
- WORD * pAPNnameSize
- ULONG * pPriDNSIPv4AddPref
- ULONG * pSecDNSIPv4AddPref
- struct UMTSQoS * pUMTSReqQoS
- struct UMTSQoS * pUMTSMinQoS
- struct GPRSRequestedQoS * pGPRSRequestedQos
- struct GPRSRequestedQoS * pGPRSMinimumQoS
- CHAR * pUsername
- WORD * pUsernameSize
- CHAR * pPassword
- WORD * pPasswordSize
- BYTE * pAuthenticationPref
- ULONG * pIPv4AddrPref

- BYTE * pPcscfAddrUsingPCO
- BYTE * pPdpAccessConFlag
- BYTE * pPcscfAddrUsingDhcp
- BYTE * pImCnFlag
- struct TFTIDParams * pTFTID1Params
- struct TFTIDParams * pTFTID2Params
- BYTE * pPdpContext
- BYTE * pSecondaryFlag
- BYTE * pPrimaryID
- USHORT * pIPv6AddPref
- struct UMTSReqQoSSigInd * pUMTSReqQoSSigInd
- struct UMTSReqQoSSigInd * pUMTSMinQosSigInd
- USHORT * pPriDNSIPv6addpref
- USHORT * pSecDNSIPv6addpref
- BYTE * pAddrAllocPref
- struct QosClassID * pQosClassID
- BYTE * pAPNDisabledFlag
- ULONG * pPDNInactivTimeout
- BYTE * pAPNClass
- BYTE * pSupportEmergencyCalls

8.888.1 Detailed Description

This structure contains Input parameters of SLQSCreateProfile and SLQSModifyProfile and output parameters of SLQSGetProfileSettings

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

pProfileName	• One or more bytes describing the profile
pProfilenameSize;	• This parameter is an input parameter and should be initialised to the size of pProfileName field. Size of this parameter is 2 bytes.
pPDPType	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile – 0x00 - PDP-IP (IPv4) – 0x01 - PDP-PPP – 0x02 - PDP-IPV6 – 0x03 - PDP-IPV4V6
pPdpHdrCompType	• PDP header compression type – 0 - PDP header compression is OFF – 1 - Manufacturer preferred compression – 2 - PDP header compression based on RFC 1144 – 3 - PDP header compression based on RFC 25074 PDP header compression based on RFC 3095

pPdpDataCompType	• PDP data compression type – 0 - PDP data compression is OFF – 1 - Manufacturer preferred compression – 2 - V.42BIS data compression – 3 - V.44 data compression
pAPNName	• Access point name
pAPNnameSize;	• This parameter is an input parameter and should be initialised to the size of pAPNName field. Size of this parameter is 2 bytes.
pPriDNSIPv4AddPref	• Primary DNS IPv4 Address Preference
pSecDNSIPv4AddPref	• Secondary DNS IPv4 Address Preference
pUMTSReqQoS	• UMTS Requested QoS
pUMTSMinQoS	• UMTS Minimum QoS
pGPRSRequestedQoS	• GPRS Minimum QoS
pUsername	• User name
pUsernameSize;	• This parameter is an input parameter and should be initialised to the size of pUsername field. Size of this parameter is 2 bytes.
pPassword	• Password
pPasswordSize;	• This parameter is an input parameter and should be initialised to the size of pPassword field. Size of this parameter is 2 bytes.

pAuthentication-Pref	• Authentication Preference – Bit map that indicates the authentication algorithm preference * Bit 0 - PAP preference · 0 - PAP is never performed · 1 - PAP may be performed * Bit 1 - CHAP preference · 0 - CHAP is never performed · 1 - CHAP may be performed * If more than one bit is set, then the device decides which authentication procedure is performed while setting up the data session. For example, the device may have a policy to select the most secure authentication mechanism.
pIPv4AddrPref	• IPv4 Address Preference
pPcscfAddr-UsingPCO	• P-CSCF Address using PCO Flag – 1 - (TRUE) implies request PCSCF address using PCO – 0 - (FALSE) implies do not request By default, this value is 0
pPdpAccess-ConFlag	• PDP access control flag – 0 - PDP access control none – 1 - PDP access control reject – 2 - PDP access control permission
pPcscfAddr-UsingDhcp	• P-CSCF address using DHCP – 1 - (TRUE) implies Request PCSCF address using DHCP – 0 - (FALSE) implies do not request By default, value is 0
pImCnFlag	• IM CN flag – 1 - (TRUE) implies request IM CN flag for this profile – 0 - (FALSE) implies do not request IM CN flag for this profile
pTFTID1Params	• Traffic Flow Template
pTFTID2Params	• Traffic Flow Template
pPdpContext	• PDP context number
pSecondaryFlag	• PDP context secondary flag – 1 - (TRUE) implies this is secondary profile – 0 - (FALSE) implies this is not secondary profile

pPrimaryID	• PDP context primary ID • function SLQSGetProfileSettings() returns a default value 0xFF if this parameter is not returned by the device
pIPv6AddPref	• IPv6 address preference Preferred IPv6 address to be assigned to the TE; actual assigned address is negotiated with the network and may differ from this value; if not specified, the IPv6 address is obtained automatically from the network
pUMTSReqQoS-SigInd	• UMTS requested QoS with Signalling Indication flag
pUMTSMinQoS-SigInd	• UMTS minimum QoS with Signalling Indication flag
pPrimaryDNSI-Pv6addpref	• Primary DNS IPv6 address preference – The value may be used as a preference during negotiation with the network; if not specified, the wireless device will attempt to obtain the DNS address automatically from the network; the negotiated value is provided to the host via DHCP
pSecondaryDN-SIPv6addpref	• Secondary DNS IPv6 address preference
paddrAllocation-Pref	• DHCP/NAS preference – This enumerated value may be used to indicate the address allocation preference * 0 - NAS signaling is used for address allocation * 1 - DHCP is used for address allocation
pQosClassID	• 3GPP LTE QoS parameters
pAPNDisabled-Flag	• Optional 1 Byte Flag indicating if the APN is disabled/enabled • If set, the profile can not be used for making data calls • Any data call is failed locally • Values: – 0 - FALSE(default) – 1 - True • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().
pPDNInactiv-Timeout	• Optional 4 Bytes indicating the duration of inactivity timer in seconds • If the PDP context/PDN connection is inactive for this duration i.e. No data Tx/Rx occurs, the PDP context/PDN connection is disconnected • Default value of zero indicates infinite value • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().

pAPNClass	• Optional 1 Byte numeric identifier representing the APN in profile • Can be set and queried but is not used by the modem • This parameter is currently read only and can be read by using the function SLQSGetProfileSettings().
pSupportEmergencyCalls	• Optional 1 Byte Flag indicating if the emergency call support is disabled/enabled • If set, the profile can be used for making emergency calls • Values: – 0 - FALSE(default) – 1 - TRUE

8.888.2 Field Documentation

8.888.2.1 BYTE* Profile3GPP::pAddrAllocPref

8.888.2.2 BYTE* Profile3GPP::pAPNClass

8.888.2.3 BYTE* Profile3GPP::pAPNDisabledFlag

8.888.2.4 CHAR* Profile3GPP::pAPNName

8.888.2.5 WORD* Profile3GPP::pAPNnameSize

8.888.2.6 BYTE* Profile3GPP::pAuthenticationPref

8.888.2.7 struct GPRSRequestedQoS* Profile3GPP::pGPRSMinimumQoS

8.888.2.8 struct GPRSRequestedQoS* Profile3GPP::pGPRSRequestedQos

8.888.2.9 BYTE* Profile3GPP::pImCnFlag

8.888.2.10 ULONG* Profile3GPP::pIPv4AddrPref

8.888.2.11 USHORT* Profile3GPP::pIPv6AddPref

8.888.2.12 CHAR* Profile3GPP::pPassword

8.888.2.13 WORD* Profile3GPP::pPasswordSize

8.888.2.14 BYTE* Profile3GPP::pPcscfAddrUsingDhcp

8.888.2.15 BYTE* Profile3GPP::pPcscfAddrUsingPCO

8.888.2.16 ULONG* Profile3GPP::pPDNInactivTimeout

8.888.2.17 BYTE* Profile3GPP::pPdpAccessConFlag

8.888.2.18 BYTE* Profile3GPP::pPdpContext

8.888.2.19 BYTE* Profile3GPP::pPdpDataCompType

8.888.2.20 **BYTE*** Profile3GPP::pPdpHdrCompType

8.888.2.21 **BYTE*** Profile3GPP::pPDPtype

8.888.2.22 **ULONG*** Profile3GPP::pPriDNSIPv4AddPref

8.888.2.23 **USHORT*** Profile3GPP::pPriDNSIPv6addpref

8.888.2.24 **BYTE*** Profile3GPP::pPrimaryID

8.888.2.25 **CHAR*** Profile3GPP::pProfilename

8.888.2.26 **WORD*** Profile3GPP::pProfilenameSize

8.888.2.27 struct **QosClassID*** Profile3GPP::pQosClassID

8.888.2.28 **ULONG*** Profile3GPP::pSecDNSIPv4AddPref

8.888.2.29 **USHORT*** Profile3GPP::pSecDNSIPv6addpref

8.888.2.30 **BYTE*** Profile3GPP::pSecondaryFlag

8.888.2.31 **BYTE*** Profile3GPP::pSupportEmergencyCalls

8.888.2.32 struct **TFTIDParams*** Profile3GPP::pTFTID1Params

8.888.2.33 struct **TFTIDParams*** Profile3GPP::pTFTID2Params

8.888.2.34 struct **UMTSQoS*** Profile3GPP::pUMTSMinQoS

8.888.2.35 struct **UMTSReqQoSSigInd*** Profile3GPP::pUMTSMinQosSigInd

8.888.2.36 struct **UMTSQoS*** Profile3GPP::pUMTSReqQoS

8.888.2.37 struct **UMTSReqQoSSigInd*** Profile3GPP::pUMTSReqQoSSigInd

8.888.2.38 **CHAR*** Profile3GPP::pUsername

8.888.2.39 **WORD*** Profile3GPP::pUsernameSize

8.889 Profile3GPP2 Struct Reference

Data Fields

- BYTE * pNegoDnsSrvrPref
- ULONG * pPppSessCloseTimerDO
- ULONG * pPppSessCloseTimer1x
- BYTE * pAllowLinger
- USHORT * pLcpAckTimeout
- USHORT * pIpcpAckTimeout
- USHORT * pAuthTimeout
- BYTE * pLcpCreqRetryCount
- BYTE * pIpcpCreqRetryCount
- BYTE * pAuthRetryCount
- BYTE * pAuthProtocol

- CHAR * pUserId
- WORD * pUserIdSize
- CHAR * pAuthPassword
- WORD * pAuthPasswordSize
- BYTE * pDataRate
- ULONG * pAppType
- BYTE * pDataMode
- BYTE * pAppPriority
- CHAR * pApnString
- WORD * pApnStringSize
- BYTE * pPdnType
- BYTE * pIsPcscfAddressNedded
- ULONG * pPrimaryV4DnsAddress
- ULONG * pSecondaryV4DnsAddress
- USHORT * pPriV6DnsAddress
- USHORT * pSecV6DnsAddress
- BYTE * pRATType
- BYTE * pAPNEnabled3GPP2
- ULONG * pPDNInactivTimeout3GPP2
- BYTE * pAPNClass3GPP2

8.889.1 Detailed Description

This structure contains the 3GPP2 profile parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

pNegoDnsSrvr-Pref	• Negotiate DNS Server Preference – 1 - (TRUE)implies request DNS addresses from the PDSN – 0 - (FALSE)implies do not request DNS addresses from the PDSN – Default value is 1 (TRUE)
pPppSessClose-TimerDO	• PPP Session Close Timer for DO – Timer value (in seconds) on DO indicating how long the PPP Session should linger before closing down
pPppSessClose-Timer1x	• PPP Session Close Timer for 1X – Timer value (in seconds) on 1X indicating how long the PPP session should linger before closing down
pAllowLinger	• Allow/disallow lingering of interface – 1 -(TRUE) implies allow lingering – 0 -(FALSE) implies do not allow lingering
pLcpAckTimeout	• LCP ACK Timeout – Value of LCP ACK Timeout in milliseconds

pIpcpAck-Timeout	• IPCP ACK Timeout – Value of IPCP ACK Timeout in milliseconds
pAuthTimeout	• AUTH Timeout – Value of Authentication Timeout in milliseconds
pLcpCreqRetry-Count	• LCP Configuration Request Retry Count
pIpcpCreqRetry-Count	• IPCP Configuration Request Retry Count
pAuthRetry-Count	• Authentication Retry Count value
pAuthProtocol	• Authentication Protocol – 1 - PAP – 2 - CHAP – 3 - PAP or CHAP
pUserId	• User ID to be used during data network authentication • maximum length allowed is 127 bytes; • QMI_ERR_ARG_TOO_LONG will be returned if the storage on the wireless device is insufficient in size to hold the value.
pUserIdSize;	• This parameter is an input parameter and should be initialised to the size of pUserId field. Size of this parameter is 2 bytes.
pAuthPassword	• Password to be used during data network authentication; • maximum length allowed is 127 bytes • QMI_ERR_ARG_TOO_LONG will be returned if the storage on the wireless device is insufficient in size to hold the value.
pAuthPassword-Size;	• This parameter is an input parameter and should be initialised to the size of pAuthPassword field. Size of this parameter is 2 bytes.
pDataRate	• Data Rate Requested – 0 - Low (Low speed Service Options (SO15) only) – 1 - Medium (SO33 + low R-SCH) – 2 - High (SO33 + high R-SCH) – Default is 2

pAppType	• Application Type: – 0x00000001 - Default Application Type – 0x00000020 - LBS Application Type – 0x00000040 - Tethered Application Type – This parameter is not used while creating/modifying a profile
pDataMode	• Data Mode to use: – 0 - CDMA or HDR (Hybrid 1X/1xEV-DO) – 1 - CDMA Only (1X only) – 2 - HDR Only (1xEV-DO only) – Default is 0
pAppPriority	• Application Priority – Numerical 1 byte value defining the application priority; higher value implies higher priority – This parameter is not used while creating/modifying a profile
pApnString	• String representing the Access Point Name • maximum length allowed is 100 bytes • QMI_ERR_ARG_TOO_LONG will be returned if the APN name is too long.
pApnStringSize;	• This parameter is an input parameter and should be initialised to the size of pApnString field. Size of this parameter is 2 bytes.
pPdnType	• Packed Data Network Type Requested: – 0 - IPv4 PDN Type – 1 - IPv6 PDN Type – 2 - IPv4 or IPv6 PDN Type – 3 - Unspecified PDN Type (implying no preference)
pIsPcscf-AddressNedded	• This boolean value is used to control if PCSCF address is requested from PDSN – 1 -(TRUE) implies request for PCSCF value from the PDSN – 0 -(FALSE) implies do not request for PCSCF value from the PDSN
pPrimaryV4Dns-Address	• IPv4 Primary DNS address – The Primary IPv4 DNS address that can be statically assigned to the UE
pSecondaryV4-DnsAddress	• IPv4 Secondary DNS address – The Secondary IPv4 DNS address that can be statically assigned to the UE
pPriV6Dns-Address	• Primary IPv6 DNS address – The Primary IPv6 DNS address that can be statically assigned to the UE

pSecV6Dns-Address	• Secondary IPv6 DNS address – The Secondary IPv6 DNS address that can be statically assigned to the UE
pRATType	• Optional 1 Byte Flag indicating RAT Type • Values: – 1 - HRPD – 2 - EHRPD – 3 - HRPD_EHRPD • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().
pAPNEnabled3-GPP2	• Optional 1 Byte Flag indicating if the APN is disabled/enabled • If disabled, the profile can not be used for making data calls • Values: – 0 - Disabled – 1 - Enabled(default value) • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().
pPDNInactiv-Timeout3GPP2	• Optional 4 Bytes indicating the duration of inactivity timer in seconds • If the PDP context/PDN connection is inactive for this duration i.e. No data Tx/Rx occurs, the PDP context/PDN connection is disconnected • Default value of zero indicates infinite value • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().
pAPNClass3GP-P2	• Optional 1 Byte numeric identifier representing the APN in profile • Can be set and queried but is not used by the modem • This parameter is currently read only and can be read by using the function SLQSGetProfile-Settings().

8.889.2 Field Documentation

8.889.2.1 BYTE* Profile3GPP2::pAllowLinger

8.889.2.2 BYTE* Profile3GPP2::pAPNClass3GPP2

8.889.2.3 BYTE* Profile3GPP2::pAPNEnabled3GPP2

8.889.2.4 CHAR* Profile3GPP2::pApnString

8.889.2.5 WORD* Profile3GPP2::pApnStringSize

8.889.2.6 BYTE* Profile3GPP2::pAppPriority

8.889.2.7 ULONG* Profile3GPP2::pAppType

8.889.2.8 CHAR* Profile3GPP2::pAuthPassword

8.889.2.9 WORD* Profile3GPP2::pAuthPasswordSize

8.889.2.10 BYTE* Profile3GPP2::pAuthProtocol

8.889.2.11 BYTE* Profile3GPP2::pAuthRetryCount

8.889.2.12 USHORT* Profile3GPP2::pAuthTimeout

8.889.2.13 BYTE* Profile3GPP2::pDataMode

8.889.2.14 BYTE* Profile3GPP2::pDataRate

8.889.2.15 USHORT* Profile3GPP2::pIpcpAckTimeout

8.889.2.16 BYTE* Profile3GPP2::pIpcpCreqRetryCount

8.889.2.17 BYTE* Profile3GPP2::pIsPcscfAddressNedded

8.889.2.18 USHORT* Profile3GPP2::pLcpAckTimeout

8.889.2.19 BYTE* Profile3GPP2::pLcpCreqRetryCount

8.889.2.20 BYTE* Profile3GPP2::pNegoDnsSrvrPref

8.889.2.21 ULONG* Profile3GPP2::pPDNInactivTimeout3GPP2

8.889.2.22 BYTE* Profile3GPP2::pPdnType

8.889.2.23 ULONG* Profile3GPP2::pPppSessCloseTimer1x

8.889.2.24 ULONG* Profile3GPP2::pPppSessCloseTimerDO

8.889.2.25 ULONG* Profile3GPP2::pPrimaryV4DnsAddress

8.889.2.26 USHORT* Profile3GPP2::pPriV6DnsAddress

8.889.2.27 BYTE* Profile3GPP2::pRATType

8.889.2.28 ULONG* Profile3GPP2::pSecondaryV4DnsAddress

8.889.2.29 USHORT* Profile3GPP2::pSecV6DnsAddress

8.889.2.30 CHAR* Profile3GPP2::pUserId

8.889.2.31 WORD* Profile3GPP2::pUserIdSize

8.890 ProfileIdentifier Struct Reference

Data Fields

- BYTE profileType
- BYTE profileIndex

8.890.1 Detailed Description

This structure contains the Profile Identifier Information

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

profileType	• Identifies the type of profile 0x00 = 3GPP
profileIndex	• Index of profile whose settings were loaded prior to session parameter negotiation for the current call. If this TLV is not present, data call parameters are based on device default settings for each parameter

8.890.2 Field Documentation

8.890.2.1 BYTE ProfileIdentifier::profileIndex

8.890.2.2 BYTE ProfileIdentifier::profileType

8.891 protocolSubtypeElement Struct Reference

Data Fields

- WORD PhysicalLayer
- WORD ControlMac
- WORD AccessMac
- WORD ForwardMac
- WORD ReverseMac
- WORD KeyExchange
- WORD AuthProt
- WORD EncryptProt
- WORD SecProt
- WORD IdleState
- WORD MultDisc
- WORD VirtStream

8.891.1 Detailed Description

This structure contains Protocol Subtype Elements for Protocol Subtype List

Parameters

PhysicalLayer	• Specifies Physical Layer Protocol subtype
ControlMac	• Specifies Control Channel MAC Protocol subtype

AccessMac	• Specifies Access Channel MAC Protocol subtype
ForwardMac	• Specifies Forward Traffic Channel MAC Protocol subtype
ReverseMac	• Specifies Reverse Traffic Channel MAC Protocol subtype
KeyExchange	• Specifies Key exchange Protocol subtype
AuthProt	• Specifies Authentication Protocol subtype
EncryptProt	• Specifies Encryption Protocol subtype
SecProt	• Specifies Security Protocol subtype
IdleState	• Specifies Idle state Protocol subtype
MultDisc	• Specifies Generic multimode capability discovery Protocol subtype
VirtStream	• Specifies Generic Virtual Stream Protocol subtype

8.891.2 Field Documentation

8.891.2.1 WORD protocolSubtypeElement::AccessMac

8.891.2.2 WORD protocolSubtypeElement::AuthProt

8.891.2.3 WORD protocolSubtypeElement::ControlMac

8.891.2.4 WORD protocolSubtypeElement::EncryptProt

8.891.2.5 WORD protocolSubtypeElement::ForwardMac

8.891.2.6 WORD protocolSubtypeElement::IdleState

8.891.2.7 WORD protocolSubtypeElement::KeyExchange

8.891.2.8 WORD protocolSubtypeElement::MultDisc

8.891.2.9 WORD protocolSubtypeElement::PhysicalLayer

8.891.2.10 WORD protocolSubtypeElement::ReverseMac

8.891.2.11 WORD protocolSubtypeElement::SecProt

8.891.2.12 WORD protocolSubtypeElement::VirtStream

8.892 PSDetachReq Struct Reference

Data Fields

- BYTE * pDetachAction

8.892.1 Detailed Description

This structure contains information about the SLQSSwiPSDetach request parameters.

Parameters

pDetachAction[IN]	• Values – 2- Initiates an immediate packet domain detach.

8.892.2 Field Documentation

8.892.2.1 BYTE* PSDetachReq::pDetachAction

8.893 PSMActiveTimerTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG activeTimer

8.893.1 Detailed Description

This structure contains the parameters for Power Save Mode active timer.

Parameters

TlvPresent	• Tlv Present.
activeTimer	Active Timer • Power Save mode active timer value (in seconds).

8.893.2 Field Documentation

8.893.2.1 ULONG PSMActiveTimerTlv::activeTimer

8.893.2.2 BYTE PSMActiveTimerTlv::TlvPresent

8.894 PSMDurationDueToOOSTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG durationDueToOOS

8.894.1 Detailed Description

This structure contains the parameters for Power Save Mode Duration due to an outage.

Parameters

TlvPresent	• Tlv Present.
durationDueTo-OOS	Duration Due to OOS • Power Save mode duration due to an outage (in seconds).

8.894.2 Field Documentation

8.894.2.1 ULONG PSMDurationDueToOOSTlv::durationDueToOOS

8.894.2.2 BYTE PSMDurationDueToOOSTlv::TlvPresent

8.895 PSMDurationThresholdTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG durationThreshold

8.895.1 Detailed Description

This structure contains the parameters for Power Save Mode Duration Threshold.

Parameters

TlvPresent	• Tlv Present.
duration-Threshold	Duration Threshold • Minimum duration for the device to benefit by entering PSM (in seconds).

8.895.2 Field Documentation

8.895.2.1 ULONG PSMDurationThresholdTlv::durationThreshold

8.895.2.2 BYTE PSMDurationThresholdTlv::TlvPresent

8.896 PSMEarlyWakeupTimeTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG earlyWakeupTime

8.896.1 Detailed Description

This structure contains the parameters for Power Save Mode early wakeup time.

Parameters

TlvPresent	• Tlv Present.
earlyWakeup-Time	Early Wakeup Time • Power Save mode early wakeup time (in seconds) indicating how early the device should exit PSM to offset for bootup and acquisition delay.

8.896.2 Field Documentation

8.896.2.1 ULONG PSMEarlyWakeupTimeTlv::earlyWakeupTime

8.896.2.2 BYTE PSMEarlyWakeupTimeTlv::TlvPresent

8.897 PSMEnableStateTlv Struct Reference

Data Fields

- BYTE TlvPresent
- BYTE enableState

8.897.1 Detailed Description

This structure contains the parameters for Power Save Mode Enable State.

Parameters

TlvPresent	• Tlv Present.
enableState	Power Save Mode Enable State Values • 0 - PSM is not enabled • 1 - PSM is enabled

8.897.2 Field Documentation

8.897.2.1 BYTE PSMEnableStateTlv::enableState

8.897.2.2 BYTE PSMEnableStateTlv::TlvPresent

8.898 PSMPeriodicUpdateTimerTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG periodicUpdateTimer

8.898.1 Detailed Description

This structure contains the parameters for Power Save Mode periodic update timer.

Parameters

TlvPresent	• Tlv Present.
periodicUpdate-Timer	Periodic Update Timer • Power Save mode periodic update timer value (in seconds).

8.898.2 Field Documentation

8.898.2.1 ULONG PSMPeriodicUpdateTimerTlv::periodicUpdateTimer

8.898.2.2 BYTE PSMPeriodicUpdateTimerTlv::TlvPresent

8.899 PSMRandomizationWindowTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG randomizationWindow

8.899.1 Detailed Description

This structure contains the parameters for Power Save Mode wakeup randomization window.

Parameters

TlvPresent	• Tlv Present.
randomization-Window	Randomization Window • Power Save mode wakeup randomization window (in seconds)

8.899.2 Field Documentation

8.899.2.1 ULONG PSMRandomizationWindowTlv::randomizationWindow

8.899.2.2 BYTE PSMRandomizationWindowTlv::TlvPresent

8.900 qaQmi3Gpp2TimeZone Struct Reference

Data Fields

- BYTE leapSeconds
- BYTE localTimeOffset
- BYTE daylightSavings

8.900.1 Detailed Description

This structure contains the 3GPP2TimeZone parameters

Parameters

leapSeconds	• leap seconds - Number of leap seconds since the start of CDMA system time.
localTimeOffset	• Local Time Offset - Offset of system time in units of 30 minutes; the value in this field conveys as 8 bit 2's compliment number.
daylightSavings	• Day Light Savings Indicator – 0x00 - OFF (daylight savings not in effect) – 0x01 - ON (daylight savings in effect)

8.900.2 Field Documentation

8.900.2.1 BYTE qaQmi3Gpp2TimeZone::daylightSavings

8.900.2.2 BYTE qaQmi3Gpp2TimeZone::leapSeconds

8.900.2.3 BYTE qaQmi3Gpp2TimeZone::localTimeOffset

8.901 qaQmiInterfaceInfo Struct Reference

Data Fields

- BYTE qaQmiinstanceid
- eQaQMIService qaQmisvctype
- ULONG v4sessionId
- ULONG v6sessionId

8.901.1 Detailed Description

Structure used to store the service, interface and session information

Parameters

qaQmiinstanceid	• The interface instance ID – 0x00 - PDP instance ID 0 – 0x01 - PDP instance ID 1 – 0x02 - PDP instance ID 2
qaQmisvctype	• The service type information. See eQaQMIService for more information
v4sessionId	• IPv4 QMI client session handle
v6sessionId	• IPv6 QMI client session handle

8.901.2 Field Documentation

8.901.2.1 BYTE qaQmiInterfaceInfo::qaQmiinstanceid

8.901.2.2 eQaQMIService qaQmiInterfaceInfo::qaQmisvctype

8.901.2.3 ULONG qaQmiInterfaceInfo::v4sessionId

8.901.2.4 ULONG qaQmiInterfaceInfo::v6sessionId

8.902 qaQmiServingSystemParam Struct Reference

Data Fields

- servSystem ServingSystem
- BYTE roamIndicatorVal
- dataSrvCapabilities DataSrvCapabilities
- currentPLMN CurrentPLMN
- WORD SystemID
- WORD NetworkID
- WORD BasestationID
- ULONG BasestationLatitude
- ULONG BasestationLongitude
- roamIndList RoamingIndicatorList
- BYTE defaultRoamInd
- qaQmi3Gpp2TimeZone Gpp2TimeZone
- BYTE CDMA_P_Rev
- BYTE GppTimeZone
- BYTE GppNetworkDSTAdjustment
- WORD Lac
- ULONG CellID
- BYTE concSvcInfo
- BYTE PRLInd
- BYTE DTMInd
- detailSvcInfo DetailedSvcInfo
- CDMASysInfoExt CDMASystemInfoExt

- BYTE hdrPersonality
- WORD trackAreaCode
- callBarStatus CallBarStatus

8.902.1 Detailed Description

This structure contains the Serving System parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

ServingSystem	• Serving System • See servSystem for more information
roamIndicatorVal	• Optional parameter indicating Roaming Indicator value • Values: – 0x00 - Roaming – 0x01 - Home – 0x02 - Flashing – 0x03 and above - Operator defined values
DataSrv-Capabilities	• Optional parameter indicating Data services capability • See dataSrvCapabilities for more information
CurrentPLMN	• Optional parameter indicating Current PLMN • See currentPLMN for more information
SystemID	• Optional parameter indicating System ID
NetworkID	• Optional parameter indicating Network ID
BaseStationID	• Optional parameter indicating Base Station Identification Number
BaseStation-Latitude	• Optional parameter indicating Base station latitude in units of 0.25 sec,expressed as a two's complement signed number with positive numbers signifying North latitude
Basestation-Longitude	• Optional parameter indicating Base station longitude in units of 0.25 sec, expressed as a Two's complement signed number with positive numbers signifying East longitude
Roaming-IndicatorList	• Optional parameter indicating Roaming Indicator List • See roamIndList for more information

defaultRoamInd	• Optional parameter indicating Default Roaming Indicator • Values: – 0x00 - Roaming – 0x01 - Home
Gpp2TimeZone	• Optional parameter indicating 3GPP2 Time Zone • See qaQmi3Gpp2TimeZone for more information
CDMA_P_Rev	• Optional parameter indicating CDMA P_Rev in use
GppTimeZone	• Optional parameter indicating Offset from Universal time, i.e., difference between local time and Universal time, in increments of 15 min. (signed value).
GppNetworkDS-TAdjustment	• Optional parameter indicating 3GPP network daylight saving adjustment • Values: – 0x00 - No adjustment for Daylight Saving Time – 0x01 - 1 hr adjustment for Daylight Saving Time – 0x02 - 2 hr adjustment for Daylight Saving Time
Lac	• Optional parameter indicating 3GPP Location Area Code
CellID	• Optional parameter indicating 3GPP Cell ID
concSvcInfo	• Optional parameter indicating 3GPP2 concurrent service Info • Values: – 0x00 - Concurrent service not available – 0x01 - Concurrent service available
PRLInd	• Optional parameter indicating 3GPP2 PRL Indicator • Values: – 0x00 - System not in PRL – 0x01 - System is in PRL
DTMInd	• Optional parameter indicating Dual Transfer Mode Indication(GSM Only) • Values: – 0x00 - DTM not supported – 0x01 - DTM supported
DetailedSvcInfo	• Optional parameter indicating Detailed service information • See detailSvcInfo for more information

CDMASystem-InfoExt	• Optional parameter indicating CDMA System Info Ext • See CDMASysInfoExt for more information
hdrPersonality	• Optional parameter indicating HDR Personality Information • Values: – 0x00 - Unknown – 0x01 - HRPD – 0x02 - eHRPD
trackAreaCode	• Optional parameter indicating Tracking area code information for LTE
CallBarStatus	• Optional parameter indicating Call Barring Status • See callBarStatus for more information

8.902.2 Field Documentation

8.902.2.1 WORD qaQmiServingSystemParam::BasestationID

8.902.2.2 ULONG qaQmiServingSystemParam::BasestationLatitude

8.902.2.3 ULONG qaQmiServingSystemParam::BasestationLongitude

8.902.2.4 callBarStatus qaQmiServingSystemParam::CallBarStatus

8.902.2.5 BYTE qaQmiServingSystemParam::CDMA_P_Rev

8.902.2.6 CDMASysInfoExt qaQmiServingSystemParam::CDMASystemInfoExt

8.902.2.7 ULONG qaQmiServingSystemParam::CellID

8.902.2.8 BYTE qaQmiServingSystemParam::concSvcInfo

8.902.2.9 currentPLMN qaQmiServingSystemParam::CurrentPLMN

8.902.2.10 dataSrvCapabilities qaQmiServingSystemParam::DataSrvCapabilities

8.902.2.11 BYTE qaQmiServingSystemParam::defaultRoamInd

8.902.2.12 detailSvcInfo qaQmiServingSystemParam::DetailedSvcInfo

8.902.2.13 BYTE qaQmiServingSystemParam::DTMInd

8.902.2.14 qaQmi3Gpp2TimeZone qaQmiServingSystemParam::Gpp2TimeZone

8.902.2.15 BYTE qaQmiServingSystemParam::GppNetworkDSTAdjustment

8.902.2.16 BYTE qaQmiServingSystemParam::GppTimeZone

8.902.2.17 BYTE qaQmiServingSystemParam::hdrPersonality

8.902.2.18 WORD qaQmiServingSystemParam::Lac

8.902.2.19 WORD qaQmiServingSystemParam::NetworkID

8.902.2.20 BYTE qaQmiServingSystemParam::PRLInd

8.902.2.21 BYTE qaQmiServingSystemParam::roamIndicatorVal

8.902.2.22 roamIndList qaQmiServingSystemParam::RoamingIndicatorList

8.902.2.23 servSystem qaQmiServingSystemParam::ServingSystem

8.902.2.24 WORD qaQmiServingSystemParam::SystemID

8.902.2.25 WORD qaQmiServingSystemParam::trackAreaCode

8.903 QmiCbkCatEventStatusReportInd Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE event_Index
- struct CatCommonEventTlv CCETlv [11]

8.903.1 Field Documentation

8.903.1.1 struct CatCommonEventTlv QmiCbkCatEventStatusReportInd::CCETlv[11]

8.903.1.2 BYTE QmiCbkCatEventStatusReportInd::event_Index

8.903.1.3 struct qmTlvResult QmiCbkCatEventStatusReportInd::results

8.904 QmiCbkLocBestAvailPosInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG status
- ULONG * pXid
- ULONGLONG * pLatitude
- ULONGLONG * pLongitude
- ULONG * pHorUncCircular
- ULONG * pAltitudeWrtEllipsoid
- ULONG * pVertUnc
- ULONGLONG * pTimestampUtc
- ULONG * pTimeUnc
- ULONG * pHorUncEllipseSemiMinor
- ULONG * pHorUncEllipseSemiMajor
- ULONG * pHorUncEllipseOrientAzimuth
- BYTE * pHorCirConf
- BYTE * pHorEllpConf

- ULONG * pHorReliability
- ULONG * pSpeedHorizontal
- ULONG * pSpeedUnc
- ULONG * pAltitudeWrtMeanSeaLevel
- BYTE * pVertConfidence
- ULONG * pVertReliability
- ULONG * pSpeedVertical
- ULONG * pSpeedVerticalUnc
- ULONG * pHeading
- ULONG * pHeadingUnc
- ULONG * pMagneticDeviation
- ULONG * pTechnologyMask
- precisionDilution * pPrecisionDilution
- gpsTime * pGpsTime
- ULONG * pTimeSrc
- sensorDataUsage * pSensorDataUsage
- svUsedforFix * pSvUsedforFix

8.904.1 Detailed Description

This structure contains Best Available Position

Parameters

status	• Valid values: – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure
xid	Transaction ID that was specified in the Get Best Available Position request.
pLatitude	• Latitude (specified in WGS84 datum) • Type - Floating point • Units - Degrees • Range - -90.0 to 90.0 • Positive values indicate northern latitude • Negative values indicate southern latitude

pLongitude	• Longitude (specified in WGS84 datum) • Type - Floating point • Units - Degrees • Range - -180.0 to 180.0 • Positive values indicate eastern latitude • Negative values indicate western latitude
pHorUncCircular	• Horizontal position uncertainty. • Units - Meters
pAltitudeWrt-Ellipsoid	• Altitude With Respect to WGS84 Ellipsoid. • Units - Meters • Range -500 to 15883
pVertUnc	• Vertical uncertainty. • Units - Meters
pTimestampUtc	• UTC timestamp • Units - Milliseconds since Jan. 1, 1970
pTimeUnc	• Time uncertainty. • Units - Milliseconds
pHorUncEllipse-SemiMinor	• Semi-minor axis of horizontal elliptical uncertainty. • Units - Meters
pHorUncEllipse-SemiMajor	• Semi-major axis of horizontal elliptical uncertainty. • Units: Meters
pHorUncEllipse-OrientAzimuth	• Elliptical horizontal uncertainty azimuth of orientation. • Units - Decimal degrees • Range - 0 to 180
pHorCirConf	• Horizontal circular uncertainty confidence • Units: Precent • Range: 0 to 99
pHorEllpConf	• Horizontal elliptical uncertainty confidence • Units: Precent • Range: 0 to 99

pHorReliability	• Values – 0 - Location reliability is not set. – 1 - Location reliability is very low; use it at your own risk – 2 - Location reliability is low; little or no cross-checking is possible. – 3 - Location reliability is medium; limited cross-check passed – 4 - Location reliability is high; strong cross-check passed
pSpeed-Horizontal	• Horizontal speed. • Units - Meters/second
pSpeedUnc	• 3-D Speed uncertainty. • Units - Meters/second.
pAltitudeWrt-MeanSeaLevel	• Altitude With Respect to Sea Level. • Units - Meters
pVertConfidence	• Vertical uncertainty confidence. • Units - Percentage • Range 0 to 99
pVertReliability	• Values – 0 - Location reliability is not set. – 1 - Location reliability is very low; use it at your own risk. – 2 - Location reliability is low; little or no cross-checking is possible – 3 - Location reliability is medium; limited cross-check passed – 4 - Location reliability is high; strong cross-check passed
pSpeedVertical	• Vertical speed. • Units - Meters/second
pSpeedVertical-Unc	• Veritical speed • Units: Meters/second
pHeading	• Heading. • Units - Degree • Range 0 to 359.999
pHeadingUnc	• Heading uncertainty. • Units - Degree • Range 0 to 359.999

pMagnetic-Deviation	• Difference between the bearing to true north and the bearing shown on a magnetic compass. The deviation is positive when the magnetic north is east of true north.
pTechnology-Mask	• Values – 0x00000001 - Satellites were used to generate the fix – 0x00000002 - Cell towers were used to generate the fix – 0x00000004 - Wi-Fi access points were used to generate the fix – 0x00000008 - Sensors were used to generate the fix – 0x00000010 - Reference Location was used to generate the fix – 0x00000020 - Coarse position injected into the location engine was used to generate the fix – 0x00000040 - AFLT was used to generate the fix – 0x00000080 - GNSS and network-provided measurements were used to generate the fix
-pPrecision-Dilution	• See precisionDilution for more information
-pGpsTime	• See gpsTime for more information
pTimeSrc	• Values – 0 - Invalid time. – 1 - Time is set by the 1X system. – 2 - Time is set by WCDMA/GSM time tagging. – 3 - Time is set by an external injection. – 4 - Time is set after decoding over-the-air GPS navigation data from one GPS satellite. – 5 - Time is set after decoding over-the-air GPS navigation data from multiple satellites. – 6 - Both time of the week and the GPS week number are known. – 7 - Time is set by the position engine after the fix is obtained – 8 - Time is set by the position engine after performing SFT, this is done when the clock time uncertainty is large. – 9 - Time is set after decoding GLO satellites. – 10- Time is set after transforming the GPS to GLO time – 11- Time is set by the sleep time tag provided by the WCDMA network. – 12- Time is set by the sleep time tag provided by the GSM network – 13- Source of the time is unknown – 14- Time is derived from the system clock (better known as the slow clock); GNSS time is maintained irrespective of the GNSS receiver state – 15- Time is set after decoding QZSS satellites. – 16- Time is set after decoding BDS satellites.
-pSensorData-Usage	• See sensorDataUsage for more information
-pSvUsedforFix	• See svUsedforFix for more information

8.904.2 Field Documentation

8.904.2.1 ULONG* QmiCbkLocBestAvailPosInd::pAltitudeWrtEllipsoid

8.904.2.2 ULONG* QmiCbkLocBestAvailPosInd::pAltitudeWrtMeanSeaLevel

8.904.2.3 gpsTime* QmiCbkLocBestAvailPosInd::pGpsTime

8.904.2.4 ULONG* QmiCbkLocBestAvailPosInd::pHeading

8.904.2.5 ULONG* QmiCbkLocBestAvailPosInd::pHeadingUnc

8.904.2.6 BYTE* QmiCbkLocBestAvailPosInd::pHorCirConf

8.904.2.7 BYTE* QmiCbkLocBestAvailPosInd::pHorEllpConf

8.904.2.8 ULONG* QmiCbkLocBestAvailPosInd::pHorReliability

8.904.2.9 ULONG* QmiCbkLocBestAvailPosInd::pHorUncCircular

8.904.2.10 ULONG* QmiCbkLocBestAvailPosInd::pHorUncEllipseOrientAzimuth

8.904.2.11 ULONG* QmiCbkLocBestAvailPosInd::pHorUncEllipseSemiMajor

8.904.2.12 ULONG* QmiCbkLocBestAvailPosInd::pHorUncEllipseSemiMinor

8.904.2.13 ULONGLONG* QmiCbkLocBestAvailPosInd::pLatitude

8.904.2.14 ULONGLONG* QmiCbkLocBestAvailPosInd::pLongitude

8.904.2.15 ULONG* QmiCbkLocBestAvailPosInd::pMagneticDeviation

8.904.2.16 precisionDilution* QmiCbkLocBestAvailPosInd::pPrecisionDilution

8.904.2.17 sensorDataUsage* QmiCbkLocBestAvailPosInd::pSensorDataUsage

8.904.2.18 ULONG* QmiCbkLocBestAvailPosInd::pSpeedHorizontal

8.904.2.19 ULONG* QmiCbkLocBestAvailPosInd::pSpeedUnc

8.904.2.20 ULONG* QmiCbkLocBestAvailPosInd::pSpeedVertical

8.904.2.21 ULONG* QmiCbkLocBestAvailPosInd::pSpeedVerticalUnc

8.904.2.22 svUsedforFix* QmiCbkLocBestAvailPosInd::pSvUsedforFix

8.904.2.23 ULONG* QmiCbkLocBestAvailPosInd::pTechnologyMask

8.904.2.24 ULONG* QmiCbkLocBestAvailPosInd::pTimeSrc

8.904.2.25 ULONGLONG* QmiCbkLocBestAvailPosInd::pTimestampUtc

8.904.2.26 ULONG* QmiCbkLocBestAvailPosInd::pTimeUnc

8.904.2.27 BYTE* QmiCbkLocBestAvailPosInd::pVertConfidence

8.904.2.28 ULONG* QmiCbkLocBestAvailPosInd::pVertReliability

8.904.2.29 ULONG* QmiCbkLocBestAvailPosInd::pVertUnc

8.904.2.30 ULONG* QmiCbkLocBestAvailPosInd::pXid

8.904.2.31 struct qmTlvResult QmiCbkLocBestAvailPosInd::results

8.904.2.32 ULONG QmiCbkLocBestAvailPosInd::status

8.905 QmiCbkLocCradleMountInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG cradleMountConfigStatus

8.905.1 Detailed Description

This structure contains LOC Cradle Mount Config Status

Parameters

cradleMount-ConfigStatus	• Values – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure

8.905.2 Field Documentation

8.905.2.1 ULONG QmiCbkLocCradleMountInd::cradleMountConfigStatus

8.905.2.2 struct qmTlvResult QmiCbkLocCradleMountInd::results

8.906 QmiCbkLocEngineStateInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG engineState

8.906.1 Detailed Description

This structure contains LOC Engine State field.

Parameters

engineState	• Location engine state. • Valid values – 1 - Location engine is on – 2 - Loction engine is off

8.906.2 Field Documentation

8.906.2.1 ULONG QmiCbkLocEngineStateInd::engineState

8.906.2.2 struct qmTlvResult QmiCbkLocEngineStateInd::results

8.907 QmiCbkLocEventNMEAInd Struct Reference

Data Fields

- struct qmTlvResult results
- CHAR ∗ pNMEAData

8.907.1 Detailed Description

NMEA Event Notification callback.

Parameters

pNMEAData	• NMEA string • Type - NULLterminated string • Maximum string length (including NULL terminator) - 201

8.907.2 Field Documentation

8.907.2.1 CHAR∗ QmiCbkLocEventNMEAInd::pNMEAData

8.907.2.2 struct qmTlvResult QmiCbkLocEventNMEAInd::results

8.908 QmiCbkLocEventTimeSyncInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG timeSyncRefCounter

8.908.1 Detailed Description

This structure contains LOC Event Time Sync Reference COunter

Parameters

timeSyncRef-Counter	• Sent by the location engine when it needs to synchronize location engine and control point (sensor processor) times.

8.908.2 Field Documentation

8.908.2.1 struct qmTlvResult QmiCbkLocEventTimeSyncInd::results

8.908.2.2 ULONG QmiCbkLocEventTimeSyncInd::timeSyncRefCounter

8.909 QmiCbkLocGetOpModeInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG status
- ULONG ∗ pMode

8.909.1 Detailed Description

This structure contains LOC Get Operating Mode field.

Parameters

Status	• Status of the Get Server request. • Valid values – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure

Operation	Mode • Valid values – eQMI_LOC_OPER_MODE_DEFAULT (1) - Use the default engine mode – eQMI_LOC_OPER_MODE_MSB (2)- Use the MS-based mode – eQMI_LOC_OPER_MODE_MSA (3)- Use the MS-assisted mode – eQMI_LOC_OPER_MODE_STANDALONE (4) - Use Standalone mode – eQMI_LOC_OPER_MODE_CELL_ID (5) - Use cell ID; this mode is only valid for GSM/UMTS networks – eQMI_LOC_OPER_MODE_WWAN (6) - Use WWAN measurements to calculate the position; if this mode is set,AFLT will be used for 1X networks and OTDOA will be used for LTE networks

8.909.2 Field Documentation

8.909.2.1 ULONG∗ QmiCbkLocGetOpModeInd::pMode

8.909.2.2 struct qmTlvResult QmiCbkLocGetOpModeInd::results

8.909.2.3 ULONG QmiCbkLocGetOpModeInd::status

8.910 QmiCbkLocGetServerInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG serverStatus
- ULONG serverType
- IPv4Info ∗ pIPv4AddrInfo
- IPv6Info ∗ pIPv6AddrInfo
- urlAddr ∗ pURL

8.910.1 Detailed Description

This structure contains LOC Get Server field.

Parameters

serverStatus	• Status of the Get Server request. • Valid values – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure
serverType	• Type of server. • Valid values – eQMI_LOC_SERVER_TYPE_CDMA_PDE (1) - Server type is CDMA PDE – eQMI_LOC_SERVER_TYPE_CDMA_MPC (2) - Server type is CDMA MPC – eQMI_LOC_SERVER_TYPE_UMTS_SLP (3) - Server type is UMTS SLP – eQMI_LOC_SERVER_TYPE_CUSTOM_PDE (4) - Server type is custom PDE
pIPv4AddrInfo	• See IPv4Info for more information.
pIPv6AddrInfo	• See IPv6Info for more information.
pURL	• See urlAddr for more information.

8.910.2 Field Documentation

8.910.2.1 IPv4Info* QmiCbkLocGetServerInd::pIPv4AddrInfo

8.910.2.2 IPv6Info* QmiCbkLocGetServerInd::pIPv6AddrInfo

8.910.2.3 urlAddr* QmiCbkLocGetServerInd::pURL

8.910.2.4 struct qmTlvResult QmiCbkLocGetServerInd::results

8.910.2.5 ULONG QmiCbkLocGetServerInd::serverStatus

8.910.2.6 ULONG QmiCbkLocGetServerInd::serverType

8.911 QmiCbkLocInjectPositionInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG status

8.911.1 Detailed Description

Contain the parameters passed for SetLocInjectPositionCallback by the device.

Parameters

status	• UTC Position Injection Status • Valid values: – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure

Note

None

8.911.2 Field Documentation

8.911.2.1 struct qmTlvResult QmiCbkLocInjectPositionInd::results

8.911.2.2 ULONG QmiCbkLocInjectPositionInd::status

8.912 QmiCbkLocInjectSensorDataInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG injectSensorDataStatus
- ULONG * pOpaqueIdentifier
- BYTE * pAccelSamplesAccepted
- BYTE * pGyroSamplesAccepted

- BYTE * pAccelTempSamplesAccepted
- BYTE * pGyroTempSamplesAccepted

8.912.1 Detailed Description

This structure contains LOC Inject Sensor Data

Parameters

injectSensorDataStatus	• Values – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure
pOpaqueIdentifier	• Sent in by the client echoed so the client can relate the indication to the request.
pAccelSamplesAccepted	• Lets the client know how many 3-axis accelerometer samples were accepted. • This field is present only if the accelerometer samples were sent in the request.
pGyroSamplesAccepted	• Lets the client know how many 3-axis gyroscope samples were accepted. • This field is present only if the gyroscope samples were sent in the request.
pAccelTempSamplesAccepted	• Lets the client know how many accelerometer temperature samples were accepted. • This field is present only if the accelerometer temperature samples were sent in the request.
pGyroTempSamplesAccepted	• Lets the client know how many gyroscope temperature samples were accepted. • This field is present only if the gyroscope temperature samples were sent in the request.

8.912.2 Field Documentation

8.912.2.1 ULONG QmiCbkLocInjectSensorDataInd::injectSensorDataStatus

8.912.2.2 BYTE* QmiCbkLocInjectSensorDataInd::pAccelSamplesAccepted

8.912.2.3 BYTE* QmiCbkLocInjectSensorDataInd::pAccelTempSamplesAccepted

8.912.2.4 BYTE* QmiCbkLocInjectSensorDataInd::pGyroSamplesAccepted

8.912.2.5 BYTE* QmiCbkLocInjectSensorDataInd::pGyroTempSamplesAccepted

8.912.2.6 ULONG* QmiCbkLocInjectSensorDataInd::pOpaqueIdentifier

8.912.2.7 struct qmTlvResult QmiCbkLocInjectSensorDataInd::results

8.913 QmiCbkLocInjectTimeInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG injectTimeSyncStatus

8.913.1 Detailed Description

This structure contains LOC Inject Time Sync Data Status

Parameters

injectTimeSyncStatus	• Values – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure

8.913.2 Field Documentation

8.913.2.1 ULONG QmiCbkLocInjectTimeInd::injectTimeSyncStatus

8.913.2.2 struct qmTlvResult QmiCbkLocInjectTimeInd::results

8.914 QmiCbkLocInjectUTCTimeInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG status

8.914.1 Detailed Description

Contain the parameters passed for SetLocInjectUTCTimeCallback by the device.

Parameters

status	• Status of the UTC Time Injection request • Valid values: – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out

Note

None

8.914.2 Field Documentation

8.914.2.1 struct qmTlvResult QmiCbkLocInjectUTCTimeInd::results

8.914.2.2 ULONG QmiCbkLocInjectUTCTimeInd::status

8.915 QmiCbkLocOpModeInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG mode

8.915.1 Detailed Description

Operation mode callback function.

Parameters

mode[OUT]	• Status of the Set Operation Mode request. • Valid values – eQMI_LOC_SUCCESS - 0 - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE - 1 - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED - 2 - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER -3 - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY - 4 - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE - 5 -Request failed because the phone is offline – eQMI_LOC_TIMEOUT - 6 - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED -7 - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY - 8 - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED - 9 - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE - 10 - Location service failed because of an XTRA version-based file format check failure

8.915.2 Field Documentation

8.915.2.1 ULONG QmiCbkLocOpModeInd::mode

8.915.2.2 struct qmTlvResult QmiCbkLocOpModeInd::results

8.916 QmiCbkLocPositionReportInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG sessionStatus
- BYTE sessionId
- ULONGLONG * pLatitude
- ULONGLONG * pLongitude
- ULONG * pHorUncCircular
- ULONG * pHorUncEllipseSemiMinor
- ULONG * pHorUncEllipseSemiMajor
- ULONG * pHorUncEllipseOrientAzimuth
- BYTE * pHorConfidence
- ULONG * pHorReliability
- ULONG * pSpeedHorizontal
- ULONG * pSpeedUnc
- ULONG * pAltitudeWrtEllipsoid
- ULONG * pAltitudeWrtMeanSeaLevel
- ULONG * pVertUnc
- BYTE * pVertConfidence
- ULONG * pVertReliability
- ULONG * pSpeedVertical
- ULONG * pHeading
- ULONG * pHeadingUnc

- ULONG * pMagneticDeviation
- ULONG * pTechnologyMask
- precisionDilution * pPrecisionDilution
- ULONGLONG * pTimestampUtc
- BYTE * pLeapSeconds
- gpsTime * pGpsTime
- ULONG * pTimeUnc
- ULONG * pTimeSrc
- sensorDataUsage * pSensorDataUsage
- ULONG * pFixId
- svUsedforFix * pSvUsedforFix
- BYTE * pAltitudeAssumed

8.916.1 Detailed Description

This structure contains Event Position Report

Parameters

sessionStatus	• Values – 0 - Session was successful – 1 - Session is still in progress; further position reports will be generated until either the fix criteria specified by the client are met or the client response timeout occurs. – 2 - Session failed.. – 3 - Fix request failed because the session timed out. – 4 - Fix request failed because the session was ended by the user. – 5 - Fix request failed due to bad parameters in the request. – 6 - Fix request failed because the phone is offline. – 7 - Fix request failed because the engine is locked
sessionId	• ID of the session that was specified in the Start request • Range - 0 to 255
pLatitude	• Latitude (specified in WGS84 datum) • Type - Floating point • Units - Degrees • Range - -90.0 to 90.0 • Positive values indicate northern latitude • Negative values indicate southern latitude
pLongitude	• Longitude (specified in WGS84 datum) • Type - Floating point • Units - Degrees • Range - -180.0 to 180.0 • Positive values indicate eastern latitude • Negative values indicate western latitude

pHorUncCircular	• Horizontal position uncertainty. • Units - Meters
pHorUncEllipse-SemiMinor	• Semi-minor axis of horizontal elliptical uncertainty. • Units - Meters
pHorUncEllipse-SemiMajor	• Semi-major axis of horizontal elliptical uncertainty. • Units: Meters
pHorUncEllipse-OrientAzimuth	• Elliptical horizontal uncertainty azimuth of orientation. • Units - Decimal degrees • Range - 0 to 180
pHorConfidence	• Horizontal uncertainty confidence. • If both elliptical and horizontal uncertainties are specified in this message, the confidence corresponds to the elliptical uncertainty. • Units - Percentage • Range 0-99
pHorReliability	• Values – 0 - Location reliability is not set. – 1 - Location reliability is very low; use it at your own risk – 2 - Location reliability is low; little or no cross-checking is possible. – 3 - Location reliability is medium; limited cross-check passed – 4 - Location reliability is high; strong cross-check passed
pSpeed-Horizontal	• Horizontal speed. • Units - Meters/second
pSpeedUnc	• 3-D Speed uncertainty. • Units - Meters/second.
pAltitudeWrt-Ellipsoid	• Altitude With Respect to WGS84 Ellipsoid. • Units - Meters • Range -500 to 15883
pAltitudeWrt-MeanSeaLevel	• Altitude With Respect to Sea Level. • Units - Meters

pVertUnc	• Vertical uncertainty. • Units - Meters
pVertConfidence	• Vertical uncertainty confidence. • Units - Percentage • Range 0 to 99
pVertReliability	• Values – 0 - Location reliability is not set. – 1 - Location reliability is very low; use it at your own risk. – 2 - Location reliability is low; little or no cross-checking is possible – 3 - Location reliability is medium; limited cross-check passed – 4 - Location reliability is high; strong cross-check passed
pSpeedVertical	• Vertical speed. • Units - Meters/second
pHeading	• Heading. • Units - Degree • Range 0 to 359.999
pHeadingUnc	• Heading uncertainty. • Units - Degree • Range 0 to 359.999
pMagnetic-Deviation	• Difference between the bearing to true north and the bearing shown on a magnetic compass. The deviation is positive when the magnetic north is east of true north.
pTechnology-Mask	• Values – 0x00000001 - Satellites were used to generate the fix – 0x00000002 - Cell towers were used to generate the fix – 0x00000004 - Wi-Fi access points were used to generate the fix – 0x00000008 - Sensors were used to generate the fix – 0x00000010 - Reference Location was used to generate the fix – 0x00000020 - Coarse position injected into the location engine was used to generate the fix – 0x00000040 - AFLT was used to generate the fix – 0x00000080 - GNSS and network-provided measurements were used to generate the fix
-pPrecision-Dilution	• See precisionDilution for more information

pTimestampUtc	• UTC timestamp • Units - Milliseconds since Jan. 1, 1970
pLeapSeconds	• Leap second information. If leapSeconds is not available, timestampUtc is calculated based on a hard-coded value for leap seconds. • Units - Seconds
-pGpsTime	• See gpsTime for more information
pTimeUnc	• Time uncertainty. • Units - Milliseconds
pTimeSrc	• Values – 0 - Invalid time. – 1 - Time is set by the 1X system. – 2 - Time is set by WCDMA/GSM time tagging. – 3 - Time is set by an external injection. – 4 - Time is set after decoding over-the-air GPS navigation data from one GPS satellite. – 5 - Time is set after decoding over-the-air GPS navigation data from multiple satellites. – 6 - Both time of the week and the GPS week number are known. – 7 - Time is set by the position engine after the fix is obtained – 8 - Time is set by the position engine after performing SFT, this is done when the clock time uncertainty is large. – 9 - Time is set after decoding GLO satellites. – 10- Time is set after transforming the GPS to GLO time – 11- Time is set by the sleep time tag provided by the WCDMA network. – 12- Time is set by the sleep time tag provided by the GSM network – 13- Source of the time is unknown – 14- Time is derived from the system clock (better known as the slow clock); GNSS time is maintained irrespective of the GNSS receiver state – 15- Time is set after decoding QZSS satellites. – 16- Time is set after decoding BDS satellites.
-pSensorData-Usage	• See sensorDataUsage for more information
pFixId	• Fix count for the session. Starts with 0 and increments by one for each successive position report for a particular session.
-pSvUsedforFix	• See svUsedforFix for more information
pAltitude-Assumed	• Indicates whether altitude is assumed or calculated.

- Value
  - 0x00 - Altitude is calculated
  - 0x01 - Altitude is assumed

8.916.2 Field Documentation

8.916.2.1 BYTE* QmiCbkLocPositionReportInd::pAltitudeAssumed

8.916.2.2 ULONG* QmiCbkLocPositionReportInd::pAltitudeWrtEllipsoid

8.916.2.3 ULONG* QmiCbkLocPositionReportInd::pAltitudeWrtMeanSeaLevel

8.916.2.4 ULONG* QmiCbkLocPositionReportInd::pFixId

8.916.2.5 gpsTime* QmiCbkLocPositionReportInd::pGpsTime

8.916.2.6 ULONG* QmiCbkLocPositionReportInd::pHeading

8.916.2.7 ULONG* QmiCbkLocPositionReportInd::pHeadingUnc

8.916.2.8 BYTE* QmiCbkLocPositionReportInd::pHorConfidence

8.916.2.9 ULONG* QmiCbkLocPositionReportInd::pHorReliability

8.916.2.10 ULONG* QmiCbkLocPositionReportInd::pHorUncCircular

8.916.2.11 ULONG* QmiCbkLocPositionReportInd::pHorUncEllipseOrientAzimuth

8.916.2.12 ULONG* QmiCbkLocPositionReportInd::pHorUncEllipseSemiMajor

8.916.2.13 ULONG* QmiCbkLocPositionReportInd::pHorUncEllipseSemiMinor

8.916.2.14 ULONGLONG* QmiCbkLocPositionReportInd::pLatitude

8.916.2.15 BYTE* QmiCbkLocPositionReportInd::pLeapSeconds

8.916.2.16 ULONGLONG* QmiCbkLocPositionReportInd::pLongitude

8.916.2.17 ULONG* QmiCbkLocPositionReportInd::pMagneticDeviation

8.916.2.18 precisionDilution* QmiCbkLocPositionReportInd::pPrecisionDilution

8.916.2.19 sensorDataUsage* QmiCbkLocPositionReportInd::pSensorDataUsage

8.916.2.20 ULONG* QmiCbkLocPositionReportInd::pSpeedHorizontal

8.916.2.21 ULONG* QmiCbkLocPositionReportInd::pSpeedUnc

8.916.2.22 ULONG* QmiCbkLocPositionReportInd::pSpeedVertical

8.916.2.23 svUsedforFix* QmiCbkLocPositionReportInd::pSvUsedforFix

8.916.2.24 ULONG* QmiCbkLocPositionReportInd::pTechnologyMask

8.916.2.25 ULONG* QmiCbkLocPositionReportInd::pTimeSrc

8.916.2.26 ULONGLONG* QmiCbkLocPositionReportInd::pTimestampUtc

8.916.2.27 ULONG* QmiCbkLocPositionReportInd::pTimeUnc

8.916.2.28 BYTE* QmiCbkLocPositionReportInd::pVertConfidence

8.916.2.29 ULONG* QmiCbkLocPositionReportInd::pVertReliability

8.916.2.30 ULONG* QmiCbkLocPositionReportInd::pVertUnc

8.916.2.31 struct qmTlvResult QmiCbkLocPositionReportInd::results

8.916.2.32 BYTE QmiCbkLocPositionReportInd::sessionId

8.916.2.33 ULONG QmiCbkLocPositionReportInd::sessionStatus

8.917 QmiCbkLocSensorStreamingInd Struct Reference

Data Fields

- struct qmTlvResult results
- accelAcceptReady * pAccelAcceptReady
- gyroAcceptReady * pGyroAcceptReady
- accelTempAcceptReady * pAccelTempAcceptReady
- gyroTempAcceptReady * pGyroTempAcceptReady

8.917.1 Detailed Description

This structure contains LOC Event Sensor Streaming Ready Status

Parameters

-pAccelAccept-Ready	• See accelAcceptReady for more information
-pGyroAccept-Ready	• See gyroAcceptReady for more information
-pAccelTemp-AcceptReady	• See accelTempAcceptReady for more information
-pGyroTemp-AcceptReady	• See gyroTempAcceptReady for more information

8.917.2 Field Documentation

8.917.2.1 accelAcceptReady* QmiCbkLocSensorStreamingInd::pAccelAcceptReady

8.917.2.2 accelTempAcceptReady* QmiCbkLocSensorStreamingInd::pAccelTempAcceptReady

8.917.2.3 gyroAcceptReady* QmiCbkLocSensorStreamingInd::pGyroAcceptReady

8.917.2.4 gyroTempAcceptReady* QmiCbkLocSensorStreamingInd::pGyroTempAcceptReady

8.917.2.5 struct qmTlvResult QmiCbkLocSensorStreamingInd::results

8.918 QmiCbkLocSetExtPowerConfigInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG status

8.918.1 Detailed Description

This structure contains LOC Set External Power Config Status

Parameters

status	• Values – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure

8.918.2 Field Documentation

8.918.2.1 struct qmTlvResult QmiCbkLocSetExtPowerConfigInd::results

8.918.2.2 ULONG QmiCbkLocSetExtPowerConfigInd::status

8.919 QmiCbkLocSetServerInd Struct Reference

Data Fields

- struct qmTlvResult results
- ULONG serverStatus

8.919.1 Detailed Description

This structure contains LOC Set Server field.

Parameters

serverStatus	• Status of the Get Server request. • Valid values – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure

8.919.2 Field Documentation

8.919.2.1 struct qmTlvResult QmiCbkLocSetServerInd::results

8.919.2.2 ULONG QmiCbkLocSetServerInd::serverStatus

8.920 QmiCbkNasEdrxChangeInfo Struct Reference

Data Fields

- struct qmTlvResult results
- EdrxEnableType sEdrxEnableType
- EdrxCycleLength sEdrxCycleLength
- EdrxPagingTimeWindow sEdrxPagingTimeWindow
- EdrxRatType sEdrxRatType
- EdrxCiotLteMode sEdrxCiotLteMode

8.920.1 Detailed Description

Structure for storing the eDRX Change Info indication parameters.

Parameters

sEdrxEnable-Type	• See EdrxEnableType for more information.
sEdrxCycle-Length	• See EdrxCycleLength for more information.

sEdrxPaging-TimeWindow	• See EdrxPagingTimeWindow for more information.
sEdrxRatType	• See EdrxRatType for more information.
sEdrxCiotLte-Mode	• See EdrxCiotLteMode for more information.

8.920.2 Field Documentation

8.920.2.1 struct qmTlvResult QmiCbkNasEdrxChangeInfo::results

8.920.2.2 EdrxCiotLteMode QmiCbkNasEdrxChangeInfo::sEdrxCiotLteMode

8.920.2.3 EdrxCycleLength QmiCbkNasEdrxChangeInfo::sEdrxCycleLength

8.920.2.4 EdrxEnableType QmiCbkNasEdrxChangeInfo::sEdrxEnableType

8.920.2.5 EdrxPagingTimeWindow QmiCbkNasEdrxChangeInfo::sEdrxPagingTimeWindow

8.920.2.6 EdrxRatType QmiCbkNasEdrxChangeInfo::sEdrxRatType

8.921 QmiCbkNasLTECphyCaInfo Struct Reference

Data Fields

- struct qmTlvResult results
- PhyCaAggScellIndType sPhyCaAggScellIndType
- PhyCaAggScellDlBw sPhyCaAggScellDlBw
- PhyCaAggScellInfo sPhyCaAggScellInfo
- PhyCaAggPcellInfo sPhyCaAggPcellInfo
- PhyCaAggScellIndex sPhyCaAggScellIndex

8.921.1 Detailed Description

Structure for storing the LTEC PHY CA indication parameters.

Parameters

pPhyCaAgg-ScellIndType	• See PhyCaAggScellIndType for more information.
sPhyCaAgg-ScellDlBw	• See PhyCaAggScellDlBw for more information.
sPhyCaAgg-ScellInfo	• See PhyCaAggScellInfo for more information.
sPhyCaAgg-PcellInfo	• See PhyCaAggPcellInfo for more information.

sPhyCaAgg-ScellIndex	• See PhyCaAggScellIndex for more information.

8.921.2 Field Documentation

8.921.2.1 struct **qmTlvResult** QmiCbkNasLTECphyCaInfo::results

8.921.2.2 **PhyCaAggPcellInfo** QmiCbkNasLTECphyCaInfo::sPhyCaAggPcellInfo

8.921.2.3 **PhyCaAggScellDlBw** QmiCbkNasLTECphyCaInfo::sPhyCaAggScellDlBw

8.921.2.4 **PhyCaAggScellIndex** QmiCbkNasLTECphyCaInfo::sPhyCaAggScellIndex

8.921.2.5 **PhyCaAggScellIndType** QmiCbkNasLTECphyCaInfo::sPhyCaAggScellIndType

8.921.2.6 **PhyCaAggScellInfo** QmiCbkNasLTECphyCaInfo::sPhyCaAggScellInfo

8.922 QmiCbkSwiOmaDmEventStatusReportInd Struct Reference

Data Fields

- struct qmTlvResult results
- struct sessionInfoTlv SITlv

8.922.1 Field Documentation

8.922.1.1 struct **qmTlvResult** QmiCbkSwiOmaDmEventStatusReportInd::results

8.922.1.2 struct **sessionInfoTlv** QmiCbkSwiOmaDmEventStatusReportInd::SITlv

8.923 QmiCbkSwiOmaDmEventStatusReportIndExt Struct Reference

Data Fields

- struct sessionInfoTlvExt SITlv

8.923.1 Field Documentation

8.923.1.1 struct **sessionInfoTlvExt** QmiCbkSwiOmaDmEventStatusReportIndExt::SITlv

8.924 QmiCbkTmdMitiLvlRptInd Struct Reference

Data Fields

- struct qmTlvResult results
- _MitigationDevInfo MitigationDevInfo
- BYTE currentMitigationLvl

8.924.1 Detailed Description

This structure contains LOC Cradle Mount Config Status

Parameters

results	• See qmTlvResult
MitigationDevInfo	• See MitigationDevInfo for more information.
currentMitigationLvl	• Current Thermal Mitigation Level

8.924.2 Field Documentation

8.924.2.1 BYTE QmiCbkTmdMitiLvlRptInd::currentMitigationLvl

8.924.2.2 _MitigationDevInfo QmiCbkTmdMitiLvlRptInd::MitigationDevInfo

8.924.2.3 struct qmTlvResult QmiCbkTmdMitiLvlRptInd::results

8.925 QmiCbkWdsStatisticsIndState Struct Reference

Data Fields

- struct qmTlvResult results
- DataULongTlv TxOkConutTlv
- DataULongTlv RxOkConutTlv
- DataULongLongTlv TxOkByteCountTlv
- DataULongLongTlv RxOkByteCountTlv
- DataULongTlv TxDropConutTlv
- DataULongTlv RxDropConutTlv

8.925.1 Detailed Description

WDS Pkt RM Transfer Statistics data structure for individual session

Parameters

results	• result Tlv Value.
TxOkConutTlv	• Tx Ok Packet Tlv Value.
RxOkConutTlv	• Rx Ok Packet Tlv Value.
TxOkByteCountTlv	• Tx Ok Byte Count Packet Tlv Value.

RxOkByteCount-Tlv	• Rx Ok Byte Count Packet Tlv Value.
TxDropConutTlv	• Tx Drop Count Packet Tlv Value.
RxDropConutTlv	• Rx Drop Count Packet Tlv Value.

8.925.2 Field Documentation

8.925.2.1 struct qmTlvResult QmiCbkWdsStatisticsIndState::results

8.925.2.2 DataULongTlv QmiCbkWdsStatisticsIndState::RxDropConutTlv

8.925.2.3 DataULongLongTlv QmiCbkWdsStatisticsIndState::RxOkByteCountTlv

8.925.2.4 DataULongTlv QmiCbkWdsStatisticsIndState::RxOkConutTlv

8.925.2.5 DataULongTlv QmiCbkWdsStatisticsIndState::TxDropConutTlv

8.925.2.6 DataULongLongTlv QmiCbkWdsStatisticsIndState::TxOkByteCountTlv

8.925.2.7 DataULongTlv QmiCbkWdsStatisticsIndState::TxOkConutTlv

8.926 qmifwinfo_s Struct Reference

Data Fields

- union {
  struct fwinfo_s g
  struct slqsfwinfo_s s
  } dev

8.926.1 Detailed Description

Top level structure for storing information about firmware images. union of structures depending on device type, MC77xx or MC83xx

Parameters

g	- structure for MC83xx devices
s	- structure for devices with SPKG CWE file support

- List of various Firmware Images Supported

```
Technology  Initials  Carrier                      Region                Network Technology
----------  --------  ---------------------------  -------------------  --------------------
D3600       S         eGOBI_IMG_CAR_SPRINT         eGOBI_IMG_REG_NA      eGOBI_IMG_TECH_CDMA
D3600       V         eGOBI_IMG_CAR_VERIZON        eGOBI_IMG_REG_NA      eGOBI_IMG_TECH_CDMA
D3600       C         eGOBI_IMG_CAR_CHINA_TELECOM  eGOBI_IMG_REG_ASIA    eGOBI_IMG_TECH_CDMA
D3600       G         eGOBI_IMG_CAR_GENERIC_CDMA   eGOBI_IMG_REG_GLOBAL  eGOBI_IMG_TECH_CDMA (item for Generic
D3600       H         eGOBI_IMG_CAR_GENERIC_CDMA   eGOBI_IMG_REG_GLOBAL  eGOBI_IMG_TECH_CDMA (item for Generic
```

```
D3200       V         eGOBI_IMG_CAR_VODAFONE       eGOBI_IMG_REG_NA      eGOBI_IMG_TECH_UMTS
D3200       A         eGOBI_IMG_CAR_ATT            eGOBI_IMG_REG_NA      eGOBI_IMG_TECH_UMTS
D3200       L         eGOBI_IMG_CAR_TMOBILE        eGOBI_IMG_REG_EU      eGOBI_IMG_TECH_UMTS
D3200       G         eGOBI_IMG_CAR_GENERIC        eGOBI_IMG_REG_GLOBAL  eGOBI_IMG_TECH_UMTS
D3200       H         eGOBI_IMG_CAR_TELEFONICA     eGOBI_IMG_REG_EU      eGOBI_IMG_TECH_UMTS
D3200       I         eGOBI_IMG_CAR_TELCOM_ITALIA  eGOBI_IMG_REG_NA      eGOBI_IMG_TECH_UMTS
D3200       O         eGOBI_IMG_CAR_ORANGE         eGOBI_IMG_REG_NA      eGOBI_IMG_TECH_UMTS
D3200       U         eGOBI_IMG_CAR_GENERIC        eGOBI_IMG_REG_GLOBAL  eGOBI_IMG_TECH_UMTS
D3200       R         eGOBI_IMG_CAR_ROGERS         eGOBI_IMG_REG_NA      eGOBI_IMG_TECH_UMTS
D3600       A         eGOBI_IMG_CAR_AERIS          eGOBI_IMG_REG_NA      eGOBI_IMG_TECH_CDMA
```

See Also

fwinfo_s
slqsfwinfo_s

8.926.2 Field Documentation

8.926.2.1 union { ... } qmifwinfo_s::dev

8.926.2.2 struct fwinfo_s qmifwinfo_s::g

8.926.2.3 struct slqsfwinfo_s qmifwinfo_s::s

8.927 QmiNas3GppNetworkInfo Struct Reference

Data Fields

- WORD pMCC
- WORD pMNC
- ULONG pInUse
- ULONG pRoaming
- ULONG pForbidden
- ULONG pPreferred
- CHAR pDesription [255]

8.927.1 Detailed Description

This structure contains the PerformNetworkScan response parameters. This structure will hold the array of the netwok scan information.

Parameters

pMCC	• Mobile Country Code
pMNC	• Mobile Networ Code
pInUse	• Is the Network the current serving Network – 0 - Unknown – 1 - Current serving network – 2 - Not current serving network, available

pRoaming	• Home/Roam Status of the Network – 0 - Unknown – 1 - Home – 2 - Roam
pForbidden	• Is the Network in the forbidden network list – 0 - Unknown – 1 - Forbidden – 2 - Not Forbidden
pPreferred	• Is the Network in the Preferred network list – 0 - Unknown – 1 - Preferred – 2 - Not Preferred
pDesription	• Network Name/Description

8.927.2 Field Documentation

8.927.2.1 CHAR QmiNas3GppNetworkInfo::pDesription[255]

8.927.2.2 ULONG QmiNas3GppNetworkInfo::pForbidden

8.927.2.3 ULONG QmiNas3GppNetworkInfo::pInUse

8.927.2.4 WORD QmiNas3GppNetworkInfo::pMCC

8.927.2.5 WORD QmiNas3GppNetworkInfo::pMNC

8.927.2.6 ULONG QmiNas3GppNetworkInfo::pPreferred

8.927.2.7 ULONG QmiNas3GppNetworkInfo::pRoaming

8.928 QmiNasGetRFBandInfoResp Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE * pInstancesSize
- struct RFBandInfoElements * pRFBandInfoElements
- RfDedicatedBandInfo * pRfDedicatedBandInfo
- RfBandInfoExtFormat * pRfBandInfoExtFormat
- RfBandwidthInfo * pRfBandwidthInfo
- LTEOperationMode * pLTEOperationMode

8.928.1 Field Documentation

8.928.1.1 BYTE* QmiNasGetRFBandInfoResp::pInstancesSize

8.928.1.2 LTEOperationMode* QmiNasGetRFBandInfoResp::pLTEOperationMode

8.928.1.3 struct RFBandInfoElements* QmiNasGetRFBandInfoResp::pRFBandInfoElements

8.928.1.4 RfBandInfoExtFormat* QmiNasGetRFBandInfoResp::pRfBandInfoExtFormat

8.928.1.5 RfBandwidthInfo* QmiNasGetRFBandInfoResp::pRfBandwidthInfo

8.928.1.6 RfDedicatedBandInfo* QmiNasGetRFBandInfoResp::pRfDedicatedBandInfo

8.928.1.7 struct qmTlvResult QmiNasGetRFBandInfoResp::results

8.929 QmiNasPerformNetworkScanResp Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE * pInstanceSize
- struct QmiNas3GppNetworkInfo * pInstances

8.929.1 Field Documentation

8.929.1.1 struct QmiNas3GppNetworkInfo* QmiNasPerformNetworkScanResp::pInstances

8.929.1.2 BYTE* QmiNasPerformNetworkScanResp::pInstanceSize

8.929.1.3 struct qmTlvResult QmiNasPerformNetworkScanResp::results

8.930 qmiSmsMessageList Struct Reference

Data Fields

- uint32_t messageIndex
- uint32_t messageTag

8.930.1 Detailed Description

This structure contains SMS message list.

Parameters

messageIndex	• Message index of each matched message
messageTag	• Messagetag

8.930.2 Field Documentation

8.930.2.1 uint32_t qmiSmsMessageList::messageIndex

8.930.2.2 uint32_t qmiSmsMessageList::messageTag

8.931 qmiWDSDataBearerTechnology Struct Reference

Data Fields

- uint8_t currentNetwork
- uint32_t ratMask
- uint32_t soMask

8.931.1 Detailed Description

Structure to hold the current data bearer technology values

Parameters

currentNetwork[-OUT]	• current selected network – 0 - UNKNOWN – 1 - 3GPP2 – 2 - 3GPP – 0xff - Invalid data.
ratMask[OUT]	RAT Mask
soMask[OUT]	SO Mask

8.931.2 Field Documentation

8.931.2.1 uint8_t qmiWDSDataBearerTechnology::currentNetwork

8.931.2.2 uint32_t qmiWDSDataBearerTechnology::ratMask

8.931.2.3 uint32_t qmiWDSDataBearerTechnology::soMask

8.932 QmiWdsIpAddressInfo Struct Reference

Data Fields

- ULONG * pIPAddressV4
- USHORT * pIPAddressV6
- BYTE * pIPv6prefixlen

8.932.1 Detailed Description

Parameters

pIPAddressV4[-OUT]	• Current IPv4 address • default value of 0 if not reported by the device.

pIPAddressV6[-OUT]	• Current IPv6 address Space for storing the 8 element array of type USHORT for the IPv6 address is allocated by the application. The IP Address is stored in the user supplied buffer as follows: User buffer: [<U0>..<U7>] IPv6 address from the network: 1234:2A01:....:5678 User buffer contents: U0 corresponds to 1234 U1 corresponds to 2A01 – ----------— – — – ----------— – — U7 corresponds to 5678
pIPv6prefixlen[-OUT]	• IPv6 prefix length in number of bits

8.932.2 Field Documentation

8.932.2.1 ULONG∗ QmiWdsIpAddressInfo::pIPAddressV4

8.932.2.2 USHORT∗ QmiWdsIpAddressInfo::pIPAddressV6

8.932.2.3 BYTE∗ QmiWdsIpAddressInfo::pIPv6prefixlen

8.933 qmiWdsRunTimeSettings Struct Reference

Data Fields

- CHAR ∗ pProfileName
- ULONG ∗ pPDPType
- CHAR ∗ pAPNName
- ULONG ∗ pPrimaryDNSV4
- ULONG ∗ pSecondaryDNSV4
- struct UMTSQoS ∗ pUMTSGrantedQoS
- struct GPRSQoS ∗ pGPRSGrantedQoS
- CHAR ∗ pUsername
- ULONG ∗ pAuthentication
- ULONG ∗ pIPAddressV4
- struct ProfileIdentifier ∗ pProfileID
- ULONG ∗ pGWAddressV4
- ULONG ∗ pSubnetMaskV4
- BYTE ∗ pPCSCFAddrPCO
- struct PCSCFIPv4ServerAddressList ∗ pServerAddrList
- struct PCSCFFQDNAddressList ∗ pPCSCFFQDNAddrList
- USHORT ∗ pPrimaryDNSV6
- USHORT ∗ pSecondaryDNSV6
- ULONG ∗ pMtu
- struct DomainNameList ∗ pDomainList
- BYTE ∗ pIPFamilyPreference

- BYTE * pIMCNflag
- WORD * pTechnology
- struct IPV6AddressInfo * pIPV6AddrInfo
- struct IPV6GWAddressInfo * pIPV6GWAddrInfo

8.933.1 Detailed Description

This structure contains the WdsRunTimeSettings Information

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

pProfileName	• Profile name One or more bytes describing the profile. Description may be a user-defined name for the profile. QMI_ERR_ARG_TOO_LONG is returned if profile_name is too long.
pPDPType	• PDP type – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6 – 0xffffffff - invalid
pAPNName	• Access point name String parameter that is a logical name used to select the GGSN and external packet data network. If value is NULL or omitted, then the subscription default value is requested. QMI_ERR_ARG_TOO_LONG is returned if the APN name is too long.
pPrimaryDNSV4	• Primary DNS IPv4 Address
pSecondaryDNSV4	• Secondary DNS IPv4 Address
pUMTSGrantedQoS	• UMTS Granted QoS
pGPRSGrantedQoS	• GPRS Granted QoS
pUsername	• User name used during data network authentication

pAuthentication	• Authentication preference – Bit 0 - PAP preference * 0 - PAP is never performed * 1 - PAP may be performed – Bit 1 - CHAP preference * 0 - CHAP is never performed * 1 - CHAP may be performed
pIPAddressV4	• IPV4 Address assigned to the TE
pProfileID	• Profile Identifier
pGWAddressV4	• IPV4 Gateway Address
pSubnetMaskV4	• IPV4 Subnet Mask
pPCSCFAddrPCO	• PCSCF address using PCO values – 1 - (TRUE) implies request PCSCF address using PCO – 0 - (FALSE) implies do not request. This is the default value.
pServerAddrList	• P-CSCF IPv4 Server Address List
pPCSCFFQDNAddrList	• P-CSCF FQDN Address List
pPrimaryDNSV6	• Primary DNS IPv6 Address
pSecondaryDNSV6	• Secondary DNS IPv6 Address
pMtu	• actual (runtime) MTU size
pDomainList	• Domain-Name List
pIPFamilyPreference	• IP family – 0x04 - IPV4 ADDR – 0x06 - IPV6 ADDR

pIMCNflag	• IM CN Flag – 0x00 - FALSE – 0x01 - TRUE
pTechnology	• Technology – CDMA - 0x8001 – UMTS - 0x8004
pIPV6Address-Info	• IPV6 Address Information
pIPV6GW-AddressInfo	• IPV6 Gateway Address Information

8.933.2 Field Documentation

8.933.2.1 CHAR∗ qmiWdsRunTimeSettings::pAPNName

8.933.2.2 ULONG∗ qmiWdsRunTimeSettings::pAuthentication

8.933.2.3 struct DomainNameList∗ qmiWdsRunTimeSettings::pDomainList

8.933.2.4 struct GPRSQoS∗ qmiWdsRunTimeSettings::pGPRSGrantedQoS

8.933.2.5 ULONG∗ qmiWdsRunTimeSettings::pGWAddressV4

8.933.2.6 BYTE∗ qmiWdsRunTimeSettings::pIMCNflag

8.933.2.7 ULONG∗ qmiWdsRunTimeSettings::pIPAddressV4

8.933.2.8 BYTE∗ qmiWdsRunTimeSettings::pIPFamilyPreference

8.933.2.9 struct IPV6AddressInfo∗ qmiWdsRunTimeSettings::pIPV6AddrInfo

8.933.2.10 struct IPV6GWAddressInfo∗ qmiWdsRunTimeSettings::pIPV6GWAddrInfo

8.933.2.11 ULONG∗ qmiWdsRunTimeSettings::pMtu

8.933.2.12 BYTE∗ qmiWdsRunTimeSettings::pPCSCFAddrPCO

8.933.2.13 struct PCSCFFQDNAddressList∗ qmiWdsRunTimeSettings::pPCSCFFQDNAddrList

8.933.2.14 ULONG∗ qmiWdsRunTimeSettings::pPDPType

8.933.2.15 ULONG∗ qmiWdsRunTimeSettings::pPrimaryDNSV4

8.933.2.16 USHORT∗ qmiWdsRunTimeSettings::pPrimaryDNSV6

8.933.2.17 struct ProfileIdentifier∗ qmiWdsRunTimeSettings::pProfileID

8.933.2.18 CHAR* qmiWdsRunTimeSettings::pProfileName

8.933.2.19 ULONG* qmiWdsRunTimeSettings::pSecondaryDNSV4

8.933.2.20 USHORT* qmiWdsRunTimeSettings::pSecondaryDNSV6

8.933.2.21 struct PCSCFIPv4ServerAddressList* qmiWdsRunTimeSettings::pServerAddrList

8.933.2.22 ULONG* qmiWdsRunTimeSettings::pSubnetMaskV4

8.933.2.23 WORD* qmiWdsRunTimeSettings::pTechnology

8.933.2.24 struct UMTSQoS* qmiWdsRunTimeSettings::pUMTSGrantedQoS

8.933.2.25 CHAR* qmiWdsRunTimeSettings::pUsername

8.934 qmTlvResult Struct Reference

Data Fields

- swi_uint256_t TlvPresenceMask
- qmulong TlvResultCode
- qmuint16 DeviceResult
- qmuint16 DeviceError

8.934.1 Field Documentation

8.934.1.1 qmuint16 qmTlvResult::DeviceError

8.934.1.2 qmuint16 qmTlvResult::DeviceResult

8.934.1.3 swi_uint256_t qmTlvResult::TlvPresenceMask

8.934.1.4 qmulong qmTlvResult::TlvResultCode

8.935 qos_BindDataPortMuxID_t Struct Reference

Data Fields

- uint8_t MuxID

8.935.1 Detailed Description

Structure that contains the request Binds a control point to a data port Mux ID data.

Parameters

MuxID	Mux ID: • 0x80-0x8F : valid value

8.935.2 Field Documentation

8.935.2.1 uint8_t qos_BindDataPortMuxID_t::MuxID

8.936 qos_BindDataPortPeripheralEndPointID_t Struct Reference

Data Fields

- uint32_t EndPointType
- uint32_t IfaceID

8.936.1 Detailed Description

Structure that contains the request Binds a control point to a data port Periapheral End Point Type data.

Parameters

EndPointType	Peripheral end point type. Values: • 0 - Reserved • 1 - HSIC • 2 - HSUSB • 3 - PCIE • 4 - Embedded
IfaceID	Peripheral interface number.

8.936.2 Field Documentation

8.936.2.1 uint32_t qos_BindDataPortPeripheralEndPointID_t::EndPointType

8.936.2.2 uint32_t qos_BindDataPortPeripheralEndPointID_t::IfaceID

8.937 qos_BindDataPortSIODataPort_t Struct Reference

Data Fields

- uint16_t SIODataPort

8.937.1 Detailed Description

Structure that contains the request Binds a control point to a data port SIO Data Port data.

Parameters

u16SIODataPort	SIO Data Port to which the client binds

8.937.2 Field Documentation

8.937.2.1 uint16_t qos_BindDataPortSIODataPort_t::SIODataPort

8.938 QosClassID Struct Reference

Data Fields

- BYTE QCI
- ULONG gDlBitRate
- ULONG maxDlBitRate
- ULONG gUlBitRate
- ULONG maxUlBitRate

8.938.1 Detailed Description

structure contains 3GPP LTE QoS parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

QCI	• QOS specified using the QOS Class Identifier (QOS) values QCI value 0 - Requests the network to assign the appropriate QCI value QCI values 1-4 - Associated with guaranteed bit rates QCI values 5-9 - Associated with non-guaranteed bit rates
gDlBitRate	• Guaranteed DL bit rate
maxDlBitRate	• maxDlBitRate
gUlBitRate	• Guaranteed UL bit rate
maxUlBitRate	• Maximum UL bit rate

8.938.2 Field Documentation

8.938.2.1 ULONG QosClassID::gDlBitRate

8.938.2.2 ULONG QosClassID::gUlBitRate

8.938.2.3 ULONG QosClassID::maxDlBitRate

8.938.2.4 ULONG QosClassID::maxUlBitRate

8.938.2.5 BYTE QosClassID::QCI

8.939 QosEventInfo Struct Reference

Data Fields

- ULONG * pDataBearer
- ULONG * pPacketsCountTX
- ULONG * pPacketsCountRX

- ULONGLONG * pTotalBytesTX
- ULONGLONG * pTotalBytesRX

8.939.1 Detailed Description

Contains the WDS event information and information about the interface

Parameters

pQmiInterface-Info	• See qaQmiInterfaceInfo for more information
pDataBearer	• Data bearer technology (NULL if not present) – 0x00 - Indicates that this field is ignored – 0x01 - CDMA 1X – 0x02 - EV-DO Rev 0 – 0x03 - GPRS – 0x04 - WCDMA – 0x05 - EV-DO Rev A – 0x06 - EDGE – 0x07 - HSDPA and WCDMA – 0x08 - WCDMA and HSUPA – 0x09 - HSDPA and HSUPA – 0x0A - LTE – 0x0B - EV-DO Rev A EHRPD – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA – 0x8000 - NULL Bearer – 0xFF - Unknown Technology
pDormancy-Status	• Dormancy status (NULL if not present) – 1 - traffic channel dormant – 2 - traffic channel active
pPacketsCount-TX	• Packets transmitted without error (NULL if not present)
pPacketsCount-RX	• Packets received without error (NULL if not present)
pTotalBytesTX	• Bytes transmitted without error (NULL if not present)
pTotalBytesRX	• Bytes received without error (NULL if not present)

8.939.2 Field Documentation

8.939.2.1 ULONG* QosEventInfo::pDataBearer

8.939.2.2 ULONG* QosEventInfo::pPacketsCountRX

8.939.2.3 ULONG* QosEventInfo::pPacketsCountTX

8.939.2.4 ULONGLONG* QosEventInfo::pTotalBytesRX

8.939.2.5 ULONGLONG* QosEventInfo::pTotalBytesTX

8.940 QosFlowInfo Struct Reference

Data Fields

- QosFlowInfoState * pQFlowState
- swiQosFlow * pTxQFlowGranted
- swiQosFlow * pRxQFlowGranted
- swiQosFilter * pTxQFilter [MAX_QOS_FILTER_TLV]
- swiQosFilter * pRxQFilter [MAX_QOS_FILTER_TLV]
- BYTE * pBearerID

8.940.1 Detailed Description

This structure contains QoS flow info

Parameters

pQFlowState	• QoS flow state information, please check QosFlowInfoState for more information
pTxQFlow-Granted	• pointer to the Tx Qos flow granted, please check swiQosFlow for more information
pRxQFlow-Granted	• pointer to the Rx Qos flow granted
pTxQFilter	• pointer to the Tx Qos filter
pRxQFilter	• pointer to the Rx Qos flow
pBearerID	• pointer to the bearer ID • Bearer ID or Radio Link Protocol (RLP) ID of the activated flow. • Valid Values - 0 to 16 • 0xFF - Invalid value.

8.940.2 Field Documentation

8.940.2.1 BYTE* QosFlowInfo::pBearerID

8.940.2.2 QosFlowInfoState* QosFlowInfo::pQFlowState

8.940.2.3 swiQosFilter* QosFlowInfo::pRxQFilter[MAX_QOS_FILTER_TLV]

8.940.2.4 swiQosFlow* QosFlowInfo::pRxQFlowGranted

8.940.2.5 swiQosFilter* QosFlowInfo::pTxQFilter[MAX_QOS_FILTER_TLV]

8.940.2.6 swiQosFlow* QosFlowInfo::pTxQFlowGranted

8.941 QosFlowInfoState Struct Reference

Data Fields

- ULONG id
- BYTE isNewFlow
- BYTE state

8.941.1 Detailed Description

This structure contains QoS flow state

Parameters

id	QoS identifier
isNewFlow	• 1 - Newly added flow2 • 0 - Existing flow
state	This indicates that the flow that was added/modified/deleted: • 0x01 - Flow activated • 0x02 - Flow modified • 0x03 - Flow deleted • 0x04 - Flow suspended • 0x05 - Flow enabled • 0x06 - Flow disabled

8.941.2 Field Documentation

8.941.2.1 ULONG QosFlowInfoState::id

8.941.2.2 BYTE QosFlowInfoState::isNewFlow

8.941.2.3 BYTE QosFlowInfoState::state

8.942 QosMap Struct Reference

Data Fields

- BYTE dscp
- ULONG qos_id
- BYTE state

8.942.1 Detailed Description

This structure contains the SLQSQosDumpMap Information

Parameters

dscp	• Differential Service Code Point(DSCP) value
qos_id	• QoS identifier
state	• QoS Flow state

8.942.2 Field Documentation

8.942.2.1 BYTE QosMap::dscp

8.942.2.2 ULONG QosMap::qos_id

8.942.2.3 BYTE QosMap::state

8.943 RankIndicatorInd Struct Reference

Data Fields

- WORD Count1
- WORD Count2

8.943.1 Field Documentation

8.943.1.1 WORD RankIndicatorInd::Count1

8.943.1.2 WORD RankIndicatorInd::Count2

8.944 RatDisabledMaskTlv Struct Reference

Data Fields

- WORD ratDisabledMask
- BYTE TlvPresent

8.944.1 Detailed Description

Contain the RAT disabled mask

Parameters

ratDisabledMask	• Bitmask representing the radio technologies that are disabled. • Bit values: – Bit 0 (0x01) - cdma2000 ® 1X – Bit 1 (0x02) - cdma2000 ® HRPD(1xEV-DO) – Bit 2 (0x04) - GSM – Bit 3 (0x08) - UMTS – Bit 4 (0x10) - LTE – Bit 5 (0x20) - TD-SCDMA – Bit 6 (0x40) - NR5G All unlisted bits are reserved for future use and the service point ignores them if used.
TlvPresent	• Tlv Present

8.944.2 Field Documentation

8.944.2.1 WORD RatDisabledMaskTlv::ratDisabledMask

8.944.2.2 BYTE RatDisabledMaskTlv::TlvPresent

8.945 readResult Struct Reference

Data Fields

- WORD contentLen
- BYTE content [255+1]

8.945.1 Detailed Description

This structure contains the information for write operation.

Parameters

contentLen	• Number of sets of content.
content[MAX_DESCRIPTION_LENGTH]	• Read content. • The content is the sequence of bytes as read from the card.

8.945.2 Field Documentation

8.945.2.1 BYTE readResult::content[255+1]

8.945.2.2 WORD readResult::contentLen

8.946 readTransparentInfo Struct Reference

Data Fields

- WORD offset
- WORD length

8.946.1 Detailed Description

This structure contains the information for read operation.

Parameters

offset	• Offset for the read operation.
length	• Length of the content to be read. • The value 0 is used to read the complete file.

8.946.2 Field Documentation

8.946.2.1 WORD readTransparentInfo::length

8.946.2.2 WORD readTransparentInfo::offset

8.947 redirNumInfo Struct Reference

Data Fields

- BYTE PI
- BYTE SI
- BYTE numType
- BYTE numPlan
- BYTE reason
- BYTE numLen
- BYTE number [255]

8.947.1 Detailed Description

This structure contains Redirecting Number Information

Parameters

PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.
SI	• Number of sets of following elements – Caller Id

SI	• Number screening indicator. • Values: – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network
numType	• Number type. • Values: – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension
numPlan	• Number plan. • Values: – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
reason	-Redirecting reason; refer to [S1, Table 3.7.5.11-1] for valid values
numLen	• Provides the length of number which follow.
number[255]	• number of numLen length, NULL terminated.

8.947.2 Field Documentation

8.947.2.1 BYTE redirNumInfo::number[255]

8.947.2.2 BYTE redirNumInfo::numLen

8.947.2.3 BYTE redirNumInfo::numPlan

8.947.2.4 BYTE redirNumInfo::numType

8.947.2.5 BYTE redirNumInfo::PI

8.947.2.6 BYTE redirNumInfo::reason

8.947.2.7 BYTE redirNumInfo::SI

8.948 registerRefresh Struct Reference

Data Fields

- BYTE registerFlag
- BYTE voteForInit
- WORD numFiles
- fileInfo arrfileInfo [255]

8.948.1 Detailed Description

This structure contains paramaters of refresh Information

Parameters

registerFlag	• Flag that indicates whether to register or deregister for refresh indications. Valid values: – 0 - Deregister – 1 - Register
voteForInit	• Flag that indicates whether to vote for the init when there is a refresh. Valid values: – 0 - Client does not vote for initialization – 1 - Client votes for initialization
numFiles	• Number of sets of the following elements: – file_id – path_len – path
arrfileInfo	• Array of file Information structure. • See /ref fileInfo for more information

8.948.2 Field Documentation

8.948.2.1 fileInfo registerRefresh::arrfileInfo[255]

8.948.2.2 WORD registerRefresh::numFiles

8.948.2.3 BYTE registerRefresh::registerFlag

8.948.2.4 BYTE registerRefresh::voteForInit

8.949 remainingRetries Struct Reference

Data Fields

- BYTE verifyLeft
- BYTE unblockLeft

8.949.1 Detailed Description

This structure contains the information about the retries remaining.

Parameters

verifyLeft	• Number of remaining attempts to verify the PIN. • 0xFF, if unavailable.
unblockLeft	• Number of remaining attempts to unblock the PIN. • 0xFF, if unavailable.

Note

This value is returned only when the enable/disable operation has failed. This information is not sent for a hidden key PIN type.

8.949.2 Field Documentation

8.949.2.1 BYTE remainingRetries::unblockLeft

8.949.2.2 BYTE remainingRetries::verifyLeft

8.950 remotePartyName Struct Reference

Data Fields

- BYTE namePI
- BYTE codingScheme
- BYTE nameLen
- BYTE callerName [255]

8.950.1 Detailed Description

This structure contains information about the names that are dialed from the device or from which a call is received on the device.

Parameters

namePI	• Name presentation indicator. – 0x00 - PRESENTATION_NAME_PRESENTATION_ALLOWED - Allowed presentation – 0x01 - PRESENTATION_NAME_PRESENTATION_RESTRICTED - Restricted presentation – 0x02 - PRESENTATION_NAME_UNAVAILABLE - Unavailable presentation – 0x03 - PRESENTATION_NAME_NAME_PRESENTATION_RESTRICTED - Restricted name presentation – 0xFF - Not Available
codingScheme	• Refer to Table10 qaGobiApiTableCodingScheme.h for coding schemes • 0xFF - Not Available
nameLen	• Provides the length of name which follow. • If zero(0) then no further information exists.
callerName[MAX_DESCRIPTION_LENGTH]	• Name in ASCII, NULL ending.

8.950.2 Field Documentation

8.950.2.1 BYTE remotePartyName::callerName[255]

8.950.2.2 BYTE remotePartyName::codingScheme

8.950.2.3 BYTE remotePartyName::nameLen

8.950.2.4 BYTE remotePartyName::namePI

8.951 remotePartyNum Struct Reference

Data Fields

- BYTE presentationInd
- BYTE numLen
- BYTE remPartyNumber [81]

8.951.1 Detailed Description

This structure contains information about the numbers that are dialed from the device or from which a call is received on the device.

Parameters

presentationInd	• Presentation indicator. – 0x00 - PRESENTATION_ALLOWED - Allowed presentation – 0x01 - PRESENTATION_RESTRICTED - Restricted presentation – 0x02 - PRESENTATION_NUM_UNAVAILABLE - Unavailable presentation – 0x04 - PRESENTATION_PAYPHONE - Payphone presentation (GSM/UMTS specific) – 0xFF - Not Available
numLen	• Provides the length of number which follow. • If zero(0) then no further information exists.
remParty-Number[MAX_-CALL_NO_LEN]	• Array of numbers in ASCII, NULL ending.

8.951.2 Field Documentation

8.951.2.1 BYTE remotePartyNum::numLen

8.951.2.2 BYTE remotePartyNum::presentationInd

8.951.2.3 BYTE remotePartyNum::remPartyNumber[81]

8.952 ReqFieldsList Struct Reference

Data Fields

- BYTE requestFieldsLen
- BYTE requestFields [256]

8.952.1 Detailed Description

This structure contains the Supported Request Fields List Information

Parameters

requestFields-Len	• Number of sets of the request fields.
requestFields	• Describes which optional field IDs are supported in QMI Request. • Array of uint8 is a bitmask where each bit represents a field ID. • Field 0-15 are mandatory, First Bit represents field ID 16, • Starting with the LSB, bit 0 represents Field ID 16, bit 1 represents ID 17.

8.952.2 Field Documentation

8.952.2.1 BYTE ReqFieldsList::requestFields[256]

8.952.2.2 BYTE ReqFieldsList::requestFieldsLen

8.953 RespFieldsList Struct Reference

Data Fields

- BYTE responseFieldsLen
- BYTE responseFields [256]

8.953.1 Detailed Description

This structure contains the Supported Response Fields List Information

Parameters

responseFields-Len	• Number of sets of the response fields.
responseFields	• Describes which optional field IDs are supported in QMI Response. • Format is same as request field.

8.953.2 Field Documentation

8.953.2.1 BYTE RespFieldsList::responseFields[256]

8.953.2.2 BYTE RespFieldsList::responseFieldsLen

8.954 RFBandInfoElements Struct Reference

Data Fields

- BYTE radioInterface
- WORD activeBandClass
- WORD activeChannel
- uint8_t radioInterface
- uint16_t activeBandClass
- uint16_t activeChannel

8.954.1 Detailed Description

This structure contains the RFBandInfo response parameters.

Parameters

radioInterface	• Radio interface technology – See Tables for Radio Interface
activeBandClass	• Active Band Class – See Tables for Band Classes

activeChannel	• Active channel (0 if channel is not relevant to the reported technology)

This structure contains the RFBandInfo response parameters.

Parameters

radioInterface	• Radio interface technology – See Tables for Radio Interface
activeBandClass	• Active Band Class – See Tables for Band Classes
activeChannel	• Active channel (0 if channel is not relevant to the reported technology)

8.954.2 Field Documentation

8.954.2.1 WORD RFBandInfoElements::activeBandClass

8.954.2.2 uint16_t RFBandInfoElements::activeBandClass

8.954.2.3 WORD RFBandInfoElements::activeChannel

8.954.2.4 uint16_t RFBandInfoElements::activeChannel

8.954.2.5 BYTE RFBandInfoElements::radioInterface

8.954.2.6 uint8_t RFBandInfoElements::radioInterface

8.955 RfBandInfoExtFormat Struct Reference

Data Fields

- BYTE TlvPresent
- BYTE * pInstancesSize
- struct RfBandInfoExtFormatElements * pRfBandInfoExtFormatParam

8.955.1 Detailed Description

This structure contains the RfBandInfoExtFormat response parameters.

Parameters

TlvPresent	• Tlv Present

pInstancesSize[-IN/OUT]	• Number of sets of the RFBandInfoElements • Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.
pRfBandInfoExt-FormatParam	• See RfBandInfoExtFormatElements for more information

8.955.2 Field Documentation

8.955.2.1 BYTE* RfBandInfoExtFormat::pInstancesSize

8.955.2.2 struct RfBandInfoExtFormatElements* RfBandInfoExtFormat::pRfBandInfoExtFormatParam

8.955.2.3 BYTE RfBandInfoExtFormat::TlvPresent

8.956 RfBandInfoExtFormatElements Struct Reference

Data Fields

- BYTE radioInterface
- WORD activeBand
- ULONG activeChannel

8.956.1 Detailed Description

This structure contains the RfBandInfoExtFormatElements response parameters.

Parameters

radioInterface	• Radio interface technology – See Tables for Radio Interface
activeBand	• Active Band Class – See Tables for Band Classes
activeChannel	• Active channel (0 if channel is not relevant to the reported technology)

8.956.2 Field Documentation

8.956.2.1 WORD RfBandInfoExtFormatElements::activeBand

8.956.2.2 ULONG RfBandInfoExtFormatElements::activeChannel

8.956.2.3 BYTE RfBandInfoExtFormatElements::radioInterface

8.957 RfBandInfoList Struct Reference

Data Fields

- BYTE * pInstanceSize
- struct RFBandInfoElements * pRFBandInfoParam

8.957.1 Detailed Description

This structure contains the RfBandInfoList response parameters.

Parameters

pInstanceSize[IN/OUT]	• Number of sets of the RFBandInfoElements • Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.
pRFBandInfoParam	• See RFBandInfoElements for more information

8.957.2 Field Documentation

8.957.2.1 BYTE* RfBandInfoList::pInstanceSize

8.957.2.2 struct RFBandInfoElements* RfBandInfoList::pRFBandInfoParam

8.958 RfBandwidthInfo Struct Reference

Data Fields

- BYTE TlvPresent
- BYTE * pInstancesSize
- struct RfBandwidthInfoElements * pRfBandwidthInfoParam

8.958.1 Detailed Description

This structure contains the RfBandwidthInfo response parameters.

Parameters

TlvPresent	• Tlv Present
pInstancesSize[IN/OUT]	• Number of sets of the RFBandInfoElements • Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.
pRfBandwidthInfoParam	• See RfBandwidthInfoElements for more information

8.958.2 Field Documentation

8.958.2.1 BYTE* RfBandwidthInfo::pInstancesSize

8.958.2.2 struct RfBandwidthInfoElements* RfBandwidthInfo::pRfBandwidthInfoParam

8.958.2.3 BYTE RfBandwidthInfo::TlvPresent

8.959 RfBandwidthInfoElements Struct Reference

Data Fields

- BYTE radioInterface
- ULONG bandwidth

8.959.1 Detailed Description

This structure contains the RfBandwidthInfoElements response parameters.

Parameters

radioInterface	• Radio interface technology – See Tables for Radio Interface
bandwidth	• Bandwidth – Values * NAS_LTE_BW_NRB_6 (0) - LTE 1.4 MHz bandwidth * NAS_LTE_BW_NRB_15 (1) - LTE 3 MHz bandwidth * NAS_LTE_BW_NRB_25 (2) - LTE 5 MHz bandwidth * NAS_LTE_BW_NRB_50 (3) - LTE 10 MHz bandwidth * NAS_LTE_BW_NRB_75 (4) - LTE 15 MHz bandwidth * NAS_LTE_BW_NRB_100 (5) - LTE 20 MHz bandwidth * NAS_NR5G_BW_NRB_6 (6) - NR5G 1.4 MHz bandwidth * NAS_NR5G_BW_NRB_15 (7) - NR5G 3 MHz bandwidth * NAS_NR5G_BW_NRB_25 (8) - NR5G 5 MHz bandwidth * NAS_NR5G_BW_NRB_50 (9) - NR5G 10 MHz bandwidth * NAS_NR5G_BW_NRB_75 (10) - NR5G 15 MHz bandwidth * NAS_NR5G_BW_NRB_100 (11) - NR5G 20 MHz bandwidth

8.959.2 Field Documentation

8.959.2.1 ULONG RfBandwidthInfoElements::bandwidth

8.959.2.2 BYTE RfBandwidthInfoElements::radioInterface

8.960 RfDedicatedBandInfo Struct Reference

Data Fields

- BYTE TlvPresent
- BYTE * pInstancesSize
- struct RfDedicatedBandInfoElements * pRfDedicatedBandInfoParam

8.960.1 Detailed Description

This structure contains the RfDedicatedBandInfo response parameters.

Parameters

TlvPresent	• Tlv Present
pInstancesSize[-IN/OUT]	• Number of sets of the RFBandInfoElements • Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.
pRfDedicated-BandInfoParam	• See RfDedicatedBandInfoElements for more information

8.960.2 Field Documentation

8.960.2.1 BYTE* RfDedicatedBandInfo::pInstancesSize

8.960.2.2 struct RfDedicatedBandInfoElements* RfDedicatedBandInfo::pRfDedicatedBandInfoParam

8.960.2.3 BYTE RfDedicatedBandInfo::TlvPresent

8.961 RfDedicatedBandInfoElements Struct Reference

Data Fields

- BYTE radioInterface
- WORD dedicatedBand

8.961.1 Detailed Description

This structure contains the RfDedicatedBandInfoElements response parameters.

Parameters

radioInterface	• Radio interface technology – See Tables for Radio Interface
dedicatedBand	• Active Band Class – See Tables for Band Classes

8.961.2 Field Documentation

8.961.2.1 WORD RfDedicatedBandInfoElements::dedicatedBand

8.961.2.2 BYTE RfDedicatedBandInfoElements::radioInterface

8.962 rmTrasnferStaticsReq Struct Reference

Data Fields

- uint8_t bResetStatistics
- uint32_t ulMask

8.962.1 Detailed Description

RM Transfer Satistics Structure

Parameters

bResetStatistics	• Reset Statistics • Values: • 0 - Not Reset • Other - Reset
ulMask	• Enable/Disable RM Transfer Satatistics Indiscation Mask • Bit 0: Tx Packet Ok • Bit 1: Rx Packet Ok • Bit 2: Tx Bytes Ok • Bit 3: Rx Bytes Ok • Bit 4: Tx Packets Dropped • Bit 5: Rx Packets Dropped • Value: -0 - Disable -1 - Enable

8.962.2 Field Documentation

8.962.2.1 uint8_t rmTrasnferStaticsReq::bResetStatistics

8.962.2.2 uint32_t rmTrasnferStaticsReq::ulMask

8.963 roamIndList Struct Reference

Data Fields

- BYTE numInstances
- BYTE radioInterface [0x0A]
- BYTE roamIndicator [0x0A]

8.963.1 Detailed Description

This structure contains the Roaming Indicator List

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

numInstances	• number of sets of radio interface currently in use and roaming indicator – defaults to zero
radioInterface	• Radio Interface currently in use • Values: – 0x01 - RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS – 0x08 - RADIO_IF_LTE - LTE
roamIndicator	• Roaming Indicator • Values: – 0x00 - Roaming – 0x01 - Home

8.963.2 Field Documentation

8.963.2.1 BYTE roamIndList::numInstances

8.963.2.2 BYTE roamIndList::radioInterface[0x0A]

8.963.2.3 BYTE roamIndList::roamIndicator[0x0A]

8.964 RoamingInfo Struct Reference

Data Fields

- BYTE TlvPresent
- BYTE roaming_ind

8.964.1 Field Documentation

8.964.1.1 BYTE RoamingInfo::roaming_ind

8.964.1.2 BYTE RoamingInfo::TlvPresent

8.965 roamTimer Struct Reference

Data Fields

- BYTE namID
- ULONG roamTimerValue

8.965.1 Detailed Description

This structure contains information about the Roam Timer.

Parameters

namID	• Index of the NAM(Number Assignment Module) to be configured. • Range 0 to 3. • Some modems support only 1 or 2 NAMs. • 0xFF,if not available.
roamTimerValue	• Time in minutes. • Cumulative air time is slammed. • 0xFFFFFFFF,if not available.

8.965.2 Field Documentation

8.965.2.1 BYTE roamTimer::namID

8.965.2.2 ULONG roamTimer::roamTimerValue

8.966 RSRPThresh Struct Reference

Data Fields

- BYTE RSRPThresListLen
- SHORT * pRSRPThresList

8.966.1 Detailed Description

This structure contains RSRP threshold related parameters.

Parameters

RSRPThresList-Len	• Length of the LTE RSRP threshold list parameter to follow
pRSRPThresList	• Sequence of thresholds delimiting current RSRP event reporting bands • Every time a new RSRP value crosses a specified threshold value, an event report indication message with the new RSRQ value is sent to the requesting control point. For this field – RSRP values are applicable only for LTE – RSRP values are measured in dBm, with a range of -44 dBm to -140 dBm – Each RSRP threshold value is a signed byte value – Maximum number of threshold values is 16 – At least one value must be specified

8.966.2 Field Documentation

8.966.2.1 SHORT* RSRPThresh::pRSRPThresList

8.966.2.2 BYTE RSRPThresh::RSRPThresListLen

8.967 rsrqInformation Struct Reference

Data Fields

- INT8 rsrq
- BYTE radioIf

8.967.1 Detailed Description

This structure contains the RSRQ Information

Parameters

rsrq	• RSRQ value in dB (signed integer value); valid range is -3 to -20 (-3 means -3 dB, -20 means -20 dB)
radioIf	• Radio interface technology of the signal being measured – 0x08 - LTE

8.967.2 Field Documentation

8.967.2.1 BYTE rsrqInformation::radioIf

8.967.2.2 INT8 rsrqInformation::rsrq

8.968 RSRQThresh Struct Reference

Data Fields

- BYTE RSRQThresListLen
- INT8 * pRSRQThresList

8.968.1 Detailed Description

This structure contains RSRQ threshold related parameters.

Parameters

RSRQThresList-Len	• Length of the LTE RSRQ threshold list parameter to follow
pRSRQThresList	• Sequence of thresholds delimiting current RSRQ event reporting bands • Every time a new RSRQ value crosses a threshold value, an event report indication message with the new RSRQ value is sent to the requesting control point. For this field – RSRQ values are applicable only for LTE – RSRQ values are measured in dBm, with a range of -20 dBm to -3 dBm – Each RSRQ threshold value is a signed byte value – Maximum number of threshold values is 16 – At least one value must be specified

8.968.2 Field Documentation

8.968.2.1 INT8* RSRQThresh::pRSRQThresList

8.968.2.2 BYTE RSRQThresh::RSRQThresListLen

8.969 RSSIThresh Struct Reference

Data Fields

- BYTE RSSIThresListLen
- INT8 * pRSSIThresList

8.969.1 Detailed Description

This structure contains RSSI threshold related parameters.

Parameters

RSSIThresList-Len	• Length of the RSSI threshold list parameter to follow
pRSSIThresList	• RSSI in dBm(signed bytes) • A value of -125 dBm or lower is used to indicate No Signal • RSSI values have the following ranges (in dBm) – CDMA is -105 to -21 – HDR is -118 to -13 – GSM is -111 to -48 – WCDMA is -121 to 0 – LTE is -120 to 0 • Threshold values specified above are used for all RATs • The maximum number of threshold values is 16, each a signed byte value.

8.969.2 Field Documentation

8.969.2.1 INT8∗ RSSIThresh::pRSSIThresList

8.969.2.2 BYTE RSSIThresh::RSSIThresListLen

8.970 RXAGCList Struct Reference

Data Fields

- WORD ∗ pRXStaticGain
- WORD ∗ pRXAIG
- WORD ∗ pRXExpThres
- WORD ∗ pRXExpSlope
- WORD ∗ pRXComprThres
- WORD ∗ pRXComprSlope

8.970.1 Detailed Description

This structure contains the SLQSGetAudioPathConfig parameters related to AV_RXAGCLIST.

Parameters

pRXStaticGain	• RX pre-compressor static gain
pRXAIG	• RX pre-compressor gain selection flag
pRXExpThres	• RX expansion threshold
pRXExpSlope	• RX expansion slope

pRXComprThres	• RX compression threshold
pRXComprSlope	• RX compression slope

8.970.2 Field Documentation

8.970.2.1 WORD* RXAGCList::pRXAIG

8.970.2.2 WORD* RXAGCList::pRXComprSlope

8.970.2.3 WORD* RXAGCList::pRXComprThres

8.970.2.4 WORD* RXAGCList::pRXExpSlope

8.970.2.5 WORD* RXAGCList::pRXExpThres

8.970.2.6 WORD* RXAGCList::pRXStaticGain

8.971 RXAVCList Struct Reference

Data Fields

- WORD * pAVRXAVCSens
- WORD * pAVRXAVCHeadroom

8.971.1 Detailed Description

This structure contains the SLQSGetAudioPathConfig parameters related to AV_RXAVCLIST.

Parameters

pAVRXAVC-Sens	• AVC variation from nominal sensitivity
pAVRXAVC-Headroom	• AVC headroom

8.971.2 Field Documentation

8.971.2.1 WORD* RXAVCList::pAVRXAVCHeadroom

8.971.2.2 WORD* RXAVCList::pAVRXAVCSens

8.972 rxInfo Struct Reference

Data Fields

- BYTE isRadioTuned

- INT32 rxPower
- INT32 ecio
- INT32 rscp
- INT32 rsrp
- ULONG phase

8.972.1 Detailed Description

This structure contains the Rx Information.

Parameters

isRadioTuned	• Whether Rx is tuned to a channel: – 0x00 - Not tuned – 0x01 - Tuned – 0xFF - Not Available • If the radio is tuned, instantaneous values are set for the signal information fields below. • If the radio is not tuned, or is delayed or invalid, the values are set depending on each technology.
rx_pwr	• Rx power value in 1/10 dbm resolution.
ecio	• ECIO in 1/10 dB; valid for CDMA, HDR, GSM, WCDMA, and LTE.
rscp	• Received signal code power in 1/10 dbm. • Valid for WCDMA.
rsrp	• Current reference signal received power in 1/10 dbm valid for LTE.
phase	• Phase in 1/100 degrees; valid for LTE. • When the phase is unknown, 0xFFFFFFFF is used.

8.972.2 Field Documentation

8.972.2.1 INT32 rxInfo::ecio

8.972.2.2 BYTE rxInfo::isRadioTuned

8.972.2.3 ULONG rxInfo::phase

8.972.2.4 INT32 rxInfo::rscp

8.972.2.5 INT32 rxInfo::rsrp

8.972.2.6 INT32 rxInfo::rxPower

8.973 RXPCMIIRFltr Struct Reference

Data Fields

- WORD * pFlag
- WORD * pStageCnt
- BYTE * pStage0Val
- BYTE * pStage1Val
- BYTE * pStage2Val
- BYTE * pStage3Val
- BYTE * pStage4Val

8.973.1 Detailed Description

This structure contains the SLQSGetAudioPathConfig parameters related to AV_RXPCMIIRFLTR.

Parameters

pFlag	• Flag – 0x0000 - IIR filter disable – 0xffff - IIR filter enable
pStageCnt	• Stage Count – 0-4
pStage0Val	• A 20 BYTE sized parameter indicating Stage 0 value – A1 – A2 – B0 – B1 – B2
pStage1Val	• A 20 BYTE sized parameter indicating Stage 1 value – A1 – A2 – B0 – B1 – B2
pStage2Val	• A 20 BYTE sized parameter indicating Stage 2 value – A1 – A2 – B0 – B1 – B2

pStage3Val	• A 20 BYTE sized parameter indicating Stage 3 value – A1 – A2 – B0 – B1 – B2
pStage4Val	• A 20 BYTE sized parameter indicating Stage 4 value – A1 – A2 – B0 – B1 – B2

8.973.2 Field Documentation

8.973.2.1 WORD* RXPCMIIRFltr::pFlag

8.973.2.2 BYTE* RXPCMIIRFltr::pStage0Val

8.973.2.3 BYTE* RXPCMIIRFltr::pStage1Val

8.973.2.4 BYTE* RXPCMIIRFltr::pStage2Val

8.973.2.5 BYTE* RXPCMIIRFltr::pStage3Val

8.973.2.6 BYTE* RXPCMIIRFltr::pStage4Val

8.973.2.7 WORD* RXPCMIIRFltr::pStageCnt

8.974 RxSigInfo Struct Reference

Data Fields

- BYTE rxChainIndex
- BYTE isRadioTuned
- INT32 rxPower
- INT32 rsrp

8.974.1 Detailed Description

This structure contains the parameters for Rx Signal Info.

Parameters

rxChainIndex	• Rx antenna path • Valid Values – 0 - Primary Rx – 1 - Diversity Rx
isRadioTuned	• Rx path is tuned to a channel or Not • Values – 0x00 - Not tuned – 0x01 - Tuned

Note

If the radio is tuned, the instantaneous values are set for the fields below. If the radio is not tuned, the values set below may be invalid.

Parameters

rxPower	• Rx power value in 1/10 dBm resolution
rsrp	• Current reference signal received power in 1/10 dBm resolution

8.974.2 Field Documentation

8.974.2.1 BYTE RxSigInfo::isRadioTuned

8.974.2.2 INT32 RxSigInfo::rsrp

8.974.2.3 BYTE RxSigInfo::rxChainIndex

8.974.2.4 INT32 RxSigInfo::rxPower

8.975 rxSignalStrengthListElement Struct Reference

Data Fields

- SHORT rxSignalStrength
- BYTE radioIf

8.975.1 Detailed Description

This structure contains the Received Signal Strength Information

Parameters

rxSignalStrength	• Received signal strength in dBm – For CDMA and UMTS, this indicates forward link pilotEc. – For GSM, the received signal strength. – For LTE, this indicates the total received wideband power observed by UE.
radioIf	• Radio interface technology of the signal being radio_if measured – 0x00 - RADIO_IF_NO_SVC - None (no service) – 0x01 - RADIO_IF_CDMA_1X - cdma2000® 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS – 0x08 - RADIO_IF_LTE - LTE

Note

First element of the RSSI list always contains the current Signal strength and Radio Interface.

8.975.2 Field Documentation

8.975.2.1 BYTE rxSignalStrengthListElement::radioIf

8.975.2.2 SHORT rxSignalStrengthListElement::rxSignalStrength

8.976 sApnExtraParams Struct Reference

Data Fields

- ULONG apnId
- BYTE ambr_ul
- BYTE ambr_dl
- BYTE ambr_ul_ext
- BYTE ambr_dl_ext
- BYTE ambr_ul_ext2
- BYTE ambr_dl_ext2

8.976.1 Detailed Description

This structure contains the Extra Apn Params

Parameters

apnId	• APN id • ID identifying the APN that the client would like to query the AMBR params
ambr_ul	• APN AMBR uplink • APN AMBR uplink values from 1 kbps to 8640 kbps

ambr_dl	• APN AMBR downlink • APN AMBR downlink values from 1 kbps to 8640 kbps
ambr_ul_ext	• Extended APN AMBR uplink • APN AMBR uplink values from 8700 kbps to 256 Mbps
ambr_dl_ext	• Extended APN AMBR downlink • APN AMBR downlink values from 8700 kbps to 256 Mbps
ambr_ul_ext2	• Second extended APN AMBR uplink • APN AMBR uplink values from 256 Mbps to 65280 Mbps
ambr_dl_ext2	• Second extended APN AMBR downlink • APN AMBR downlink values from 256 Mbps to 65280 Mbps

8.976.2 Field Documentation

8.976.2.1 BYTE sApnExtraParams::ambr_dl

8.976.2.2 BYTE sApnExtraParams::ambr_dl_ext

8.976.2.3 BYTE sApnExtraParams::ambr_dl_ext2

8.976.2.4 BYTE sApnExtraParams::ambr_ul

8.976.2.5 BYTE sApnExtraParams::ambr_ul_ext

8.976.2.6 BYTE sApnExtraParams::ambr_ul_ext2

8.976.2.7 ULONG sApnExtraParams::apnId

8.977 satelliteInfo Struct Reference

Data Fields

- BYTE svListLen
- ULONG validMask
- ULONG system
- WORD gnssSvId
- BYTE healthStatus
- ULONG svStatus
- BYTE svInfoMask
- FLOAT elevation
- FLOAT azimuth
- FLOAT snr

8.977.1 Detailed Description

Contain fields in struct satelliteInfo

Parameters

svListLen	• number of sets of the following elements: – validMask – system – gnssSvid – healthStatus – svStatus – svInfoMask – elevation – azimuth – snr
validMask	• Bitmask indicating which of the fields in this TLV are valid. Valid bitmasks: – 0x00000001 - VALID_SYSTEM – 0x00000002 - VALID_GNSS_SVID – 0x00000004 - VALID_HEALTH_STATUS – 0x00000008 - VALID_PROCESS_STATUS – 0x00000010 - VALID_SVINFO_MASK – 0x00000020 - VALID_ELEVATION – 0x00000040 - VALID_AZIMUTH – 0x00000080 - VALID_SNR
system	• Indicates to which constellation this SV belongs. Valid values: – eQMI_LOC_SV_SYSTEM_GPS (1) - GPS satellite – eQMI_LOC_SV_SYSTEM_GALILEO (2) - GALILEO satellite – eQMI_LOC_SV_SYSTEM_SBAS (3) - SBAS satellite – eQMI_LOC_SV_SYSTEM_COMPASS (4) - COMPASS satellite – eQMI_LOC_SV_SYSTEM_GLONASS (5) - GLONASS satellite – eQMI_LOC_SV_SYSTEM_BDS (6) - BDS satellite
gnssSvId	• GNSS SV ID. The GPS and GLONASS SVs can be disambiguated using the system field. Range: – FOR GPS: 1 to 32 – FOR GLONASS: 1 to 32 – FOR SBAS: 120 to 151 – for BDS: 201 to 237
healthStatus	• health status. Range: 0 - 1 – 0 - unhealthy – 1 - healthy

svStatus	• SV process status. Valid values: – eQMI_LOC_SV_STATUS_IDLE (1) - SV is not being actively processed – eQMI_LOC_SV_STATUS_SEARCH (2) - The system is searching for this SV – eQMI_LOC_SV_STATUS_TRACK (3) - SV is being tracked
svInfoMask	• Indicates whether almanac and ephemeris information is available. Valid bitmasks: – 0x01 - SVINFO_HAS_EPHEMERIS – 0x02 - SVINFO_HAS_ALMANAC
elevation	• SV elevation angle. – Units: Degrees – Range: 0 to 90
azimuth	• SV azimuth angle. – Units: Degrees – Range: 0 to 360
snr	• SV signal-to-noise ratio – Units: dB-Hz

Note

None

8.977.2 Field Documentation

8.977.2.1 FLOAT satelliteInfo::azimuth

8.977.2.2 FLOAT satelliteInfo::elevation

8.977.2.3 WORD satelliteInfo::gnssSvId

8.977.2.4 BYTE satelliteInfo::healthStatus

8.977.2.5 FLOAT satelliteInfo::snr

8.977.2.6 BYTE satelliteInfo::svInfoMask

8.977.2.7 BYTE satelliteInfo::svListLen

8.977.2.8 ULONG satelliteInfo::svStatus

8.977.2.9 ULONG satelliteInfo::system

8.977.2.10 ULONG satelliteInfo::validMask

8.978 SccRxInfo Struct Reference

Data Fields

- INT32 rsrq
- SHORT snr
- BYTE numInstances
- RxSigInfo sigInfo [255]
- BYTE TlvPresent

8.978.1 Detailed Description

This structure contains information about the SccRxInfo parameters.

Parameters

rsrq	• Current reference signal • Receive quality in 1/10 dB resolution
snr	• Reference signal signal-to-noise ratio in dB. • Range -10 to 30
numInstances	• Number of sets of the following – rxChainIndex – isRadioTuned – rxPower – rsrp
sigInfo	• See RxSigInfo for more information
TlvPresent	• Tlv Present.

8.978.2 Field Documentation

8.978.2.1 BYTE SccRxInfo::numInstances

8.978.2.2 INT32 SccRxInfo::rsrq

8.978.2.3 RxSigInfo SccRxInfo::sigInfo[255]

8.978.2.4 SHORT SccRxInfo::snr

8.978.2.5 BYTE SccRxInfo::TlvPresent

8.979 sensorData Struct Reference

Data Fields

- ULONG timeOfFirstSample
- BYTE flags
- BYTE sensorDataLen
- WORD timeOffset [64]
- ULONG xAxis [64]
- ULONG yAxis [64]
- ULONG zAxis [64]

8.979.1 Detailed Description

This structure specifies information regarding the 3-Axis Sensor Data.

Parameters

timeOfFirst-Sample	• Denotes a full 32-bit time stamp of the first (oldest) sample in this message. • The time stamp is in the time reference scale that is used by the sensor time source. • Units - Milliseconds
flags	• Flags to indicate any deviation from the default measurement assumptions. • All unused bits in this field must be set to 0. • Valid bitmasks – 0x01 - Bitmask to specify that a sign reversal is required while interpreting the sensor data; only applies to the accelerometer samples – 0x02 - Bitmask to specify that the sensor time stamp is the same as the modem time stamp
sensorDataLen	• Number of sets of the following elements – timeOffset – xAxis – yAxis – zAxis
timeOffset	• Sample time offset • Units - Milliseconds
xAxis	• Sensor x-axis sample. • Units Accelerometer - Meters/seconds square • Units Gyroscope - Radians/second
yAxis	• Sensor Y-axis sample. • Units Accelerometer - Meters/seconds square • Units Gyroscope - Radians/second

xAxis	• Sensor Z-axis sample. • Units Accelerometer - Meters/seconds square • Units Gyroscope - Radians/second

8.979.2 Field Documentation

8.979.2.1 BYTE sensorData::flags

8.979.2.2 BYTE sensorData::sensorDataLen

8.979.2.3 ULONG sensorData::timeOfFirstSample

8.979.2.4 WORD sensorData::timeOffset[64]

8.979.2.5 ULONG sensorData::xAxis[64]

8.979.2.6 ULONG sensorData::yAxis[64]

8.979.2.7 ULONG sensorData::zAxis[64]

8.980 sensorData_t Struct Reference

Data Fields

- uint32_t timeOfFirstSample
- uint8_t flags
- uint8_t sensorDataLen
- uint16_t timeOffset [64]
- uint32_t xAxis [64]
- uint32_t yAxis [64]
- uint32_t zAxis [64]

8.980.1 Detailed Description

This structure specifies information regarding the 3-Axis Sensor Data. Please check has_<Param_Name> field for presence of optional parameters

Parameters

timeOfFirst-Sample	• Denotes a full 32-bit time stamp of the first (oldest) sample in this message. • The time stamp is in the time reference scale that is used by the sensor time source. • Units - Milliseconds

flags	• Flags to indicate any deviation from the default measurement assumptions. • All unused bits in this field must be set to 0. • Valid bitmasks – 0x01 - Bitmask to specify that a sign reversal is required while interpreting the sensor data; only applies to the accelerometer samples – 0x02 - Bitmask to specify that the sensor time stamp is the same as the modem time stamp
sensorDataLen	• Number of sets of the following elements – timeOffset – xAxis – yAxis – zAxis
timeOffset	• Sample time offset • Units - Milliseconds
xAxis	• Sensor x-axis sample. • Units Accelerometer - Meters/seconds square • Units Gyroscope - Radians/second
yAxis	• Sensor Y-axis sample. • Units Accelerometer - Meters/seconds square • Units Gyroscope - Radians/second
xAxis	• Sensor Z-axis sample. • Units Accelerometer - Meters/seconds square • Units Gyroscope - Radians/second

8.980.2 Field Documentation

8.980.2.1 uint8_t sensorData_t::flags

8.980.2.2 uint8_t sensorData_t::sensorDataLen

8.980.2.3 uint32_t sensorData_t::timeOfFirstSample

8.980.2.4 uint16_t sensorData_t::timeOffset[64]

8.980.2.5 uint32_t sensorData_t::xAxis[64]

8.980.2.6 uint32_t sensorData_t::yAxis[64]

8.980.2.7 uint32_t sensorData_t::zAxis[64]

8.981 sensorDataUsage_s Struct Reference

Data Fields

- ULONG usageMask
- ULONG aidingIndicatorMask

8.981.1 Detailed Description

This structure contains Sensor Data Usage info.

Parameters

usageMask	• Specifies which sensors were used in calculating the position in the position report.

- Value
  - 0x00000001 - Accelerometer used
  - 0x00000002 - Gyroscope used

Parameters

aidingIndicator-Mask	

  - Specifies which results were aided by sensors.
- Value
  - 0x00000001 - AIDED_HEADING
  - 0x00000002 - AIDED_SPEED
  - 0x00000004 - AIDED_POSITION
  - 0x00000008 - AIDED_VELOCITY

8.981.2 Field Documentation

8.981.2.1 ULONG sensorDataUsage_s::aidingIndicatorMask

8.981.2.2 ULONG sensorDataUsage_s::usageMask

8.982 serialNumbersInfo Struct Reference

Data Fields

- BYTE esnSize
- CHAR * pESNString
- BYTE imeiSize
- CHAR * pIMEIString
- BYTE meidSize
- CHAR * pMEIDString
- BYTE imeiSvnSize
- CHAR * pImeiSvnString

8.982.1 Detailed Description

Returns all the serial numbers assigned to the device. These serial numbers include the ESN (Electronic serial number of the device), the IMEI (International Mobile Equipment Identity) and MEID (Mobile Equipment Identifier).

Parameters

esnSize	• The maximum number of characters (including NULL terminator) that the ESN string array can contain
pESNString[OUT]	• NULL-terminated ESN string. Empty string is returned when ESN is not supported/programmed
imeiSize	• The maximum number of characters (including NULL terminator) that the IMEI string array can contain
pIMEIString[OUT]	• NULL terminated IMEI string. Empty string is returned when IMEI is not supported/programmed
meidSize	• The maximum number of characters (including NULL terminator) that the MEID string array can contain
pMEIDString[OUT]	• NULL-terminated MEID string. Empty string is returned when MEID is not supported/programmed
imeiSvnSize	• The maximum number of characters (including NULL terminator) that the IMEI SVN string array can contain.
pImeiSvnString[OUT]	• NULL-terminated IMEI SVN string. Empty string is returned when IMEI SVN is not supported/programmed.

8.982.2 Field Documentation

8.982.2.1 BYTE serialNumbersInfo::esnSize

8.982.2.2 BYTE serialNumbersInfo::imeiSize

8.982.2.3 BYTE serialNumbersInfo::imeiSvnSize

8.982.2.4 BYTE serialNumbersInfo::meidSize

8.982.2.5 CHAR* serialNumbersInfo::pESNString

8.982.2.6 CHAR* serialNumbersInfo::pIMEIString

8.982.2.7 CHAR* serialNumbersInfo::pImeiSvnString

8.982.2.8 CHAR* serialNumbersInfo::pMEIDString

8.983 serviceProviderName Struct Reference

Data Fields

- BYTE displayCondition
- BYTE spnLength
- BYTE spn [255]

8.983.1 Detailed Description

This structure contains Service Provider Name as defined in 3GPP TS 31.102 (Section 4.2.12) from multiple sources.

Parameters

displayCondition	• Display condition.
spnLength	• It provides length of spn.
spn	• Service provider name string must use: The SMS default 7-bit coded alphabet as defined in 3GPP TS 23.038 with bit 8 set to 9.

8.983.2 Field Documentation

8.983.2.1 BYTE serviceProviderName::displayCondition

8.983.2.2 BYTE serviceProviderName::spn[255]

8.983.2.3 BYTE serviceProviderName::spnLength

8.984 ServingSystemInfo Struct Reference

Data Fields

- BYTE registrationState
- BYTE csAttachState
- BYTE psAttachState
- BYTE selectedNetwork
- BYTE radioInterfaceNo
- BYTE radioInterfaceList [255]
- BYTE hdrPersonality

8.984.1 Detailed Description

This structure will hold the serving system parameters information

Parameters

registrationState	- Registration state of the mobile • 0 - QMI_NAS_NOT_REGISTERED Not registered;mobile is not currently searching for a new network to provide service • 1 - QMI_NAS_REGISTERED Registered with a network • 2 - QMI_NAS_NOT_REGISTERED_SEARCHING Not registered, but mobile is currently searching for a new network to provide service • 3 - QMI_NAS_REGISTRATION_DENIED Registration denied by the visible network • 4 - QMI_NAS_REGISTRATION_UNKNOWN Registration state is unknown
csAttachState	- Circuit Switch domain attach state of the mobile • 0 - Unknown or not applicable • 1 - Attached • 2 - Detached
psAttachState	- Packet domain attach state of the mobile • 0 - Unknown or not applicable • 1 - Attached • 2 - Detached
selectedNetwork	- Type of selected radio access network • 0x00 - Unknown • 0x01 - 3GPP2 network • 0x02 - 3GPP network
radioInterfaceNo	- Number of radio interfaces currently in use; this indicates how many radio_if identifiers follow this field
radioInterface-List	- Radio interface currently in use (each is 1 byte) • 0x00 - None (no service) • 0x01 - cdma2000 1X • 0x02 - cdma2000 HRPD (1xEV-DO) • 0x03 - AMPS • 0x04 - GSM • 0x05 - UMTS • 0x08 - LTE
hdrPersonality	- HDR personality information (valid only for EVDO) • 0x00 - Unknown • 0x01 - HRPD • 0x02 - eHRPD

Note: None

8.984.2 Field Documentation

8.984.2.1 BYTE ServingSystemInfo::csAttachState

8.984.2.2 BYTE ServingSystemInfo::hdrPersonality

8.984.2.3 BYTE ServingSystemInfo::psAttachState

8.984.2.4 BYTE ServingSystemInfo::radioInterfaceList[255]

8.984.2.5 BYTE ServingSystemInfo::radioInterfaceNo

8.984.2.6 BYTE ServingSystemInfo::registrationState

8.984.2.7 BYTE ServingSystemInfo::selectedNetwork

8.985 servSystem Struct Reference

Data Fields

- BYTE regState
- BYTE csAttachState
- BYTE psAttachState
- BYTE selNetwork
- BYTE numRadioInterfaces
- BYTE radioInterface [0x0A]

8.985.1 Detailed Description

This structure contains the Serving System parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

regState	• Registration state - Registration state of the mobile • Values: – 0 - Not Registered; mobile is not currently searching for a new network to provide service – 1 - Registered with a network – 2 - Not registered, but mobile is currently searching for a new network to provide service – 3 - Registration denied by visible network – 4 - Registration state is unknown
csAttachState	• CS Attach State - Circuit-switched domain attach state of the mobile • Values: – 0 - Unknown or not applicable – 1 - Attached – 2 - Detached
psAttachState	• PS Attach State - Packet-switched domain attach state of the mobile • Values: – 0 - Unknown or not applicable – 1 - Attached – 2 - Detached

selNetwork	• Selected Network - Type of selected radio access network • Values: – 0 - Unknown – 1 - 3GPP2 network – 2 - 3GPP network
numRadio-Interfaces	• In Use Radio Interfaces Number – Number of radio interfaces currently in use – defaults to zero
radioInterface	• Radio Interface(s) modem discovered • Values: – 0x00 - RADIO_IF_NO_SVC - None(no service) – 0x01 - RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x03 - RADIO_IF_AMPS - AMPS – 0x04 - RADIO_IF_GSM - GSM – 0x05 - RADIO_IF_UMTS - UMTS – 0x08 - RADIO_IF_LTE - LTE

8.985.2 Field Documentation

8.985.2.1 BYTE servSystem::csAttachState

8.985.2.2 BYTE servSystem::numRadioInterfaces

8.985.2.3 BYTE servSystem::psAttachState

8.985.2.4 BYTE servSystem::radioInterface[0x0A]

8.985.2.5 BYTE servSystem::regState

8.985.2.6 BYTE servSystem::selNetwork

8.986 sessionInfo Union Reference

Data Fields

- struct omaDmFotaTlv omaDmFota
- struct omaDmConfigTlv omaDmConfig
- struct omaDmNotificationsTlv omaDmNotifications

8.986.1 Detailed Description

This union sessionInfo consist of omaDmFotaTlv, omaDmConfigTlv and omaDmNotificationsTlv, out of which one will be unpacked against pEventFields.

8.986.2 Field Documentation

8.986.2.1 struct omaDmConfigTlv sessionInfo::omaDmConfig

8.986.2.2 struct omaDmFotaTlv sessionInfo::omaDmFota

8.986.2.3 struct omaDmNotificationsTlv sessionInfo::omaDmNotifications

8.987 sessionInfoExt Union Reference

Data Fields

- struct omaDmFotaTlvExt omaDmFota
- struct omaDmConfigTlvExt omaDmConfig

8.987.1 Detailed Description

This union sessionInfo consist of omaDmFotaTlv and omaDmConfigTlv, out of which one will be unpacked against pEventFields.

8.987.2 Field Documentation

8.987.2.1 struct omaDmConfigTlvExt sessionInfoExt::omaDmConfig

8.987.2.2 struct omaDmFotaTlvExt sessionInfoExt::omaDmFota

8.988 sessionInfoTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG sessionType
- sessionInformation sessionInfo

8.988.1 Detailed Description

Structure used to store all sessionInfo(Union)TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
sessionType	- sessiontype Value

8.988.2 Field Documentation

8.988.2.1 sessionInformation sessionInfoTlv::sessionInfo

8.988.2.2 ULONG sessionInfoTlv::sessionType

8.988.2.3 BYTE sessionInfoTlv::TlvPresent

8.989 sessionInfoTlvExt Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG sessionType
- sessionInformationExt sessionInfo

8.989.1 Detailed Description

Structure used to store all sessionInfo(Union)TLV Value.

Parameters

TlvPresent	- Boolean indicating the presence of the TLV in the QMI response
sessionType	- sessiontype Value

8.989.2 Field Documentation

8.989.2.1 sessionInformationExt sessionInfoTlvExt::sessionInfo

8.989.2.2 ULONG sessionInfoTlvExt::sessionType

8.989.2.3 BYTE sessionInfoTlvExt::TlvPresent

8.990 SetAudioPathConfigReq Struct Reference

Data Fields

- BYTE Profile
- BYTE * pECMode
- BYTE * pNSEnable
- WORD * pTXGain
- WORD * pDTMFTXGain
- WORD * pCodecSTGain
- TXPCMIIRFltr * pTXPCMIIRFltr
- RXPCMIIRFltr * pRXPCMIIRFltr
- BYTE * pRXAVCAGCSwitch
- BYTE * pTXAVCSwitch
- RXAGCList * pRXAGCList
- RXAVCList * pRXAVCList
- TXAGCList * pTXAGCList

8.990.1 Detailed Description

This structure contains the SLQSSetAudioPathConfig request parameters.

Parameters

Profile	[Mandatory] • Audio Profile – 0-9

pECMode	[Optional] • AV_EC – 0 - Echo cancellation off – 1 - Handset echo mode – 2 - Headset mode – 3 - Car kit mode – 4 - Speaker Mode
pNSEnable	[Optional] • Noise Suppression – 0 - Noise suppression off – 1 - Noise suppression on
pTXGain	[Optional] • TX Voice volume – 0x0000 - 0xffff
pDTMFTXGain	[Optional] • AV_DTMFTXG – 0x0000 - 0xffff
pCodecSTGain	[Optional] • AV_CODECSTG – 0x0000 - 0xffff
pTXPCMIIRFltr	[Optional] • See TXPCMIIRFltr for more information
pRXPCMIIRFltr	[Optional] • See RXPCMIIRFltr for more information
pRXAVCAGC-Switch	[Optional] • RX AVC/AGC Switch
pTXAVCSwitch	[Optional] • TX AVC Switch
pRXAGCList	[Optional] • See RXAGCList for more information
pRXAVCList	[Optional] • See RXAVCList for more information
pTXAGCList	[Optional] • See TXAGCList for more information

8.990.2 Field Documentation

8.990.2.1 WORD* SetAudioPathConfigReq::pCodecSTGain

8.990.2.2 WORD* SetAudioPathConfigReq::pDTMFTXGain

8.990.2.3 BYTE* SetAudioPathConfigReq::pECMode

8.990.2.4 BYTE* SetAudioPathConfigReq::pNSEnable

8.990.2.5 BYTE SetAudioPathConfigReq::Profile

8.990.2.6 RXAGCList* SetAudioPathConfigReq::pRXAGCList

8.990.2.7 BYTE* SetAudioPathConfigReq::pRXAVCAGCSwitch

8.990.2.8 RXAVCList* SetAudioPathConfigReq::pRXAVCList

8.990.2.9 RXPCMIIRFltr* SetAudioPathConfigReq::pRXPCMIIRFltr

8.990.2.10 TXAGCList* SetAudioPathConfigReq::pTXAGCList

8.990.2.11 BYTE* SetAudioPathConfigReq::pTXAVCSwitch

8.990.2.12 WORD* SetAudioPathConfigReq::pTXGain

8.990.2.13 TXPCMIIRFltr* SetAudioPathConfigReq::pTXPCMIIRFltr

8.991 SetAudioProfileReq Struct Reference

Data Fields

- BYTE Profile
- BYTE EarMute
- BYTE MicMute
- BYTE Generator
- BYTE Volume

8.991.1 Detailed Description

This structure contains the SLQSSetAudioProfile request parameters.

Parameters

Profile	• Audio Profile – 0 - Handset – 1 - Headset – 2 - Car Kit – 3 - Speaker phone – 4 - Auxiliary – 5 - TTY – 6 - Auxiliary external PCM – 7 - Primary external PCM – 8 - External slave PCM – 9 - I2S

EarMute	• Ear Mute Setting – 0 - unmuted – 1 - muted
MicMute	• MIC Mute Setting – 0 - unmuted – 1 - muted
Generator	• Audio Generator – 0 - Voice – 1 - Key Beep – 2 - MIDI
Volume	• Audio Volume Level – 0 to 7

8.991.2 Field Documentation

8.991.2.1 BYTE SetAudioProfileReq::EarMute

8.991.2.2 BYTE SetAudioProfileReq::Generator

8.991.2.3 BYTE SetAudioProfileReq::MicMute

8.991.2.4 BYTE SetAudioProfileReq::Profile

8.991.2.5 BYTE SetAudioProfileReq::Volume

8.992 SetAudioVolTLBConfigReq Struct Reference

Data Fields

- BYTE Profile
- BYTE Generator
- BYTE Volume
- BYTE Item
- WORD VolValue

8.992.1 Detailed Description

This structure contains the SLQSSetAudioVolTLBConfig request parameters

Parameters

Profile	• Audio Profile – 0-9

Generator	• Audio Generator – 0-2
Volume	• Audio Volume Level – 0-7
Item	• Item – 13 - AV_RXVOLDB – 14 - AV_DTMFVOLDB – 15 - AV_PAD
Value	• Value to be set to the volume table

8.992.2 Field Documentation

8.992.2.1 BYTE SetAudioVolTLBConfigReq::Generator

8.992.2.2 BYTE SetAudioVolTLBConfigReq::Item

8.992.2.3 BYTE SetAudioVolTLBConfigReq::Profile

8.992.2.4 BYTE SetAudioVolTLBConfigReq::Volume

8.992.2.5 WORD SetAudioVolTLBConfigReq::VolValue

8.993 SetAudioVolTLBConfigResp Struct Reference

Data Fields

- WORD ResCode

8.993.1 Detailed Description

This structure contains the SLQSSetAudioVolTLBConfig response parameters.

Parameters

ResCode	• Result of requested item

8.993.2 Field Documentation

8.993.2.1 WORD SetAudioVolTLBConfigResp::ResCode

8.994 setCustomSettingV2 Struct Reference

Data Fields

- CHAR cust_id [64+1]
- WORD value_length
- BYTE cust_value [8+1]

8.994.1 Detailed Description

This structure contains customization settings set to modem

Parameters

cust_id[IN]	• Customization ID (Maximum 64 bytes)
value_length[IN]	• length of cust_value field
cust_value[IN]	• Customization Setting Value (Maximum 8 bytes)

8.994.2 Field Documentation

8.994.2.1 CHAR setCustomSettingV2::cust_id[64+1]

8.994.2.2 BYTE setCustomSettingV2::cust_value[8+1]

8.994.2.3 WORD setCustomSettingV2::value_length

8.995 setDyingGaspCfg Struct Reference

Data Fields

- BYTE * pDestSMSNum
- BYTE * pDestSMSContent

8.995.1 Detailed Description

This struture contains the TLV required to get the Dysing GASP Config.

Parameters

pDestSMSNum[-OUT]	• SMS Destination Number as string of 8 bit ASCII Characters Max 20 chars. • Optional parameter.
pDestSMS-Content[OUT]	• SMS COntent as a string of 8 bit ASCII text characters Max 160 chars. • Optional parameter.

8.995.2 Field Documentation

8.995.2.1 BYTE* setDyingGaspCfg::pDestSMSContent

8.995.2.2 BYTE* setDyingGaspCfg::pDestSMSNum

8.996 SetIMSSMSConfigReq Struct Reference

Data Fields

- BYTE * pSMSFormat
- BYTE * pSMSOverIPNwInd
- BYTE * pPhoneCtxtURILen
- BYTE * pPhoneCtxtURI

8.996.1 Detailed Description

This structure contains the SLQSSetIMSSMSConfig request parameters.

Parameters

pSMSFormat	• SMS format – 0 - 3GPP – 1 - 3GPP2
pSMSOverIPNw-Ind	• SMS over IP Network Indication Flag – TRUE - Turn on mobile-originated SMS – FALSE - Turn off mobile-originated SMS
pPhoneCtxtURI-Len	• Length of Phone context Universal Resource Identifier to follow
pPhoneCtxtURI	• Phone context universal resource identifier • Length of this string must be specified in pPhoneCtxtURILen parameter

8.996.2 Field Documentation

8.996.2.1 BYTE* SetIMSSMSConfigReq::pPhoneCtxtURI

8.996.2.2 BYTE* SetIMSSMSConfigReq::pPhoneCtxtURILen

8.996.2.3 BYTE* SetIMSSMSConfigReq::pSMSFormat

8.996.2.4 BYTE* SetIMSSMSConfigReq::pSMSOverIPNwInd

8.997 SetIMSSMSConfigResp Struct Reference

Data Fields

- BYTE * pSettingResp

8.997.1 Detailed Description

This structure contains the SLQSSetIMSSMSConfig response parameters.

Parameters

pSettingResp	• Settings standard response type. A settings specific error code is returned when the standard response error type is QMI_ERR_CAUSE_CODE

8.997.2 Field Documentation

8.997.2.1 BYTE* SetIMSSMSConfigResp::pSettingResp

8.998 SetIMSUserConfigReq Struct Reference

Data Fields

- BYTE * pIMSDomainLen
- BYTE * pIMSDomain

8.998.1 Detailed Description

This structure contains the SLQSSetIMSUserConfig request parameters.

Parameters

pIMSDomainLen	• Length of IMS Domain Name to follow
pIMSDomain	• IMS domain name

8.998.2 Field Documentation

8.998.2.1 BYTE* SetIMSUserConfigReq::pIMSDomain

8.998.2.2 BYTE* SetIMSUserConfigReq::pIMSDomainLen

8.999 SetIMSUserConfigResp Struct Reference

Data Fields

- BYTE * pSettingResp

8.999.1 Detailed Description

This structure contains the SLQSSetIMSUserConfig response parameters.

Parameters

pSettingResp	• Settings standard response type. A settings specific error code is returned when the standard response error type is QMI_ERR_CAUSE_CODE

8.999.2 Field Documentation

8.999.2.1 BYTE* SetIMSUserConfigResp::pSettingResp

8.1000 SetIMSVoIPConfigReq Struct Reference

Data Fields

- WORD * pSessionExpiryTimer
- WORD * pMinSessionExpiryTimer
- BYTE * pAmrWbEnable
- BYTE * pScrAmrEnable
- BYTE * pScrAmrWbEnable
- BYTE * pAmrMode
- WORD * pAmrWBMode
- BYTE * pAmrOctetAligned
- BYTE * pAmrWBOctetAligned
- WORD * pRingingTimer
- WORD * pRingBackTimer
- WORD * pRTPRTCPInactTimer

8.1000.1 Detailed Description

This structure contains the SLQSSetIMSVoIPConfig request parameters.

Parameters

pSessionExpiry-Timer	• Session duration, in seconds
pMinSession-ExpiryTimer	• Minimum allowed value for session expiry timer, in seconds
pAmrWbEnable	• Flag to enable/disable Adaptive Multirate Codec(AMR) WideBand(WB) audio • Values: – True - Enable – False - Disable

pScrAmrEnable	• Flag to enable/disable Source Control Rate(SCR) for AMR NarrowBand (NB) • Values: – True - Enable – False - Disable
pScrAmrWb-Enable	• Flag to enable/disable SCR for AMR WB Audio • Values: – True - Enable – False - Disable
pAmrMode	• BitMask for AMR NB modes allowed • Values: – 0x1 - 4.75 kbps – 0x2 - 5.15 kbps – 0x4 - 5.9 kbps – 0x8 - 6.17 kbps – 0x10 - 7.4 kbps – 0x20 - 7.95 kbps – 0x40 - 10.2 kbps – 0x80 - 12.2 kbps
pAmrWBMode	• BitMask for AMR WB modes allowed • Values: – 0x1 - 6.60 kbps – 0x2 - 8.85 kbps – 0x4 - 12.65 kbps – 0x8 - 14.25 kbps – 0x10 - 15.85 kbps – 0x20 - 18.25 kbps – 0x40 - 19.85 kbps – 0x80 - 23.05 kbps – 0x100 - 23.85 kbps
pAmrOctet-Aligned	• Flag to indicate if the octet is aligned for AMR NB Audio • Values: – True - Aligned – False - Not aligned, Bandwidth Efficient mode
pAmrWBOctet-Aligned	• Flag to indicate if the octet is aligned for AMR WB Audio • Values: – True - Aligned – False - Not aligned, Bandwidth Efficient mode

pRingingTimer	• Duration of ringing timer, in seconds. The ringing timer starts on the ringing event. If the call is not answered within the duration of this timer, the call is disconnected.
pRingBackTimer	• Duration of ringback timer, in seconds. The ringback timer starts on the ringback event. If the call is not answered within the duration of this timer, the call is disconnected.
pRTPRTCP-InactTimer	• Duration of RTP/RTCP inactivity timer, in seconds. If no RTP/RTCP packet is received prior to the expiry of this timer, the call is disconnected.

8.1000.2 Field Documentation

8.1000.2.1 BYTE∗ SetIMSVoIPConfigReq::pAmrMode

8.1000.2.2 BYTE∗ SetIMSVoIPConfigReq::pAmrOctetAligned

8.1000.2.3 BYTE∗ SetIMSVoIPConfigReq::pAmrWbEnable

8.1000.2.4 WORD∗ SetIMSVoIPConfigReq::pAmrWBMode

8.1000.2.5 BYTE∗ SetIMSVoIPConfigReq::pAmrWBOctetAligned

8.1000.2.6 WORD∗ SetIMSVoIPConfigReq::pMinSessionExpiryTimer

8.1000.2.7 WORD∗ SetIMSVoIPConfigReq::pRingBackTimer

8.1000.2.8 WORD∗ SetIMSVoIPConfigReq::pRingingTimer

8.1000.2.9 WORD∗ SetIMSVoIPConfigReq::pRTPRTCPInactTimer

8.1000.2.10 BYTE∗ SetIMSVoIPConfigReq::pScrAmrEnable

8.1000.2.11 BYTE∗ SetIMSVoIPConfigReq::pScrAmrWbEnable

8.1000.2.12 WORD∗ SetIMSVoIPConfigReq::pSessionExpiryTimer

8.1001 SetIMSVoIPConfigResp Struct Reference

Data Fields

- BYTE ∗ pSettingResp

8.1001.1 Detailed Description

This structure contains the SLQSSetIMSVoIPConfig response parameters.

Parameters

pSettingResp	• Settings standard response type. A settings specific error code is returned when the standard response error type is QMI_ERR_CAUSE_CODE

8.1001.2 Field Documentation

8.1001.2.1 BYTE* SetIMSVoIPConfigResp::pSettingResp

8.1002 setIntfaceCfgTlv Struct Reference

Data Fields

- ULONG CfgValue

8.1002.1 Detailed Description

This structure contains the parameters for host usb interface composition

Parameters

CfgValue	• Host composition bit mask, see supported USB interface bitmasks, not supported by QMI object setting for 9x50 modules – 0x00000001 - DIAG interface – 0x00000002 - ADB interface – 0x00000004 - NMEA interface – 0x00000008 - MODEM interface – 0x00000010 - RESERVED5 – 0x00000020 - RESERVED6 – 0x00000040 - RESERVED7 – 0x00000080 - RESERVED8 – 0x00000100 - RMENT0 interface – 0x00000200 - RESERVED10 – 0x00000400 - RMENT1 interface – 0x00000800 - RESERVED12 – 0x00001000 - MBIM interface – 0x00002000 - RESERVED14 – 0x00004000 - RNDIS interface – 0x00008000 - RESERVED16 – 0x00010000 - AUDIO interface – 0x00020000 - RESERVED18 – 0x00080000 - ECM interface – 0x00100000 - RESERVED21 – 0x00200000 - RESERVED22 – 0xFFC00000 - RESERVED

8.1002.2 Field Documentation

8.1002.2.1 ULONG setIntfaceCfgTlv::CfgValue

8.1003 SetLocGetServerCallbackPara Struct Reference

Data Fields

- LocGetServerReq * pReq
- tFNGetServer * pCallback

8.1003.1 Detailed Description

Get LOC Server Indication callback argument.

Parameters

pReq[IN]	• See LocGetServerReq for more information.
pCallback[IN]	• Callback function pointer (0 - Disable) • See tFNGetServer for more information.

8.1003.2 Field Documentation

8.1003.2.1 tFNGetServer* SetLocGetServerCallbackPara::pCallback

8.1003.2.2 LocGetServerReq* SetLocGetServerCallbackPara::pReq

8.1004 SetLocSetServerCallbackParam Struct Reference

Data Fields

- LocSetServerReq * pReq
- tFNSetServer pCallback

8.1004.1 Detailed Description

Set LOC Server Indication callback parameter.

Parameters

pReq[IN]	• See LocSetServerReq for more information.
pCallback[IN]	• Callback function pointer (0 - Disable) • See tFNSetServer for more information.

8.1004.2 Field Documentation

8.1004.2.1 tFNSetServer SetLocSetServerCallbackParam::pCallback

8.1004.2.2 LocSetServerReq* SetLocSetServerCallbackParam::pReq

8.1005 SetM2MAudioAVCFGReq Struct Reference

Data Fields

- BYTE Profile
- BYTE Device
- BYTE PIFACEId
- PCMparams * pPCMParams

8.1005.1 Detailed Description

This structure contains the SLQSSetM2MAudioAVCFG request parameters.

Parameters

Profile	• Audio Profile – 0-5
Device	• ACDB Device • See qaGobiApiTableSwiAudio.h for more information on ACDB Device
PIFACEId	• Physical Interface • See qaGobiApiTableSwiAudio.h for more information on physical interface
pPCMParams	• PCM parameters • See PCMparams for more information

8.1005.2 Field Documentation

8.1005.2.1 BYTE SetM2MAudioAVCFGReq::Device

8.1005.2.2 BYTE SetM2MAudioAVCFGReq::PIFACEId

8.1005.2.3 PCMparams* SetM2MAudioAVCFGReq::pPCMParams

8.1005.2.4 BYTE SetM2MAudioAVCFGReq::Profile

8.1006 SetM2MAudioLPBKReq Struct Reference

Data Fields

- BYTE Enable

8.1006.1 Detailed Description

This structure contains the SLQSSetM2MAudioLPBK request parameters.

Parameters

Enable	• Operation to be performed – 0 - stop – 1 - VOCODER loop – 2 - internal codec loop

8.1006.2 Field Documentation

8.1006.2.1 BYTE SetM2MAudioLPBKReq::Enable

8.1007 SetM2MAudioProfileReq Struct Reference

Data Fields

- BYTE Profile
- BYTE * pEarMute
- BYTE * pMicMute
- BYTE * pGenerator
- BYTE * pVolume
- BYTE * pCwtMute

8.1007.1 Detailed Description

This structure contains the SLQSSetM2MAudioProfile request parameters.

Parameters

Profile	• Audio Profile Number – 0-5
pEarMute	• Ear Mute – 0 - mute – 1 - unmute
pMicMute	• Mic Mute – 0 - mute – 1 - unmute
pGenerator	• Generator – 0 - voice

pVolume	• Set RX Volume level – 0-5
pCwtMute	• Call Waiting Tone Mute – 0 - Mute – 1 - UnMute

8.1007.2 Field Documentation

8.1007.2.1 BYTE* SetM2MAudioProfileReq::pCwtMute

8.1007.2.2 BYTE* SetM2MAudioProfileReq::pEarMute

8.1007.2.3 BYTE* SetM2MAudioProfileReq::pGenerator

8.1007.2.4 BYTE* SetM2MAudioProfileReq::pMicMute

8.1007.2.5 BYTE SetM2MAudioProfileReq::Profile

8.1007.2.6 BYTE* SetM2MAudioProfileReq::pVolume

8.1008 SetM2MAudioVolumeReq Struct Reference

Data Fields

- BYTE Profile
- BYTE Generator
- BYTE Level

8.1008.1 Detailed Description

This structure contains the SLQSSetM2MAudioProfile request parameters.

Parameters

Profile	• Audio Profile Number – 0-5
Generator	• Generator – 0 - voice
Level	• Audio volume level – 0-5

8.1008.2 Field Documentation

8.1008.2.1 BYTE SetM2MAudioVolumeReq::Generator

8.1008.2.2 BYTE SetM2MAudioVolumeReq::Level

8.1008.2.3 BYTE SetM2MAudioVolumeReq::Profile

8.1009 SetM2MAVMuteReq Struct Reference

Data Fields

- BYTE Profile
- BYTE EarMute
- BYTE MicMute
- BYTE * pCwtMute

8.1009.1 Detailed Description

This structure contains the SLQSSetM2MAVMute request parameters.

Parameters

Profile	• Audio Profile Number – 0-5
EarMute	• Ear Mute – 0-1
MicMute	• Mic Mute – 0-1
pCwtMute	[Optional] • Call Waiting Tone Mute – 0-1

8.1009.2 Field Documentation

8.1009.2.1 BYTE SetM2MAVMuteReq::EarMute

8.1009.2.2 BYTE SetM2MAVMuteReq::MicMute

8.1009.2.3 BYTE* SetM2MAVMuteReq::pCwtMute

8.1009.2.4 BYTE SetM2MAVMuteReq::Profile

8.1010 SetM2MSpkrGainReq Struct Reference

Data Fields

- BYTE Profile
- WORD Value

8.1010.1 Detailed Description

This structure contains the SLQSSetM2MSpkrGain request parameters.

Parameters

Profile	• Audio Profile Number – 0-5
Value	• RX speakerphone gain – 0x0 - 0x7fff

8.1010.2 Field Documentation

8.1010.2.1 BYTE SetM2MSpkrGainReq::Profile

8.1010.2.2 WORD SetM2MSpkrGainReq::Value

8.1011 setPINProtection Struct Reference

Data Fields

- BYTE pinID
- BYTE pinOperation
- BYTE pinLength
- BYTE pinValue [255]

8.1011.1 Detailed Description

This structure contains the information about the pin protection parameters that need to be set.

Parameters

pinID	• Indicates the PIN ID to be enabled or disabled. – 1 - PIN1 (also called PIN) – 2 - PIN2 – 3 - Universal PIN – 4 - Hidden key
pinOperation	• Indicates whether the PIN is enabled or disabled. – 0 - Disable the PIN – 1 - Enable the PIN

pinLength	• Length of the following elements i.e. pin value.
pinValue[MAX_-DESCRIPTION-_LENGTH]	• PIN value. • This value is a sequence of ASCII characters.

8.1011.2 Field Documentation

8.1011.2.1 BYTE setPINProtection::pinID

8.1011.2.2 BYTE setPINProtection::pinLength

8.1011.2.3 BYTE setPINProtection::pinOperation

8.1011.2.4 BYTE setPINProtection::pinValue[255]

8.1012 SetRegMgrConfigReq Struct Reference

Data Fields

- WORD * pPriCSCFPort
- BYTE * pCSCFPortNameLen
- BYTE * pCSCFPortName
- BYTE * pIMSTestMode

8.1012.1 Detailed Description

This structure contains the SLQSSetRegMgrConfig request parameters.

Parameters

pPriCSCFPort	• Primary call session control function port
pCSCFPort-NameLen	• Length of the CSCF Port name parameter to follow
pCSCFPort-Name	• Call Session control port, fully qualified domain name • Length of this string must be specified in pCSCFPortNameLen parameter
pIMSTestMode	• IMS Test mode Enabled. – TRUE - Enable, no IMS registration – FALSE - Disable, IMS registration is initiated

8.1012.2 Field Documentation

8.1012.2.1 BYTE* SetRegMgrConfigReq::pCSCFPortName

8.1012.2.2 BYTE* SetRegMgrConfigReq::pCSCFPortNameLen

8.1012.2.3 BYTE* SetRegMgrConfigReq::pIMSTestMode

8.1012.2.4 WORD* SetRegMgrConfigReq::pPriCSCFPort

8.1013 SetRegMgrConfigResp Struct Reference

Data Fields

- BYTE * pSettingResp

8.1013.1 Detailed Description

This structure contains the SLQSSetRegMgrConfig response parameters.

Parameters

pSettingResp	• Settings standard response type. A settings specific error code is returned when the standard response error type is QMI_ERR_CAUSE_CODE

8.1013.2 Field Documentation

8.1013.2.1 BYTE* SetRegMgrConfigResp::pSettingResp

8.1014 setSignalStrengthInfo Struct Reference

Data Fields

- CDMARSSIThresh * pCDMARSSIThresh
- WORD * pCDMARSSIDelta
- CDMAECIOThresh * pCDMAECIOThresh
- WORD * pCDMAECIODelta
- HDRRSSIThresh * pHDRRSSIThresh
- WORD * pHDRRSSIDelta
- HDRECIOThresh * pHDRECIOThresh
- WORD * pHDRECIODelta
- HDRSINRThreshold * pHDRSINRThresh
- WORD * pHDRSINRDelta
- HDRIOThresh * pHDRIOThresh
- WORD * pHDRIODelta
- GSMRSSIThresh * pGSMRSSIThresh
- WORD * pGSMRSSIDelta
- WCDMARSSIThresh * pWCDMARSSIThresh
- WORD * pWCDMARSSIDelta
- WCDMAECIOThresh * pWCDMAECIOThresh
- WORD * pWCDMAECIODelta
- LTERSSIThresh * pLTERSSIThresh
- WORD * pLTERSSIDelta

- LTESNRThreshold * pLTESNRThresh
- WORD * pLTESNRDelta
- LTERSRQThresh * pLTERSRQThresh
- WORD * pLTERSRQDelta
- LTERSRPThresh * pLTERSRPThresh
- WORD * pLTERSRPDelta
- LTESigRptConfig * pLTESigRptConfig
- TDSCDMARSCPThresh * pTDSCDMARSCPThresh
- WORD * pTDSCDMARSCPDelta
- TDSCDMARSSIThresh * pTDSCDMARSSIThresh
- ULONG * pTDSCDMARSSIDelta
- TDSCDMAECIOThresh * pTDSCDMAECIOThresh
- ULONG * pTDSCDMAECIODelta
- TDSCDMASINRThresh * pTDSCDMASINRThresh
- ULONG * pTDSCDMASINRDelta

8.1014.1 Detailed Description

This structure contains the Signal Strength reporting thresholds Item information.

Parameters

pCDMARSSI-Thresh	• CDMA RSSI threshold List • See CDMARSSIThresh for more details
pCDMARSSI-Delta	• RSSI delta (in units of 0.1 dBm). • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pCDMAECIO-Thresh	• CDMA ECIO Threshold List • See CDMAECIOThresh for more details
pCDMAECIO-Delta	• ECIO delta (in units of 0.1 dB). • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pHDRRSSI-Thresh	• HDR RSSI Threshold List • See HDRRSSIThresh for more details
pHDRRSSIDelta	• RSSI delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pHDRECIO-Thresh	• HDR ECIO Threshold List • See HDRECIOThresh for more details
pHDRECIODelta	• ECIO delta (in units of 0.1 dB) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.

pHDRSINR-Thresh	• HDR SINR Threshold List • See HDRSINRThreshold for more details
pHDRSINRDelta	• SINR delta (in units of 1 SINR level) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pHDRIOThresh	• HDR IO Threshold List • See HDRIOThresh for more details
pHDRIODelta	• IO delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pGSMRSSI-Thresh	• GSM RSSI Threshold List • See GSMRSSIThresh for more details
pGSMRSSIDelta	• RSSI delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pWCDMARSSI-Thresh	• WCDMA RSSI Threshold List • See WCDMARSSIThresh for more details
pWCDMARSSI-Delta	• RSSI delta (in units of 0.1 dBm). • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pWCDMAECIO-Thresh	• WCDMA ECIO Threshold List • See WCDMAECIOThresh for more details
pWCDMAECIO-Delta	• ECIO delta (in units of 0.1 dB) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pLTERSSI-Thresh	• LTE RSSI Threshold List • See LTERSSIThresh for more details
pLTERSSIDelta	• RSSI delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pLTESNR-Thresh	• LTE SNR Threshold List • See LTESNRThreshold for more details

pLTESNRDelta	• SNR delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pLTERSRQ-Thresh	• LTE RSRQ Threshold List • See LTERSRQThresh for more details
pLTERSRQ-Delta	• RSRQ delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pLTERSRP-Thresh	• LTE RSRP Threshold List • See LTERSRPThresh for more details
pLTERSRPDelta	• RSRP delta (in units of 0.1 dBm). • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pLTESigRpt-Config	• LTE Signal Report Config • See LTESigRptConfig for more details
pTDSCDMARS-CPThresh	• TDSCDMA RSCP Threshold List • See TDSCDMARSCPThresh for more details
pTDSCDMARS-CPDelta	• RSCP delta (in units of 0.1 dBm) • A value of 0 is rejected with a QMI_ERR_INVALID_ARG error.
pTDSCDMARS-SIThresh	• TDSCDMA RSSI Threshold List • See TDSCDMARSSIThresh for more details
pTDSCDMARS-SIDelta	• RSSI delta (in dBm) used by TD-SCDMA.
pTDSCDMAECI-OThresh	• TDSCDMA ECIO Threshold List • See TDSCDMAECIOThresh for more details
pTDSCDMAECI-ODelta	• ECIO delta (in dB) used by TD-SCDMA
pTDSCDMASIN-RThresh	• TDSCDMA SINR Threshold List • See TDSCDMASINRThresh for more details
pTDSCDMASIN-RDelta	• SINR delta (in dB) used by TD-SCDMA.

8.1014.2 Field Documentation

8.1014.2.1 WORD* setSignalStrengthInfo::pCDMAECIODelta

8.1014.2.2 CDMAECIOThresh* setSignalStrengthInfo::pCDMAECIOThresh

8.1014.2.3 WORD* setSignalStrengthInfo::pCDMARSSIDelta

8.1014.2.4 CDMARSSIThresh* setSignalStrengthInfo::pCDMARSSIThresh

8.1014.2.5 WORD* setSignalStrengthInfo::pGSMRSSIDelta

8.1014.2.6 GSMRSSIThresh* setSignalStrengthInfo::pGSMRSSIThresh

8.1014.2.7 WORD* setSignalStrengthInfo::pHDRECIODelta

8.1014.2.8 HDRECIOThresh* setSignalStrengthInfo::pHDRECIOThresh

8.1014.2.9 WORD* setSignalStrengthInfo::pHDRIODelta

8.1014.2.10 HDRIOThresh* setSignalStrengthInfo::pHDRIOThresh

8.1014.2.11 WORD* setSignalStrengthInfo::pHDRRSSIDelta

8.1014.2.12 HDRRSSIThresh* setSignalStrengthInfo::pHDRRSSIThresh

8.1014.2.13 WORD* setSignalStrengthInfo::pHDRSINRDelta

8.1014.2.14 HDRSINRThreshold* setSignalStrengthInfo::pHDRSINRThresh

8.1014.2.15 WORD* setSignalStrengthInfo::pLTERSRPDelta

8.1014.2.16 LTERSRPThresh* setSignalStrengthInfo::pLTERSRPThresh

8.1014.2.17 WORD* setSignalStrengthInfo::pLTERSRQDelta

8.1014.2.18 LTERSRQThresh* setSignalStrengthInfo::pLTERSRQThresh

8.1014.2.19 WORD* setSignalStrengthInfo::pLTERSSIDelta

8.1014.2.20 LTERSSIThresh* setSignalStrengthInfo::pLTERSSIThresh

8.1014.2.21 LTESigRptConfig* setSignalStrengthInfo::pLTESigRptConfig

8.1014.2.22 WORD* setSignalStrengthInfo::pLTESNRDelta

8.1014.2.23 LTESNRThreshold* setSignalStrengthInfo::pLTESNRThresh

8.1014.2.24 ULONG* setSignalStrengthInfo::pTDSCDMAECIODelta

8.1014.2.25 TDSCDMAECIOThresh* setSignalStrengthInfo::pTDSCDMAECIOThresh

8.1014.2.26 WORD* setSignalStrengthInfo::pTDSCDMARSCPDelta

8.1014.2.27 TDSCDMARSCPThresh* setSignalStrengthInfo::pTDSCDMARSCPThresh

8.1014.2.28 ULONG∗ setSignalStrengthInfo::pTDSCDMARSSIDelta

8.1014.2.29 TDSCDMARSSIThresh∗ setSignalStrengthInfo::pTDSCDMARSSIThresh

8.1014.2.30 ULONG∗ setSignalStrengthInfo::pTDSCDMASINRDelta

8.1014.2.31 TDSCDMASINRThresh∗ setSignalStrengthInfo::pTDSCDMASINRThresh

8.1014.2.32 WORD∗ setSignalStrengthInfo::pWCDMAECIODelta

8.1014.2.33 WCDMAECIOThresh∗ setSignalStrengthInfo::pWCDMAECIOThresh

8.1014.2.34 WORD∗ setSignalStrengthInfo::pWCDMARSSIDelta

8.1014.2.35 WCDMARSSIThresh∗ setSignalStrengthInfo::pWCDMARSSIThresh

8.1015 SetSIPConfigReq Struct Reference

Data Fields

- WORD ∗ pSIPLocalPort
- ULONG ∗ pTimerSIPReg
- ULONG ∗ pSubscribeTimer
- ULONG ∗ pTimerT1
- ULONG ∗ pTimerT2
- ULONG ∗ pTimerTf
- BYTE ∗ pSigCompEnabled

8.1015.1 Detailed Description

This structure contains the SLQSSetSIPConfig request parameters.

Parameters

pSIPLocalPort	• Primary call session control function SIP port number
pTimerSIPReg	• Initial SIP registration duration from the User equipment, in seconds
pSubscribeTimer	• Duration of the subscription by the UE for IMS registration notifications, in seconds
pTimerT1	• RTT estimate, in milliseconds
pTimerT2	• The maximum retransmit interval for non-invite requests and invite responses, in milliseconds
pTimerTf	• Non-invite transaction timeout timer, in milliseconds

pSigComp-Enabled	• Sig Comp Status – TRUE - Enable – FALSE - Disable

8.1015.2 Field Documentation

8.1015.2.1 BYTE* SetSIPConfigReq::pSigCompEnabled

8.1015.2.2 WORD* SetSIPConfigReq::pSIPLocalPort

8.1015.2.3 ULONG* SetSIPConfigReq::pSubscribeTimer

8.1015.2.4 ULONG* SetSIPConfigReq::pTimerSIPReg

8.1015.2.5 ULONG* SetSIPConfigReq::pTimerT1

8.1015.2.6 ULONG* SetSIPConfigReq::pTimerT2

8.1015.2.7 ULONG* SetSIPConfigReq::pTimerTf

8.1016 SetSIPConfigResp Struct Reference

Data Fields

- BYTE * pSettingResp

8.1016.1 Detailed Description

This structure contains the SLQSSetSIPConfig response parameters.

Parameters

pSettingResp	• Settings standard response type. A settings specific error code is returned when the standard response error type is QMI_ERR_CAUSE_CODE

8.1016.2 Field Documentation

8.1016.2.1 BYTE* SetSIPConfigResp::pSettingResp

8.1017 sGetDeviceSeriesResult Struct Reference

Data Fields

- enum eGobiDeviceSeries eDevice
- ULONG uResult

8.1017.1 Detailed Description

This structure contains the Device Series

Parameters

eGobiDevice-Series	• The number of device in the device series
uResult	-eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

8.1017.2 Field Documentation

8.1017.2.1 enum eGobiDeviceSeries sGetDeviceSeriesResult::eDevice

8.1017.2.2 ULONG sGetDeviceSeriesResult::uResult

8.1018 sidNid Struct Reference

Data Fields

- WORD nid
- WORD sid

8.1018.1 Detailed Description

This structure contains the parameters for SidNid Information

Parameters

nid	• Network ID
sid	• System ID

8.1018.2 Field Documentation

8.1018.2.1 WORD sidNid::nid

8.1018.2.2 WORD sidNid::sid

8.1019 sigInfo Struct Reference

Data Fields

- RSSIThresh * pRSSIThresh
- ECIOThresh * pECIOThresh
- HDRSINRThresh * pHDRSINRThresh
- LTESNRThresh * pLTESNRThresh
- IOThresh * pIOThresh
- RSRQThresh * pRSRQThresh

- RSRPThresh * pRSRPThresh
- LTESigRptCfg * pLTESigRptCfg
- TDSCDMASINRCONFThresh * pTDSCDMASINRCONFThresh

8.1019.1 Detailed Description

This structure contains the 3gpp Configuration Item information.

Parameters

pRSSIThresh	• RSSI threshold List • See RSSIThresh for more details
pECIOThresh	• ECIO Threshold List • See ECIOThresh for more details
pHDRSINR-Thresh	• HDR SINR Threshold List • See HDRSINRThresh for more details
pLTESNR-Thresh	• LTE SNR Threshold List • See LTESNRThresh for more details
pIOThresh	• IO Threshold List • See IOThresh for more details
pRSRQThresh	• RSRQ Threshold List • See RSRQThresh for more details
pRSRPThresh	• RSRP Threshold List • See RSRPThresh for more details
pLTESigRptCfg	• LTE signal report config • See LTESigRptCfg for more details
pTDSCDMASIN-RCONFThresh	• TD-SCDMA SINR Threshold List • See TDSCDMASINRCONFThresh for more details

8.1019.2 Field Documentation

8.1019.2.1 ECIOThresh* sigInfo::pECIOThresh

8.1019.2.2 HDRSINRThresh* sigInfo::pHDRSINRThresh

8.1019.2.3 IOThresh* sigInfo::pIOThresh

8.1019.2.4 LTESigRptCfg* sigInfo::pLTESigRptCfg

8.1019.2.5 LTESNRThresh* sigInfo::pLTESNRThresh

8.1019.2.6 RSRPThresh* sigInfo::pRSRPThresh

8.1019.2.7 RSRQThresh* sigInfo::pRSRQThresh

8.1019.2.8 RSSIThresh* sigInfo::pRSSIThresh

8.1019.2.9 TDSCDMASINRCONFThresh* sigInfo::pTDSCDMASINRCONFThresh

8.1020 signalInfo Struct Reference

Data Fields

- BYTE signalType
- BYTE alertPitch
- BYTE signal

8.1020.1 Detailed Description

This structure contains Signal Information

Parameters

signalType	• Call identifier for the call.
alertPitch	• Signal Information
signal	• Caller ID Information

8.1020.2 Field Documentation

8.1020.2.1 BYTE signalInfo::alertPitch

8.1020.2.2 BYTE signalInfo::signal

8.1020.2.3 BYTE signalInfo::signalType

8.1021 SignalStrengthDataType Struct Reference

Data Fields

- BYTE thresholdsSize
- INT8 thresholds [5]

8.1021.1 Field Documentation

8.1021.1.1 INT8 SignalStrengthDataType::thresholds[5]

8.1021.1.2 BYTE SignalStrengthDataType::thresholdsSize

8.1022 simBusyStatus Struct Reference

Data Fields

- BYTE simBusyLength
- BYTE simBusy [255]

8.1022.1 Detailed Description

This structure contains Sim Busy Status Information.

Parameters

simBusyLength	• Number of sets of the following elements. i.e. simBusy
simBusy[MAX_-DESCRIPTION-_LENGTH]	• Indicates the status of the valid card. – 0 - Sim card is not busy – 1 - Sim card is busy

8.1022.2 Field Documentation

8.1022.2.1 BYTE simBusyStatus::simBusy[255]

8.1022.2.2 BYTE simBusyStatus::simBusyLength

8.1023 slot_t Struct Reference

Data Fields

- uint32_t uPhyCardStatus
- uint32_t uPhySlotStatus
- uint8_t bLogicalSlot
- uint8_t bICCIDLength
- uint8_t bICCID [255]

8.1023.1 Detailed Description

This structure contains information of the response parameters associated with a Get Slots Status API.

Parameters

uPhyCardStatus	• State of the card in the Pyhsical Slot Status. – 0x00 - Unknown. – 0x01 - Absent. – 0x02 - Present.
uPhySlotStatus	• State of the Physical Slot status. – 0x00 Inactive. – 0x01 Activate.
bLogicalSlot	• Logical Slot associated with this physical slot. THis is valid if the physical slot is active. – 1 - Slot 1. – 2 - Slot 2. – 3 - Slot 3. – 4 - Slot 4. – 5 - Slot 5.
bLogicalSlot	• Number of sets the sets of ICCCID
bICCID[MAX_ICCID_LENGTH]	• Contains the ICCID of the card in the physical slot.

8.1023.2 Field Documentation

8.1023.2.1 uint8_t slot_t::bICCID[255]

8.1023.2.2 uint8_t slot_t::bICCIDLength

8.1023.2.3 uint8_t slot_t::bLogicalSlot

8.1023.2.4 uint32_t slot_t::uPhyCardStatus

8.1023.2.5 uint32_t slot_t::uPhySlotStatus

8.1024 slotInf Struct Reference

Data Fields

- uint8_t cardState
- uint8_t upinState
- uint8_t upinRetries
- uint8_t upukRetries
- uint8_t errorState
- uint8_t numApp
- appStats AppStatus [10]

8.1024.1 Detailed Description

This structure contains information about the SLOTS present.

Parameters

cardState	• Indicates the state of the card for each slot. – 0 - Absent – 1 - Present – 2 - Error
upinState	• Indicates the state of UPIN. – 0 - Unknown – 1 - Enabled and not verified – 2 - Enabled and verified – 3 - Disabled – 4 - Blocked – 5 - Permanently blocked – 0xFF - Not Available
upinRetries	• Indicates the number of retries remaining to verify the UPIN. • If 0xFF, information not available.
upukRetries	• Indicates the number of retries remaining to unblock the UPIN. • If 0xFF, information not available.
errorState	• Indicates the reason for the card error, and is valid only when the card state is Error – 0 - Unknown – 1 - Power down – 2 - Poll error – 3 - No ATR received – 4 - Volt mismatch – 5 - Parity error – 6 - Unknown; possibly removed – 7 - Card returned technical problems – 0xFF - Not Available • Other values are possible and reserved for future use. • When an unknown value is received, it is to be handled as "Unknown".
numApp	• Indicates the number of applications available on the card. • The following block is repeated for each application. i.e. AppStatus. • If zero(0) then no AppStatus information exists.
AppStatus[MAX_NO_OF_APPLICATIONS]	• See appStats for more information.

8.1024.2 Field Documentation

8.1024.2.1 appStats slotInf::AppStatus[10]

8.1024.2.2 uint8_t slotInf::cardState

8.1024.2.3 uint8_t slotInf::errorState

8.1024.2.4 uint8_t slotInf::numApp

8.1024.2.5 uint8_t slotInf::upinRetries

8.1024.2.6 uint8_t slotInf::upinState

8.1024.2.7 uint8_t slotInf::upukRetries

8.1025 slotInfo Struct Reference

Data Fields

- BYTE cardState
- BYTE upinState
- BYTE upinRetries
- BYTE upukRetries
- BYTE errorState
- BYTE numApp
- appStatus AppStatus [10]

8.1025.1 Detailed Description

This structure contains information about the SLOTS present.

Parameters

cardState	• Indicates the state of the card for each slot. – 0 - Absent – 1 - Present – 2 - Error
upinState	• Indicates the state of UPIN. – 0 - Unknown – 1 - Enabled and not verified – 2 - Enabled and verified – 3 - Disabled – 4 - Blocked – 5 - Permanently blocked – 0xFF - Not Available
upinRetries	• Indicates the number of retries remaining to verify the UPIN. • If 0xFF, information not available.

upukRetries	• Indicates the number of retries remaining to unblock the UPIN. • If 0xFF, information not available.
errorState	• Indicates the reason for the card error, and is valid only when the card state is Error – 0 - Unknown – 1 - Power down – 2 - Poll error – 3 - No ATR received – 4 - Volt mismatch – 5 - Parity error – 6 - Unknown; possibly removed – 7 - Card returned technical problems – 0xFF - Not Available • Other values are possible and reserved for future use. • When an unknown value is received, it is to be handled as "Unknown".
numApp	• Indicates the number of applications available on the card. • The following block is repeated for each application. i.e. AppStatus. • If zero(0) then no AppStatus information exists.
AppStatus[MAX_NO_OF_APPLICATIONS]	• See appStatus for more information.

8.1025.2 Field Documentation

8.1025.2.1 appStatus slotInfo::AppStatus[10]

8.1025.2.2 BYTE slotInfo::cardState

8.1025.2.3 BYTE slotInfo::errorState

8.1025.2.4 BYTE slotInfo::numApp

8.1025.2.5 BYTE slotInfo::upinRetries

8.1025.2.6 BYTE slotInfo::upinState

8.1025.2.7 BYTE slotInfo::upukRetries

8.1026 slots_t Struct Reference

Data Fields

- slot_t uimSlotStatus [255]

8.1026.1 Detailed Description

This structure contains slots status.

Parameters

uimSlotStatus	• See slot_t

8.1026.2 Field Documentation

8.1026.2.1 slot_t slots_t::uimSlotStatus[255]

8.1027 slqsautoconnect Struct Reference

Data Fields

- BOOL action
- BYTE acsetting
- BYTE acroamsetting

8.1027.1 Detailed Description

structure contains autoconnect settings parameters

Parameters

action	• 0 - get autoconnect settings • 1 - set autoconnect settings
acsetting	• Current autoconnect setting: – 0x00 - Autoconnect disabled – 0x01 - Autoconnect enabled – 0x02 - Autoconnect paused (resume on powercycle)
acroamsetting	• Current autoconnect roaming status – 0x00 - Autoconnect always allowed – 0x01 - Autoconnect while in home service area only

8.1027.2 Field Documentation

8.1027.2.1 BYTE slqsautoconnect::acroamsetting

8.1027.2.2 BYTE slqsautoconnect::acsetting

8.1027.2.3 BOOL slqsautoconnect::action

8.1028 SLQSDeleteProfileParams Struct Reference

Data Fields

- BYTE profileType
- BYTE profileIndex

8.1028.1 Detailed Description

This structure contains the information about the profile to be deleted.

Parameters

profileType	• Identifies the type of profile – 0x00 - 3GPP • Note: Deletion of 3GPP2 profiles is not supported.
profileIndex	• Index of the configured profile to be deleted – Value between 1 - 16 (EM/MC73xx or earlier) – Value between 1 - 24 (EM/MC74xx onwards)

8.1028.2 Field Documentation

8.1028.2.1 BYTE SLQSDeleteProfileParams::profileIndex

8.1028.2.2 BYTE SLQSDeleteProfileParams::profileType

8.1029 slqsfwinfo_s Struct Reference

Data Fields

- CHAR modelid_str [20]
- CHAR bootversion_str [85]
- CHAR appversion_str [85]
- CHAR sku_str [15]
- CHAR packageid_str [85]
- CHAR carrier_str [20]
- CHAR priversion_str [16]
- CHAR cur_carr_name [17]
- CHAR cur_carr_rev [13]

8.1029.1 Detailed Description

SPKG CWE firmware image info structure

Parameters

modelid_str	• device model identifier string

bootversion_str	• firmware boot version string
appversion_str	• firmware application version string
sku_str	• SKU(PRI) string
packageid_str	• package identifier string
carrier_str	• carrier string • See qaGobiApiTableCarrierCodes.h for carrier codes
priversion_str	• PRI version string
cur_carr_name	• Current PRI Carrier Name
cur_carr_rev	• Current PRI Carrier Revision

8.1029.2 Field Documentation

8.1029.2.1 CHAR slqsfwinfo_s::appversion_str[85]

8.1029.2.2 CHAR slqsfwinfo_s::bootversion_str[85]

8.1029.2.3 CHAR slqsfwinfo_s::carrier_str[20]

8.1029.2.4 CHAR slqsfwinfo_s::cur_carr_name[17]

8.1029.2.5 CHAR slqsfwinfo_s::cur_carr_rev[13]

8.1029.2.6 CHAR slqsfwinfo_s::modelid_str[20]

8.1029.2.7 CHAR slqsfwinfo_s::packageid_str[85]

8.1029.2.8 CHAR slqsfwinfo_s::priversion_str[16]

8.1029.2.9 CHAR slqsfwinfo_s::sku_str[15]

8.1030 slqsfwpartno_s Struct Reference

Data Fields

- CHAR partno_str [15]

8.1030.1 Detailed Description

SPKG CWE firmware image part number structure

Parameters

partno_str	• part number string of the provided firmware image

8.1030.2 Field Documentation

8.1030.2.1 CHAR slqsfwpartno_s::partno_str[15]

8.1031 SlqsNas3GppNetworkInfo Struct Reference

Data Fields

- WORD MCC
- WORD MNC
- ULONG InUse
- ULONG Roaming
- ULONG Forbidden
- ULONG Preferred
- CHAR Description [255]

8.1031.1 Detailed Description

Contain the 3GPP network information.

Parameters

MCC	• Mobile Country Code
MNC	• Mobile Network Code
InUse	• Is the Network the current serving Network – 0 - Unknown – 1 - Current serving network – 2 - Not current serving network, available
Roaming	• Home/Roam Status of the Network – 0 - Unknown – 1 - Home – 2 - Roam

Forbidden	• Is the Network in the forbidden network list – 0 - Unknown – 1 - Forbidden – 2 - Not Forbidden
Preferred	• Is the Network in the Preferred network list – 0 - Unknown – 1 - Preferred – 2 - Not Preferred
Description	• Network Name/Description • This is a NULL terminated string.

8.1031.2 Field Documentation

8.1031.2.1 CHAR SlqsNas3GppNetworkInfo::Description[255]

8.1031.2.2 ULONG SlqsNas3GppNetworkInfo::Forbidden

8.1031.2.3 ULONG SlqsNas3GppNetworkInfo::InUse

8.1031.2.4 WORD SlqsNas3GppNetworkInfo::MCC

8.1031.2.5 WORD SlqsNas3GppNetworkInfo::MNC

8.1031.2.6 ULONG SlqsNas3GppNetworkInfo::Preferred

8.1031.2.7 ULONG SlqsNas3GppNetworkInfo::Roaming

8.1032 SlqsNasPCICellInfo Struct Reference

Data Fields

- ULONG freq
- WORD cellID
- ULONG GlobalCellID
- BYTE PlmnLen
- struct SlqsNasPcsDigit slqsNasPcsDigit [255]

8.1032.1 Detailed Description

Contain the PCI Info : Cell Information

Parameters

freq	• Aboslute cell's frequency. Range 0 to 65535.

cellID	• Cell ID.
GlobalCellID	• Global Cell ID.
PlmnLen	• Number of Plmn(slqsNasPcsDigit) information sets.
slqsNasPcsDigit	• See SlqsNasPcsDigit for more information.

8.1032.2 Field Documentation

8.1032.2.1 WORD SlqsNasPCICellInfo::cellID

8.1032.2.2 ULONG SlqsNasPCICellInfo::freq

8.1032.2.3 ULONG SlqsNasPCICellInfo::GlobalCellID

8.1032.2.4 BYTE SlqsNasPCICellInfo::PlmnLen

8.1032.2.5 struct SlqsNasPcsDigit SlqsNasPCICellInfo::slqsNasPcsDigit[255]

8.1033 SlqsNasPCIInfo Struct Reference

Data Fields

- BYTE PCICellInfoLen
- struct SlqsNasPCICellInfo PCICellInfo [255]
- WORD rsrp
- WORD rsrpRx0
- WORD rsrpRx1
- WORD rsrq
- WORD rsrqRx0
- WORD rsrqRx1

8.1033.1 Detailed Description

Contain the PCI Info

Parameters

PCICellInfoLen	• Number of PCI Cell Info(PCICellInfo) information sets.
PCICellInfo	• See SlqsNasPCICellInfo for more information.
rsrp	• Combined RSRP.

rsrpRx0	• Rx0 RSRP.
rsrpRx1	• Rx1 RSRP.
rsrq	• Combined RSRQ.
rsrqRx0	• Rx0 RSRQ.
rsrpRx1	• Rx1 RSRQ.

8.1033.2 Field Documentation

8.1033.2.1 struct SIqsNasPCICellInfo SIqsNasPCIInfo::PCICellInfo[255]

8.1033.2.2 BYTE SIqsNasPCIInfo::PCICellInfoLen

8.1033.2.3 WORD SIqsNasPCIInfo::rsrp

8.1033.2.4 WORD SIqsNasPCIInfo::rsrpRx0

8.1033.2.5 WORD SIqsNasPCIInfo::rsrpRx1

8.1033.2.6 WORD SIqsNasPCIInfo::rsrq

8.1033.2.7 WORD SIqsNasPCIInfo::rsrqRx0

8.1033.2.8 WORD SIqsNasPCIInfo::rsrqRx1

8.1034 SIqsNasPcsDigit Struct Reference

Data Fields

- WORD MCC
- WORD MNC
- BYTE includes_pcs_digit

8.1034.1 Detailed Description

Contain the PCS Digit information

Parameters

MCC	• Mobile Country Code
MNC	• Mobile Network Code

includes_pcs_-digit	• this field is use to interpret the length of corresponding MNC reported • 0x01 - MNC is a three-digit value • 0x00 - MNC is a two-digit value

8.1034.2 Field Documentation

8.1034.2.1 BYTE SlqsNasPcsDigit::includes_pcs_digit

8.1034.2.2 WORD SlqsNasPcsDigit::MCC

8.1034.2.3 WORD SlqsNasPcsDigit::MNC

8.1035 slqssendasyncsmsparams_s Struct Reference

Data Fields

- ULONG messageFormat
- ULONG messageSize
- BYTE * pMessage
- BYTE * pForceOnDC
- BYTE * pServiceOption
- BYTE * pFollowOnDC
- BYTE * pLinktimer
- BYTE * pSmsOnIms
- BYTE * pRetryMessage
- ULONG * pRetryMessageId
- ULONG * pUserData

8.1035.1 Detailed Description

This structure contains SMS parameters

Parameters

messageFormat	• Message format
	• Values:
	  – 0 - CDMA (IS-637B)
	  – 1 - 5 (Reserved)
	  – 6 - GSM/WCDMA PP

messageSize	• The length of the message contents in bytes
pMessage	• The message contents

pForceOnDC	• Force the message to be sent on the CDMA dedicated channel. • Values: – 0x00 - Do not care about the channel on which the message is sent – 0x01 - Request to send the message over the dedicated channel
pServiceOption	• Service option: • Values: – 0x00 - SO_AUTO - AUTO (choose the best service option) – 0x06 - SO_6 - Service option 6 – 0x0E - SO_14 - Service option 14
pFollowOnDC	• Flag to request not to disconnect the CDMA dedicated channel after the send operation is complete. • This TLV can be included if more messages are expected to follow. • Values: – 0x01 - FOLLOW_ON_DC_ON - On (don't disconnect after send operation) Any value other than 0x01 is treated as an absence of this TLV.
pLinktimer	• Keeps the GW SMS link open for the specified number of seconds; can be enabled if more messages are expected to follow
pSmsOnIms	• Indicates whether the message is to be sent on IMS. • Values: – 0x00 - Message is not to be sent on IMS – 0x01 - Message is to be sent on IMS – 0x02 to 0xFF - Reserved
pRetryMessage	• Indicates this message is a retry message. • Values: – 0x01 - WMS_MESSAGE_IS_A_RETRY - Message is a retry message Note: Any value other than 0x01 in this field is treated as an absence of this TLV.
pRetryMessage-Id	• Message ID to be used in the retry message. • The message ID specified here is used instead of the messsage ID encoded in the raw message.
pUserData	• Enables the control point to associate the request with the corresponding indication. • The control point might send numerous requests. • This TLV will help the control point to identify the request for which the received indication belongs.

8.1035.2 Field Documentation

8.1035.2.1 ULONG slqssendasyncsmsparams_s::messageFormat

8.1035.2.2 ULONG slqssendasyncsmsparams_s::messageSize

8.1035.2.3 BYTE* slqssendasyncsmsparams_s::pFollowOnDC

8.1035.2.4 BYTE* slqssendasyncsmsparams_s::pForceOnDC

8.1035.2.5 BYTE* slqssendasyncsmsparams_s::pLinktimer

8.1035.2.6 BYTE* slqssendasyncsmsparams_s::pMessage

8.1035.2.7 BYTE* slqssendasyncsmsparams_s::pRetryMessage

8.1035.2.8 ULONG* slqssendasyncsmsparams_s::pRetryMessageId

8.1035.2.9 BYTE* slqssendasyncsmsparams_s::pServiceOption

8.1035.2.10 BYTE* slqssendasyncsmsparams_s::pSmsOnIms

8.1035.2.11 ULONG* slqssendasyncsmsparams_s::pUserData

8.1036 slqssendsmsparams_s Struct Reference

Data Fields

- ULONG messageFormat
- ULONG messageSize
- BYTE * pMessage
- USHORT messageID
- ULONG messageFailureCode
- BYTE * pLinktimer
- BYTE * pSmsOnIms

8.1036.1 Detailed Description

This structure contains SMS parameters

Parameters

messageFormat[IN]	• Message format – 0 - CDMA (IS-637B) – 1 - 5 (Reserved) – 6 - GSM/WCDMA PP
messageSize[IN]	• The length of the message contents in bytes
pMessage[IN]	• The message contents in PDU format contains SMS header and payload message
pMessageID[OUT]	• message reference ID

pMessageFailureCode[OUT]	• (Optional) Message Failure Code • If cause code is not provided, then value will be 0xFFFFFFFF
pSmsOnIms[IN]	• (Optional) SMS on IMS • Indicates whether the message is to be sent on IMS. • Values: – 0x00 - Message is not to be sent on IMS – 0x01 - Message is to be sent on IMS – 0x02 to 0xFF - Reserved
pLinktimer[IN]	• (Optional) Link Timer • Keeps the GW SMS link open for the specified number of seconds; can be enabled if more messages are expected to follow

8.1036.2 Field Documentation

8.1036.2.1 ULONG slqssendsmsparams_s::messageFailureCode

8.1036.2.2 ULONG slqssendsmsparams_s::messageFormat

8.1036.2.3 USHORT slqssendsmsparams_s::messageID

8.1036.2.4 ULONG slqssendsmsparams_s::messageSize

8.1036.2.5 BYTE* slqssendsmsparams_s::pLinktimer

8.1036.2.6 BYTE* slqssendsmsparams_s::pMessage

8.1036.2.7 BYTE* slqssendsmsparams_s::pSmsOnIms

8.1037 slqsSessionStateInfo Struct Reference

Data Fields

- qaQmiInterfaceInfo * pQmiInterfaceInfo
- ULONG reconfiguration_required
- ULONG state
- ULONG sessionEndReason

8.1037.1 Detailed Description

Contains the session state information and information about the interface

Parameters

pQmiInterfaceInfo	• See qaQmiInterfaceInfo for more information

state	• Current Link Status – 1 Disconnected – 2 Connected – 3 Suspended (Unsupported) – 4 Authenticating
reconfiguration_-required	• Indicates if host needs to be reconfigured – 0 No need to reconfigure – 1 Reconfiguration required
sessionEnd-Reason	• See qaGobiApiTableCallEndReasons.h for Call End Reason

8.1037.2 Field Documentation

8.1037.2.1 qaQmiInterfaceInfo* slqsSessionStateInfo::pQmiInterfaceInfo

8.1037.2.2 ULONG slqsSessionStateInfo::reconfiguration_required

8.1037.2.3 ULONG slqsSessionStateInfo::sessionEndReason

8.1037.2.4 ULONG slqsSessionStateInfo::state

8.1038 SLQSSetDHCPv4ClientLeaseStatusCallbackParam Struct Reference

Data Fields

- BYTE instance
- tFNDHCPv4ClientLeaseStatus * pCallback

8.1038.1 Detailed Description

DHCPv4 client lease status message callback function parameter.

Parameters

instance[IN]	• QMI instance
pCallback[IN]	• Callback function pointer (0 - Disable)

8.1038.2 Field Documentation

8.1038.2.1 BYTE SLQSSetDHCPv4ClientLeaseStatusCallbackParam::instance

8.1038.2.2 tFNDHCPv4ClientLeaseStatus* SLQSSetDHCPv4ClientLeaseStatusCallbackParam::pCallback

8.1039 slqsSignalStrengthInfo Struct Reference

Data Fields

- USHORT signalStrengthReqMask
- USHORT rxSignalStrengthListLen
- struct rxSignalStrengthListElement rxSignalStrengthList [18]
- USHORT ecioListLen
- struct ecioListElement ecioList [18]
- INT32 Io
- BYTE sinr
- USHORT errorRateListLen
- struct errorRateListElement errorRateList [18]
- struct rsrqInformation rsrqInfo
- SHORT ltesnr
- SHORT ltersrp

8.1039.1 Detailed Description

This structure contains the Signal Strength Information

Parameters

signalStrength-ReqMask[IN]	• Request Mask – Request additional signal information for: Bit 0 - RSSI Information bit Valid values are: 0 - Do Not Request Additional Info for RSSI 1 - Request Additional Info for RSSI Bit 1 - ECIO Information bit Valid values are: 0 - Do Not Request Additional Info for ECIO 1 - Request Additional Info for ECIO Bit 2 - IO Information bit Valid values are: 0 - Do Not Request Additional Info for IO 1 - Request Additional Info for IO Bit 3 - SINR Information bit Valid values are: 0 - Do Not Request Additional Info for SINR 1 - Request Additional Info for SINR Bit 4 - ERROR RATE Information bit Valid values are: 0 - Do Not Request Additional Info for Error Rate 1 - Request Additional Info for Error Rate Bit 5 - RSRQ Information bit Valid values are: 0 - Do Not Request Additional Info for RSRQ 1 - Request Additional Info for RSRQ Bit 6 - LTE SNR information bit Valid values are: 0 - Do not request additional information for LTE SNR 1 - Request additional information for LTE SNR Bit 7 - LTE RSRP Information bit Valid values are: 0 - Do not request additional information for LTE RSRP 1 - Request additional information for LTE RSRP

rxSignalStrengthListLen[OUT]	• Number of elements in Receive Signal Strength List
rxSignalStrengthList[OUT]	• See rxSignalStrengthListElement for more information
ecioListLen[OUT]	• Number of elements in ECIO List
ecioList[OUT]	• See ecioListElement for more information
Io[OUT]	• Received Io in dBm; IO is only applicable for 1xEV-DO
sinr[OUT]	• SINR level – SINR is only applicable for 1xEV-DO; valid levels are 0 to 8 where maximum value for 0 - SINR_LEVEL_0 is -9 dB 1 - SINR_LEVEL_1 is -6 dB 2 - SINR_LEVEL_2 is -4.5 dB 3 - SINR_LEVEL_3 is -3 dB 4 - SINR_LEVEL_4 is -2 dB 5 - SINR_LEVEL_5 is +1 dB 6 - SINR_LEVEL_6 is +3 dB 7 - SINR_LEVEL_7 is +6 dB 8 - SINR_LEVEL_8 is +9 dB
errorRateListLen[OUT]	• Number of elements in Error Rate List
errorRateList[OUT]	• See errorRateListElement for more information
rsrqInfo[OUT]	• See rsrqInformation for more information
ltesnr[OUT]	• LTE SNR level as a scaled integer in units of 0.1 dB; e.g., -16 dB has a value of -160 and 24.6 dB has a value of 246. LTE SNR is included only when the current serving system is LTE
ltersrp[OUT]	• LTE SNR level as a scaled integer in units of 0.1 dB; e.g., -16 dB has a value of -160 and 24.6 dB has a value of 246. LTE SNR is included only when the current serving system is LTE

8.1039.2 Field Documentation

8.1039.2.1 struct ecioListElement slqsSignalStrengthInfo::ecioList[18]

8.1039.2.2 USHORT slqsSignalStrengthInfo::ecioListLen

8.1039.2.3 struct errorRateListElement slqsSignalStrengthInfo::errorRateList[18]

8.1039.2.4 USHORT slqsSignalStrengthInfo::errorRateListLen

8.1039.2.5 INT32 slqsSignalStrengthInfo::Io

8.1039.2.6 SHORT slqsSignalStrengthInfo::ltersrp

8.1039.2.7 SHORT slqsSignalStrengthInfo::lte snr

8.1039.2.8 struct rsrqInformation slqsSignalStrengthInfo::rsrqInfo

8.1039.2.9 struct rxSignalStrengthListElement slqsSignalStrengthInfo::rxSignalStrengthList[18]

8.1039.2.10 USHORT slqsSignalStrengthInfo::rxSignalStrengthListLen

8.1039.2.11 USHORT slqsSignalStrengthInfo::signalStrengthReqMask

8.1039.2.12 BYTE slqsSignalStrengthInfo::sinr

8.1040 SLQSSignalStrengthsIndReq Struct Reference

Data Fields

- BYTE rxSignalStrengthDelta
- BYTE ecioDelta
- BYTE ioDelta
- BYTE sinrDelta
- BYTE rsrqDelta
- BYTE ecioThresholdListLen
- SHORT ecioThresholdList [10]
- BYTE sinrThresholdListLen
- BYTE sinrThresholdList [5]
- WORD lteSnrDelta
- BYTE lteRsrpDelta

8.1040.1 Detailed Description

Structure for storing the input parameters passed for SLQSSetSignalStrengthsCallback by the user.

Parameters

rxSignal-StrengthDelta	• RSSI delta(in dBm) at which an event report indication, including the current RSSI, will be sent to the requesting control point.
ecioDelta	• ECIO delta at which an event report indication, ecioDelta including the current ECIO, will be sent to the requesting control point. • ECIO delta is an unsigned 1 byte value that increments in negative 0.5 dBm, e.g., ecio_delta of 2 means a change of -1 dBm.
ioDelta	• IO delta (in dBm) at which an event report indication, ioDelta including the current IO, will be sent to the requesting control point.
sinrDelta	• SINR delta level at which an event report indication, sinrDelta including the current SINR, will be sent to the requesting control point.
rsrqDelta	• RSRQ delta level at which an event report indication, including the current RSRQ, will be sent to the requesting control point.

ecioThreshold-ListLen	• Number of elements in the ECIO threshold list.
ecioThreshold-List	• A sequence of thresholds delimiting EcIo event reporting bands. Every time a new EcIo value crosses a threshold value, an event report indication message with the new ECIO value is sent to the requesting control point. For this field: – Maximum number of threshold values is 10 – At least one value must be specified.
sinrThreshold-ListLen	• Number of elements in the SINR threshold list.
sinrThreshold-List	• A sequence of thresholds delimiting SINR event reporting bands. Every time a new SINR value crosses a threshold value, an event report indication message with the new sinr value is sent to the requesting control point. For this field: – Maximum number of threshold values is 5 – At least one value must be specified.
ltesnrdelta	• LTE SNR delta level at which an event report indication, including the current SNR, will be sent to the requesting control point. LTE SNR delta level is an unsigned 2 byte value, representing the delta in units of 0.1 dB, e.g., lte_snr_delta of 3 means a change 0.3dB.
ltersrpdelta	-LTE RSRP delta level at which an event report -indication, including the current RSRP, will be sent -to the requesting control point. LTE RSRP delta -level is an unsigned 1 byte value, representing the -delta in dB.

Note

None

8.1040.2 Field Documentation

8.1040.2.1 BYTE SLQSSignalStrengthsIndReq::ecioDelta

8.1040.2.2 SHORT SLQSSignalStrengthsIndReq::ecioThresholdList[10]

8.1040.2.3 BYTE SLQSSignalStrengthsIndReq::ecioThresholdListLen

8.1040.2.4 BYTE SLQSSignalStrengthsIndReq::ioDelta

8.1040.2.5 BYTE SLQSSignalStrengthsIndReq::lteRsrpDelta

8.1040.2.6 WORD SLQSSignalStrengthsIndReq::lteSnrDelta

8.1040.2.7 BYTE SLQSSignalStrengthsIndReq::rsrqDelta

8.1040.2.8 BYTE SLQSSignalStrengthsIndReq::rxSignalStrengthDelta

8.1040.2.9 BYTE SLQSSignalStrengthsIndReq::sinrDelta

8.1040.2.10 BYTE SLQSSignalStrengthsIndReq::sinrThresholdList[5]

8.1040.2.11 BYTE SLQSSignalStrengthsIndReq::sinrThresholdListLen

8.1041 SLQSSignalStrengthsInformation Struct Reference

Data Fields

- struct rxSignalStrengthListElement rxSignalStrengthInfo
- struct ecioListElement ecioInfo
- ULONG io
- BYTE sinr
- struct errorRateListElement errorRateInfo
- struct rsrqInformation rsrqInfo
- struct lteSnrinformation lteSnrinfo
- struct lteRsrpinformation lteRsrpinfo

8.1041.1 Detailed Description

Structure for Received Signal Strength Information.

Parameters

rxSignal-StrengthInfo	• See rxSignalStrengthListElement for more information.
ecioInfo	• See ecioListElement for more information.
io	• Received IO in dBm; IO is only applicable for 1xEV-DO.
sinr	• SINR level – SINR is only applicable for 1xEV-DO; valid levels are 0 to 8 where maximum value for 0 - SINR_LEVEL_0 is -9 dB 1 - SINR_LEVEL_1 is -6 dB 2 - SINR_LEVEL_2 is -4.5 dB 3 - SINR_LEVEL_3 is -3 dB 4 - SINR_LEVEL_4 is -2 dB 5 - SINR_LEVEL_5 is +1 dB 6 - SINR_LEVEL_6 is +3 dB 7 - SINR_LEVEL_7 is +6 dB 8 - SINR_LEVEL_8 is +9 dB
errorRateInfo	• See errorRateListElement for more information.
rsrqInfo	• See rsrqInformation for more information.
lteSnrinfo	• See lteSnrinformation for more information.
lteRsrpinfo	• See lteRsrpinformation for more information.

Note

None

8.1041.2 Field Documentation

8.1041.2.1 struct ecioListElement SLQSSignalStrengthsInformation::ecioInfo

8.1041.2.2 struct errorRateListElement SLQSSignalStrengthsInformation::errorRateInfo

8.1041.2.3 ULONG SLQSSignalStrengthsInformation::io

8.1041.2.4 struct lteRsrpinformation SLQSSignalStrengthsInformation::lteRsrpinfo

8.1041.2.5 struct lteSnrinformation SLQSSignalStrengthsInformation::lteSnrinfo

8.1041.2.6 struct rsrqInformation SLQSSignalStrengthsInformation::rsrqInfo

8.1041.2.7 struct rxSignalStrengthListElement SLQSSignalStrengthsInformation::rxSignalStrengthInfo

8.1041.2.8 BYTE SLQSSignalStrengthsInformation::sinr

8.1042 SLQSTmdMitigationLvlRptCallbackParam Struct Reference

Data Fields

- TmdMitigationLvlIndReq * pReq
- tFNMitiLvlRpt pCallback

8.1042.1 Detailed Description

Thermal Mitigation callback parameter.

Parameters

pReq	• See TmdMitigationLvlIndReq for more information.
pCallback	• See tFNMitiLvlRpt for more information.

8.1042.2 Field Documentation

8.1042.2.1 tFNMitiLvlRpt SLQSTmdMitigationLvlRptCallbackParam::pCallback

8.1042.2.2 TmdMitigationLvlIndReq* SLQSTmdMitigationLvlRptCallbackParam::pReq

8.1043 slqsWdsEventInfo Struct Reference

Data Fields

- qaQmiInterfaceInfo * pQmiInterfaceInfo
- ULONG * pDormancyStatus
- ULONG * pDataBearer
- ULONG * pPacketsCountTX
- ULONG * pPacketsCountRX

- ULONGLONG * pTotalBytesTX
- ULONGLONG * pTotalBytesRX

8.1043.1 Detailed Description

Contains the WDS event information and information about the interface

Parameters

pQmiInterface-Info	• See qaQmiInterfaceInfo for more information
pDataBearer,-	Data bearer technology (NULL if not present) • 0x00 - Indicates that this field is ignored • 0x01 - CDMA 1X • 0x02 - EV-DO Rev 0 • 0x03 - GPRS • 0x04 - WCDMA • 0x05 - EV-DO Rev A • 0x06 - EDGE • 0x07 - HSDPA and WCDMA • 0x08 - WCDMA and HSUPA • 0x09 - HSDPA and HSUPA • 0x0A - LTE • 0x0B - EV-DO Rev A EHRPD • 0x0C - HSDPA+ and WCDMA • 0x0D - HSDPA+ and HSUPA • 0x0E - DC_HSDPA+ and WCDMA • 0x0F - DC_HSDPA+ and HSUPA • 0x8000 - NULL Bearer • 0xFF - Unknown Technology
pDormancy-Status	• Dormancy status (NULL if not present) – 1 - traffic channel dormant – 2 - traffic channel active
pPacketsCount-TX	• Packets transmitted without error (NULL if not present)
pPacketsCount-RX	• Packets received without error (NULL if not present)
pTotalBytesTX	• Bytes transmitted without error (NULL if not present)
pTotalBytesRX	• Bytes received without error (NULL if not present)

8.1043.2 Field Documentation

8.1043.2.1 ULONG* slqsWdsEventInfo::pDataBearer

8.1043.2.2 ULONG* slqsWdsEventInfo::pDormancyStatus

8.1043.2.3 ULONG* slqsWdsEventInfo::pPacketsCountRX

8.1043.2.4 ULONG* slqsWdsEventInfo::pPacketsCountTX

8.1043.2.5 qaQmiInterfaceInfo* slqsWdsEventInfo::pQmiInterfaceInfo

8.1043.2.6 ULONGLONG* slqsWdsEventInfo::pTotalBytesRX

8.1043.2.7 ULONGLONG* slqsWdsEventInfo::pTotalBytesTX

8.1044 sms_BroadcastConfig Struct Reference

Data Fields

- uint16_t fromServiceId
- uint16_t toServiceId
- uint8_t selected

8.1044.1 Detailed Description

This structure contains BroadcastConfig parameters

Parameters

fromServiceId	• Starting point of range of CBM message identifiers
toServiceId	• Ending point of range of CBM message identifiers
selected	• Range of CBM message identifiers indicated by from_service_id and to_service_id – 0x00 - Not selected – 0x01 - Selected

8.1044.2 Field Documentation

8.1044.2.1 uint16_t sms_BroadcastConfig::fromServiceId

8.1044.2.2 uint8_t sms_BroadcastConfig::selected

8.1044.2.3 uint16_t sms_BroadcastConfig::toServiceId

8.1045 sms_CDMABroadcastConfig Struct Reference

Data Fields

- uint16_t serviceCategory

- uint16_t language
- uint8_t selected

8.1045.1 Detailed Description

This structure contains CDMABroadcastConfig parameters

Parameters

serviceCategory	• Service category
language	• Language
selected	• Specified service_category and language – 0x00 - Not selected – 0x01 - Selected

8.1045.2 Field Documentation

8.1045.2.1 uint16_t sms_CDMABroadcastConfig::language

8.1045.2.2 uint8_t sms_CDMABroadcastConfig::selected

8.1045.2.3 uint16_t sms_CDMABroadcastConfig::serviceCategory

8.1046 sms_DateTime Struct Reference

Data Fields

- CHAR data [0x09]

8.1046.1 Field Documentation

8.1046.1.1 CHAR sms_DateTime::data[0x09]

8.1047 sms_getIndicationReg Struct Reference

Data Fields

- uint8_t * pRegTransLayerInfoEvt
- uint8_t * pRegTransNWRegInfoEvt
- uint8_t * pRegCallStatInfoEvt

8.1047.1 Detailed Description

This structure contains Get Indication Register Response parameters

Parameters

pRegTrans-LayerInfoEvt	- • Optional parameter indicating registration status of transport layer information events • Values: – 0x00 - Disabled – 0x01 - Enabled
pRegTransNW-RegInfoEvt	- • Optional parameter indicating registration status of transport network registration information events • Values: – 0x00 - Disabled – 0x01 - Enabled
pRegCallStat-InfoEvt	- • Optional parameter indicating registration status of call status information events • Values: – 0x00 - Disabled – 0x01 - Enabled

8.1047.2 Field Documentation

8.1047.2.1 uint8_t* sms_getIndicationReg::pRegCallStatInfoEvt

8.1047.2.2 uint8_t* sms_getIndicationReg::pRegTransLayerInfoEvt

8.1047.2.3 uint8_t* sms_getIndicationReg::pRegTransNWRegInfoEvt

8.1048 sms_getMsgWaitingInfo Struct Reference

Data Fields

- uint8_t numInstances
- sms_messageWaitingInfoContent msgWaitInfo [0xFF]

8.1048.1 Detailed Description

This structure contains Get Message Waiting Info Response parameters

Parameters

numInstances	• Number of sets of the elements in structure sms_messageWaitingInfoContent
pMsgWaitInfo	• Pointer to structure of sms_messageWaitingInfoContent. – See sms_messageWaitingInfoContent for more information.

8.1048.2 Field Documentation

8.1048.2.1 sms_messageWaitingInfoContent sms_getMsgWaitingInfo::msgWaitInfo[0xFF]

8.1048.2.2 uint8_t sms_getMsgWaitingInfo::numInstances

8.1049 sms_getTransLayerInfo Struct Reference

Data Fields

- uint8_t * pRegInd
- sms_transLayerInfo * pTransLayerInfo

8.1049.1 Detailed Description

This structure contains Get Transport Layer Info Response parameters

Parameters

pRegInd	- • Optional parameter indicating if transport layer is registered • Values: – 0x00 - Transport layer is not registered – 0x01 - Transport layer is registered • returns a default value 0xFF if no response is received from the device.
pTransLayerInfo	• Pointer to structure of sms_transLayerInfo. – Optional parameter – See sms_transLayerInfo for more information • returns a default value 0xFF for parameter values if no response is received from the device.

8.1049.2 Field Documentation

8.1049.2.1 uint8_t* sms_getTransLayerInfo::pRegInd

8.1049.2.2 sms_transLayerInfo* sms_getTransLayerInfo::pTransLayerInfo

8.1050 sms_getTransNWRegInfo Struct Reference

Data Fields

- uint8_t * pRegStatus

8.1050.1 Detailed Description

This structure contains transport network registration info parameter

Parameters

pRegStatus	- • Optional parameter indicating transport layer network registration status • Values: – 0x00 - No service – 0x01 - In progress – 0x02 - Failed – 0x03 - Limited Service – 0x04 - Full Service • returns a default value 0xFF if no response is received from the device.

8.1050.2 Field Documentation

8.1050.2.1 uint8_t* sms_getTransNWRegInfo::pRegStatus

8.1051 sms_maxStorageSizeReq Struct Reference

Data Fields

- uint8_t storageType
- uint8_t * pMessageMode

8.1051.1 Detailed Description

This structure contains get store max size request parameters

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
pMessage-Mode(optional	parameter) • 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)

Note

The Message Mode TLV must be included if the device is capable of supporting more than one protocol

8.1051.2 Field Documentation

8.1051.2.1 uint8_t* sms_maxStorageSizeReq::pMessageMode

8.1051.2.2 uint8_t sms_maxStorageSizeReq::storageType

8.1052 sms_maxStorageSizeResp Struct Reference

Data Fields

- uint32_t maxStorageSize
- uint32_t freeSlots

8.1052.1 Detailed Description

This structure contains get store max size response parameters

Parameters

maxStorageSize	- • Memory Store Size
freeSlots	- • Optional parameter indicating how much Memory is available • returns a default value 0xFFFFFFFF for parameter values if no response is received from the device.

8.1052.2 Field Documentation

8.1052.2.1 uint32_t sms_maxStorageSizeResp::freeSlots

8.1052.2.2 uint32_t sms_maxStorageSizeResp::maxStorageSize

8.1053 sms_messageWaitingInfoContent Struct Reference

Data Fields

- uint8_t msgType
- uint8_t activeInd
- uint8_t msgCount

8.1053.1 Detailed Description

This structure contains message waiting information per instance

Parameters

msgType	• Message type – 0x00 - MWI_MESSAGE_TYPE_VOICMAIL - Voicemail – 0x01 - MWI_MESSAGE_TYPE_FAX - Fax – 0X02 - MWI_MESSAGE_TYPE_EMAIL - Email – 0x03 - MWI_MESSAGE_TYPE_OTHER - Other – 0x04 - MWI_MESSAGE_TYPE_VIDEOMAIL - Videomail
activeInd	• Indicates whether the indication is active – 0x00 - Inactive – 0x01 - Active

msgCount	• Number of messages

8.1053.2 Field Documentation

8.1053.2.1 uint8_t sms_messageWaitingInfoContent::activeInd

8.1053.2.2 uint8_t sms_messageWaitingInfoContent::msgCount

8.1053.2.3 uint8_t sms_messageWaitingInfoContent::msgType

8.1054 sms_msgProtocolResp Struct Reference

Data Fields

- uint8_t msgProtocol

8.1054.1 Detailed Description

This structure contains get message protocol response parameters

Parameters

msgProtocol	- • Message Protocol • Values: – 0x00 - MESSAGE_PROTOCOL_CDMA – 0x01 - MESSAGE_PROTOCOL_WCDMA

8.1054.2 Field Documentation

8.1054.2.1 uint8_t sms_msgProtocolResp::msgProtocol

8.1055 sms_qaQmi3GPP2BroadcastCfgInfo Struct Reference

Data Fields

- uint8_t activated_ind
- uint16_t num_instances
- sms_CDMABroadcastConfig CDMABroadcastConfig [0x05]

8.1055.1 Detailed Description

This structure contains the 3GPP2 Broadcast Configuration Information parameters

Parameters

activated_ind	• Broadcast SMS – 0x00 - Deactivated – 0x01 - Activated
num_instances	• Number of sets (N) of parameters Following each set describes one entry in the broadcast configuration table. – serviceCategory – language – selected
broadcastConfig	• A CDMABroadcastConfig structure array. • Further defined by the structure sms_CDMABroadcastConfig

8.1055.2 Field Documentation

8.1055.2.1 uint8_t sms_qaQmi3GPP2BroadcastCfgInfo::activated_ind

8.1055.2.2 sms_CDMABroadcastConfig sms_qaQmi3GPP2BroadcastCfgInfo::CDMABroadcastConfig[0x05]

8.1055.2.3 uint16_t sms_qaQmi3GPP2BroadcastCfgInfo::num_instances

8.1056 sms_qaQmi3GPPBroadcastCfgInfo Struct Reference

Data Fields

- uint8_t activated_ind
- uint16_t num_instances
- sms_BroadcastConfig broadcastConfig [0x05]

8.1056.1 Detailed Description

This structure contains the 3GPP Broadcast Configuration Information parameters

Parameters

activated_ind	• Broadcast SMS – 0x00 - Deactivated – 0x01 - Activated
num_instances	• Number of sets (N) of parameters Following each set describes one entry in the broadcast configuration table. – fromServiceId – toServiceId – selected

broadcastConfig	• A BroadcastConfig structure array. • Further defined by the structure sms_BroadcastConfig

8.1056.2 Field Documentation

8.1056.2.1 uint8_t sms_qaQmi3GPPBroadcastCfgInfo::activated_ind

8.1056.2.2 sms_BroadcastConfig sms_qaQmi3GPPBroadcastCfgInfo::broadcastConfig[0x05]

8.1056.2.3 uint16_t sms_qaQmi3GPPBroadcastCfgInfo::num_instances

8.1057 sms_routeEntry Struct Reference

Data Fields

- uint8_t messageType
- uint8_t messageClass
- uint8_t routeStorage
- uint8_t receiptAction

8.1057.1 Detailed Description

This structure contains SMS route entry details

Parameters

messageType	- • Message type matching this route • Values: – 0x00 - MESSAGE_TYPE_POINT_TO_POINT
messageClass	- • Message Class • Values: – 0x00 - MESSAGE_CLASS_0 – 0x01 - MESSAGE_CLASS_1 – 0x02 - MESSAGE_CLASS_2 – 0x03 - MESSAGE_CLASS_3 – 0x04 - MESSAGE_CLASS_NONE – 0x05 - MESSAGE_CLASS_CDMA
routeStorage	- • If the receiptAction is store where to store the message • Values: – 0x00 - STORAGE_TYPE_UIM – 0x01 - STORAGE_TYPE_NV – 0xFF - STORAGE_TYPE_NONE

receiptAction	- • Action to be taken on receipt of a message matching the specified type and class for this route • Values: – 0x00 - DISCARD (discarded without notification) – 0x01 - STORE AND NOTIFY (stored and notified to the registered clients) – 0x02 - TRANSFER ONLY (transferred to the client, client expected to send the ACK) – 0x03 - TRANSFER AND ACK (transferred to the client, device expected to send the ACK)

8.1057.2 Field Documentation

8.1057.2.1 uint8_t sms_routeEntry::messageClass

8.1057.2.2 uint8_t sms_routeEntry::messageType

8.1057.2.3 uint8_t sms_routeEntry::receiptAction

8.1057.2.4 uint8_t sms_routeEntry::routeStorage

8.1058 sms_sendAsyncsmsParams Struct Reference

Data Fields

- uint32_t messageFormat
- uint32_t messageSize
- uint8_t * pMessage
- uint8_t * pForceOnDC
- uint8_t * pServiceOption
- uint8_t * pFollowOnDC
- uint8_t * pLinktimer
- uint8_t * pSmsOnIms
- uint8_t * pRetryMessage
- uint32_t * pRetryMessageId
- uint32_t * pUserData

8.1058.1 Detailed Description

This structure contains SMS parameters

Parameters

messageFormat	• Message format • Values: – 0 - CDMA (IS-637B) – 1 - 5 (Reserved) – 6 - GSM/WCDMA PP
messageSize	• The length of the message contents in bytes

pMessage	• The message contents
pForceOnDC	• Force the message to be sent on the CDMA dedicated channel. • Values: – 0x00 - Do not care about the channel on which the message is sent – 0x01 - Request to send the message over the dedicated channel
pServiceOption	• Service option: • Values: – 0x00 - SO_AUTO - AUTO (choose the best service option) – 0x06 - SO_6 - Service option 6 – 0x0E - SO_14 - Service option 14
pFollowOnDC	• Flag to request not to disconnect the CDMA dedicated channel after the send operation is complete. • This TLV can be included if more messages are expected to follow. • Values: – 0x01 - FOLLOW_ON_DC_ON - On (don't disconnect after send operation) Any value other than 0x01 is treated as an absence of this TLV.
pLinktimer	• Keeps the GW SMS link open for the specified number of seconds; can be enabled if more messages are expected to follow
pSmsOnIms	• Indicates whether the message is to be sent on IMS. • Values: – 0x00 - Message is not to be sent on IMS – 0x01 - Message is to be sent on IMS – 0x02 to 0xFF - Reserved
pRetryMessage	• Indicates this message is a retry message. • Values: – 0x01 - WMS_MESSAGE_IS_A_RETRY - Message is a retry message Note: Any value other than 0x01 in this field is treated as an absence of this TLV.
pRetryMessage-Id	• Message ID to be used in the retry message. • The message ID specified here is used instead of the messsage ID encoded in the raw message.
pUserData	• Enables the control point to associate the request with the corresponding indication. • The control point might send numerous requests. • This TLV will help the control point to identify the request for which the received indication belongs.

8.1058.2 Field Documentation

8.1058.2.1 uint32_t sms_sendAsyncsmsParams::messageFormat

8.1058.2.2 uint32_t sms_sendAsyncsmsParams::messageSize

8.1058.2.3 uint8_t* sms_sendAsyncsmsParams::pFollowOnDC

8.1058.2.4 uint8_t* sms_sendAsyncsmsParams::pForceOnDC

8.1058.2.5 uint8_t* sms_sendAsyncsmsParams::pLinktimer

8.1058.2.6 uint8_t* sms_sendAsyncsmsParams::pMessage

8.1058.2.7 uint8_t* sms_sendAsyncsmsParams::pRetryMessage

8.1058.2.8 uint32_t* sms_sendAsyncsmsParams::pRetryMessageId

8.1058.2.9 uint8_t* sms_sendAsyncsmsParams::pServiceOption

8.1058.2.10 uint8_t* sms_sendAsyncsmsParams::pSmsOnIms

8.1058.2.11 uint32_t* sms_sendAsyncsmsParams::pUserData

8.1059 sms_setIndicationReg Struct Reference

Data Fields

- uint8_t * pRegTransLayerInfoEvt
- uint8_t * pRegTransNWRegInfoEvt
- uint8_t * pRegCallStatInfoEvt

8.1059.1 Detailed Description

This structure contains Indication Register request parameters

Parameters

pRegTrans-LayerInfoEvt	- • Optional parameter indicating registration status of transport layer information events • Values: – 0x00 - Disabled – 0x01 - Enabled – NULL - No change - specifying NULL indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device
pRegTransNW-RegInfoEvt	- • Optional parameter indicating registration status of transport network registration information events • Values: – 0x00 - Disabled – 0x01 - Enabled – NULL - No change - specifying NULL indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device

pRegCallStat-InfoEvt	- • Optional parameter indicating registration status of call status information events • Values: – 0x00 - Disabled – 0x01 - Enabled – NULL - No change - specifying NULL indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device

8.1059.2 Field Documentation

8.1059.2.1 uint8_t* sms_setIndicationReg::pRegCallStatInfoEvt

8.1059.2.2 uint8_t* sms_setIndicationReg::pRegTransLayerInfoEvt

8.1059.2.3 uint8_t* sms_setIndicationReg::pRegTransNWRegInfoEvt

8.1060 sms_setRoutesReq Struct Reference

Data Fields

- uint16_t numOfRoutes
- sms_routeEntry routeList [0x0A]
- uint8_t * pTransferStatusReport

8.1060.1 Detailed Description

This structure contains SMS route request parameters

Parameters

numOfRoutes	- • Number of sets of the following element
routeList	- • Array containing the set of sms_routeEntry
pTransferStatus-Report	- • 0x01 - Status report are transferred to the client (optional)

8.1060.2 Field Documentation

8.1060.2.1 uint16_t sms_setRoutesReq::numOfRoutes

8.1060.2.2 uint8_t* sms_setRoutesReq::pTransferStatusReport

8.1060.2.3 sms_routeEntry sms_setRoutesReq::routeList[0x0A]

8.1061 sms_timestemp Struct Reference

Data Fields

- BYTE data [8]

8.1061.1 Field Documentation

8.1061.1.1 BYTE sms_timestemp::data[8]

8.1062 sms_transLayerInfo Struct Reference

Data Fields

- uint8_t TransType
- uint8_t TransCap

8.1062.1 Detailed Description

This structure contains Transport Layer Information

Parameters

TransType	• Transport Type – 0x00 - IMS
TransCap	• Transport Capability • Values: – 0x00 - CDMA – 0x01 - GW

8.1062.2 Field Documentation

8.1062.2.1 uint8_t sms_transLayerInfo::TransCap

8.1062.2.2 uint8_t sms_transLayerInfo::TransType

8.1063 SMSAsyncRawSend_s Struct Reference

Data Fields

- struct qmTlvResult results
- WORD sendStatus
- WORD messageID
- WORD causeCode
- BYTE errorClass
- WORD RPCause
- BYTE TPCause
- BYTE msgDelFailureType
- BYTE msgDelFailureCause
- BYTE alphaIDLen

- BYTE * pAlphaID
- ULONG userData

8.1063.1 Detailed Description

This structure contains SMS parameters

Parameters

sendStatus	• Send Status • Values: – QMI_ERR_NONE - No error in the request – QMI_ERR_CAUSE_CODE - SMS cause code – QMI_ERR_MESSAGE_DELIVERY_FAILURE - Message could not be delivered – QMI_ERR_NO_MEMORY - Device could not allocate memory to formulate a response
messageID	• Unique ID assigned by WMS for non-retry messages.
causeCode	• WMS cause code
errorClass	• Error Class • Values: – 0x00 - ERROR_CLASS_TEMPORARY – 0x01 - ERROR_CLASS_PERMANENT
RPCause	• GW RP cause
TPCause	• GW TP Cause
msgDelFailure-Type	• Message delivery failure type • Values: – 0x00 - WMS_MESSAGE_DELIVERY_FAILURE_TEMPORARY – 0x01 - WMS_MESSAGE_DELIVERY_FAILURE_PERMANENT
msgDelFailure-Cause	• Message delivery failure cause • Values: – 0x00 - WMS_MESSAGE_BLOCKED_DUE_TO_CALL_CONTROL
alphaIDLen	• Number of sets of the pAlphaID
pAlphaID	• Alpha ID

userData	• Identifies the request associated with this indication.

8.1063.2 Field Documentation

8.1063.2.1 BYTE SMSAsyncRawSend_s::alphaIDLen

8.1063.2.2 WORD SMSAsyncRawSend_s::causeCode

8.1063.2.3 BYTE SMSAsyncRawSend_s::errorClass

8.1063.2.4 WORD SMSAsyncRawSend_s::messageID

8.1063.2.5 BYTE SMSAsyncRawSend_s::msgDelFailureCause

8.1063.2.6 BYTE SMSAsyncRawSend_s::msgDelFailureType

8.1063.2.7 BYTE* SMSAsyncRawSend_s::pAlphaID

8.1063.2.8 struct qmTlvResult SMSAsyncRawSend_s::results

8.1063.2.9 WORD SMSAsyncRawSend_s::RPCause

8.1063.2.10 WORD SMSAsyncRawSend_s::sendStatus

8.1063.2.11 BYTE SMSAsyncRawSend_s::TPCause

8.1063.2.12 ULONG SMSAsyncRawSend_s::userData

8.1064 SMSCAddress Struct Reference

Data Fields

- BYTE length
- BYTE data [256]

8.1064.1 Detailed Description

This structure holds SMSC information

Parameters

length	• Number of sets of following element
data	• SMSC address

8.1064.2 Field Documentation

8.1064.2.1 BYTE SMSCAddress::data[256]

8.1064.2.2 BYTE SMSCAddress::length

8.1065 sMSCAddressInfo Struct Reference

Data Fields

- uint8_t length
- uint8_t data [256]

8.1065.1 Detailed Description

This structure contains SMSC information

Parameters

length	• Number of sets of following element
data	• SMSC address

8.1065.2 Field Documentation

8.1065.2.1 uint8_t sMSCAddressInfo::data[256]

8.1065.2.2 uint8_t sMSCAddressInfo::length

8.1066 sMSCAddressTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- sMSCAddressInfo SMSCInfo

8.1066.1 Detailed Description

This structure contains SMSC TLV information

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response
SMSCInfo	• SMSC Address • See sMSCAddressInfo for more information

8.1066.2 Field Documentation

8.1066.2.1 sMSCAddressInfo sMSCAddressTlv::SMSCInfo

8.1066.2.2 uint8_t sMSCAddressTlv::TlvPresent

8.1067 SMSEtwsMessage Struct Reference

Data Fields

- BYTE notificationType
- WORD length
- BYTE data [1254]

8.1067.1 Detailed Description

This structure holds information related earthquake and Tsunami warning system

Parameters

notificationType	• Message mode 0x00 - Primary 0x01 - Secondary GSM 0x02 - Secondary UMTS
length	• Number of sets of following elements
data	• Raw message data

8.1067.2 Field Documentation

8.1067.2.1 BYTE SMSEtwsMessage::data[1254]

8.1067.2.2 WORD SMSEtwsMessage::length

8.1067.2.3 BYTE SMSEtwsMessage::notificationType

8.1068 sMSEtwsMessageInfo Struct Reference

Data Fields

- uint8_t notificationType
- uint16_t length
- uint8_t data [1254]

8.1068.1 Detailed Description

This structure contains ETWS information

Parameters

notificationType	• Message mode 0x00 - Primary 0x01 - Secondary GSM 0x02 - Secondary UMTS

length	• Number of sets of following elements
data	• Raw message data

8.1068.2 Field Documentation

8.1068.2.1 uint8_t sMSEtwsMessageInfo::data[1254]

8.1068.2.2 uint16_t sMSEtwsMessageInfo::length

8.1068.2.3 uint8_t sMSEtwsMessageInfo::notificationType

8.1069 sMSEtwsMessageTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- sMSEtwsMessageInfo EtwsMessageInfo

8.1069.1 Detailed Description

This structure contains ETWS TLV information

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response
EtwsMessage-Info	• ETWS Message • See sMSEtwsMessageInfo for more information

8.1069.2 Field Documentation

8.1069.2.1 sMSEtwsMessageInfo sMSEtwsMessageTlv::EtwsMessageInfo

8.1069.2.2 uint8_t sMSEtwsMessageTlv::TlvPresent

8.1070 SMSEtwsPlmn Struct Reference

Data Fields

- WORD mobileCountryCode
- WORD mobileNetworkCode

8.1070.1 Detailed Description

This structure holds information related ETWS PLMN

Parameters

mobileCountry-Code	• 16 bit representation of MCC value range : 0 -999
mobileNetwork-Code	• 16 bit representation of MNC value range : 0 -999

8.1070.2 Field Documentation

8.1070.2.1 WORD SMSEtwsPlmn::mobileCountryCode

8.1070.2.2 WORD SMSEtwsPlmn::mobileNetworkCode

8.1071 sMSEtwsPlmnInfo Struct Reference

Data Fields

- uint16_t mobileCountryCode
- uint16_t mobileNetworkCode

8.1071.1 Detailed Description

This structure contains ETWS PLMN information

Parameters

mobileCountry-Code	• 16 bit representation of MCC value range : 0 -999
mobileNetwork-Code	• 16 bit representation of MNC value range : 0 -999

8.1071.2 Field Documentation

8.1071.2.1 uint16_t sMSEtwsPlmnInfo::mobileCountryCode

8.1071.2.2 uint16_t sMSEtwsPlmnInfo::mobileNetworkCode

8.1072 SMSEventInfo_s Struct Reference

Data Fields

- BYTE smsEventType
- SMSMTMessageInfo * pMTMessageInfo
- SMSTransferRouteMTMessageInfo * pTransferRouteMTMessageInfo
- SMSMessageModeInfo * pMessageModeInfo

- SMSEtwsMessageInfo * pEtwsMessageInfo
- SMSEtwsPlmnInfo * pEtwsPlmnInfo
- SMSCAddressInfo * pSMSCAddressInfo
- SMSOnIMSInfo * pSMSOnIMSInfo

8.1072.1 Detailed Description

This structure will hold the information related to received SMS events

Parameters

smsEventType	• Type of the SMS events that are received. This is a bit map of SMSEventType. Only the parameters (which follows) related to the events received would be filled, and the rest of the parameters would be NULL
pMTMessageInfo	• pointer to the SMSMTMessageInfo structure NULL, if this event is not present in the smsEventType parameter
pTransferRouteMTMessageInfo	• pointer to the SMSTransferRouteMTMessageInfo structure . NULL, if this event is not present in the smsEventType parameter
pMessageModeInfo	• pointer to the SMSMessageModeInfo structure NULL, if this event is not present in the smsEventType parameter
pEtwsMessageInfo	• pointer to the SMSEtwsMessageInfo structure NULL, if this event is not present in the smsEventType parameter
pEtwsPlmnInfo	• pointer to the SMSEtwsPlmnInfo structure NULL, if this event is not present in the smsEventType parameter
pSMSCAddressInfo	• pointer to the SMSCAddressInfo structure NULL, if this event is not present in the smsEventType parameter
pSMSOnIMSInfo	• pointer to the SMSOnIMSInfo structure NULL, if this event is not present in the smsEventType parameter Note: None

8.1072.2 Field Documentation

8.1072.2.1 SMSEtwsMessageInfo* SMSEventInfo_s::pEtwsMessageInfo

8.1072.2.2 SMSEtwsPlmnInfo* SMSEventInfo_s::pEtwsPlmnInfo

8.1072.2.3 SMSMessageModeInfo* SMSEventInfo_s::pMessageModeInfo

8.1072.2.4 SMSMTMessageInfo* SMSEventInfo_s::pMTMessageInfo

8.1072.2.5 SMSCAddressInfo* SMSEventInfo_s::pSMSCAddressInfo

8.1072.2.6 SMSOnIMSInfo* SMSEventInfo_s::pSMSOnIMSInfo

8.1072.2.7 SMSTransferRouteMTMessageInfo* SMSEventInfo_s::pTransferRouteMTMessageInfo

8.1072.2.8 BYTE SMSEventInfo_s::smsEventType

8.1073 smsMaxStorageSizeReq Struct Reference

Data Fields

- BYTE storageType
- BYTE * pMessageMode

8.1073.1 Detailed Description

This structure contains get store max size resquest parameters

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
pMessage-Mode(optional	parameter) • 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)

Note

The Message Mode TLV must be included if the device is capable of supporting more than one protocol

8.1073.2 Field Documentation

8.1073.2.1 BYTE* smsMaxStorageSizeReq::pMessageMode

8.1073.2.2 BYTE smsMaxStorageSizeReq::storageType

8.1074 smsMaxStorageSizeResp Struct Reference

Data Fields

- ULONG maxStorageSize
- ULONG freeSlots

8.1074.1 Detailed Description

This structure contains get store max size response parameters

Parameters

maxStorageSize	- • Memory Store Size
freeSlots	- • Optional parameter indicating how much Memory is available • function SLQSSmsGetMaxStorageSize() returns a default value 0xFFFFFFFF for parameter values if no response is received from the device.

8.1074.2 Field Documentation

8.1074.2.1 ULONG smsMaxStorageSizeResp::freeSlots

8.1074.2.2 ULONG smsMaxStorageSizeResp::maxStorageSize

8.1075 SMSMemoryInfo Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE storageType
- BYTE messageMode

8.1075.1 Detailed Description

This structure holds information related to memory

Parameters

storageType	• Indicates the type of memory storage 0x00 - STORAGE_TYPE_UIM 0x01 - STORAGE_TYPE_NV
messageMode	• Indicates the type of memory mode 0x00 - MESSAGE_MODE_CDMA - CDMA 0x01 - MESSAGE_MODE_GW - GW

8.1075.2 Field Documentation

8.1075.2.1 BYTE SMSMemoryInfo::messageMode

8.1075.2.2 struct qmTlvResult SMSMemoryInfo::results

8.1075.2.3 BYTE SMSMemoryInfo::storageType

8.1076 SMSMessageMode Struct Reference

Data Fields

- BYTE messageMode

8.1076.1 Detailed Description

This structure holds information related to message mode

Parameters

messageMode	• Message mode 0x00 - CDMA 0x01 - GW

8.1076.2 Field Documentation

8.1076.2.1 BYTE SMSMessageMode::messageMode

8.1077 sMSMessageModeInfo Struct Reference

Data Fields

- uint8_t messageMode

8.1077.1 Detailed Description

This structure contains message mode information.

Parameters

messageMode	• Message Mode – 0x00 - CDMA – 0x01 - GW

8.1077.2 Field Documentation

8.1077.2.1 uint8_t sMSMessageModeInfo::messageMode

8.1078 smsMsgprotocolResp Struct Reference

Data Fields

- BYTE msgProtocol

8.1078.1 Detailed Description

This structure contains get message protocol response parameters

Parameters

msgProtocol	- • Message Protocol • Values: – 0x00 - MESSAGE_PROTOCOL_CDMA – 0x01 - MESSAGE_PROTOCOL_WCDMA

8.1078.2 Field Documentation

8.1078.2.1 BYTE smsMsgprotocolResp::msgProtocol

8.1079 SMSMTMessage Struct Reference

Data Fields

- ULONG storageType
- ULONG messageIndex

8.1079.1 Detailed Description

This structure holds information related to MT SMS

Parameters

storageType	• SMS message storage type for the new message 0 - UIM 1 - NV
messageIndex	• Index of the new message

8.1079.2 Field Documentation

8.1079.2.1 ULONG SMSMTMessage::messageIndex

8.1079.2.2 ULONG SMSMTMessage::storageType

8.1080 sMSMTMessageInfo Struct Reference

Data Fields

- uint32_t storageType
- uint32_t messageIndex

8.1080.1 Detailed Description

This structure contains MT message information.

Parameters

storageType	memory storage 0x00-UIM 0x01-NV
messageIndex	MT Message index

8.1080.2 Field Documentation

8.1080.2.1 uint32_t sMSMTMessageInfo::messageIndex

8.1080.2.2 uint32_t sMSMTMessageInfo::storageType

8.1081 SMSOnIMS Struct Reference

Data Fields

- BYTE smsOnIMS

8.1081.1 Detailed Description

This structure holds information related to message mode

Parameters

smsOnIMS	• Indicates whether the message is received from IMS 0x00 - Message is not received from IMS 0x01 - Message is received from IMS 0x02-0xFF - Reserved Note: In multiple modem solutions, this TLV may be used to help the client determine with which modem to communicate. This TLV may not be supported on all implementations.

8.1081.2 Field Documentation

8.1081.2.1 BYTE SMSOnIMS::smsOnIMS

8.1082 sMSOnIMSInfo Struct Reference

Data Fields

- uint8_t smsOnIMS

8.1082.1 Detailed Description

This structure contains SMS on IMS information

Parameters

smsOnIMS	SMS on IMS

8.1082.2 Field Documentation

8.1082.2.1 uint8_t sMSOnIMSInfo::smsOnIMS

8.1083 sMSOnIMSTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- sMSOnIMSInfo IMSInfo

8.1083.1 Detailed Description

This structure contains SMS on IMS TLV information.

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response
IMSInfo	• SMS on IMS • See sMSOnIMSInfo for more information

8.1083.2 Field Documentation

8.1083.2.1 sMSOnIMSInfo sMSOnIMSTlv::IMSInfo

8.1083.2.2 uint8_t sMSOnIMSTlv::TlvPresent

8.1084 smsRouteEntry Struct Reference

Data Fields

- BYTE messageType
- BYTE messageClass
- BYTE routeStorage
- BYTE receiptAction

8.1084.1 Detailed Description

This structure contains SMS route entry details

Parameters

messageType	- • Message type matching this route • Values: – 0x00 - MESSAGE_TYPE_POINT_TO_POINT
messageClass	- • Message Class • Values: – 0x00 - MESSAGE_CLASS_0 – 0x01 - MESSAGE_CLASS_1 – 0x02 - MESSAGE_CLASS_2 – 0x03 - MESSAGE_CLASS_3 – 0x04 - MESSAGE_CLASS_NONE – 0x05 - MESSAGE_CLASS_CDMA
routeStorage	- • If the receiptAction is store where to store the message • Values: – 0x00 - STORAGE_TYPE_UIM – 0x01 - STORAGE_TYPE_NV – 0xFF - STORAGE_TYPE_NONE
receiptAction	- • Action to be taken on receipt of a message matching the specified type and class for this route • Values: – 0x00 - DISCARD (discarded without notification) – 0x01 - STORE AND NOTIFY (stored and notified to the registered clients) – 0x02 - TRANSFER ONLY (transferred to the client, client expected to send the ACK) – 0x03 - TRANSFER AND ACK (transferred to the client, device expected to send the ACK)

8.1084.2 Field Documentation

8.1084.2.1 BYTE smsRouteEntry::messageClass

8.1084.2.2 BYTE smsRouteEntry::messageType

8.1084.2.3 BYTE smsRouteEntry::receiptAction

8.1084.2.4 BYTE smsRouteEntry::routeStorage

8.1085 smsSetRoutesReq Struct Reference

Data Fields

- WORD numOfRoutes
- smsRouteEntry routeList [0x0A]
- BYTE * pTransferStatusReport

8.1085.1 Detailed Description

This structure contains SMS route request parameters

Parameters

numOfRoutes	- • Number of sets of the following element
routeList	- • Array containing the set of smsRouteEntry
pTransferStatus-Report	- • 0x01 - Status reoprt are transferred to the client (optional)

8.1085.2 Field Documentation

8.1085.2.1 WORD smsSetRoutesReq::numOfRoutes

8.1085.2.2 BYTE* smsSetRoutesReq::pTransferStatusReport

8.1085.2.3 smsRouteEntry smsSetRoutesReq::routeList[0x0A]

8.1086 SMSTransferRouteMTMessage Struct Reference

Data Fields

- BYTE ackIndicator
- ULONG transactionID
- BYTE format
- WORD length
- BYTE data [256]

8.1086.1 Detailed Description

This structure holds information related to transfer route MT SMS

Parameters

ackIndicator	• Parameter to indicate if ACK must be sent by the control point 0x00 - Send ACK 0x01 - Do not send ACK
transactionID	• Transaction ID of the message
format	• Message format 0x00 - CDMA 0x02 - 0x05 - Reserved 0x06 - GW_PP 0x07 - GW_BC
length	• Length of the raw message. This length should not exceed the maximum WMS payload length of 256 bytes

data	• Raw message data

8.1086.2 Field Documentation

8.1086.2.1 BYTE SMSTransferRouteMTMessage::ackIndicator

8.1086.2.2 BYTE SMSTransferRouteMTMessage::data[256]

8.1086.2.3 BYTE SMSTransferRouteMTMessage::format

8.1086.2.4 WORD SMSTransferRouteMTMessage::length

8.1086.2.5 ULONG SMSTransferRouteMTMessage::transactionID

8.1087 sMSTransferRouteMTMessageInfo Struct Reference

Data Fields

- uint8_t ackIndicator
- uint32_t transactionID
- uint8_t format
- uint16_t length
- uint8_t data [256]

8.1087.1 Detailed Description

This structure contains Transfer route MT message information.

Parameters

ackIndicator	• Parameter to indicate if ACK must be sent by the control point 0x00 - Send ACK 0x01 - Do not send ACK
transactionID	• Transaction ID of the message
format	• Message format 0x00 - CDMA 0x02 - 0x05 - Reserved 0x06 - GW_PP 0x07 - GW_BC
length	• Length of the raw message. This length should not exceed the maximum WMS payload length of 256 bytes
data	• Raw message data

8.1087.2 Field Documentation

8.1087.2.1 uint8_t sMSTransferRouteMTMessageInfo::ackIndicator

8.1087.2.2 uint8_t sMSTransferRouteMTMessageInfo::data[256]

8.1087.2.3 uint8_t sMSTransferRouteMTMessageInfo::format

8.1087.2.4 uint16_t sMSTransferRouteMTMessageInfo::length

8.1087.2.5 uint32_t sMSTransferRouteMTMessageInfo::transactionID

8.1088 sQosFlowStat Struct Reference

Data Fields

- ULONG bearerId
- ULONG tx_pkt
- ULONG tx_pkt_drp
- ULONGLONG tx_bytes
- ULONGLONG tx_bytes_drp

8.1088.1 Detailed Description

This structure contains the Data statistic per QoS flow

Parameters

bearerId	• Bearer ID
tx_pkt	• number of sent packets for the QoS flow ID
tx_pkt_drp	• number of dropped(TX) packets for the QoS flow ID
tx_bytes	• number of sent bytes for the QoS flow ID
tx_bytes_drp	• number of dropped(TX) bytes for the QoS flow ID

8.1088.2 Field Documentation

8.1088.2.1 ULONG sQosFlowStat::bearerId

8.1088.2.2 ULONGLONG sQosFlowStat::tx_bytes

8.1088.2.3 ULONGLONG sQosFlowStat::tx_bytes_drp

8.1088.2.4 ULONG sQosFlowStat::tx_pkt

8.1088.2.5 ULONG sQosFlowStat::tx_pkt_drp

8.1089 sQosStat Struct Reference

Data Fields

- ULONG apnId
- ULONG total_tx_pkt
- ULONG total_tx_pkt_drp
- ULONG total_rx_pkt
- ULONGLONG total_tx_bytes
- ULONGLONG total_tx_bytes_drp
- ULONGLONG total_rx_bytes
- ULONG numQosFlow
- sQosFlowStat qosFlow [(10)]

8.1089.1 Detailed Description

This structure contains the Data statistic per QoS flow

Parameters

apnId	• APN id • ID identifing the connected APN that the client would like to query the data statistic for
total_tx_pkt	• sum of all packets sent
total_tx_pkt_drp	• sum of all(TX) packets dropped
total_rx_pkt	• sum of all packets received
total_tx_bytes	• sum of all bytes sent
toal_tx_bytes_drp	• sum of all(TX) bytes dropped
total_rx_bytes	• number of received bytes for the QoS flow ID
numQosFlow	• pointer to number of QoS flow Stat
qosFlow[MAX_QOS_SPEC_PER_APN]	• Data statistic per QoS flow • See sQosFlowStat for more information • See MAX_QOS_SPEC_PER_APN for more information

8.1089.2 Field Documentation

8.1089.2.1 ULONG sQosStat::apnId

8.1089.2.2 ULONG sQosStat::numQosFlow

8.1089.2.3 sQosFlowStat sQosStat::qosFlow[(10)]

8.1089.2.4 ULONGLONG sQosStat::total_rx_bytes

8.1089.2.5 ULONG sQosStat::total_rx_pkt

8.1089.2.6 ULONGLONG sQosStat::total_tx_bytes

8.1089.2.7 ULONGLONG sQosStat::total_tx_bytes_drp

8.1089.2.8 ULONG sQosStat::total_tx_pkt

8.1089.2.9 ULONG sQosStat::total_tx_pkt_drp

8.1090 SrvStatusInfo Struct Reference

Data Fields

- BYTE srvStatus
- BYTE isPrefDataPath

8.1090.1 Detailed Description

Structure for storing the service status information for CDMA and HDR networks.

Parameters

srvStatus	• Service status of the system. – 0x00 - No service – 0x01 - Limited service – 0x02 - Service – 0x03 - Limited regional service – 0x04 - Power save – 0xFF - Not Available
isPrefDataPath	• Whether the RAT is the preferred data path. – 0x00 - Not preferred – 0x01 - Preferred – 0xFF - Not Available

8.1090.2 Field Documentation

8.1090.2.1 BYTE SrvStatusInfo::isPrefDataPath

8.1090.2.2 BYTE SrvStatusInfo::srvStatus

8.1091 ssdatasession_params Struct Reference

Data Fields

- BOOL action
- BYTE instanceId
- ULONG * pTechnology
- ULONG * pProfileId3GPP
- ULONG * pProfileId3GPP2
- ULONG sessionId
- ULONG failureReason
- ULONG failureReasonv4
- ULONG failureReasonv6
- ULONG rcv4
- ULONG rcv6
- ULONG v4sessionId
- ULONG v6sessionId
- BYTE ipfamily
- ULONG * pAuthentication
- CHAR * pUsername
- CHAR * pPassword
- ULONG verbFailReasonType
- ULONG verbFailReason

8.1091.1 Detailed Description

This structure contains the start/stop data session params Information

Parameters

action	• 1 - Start Session • 0 - Stop Session
instanceId	• PDP Instance. • Instance ID corresponding to the session ID
pTechnology	• Indicates the technology preference (optional) – 1 - UMTS – 2 - CDMA – 3 - eMBMS – 4 - Modem Link Label. Modem Link is an interface for transferring data between entities on AP and modem.
pProfileId3GPP	• configured 3GPP profile identifier
pProfileId3GPP2	• configured 3GPP2 profile identifier

sessionId[IN\OUT]	• [IN] - Passed session ID when stopping the data session • [OUT] - Assigned session ID when starting a data session
failureReason	• Reason data session failed to be established • See qaGobiApiTableCallEndReasons.h for Call End Reason
failureReasonv4	• Reason v4 data session failed to be established • See qaGobiApiTableCallEndReasons.h for Call End Reason
failureReasonv6	• Reason v6 data session failed to be established • See qaGobiApiTableCallEndReasons.h for Call End Reason
rc4	• v4 result code • See qmerrno.h
rc6	• v6 result code • See qmerrno.h
v4sessionId	• Do not modify - used for internal management of data sessions • Non zero value indicates that a session is active
v6sessionId	• Do not modify - used for internal management of data sessions • Non zero value indicates that a session is active
ipfamily	• 4 for an IPv4 data session • 6 for an IPv6 data session • 7 for an IPv4v6 data session
pAuthentication	• Authentication type, it can be PAP or CHAP
pUsername	• username for authentication process
pPassword	• password for authentication process
verbFailReasonType	• Parameter describing type of verbose failure reason • See qaGobiApiTableCallEndReasons.h for Call End Reason Type

verbFailReason	• Verbose reason explaining why call failed. Depends on verbFailReasonType parameter • See qaGobiApiTableCallEndReasons.h for Call End Reason

8.1091.2 Field Documentation

8.1091.2.1 BOOL ssdatasession_params::action

8.1091.2.2 ULONG ssdatasession_params::failureReason

8.1091.2.3 ULONG ssdatasession_params::failureReasonv4

8.1091.2.4 ULONG ssdatasession_params::failureReasonv6

8.1091.2.5 BYTE ssdatasession_params::instanceId

8.1091.2.6 BYTE ssdatasession_params::ipfamily

8.1091.2.7 ULONG* ssdatasession_params::pAuthentication

8.1091.2.8 CHAR* ssdatasession_params::pPassword

8.1091.2.9 ULONG* ssdatasession_params::pProfileId3GPP

8.1091.2.10 ULONG* ssdatasession_params::pProfileId3GPP2

8.1091.2.11 ULONG* ssdatasession_params::pTechnology

8.1091.2.12 CHAR* ssdatasession_params::pUsername

8.1091.2.13 ULONG ssdatasession_params::rcv4

8.1091.2.14 ULONG ssdatasession_params::rcv6

8.1091.2.15 ULONG ssdatasession_params::sessionId

8.1091.2.16 ULONG ssdatasession_params::v4sessionId

8.1091.2.17 ULONG ssdatasession_params::v6sessionId

8.1091.2.18 ULONG ssdatasession_params::verbFailReason

8.1091.2.19 ULONG ssdatasession_params::verbFailReasonType

8.1092 supportedIntBitmaskTlv Struct Reference

Data Fields

- BYTE TlvPresent
- ULONG ValidBitmasks

8.1092.1 Detailed Description

This structure contains the parameters for supported usb bitmasks

Parameters

TlvPresent	• Tlv Present.
ValidBitmasks	• for current configuration type, this is the supported bitmasks that the host can change.

8.1092.2 Field Documentation

8.1092.2.1 BYTE supportedIntBitmaskTlv::TlvPresent

8.1092.2.2 ULONG supportedIntBitmaskTlv::ValidBitmasks

8.1093 SupportedMsgList Struct Reference

Data Fields

- WORD supportedMsgLen
- BYTE supportedMsgs [256]

8.1093.1 Detailed Description

This structure contains the Supported Messages List Information

Parameters

supportedMsg-Len	• Number of sets of the supported messages
supportedMsgs	• Array of uint8 is a bitmask where each bit represents a message ID. • Starting with the LSB, bit 0 represents message ID 0, bit 1 represents message ID 1.

8.1093.2 Field Documentation

8.1093.2.1 WORD SupportedMsgList::supportedMsgLen

8.1093.2.2 BYTE SupportedMsgList::supportedMsgs[256]

8.1094 SUPSInfo Struct Reference

Data Fields

- BYTE svcType
- BYTE isModByCC

8.1094.1 Detailed Description

This structure contains information about the Supplementary Services.

Parameters

svcType	• Service type. – 0x01 - SERVICE_TYPE_ACTIVATE - Activate – 0x02 - SERVICE_TYPE_DEACTIVATE - Deactivate – 0x03 - SERVICE_TYPE_REGISTER - Register – 0x04 - SERVICE_TYPE_ERASE - Erase – 0x05 - SERVICE_TYPE_INTERROGATE - Interrogate – 0x06 - SERVICE_TYPE_REGISTER_PASSWORD - Register password – 0x07 - SERVICE_TYPE_USSD - USSD
isModByCC	• Indicates whether the supplementary service data is modified by the card (SIM/USIM) as part of the call control: – 0 - False – 1 - True

8.1094.2 Field Documentation

8.1094.2.1 BYTE SUPSInfo::isModByCC

8.1094.2.2 BYTE SUPSInfo::svcType

8.1095 SV Struct Reference

Data Fields

- WORD id
- ULONG system
- BYTE mask

8.1095.1 Detailed Description

This structure contains the Delete SV Info

Parameters

id	• SV ID of the satellite whose data is to be deleted • Range: – For GPS: 1 to 32 – For SBAS: 33 to 64 – For GLONASS: 65 to 96

system	• Indicates to which constellation this SV belongs • Valid values: – eQMI_LOC_SV_SYSTEM_GPS (1) - GPS satellite – eQMI_LOC_SV_SYSTEM_GALILEO (2) - GALILEO satellite – eQMI_LOC_SV_SYSTEM_SBAS (3) - SBAS satellite – eQMI_LOC_SV_SYSTEM_COMPASS (4) - COMPASS satellite – eQMI_LOC_SV_SYSTEM_GLONASS (5) - GLONASS satellite – eQMI_LOC_SV_SYSTEM_BDS (6) - BDS satellite
mask	• Indicates if the ephemeris or almanac for a satellite is to be deleted • Valid values: – 0x01 - DELETE_EPHEMERIS – 0x02 - DELETE_ALMANAC

8.1095.2 Field Documentation

8.1095.2.1 WORD SV::id

8.1095.2.2 BYTE SV::mask

8.1095.2.3 ULONG SV::system

8.1096 SVInfo Struct Reference

Data Fields

- BYTE len
- SV * pSV

8.1096.1 Detailed Description

This structure contains the elements of Delete SV Info

Parameters

len	• Number of sets of the following elements in struct SV: – gnssSvId – system – deleteSvInfoMask
pSV	• Pointer to struct SV. See SV for more information

8.1096.2 Field Documentation

8.1096.2.1 BYTE SVInfo::len

8.1096.2.2 SV* SVInfo::pSV

8.1097 svUsedforFix_s Struct Reference

Data Fields

- BYTE gnssSvUsedList_len
- WORD gnssSvUsedList [255]

8.1097.1 Detailed Description

This structure contains SVs Used to Calculate the Fix.

Parameters

gnssSvUsedList-_len	• Number of sets of gnssSvUsedList
pGnssSvUsed-List	• Entry in the list contains the SV ID of a satellite used for calculating this position report. • Following information is associated with each SV ID: – GPS - 1 to 32 – SBAS - 33 to 64 – GLONASS - 65 to 96 – QZSS - 193 to 197 – BDS - 201 to 237

8.1097.2 Field Documentation

8.1097.2.1 WORD svUsedforFix_s::gnssSvUsedList[255]

8.1097.2.2 BYTE svUsedforFix_s::gnssSvUsedList_len

8.1098 SWI_STRUCT_CarrierImage Struct Reference

Data Fields

- ULONG m_nCarrierId
- ULONG m_nFolderId
- ULONG m_nStorage
- BYTE m_FwImageId [100]
- BYTE m_FwBuildId [100]
- BYTE m_PriImageId [100]
- BYTE m_PriBuildId [100]

8.1098.1 Detailed Description

This structure contains the Carrier Image parameters.

Parameters

m_nCarrierId	• Unique numeric carrier ID indicating the carrier that the following images belong to
m_nFolderId	• Unique numeric folder ID indicating the folder where the images should reside on the host storage.
m_nStorage	• Information of storage type • Values – 0 - Device – 1 - Host
m_FwImageId	• Firmware image ID
m_FwBuildId	• Firmware build ID
m_PriImageId	• PRI image ID
m_PriBuildId	• PRI build ID

8.1098.2 Field Documentation

8.1098.2.1 BYTE SWI_STRUCT_CarrierImage::m_FwBuildId[100]

8.1098.2.2 BYTE SWI_STRUCT_CarrierImage::m_FwImageId[100]

8.1098.2.3 ULONG SWI_STRUCT_CarrierImage::m_nCarrierId

8.1098.2.4 ULONG SWI_STRUCT_CarrierImage::m_nFolderId

8.1098.2.5 ULONG SWI_STRUCT_CarrierImage::m_nStorage

8.1098.2.6 BYTE SWI_STRUCT_CarrierImage::m_PriBuildId[100]

8.1098.2.7 BYTE SWI_STRUCT_CarrierImage::m_PriImageId[100]

8.1099 swi_uint256_t Struct Reference

Data Fields

- uint16_t word [16]

8.1099.1 Detailed Description

SWI 256 bit data type

8.1099.2 Field Documentation

8.1099.2.1 uint16_t swi_uint256_t::word[16]

8.1100 swidms_ehrpdMTUSizeTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint16_t ehrpdMTUSize

8.1100.1 Detailed Description

This structure contains the parameters for EHRPD MTU Size.

Parameters

TlvPresent	• Tlv Present.
ehrpdMTUSize	EHRPD size • Size of EHRPD MTU

8.1100.2 Field Documentation

8.1100.2.1 uint16_t swidms_ehrpdMTUSizeTlv::ehrpdMTUSize

8.1100.2.2 uint8_t swidms_ehrpdMTUSizeTlv::TlvPresent

8.1101 swidms_hrpdMTUSizeTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint16_t hrpdMTUSize

8.1101.1 Detailed Description

This structure contains the parameters for HRPD MTU Size.

Parameters

TlvPresent	• Tlv Present.
hrpdMTUSize	HRPD size • Size of HRPD MTU

8.1101.2 Field Documentation

8.1101.2.1 uint16_t swidms_hrpdMTUSizeTlv::hrpdMTUSize

8.1101.2.2 uint8_t swidms_hrpdMTUSizeTlv::TlvPresent

8.1102 swidms_intfaceCfgTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t CurrentCfgType
- uint32_t CfgValue

8.1102.1 Detailed Description

This structure contains the parameters for host usb interface composition

Parameters

TlvPresent	• Tlv Present.
CurrentCfgType	• Current configure type, see values below: – 1 - MBIM – 2 - USBIF + PCIE – 3 - RMNET – 4 - RNDIS – 5 - PCIE only

CfgValue	• Host composition bit mask, see supported USB interface bitmasks, not supported by QMI object setting for 9x50 modules – 0x00000001 - DIAG interface – 0x00000002 - ADB interface – 0x00000004 - NMEA interface – 0x00000008 - MODEM interface – 0x00000010 - RESERVED5 – 0x00000020 - RESERVED6 – 0x00000040 - RESERVED7 – 0x00000080 - RESERVED8 – 0x00000100 - RMENT0 interface – 0x00000200 - RESERVED10 – 0x00000400 - RMENT1 interface – 0x00000800 - RESERVED12 – 0x00001000 - MBIM interface – 0x00002000 - RESERVED14 – 0x00004000 - RNDIS interface – 0x00008000 - RESERVED16 – 0x00010000 - AUDIO interface – 0x00020000 - RESERVED18 – 0x00080000 - ECM interface – 0x00100000 - RESERVED21 – 0x00200000 - RESERVED22 – 0xFFC00000 - RESERVED

8.1102.2 Field Documentation

8.1102.2.1 uint32_t swidms_intfaceCfgTlv::CfgValue

8.1102.2.2 uint32_t swidms_intfaceCfgTlv::CurrentCfgType

8.1102.2.3 uint8_t swidms_intfaceCfgTlv::TlvPresent

8.1103 swidms_mtuSize3gppTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint16_t MTUSize3gpp

8.1103.1 Detailed Description

This structure contains the parameters for 3GPP MTU Size.

Parameters

TlvPresent	• Tlv Present.

MTUSize3gpp	3GPP MTU size • Size of 3GPP MTU

8.1103.2 Field Documentation

8.1103.2.1 uint16_t swidms_mtuSize3gppTlv::MTUSize3gpp

8.1103.2.2 uint8_t swidms_mtuSize3gppTlv::TlvPresent

8.1104 swidms_supportedIntBitmaskTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t ValidBitmasks

8.1104.1 Detailed Description

This structure contains the parameters for supported usb bitmasks

Parameters

TlvPresent	• Tlv Present.
ValidBitmasks	• for current configuration type, this is the supported bitmasks that the host can change.

8.1104.2 Field Documentation

8.1104.2.1 uint8_t swidms_supportedIntBitmaskTlv::TlvPresent

8.1104.2.2 uint32_t swidms_supportedIntBitmaskTlv::ValidBitmasks

8.1105 swidms_SwiDmsGetHWWatchdog Struct Reference

Data Fields

- uint32_t timeout
- uint32_t resetDelay
- uint8_t enable
- uint32_t count

8.1105.1 Detailed Description

This structure contains the parameters for hardware watchdog settings

Parameters

timeout	• timeout value for HW watchdog (unit in second)
resetDelay	• delay before reset after watchdog timeout (unit in second)
enable	• 0 to disable watchdog; 1 to enable watchdog
count	• once <timeout> has occurred, the <count> will be increased by 1 and the timer will be restarted automatically. This <count> indicates the number of renewals.

8.1105.2 Field Documentation

8.1105.2.1 uint32_t swidms_SwiDmsGetHWWatchdog::count

8.1105.2.2 uint8_t swidms_SwiDmsGetHWWatchdog::enable

8.1105.2.3 uint32_t swidms_SwiDmsGetHWWatchdog::resetDelay

8.1105.2.4 uint32_t swidms_SwiDmsGetHWWatchdog::timeout

8.1106 swidms_usbMTUSizeTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint16_t UsbMTUSize

8.1106.1 Detailed Description

This structure contains the parameters for USB MTU Size

Parameters

TlvPresent	• Tlv Present.
UsbMTUSize	USB MTU size • Size of USB MTU

8.1106.2 Field Documentation

8.1106.2.1 uint8_t swidms_usbMTUSizeTlv::TlvPresent

8.1106.2.2 uint16_t swidms_usbMTUSizeTlv::UsbMTUSize

8.1107 SwiDmsGetHWWatchdog Struct Reference

Data Fields

- ULONG timeout
- ULONG resetDelay
- BYTE enable
- ULONG count

8.1107.1 Detailed Description

This structure contains the get hardware watchdog settings response

Parameters

timeout	• timeout value for HW watchdog (unit in second)
resetDelay	• delay before reset after watchdog timeout (unit in second)
enable	• 0 to disable watchdog; 1 to enable watchdog
count	• once <timeout> has occurred, the <count> will be increased by 1 and the timer will be restarted automatically. This <count> indicates the number of renewals.

8.1107.2 Field Documentation

8.1107.2.1 ULONG SwiDmsGetHWWatchdog::count

8.1107.2.2 BYTE SwiDmsGetHWWatchdog::enable

8.1107.2.3 ULONG SwiDmsGetHWWatchdog::resetDelay

8.1107.2.4 ULONG SwiDmsGetHWWatchdog::timeout

8.1108 SwiDmsGetMTUResp Struct Reference

Data Fields

- mtuSize3gppTlv * pMTUSize3gpp
- hrpdMTUSizeTlv * pHrpdMTUSize
- ehrpdMTUSizeTlv * pEhrpdMTUSize
- usbMTUSizeTlv * pUsbMTUSize

8.1108.1 Detailed Description

This structure contains the Get MTU Response parameter.

Parameters

pMTUSize3gpp	[Optional] • See mtuSize3gppTlv for more information
pHrpdMTUSize	[Optional] • See hrpdMTUSizeTlv for more information
pEhrpdMTUSize	[Optional] • See ehrpdMTUSizeTlv for more information
pUsbMTUSize	[Optional] • See usbMTUSizeTlv for more information

8.1108.2 Field Documentation

8.1108.2.1 ehrpdMTUSizeTlv∗ SwiDmsGetMTUResp::pEhrpdMTUSize

8.1108.2.2 hrpdMTUSizeTlv∗ SwiDmsGetMTUResp::pHrpdMTUSize

8.1108.2.3 mtuSize3gppTlv∗ SwiDmsGetMTUResp::pMTUSize3gpp

8.1108.2.4 usbMTUSizeTlv∗ SwiDmsGetMTUResp::pUsbMTUSize

8.1109 SwiDmsGetSecureInfoResp Struct Reference

Data Fields

- BYTE secureBootEnabled
- BYTE memoryDumpAllowed
- BYTE jtagAccessAllowed

8.1109.1 Detailed Description

This structure contains the Get Secure Info Response parameter.

Parameters

secureBootEnabled	[Mandatory] 0- Disabled 1- Enabled
memoryDumpAllowed	[Mandatory] 0- Disallowed 1- Allowed
jtagAccessAllowed	[Mandatory] 0- Disallowed 1- Allowed

8.1109.2 Field Documentation

8.1109.2.1 BYTE SwiDmsGetSecureInfoResp::jtagAccessAllowed

8.1109.2.2 BYTE SwiDmsGetSecureInfoResp::memoryDumpAllowed

8.1109.2.3 BYTE SwiDmsGetSecureInfoResp::secureBootEnabled

8.1110 SwiDmsGetUsbCompResp Struct Reference

Data Fields

- intfaceCfgTlv * pInterfaceCfg
- supportedIntBitmaskTlv * pSupportedBitmasks

8.1110.1 Detailed Description

This structure contains the get usb composition response

Parameters

pInterfaceCfg	• See intfaceCfgTlv for more information
pSupported-Bitmasks	[Optional] • See supportedIntBitmaskTlv for more information

8.1110.2 Field Documentation

8.1110.2.1 intfaceCfgTlv* SwiDmsGetUsbCompResp::pInterfaceCfg

8.1110.2.2 supportedIntBitmaskTlv* SwiDmsGetUsbCompResp::pSupportedBitmasks

8.1111 SwiDmsSetHWWatchdog Struct Reference

Data Fields

- ULONG timeout
- ULONG resetDelay
- BYTE enable

8.1111.1 Detailed Description

This structure contains the set hardware watchdog settings

Parameters

timeout	• timeout value for HW watchdog (unit in second)
resetDelay	• delay before reset after watchdog timeout (unit in second)
enable	• 0 to disable watchdog; 1 to enable watchdog

8.1111.2 Field Documentation

8.1111.2.1 BYTE SwiDmsSetHWWatchdog::enable

8.1111.2.2 ULONG SwiDmsSetHWWatchdog::resetDelay

8.1111.2.3 ULONG SwiDmsSetHWWatchdog::timeout

8.1112 SwiDmsSLQSGetUsbNetNum Struct Reference

Data Fields

- BYTE usbNetNum

8.1112.1 Detailed Description

This structure contains QMAP configuration

Parameters

usbNetNum	• Number of usb net • Range is 0-8

8.1112.2 Field Documentation

8.1112.2.1 BYTE SwiDmsSLQSGetUsbNetNum::usbNetNum

8.1113 SwiDmsUIMSelectReq Struct Reference

Data Fields

- BYTE uim_select

8.1113.1 Detailed Description

This structure contains the Swi UIM select parameter.

Parameters

uim_select	• Selection of UIM Card – 0 - Slot 1 (External UIM Interface) – 1 - Slot 2 (Embedded UIM) – 2 - Remote UIM – 3 - Auto switch

Note

Auto switch is applicable only if UIMAUTOSWITCH feature is enabled. This feature will activate the auto-switch mechanism if it is inactive.

8.1113.2 Field Documentation

8.1113.2.1 BYTE SwiDmsUIMSelectReq::uim_select

8.1114 SwiLocGetAutoStartResp Struct Reference

Data Fields

- BYTE function
- BOOL function_reported
- BYTE fix_type
- BOOL fix_type_reported
- BYTE max_time
- BOOL max_time_reported
- ULONG max_dist
- BOOL max_dist_reported
- ULONG fix_rate
- BOOL fix_rate_reported

8.1114.1 Detailed Description

This structure contains SWI LOC Get Auto Start setting

Parameters

function	• Setting to indicate when modem should start an automatic GNSS fix – 0 - disabled – 1 - At bootup – 2 - When NMEA port is opened
function_reported	• 0 - not reported by modem • 1 - reported by modem
fix_type	• Type of GNSS fix: – 1 - Default Engine mode – 2 - MS-Based – 3 - MS-Assisted – 4 - Standalone
fix_type_reported	• 0 - not reported by modem • 1 - reported by modem
max_time	• Maximum time allowed for the receiver to get a fix in seconds • Valid range: 1-255
max_time_reported	• 0 - not reported by modem • 1 - reported by modem

max_dist	• Maximum uncertainty of a fix measured by distance in meters • Valid range: 1 - 4294967280
max_dist_reported	• 0 - not reported by modem • 1 - reported by modem
fix_rate	• Time between fixes in seconds • Valid range: 1–65535
fix_rate_reported	• 0 - not reported by modem • 1 - reported by modem

8.1114.2 Field Documentation

8.1114.2.1 ULONG SwiLocGetAutoStartResp::fix_rate

8.1114.2.2 BOOL SwiLocGetAutoStartResp::fix_rate_reported

8.1114.2.3 BYTE SwiLocGetAutoStartResp::fix_type

8.1114.2.4 BOOL SwiLocGetAutoStartResp::fix_type_reported

8.1114.2.5 BYTE SwiLocGetAutoStartResp::function

8.1114.2.6 BOOL SwiLocGetAutoStartResp::function_reported

8.1114.2.7 ULONG SwiLocGetAutoStartResp::max_dist

8.1114.2.8 BOOL SwiLocGetAutoStartResp::max_dist_reported

8.1114.2.9 BYTE SwiLocGetAutoStartResp::max_time

8.1114.2.10 BOOL SwiLocGetAutoStartResp::max_time_reported

8.1115 SwiLocSetAutoStartReq Struct Reference

Data Fields

- BYTE function
- BOOL set_function
- BYTE fix_type
- BOOL set_fix_type
- BYTE max_time
- BOOL set_max_time
- ULONG max_dist
- BOOL set_max_dist
- ULONG fix_rate
- BOOL set_fix_rate

8.1115.1 Detailed Description

This structure contains SWI LOC Get Auto Start setting

Parameters

function	• Setting to indicate when modem should start an automatic GNSS fix – 0 - disabled – 1 - At bootup – 2 - When NMEA port is opened
set_function	• 0 - do not set to modem • 1 - set to modem
fix_type	• Type of GNSS fix: – 1 - Default Engine mode – 2 - MS-Based – 3 - MS-Assisted – 4 - Standalone
set_fix_type	• 0 - do not set to modem • 1 - set to modem
max_time	• Maximum time allowed for the receiver to get a fix in seconds • Valid range: 1-255
set_max_time	• 0 - do not set to modem • 1 - set to modem
max_dist	• Maximum uncertainty of a fix measured by distance in meters • Valid range: 1 - 4294967280
set_max_dist	• 0 - do not set to modem • 1 - set to modem
fix_rate	• Time between fixes in seconds • Valid range: 1–65535
set_fix_rate	• 0 - do not set to modem • 1 - set to modem

8.1115.2 Field Documentation

8.1115.2.1 ULONG SwiLocSetAutoStartReq::fix_rate

8.1115.2.2 BYTE SwiLocSetAutoStartReq::fix_type

8.1115.2.3 BYTE SwiLocSetAutoStartReq::function

8.1115.2.4 ULONG SwiLocSetAutoStartReq::max_dist

8.1115.2.5 BYTE SwiLocSetAutoStartReq::max_time

8.1115.2.6 BOOL SwiLocSetAutoStartReq::set_fix_rate

8.1115.2.7 BOOL SwiLocSetAutoStartReq::set_fix_type

8.1115.2.8 BOOL SwiLocSetAutoStartReq::set_function

8.1115.2.9 BOOL SwiLocSetAutoStartReq::set_max_dist

8.1115.2.10 BOOL SwiLocSetAutoStartReq::set_max_time

8.1116 swiModemStatusResp Struct Reference

Data Fields

- CommInfo commonInfo
- LTEInfo * pLTEInfo

8.1116.1 Detailed Description

Structure for storing the SLQS Nas Swi Modem Status response parameters.

Parameters

commonInfo	(mandatory) • See CommInfo for more information
pLTEInfo	(optional) • See LTEInfo for more information

8.1116.2 Field Documentation

8.1116.2.1 CommInfo swiModemStatusResp::commonInfo

8.1116.2.2 LTEInfo* swiModemStatusResp::pLTEInfo

8.1117 SwiOTAMsg_s Struct Reference

Data Fields

- ULONG type
- WORD data_len
- BYTE data [2048]
- LteNasReleaseInfo * pLteNasRelInfo

- ULONGLONG * pTime

8.1117.1 Detailed Description

This structure contains OTA message

Parameters

type	• message type – 0 - LTE ESM uplink – 1 - LTE ESM downlink – 2 - LTE EMM uplink – 3 - LTE EMM downlink – 4 - GSM/UMTS uplink – 5 - GSM/UMTS downlink
data_len	• OTA Message Content Length
data	• OTA Message Content
pLteNasRelInfo	• LTE NAS Release Info • see LteNasReleaseInfo for details
pTime	• Seconds in local time since Jan. 6th 1980 00:00:00 UTC

8.1117.2 Field Documentation

8.1117.2.1 BYTE SwiOTAMsg_s::data[2048]

8.1117.2.2 WORD SwiOTAMsg_s::data_len

8.1117.2.3 LteNasReleaseInfo* SwiOTAMsg_s::pLteNasRelInfo

8.1117.2.4 ULONGLONG* SwiOTAMsg_s::pTime

8.1117.2.5 ULONG SwiOTAMsg_s::type

8.1118 swiPDPRuntimeSettingsReq Struct Reference

Data Fields

- BYTE contextId
- BYTE contextType

8.1118.1 Detailed Description

This structure contains the PDP Runtime Settings Request parameters.

Parameters

contextId	• Context Identifier
contextType	• Identifies technology type – 0 - 3GPP – 1 - 3GPP2

8.1118.2 Field Documentation

8.1118.2.1 BYTE swiPDPRuntimeSettingsReq::contextId

8.1118.2.2 BYTE swiPDPRuntimeSettingsReq::contextType

8.1119 swiPDPRuntimeSettingsResp Struct Reference

Data Fields

- BYTE * pContextId
- BYTE * pBearerId
- CHAR * pAPNName
- ULONG * pIPv4Address
- ULONG * pIPv4GWAddress
- ULONG * pPrDNSIPv4Address
- ULONG * pSeDNSIPv4Address
- struct IPV6AddressInfo * pIPv6Address
- struct IPV6AddressInfo * pIPv6GWAddress
- WORD * pPrDNSIPv6Address
- WORD * pSeDNSIPv6Address
- ULONG * pPrPCSCFIPv4Address
- ULONG * pSePCSCFIPv4Address
- WORD * pPrPCSCFIPv6Address
- WORD * pSePCSCFIPv6Address

8.1119.1 Detailed Description

This structure contains the response parameters retrieved by the API SLQSWdsSwiPDPRuntimeSettings

Parameters

pContextId	(optional) • Context Identifier – 0xFF - Not Available
pBearerId	(optional) • Bearer Identity • An EPS bearer identity uniquely identifies an EPS bearer for one UE accessing via E-UTRAN. The EPS Bearer Identity is allocated by the MME. – 0xFF - Not Available

pAPNName	(optional) • APN name associated with the context id – NULL terminated by default.
pIPv4Address	(optional) • IPv4 Address – 0xFFFF - Not Available
pIPv4GW-Address	(optional) • IPv4 Gateway Address – 0xFFFF - Not Available
pPrDNSIPv4-Address	(optional) • Primary DNS IPv4 Address – 0xFFFF - Not Available
pSeDNSIPv4-Address	(optional) • Secondary DNS IPv4 Address – 0xFFFF - Not Available
pIPv6Address	(optional) • IPv6 Address • See IPV6AddressInfo for more information
pIPv6GW-Address	(optional) • IPv6 Gateway Address • See IPV6AddressInfo for more information
pPrDNSIPv6-Address	(optional) • Primary IPv6 DNS Address(in network byte order) • This is an 8-element array of 16-bit numbers, each of which is in big-endian format
pSeDNSIPv6-Address	(optional) • Secondary IPv6 DNS Address(in network byte order) • This is an 8-element array of 16-bit numbers, each of which is in big-endian format
pPrPCSCFIPv4-Address	(optional) • Primary PCSCF IPv4 Address
pSePCSCFIPv4-Address	(optional) • Secondary PCSCF IPv4 Address
pPrPCSCFIPv6-Address	(optional) • Primary PCSCF IPv6 Address • This is an 8-element array of 16-bit numbers, each of which is in big-endian format
pSePCSCFIPv6-Address	(optional) • Secondary PCSCF IPv6 Address • This is an 8-element array of 16-bit numbers, each of which is in big-endian format

Note

Parameters which are mentioned as NULL will be ignored.

8.1119.2 Field Documentation

8.1119.2.1 CHAR* swiPDPRuntimeSettingsResp::pAPNName

8.1119.2.2 BYTE* swiPDPRuntimeSettingsResp::pBearerId

8.1119.2.3 BYTE* swiPDPRuntimeSettingsResp::pContextId

8.1119.2.4 ULONG* swiPDPRuntimeSettingsResp::pIPv4Address

8.1119.2.5 ULONG* swiPDPRuntimeSettingsResp::pIPv4GWAddress

8.1119.2.6 struct IPV6AddressInfo* swiPDPRuntimeSettingsResp::pIPv6Address

8.1119.2.7 struct IPV6AddressInfo* swiPDPRuntimeSettingsResp::pIPv6GWAddress

8.1119.2.8 ULONG* swiPDPRuntimeSettingsResp::pPrDNSIPv4Address

8.1119.2.9 WORD* swiPDPRuntimeSettingsResp::pPrDNSIPv6Address

8.1119.2.10 ULONG* swiPDPRuntimeSettingsResp::pPrPCSCFIPv4Address

8.1119.2.11 WORD* swiPDPRuntimeSettingsResp::pPrPCSCFIPv6Address

8.1119.2.12 ULONG* swiPDPRuntimeSettingsResp::pSeDNSIPv4Address

8.1119.2.13 WORD* swiPDPRuntimeSettingsResp::pSeDNSIPv6Address

8.1119.2.14 ULONG* swiPDPRuntimeSettingsResp::pSePCSCFIPv4Address

8.1119.2.15 WORD* swiPDPRuntimeSettingsResp::pSePCSCFIPv6Address

8.1120 swiQosFilter Struct Reference

Data Fields

- BYTE index
- BYTE version
- IPv4Addr * pIPv4SrcAddr
- IPv4Addr * pIPv4DstAddr
- BYTE * pNxtHdrProto
- Tos * pTos
- IPv6Addr * pIPv6SrcAddr
- IPv6Addr * pIPv6DstAddr
- IPv6TrafCls * pIPv6TrafCls
- ULONG * pIPv6Label
- Port * pTCPSrcPort
- Port * pTCPDstPort
- Port * pUDPSrcPort
- Port * pUDPDstPort
- ULONG * pEspSpi

- WORD ∗ pPrecedence
- WORD ∗ pId
- Port ∗ pTranSrcPort
- Port ∗ pTranDstPort

8.1120.1 Detailed Description

This structure contains the QoS Filter Request

Parameters

index	IP filter index Integer that uniquely identifies each filter instance This TLV must be present in the request
version	IP filter version Identifies whether the filter is associated with IPv4 or IPv6; value specified also implies that only TLVs defined for that IP version, i.e., TLVs with IPv4 or IPv6 in the name, can be specified • 0x04 - IPv4 • 0x06 - Ipv6
pIPv4SrcAddr	IPv4 filter soruce address See IPv4Addr for more information • Implemented only for unsolicited indication
pIPv4DstAddr	IPv4 filter destination address See IPv4Addr for more information • Implemented only for unsolicited indication
pNxtHdrProto	IP filter next header protocol This TLV must be present if any non-IP filter TLV(s) are provided If this field is specified, only IP packets belonging to specified higher layer protocol are considered when filtering The following protocols may be specified: • 0x01 = ICMP • 0x06 = TCP • 0x11 = UDP • 0x32 = ESP Note: The next header protocol field will be set to 0xFD (TCP & UDP) if a TFT is received specifying a source or destination port number, but IP next header type is not specified.
pTos	IPv4 filter type of service See Tos for more information
pIPv6SrcAddr	IPv6 filter soruce address See IPv6Addr for more information • Implemented only for unsolicited indication
pIPv6DstAddr	IPv6 filter destination address See IPv6Addr for more information • Implemented only for unsolicited indication
pIPv6TrafCls	IPv6 filter traffic class See IPv6TrafCls for more information
pIPv6Label	IPv6 flow label Packet matches the IPv6 flow label filter if: (∗pIPv6Label == flow label in the IPv6 header) • Implemented only for unsolicited indication
pTCPSrcPort	TCP filter source port filter See Port for more information • Implemented only for unsolicited indication
pTCPDstPort	TCP filter destination port filter See Port for more information • Implemented only for unsolicited indication
pUDPSrcPort	UDP filter source port filter See Port for more information • Implemented only for unsolicited indication

pUDPDstPort	UDP filter destination port filter See Port for more information • Implemented only for unsolicited indication
pEspSpi	ESP filter security policy index Security policy index to uniquely identify each IP flow for filtering encrypted packets for encapsulating security payload • Implemented only for unsolicited indication
pPrecedence	Filter Precedence Specifies the order in which filters are applied; lower numerical value has higher precedence Note: This TLV only applies to network-initiated QoS; QoS requests containing this TLV from control points will be ignored
pId	Filter ID Unique identifier for each filter;filter ID is assigned by the modem Note: This TLV only applies to network-initiated QoS; QoS requests containing this TLV from control points will be ignored
pTranSrcPort	Transport protocolfilter source port See Port for more information • Implemented only for unsolicited indication
pUDPDstPort	Transport protocol filter destination port See Port for more information • Implemented only for unsolicited indication

8.1120.2 Field Documentation

8.1120.2.1 BYTE swiQosFilter::index

8.1120.2.2 ULONG* swiQosFilter::pEspSpi

8.1120.2.3 WORD* swiQosFilter::pId

8.1120.2.4 IPv4Addr* swiQosFilter::pIPv4DstAddr

8.1120.2.5 IPv4Addr* swiQosFilter::pIPv4SrcAddr

8.1120.2.6 IPv6Addr* swiQosFilter::pIPv6DstAddr

8.1120.2.7 ULONG* swiQosFilter::pIPv6Label

8.1120.2.8 IPv6Addr* swiQosFilter::pIPv6SrcAddr

8.1120.2.9 IPv6TrafCls* swiQosFilter::pIPv6TrafCls

8.1120.2.10 BYTE* swiQosFilter::pNxtHdrProto

8.1120.2.11 WORD* swiQosFilter::pPrecedence

8.1120.2.12 Port* swiQosFilter::pTCPDstPort

8.1120.2.13 Port* swiQosFilter::pTCPSrcPort

8.1120.2.14 Tos* swiQosFilter::pTos

8.1120.2.15 Port* swiQosFilter::pTranDstPort

8.1120.2.16 Port* swiQosFilter::pTranSrcPort

8.1120.2.17 Port* swiQosFilter::pUDPDstPort

8.1120.2.18 Port* swiQosFilter::pUDPSrcPort

8.1120.2.19 BYTE swiQosFilter::version

8.1121 swiQosFlow Struct Reference

Data Fields

- BYTE index
- WORD * pProfileId3GPP2
- BYTE * p3GPP2Pri
- BYTE * pTrafficClass
- dataRate * pDataRate
- tokenBucket * pTokenBucket
- ULONG * pLatency
- ULONG * pJitter
- pktErrRate * pPktErrRate
- ULONG * pMinPolicedPktSz
- ULONG * pMaxAllowedPktSz
- WORD * p3GPPResResidualBER
- BYTE * p3GPPTraHdlPri
- BYTE * p3GPPImCn
- BYTE * p3GPPSigInd
- BYTE * pLteQci

8.1121.1 Detailed Description

This structure contains the QoS Flow Request

Parameters

index	• IP flow index • Integer that uniquely identifies each flow instance • Unique index must be assigned by the control point to every flow_spec instance
pProfileId3GPP2	• IP flow 3GPP2 profile ID • A profile ID is shorthand for a defined set of QoS flow parameters specified by the network; to be present while requesting QoS for a CDMA device
p3GPP2Pri	• IP flow 3GPP2 flow priority • Flow priority used by the network in case of contention between flows with same QoS; this parameter applies for CDMA devices
pTrafficClass	• IP flow traffic class • Integer that designates the requested traffic class: • 0 - Conversational • 1 - Streaming • 2 - Interactive • 3 - Background

pDataRate	• IP flow data rate min max • See dataRate for more information
pTokenBucket	• IP flow data rate token bucket • See tokenBucket for more information
pLatency	• IP flow latency • Maximum delay (in milliseconds) that can be tolerated by an IP packet during transfer through the wireless link
pJitter	• IP flow jitter • Difference between the maximum and minimum latency (in milliseconds) that can be tolerated by an IP packet during the transfer through the wireless link
pPktErrRate	• IP flow packet error rate • See pktErrRate for more information
pMinPolicedPkt-Sz	• IP flow minimum policed packet size • Integer that defines the minimum packet size (in bytes) that will be policed for QoS guarantees; any IP packets that are smaller than the minimum specified policed size may not receive requested QoS
pMaxAllowed-PktSz	• IP flow maximum allowed packet size • Integer that defines the maximum packet size (in bytes) allowed in the IP flow; any IP packets greater in size than the maximum allowed packet size are not queued for transmission
p3GPPRes-ResidualBER	• IP flow 3GPP residual bit error rate • residual_bit_error_rate • 0 = 5∗10-2 residual BER • 1 = 1∗10-2 residual BER • 2 = 5∗10-3 residual BER • 3 = 4∗10-3 residual BER • 4 = 1∗10-3 residual BER • 5 = 1∗10-4 residual BER • 6 = 1∗10-5 residual BER • 7 = 1∗10-6 residual BER • 8 = 6∗10-8 residual BER • Integer that indicates the undetected BER for each IP flow in the delivered packets; Tapplies only to 3GPP networks

p3GPPTraHdlPri	• 3GPP traffic handling priority • 0 - Relative traffic handling priority 1 • 1 - Relative traffic handling priority 2 • 2 - Relative traffic handling priority 3 • Defines the relative priority of the flow; applies only to 3GPP networks
p3GPPImCn	• IP flow 3GPP IM CN flag • IM CN subsystem signaling flag: • 0x00 - FALSE • 0x01 - TRUE • This parameter applies only to 3GPP networks
p3GPPSigInd	• IP flow 3GPP signaling indication • 0x00 - FALSE • 0x01 - TRUE • This parameter applies only to 3GPP networks

pLteQci	• LTE QoS Class Identifier
	• QoS Class Identifier(QCI) is a required parameter to request QoS in LTE
	• QCI values:
	  – QCI value 0 requests the network to assign the appropriate QCI value
	  – QCI values 1-4 are associated with guaranteed bitrates
	  – QCI values 5-9 are associated with nonguaranteed bitrates, so the values specified as guaranteed and maximum bitrates are ignored

8.1121.2 Field Documentation

8.1121.2.1 BYTE swiQosFlow::index

8.1121.2.2 BYTE* swiQosFlow::p3GPP2Pri

8.1121.2.3 BYTE* swiQosFlow::p3GPPImCn

8.1121.2.4 WORD* swiQosFlow::p3GPPResResidualBER

8.1121.2.5 BYTE* swiQosFlow::p3GPPSigInd

8.1121.2.6 BYTE* swiQosFlow::p3GPPTraHdlPri

8.1121.2.7 dataRate* swiQosFlow::pDataRate

8.1121.2.8 ULONG* swiQosFlow::pJitter

8.1121.2.9 ULONG* swiQosFlow::pLatency

8.1121.2.10 BYTE* swiQosFlow::pLteQci

8.1121.2.11 ULONG* swiQosFlow::pMaxAllowedPktSz

8.1121.2.12 ULONG* swiQosFlow::pMinPolicedPktSz

8.1121.2.13 pktErrRate* swiQosFlow::pPktErrRate

8.1121.2.14 WORD* swiQosFlow::pProfileId3GPP2

8.1121.2.15 tokenBucket* swiQosFlow::pTokenBucket

8.1121.2.16 BYTE* swiQosFlow::pTrafficClass

8.1122 swiQosGranted Struct Reference

Data Fields

- swiQosFlow * pTxFlow
- swiQosFlow * pRxFlow

8.1122.1 Detailed Description

This structure contains the QoS granted flow

Parameters

pTxFlow	See swiQosFlow for more information
pRxFlow	See swiQosFlow for more information

8.1122.2 Field Documentation

8.1122.2.1 swiQosFlow* swiQosGranted::pRxFlow

8.1122.2.2 swiQosFlow* swiQosGranted::pTxFlow

8.1123 swiQosIds Struct Reference

Data Fields

- BYTE sz
- ULONG * pIds

8.1123.1 Detailed Description

This structure contains the QoS Response parameters.

Parameters

sz	Number of QoS identifiers
pIds	Identifier for the QoS flow requested; number of QoS identifiers present will be equal to number of QoS specs requested in the QoS Request message

8.1123.2 Field Documentation

8.1123.2.1 ULONG* swiQosIds::pIds

8.1123.2.2 BYTE swiQosIds::sz

8.1124 swiQosModifyReq Struct Reference

Data Fields

- ULONG id
- swiQosFlow * pTxFlow
- swiQosFlow * pRxFlow
- swiQosFilter * pTxFilter
- swiQosFilter * pRxFilter

8.1124.1 Detailed Description

This structure contains the QoS Request parameters.

Parameters

id	Identifier for the QoS flow/instance that has been negotiated and that needs to be modified The QoS_identifier is used to reference the actual flow/filter specifications that are in effect as a result of the negotiation triggered by QMI_QOS_REQUEST_QOS_REQ
pTxFlow	See swiQosFlow for more information
pRxFlow	See swiQosFlow for more information
pTxFilter	See swiQosFilter for more information
pRxFilter	See swiQosFilter for more information

8.1124.2 Field Documentation

8.1124.2.1 ULONG swiQosModifyReq::id

8.1124.2.2 swiQosFilter* swiQosModifyReq::pRxFilter

8.1124.2.3 swiQosFlow* swiQosModifyReq::pRxFlow

8.1124.2.4 swiQosFilter* swiQosModifyReq::pTxFilter

8.1124.2.5 swiQosFlow* swiQosModifyReq::pTxFlow

8.1125 swiQosReq Struct Reference

Data Fields

- BYTE index
- swiQosFlow * pTxFlow
- swiQosFlow * pRxFlow
- swiQosFilter * pTxFilter
- swiQosFilter * pRxFilter

8.1125.1 Detailed Description

This structure contains the QoS Request parameters.

Parameters

index	• An integer that uniquely identifies each QoS spec included in the QoS request message
pTxFlow	• See swiQosFlow for more information
pRxFlow	• See swiQosFlow for more information
pTxFilter	• See swiQosFilter for more information
pRxFilter	• See swiQosFilter for more information

8.1125.2 Field Documentation

8.1125.2.1 BYTE swiQosReq::index

8.1125.2.2 swiQosFilter* swiQosReq::pRxFilter

8.1125.2.3 swiQosFlow* swiQosReq::pRxFlow

8.1125.2.4 swiQosFilter* swiQosReq::pTxFilter

8.1125.2.5 swiQosFlow* swiQosReq::pTxFlow

8.1126 swiRMTrasnferStaticsReq Struct Reference

Data Fields

- BYTE bResetStatistics
- ULONG ulMask

8.1126.1 Detailed Description

RM Transfer Satistics Structure

Parameters

bResetStatistics	• Reset Statistics • Values: • 0 - Not Reset • Other - Reset

ulMask	• Enable/Disable RM Transfer Satatistics Indiscation Mask • Bit 0: Tx Packet Ok • Bit 1: Rx Packet Ok • Bit 2: Tx Bytes Ok • Bit 3: Rx Bytes Ok • Bit 4: Tx Packets Dropped • Bit 5: Rx Packets Dropped • Value: -0 - Disable -1 - Enable

8.1126.2 Field Documentation

8.1126.2.1 BYTE swiRMTrasnferStaticsReq::bResetStatistics

8.1126.2.2 ULONG swiRMTrasnferStaticsReq::ulMask

8.1127 sysInfoCommon Struct Reference

Data Fields

- BYTE srvDomainValid
- BYTE srvDomain
- BYTE srvCapabilityValid
- BYTE srvCapability
- BYTE roamStatusValid
- BYTE roamStatus
- BYTE isSysForbiddenValid
- BYTE isSysForbidden

8.1127.1 Detailed Description

Structure for storing the System Information common to CDMA, HDR, GSM, WCDMA and LTE networks.

Parameters

srvDomainValid	• Indicates whether the service domain is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
srvDomain	• Service domain registered on the system. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available

srvCapability-Valid	• Indicates whether the service capability is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
srvCapability	• Current system's service capability. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available
roamStatusValid	• Indicates whether the roaming status is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
roamStatus	• Current roaming status. – 0x00 - Off – 0x01 - On – 0x02 - Blinking – 0x03 - Out of the neighborhood – 0x04 - Out of the building – 0x05 - Preferred system – 0x06 - Available system – 0x07 - Alliance partner – 0x08 - Premium partner – 0x09 - Full service – 0x0A - Partial service – 0x0B - Banner is on – 0x0C - Banner is off – 0x0D to 0x3F - Reserved for Standard Enhanced Roaming Indicator Numbers – 0x40 to 0x7F - Reserved for Non-Standard Enhanced Roaming Indicator Numbers – 0x40 to 0xFF - Reserved. – 0xFF - Not Available • Values from 0x02 onward are only applicable for 3GPP2
isSysForbidden-Valid	• Indicates whether the forbidden system is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

isSysForbidden	• Whether the system is forbidden. – 0x00 - Not forbidden – 0x01 - Forbidden – 0xFF - Not Available

8.1127.2 Field Documentation

8.1127.2.1 BYTE sysInfoCommon::isSysForbidden

8.1127.2.2 BYTE sysInfoCommon::isSysForbiddenValid

8.1127.2.3 BYTE sysInfoCommon::roamStatus

8.1127.2.4 BYTE sysInfoCommon::roamStatusValid

8.1127.2.5 BYTE sysInfoCommon::srvCapability

8.1127.2.6 BYTE sysInfoCommon::srvCapabilityValid

8.1127.2.7 BYTE sysInfoCommon::srvDomain

8.1127.2.8 BYTE sysInfoCommon::srvDomainValid

8.1128 sysSelectPrefParamsExt Struct Reference

Data Fields

- sysSelectPrefParams * pSysSelectPrefParams
- struct lteBandPrefExt * pLTEBandPrefExt
- ULONGLONG * pCiotLteOpModePref
- ULONGLONG * pLteM1BandPref
- ULONGLONG * pLteNb1BandPref
- ULONG * pCiotLteOpMode
- struct ciotAcqOrderPref * pCiotAcqOrderPref
- struct nr5gBandPref * pNr5gBandPref

8.1128.1 Detailed Description

Contain the system selection preferences.

Parameters

pSysSelectPrefParams[IN]	• See sysSelectPrefParams for more information
pLTEBandPrefExt[IN]	• LTE Band Preference Extended • see lteBandPrefExt for more information

pCiotLteOp-ModePref[IN]	• CIOT LTE Operational Mode Preference • Bitmask representing the CIoT LTE operational mode preference to be set. • Values : – Bit 0 - LTE wideband – Bit 1 - LTE M1 – Bit 2 - LTE NB1 All unlisted bits are reserved for future use and the service point ignores them if used. If this TLV is not present, the modem will use the value read from the NV during bootup.

pLteM1Band-Pref[IN]	• Bitmask representing the LTE M1 band preference to be set. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127

- If this field is not present, the modem will use the M1 band preference value read from the NV.

Parameters

pLteNb1Band-Pref[IN]	• Bitmask representing the LTE NB1 band preference to be set. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127 • If this field is not present, the modem will use the NB1 band preference value read from the NV.

pCiotLteOpMode	• This TLV is used when the net_sel_pref is MANUAL and RAT TLV is LTE. • This TLV indicates the the operational mode to be used during the manual LTE PLMN selection. • Values : – 0x00 - No service – 0x01 - Camped on LTE wideband – 0x02 - Camped on LTE M1 – 0x03 - Camped on LTE NB1
pCiotAcqOrder-Pref[IN]	• CIOT Acquisition Order Preference • see ciotAcqOrderPref for more information
pNr5gBandPref[-IN]	• NR5G Band Preference • see nr5gBandPref for more information

8.1128.2 Field Documentation

8.1128.2.1 struct ciotAcqOrderPref* sysSelectPrefParamsExt::pCiotAcqOrderPref

8.1128.2.2 ULONG* sysSelectPrefParamsExt::pCiotLteOpMode

8.1128.2.3 ULONGLONG* sysSelectPrefParamsExt::pCiotLteOpModePref

8.1128.2.4 struct lteBandPrefExt* sysSelectPrefParamsExt::pLTEBandPrefExt

8.1128.2.5 ULONGLONG* sysSelectPrefParamsExt::pLteM1BandPref

8.1128.2.6 ULONGLONG* sysSelectPrefParamsExt::pLteNb1BandPref

8.1128.2.7 struct nr5gBandPref* sysSelectPrefParamsExt::pNr5gBandPref

8.1128.2.8 sysSelectPrefParams* sysSelectPrefParamsExt::pSysSelectPrefParams

8.1129 t_gpsTime Struct Reference

Data Fields

- USHORT gpsWeek
- ULONG gpsTimeOfWeekMs

8.1129.1 Field Documentation

8.1129.1.1 ULONG t_gpsTime::gpsTimeOfWeekMs

8.1129.1.2 USHORT t_gpsTime::gpsWeek

8.1130 t_sensor Struct Reference

Data Fields

- ULONG usageMask
- ULONG aidingIndicatorMask

8.1130.1 Field Documentation

8.1130.1.1 ULONG t_sensor::aidingIndicatorMask

8.1130.1.2 ULONG t_sensor::usageMask

8.1131 t_Sv Struct Reference

Data Fields

- BYTE len
- USHORT entries [255]

8.1131.1 Field Documentation

8.1131.1.1 USHORT t_Sv::entries[255]

8.1131.1.2 BYTE t_Sv::len

8.1132 TDSCDMAECIOThresh Struct Reference

Data Fields

- BYTE TDSCDMAECIOThreshListLen
- ULONG * pTDSCDMAECIOThreshList

8.1132.1 Detailed Description

This structure contains TDSCDMA ECIO threshold related parameters.

Parameters

TDSCDMAECIOThreshListLen	• Length of the TDSCDMA ECIO threshold list parameter to follow
pTDSCDMAECIOThreshList	• Array of ECIO thresholds (in dB) used by TD-SCDMA • Maximum of 32 values.

8.1132.2 Field Documentation

8.1132.2.1 ULONG* TDSCDMAECIOThresh::pTDSCDMAECIOThreshList

8.1132.2.2 BYTE TDSCDMAECIOThresh::TDSCDMAECIOThreshListLen

8.1133 TDSCDMARSCPThresh Struct Reference

Data Fields

- BYTE TDSCDMARSCPThreshListLen
- WORD * pTDSCDMARSCPThreshList

8.1133.1 Detailed Description

This structure contains TDSCDMA RSCP threshold related parameters.

Parameters

TDSCDMARSCPThreshListLen	• Length of the TDSCDMA RSCP threshold list parameter to follow
pTDSCDMARSCPThreshList	• Array of RSCP thresholds (in units of 0.1 dBm) • Maximum of 32 values • Range for RSCP values: -120 to -25 (in dBm).

8.1133.2 Field Documentation

8.1133.2.1 WORD* TDSCDMARSCPThresh::pTDSCDMARSCPThreshList

8.1133.2.2 BYTE TDSCDMARSCPThresh::TDSCDMARSCPThreshListLen

8.1134 TDSCDMARSSIThresh Struct Reference

Data Fields

- BYTE TDSCDMARSSIThreshListLen
- ULONG * pTDSCDMARSSIThreshList

8.1134.1 Detailed Description

This structure contains TDSCDMA RSSI threshold related parameters.

Parameters

TDSCDMARSSIThreshListLen	• Length of the TDSCDMA RSSI threshold list parameter to follow
pTDSCDMARSSIThreshList	• Array of RSSI thresholds (in dBm) used by TD-SCDMA • Maximum of 32 values.

8.1134.2 Field Documentation

8.1134.2.1 ULONG* TDSCDMARSSIThresh::pTDSCDMARSSIThreshList

8.1134.2.2 BYTE TDSCDMARSSIThresh::TDSCDMARSSIThreshListLen

8.1135 tdscdmaSigInfoExt Struct Reference

Data Fields

- float rssi
- float rscp
- float ecio
- float sinr

8.1135.1 Detailed Description

This structure contains the TDSCDMA Signal Strength Info Extended

Parameters

rssi	• Measured RSSI in dB
rscp[Optional]	• Measured RSCP in dBm
ecio[Optional]	• Measured ECIO in dBm.
sinr[Optional]	• Measured SINR in dB. -15 dB is sent to clients if the actual SINR is less than -15 dB

8.1135.2 Field Documentation

8.1135.2.1 float tdscdmaSigInfoExt::ecio

8.1135.2.2 float tdscdmaSigInfoExt::rscp

8.1135.2.3 float tdscdmaSigInfoExt::rssi

8.1135.2.4 float tdscdmaSigInfoExt::sinr

8.1136 TDSCDMASigInfoExt Struct Reference

Data Fields

- FLOAT rssi
- FLOAT rscp
- FLOAT ecio
- FLOAT sinr

8.1136.1 Detailed Description

This structure contains the TDSCDMA Signal Strength Info Extended

Parameters

rssi	• Measured RSSI in dB
rscp[Optional]	• Measured RSCP in dBm
ecio[Optional]	• Measured ECIO in dBm.
sinr[Optional]	• Measured SINR in dB. -15 dB is sent to clients if the actual SINR is less than -15 dB

8.1136.2 Field Documentation

8.1136.2.1 FLOAT TDSCDMASigInfoExt::ecio

8.1136.2.2 FLOAT TDSCDMASigInfoExt::rscp

8.1136.2.3 FLOAT TDSCDMASigInfoExt::rssi

8.1136.2.4 FLOAT TDSCDMASigInfoExt::sinr

8.1137 TDSCDMASINRCONFThresh Struct Reference

Data Fields

- BYTE TDSCDMASINRCONFThreshListLen
- FLOAT * pTDSCDMASINRCONFThreshList

8.1137.1 Detailed Description

This structure contains TDSCDMA SINR threshold related parameters.

Parameters

TDSCDMASINRCONFThreshListLen	• Length of the TDSCDMA SINR threshold list parameter to follow
pTDSCDMASINRCONFThreshList	• Array of SINR thresholds (in dB) used by TD-SCDMA • Maximum of 32 values

8.1137.2 Field Documentation

8.1137.2.1 FLOAT* TDSCDMASINRCONFThresh::pTDSCDMASINRCONFThreshList

8.1137.2.2 BYTE TDSCDMASINRCONFThresh::TDSCDMASINRCONFThreshListLen

8.1138 TDSCDMASINRThresh Struct Reference

Data Fields

- BYTE TDSCDMASINRThreshListLen
- ULONG * pTDSCDMASINRThreshList

8.1138.1 Detailed Description

This structure contains TDSCDMA SINR threshold related parameters.

Parameters

TDSCDMASINRThreshListLen	• Length of the TDSCDMA SINR threshold list parameter to follow
pTDSCDMASINRThreshList	• Array of SINR thresholds (in dB) used by TD-SCDMA • Maximum of 32 values

8.1138.2 Field Documentation

8.1138.2.1 ULONG* TDSCDMASINRThresh::pTDSCDMASINRThreshList

8.1138.2.2 BYTE TDSCDMASINRThresh::TDSCDMASINRThreshListLen

8.1139 tempData_t Struct Reference

Data Fields

- uint32_t timeSource
- uint32_t timeOfFirstSample
- uint8_t temperatureDataLen
- uint16_t timeOffset [64]
- uint32_t temperature [64]

8.1139.1 Detailed Description

This structure specifies information regarding the Temperature Data. Please check has_<Param_Name> field for presence of optional parameters

Parameters

timeSource	• Time source of the sensor data • Valid values – 0 - Sensor time source is unspecified – 1 - Time source is common between the sensors and the location engine

timeOfFirst-Sample	• Denotes a full 32-bit time stamp of the first (oldest) sample in this message. • The time stamp is in the time reference scale that is used by the sensor time source. • Units - Milliseconds
temperature-DataLen	• Number of sets of the following elements – timeOffset – temperature
timeOffset	• Sample time offset • Units - Milliseconds
temperature	• Sensor temperature. • Type - Floating point • Units - Degrees Celsius • Range -50 to +100.00

8.1139.2 Field Documentation

8.1139.2.1 uint32_t tempData_t::temperature[64]

8.1139.2.2 uint8_t tempData_t::temperatureDataLen

8.1139.2.3 uint32_t tempData_t::timeOfFirstSample

8.1139.2.4 uint16_t tempData_t::timeOffset[64]

8.1139.2.5 uint32_t tempData_t::timeSource

8.1140 tempratureData Struct Reference

Data Fields

- ULONG timeSource
- ULONG timeOfFirstSample
- BYTE temperatureDataLen
- WORD timeOffset [64]
- ULONG temperature [64]

8.1140.1 Detailed Description

This structure specifies information regarding the Temperature Data.

Parameters

timeSource	• Time source of the sensor data • Valid values – 0 - Sensor time source is unspecified – 1 - Time source is common between the sensors and the location engine
timeOfFirst-Sample	• Denotes a full 32-bit time stamp of the first (oldest) sample in this message. • The time stamp is in the time reference scale that is used by the sensor time source. • Units - Milliseconds
temperature-DataLen	• Number of sets of the following elements – timeOffset – temperature
timeOffset	• Sample time offset • Units - Milliseconds
temperature	• Sensor temperature. • Type - Floating point • Units - Degrees Celsius • Range -50 to +100.00

8.1140.2 Field Documentation

8.1140.2.1 ULONG temprature Data::temperature[64]

8.1140.2.2 BYTE temprature Data::temperatureDataLen

8.1140.2.3 ULONG temprature Data::timeOfFirstSample

8.1140.2.4 WORD temprature Data::timeOffset[64]

8.1140.2.5 ULONG temprature Data::timeSource

8.1141 TFTIDParams Struct Reference

Data Fields

- BYTE filterId
- BYTE eValid
- BYTE ipVersion
- WORD * pSourceIP
- BYTE sourceIPMask
- BYTE nextHeader
- WORD destPortRangeStart
- WORD destPortRangeEnd
- WORD srcPortRangeStart

- WORD srcPortRangeEnd
- ULONG IPSECSPI
- WORD tosMask
- ULONG flowLabel

8.1141.1 Detailed Description

structure contains traffic flow template parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

filterId	• Filter identifier
eValid	• Evaluation precedence index
pVersion	• IP version number – 4 - IPv4 – 6 - IPv6
sourceIP	• Source IP address – IPv4 - Fill the first 4 bytes – IPv6 - Fill all the 16 bytes
sourceIPMask	• Mask value for the source address
nextHeader	• Next header/protocol value
destPortRange-Start	• Start value of the destination port range
destPortRange-End	• End value of the destination port range
srcPortRange-Start	• Start value of the source port range
srcPortRange-End	• End value of the source port range
IPSECSPI	• IPSEC security parameter index
tosMask	• TOS mask (Traffic class for IPv6)

flowLabel	• Flow label

8.1141.2 Field Documentation

8.1141.2.1 WORD TFTIDParams::destPortRangeEnd

8.1141.2.2 WORD TFTIDParams::destPortRangeStart

8.1141.2.3 BYTE TFTIDParams::eValid

8.1141.2.4 BYTE TFTIDParams::filterId

8.1141.2.5 ULONG TFTIDParams::flowLabel

8.1141.2.6 ULONG TFTIDParams::IPSECSPI

8.1141.2.7 BYTE TFTIDParams::ipVersion

8.1141.2.8 BYTE TFTIDParams::nextHeader

8.1141.2.9 WORD* TFTIDParams::pSourceIP

8.1141.2.10 BYTE TFTIDParams::sourceIPMask

8.1141.2.11 WORD TFTIDParams::srcPortRangeEnd

8.1141.2.12 WORD TFTIDParams::srcPortRangeStart

8.1141.2.13 WORD TFTIDParams::tosMask

8.1142 timeInfo Struct Reference

Data Fields

- WORD year
- BYTE month
- BYTE day
- BYTE hour
- BYTE minute
- BYTE second
- BYTE dayOfWeek
- INT8 timeZone
- BYTE dayLtSavingAdj
- BYTE radioInterface
- BYTE TlvPresent

8.1142.1 Detailed Description

This structure contains the parameters for Network Time.

Parameters

year	• Year
month	• Month • 1 is January and 12 is December
day	• Day • Range - 1 to 31
hour	• Hour • Range - 0 to 59
minute	• Minute • Range - 0 to 59
second	• Second • Range - 0 to 59
dayOfWeek	• Day of the week • 0 is Monday and 6 is Sunday
timeZone	• Offset from Universal time • The difference between local time and Universal time, in increments of 15 min • Signed Value
dayLtSavingAdj	• Daylight saving adjustment in hours • Possible values - 0, 1, and 2. • This field is ignored if radio_if is NAS_RADIO_IF_CDMA_1XEVDO
radioInterface	• Radio interface from which the information comes • Values – 0x01 - NAS_RADIO_IF_CDMA_1X - cdma2000 1X – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO) – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE – 0x09 - NAS_RADIO_IF_TDSCDMA -TD-SCDMA
TlvPresent	• Tlv Present.

8.1142.2 Field Documentation

8.1142.2.1 BYTE timeInfo::day

8.1142.2.2 BYTE timeInfo::dayLtSavingAdj

8.1142.2.3 BYTE timeInfo::dayOfWeek

8.1142.2.4 BYTE timeInfo::hour

8.1142.2.5 BYTE timeInfo::minute

8.1142.2.6 BYTE timeInfo::month

8.1142.2.7 BYTE timeInfo::radioInterface

8.1142.2.8 BYTE timeInfo::second

8.1142.2.9 INT8 timeInfo::timeZone

8.1142.2.10 BYTE timeInfo::TlvPresent

8.1142.2.11 WORD timeInfo::year

8.1143 TmdDeRegNotMitigationLvlReq Struct Reference

Data Fields

- BYTE mitigationDevIDLen
- CHAR mitigationDevID [255]

8.1143.1 Detailed Description

This structure contains mitigation devices Level deregister request parameters

Parameters

mitigationDevID-Len	• Number of sets of the following elements – mitigation_dev_id
mitigationDevID	• Mitigation device ID

8.1143.2 Field Documentation

8.1143.2.1 CHAR TmdDeRegNotMitigationLvlReq::mitigationDevID[255]

8.1143.2.2 BYTE TmdDeRegNotMitigationLvlReq::mitigationDevIDLen

8.1144 TmdGetMitigationDevListResp Struct Reference

Data Fields

- BYTE * pMitigationDevListLen
- mitigationDevList * pMitigationDevList

8.1144.1 Detailed Description

This structure contains mitigation devices list from the remote endpoint

Parameters

pMitigationDevListLen	• Mitigation Device List Length (Optional) • Number of sets of the following elements • pMitigationDevList
pMitigationDevList	• Mitigation Device List (Optional) • See mitigationDevList for more information.

8.1144.2 Field Documentation

8.1144.2.1 mitigationDevList* TmdGetMitigationDevListResp::pMitigationDevList

8.1144.2.2 BYTE* TmdGetMitigationDevListResp::pMitigationDevListLen

8.1145 TmdGetMitigationLvlReq Struct Reference

Data Fields

- BYTE mitigationDevIDLen
- CHAR mitigationDevID [255]

8.1145.1 Detailed Description

This structure contains mitigation devices Level request parameters

Parameters

mitigationDevIDLen	• Number of sets of the following elements – mitigation_dev_id
mitigationDevID	• Mitigation device ID

8.1145.2 Field Documentation

8.1145.2.1 CHAR TmdGetMitigationLvlReq::mitigationDevID[255]

8.1145.2.2 BYTE TmdGetMitigationLvlReq::mitigationDevIDLen

8.1146 TmdGetMitigationLvlResp Struct Reference

Data Fields

- BYTE * pCurrentmitigationLvl
- BYTE * pReqMitigationLvl

8.1146.1 Detailed Description

This structure contains mitigation devices Level request parameters

Parameters

pCurrentmitigationLvl	• Current thermal mitigation level (Optional)
pReqMitigationLvl	• Requested Thermal Mitigation Level (Optional) • The requested thermal mitigation level from the client. The default is zero if the client has not previously set the mitigation level.

8.1146.2 Field Documentation

8.1146.2.1 BYTE* TmdGetMitigationLvlResp::pCurrentmitigationLvl

8.1146.2.2 BYTE* TmdGetMitigationLvlResp::pReqMitigationLvl

8.1147 TmdMitigationLvlIndReq Struct Reference

Data Fields

- BYTE mitigationDevIDLen
- CHAR mitigationDevID [255]

8.1147.1 Detailed Description

This structure contains mitigation Level Indication request parameters

Parameters

mitigationDevIDLen	• Number of sets of the following elements – mitigation_dev_id
mitigationDevID	• Mitigation device ID

8.1147.2 Field Documentation

8.1147.2.1 CHAR TmdMitigationLvlIndReq::mitigationDevID[255]

8.1147.2.2 BYTE TmdMitigationLvlIndReq::mitigationDevIDLen

8.1148 TmdRegNotMitigationLvlReq Struct Reference

Data Fields

- BYTE mitigationDevIDLen
- CHAR mitigationDevID [255]

8.1148.1 Detailed Description

This structure contains mitigation devices Level register request parameters

Parameters

mitigationDevID-Len	• Number of sets of the following elements – mitigation_dev_id
mitigationDevID	• Mitigation device ID

8.1148.2 Field Documentation

8.1148.2.1 CHAR TmdRegNotMitigationLvlReq::mitigationDevID[255]

8.1148.2.2 BYTE TmdRegNotMitigationLvlReq::mitigationDevIDLen

8.1149 tokenBucket Struct Reference

Data Fields

- ULONG peakRate
- ULONG tokenRate
- ULONG bucketSz

8.1149.1 Detailed Description

This structure contains the TP flow data rate token bucket

Parameters

peakRate	Maximum rate at which data can be transmitted when the token bucket is full (bits per second)
tokenRate	Rate at which tokens will be put in the token bucket (bits per second); a token is required to be present in the bucket to send a byte of data
bucketSz	Maximum number of tokens that can be accumulated at any instance (bytes); controls the size of the burst that is allowed at any given time

8.1149.2 Field Documentation

8.1149.2.1 ULONG tokenBucket::bucketSz

8.1149.2.2 ULONG tokenBucket::peakRate

8.1149.2.3 ULONG tokenBucket::tokenRate

8.1150 Tos Struct Reference

Data Fields

- BYTE val
- BYTE mask

8.1150.1 Detailed Description

This structure contains the IPv4 filter type of service

Parameters

val	Type of service value
mask	Packet matches the TOS filter if: (IPv4_filter_tos_val and IPv4_filter_tos_mask) == (TOS value in the IP packet & IPv4_filter_tos_mask) Example: • IPv4_filter_tos_val = 00101000 • IPv4_filter_tos_mask = 11111100 The filter will compare only the first 6 bits in the IPv4_filter_-type_of_service with the first 6 bits in the TOS field of the IP packet. The first 6 bits in the TOS field of the IP packet must be 001010 to match the filter. The last 2 bits can be anything since they are ignored by filtering.

8.1150.2 Field Documentation

8.1150.2.1 BYTE Tos::mask

8.1150.2.2 BYTE Tos::val

8.1151 transferRouteMessageTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- sMSTransferRouteMTMessageInfo TransferRouteMTMessageInfo

8.1151.1 Detailed Description

This structure contains Transfer route MT message TLV information.

Parameters

TlvPresent	• Boolean indicating the presence of the TLV in the QMI response

TransferRouteMTMessageInfo	• Transfer Route MT Message • See sMSTransferRouteMTMessageInfo for more information

8.1151.2 Field Documentation

8.1151.2.1 uint8_t transferRouteMessageTlv::TlvPresent

8.1151.2.2 sMSTransferRouteMTMessageInfo transferRouteMessageTlv::TransferRouteMTMessageInfo

8.1152 TransferStatInd Struct Reference

Data Fields

- BYTE StatsPeriod
- ULONG StatsMask

8.1152.1 Detailed Description

This structure contains Transfer Statistcics Indicator

Parameters

StatsPeriod	• Period between transfer statistics reports – 0 - Do not report – Other - Period between reports (seconds)
StatsMask	• Requested statistic bit mask. Each bit set causes the corresponding optional TLV to be sent in the indication. All unlisted bits are reserviced for future use and must be set to zero. – 0x00000040 - Tx bytes OK – 0x00000080 - Rx bytes OK

8.1152.2 Field Documentation

8.1152.2.1 ULONG TransferStatInd::StatsMask

8.1152.2.2 BYTE TransferStatInd::StatsPeriod

8.1153 TransferStatsDataType Struct Reference

Data Fields

- BYTE interval

8.1153.1 Field Documentation

8.1153.1.1 BYTE TransferStatsDataType::interval

8.1154 TrStatInd Struct Reference

Data Fields

- BYTE statsPeriod
- ULONG statsMask

8.1154.1 Detailed Description

This structure contains the information about the Transfer Statistics Indicator parameters.

Parameters

statsPeriod	• Period between transfer statistics reports. – 0 - Do not report – Other - Period between reports (seconds)
statsMask	• Requested statistic bit mask. – 0x00000001 - Tx packets OK – 0x00000002 - Rx packets OK – 0x00000004 - Tx packet errors – 0x00000008 - Rx packet errors – 0x00000010 - Tx overflows – 0x00000020 - Rx overflows – 0x00000040 - Tx bytes OK – 0x00000080 - Rx bytes OK • Each bit set causes the corresponding optional information to be sent in SLQSWdsEventReportCallBack. • All unlisted bits are reserved for future use and must be set to zero.

8.1154.2 Field Documentation

8.1154.2.1 ULONG TrStatInd::statsMask

8.1154.2.2 BYTE TrStatInd::statsPeriod

8.1155 trueIMSI Struct Reference

Data Fields

- BYTE mccT [3]
- WORD imsiT1112
- BYTE imsiTS1 [7]
- BYTE imsiTS2 [3]
- BYTE imsiTaddrNum

8.1155.1 Detailed Description

This structure contains the parameters for True IMSI Information

Parameters

mccT	• ASCII character representation of MCC_T
imsiT1112	• ASCII character representation of IMSI_T_11_12 value – 0xFFFF - Not Available
imsiTS1	• ASCII character representation of IMSI_T_S1 value
imsiTS2	• ASCII character representation of IMSI_T_S2 value
imsiTaddrNum	• Value of IMSI_T_ADDR_NUM – 0xFF - Not Available

8.1155.2 Field Documentation

8.1155.2.1 WORD truelMSI::imsiT1112

8.1155.2.2 BYTE truelMSI::imsiTaddrNum

8.1155.2.3 BYTE truelMSI::imsiTS1[7]

8.1155.2.4 BYTE truelMSI::imsiTS2[3]

8.1155.2.5 BYTE truelMSI::mccT[3]

8.1156 TXAGCList Struct Reference

Data Fields

- WORD * pTXStaticGain
- WORD * pTXAIG
- WORD * pTXExpThres
- WORD * pTXExpSlope
- WORD * pTXComprThres
- WORD * pTXComprSlope

8.1156.1 Detailed Description

This structure contains the SLQSGetAudioPathConfig parameters related to AV_TXAGCLIST.

Parameters

pTXStaticGain	• TX pre-compressor static gain
pTXAIG	• TX pre-compressor gain selection flag
pTXExpThres	• TX expansion threshold
pTXExpSlope	• TX expansion slope
pTXComprThres	• TX compression threshold
pTXComprSlope	• TX compression slope

8.1156.2 Field Documentation

8.1156.2.1 WORD* TXAGCList::pTXAIG

8.1156.2.2 WORD* TXAGCList::pTXComprSlope

8.1156.2.3 WORD* TXAGCList::pTXComprThres

8.1156.2.4 WORD* TXAGCList::pTXExpSlope

8.1156.2.5 WORD* TXAGCList::pTXExpThres

8.1156.2.6 WORD* TXAGCList::pTXStaticGain

8.1157 txInfo Struct Reference

Data Fields

- BYTE isInTraffic
- INT32 txPower

8.1157.1 Detailed Description

This structure contains the Tx Information.

Parameters

isInTraffic	• Whether the device is in traffic.
	  – 0x00 - not in traffic
	  – 0x01 - in traffic
	• The txPower field is only meaningful when in the device is in traffic.

txPower	• Tx power value in 1/10 dbm.

8.1157.2 Field Documentation

8.1157.2.1 BYTE txInfo::isInTraffic

8.1157.2.2 INT32 txInfo::txPower

8.1158 TXPCMIIRFltr Struct Reference

Data Fields

- WORD * pFlag
- WORD * pStageCnt
- BYTE * pStage0Val
- BYTE * pStage1Val
- BYTE * pStage2Val
- BYTE * pStage3Val
- BYTE * pStage4Val

8.1158.1 Detailed Description

This structure contains the SLQSGetAudioPathConfig parameters related to AV_TXPCMIIRFLTR.

Parameters

pFlag	• Flag – 0x0000 - IIR filter disable – 0xffff - IIR filter enable
pStageCnt	• Stage Count – 0-4
pStage0Val	• A 20 BYTE sized parameter indicating Stage 0 value – A1 – A2 – B0 – B1 – B2

pStage1Val	• A 20 BYTE sized parameter indicating Stage 1 value – A1 – A2 – B0 – B1 – B2
pStage2Val	• A 20 BYTE sized parameter indicating Stage 2 value – A1 – A2 – B0 – B1 – B2
pStage3Val	• A 20 BYTE sized parameter indicating Stage 3 value – A1 – A2 – B0 – B1 – B2
pStage4Val	• A 20 BYTE sized parameter indicating Stage 4 value – A1 – A2 – B0 – B1 – B2

8.1158.2 Field Documentation

8.1158.2.1 WORD* TXPCMIIRFItr::pFlag

8.1158.2.2 BYTE* TXPCMIIRFItr::pStage0Val

8.1158.2.3 BYTE* TXPCMIIRFItr::pStage1Val

8.1158.2.4 BYTE* TXPCMIIRFItr::pStage2Val

8.1158.2.5 BYTE* TXPCMIIRFItr::pStage3Val

8.1158.2.6 BYTE* TXPCMIIRFItr::pStage4Val

8.1158.2.7 WORD* TXPCMIIRFItr::pStageCnt

8.1159 uim_appStatus Struct Reference

Data Fields

- uint8_t appType
- uint8_t appState
- uint8_t persoState
- uint8_t persoFeature
- uint8_t persoRetries
- uint8_t persoUnblockRetries
- uint8_t aidLength
- uint8_t aidVal [255]
- uint8_t univPin
- uint8_t pin1State
- uint8_t pin1Retries
- uint8_t puk1Retries
- uint8_t pin2State
- uint8_t pin2Retries
- uint8_t puk2Retries

8.1159.1 Detailed Description

This structure contains Application Status Information loaded on the card.

Parameters

appType	• Indicates the type of the application. – 0 - Unknown – 1 - SIM card – 2 - USIM application – 3 - RUIM card – 4 - CSIM application – 5 - ISIM application • Other values are reserved for the future and are to be handled as "Unknown".
appState	• Indicates the state of the application. – 0 - Unknown – 1 - Detected – 2 - PIN1 or UPIN is required – 3 - PUK1 or PUK for UPIN is required – 4 - Personalization state must be checked – 5 - PIN1 is blocked – 6 - Illegal – 7 - Ready
persoState	• Indicates the state of the personalization for the application. – 0 - Unknown – 1 - Personalization operation is in progress – 2 - Ready – 3 - Personalization code is required – 4 - PUK for personalization code is required – 5 - Permanently blocked

persoFeature	• Indicates the personalization feature. • This applies only when a personalization code is required to deactivate or unblock personalization. – 0 - GW network personalization – 1 - GW network subset personalization – 2 - GW service provider personalization – 3 - GW corporate personalization – 4 - GW UIM personalization – 5 - 1X network type 1 personalization – 6 - 1X network type 2 personalization – 7 - 1X HRPD personalization – 8 - 1X service provider personalization – 9 - 1X corporate personalization – 10 - 1X RUIM personalization – 11 - Unknown
persoRetries	• Indicates the number of retries remaining to disable the personalization.
persoUnblockRetries	• Indicates the number of retries remaining to unblock the personalization.
aidLength	• Number of sets of the following elements. i.e. aidVal • If zero(0) then no aidVal information exists.
aidVal[MAX_DESCRIPTION_LENGTH]	• Application identifier value.
univPin	• Indicates whether UPIN replaces PIN1. – 0 - PIN1 is used – 1 - UPIN replaces PIN1
pin1State	• Indicates the state of PIN1. – 0 - Unknown – 1 - Enabled and not verified – 2 - Enabled and verified – 3 - Disabled – 4 - Blocked – 5 - Permanently blocked
pin1Retries	• Indicates the number of retries remaining to verify PIN1.
puk1Retries	• Indicates the number of retries remaining to unblock PIN1.

pin2State	• Indicates the state of PIN2. – 0 - Unknown – 1 - Enabled and not verified – 2 - Enabled and verified – 3 - Disabled – 4 - Blocked – 5 - Permanently blocked
pin2Retries	• Indicates the number of retries remaining to verify PIN2.
puk2Retries	• Indicates the number of retries remaining to unblock PIN2.

8.1159.2 Field Documentation

8.1159.2.1 uint8_t uim_appStatus::aidLength

8.1159.2.2 uint8_t uim_appStatus::aidVal[255]

8.1159.2.3 uint8_t uim_appStatus::appState

8.1159.2.4 uint8_t uim_appStatus::appType

8.1159.2.5 uint8_t uim_appStatus::persoFeature

8.1159.2.6 uint8_t uim_appStatus::persoRetries

8.1159.2.7 uint8_t uim_appStatus::persoState

8.1159.2.8 uint8_t uim_appStatus::persoUnblockRetries

8.1159.2.9 uint8_t uim_appStatus::pin1Retries

8.1159.2.10 uint8_t uim_appStatus::pin1State

8.1159.2.11 uint8_t uim_appStatus::pin2Retries

8.1159.2.12 uint8_t uim_appStatus::pin2State

8.1159.2.13 uint8_t uim_appStatus::puk1Retries

8.1159.2.14 uint8_t uim_appStatus::puk2Retries

8.1159.2.15 uint8_t uim_appStatus::univPin

8.1160 uim_authenticateResult Struct Reference

Data Fields

- uint16_t contentLen

- uint8_t content [1024]

8.1160.1 Detailed Description

This structure contains the information about the authenticate result.

Parameters

contentLen	• Length of the following elements i.e. content.
content[UIM_MAX_CONTENT_LENGTH]	• Authenticate data. • This value is a sequence of bytes returned from the card.

8.1160.2 Field Documentation

8.1160.2.1 uint8_t uim_authenticateResult::content[1024]

8.1160.2.2 uint16_t uim_authenticateResult::contentLen

8.1161 uim_authenticationData Struct Reference

Data Fields

- uint8_t context
- uint16_t dataLen
- uint8_t data [1024]

8.1161.1 Detailed Description

This structure contains the Session Information.

Parameters

context	• Authenticate context. – 0 - Runs the GSM algorithm (valid only on a 2GSIM card) – 1 - Runs the CAVE algorithm (valid only on a RUIM card) – 2 - GSM security context (valid only on a USIM application) – 3 - 3G security context (valid only on a USIM application) – 4 - VGCS/VBS security context (valid only on aUSIM application) – 5 - GBA security context, Bootstrapping mode (valid only on a USIM or ISIM application) – 6 - GBA security context, NAF Derivation mode (valid only on a USIM or ISIM application) – 7 - MBMS security context, MSK Update mode (valid only on a USIM application) – 8 - MBMS security context, MTK Generation mode (valid only on a USIM application) – 9 - MBMS security context, MSK Deletion mode (valid only on a USIM application) – 10 - MBMS security context, MUK Deletion mode (valid only on a USIM application) – 11 - IMS AKA security context (valid only on aISIM application) – 12 - HTTP-digest security context (valid only onan ISIM application) – 13 - Compute IP authentication, CHAP (valid onlyon RUIM or CSIM) – 14 - Compute IP authentication, MN-HA authenticator (valid only on RUIM or CSIM) – 15 - Compute IP authentication, MIP-RRQ hash (valid only on RUIM or CSIM) – 16 - Compute IP authentication, MN-AAA authenticator (valid only on RUIM or CSIM) – 17 - Compute IP authentication, HRPD access authenticator (valid only on RUIM or CSIM) • Other values are possible and reserved for future use.
dataLen	• Length of the following elements i.e. data.
data[UIM_MAX_DESCRIPTION_LENGTH]	• Authenticate Data.

8.1161.2 Field Documentation

8.1161.2.1 uint8_t uim_authenticationData::context

8.1161.2.2 uint8_t uim_authenticationData::data[1024]

8.1161.2.3 uint16_t uim_authenticationData::dataLen

8.1162 uim_cardResult Struct Reference

Data Fields

- uint8_t sw1
- uint8_t sw2

8.1162.1 Detailed Description

This structure contains the information about the card result.

Parameters

sw1	• SW1 received from the card.
sw2	• SW2 received from the card.

8.1162.2 Field Documentation

8.1162.2.1 uint8_t uim_cardResult::sw1

8.1162.2.2 uint8_t uim_cardResult::sw2

8.1163 uim_cardStatus Struct Reference

Data Fields

- uint16_t indexGwPri
- uint16_t index1xPri
- uint16_t indexGwSec
- uint16_t index1xSec
- uint8_t numSlot
- uim_slotInfo SlotInfo [5]

8.1163.1 Detailed Description

This structure contains Card Status Information.

Parameters

indexGwPri	• Index of the primary GW provisioning application. • The most significant byte indicates the slot (starting from 0), while the least significant byte indicates the application for that slot (starting from 0). • The value 0xFFFF identifies when the session does not exist.
index1xPri	• Index of the primary 1X provisioning application. • The most significant byte indicates the slot (starting from 0), while the least significant byte indicates the application for that slot (starting from 0). • The value 0xFFFF identifies when the session does not exist.
indexGwSec	• Index of the secondary GW provisioning application. • The most significant byte indicates the slot (starting from 0), while the least significant byte indicates the application for that slot (starting from 0). • The value 0xFFFF identifies when the session does not exist.

index1xSec	• Index of the secondary GW provisioning application. • The most significant byte indicates the slot (starting from 0), while the least significant byte indicates the application for that slot (starting from 0). • The value 0xFFFF identifies when the session does not exist.
numSlot	• Indicates the number of slots available on the device. • The following block is repeated for each slot. i.e. cardState • If zero(0) then no cardState information exists.
SlotInfo	• See uim_slotInfo for more information.

8.1163.2 Field Documentation

8.1163.2.1 uint16_t uim_cardStatus::index1xPri

8.1163.2.2 uint16_t uim_cardStatus::index1xSec

8.1163.2.3 uint16_t uim_cardStatus::indexGwPri

8.1163.2.4 uint16_t uim_cardStatus::indexGwSec

8.1163.2.5 uint8_t uim_cardStatus::numSlot

8.1163.2.6 uim_slotInfo uim_cardStatus::SlotInfo[5]

8.1164 uim_changeUIMPIN Struct Reference

Data Fields

- uint8_t pinID
- uint8_t oldPINLen
- uint8_t oldPINVal [255]
- uint8_t pinLen
- uint8_t pinVal [255]

8.1164.1 Detailed Description

This structure contains the information about the pin parameters that need to be verified.

Parameters

pinID	• Indicates the PIN ID to be changed. – 1 - PIN1 (also called PIN) – 2 - PIN2 – 3 - Universal PIN – 4 - Hidden key

oldPINLen	• Length of the following elements i.e. old pin value.
oldPINVal[MAX_DESCRIPTION_LENGTH]	• Old PIN value. • This value is a sequence of ASCII characters.
pinLen	• Length of the following elements i.e. new pin value.
pinVal[MAX_DESCRIPTION_LENGTH]	• New PIN value. • This value is a sequence of ASCII characters.

8.1164.2 Field Documentation

8.1164.2.1 uint8_t uim_changeUIMPIN::oldPINLen

8.1164.2.2 uint8_t uim_changeUIMPIN::oldPINVal[255]

8.1164.2.3 uint8_t uim_changeUIMPIN::pinID

8.1164.2.4 uint8_t uim_changeUIMPIN::pinLen

8.1164.2.5 uint8_t uim_changeUIMPIN::pinVal[255]

8.1165 uim_depersonalizationInformation Struct Reference

Data Fields

- uint8_t feature
- uint8_t operation
- uint8_t ckLen
- uint8_t ckVal [255]

8.1165.1 Detailed Description

This structure contains the Depersonalization Information.

Parameters

feature	• Indicates the personalization feature to de-activate or unblock. – 0 - GW network personalization – 1 - GW network subset personalization – 2 - GW service provider personalization – 3 - GW corporate personalization – 4 - GW UIM personalization – 5 - 1X network type 1 personalization – 6 - 1X network type 2 personalization – 7 - 1X HRPD personalization – 8 - 1X service provider personalization – 9 - 1X corporate personalization – 10 - 1X RUIM personalization
operation	• Indicates the operation to perform. – 0 - Deactivate personalization. – 1 - Unblock personalization.
ckLen	• Length of the following elements i.e. control key value.
ckVal[MAX_DESCRIPTION_LENGTH]	• Control key value. • This value is a sequence of ASCII characters.

8.1165.2 Field Documentation

8.1165.2.1 uint8_t uim_depersonalizationInformation::ckLen

8.1165.2.2 uint8_t uim_depersonalizationInformation::ckVal[255]

8.1165.2.3 uint8_t uim_depersonalizationInformation::feature

8.1165.2.4 uint8_t uim_depersonalizationInformation::operation

8.1166 uim_encryptedPIN1 Struct Reference

Data Fields

- uint8_t pin1Len
- uint8_t pin1Val [255]

8.1166.1 Detailed Description

This structure contains the encrypted PIN1 Information.

Parameters

pin1Len	• Number of sets of the following elements ie encrypted PIN1 value. • If zero(0), no information follows.
pin1Val	• Encrypted PIN1 value.

Note

This value is returned only when PIN1 is enabled successfully and the feature is supported.

8.1166.2 Field Documentation

8.1166.2.1 uint8_t uim_encryptedPIN1::pin1Len

8.1166.2.2 uint8_t uim_encryptedPIN1::pin1Val[255]

8.1167 uim_fileAttributes Struct Reference

Data Fields

- uint16_t fileSize
- uint16_t fileID
- uint8_t fileType
- uint16_t recordSize
- uint16_t recordCount
- uint8_t secRead
- uint16_t secReadMask
- uint8_t secWrite
- uint16_t secWriteMask
- uint8_t secIncrease
- uint16_t secIncreaseMask
- uint8_t secDeactivate
- uint16_t secDeactivateMask
- uint8_t secActivate
- uint16_t secActivateMask
- uint16_t rawLen
- uint8_t rawValue [255]

8.1167.1 Detailed Description

This structure contains the information about the File Attributes.

Parameters

fileSize	• Indicates the size of the file.
fileID	• Indicates the ID of the file.

fileType	• Indicates the type of the file. – 0 - Transparent – 1 - Cyclic – 2 - Linear fixed – 3 - Dedicated file – 4 - Master file
recordSize	• Indicates the size of the records. • Only for cyclic and linear fixed files
recordCount	• Indicates the total no. of the records. • Only for linear fixed files
secRead	• Read security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secReadMask	• Mask with read security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM
secWrite	• Write security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secWriteMask	• Mask with write security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM

secIncrease	• Increase security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secIncrease-Mask	• Mask with increase security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM
secDeactivate	• Deactivate security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secDeactivate-Mask	• Mask with deactivate security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM
secActivate	• Activate security attributes. – 0 - Always – 1 - Never – 2 - AND condition – 3 - OR condition – 4 - Single condition
secActivateMask	• Mask with activate security attributes. • This field is valid only when required by security attributes. – Bit 0 - PIN1 – Bit 1 - PIN2 – Bit 2 - UPIN – Bit 3 - ADM
rawLen	• Length of the following elements i.e. raw value.

rawValue[MAX_-DESCRIPTION-_LENGTH]	• Raw value of file attributes.

8.1167.2 Field Documentation

8.1167.2.1 uint16_t uim_fileAttributes::fileID

8.1167.2.2 uint16_t uim_fileAttributes::fileSize

8.1167.2.3 uint8_t uim_fileAttributes::fileType

8.1167.2.4 uint16_t uim_fileAttributes::rawLen

8.1167.2.5 uint8_t uim_fileAttributes::rawValue[255]

8.1167.2.6 uint16_t uim_fileAttributes::recordCount

8.1167.2.7 uint16_t uim_fileAttributes::recordSize

8.1167.2.8 uint8_t uim_fileAttributes::secActivate

8.1167.2.9 uint16_t uim_fileAttributes::secActivateMask

8.1167.2.10 uint8_t uim_fileAttributes::secDeactivate

8.1167.2.11 uint16_t uim_fileAttributes::secDeactivateMask

8.1167.2.12 uint8_t uim_fileAttributes::secIncrease

8.1167.2.13 uint16_t uim_fileAttributes::secIncreaseMask

8.1167.2.14 uint8_t uim_fileAttributes::secRead

8.1167.2.15 uint16_t uim_fileAttributes::secReadMask

8.1167.2.16 uint8_t uim_fileAttributes::secWrite

8.1167.2.17 uint16_t uim_fileAttributes::secWriteMask

8.1168 uim_fileInfo Struct Reference

Data Fields

- uint16_t fileID
- uint8_t pathLen
- uint16_t path [255]

8.1168.1 Detailed Description

This structure contains paramaters for file Information

Parameters

fileID	• This is Identifier to SIM files; e.g. in UIM "6F07" is Identifier of IMSI File
pathLen	• Length of file Path
path	• Path value. This value must be the complete path of the file, which is a sequence block of 2 bytes (e.g., 0x3F00 0x7FFF) is for LTE (0x3F00 ,0x7F20) is for GSM.

8.1168.2 Field Documentation

8.1168.2.1 uint16_t uim_fileInfo::fileID

8.1168.2.2 uint16_t uim_fileInfo::path[255]

8.1168.2.3 uint8_t uim_fileInfo::pathLen

8.1169 uim_hotSwapStatus Struct Reference

Data Fields

- uint8_t hotSwapLength
- uint8_t hotSwap [255]

8.1169.1 Detailed Description

This structure contains Hot Swap Status Information.

Parameters

hotSwapLength	• Number of sets of the following elements. i.e. hot_swap
hotSwap	• Indicates the status of the hot-swap switch. – 0 - Hot-swap is not supported – 1 - Hot-swap is supported, but the status of the switch is not supported – 2 - Switch indicates that the card is present – 3 - Switch indicates that the card is not present

8.1169.2 Field Documentation

8.1169.2.1 uint8_t uim_hotSwapStatus::hotSwap[255]

8.1169.2.2 uint8_t uim_hotSwapStatus::hotSwapLength

8.1170 uim_personalizationStatus Struct Reference

Data Fields

- uint8_t numFeatures
- uint8_t feature [12]
- uint8_t verifyLeft [12]
- uint8_t unblockLeft [12]

8.1170.1 Detailed Description

This structure contains the information about the card result.

Parameters

numFeatures	• Number of active personalization features. The following block is repeated for each feature.
feature	• Indicates the personalization feature to deactivate or unblock. Valid values: – 0 - GW network personalization – 1 - GW network subset personalization – 2 - GW service provider personalization – 3 - GW corporate personalization – 4 - GW UIM personalization – 5 - 1X network type 1 personalization – 6 - 1X network type 2 personalization – 7 - 1X HRPD personalization – 8 - 1X service provider personalization – 9 - 1X corporate personalization – 10 - 1X RUIM personalization
verifyLeft	• Number of the remaining attempts to verify the personalization feature.
unblockLeft	• Number of the remaining attempts to unblock the personalization feature.

8.1170.2 Field Documentation

8.1170.2.1 uint8_t uim_personalizationStatus::feature[12]

8.1170.2.2 uint8_t uim_personalizationStatus::numFeatures

8.1170.2.3 uint8_t uim_personalizationStatus::unblockLeft[12]

8.1170.2.4 uint8_t uim_personalizationStatus::verifyLeft[12]

8.1171 uim_readResult Struct Reference

Data Fields

- uint16_t contentLen
- uint8_t content [255]

8.1171.1 Detailed Description

This structure contains the information for write operation.

Parameters

contentLen	• Number of sets of content.
content[255]	• Read content. • The content is the sequence of bytes as read from the card.

8.1171.2 Field Documentation

8.1171.2.1 uint8_t uim_readResult::content[255]

8.1171.2.2 uint16_t uim_readResult::contentLen

8.1172 uim_readTransparentInfo Struct Reference

Data Fields

- uint16_t offset
- uint16_t length

8.1172.1 Detailed Description

This structure contains the information for read operation.

Parameters

offset	• Offset for the read operation.
length	• Length of the content to be read. • The value 0 is used to read the complete file.

8.1172.2 Field Documentation

8.1172.2.1 uint16_t uim_readTransparentInfo::length

8.1172.2.2 uint16_t uim_readTransparentInfo::offset

8.1173 uim_refreshevent Struct Reference

Data Fields

- uint8_t stage
- uint8_t mode

- uint8_t sessionType
- uint8_t aidLength
- uint8_t aid [255]
- uint16_t numOfFiles
- uim_fileInfo arrfileInfo [255]

8.1173.1 Detailed Description

This structure contains information of parameters associated with the Refresh Event.

Parameters

stage	• Indicates the stage of the Refresh procedure. – 0 - Waiting for OK to refresh – 1 - Refresh started – 2 - Refresh ended successfully – 3 - Refresh failed
mode	• Indicates the Refresh mode. – 0 - Reset – 1 - Init – 2 - Init and FCN – 3 - FCN – 4 - Init and Full FCN – 5 - Application reset – 6 - 3G session reset
sessionType	• Indicates the session type. – 0 - Primary GW provisioning – 1 - Primary 1X provisioning – 2 - Secondary GW provisioning – 3 - Secondary 1X provisioning – 4 - Nonprovisioning on slot 1 – 5 - Nonprovisioning on slot 2 – 6 - Card on slot 1 – 7 - Card on slot 2 – 8 - Logical channel on slot 1 – 9 - Logical channel on slot 2
aidLength	• Number of sets of the following elements – Application Identifier
aid	• Application identifier value or channel ID. This value is required for non-provisioning and for logical channel session types. It is ignored in all other cases

numFiles	• Number of sets of the following elements: – file_id – path_len – path
arrfileInfo	• Array of file Information struct

8.1173.2 Field Documentation

8.1173.2.1 uint8_t uim_refreshevent::aid[255]

8.1173.2.2 uint8_t uim_refreshevent::aidLength

8.1173.2.3 uim_fileInfo uim_refreshevent::arrfileInfo[255]

8.1173.2.4 uint8_t uim_refreshevent::mode

8.1173.2.5 uint16_t uim_refreshevent::numOfFiles

8.1173.2.6 uint8_t uim_refreshevent::sessionType

8.1173.2.7 uint8_t uim_refreshevent::stage

8.1174 uim_registerRefresh Struct Reference

Data Fields

- uint8_t registerFlag
- uint8_t voteForInit
- uint16_t numFiles
- uim_fileInfo arrfileInfo [255]

8.1174.1 Detailed Description

This structure contains parameters of refresh Information

Parameters

registerFlag	• Flag that indicates whether to register or deregister for refresh indications. Valid values: – 0 - Deregister – 1 - Register
voteForInit	• Flag that indicates whether to vote for the init when there is a refresh. Valid values: – 0 - Client does not vote for initialization – 1 - Client votes for initialization

numFiles	• Number of sets of the following elements: – file_id – path_len – path
arrfileInfo	• Array of file Information structure. • See uim_fileInfo for more information

8.1174.2 Field Documentation

8.1174.2.1 uim_fileInfo uim_registerRefresh::arrfileInfo[255]

8.1174.2.2 uint16_t uim_registerRefresh::numFiles

8.1174.2.3 uint8_t uim_registerRefresh::registerFlag

8.1174.2.4 uint8_t uim_registerRefresh::voteForInit

8.1175 uim_remainingRetries Struct Reference

Data Fields

- uint8_t verifyLeft
- uint8_t unblockLeft

8.1175.1 Detailed Description

This structure contains the information about the retries remaining.

Parameters

verifyLeft	• Number of remaining attempts to verify the PIN. • 0xFF, if unavailable.
unblockLeft	• Number of remaining attempts to unblock the PIN. • 0xFF, if unavailable.

Note

This value is returned only when the enable/disable operation has failed. This information is not sent for a hidden key PIN type.

8.1175.2 Field Documentation

8.1175.2.1 uint8_t uim_remainingRetries::unblockLeft

8.1175.2.2 uint8_t uim_remainingRetries::verifyLeft

8.1176 uim_sessionInformation Struct Reference

Data Fields

- uint8_t sessionType
- uint8_t aidLength
- uint8_t aid [255]

8.1176.1 Detailed Description

This structure contains the Session Information.

Parameters

sessionType	• Indicates the session type. – 0 - Primary GW provisioning – 1 - Primary 1X provisioning – 2 - Secondary GW provisioning – 3 - Secondary 1X provisioning – 4 - Non-provisioning on slot 1 – 5 - Non-provisioning on slot 2 – 6 - Card on slot 1 – 7 - Card on slot 2 – 8 - Logical channel on slot 1 – 9 - Logical channel on slot 2
aidLength	• Length of the following elements i.e. Application Identifier.
aid	• Application identifier value or channel ID. • This value is required for non-provisioning and for logical channel session types. It is ignored in all other cases.

8.1176.2 Field Documentation

8.1176.2.1 uint8_t uim_sessionInformation::aid[255]

8.1176.2.2 uint8_t uim_sessionInformation::aidLength

8.1176.2.3 uint8_t uim_sessionInformation::sessionType

8.1177 uim_setPINProtection Struct Reference

Data Fields

- uint8_t pinID
- uint8_t pinOperation

- uint8_t pinLength
- uint8_t pinValue [255]

8.1177.1 Detailed Description

This structure contains the information about the pin protection parameters that need to be set.

Parameters

pinID	• Indicates the PIN ID to be enabled or disabled. – 1 - PIN1 (also called PIN) – 2 - PIN2 – 3 - Universal PIN – 4 - Hidden key
pinOperation	• Indicates whether the PIN is enabled or disabled. – 0 - Disable the PIN – 1 - Enable the PIN
pinLength	• Length of the following elements i.e. pin value.
pinValue[MAX_-DESCRIPTION-_LENGTH]	• PIN value. • This value is a sequence of ASCII characters.

8.1177.2 Field Documentation

8.1177.2.1 uint8_t uim_setPINProtection::pinID

8.1177.2.2 uint8_t uim_setPINProtection::pinLength

8.1177.2.3 uint8_t uim_setPINProtection::pinOperation

8.1177.2.4 uint8_t uim_setPINProtection::pinValue[255]

8.1178 uim_simBusyStatus Struct Reference

Data Fields

- uint8_t simBusyLength
- uint8_t simBusy [255]

8.1178.1 Detailed Description

This structure contains Sim Busy Status Information.

Parameters

simBusyLength	• Number of sets of the following elements. i.e. simBusy
simBusy[MAX_-DESCRIPTION-_LENGTH]	• Indicates the status of the valid card. – 0 - Sim card is not busy – 1 - Sim card is busy

8.1178.2 Field Documentation

8.1178.2.1 uint8_t uim_simBusyStatus::simBusy[255]

8.1178.2.2 uint8_t uim_simBusyStatus::simBusyLength

8.1179 uim_slotInfo Struct Reference

Data Fields

- uint8_t cardState
- uint8_t upinState
- uint8_t upinRetries
- uint8_t upukRetries
- uint8_t errorState
- uint8_t numApp
- uim_appStatus AppStatus [10]

8.1179.1 Detailed Description

This structure contains information about the SLOTS present.

Parameters

cardState	• Indicates the state of the card for each slot. – 0 - Absent – 1 - Present – 2 - Error
upinState	• Indicates the state of UPIN. – 0 - Unknown – 1 - Enabled and not verified – 2 - Enabled and verified – 3 - Disabled – 4 - Blocked – 5 - Permanently blocked – 0xFF - Not Available

upinRetries	• Indicates the number of retries remaining to verify the UPIN. • If 0xFF, information not available.
upukRetries	• Indicates the number of retries remaining to unblock the UPIN. • If 0xFF, information not available.
errorState	• Indicates the reason for the card error, and is valid only when the card state is Error – 0 - Unknown – 1 - Power down – 2 - Poll error – 3 - No ATR received – 4 - Volt mismatch – 5 - Parity error – 6 - Unknown; possibly removed – 7 - Card returned technical problems – 0xFF - Not Available • Other values are possible and reserved for future use. • When an unknown value is received, it is to be handled as "Unknown".
numApp	• Indicates the number of applications available on the card. • The following block is repeated for each application. i.e. AppStatus. • If zero(0) then no AppStatus information exists.
AppStatus	• See uim_appStatus for more information.

8.1179.2 Field Documentation

8.1179.2.1 uim_appStatus uim_slotInfo::AppStatus[10]

8.1179.2.2 uint8_t uim_slotInfo::cardState

8.1179.2.3 uint8_t uim_slotInfo::errorState

8.1179.2.4 uint8_t uim_slotInfo::numApp

8.1179.2.5 uint8_t uim_slotInfo::upinRetries

8.1179.2.6 uint8_t uim_slotInfo::upinState

8.1179.2.7 uint8_t uim_slotInfo::upukRetries

8.1180 uim_UIMSessionInformation Struct Reference

Data Fields

- uint8_t sessionType

- uint8_t aidLength
- uint8_t aid [255]

8.1180.1 Detailed Description

This structure contains the Session Information.

Parameters

sessionType	• Indicates the session type. – 0 - Primary GW provisioning – 1 - Primary 1X provisioning – 2 - Secondary GW provisioning – 3 - Secondary 1X provisioning – 4 - Non-provisioning on slot 1 – 5 - Non-provisioning on slot 2 – 6 - Card on slot 1 – 7 - Card on slot 2 – 8 - Logical channel on slot 1 – 9 - Logical channel on slot 2
aidLength	• Length of the following elements i.e. Application Identifier.
aid	• Application identifier value or channel ID. • This value is required for non-provisioning and for logical channel session types. It is ignored in all other cases.

8.1180.2 Field Documentation

8.1180.2.1 uint8_t uim_UIMSessionInformation::aid[255]

8.1180.2.2 uint8_t uim_UIMSessionInformation::aidLength

8.1180.2.3 uint8_t uim_UIMSessionInformation::sessionType

8.1181 uim_unblockUIMPIN Struct Reference

Data Fields

- uint8_t pinID
- uint8_t pukLen
- uint8_t pukVal [255]
- uint8_t newPINLen
- uint8_t newPINVal [255]

8.1181.1 Detailed Description

This structure contains the information about the unblock pin parameters.

Parameters

pinID	• Indicates the PIN ID to be changed. – 1 - PIN1 (also called PIN) – 2 - PIN2 – 3 - Universal PIN
pukLen	• Length of the following elements i.e. puk value.
pukVal[UIM_MAX_DESCRIPTION_LENGTH]	• PIN Unlock Key value. • This value is a sequence of ASCII characters.
newPINLen	• Length of the following elements i.e. new pin value.
newPINVal[UIM_MAX_DESCRIPTION_LENGTH]	• New PIN value. • This value is a sequence of ASCII characters.

8.1181.2 Field Documentation

8.1181.2.1 uint8_t uim_unblockUIMPIN::newPINLen

8.1181.2.2 uint8_t uim_unblockUIMPIN::newPINVal[255]

8.1181.2.3 uint8_t uim_unblockUIMPIN::pinID

8.1181.2.4 uint8_t uim_unblockUIMPIN::pukLen

8.1181.2.5 uint8_t uim_unblockUIMPIN::pukVal[255]

8.1182 uim_validCardStatus Struct Reference

Data Fields

- uint8_t validCardLength
- uint8_t validCard [255]

8.1182.1 Detailed Description

This structure contains Valid Card Status Information.

Parameters

validCardLength	• Number of sets of the following elements. i.e. validCard
validCard[MAX_-DESCRIPTION-_LENGTH]	• Indicates the status of the valid card. – 0 - Status of the card is unknown – 1 - Status of the card is valid

8.1182.2 Field Documentation

8.1182.2.1 uint8_t uim_validCardStatus::validCard[255]

8.1182.2.2 uint8_t uim_validCardStatus::validCardLength

8.1183 uim_verifyUIMPIN Struct Reference

Data Fields

- uint8_t pinID
- uint8_t pinLen
- uint8_t pinVal [255]

8.1183.1 Detailed Description

This structure contains the information about the pin parameters that need to be verified.

Parameters

pinID	• Indicates the PIN ID to be verified. – 1 - PIN1 (also called PIN) – 2 - PIN2 – 3 - Universal PIN – 4 - Hidden key
pinLen	• Length of the following elements i.e. pin value.
pinVal[MAX_DE-SCRIPTION_LE-NGTH]	• PIN value. • This value is a sequence of ASCII characters.

8.1183.2 Field Documentation

8.1183.2.1 uint8_t uim_verifyUIMPIN::pinID

8.1183.2.2 uint8_t uim_verifyUIMPIN::pinLen

8.1183.2.3 uint8_t uim_verifyUIMPIN::pinVal[255]

8.1184 UIMAuthenticateReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- authenticationData authData
- ULONG * pIndicationToken

8.1184.1 Detailed Description

This structure contains information of the request parameters associated with a Authenticate API.

Parameters

sessionInfo	• See UIMSessionInformation for more information.
authData	• See authenticationData for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.1184.2 Field Documentation

8.1184.2.1 authenticationData UIMAuthenticateReq::authData

8.1184.2.2 ULONG* UIMAuthenticateReq::pIndicationToken

8.1184.2.3 UIMSessionInformation UIMAuthenticateReq::sessionInfo

8.1185 UIMAuthenticateResp Struct Reference

Data Fields

- cardResult * pCardResult
- authenticateResult * pAuthenticateResult
- ULONG * pIndicationToken

8.1185.1 Detailed Description

This structure contains information of the response parameters associated with a Authenticate API.

Parameters

pCard-Result(optional)	• See cardResult for more information.
pAuthenticate-Result(optional)	• See authenticateResult for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not returned.

8.1185.2 Field Documentation

8.1185.2.1 authenticateResult* UIMAuthenticateResp::pAuthenticateResult

8.1185.2.2 cardResult* UIMAuthenticateResp::pCardResult

8.1185.2.3 ULONG* UIMAuthenticateResp::pIndicationToken

8.1186 UimAutoSwitchActSlotTlv Struct Reference

Data Fields

- BYTE uimAutoSwitchActSlot
- BYTE TlvPresent

8.1186.1 Detailed Description

This structure contains the TLV required to Get UIM auto active slot Tlv.

Parameters

uimAutoSwitch-ActSlot[Optional]	• When UIMAUTOSWITCH feature enabled and SIM auto-switch is activated, indicates currently active UIM slot. • Values – 0 - slot 1 (e.g. external SIM) – 1 - slot 2 (e.g. embedded SIM)
TlvPresent	• Tlv Present.

8.1186.2 Field Documentation

8.1186.2.1 BYTE UimAutoSwitchActSlotTlv::TlvPresent

8.1186.2.2 BYTE UimAutoSwitchActSlotTlv::uimAutoSwitchActSlot

8.1187 UIMChangePinReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- changeUIMPIN changePIN
- BYTE * pKeyReferenceID
- ULONG * pIndicationToken

8.1187.1 Detailed Description

This structure contains information of the request parameters associated with a Change PIN API.

Parameters

sessionInfo	• See UIMSessionInformation for more information.
changePIN	• See changeUIMPIN for more information.
pKeyReferenceID(optional)	• Indicates the PIN key reference ID. • Indicates the PIN key reference ID. Valid values are from 1 to 8, respectively, for application 1 to application 8. • This TLV is used only for PIN1 and PIN2 and is ignored in all other cases.
pIndicationToken(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.1187.2 Field Documentation

8.1187.2.1 changeUIMPIN UIMChangePinReq::changePIN

8.1187.2.2 ULONG* UIMChangePinReq::pIndicationToken

8.1187.2.3 BYTE* UIMChangePinReq::pKeyReferenceID

8.1187.2.4 UIMSessionInformation UIMChangePinReq::sessionInfo

8.1188 UIMDepersonalizationReq Struct Reference

Data Fields

- depersonalizationInformation depersonilisationInfo

8.1188.1 Detailed Description

This structure contains information of the request parameters associated with a Depersonalization API.

Parameters

depersonilisation-Info	• See depersonalizationInformation for more information.

8.1188.2 Field Documentation

8.1188.2.1 depersonalizationInformation UIMDepersonalizationReq::depersonilisationInfo

8.1189 UIMDepersonalizationResp Struct Reference

Data Fields

- remainingRetries * pRemainingRetries

8.1189.1 Detailed Description

This structure contains information of the response parameters associated with a Depersonalization API.

Parameters

pRemaining-Retries(optional)	• See remainingRetries for more information.

Note

Using NULL for the pointers would make sure that the parameter is not returned.

8.1189.2 Field Documentation

8.1189.2.1 remainingRetries* UIMDepersonalizationResp::pRemainingRetries

8.1190 UIMEventRegisterReqResp Struct Reference

Data Fields

- ULONG eventMask

8.1190.1 Detailed Description

This structure contains information of the request parameters associated with a SLQSUIMEventRegister.

Parameters

eventMask(-Mandatory)	• Bitmask of the events that were successfully enabled. This result can be different from the mask used in the request when notifications are not supported. Additional bits are reserved for future use. – Bit 0 - Card status – Bit 1 - SAP connection – Bit 4 - Physical Slot Status

8.1190.2 Field Documentation

8.1190.2.1 ULONG UIMEventRegisterReqResp::eventMask

8.1191 UIMGetCardStatusResp Struct Reference

Data Fields

- cardStatus ∗ pCardStatus
- hotSwapStatus ∗ pHotSwapStatus

8.1191.1 Detailed Description

This structure contains information of the response parameters associated with a Get Card Status API.

Parameters

pCard-Status(optional)	• See cardStatus for more information.
pHotSwap-Status(optional)	• See hotSwapStatus for more information.

Note

Using NULL for the pointers would make sure that the parameter is not returned.

8.1191.2 Field Documentation

8.1191.2.1 cardStatus∗ UIMGetCardStatusResp::pCardStatus

8.1191.2.2 hotSwapStatus∗ UIMGetCardStatusResp::pHotSwapStatus

8.1192 UIMGetCardStatusRespV2 Struct Reference

Data Fields

- cardStatus ∗ pCardStatus
- hotSwapStatus ∗ pHotSwapStatus
- validCardStatus ∗ pValidCardStatus
- simBusyStatus ∗ pSimBusyStatus

8.1192.1 Detailed Description

This structure contains information of the response parameters associated with a Get Card Status API.

Parameters

pCard-Status(optional)	• See cardStatus for more information.
pHotSwap-Status(optional)	• See hotSwapStatus for more information.
pValidCard-Status(optional)	• See validCardStatus for more information.
pSimBusy-Status(optional)	• See simBusyStatus for more information.

Note

Using NULL for the pointers would make sure that the parameter is not returned.

8.1192.2 Field Documentation

8.1192.2.1 cardStatus∗ UIMGetCardStatusRespV2::pCardStatus

8.1192.2.2 hotSwapStatus∗ UIMGetCardStatusRespV2::pHotSwapStatus

8.1192.2.3 simBusyStatus∗ UIMGetCardStatusRespV2::pSimBusyStatus

8.1192.2.4 validCardStatus∗ UIMGetCardStatusRespV2::pValidCardStatus

8.1193 UIMGetConfigurationReq Struct Reference

Data Fields

- ULONG ∗ pConfigurationMask

8.1193.1 Detailed Description

This structure contains information of the request parameters associated with to gets the modem configuration for the UIM module API.

Parameters

pConfiguration-Mask(optional)	• Requested configurations – Bit 0 - Automatic selection – Bit 1 - Personalization status – Bit 2 - Halt subscription – All other bits are reserved for future use

Note

- if the TLV is missing, the service returns all configuration items in the response.

8.1193.2 Field Documentation

8.1193.2.1 ULONG* UIMGetConfigurationReq::pConfigurationMask

8.1194 UIMGetConfigurationResp Struct Reference

Data Fields

- BYTE * pAutoSelection
- personalizationStatus * pPersonalizationStatus
- BYTE * pHaltSubscription

8.1194.1 Detailed Description

This structure contains information of the response parameters associated with a Read Transparent API.

Parameters

pAutoSelection(optional)	• Indicates whether the modem is configured to automatically select the provisioning sessions at powerup. • Valid values – 0 - Automatic provisioning is off – 1 - Automatic provisioning is on
pPersonalizationStatus(optional)	• See personalizationStatus for more information.
pHaltSubscription(optional)	• Indicates if the modem is configured to publish the subscription after successful initialization. • Valid values – 0 - Modem proceeds with publishing the subscription – 1 - Modem does not publish the subscription

8.1194.2 Field Documentation

8.1194.2.1 BYTE* UIMGetConfigurationResp::pAutoSelection

8.1194.2.2 BYTE* UIMGetConfigurationResp::pHaltSubscription

8.1194.2.3 personalizationStatus* UIMGetConfigurationResp::pPersonalizationStatus

8.1195 UIMGetFileAttributesReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- fileInfo fileIndex

- ULONG * pIndicationToken

8.1195.1 Detailed Description

This structure contains information of the request parameters associated with a Get File Attributes API.

Parameters

sessionInfo	• See UIMSessionInformation for more information.
fileIndex	• See fileInfo for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.1195.2 Field Documentation

8.1195.2.1 fileInfo UIMGetFileAttributesReq::fileIndex

8.1195.2.2 ULONG* UIMGetFileAttributesReq::pIndicationToken

8.1195.2.3 UIMSessionInformation UIMGetFileAttributesReq::sessionInfo

8.1196 UIMGetFileAttributesResp Struct Reference

Data Fields

- cardResult * pCardResult
- fileAttributes * pFileAttributes
- ULONG * pIndicationToken

8.1196.1 Detailed Description

This structure contains information of the response parameters associated with a Get File Attributes API.

Parameters

pCard-Result(optional)	• See cardResult for more information.
pFile-Attributes(optional)	• See fileAttributes for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not returned.

8.1196.2 Field Documentation

8.1196.2.1 cardResult* UIMGetFileAttributesResp::pCardResult

8.1196.2.2 fileAttributes* UIMGetFileAttributesResp::pFileAttributes

8.1196.2.3 ULONG* UIMGetFileAttributesResp::pIndicationToken

8.1197 UIMGetSlotsStatusResp Struct Reference

Data Fields

- BYTE * pNumberOfPhySlot
- UIMSlotsStatus * pUimSlotsStatus

8.1197.1 Detailed Description

This structure contains information of the response parameters associated with a Get Slots Status API.

Parameters

pNumberOfPhy-Slot	• Number of sets of the Slot Status.
pUimSlotsStatus	• Slots Status See UIMSlotsStatus for more information..

8.1197.2 Field Documentation

8.1197.2.1 BYTE* UIMGetSlotsStatusResp::pNumberOfPhySlot

8.1197.2.2 UIMSlotsStatus* UIMGetSlotsStatusResp::pUimSlotsStatus

8.1198 UIMPinResp Struct Reference

Data Fields

- remainingRetries * pRemainingRetries
- encryptedPIN1 * pEncryptedPIN1
- ULONG * pIndicationToken

8.1198.1 Detailed Description

This structure contains information of the response parameters associated with a set of PIN related API's.

Parameters

pRemaining-Retries(optional)	• See remainingRetries for more information.
pEncryptedPI-N1(optional)	• See encryptedPIN1 for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result is provided in a subsequent indication. • 0xFFFFFFFF, if unavailable

Note

Using NULL for the pointers would make sure that the parameter is not returned.

8.1198.2 Field Documentation

8.1198.2.1 encryptedPIN1∗ UIMPinResp::pEncryptedPIN1

8.1198.2.2 ULONG∗ UIMPinResp::pIndicationToken

8.1198.2.3 remainingRetries∗ UIMPinResp::pRemainingRetries

8.1199 UIMPinRespV2 Struct Reference

Data Fields

- remainingRetries ∗ pRemainingRetries
- encryptedPIN1 ∗ pEncryptedPIN1
- ULONG ∗ pIndicationToken
- cardResult ∗ pCardResult

8.1199.1 Detailed Description

This structure contains information of the response parameters associated with a set of PIN related API's.

Parameters

pRemaining-Retries(optional)	• See remainingRetries for more information.
pEncryptedPI-N1(optional)	• See encryptedPIN1 for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result is provided in a subsequent indication. • 0xFFFFFFFF, if unavailable
pCard-Result(optional)	• See cardResult for more information.

Note

Using NULL for the pointers would make sure that the parameter is not returned.

8.1199.2 Field Documentation

8.1199.2.1 cardResult∗ UIMPinRespV2::pCardResult

8.1199.2.2 encryptedPIN1∗ UIMPinRespV2::pEncryptedPIN1

8.1199.2.3 ULONG∗ UIMPinRespV2::pIndicationToken

8.1199.2.4 remainingRetries∗ UIMPinRespV2::pRemainingRetries

8.1200 UIMPowerDownReq Struct Reference

Data Fields

- BYTE slot

8.1200.1 Detailed Description

This structure contains information of the request parameters associated with a Power Down.

Parameters

slot	• Indicates the slot to be used. – 1 - Slot 1 – 2 - Slot 2

8.1200.2 Field Documentation

8.1200.2.1 BYTE UIMPowerDownReq::slot

8.1201 UIMPowerUpReq Struct Reference

Data Fields

- BYTE slot
- BYTE ∗ pIgnoreHotSwapSwitch

8.1201.1 Detailed Description

This structure contains information of the request parameters associated with a Power Down.

Parameters

slot	• Indicates the slot to be used. – 1 - Slot 1 – 2 - Slot 2

pIgnoreHot-Swap-Switch(optional)	• Hot-swap switch status. – 0 - Checks the hot-swap switch status – 1 - Ignores the hot-swap switch status

8.1201.2 Field Documentation

8.1201.2.1 BYTE* UIMPowerUpReq::pIgnoreHotSwapSwitch

8.1201.2.2 BYTE UIMPowerUpReq::slot

8.1202 UIMReadTransparentReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- fileInfo fileIndex
- readTransparentInfo readTransparent
- ULONG * pIndicationToken
- BYTE * pEncryptData

8.1202.1 Detailed Description

This structure contains information of the request parameters associated with a Read Transparent API.

Parameters

sessionInfo	• See UIMSessionInformation for more information.
fileIndex	• See fileInfo for more information.
readTransparent	• See readTransparentInfo for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.
pEncrypt-Data(optional)	• Encrypt Data. • Indicates whether the data read from the card is to be encrypted.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.1202.2 Field Documentation

8.1202.2.1 fileInfo UIMReadTransparentReq::fileIndex

8.1202.2.2 BYTE* UIMReadTransparentReq::pEncryptData

8.1202.2.3 ULONG* UIMReadTransparentReq::pIndicationToken

8.1202.2.4 readTransparentInfo UIMReadTransparentReq::readTransparent

8.1202.2.5 UIMSessionInformation UIMReadTransparentReq::sessionInfo

8.1203 UIMReadTransparentResp Struct Reference

Data Fields

- cardResult * pCardResult
- readResult * pReadResult
- ULONG * pIndicationToken
- BYTE * pEncryptedData

8.1203.1 Detailed Description

This structure contains information of the response parameters associated with a Read Transparent API.

Parameters

pCardResult	• See cardResult for more information.
pReadResult	• See readResult for more information.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.
pEncrypted-Data(optional)	• Encrypted Data. • Indicates whether the data from the card passed in read_result is encrypted.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.1203.2 Field Documentation

8.1203.2.1 cardResult* UIMReadTransparentResp::pCardResult

8.1203.2.2 BYTE* UIMReadTransparentResp::pEncryptedData

8.1203.2.3 ULONG* UIMReadTransparentResp::pIndicationToken

8.1203.2.4 readResult* UIMReadTransparentResp::pReadResult

8.1204 UIMRefreshCompleteReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- BYTE refreshComplete

8.1204.1 Detailed Description

This structure contains information of the request parameters associated with a SLQSUIMRefreshComplete.

Parameters

sessionInfo(-Mandatory)	• See UIMSessionInformation for more information.
refresh-Complete(-Mandatory)	• Indicates whether the refresh was successful. Valid values: – 0 - Refresh was not completed successfully – 1 - Refresh was completed successfully

8.1204.2 Field Documentation

8.1204.2.1 BYTE UIMRefreshCompleteReq::refreshComplete

8.1204.2.2 UIMSessionInformation UIMRefreshCompleteReq::sessionInfo

8.1205 UIMRefreshEvent Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE stage
- BYTE mode
- BYTE sessionType
- BYTE aidLength
- BYTE aid [255]
- WORD numOfFiles
- fileInfo arrfileInfo [255]

8.1205.1 Detailed Description

This structure contains information of parameters associated with the Refresh Event.

Parameters

stage	• Indicates the stage of the Refresh procedure. – 0 - Waiting for OK to refresh – 1 - Refresh started – 2 - Refresh ended successfully – 3 - Refresh failed

mode	• Indicates the Refresh mode. – 0 - Reset – 1 - Init – 2 - Init and FCN – 3 - FCN – 4 - Init and Full FCN – 5 - Application reset – 6 - 3G session reset
sessionType	• Indicates the session type. – 0 - Primary GW provisioning – 1 - Primary 1X provisioning – 2 - Secondary GW provisioning – 3 - Secondary 1X provisioning – 4 - Nonprovisioning on slot 1 – 5 - Nonprovisioning on slot 2 – 6 - Card on slot 1 – 7 - Card on slot 2 – 8 - Logical channel on slot 1 – 9 - Logical channel on slot 2
aidLength	• Number of sets of the following elements – Application Identifier
aid	• Application identifier value or channel ID. This value is required for non-provisioning and for logical channel session types. It is ignored in all other cases
numFiles	• Number of sets of the following elements: – file_id – path_len – path
arrfileInfo	• Array of file Information struct

8.1205.2 Field Documentation

8.1205.2.1 BYTE UIMRefreshEvent::aid[255]

8.1205.2.2 BYTE UIMRefreshEvent::aidLength

8.1205.2.3 fileInfo UIMRefreshEvent::arrfileInfo[255]

8.1205.2.4 BYTE UIMRefreshEvent::mode

8.1205.2.5 WORD UIMRefreshEvent::numOfFiles

8.1205.2.6 struct qmTlvResult UIMRefreshEvent::results

8.1205.2.7 BYTE UIMRefreshEvent::sessionType

8.1205.2.8 BYTE UIMRefreshEvent::stage

8.1206 UIMRefreshGetLastEventReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo

8.1206.1 Detailed Description

This structure contains information of the request parameters associated with a SLQSUIMRefreshGetLastEvent.

Parameters

sessionInfo(-Mandatory)	• See UIMSessionInformation for more information.

8.1206.2 Field Documentation

8.1206.2.1 UIMSessionInformation UIMRefreshGetLastEventReq::sessionInfo

8.1207 UIMRefreshGetLastEventResp Struct Reference

Data Fields

- UIMRefreshEvent * pRefreshEvent

8.1207.1 Detailed Description

This structure contains information of the response parameters associated with a SLQSUIMRefreshGetLastEvent.

Parameters

refreshEvent(-Optional)	• See UIMRefreshEvent for more information.

8.1207.2 Field Documentation

8.1207.2.1 UIMRefreshEvent* UIMRefreshGetLastEventResp::pRefreshEvent

8.1208 UIMRefreshOKReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- BYTE OKtoRefresh

8.1208.1 Detailed Description

This structure contains Parameters of the Session Information

Parameters

sessionInfo	• Session Information • See UIMSessionInformation for more information
OKtoRefresh	• Indicates whether a refresh is OK. Valid values: – 0 - Not OK to refresh – 1 - OK to refresh

8.1208.2 Field Documentation

8.1208.2.1 BYTE UIMRefreshOKReq::OKtoRefresh

8.1208.2.2 UIMSessionInformation UIMRefreshOKReq::sessionInfo

8.1209 UIMRefreshRegisterReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- registerRefresh regRefresh

8.1209.1 Detailed Description

This structure contains information of the request parameters associated with a Refresh Register.

Parameters

sessionInfo	• Session Information params • See UIMSessionInformation for more information
regRefresh	• Register Refresh parameters • See registerRefresh for more information

8.1209.2 Field Documentation

8.1209.2.1 registerRefresh UIMRefreshRegisterReq::regRefresh

8.1209.2.2 UIMSessionInformation UIMRefreshRegisterReq::sessionInfo

8.1210 UIMSessionInformation Struct Reference

Data Fields

- BYTE sessionType
- BYTE aidLength
- BYTE aid [255]

8.1210.1 Detailed Description

This structure contains the Session Information.

Parameters

sessionType	• Indicates the session type. – 0 - Primary GW provisioning – 1 - Primary 1X provisioning – 2 - Secondary GW provisioning – 3 - Secondary 1X provisioning – 4 - Non-provisioning on slot 1 – 5 - Non-provisioning on slot 2 – 6 - Card on slot 1 – 7 - Card on slot 2 – 8 - Logical channel on slot 1 – 9 - Logical channel on slot 2
aidLength	• Length of the following elements i.e. Application Identifier.
aid	• Application identifier value or channel ID. • This value is required for non-provisioning and for logical channel session types. It is ignored in all other cases.

8.1210.2 Field Documentation

8.1210.2.1 BYTE UIMSessionInformation::aid[255]

8.1210.2.2 BYTE UIMSessionInformation::aidLength

8.1210.2.3 BYTE UIMSessionInformation::sessionType

8.1211 UIMSetPinProtectionReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- setPINProtection pinProtection

- BYTE * pKeyReferenceID
- ULONG * pIndicationToken

8.1211.1 Detailed Description

This structure contains information of the request parameters associated with a set pin protection API.

Parameters

sessionInfo	• See UIMSessionInformation for more information.
pinProtection	• See setPINProtection for more information.
pKeyReferenceID(optional)	• Indicates the PIN key reference ID. • Indicates the PIN key reference ID. Valid values are from 1 to 8, respectively, for application 1 to application 8. • This TLV is used only for PIN1 and PIN2 and is ignored in all other cases.
pIndicationToken(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.1211.2 Field Documentation

8.1211.2.1 ULONG* UIMSetPinProtectionReq::pIndicationToken

8.1211.2.2 setPINProtection UIMSetPinProtectionReq::pinProtection

8.1211.2.3 BYTE* UIMSetPinProtectionReq::pKeyReferenceID

8.1211.2.4 UIMSessionInformation UIMSetPinProtectionReq::sessionInfo

8.1212 UIMSlotsStatus Struct Reference

Data Fields

- UIMSlotStatus uimSlotStatus [255]

8.1212.1 Detailed Description

This structure contains information of the response parameters associated with a Get Slots Status API.

Parameters

uimSlotStatus[MAX_SLOTS_STATUS]	• Contain all slots status.

8.1212.2 Field Documentation

8.1212.2.1 UIMSlotStatus UIMSlotsStatus::uimSlotStatus[255]

8.1213 UIMSlotStatus Struct Reference

Data Fields

- ULONG uPhyCardStatus
- ULONG uPhySlotStatus
- BYTE bLogicalSlot
- BYTE bICCIDLength
- BYTE bICCID [255]

8.1213.1 Detailed Description

This structure contains information of the response parameters associated with a Get Slots Status API.

Parameters

uPhyCardStatus	• State of the card in the Pyhsical Slot Status. – 0x00 - Unknown. – 0x01 - Absent. – 0x02 - Present.
uPhySlotStatus	• State of the Physical Slot status. – 0x00 Inactive. – 0x01 Activate.
bLogicalSlot	• Logical Slot associated with this physical slot. THis is valid if the physical slot is active. – 1 - Slot 1. – 2 - Slot 2. – 3 - Slot 3. – 4 - Slot 4. – 5 - Slot 5.
bLogicalSlot	• Number of sets the sets of ICCCID
bICCID[MAX_ICCID_LENGTH]	• Contains the ICCID of the card in the physical slot.

8.1213.2 Field Documentation

8.1213.2.1 BYTE UIMSlotStatus::bICCID[255]

8.1213.2.2 BYTE UIMSlotStatus::bICCIDLength

8.1213.2.3 BYTE UIMSlotStatus::bLogicalSlot

8.1213.2.4 ULONG UIMSlotStatus::uPhyCardStatus

8.1213.2.5 ULONG UIMSlotStatus::uPhySlotStatus

8.1214 UIMSlotStatusChangeInfo Struct Reference

Data Fields

- struct qmTlvResult results
- UIMSlotsStatus slotsstatusChange
- BYTE bNumberOfPhySlots

8.1214.1 Detailed Description

Structure consist of cardstatus params

Parameters

slotstatus-Change	• See UIMSlotStatus for more information
bNumberOfPhy-Slots	• Number of Physical Slot(s)

8.1214.2 Field Documentation

8.1214.2.1 BYTE UIMSlotStatusChangeInfo::bNumberOfPhySlots

8.1214.2.2 struct qmTlvResult UIMSlotStatusChangeInfo::results

8.1214.2.3 UIMSlotsStatus UIMSlotStatusChangeInfo::slotsstatusChange

8.1215 UIMStatusChangeInfo Struct Reference

Data Fields

- struct qmTlvResult results
- cardStatus statusChange

8.1215.1 Detailed Description

Structure consist of cardstatus params

Parameters

statusChange	• See cardStatus for more information

8.1215.2 Field Documentation

8.1215.2.1 struct qmTlvResult UIMStatusChangeInfo::results

8.1215.2.2 cardStatus UIMStatusChangeInfo::statusChange

8.1216 UIMSwitchSlotReq Struct Reference

Data Fields

- BYTE bLogicalSlot
- ULONG ulPhysicalSlot

8.1216.1 Detailed Description

This structure contains information of the request parameters associated with a Switch Slot.

Parameters

bLogicalSlot	• Indicates the slot to be used. – 1 - Slot 1 – 2 - Slot 2 – 3 - Slot 3 – 4 - Slot 4 – 5 - Slot 5
bPhysicalSlot	• 1 - Slot 1 • 2 - Slot 2 • 3 - Slot 3 • 4 - Slot 4 • 5 - Slot 5

8.1216.2 Field Documentation

8.1216.2.1 BYTE UIMSwitchSlotReq::bLogicalSlot

8.1216.2.2 ULONG UIMSwitchSlotReq::ulPhysicalSlot

8.1217 UIMUnblockPinReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- unblockUIMPIN unblockPIN
- BYTE * pKeyReferenceID
- ULONG * pIndicationToken

8.1217.1 Detailed Description

This structure contains information of the request parameters associated with a Unblock PIN API.

Parameters

sessionInfo	• See UIMSessionInformation for more information.
unblockPIN	• See unblockUIMPIN for more information.
pKeyReferenceI-D(optional)	• Indicates the PIN key reference ID. • Indicates the PIN key reference ID. Valid values are from 1 to 8, respectively, for application 1 to application 8. • This TLV is used only for PIN1 and PIN2 and is ignored in all other cases.
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.1217.2 Field Documentation

8.1217.2.1 ULONG∗ UIMUnblockPinReq::pIndicationToken

8.1217.2.2 BYTE∗ UIMUnblockPinReq::pKeyReferenceID

8.1217.2.3 UIMSessionInformation UIMUnblockPinReq::sessionInfo

8.1217.2.4 unblockUIMPIN UIMUnblockPinReq::unblockPIN

8.1218 UIMVerifyPinReq Struct Reference

Data Fields

- UIMSessionInformation sessionInfo
- verifyUIMPIN verifyPIN
- encryptedPIN1 ∗ pEncryptedPIN1
- BYTE ∗ pKeyReferenceID
- ULONG ∗ pIndicationToken

8.1218.1 Detailed Description

This structure contains information of the request parameters associated with a verify PIN API.

Parameters

sessionInfo	• See UIMSessionInformation for more information.
verifyPIN	• See verifyUIMPIN for more information.
pEncryptedPIN1(optional)	• See encryptedPIN1 for more information.
pKeyReferenceID(optional)	• Indicates the PIN key reference ID. • Indicates the PIN key reference ID. Valid values are from 1 to 8, respectively, for application 1 to application 8. • This TLV is used only for PIN1 and PIN2 and is ignored in all other cases.
pIndicationToken(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication.

Note

Using NULL for the pointers would make sure that the parameter is not added to the request.

8.1218.2 Field Documentation

8.1218.2.1 encryptedPIN1* UIMVerifyPinReq::pEncryptedPIN1

8.1218.2.2 ULONG* UIMVerifyPinReq::pIndicationToken

8.1218.2.3 BYTE* UIMVerifyPinReq::pKeyReferenceID

8.1218.2.4 UIMSessionInformation UIMVerifyPinReq::sessionInfo

8.1218.2.5 verifyUIMPIN UIMVerifyPinReq::verifyPIN

8.1219 UMTSInfo Struct Reference

Data Fields

- WORD cellID
- BYTE plmn [3]
- WORD lac
- WORD uarfcn
- WORD psc
- SHORT rscp
- SHORT ecio
- BYTE umtsInst
- UMTSinstInfo UMTSInstInfo [255]
- BYTE geranInst
- geranInstInfo GeranInstInfo [255]

8.1219.1 Detailed Description

This structure contains information about the UMTS Network.

Parameters

cellID	• Cell ID. • 0xFFFFFFFF indicates cell ID information is not present.
plmn[PLMN_LENGTH]	• MCC/MNC information coded as octet 3, 4, and 5. • This field is ignored when nmrCellID is not present.
lac	• Location area code. • This field is ignored when nmrCellID is not present. – 0xFFFF - Not Available
uarfcn	• UTRA absolute RF channel number. – 0xFFFF - Not Available
psc	• Primary scrambling code. – 0xFFFF - Not Available
rscp	• Received signal code power. – 0xFFFF - Not Available
ecio	• ECIO(Signal-to-Interference-ratio). – 0xFFFF - Not Available
umtsInst	• Provides the number of set of UMTS info instances. • If 0(zero), then no information follows it.
UMTSInstInfo[MAX_DESCRIPTION_LENGTH]	• See UMTSinstInfo for more information.
geranInst	• Provides the number of set of GERAN info instances. • If 0(zero), then no information follows it.
GeranInstInfo[MAX_DESCRIPTION_LENGTH]	• See geranInstInfo for more information.

8.1219.2 Field Documentation

8.1219.2.1 WORD UMTSInfo::cellID

8.1219.2.2 SHORT UMTSInfo::ecio

8.1219.2.3 BYTE UMTSInfo::geranInst

8.1219.2.4 geranInstInfo UMTSInfo::GeranInstInfo[255]

8.1219.2.5 WORD UMTSInfo::lac

8.1219.2.6 BYTE UMTSInfo::plmn[3]

8.1219.2.7 WORD UMTSInfo::psc

8.1219.2.8 SHORT UMTSInfo::rscp

8.1219.2.9 WORD UMTSInfo::uarfcn

8.1219.2.10 BYTE UMTSInfo::umtsInst

8.1219.2.11 UMTSinstInfo UMTSInfo::UMTSInstInfo[255]

8.1220 UMTSinstInfo Struct Reference

Data Fields

- WORD umtsUarfcn
- WORD umtsPsc
- SHORT umtsRscp
- SHORT umtsEcio

8.1220.1 Detailed Description

This structure contains information about the UMTS Instances in UMTS Network.

Parameters

umtsUarfcn	• UTRA absolute RF channel number.
umtsPsc	• Primary scrambling code.
umtsRscp	• Received signal code power.
umtsEcio	• ECIO(Signal-to-Interference-ratio).

8.1220.2 Field Documentation

8.1220.2.1 SHORT UMTSinstInfo::umtsEcio

8.1220.2.2 WORD UMTSinstInfo::umtsPsc

8.1220.2.3 SHORT UMTSinstInfo::umtsRscp

8.1220.2.4 WORD UMTSinstInfo::umtsUarfcn

8.1221 umtsLTENbrCell Struct Reference

Data Fields

- WORD earfcn
- WORD pci
- ULONG rsrp
- ULONG rsrq
- SHORT srxlev
- BYTE cellIsTDD

8.1221.1 Detailed Description

This structure contains information about the UMTS LTE neighbour Cell.

Parameters

earfcn	• E-UTRA absolute RF channel number of the detected cell.
pci	• Physical cell ID of the detected cell. • Range is defined in 3GPP TS 36.211
rsrp	• Current received signal strength indication (in dBm) of the detected cell.
rsrq	• Current reference signal received quality (in dB) of the detected cell.
srxlev	• Cell selection Rx level (Srxlev) value of the detected cell in linear scale. • This field is only valid when wcdma_rrc_state is not NAS_WCDMA_RRC_STATE_CEL_FACH or NAS_WCDMA_RRC_STATE_CELL_DCH.
cellIsTDD	• TRUE if the cell is TDD; FALSE if the cell is FDD.

8.1221.2 Field Documentation

8.1221.2.1 BYTE umtsLTENbrCell::cellIsTDD

8.1221.2.2 WORD umtsLTENbrCell::earfcn

8.1221.2.3 WORD umtsLTENbrCell::pci

8.1221.2.4 ULONG umtsLTENbrCell::rsrp

8.1221.2.5 ULONG umtsLTENbrCell::rsrq

8.1221.2.6 SHORT umtsLTENbrCell::srxlev

8.1222 UMTSMinQoS Struct Reference

Data Fields

- BYTE trafficClass
- ULONG maxUplinkBitrate
- ULONG maxDownlinkBitrate
- ULONG grntUplinkBitrate
- ULONG grntDownlinkBitrate
- BYTE qosDeliveryOrder
- ULONG maxSDUSize
- BYTE sduErrorRatio
- BYTE resBerRatio
- BYTE deliveryErrSDU
- ULONG transferDelay
- ULONG trafficPriority

8.1222.1 Detailed Description

This structure contains the UMTS Quality Of Service Information

Parameters

trafficClass	• 0x00 - Subscribed • 0x01 - Conversational • 0x02 - Streaming • 0x03 - Interactive • 0x04 - Background
maxUplinkBitrate	• Maximum uplink bit rate in bits/sec
maxDownlink-Bitrate	• Maximum downlink bit rate in bits/sec
grntUplinkBitrate	• Guaranteed uplink bit rate in bits/sec
grntDownlink-Bitrate	• Guaranteed downlink bit rate in bits/sec
qosDelivery-Order	- Qos delivery order • 0x00 - Subscribe • 0x01 - Delivery order on • 0x02 - Delivery order off
maxSDUSize	• Maximum SDU size

sduErrorRatio	- SDU error ratio • Target value for fraction of SDUs lost or detected as erroneous. • 0x00 - Subscribe • 0x01 - 1∗10^(-2) • 0x02 - 7∗10^(-3) • 0x03 - 1∗10^(-3) • 0x04 - 1∗10^(-4) • 0x05 - 1∗10^(-5) • 0x06 - 1∗10^(-6) • 0x07 - 1∗10^(-1)
resBerRatio	- Residual bit error ratio • Target value for undetected bit error ratio in in the delivered SDUs. • 0x00 - Subscribe • 0x01 - 5∗10^(-2) • 0x02 - 1∗10^(-2) • 0x03 - 5∗10^(-3) • 0x04 - 4∗10^(-3) • 0x05 - 1∗10^(-3) • 0x06 - 1∗10^(-4) • 0x07 - 1∗10^(-5) • 0x08 - 1∗10^(-6) • 0x09 - 1∗10^(-8)
deliveryErrSDU	- delivery of erroneous SDUs • Indicates whether SDUs detected as erroneous shall be delivered or not. • 0x00 - Subscribe • 0x01 - 5∗10^(-2) • 0x02 - 1∗10^(-2) • 0x03 - 5∗10^(-3) • 0x04 - 4∗10^(-3) • 0x05 - 1∗10^(-3) • 0x06 - 1∗10^(-4) • 0x07 - 1∗10^(-5) • 0x08 - 1∗10^(-6) • 0x09 - 1∗10^(-8)
transferDelay	- Transfer delay (ms) • Indicates the targeted time between a request to transfer an SDU at one SAP to its delivery at the other SAP in milliseconds.
trafficPriority	- Transfer handling priority • Specifies the relative importance for handling of SDUs that belong to the UMTS bearer, compared to the SDUs of other bearers.

8.1222.2 Field Documentation

8.1222.2.1 BYTE UMTSMinQoS::deliveryErrSDU

8.1222.2.2 ULONG UMTSMinQoS::grntDownlinkBitrate

8.1222.2.3 ULONG UMTSMinQoS::grntUplinkBitrate

8.1222.2.4 ULONG UMTSMinQoS::maxDownlinkBitrate

8.1222.2.5 ULONG UMTSMinQoS::maxSDUSize

8.1222.2.6 ULONG UMTSMinQoS::maxUplinkBitrate

8.1222.2.7 BYTE UMTSMinQoS::qosDeliveryOrder

8.1222.2.8 BYTE UMTSMinQoS::resBerRatio

8.1222.2.9 BYTE UMTSMinQoS::sduErrorRatio

8.1222.2.10 BYTE UMTSMinQoS::trafficClass

8.1222.2.11 ULONG UMTSMinQoS::trafficPriority

8.1222.2.12 ULONG UMTSMinQoS::transferDelay

8.1223 UMTSQoS Struct Reference

Data Fields

- BYTE trafficClass
- ULONG maxUplinkBitrate
- ULONG maxDownlinkBitrate
- ULONG grntUplinkBitrate
- ULONG grntDownlinkBitrate
- BYTE qosDeliveryOrder
- ULONG maxSDUSize
- BYTE sduErrorRatio
- BYTE resBerRatio
- BYTE deliveryErrSDU
- ULONG transferDelay
- ULONG trafficPriority

8.1223.1 Detailed Description

This structure contains the UMTS Quality Of Service Information

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

trafficClass	• 0x00 - Subscribed • 0x01 - Conversational • 0x02 - Streaming • 0x03 - Interactive • 0x04 - Background

maxUplinkBitrate	• Maximum uplink bit rate in bits/sec
maxDownlink-Bitrate	• Maximum downlink bit rate in bits/sec
grntUplinkBitrate	• Guaranteed uplink bit rate in bits/sec
grntDownlink-Bitrate	• Guranteed downlink bit rate in bits/sec
qosDelivery-Order	- Qos delivery order • 0x00 - Subscribe • 0x01 - delivery order on • 0x02 - delivery order off
maxSDUSize	• Maximum SDU size
sduErrorRatio	- SDU error ratio • Target value for fraction of SDUs lost or detected as erroneous. • 0x00 - Subscribe • 0x01 - 1∗10^(-2) • 0x02 - 7∗10^(-3) • 0x03 - 1∗10^(-3) • 0x04 - 1∗10^(-4) • 0x05 - 1∗10^(-5) • 0x06 - 1∗10^(-6) • 0x07 - 1∗10^(-1)
resBerRatio	- Residual bit error ratio • Target value for undetected bit error ratio in in the delivered SDUs. • 0x00 - Subscribe • 0x01 - 5∗10^(-2) • 0x02 - 1∗10^(-2) • 0x03 - 5∗10^(-3) • 0x04 - 4∗10^(-3) • 0x05 - 1∗10^(-3) • 0x06 - 1∗10^(-4) • 0x07 - 1∗10^(-5) • 0x08 - 1∗10^(-6) • 0x09 - 1∗10^(-8)

deliveryErrSDU	- Delivery of erroneous SDUs • Indicates whether SDUs detected as erroneous shall be delivered or not. • 0x00 - Subscribe • 0x01 - 5∗10^(-2) • 0x02 - 1∗10^(-2) • 0x03 - 5∗10^(-3) • 0x04 - 4∗10^(-3) • 0x05 - 1∗10^(-3) • 0x06 - 1∗10^(-4) • 0x07 - 1∗10^(-5) • 0x08 - 1∗10^(-6) • 0x09 - 1∗10^(-8)
transferDelay	- Transfer delay (ms) • Indicates the targeted time between a request to transfer an SDU at one SAP to its delivery at the other SAP in milliseconds.
trafficPriority	- Transfer handling priority • Specifies the relative importance for handling of SDUs that belong to the UMTS bearer, compared to the SDUs of other bearers.

8.1223.2 Field Documentation

8.1223.2.1 BYTE UMTSQoS::deliveryErrSDU

8.1223.2.2 ULONG UMTSQoS::grntDownlinkBitrate

8.1223.2.3 ULONG UMTSQoS::grntUplinkBitrate

8.1223.2.4 ULONG UMTSQoS::maxDownlinkBitrate

8.1223.2.5 ULONG UMTSQoS::maxSDUSize

8.1223.2.6 ULONG UMTSQoS::maxUplinkBitrate

8.1223.2.7 BYTE UMTSQoS::qosDeliveryOrder

8.1223.2.8 BYTE UMTSQoS::resBerRatio

8.1223.2.9 BYTE UMTSQoS::sduErrorRatio

8.1223.2.10 BYTE UMTSQoS::trafficClass

8.1223.2.11 ULONG UMTSQoS::trafficPriority

8.1223.2.12 ULONG UMTSQoS::transferDelay

8.1224 UMTSReqQoSSigInd Struct Reference

Data Fields

- struct UMTSQoS UMTSReqQoS
- BYTE SigInd

8.1224.1 Detailed Description

structure contains UMTS requested QoS with Signaling Indication flag

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

UMTSReqQoS	• Contains the UMTS Quality Of Service Information
SigInd	- Signaling Indication flag • TRUE - Signaling indication ON • FALSE - Signaling indication OFF

8.1224.2 Field Documentation

8.1224.2.1 BYTE UMTSReqQoSSigInd::SigInd

8.1224.2.2 struct UMTSQoS UMTSReqQoSSigInd::UMTSReqQoS

8.1225 unblockUIMPIN Struct Reference

Data Fields

- BYTE pinID
- BYTE pukLen
- BYTE pukVal [255]
- BYTE newPINLen
- BYTE newPINVal [255]

8.1225.1 Detailed Description

This structure contains the information about the unblock pin parameters.

Parameters

pinID	• Indicates the PIN ID to be changed. – 1 - PIN1 (also called PIN) – 2 - PIN2 – 3 - Universal PIN
pukLen	• Length of the following elements i.e. puk value.

pukVal[MAX_PUK_LENGTH]	• PIN Unlock Key value. • This value is a sequence of ASCII characters.
pinLen	• Length of the following elements i.e. new pin value.
pinVal[MAX_DESCRIPTION_LENGTH]	• New PIN value. • This value is a sequence of ASCII characters.

8.1225.2 Field Documentation

8.1225.2.1 BYTE unblockUIMPIN::newPINLen

8.1225.2.2 BYTE unblockUIMPIN::newPINVal[255]

8.1225.2.3 BYTE unblockUIMPIN::pinID

8.1225.2.4 BYTE unblockUIMPIN::pukLen

8.1225.2.5 BYTE unblockUIMPIN::pukVal[255]

8.1226 UniversalTime Struct Reference

Data Fields

- WORD year
- BYTE month
- BYTE day
- BYTE hour
- BYTE minute
- BYTE second
- BYTE dayOfWeek

8.1226.1 Detailed Description

This structure contains the parameters for Universal Time Information.

Parameters

year	• Year.
month	• Month. – 1 is January and 12 is December.
day	• Day. – Range 1 to 31.

hour	• Hour. – Range 0 to 59.
minute	• Minute. – Range 0 to 59.
second	• Second. – Range 0 to 59.
dayOfWeek	• Day of the Week. – 0 is Monday and 6 is Sunday.

8.1226.2 Field Documentation

8.1226.2.1 BYTE UniversalTime::day

8.1226.2.2 BYTE UniversalTime::dayOfWeek

8.1226.2.3 BYTE UniversalTime::hour

8.1226.2.4 BYTE UniversalTime::minute

8.1226.2.5 BYTE UniversalTime::month

8.1226.2.6 BYTE UniversalTime::second

8.1226.2.7 WORD UniversalTime::year

8.1227 unpack_dms_GetActivationState_t Struct Reference

Data Fields

- uint8_t state
- swi_uint256_t ParamPresenceMask

8.1227.1 Detailed Description

This structure contains unpack_dms_GetActivationState parameters.

Parameters

state[OUT]	• Service Activation Code 0 - Service not activated 1 - Service activated 2 - Activation connecting 3 - Activation connected 4 - OTASP security authenticated 5 - OTASP NAM downloaded 6 - OTASP MDN downloaded 7 - OTASP IMSI downloaded 8 - OTASP PRL downloaded 9 - OTASP SPC downloaded 10 - OTASP settings committed • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1227.2 Field Documentation

8.1227.2.1 swi_uint256_t unpack_dms_GetActivationState_t::ParamPresenceMask

8.1227.2.2 uint8_t unpack_dms_GetActivationState_t::state

8.1228 unpack_dms_GetBandCapability_t Struct Reference

Data Fields

- uint64_t BandCapability
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1228.1 Detailed Description

Structure to store the band capability of the device.

Parameters

BandCapability	Bitmask of bands supported by the device • Bit 0 - Band class 0, A-system • Bit 1 - Band class 0, B-system • Bit 2 - Band class 1, all blocks • Bit 3 - Band class 2 • Bit 4 - Band class 3, A-system • Bit 5 - Band class 4, all blocks • Bit 6 - Band class 5, all blocks • Bit 7 - GSM DCS band (1800) • Bit 8 - GSM Extended GSM (E-GSM) band (900) • Bit 9 - GSM Primary GSM (P-GSM) band (900) • Bit 10 - Band class 6 • Bit 11 - Band class 7 • Bit 12 - Band class 8 • Bit 13 - Band class 9 • Bit 14 - Band class 10 • Bit 15 - Band class 11 • Bit 16 - GSM 450 band • Bit 17 - GSM 480 band • Bit 18 - GSM 750 band • Bit 19 - GSM 850 band • Bit 20 - GSM railways GSM band (900) • Bit 21 - GSM PCS band (1900) • Bit 22 - WCDMA (Europe, Japan, and China) 2100 band • Bit 23 - WCDMA US PCS 1900 band • Bit 24 - WCDMA (Europe and China) DCS 1800 band • Bit 25 - WCDMA US 1700 band • Bit 26 - WCDMA US 850 band • Bit 27 - WCDMA Japan 800 band • Bit 28 - Band class 12 • Bit 29 - Band class 14 • Bit 30 - Reserved • Bit 31 - Band class 15 • Bits 32 through 47 - Reserved • Bit 48 - WCDMA Europe 2600 band • Bit 49 - WCDMA Europe and Japan 900 band • Bit 50 - WCDMA Japan 1700 band • Bits 51 through 55 - Reserved • Bit 56 - Band class 16 • Bit 57 - Band class 17 • Bit 58 - Band class 18 • Bit 59 - Band class 19 • Bit 60 - WCDMA Japan 850 band • Bit 61 - WCDMA 1500 band • Bits 62 and 63 - Reserved

- Bit to check in ParamPresenceMask - **1**

Parameters

Tlvresult	• unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1228.2 Field Documentation

8.1228.2.1 uint64_t unpack_dms_GetBandCapability_t::BandCapability

8.1228.2.2 swi_uint256_t unpack_dms_GetBandCapability_t::ParamPresenceMask

8.1228.2.3 uint16_t unpack_dms_GetBandCapability_t::Tlvresult

8.1229 unpack_dms_GetCrashAction_t Struct Reference

Data Fields

- uint8_t DevCrashState
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1229.1 Detailed Description

This structure is used to store the Crash State from the device.

Parameters

DevCrashState	• Device Crash State • Values: – 0 - USB Memory Download Modem will reset after a crash and will stay in USB download mode with only ttyUSB0 enumerated. ramdump tool is to be used to recover the crash dump. Modem needs to be reset again to come back in ONLINE mode. – 1 - Reset Modem will reset and come back in ONLINE mode. Minimal crash data will be available and can be extracted with at!gcdump? AT command or SLQSSwiGetCrashInfo() SDK API – 2 - No action • Bit to check in ParamPresenceMask - **1**
Tlvresult	• unpack Tlv result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1229.2 Field Documentation

8.1229.2.1 uint8_t unpack_dms_GetCrashAction_t::DevCrashState

8.1229.2.2 swi_uint256_t unpack_dms_GetCrashAction_t::ParamPresenceMask

8.1229.2.3 uint16_t unpack_dms_GetCrashAction_t::Tlvresult

8.1230 unpack_dms_GetCustFeature_t Struct Reference

Data Fields

- uint32_t GpsEnable
- uint8_t DisableIMSI
- uint16_t IPFamSupport
- uint8_t RMAutoConnect
- uint8_t GPSSel
- uint8_t SMSSupport
- uint8_t IsVoiceEnabled
- uint8_t DHCPRelayEnabled
- uint8_t GPSLPM
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1230.1 Detailed Description

This structure contains current settings of custom features

Parameters

GpsEnable	• describes if GPS is enabled or disabled • values: – 0x00 - GPS is disabled – 0x01 - GPS is enabled • Bit to check in ParamPresenceMask - **16**
DisableIMSI	• optional 1 byte parameter • describes if IMSI display is enabled or disabled • values: – 0x00 - Allow display of IMSI – 0x01 - Do not display IMSI • Bit to check in ParamPresenceMask - **17**
IPFamSupport	• optional 2 byte BitMask • bitmask representing the IP families supported • values: – 0x01 - IPv4 – 0x02 - IPv6 – 0x04 - IPv4v6 • Bit to check in ParamPresenceMask - **18**

RMAutoConnect	• optional 1 byte parameter • QMI Mode RM Net Auto Connect Support • values: – 0x00 - Not Supported – 0x01 - Supported • Bit to check in ParamPresenceMask - **19**
GPSSel	• optional 1 byte parameter • GPS Antenna Select • values: – 0x00 - Dedicated GPS Port – 0x01 - GPS Rx over AUX Port – 0x02 - GPS Rx over dedicated GPS port with no bias voltage applied • Bit to check in ParamPresenceMask - **20**
SMSSupport	• optional 1 byte parameter • SMS support • values: – 0x00 - Not supported – 0x01 - supported • Bit to check in ParamPresenceMask - **21** • Used to determine whether or not to hide SMS from user
IsVoiceEnabled	• optional 1 byte parameter • Voice support • values: – 0x00 - Enable voice on both AT and QMI interface (default) – 0x01 - Reserved – 0x02 - Disable voice on both AT and QMI interface • Bit to check in ParamPresenceMask - **22**
DHCPRelay-Enabled	• optional 1 byte parameter • DHCP Relay support • values: – 0x00 - Disable DHCP relay – 0x01 - Enable DHCP relay • Bit to check in ParamPresenceMask - **23**
GPSLPM	• optional 1 byte parameter • GPSLPM support • values: – 0x00 - Enable GPS in Low Power Mode – 0x01 - Disable GPS in Low Power Mode • Bit to check in ParamPresenceMask - **24**

Tlvresult	• unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1230.2 Field Documentation

8.1230.2.1 uint8_t unpack_dms_GetCustFeature_t::DHCPRelayEnabled

8.1230.2.2 uint8_t unpack_dms_GetCustFeature_t::DisableIMSI

8.1230.2.3 uint32_t unpack_dms_GetCustFeature_t::GpsEnable

8.1230.2.4 uint8_t unpack_dms_GetCustFeature_t::GPSLPM

8.1230.2.5 uint8_t unpack_dms_GetCustFeature_t::GPSSel

8.1230.2.6 uint16_t unpack_dms_GetCustFeature_t::IPFamSupport

8.1230.2.7 uint8_t unpack_dms_GetCustFeature_t::IsVoiceEnabled

8.1230.2.8 swi_uint256_t unpack_dms_GetCustFeature_t::ParamPresenceMask

8.1230.2.9 uint8_t unpack_dms_GetCustFeature_t::RMAutoConnect

8.1230.2.10 uint8_t unpack_dms_GetCustFeature_t::SMSSupport

8.1230.2.11 uint16_t unpack_dms_GetCustFeature_t::Tlvresult

8.1231 unpack_dms_GetCustFeaturesV2_t Struct Reference

Data Fields

- DMSgetCustomFeatureV2 GetCustomFeatureV2
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1231.1 Detailed Description

This structure contains customization settings set to modem unpack

Parameters

GetCustom-FeatureV2	• See DMSgetCustomFeatureV2 for more information
	• pCustSettingInfo
	  – Bit to check in ParamPresenceMask - **32**
	• pCustSettingList
	  – Bit to check in ParamPresenceMask - **33**

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1231.2 Field Documentation

8.1231.2.1 DMSgetCustomFeatureV2 unpack_dms_GetCustFeaturesV2_t::GetCustomFeatureV2

8.1231.2.2 swi_uint256_t unpack_dms_GetCustFeaturesV2_t::ParamPresenceMask

8.1231.2.3 uint16_t unpack_dms_GetCustFeaturesV2_t::Tlvresult

8.1232 unpack_dms_GetDeviceCap_t Struct Reference

Data Fields

- uint32_t MaxTXChannelRate
- uint32_t MaxRXChannelRate
- uint32_t DataServiceCapability
- uint32_t SimCapability
- uint32_t RadioIfacesSize
- uint8_t RadioIfaces [64]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1232.1 Detailed Description

Structure to store the device capabilities

Parameters

MaxTXChannel-Rate	• Maximum transmission rate (in bps) supported by the device • In multi-technology devices, this value will be the greatest rate among all supported technologies • Bit to check in ParamPresenceMask - **1**
MaxRXChannel-Rate	• Maximum reception rate (in bps) supported by the device • In multi-technology devices, this value will be the greatest rate among all supported technologies • Bit to check in ParamPresenceMask - **1**
DataService-Capability	• CS/PS data service capability – 0 - No data services supported – 1 - Only Circuit Switched (CS) services supported – 2 - Only Packet Switched (PS) services supported – 3 - Simultaneous CS and PS – 4 - Non-simultaneous CS and PS • Bit to check in ParamPresenceMask - **1**

SimCapability	Device SIM capability • 0 - SIM not supported • 1 - SIM supported

- Bit to check in ParamPresenceMask - **1**

Parameters

RadioIfacesSize	• Upon input, the maximum number of elements that the radio interface array can contain • Upon successful output, actual number of elements in the radio interface array • Bit to check in ParamPresenceMask - **1**
RadioIfaces	• Radio interface array. This is a structure of array containing the elements below. uint8_t RadioIfaces – See qaGobiApiTableRadioInterfaces.h for Radio Interfaces • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1232.2 Field Documentation

8.1232.2.1 uint32_t unpack_dms_GetDeviceCap_t::DataServiceCapability

8.1232.2.2 uint32_t unpack_dms_GetDeviceCap_t::MaxRXChannelRate

8.1232.2.3 uint32_t unpack_dms_GetDeviceCap_t::MaxTXChannelRate

8.1232.2.4 swi_uint256_t unpack_dms_GetDeviceCap_t::ParamPresenceMask

8.1232.2.5 uint8_t unpack_dms_GetDeviceCap_t::RadioIfaces[64]

8.1232.2.6 uint32_t unpack_dms_GetDeviceCap_t::RadioIfacesSize

8.1232.2.7 uint32_t unpack_dms_GetDeviceCap_t::SimCapability

8.1232.2.8 uint16_t unpack_dms_GetDeviceCap_t::Tlvresult

8.1233 unpack_dms_GetDeviceCapabilities_t Struct Reference

Data Fields

- uint32_t maxTxChannelRate
- uint32_t maxRxChannelRate
- uint32_t dataServiceCaCapability

- uint32_t simCapability
- uint32_t radioIfacesSize
- uint8_t RadioIfaces [255]
- swi_uint256_t ParamPresenceMask

8.1233.1 Detailed Description

Gets the device capabilities structure

Parameters

maxTxChannelRate	• Maximum transmission rate (in bps) supported by the device • In multi-technology devices, this value will be the greatest rate among all supported technologies • Bit to check in ParamPresenceMask - **1**
maxRxChannelRate	• Maximum reception rate (in bps) supported by the device • In multi-technology devices, this value will be the greatest rate among all supported technologies • Bit to check in ParamPresenceMask - **1**
dataServiceCaCapability	• CS/PS data service capability – 0 - No data services supported – 1 - Only Circuit Switched (CS) services supported – 2 - Only Packet Switched (PS) services supported – 3 - Simultaneous CS and PS – 4 - Non-simultaneous CS and PS • Bit to check in ParamPresenceMask - **1**
simCapability	• Device SIM capability – 0 - SIM not supported – 1 - SIM supported • Bit to check in ParamPresenceMask - **1**
radioIfacesSize	• Upon input, the maximum number of elements that the radio interface array can contain • Upon successful output, actual number of elements in the radio interface array • Bit to check in ParamPresenceMask - **1**
RadioIfaces[OUT]	• Radio interface array. This is a structure of array containing the elements below. – See qaGobiApiTableRadioInterfaces.h for Radio Interfaces • Bit to check in ParamPresenceMask - **1**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1233.2 Field Documentation

8.1233.2.1 uint32_t unpack_dms_GetDeviceCapabilities_t::dataServiceCaCapability

8.1233.2.2 uint32_t unpack_dms_GetDeviceCapabilities_t::maxRxChannelRate

8.1233.2.3 uint32_t unpack_dms_GetDeviceCapabilities_t::maxTxChannelRate

8.1233.2.4 swi_uint256_t unpack_dms_GetDeviceCapabilities_t::ParamPresenceMask

8.1233.2.5 uint8_t unpack_dms_GetDeviceCapabilities_t::RadioIfaces[255]

8.1233.2.6 uint32_t unpack_dms_GetDeviceCapabilities_t::radioIfacesSize

8.1233.2.7 uint32_t unpack_dms_GetDeviceCapabilities_t::simCapability

8.1234 unpack_dms_GetDeviceHardwareRev_t Struct Reference

Data Fields

- uint8_t stringSize
- char String [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1234.1 Detailed Description

Structure to store the hardware revision of the device

Parameters

stringSize	• The maximum number of characters (including NULL terminator) that the string array can contain • Bit to check in ParamPresenceMask - **1**
String	• NULL terminated Hardware Revision string • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1234.2 Field Documentation

8.1234.2.1 swi_uint256_t unpack_dms_GetDeviceHardwareRev_t::ParamPresenceMask

8.1234.2.2 char unpack_dms_GetDeviceHardwareRev_t::String[255]

8.1234.2.3 uint8_t unpack_dms_GetDeviceHardwareRev_t::stringSize

8.1234.2.4 uint16_t unpack_dms_GetDeviceHardwareRev_t::Tlvresult

8.1235 unpack_dms_GetDeviceMfr_t Struct Reference

Data Fields

- uint8_t stringSize
- char String [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1235.1 Detailed Description

This structure is used to store unpack_dms_GetDeviceMfr parameters

Parameters

stringSize	• The maximum number of characters (including NULL terminator) that the string array can contain

- Bit to check in ParamPresenceMask - **1**

Parameters

String	• NULL terminated Device Manufacture string • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **1**
Tlvresult	• unpack Tlv result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1235.2 Field Documentation

8.1235.2.1 swi_uint256_t unpack_dms_GetDeviceMfr_t::ParamPresenceMask

8.1235.2.2 char unpack_dms_GetDeviceMfr_t::String[255]

8.1235.2.3 uint8_t unpack_dms_GetDeviceMfr_t::stringSize

8.1235.2.4 uint16_t unpack_dms_GetDeviceMfr_t::Tlvresult

8.1236 unpack_dms_GetDeviceSerialNumbers_t Struct Reference

Data Fields

- uint8_t esnSize

- char ESNString [255]
- uint8_t imeiSize
- char IMEIString [255]
- uint8_t meidSize
- char MEIDString [255]
- uint8_t imeiSvnSize
- char ImeiSvnString [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1236.1 Detailed Description

This structure used to store unpack_dms_GetDeviceSerialNumbers parameters

Parameters

esnSize	• The maximum number of characters (including NULL terminator) that the ESN string array can contain • Bit to check in ParamPresenceMask - **16**
ESNString	• NULL-terminated ESN string. Empty string is returned when ESN is not supported/programmed • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **16**
imeiSize	• The maximum number of characters (including NULL terminator) that the IMEI string array can contain • Bit to check in ParamPresenceMask - **17**
IMEIString	• NULL terminated IMEI string. Empty string is returned when IMEI is not supported/programmed • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **17**
meidSize	• The maximum number of characters (including NULL terminator) that the MEID string array can contain • Bit to check in ParamPresenceMask - **18**
MEIDString	• NULL-terminated MEID string. Empty string is returned when MEID is not supported/programmed • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **18**
imeiSvnSize	• The maximum number of characters (including NULL terminator) that the IMEI SVN string array can contain. • Bit to check in ParamPresenceMask - **19**

ImeiSvnString	• NULL-terminated IMEI SVN string. Empty string is returned when IMEI SVN is not supported/programmed. • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **19**
Tlvresult	• unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1236.2 Field Documentation

8.1236.2.1 uint8_t unpack_dms_GetDeviceSerialNumbers_t::esnSize

8.1236.2.2 char unpack_dms_GetDeviceSerialNumbers_t::ESNString[255]

8.1236.2.3 uint8_t unpack_dms_GetDeviceSerialNumbers_t::imeiSize

8.1236.2.4 char unpack_dms_GetDeviceSerialNumbers_t::IMEIString[255]

8.1236.2.5 uint8_t unpack_dms_GetDeviceSerialNumbers_t::imeiSvnSize

8.1236.2.6 char unpack_dms_GetDeviceSerialNumbers_t::ImeiSvnString[255]

8.1236.2.7 uint8_t unpack_dms_GetDeviceSerialNumbers_t::meidSize

8.1236.2.8 char unpack_dms_GetDeviceSerialNumbers_t::MEIDString[255]

8.1236.2.9 swi_uint256_t unpack_dms_GetDeviceSerialNumbers_t::ParamPresenceMask

8.1236.2.10 uint16_t unpack_dms_GetDeviceSerialNumbers_t::Tlvresult

8.1237 unpack_dms_GetFirmwareInfo_t Struct Reference

Data Fields

- char modelid_str [20]
- char bootversion_str [85]
- char appversion_str [85]
- char sku_str [15]
- char packageid_str [85]
- char carrier_str [20]
- char priversion_str [16]
- char cur_carr_name [17]
- char cur_carr_rev [13]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1237.1 Detailed Description

This structure used to store unpack_dms_GetFirmwareInfo parameters

Parameters

modelid_str	- Mode ID String. • NULL-terminated Mode ID String. • Bit to check in ParamPresenceMask - **16**
bootversion_str	- Boot Version. • NULL-terminated Boot Version String. • Bit to check in ParamPresenceMask - **17**
appversion_str	- Application Version String. • NULL-terminated Application Version String. • Bit to check in ParamPresenceMask - **18**
sku_str	- SKU String. • NULL-terminated SKU String. • Bit to check in ParamPresenceMask - **19**
packageid_str	- Package ID String. • NULL-terminated Package ID String. • deprecated on EM/MC74xx(9x30) devices • Bit to check in ParamPresenceMask - **20**
carrier_str	- Carrier String. • NULL-terminated Carrier String. • Bit to check in ParamPresenceMask - **21**
priversion_str	- PRI Version String. • NULL-terminated PRI Version String. • Bit to check in ParamPresenceMask - **22**
cur_carr_name	- Current Carrier Name String. • NULL-terminated Current Carrier Name String. • Bit to check in ParamPresenceMask - **23**
cur_carr_rev	- Current Carrier Revision String. • NULL-terminated Current Carrier Revision String. • Bit to check in ParamPresenceMask - **24**
Tlvresult	- unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1237.2 Field Documentation

8.1237.2.1 char unpack_dms_GetFirmwareInfo_t::appversion_str[85]

8.1237.2.2 char unpack_dms_GetFirmwareInfo_t::bootversion_str[85]

8.1237.2.3 char unpack_dms_GetFirmwareInfo_t::carrier_str[20]

8.1237.2.4 char unpack_dms_GetFirmwareInfo_t::cur_carr_name[17]

8.1237.2.5 char unpack_dms_GetFirmwareInfo_t::cur_carr_rev[13]

8.1237.2.6 char unpack_dms_GetFirmwareInfo_t::modelid_str[20]

8.1237.2.7 char unpack_dms_GetFirmwareInfo_t::packageid_str[85]

8.1237.2.8 swi_uint256_t unpack_dms_GetFirmwareInfo_t::ParamPresenceMask

8.1237.2.9 char unpack_dms_GetFirmwareInfo_t::priversion_str[16]

8.1237.2.10 char unpack_dms_GetFirmwareInfo_t::sku_str[15]

8.1237.2.11 uint16_t unpack_dms_GetFirmwareInfo_t::Tlvresult

8.1238 unpack_dms_GetFirmwareRevision_t Struct Reference

Data Fields

- uint8_t amssSize
- char AMSSString [255]
- char PRIString [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1238.1 Detailed Description

This structure used to store unpack_dms_GetFirmwareRevision parameters

Parameters

amssSize	• Maximum number of characters (including NULL terminator) that the AMSS string array can contain. • Bit to check in ParamPresenceMask - **1**
AMSSString	• NULL-terminated AMSS revision string. • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **1**
PRIString[OUT]	• NULL-terminated PRI revision string. • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **17**
Tlvresult	• unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1238.2 Field Documentation

8.1238.2.1 uint8_t unpack_dms_GetFirmwareRevision_t::amssSize

8.1238.2.2 char unpack_dms_GetFirmwareRevision_t::AMSSString[255]

8.1238.2.3 swi_uint256_t unpack_dms_GetFirmwareRevision_t::ParamPresenceMask

8.1238.2.4 char unpack_dms_GetFirmwareRevision_t::PRIString[255]

8.1238.2.5 uint16_t unpack_dms_GetFirmwareRevision_t::Tlvresult

8.1239 unpack_dms_GetFirmwareRevisions_t Struct Reference

Data Fields

- uint8_t amssSize
- char AMSSString [255]
- uint8_t bootSize
- char BootString [255]
- uint8_t priSize
- char PRIString [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1239.1 Detailed Description

This structure used to store unpack_dms_GetFirmwareRevisions parameters

Parameters

amssSize	• Maximum number of characters (including NULL terminator) that the AMSS string array can contain • Bit to check in ParamPresenceMask - **1**
AMSSString	• NULL-terminated AMSS revision string • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **1**
bootSize	• Maximum number of characters (including NULL terminator) that the boot string array can contain • Bit to check in ParamPresenceMask - **16**
BootString	• NULL-terminated boot code revision string • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **16**
priSize	• Maximum number of characters (including NULL terminator) that the PRI string array can contain • Bit to check in ParamPresenceMask - **17**

PRIString	• NULL-terminated PRI revision string • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **17**
Tlvresult	• unpack Tlv Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1239.2 Field Documentation

8.1239.2.1 uint8_t unpack_dms_GetFirmwareRevisions_t::amssSize

8.1239.2.2 char unpack_dms_GetFirmwareRevisions_t::AMSSString[255]

8.1239.2.3 uint8_t unpack_dms_GetFirmwareRevisions_t::bootSize

8.1239.2.4 char unpack_dms_GetFirmwareRevisions_t::BootString[255]

8.1239.2.5 swi_uint256_t unpack_dms_GetFirmwareRevisions_t::ParamPresenceMask

8.1239.2.6 uint8_t unpack_dms_GetFirmwareRevisions_t::priSize

8.1239.2.7 char unpack_dms_GetFirmwareRevisions_t::PRIString[255]

8.1239.2.8 uint16_t unpack_dms_GetFirmwareRevisions_t::Tlvresult

8.1240 unpack_dms_GetFSN_t Struct Reference

Data Fields

- char String [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1240.1 Detailed Description

This structure used to store Factory Sequence Number parameter

Parameters

String	• Facorty Sequence Number • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack Result

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1240.2 Field Documentation

8.1240.2.1 swi_uint256_t unpack_dms_GetFSN_t::ParamPresenceMask

8.1240.2.2 char unpack_dms_GetFSN_t::String[255]

8.1240.2.3 uint16_t unpack_dms_GetFSN_t::Tlvresult

8.1241 unpack_dms_GetHardwareRevision_t Struct Reference

Data Fields

- char hwVer [255]
- swi_uint256_t ParamPresenceMask

8.1241.1 Detailed Description

This structure used to store unpack_dms_GetHardwareRevision parameters

Parameters

hwVer	- Hardware version • NULL-terminated string • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1241.2 Field Documentation

8.1241.2.1 char unpack_dms_GetHardwareRevision_t::hwVer[255]

8.1241.2.2 swi_uint256_t unpack_dms_GetHardwareRevision_t::ParamPresenceMask

8.1242 unpack_dms_GetIMSI_t Struct Reference

Data Fields

- char imsi [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1242.1 Detailed Description

This structure used to store unpack_dms_GetIMSI parameters

Parameters

imsi	- IMSI no. • NULL-terminated String. • Bit to check in ParamPresenceMask - **1**
Tlvresult	- unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1242.2 Field Documentation

8.1242.2.1 char unpack_dms_GetIMSI_t::imsi[255]

8.1242.2.2 swi_uint256_t unpack_dms_GetIMSI_t::ParamPresenceMask

8.1242.2.3 uint16_t unpack_dms_GetIMSI_t::Tlvresult

8.1243 unpack_dms_GetManufacturer_t Struct Reference

Data Fields

- char manufacturer [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1243.1 Detailed Description

This structure is used to store device manufacturer information.

Parameters

manufacturer[OUT]	• NULL terminated string • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1243.2 Field Documentation

8.1243.2.1 char unpack_dms_GetManufacturer_t::manufacturer[255]

8.1243.2.2 swi_uint256_t unpack_dms_GetManufacturer_t::ParamPresenceMask

8.1243.2.3 uint16_t unpack_dms_GetManufacturer_t::Tlvresult

8.1244 unpack_dms_GetModelID_t Struct Reference

Data Fields

- char modelid [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1244.1 Detailed Description

This structure used to store unpack_dms_GetModelID parameters

Parameters

modelid	- Device model id. • NULL-terminated String. • Bit to check in ParamPresenceMask - **1**
Tlvresult	- unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1244.2 Field Documentation

8.1244.2.1 char unpack_dms_GetModelID_t::modelid[255]

8.1244.2.2 swi_uint256_t unpack_dms_GetModelID_t::ParamPresenceMask

8.1244.2.3 uint16_t unpack_dms_GetModelID_t::Tlvresult

8.1245 unpack_dms_GetNetworkTime_t Struct Reference

Data Fields

- uint16_t source
- uint64_t timestamp
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1245.1 Detailed Description

This structure used to store unpack_dms_GetNetworkTime parameters

Parameters

source	• Source of timestamp 0 - 32 kHz device clock 1 - CDMA network 2 - cdma2000 1xEV-DO network • Bit to check in ParamPresenceMask - **1**

timestamp	• Count of 1.25 ms that have elapsed from the start of GPS time (Jan 6, 1980) • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

The source of the timestamp provided specifies how the timestamp was determined. The first network time that is available will be returned. If no network time is available, the timestamp is taken from the 32 kHz slow-clock of the device.

8.1245.2 Field Documentation

8.1245.2.1 swi_uint256_t unpack_dms_GetNetworkTime_t::ParamPresenceMask

8.1245.2.2 uint16_t unpack_dms_GetNetworkTime_t::source

8.1245.2.3 uint64_t unpack_dms_GetNetworkTime_t::timestamp

8.1245.2.4 uint16_t unpack_dms_GetNetworkTime_t::Tlvresult

8.1246 unpack_dms_GetOfflineReason_t Struct Reference

Data Fields

- uint32_t ∗ pReasonMask
- uint32_t ∗ pbPlatform
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1246.1 Detailed Description

This structure is used to store reason why the operating mode of the device is currently offline.

Parameters

pReasonMask[-OUT]	• Optional parameter • Bitmask of offline reasons – 0x00000001 - Host image configuration issue – 0x00000002 - PRI image configuration issue – 0x00000004 - PRI version incompatible – 0x00000008 - PRI copy issue – All others - Reserved • Bit to check in ParamPresenceMask - **16**

pbPlatform[OUT]	• Optional parameter • Is the device offline due to a platform restriction? – 0 - No – 1 - Yes • Bit to check in ParamPresenceMask - **17**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1246.2 Field Documentation

8.1246.2.1 swi_uint256_t unpack_dms_GetOfflineReason_t::ParamPresenceMask

8.1246.2.2 uint32_t∗ unpack_dms_GetOfflineReason_t::pbPlatform

8.1246.2.3 uint32_t∗ unpack_dms_GetOfflineReason_t::pReasonMask

8.1246.2.4 uint16_t unpack_dms_GetOfflineReason_t::Tlvresult

8.1247 unpack_dms_GetPower_t Struct Reference

Data Fields

- uint32_t OperationMode
- uint32_t OfflineReason
- uint32_t HardwareControlledMode
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1247.1 Detailed Description

This structure used to store unpack_dms_GetPower parameters

Parameters

OperationMode	- operating mode. • 0 - Online (default). • 1 - Low power (airplane) mode. • 2 - Factory test mode. • 3 - Offline. • 4 - Resetting. • 5 - Power off. • 6 - Persistent low power (airplane) mode. • 7 - Mode - only low power. • Bit to check in ParamPresenceMask - **1**

Note

Valid transitions for Power Modes

- Online to Low Power, Persistent low power, Factory test, Offline or Shut Down
- Low power to online, Persistent low power, Offline, or Shut Down
- Persistent low power to Online, Low power, Offline or Shut down
- Factory test to online
- Offline to Reset

Parameters

OfflineReason	- offline reason. • 0x0001 - Host image misconfiguration. • 0x0002 - PRI image misconfiguration. • 0x0004 - PRI version incompatible. • 0x0008 - Device memory is full,cannot copy PRI information. • Bit to check in ParamPresenceMask - **16**
HardwareControlledMode	- hardware restricted mode. • 0x00 - FALSE. • 0x01 - TRUE. • Bit to check in ParamPresenceMask - **17**
Tlvresult	- unpack Tlv Result.
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1247.2 Field Documentation

8.1247.2.1 uint32_t unpack_dms_GetPower_t::HardwareControlledMode

8.1247.2.2 uint32_t unpack_dms_GetPower_t::OfflineReason

8.1247.2.3 uint32_t unpack_dms_GetPower_t::OperationMode

8.1247.2.4 swi_uint256_t unpack_dms_GetPower_t::ParamPresenceMask

8.1247.2.5 uint16_t unpack_dms_GetPower_t::Tlvresult

8.1248 unpack_dms_GetPRLVersion_t Struct Reference

Data Fields

- uint8_t u8PRLPreference
- uint16_t u16PRLVersion
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1248.1 Detailed Description

This structure used to store unpack_dms_GetPRLVersion parameters

Parameters

u8PRL-Preference	• PRL Preference – 0 - Unset – 1 - Set • Bit to check in ParamPresenceMask - **17**
u16PRLVersion	• PRL version of device. • Bit to check in ParamPresenceMask - **16**
Tlvresult	• unpack Tlv Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1248.2 Field Documentation

8.1248.2.1 swi_uint256_t unpack_dms_GetPRLVersion_t::ParamPresenceMask

8.1248.2.2 uint16_t unpack_dms_GetPRLVersion_t::Tlvresult

8.1248.2.3 uint16_t unpack_dms_GetPRLVersion_t::u16PRLVersion

8.1248.2.4 uint8_t unpack_dms_GetPRLVersion_t::u8PRLPreference

8.1249 unpack_dms_GetSerialNumbers_t Struct Reference

Data Fields

- char esn [255]
- char imei_no [255]
- char meid [255]
- char imeisv_svn [255]
- swi_uint256_t ParamPresenceMask

8.1249.1 Detailed Description

This structure used to store unpack_dms_GetSerialNumbers parameters

Parameters

esn	- Electronic Serial Number of the device. • NULL-terminated ESN string. Empty string is returned when ESN is not supported/programmed. • Bit to check in ParamPresenceMask - **16**
imei_no	- International Mobile Equipment Identity of the device. • NULL terminated IMEI string. Empty string is returned when IMEI is not supported/programmed. • Bit to check in ParamPresenceMask - **17**

meid	- Mobile Equipment Identifier of the device. • NULL-terminated MEID string. Empty string is returned when MEID is not supported/programmed. • Bit to check in ParamPresenceMask - **18**
imeisv_svn	- NULL-terminated IMEI SVN string. Empty string is returned when IMEI SVN is not supported/programmed.imei software version revision. • Bit to check in ParamPresenceMask - **19**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1249.2 Field Documentation

8.1249.2.1 char unpack_dms_GetSerialNumbers_t::esn[255]

8.1249.2.2 char unpack_dms_GetSerialNumbers_t::imei_no[255]

8.1249.2.3 char unpack_dms_GetSerialNumbers_t::imeisv_svn[255]

8.1249.2.4 char unpack_dms_GetSerialNumbers_t::meid[255]

8.1249.2.5 swi_uint256_t unpack_dms_GetSerialNumbers_t::ParamPresenceMask

8.1250 unpack_dms_GetUSBComp_t Struct Reference

Data Fields

- uint8_t USBComp
- uint8_t NumSupUSBComps
- uint8_t SupUSBComps [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1250.1 Detailed Description

This structure is used to store retrieved USB Composition

Parameters

USBComp	• Current USB Composition(optional parameter) • Values: – 0..5 - Reserved (non-QMI) – 6 - DM NMEA AT QMI – 7 - DM NMEA AT QMI1 QMI2 QMI3 – 8 - DM NMEA AT MBIM – 9 - MBIM – 10 - NMEA MBIM – 11 - DM MBIM – 12 - DM NMEA MBIM 13-22 are combined compositions. One is for Win8 MBIM interfaces, another is for legacy QMI interfaces – 13 - 6 for QMI, 8 for MBIM – 14 - 6 for QMI, 9 for MBIM – 15 - 6 for QMI, 10 for MBIM – 16 - 6 for QMI, 11 for MBIM – 17 - 6 for QMI, 12 for MBIM – 18 - 7 for QMI, 8 for MBIM – 19 - 7 for QMI, 9 for MBIM – 20 - 7 for QMI, 10 for MBIM – 21 - 7 for QMI, 11 for MBIM – 22 - 7 for QMI, 12 for MBIM • Bit to check in ParamPresenceMask - **16**
NumSupUSB-Comps	• Number of supported USB compositions in the parameter to follow • Range - 0-255 • Bit to check in ParamPresenceMask - **17**

SupUSBComps	• Optional parameter • List of supported USB compositions(1 Byte each - Max 255) • Total length is defined by pNumSupUSBComps parameter • Values: – 0..5 - Reserved (non-QMI) – 6 - DM NMEA AT QMI – 7 - DM NMEA AT QMI1 QMI2 QMI3 – 8 - DM NMEA AT MBIM – 9 - MBIM – 10 - NMEA MBIM – 11 - DM MBIM – 12 - DM NMEA MBIM 13-22 are combined compositions. One is for Win8 MBIM interfaces, another is for legacy QMI interfaces – 13 - 6 for QMI, 8 for MBIM – 14 - 6 for QMI, 9 for MBIM – 15 - 6 for QMI, 10 for MBIM – 16 - 6 for QMI, 11 for MBIM – 17 - 6 for QMI, 12 for MBIM – 18 - 7 for QMI, 8 for MBIM – 19 - 7 for QMI, 9 for MBIM – 20 - 7 for QMI, 10 for MBIM – 21 - 7 for QMI, 11 for MBIM – 22 - 7 for QMI, 12 for MBIM • Bit to check in ParamPresenceMask - **17**
Tlvresult	• unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1250.2 Field Documentation

8.1250.2.1 uint8_t unpack_dms_GetUSBComp_t::NumSupUSBComps

8.1250.2.2 swi_uint256_t unpack_dms_GetUSBComp_t::ParamPresenceMask

8.1250.2.3 uint8_t unpack_dms_GetUSBComp_t::SupUSBComps[255]

8.1250.2.4 uint16_t unpack_dms_GetUSBComp_t::Tlvresult

8.1250.2.5 uint8_t unpack_dms_GetUSBComp_t::USBComp

8.1251 unpack_dms_GetVoiceNumber_t Struct Reference

Data Fields

- uint8_t voiceNumberSize

- char VoiceNumber [255]
- uint8_t minSize
- char MIN [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1251.1 Detailed Description

Structure to store the voice number in use by the device

Parameters

voiceNumber-Size	• Maximum number of characters (including NULL terminator) that the voice number array can contain. • Bit to check in ParamPresenceMask - **1**
VoiceNumber	• Voice number string: MDN or MS ISDN • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **1**
minSize	• Maximum number of characters (including NULL terminator) that the MIN array can contain. • Bit to check in ParamPresenceMask - **16**
MIN	• Optional Parameter • MIN string: Empty string returned when MIN is not supported/ programmed. • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **16**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1251.2 Field Documentation

8.1251.2.1 char unpack_dms_GetVoiceNumber_t::MIN[255]

8.1251.2.2 uint8_t unpack_dms_GetVoiceNumber_t::minSize

8.1251.2.3 swi_uint256_t unpack_dms_GetVoiceNumber_t::ParamPresenceMask

8.1251.2.4 uint16_t unpack_dms_GetVoiceNumber_t::Tlvresult

8.1251.2.5 char unpack_dms_GetVoiceNumber_t::VoiceNumber[255]

8.1251.2.6 uint8_t unpack_dms_GetVoiceNumber_t::voiceNumberSize

8.1252 unpack_dms_PSMCfgChange_ind_t Struct Reference

Data Fields

- dms_PSMEnableStateIndTlv EnableState
- dms_PSMActiveTimerIndTlv ActiveTimer
- dms_PSMPeriodicUpdateTimerIndTlv PeriodicUpdateTimer
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1252.1 Detailed Description

DMS Event Report indication structure

Parameters

EnableState	• See dms_PSMEnableStateIndTlv • Bit to check in ParamPresenceMask - **16**
ActiveTimer	• See dms_PSMActiveTimerIndTlv • Bit to check in ParamPresenceMask - **17**
PeriodicUpdate-Timer	• See dms_PSMPeriodicUpdateTimerIndTlv • Bit to check in ParamPresenceMask - **18**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1252.2 Field Documentation

8.1252.2.1 dms_PSMActiveTimerIndTlv unpack_dms_PSMCfgChange_ind_t::ActiveTimer

8.1252.2.2 dms_PSMEnableStateIndTlv unpack_dms_PSMCfgChange_ind_t::EnableState

8.1252.2.3 swi_uint256_t unpack_dms_PSMCfgChange_ind_t::ParamPresenceMask

8.1252.2.4 dms_PSMPeriodicUpdateTimerIndTlv unpack_dms_PSMCfgChange_ind_t::PeriodicUpdateTimer

8.1252.2.5 uint16_t unpack_dms_PSMCfgChange_ind_t::Tlvresult

8.1253 unpack_dms_ResetToFactoryDefaults_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1253.1 Detailed Description

This structure contains reset to factory default unpack

Parameters

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1253.2 Field Documentation

8.1253.2.1 swi_uint256_t unpack_dms_ResetToFactoryDefaults_t::ParamPresenceMask

8.1253.2.2 uint16_t unpack_dms_ResetToFactoryDefaults_t::Tlvresult

8.1254 unpack_dms_SetActivationStatusCallback_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1254.1 Detailed Description

This structure is used to store Set Service Activation Status callback parameter unpack.

Parameters

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1254.2 Field Documentation

8.1254.2.1 swi_uint256_t unpack_dms_SetActivationStatusCallback_t::ParamPresenceMask

8.1254.2.2 uint16_t unpack_dms_SetActivationStatusCallback_t::Tlvresult

8.1255 unpack_dms_SetCrashAction_t Struct Reference

Data Fields

- uint8_t notused
- swi_uint256_t ParamPresenceMask

8.1255.1 Detailed Description

This structure is used to store unpack_dms_SetCrashAction parameters

Parameters

notused	• unpack Tlv result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1255.2 Field Documentation

8.1255.2.1 uint8_t unpack_dms_SetCrashAction_t::notused

8.1255.2.2 swi_uint256_t unpack_dms_SetCrashAction_t::ParamPresenceMask

8.1256 unpack_dms_SetCustFeature_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1256.1 Detailed Description

This structure is used to store unpack_dms_SetCustFeature parameters

Parameters

Tlvresult	• unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1256.2 Field Documentation

8.1256.2.1 swi_uint256_t unpack_dms_SetCustFeature_t::ParamPresenceMask

8.1256.2.2 uint16_t unpack_dms_SetCustFeature_t::Tlvresult

8.1257 unpack_dms_SetCustFeaturesV2_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1257.1 Detailed Description

This structure contains customization settings set to modem unpack

Parameters

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1257.2 Field Documentation

8.1257.2.1 swi_uint256_t unpack_dms_SetCustFeaturesV2_t::ParamPresenceMask

8.1257.2.2 uint16_t unpack_dms_SetCustFeaturesV2_t::Tlvresult

8.1258 unpack_dms_SetEventReport_ind_t Struct Reference

Data Fields

- dms_ActivationStatusTlv ActivationStatusTlv
- dms_OperatingModeTlv OperatingModeTlv
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1258.1 Detailed Description

DMS Event Report indication structure

Parameters

ActivationStatus-Tlv	• See dms_ActivationStatusTlv • Bit to check in ParamPresenceMask - **19**
OperatingMode-Tlv	• See dms_OperatingModeTlv • Bit to check in ParamPresenceMask - **20**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1258.2 Field Documentation

8.1258.2.1 dms_ActivationStatusTlv unpack_dms_SetEventReport_ind_t::ActivationStatusTlv

8.1258.2.2 dms_OperatingModeTlv unpack_dms_SetEventReport_ind_t::OperatingModeTlv

8.1258.2.3 swi_uint256_t unpack_dms_SetEventReport_ind_t::ParamPresenceMask

8.1258.2.4 uint16_t unpack_dms_SetEventReport_ind_t::Tlvresult

8.1259 unpack_dms_SetEventReport_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1259.1 Detailed Description

This structure is used to store unpack_dms_SetEventReport parameters.

Parameters

Tlvresult	• unpack Tlv result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1259.2 Field Documentation

8.1259.2.1 swi_uint256_t unpack_dms_SetEventReport_t::ParamPresenceMask

8.1259.2.2 uint16_t unpack_dms_SetEventReport_t::Tlvresult

8.1260 unpack_dms_SetFirmwarePreference_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1260.1 Detailed Description

This structure is used to store unpack_dms_SetFirmwarePreference parameters

Parameters

Tlvresult	• unpack Tlv result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1260.2 Field Documentation

8.1260.2.1 swi_uint256_t unpack_dms_SetFirmwarePreference_t::ParamPresenceMask

8.1260.2.2 uint16_t unpack_dms_SetFirmwarePreference_t::Tlvresult

8.1261 unpack_dms_SetIndicationRegister_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1261.1 Detailed Description

This structure is used to store unpack_dms_SetIndicationRegister parameters.

Parameters

Tlvresult	• unpack Tlv result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1261.2 Field Documentation

8.1261.2.1 swi_uint256_t unpack_dms_SetIndicationRegister_t::ParamPresenceMask

8.1261.2.2 uint16_t unpack_dms_SetIndicationRegister_t::Tlvresult

8.1262 unpack_dms_SetPower_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1262.1 Detailed Description

Structure to store unpack the operating mode of the device.

Parameters

Tlvresult	• unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1262.2 Field Documentation

8.1262.2.1 swi_uint256_t unpack_dms_SetPower_t::ParamPresenceMask

8.1262.2.2 uint16_t unpack_dms_SetPower_t::Tlvresult

8.1263 unpack_dms_SetUSBComp_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1263.1 Detailed Description

This structure is used to store unpack USB composition information

Parameters

Tlvresult	• unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1263.2 Field Documentation

8.1263.2.1 swi_uint256_t unpack_dms_SetUSBComp_t::ParamPresenceMask

8.1263.2.2 uint16_t unpack_dms_SetUSBComp_t::Tlvresult

8.1264 unpack_dms_SLQSDmsSwiGetPCInfo_t Struct Reference

Data Fields

- uint8_t opMode
- int has_LpmFlag
- uint32_t LpmFlag
- int has_Wdisable
- uint8_t Wdisable
- int has_PowerOffMode
- uint8_t PowerOffMode
- int has_PersistentLpm
- uint8_t PersistentLpm
- swi_uint256_t ParamPresenceMask

8.1264.1 Detailed Description

This structure contains the TLV required to Get device power control status information.

Parameters

opMode	• Selected operating mode. • Values – 0 - Online – 1 - Low power – 2 - Factory Test mode – 3 - Offline – 4 - Resetting – 5 - Shutting down – 6 - Persistent low power – 8 - Conducting network test for GSM/WCDMA • Bit to check in ParamPresenceMask - **1**
has_LpmFlag	LPM Flag Availability. • 0 : Unavailable. • 1 : Available.

- Bit to check in ParamPresenceMask - **16**

Parameters

LpmFlag[-Optional]	• LPM Force Flags • Bitmask – bit0 - Tracks the state of W_DISABLE TLV, indicating state of the W_DISABLE switch. – bit1 - Set if LPM is requested by a host request, such as AT command, QMI or MBIM request. Cleared by a host request to return to online mode. Also set when the device is cold or warm booted in persistent LPM. – bit2 - Set when the device temperature is outside the valid operating range. Cleared if the temperature returns to the normal range. – bit3 - Set when the device voltage is outside the valid operating range. Cleared if the voltage returns to the normal range. – bit4 - Set on power up when BIOS locking is enabled. Cleared when the host has disabled the BIOS lock. – bit5 - Set if the current device configuration does not match the GOBI image preference. – bit6-31 - Additional LPM causes may be added to future products. • Bit to check in ParamPresenceMask - **16**
has_Wdisable	W-Disable Availability. • 0 : Unavailable. • 1 : Available.

- Bit to check in ParamPresenceMask - **17**

Parameters

Wdisable[-Optional]	• W_DISABLE • Values – 0 - Switch set to ON position – 1 - Switch set to OFF position • Bit to check in ParamPresenceMask - **17**
has_PowerOff-Mode	Power off mode Availability. • 0 : Unavailable. • 1 : Available.

- Bit to check in ParamPresenceMask - **18**

Parameters

PowerOffMode[-Optional]	• Power-off Mode • Action taken when W_DISABLE is switched to the OFF position – 0 - LPM – 1 - Shutdown – 2 - Ignore • Bit to check in ParamPresenceMask - **18**
has_Persistent-Lpm	Persistent LPM Availability. • 0 : Unavailable. • 1 : Available.

- Bit to check in ParamPresenceMask - **19**

Parameters

PersistentLpm[-Optional]	• LPM Persistence • Values – 0 - Non-persistent LPM – 1 - Persistent LPM • Bit to check in ParamPresenceMask - **19**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1264.2 Field Documentation

8.1264.2.1 int unpack_dms_SLQSDmsSwiGetPCInfo_t::has_LpmFlag

8.1264.2.2 int unpack_dms_SLQSDmsSwiGetPCInfo_t::has_PersistentLpm

8.1264.2.3 int unpack_dms_SLQSDmsSwiGetPCInfo_t::has_PowerOffMode

8.1264.2.4 int unpack_dms_SLQSDmsSwiGetPCInfo_t::has_Wdisable

8.1264.2.5 uint32_t unpack_dms_SLQSDmsSwiGetPCInfo_t::LpmFlag

8.1264.2.6 uint8_t unpack_dms_SLQSDmsSwiGetPCInfo_t::opMode

8.1264.2.7 swi_uint256_t unpack_dms_SLQSDmsSwiGetPCInfo_t::ParamPresenceMask

8.1264.2.8 uint8_t unpack_dms_SLQSDmsSwiGetPCInfo_t::PersistentLpm

8.1264.2.9 uint8_t unpack_dms_SLQSDmsSwiGetPCInfo_t::PowerOffMode

8.1264.2.10 uint8_t unpack_dms_SLQSDmsSwiGetPCInfo_t::Wdisable

8.1265 unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t Struct Reference

Data Fields

- uint8_t type
- uint8_t source
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1265.1 Detailed Description

This structure contains the TLV required to Get Reset Info.

Parameters

type[OUT]	• type of reset or power down, possible values listed below: – 0 - unknown – 1 - warm – 2 - hard – 3 - crash – 4 - power down • Bit to check in ParamPresenceMask - **1**
source[OUT]	• entity which initiated the reset or power down, possible values listed below: – 0 - unknown – 1 - user requested (AT!RESET, AT!BOOTHOLD, FW/PRI download - including host-initiated image switching) – 2 - hardware switch (W_DISABLE) – 3 - temperature critical – 4 - voltage critical – 5 - configuration update (SIM-based image switching, RMA reset, NVUPs which request a reset) – 6 - LWM2M (Light Weight M2M client (internal process for LWM2M)) – 7 - OMA-DM – 8 - FOTA

- Bit to check in ParamPresenceMask - **1**

Parameters

Tlvresult[OUT]	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1265.2 Field Documentation

8.1265.2.1 swi_uint256_t unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t::ParamPresenceMask

8.1265.2.2 uint8_t unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t::source

8.1265.2.3 uint16_t unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t::Tlvresult

8.1265.2.4 uint8_t unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t::type

8.1266 unpack_dms_SLQSDmsSwiGetResetInfo_t Struct Reference

Data Fields

- uint8_t type
- uint8_t source
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1266.1 Detailed Description

This structure contains the TLV required to Get Reset Info.

Parameters

type[OUT]	• type of reset or power down, possible values listed below: – 0 - unknown – 1 - warm – 2 - hard – 3 - crash – 4 - power down • Bit to check in ParamPresenceMask - **1**

source[OUT]	• entity which initiated the reset or power down, possible values listed below: – 0 - unknown – 1 - user requested (AT!RESET, AT!BOOTHOLD, FW/PRI download - including host-initiated image switching) – 2 - hardware switch (W_DISABLE) – 3 - temperature critical – 4 - voltage critical – 5 - configuration update (SIM-based image switching, RMA reset, NVUPs which request a reset) – 6 - LWM2M (Light Weight M2M client (internal process for LWM2M)) – 7 - OMA-DM – 8 - FOTA

- Bit to check in ParamPresenceMask - **1**

Parameters

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1266.2 Field Documentation

8.1266.2.1 swi_uint256_t unpack_dms_SLQSDmsSwiGetResetInfo_t::ParamPresenceMask

8.1266.2.2 uint8_t unpack_dms_SLQSDmsSwiGetResetInfo_t::source

8.1266.2.3 uint16_t unpack_dms_SLQSDmsSwiGetResetInfo_t::Tlvresult

8.1266.2.4 uint8_t unpack_dms_SLQSDmsSwiGetResetInfo_t::type

8.1267 unpack_dms_SLQSDmsSwiGetUimSelection_t Struct Reference

Data Fields

- uint8_t uimSelect
- dms_UimAutoSwitchActSlotTlv * pUimAutoSwitchActSlot
- swi_uint256_t ParamPresenceMask

8.1267.1 Detailed Description

Structure contains the TLV required to Get currently selected active UIM slot.

Parameters

uimSelect	• Active selected UIM slot • Values – 0 - slot 1 (e.g. external SIM) – 1 - slot 2 (e.g. embedded SIM) – 2 - remote SIM (if supported) – 3 - SIM auto-switch activated

- Bit to check in ParamPresenceMask - **1**

Parameters

pUimAuto-SwitchActSlot	• UIM Auto Switch Active slot • see dms_UimAutoSwitchActSlotTlv for more information • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

: None

8.1267.2 Field Documentation

8.1267.2.1 swi_uint256_t unpack_dms_SLQSDmsSwiGetUimSelection_t::ParamPresenceMask

8.1267.2.2 dms_UimAutoSwitchActSlotTlv* unpack_dms_SLQSDmsSwiGetUimSelection_t::pUimAutoSwitchActSlot

8.1267.2.3 uint8_t unpack_dms_SLQSDmsSwiGetUimSelection_t::uimSelect

8.1268 unpack_dms_SLQSDmsSwiIndicationRegister_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1268.1 Detailed Description

This structure contains set registration state for different indication unpack

Parameters

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1268.2 Field Documentation

8.1268.2.1 swi_uint256_t unpack_dms_SLQSDmsSwiIndicationRegister_t::ParamPresenceMask

8.1268.2.2 uint16_t unpack_dms_SLQSDmsSwiIndicationRegister_t::Tlvresult

8.1269 unpack_dms_SLQSGetBandCapability_t Struct Reference

Data Fields

- uint64_t bandCapability
- int is_LteBandCapability_Available
- uint64_t LteBandCapability
- int is_TdsBandCapability_Available
- uint64_t TdsBandCapability
- swi_uint256_t ParamPresenceMask

8.1269.1 Detailed Description

This structure contains the Band Capabilities response.

Please check is_<Param_Name>_Available field for presence of optional parameters

Parameters

bandCapability[-OUT]	Bitmask of bands supported by the device • Bit 0 - Band class 0, A-system • Bit 1 - Band class 0, B-system • Bit 2 - Band class 1, all blocks • Bit 3 - Band class 2 • Bit 4 - Band class 3, A-system • Bit 5 - Band class 4, all blocks • Bit 6 - Band class 5, all blocks • Bit 7 - GSM DCS band (1800) • Bit 8 - GSM Extended GSM (E-GSM) band (900) • Bit 9 - GSM Primary GSM (P-GSM) band (900) • Bit 10 - Band class 6 • Bit 11 - Band class 7 • Bit 12 - Band class 8 • Bit 13 - Band class 9 • Bit 14 - Band class 10 • Bit 15 - Band class 11 • Bit 16 - GSM 450 band • Bit 17 - GSM 480 band • Bit 18 - GSM 750 band • Bit 19 - GSM 850 band • Bit 20 - GSM railways GSM band (900) • Bit 21 - GSM PCS band (1900) • Bit 22 - WCDMA (Europe, Japan, and China) 2100 band • Bit 23 - WCDMA US PCS 1900 band • Bit 24 - WCDMA (Europe and China) DCS 1800 band • Bit 25 - WCDMA US 1700 band • Bit 26 - WCDMA US 850 band • Bit 27 - WCDMA Japan 800 band • Bit 28 - Band class 12 • Bit 29 - Band class 14 • Bit 30 - Reserved • Bit 31 - Band class 15 • Bits 32 through 47 - Reserved • Bit 48 - WCDMA Europe 2600 band • Bit 49 - WCDMA Europe and Japan 900 band • Bit 50 - WCDMA Japan 1700 band • Bits 51 through 55 - Reserved • Bit 56 - Band class 16 • Bit 57 - Band class 17 • Bit 58 - Band class 18 • Bit 59 - Band class 19 • Bit 60 - WCDMA Japan 850 band • Bit 61 - WCDMA 1500 band • Bits 62 and 63 - Reserved • Bit to check in ParamPresenceMask - **1**

is_LteBand-Capability_-Available[OUT]	LTE Band Capabilities Availability. • 0 : Unavailable. • 1 : Available. • Bit to check in ParamPresenceMask - **16**

LteBand-Capability[OUT]	Bitmask of LTE bands supported by the device • Bit 0 - LTE EUTRAN Band 1 UL:1920-1980; DL: 2110-2170 • Bit 1 - LTE EUTRAN Band 2 UL:1850-1910; DL: 1930-1990 • Bit 2 - LTE EUTRAN Band 3 UL:1710-1785; DL: 1805-1880 • Bit 3 - LTE EUTRAN Band 4 UL:1710-1755; DL: 2110-2155 • Bit 4 - LTE EUTRAN Band 5 UL: 824-849; DL: 869-894 • Bit 5 - LTE EUTRAN Band 6 UL: 830-840; DL: 875-885 • Bit 6 - LTE EUTRAN Band 7 UL:2500-2570; DL: 2620-2690 • Bit 7 - LTE EUTRAN Band 8 UL: 880-915; DL: 925-960 • Bit 8 - LTE EUTRAN Band 9 UL:1749.9-1784.9; DL: 1844.9-1879.9 • Bit 9 - LTE EUTRAN Band 10 UL:1710-1770; DL: 2110-2170 • Bit 10 - LTE EUTRAN Band 11 UL:1427.9-1452.9; DL: 1475.9-1500.9 • Bit 11 - LTE EUTRAN Band 12 UL:698-716; DL: 728-746 • Bit 12 - LTE EUTRAN Band 13 UL: 777-787; DL: 746-756 • Bit 13 - LTE EUTRAN Band 14 UL: 788-798; DL: 758-768 • Bits 14 and 15 - Reserved • Bit 16 - LTE EUTRAN Band 17 UL: 704-716; DL: 734-746 • Bit 17 - LTE EUTRAN Band 18 UL: 815-830; DL: 860-875 • Bit 18 - LTE EUTRAN Band 19 UL: 830-845; DL: 875-890 • Bit 19 - LTE EUTRAN Band 20 UL: 832-862; DL: 791-821 • Bit 20 - LTE EUTRAN Band 21 UL: 1447.9-1462.9; DL: 1495.9-1510.9 • Bit 21 - Reserved • Bit 22 - LTE EUTRAN Band 23 UL: 2000-2020; DL: 2180-2200 • Bit 23 - LTE EUTRAN Band 24 UL: 1626.5-1660.5; DL: 1525-1559 • Bit 24 - LTE EUTRAN Band 25 UL: 1850-1915; DL: 1930-1995 • Bit 25 - LTE EUTRAN Band 26 UL: 814-849; DL: 859-894 • Bit 26 - Reserved • Bit 27 - LTE EUTRAN Band 28 UL: 703-748; DL: 758-803 • Bit 28 - LTE EUTRAN Band 29 UL: 1850-1910 or 1710-1755; DL: 716-728 • Bit 29 - LTE EUTRAN Band 30 UL: 2350-2360; DL: 2305-2315 • Bit 30 - Reserved • Bit 31 - LTE EUTRAN Band 32 DL: 9920-10359 • Bit 32 - LTE EUTRAN Band 33 UL: 1900-1920; DL: 1900-1920 • Bit 33 - LTE EUTRAN Band 34 UL: 2010-2025; DL: 2010-2025 • Bit 34 - LTE EUTRAN Band 35 UL: 1850-1910; DL: 1850-1910 • Bit 35 - LTE EUTRAN Band 36 UL: 1930-1990; DL: 1930-1990 • Bit 36 - LTE EUTRAN Band 37 UL: 1910-1930; DL: 1910-1930 • Bit 37 - LTE EUTRAN Band 38 UL: 2570-2620; DL: 2570-2620 • Bit 38 - LTE EUTRAN Band 39 UL: 1880-1920; DL: 1880-1920 • Bit 39 - LTE EUTRAN Band 40 UL: 2300-2400; DL: 2300-2400 • Bit 40 - LTE EUTRAN Band 41 UL: 2496-2690; DL: 2496-2690 • Bit 41 - LTE EUTRAN Band 42 UL: 3400-3600; DL: 3400-3600 • Bit 42 - LTE EUTRAN Band 43 UL: 3600-3800; DL: 3600-3800 • Bits 43 through 64 - Reserved • Bit to check in ParamPresenceMask - **16**

is_TdsBand-Capability_-Available[OUT]	TDS Band Capabilities Availability. • 0 : Unavailable. • 1 : Available. • Bit to check in ParamPresenceMask - **17**
TdsBand-Capability[OUT]	Bitmask of TDS bands supported by the device. • Bit 0 - TDS Band A 1900 to 1920 MHz, 2010 to 2020 MHz • Bit 1 - TDS Band B 1850 to 1910 MHz, 1930 to 1990 MHz • Bit 2 - TDS Band C 1910 to 1930 MHz • Bit 3 - TDS Band D 2570 to 2620 MHz • Bit 4 - TDS Band E 2300 to 2400 MHz • Bit 5 - TDS Band F 1880 to 1920 MHz • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1269.2 Field Documentation

8.1269.2.1 uint64_t unpack_dms_SLQSGetBandCapability_t::bandCapability

8.1269.2.2 int unpack_dms_SLQSGetBandCapability_t::is_LteBandCapability_Available

8.1269.2.3 int unpack_dms_SLQSGetBandCapability_t::is_TdsBandCapability_Available

8.1269.2.4 uint64_t unpack_dms_SLQSGetBandCapability_t::LteBandCapability

8.1269.2.5 swi_uint256_t unpack_dms_SLQSGetBandCapability_t::ParamPresenceMask

8.1269.2.6 uint64_t unpack_dms_SLQSGetBandCapability_t::TdsBandCapability

8.1270 unpack_dms_SLQSGetERIFile_t Struct Reference

Data Fields

- eriDataparams eriFile
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1270.1 Detailed Description

This structure contains Get ERI file unpack

Parameters

eriFile	• Pointer to structure ERIFileparams • See eriDataparams for more information • Bit to check in ParamPresenceMask - **1**

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1270.2 Field Documentation

8.1270.2.1 eriDataparams unpack_dms_SLQSGetERIFile_t::eriFile

8.1270.2.2 swi_uint256_t unpack_dms_SLQSGetERIFile_t::ParamPresenceMask

8.1270.2.3 uint16_t unpack_dms_SLQSGetERIFile_t::Tlvresult

8.1271 unpack_dms_SLQSGetPowerSaveModeConfig_t Struct Reference

Data Fields

- dms_PSMEnableStateTlv * pPsmEnableState
- dms_PSMDurationThresholdTlv * pDurationThreshold
- dms_PSMDurationDueToOOSTlv * pDurationDueToOOS
- dms_PSMRandomizationWindowTlv * pRandomizationWindow
- dms_PSMActiveTimerTlv * pActiveTimer
- dms_PSMPeriodicUpdateTimerTlv * pPeriodicUpdateTimer
- dms_PSMEarlyWakeupTimeTlv * pEarlyWakeupTime
- swi_uint256_t ParamPresenceMask

8.1271.1 Detailed Description

This structure contains the Power Save Mode (PSM) configuration parameter.

Parameters

pPsmEnable-State	[Optional] • See dms_PSMEnableStateTlv for more information • Bit to check in ParamPresenceMask - **16**
pDuration-Threshold	[Optional] • See dms_PSMDurationThresholdTlv for more information • Bit to check in ParamPresenceMask - **17**
pDurationDueTo-OOS	[Optional] • See dms_PSMDurationDueToOOSTlv for more information • Bit to check in ParamPresenceMask - **18**
pRandomization-Window	[Optional] • See dms_PSMRandomizationWindowTlv for more information • Bit to check in ParamPresenceMask - **19**

pActiveTimer	[Optional] • See dms_PSMActiveTimerTlv for more information • Bit to check in ParamPresenceMask - **20**
pPeriodic-UpdateTimer	[Optional] • See dms_PSMPeriodicUpdateTimerTlv for more information • Bit to check in ParamPresenceMask - **21**
pEarlyWakeup-Time	[Optional] • See dms_PSMEarlyWakeupTimeTlv for more information • Bit to check in ParamPresenceMask - **22**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1271.2 Field Documentation

8.1271.2.1 dms_PSMActiveTimerTlv* unpack_dms_SLQSGetPowerSaveModeConfig_t::pActiveTimer

8.1271.2.2 swi_uint256_t unpack_dms_SLQSGetPowerSaveModeConfig_t::ParamPresenceMask

8.1271.2.3 dms_PSMDurationDueToOOSTlv* unpack_dms_SLQSGetPowerSaveModeConfig_t::pDurationDueToOOS

8.1271.2.4 dms_PSMDurationThresholdTlv* unpack_dms_SLQSGetPowerSaveModeConfig_t::pDurationThreshold

8.1271.2.5 dms_PSMEarlyWakeupTimeTlv* unpack_dms_SLQSGetPowerSaveModeConfig_t::pEarlyWakeupTime

8.1271.2.6 dms_PSMPeriodicUpdateTimerTlv* unpack_dms_SLQSGetPowerSaveModeConfig_t::pPeriodicUpdateTimer

8.1271.2.7 dms_PSMEnableStateTlv* unpack_dms_SLQSGetPowerSaveModeConfig_t::pPsmEnableState

8.1271.2.8 dms_PSMRandomizationWindowTlv* unpack_dms_SLQSGetPowerSaveModeConfig_t::pRandomization-Window

8.1272 unpack_dms_SLQSSetPowerSaveModeConfig_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1272.1 Detailed Description

This structure is used to store unpack_dms_SLQSSetPowerSaveModeConfig parameters.

Parameters

Tlvresult	• unpack Tlv result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1272.2 Field Documentation

8.1272.2.1 swi_uint256_t unpack_dms_SLQSSetPowerSaveModeConfig_t::ParamPresenceMask

8.1272.2.2 uint16_t unpack_dms_SLQSSetPowerSaveModeConfig_t::Tlvresult

8.1273 unpack_dms_SLQSSwiClearDyingGaspStatistics_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1273.1 Detailed Description

This structure contains Clear Dying GASP unpack

Parameters

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1273.2 Field Documentation

8.1273.2.1 swi_uint256_t unpack_dms_SLQSSwiClearDyingGaspStatistics_t::ParamPresenceMask

8.1273.2.2 uint16_t unpack_dms_SLQSSwiClearDyingGaspStatistics_t::Tlvresult

8.1274 unpack_dms_SLQSSwiGetCrashInfo_t Struct Reference

Data Fields

- uint16_t Tlvresult
- crashInfoParams crashInfoParam
- swi_uint256_t ParamPresenceMask

8.1274.1 Detailed Description

This structure contains SWI get crash information unpack information

Parameters

Tlvresult	• Unpack Result
crashInfoParam[-OUT]	• See crashInfoParams • crashStatus – Bit to check in ParamPresenceMask - **1** • crashInfo – Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1274.2 Field Documentation

8.1274.2.1 crashInfoParams unpack_dms_SLQSSwiGetCrashInfo_t::crashInfoParam

8.1274.2.2 swi_uint256_t unpack_dms_SLQSSwiGetCrashInfo_t::ParamPresenceMask

8.1274.2.3 uint16_t unpack_dms_SLQSSwiGetCrashInfo_t::Tlvresult

8.1275 unpack_dms_SLQSSwiGetDyingGaspCfg_t Struct Reference

Data Fields

- packgetDyingGaspCfg * pGetDyingGaspCfg
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1275.1 Detailed Description

This structure contains Get Dying GASP Config unpack

Parameters

pGetDyingGasp-Cfg	• See packgetDyingGaspCfg • pDestSMSNum. – Bit to check in ParamPresenceMask - **16** • pDestSMSContent. – Bit to check in ParamPresenceMask - **17**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1275.2 Field Documentation

8.1275.2.1 swi_uint256_t unpack_dms_SLQSSwiGetDyingGaspCfg_t::ParamPresenceMask

8.1275.2.2 packgetDyingGaspCfg* unpack_dms_SLQSSwiGetDyingGaspCfg_t::pGetDyingGaspCfg

8.1275.2.3 uint16_t unpack_dms_SLQSSwiGetDyingGaspCfg_t::Tlvresult

8.1276 unpack_dms_SLQSSwiGetDyingGaspStatistics_t Struct Reference

Data Fields

- packgetDyingGaspStatistics * pGetDyingGaspStatistics
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1276.1 Detailed Description

This structure contains Get Dying GASP Statistics unpack.

Parameters

pGetDyingGasp-Statistics	• See packgetDyingGaspStatistics • pTimeStamp. – Bit to check in ParamPresenceMask - **16** • pSMSAttemptedFlag. – Bit to check in ParamPresenceMask - **17**
Tlvresult	• Unpack Result

8.1276.2 Field Documentation

8.1276.2.1 swi_uint256_t unpack_dms_SLQSSwiGetDyingGaspStatistics_t::ParamPresenceMask

8.1276.2.2 packgetDyingGaspStatistics* unpack_dms_SLQSSwiGetDyingGaspStatistics_t::pGetDyingGaspStatistics

8.1276.2.3 uint16_t unpack_dms_SLQSSwiGetDyingGaspStatistics_t::Tlvresult

8.1277 unpack_dms_SLQSSwiGetFirmwareCurr_t Struct Reference

Data Fields

- uint8_t numEntries
- image_info_t * pCurrImgInfo
- char priver [16]
- char pkgver [16]
- char fwvers [16]
- char carrier [16]
- swi_uint256_t ParamPresenceMask

8.1277.1 Detailed Description

This structure is used to store unpack_dms_SLQSSwiGetFirmwareCurr parameters

Parameters

numEntries[IN/-OUT]	• Number of entries in the image list to follow • The size of the list pCurrImgInfo must be specified when calling the API – Bit to check in ParamPresenceMask - **1**
pCurrImgInfo[O-UT]	• Currently Active Image List – Bit to check in ParamPresenceMask - **1**
priver[OUT]	• PRI version of the currently running firmware • Bit to check in ParamPresenceMask - **1**
pkgver[OUT]	• Package version of the currently running firmware • Bit to check in ParamPresenceMask - **1**
fwvers[OUT]	• firmware version of the currently running firmware • Bit to check in ParamPresenceMask - **1**
carrier[OUT]	• Carrier string of the currently running firmware • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1277.2 Field Documentation

8.1277.2.1 char unpack_dms_SLQSSwiGetFirmwareCurr_t::carrier[16]

8.1277.2.2 char unpack_dms_SLQSSwiGetFirmwareCurr_t::fwvers[16]

8.1277.2.3 uint8_t unpack_dms_SLQSSwiGetFirmwareCurr_t::numEntries

8.1277.2.4 swi_uint256_t unpack_dms_SLQSSwiGetFirmwareCurr_t::ParamPresenceMask

8.1277.2.5 image_info_t* unpack_dms_SLQSSwiGetFirmwareCurr_t::pCurrImgInfo

8.1277.2.6 char unpack_dms_SLQSSwiGetFirmwareCurr_t::pkgver[16]

8.1277.2.7 char unpack_dms_SLQSSwiGetFirmwareCurr_t::priver[16]

8.1278 unpack_dms_SLQSSwiGetFwUpdateStatus_t Struct Reference

Data Fields

- uint32_t ResCode
- uint8_t imgType
- uint32_t refData
- uint8_t refString [15]
- uint8_t logString [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1278.1 Detailed Description

This structure is used to store Firmware Update Status

Parameters

ResCode	• FW Update Result Code • Values: – 0x00000001 - Successful – 0xFFFFFFFF - Unknown (due to power off reset after firmware update) – 0x100000nn - File update errors while nn will be the exact error number: * 00 - General error – 0x200000nn - NVUP update errors while nn will be the exact error number: * 00 - General error – 0x40000nnn - FOTA update agent errors while nnn will be the exact error number: * 000 ∼ 0FF - Insignia defined error code * 100 ∼ 1FF - Sierra defined error code * See qaGobiApiTableFwDldErrorCodes.h for more detailed information – 0x800000nn - FDT/SSDP reported errors while nn will be the exact error number * See qaGobiApiTableFwDldErrorCodes.h for more detailed information • Bit to check in ParamPresenceMask - **16**
imgType	• Optional parameter • Firmware image type that failed the update • Bit to check in ParamPresenceMask - **17**
refData	• Optional parameter • Failed image reference data • This is normally the offset of the image that caused the failure • Bit to check in ParamPresenceMask - **18**
refString	• Optional parameter • Failed image reference string. This is normally the partition name of the image that caused the failure if applicable. • Bit to check in ParamPresenceMask - **19**

logString	• Optional parameter • Failed image reference string. This is normally the partition name of the image that caused the failure if applicable. • Bit to check in ParamPresenceMask - **20**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1278.2 Field Documentation

8.1278.2.1 uint8_t unpack_dms_SLQSSwiGetFwUpdateStatus_t::imgType

8.1278.2.2 uint8_t unpack_dms_SLQSSwiGetFwUpdateStatus_t::logString[255]

8.1278.2.3 swi_uint256_t unpack_dms_SLQSSwiGetFwUpdateStatus_t::ParamPresenceMask

8.1278.2.4 uint32_t unpack_dms_SLQSSwiGetFwUpdateStatus_t::refData

8.1278.2.5 uint8_t unpack_dms_SLQSSwiGetFwUpdateStatus_t::refString[15]

8.1278.2.6 uint32_t unpack_dms_SLQSSwiGetFwUpdateStatus_t::ResCode

8.1278.2.7 uint16_t unpack_dms_SLQSSwiGetFwUpdateStatus_t::Tlvresult

8.1279 unpack_dms_SLQSSwiGetHostDevInfo_t Struct Reference

Data Fields

- uint16_t Tlvresult
- char manString [255]
- char modelString [255]
- char swVerString [255]
- char plasmaIDString [255]
- char hostID [255]
- swi_uint256_t ParamPresenceMask

8.1279.1 Detailed Description

This structure contains SWI get host device info unpack information

Parameters

Tlvresult	• unpack Result

manString[OUT]	• Host Device Manufacturer Name • Null terminated ASCII String • Bit to check in ParamPresenceMask - **16**
modelString[OUT]	• Host Device Model String • Null terminated ASCII String • Bit to check in ParamPresenceMask - **17**
swVerString[OUT]	• Host Device Software Version String • Null terminated ASCII string • Bit to check in ParamPresenceMask - **18**
plasmaIDString[OUT]	• Host Device Plasma ID String • Null terminated alphanumeric ASCII String. • Bit to check in ParamPresenceMask - **19**
hostID[OUT]	• Device Host ID String • Null terminated alphanumeric ASCII String. • Bit to check in ParamPresenceMask - **20**
ParamPresenceMask[OUT]	• bitmask representation to indicate valid parameters.

8.1279.2 Field Documentation

8.1279.2.1 char unpack_dms_SLQSSwiGetHostDevInfo_t::hostID[255]

8.1279.2.2 char unpack_dms_SLQSSwiGetHostDevInfo_t::manString[255]

8.1279.2.3 char unpack_dms_SLQSSwiGetHostDevInfo_t::modelString[255]

8.1279.2.4 swi_uint256_t unpack_dms_SLQSSwiGetHostDevInfo_t::ParamPresenceMask

8.1279.2.5 char unpack_dms_SLQSSwiGetHostDevInfo_t::plasmaIDString[255]

8.1279.2.6 char unpack_dms_SLQSSwiGetHostDevInfo_t::swVerString[255]

8.1279.2.7 uint16_t unpack_dms_SLQSSwiGetHostDevInfo_t::Tlvresult

8.1280 unpack_dms_SLQSSwiGetOSInfo_t Struct Reference

Data Fields

- uint16_t Tlvresult
- char nameString [255]
- char versionString [255]

- swi_uint256_t ParamPresenceMask

8.1280.1 Detailed Description

This structure contains SWI get host os info unpack information

Parameters

Tlvresult	• Unpack Result
nameString[OUT]	• Host operating system name • Bit to check in ParamPresenceMask - **16**
VersionString[OUT]	• Host operating system version • Bit to check in ParamPresenceMask - **17**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1280.2 Field Documentation

8.1280.2.1 char unpack_dms_SLQSSwiGetOSInfo_t::nameString[255]

8.1280.2.2 swi_uint256_t unpack_dms_SLQSSwiGetOSInfo_t::ParamPresenceMask

8.1280.2.3 uint16_t unpack_dms_SLQSSwiGetOSInfo_t::Tlvresult

8.1280.2.4 char unpack_dms_SLQSSwiGetOSInfo_t::versionString[255]

8.1281 unpack_dms_SLQSSwiGetSerialNoExt_t Struct Reference

Data Fields

- uint16_t Tlvresult
- char meidString [8]
- swi_uint256_t ParamPresenceMask

8.1281.1 Detailed Description

This structure contains SWI get device serial number extension unpack information

Parameters

Tlvresult	• pack Result
meidString[OUT]	• optional parameter, mobile equipment identifier • Bit to check in ParamPresenceMask - **16**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1281.2 Field Documentation

8.1281.2.1 char unpack_dms_SLQSSwiGetSerialNoExt_t::meidString[8]

8.1281.2.2 swi_uint256_t unpack_dms_SLQSSwiGetSerialNoExt_t::ParamPresenceMask

8.1281.2.3 uint16_t unpack_dms_SLQSSwiGetSerialNoExt_t::Tlvresult

8.1282 unpack_dms_SLQSSwiSetDyingGaspCfg_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1282.1 Detailed Description

This structure contains set Dying GASP Config unpack

Parameters

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1282.2 Field Documentation

8.1282.2.1 swi_uint256_t unpack_dms_SLQSSwiSetDyingGaspCfg_t::ParamPresenceMask

8.1282.2.2 uint16_t unpack_dms_SLQSSwiSetDyingGaspCfg_t::Tlvresult

8.1283 unpack_dms_SLQSSwiSetHostDevInfo_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1283.1 Detailed Description

This structure contains SWI set host dev info unpack

Parameters

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1283.2 Field Documentation

8.1283.2.1 swi_uint256_t unpack_dms_SLQSSwiSetHostDevInfo_t::ParamPresenceMask

8.1283.2.2 uint16_t unpack_dms_SLQSSwiSetHostDevInfo_t::Tlvresult

8.1284 unpack_dms_SLQSSwiSetOSInfo_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1284.1 Detailed Description

This structure contains SWI set host OS info unpack

Parameters

Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1284.2 Field Documentation

8.1284.2.1 swi_uint256_t unpack_dms_SLQSSwiSetOSInfo_t::ParamPresenceMask

8.1284.2.2 uint16_t unpack_dms_SLQSSwiSetOSInfo_t::Tlvresult

8.1285 unpack_dms_SLQSUIMGetState_t Struct Reference

Data Fields

- uint8_t state
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1285.1 Detailed Description

This structure contains UIM get state unpack information

Parameters

state[OUT]	• UIM state • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1285.2 Field Documentation

8.1285.2.1 swi_uint256_t unpack_dms_SLQSUIMGetState_t::ParamPresenceMask

8.1285.2.2 uint8_t unpack_dms_SLQSUIMGetState_t::state

8.1285.2.3 uint16_t unpack_dms_SLQSUIMGetState_t::Tlvresult

8.1286 unpack_dms_SwiEventReportCallBack_ind_t Struct Reference

Data Fields

- dms_TemperatureTlv TempTlv
- dms_VoltageTlv VoltTlv
- dms_UimStatusTlv UimStatusTlv
- swi_uint256_t ParamPresenceMask

8.1286.1 Detailed Description

Structure used to SWI event report indication parameters.

Parameters

TempTlv	• Temperature status tlv • See dms_TemperatureTlv for more information
VoltTlv	• Voltage status tlv • see dms_VoltageTlv for more information
UimStatusTlv	• UIM status tlv • see dms_UimStatusTlv for more information
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

: None

8.1286.2 Field Documentation

8.1286.2.1 swi_uint256_t unpack_dms_SwiEventReportCallBack_ind_t::ParamPresenceMask

8.1286.2.2 dms_TemperatureTlv unpack_dms_SwiEventReportCallBack_ind_t::TempTlv

8.1286.2.3 dms_UimStatusTlv unpack_dms_SwiEventReportCallBack_ind_t::UimStatusTlv

8.1286.2.4 dms_VoltageTlv unpack_dms_SwiEventReportCallBack_ind_t::VoltTlv

8.1287 unpack_dms_SwiSetEventReport_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1287.1 Detailed Description

This structure is used to store unpack_dms_SwiSetEventReport parameters.

Parameters

Tlvresult	• unpack Tlv result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1287.2 Field Documentation

8.1287.2.1 swi_uint256_t unpack_dms_SwiSetEventReport_t::ParamPresenceMask

8.1287.2.2 uint16_t unpack_dms_SwiSetEventReport_t::Tlvresult

8.1288 unpack_dms_SwiUimSelect_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1288.1 Detailed Description

This structure is used to store unpack_dms_SwiUimSelect parameters.

Parameters

Tlvresult	• unpack Tlv result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1288.2 Field Documentation

8.1288.2.1 swi_uint256_t unpack_dms_SwiUimSelect_t::ParamPresenceMask

8.1288.2.2 uint16_t unpack_dms_SwiUimSelect_t::Tlvresult

8.1289 unpack_dms_UIMGetControlKeyStatus_t Struct Reference

Data Fields

- uint8_t facilityState
- uint8_t verifyRetriesLeft
- uint8_t unblockRetriesLeft
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1289.1 Detailed Description

This structure contains PIN retries status

Parameters

facilityState[OUT]	• Control key status
	  – 0 - Deactivated
	  – 1 - Activated
	  – 2 - Blocked
	• Bit to check in ParamPresenceMask - **1**

verifyRetries-Left[OUT]	• Optional parameter • Upon operational failure, this will indicate number of retries left, after which PIN will be blocked. • Bit to check in ParamPresenceMask - **1**
unblockRetries-Left[OUT]	• Optional parameter • Upon operational failure, this will indicate number of unblock retries left, after which the PIN will be permanently blocked i.e. UIM is unusable. • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1289.2 Field Documentation

8.1289.2.1 uint8_t unpack_dms_UIMGetControlKeyStatus_t::facilityState

8.1289.2.2 swi_uint256_t unpack_dms_UIMGetControlKeyStatus_t::ParamPresenceMask

8.1289.2.3 uint16_t unpack_dms_UIMGetControlKeyStatus_t::Tlvresult

8.1289.2.4 uint8_t unpack_dms_UIMGetControlKeyStatus_t::unblockRetriesLeft

8.1289.2.5 uint8_t unpack_dms_UIMGetControlKeyStatus_t::verifyRetriesLeft

8.1290 unpack_dms_UIMGetICCID_t Struct Reference

Data Fields

- uint8_t stringSize
- uint8_t String [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1290.1 Detailed Description

This structure is used to store unpack_dms_UIMGetICCID parameters.

Parameters

stringSize	• Size of String. • Bit to check in ParamPresenceMask - **1**
String	• ICCID String. • Maximum Length is 255 Bytes • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unack result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1290.2 Field Documentation

8.1290.2.1 swi_uint256_t unpack_dms_UIMGetICCID_t::ParamPresenceMask

8.1290.2.2 uint8_t unpack_dms_UIMGetICCID_t::String[255]

8.1290.2.3 uint8_t unpack_dms_UIMGetICCID_t::stringSize

8.1290.2.4 uint16_t unpack_dms_UIMGetICCID_t::Tlvresult

8.1291 unpack_dms_UIMGetPINStatus_t Struct Reference

Data Fields

- uint8_t p1Status
- uint8_t p1VerifyRetriesLeft
- uint8_t p1UnblockRetriesLeft
- uint8_t p2Status
- uint8_t p2VerifyRetriesLeft
- uint8_t p2UnblockRetriesLeft
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1291.1 Detailed Description

This structure contains Get PIN Status unpack information

Parameters

p1Status[OUT]	• PIN1 status(0xFFFFFFFF - Unknown) – 0 - PIN not initialized – 1 - PIN enabled, not verified – 2 - PIN enabled, verified – 3 - PIN disabled – 4 - PIN blocked – 5 - PIN permanently blocked • Bit to check in ParamPresenceMask - **17**
p1VerifyRetries-Left[OUT]	• Optional parameter • Upon operational failure, this will indicate number of retries left of PIN1, after which PIN will be blocked. • Bit to check in ParamPresenceMask - **17**
p1Unblock-RetriesLeft[OUT]	• Optional parameter • Upon operational failure, this will indicate number of unblock retries left of PIN1, after which the PIN will be permanently blocked i.e. UIM is unusable. • Bit to check in ParamPresenceMask - **17**
p2Status[OUT]	• PIN2 status(0xFFFFFFFF - Unknown) – 0 - PIN not initialized – 1 - PIN enabled, not verified – 2 - PIN enabled, verified – 3 - PIN disabled – 4 - PIN blocked – 5 - PIN permanently blocked • Bit to check in ParamPresenceMask - **18**

p2VerifyRetries-Left[OUT]	• Optional parameter • Upon operational failure, this will indicate number of retries left of PIN2, after which PIN will be blocked. • Bit to check in ParamPresenceMask - **18**
p2Unblock-RetriesLeft[OUT]	• Optional parameter • Upon operational failure, this will indicate number of unblock retries left of PIN2, after which the PIN will be permanently blocked i.e. UIM is unusable. • Bit to check in ParamPresenceMask - **18**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1291.2 Field Documentation

8.1291.2.1 uint8_t unpack_dms_UIMGetPINStatus_t::p1Status

8.1291.2.2 uint8_t unpack_dms_UIMGetPINStatus_t::p1UnblockRetriesLeft

8.1291.2.3 uint8_t unpack_dms_UIMGetPINStatus_t::p1VerifyRetriesLeft

8.1291.2.4 uint8_t unpack_dms_UIMGetPINStatus_t::p2Status

8.1291.2.5 uint8_t unpack_dms_UIMGetPINStatus_t::p2UnblockRetriesLeft

8.1291.2.6 uint8_t unpack_dms_UIMGetPINStatus_t::p2VerifyRetriesLeft

8.1291.2.7 swi_uint256_t unpack_dms_UIMGetPINStatus_t::ParamPresenceMask

8.1291.2.8 uint16_t unpack_dms_UIMGetPINStatus_t::Tlvresult

8.1292 unpack_dms_UIMSetControlKeyProtection_t Struct Reference

Data Fields

- uint8_t verifyRetriesLeft
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1292.1 Detailed Description

This structure contains UIM Set control key protection unpack information

Parameters

verifyRetries-Left[OUT]	• Optional parameter • number of retries left after which the control key is blocked • Bit to check in ParamPresenceMask - **16**
Tlvresult	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1292.2 Field Documentation

8.1292.2.1 swi_uint256_t unpack_dms_UIMSetControlKeyProtection_t::ParamPresenceMask

8.1292.2.2 uint16_t unpack_dms_UIMSetControlKeyProtection_t::Tlvresult

8.1292.2.3 uint8_t unpack_dms_UIMSetControlKeyProtection_t::verifyRetriesLeft

8.1293 unpack_dms_UIMSetPINProtection_t Struct Reference

Data Fields

- uint8_t verifyRetriesLeft
- uint8_t unblockRetriesLeft
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1293.1 Detailed Description

This structure contains PIN retries status

Parameters

verifyRetries-Left[OUT]	• Optional parameter • Upon operational failure, this will indicate number of retries left, after which PIN will be blocked. • Bit to check in ParamPresenceMask - **16**
unblockRetries-Left[OUT]	• Optional parameter • Upon operational failure, this will indicate number of unblock retries left, after which the PIN will be permanently blocked i.e. UIM is unusable. • Bit to check in ParamPresenceMask - **16**
Tlvresult[OUT]	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1293.2 Field Documentation

8.1293.2.1 swi_uint256_t unpack_dms_UIMSetPINProtection_t::ParamPresenceMask

8.1293.2.2 uint16_t unpack_dms_UIMSetPINProtection_t::Tlvresult

8.1293.2.3 uint8_t unpack_dms_UIMSetPINProtection_t::unblockRetriesLeft

8.1293.2.4 uint8_t unpack_dms_UIMSetPINProtection_t::verifyRetriesLeft

8.1294 unpack_dms_UIMUnblockControlKey_t Struct Reference

Data Fields

- uint8_t unblockRetriesLeft
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1294.1 Detailed Description

This structure contains UIM Set control key protection unpack information

Parameters

unblockRetries-Left[OUT]	• Optional parameter • number of unblock retries left after which the control key is permanently blocked • Bit to check in ParamPresenceMask - **16**
Tlvresult[OUT]	• Unpack Result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1294.2 Field Documentation

8.1294.2.1 swi_uint256_t unpack_dms_UIMUnblockControlKey_t::ParamPresenceMask

8.1294.2.2 uint16_t unpack_dms_UIMUnblockControlKey_t::Tlvresult

8.1294.2.3 uint8_t unpack_dms_UIMUnblockControlKey_t::unblockRetriesLeft

8.1295 unpack_fms_GetImagesPreference_t Struct Reference

Data Fields

- uint32_t ImageListSize
- FMSPrefImageList * pImageList
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1295.1 Detailed Description

This structure contains the Get Image Preference information unpack

Parameters

listSize	• The number of elements in the image list
pListEntries	• Array of Image entries with size provided by previous field • See FMSImageElement • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack result

8.1295.2 Field Documentation

8.1295.2.1 uint32_t unpack_fms_GetImagesPreference_t::ImageListSize

8.1295.2.2 swi_uint256_t unpack_fms_GetImagesPreference_t::ParamPresenceMask

8.1295.2.3 FMSPrefImageList* unpack_fms_GetImagesPreference_t::pImageList

8.1295.2.4 uint16_t unpack_fms_GetImagesPreference_t::Tlvresult

8.1296 unpack_fms_GetStoredImages_t Struct Reference

Data Fields

- uint32_t imagelistSize
- FMSImageList imageList
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1296.1 Detailed Description

This structure contains the Get Stored Images unpack

Parameters

listSize	• The number of elements in the image list
imageList	• Array of Image entries with size provided by previous field • See FMSImageElement • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack result

8.1296.2 Field Documentation

8.1296.2.1 FMSImageList unpack_fms_GetStoredImages_t::imageList

8.1296.2.2 uint32_t unpack_fms_GetStoredImages_t::imagelistSize

8.1296.2.3 swi_uint256_t unpack_fms_GetStoredImages_t::ParamPresenceMask

8.1296.2.4 uint16_t unpack_fms_GetStoredImages_t::Tlvresult

8.1297 unpack_fms_SetImagesPreference_t Struct Reference

Data Fields

- uint32_t ImageTypesSize
- uint8_t ImageTypes [255]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1297.1 Detailed Description

This structure contains the Set Images Preference unpack

Parameters

ImageTypesSize	• Image Type Size
ImageTypes	• Image Type • Bit to check in ParamPresenceMask - **1**
Tlvresult	• Unpack result

8.1297.2 Field Documentation

8.1297.2.1 uint8_t unpack_fms_SetImagesPreference_t::ImageTypes[255]

8.1297.2.2 uint32_t unpack_fms_SetImagesPreference_t::ImageTypesSize

8.1297.2.3 swi_uint256_t unpack_fms_SetImagesPreference_t::ParamPresenceMask

8.1297.2.4 uint16_t unpack_fms_SetImagesPreference_t::Tlvresult

8.1298 unpack_loc_BestAvailPos_Ind_t Struct Reference

Data Fields

- uint32_t status
- uint32_t * pXid
- uint64_t * pLatitude

- uint64_t * pLongitude
- uint32_t * pHorUncCircular
- uint32_t * pAltitudeWrtEllipsoid
- uint32_t * pVertUnc
- uint64_t * pTimestampUtc
- uint32_t * pTimeUnc
- uint32_t * pHorUncEllipseSemiMinor
- uint32_t * pHorUncEllipseSemiMajor
- uint32_t * pHorUncEllipseOrientAzimuth
- uint8_t * pHorCirConf
- uint8_t * pHorEllpConf
- uint32_t * pHorReliability
- uint32_t * pSpeedHorizontal
- uint32_t * pSpeedUnc
- uint32_t * pAltitudeWrtMeanSeaLevel
- uint8_t * pVertConfidence
- uint32_t * pVertReliability
- uint32_t * pSpeedVertical
- uint32_t * pSpeedVerticalUnc
- uint32_t * pHeading
- uint32_t * pHeadingUnc
- uint32_t * pMagneticDeviation
- uint32_t * pTechnologyMask
- loc_precisionDilution * pPrecisionDilution
- loc_gpsTime * pGpsTime
- uint32_t * pTimeSrc
- loc_sensorDataUsage * pSensorDataUsage
- loc_svUsedforFix * pSvUsedforFix
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1298.1 Detailed Description

This structure contains Best Available Position

Parameters

status	• Valid values: – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure • Bit to check in ParamPresenceMask - **1**
xid	Transaction ID that was specified in the Get Best Available Position request. • Bit to check in ParamPresenceMask - **16**
pLatitude	• Latitude (specified in WGS84 datum) • Type - Floating point • Units - Degrees • Range - -90.0 to 90.0 • Positive values indicate northern latitude • Negative values indicate southern latitude • Bit to check in ParamPresenceMask - **17**
pLongitude	• Longitude (specified in WGS84 datum) • Type - Floating point • Units - Degrees • Range - -180.0 to 180.0 • Positive values indicate eastern latitude • Negative values indicate western latitude • Bit to check in ParamPresenceMask - **18**
pHorUncCircular	• Horizontal position uncertainty. • Units - Meters • Bit to check in ParamPresenceMask - **19**

pAltitudeWrt-Ellipsoid	• Altitude With Respect to WGS84 Ellipsoid. • Units - Meters • Range -500 to 15883 • Bit to check in ParamPresenceMask - **20**
pVertUnc	• Vertical uncertainty. • Units - Meters • Bit to check in ParamPresenceMask - **21**
pTimestampUtc	• UTC timestamp • Units - Milliseconds since Jan. 1, 1970 • Bit to check in ParamPresenceMask - **22**
pTimeUnc	• Time uncertainty. • Units - Milliseconds • Bit to check in ParamPresenceMask - **23**
pHorUncEllipse-SemiMinor	• Semi-minor axis of horizontal elliptical uncertainty. • Units - Meters • Bit to check in ParamPresenceMask - **24**
pHorUncEllipse-SemiMajor	• Semi-major axis of horizontal elliptical uncertainty. • Units: Meters • Bit to check in ParamPresenceMask - **25**
pHorUncEllipse-OrientAzimuth	• Elliptical horizontal uncertainty azimuth of orientation. • Units - Decimal degrees • Range - 0 to 180 • Bit to check in ParamPresenceMask - **26**
pHorCirConf	• Horizontal circular uncertainty confidence • Units: Precent • Range: 0 to 99 • Bit to check in ParamPresenceMask - **27**
pHorEllpConf	• Horizontal elliptical uncertainty confidence • Units: Precent • Range: 0 to 99 • Bit to check in ParamPresenceMask - **28**

pHorReliability	• Values – 0 - Location reliability is not set. – 1 - Location reliability is very low; use it at your own risk – 2 - Location reliability is low; little or no cross-checking is possible. – 3 - Location reliability is medium; limited cross-check passed – 4 - Location reliability is high; strong cross-check passed • Bit to check in ParamPresenceMask - **29**
pSpeed-Horizontal	• Horizontal speed. • Units - Meters/second • Bit to check in ParamPresenceMask - **30**
pSpeedUnc	• 3-D Speed uncertainty. • Units - Meters/second. • Bit to check in ParamPresenceMask - **31**
pAltitudeWrt-MeanSeaLevel	• Altitude With Respect to Sea Level. • Units - Meters • Bit to check in ParamPresenceMask - **32**
pVertConfidence	• Vertical uncertainty confidence. • Units - Percentage • Range 0 to 99 • Bit to check in ParamPresenceMask - **33**
pVertReliability	• Values – 0 - Location reliability is not set. – 1 - Location reliability is very low; use it at your own risk. – 2 - Location reliability is low; little or no cross-checking is possible – 3 - Location reliability is medium; limited cross-check passed – 4 - Location reliability is high; strong cross-check passed • Bit to check in ParamPresenceMask - **34**
pSpeedVertical	• Vertical speed. • Units - Meters/second • Bit to check in ParamPresenceMask - **35**
pSpeedVertical-Unc	• Veritical speed • Units: Meters/second • Bit to check in ParamPresenceMask - **36**

pHeading	• Heading. • Units - Degree • Range 0 to 359.999 • Bit to check in ParamPresenceMask - **37**
pHeadingUnc	• Heading uncertainty. • Units - Degree • Range 0 to 359.999 • Bit to check in ParamPresenceMask - **38**
pMagnetic-Deviation	• Difference between the bearing to true north and the bearing shown on a magnetic compass. The deviation is positive when the magnetic north is east of true north. • Bit to check in ParamPresenceMask - **39**
pTechnology-Mask	• Values – 0x00000001 - Satellites were used to generate the fix – 0x00000002 - Cell towers were used to generate the fix – 0x00000004 - Wi-Fi access points were used to generate the fix – 0x00000008 - Sensors were used to generate the fix – 0x00000010 - Reference Location was used to generate the fix – 0x00000020 - Coarse position injected into the location engine was used to generate the fix – 0x00000040 - AFLT was used to generate the fix – 0x00000080 - GNSS and network-provided measurements were used to generate the fix • Bit to check in ParamPresenceMask - **40**
-pPrecision-Dilution	• See loc_precisionDilution for more information • Bit to check in ParamPresenceMask - **41**
-pGpsTime	• See loc_gpsTime for more information • Bit to check in ParamPresenceMask - **42**

pTimeSrc	• Values – 0 - Invalid time. – 1 - Time is set by the 1X system. – 2 - Time is set by WCDMA/GSM time tagging. – 3 - Time is set by an external injection. – 4 - Time is set after decoding over-the-air GPS navigation data from one GPS satellite. – 5 - Time is set after decoding over-the-air GPS navigation data from multiple satellites. – 6 - Both time of the week and the GPS week number are known. – 7 - Time is set by the position engine after the fix is obtained – 8 - Time is set by the position engine after performing SFT, this is done when the clock time uncertainty is large. – 9 - Time is set after decoding GLO satellites. – 10- Time is set after transforming the GPS to GLO time – 11- Time is set by the sleep time tag provided by the WCDMA network. – 12- Time is set by the sleep time tag provided by the GSM network – 13- Source of the time is unknown – 14- Time is derived from the system clock (better known as the slow clock); GNSS time is maintained irrespective of the GNSS receiver state – 15- Time is set after decoding QZSS satellites. – 16- Time is set after decoding BDS satellites. • Bit to check in ParamPresenceMask - **43**
-pSensorData-Usage	• See loc_sensorDataUsage for more information • Bit to check in ParamPresenceMask - **44**
-pSvUsedforFix	• See loc_svUsedforFix for more information • Bit to check in ParamPresenceMask - **45**

8.1298.2 Field Documentation

8.1298.2.1 uint32_t* unpack_loc_BestAvailPos_Ind_t::pAltitudeWrtEllipsoid

8.1298.2.2 uint32_t* unpack_loc_BestAvailPos_Ind_t::pAltitudeWrtMeanSeaLevel

8.1298.2.3 swi_uint256_t unpack_loc_BestAvailPos_Ind_t::ParamPresenceMask

8.1298.2.4 loc_gpsTime* unpack_loc_BestAvailPos_Ind_t::pGpsTime

8.1298.2.5 uint32_t* unpack_loc_BestAvailPos_Ind_t::pHeading

8.1298.2.6 uint32_t* unpack_loc_BestAvailPos_Ind_t::pHeadingUnc

8.1298.2.7 uint8_t* unpack_loc_BestAvailPos_Ind_t::pHorCirConf

8.1298.2.8 uint8_t* unpack_loc_BestAvailPos_Ind_t::pHorEllpConf

8.1298.2.9 uint32_t* unpack_loc_BestAvailPos_Ind_t::pHorReliability

8.1298.2.10 uint32_t* unpack_loc_BestAvailPos_Ind_t::pHorUncCircular

8.1298.2.11 uint32_t* unpack_loc_BestAvailPos_Ind_t::pHorUncEllipseOrientAzimuth

8.1298.2.12 uint32_t* unpack_loc_BestAvailPos_Ind_t::pHorUncEllipseSemiMajor

8.1298.2.13 uint32_t* unpack_loc_BestAvailPos_Ind_t::pHorUncEllipseSemiMinor

8.1298.2.14 uint64_t* unpack_loc_BestAvailPos_Ind_t::pLatitude

8.1298.2.15 uint64_t* unpack_loc_BestAvailPos_Ind_t::pLongitude

8.1298.2.16 uint32_t* unpack_loc_BestAvailPos_Ind_t::pMagneticDeviation

8.1298.2.17 **loc_precisionDilution*** unpack_loc_BestAvailPos_Ind_t::pPrecisionDilution

8.1298.2.18 **loc_sensorDataUsage*** unpack_loc_BestAvailPos_Ind_t::pSensorDataUsage

8.1298.2.19 uint32_t* unpack_loc_BestAvailPos_Ind_t::pSpeedHorizontal

8.1298.2.20 uint32_t* unpack_loc_BestAvailPos_Ind_t::pSpeedUnc

8.1298.2.21 uint32_t* unpack_loc_BestAvailPos_Ind_t::pSpeedVertical

8.1298.2.22 uint32_t* unpack_loc_BestAvailPos_Ind_t::pSpeedVerticalUnc

8.1298.2.23 **loc_svUsedforFix*** unpack_loc_BestAvailPos_Ind_t::pSvUsedforFix

8.1298.2.24 uint32_t* unpack_loc_BestAvailPos_Ind_t::pTechnologyMask

8.1298.2.25 uint32_t* unpack_loc_BestAvailPos_Ind_t::pTimeSrc

8.1298.2.26 uint64_t* unpack_loc_BestAvailPos_Ind_t::pTimestampUtc

8.1298.2.27 uint32_t* unpack_loc_BestAvailPos_Ind_t::pTimeUnc

8.1298.2.28 uint8_t* unpack_loc_BestAvailPos_Ind_t::pVertConfidence

8.1298.2.29 uint32_t* unpack_loc_BestAvailPos_Ind_t::pVertReliability

8.1298.2.30 uint32_t* unpack_loc_BestAvailPos_Ind_t::pVertUnc

8.1298.2.31 uint32_t* unpack_loc_BestAvailPos_Ind_t::pXid

8.1298.2.32 uint32_t unpack_loc_BestAvailPos_Ind_t::status

8.1298.2.33 uint16_t unpack_loc_BestAvailPos_Ind_t::Tlvresult

8.1299 unpack_loc_CradleMountCallback_Ind_t Struct Reference

Data Fields

- uint32_t cradleMountConfigStatus
- swi_uint256_t ParamPresenceMask

8.1299.1 Detailed Description

This structure contains LOC Cradle Mount Config Status

Parameters

cradleMount-ConfigStatus	• Values – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure • Bit to check in ParamPresenceMask - **1**

8.1299.2 Field Documentation

8.1299.2.1 uint32_t unpack_loc_CradleMountCallback_Ind_t::cradleMountConfigStatus

8.1299.2.2 swi_uint256_t unpack_loc_CradleMountCallback_Ind_t::ParamPresenceMask

8.1300 unpack_loc_Delete_Assist_Data_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1300.1 Detailed Description

This structure contains LOC delete assist data unpack

Parameters

Tlvresult	• Unpack result. • Bit to check in ParamPresenceMask - **2**

8.1300.2 Field Documentation

8.1300.2.1 swi_uint256_t unpack_loc_Delete_Assist_Data_t::ParamPresenceMask

8.1300.2.2 uint16_t unpack_loc_Delete_Assist_Data_t::Tlvresult

8.1301 unpack_loc_DeleteAssistData_Ind_t Struct Reference

Data Fields

- uint32_t status
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1301.1 Detailed Description

Contain the parameters passed for SetLocDeleteAssistDataCallback by the device.

Parameters

status	• Status of the Delete Assist Data request • Valid values: – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure • Bit to check in ParamPresenceMask - **1**
Tlvresult	• unpack result

8.1301.2 Field Documentation

8.1301.2.1 swi_uint256_t unpack_loc_DeleteAssistData_Ind_t::ParamPresenceMask

8.1301.2.2 uint32_t unpack_loc_DeleteAssistData_Ind_t::status

8.1301.2.3 uint16_t unpack_loc_DeleteAssistData_Ind_t::Tlvresult

8.1302 unpack_loc_EngineState_Ind_t Struct Reference

Data Fields

- uint32_t engineState
- uint16_t Tlvresult

- swi_uint256_t ParamPresenceMask

8.1302.1 Detailed Description

This structure contains LOC Engine State field.

Parameters

engineState	• Location engine state.
	• Valid values
	  – 1 - Location engine is on
	  – 2 - Loction engine is off
	• Bit to check in ParamPresenceMask - **1**

Tlvresult	• unpack result

8.1302.2 Field Documentation

8.1302.2.1 uint32_t unpack_loc_EngineState_Ind_t::engineState

8.1302.2.2 swi_uint256_t unpack_loc_EngineState_Ind_t::ParamPresenceMask

8.1302.2.3 uint16_t unpack_loc_EngineState_Ind_t::Tlvresult

8.1303 unpack_loc_EventNMEA_Ind_t Struct Reference

Data Fields

- char NMEAData [201]
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1303.1 Detailed Description

Contain the parameters passed for SetLocEventMaskNMEACallback by the device.

Parameters

NMEAData	• NMEA string • Type - NULL terminated string • Maximum string length (including NULL terminator) - 201 • Bit to check in ParamPresenceMask - **1**
Tlvresult	• unpack result

8.1303.2 Field Documentation

8.1303.2.1 char unpack_loc_EventNMEA_Ind_t::NMEAData[201]

8.1303.2.2 swi_uint256_t unpack_loc_EventNMEA_Ind_t::ParamPresenceMask

8.1303.2.3 uint16_t unpack_loc_EventNMEA_Ind_t::Tlvresult

8.1304 unpack_loc_EventRegister_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1304.1 Detailed Description

This structure contains Event Register unpack

Parameters

Tlvresult	• Unpack result. • Bit to check in ParamPresenceMask - **2**

8.1304.2 Field Documentation

8.1304.2.1 swi_uint256_t unpack_loc_EventRegister_t::ParamPresenceMask

8.1304.2.2 uint16_t unpack_loc_EventRegister_t::Tlvresult

8.1305 unpack_loc_EventTimeSyncCallback_Ind_t Struct Reference

Data Fields

- uint32_t timeSyncRefCounter
- swi_uint256_t ParamPresenceMask

8.1305.1 Detailed Description

This structure contains LOC Event Time Sync Reference COunter

Parameters

timeSyncRef-Counter	• Sent by the location engine when it needs to synchronize location engine and control point (sensor processor) times. • Bit to check in ParamPresenceMask - **1**

8.1305.2 Field Documentation

8.1305.2.1 swi_uint256_t unpack_loc_EventTimeSyncCallback_Ind_t::ParamPresenceMask

8.1305.2.2 uint32_t unpack_loc_EventTimeSyncCallback_Ind_t::timeSyncRefCounter

8.1306 unpack_loc_GetOpMode_Ind_t Struct Reference

Data Fields

- uint32_t Status
- uint32_t * pMode
- swi_uint256_t ParamPresenceMask

8.1306.1 Detailed Description

Contain the parameters passed for SetLocGetOpModeCallback by the device.

Parameters

Status	• Status of the Get Server request. • Valid values – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure – 0xffffffff - Invalid data. • Bit to check in ParamPresenceMask - **1**

pMode	• Current operation mode. • Valid values: – eQMI_LOC_OPER_MODE_DEFAULT(1) - Use the default engine mode – eQMI_LOC_OPER_MODE_MSB (2)- Use the MS-based mode – eQMI_LOC_OPER_MODE_MSA (3)- Use the MS-assisted mode – eQMI_LOC_OPER_MODE_STANDALONE (4) - Use Standalone mode – eQMI_LOC_OPER_MODE_CELL_ID (5) - Use cell ID; this mode is only valid for GSM/UMTS networks – eQMI_LOC_OPER_MODE_WWAN(6) - Use WWAN measurements to calculate the position; if this mode is set, AFLT will be used for 1X networks and OTDOA will be used for LTE networks • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1306.2 Field Documentation

8.1306.2.1 swi_uint256_t unpack_loc_GetOpMode_Ind_t::ParamPresenceMask

8.1306.2.2 uint32_t∗ unpack_loc_GetOpMode_Ind_t::pMode

8.1306.2.3 uint32_t unpack_loc_GetOpMode_Ind_t::Status

8.1307 unpack_loc_GetServer_Ind_t Struct Reference

Data Fields

- uint32_t serverStatus
- uint32_t serverType
- loc_IPv4Info ∗ pIPv4AddrInfo
- loc_IPv6Info ∗ pIPv6AddrInfo
- loc_urlAddr ∗ pURL
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1307.1 Detailed Description

Contain the parameters passed for SetLocGetServerCallback by the device.

Parameters

serverStatus	• Status of the Get Server request. • Valid values – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure • Bit to check in ParamPresenceMask - **1**
serverType	• Type of server. • Valid values – eQMI_LOC_SERVER_TYPE_CDMA_PDE (1) - Server type is CDMA PDE – eQMI_LOC_SERVER_TYPE_CDMA_MPC (2) - Server type is CDMA MPC – eQMI_LOC_SERVER_TYPE_UMTS_SLP (3) - Server type is UMTS SLP – eQMI_LOC_SERVER_TYPE_CUSTOM_PDE (4) - Server type is custom PDE • Bit to check in ParamPresenceMask - **2**
pIPv4AddrInfo	• See loc_IPv4Info for more information. • Bit to check in ParamPresenceMask - **16**
pIPv6AddrInfo	• See loc_IPv6Info for more information. • Bit to check in ParamPresenceMask - **17**
pURL	• See loc_urlAddr for more information. • Bit to check in ParamPresenceMask - **18**

8.1307.2 Field Documentation

8.1307.2.1 swi_uint256_t unpack_loc_GetServer_Ind_t::ParamPresenceMask

8.1307.2.2 loc_IPv4Info* unpack_loc_GetServer_Ind_t::pIPv4AddrInfo

8.1307.2.3 loc_IPv6Info* unpack_loc_GetServer_Ind_t::pIPv6AddrInfo

8.1307.2.4 loc_urlAddr* unpack_loc_GetServer_Ind_t::pURL

8.1307.2.5 uint32_t unpack_loc_GetServer_Ind_t::serverStatus

8.1307.2.6 uint32_t unpack_loc_GetServer_Ind_t::serverType

8.1307.2.7 uint16_t unpack_loc_GetServer_Ind_t::Tlvresult

8.1308 unpack_loc_GnssSvInfo_Ind_t Struct Reference

Data Fields

- uint8_t altitudeAssumed
- loc_satelliteInfo * pSatelliteInfo
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1308.1 Detailed Description

Contain the parameters passed for SetLocGnssSvInfoCallback by the device.

Parameters

altitudeAssumed	• Indicates whether altitude is assumed or calculated – 0x00 (FALSE) - Valid altitude is calculated – 0x01 (TRUE) - Valid altitude is assumed; there may not be enough satellites to determine precise altitude • Bit to check in ParamPresenceMask - **1**
pSatelliteInfo	• See loc_satelliteInfo for more information. • Bit to check in ParamPresenceMask - **16**
Tlvresult	• unpack result

8.1308.2 Field Documentation

8.1308.2.1 uint8_t unpack_loc_GnssSvInfo_Ind_t::altitudeAssumed

8.1308.2.2 swi_uint256_t unpack_loc_GnssSvInfo_Ind_t::ParamPresenceMask

8.1308.2.3 loc_satelliteInfo* unpack_loc_GnssSvInfo_Ind_t::pSatelliteInfo

8.1308.2.4 uint16_t unpack_loc_GnssSvInfo_Ind_t::Tlvresult

8.1309 unpack_loc_InjectPositionCallback_Ind_t Struct Reference

Data Fields

- uint32_t status

- swi_uint256_t ParamPresenceMask

8.1309.1 Detailed Description

Contain the parameters passed for LOC Inject Position indication by the device.

Parameters

status	• Position Injection Status • Valid values: – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure • Bit to check in ParamPresenceMask - **1**

Note

None

8.1309.2 Field Documentation

8.1309.2.1 swi_uint256_t unpack_loc_InjectPositionCallback_Ind_t::ParamPresenceMask

8.1309.2.2 uint32_t unpack_loc_InjectPositionCallback_Ind_t::status

8.1310 unpack_loc_InjectSensorDataCallback_Ind_t Struct Reference

Data Fields

- uint32_t injectSensorDataStatus
- uint32_t * pOpaqueIdentifier
- uint8_t * pAccelSamplesAccepted
- uint8_t * pGyroSamplesAccepted
- uint8_t * pAccelTempSamplesAccepted
- uint8_t * pGyroTempSamplesAccepted
- swi_uint256_t ParamPresenceMask

8.1310.1 Detailed Description

This structure contains LOC Inject Sensor Data

Parameters

injectSensorDataStatus	• Values – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure • Bit to check in ParamPresenceMask - **1**
pOpaqueIdentifier[OPTIONAL]	• Sent in by the client echoed so the client can relate the indication to the request. • NULL when this TLV not present • Bit to check in ParamPresenceMask - **16**
pAccelSamplesAccepted[OPTIONAL]	• Lets the client know how many 3-axis accelerometer samples were accepted. • This field is present only if the accelerometer samples were sent in the request. • NULL when this TLV not present • Bit to check in ParamPresenceMask - **17**
pGyroSamplesAccepted[OPTIONAL]	• Lets the client know how many 3-axis gyroscope samples were accepted. • This field is present only if the gyroscope samples were sent in the request. • NULL when this TLV not present • Bit to check in ParamPresenceMask - **18**
pAccelTempSamplesAccepted[OPTIONAL]	• Lets the client know how many accelerometer temperature samples were accepted. • This field is present only if the accelerometer temperature samples were sent in the request. • NULL when this TLV not present • Bit to check in ParamPresenceMask - **19**
pGyroTempSamplesAccepted[OPTIONAL]	• Lets the client know how many gyroscope temperature samples were accepted. • This field is present only if the gyroscope temperature samples were sent in the request. • NULL when this TLV not present • Bit to check in ParamPresenceMask - **20**

8.1310.2 Field Documentation

8.1310.2.1 uint32_t unpack_loc_InjectSensorDataCallback_Ind_t::injectSensorDataStatus

8.1310.2.2 uint8_t* unpack_loc_InjectSensorDataCallback_Ind_t::pAccelSamplesAccepted

8.1310.2.3 uint8_t* unpack_loc_InjectSensorDataCallback_Ind_t::pAccelTempSamplesAccepted

8.1310.2.4 swi_uint256_t unpack_loc_InjectSensorDataCallback_Ind_t::ParamPresenceMask

8.1310.2.5 uint8_t* unpack_loc_InjectSensorDataCallback_Ind_t::pGyroSamplesAccepted

8.1310.2.6 uint8_t* unpack_loc_InjectSensorDataCallback_Ind_t::pGyroTempSamplesAccepted

8.1310.2.7 uint32_t* unpack_loc_InjectSensorDataCallback_Ind_t::pOpaqueIdentifier

8.1311 unpack_loc_InjectTimeSyncDataCallback_Ind_t Struct Reference

Data Fields

- uint32_t injectTimeSyncStatus
- swi_uint256_t ParamPresenceMask

8.1311.1 Detailed Description

This structure contains LOC Inject Time Sync Data Status

Parameters

injectTimeSyncStatus	• Values – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure

- * - Bit to check in ParamPresenceMask - **1**

8.1311.2 Field Documentation

8.1311.2.1 uint32_t unpack_loc_InjectTimeSyncDataCallback_Ind_t::injectTimeSyncStatus

8.1311.2.2 swi_uint256_t unpack_loc_InjectTimeSyncDataCallback_Ind_t::ParamPresenceMask

8.1312 unpack_loc_InjectUTCTimeCallback_Ind_t Struct Reference

Data Fields

- uint32_t status
- swi_uint256_t ParamPresenceMask

8.1312.1 Detailed Description

Contain the parameters passed for Inject UTC time indication by the device.

Parameters

status	• Status of the UTC Time Injection request • Valid values: – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure • Bit to check in ParamPresenceMask - **1**

Note

None

8.1312.2 Field Documentation

8.1312.2.1 swi_uint256_t unpack_loc_InjectUTCTimeCallback_Ind_t::ParamPresenceMask

8.1312.2.2 uint32_t unpack_loc_InjectUTCTimeCallback_Ind_t::status

8.1313 unpack_loc_PositionRpt_Ind_t Struct Reference

Data Fields

- uint32_t sessionStatus
- uint8_t sessionId
- uint64_t * pLatitude
- uint64_t * pLongitude
- uint32_t * pHorUncCircular
- uint32_t * pHorUncEllipseSemiMinor
- uint32_t * pHorUncEllipseSemiMajor
- uint32_t * pHorUncEllipseOrientAzimuth
- uint8_t * pHorConfidence
- uint32_t * pHorReliability
- uint32_t * pSpeedHorizontal
- uint32_t * pSpeedUnc
- uint32_t * pAltitudeWrtEllipsoid
- uint32_t * pAltitudeWrtMeanSeaLevel
- uint32_t * pVertUnc
- uint8_t * pVertConfidence

- uint32_t * pVertReliability
- uint32_t * pSpeedVertical
- uint32_t * pHeading
- uint32_t * pHeadingUnc
- uint32_t * pMagneticDeviation
- uint32_t * pTechnologyMask
- loc_precisionDilution * pPrecisionDilution
- uint64_t * pTimestampUtc
- uint8_t * pLeapSeconds
- loc_gpsTime * pGpsTime
- uint32_t * pTimeUnc
- uint32_t * pTimeSrc
- loc_sensorDataUsage * pSensorDataUsage
- uint32_t * pFixId
- loc_svUsedforFix * pSvUsedforFix
- uint8_t * pAltitudeAssumed
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1313.1 Detailed Description

This structure contains Event Position Report Indication unpack

Parameters

sessionStatus	• Values – 0 - Session was successful – 1 - Session is still in progress; further position reports will be generated until either the fix criteria specified by the client are met or the client response timeout occurs. – 2 - Session failed.. – 3 - Fix request failed because the session timed out. – 4 - Fix request failed because the session was ended by the user. – 5 - Fix request failed due to bad parameters in the request. – 6 - Fix request failed because the phone is offline. – 7 - Fix request failed because the engine is locked • Bit to check in ParamPresenceMask - **1**
sessionId	• ID of the session that was specified in the Start request • Range - 0 to 255 • Bit to check in ParamPresenceMask - **2**
pLatitude	• Latitude (specified in WGS84 datum) • Type - Floating point • Units - Degrees • Range - -90.0 to 90.0 • Positive values indicate northern latitude • Negative values indicate southern latitude • Bit to check in ParamPresenceMask - **16**

pLongitude	• Longitude (specified in WGS84 datum) • Type - Floating point • Units - Degrees • Range - -180.0 to 180.0 • Positive values indicate eastern latitude • Negative values indicate western latitude • Bit to check in ParamPresenceMask - **17**
pHorUncCircular	• Horizontal position uncertainty. • Units - Meters • Bit to check in ParamPresenceMask - **18**
pHorUncEllipse-SemiMinor	• Semi-minor axis of horizontal elliptical uncertainty. • Units - Meters • Bit to check in ParamPresenceMask - **19**
pHorUncEllipse-SemiMajor	• Semi-major axis of horizontal elliptical uncertainty. • Units: Meters • Bit to check in ParamPresenceMask - **20**
pHorUncEllipse-OrientAzimuth	• Elliptical horizontal uncertainty azimuth of orientation. • Units - Decimal degrees • Range - 0 to 180 • Bit to check in ParamPresenceMask - **21**
pHorConfidence	• Horizontal uncertainty confidence. • If both elliptical and horizontal uncertainties are specified in this message, the confidence corresponds to the elliptical uncertainty. • Units - Percentage • Range 0-99 • Bit to check in ParamPresenceMask - **22**

pHorReliability	• Values
	  – 0 - Location reliability is not set.
	  – 1 - Location reliability is very low; use it at your own risk
	  – 2 - Location reliability is low; little or no cross-checking is possible.
	  – 3 - Location reliability is medium; limited cross-check passed
	  – 4 - Location reliability is high; strong cross-check passed

- Bit to check in ParamPresenceMask - **23**

Parameters

pSpeed-Horizontal	• Horizontal speed. • Units - Meters/second • Bit to check in ParamPresenceMask - **24**
pSpeedUnc	• 3-D Speed uncertainty. • Units - Meters/second. • Bit to check in ParamPresenceMask - **25**
pAltitudeWrt-Ellipsoid	• Altitude With Respect to WGS84 Ellipsoid. • Units - Meters • Range -500 to 15883 • Bit to check in ParamPresenceMask - **26**
pAltitudeWrt-MeanSeaLevel	• Altitude With Respect to Sea Level. • Units - Meters • Bit to check in ParamPresenceMask - **27**
pVertUnc	• Vertical uncertainty. • Units - Meters • Bit to check in ParamPresenceMask - **28**
pVertConfidence	• Vertical uncertainty confidence. • Units - Percentage • Range 0 to 99 • Bit to check in ParamPresenceMask - **29**
pVertReliability	• Values – 0 - Location reliability is not set. – 1 - Location reliability is very low; use it at your own risk. – 2 - Location reliability is low; little or no cross-checking is possible – 3 - Location reliability is medium; limited cross-check passed – 4 - Location reliability is high; strong cross-check passed – Bit to check in ParamPresenceMask - **30**
pSpeedVertical	• Vertical speed. • Units - Meters/second • Bit to check in ParamPresenceMask - **31**

pHeading	• Heading. • Units - Degree • Range 0 to 359.999 • Bit to check in ParamPresenceMask - **32**
pHeadingUnc	• Heading uncertainty. • Units - Degree • Range 0 to 359.999 • Bit to check in ParamPresenceMask - **33**
pMagnetic-Deviation	• Difference between the bearing to true north and the bearing shown on a magnetic compass. The deviation is positive when the magnetic north is east of true north. • Bit to check in ParamPresenceMask - **34**
pTechnology-Mask	• Values – 0x00000001 - Satellites were used to generate the fix – 0x00000002 - Cell towers were used to generate the fix – 0x00000004 - Wi-Fi access points were used to generate the fix – 0x00000008 - Sensors were used to generate the fix – 0x00000010 - Reference Location was used to generate the fix – 0x00000020 - Coarse position injected into the location engine was used to generate the fix – 0x00000040 - AFLT was used to generate the fix – 0x00000080 - GNSS and network-provided measurements were used to generate the fix • Bit to check in ParamPresenceMask - **35**
pPrecision-Dilution	• See loc_precisionDilution for more information • Bit to check in ParamPresenceMask - **36**
pTimestampUtc	• UTC timestamp • Units - Milliseconds since Jan. 1, 1970 • Bit to check in ParamPresenceMask - **37**
pLeapSeconds	• Leap second information. If leapSeconds is not available, timestampUtc is calculated based on a hard-coded value for leap seconds. • Units - Seconds • Bit to check in ParamPresenceMask - **38**
pGpsTime	• See loc_gpsTime for more information • Bit to check in ParamPresenceMask - **39**

pTimeUnc	• Time uncertainty. • Units - Milliseconds • Bit to check in ParamPresenceMask - **40**
pTimeSrc	• Values – 0 - Invalid time. – 1 - Time is set by the 1X system. – 2 - Time is set by WCDMA/GSM time tagging. – 3 - Time is set by an external injection. – 4 - Time is set after decoding over-the-air GPS navigation data from one GPS satellite. – 5 - Time is set after decoding over-the-air GPS navigation data from multiple satellites. – 6 - Both time of the week and the GPS week number are known. – 7 - Time is set by the position engine after the fix is obtained – 8 - Time is set by the position engine after performing SFT, this is done when the clock time uncertainty is large. – 9 - Time is set after decoding GLO satellites. – 10- Time is set after transforming the GPS to GLO time – 11- Time is set by the sleep time tag provided by the WCDMA network. – 12- Time is set by the sleep time tag provided by the GSM network – 13- Source of the time is unknown – 14- Time is derived from the system clock (better known as the slow clock); GNSS time is maintained irrespective of the GNSS receiver state – 15- Time is set after decoding QZSS satellites. – 16- Time is set after decoding BDS satellites.

- Bit to check in ParamPresenceMask - **41**

Parameters

pSensorData-Usage	• See loc_sensorDataUsage for more information • Bit to check in ParamPresenceMask - **42**
pFixId	• Fix count for the session. Starts with 0 and increments by one for each successive position report for a particular session. • Bit to check in ParamPresenceMask - **43**
pSvUsedforFix	• See loc_svUsedforFix for more information • Bit to check in ParamPresenceMask - **44**
pAltitude-Assumed	• Indicates whether altitude is assumed or calculated. • Value – 0x00 - Altitude is calculated – 0x01 - Altitude is assumed • Bit to check in ParamPresenceMask - **45**

8.1313.2 Field Documentation

8.1313.2.1 uint8_t* unpack_loc_PositionRpt_Ind_t::pAltitudeAssumed

8.1313.2.2 uint32_t* unpack_loc_PositionRpt_Ind_t::pAltitudeWrtEllipsoid

8.1313.2.3 uint32_t* unpack_loc_PositionRpt_Ind_t::pAltitudeWrtMeanSeaLevel

8.1313.2.4 swi_uint256_t unpack_loc_PositionRpt_Ind_t::ParamPresenceMask

8.1313.2.5 uint32_t* unpack_loc_PositionRpt_Ind_t::pFixId

8.1313.2.6 loc_gpsTime* unpack_loc_PositionRpt_Ind_t::pGpsTime

8.1313.2.7 uint32_t* unpack_loc_PositionRpt_Ind_t::pHeading

8.1313.2.8 uint32_t* unpack_loc_PositionRpt_Ind_t::pHeadingUnc

8.1313.2.9 uint8_t* unpack_loc_PositionRpt_Ind_t::pHorConfidence

8.1313.2.10 uint32_t* unpack_loc_PositionRpt_Ind_t::pHorReliability

8.1313.2.11 uint32_t* unpack_loc_PositionRpt_Ind_t::pHorUncCircular

8.1313.2.12 uint32_t* unpack_loc_PositionRpt_Ind_t::pHorUncEllipseOrientAzimuth

8.1313.2.13 uint32_t* unpack_loc_PositionRpt_Ind_t::pHorUncEllipseSemiMajor

8.1313.2.14 uint32_t* unpack_loc_PositionRpt_Ind_t::pHorUncEllipseSemiMinor

8.1313.2.15 uint64_t* unpack_loc_PositionRpt_Ind_t::pLatitude

8.1313.2.16 uint8_t* unpack_loc_PositionRpt_Ind_t::pLeapSeconds

8.1313.2.17 uint64_t* unpack_loc_PositionRpt_Ind_t::pLongitude

8.1313.2.18 uint32_t* unpack_loc_PositionRpt_Ind_t::pMagneticDeviation

8.1313.2.19 loc_precisionDilution* unpack_loc_PositionRpt_Ind_t::pPrecisionDilution

8.1313.2.20 loc_sensorDataUsage* unpack_loc_PositionRpt_Ind_t::pSensorDataUsage

8.1313.2.21 uint32_t* unpack_loc_PositionRpt_Ind_t::pSpeedHorizontal

8.1313.2.22 uint32_t* unpack_loc_PositionRpt_Ind_t::pSpeedUnc

8.1313.2.23 uint32_t* unpack_loc_PositionRpt_Ind_t::pSpeedVertical

8.1313.2.24 loc_svUsedforFix* unpack_loc_PositionRpt_Ind_t::pSvUsedforFix

8.1313.2.25 uint32_t* unpack_loc_PositionRpt_Ind_t::pTechnologyMask

8.1313.2.26 uint32_t* unpack_loc_PositionRpt_Ind_t::pTimeSrc

8.1313.2.27 uint64_t* unpack_loc_PositionRpt_Ind_t::pTimestampUtc

8.1313.2.28 uint32_t* unpack_loc_PositionRpt_Ind_t::pTimeUnc

8.1313.2.29 uint8_t* unpack_loc_PositionRpt_Ind_t::pVertConfidence

8.1313.2.30 uint32_t* unpack_loc_PositionRpt_Ind_t::pVertReliability

8.1313.2.31 uint32_t* unpack_loc_PositionRpt_Ind_t::pVertUnc

8.1313.2.32 uint8_t unpack_loc_PositionRpt_Ind_t::sessionId

8.1313.2.33 uint32_t unpack_loc_PositionRpt_Ind_t::sessionStatus

8.1313.2.34 uint16_t unpack_loc_PositionRpt_Ind_t::Tlvresult

8.1314 unpack_loc_SensorStreamingCallback_Ind_t Struct Reference

Data Fields

- loc_accelAcceptReady * pAccelAcceptReady
- loc_gyroAcceptReady * pGyroAcceptReady
- loc_accelTempAcceptReady * pAccelTempAcceptReady
- loc_gyroTempAcceptReady * pGyroTempAcceptReady
- swi_uint256_t ParamPresenceMask

8.1314.1 Detailed Description

This structure contains LOC Event Sensor Streaming Ready Status

Parameters

-pAccelAcceptReady[OPTIONAL]	• See loc_accelAcceptReady for more information • Bit to check in ParamPresenceMask - **16**
-pGyroAcceptReady[OPTIONAL]	• See loc_gyroAcceptReady for more information • Bit to check in ParamPresenceMask - **17**
-pAccelTempAcceptReady[OPTIONAL]	• See loc_accelTempAcceptReady for more information • Bit to check in ParamPresenceMask - **18**
-pGyroTempAcceptReady[OPTIONAL]	• See loc_gyroTempAcceptReady for more information • Bit to check in ParamPresenceMask - **19**

8.1314.2 Field Documentation

8.1314.2.1 loc_accelAcceptReady* unpack_loc_SensorStreamingCallback_Ind_t::pAccelAcceptReady

8.1314.2.2 loc_accelTempAcceptReady* unpack_loc_SensorStreamingCallback_Ind_t::pAccelTempAcceptReady

8.1314.2.3 swi_uint256_t unpack_loc_SensorStreamingCallback_Ind_t::ParamPresenceMask

8.1314.2.4 loc_gyroAcceptReady* unpack_loc_SensorStreamingCallback_Ind_t::pGyroAcceptReady

8.1314.2.5 loc_gyroTempAcceptReady* unpack_loc_SensorStreamingCallback_Ind_t::pGyroTempAcceptReady

8.1315 unpack_loc_SetExtPowerConfig_Ind_t Struct Reference

Data Fields

- uint32_t status
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1315.1 Detailed Description

This structure contains LOC Set External Power Configure status field.

Parameters

status	• Valid values – 0 - Request was completed successfully – 1 - Request failed because of a general failure. – 2 - Request failed because it is not supported. – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - engine could not allocate sufficient memory – 9 - Request failed because the maximum number of Geofences are already programmed – 10 -Location service failed because of an XTRA version-based file format check failure • Bit to check in ParamPresenceMask - **1**
Tlvresult	• unpack result

8.1315.2 Field Documentation

8.1315.2.1 swi_uint256_t unpack_loc_SetExtPowerConfig_Ind_t::ParamPresenceMask

8.1315.2.2 uint32_t unpack_loc_SetExtPowerConfig_Ind_t::status

8.1315.2.3 uint16_t unpack_loc_SetExtPowerConfig_Ind_t::Tlvresult

8.1316 unpack_loc_SetExtPowerState_t Struct Reference

Data Fields

- uint16_t Tlvresult

- swi_uint256_t ParamPresenceMask

8.1316.1 Detailed Description

This structure contains Set Ext Power State unpack

Parameters

Tlvresult	• Unpack result. • Bit to check in ParamPresenceMask - **2**

8.1316.2 Field Documentation

8.1316.2.1 swi_uint256_t unpack_loc_SetExtPowerState_t::ParamPresenceMask

8.1316.2.2 uint16_t unpack_loc_SetExtPowerState_t::Tlvresult

8.1317 unpack_loc_SetOperationMode_Ind_t Struct Reference

Data Fields

- uint32_t status
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1317.1 Detailed Description

This structure contains LOC Set External Power Configure status field.

Parameters

status	• Status of the Set Operation Mode request. • Valid values: – 0 - Request was completed successfully – 1 - Request failed because of a general failure – 2 - Request failed because it is not supported – 3 - Request failed because it contained invalid parameters – 4 - Request failed because the engine is busy – 5 - Request failed because the phone is offline – 6 - Request failed because it timed out – 7 - Request failed because an undefined configuration was requested – 8 - Request failed because the engine could not allocate sufficient memory for the request – 9 - Request failed because the maximum number of Geofences are already programmed – 10 - Location service failed because of an XTRA version-based file format check failure • Bit to check in ParamPresenceMask - **1**
Tlvresult	• unpack result

8.1317.2 Field Documentation

8.1317.2.1 swi_uint256_t unpack_loc_SetOperationMode_Ind_t::ParamPresenceMask

8.1317.2.2 uint32_t unpack_loc_SetOperationMode_Ind_t::status

8.1317.2.3 uint16_t unpack_loc_SetOperationMode_Ind_t::Tlvresult

8.1318 unpack_loc_SetOperationMode_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1318.1 Detailed Description

This structure contains Set Operation Mode unpack

Parameters

Tlvresult	• Unpack result. • Bit to check in ParamPresenceMask - **2**

8.1318.2 Field Documentation

8.1318.2.1 swi_uint256_t unpack_loc_SetOperationMode_t::ParamPresenceMask

8.1318.2.2 uint16_t unpack_loc_SetOperationMode_t::Tlvresult

8.1319 unpack_loc_SetServer_Ind_t Struct Reference

Data Fields

- uint32_t serverStatus
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1319.1 Detailed Description

Contain the parameters passed for SetLocSetServerCallback by the device.

Parameters

serverStatus	• Status of the Get Server request. • Valid values – eQMI_LOC_SUCCESS (0) - Request was completed successfully – eQMI_LOC_GENERAL_FAILURE (1) - Request failed because of a general failure – eQMI_LOC_UNSUPPORTED (2) - Request failed because it is not supported – eQMI_LOC_INVALID_PARAMETER (3) - Request failed because it contained invalid parameters – eQMI_LOC_ENGINE_BUSY (4) - Request failed because the engine is busy – eQMI_LOC_PHONE_OFFLINE (5) - Request failed because the phone is offline – eQMI_LOC_TIMEOUT (6) - Request failed because it timed out – eQMI_LOC_CONFIG_NOT_SUPPORTED (7) - Request failed because an undefined configuration was requested – eQMI_LOC_INSUFFICIENT_MEMORY (8) - Request failed because the engine could not allocate sufficient memory for the request – eQMI_LOC_MAX_GEOFENCE_PROGRAMMED (9) - Request failed because the maximum number of Geofences are already programmed – eQMI_LOC_XTRA_VERSION_CHECK_FAILURE (10) - Location service failed because of an XTRA version-based file format check failure – 0xffffffff - Invalid data. • Bit to check in ParamPresenceMask - **1**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1319.2 Field Documentation

8.1319.2.1 swi_uint256_t unpack_loc_SetServer_Ind_t::ParamPresenceMask

8.1319.2.2 uint32_t unpack_loc_SetServer_Ind_t::serverStatus

8.1319.2.3 uint16_t unpack_loc_SetServer_Ind_t::Tlvresult

8.1320 unpack_loc_SLQSLOCGetBestAvailPos_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1320.1 Detailed Description

This structure contains Set Operation Mode unpack

Parameters

Tlvresult	• Unpack result. • Bit to check in ParamPresenceMask - **2**

8.1320.2 Field Documentation

8.1320.2.1 swi_uint256_t unpack_loc_SLQSLOCGetBestAvailPos_t::ParamPresenceMask

8.1320.2.2 uint16_t unpack_loc_SLQSLOCGetBestAvailPos_t::Tlvresult

8.1321 unpack_loc_SLQSLOCGetOpMode_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1321.1 Detailed Description

This structure contains Start LOC unpack

Parameters

Tlvresult	• Unpack result. • Bit to check in ParamPresenceMask - **2**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1321.2 Field Documentation

8.1321.2.1 swi_uint256_t unpack_loc_SLQSLOCGetOpMode_t::ParamPresenceMask

8.1321.2.2 uint16_t unpack_loc_SLQSLOCGetOpMode_t::Tlvresult

8.1322 unpack_loc_Start_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1322.1 Detailed Description

This structure contains Start LOC unpack

Parameters

Tlvresult	• Unpack result. • Bit to check in ParamPresenceMask - **2**

8.1322.2 Field Documentation

8.1322.2.1 swi_uint256_t unpack_loc_Start_t::ParamPresenceMask

8.1322.2.2 uint16_t unpack_loc_Start_t::Tlvresult

8.1323 unpack_loc_Stop_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1323.1 Detailed Description

This structure contains Stop LOC unpack

Parameters

Tlvresult	• Unpack result. • Bit to check in ParamPresenceMask - **2**

8.1323.2 Field Documentation

8.1323.2.1 swi_uint256_t unpack_loc_Stop_t::ParamPresenceMask

8.1323.2.2 uint16_t unpack_loc_Stop_t::Tlvresult

8.1324 unpack_nas_GetACCOLC_t Struct Reference

Data Fields

- uint8_t * pAccolc
- swi_uint256_t ParamPresenceMask

8.1324.1 Detailed Description

Retrieves information about the access overload class unpack structure

Parameters

pAccolc	• An 8-bit integer representation of the ACCOLC. – Range: 0 to 15 (0x00 to 0x0F). • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1324.2 Field Documentation

8.1324.2.1 uint8_t* unpack_nas_GetACCOLC_t::pAccolc

8.1324.2.2 swi_uint256_t unpack_nas_GetACCOLC_t::ParamPresenceMask

8.1325 unpack_nas_GetANAAAAuthenticationStatus_t Struct Reference

Data Fields

- uint32_t * pAuthStatus
- swi_uint256_t ParamPresenceMask

8.1325.1 Detailed Description

AN-AAA authentication status of the device

Parameters

AN-AAA	Authentication Status. • Status of the last AN-AAA authentication request, if any, for the current 1xEV-DO session. – 0 - AAA_STATUS_FAILED - Authentication failed – 1 - AAA_STATUS_SUCCESS - Authentication success – 2 - AAA_STATUS_NO_REQUEST - No authentication requested • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1325.2 Field Documentation

8.1325.2.1 swi_uint256_t unpack_nas_GetANAAAAuthenticationStatus_t::ParamPresenceMask

8.1325.2.2 uint32_t* unpack_nas_GetANAAAAuthenticationStatus_t::pAuthStatus

8.1326 unpack_nas_GetCDMANetworkParameters_t Struct Reference

Data Fields

- uint8_t SCI
- uint8_t SCM
- uint8_t RegHomeSID
- uint8_t RegForeignSID
- uint8_t RegForeignNID
- uint8_t ForceRev0
- uint8_t CustomSCP
- uint32_t Protocol
- uint32_t Broadcast
- uint32_t Application
- uint32_t Roaming
- swi_uint256_t ParamPresenceMask

8.1326.1 Detailed Description

Gets the current CDMA network parameters

Parameters

SCI	• Slot cycle index • Bit to check in ParamPresenceMask - **17**
SCM	• Station class mark • Bit to check in ParamPresenceMask - **18**
RegHomeSID	• Register on home SID – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **19**
RegForeignSID	• Register on foreign SID – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **19**
RegForeignNID	• Register on foreign NID – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **19**
ForceRev0	• Force CDMA 1x-EV-DO Rev. 0 mode – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **20**
CustomSCP	• Use a custom config for CDMA 1x-EV-DO SCP – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **21**

Protocol	• Protocol mask for custom SCP config – 0x00000001 - Subtype 2 Physical Layer – 0x00000002 - Enhanced CCMAC – 0x00000004 - Enhanced ACMAC – 0x00000008 - Enhanced FTCMAC – 0x00000010 - Subtype 3 RTCMAC – 0x00000020 - Subsystem 1 RTCMAC – 0x00000040 - Enhanced Idle – 0x00000080 - Generic Multimode Capable Disc Port • Bit to check in ParamPresenceMask - **21**
Broadcast	• Broadcast mask for custom SCP config – 0x00000001 - Generic broadcast enabled • Bit to check in ParamPresenceMask - **21**
Application	• Application mask for custom SCP config – 0x00000001 - SN Multiflow Packet Application – 0x00000002 - SN Enhanced Multiflow Packet Application • Bit to check in ParamPresenceMask - **21**
Roaming	• Roaming preference – 0 - Automatic – 1 - Home Only – 2 - Affiliated Roaming Only – 3 - Home and Affiliated Roaming • Bit to check in ParamPresenceMask - **22**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1326.2 Field Documentation

8.1326.2.1 uint32_t unpack_nas_GetCDMANetworkParameters_t::Application

8.1326.2.2 uint32_t unpack_nas_GetCDMANetworkParameters_t::Broadcast

8.1326.2.3 uint8_t unpack_nas_GetCDMANetworkParameters_t::CustomSCP

8.1326.2.4 uint8_t unpack_nas_GetCDMANetworkParameters_t::ForceRev0

8.1326.2.5 swi_uint256_t unpack_nas_GetCDMANetworkParameters_t::ParamPresenceMask

8.1326.2.6 uint32_t unpack_nas_GetCDMANetworkParameters_t::Protocol

8.1326.2.7 uint8_t unpack_nas_GetCDMANetworkParameters_t::RegForeignNID

8.1326.2.8 uint8_t unpack_nas_GetCDMANetworkParameters_t::RegForeignSID

8.1326.2.9 uint8_t unpack_nas_GetCDMANetworkParameters_t::RegHomeSID

8.1326.2.10 uint32_t unpack_nas_GetCDMANetworkParameters_t::Roaming

8.1326.2.11 uint8_t unpack_nas_GetCDMANetworkParameters_t::SCI

8.1326.2.12 uint8_t unpack_nas_GetCDMANetworkParameters_t::SCM

8.1327 unpack_nas_GetHomeNetwork3GPP2_t Struct Reference

Data Fields

- uint16_t * pMCC
- uint16_t * pMNC
- uint8_t nameSize
- uint8_t * pName
- uint16_t * pSID
- uint16_t * pNID
- uint16_t * pNw2MCC
- uint16_t * pNw2MNC
- uint8_t * pNw2DescDisp
- uint8_t * pNw2DescEnc
- uint8_t * pNw2DescLen
- uint8_t * pNw2Name
- swi_uint256_t ParamPresenceMask

8.1327.1 Detailed Description

Structure for HomeNetwork3GPP2 unpack.

Parameters

pMCC	• Mobile country code (UMTS only). • Bit to check in ParamPresenceMask - **1**
pMNC	• Mobile network code (UMTS only). • Bit to check in ParamPresenceMask - **1**
nameSize	• Maximum number of characters (including NULL terminator) that network name array can contain (UMTS only). • Bit to check in ParamPresenceMask - **1**
pName	• Network name or description represented as a NULL terminated string (empty string returned when unknown) (UMTS only). • Bit to check in ParamPresenceMask - **1**

pSID	• Home network system ID
	  – 0xFFFF - Unknown.
	  – Only applies to cdma2000
	• Bit to check in ParamPresenceMask - **16**

pNID	• Home network ID
	  – 0xFFFF - Unknown.
	  – Only applies to cdma2000
	• Bit to check in ParamPresenceMask - **16**

pNw2MCC	• Mobile country code (3GPP2 only). • Range : 0 to 999 • Bit to check in ParamPresenceMask - **17**
pNw2MNC	• Mobile network code (3GPP2 only). • Range : 0 to 999 • Bit to check in ParamPresenceMask - **17**

pNw2DescDisp	• Network Name Display (3GPP2 only). -Valid Value
	  – 0x00 - Do not display
	  – 0x01 - Display
	  – 0xFF - Unknown
	• Bit to check in ParamPresenceMask - **17**

pNw2DescEnc	• Encoding of the network description (3GPP2 only).
	• Valid Value
	  – 0x00 - Octet, unspecified
	  – 0x02 - 7-bit ASCII (liteqmi_helper_decode7bitAsciiEncString)
	  – 0x04 - Unicode
	  – 0x09 - GSM 7-bit default
	• Bit to check in ParamPresenceMask - **17**

pNw2DescLen	• Network Description Length (3GPP2 only). • Bit to check in ParamPresenceMask - **17**
pNw2Name	• Network Name (3GPP2 only). • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1327.2 Field Documentation

8.1327.2.1 uint8_t unpack_nas_GetHomeNetwork3GPP2_t::nameSize

8.1327.2.2 swi_uint256_t unpack_nas_GetHomeNetwork3GPP2_t::ParamPresenceMask

8.1327.2.3 uint16_t* unpack_nas_GetHomeNetwork3GPP2_t::pMCC

8.1327.2.4 uint16_t* unpack_nas_GetHomeNetwork3GPP2_t::pMNC

8.1327.2.5 uint8_t* unpack_nas_GetHomeNetwork3GPP2_t::pName

8.1327.2.6 uint16_t* unpack_nas_GetHomeNetwork3GPP2_t::pNID

8.1327.2.7 uint8_t* unpack_nas_GetHomeNetwork3GPP2_t::pNw2DescDisp

8.1327.2.8 uint8_t* unpack_nas_GetHomeNetwork3GPP2_t::pNw2DescEnc

8.1327.2.9 uint8_t* unpack_nas_GetHomeNetwork3GPP2_t::pNw2DescLen

8.1327.2.10 uint16_t* unpack_nas_GetHomeNetwork3GPP2_t::pNw2MCC

8.1327.2.11 uint16_t* unpack_nas_GetHomeNetwork3GPP2_t::pNw2MNC

8.1327.2.12 uint8_t* unpack_nas_GetHomeNetwork3GPP2_t::pNw2Name

8.1327.2.13 uint16_t* unpack_nas_GetHomeNetwork3GPP2_t::pSID

8.1328 unpack_nas_GetHomeNetwork_t Struct Reference

Data Fields

- uint16_t mcc
- uint16_t mnc
- char name [255]
- uint16_t sid
- uint16_t nid
- swi_uint256_t ParamPresenceMask

8.1328.1 Detailed Description

This structure contains unpack get get home network parameters.

Parameters

mcc	• Mobile country code (UMTS only). • A 16-bit integer representation of MCC. Range: 0 to 999. • Bit to check in ParamPresenceMask - **1**
mnc	• Mobile network code (UMTS only). • A 16-bit integer representation of MNC. Range: 0 to 999. • Bit to check in ParamPresenceMask - **1**

name	• Network name or description represented as a NULL terminated string (empty string returned when unknown) (UMTS only). • Bit to check in ParamPresenceMask - **1**
sid	• Home network system ID – 0xFFFF - Unknown. – Only applies to cdma2000 • Bit to check in ParamPresenceMask - **16**
nid	• Home network ID – 0xFFFF - Unknown. – Only applies to cdma2000 • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1328.2 Field Documentation

8.1328.2.1 uint16_t unpack_nas_GetHomeNetwork_t::mcc

8.1328.2.2 uint16_t unpack_nas_GetHomeNetwork_t::mnc

8.1328.2.3 char unpack_nas_GetHomeNetwork_t::name[255]

8.1328.2.4 uint16_t unpack_nas_GetHomeNetwork_t::nid

8.1328.2.5 swi_uint256_t unpack_nas_GetHomeNetwork_t::ParamPresenceMask

8.1328.2.6 uint16_t unpack_nas_GetHomeNetwork_t::sid

8.1329 unpack_nas_GetNetworkPreference_t Struct Reference

Data Fields

- uint32_t ActiveTechPref
- uint32_t Duration
- uint32_t PersistentTechPref
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1329.1 Detailed Description

Returns the network registration preference. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use unpack_nas_SLQSGetSys-SelectionPref() for new firmware versions and new modules

Parameters

TechnologyPref[-OUT]	• Bitmask representing the radio technology preference set. • No bits set indicates to the device to automatically determine the technology to use • Values: – Bit 0 - Technology is 3GPP2 – Bit 1 - Technology is 3GPP • Any combination of the following may be returned: – Bit 2 - Analog - AMPS if 3GPP2, GSM if 3GPP – Bit 3 - Digital - CDMA if 3GPP2, WCDMA if 3GPP – Bit 4 - HDR – Bit 5 - LTE – Bits 6 to 15 - Reserved • Bit to check in ParamPresenceMask - **1**
Duration[OUT]	• Duration of active preference – 0 - Permanent – 1 - Power cycle – 2 - Until the end of the next call or a power cycle – 3 - Until the end of the next call, a specified time, or a power cycle – 4 to 6 - Until the end of the next call • Bit to check in ParamPresenceMask - **1**
Persistent-TechnologyPref[-OUT]	• Bit field representing persistent radio technology preference – Same representation as the pTechnologyPref parameter • Bit to check in ParamPresenceMask - **16**
Tlvresult	• unpack result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1329.2 Field Documentation

8.1329.2.1 uint32_t unpack_nas_GetNetworkPreference_t::ActiveTechPref

8.1329.2.2 uint32_t unpack_nas_GetNetworkPreference_t::Duration

8.1329.2.3 swi_uint256_t unpack_nas_GetNetworkPreference_t::ParamPresenceMask

8.1329.2.4 uint32_t unpack_nas_GetNetworkPreference_t::PersistentTechPref

8.1329.2.5 uint16_t unpack_nas_GetNetworkPreference_t::Tlvresult

8.1330 unpack_nas_GetRFInfo_t Struct Reference

Data Fields

- uint8_t instancesSize
- RFBandInfoElements RFBandInfoElements [255]
- swi_uint256_t ParamPresenceMask

8.1330.1 Detailed Description

Structur to strore the RFInfoList

Parameters

instanceSize	• Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.
RFBandInfo-Elements	• RF info instances array – See RFBandInfoElements for more information • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1330.2 Field Documentation

8.1330.2.1 uint8_t unpack_nas_GetRFInfo_t::instancesSize

8.1330.2.2 swi_uint256_t unpack_nas_GetRFInfo_t::ParamPresenceMask

8.1330.2.3 RFBandInfoElements unpack_nas_GetRFInfo_t::RFBandInfoElements[255]

8.1331 unpack_nas_GetServingNetwork_t Struct Reference

Data Fields

- uint32_t RegistrationState
- uint32_t CSDomain
- uint32_t PSDomain
- uint32_t RAN
- uint8_t RadioIfacesSize
- uint8_t RadioIfaces [255]
- uint32_t Roaming
- uint16_t MCC
- uint16_t MNC
- uint8_t nameSize
- uint8_t Name [255]
- uint8_t DataCapsLen
- uint8_t DataCaps [255]
- swi_uint256_t ParamPresenceMask

8.1331.1 Detailed Description

This structure contains unpack get get serving network parameters.

Parameters

Registration-State	• Registration state: – 0 - Not registered – 1 - Registered – 2 - Searching/Not Registered – 3 - Registration Denied – 4 - Unknown • Bit to check in ParamPresenceMask - **1**
CSDomain	• Circuit switch domain status: – 0 - Unknown/Not Applicable – 1 - Attached – 2 - Detached • Bit to check in ParamPresenceMask - **1**
PSDomain	• Packet switch domain status – 0 - Unknown/Not Applicable – 1 - Attached – 2 - Detached • Bit to check in ParamPresenceMask - **1**
RAN	• Type of radio access network on which mobile is registered: – 0 - Unknown – 1 - cdma2000 network – 2 - UMTS network • Bit to check in ParamPresenceMask - **1**
RadioIfacesSize	• Upon input, maximum number of elements that the radio interface array contain. • Upon successful output, actual number of elements in the radio interface array. • Bit to check in ParamPresenceMask - **1**
RadioIfaces	• An array of Radio Interface Technology – See qaGobiApiTableRadioInterfaces.h for the Radio Interface Technologies • Bit to check in ParamPresenceMask - **1**
Roaming	• Roaming indicator • Bit to check in ParamPresenceMask - **16**
MCC	• Mobile country code • Bit to check in ParamPresenceMask - **18**

MNC	• Mobile network code • Bit to check in ParamPresenceMask - **18**
nameSize	• Maximum number of characters (including NULL terminator) that network name array can contain; applicable only for UMTS networks • Bit to check in ParamPresenceMask - **18**
Name	• Network name or description represented as a NULL terminated string; empty string is returned when unknown; applicable only for UMTS networks • Bit to check in ParamPresenceMask - **18**
DataCapsLen[IN/OUT]	• Upon input, the maximum number of elements the data capabilities array can contain. • Upon output, the actual number of elements in the data capabilities array. • Bit to check in ParamPresenceMask - **17**
DataCaps[OUT]	• Data capabilities array of unsigned long type – 1 - GPRS – 2 - EDGE – 3 - HSDPA – 4 - HSUPA – 5 - WCDMA – 6 - CDMA 1xRTT – 7 - CDMA 1xEV-DO Rev 0 – 8 - CDMA 1xEV-DO Rev. A – 9 - GSM – 10 - EVDO Rev. B – 11 - LTE – 12 - HSDPA Plus – 13 - Dual Carrier HSDPA Plus • Bit to check in ParamPresenceMask - **17**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1331.2 Field Documentation

8.1331.2.1 uint32_t unpack_nas_GetServingNetwork_t::CSDomain

8.1331.2.2 uint8_t unpack_nas_GetServingNetwork_t::DataCaps[255]

8.1331.2.3 uint8_t unpack_nas_GetServingNetwork_t::DataCapsLen

8.1331.2.4 uint16_t unpack_nas_GetServingNetwork_t::MCC

8.1331.2.5 uint16_t unpack_nas_GetServingNetwork_t::MNC

8.1331.2.6 uint8_t unpack_nas_GetServingNetwork_t::Name[255]

8.1331.2.7 uint8_t unpack_nas_GetServingNetwork_t::nameSize

8.1331.2.8 swi_uint256_t unpack_nas_GetServingNetwork_t::ParamPresenceMask

8.1331.2.9 uint32_t unpack_nas_GetServingNetwork_t::PSDomain

8.1331.2.10 uint8_t unpack_nas_GetServingNetwork_t::RadioIfaces[255]

8.1331.2.11 uint8_t unpack_nas_GetServingNetwork_t::RadioIfacesSize

8.1331.2.12 uint32_t unpack_nas_GetServingNetwork_t::RAN

8.1331.2.13 uint32_t unpack_nas_GetServingNetwork_t::RegistrationState

8.1331.2.14 uint32_t unpack_nas_GetServingNetwork_t::Roaming

8.1332 unpack_nas_GetServingNetworkCapabilities_t Struct Reference

Data Fields

- uint8_t DataCapsLen
- uint8_t DataCaps [255]
- swi_uint256_t ParamPresenceMask

8.1332.1 Detailed Description

This structure contains unpack get serving network capabilities parameters.

Parameters

DataCapsLen	• Upon input, the maximum number of elements the data capabilities array can contain. • Upon output, the actual number of elements in the data capabilities array. • Bit to check in ParamPresenceMask - **17**
DataCaps[OUT]	• Data capabilities array of unsigned long type – 1 - GPRS – 2 - EDGE – 3 - HSDPA – 4 - HSUPA – 5 - WCDMA – 6 - CDMA 1xRTT – 7 - CDMA 1xEV-DO Rev 0 – 8 - CDMA 1xEV-DO Rev. A – 9 - GSM – 10 - EVDO Rev. B – 11 - LTE – 12 - HSDPA Plus – 13 - Dual Carrier HSDPA Plus • Bit to check in ParamPresenceMask - **17**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1332.2 Field Documentation

8.1332.2.1 uint8_t unpack_nas_GetServingNetworkCapabilities_t::DataCaps[255]

8.1332.2.2 uint8_t unpack_nas_GetServingNetworkCapabilities_t::DataCapsLen

8.1332.2.3 swi_uint256_t unpack_nas_GetServingNetworkCapabilities_t::ParamPresenceMask

8.1333 unpack_nas_GetSignalStrengths_t Struct Reference

Data Fields

- uint32_t len
- signed char rssi [8]
- uint32_t radio [8]
- swi_uint256_t ParamPresenceMask

8.1333.1 Detailed Description

This structure contains unpack get signal strengths parameters.

Parameters

len	• number of rssi & radio items following
rssi	• signal strength array • Bit to check in ParamPresenceMask - **16**
radio	• radio interface array • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1333.2 Field Documentation

8.1333.2.1 uint32_t unpack_nas_GetSignalStrengths_t::len

8.1333.2.2 swi_uint256_t unpack_nas_GetSignalStrengths_t::ParamPresenceMask

8.1333.2.3 uint32_t unpack_nas_GetSignalStrengths_t::radio[8]

8.1333.2.4 signed char unpack_nas_GetSignalStrengths_t::rssi[8]

8.1334 unpack_nas_PerformNetworkScan_t Struct Reference

Data Fields

- uint8_t * p3GppNetworkInstanceSize
- nas_QmiNas3GppNetworkInfo * p3GppNetworkInfoInstances
- uint8_t * pRATInstanceSize
- nas_QmiNas3GppNetworkRAT * pRATINstance
- uint8_t * pPCSInstanceSize
- nas_QmisNasPcsDigit * pPCSInstance
- uint32_t * pScanResult
- nas_QmisNasSlqsNasPCIInfo * pPCIInfo
- nas_lteOpModeTlv * pLteOpModeTlv
- swi_uint256_t ParamPresenceMask

8.1334.1 Detailed Description

Contain the network scan information.

Parameters

p3GppNetwork-InstanceSize	• Upon input, maximum number of elements that the network info instance array can contain. • Upon successful output, the actual number of elements in the network info instance array. • Bit to check in ParamPresenceMask - **16**
p3GppNetwork-InfoInstances	• Network info instance array – See nas_QmiNas3GppNetworkInfo for more information • Bit to check in ParamPresenceMask - **16**
pRATInstance-Size	• Upon input, maximum number of elements that the RAT info instance array can contain. • Upon successful output, the actual number of elements in the RAT info instance array. • Bit to check in ParamPresenceMask - **17**
pRATINstance	• RAT info instance array – See nas_QmiNas3GppNetworkRAT for more information • Bit to check in ParamPresenceMask - **17**
pPCSInstance-Size	• Upon input, maximum number of elements that the PCS Digit info instance array can contain. • Upon successful output, the actual number of elements in the PCS Digit info instance array. • Bit to check in ParamPresenceMask - **18**
pPCSInstance	• PCS Digit info instance array – See nas_QmisNasPcsDigit for more information • Bit to check in ParamPresenceMask - **18**

pScanResult	• status of network scan • 0x00 - scan successful • 0x01 - scan was aborted • 0x02 - scan did not complete due to a radio link failure recovery in progress • Bit to check in ParamPresenceMask - **19**
pPCIInfo	• PCI Information – See nas_QmisNasSlqsNasPCIInfo for more information • Bit to check in ParamPresenceMask - **23**
pLteOpMode-Tlv[OUT]	• LTE Operational Mode. • See nas_lteOpModeTlv for more information. • Bit to check in ParamPresenceMask - **26**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1334.2 Field Documentation

8.1334.2.1 nas_QmiNas3GppNetworkInfo* unpack_nas_PerformNetworkScan_t::p3GppNetworkInfoInstances

8.1334.2.2 uint8_t* unpack_nas_PerformNetworkScan_t::p3GppNetworkInstanceSize

8.1334.2.3 swi_uint256_t unpack_nas_PerformNetworkScan_t::ParamPresenceMask

8.1334.2.4 nas_lteOpModeTlv* unpack_nas_PerformNetworkScan_t::pLteOpModeTlv

8.1334.2.5 nas_QmisNasSlqsNasPCIInfo* unpack_nas_PerformNetworkScan_t::pPCIInfo

8.1334.2.6 nas_QmisNasPcsDigit* unpack_nas_PerformNetworkScan_t::pPCSInstance

8.1334.2.7 uint8_t* unpack_nas_PerformNetworkScan_t::pPCSInstanceSize

8.1334.2.8 nas_QmiNas3GppNetworkRAT* unpack_nas_PerformNetworkScan_t::pRATINstance

8.1334.2.9 uint8_t* unpack_nas_PerformNetworkScan_t::pRATInstanceSize

8.1334.2.10 uint32_t* unpack_nas_PerformNetworkScan_t::pScanResult

8.1335 unpack_nas_SetDataCapabilitiesCallback_ind_t Struct Reference

Data Fields

- uint8_t dataCapsSize
- uint8_t dataCaps [255]
- swi_uint256_t ParamPresenceMask

8.1335.1 Detailed Description

This structure contains unpack set data capabilities callback indication parameters.

Parameters

dataCapsSize	• Number of Data Capabilities • Bit to check in ParamPresenceMask - **17**
dataCaps	• Data Capabilities • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1335.2 Field Documentation

8.1335.2.1 uint8_t unpack_nas_SetDataCapabilitiesCallback_ind_t::dataCaps[255]

8.1335.2.2 uint8_t unpack_nas_SetDataCapabilitiesCallback_ind_t::dataCapsSize

8.1335.2.3 swi_uint256_t unpack_nas_SetDataCapabilitiesCallback_ind_t::ParamPresenceMask

8.1336 unpack_nas_SetEventReportInd_t Struct Reference

Data Fields

- nas_SignalStrengthTlv SSTlv
- nas_RFInfoTlv RFTlv
- nas_RejectReasonTlv RRTlv
- nas_SLQSSignalStrengthsTlv SLQSSSTlv
- swi_uint256_t ParamPresenceMask

8.1336.1 Detailed Description

This structure contains unpack set event report indication parameters.

Parameters

SSTlv	• signal strength tlv • Bit to check in ParamPresenceMask - **16**
RFTlv	• RF tlv • Bit to check in ParamPresenceMask - **17**
RRTlv	• RR tlv • Bit to check in ParamPresenceMask - **18**

SLQSSSTlv	• signal strength complete info tlv • Bit to check in ParamPresenceMask - **19** • Bit to check in ParamPresenceMask - **20** • Bit to check in ParamPresenceMask - **21** • Bit to check in ParamPresenceMask - **22** • Bit to check in ParamPresenceMask - **23** • Bit to check in ParamPresenceMask - **24** • Bit to check in ParamPresenceMask - **25** • Bit to check in ParamPresenceMask - **26**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1336.2 Field Documentation

8.1336.2.1 swi_uint256_t unpack_nas_SetEventReportInd_t::ParamPresenceMask

8.1336.2.2 nas_RFInfoTlv unpack_nas_SetEventReportInd_t::RFTlv

8.1336.2.3 nas_RejectReasonTlv unpack_nas_SetEventReportInd_t::RRTlv

8.1336.2.4 nas_SLQSSignalStrengthsTlv unpack_nas_SetEventReportInd_t::SLQSSSTlv

8.1336.2.5 nas_SignalStrengthTlv unpack_nas_SetEventReportInd_t::SSTlv

8.1337 unpack_nas_SetNasLTECphyCaIndCallback_ind_t Struct Reference

Data Fields

- nas_PhyCaAggScellIndType sPhyCaAggScellIndType
- nas_PhyCaAggScellDlBw sPhyCaAggScellDlBw
- nas_PhyCaAggScellInfo sPhyCaAggScellInfo
- nas_PhyCaAggPcellInfo sPhyCaAggPcellInfo
- nas_PhyCaAggScellIndex sPhyCaAggScellIndex
- swi_uint256_t ParamPresenceMask

8.1337.1 Detailed Description

Structure for storing the LTE PHY CA indication parameters.

Parameters

pPhyCaAgg-ScellIndType	• See nas_PhyCaAggScellIndType for more information. • Bit to check in ParamPresenceMask - **1**
sPhyCaAgg-ScellDlBw	• See nas_PhyCaAggScellDlBw for more information. • Bit to check in ParamPresenceMask - **16**

sPhyCaAgg-ScellInfo	• See nas_PhyCaAggScellInfo for more information. • Bit to check in ParamPresenceMask - **17**
sPhyCaAgg-PcellInfo	• See nas_PhyCaAggPcellInfo for more information. • Bit to check in ParamPresenceMask - **18**
sPhyCaAgg-ScellIndex	• See nas_PhyCaAggScellIndex for more information. • Bit to check in ParamPresenceMask - **19**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1337.2 Field Documentation

8.1337.2.1 swi_uint256_t unpack_nas_SetNasLTECphyCaIndCallback_ind_t::ParamPresenceMask

8.1337.2.2 nas_PhyCaAggPcellInfo unpack_nas_SetNasLTECphyCaIndCallback_ind_t::sPhyCaAggPcellInfo

8.1337.2.3 nas_PhyCaAggScellDlBw unpack_nas_SetNasLTECphyCaIndCallback_ind_t::sPhyCaAggScellDlBw

8.1337.2.4 nas_PhyCaAggScellIndex unpack_nas_SetNasLTECphyCaIndCallback_ind_t::sPhyCaAggScellIndex

8.1337.2.5 nas_PhyCaAggScellIndType unpack_nas_SetNasLTECphyCaIndCallback_ind_t::sPhyCaAggScellIndType

8.1337.2.6 nas_PhyCaAggScellInfo unpack_nas_SetNasLTECphyCaIndCallback_ind_t::sPhyCaAggScellInfo

8.1338 unpack_nas_SetNetworkPreference_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1338.1 Detailed Description

This structure contains unpack set network preference parameters.

Parameters

Tlvresult	• unpack result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1338.2 Field Documentation

8.1338.2.1 swi_uint256_t unpack_nas_SetNetworkPreference_t::ParamPresenceMask

8.1338.2.2 uint16_t unpack_nas_SetNetworkPreference_t::Tlvresult

8.1339 unpack_nas_SetRoamingIndicatorCallback_ind_t Struct Reference

Data Fields

- uint8_t roaming
- swi_uint256_t ParamPresenceMask

8.1339.1 Detailed Description

This structure contains unpack set roaming indicator callback indication parameters.

Parameters

roaming	• Roaming Indication – 0 - Roaming – 1 - Home – 2 - Roaming partner – >2 - Operator defined values • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1339.2 Field Documentation

8.1339.2.1 swi_uint256_t unpack_nas_SetRoamingIndicatorCallback_ind_t::ParamPresenceMask

8.1339.2.2 uint8_t unpack_nas_SetRoamingIndicatorCallback_ind_t::roaming

8.1340 unpack_nas_SetServingSystemCallback_ind_t Struct Reference

Data Fields

- NASServingSystemInfo SSInfo
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1340.1 Detailed Description

This structure contains unpack set serving system callback indication parameters.

Parameters

SSInfo	• Serving system parameters information – See NASServingSystemInfo for more details • Bit to check in ParamPresenceMask - **1**
TIvresult	• unpack result • Bit to check in ParamPresenceMask - **2**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1340.2 Field Documentation

8.1340.2.1 swi_uint256_t unpack_nas_SetServingSystemCallback_ind_t::ParamPresenceMask

8.1340.2.2 NASServingSystemInfo unpack_nas_SetServingSystemCallback_ind_t::SSInfo

8.1340.2.3 uint16_t unpack_nas_SetServingSystemCallback_ind_t::TIvresult

8.1341 unpack_nas_SLQSGetErrorRate_t Struct Reference

Data Fields

- uint16_t * pCDMAFrameErrRate
- uint16_t * pHDRPackErrRate
- uint8_t * pGSMBER
- uint8_t * pWCDMABER
- swi_uint256_t ParamPresenceMask

8.1341.1 Detailed Description

Structure for Error Rate unpack parameters.

Parameters

pCDMAFrame-ErrRate	• CDMA Frame Error Rate • Valid error rate values between 1 and 10000 are returned to indicate the percentage, e.g., a value of 300 means the error rate is 3%. • A value of 0xFFFF indicates that the error rate is unknown/unavailable. • Bit to check in ParamPresenceMask - **16**
pHDRPackErr-Rate	• HDR Packet Error Rate • Valid error rate values between 1 and 10000 are returned to indicate the percentage, e.g., a value of 300 means the error rate is 3%. • A value of 0xFFFF indicates that the error rate is unknown/unavailable. • Bit to check in ParamPresenceMask - **17**

pGSMBER	• GSM Bit Error Rate • Valid error rate values between 1 and 100 are returned to indicate the percentage value. • A 0% block error rate (BLER) indicates No Data. • Bit to check in ParamPresenceMask - **18**
pWCDMABER	• WCDMA Block Error Rate • Valid error rate values between 1 and 100 are returned to indicate the percentage value. • A value of 0xFF indicates that the error rate is unknown/unavailable. • Bit to check in ParamPresenceMask - **19**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1341.2 Field Documentation

8.1341.2.1 swi_uint256_t unpack_nas_SLQSGetErrorRate_t::ParamPresenceMask

8.1341.2.2 uint16_t* unpack_nas_SLQSGetErrorRate_t::pCDMAFrameErrRate

8.1341.2.3 uint8_t* unpack_nas_SLQSGetErrorRate_t::pGSMBER

8.1341.2.4 uint16_t* unpack_nas_SLQSGetErrorRate_t::pHDRPackErrRate

8.1341.2.5 uint8_t* unpack_nas_SLQSGetErrorRate_t::pWCDMABER

8.1342 unpack_nas_SlqsGetLTECphyCAInfo_t Struct Reference

Data Fields

- NasGetLTECphyCaInfo LTECphyCaInfo
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1342.1 Detailed Description

This structure contains unpack get carrier aggregation event information parameters.

Parameters

LTECphyCa	• Carrier aggregation event information – See NasGetLTECphyCaInfo for more details
Tlvresult	• unpack result • Bit to check in ParamPresenceMask - **2**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1342.2 Field Documentation

8.1342.2.1 NasGetLTECphyCaInfo unpack_nas_SlqsGetLTECphyCAInfo_t::LTECphyCaInfo

8.1342.2.2 swi_uint256_t unpack_nas_SlqsGetLTECphyCAInfo_t::ParamPresenceMask

8.1342.2.3 uint16_t unpack_nas_SlqsGetLTECphyCAInfo_t::Tlvresult

8.1343 unpack_nas_SLQSGetNetworkTime_t Struct Reference

Data Fields

- nas_timeInfo ∗ p3GPP2TimeInfo
- nas_timeInfo ∗ p3GPPTimeInfo
- swi_uint256_t ParamPresenceMask

8.1343.1 Detailed Description

This structure contains information about the GetNetworkTime response parameters.

Parameters

p3GPP2TimeInfo	[Optional] • See nas_timeInfo for more information

- ∗ - Bit to check in ParamPresenceMask - **16**

  Parameters

p3GPPTimeInfo	[Optional] – See nas_timeInfo for more information

- ∗ - Bit to check in ParamPresenceMask - **17**

  Parameters

ParamPresenceMask	– bitmask representation to indicate valid parameters.

8.1343.2 Field Documentation

8.1343.2.1 nas_timeInfo∗ unpack_nas_SLQSGetNetworkTime_t::p3GPP2TimeInfo

8.1343.2.2 nas_timeInfo∗ unpack_nas_SLQSGetNetworkTime_t::p3GPPTimeInfo

8.1343.2.3 swi_uint256_t unpack_nas_SLQSGetNetworkTime_t::ParamPresenceMask

8.1344 unpack_nas_SLQSGetOperatorNameData_t Struct Reference

Data Fields

- nas_serviceProviderName ∗ pSrvcProviderName
- nas_operatorPLMNList ∗ pOperatorPLMNList

- nas_PLMNNetworkName * pPLMNNetworkName
- nas_operatorNameString * pOperatorNameString
- nas_PLMNNetworkNameData * pNITZInformation
- swi_uint256_t ParamPresenceMask

8.1344.1 Detailed Description

Structure for Operator Name unpack.

Parameters

pSrvcProvider-Name	• Refer nas_serviceProviderName for details (Optional). • Can provide NULL if this parameter is not required. • Bit to check in ParamPresenceMask - **16**
pOperatorPLM-NList	• Refer nas_operatorPLMNList for details (Optional). • Can provide NULL if this parameter is not required. • Bit to check in ParamPresenceMask - **17**
pPLMNNetwork-Name	• Refer nas_PLMNNetworkName for details (Optional). • Can provide NULL if this parameter is not required. • Bit to check in ParamPresenceMask - **18**
pOperatorName-String	• Refer nas_operatorNameString for details (Optional). • Can provide NULL if this parameter is not required. • Bit to check in ParamPresenceMask - **19**
pNITZ-Information	• Refer nas_PLMNNetworkNameData for details (Optional). • Can provide NULL if this parameter is not required. • Bit to check in ParamPresenceMask - **20**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1344.2 Field Documentation

8.1344.2.1 swi_uint256_t unpack_nas_SLQSGetOperatorNameData_t::ParamPresenceMask

8.1344.2.2 nas_PLMNNetworkNameData* unpack_nas_SLQSGetOperatorNameData_t::pNITZInformation

8.1344.2.3 nas_operatorNameString* unpack_nas_SLQSGetOperatorNameData_t::pOperatorNameString

8.1344.2.4 nas_operatorPLMNList* unpack_nas_SLQSGetOperatorNameData_t::pOperatorPLMNList

8.1344.2.5 nas_PLMNNetworkName* unpack_nas_SLQSGetOperatorNameData_t::pPLMNNetworkName

8.1344.2.6 nas_serviceProviderName* unpack_nas_SLQSGetOperatorNameData_t::pSrvcProviderName

8.1345 unpack_nas_SLQSGetPLMNName_t Struct Reference

Data Fields

- uint8_t spnEncoding
- uint8_t spnLength
- char spn [255]
- uint8_t shortNameEn
- uint8_t shortNameCI
- uint8_t shortNameSB
- char shortNameLen
- uint8_t shortName [255]
- uint8_t longNameEn
- uint8_t longNameCI
- uint8_t longNameSB
- uint8_t longNameLen
- char longName [255]
- swi_uint256_t ParamPresenceMask

8.1345.1 Detailed Description

This structure contains unpack get operator name for specificed network parameters.

Parameters

spnEncoding	• Coding scheme used for service provider name. This value is ignored if spn_len is zero Values: – 0x00 - SMS default 7-bit coded alphabet as defined in 3GPP TS 23.038 with bit 8 set to 0 – 0x01 - UCS2 (16 bit, little-endian) 3GPP TS 23.038 – Note: This value is ignored if spnLength is zero. • Bit to check in ParamPresenceMask - **16**
spnLength	• Length of SPN which follows • Note: This SPN value is ignored if spnLength is zero and spnEncoding is 0xff. • Bit to check in ParamPresenceMask - **16**
spn	• Service Provider name string • Bit to check in ParamPresenceMask - **16**
shortNameEn	• Coding scheme used for PLMN short name. This value is ignored if PLMN short name length is zero Values: – 0x00 - SMS default 7-bit coded alphabet as defined in 3GPP TS 23.038 with bit 8 set to 0 – 0x01 - UCS2 (16 bit, little-endian) 3GPP TS 23.038 – Note: This value is ignored if shortNameLen is zero. • Bit to check in ParamPresenceMask - **16**

shortNameCI	• Indicates whether the country initials are to be added to the shortName. This value is ignored if shortNameLen is zero. Values: – 0x00 - Do not add the letters for the countrys initials to the name – 0x01 - Add the countrys initials and a text string to the name – 0xFF - Not specified – Note: This value is ignored if shortNameLen is zero. • Bit to check in ParamPresenceMask - **16**
shortNameSB	• PLMN short name spare bits. This value is ignored if shortNameLen is zero. Values: – 0x01 - Bit 8 is spare and set to 0 in octet – 0x02 - Bits 7 and 8 are spare and set to 0 in octet n – 0x03 - Bits 6 to 8 (inclusive) are spare and set to 0 in octet n – 0x04 - Bits 5 to 8 (inclusive) are spare and set to 0 in octet n – 0x05 - Bits 4 to 8 (inclusive) are spare and set to 0 in octet n – 0x06 - Bits 3 to 8 (inclusive) are spare and set to 0 in octet n – 0x07 - Bits 2 to 8 (inclusive) are spare and set to 0 in octet n – 0x00 - Carries no information about the number of spare bits in octet n – Note: This value is ignored if shortNameLen is zero. • Bit to check in ParamPresenceMask - **16**
shortNameLen	• Length of shortName which follows • Note: This shortName value is ignored if shortNameLen is zero and shortNameEn is 0xff. • Bit to check in ParamPresenceMask - **16**
shortName	• PLMN short name • Bit to check in ParamPresenceMask - **16**
longNameEn	• Coding scheme used for PLMN long name. This value is ignored if PLMN long name length is zero Values: – 0x00 - SMS default 7-bit coded alphabet as defined in 3GPP TS 23.038 with bit 8 set to 0 – 0x01 - UCS2 (16 bit, little-endian) 3GPP TS 23.038 – Note: This value is ignored if shortNameLen is zero. • Bit to check in ParamPresenceMask - **16**
longNameCI	• Indicates whether the country initials are to be added to the longName. This value is ignored if longNameLen is zero. Values: – 0x00 - Do not add the letters for the countrys initials to the name – 0x01 - Add the countrys initials and a text string to the name – 0xFF - Not specified – Note: This value is ignored if shortNameLen is zero. • Bit to check in ParamPresenceMask - **16**

longNameSB	• PLMN long name spare bits. This value is ignored if longNameLen is zero. Values: – 0x01 - Bit 8 is spare and set to 0 in octet – 0x02 - Bits 7 and 8 are spare and set to 0 in octet n – 0x03 - Bits 6 to 8 (inclusive) are spare and set to 0 in octet n – 0x04 - Bits 5 to 8 (inclusive) are spare and set to 0 in octet n – 0x05 - Bits 4 to 8 (inclusive) are spare and set to 0 in octet n – 0x06 - Bits 3 to 8 (inclusive) are spare and set to 0 in octet n – 0x07 - Bits 2 to 8 (inclusive) are spare and set to 0 in octet n – 0x00 - Carries no information about the number of spare bits in octet n – Note: This value is ignored if shortNameLen is zero. • Bit to check in ParamPresenceMask - **16**
longNameLen	• Length of longName which follows • Note: This longName value is ignored if longNameLen is zero and longNameEn is 0xff. • Bit to check in ParamPresenceMask - **16**
longName	• PLMN long name • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1345.2 Field Documentation

8.1345.2.1 char unpack_nas_SLQSGetPLMNName_t::longName[255]

8.1345.2.2 uint8_t unpack_nas_SLQSGetPLMNName_t::longNameCl

8.1345.2.3 uint8_t unpack_nas_SLQSGetPLMNName_t::longNameEn

8.1345.2.4 uint8_t unpack_nas_SLQSGetPLMNName_t::longNameLen

8.1345.2.5 uint8_t unpack_nas_SLQSGetPLMNName_t::longNameSB

8.1345.2.6 swi_uint256_t unpack_nas_SLQSGetPLMNName_t::ParamPresenceMask

8.1345.2.7 uint8_t unpack_nas_SLQSGetPLMNName_t::shortName[255]

8.1345.2.8 uint8_t unpack_nas_SLQSGetPLMNName_t::shortNameCl

8.1345.2.9 uint8_t unpack_nas_SLQSGetPLMNName_t::shortNameEn

8.1345.2.10 char unpack_nas_SLQSGetPLMNName_t::shortNameLen

8.1345.2.11 uint8_t unpack_nas_SLQSGetPLMNName_t::shortNameSB

8.1345.2.12 char unpack_nas_SLQSGetPLMNName_t::spn[255]

8.1345.2.13 uint8_t unpack_nas_SLQSGetPLMNName_t::spnEncoding

8.1345.2.14 uint8_t unpack_nas_SLQSGetPLMNName_t::spnLength

8.1346 unpack_nas_SLQSGetServingSystem_t Struct Reference

Data Fields

- nas_servSystem ServingSystem
- uint8_t RoamIndicatorVal
- nas_dataSrvCapabilities DataSrvCapabilities
- nas_currentPLMN CurrentPLMN
- uint16_t SystemID
- uint16_t NetworkID
- uint16_t BasestationID
- uint32_t BasestationLatitude
- uint32_t BasestationLongitude
- nas_roamIndList RoamingIndicatorList
- uint8_t DefaultRoamInd
- nas_qaQmi3Gpp2TimeZone Gpp2TimeZone
- uint8_t CDMA_P_Rev
- uint8_t GppTimeZone
- uint8_t GppNetworkDSTAdjustment
- uint16_t Lac
- uint32_t CellID
- uint8_t ConcSvcInfo
- uint8_t PRLInd
- uint8_t DTMInd
- nas_detailSvcInfo DetailedSvcInfo
- nas_CDMASysInfoExt CDMASystemInfoExt
- uint8_t HdrPersonality
- uint16_t TrackAreaCode
- nas_callBarStatus CallBarStatus
- swi_uint256_t ParamPresenceMask

8.1346.1 Detailed Description

This structure contains the Serving System parameters

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Parameters

ServingSystem	• Serving System • See nas_servSystem for more information • Bit to check in ParamPresenceMask - **1**

RoamIndicator-Val	• Optional parameter indicating Roaming Indicator value • Values: – 0x00 - Roaming – 0x01 - Home – 0x02 - Flashing – 0x03 and above - Operator defined values • Bit to check in ParamPresenceMask - **16**
DataSrv-Capabilities	• Optional parameter indicating Data services capability • See nas_dataSrvCapabilities for more information • Bit to check in ParamPresenceMask - **17**
CurrentPLMN	• Optional parameter indicating Current PLMN • See nas_currentPLMN for more information • Bit to check in ParamPresenceMask - **18**
SystemID	• Optional parameter indicating System ID • Bit to check in ParamPresenceMask - **19**
NetworkID	• Optional parameter indicating Network ID • Bit to check in ParamPresenceMask - **19**
BaseStationID	• Optional parameter indicating Base Station Identification Number • Bit to check in ParamPresenceMask - **20**
BaseStation-Latitude	• Optional parameter indicating Base station latitude in units of 0.25 sec,expressed as a two's complement signed number with positive numbers signifying North latitude • Bit to check in ParamPresenceMask - **20**
Basestation-Longitude	• Optional parameter indicating Base station longitude in units of 0.25 sec, expressed as a Two's complement signed number with positive numbers signifying East longitude • Bit to check in ParamPresenceMask - **20**
Roaming-IndicatorList	• Optional parameter indicating Roaming Indicator List • See nas_roamIndList for more information • Bit to check in ParamPresenceMask - **21**

DefaultRoamInd	• Optional parameter indicating Default Roaming Indicator • Values: – 0x00 - Roaming – 0x01 - Home • Bit to check in ParamPresenceMask - **22**
Gpp2TimeZone	• Optional parameter indicating 3GPP2 Time Zone • See nas_qaQmi3Gpp2TimeZone for more information • Bit to check in ParamPresenceMask - **23**
CDMA_P_Rev	• Optional parameter indicating CDMA P_Rev in use • Bit to check in ParamPresenceMask - **24**
GppTimeZone	• Optional parameter indicating Offset from Universal time, i.e., difference between local time and Universal time, in increments of 15 min. (signed value). • Bit to check in ParamPresenceMask - **26**
GppNetworkDS-TAdjustment	• Optional parameter indicating 3GPP network daylight saving adjustment • Values: – 0x00 - No adjustment for Daylight Saving Time – 0x01 - 1 hr adjustment for Daylight Saving Time – 0x02 - 2 hr adjustment for Daylight Saving Time • Bit to check in ParamPresenceMask - **27**
Lac	• Optional parameter indicating 3GPP Location Area Code • Bit to check in ParamPresenceMask - **28**
CellID	• Optional parameter indicating 3GPP Cell ID • Bit to check in ParamPresenceMask - **29**
ConcSvcInfo	• Optional parameter indicating 3GPP2 concurrent service Info • Values: – 0x00 - Concurrent service not available – 0x01 - Concurrent service available • Bit to check in ParamPresenceMask - **30**
PRLInd	• Optional parameter indicating 3GPP2 PRL Indicator • Values: – 0x00 - System not in PRL – 0x01 - System is in PRL • Bit to check in ParamPresenceMask - **31**

DTMInd	• Optional parameter indicating Dual Transfer Mode Indication(GSM Only) • Values: – 0x00 - DTM not supported – 0x01 - DTM supported • Bit to check in ParamPresenceMask - **32**
DetailedSvcInfo	• Optional parameter indicating Detailed service information • See nas_detailSvcInfo for more information • Bit to check in ParamPresenceMask - **33**
CDMASystem-InfoExt	• Optional parameter indicating CDMA System Info Ext • See nas_CDMASysInfoExt for more information • Bit to check in ParamPresenceMask - **34**
HdrPersonality	• Optional parameter indicating HDR Personality Information • Values: – 0x00 - Unknown – 0x01 - HRPD – 0x02 - eHRPD • Bit to check in ParamPresenceMask - **35**
TrackAreaCode	• Optional parameter indicating Tracking area code information for LTE • Bit to check in ParamPresenceMask - **36**
CallBarStatus	• Optional parameter indicating Call Barring Status • See nas_callBarStatus for more information • Bit to check in ParamPresenceMask - **37**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1346.2 Field Documentation

8.1346.2.1 uint16_t unpack_nas_SLQSGetServingSystem_t::BasestationID

8.1346.2.2 uint32_t unpack_nas_SLQSGetServingSystem_t::BasestationLatitude

8.1346.2.3 uint32_t unpack_nas_SLQSGetServingSystem_t::BasestationLongitude

8.1346.2.4 nas_callBarStatus unpack_nas_SLQSGetServingSystem_t::CallBarStatus

8.1346.2.5 uint8_t unpack_nas_SLQSGetServingSystem_t::CDMA_P_Rev

8.1346.2.6 nas_CDMASysInfoExt unpack_nas_SLQSGetServingSystem_t::CDMASystemInfoExt

8.1346.2.7 uint32_t unpack_nas_SLQSGetServingSystem_t::CellID

8.1346.2.8 uint8_t unpack_nas_SLQSGetServingSystem_t::ConcSvcInfo

8.1346.2.9 nas_currentPLMN unpack_nas_SLQSGetServingSystem_t::CurrentPLMN

8.1346.2.10 nas_dataSrvCapabilities unpack_nas_SLQSGetServingSystem_t::DataSrvCapabilities

8.1346.2.11 uint8_t unpack_nas_SLQSGetServingSystem_t::DefaultRoamInd

8.1346.2.12 nas_detailSvcInfo unpack_nas_SLQSGetServingSystem_t::DetailedSvcInfo

8.1346.2.13 uint8_t unpack_nas_SLQSGetServingSystem_t::DTMInd

8.1346.2.14 nas_qaQmi3Gpp2TimeZone unpack_nas_SLQSGetServingSystem_t::Gpp2TimeZone

8.1346.2.15 uint8_t unpack_nas_SLQSGetServingSystem_t::GppNetworkDSTAdjustment

8.1346.2.16 uint8_t unpack_nas_SLQSGetServingSystem_t::GppTimeZone

8.1346.2.17 uint8_t unpack_nas_SLQSGetServingSystem_t::HdrPersonality

8.1346.2.18 uint16_t unpack_nas_SLQSGetServingSystem_t::Lac

8.1346.2.19 uint16_t unpack_nas_SLQSGetServingSystem_t::NetworkID

8.1346.2.20 swi_uint256_t unpack_nas_SLQSGetServingSystem_t::ParamPresenceMask

8.1346.2.21 uint8_t unpack_nas_SLQSGetServingSystem_t::PRLInd

8.1346.2.22 uint8_t unpack_nas_SLQSGetServingSystem_t::RoamIndicatorVal

8.1346.2.23 nas_roamIndList unpack_nas_SLQSGetServingSystem_t::RoamingIndicatorList

8.1346.2.24 nas_servSystem unpack_nas_SLQSGetServingSystem_t::ServingSystem

8.1346.2.25 uint16_t unpack_nas_SLQSGetServingSystem_t::SystemID

8.1346.2.26 uint16_t unpack_nas_SLQSGetServingSystem_t::TrackAreaCode

8.1347 unpack_nas_SLQSGetSignalStrength_t Struct Reference

Data Fields

- uint16_t signalStrengthReqMask
- uint16_t rxSignalStrengthListLen
- nas_rxSignalStrengthListElement rxSignalStrengthList [18]
- uint16_t ecioListLen
- nas_ecioListElement ecioList [18]
- int32_t Io
- uint8_t sinr
- uint16_t errorRateListLen
- nas_errorRateListElement errorRateList [18]
- nas_rsrqInformation rsrqInfo
- int16_t ltesnr

- int16_t ltersrp
- swi_uint256_t ParamPresenceMask

8.1347.1 Detailed Description

This structure contains the Signal Strength Information

Parameters

signalStrength-ReqMask	• Request Mask – Request additional signal information for: Bit 0 - RSSI Information bit Valid values are: 0 - Do Not Request Additional Info for RSSI 1 - Request Additional Info for RSSI Bit 1 - ECIO Information bit Valid values are: 0 - Do Not Request Additional Info for ECIO 1 - Request Additional Info for ECIO Bit 2 - IO Information bit Valid values are: 0 - Do Not Request Additional Info for IO 1 - Request Additional Info for IO Bit 3 - SINR Information bit Valid values are: 0 - Do Not Request Additional Info for SINR 1 - Request Additional Info for SINR Bit 4 - ERROR RATE Information bit Valid values are: 0 - Do Not Request Additional Info for Error Rate 1 - Request Additional Info for Error Rate Bit 5 - RSRQ Information bit Valid values are: 0 - Do Not Request Additional Info for RSRQ 1 - Request Additional Info for RSRQ Bit 6 - LTE SNR information bit Valid values are: 0 - Do not request additional information for LTE SNR 1 - Request additional information for LTE SNR Bit 7 - LTE RSRP Information bit Valid values are: 0 - Do not request additional information for LTE RSRP 1 - Request additional information for LTE RSRP • Bit to check in ParamPresenceMask - **1**
rxSignal-StrengthListLen	• Number of elements in Receive Signal Strength List • Bit to check in ParamPresenceMask - **17**
rxSignal-StrengthList	• See nas_rxSignalStrengthListElement for more information • Bit to check in ParamPresenceMask - **17**
ecioListLen	• Number of elements in ECIO List • Bit to check in ParamPresenceMask - **18**

ecioList	• See nas_ecioListElement for more information • Bit to check in ParamPresenceMask - **18**
Io	• Received Io in dBm; IO is only applicable for 1xEV-DO • Bit to check in ParamPresenceMask - **19**
sinr	• SINR level – SINR is only applicable for 1xEV-DO; valid levels are 0 to 8 where maximum value for 0 - SINR_LEVEL_0 is -9 dB 1 - SINR_LEVEL_1 is -6 dB 2 - SINR_LEVEL_2 is -4.5 dB 3 - SINR_LEVEL_3 is -3 dB 4 - SINR_LEVEL_4 is -2 dB 5 - SINR_LEVEL_5 is +1 dB 6 - SINR_LEVEL_6 is +3 dB 7 - SINR_LEVEL_7 is +6 dB 8 - SINR_LEVEL_8 is +9 dB • Bit to check in ParamPresenceMask - **20**
errorRateListLen	• Number of elements in Error Rate List • Bit to check in ParamPresenceMask - **21**
errorRateList	• See nas_errorRateListElement for more information • Bit to check in ParamPresenceMask - **21**
rsrqInfo	• See nas_rsrqInformation for more information • Bit to check in ParamPresenceMask - **22**
ltesnr	• LTE SNR level as a scaled integer in units of 0.1 dB; e.g., -16 dB has a value of -160 and 24.6 dB has a value of 246. LTE SNR is included only when the current serving system is LTE • Bit to check in ParamPresenceMask - **23**
ltersrp	• LTE SNR level as a scaled integer in units of 0.1 dB; e.g., -16 dB has a value of -160 and 24.6 dB has a value of 246. LTE SNR is included only when the current serving system is LTE • Bit to check in ParamPresenceMask - **24**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1347.2 Field Documentation

8.1347.2.1 **nas_ecioListElement** unpack_nas_SLQSGetSignalStrength_t::ecioList[18]

8.1347.2.2 uint16_t unpack_nas_SLQSGetSignalStrength_t::ecioListLen

8.1347.2.3 **nas_errorRateListElement** unpack_nas_SLQSGetSignalStrength_t::errorRateList[18]

8.1347.2.4 uint16_t unpack_nas_SLQSGetSignalStrength_t::errorRateListLen

8.1347.2.5 int32_t unpack_nas_SLQSGetSignalStrength_t::Io

8.1347.2.6 int16_t unpack_nas_SLQSGetSignalStrength_t::ltersrp

8.1347.2.7 int16_t unpack_nas_SLQSGetSignalStrength_t::ltesnr

8.1347.2.8 swi_uint256_t unpack_nas_SLQSGetSignalStrength_t::ParamPresenceMask

8.1347.2.9 nas_rsrqInformation unpack_nas_SLQSGetSignalStrength_t::rsrqInfo

8.1347.2.10 nas_rxSignalStrengthListElement unpack_nas_SLQSGetSignalStrength_t::rxSignalStrengthList[18]

8.1347.2.11 uint16_t unpack_nas_SLQSGetSignalStrength_t::rxSignalStrengthListLen

8.1347.2.12 uint16_t unpack_nas_SLQSGetSignalStrength_t::signalStrengthReqMask

8.1347.2.13 uint8_t unpack_nas_SLQSGetSignalStrength_t::sinr

8.1348 unpack_nas_SLQSGetSysInfo_t Struct Reference

Data Fields

- nas_SrvStatusInfo * pCDMASrvStatusInfo
- nas_SrvStatusInfo * pHDRSrvStatusInfo
- nas_GSMSrvStatusInfo * pGSMSrvStatusInfo
- nas_GSMSrvStatusInfo * pWCDMASrvStatusInfo
- nas_GSMSrvStatusInfo * pLTESrvStatusInfo
- nas_CDMASysInfo * pCDMASysInfo
- nas_HDRSysInfo * pHDRSysInfo
- nas_GSMSysInfo * pGSMSysInfo
- nas_WCDMASysInfo * pWCDMASysInfo
- nas_LTESysInfo * pLTESysInfo
- nas_AddCDMASysInfo * pAddCDMASysInfo
- uint16_t * pAddHDRSysInfo
- nas_AddSysInfo * pAddGSMSysInfo
- nas_AddSysInfo * pAddWCDMASysInfo
- uint16_t * pAddLTESysInfo
- nas_CallBarringSysInfo * pGSMCallBarringSysInfo
- nas_CallBarringSysInfo * pWCDMACallBarringSysInfo
- uint8_t * pLTEVoiceSupportSysInfo
- uint8_t * pGSMCipherDomainSysInfo
- uint8_t * pWCDMACipherDomainSysInfo
- uint32_t * pCampedCiotLteOpMode
- swi_uint256_t ParamPresenceMask

8.1348.1 Detailed Description

This structure contains unpack get system information parameters.

Parameters

pCDMASrvStatusInfo	• See nas_SrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **16**
pHDRSrvStatusInfo	• See nas_SrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **17**
pGSMSrvStatusInfo	• See nas_GSMSrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **18**
pWCDMASrvStatusInfo	• See nas_GSMSrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **19**
pLTESrvStatusInfo	• See nas_GSMSrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **20**
pCDMASysInfo	• See nas_CDMASysInfo for more information. • Bit to check in ParamPresenceMask - **21**
pHDRSysInfo	• See nas_HDRSysInfo for more information. • Bit to check in ParamPresenceMask - **22**
pGSMSysInfo	• See nas_GSMSysInfo for more information. • Bit to check in ParamPresenceMask - **23**
pWCDMASysInfo	• See nas_WCDMASysInfo for more information. • Bit to check in ParamPresenceMask - **24**
pLTESysInfo	• See nas_LTESysInfo for more information. • Bit to check in ParamPresenceMask - **25**
pAddCDMASysInfo	• See nas_AddCDMASysInfo for more information. • Bit to check in ParamPresenceMask - **26**
pAddHDRSysInfo	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used. • Bit to check in ParamPresenceMask - **27**

pAddGSMSysInfo	• See nas_AddSysInfo for more information. • Bit to check in ParamPresenceMask - **28**
pAddWCDMASysInfo	• See nas_AddSysInfo for more information. • Bit to check in ParamPresenceMask - **29**
pAddLTESysInfo	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used. • Bit to check in ParamPresenceMask - **30**
pGSMCallBarringSysInfo	• See nas_CallBarringSysInfo for more information. • Bit to check in ParamPresenceMask - **31**
pWCDMACallBarringSysInfo	• See nas_CallBarringSysInfo for more information. • Bit to check in ParamPresenceMask - **32**
pLTEVoiceSupportSysInfo	• Indicates voice support status on LTE. – 0x00 - Voice is not supported – 0x01 - Voice is supported • Bit to check in ParamPresenceMask - **33**
pGSMCipherDomainSysInfo	• Ciphering on the service domain. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched • Bit to check in ParamPresenceMask - **34**
pWCDMACipherDomainSysInfo	• Ciphering on the service domain. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched • Bit to check in ParamPresenceMask - **35**

pCampedCiot-LteOpMode	• Camped CIOT LTE Operational Mode. • Values – NAS_CIOT_SYS_MODE_NO_SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_NB1 (0x03) - Camped on LTE NB1 • Bit to check in ParamPresenceMask - **73**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1348.2 Field Documentation

8.1348.2.1 nas_AddCDMASysInfo∗ unpack_nas_SLQSGetSysInfo_t::pAddCDMASysInfo

8.1348.2.2 nas_AddSysInfo∗ unpack_nas_SLQSGetSysInfo_t::pAddGSMSysInfo

8.1348.2.3 uint16_t∗ unpack_nas_SLQSGetSysInfo_t::pAddHDRSysInfo

8.1348.2.4 uint16_t∗ unpack_nas_SLQSGetSysInfo_t::pAddLTESysInfo

8.1348.2.5 nas_AddSysInfo∗ unpack_nas_SLQSGetSysInfo_t::pAddWCDMASysInfo

8.1348.2.6 swi_uint256_t unpack_nas_SLQSGetSysInfo_t::ParamPresenceMask

8.1348.2.7 uint32_t∗ unpack_nas_SLQSGetSysInfo_t::pCampedCiotLteOpMode

8.1348.2.8 nas_SrvStatusInfo∗ unpack_nas_SLQSGetSysInfo_t::pCDMASrvStatusInfo

8.1348.2.9 nas_CDMASysInfo∗ unpack_nas_SLQSGetSysInfo_t::pCDMASysInfo

8.1348.2.10 nas_CallBarringSysInfo∗ unpack_nas_SLQSGetSysInfo_t::pGSMCallBarringSysInfo

8.1348.2.11 uint8_t∗ unpack_nas_SLQSGetSysInfo_t::pGSMCipherDomainSysInfo

8.1348.2.12 nas_GSMSrvStatusInfo∗ unpack_nas_SLQSGetSysInfo_t::pGSMSrvStatusInfo

8.1348.2.13 nas_GSMSysInfo∗ unpack_nas_SLQSGetSysInfo_t::pGSMSysInfo

8.1348.2.14 nas_SrvStatusInfo∗ unpack_nas_SLQSGetSysInfo_t::pHDRSrvStatusInfo

8.1348.2.15 nas_HDRSysInfo∗ unpack_nas_SLQSGetSysInfo_t::pHDRSysInfo

8.1348.2.16 nas_GSMSrvStatusInfo∗ unpack_nas_SLQSGetSysInfo_t::pLTESrvStatusInfo

8.1348.2.17 nas_LTESysInfo∗ unpack_nas_SLQSGetSysInfo_t::pLTESysInfo

8.1348.2.18 uint8_t∗ unpack_nas_SLQSGetSysInfo_t::pLTEVoiceSupportSysInfo

8.1348.2.19 nas_CallBarringSysInfo∗ unpack_nas_SLQSGetSysInfo_t::pWCDMACallBarringSysInfo

8.1348.2.20 uint8_t* unpack_nas_SLQSGetSysInfo_t::pWCDMACipherDomainSysInfo

8.1348.2.21 nas_GSMSrvStatusInfo* unpack_nas_SLQSGetSysInfo_t::pWCDMASrvStatusInfo

8.1348.2.22 nas_WCDMASysInfo* unpack_nas_SLQSGetSysInfo_t::pWCDMASysInfo

8.1349 unpack_nas_SLQSGetSysSelectionPref_t Struct Reference

Data Fields

- uint8_t * pEmerMode
- uint16_t * pModePref
- uint64_t * pBandPref
- uint16_t * pPRLPref
- uint16_t * pRoamPref
- uint64_t * pLTEBandPref
- uint8_t * pNetSelPref
- uint32_t * pSrvDomainPref
- uint32_t * pGWAcqOrderPref
- swi_uint256_t ParamPresenceMask

8.1349.1 Detailed Description

This structure contains unpack get get system selection preferences parameters.

Parameters

pEmerMode	• Optional parameter specifying the emergency Mode • Values: – 0 - OFF (normal) – 1 - ON (Emergency)

- * - Bit to check in ParamPresenceMask - **16**

Parameters

pModePref	– Optional parameter – Bit Mask indicating the radio technology mode preference – Bit values: * Bit 0 - cdma2000 1x * Bit 1 - cdma2000 HRPD(1xEV-DO) * Bit 2 - GSM * Bit 3 - UMTS * Bit 4 - LTE

- * - Bit to check in ParamPresenceMask - **17**

Parameters

pBandPref	– Optional parameter – Bit mask representing the band preference – Bit values: * Bit 0 - Band Class 0, A-System * Bit 1 - Band Class 0, B-System, Band Class 0 AB, GSM 850 Band * Bit 2 - Band Class 1, all blocks * Bit 3 - Band Class 2 place holder * Bit 4 - Band Class 3, A-System * Bit 5 - Band Class 4, all blocks * Bit 6 - Band Class 5, all blocks * Bit 7 - GSM_DCS_1800 band * Bit 8 - GSM Extended GSM (E-GSM) 900 band * Bit 9 - GSM Primary GSM (P-GSM) 900 band * Bit 10 - Band Class 6 * Bit 11 - Band Class 7 * Bit 12 - Band Class 8 * Bit 13 - Band Class 9 * Bit 14 - Band Class 10 * Bit 15 - Band Class 11 * Bit 16 - GSM 450 band * Bit 17 - GSM 480 band * Bit 18 - GSM 750 band * Bit 19 - GSM 850 band * Bit 20 - GSM Railways GSM 900 Band * Bit 21 - GSM PCS 1900 band * Bit 22 - WCDMA Europe, Japan, and China IMT 2100 band * Bit 23 - WCDMA U.S. PCS 1900 band * Bit 24 - WCDMA Europe and China DCS 1800 band * Bit 25 - WCDMA U.S. 1700 band * Bit 26 - WCDMA U.S. 850 band * Bit 27 - WCDMA Japan 800 band * Bit 28 - Band Class 12 * Bit 29 - Band Class 14 * Bit 30 - Reserved * Bit 31 - Band Class 15 * Bit 32 to 47 - Reserved * Bit 48 - WCDMA Europe 2600 band * Bit 49 - WCDMA Europe and Japan 900 band * Bit 50 - WCDMA Japan 1700 band * Bit 51 to 55 - Reserved * Bit 56 - Band Class 16 * Bit 57 - Band Class 17 * Bit 58 - Band Class 18 * Bit 59 - Band Class 19 * Bit 60 to 64 - Reserved

- $*$ - Bit to check in ParamPresenceMask - **18**

Parameters

pPRLPref	– Optional parameter indicating the CDMA PRL Preference – Values: * 0x0001 - Acquire available system only on the A side * 0x0002 - Acquire available system only on the B side * 0x3FFF - Acquire any available systems

- ∗ - Bit to check in ParamPresenceMask - **19**

Parameters

pRoamPref	– Optional parameter indicating the roaming Preference – Values: * 0x01 - Acquire only systems for which the roaming indicator is off * 0x02 - Acquire a system as long as its roaming indicator is not off * 0x03 - Acquire only systems for which the roaming indicator is off or solid on, i.e. not flashing; CDMA only * 0xFF - Acquire systems, regardless of their roaming indicator

- ∗ - Bit to check in ParamPresenceMask - **20**

Parameters

pLTEBandPref	– Optional parameter – Bit mask representing the LTE band preference – Bit Values * Bit 0 - E-UTRA Operating Band 1 * Bit 1 - E-UTRA Operating Band 2 * Bit 2 - E-UTRA Operating Band 3 * Bit 3 - E-UTRA Operating Band 4 * Bit 4 - E-UTRA Operating Band 5 * Bit 5 - E-UTRA Operating Band 6 * Bit 6 - E-UTRA Operating Band 7 * Bit 7 - E-UTRA Operating Band 8 * Bit 8 - E-UTRA Operating Band 9 * Bit 9 - E-UTRA Operating Band 10 * Bit 10 - E-UTRA Operating Band 11 * Bit 11 - E-UTRA Operating Band 12 * Bit 12 - E-UTRA Operating Band 13 * Bit 13 - E-UTRA Operating Band 14 * Bit 16 - E-UTRA Operating Band 17 * Bit 17 - E-UTRA Operating Band 18 * Bit 18 - E-UTRA Operating Band 19 * Bit 19 - E-UTRA Operating Band 20 * Bit 20 - E-UTRA Operating Band 21 * Bit 32 - E-UTRA Operating Band 33 * Bit 33 - E-UTRA Operating Band 34 * Bit 34 - E-UTRA Operating Band 35 * Bit 35 - E-UTRA Operating Band 36 * Bit 36 - E-UTRA Operating Band 37 * Bit 37 - E-UTRA Operating Band 38 * Bit 38 - E-UTRA Operating Band 39 * Bit 39 - E-UTRA Operating Band 40 * All other bits are reserved

- ∗ - Bit to check in ParamPresenceMask - **21**

Parameters

pNetSelPref	– Optional parameter indicating network selection preference – Values: * 0x00 - Automatic network selection * 0x01 - Manual network selection.

- ∗ - Bit to check in ParamPresenceMask - **22**

Parameters

pSrvDomainPref	– Optional parameter indicating Service domain preference – Values: * 0x00 - Circuit switched only * 0x01 - Packet switched only * 0x02 - Circuit switched and packet switched * 0x03 - Packet switched attach * 0x04 - Packet switched detach

- ∗ - Bit to check in ParamPresenceMask - **24**

Parameters

pGWAcqOrder-Pref	– Optional parameter indicating GSM/WCDMA Acquisition order Preference – Values: * 0x00 - Automatic * 0x01 - GSM then WCDMA * 0x02 - WCDMA then GSM

- ∗ - Bit to check in ParamPresenceMask - **25**

Parameters

ParamPresence-Mask	– bitmask representation to indicate valid parameters.

8.1349.2 Field Documentation

8.1349.2.1 swi_uint256_t unpack_nas_SLQSGetSysSelectionPref_t::ParamPresenceMask

8.1349.2.2 uint64_t∗ unpack_nas_SLQSGetSysSelectionPref_t::pBandPref

8.1349.2.3 uint8_t∗ unpack_nas_SLQSGetSysSelectionPref_t::pEmerMode

8.1349.2.4 uint32_t∗ unpack_nas_SLQSGetSysSelectionPref_t::pGWAcqOrderPref

8.1349.2.5 uint64_t∗ unpack_nas_SLQSGetSysSelectionPref_t::pLTEBandPref

8.1349.2.6 uint16_t∗ unpack_nas_SLQSGetSysSelectionPref_t::pModePref

8.1349.2.7 uint8_t∗ unpack_nas_SLQSGetSysSelectionPref_t::pNetSelPref

8.1349.2.8 uint16_t∗ unpack_nas_SLQSGetSysSelectionPref_t::pPRLPref

8.1349.2.9 uint16_t∗ unpack_nas_SLQSGetSysSelectionPref_t::pRoamPref

8.1349.2.10 uint32_t∗ unpack_nas_SLQSGetSysSelectionPref_t::pSrvDomainPref

8.1350 unpack_nas_SLQSGetSysSelectionPrefExt_t Struct Reference

Data Fields

- nas_EmerModeTlv * pEmerMode
- nas_ModePrefTlv * pModePref
- nas_BandPrefTlv * pBandPref
- nas_PRLPrefTlv * pPRLPref
- nas_RoamPrefTlv * pRoamPref
- nas_LTEBandPrefTlv * pLTEBandPref
- nas_NetSelPrefTlv * pNetSelPref
- nas_SrvDomainPrefTlv * pSrvDomainPref
- nas_GWAcqOrderPrefTlv * pGWAcqOrderPref
- nas_AcqOrderPrefTlv * pAcqOrderPref
- nas_RatDisabledMaskTlv * pRatDisabledMask
- nas_CiotLteOpModePrefTlv * pCiotLteOpModePref
- nas_LteM1BandPrefTlv * pLteM1BandPref
- nas_LteNb1BandPrefTlv * pLteNb1BandPref
- nas_CiotAcqOrderPrefTlv * pCiotAcqOrderPref
- nas_NR5gBandPrefTlv * pNr5gBandPref
- nas_LTEBandPrefExtTlv * pLTEBandPrefExt

8.1350.1 Detailed Description

Structure for storing the current preferred system selection settings for the device.

Parameters

pEmerMode	• Optional parameter specifying the emergency Mode • See nas_EmerModeTlv for more information
pModePref	• Optional parameterindicating the radio technology mode preference • See nas_ModePrefTlv for more information
pBandPref	• Optional parameter representing the band preference • See nas_BandPrefTlv for more information
pPRLPref	• Optional parameter indicating the CDMA PRL Preference • See nas_PRLPrefTlv for more information
pRoamPref	• Optional parameter indicating the roaming Preference • See nas_RoamPrefTlv for more information
pLTEBandPref	• Optional parameter representing the LTE band preference • See nas_LTEBandPrefTlv for more information
pNetSelPref	• Optional parameter indicating network selection preference • See nas_NetSelPrefTlv for more information

pSrvDomainPref	• Optional parameter indicating Service domain preference • See nas_SrvDomainPrefTlv for more information
pGWAcqOrder-Pref	• Optional parameter indicating GSM/WCDMA Acquisition order Preference • See nas_GWAcqOrderPrefTlv for more information
pAcqOrderPref	• Optional parameter • Acquisition Order Preference • See nas_AcqOrderPrefTlv for more information
pRatDisabled-Mask	• Optional parameter representing the radio technologies that are disabled. • See nas_RatDisabledMaskTlv for more information
pCiotLteOp-ModePref	• Optional parameter • CIOT LTE Operational Mode Preference • See nas_CiotLteOpModePrefTlv for more information
pLteM1BandPref	• Optional parameter representing the LTE M1 band preference • See nas_LteM1BandPrefTlv for more information
pLteNb1Band-Pref	• Optional parameter representing the LTE NB1 band preference. • See nas_LteNb1BandPrefTlv for more information
pCiotAcqOrder-Pref	• Optional parameter indicating CIOT Acquisition Order Preference • See nas_CiotAcqOrderPrefTlv for more information
pNr5gBandPref	• Optional parameter indicating NR5G Band Preference • See nas_NR5gBandPrefTlv for more information
pLTEBandPref-Ext	• Optional parameter indicating LTE Band Preference Extended • See nas_LTEBandPrefExtTlv for more information

8.1350.2 Field Documentation

8.1350.2.1 nas_AcqOrderPrefTlv∗ unpack_nas_SLQSGetSysSelectionPrefExt_t::pAcqOrderPref

8.1350.2.2 nas_BandPrefTlv∗ unpack_nas_SLQSGetSysSelectionPrefExt_t::pBandPref

8.1350.2.3 nas_CiotAcqOrderPrefTlv∗ unpack_nas_SLQSGetSysSelectionPrefExt_t::pCiotAcqOrderPref

8.1350.2.4 nas_CiotLteOpModePrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pCiotLteOpModePref

8.1350.2.5 nas_EmerModeTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pEmerMode

8.1350.2.6 nas_GWAcqOrderPrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pGWAcqOrderPref

8.1350.2.7 nas_LTEBandPrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pLTEBandPref

8.1350.2.8 nas_LTEBandPrefExtTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pLTEBandPrefExt

8.1350.2.9 nas_LteM1BandPrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pLteM1BandPref

8.1350.2.10 nas_LteNb1BandPrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pLteNb1BandPref

8.1350.2.11 nas_ModePrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pModePref

8.1350.2.12 nas_NetSelPrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pNetSelPref

8.1350.2.13 nas_NR5gBandPrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pNr5gBandPref

8.1350.2.14 nas_PRLPrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pPRLPref

8.1350.2.15 nas_RatDisabledMaskTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pRatDisabledMask

8.1350.2.16 nas_RoamPrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pRoamPref

8.1350.2.17 nas_SrvDomainPrefTlv* unpack_nas_SLQSGetSysSelectionPrefExt_t::pSrvDomainPref

8.1351 unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t Struct Reference

Data Fields

- nas_EdrxEnableType edrxEnableTypeTlv
- nas_EdrxCycleLength edrxCycleLengthTlv
- nas_EdrxPagingTimeWindow edrxPagingTimeWindowTlv
- nas_EdrxRatType edrxRatTypeTlv
- nas_EdrxCiotLteMode edrxCiotLteModeTlv
- swi_uint256_t ParamPresenceMask

8.1351.1 Detailed Description

Structure for storing the eDRX Change Info indication parameters.

Parameters

edrxEnableTypeTlv	• See nas_EdrxEnableType for more information. • Bit to check in ParamPresenceMask - **16**
edrxCycleLengthTlv	• See nas_EdrxCycleLength for more information. • Bit to check in ParamPresenceMask - **17**

edrxPagingTime-WindowTlv	• See nas_EdrxPagingTimeWindow for more information. • Bit to check in ParamPresenceMask - **18**
edrxRatTypeTlv	• See nas_EdrxRatType for more information. • Bit to check in ParamPresenceMask - **19**
edrxCiotLte-ModeTlv	• See nas_EdrxCiotLteMode for more information. • Bit to check in ParamPresenceMask - **20**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1351.2 Field Documentation

8.1351.2.1 nas_EdrxCiotLteMode unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t::edrxCiotLteModeTlv

8.1351.2.2 nas_EdrxCycleLength unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t::edrxCycleLengthTlv

8.1351.2.3 nas_EdrxEnableType unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t::edrxEnableTypeTlv

8.1351.2.4 nas_EdrxPagingTimeWindow unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t::edrxPagingTimeWindow-Tlv

8.1351.2.5 nas_EdrxRatType unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t::edrxRatTypeTlv

8.1351.2.6 swi_uint256_t unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t::ParamPresenceMask

8.1352 unpack_nas_SLQSNasGet3GPP2Subscription_t Struct Reference

Data Fields

- nas_namName * pNAMNameInfo
- nas_dirNum * pDirNum
- nas_homeSIDNID * pHomeSIDNID
- nas_minBasedIMSI * pMinBasedIMSI
- nas_trueIMSI * pTrueIMSI
- nas_CDMAChannel * pCDMAChannel
- swi_uint256_t ParamPresenceMask

8.1352.1 Detailed Description

Structure for 3GPP2Subscription unpack.

Parameters

pNAMNameInfo	[Optional] • See nas_namName for more information • Bit to check in ParamPresenceMask - **16**

pDirNum	[Optional] • See nas_dirNum for more information • Bit to check in ParamPresenceMask - **17**
pHomeSIDNID	[Optional] • See nas_homeSIDNID for more information • Bit to check in ParamPresenceMask - **18**
pMinBasedIMSI	[Optional] • See nas_minBasedIMSI for more information • Bit to check in ParamPresenceMask - **19**
pTrueIMSI	[Optional] • See nas_trueIMSI for more information • Bit to check in ParamPresenceMask - **20**
pCDMAChannel	[Optional] • See nas_CDMAChannel for more information • Bit to check in ParamPresenceMask - **21**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1352.2 Field Documentation

8.1352.2.1 swi_uint256_t unpack_nas_SLQSNasGet3GPP2Subscription_t::ParamPresenceMask

8.1352.2.2 nas_CDMAChannel* unpack_nas_SLQSNasGet3GPP2Subscription_t::pCDMAChannel

8.1352.2.3 nas_dirNum* unpack_nas_SLQSNasGet3GPP2Subscription_t::pDirNum

8.1352.2.4 nas_homeSIDNID* unpack_nas_SLQSNasGet3GPP2Subscription_t::pHomeSIDNID

8.1352.2.5 nas_minBasedIMSI* unpack_nas_SLQSNasGet3GPP2Subscription_t::pMinBasedIMSI

8.1352.2.6 nas_namName* unpack_nas_SLQSNasGet3GPP2Subscription_t::pNAMNameInfo

8.1352.2.7 nas_trueIMSI* unpack_nas_SLQSNasGet3GPP2Subscription_t::pTrueIMSI

8.1353 unpack_nas_SLQSNasGetCellLocationInfo_t Struct Reference

Data Fields

- nas_GERANInfo * pGERANInfo
- nas_UMTSInfo * pUMTSInfo
- nas_CDMAInfo * pCDMAInfo
- nas_LTEInfoIntrafreq * pLTEInfoIntrafreq
- nas_LTEInfoInterfreq * pLTEInfoInterfreq
- nas_LTEInfoNeighboringGSM * pLTEInfoNeighboringGSM
- nas_LTEInfoNeighboringWCDMA * pLTEInfoNeighboringWCDMA
- uint32_t * pUMTSCellID

- nas_WCDMAInfoLTENeighborCell * pWCDMAInfoLTENeighborCell
- swi_uint256_t ParamPresenceMask

8.1353.1 Detailed Description

This structure contains information about the Get Cell Location response parameters.

Parameters

pGERANInfo	• See nas_GERANInfo for more information. • Bit to check in ParamPresenceMask - **16**
pUMTSInfo	• See nas_UMTSInfo for more information. • Bit to check in ParamPresenceMask - **17**
pCDMAInfo	• See nas_CDMAInfo for more information. • Bit to check in ParamPresenceMask - **18**
pLTEInfo-Intrafreq	• See nas_LTEInfoIntrafreq for more information. • Bit to check in ParamPresenceMask - **19**
pLTEInfo-Interfreq	• See nas_LTEInfoInterfreq for more information. • Bit to check in ParamPresenceMask - **20**
pLTEInfo-NeighboringGSM	• See nas_LTEInfoNeighboringGSM for more information. • Bit to check in ParamPresenceMask - **21**
pLTEInfo-NeighboringWCDMA	• See nas_LTEInfoNeighboringWCDMA for more information. • Bit to check in ParamPresenceMask - **22**
pUMTSCellID	• Cell ID. • 0xFFFFFFFF indicates cell ID information is not present. • Bit to check in ParamPresenceMask - **23**
pWCDMAInfoLTENeighborCell	• See nas_WCDMAInfoLTENeighborCell for more information. • Bit to check in ParamPresenceMask - **24**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1353.2 Field Documentation

8.1353.2.1 swi_uint256_t unpack_nas_SLQSNasGetCellLocationInfo_t::ParamPresenceMask

8.1353.2.2 nas_CDMAInfo* unpack_nas_SLQSNasGetCellLocationInfo_t::pCDMAInfo

8.1353.2.3 nas_GERANInfo* unpack_nas_SLQSNasGetCellLocationInfo_t::pGERANInfo

8.1353.2.4 nas_LTEInfoInterfreq* unpack_nas_SLQSNasGetCellLocationInfo_t::pLTEInfoInterfreq

8.1353.2.5 nas_LTEInfoIntrafreq* unpack_nas_SLQSNasGetCellLocationInfo_t::pLTEInfoIntrafreq

8.1353.2.6 nas_LTEInfoNeighboringGSM* unpack_nas_SLQSNasGetCellLocationInfo_t::pLTEInfoNeighboringGSM

8.1353.2.7 nas_LTEInfoNeighboringWCDMA* unpack_nas_SLQSNasGetCellLocationInfo_t::pLTEInfoNeighboringWCDMA

8.1353.2.8 uint32_t* unpack_nas_SLQSNasGetCellLocationInfo_t::pUMTSCellID

8.1353.2.9 nas_UMTSInfo* unpack_nas_SLQSNasGetCellLocationInfo_t::pUMTSInfo

8.1353.2.10 nas_WCDMAInfoLTENeighborCell* unpack_nas_SLQSNasGetCellLocationInfo_t::pWCDMAInfoLTENeighborCell

8.1354 unpack_nas_SLQSNASGeteDRXParams_t Struct Reference

Data Fields

- uint8_t * pCycleLen
- uint8_t * pPagingTimeWindow
- uint8_t * pEdrxEnable
- swi_uint256_t ParamPresenceMask

8.1354.1 Detailed Description

This structure contains the SLQSNASGeteDRXParams unpack parameters.

Parameters

pCycleLen	[Optional] • eDRX cycle length • Value is per 3GPP TS 24.008 Rel-13 Section 10.5.5.32 • Bit to check in ParamPresenceMask - **16**
pPagingTime-Window	[Optional] • eDRX paging time window • Value is per 3GPP TS 24.008 Rel-13 Section10.5.5.32 • Bit to check in ParamPresenceMask - **17**
pEdrxEnable	[Optional] • eDRX Enable • Values – 0x00 - Disable – 0x01 - Enable • Bit to check in ParamPresenceMask - **18**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1354.2 Field Documentation

8.1354.2.1 swi_uint256_t unpack_nas_SLQSNASGeteDRXParams_t::ParamPresenceMask

8.1354.2.2 uint8_t* unpack_nas_SLQSNASGeteDRXParams_t::pCycleLen

8.1354.2.3 uint8_t* unpack_nas_SLQSNASGeteDRXParams_t::pEdrxEnable

8.1354.2.4 uint8_t* unpack_nas_SLQSNASGeteDRXParams_t::pPagingTimeWindow

8.1355 unpack_nas_SLQSNASGeteDRXParamsExt_t Struct Reference

Data Fields

- uint8_t * pCycleLen
- uint8_t * pPagingTimeWindow
- uint8_t * pEdrxEnable
- uint8_t * pEdrxRAT
- uint32_t * pLteOpMode
- swi_uint256_t ParamPresenceMask

8.1355.1 Detailed Description

This structure contains the SLQSNASGeteDRXParams unpack parameters.

Parameters

pCycleLen	[Optional] • eDRX cycle length • Value is per 3GPP TS 24.008 Rel-13 Section 10.5.5.32 • Bit to check in ParamPresenceMask - **16**
pPagingTime-Window	[Optional] • eDRX paging time window • Value is per 3GPP TS 24.008 Rel-13 Section10.5.5.32 • Bit to check in ParamPresenceMask - **17**
pEdrxEnable	[Optional] • eDRX Enable • Values – 0x00 - Disable – 0x01 - Enable • Bit to check in ParamPresenceMask - **18**

pEdrxRAT	[Optional] • eDRX Radio Access Technology • Values – NAS_RADIO_IF_NO_SVC (0x00) - None (no service) – NAS_RADIO_IF_CDMA_1X (0x01) - cdma2000 ® 1X – NAS_RADIO_IF_CDMA_1XEVDO (0x02) - cdma2000 ® HRPD (1xEV-DO) – NAS_RADIO_IF_AMPS (0x03) - AMPS – NAS_RADIO_IF_GSM (0x04) - GSM – NAS_RADIO_IF_UMTS (0x05) - UMTS – NAS_RADIO_IF_WLAN (0x06) - WLAN – NAS_RADIO_IF_GPS (0x07) - GPS – NAS_RADIO_IF_LTE (0x08) - LTE – NAS_RADIO_IF_TDSCDMA (0x09) - TD-SCDMA – NAS_RADIO_IF_LTE_M1 (0x0a) - LTE-M1 – NAS_RADIO_IF_LTE_NB1 (0x0b) - LTE-NB1 – NAS_RADIO_IF_NO_CHANGE (-1) - No change • Bit to check in ParamPresenceMask - **19**
pLteOpMode	[Optional] • LTE Operational Mode • Values – NAS_CIOT_SYS_MODE_NO_ SRV (0x00) - No service – NAS_CIOT_SYS_MODE_LTE_ WB (0x01) - Camped on LTE wideband – NAS_CIOT_SYS_MODE_LTE_ M1 (0x02) - Camped on LTE M1 – NAS_CIOT_SYS_MODE_LTE_ NB1 (0x03) - Camped on LTE NB1 • Bit to check in ParamPresenceMask - **20**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1355.2 Field Documentation

8.1355.2.1 swi_uint256_t unpack_nas_SLQSNASGeteDRXParamsExt_t::ParamPresenceMask

8.1355.2.2 uint8_t* unpack_nas_SLQSNASGeteDRXParamsExt_t::pCycleLen

8.1355.2.3 uint8_t* unpack_nas_SLQSNASGeteDRXParamsExt_t::pEdrxEnable

8.1355.2.4 uint8_t* unpack_nas_SLQSNASGeteDRXParamsExt_t::pEdrxRAT

8.1355.2.5 uint32_t* unpack_nas_SLQSNASGeteDRXParamsExt_t::pLteOpMode

8.1355.2.6 uint8_t* unpack_nas_SLQSNASGeteDRXParamsExt_t::pPagingTimeWindow

8.1356 unpack_nas_SLQSNASGetForbiddenNetworks_t Struct Reference

Data Fields

- nas_ForbiddenNetworks3GPP * pForbiddenNetworks3GPP
- swi_uint256_t ParamPresenceMask

8.1356.1 Detailed Description

This structure contains the SLQSNASGeteDRXParams request parameters.

Parameters

pForbidden-Networks3GPP	[Optional] • See nas_ForbiddenNetworks3GPP for more information. • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1356.2 Field Documentation

8.1356.2.1 swi_uint256_t unpack_nas_SLQSNASGetForbiddenNetworks_t::ParamPresenceMask

8.1356.2.2 nas_ForbiddenNetworks3GPP* unpack_nas_SLQSNASGetForbiddenNetworks_t::pForbiddenNetworks3GPP

8.1357 unpack_nas_SLQSNasGetHDRColorCode_t Struct Reference

Data Fields

- uint8_t * pColorCode
- swi_uint256_t ParamPresenceMask

8.1357.1 Detailed Description

Structure for storing the current preferred system selection settings for the device.

Parameters

pColorCode	[Optional] • Color code value • Color code corresponding to the sector to which the AT is sending the access probe • See 3GPP2 C.S0024-B V3.0, Section 7.11.6.2.1 for more information. – 0xFF - Not Available • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1357.2 Field Documentation

8.1357.2.1 swi_uint256_t unpack_nas_SLQSNasGetHDRColorCode_t::ParamPresenceMask

8.1357.2.2 uint8_t* unpack_nas_SLQSNasGetHDRColorCode_t::pColorCode

8.1358 unpack_nas_SLQSNasGetRFInfo_t Struct Reference

Data Fields

- nas_RfBandInfoList rfbandInfoList
- nas_RfDedicatedBandInfo * pRfDedicatedBandInfo
- nas_RfBandInfoExtFormat * pRfBandInfoExtFormat
- nas_RfBandwidthInfo * pRfBandwidthInfo
- nas_LTEOperationMode * pLTEOperationMode
- uint16_t Tlvresult

8.1358.1 Detailed Description

This structure contains the SLQSNasGetRFInfo response parameters.

Parameters

rfbandInfoList	• See nas_RfBandInfoList for more information
pRfDedicated-BandInfo	[Optional] • See nas_RfDedicatedBandInfo for more information
pRfBandInfoExt-Format	[Optional] • See nas_RfBandInfoExtFormat for more information
pRfBandwidth-Info	[Optional] • See nas_RfBandwidthInfo for more information
pLTEOpration-Mode	[Optional] • See nas_LTEOperationMode for more information

8.1358.2 Field Documentation

8.1358.2.1 nas_LTEOperationMode* unpack_nas_SLQSNasGetRFInfo_t::pLTEOperationMode

8.1358.2.2 nas_RfBandInfoExtFormat* unpack_nas_SLQSNasGetRFInfo_t::pRfBandInfoExtFormat

8.1358.2.3 nas_RfBandwidthInfo* unpack_nas_SLQSNasGetRFInfo_t::pRfBandwidthInfo

8.1358.2.4 nas_RfDedicatedBandInfo* unpack_nas_SLQSNasGetRFInfo_t::pRfDedicatedBandInfo

8.1358.2.5 nas_RfBandInfoList unpack_nas_SLQSNasGetRFInfo_t::rfbandInfoList

8.1358.2.6 uint16_t unpack_nas_SLQSNasGetRFInfo_t::Tlvresult

8.1359 unpack_nas_SLQSNasGetSigInfo_t Struct Reference

Data Fields

- cdmaSSInfo CDMASSInfo
- hdrSSInfo HDRSSInfo
- int8_t GSMSSInfo
- cdmaSSInfo WCDMASSInfo
- lteSSInfo LTESSInfo

- swi_uint256_t ParamPresenceMask

8.1359.1 Detailed Description

This structure contains the SLQSNasGetSigInfo response parameters.

Parameters

CDMASSInfo	• See cdmaSSInfo for more information • Bit to check in ParamPresenceMask - **16**
HDRSSInfo	• See hdrSSInfo for more information • Bit to check in ParamPresenceMask - **17**
GSMSSInfo	• GSM signal strength is the RSSI in dBm (signed value). • A value of -125 dBm or lower is used to indicate No Signal. • Bit to check in ParamPresenceMask - **18**
WCDMASSInfo	• See cdmaSSInfo for more information • Bit to check in ParamPresenceMask - **19**
LTESSInfo	• See lteSSInfo for more information • Bit to check in ParamPresenceMask - **20**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1359.2 Field Documentation

8.1359.2.1 **cdmaSSInfo** unpack_nas_SLQSNasGetSigInfo_t::CDMASSInfo

8.1359.2.2 int8_t unpack_nas_SLQSNasGetSigInfo_t::GSMSSInfo

8.1359.2.3 **hdrSSInfo** unpack_nas_SLQSNasGetSigInfo_t::HDRSSInfo

8.1359.2.4 **lteSSInfo** unpack_nas_SLQSNasGetSigInfo_t::LTESSInfo

8.1359.2.5 **swi_uint256_t** unpack_nas_SLQSNasGetSigInfo_t::ParamPresenceMask

8.1359.2.6 **cdmaSSInfo** unpack_nas_SLQSNasGetSigInfo_t::WCDMASSInfo

8.1360 unpack_nas_SLQSNasGetTxRxInfo_t Struct Reference

Data Fields

- nas_rxInfo * pRXChain0Info
- nas_rxInfo * pRXChain1Info

- nas_txInfo * pTXInfo
- swi_uint256_t ParamPresenceMask

8.1360.1 Detailed Description

Structure for TxRx Info unpack

Parameters

pRXChain0Info	[Optional] • See nas_rxInfo for more information. • Bit to check in ParamPresenceMask - **16**
pRXChain1Info	[Optional] • See nas_rxInfo for more information. • Bit to check in ParamPresenceMask - **17**
pTXInfo	[Optional] • See nas_txInfo for more information. • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1360.2 Field Documentation

8.1360.2.1 swi_uint256_t unpack_nas_SLQSNasGetTxRxInfo_t::ParamPresenceMask

8.1360.2.2 nas_rxInfo* unpack_nas_SLQSNasGetTxRxInfo_t::pRXChain0Info

8.1360.2.3 nas_rxInfo* unpack_nas_SLQSNasGetTxRxInfo_t::pRXChain1Info

8.1360.2.4 nas_txInfo* unpack_nas_SLQSNasGetTxRxInfo_t::pTXInfo

8.1361 unpack_nas_SLQSNasNetworkRejectCallback_Ind_t Struct Reference

Data Fields

- uint8_t radioIf
- LITE_TYPE_OF_SERVICE_DOMAIN serviceDomain
- uint8_t rejectCause
- nas_PlmnID * pPlmnId
- nas_CsgId * pCsgId
- nas_LteOpMode * pLteOpMode
- swi_uint256_t ParamPresenceMask

8.1361.1 Detailed Description

Structure for storing the network reject indication parameters.

Parameters

radioIf	• Radio interface from which to get the information. Values: – 0x04 - NAS_RADIO_IF_GSM - GSM – 0x05 - NAS_RADIO_IF_UMTS - UMTS – 0x08 - NAS_RADIO_IF_LTE - LTE – 0x09 - NAS_RADIO_IF_TDSCDMA - TDSCDMA • Bit to check in ParamPresenceMask - **1**
serviceDomain	• Type of service domain in which the registration is rejected. Values: – 0x00 - LITE_SYS_SRV_DOMAIN_NO_SRV - No service – 0x01 - LITE_SYS_SRV_DOMAIN_CS_ONLY - Circuit-switched only – 0x02 - LITE_SYS_SRV_DOMAIN_PS_ONLY - Packet-switched only – 0x03 - LITE_SYS_SRV_DOMAIN_CS_PS - Circuit-switched and packet-switched – 0x04 - LITE_SYS_SRV_DOMAIN_CAMPED - Camped • Bit to check in ParamPresenceMask - **2**

rejectCause	• Reject cause values. – 2 - IMSI unknown in HLR – 3 - Illegal MS – 4 - IMSI unknown in VLR – 5 - IMEI not accepted – 6 - Illegal ME – 7 - EPS services not allowed – 8 - EPS services and non-EPS services not allowed – 9 - UE identity cannot be derived by the network – 10 - Implicitly detached – 11 - PLMN not allowed – 12 - Location Area not allowed – 13 - Roaming not allowed in this location area – 14 - EPS services not allowed in this PLMN – 15 - No Suitable Cells In Location Area – 16 - MSC temporarily not reachable – 17 - Network failure – 18 - CS domain not available – 19 - ESM failure – 20 - MAC failure – 21 - Synch failure – 22 - Congestion – 23 - GSM authentication unacceptable – 24 - Security mode rejected, unspecified – 25 - Not authorized for this CSG – 26 - Non-EPS authentication unacceptable – 32 - Service option not supported – 33 - Requested service option not subscribed – 34 - Service option temporarily out of order – 38 - Call cannot be identified – 48 to 63 - retry upon entry into a new cell – 95 - Semantically incorrect message – 96 - Invalid mandatory information – 97 - Message type non-existent or not implemented – 98 - Message type not compatible with the protocol state – 99 - Information element non-existent or not implemented – 100 - Conditional IE error – 101 - Message not compatible with the protocol state – 111 - Protocol error, unspecified – Note - Any other value received by the mobile station shall be treated as 34, 'Service option temporarily out of order'. * Any other value received by the network shall be treated as 111, 'Protocol error, unspecified'. See 3GPP TS 24.008, Section 4.4.4.7 and Section 10.5.3.6 See qaGobiApiTableCallEndReasons.h for Call End reasons • Bit to check in ParamPresenceMask - **3**

pPlmnId	(optional) • See nas_PlmnID for more information • Bit to check in ParamPresenceMask - **16**
pCsgId	(optional) • See nas_CsgId for more information. • Bit to check in ParamPresenceMask - **17**
pLteOpMode	(optional) • See nas_LteOpMode for more information. • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1361.2 Field Documentation

8.1361.2.1 swi_uint256_t unpack_nas_SLQSNasNetworkRejectCallback_Ind_t::ParamPresenceMask

8.1361.2.2 nas_CsgId∗ unpack_nas_SLQSNasNetworkRejectCallback_Ind_t::pCsgId

8.1361.2.3 nas_LteOpMode∗ unpack_nas_SLQSNasNetworkRejectCallback_Ind_t::pLteOpMode

8.1361.2.4 nas_PlmnID∗ unpack_nas_SLQSNasNetworkRejectCallback_Ind_t::pPlmnId

8.1361.2.5 uint8_t unpack_nas_SLQSNasNetworkRejectCallback_Ind_t::radioIf

8.1361.2.6 uint8_t unpack_nas_SLQSNasNetworkRejectCallback_Ind_t::rejectCause

8.1361.2.7 LITE_TYPE_OF_SERVICE_DOMAIN unpack_nas_SLQSNasNetworkRejectCallback_Ind_t::serviceDomain

8.1362 unpack_nas_SLQSNasNetworkTimeCallBack_ind_t Struct Reference

Data Fields

- nas_UniversalTime universalTime
- uint8_t ∗ pTimeZone
- uint8_t ∗ pDayltSavAdj
- uint8_t ∗ pRadioInterface
- swi_uint256_t ParamPresenceMask

8.1362.1 Detailed Description

Structure for storing the NAS Network Time indication parameters.

Parameters

universalTime	• See nas_UniversalTime for more information. • Bit to check in ParamPresenceMask - **1**

pTimeZone	• Time Zone. • Offset from Universal time, i.e., the difference between local time and Universal time, in increments of 15 min (signed value). • Bit to check in ParamPresenceMask - **16**
pDayltSavAdj	• Daylight Saving Adjustment. • Daylight saving adjustment in hr. – Possible values: 0, 1, and 2. • Bit to check in ParamPresenceMask - **17**

pRadioInterface	• Radio interface from which the information comes
	• Values
	  – 0x01 - NAS_RADIO_IF_CDMA_1X - cdma2000 1X
	  – 0x02 - NAS_RADIO_IF_CDMA_1XEVDO - cdma2000 HRPD (1xEV-DO)
	  – 0x04 - NAS_RADIO_IF_GSM - GSM
	  – 0x05 - NAS_RADIO_IF_UMTS - UMTS
	  – 0x08 - NAS_RADIO_IF_LTE - LTE
	  – 0x09 - NAS_RADIO_IF_TDSCDMA -TD-SCDMA
	• Bit to check in ParamPresenceMask - **18**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1362.2 Field Documentation

8.1362.2.1 swi_uint256_t unpack_nas_SLQSNasNetworkTimeCallBack_ind_t::ParamPresenceMask

8.1362.2.2 uint8_t* unpack_nas_SLQSNasNetworkTimeCallBack_ind_t::pDayltSavAdj

8.1362.2.3 uint8_t* unpack_nas_SLQSNasNetworkTimeCallBack_ind_t::pRadioInterface

8.1362.2.4 uint8_t* unpack_nas_SLQSNasNetworkTimeCallBack_ind_t::pTimeZone

8.1362.2.5 nas_UniversalTime unpack_nas_SLQSNasNetworkTimeCallBack_ind_t::universalTime

8.1363 unpack_nas_SLQSNasSigInfoCallback_ind_t Struct Reference

Data Fields

- cdmaSSInfo * pCDMASigInfo
- hdrSSInfo * pHDRSigInfo
- int8_t * pGSMSigInfo
- cdmaSSInfo * pWCDMASigInfo
- lteSSInfo * pLTESigInfo
- int8_t * pRscp
- tdscdmaSigInfoExt * pTDSCDMASigInfoExt
- swi_uint256_t ParamPresenceMask

8.1363.1 Detailed Description

Structure for storing the nasSigInfo indication parameters.

Parameters

pCDMASigInfo	• See cdmaSSInfo for more information. • Bit to check in ParamPresenceMask - **16**
pHDRSigInfo	• See hdrSSInfo for more information. • Bit to check in ParamPresenceMask - **17**
pGSMSigInfo	• one byte value, GSM signal strength is the RSSI in dBm (signed value). A value of -125 dBm or lower is used to indicate No Signal • Bit to check in ParamPresenceMask - **18**
pWCDMASigInfo	• See cdmaSSInfo for more information. • Bit to check in ParamPresenceMask - **19**
pLTESigInfo	• See lteSSInfo for more information. • Bit to check in ParamPresenceMask - **20**
pRscp	• RSCP of the Primary Common Control Physical Channel (PCCPCH) in dBm. Measurement range: -120 dBm to -25 dBm. • Bit to check in ParamPresenceMask - **21**
pTDSCDMASig-InfoExt	• See tdscdmaSigInfoExt for more information. • Bit to check in ParamPresenceMask - **22**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1363.2 Field Documentation

8.1363.2.1 swi_uint256_t unpack_nas_SLQSNasSigInfoCallback_ind_t::ParamPresenceMask

8.1363.2.2 cdmaSSInfo* unpack_nas_SLQSNasSigInfoCallback_ind_t::pCDMASigInfo

8.1363.2.3 int8_t* unpack_nas_SLQSNasSigInfoCallback_ind_t::pGSMSigInfo

8.1363.2.4 hdrSSInfo* unpack_nas_SLQSNasSigInfoCallback_ind_t::pHDRSigInfo

8.1363.2.5 lteSSInfo* unpack_nas_SLQSNasSigInfoCallback_ind_t::pLTESigInfo

8.1363.2.6 int8_t* unpack_nas_SLQSNasSigInfoCallback_ind_t::pRscp

8.1363.2.7 tdscdmaSigInfoExt∗ unpack_nas_SLQSNasSigInfoCallback_ind_t::pTDSCDMASigInfoExt

8.1363.2.8 cdmaSSInfo∗ unpack_nas_SLQSNasSigInfoCallback_ind_t::pWCDMASigInfo

8.1364 unpack_nas_SLQSNASSwiGetChannelLock_t Struct Reference

Data Fields

- nas_wcdmaUARFCN ∗ pWcdmaUARFCN
- nas_lteEARFCN ∗ pLteEARFCN
- nas_ltePCI ∗ pLtePCI
- swi_uint256_t ParamPresenceMask

8.1364.1 Detailed Description

Structure for Get Channel Lock unpack.

Parameters

pWcdmaUARFCN	[Optional] • See nas_wcdmaUARFCN for more information • Bit to check in ParamPresenceMask - **16**
pLteEARFCN	[Optional] • See nas_lteEARFCN for more information • Bit to check in ParamPresenceMask - **17**
pLtePCI	[Optional] • See nas_ltePCI for more information • Bit to check in ParamPresenceMask - **18**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1364.2 Field Documentation

8.1364.2.1 swi_uint256_t unpack_nas_SLQSNASSwiGetChannelLock_t::ParamPresenceMask

8.1364.2.2 nas_lteEARFCN∗ unpack_nas_SLQSNASSwiGetChannelLock_t::pLteEARFCN

8.1364.2.3 nas_ltePCI∗ unpack_nas_SLQSNASSwiGetChannelLock_t::pLtePCI

8.1364.2.4 nas_wcdmaUARFCN∗ unpack_nas_SLQSNASSwiGetChannelLock_t::pWcdmaUARFCN

8.1365 unpack_nas_SLQSNasSwiModemStatus_t Struct Reference

Data Fields

- nas_CommInfo commonInfo
- nas_LTEInfo ∗ pLTEInfo
- swi_uint256_t ParamPresenceMask

8.1365.1 Detailed Description

Structure for storing the SLQS Nas Swi Modem Status response parameters.

Parameters

commonInfo	(mandatory) • See nas_CommInfo for more information • Bit to check in ParamPresenceMask - **1**
pLTEInfo	(optional) • See nas_LTEInfo for more information • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1365.2 Field Documentation

8.1365.2.1 nas_CommInfo unpack_nas_SLQSNasSwiModemStatus_t::commonInfo

8.1365.2.2 swi_uint256_t unpack_nas_SLQSNasSwiModemStatus_t::ParamPresenceMask

8.1365.2.3 nas_LTEInfo* unpack_nas_SLQSNasSwiModemStatus_t::pLTEInfo

8.1366 unpack_nas_SLQSNasSwiOTAMessageCallback_ind_t Struct Reference

Data Fields

- NASQmiCbkNasSwiOTAMessageInd Info
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1366.1 Detailed Description

This structure contains unpack OTA message indication parameters.

Parameters

Info	• Structure used to store all QMI Notification Info. – See NASQmiCbkNasSwiOTAMessageInd for more details
Tlvresult	• unpack result • Bit to check in ParamPresenceMask - **2**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1366.2 Field Documentation

8.1366.2.1 NASQmiCbkNasSwiOTAMessageInd unpack_nas_SLQSNasSwiOTAMessageCallback_ind_t::Info

8.1366.2.2 swi_uint256_t unpack_nas_SLQSNasSwiOTAMessageCallback_ind_t::ParamPresenceMask

8.1366.2.3 uint16_t unpack_nas_SLQSNasSwiOTAMessageCallback_ind_t::Tlvresult

8.1367 unpack_nas_SLQSNasTimerCallback_ind_t Struct Reference

Data Fields

- char t3396_apn [101]
- uint8_t t3396_plmn_id [3]
- uint32_t t3396_val
- swi_uint256_t ParamPresenceMask

8.1367.1 Detailed Description

Structure for Network Timer indication parameters.

Parameters

t3396_apn	• apn • Bit to check in ParamPresenceMask - **16**
t3396_plmn_id	• plmn id • Bit to check in ParamPresenceMask - **16**
t3396_val	• timer value • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1367.2 Field Documentation

8.1367.2.1 swi_uint256_t unpack_nas_SLQSNasTimerCallback_ind_t::ParamPresenceMask

8.1367.2.2 char unpack_nas_SLQSNasTimerCallback_ind_t::t3396_apn[101]

8.1367.2.3 uint8_t unpack_nas_SLQSNasTimerCallback_ind_t::t3396_plmn_id[3]

8.1367.2.4 uint32_t unpack_nas_SLQSNasTimerCallback_ind_t::t3396_val

8.1368 unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t Struct Reference

Data Fields

- NASQmiCbkNasSystemSelPrefInd Info
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1368.1 Detailed Description

This structure contains unpack set system selection preference callback indication parameters.

Parameters

Info	• Structure used to store all QMI Notification Info. – See NASQmiCbkNasSystemSelPrefInd for more details
Tlvresult	• unpack result • Bit to check in ParamPresenceMask - **2**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1368.2 Field Documentation

8.1368.2.1 NASQmiCbkNasSystemSelPrefInd unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t::Info

8.1368.2.2 swi_uint256_t unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t::ParamPresenceMask

8.1368.2.3 uint16_t unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t::Tlvresult

8.1369 unpack_nas_SLQSSwiGetHDRPersonality_t Struct Reference

Data Fields

- uint16_t * pCurrentPersonality
- uint8_t * pPersonalityListLength
- nas_protocolSubtypeElement * pProtocolSubtypeElement
- swi_uint256_t ParamPresenceMask

8.1369.1 Detailed Description

Structure for HDRPersonality unpack.

Parameters

pCurrent-Personality[Out]	• Current active personality index. • Bit to check in ParamPresenceMask - **16**

pPersonalityList-Length[In/Out]	• Number of Personality Protocol Subtype contains in this response. • maximum input value is 3 • Bit to check in ParamPresenceMask - **17**
pProtocol-Subtype-Element[Out]	• See nas_protocolSubtypeElement for more information. • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1369.2 Field Documentation

8.1369.2.1 swi_uint256_t unpack_nas_SLQSSwiGetHDRPersonality_t::ParamPresenceMask

8.1369.2.2 uint16_t* unpack_nas_SLQSSwiGetHDRPersonality_t::pCurrentPersonality

8.1369.2.3 uint8_t* unpack_nas_SLQSSwiGetHDRPersonality_t::pPersonalityListLength

8.1369.2.4 nas_protocolSubtypeElement* unpack_nas_SLQSSwiGetHDRPersonality_t::pProtocolSubtypeElement

8.1370 unpack_nas_SLQSSwiGetHDRProtSubtype_t Struct Reference

Data Fields

- uint16_t * pCurrentPrsnlty
- uint8_t * pPersonalityListLength
- nas_protocolSubtypeElement * pProtoSubTypElmnt
- uint64_t * pAppSubType
- swi_uint256_t ParamPresenceMask

8.1370.1 Detailed Description

Structure for HDRProtSubtype unpack.

Parameters

pCurrent-Personality	• Current active personality index. • Bit to check in ParamPresenceMask - **16**
pPersonalityList-Length	• Number of Personality Protocol Subtype contains in this response. • maximum input value is 4 • Bit to check in ParamPresenceMask - **17**
pProtocol-SubtypeElement	• See nas_protocolSubtypeElement for more information. • Bit to check in ParamPresenceMask - **17**

pAppSubType	• Stream application subtype • Application subtype for each stream • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1370.2 Field Documentation

8.1370.2.1 uint64_t∗ unpack_nas_SLQSSwiGetHDRProtSubtype_t::pAppSubType

8.1370.2.2 swi_uint256_t unpack_nas_SLQSSwiGetHDRProtSubtype_t::ParamPresenceMask

8.1370.2.3 uint16_t∗ unpack_nas_SLQSSwiGetHDRProtSubtype_t::pCurrentPrsnlty

8.1370.2.4 uint8_t∗ unpack_nas_SLQSSwiGetHDRProtSubtype_t::pPersonalityListLength

8.1370.2.5 nas_protocolSubtypeElement∗ unpack_nas_SLQSSwiGetHDRProtSubtype_t::pProtoSubTypElmnt

8.1371 unpack_nas_SLQSSwiGetHRPDStats_t Struct Reference

Data Fields

- nas_DRCParams ∗ pDRCParams
- uint8_t ∗ pUATI
- nas_PilotSetData ∗ pPilotSetData
- swi_uint256_t ParamPresenceMask

8.1371.1 Detailed Description

Structure for HRPD Stats unpack.

Parameters

pDRCParams	• See nas_DRCParams for more information. • Bit to check in ParamPresenceMask - **16**
pUATI	• A 128-bit address that includes the access terminal identifier and subnet ID • Size must be 16 bytes • Bit to check in ParamPresenceMask - **17**
pPilotSetData	• See nas_PilotSetData for more information. • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1371.2 Field Documentation

8.1371.2.1 swi_uint256_t unpack_nas_SLQSSwiGetHRPDStats_t::ParamPresenceMask

8.1371.2.2 nas_DRCParams* unpack_nas_SLQSSwiGetHRPDStats_t::pDRCParams

8.1371.2.3 nas_PilotSetData* unpack_nas_SLQSSwiGetHRPDStats_t::pPilotSetData

8.1371.2.4 uint8_t* unpack_nas_SLQSSwiGetHRPDStats_t::pUATI

8.1372 unpack_nas_SLQSSwiGetLteCQI_t Struct Reference

Data Fields

- uint8_t ValidityCW0
- uint8_t CQIValueCW0
- uint8_t ValidityCW1
- uint8_t CQIValueCW1
- swi_uint256_t ParamPresenceMask

8.1372.1 Detailed Description

This structure contains paramaters unpack fetch CQI parameters for LTE data session.

Parameters

ValidityCW0[OUT]	• Values – 0- Invalid. – 1- Valid. • Bit to check in ParamPresenceMask - **1**
CQIValueCW0[OUT]	• Values – Range 0∼15 • Bit to check in ParamPresenceMask - **1**
ValidityCW1[OUT]	• Values – 0- Invalid. – 1- Valid. • Bit to check in ParamPresenceMask - **1**
CQIValueCW1[OUT]	• Values – Range 0∼15 • Bit to check in ParamPresenceMask - **1**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1372.2 Field Documentation

8.1372.2.1 uint8_t unpack_nas_SLQSSwiGetLteCQI_t::CQIValueCW0

8.1372.2.2 uint8_t unpack_nas_SLQSSwiGetLteCQI_t::CQIValueCW1

8.1372.2.3 swi_uint256_t unpack_nas_SLQSSwiGetLteCQI_t::ParamPresenceMask

8.1372.2.4 uint8_t unpack_nas_SLQSSwiGetLteCQI_t::ValidityCW0

8.1372.2.5 uint8_t unpack_nas_SLQSSwiGetLteCQI_t::ValidityCW1

8.1373 unpack_nas_SLQSSwiGetLteSccRxInfo_t Struct Reference

Data Fields

- nas_SccRxInfo * pSccRxInfo
- swi_uint256_t ParamPresenceMask

8.1373.1 Detailed Description

This structure contains unpack get LTE Secondary carrier Rx signal level information parameters.

Parameters

pSccRxInfo	Secondary carrier Rx signal level info • See nas_SccRxInfo – Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1373.2 Field Documentation

8.1373.2.1 swi_uint256_t unpack_nas_SLQSSwiGetLteSccRxInfo_t::ParamPresenceMask

8.1373.2.2 nas_SccRxInfo* unpack_nas_SLQSSwiGetLteSccRxInfo_t::pSccRxInfo

8.1374 unpack_nas_SLQSSwiHDRPersonalityCallback_Ind_t Struct Reference

Data Fields

- nas_HDRPersonality_Ind_Data * pHDRPersInd
- swi_uint256_t ParamPresenceMask

8.1374.1 Detailed Description

Structure for HDR Personality indication unpack.

Parameters

pHDRPersInd	• See nas_HDRPersonality_Ind_Data for more information.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1374.2 Field Documentation

8.1374.2.1 swi_uint256_t unpack_nas_SLQSSwiHDRPersonalityCallback_Ind_t::ParamPresenceMask

8.1374.2.2 nas_HDRPersonality_Ind_Data* unpack_nas_SLQSSwiHDRPersonalityCallback_Ind_t::pHDRPersInd

8.1375 unpack_nas_SLQSSwiNetworkDebug_t Struct Reference

Data Fields

- uint8_t * pObjectVer
- nas_NetworkStat1x * pNetworkStat1x
- nas_NetworkStatEVDO * pNetworkStatEVDO
- nas_DeviceConfigDetail * pDeviceConfigDetail
- nas_DataStatusDetail * pDataStatusDetail
- swi_uint256_t ParamPresenceMask

8.1375.1 Detailed Description

Structure for SwiNetworkDebug unpack.

Parameters

pObjectVer	• Object's version number for the host to handle
	  – 0xFF - NA
	  – Others - shows in decimal
	• Bit to check in ParamPresenceMask - **16**

pNetworkStat1x	• See nas_NetworkStat1x for more information • Bit to check in ParamPresenceMask - **17**
pNetworkStatE-VDO	• See nas_NetworkStatEVDO for more information. • Bit to check in ParamPresenceMask - **18**
pDeviceConfig-Detail	• See nas_DeviceConfigDetail for more information. • Bit to check in ParamPresenceMask - **19**
pDataStatus-Detail	• See nas_DataStatusDetail for more information. • Bit to check in ParamPresenceMask - **20**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1375.2 Field Documentation

8.1375.2.1 swi_uint256_t unpack_nas_SLQSSwiNetworkDebug_t::ParamPresenceMask

8.1375.2.2 nas_DataStatusDetail* unpack_nas_SLQSSwiNetworkDebug_t::pDataStatusDetail

8.1375.2.3 nas_DeviceConfigDetail* unpack_nas_SLQSSwiNetworkDebug_t::pDeviceConfigDetail

8.1375.2.4 nas_NetworkStat1x* unpack_nas_SLQSSwiNetworkDebug_t::pNetworkStat1x

8.1375.2.5 nas_NetworkStatEVDO* unpack_nas_SLQSSwiNetworkDebug_t::pNetworkStatEVDO

8.1375.2.6 uint8_t* unpack_nas_SLQSSwiNetworkDebug_t::pObjectVer

8.1376 unpack_nas_SLQSSwiRandIndicatorCallback_Ind_t Struct Reference

Data Fields

- nas_RankIndicatorTlv rankIndicatorTlv
- swi_uint256_t ParamPresenceMask

8.1376.1 Detailed Description

Structure for Rank Indicator indication unpack.

Parameters

rankIndicatorTlv	• See nas_RankIndicatorTlv for more information. • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1376.2 Field Documentation

8.1376.2.1 swi_uint256_t unpack_nas_SLQSSwiRandIndicatorCallback_Ind_t::ParamPresenceMask

8.1376.2.2 nas_RankIndicatorTlv unpack_nas_SLQSSwiRandIndicatorCallback_Ind_t::rankIndicatorTlv

8.1377 unpack_nas_SLQSSysInfoCallback_ind_t Struct Reference

Data Fields

- nas_SrvStatusInfo * pCDMASrvStatusInfo
- nas_SrvStatusInfo * pHDRSrvStatusInfo
- nas_GSMSrvStatusInfo * pGSMSrvStatusInfo

- nas_GSMSrvStatusInfo * pWCDMASrvStatusInfo
- nas_GSMSrvStatusInfo * pLTESrvStatusInfo
- nas_CDMASysInfo * pCDMASysInfo
- nas_HDRSysInfo * pHDRSysInfo
- nas_GSMSysInfo * pGSMSysInfo
- nas_WCDMASysInfo * pWCDMASysInfo
- nas_LTESysInfo * pLTESysInfo
- nas_AddCDMASysInfo * pAddCDMASysInfo
- uint16_t * pAddHDRSysInfo
- nas_AddSysInfo * pAddGSMSysInfo
- nas_AddSysInfo * pAddWCDMASysInfo
- uint16_t * pAddLTESysInfo
- nas_CallBarringSysInfo * pGSMCallBarringSysInfo
- nas_CallBarringSysInfo * pWCDMACallBarringSysInfo
- uint8_t * pLTEVoiceSupportSysInfo
- uint8_t * pGSMCipherDomainSysInfo
- uint8_t * pWCDMACipherDomainSysInfo
- uint8_t * pSysInfoNoChange
- nas_LteCiotOpModeTlv * pLteCiotOpModeTlv
- nas_NR5GSerStatTlv * pNR5GSerStatTlv
- nas_NR5GSystemInfoTlv * pNR5GSystemInfoTlv
- nas_NR5GCellStatusTlv * pNR5GCellStatus
- swi_uint256_t ParamPresenceMask

8.1377.1 Detailed Description

This structure contains unpack system information callback indication parameters.

Parameters

pCDMASrv-StatusInfo	• See nas_SrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **16**
pHDRSrvStatus-Info	• See nas_SrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **17**
pGSMSrvStatus-Info	• See nas_GSMSrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **18**
pWCDMASrv-StatusInfo	• See nas_GSMSrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **19**
pLTESrvStatus-Info	• See nas_GSMSrvStatusInfo for more information. • Bit to check in ParamPresenceMask - **20**
pCDMASysInfo	• See nas_CDMASysInfo for more information. • Bit to check in ParamPresenceMask - **21**

pHDRSysInfo	• See nas_HDRSysInfo for more information. • Bit to check in ParamPresenceMask - **22**
pGSMSysInfo	• See nas_GSMSysInfo for more information. • Bit to check in ParamPresenceMask - **23**
pWCDMASys-Info	• See nas_WCDMASysInfo for more information. • Bit to check in ParamPresenceMask - **24**
pLTESysInfo	• See nas_LTESysInfo for more information. • Bit to check in ParamPresenceMask - **25**
pAddCDMASys-Info	• See nas_AddCDMASysInfo for more information. • Bit to check in ParamPresenceMask - **26**
pAddHDRSys-Info	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used. • Bit to check in ParamPresenceMask - **27**
pAddGSMSys-Info	• See nas_AddSysInfo for more information. • Bit to check in ParamPresenceMask - **28**
pAddWCDMA-SysInfo	• See nas_AddSysInfo for more information. • Bit to check in ParamPresenceMask - **29**
pAddLTESysInfo	• System table index referencing the beginning of the geo in which the current serving system is present. • When the system index is not known, 0xFFFF is used. • Bit to check in ParamPresenceMask - **30**
pGSMCall-BarringSysInfo	• See nas_CallBarringSysInfo for more information. • Bit to check in ParamPresenceMask - **31**
pWCDMACall-BarringSysInfo	• See nas_CallBarringSysInfo for more information. • Bit to check in ParamPresenceMask - **32**

pLTEVoice-SupportSysInfo	• Indicates voice support status on LTE. – 0x00 - Voice is not supported – 0x01 - Voice is supported • Bit to check in ParamPresenceMask - **33**
pGSMCipher-DomainSysInfo	• Ciphering on the service domain. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched • Bit to check in ParamPresenceMask - **34**
pWCDMA-CipherDomain-SysInfo	• Ciphering on the service domain. – 0x00 - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched • Bit to check in ParamPresenceMask - **35**
pSysInfoNo-Change	• System Info No Change. • Flag used to notify clients that a request to select a network ended with no change in the PLMN. – 0x01 - No change in system information • Bit to check in ParamPresenceMask - **36**
pLteCiotOp-ModeTlv	• See nas_LteCiotOpModeTlv for more information. • Bit to check in ParamPresenceMask - **75**
pNR5GSerStat-Tlv	• See nas_NR5GSerStatTlv for more information. • Bit to check in ParamPresenceMask - **76**
pNR5GSystem-InfoTlv	• See nas_NR5GSystemInfoTlv for more information. • Bit to check in ParamPresenceMask - **77**
pNR5GCell-StatusTlv	• See nas_NR5GCellStatusTlv for more information. • Bit to check in ParamPresenceMask - **78**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1377.2 Field Documentation

8.1377.2.1 **nas_AddCDMASysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pAddCDMASysInfo

8.1377.2.2 **nas_AddSysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pAddGSMSysInfo

8.1377.2.3 uint16_t* unpack_nas_SLQSSysInfoCallback_ind_t::pAddHDRSysInfo

8.1377.2.4 uint16_t* unpack_nas_SLQSSysInfoCallback_ind_t::pAddLTESysInfo

8.1377.2.5 **nas_AddSysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pAddWCDMASysInfo

8.1377.2.6 **swi_uint256_t** unpack_nas_SLQSSysInfoCallback_ind_t::ParamPresenceMask

8.1377.2.7 **nas_SrvStatusInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pCDMASrvStatusInfo

8.1377.2.8 **nas_CDMASysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pCDMASysInfo

8.1377.2.9 **nas_CallBarringSysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pGSMCallBarringSysInfo

8.1377.2.10 uint8_t* unpack_nas_SLQSSysInfoCallback_ind_t::pGSMCipherDomainSysInfo

8.1377.2.11 **nas_GSMSrvStatusInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pGSMSrvStatusInfo

8.1377.2.12 **nas_GSMSysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pGSMSysInfo

8.1377.2.13 **nas_SrvStatusInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pHDRSrvStatusInfo

8.1377.2.14 **nas_HDRSysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pHDRSysInfo

8.1377.2.15 **nas_LteCiotOpModeTlv*** unpack_nas_SLQSSysInfoCallback_ind_t::pLteCiotOpModeTlv

8.1377.2.16 **nas_GSMSrvStatusInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pLTESrvStatusInfo

8.1377.2.17 **nas_LTESysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pLTESysInfo

8.1377.2.18 uint8_t* unpack_nas_SLQSSysInfoCallback_ind_t::pLTEVoiceSupportSysInfo

8.1377.2.19 **nas_NR5GCellStatusTlv*** unpack_nas_SLQSSysInfoCallback_ind_t::pNR5GCellStatus

8.1377.2.20 **nas_NR5GSerStatTlv*** unpack_nas_SLQSSysInfoCallback_ind_t::pNR5GSerStatTlv

8.1377.2.21 **nas_NR5GSystemInfoTlv*** unpack_nas_SLQSSysInfoCallback_ind_t::pNR5GSystemInfoTlv

8.1377.2.22 uint8_t* unpack_nas_SLQSSysInfoCallback_ind_t::pSysInfoNoChange

8.1377.2.23 **nas_CallBarringSysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pWCDMACallBarringSysInfo

8.1377.2.24 uint8_t* unpack_nas_SLQSSysInfoCallback_ind_t::pWCDMACipherDomainSysInfo

8.1377.2.25 **nas_GSMSrvStatusInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pWCDMASrvStatusInfo

8.1377.2.26 **nas_WCDMASysInfo*** unpack_nas_SLQSSysInfoCallback_ind_t::pWCDMASysInfo

8.1378 unpack_omaDmConfigTlv_t Struct Reference

Data Fields

- uint8_t state
- uint8_t userInputReq
- uint16_t userInputTimeout
- uint16_t alertmsglength
- uint8_t alertmsg [256]

8.1378.1 Detailed Description

This structure will hold the SwiOmaDmConfig session parameters information.

Parameters

state	• 0x01 - OMA-DM Read Request • 0x02 - OMA-DM Change Request • 0x03 - OMA-DM Config Complete
userInputReq	- Bit mask of available user inputs • 0x00 - No user input required.Informational indication • 0x01 - Accept • 0x02 - Reject
userInput-Timeout	• Timeout for user input in minutes. A value of 0 means no time-out
alertmsglength	• Length of Alert message string in bytes
alertmsg	• Alert message in UCS2 (Max 256 characters)

8.1378.2 Field Documentation

8.1378.2.1 uint8_t unpack_omaDmConfigTlv_t::alertmsg[256]

8.1378.2.2 uint16_t unpack_omaDmConfigTlv_t::alertmsglength

8.1378.2.3 uint8_t unpack_omaDmConfigTlv_t::state

8.1378.2.4 uint8_t unpack_omaDmConfigTlv_t::userInputReq

8.1378.2.5 uint16_t unpack_omaDmConfigTlv_t::userInputTimeout

8.1379 unpack_omaDmFotaTlv_t Struct Reference

Data Fields

- uint8_t state
- uint8_t userInputReq
- uint16_t userInputTimeout
- uint32_t fwdloadsize

- uint32_t fwloadComplete
- uint16_t updateCompleteStatus
- uint8_t severity
- uint16_t versionlength
- uint8_t version [256]
- uint16_t namelength
- uint8_t package_name [256]
- uint16_t descriptionlength
- uint8_t description [256]
- uint8_t sessionType

8.1379.1 Detailed Description

This structure will hold the SwiOmaDmFota session parameters information.

Parameters

state	• 0x01 - No Firmware available • 0x02 - Query Firmware Download • 0x03 - Firmware Downloading • 0x04 - Firmware downloaded • 0x05 - Query Firmware Update • 0x06 - Firmware updating • 0x07 - Firmware updated
userInputReq	- Bit mask of available user inputs • 0x00 - No user input required.Informational indication • 0x01 - Accept • 0x02 - Reject
userInput-Timeout	• Timeout for user input in minutes. A value of 0 means no time-out
fwdloadsize	• The size (in bytes) of the firmware update package
fwloadComplete	• The number of bytes downloaded. Need to determine how often to send this message for progress bar notification. Every 500ms or 5% increment.
update-CompleteStatus	• This field should be looked at only when the OMADM session is complete. • See qaGobiApiTableSwiOMADMUpdateCompleteStatus.h for update complete status.
severity	• 0x01 - Mandatory • 0x02 - Optional
versionlength	• Length of FW Version string in bytes
version	• FW Version string in ASCII (Max 256 characters)

namelength	• Length Package Name string in bytes
package_name	• Package Name in UCS2 (Max 256 characters)
descriptionlength	• Length of description in bytes
description	• Description of Update Package in USC2 (Max 256 characters)
sessionType	• 0x00 - Client initiated • 0x01 - Network initiated

8.1379.2 Field Documentation

8.1379.2.1 uint8_t unpack_omaDmFotaTlv_t::description[256]

8.1379.2.2 uint16_t unpack_omaDmFotaTlv_t::descriptionlength

8.1379.2.3 uint32_t unpack_omaDmFotaTlv_t::fwdloadsize

8.1379.2.4 uint32_t unpack_omaDmFotaTlv_t::fwloadComplete

8.1379.2.5 uint16_t unpack_omaDmFotaTlv_t::namelength

8.1379.2.6 uint8_t unpack_omaDmFotaTlv_t::package_name[256]

8.1379.2.7 uint8_t unpack_omaDmFotaTlv_t::sessionType

8.1379.2.8 uint8_t unpack_omaDmFotaTlv_t::severity

8.1379.2.9 uint8_t unpack_omaDmFotaTlv_t::state

8.1379.2.10 uint16_t unpack_omaDmFotaTlv_t::updateCompleteStatus

8.1379.2.11 uint8_t unpack_omaDmFotaTlv_t::userInputReq

8.1379.2.12 uint16_t unpack_omaDmFotaTlv_t::userInputTimeout

8.1379.2.13 uint8_t unpack_omaDmFotaTlv_t::version[256]

8.1379.2.14 uint16_t unpack_omaDmFotaTlv_t::versionlength

8.1380 unpack_omaDmNotificationsTlv_t Struct Reference

Data Fields

- uint8_t notification
- uint16_t sessionStatus

8.1380.1 Detailed Description

This structure will hold the SwiOmaDmConfig session notification parameters information.

Parameters

notification	• 0x01 - GPS settings change • 0x02 - Device reset • 0x03 - Device factory reset • 0x04 - CI-DC Session start • 0x05 - CI-DC Session end • 0x06 - CI-PRL Session start • 0x07 - CI-PRL Session end • 0x08 - CI-FUMO Session start • 0x09 - CI-FUMO session end • 0x0A - HFA-DC Session start • 0x0B - HFA-DC Session end • 0x0C - HFA-PRL Session start • 0x0D - HFA-PRL Session end • 0x0E - HFA-FUMO Session start • 0x0F - HFA-FUMO session end • 0x10 - NI Session start • 0x11 - NI session end
sessionStatus	• This field will set to the session status for notifications that occur at the end of a session, zero for all other notifications • See qaGobiApiTableSwiOMADMSessionStatus.h for session completion code.

8.1380.2 Field Documentation

8.1380.2.1 uint8_t unpack_omaDmNotificationsTlv_t::notification

8.1380.2.2 uint16_t unpack_omaDmNotificationsTlv_t::sessionStatus

8.1381 unpack_pds_GetPDSDefaults_t Struct Reference

Data Fields

- uint32_t * pOperation
- uint8_t * pTimeout
- uint32_t * pInterval
- uint32_t * pAccuracy
- swi_uint256_t ParamPresenceMask

8.1381.1 Detailed Description

Structure contain session configuration parameters.

Parameters

pOperation	• Current session operating mode – 0 - Standalone – 1 - MS based – 2 - MS assisted • Bit to check in ParamPresenceMask - **1**
pTimeout	• Maximum amount of time (seconds) to work on each fix, maximum is 255 • Bit to check in ParamPresenceMask - **1**
pInterval	• Interval (seconds) between fix requests • Bit to check in ParamPresenceMask - **1**
pAccuracy	• Preferred accuracy threshold (meters) • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1381.2 Field Documentation

8.1381.2.1 uint32_t∗ unpack_pds_GetPDSDefaults_t::pAccuracy

8.1381.2.2 swi_uint256_t unpack_pds_GetPDSDefaults_t::ParamPresenceMask

8.1381.2.3 uint32_t∗ unpack_pds_GetPDSDefaults_t::pInterval

8.1381.2.4 uint32_t∗ unpack_pds_GetPDSDefaults_t::pOperation

8.1381.2.5 uint8_t∗ unpack_pds_GetPDSDefaults_t::pTimeout

8.1382 unpack_pds_GetPDSState_t Struct Reference

Data Fields

- uint32_t ∗ pEnabledStatus
- uint32_t ∗ pTrackingStatus
- swi_uint256_t ParamPresenceMask

8.1382.1 Detailed Description

Structure contain parameters of current PDS state.

Parameters

pEnabledStatus	• Current PDS state – 0 - disable – 1 - enable • Bit to check in ParamPresenceMask - **1**
pTrackingStatus	• Current PDS tracking session state • Values: – 0x00 - Unknown – 0x01 - Inactive – 0x02 - Active • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1382.2 Field Documentation

8.1382.2.1 swi_uint256_t unpack_pds_GetPDSState_t::ParamPresenceMask

8.1382.2.2 uint32_t∗ unpack_pds_GetPDSState_t::pEnabledStatus

8.1382.2.3 uint32_t∗ unpack_pds_GetPDSState_t::pTrackingStatus

8.1383 unpack_pds_GetPortAutomaticTracking_t Struct Reference

Data Fields

- uint32_t ∗ pbAuto
- swi_uint256_t ParamPresenceMask

8.1383.1 Detailed Description

Structure contain the parameter of automatic tracking configuration for the NMEA COM port.

Parameters

pbAuto	• Automatic tracking enabled for NMEA COM port – 0x00 - Disabled – 0x01 - Enabled – Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1383.2 Field Documentation

8.1383.2.1 swi_uint256_t unpack_pds_GetPortAutomaticTracking_t::ParamPresenceMask

8.1383.2.2 uint32_t* unpack_pds_GetPortAutomaticTracking_t::pbAuto

8.1384 unpack_pds_GetServiceAutomaticTracking_t Struct Reference

Data Fields

- uint32_t * pbAuto
- swi_uint256_t ParamPresenceMask

8.1384.1 Detailed Description

Structure contain the parameter for automatic tracking state.

Parameters

pbAuto	• Automatic tracking session started for service – 0x00 - Disabled – 0x01 - Enabled • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1384.2 Field Documentation

8.1384.2.1 swi_uint256_t unpack_pds_GetServiceAutomaticTracking_t::ParamPresenceMask

8.1384.2.2 uint32_t* unpack_pds_GetServiceAutomaticTracking_t::pbAuto

8.1385 unpack_pds_GetXTRAAutomaticDownload_t Struct Reference

Data Fields

- uint32_t * pbEnabled
- uint16_t * pInterval
- swi_uint256_t ParamPresenceMask

8.1385.1 Detailed Description

Structure contain the parameter of automatic tracking configuration for the NMEA COM port.

Parameters

pbEnabled	• Automatic XTRA download status – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **16**

pInterval	• Interval (hours) between XTRA downloads • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1385.2 Field Documentation

8.1385.2.1 swi_uint256_t unpack_pds_GetXTRAAutomaticDownload_t::ParamPresenceMask

8.1385.2.2 uint32_t∗ unpack_pds_GetXTRAAutomaticDownload_t::pbEnabled

8.1385.2.3 uint16_t∗ unpack_pds_GetXTRAAutomaticDownload_t::pInterval

8.1386 unpack_pds_GetXTRANetwork_t Struct Reference

Data Fields

- uint32_t ∗ pPreference
- swi_uint256_t ParamPresenceMask

8.1386.1 Detailed Description

Structure contain the parameter for XTRA WWAN network preference

Parameters

pPreference	• XTRA WWAN network preference – 0x00 - None (any available network) – 0x01 - Home-only, only when on home systems – 0x02 - Roam-only, only when on non-home systems • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1386.2 Field Documentation

8.1386.2.1 swi_uint256_t unpack_pds_GetXTRANetwork_t::ParamPresenceMask

8.1386.2.2 uint32_t∗ unpack_pds_GetXTRANetwork_t::pPreference

8.1387 unpack_pds_GetXTRAValidity_t Struct Reference

Data Fields

- uint16_t ∗ pGPSWeek

- uint16_t * pGPSWeekOffset
- uint16_t * pDuration
- swi_uint256_t ParamPresenceMask

8.1387.1 Detailed Description

Structure contain the parameter for XTRA database validity period

Parameters

pGPSWeek	• Starting GPS week of validity period • Bit to check in ParamPresenceMask - **19**
pGPSWeek-Offset	• Starting GPS week offset (minutes) of validity period • Bit to check in ParamPresenceMask - **19**
pDuration	• Length of validity period (hours) • NULL pointer - Invalid data. • Bit to check in ParamPresenceMask - **19**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1387.2 Field Documentation

8.1387.2.1 swi_uint256_t unpack_pds_GetXTRAValidity_t::ParamPresenceMask

8.1387.2.2 uint16_t* unpack_pds_GetXTRAValidity_t::pDuration

8.1387.2.3 uint16_t* unpack_pds_GetXTRAValidity_t::pGPSWeek

8.1387.2.4 uint16_t* unpack_pds_GetXTRAValidity_t::pGPSWeekOffset

8.1388 unpack_pds_SetEventReport_Ind_t Struct Reference

Data Fields

- uint8_t has_PositionDataNMEA
- char PositionDataNMEA [200]
- uint8_t has_dLongitude
- double dLongitude
- uint8_t has_dLatitude
- double dLatitude
- uint8_t has_SessionStatus
- uint8_t SessionStatus
- uint8_t has_posSrc
- uint32_t posSrc
- swi_uint256_t ParamPresenceMask

8.1388.1 Detailed Description

Structure contain the parameter for the Set event report Indication. Please check has_<Param_Name> field for presence of optional parameters

Parameters

PositionDataNMEA	• Position Data NMEA. • String containing the position data in NMEA sentence format (maximum 200 bytes). • Bit to check in ParamPresenceMask - **16**
dLongitude	• Longitude position referenced to the WGS-84 reference ellipsoid, counting positive angles east of the Greenwich Meridian and negative angles west of the Greenwich Meridian. • Units - Decimal degrees • Range - -180 to +180 • Note - Value is in double float format • Bit to check in ParamPresenceMask - **19**
dLatitude	• Latitude position referenced to the WGS-84 reference ellipsoid, counting positive angles north of the equator and negative angles south of the equator. • Units: Decimal degrees • Range: -90 to +90 • Note - Value is in double float format • Bit to check in ParamPresenceMask - **19**
session_status	• Position Session Status • Status of current session. • Values – 0x00 - Success – 0x01 - In progress – 0x02 - General failure – 0x03 - Timeout – 0x04 - User ended the session – 0x05 - Bad parameter – 0x06 - Phone is offline – 0x07 - Engine is locked – 0x08 - E911 session in progress • Bit to check in ParamPresenceMask - **18** • Note - This TLV is always sent while a fix is being generated or if it halts due to an error. The Parsed Position Data TLV (0x13) is included if the session status is Success (0x00) or In Progress (0x01); otherwise this TLV is passed alone.

posSrc	• Position Source • This TLV is always sent with the Parsed Position Data TLV (0x13) when the latitude/longitude is marked as valid. Source of the position (bitmask). • Values – 0x00000001 - GPS – 0x00000002 - Cell ID – 0x00000004 - GLONASS – 0x00000008 - Network – 0x00000010 - External position injection • Bit to check in ParamPresenceMask - **28**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1388.2 Field Documentation

8.1388.2.1 double unpack_pds_SetEventReport_Ind_t::dLatitude

8.1388.2.2 double unpack_pds_SetEventReport_Ind_t::dLongitude

8.1388.2.3 uint8_t unpack_pds_SetEventReport_Ind_t::has_dLatitude

8.1388.2.4 uint8_t unpack_pds_SetEventReport_Ind_t::has_dLongitude

8.1388.2.5 uint8_t unpack_pds_SetEventReport_Ind_t::has_PositionDataNMEA

8.1388.2.6 uint8_t unpack_pds_SetEventReport_Ind_t::has_posSrc

8.1388.2.7 uint8_t unpack_pds_SetEventReport_Ind_t::has_SessionStatus

8.1388.2.8 swi_uint256_t unpack_pds_SetEventReport_Ind_t::ParamPresenceMask

8.1388.2.9 char unpack_pds_SetEventReport_Ind_t::PositionDataNMEA[200]

8.1388.2.10 uint32_t unpack_pds_SetEventReport_Ind_t::posSrc

8.1388.2.11 uint8_t unpack_pds_SetEventReport_Ind_t::SessionStatus

8.1389 unpack_pds_SetPdsState_Ind_t Struct Reference

Data Fields

- uint16_t TlvPresent
- uint32_t EnabledStatus
- uint32_t TrackingStatus
- swi_uint256_t ParamPresenceMask

8.1389.1 Detailed Description

Structure contain the parameter for the Set PDS State Indication.

Parameters

EnabledStatus	• GPS service state. • Values – 0x00 - Disable – 0x01 - Enable • Bit to check in ParamPresenceMask - **1**
TrackingStatus	• Tracking session state. • Values – 0x00 - Unknown – 0x01 - Inactive – 0x02 - Active • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1389.2 Field Documentation

8.1389.2.1 uint32_t unpack_pds_SetPdsState_Ind_t::EnabledStatus

8.1389.2.2 swi_uint256_t unpack_pds_SetPdsState_Ind_t::ParamPresenceMask

8.1389.2.3 uint16_t unpack_pds_SetPdsState_Ind_t::TlvPresent

8.1389.2.4 uint32_t unpack_pds_SetPdsState_Ind_t::TrackingStatus

8.1390 unpack_pds_SLQSGetAGPSConfig_t Struct Reference

Data Fields

- uint32_t * pServerAddress
- uint32_t * pServerPort
- uint8_t * pServerURL
- uint8_t * pServerURLLength
- swi_uint256_t ParamPresenceMask

8.1390.1 Detailed Description

Structure contain the parameter for PDS AGPS (MS-based) configuration unpack.

Parameters

pServerAddress	• IPv4 address of AGPS server. "0" if not set • Bit to check in ParamPresenceMask - **16**
pServerPort	• Port number of AGPS server. "0" if not set • Bit to check in ParamPresenceMask - **16**

pServerURL	• URL of the AGPS server. "0" if not set • Bit to check in ParamPresenceMask - **17**
pServerURL-Length	• URL length of AGPS server. "0" if not set • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1390.2 Field Documentation

8.1390.2.1 swi_uint256_t unpack_pds_SLQSGetAGPSConfig_t::ParamPresenceMask

8.1390.2.2 uint32_t* unpack_pds_SLQSGetAGPSConfig_t::pServerAddress

8.1390.2.3 uint32_t* unpack_pds_SLQSGetAGPSConfig_t::pServerPort

8.1390.2.4 uint8_t* unpack_pds_SLQSGetAGPSConfig_t::pServerURL

8.1390.2.5 uint8_t* unpack_pds_SLQSGetAGPSConfig_t::pServerURLLength

8.1391 unpack_pds_SLQSGetGPSStateInfo_t Struct Reference

Data Fields

- uint8_t EngineState
- uint32_t ValidMask
- uint64_t Latitude
- uint64_t Longitude
- uint32_t HorizontalUncertainty
- uint32_t Altitude
- uint32_t VerticalUncertainty
- uint32_t TimeStmp_tow_ms
- uint16_t TimeStmp_gps_week
- uint32_t Time_uncert_ms
- uint8_t Iono_valid
- uint32_t gps_ephemeris_sv_msk
- uint32_t gps_almanac_sv_msk
- uint32_t gps_health_sv_msk
- uint32_t gps_visible_sv_msk
- uint32_t glo_ephemeris_sv_msk
- uint32_t glo_almanac_sv_msk
- uint32_t glo_health_sv_msk
- uint32_t glo_visible_sv_msk
- uint32_t sbas_ephemeris_sv_msk
- uint32_t sbas_almanac_sv_msk
- uint32_t sbas_health_sv_msk
- uint32_t sbas_visible_sv_msk
- uint16_t xtra_start_gps_week

- uint16_t xtra_start_gps_minutes
- uint16_t xtra_valid_duration_hours
- swi_uint256_t ParamPresenceMask

8.1391.1 Detailed Description

Structure contain the parameter for GPS state Info.

Parameters

EngineState	• Values: – 0 - OFF – 1 - ON • This field is always valid • Bit to check in ParamPresenceMask - **16**
ValidMask	• Mask of valid state information data. • Values: – 0x00000001 - Position(latitude/longitude/horizontal uncertainty) – 0x00000002 - Altitude and vertical uncertainty – 0x00000004 - Time ms – 0x00000008 - Time week number – 0x00000010 - Time uncertainty – 0x00000020 - Iono validity – 0x00000040 - GPS ephemeris – 0x00000080 - GPS almanac – 0x00000100 - GPS health – 0x00000200 - GPS visible SVs – 0x00000400 - GLONASS ephemeris – 0x00000800 - GLONASS almanac – 0x00001000 - GLONASS health – 0x00002000 - GLONASS visible SVs – 0x00004000 - SBAS ephemeris – 0x00008000 - SBAS almanac – 0x00010000 - SBAS health – 0x00020000 - SBAS visible SVs – 0x00040000 - XTRA information • Bit to check in ParamPresenceMask - **16**
Latitude	• Latitude position referenced to the WGS-84 reference ellipsoid, counting positive angles north of the equator and negative angles south of the equator. • Units: Decimal degrees • Range: -90 to +90 degrees. • Value is in double float format (refer to IEEE Std 754-1985) • Bit to check in ParamPresenceMask - **16**

Longitude	• Longitude position referenced to the WGS-84 reference ellipsoid, counting positive angles east of the Greenwich Meridian and negative angles west of Greenwich meridian. • Units: Decimal degrees • Range: -180 to +180 degrees • Value is in double float format (refer to IEEE Std 754-1985) • Bit to check in ParamPresenceMask - **16**
Horizontal-Uncertainty	• Circular horizontal uncertainty (in meters). The uncertainty is provided at 63 percent confidence. • Value is in single float format (refer to IEEE Std 754-1985) • Bit to check in ParamPresenceMask - **16**
Altitude	• Height above the WGS-84 reference ellipsoid. Value conveys height (in meters) plus 500 m • Range -500 to 15883 • Value in single float format (refer to IEEE Std 754-1985) • Bit to check in ParamPresenceMask - **16**
Vertical-Uncertainty	• Vertical uncertainty (in meters). The uncertainty is provided at 68 percent confidence. • Value in single float format (refer to IEEE Std 754-1985) • Bit to check in ParamPresenceMask - **16**
TimeStmp_tow_-ms	• Time stamp in GPS time of week(in milliseconds) • Bit to check in ParamPresenceMask - **16**
TimeStmp_gps-_week	• GPS week number • Bit to check in ParamPresenceMask - **16**
Time_uncert_ms	• Time uncertainty (in milliseconds). The uncertainty is provided at 99 percent confidence. • Bit to check in ParamPresenceMask - **16**

Iono_valid	• Iono validity.
	• Values:
	  – 0 - Invalid
	  – 1 - Valid
	• Bit to check in ParamPresenceMask - **16**

gps_ephemeris-_sv_msk	• GPS SV mask for ephemeris; if the bit is set, ephemeris for that SV is available. • Bit to check in ParamPresenceMask - **16**
gps_almanac_-sv_msk	• GPS SV mask for almanac; if the bit is set, almanac for that SV is available. • Bit to check in ParamPresenceMask - **16**

gps_health_sv_msk	• GPS SV mask for health; if the bit is set, health for that SV is available. • Bit to check in ParamPresenceMask - **16**
gps_visible_sv_msk	• GPS SV mask for visible Svs; if the bit is set, the SV is available. • Bit to check in ParamPresenceMask - **16**
glo_ephemeris_sv_msk	• GLONASS SV mask for ephemeris; if the bit is set, ephemeris for that SV is available. • Bit to check in ParamPresenceMask - **16**
glo_almanac_sv_msk	• GLONASS SV mask for almanac; if the bit is set, almanac for that SV is available. • Bit to check in ParamPresenceMask - **16**
glo_health_sv_msk	• GLONASS SV mask for health; if the bit is set, health for that SV is available. • Bit to check in ParamPresenceMask - **16**
glo_visible_sv_msk	• GLONASS SV mask for visible SVs; if the bit is set, the SV is available. • Bit to check in ParamPresenceMask - **16**
sbas_ephemeris_sv_msk	• SBAS SV mask for ephemeris; if the bit is set, ephemeris for that SV is available. • Bit to check in ParamPresenceMask - **16**
sbas_almanac_sv_msk	• SBAS SV mask for almanac; if the bit is set, almanac for that SV is available. • Bit to check in ParamPresenceMask - **16**
sbas_health_sv_msk	• SBAS SV mask for health; if the bit is set, health for that SV is available. • Bit to check in ParamPresenceMask - **16**
sbas_visible_sv_msk	• SBAS SV mask for visible SVs; if the bit is set, the SV is available. • Bit to check in ParamPresenceMask - **16**
xtra_start_gps_week	• Current XTRA information is valid starting from this GPS week number • Bit to check in ParamPresenceMask - **16**
xtra_start_gps_minutes	• Current XTRA information is valid starting from the GPS minutes with the GPS week • Bit to check in ParamPresenceMask - **16**
xtra_valid_duration_hours	• XTRA information is valid for this many hours starting from the specified GPS week/minutes • Bit to check in ParamPresenceMask - **16**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1391.2 Field Documentation

8.1391.2.1 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::Altitude

8.1391.2.2 uint8_t unpack_pds_SLQSGetGPSStateInfo_t::EngineState

8.1391.2.3 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::glo_almanac_sv_msk

8.1391.2.4 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::glo_ephemeris_sv_msk

8.1391.2.5 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::glo_health_sv_msk

8.1391.2.6 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::glo_visible_sv_msk

8.1391.2.7 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::gps_almanac_sv_msk

8.1391.2.8 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::gps_ephemeris_sv_msk

8.1391.2.9 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::gps_health_sv_msk

8.1391.2.10 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::gps_visible_sv_msk

8.1391.2.11 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::HorizontalUncertainty

8.1391.2.12 uint8_t unpack_pds_SLQSGetGPSStateInfo_t::Iono_valid

8.1391.2.13 uint64_t unpack_pds_SLQSGetGPSStateInfo_t::Latitude

8.1391.2.14 uint64_t unpack_pds_SLQSGetGPSStateInfo_t::Longitude

8.1391.2.15 swi_uint256_t unpack_pds_SLQSGetGPSStateInfo_t::ParamPresenceMask

8.1391.2.16 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::sbas_almanac_sv_msk

8.1391.2.17 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::sbas_ephemeris_sv_msk

8.1391.2.18 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::sbas_health_sv_msk

8.1391.2.19 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::sbas_visible_sv_msk

8.1391.2.20 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::Time_uncert_ms

8.1391.2.21 uint16_t unpack_pds_SLQSGetGPSStateInfo_t::TimeStmp_gps_week

8.1391.2.22 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::TimeStmp_tow_ms

8.1391.2.23 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::ValidMask

8.1391.2.24 uint32_t unpack_pds_SLQSGetGPSStateInfo_t::VerticalUncertainty

8.1391.2.25 uint16_t unpack_pds_SLQSGetGPSStateInfo_t::xtra_start_gps_minutes

8.1391.2.26 uint16_t unpack_pds_SLQSGetGPSStateInfo_t::xtra_start_gps_week

8.1391.2.27 uint16_t unpack_pds_SLQSGetGPSStateInfo_t::xtra_valid_duration_hours

8.1392 unpack_qmi_t Struct Reference

Data Fields

- enum msgtype type
- uint16_t msgid
- uint16_t xid

8.1392.1 Detailed Description

qmi response context

Parameters

out	*type*	message type
out	*msgid*	message id
out	*xid*	transaction id

8.1392.2 Field Documentation

8.1392.2.1 uint16_t unpack_qmi_t::msgid

8.1392.2.2 enum msgtype unpack_qmi_t::type

8.1392.2.3 uint16_t unpack_qmi_t::xid

8.1393 unpack_qos_BindDataPort_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1393.1 Detailed Description

This structure contains unpack Qos BindDataPort.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1393.2 Field Documentation

8.1393.2.1 swi_uint256_t unpack_qos_BindDataPort_t::ParamPresenceMask

8.1394 unpack_qos_dataRate_t Struct Reference

Data Fields

- uint32_t dataRateMax
- uint32_t guaranteedRate

8.1394.1 Detailed Description

This structure contains the IP flow data rate min max

Parameters

dataRateMax	Maximum required data rate (bits per second)
guaranteedRate	Minimum guaranteed data rate (bits per second)

8.1394.2 Field Documentation

8.1394.2.1 uint32_t unpack_qos_dataRate_t::dataRateMax

8.1394.2.2 uint32_t unpack_qos_dataRate_t::guaranteedRate

8.1395 unpack_qos_IPv4Addr_t Struct Reference

Data Fields

- uint32_t addr
- uint32_t subnetMask

8.1395.1 Detailed Description

This structure contains the IPv4 filter address

Parameters

addr	IPv4 address
subnetMask	A packet matches if: • (addr and subnetMask) == (IP pkt addr & subnetMask) Callers to set up a filter with a range of source addresses, if needed; subnet mask of all 1s (255.255.255.255) specifies a single address value

8.1395.2 Field Documentation

8.1395.2.1 uint32_t unpack_qos_IPv4Addr_t::addr

8.1395.2.2 uint32_t unpack_qos_IPv4Addr_t::subnetMask

8.1396 unpack_qos_IPv6Addr_t Struct Reference

Data Fields

- uint8_t addr [16]

- uint8_t prefixLen

8.1396.1 Detailed Description

This structure contains the IPv6 filter address

Parameters

addr	IPv6 address (in network byte order); this is a 16-byte byte array (in Big-endian format)
prefixLen	IPv6 filter prefix length; can take a value between 0 and 128 Note: A packet matches if the IPv6 source address bytes until the prefix lengths are equal. Therefore prefix length can be used to set a filter with a range of source addresses. A prefix length of 128 specifies a single address value.

8.1396.2 Field Documentation

8.1396.2.1 uint8_t unpack_qos_IPv6Addr_t::addr[16]

8.1396.2.2 uint8_t unpack_qos_IPv6Addr_t::prefixLen

8.1397 unpack_qos_IPv6TrafCls_t Struct Reference

Data Fields

- uint8_t val
- uint8_t mask

8.1397.1 Detailed Description

This structure contains the IPv6 filter traffic class

Parameters

val	The traffic class value
mask	The packet matches the traffic class filter if: (IPv6_filter_traffic_class_val and IPv6_filter_traffic_class_mask) == (Traffic class value in the IP packet & IPv6_filter_traffic_class_mask) Example: • IPv6_filter_tc_val = 00101000 • IPv6_filter_tc_mask = 11111100 Filter will compare only the first 6 bits in IPv6_filter_traffic_class with the first 6 bits in the traffic class field of the IP packet; first 6 bits in the traffic class field of the IP packet must be 001010 to match filter; last 2 bits can be anything, since they are ignored by filtering

8.1397.2 Field Documentation

8.1397.2.1 uint8_t unpack_qos_IPv6TrafCls_t::mask

8.1397.2.2 uint8_t unpack_qos_IPv6TrafCls_t::val

8.1398 unpack_qos_pktErrRate_t Struct Reference

Data Fields

- uint16_t multiplier

- uint16_t exponent

8.1398.1 Detailed Description

This structure contains the IP flow packet error rate

Parameters

multiplier	Factor m in calculating packet error rate: E = m∗10∗∗(-p)
exponent	Factor p in calculating packet error rate (see above)

8.1398.2 Field Documentation

8.1398.2.1 uint16_t unpack_qos_pktErrRate_t::exponent

8.1398.2.2 uint16_t unpack_qos_pktErrRate_t::multiplier

8.1399 unpack_qos_Port_t Struct Reference

Data Fields

- uint16_t port
- uint16_t range

8.1399.1 Detailed Description

This structure contains the Port Filter

Parameters

port	port value of the filter
range	range specifies the number of ports to be included in the filter starting from port; filter will match if port in the IP packet lies between port and (port + range) Range value of 0 implies that only one value of the port is valid, as specified by the port

8.1399.2 Field Documentation

8.1399.2.1 uint16_t unpack_qos_Port_t::port

8.1399.2.2 uint16_t unpack_qos_Port_t::range

8.1400 unpack_qos_QosFlowInfo_t Struct Reference

Data Fields

- unpack_qos_QosFlowInfoState_t QFlowState
- uint8_t is_TxQFlowGranted_Available
- unpack_qos_swiQosFlow_t TxQFlowGranted
- uint8_t is_RxQFlowGranted_Available
- unpack_qos_swiQosFlow_t RxQFlowGranted
- uint8_t NumTxFilters
- unpack_qos_swiQosFilter_t TxQFilter [25]
- uint8_t NumRxFilters

- unpack_qos_swiQosFilter_t RxQFilter [25]
- uint8_t BearerID

8.1400.1 Detailed Description

Structure with QoS flow details.

Please check is_<Param_Name>_Available field for presence of optional parameters

Parameters

QFlowState	• QoS flow state information, please check unpack_qos_QosFlowInfoState_t for more information
is_TxQFlowGranted_Available	• TRUE if optional TxQFlowGranted is available
TxQFlowGranted	• The Tx Qos flow granted, please check unpack_qos_swiQosFlow_t for more information
is_RxQFlowGranted_Available	• TRUE if optional RxQFlowGranted is available
RxQFlowGranted	• The Rx Qos flow granted, please check unpack_qos_swiQosFlow_t for more information
NumTxFilters	• Number of Tx filters available
TxQFilter	• The Tx Qos filter, please check unpack_qos_swiQosFilter_t for more information • See LITEQMI_MAX_QOS_FILTERS for more information
NumRxFilters	• Number of Tx filters available
RxQFilter	• The Rx Qos filter, please check unpack_qos_swiQosFilter_t for more information • See LITEQMI_MAX_QOS_FILTERS for more information
BearerID	• The bearer ID • Bearer ID or Radio Link Protocol (RLP) ID of the activated flow. • Valid Values - 0 to 16 • 0xFF - Invalid value.

8.1400.2 Field Documentation

8.1400.2.1 uint8_t unpack_qos_QosFlowInfo_t::BearerID

8.1400.2.2 uint8_t unpack_qos_QosFlowInfo_t::is_RxQFlowGranted_Available

8.1400.2.3 uint8_t unpack_qos_QosFlowInfo_t::is_TxQFlowGranted_Available

8.1400.2.4 uint8_t unpack_qos_QosFlowInfo_t::NumRxFilters

8.1400.2.5 uint8_t unpack_qos_QosFlowInfo_t::NumTxFilters

8.1400.2.6 unpack_qos_QosFlowInfoState_t unpack_qos_QosFlowInfo_t::QFlowState

8.1400.2.7 unpack_qos_swiQosFilter_t unpack_qos_QosFlowInfo_t::RxQFilter[25]

8.1400.2.8 unpack_qos_swiQosFlow_t unpack_qos_QosFlowInfo_t::RxQFlowGranted

8.1400.2.9 unpack_qos_swiQosFilter_t unpack_qos_QosFlowInfo_t::TxQFilter[25]

8.1400.2.10 unpack_qos_swiQosFlow_t unpack_qos_QosFlowInfo_t::TxQFlowGranted

8.1401 unpack_qos_QosFlowInfoState_t Struct Reference

Data Fields

- uint32_t id
- uint8_t isNewFlow
- uint8_t state

8.1401.1 Detailed Description

This structure contains QoS flow state

Parameters

id	QoS identifier
isNewFlow	• 1 - Newly added flow • 0 - Existing flow
state	This indicates that the flow that was added/modified/deleted: • 0x01 - Flow activated • 0x02 - Flow modified • 0x03 - Flow deleted • 0x04 - Flow suspended • 0x05 - Flow enabled • 0x06 - Flow disabled

8.1401.2 Field Documentation

8.1401.2.1 uint32_t unpack_qos_QosFlowInfoState_t::id

8.1401.2.2 uint8_t unpack_qos_QosFlowInfoState_t::isNewFlow

8.1401.2.3 uint8_t unpack_qos_QosFlowInfoState_t::state

8.1402 unpack_qos_SLQSQosGetNetworkStatus_t Struct Reference

Data Fields

- uint8_t NWQoSStatus
- swi_uint256_t ParamPresenceMask

8.1402.1 Detailed Description

Structure that contains the response to get NW QoS status command

Parameters

NWQoSStatus	Network QoS support status • 0 - No QoS support in network • 1 - Network supports QoS • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1402.2 Field Documentation

8.1402.2.1 uint8_t unpack_qos_SLQSQosGetNetworkStatus_t::NWQoSStatus

8.1402.2.2 swi_uint256_t unpack_qos_SLQSQosGetNetworkStatus_t::ParamPresenceMask

8.1403 unpack_qos_SLQSQosSwiReadApnExtraParams_t Struct Reference

Data Fields

- uint32_t apnId
- uint8_t ambr_ul
- uint8_t ambr_dl
- uint8_t ambr_ul_ext
- uint8_t ambr_dl_ext
- uint8_t ambr_ul_ext2
- uint8_t ambr_dl_ext2
- swi_uint256_t ParamPresenceMask

8.1403.1 Detailed Description

Structure that contains extra APN parameters

Parameters

apnId	• APN id • ID identifing the APN that the client would like to query the AMBR params • Bit to check in ParamPresenceMask - **3**

ambr_ul	• APN AMBR uplink • APN AMBR uplink values from 1 kbps to 8640 kbps • Bit to check in ParamPresenceMask - **3**
ambr_dl	• APN AMBR downlink • APN AMBR downlink values from 1 kbps to 8640 kbps • Bit to check in ParamPresenceMask - **3**
ambr_ul_ext	• Extended APN AMBR uplink • APN AMBR uplink values from 8700 kbps to 256 Mbps • Bit to check in ParamPresenceMask - **3**
ambr_dl_ext	• Extended APN AMBR downlink • APN AMBR downlink values from 8700 kbps to 256 Mbps • Bit to check in ParamPresenceMask - **3**
ambr_ul_ext2	• Second extended APN AMBR uplink • APN AMBR uplink values from 256 Mbps to 65280 Mbps • Bit to check in ParamPresenceMask - **3**
ambr_dl_ext2	• Second extended APN AMBR downlink • APN AMBR downlink values from 256 Mbps to 65280 Mbps • Bit to check in ParamPresenceMask - **3**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1403.2 Field Documentation

8.1403.2.1 uint8_t unpack_qos_SLQSQosSwiReadApnExtraParams_t::ambr_dl

8.1403.2.2 uint8_t unpack_qos_SLQSQosSwiReadApnExtraParams_t::ambr_dl_ext

8.1403.2.3 uint8_t unpack_qos_SLQSQosSwiReadApnExtraParams_t::ambr_dl_ext2

8.1403.2.4 uint8_t unpack_qos_SLQSQosSwiReadApnExtraParams_t::ambr_ul

8.1403.2.5 uint8_t unpack_qos_SLQSQosSwiReadApnExtraParams_t::ambr_ul_ext

8.1403.2.6 uint8_t unpack_qos_SLQSQosSwiReadApnExtraParams_t::ambr_ul_ext2

8.1403.2.7 uint32_t unpack_qos_SLQSQosSwiReadApnExtraParams_t::apnId

8.1403.2.8 swi_uint256_t unpack_qos_SLQSQosSwiReadApnExtraParams_t::ParamPresenceMask

8.1404 unpack_qos_SLQSQosSwiReadDataStats_t Struct Reference

Data Fields

- uint32_t apnId
- uint32_t total_tx_pkt
- uint32_t total_tx_pkt_drp
- uint32_t total_rx_pkt
- uint64_t total_tx_bytes
- uint64_t total_tx_bytes_drp
- uint64_t total_rx_bytes
- uint32_t numQosFlow
- unpack_QosFlowStat_t qosFlow [10]
- swi_uint256_t ParamPresenceMask

8.1404.1 Detailed Description

Structure that contains APN data statistics

Parameters

apnId	• APN id • ID identifing the connected APN that the client would like to query the data statistic for • Bit to check in ParamPresenceMask - **3**
total_tx_pkt	• sum of all packets sent • Bit to check in ParamPresenceMask - **3**
total_tx_pkt_drp	• sum of all(TX) packets dropped • Bit to check in ParamPresenceMask - **3**
total_rx_pkt	• sum of all packets received • Bit to check in ParamPresenceMask - **3**
total_tx_bytes	• sum of all bytes sent • Bit to check in ParamPresenceMask - **3**
total_tx_bytes_drp	• sum of all(TX) bytes dropped • Bit to check in ParamPresenceMask - **3**
total_rx_bytes	• number of received bytes for the QoS flow ID • Bit to check in ParamPresenceMask - **3**
numQosFlow	• pointer to number of QoS flow Stat • Bit to check in ParamPresenceMask - **4**

qosFlow[LITEQMI_MAX_QOS_FLOW_PER_APN_STATS]	• Data statistic per QoS flow • See unpack_QosFlowStat_t for more information • See LITEQMI_MAX_QOS_FLOW_PER_APN_STATS for more information • Bit to check in ParamPresenceMask - **4**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1404.2 Field Documentation

8.1404.2.1 uint32_t unpack_qos_SLQSQosSwiReadDataStats_t::apnId

8.1404.2.2 uint32_t unpack_qos_SLQSQosSwiReadDataStats_t::numQosFlow

8.1404.2.3 swi_uint256_t unpack_qos_SLQSQosSwiReadDataStats_t::ParamPresenceMask

8.1404.2.4 unpack_QosFlowStat_t unpack_qos_SLQSQosSwiReadDataStats_t::qosFlow[10]

8.1404.2.5 uint64_t unpack_qos_SLQSQosSwiReadDataStats_t::total_rx_bytes

8.1404.2.6 uint32_t unpack_qos_SLQSQosSwiReadDataStats_t::total_rx_pkt

8.1404.2.7 uint64_t unpack_qos_SLQSQosSwiReadDataStats_t::total_tx_bytes

8.1404.2.8 uint64_t unpack_qos_SLQSQosSwiReadDataStats_t::total_tx_bytes_drp

8.1404.2.9 uint32_t unpack_qos_SLQSQosSwiReadDataStats_t::total_tx_pkt

8.1404.2.10 uint32_t unpack_qos_SLQSQosSwiReadDataStats_t::total_tx_pkt_drp

8.1405 unpack_qos_SLQSSetQosEventCallback_ind_t Struct Reference

Data Fields

- uint8_t NumFlows
- unpack_qos_QosFlowInfo_t QosFlowInfo [8]
- swi_uint256_t ParamPresenceMask

8.1405.1 Detailed Description

Structure with QoS event details

Parameters

NumFlows	• Number of QoS flows available • Bit to check in ParamPresenceMask - **16**

QosFlowInfo	• The Qos flow details, please check unpack_qos_QosFlowInfo_t for more information • See LITEQMI_MAX_QOS_FLOWS for more information • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1405.2 Field Documentation

8.1405.2.1 uint8_t unpack_qos_SLQSSetQosEventCallback_ind_t::NumFlows

8.1405.2.2 swi_uint256_t unpack_qos_SLQSSetQosEventCallback_ind_t::ParamPresenceMask

8.1405.2.3 unpack_qos_QosFlowInfo_t unpack_qos_SLQSSetQosEventCallback_ind_t::QosFlowInfo[8]

8.1406 unpack_qos_SLQSSetQosEventCallback_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1406.1 Detailed Description

This structure contains unpack QOS SLQSSetQosEventCallback. param ParamPresenceMask

- bitmask representation to indicate valid parameters.

8.1406.2 Field Documentation

8.1406.2.1 swi_uint256_t unpack_qos_SLQSSetQosEventCallback_t::ParamPresenceMask

8.1407 unpack_qos_SLQSSetQosNWStatusCallback_ind_t Struct Reference

Data Fields

- uint8_t status
- swi_uint256_t ParamPresenceMask

8.1407.1 Detailed Description

Structure with network's QoS status

Parameters

status	Network QoS support status • 0x00 - Current network does not support QoS • 0x01 - Current network supports QoS • Bit to check in ParamPresenceMask - **1**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

- Technology Supported: CDMA

8.1407.2 Field Documentation

8.1407.2.1 swi_uint256_t unpack_qos_SLQSSetQosNWStatusCallback_ind_t::ParamPresenceMask

8.1407.2.2 uint8_t unpack_qos_SLQSSetQosNWStatusCallback_ind_t::status

8.1408 unpack_qos_SLQSSetQosPriEventCallback_ind_t Struct Reference

Data Fields

- uint16_t event
- swi_uint256_t ParamPresenceMask

8.1408.1 Detailed Description

Structure with QoS primary flow events

Parameters

event	Event which causes this indication: • 0x0001 - Primary flow QoS modify operation success • 0x0002 - Primary flow QoS modify operation failure • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1408.2 Field Documentation

8.1408.2.1 uint16_t unpack_qos_SLQSSetQosPriEventCallback_ind_t::event

8.1408.2.2 swi_uint256_t unpack_qos_SLQSSetQosPriEventCallback_ind_t::ParamPresenceMask

8.1409 unpack_qos_SLQSSetQosStatusCallback_ind_t Struct Reference

Data Fields

- uint32_t id
- uint8_t status
- uint8_t event
- uint8_t reason
- swi_uint256_t ParamPresenceMask

8.1409.1 Detailed Description

Structure with QoS status indication details

Parameters

id	• Index identifying the QoS flow whose status is being reported • Bit to check in ParamPresenceMask - **1**
status	Current QoS flow status: • 0x01 - QMI_QOS_STATUS_ACTIVATED • 0x02 - QMI_QOS_STATUS_SUSPENDED • 0x03 - QMI_QOS_STATUS_GONE • Bit to check in ParamPresenceMask - **1**
event	• 0x01 - QMI_QOS_ACTIVATED_EV • 0x02 - QMI_QOS_SUSPENDED_EV • 0x03 - QMI_QOS_GONE_EV • 0x04 - QMI_QOS_MODIFY_ACCEPTED_EV • 0x05 - QMI_QOS_MODIFY_REJECTED_EV • 0x06 - QMI_QOS_INFO_CODE_UPDATED_EV • Bit to check in ParamPresenceMask - **1**
reason	• 0x01 - QMI_QOS_INVALID_PARAMS • 0x02 - QMI_QOS_INTERNAL_CALL_ENDED • 0x03 - QMI_QOS_INTERNAL_ERROR • 0x04 - QMI_QOS_INSUFFICIENT_LOCAL_Resources • 0x05 - QMI_QOS_TIMED_OUT_OPERATION • 0x06 - QMI_QOS_INTERNAL_UNKNOWN_CAUSE_CODE • 0x07 - QMI_QOS_INTERNAL_MODIFY_IN_PROGRESS • 0x08 - QMI_QOS_NOT_SUPPORTED • 0x09 - QMI_QOS_NOT_AVAILABLE • 0x0A - QMI_QOS_NOT_GUARANTEED • 0x0B - QMI_QOS_INSUFFICIENT_NETWORK_RESOURCES • 0x0C - QMI_QOS_AWARE_SYSTEM • 0x0D - QMI_QOS_UNAWARE_SYSTEM • 0x0E - QOS_REJECTED_OPERATION • 0x0F - QMI_QOS_WILL_GRANT_WHEN_QOS_RESUMED • 0x10 - QMI_QOS_NETWORK_CALL_ENDED • 0x11 - QMI_QOS_NETWORK_SERVICE_NOT_AVAILABLE • 0x12 - QMI_QOS_NETWORK_L2_LINK_RELEASED • 0x13 - QMI_QOS_NETWORK_L2_LINK_REESTAB_REJ • 0x14 - QMI_QOS_NETWORK_L2_LINK_REESTAB_IND • 0x15 - QMI_QOS_NETWORK_UNKNOWN_CAUSE_CODE • 0x16 - QMI_NETWORK_BUSY • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1409.2 Field Documentation

8.1409.2.1 uint8_t unpack_qos_SLQSSetQosStatusCallback_ind_t::event

8.1409.2.2 uint32_t unpack_qos_SLQSSetQosStatusCallback_ind_t::id

8.1409.2.3 swi_uint256_t unpack_qos_SLQSSetQosStatusCallback_ind_t::ParamPresenceMask

8.1409.2.4 uint8_t unpack_qos_SLQSSetQosStatusCallback_ind_t::reason

8.1409.2.5 uint8_t unpack_qos_SLQSSetQosStatusCallback_ind_t::status

8.1410 unpack_qos_swiQosFilter_t Struct Reference

Data Fields

- uint8_t index
- uint8_t version
- uint8_t is_IPv4SrcAddr_Available
- unpack_qos_IPv4Addr_t IPv4SrcAddr
- uint8_t is_IPv4DstAddr_Available
- unpack_qos_IPv4Addr_t IPv4DstAddr
- uint8_t is_NxtHdrProto_Available
- uint8_t NxtHdrProto
- uint8_t is_IPv4Tos_Available
- unpack_qos_Tos_t IPv4Tos
- uint8_t is_IPv6SrcAddr_Available
- unpack_qos_IPv6Addr_t IPv6SrcAddr
- uint8_t is_IPv6DstAddr_Available
- unpack_qos_IPv6Addr_t IPv6DstAddr
- uint8_t is_IPv6TrafCls_Available
- unpack_qos_IPv6TrafCls_t IPv6TrafCls
- uint8_t is_IPv6Label_Available
- uint32_t IPv6Label
- uint8_t is_TCPSrcPort_Available
- unpack_qos_Port_t TCPSrcPort
- uint8_t is_TCPDstPort_Available
- unpack_qos_Port_t TCPDstPort
- uint8_t is_UDPSrcPort_Available
- unpack_qos_Port_t UDPSrcPort
- uint8_t is_UDPDstPort_Available
- unpack_qos_Port_t UDPDstPort
- uint8_t is_EspSpi_Available
- uint32_t EspSpi
- uint8_t is_Precedence_Available
- uint16_t Precedence
- uint8_t is_Id_Available
- uint16_t Id
- uint8_t is_TranSrcPort_Available
- unpack_qos_Port_t TranSrcPort
- uint8_t is_TranDstPort_Available
- unpack_qos_Port_t TranDstPort

8.1410.1 Detailed Description

This structure contains the QoS Filter Request.

Please check is_<Param_Name>_Available field for presence of optional parameters

Parameters

index	Mandatory parameter IP filter index Integer that uniquely identifies each filter instance This TLV must be present in the request
version	Mandatory parameter IP filter version Identifies whether the filter is associated with IPv4 or IPv6; value specified also implies that only TLVs defined for that IP version, i.e., TLVs with IPv4 or IPv6 in the name, can be specified • 0x04 - IPv4 • 0x06 - Ipv6
IPv4SrcAddr	IPv4 filter soruce address See unpack_qos_IPv4Addr_t for more information • Implemented only for unsolicited indication
IPv4DstAddr	IPv4 filter destination address See unpack_qos_IPv4Addr_t for more information • Implemented only for unsolicited indication
NxtHdrProto	IP filter next header protocol This TLV must be present if any non-IP filter TLV(s) are provided If this field is specified, only IP packets belonging to specified higher layer protocol are considered when filtering The following protocols may be specified: • 0x01 = ICMP • 0x06 = TCP • 0x11 = UDP • 0x32 = ESP Note: The next header protocol field will be set to 0xFD (TCP & UDP) if a TFT is received specifying a source or destination port number, but IP next header type is not specified.
IPv4Tos	IPv4 filter type of service See unpack_qos_Tos_t for more information
IPv6SrcAddr	IPv6 filter soruce address See unpack_qos_IPv6Addr_t for more information • Implemented only for unsolicited indication
IPv6DstAddr	IPv6 filter destination address See unpack_qos_IPv6Addr_t for more information • Implemented only for unsolicited indication
IPv6TrafCls	IPv6 filter traffic class See unpack_qos_IPv6TrafCls_t for more information
IPv6Label	IPv6 flow label Packet matches the IPv6 flow label filter if: (∗pIPv6Label == flow label in the IPv6 header) • Implemented only for unsolicited indication
TCPSrcPort	TCP filter source port filter See unpack_qos_Port_t for more information • Implemented only for unsolicited indication
TCPDstPort	TCP filter destination port filter See unpack_qos_Port_t for more information • Implemented only for unsolicited indication
UDPSrcPort	UDP filter source port filter See unpack_qos_Port_t for more information • Implemented only for unsolicited indication
UDPDstPort	UDP filter destination port filter See unpack_qos_Port_t for more information • Implemented only for unsolicited indication

EspSpi	ESP filter security policy index Security policy index to uniquely identify each IP flow for filtering encrypted packets for encapsulating security payload • Implemented only for unsolicited indication
Precedence	Filter Precedence Specifies the order in which filters are applied; lower numerical value has higher precedence Note: This TLV only applies to network-initiated QoS; QoS requests containing this TLV from control points will be ignored
Id	Filter ID Unique identifier for each filter;filter ID is assigned by the modem Note: This TLV only applies to network-initiated QoS; QoS requests containing this TLV from control points will be ignored
TranSrcPort	Transport protocolfilter source port See unpack_qos_Port_t for more information • Implemented only for unsolicited indication
UDPDstPort	Transport protocol filter destination port See unpack_qos_Port_t for more information • Implemented only for unsolicited indication

8.1410.2 Field Documentation

8.1410.2.1 uint32_t unpack_qos_swiQosFilter_t::EspSpi

8.1410.2.2 uint16_t unpack_qos_swiQosFilter_t::Id

8.1410.2.3 uint8_t unpack_qos_swiQosFilter_t::index

8.1410.2.4 unpack_qos_IPv4Addr_t unpack_qos_swiQosFilter_t::IPv4DstAddr

8.1410.2.5 unpack_qos_IPv4Addr_t unpack_qos_swiQosFilter_t::IPv4SrcAddr

8.1410.2.6 unpack_qos_Tos_t unpack_qos_swiQosFilter_t::IPv4Tos

8.1410.2.7 unpack_qos_IPv6Addr_t unpack_qos_swiQosFilter_t::IPv6DstAddr

8.1410.2.8 uint32_t unpack_qos_swiQosFilter_t::IPv6Label

8.1410.2.9 unpack_qos_IPv6Addr_t unpack_qos_swiQosFilter_t::IPv6SrcAddr

8.1410.2.10 unpack_qos_IPv6TrafCls_t unpack_qos_swiQosFilter_t::IPv6TrafCls

8.1410.2.11 uint8_t unpack_qos_swiQosFilter_t::is_EspSpi_Available

8.1410.2.12 uint8_t unpack_qos_swiQosFilter_t::is_Id_Available

8.1410.2.13 uint8_t unpack_qos_swiQosFilter_t::is_IPv4DstAddr_Available

8.1410.2.14 uint8_t unpack_qos_swiQosFilter_t::is_IPv4SrcAddr_Available

8.1410.2.15 uint8_t unpack_qos_swiQosFilter_t::is_IPv4Tos_Available

8.1410.2.16 uint8_t unpack_qos_swiQosFilter_t::is_IPv6DstAddr_Available

8.1410.2.17 uint8_t unpack_qos_swiQosFilter_t::is_IPv6Label_Available

8.1410.2.18 uint8_t unpack_qos_swiQosFilter_t::is_IPv6SrcAddr_Available

8.1410.2.19 uint8_t unpack_qos_swiQosFilter_t::is_IPv6TrafCls_Available

8.1410.2.20 uint8_t unpack_qos_swiQosFilter_t::is_NxtHdrProto_Available

8.1410.2.21 uint8_t unpack_qos_swiQosFilter_t::is_Precedence_Available

8.1410.2.22 uint8_t unpack_qos_swiQosFilter_t::is_TCPDstPort_Available

8.1410.2.23 uint8_t unpack_qos_swiQosFilter_t::is_TCPSrcPort_Available

8.1410.2.24 uint8_t unpack_qos_swiQosFilter_t::is_TranDstPort_Available

8.1410.2.25 uint8_t unpack_qos_swiQosFilter_t::is_TranSrcPort_Available

8.1410.2.26 uint8_t unpack_qos_swiQosFilter_t::is_UDPDstPort_Available

8.1410.2.27 uint8_t unpack_qos_swiQosFilter_t::is_UDPSrcPort_Available

8.1410.2.28 uint8_t unpack_qos_swiQosFilter_t::NxtHdrProto

8.1410.2.29 uint16_t unpack_qos_swiQosFilter_t::Precedence

8.1410.2.30 unpack_qos_Port_t unpack_qos_swiQosFilter_t::TCPDstPort

8.1410.2.31 unpack_qos_Port_t unpack_qos_swiQosFilter_t::TCPSrcPort

8.1410.2.32 unpack_qos_Port_t unpack_qos_swiQosFilter_t::TranDstPort

8.1410.2.33 unpack_qos_Port_t unpack_qos_swiQosFilter_t::TranSrcPort

8.1410.2.34 unpack_qos_Port_t unpack_qos_swiQosFilter_t::UDPDstPort

8.1410.2.35 unpack_qos_Port_t unpack_qos_swiQosFilter_t::UDPSrcPort

8.1410.2.36 uint8_t unpack_qos_swiQosFilter_t::version

8.1411 unpack_qos_swiQosFlow_t Struct Reference

Data Fields

- uint8_t index
- uint8_t is_ProfileId3GPP2_Available
- uint16_t ProfileId3GPP2
- uint8_t is_val_3GPP2Pri_Available
- uint8_t val_3GPP2Pri
- uint8_t is_TrafficClass_Available
- uint8_t TrafficClass
- uint8_t is_DataRate_Available
- unpack_qos_dataRate_t DataRate
- uint8_t is_TokenBucket_Available
- unpack_qos_tokenBucket_t TokenBucket
- uint8_t is_Latency_Available
- uint32_t Latency
- uint8_t is_Jitter_Available
- uint32_t Jitter

- uint8_t is_PktErrRate_Available
- unpack_qos_pktErrRate_t PktErrRate
- uint8_t is_MinPolicedPktSz_Available
- uint32_t MinPolicedPktSz
- uint8_t is_MaxAllowedPktSz_Available
- uint32_t MaxAllowedPktSz
- uint8_t is_val_3GPPResResidualBER_Available
- uint16_t val_3GPPResResidualBER
- uint8_t is_val_3GPPTraHdlPri_Available
- uint8_t val_3GPPTraHdlPri
- uint8_t is_val_3GPPImCn_Available
- uint8_t val_3GPPImCn
- uint8_t is_val_3GPPSigInd_Available
- uint8_t val_3GPPSigInd
- uint8_t is_LteQci_Available
- uint8_t LteQci

8.1411.1 Detailed Description

This structure contains the QoS Flow Request.

Please check is_<Param_Name>_Available field for presence of optional parameters

Parameters

index	• Mandatory parameter • IP flow index • Integer that uniquely identifies each flow instance • Unique index must be assigned by the control point to every flow_spec instance
ProfileId3GPP2	• IP flow 3GPP2 profile ID • A profile ID is shorthand for a defined set of QoS flow parameters specified by the network; to be present while requesting QoS for a CDMA device
val_3GPP2Pri	• IP flow 3GPP2 flow priority • Flow priority used by the network in case of contention between flows with same QoS; this parameter applies for CDMA devices
TrafficClass	• IP flow traffic class • Integer that designates the requested traffic class: • 0 - Conversational • 1 - Streaming • 2 - Interactive • 3 - Background
DataRate	• IP flow data rate min max • See unpack_qos_dataRate_t for more information

TokenBucket	• IP flow data rate token bucket • See unpack_qos_tokenBucket_t for more information
Latency	• IP flow latency • Maximum delay (in milliseconds) that can be tolerated by an IP packet during transfer through the wireless link
Jitter	• IP flow jitter • Difference between the maximum and minimum latency (in milliseconds) that can be tolerated by an IP packet during the transfer through the wireless link
PktErrRate	• IP flow packet error rate • See unpack_qos_pktErrRate_t for more information
MinPolicedPktSz	• IP flow minimum policed packet size • Integer that defines the minimum packet size (in bytes) that will be policed for QoS guarantees; any IP packets that are smaller than the minimum specified policed size may not receive requested QoS
MaxAllowedPktSz	• IP flow maximum allowed packet size • Integer that defines the maximum packet size (in bytes) allowed in the IP flow; any IP packets greater in size than the maximum allowed packet size are not queued for transmission
val_3GPPResResidualBER	• IP flow 3GPP residual bit error rate • residual_bit_error_rate • 0 = 5∗10-2 residual BER • 1 = 1∗10-2 residual BER • 2 = 5∗10-3 residual BER • 3 = 4∗10-3 residual BER • 4 = 1∗10-3 residual BER • 5 = 1∗10-4 residual BER • 6 = 1∗10-5 residual BER • 7 = 1∗10-6 residual BER • 8 = 6∗10-8 residual BER • Integer that indicates the undetected BER for each IP flow in the delivered packets; Tapplies only to 3GPP networks
val_3GPPTraHdlPri	• 3GPP traffic handling priority • 0 - Relative traffic handling priority 1 • 1 - Relative traffic handling priority 2 • 2 - Relative traffic handling priority 3 • Defines the relative priority of the flow; applies only to 3GPP networks

val_3GPPImCn	• IP flow 3GPP IM CN flag • IM CN subsystem signaling flag: • 0x00 - FALSE • 0x01 - TRUE • This parameter applies only to 3GPP networks
val_3GPPSigInd	• IP flow 3GPP signaling indication • 0x00 - FALSE • 0x01 - TRUE • This parameter applies only to 3GPP networks
LteQci	• LTE QoS Class Identifier • QoS Class Identifier(QCI) is a required parameter to request QoS in LTE • QCI values: – QCI value 0 requests the network to assign the appropriate QCI value – QCI values 1-4 are associated with guaranteed bitrates – QCI values 5-9 are associated with nonguaranteed bitrates, so the values specified as guaranteed and maximum bitrates are ignored

8.1411.2 Field Documentation

8.1411.2.1 unpack_qos_dataRate_t unpack_qos_swiQosFlow_t::DataRate

8.1411.2.2 uint8_t unpack_qos_swiQosFlow_t::index

8.1411.2.3 uint8_t unpack_qos_swiQosFlow_t::is_DataRate_Available

8.1411.2.4 uint8_t unpack_qos_swiQosFlow_t::is_Jitter_Available

8.1411.2.5 uint8_t unpack_qos_swiQosFlow_t::is_Latency_Available

8.1411.2.6 uint8_t unpack_qos_swiQosFlow_t::is_LteQci_Available

8.1411.2.7 uint8_t unpack_qos_swiQosFlow_t::is_MaxAllowedPktSz_Available

8.1411.2.8 uint8_t unpack_qos_swiQosFlow_t::is_MinPolicedPktSz_Available

8.1411.2.9 uint8_t unpack_qos_swiQosFlow_t::is_PktErrRate_Available

8.1411.2.10 uint8_t unpack_qos_swiQosFlow_t::is_ProfileId3GPP2_Available

8.1411.2.11 uint8_t unpack_qos_swiQosFlow_t::is_TokenBucket_Available

8.1411.2.12 uint8_t unpack_qos_swiQosFlow_t::is_TrafficClass_Available

8.1411.2.13 uint8_t unpack_qos_swiQosFlow_t::is_val_3GPP2Pri_Available

8.1411.2.14 uint8_t unpack_qos_swiQosFlow_t::is_val_3GPPImCn_Available

8.1411.2.15 uint8_t unpack_qos_swiQosFlow_t::is_val_3GPPResResidualBER_Available

8.1411.2.16 uint8_t unpack_qos_swiQosFlow_t::is_val_3GPPSigInd_Available

8.1411.2.17 uint8_t unpack_qos_swiQosFlow_t::is_val_3GPPTraHdlPri_Available

8.1411.2.18 uint32_t unpack_qos_swiQosFlow_t::Jitter

8.1411.2.19 uint32_t unpack_qos_swiQosFlow_t::Latency

8.1411.2.20 uint8_t unpack_qos_swiQosFlow_t::LteQci

8.1411.2.21 uint32_t unpack_qos_swiQosFlow_t::MaxAllowedPktSz

8.1411.2.22 uint32_t unpack_qos_swiQosFlow_t::MinPolicedPktSz

8.1411.2.23 unpack_qos_pktErrRate_t unpack_qos_swiQosFlow_t::PktErrRate

8.1411.2.24 uint16_t unpack_qos_swiQosFlow_t::ProfileId3GPP2

8.1411.2.25 unpack_qos_tokenBucket_t unpack_qos_swiQosFlow_t::TokenBucket

8.1411.2.26 uint8_t unpack_qos_swiQosFlow_t::TrafficClass

8.1411.2.27 uint8_t unpack_qos_swiQosFlow_t::val_3GPP2Pri

8.1411.2.28 uint8_t unpack_qos_swiQosFlow_t::val_3GPPImCn

8.1411.2.29 uint16_t unpack_qos_swiQosFlow_t::val_3GPPResResidualBER

8.1411.2.30 uint8_t unpack_qos_swiQosFlow_t::val_3GPPSigInd

8.1411.2.31 uint8_t unpack_qos_swiQosFlow_t::val_3GPPTraHdlPri

8.1412 unpack_qos_tokenBucket_t Struct Reference

Data Fields

- uint32_t peakRate
- uint32_t tokenRate
- uint32_t bucketSz

8.1412.1 Detailed Description

This structure contains the TP flow data rate token bucket

Parameters

peakRate	Maximum rate at which data can be transmitted when the token bucket is full (bits per second)
tokenRate	Rate at which tokens will be put in the token bucket (bits per second); a token is required to be present in the bucket to send a byte of data
bucketSz	Maximum number of tokens that can be accumulated at any instance (bytes); controls the size of the burst that is allowed at any given time

8.1412.2 Field Documentation

8.1412.2.1 uint32_t unpack_qos_tokenBucket_t::bucketSz

8.1412.2.2 uint32_t unpack_qos_tokenBucket_t::peakRate

8.1412.2.3 uint32_t unpack_qos_tokenBucket_t::tokenRate

8.1413 unpack_qos_Tos_t Struct Reference

Data Fields

- uint8_t val
- uint8_t mask

8.1413.1 Detailed Description

This structure contains the IPv4 filter type of service

Parameters

val	Type of service value
mask	Packet matches the TOS filter if: (IPv4_filter_tos_val and IPv4_filter_tos_mask) == (TOS value in the IP packet & IPv4_filter_tos_mask) Example: • IPv4_filter_tos_val = 00101000 • IPv4_filter_tos_mask = 11111100 The filter will compare only the first 6 bits in the IPv4_filter_-type_of_service with the first 6 bits in the TOS field of the IP packet. The first 6 bits in the TOS field of the IP packet must be 001010 to match the filter. The last 2 bits can be anything since they are ignored by filtering.

8.1413.2 Field Documentation

8.1413.2.1 uint8_t unpack_qos_Tos_t::mask

8.1413.2.2 uint8_t unpack_qos_Tos_t::val

8.1414 unpack_QosFlowStat_t Struct Reference

Data Fields

- uint32_t bearerId
- uint32_t tx_pkt
- uint32_t tx_pkt_drp
- uint64_t tx_bytes
- uint64_t tx_bytes_drp

8.1414.1 Detailed Description

This structure contains the Data statistic per QoS flow

Parameters

bearerId	• Bearer ID
tx_pkt	• number of sent packets for the QoS flow ID
tx_pkt_drp	• number of dropped(TX) packets for the QoS flow ID
tx_bytes	• number of sent bytes for the QoS flow ID
tx_bytes_drp	• number of dropped(TX) bytes for the QoS flow ID

8.1414.2 Field Documentation

8.1414.2.1 uint32_t unpack_QosFlowStat_t::bearerId

8.1414.2.2 uint64_t unpack_QosFlowStat_t::tx_bytes

8.1414.2.3 uint64_t unpack_QosFlowStat_t::tx_bytes_drp

8.1414.2.4 uint32_t unpack_QosFlowStat_t::tx_pkt

8.1414.2.5 uint32_t unpack_QosFlowStat_t::tx_pkt_drp

8.1415 unpack_result_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1415.1 Detailed Description

unpack result struct

Parameters

`out`	*Tlvresult*	
`out`	*ParamPresence-Mask*	Parameter presence bit mask

8.1415.2 Field Documentation

8.1415.2.1 swi_uint256_t unpack_result_t::ParamPresenceMask

8.1415.2.2 uint16_t unpack_result_t::Tlvresult

8.1416 unpack_rms_GetSMSWake_t Struct Reference

Data Fields

- uint32_t enabled
- uint32_t wake_mask
- swi_uint256_t ParamPresenceMask

8.1416.1 Detailed Description

Unpack get SMS wake parameters

Parameters

enabled	• SMS wake functionality enabled – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **16**
wake_mask	• SMS wake mask to search for incoming messages (only relevant when enabled) • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1416.2 Field Documentation

8.1416.2.1 uint32_t unpack_rms_GetSMSWake_t::enabled

8.1416.2.2 swi_uint256_t unpack_rms_GetSMSWake_t::ParamPresenceMask

8.1416.2.3 uint32_t unpack_rms_GetSMSWake_t::wake_mask

8.1417 unpack_rms_SetSMSWake_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1417.1 Detailed Description

This structure contains unpack Set SMS Wake.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1417.2 Field Documentation

8.1417.2.1 swi_uint256_t unpack_rms_SetSMSWake_t::ParamPresenceMask

8.1418 unpack_RMTransferStatistics_ind_t Struct Reference

Data Fields

- wds_DataULongTlv TxOkConutTlv
- wds_DataULongTlv RxOkConutTlv
- wds_DataULongLongTlv TxOkByteCountTlv
- wds_DataULongLongTlv RxOkByteCountTlv
- wds_DataULongTlv TxDropConutTlv
- wds_DataULongTlv RxDropConutTlv
- swi_uint256_t ParamPresenceMask

8.1418.1 Detailed Description

WDS packet RM Transfer Statistics data structure for individual session

Parameters

TxOkConutTlv	• Tx Ok Packet Tlv Value. • Bit to check in ParamPresenceMask - **16**
RxOkConutTlv	• Rx Ok Packet Tlv Value. • Bit to check in ParamPresenceMask - **17**
TxOkByteCount-Tlv	• Tx Ok Byte Count Packet Tlv Value. • Bit to check in ParamPresenceMask - **25**
RxOkByteCount-Tlv	• Rx Ok Byte Count Packet Tlv Value. • Bit to check in ParamPresenceMask - **26**
TxDropConutTlv	• Tx Drop Count Packet Tlv Value. • Bit to check in ParamPresenceMask - **37**
RxDropConutTlv	• Rx Drop Count Packet Tlv Value. • Bit to check in ParamPresenceMask - **38**

8.1418.2 Field Documentation

8.1418.2.1 swi_uint256_t unpack_RMTransferStatistics_ind_t::ParamPresenceMask

8.1418.2.2 wds_DataULongTlv unpack_RMTransferStatistics_ind_t::RxDropConutTlv

8.1418.2.3 wds_DataULongLongTlv unpack_RMTransferStatistics_ind_t::RxOkByteCountTlv

8.1418.2.4 wds_DataULongTlv unpack_RMTransferStatistics_ind_t::RxOkConutTlv

8.1418.2.5 wds_DataULongTlv unpack_RMTransferStatistics_ind_t::TxDropConutTlv

8.1418.2.6 wds_DataULongLongTlv unpack_RMTransferStatistics_ind_t::TxOkByteCountTlv

8.1418.2.7 wds_DataULongTlv unpack_RMTransferStatistics_ind_t::TxOkConutTlv

8.1419 unpack_sar_SLQSGetRfSarState_t Struct Reference

Data Fields

- uint32_t ∗ pSarRFState
- swi_uint256_t ParamPresenceMask

8.1419.1 Detailed Description

This structure contains unpack get RF SAR state parameter.

Parameters

pSarRFState	• SAR RF State – QMI_SAR_RF_STATE_DEFAULT – QMI_SAR_RF_STATE_1 – QMI_SAR_RF_STATE_2 – QMI_SAR_RF_STATE_3 – QMI_SAR_RF_STATE_4 – QMI_SAR_RF_STATE_5 – QMI_SAR_RF_STATE_6 – QMI_SAR_RF_STATE_7 – QMI_SAR_RF_STATE_8 • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1419.2 Field Documentation

8.1419.2.1 swi_uint256_t unpack_sar_SLQSGetRfSarState_t::ParamPresenceMask

8.1419.2.2 uint32_t∗ unpack_sar_SLQSGetRfSarState_t::pSarRFState

8.1420 unpack_sms_GetSMSCAddress_t Struct Reference

Data Fields

- uint8_t addressSize
- uint8_t ∗ pSMSCAddress

- uint8_t typeSize
- uint8_t * pSMSCType
- swi_uint256_t ParamPresenceMask

8.1420.1 Detailed Description

Structure contains Gets the SMS center address parameters.

Parameters

addressSize	• The maximum number of characters (including NULL terminator) that the SMS center address array can contain. • Bit to check in ParamPresenceMask - **1**
pSMSCAddress	• The SMS center address represented as a NULL terminated string. • Bit to check in ParamPresenceMask - **1**
typeSize	• The maximum number of characters (including NULL terminator) that the SMS center address type array can contain. • Bit to check in ParamPresenceMask - **1**
pSMSCType	• The SMS center address type represented as a NULL terminated string. • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1420.2 Field Documentation

8.1420.2.1 uint8_t unpack_sms_GetSMSCAddress_t::addressSize

8.1420.2.2 swi_uint256_t unpack_sms_GetSMSCAddress_t::ParamPresenceMask

8.1420.2.3 uint8_t* unpack_sms_GetSMSCAddress_t::pSMSCAddress

8.1420.2.4 uint8_t* unpack_sms_GetSMSCAddress_t::pSMSCType

8.1420.2.5 uint8_t unpack_sms_GetSMSCAddress_t::typeSize

8.1421 unpack_sms_SaveSMS_t Struct Reference

Data Fields

- uint32_t * pMessageIndex
- swi_uint256_t ParamPresenceMask

8.1421.1 Detailed Description

This structure contains unpack save SMS parameter.

Parameters

pMessageIndex	• The message index assigned by the device • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1421.2 Field Documentation

8.1421.2.1 swi_uint256_t unpack_sms_SaveSMS_t::ParamPresenceMask

8.1421.2.2 uint32_t* unpack_sms_SaveSMS_t::pMessageIndex

8.1422 unpack_sms_SendSMS_t Struct Reference

Data Fields

- uint16_t messageID
- uint32_t messageFailureCode
- swi_uint256_t ParamPresenceMask

8.1422.1 Detailed Description

This structure contains unpack send SMS parameters.

Parameters

messageID	• WMS message ID • Bit to check in ParamPresenceMask - **1**
messageFailure-Code	• pointer to message failure code. • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1422.2 Field Documentation

8.1422.2.1 uint32_t unpack_sms_SendSMS_t::messageFailureCode

8.1422.2.2 uint16_t unpack_sms_SendSMS_t::messageID

8.1422.2.3 swi_uint256_t unpack_sms_SendSMS_t::ParamPresenceMask

8.1423 unpack_sms_SetNewSMSCallback_ind_t Struct Reference

Data Fields

- newMTMessageTlv NewMMTlv
- transferRouteMessageTlv TRMessageTlv
- messageModeTlv MMTlv
- sMSEtwsMessageTlv ETWSTlv
- eTWSPLMNInfoTlv ETWSPLMNTlv
- sMSCAddressTlv SMSCTlv
- sMSOnIMSTlv IMSTlv
- swi_uint256_t ParamPresenceMask

8.1423.1 Detailed Description

This structure contains unpack new SMS callback indication.

Parameters

NewMMTlv	• MT message • See newMTMessageTlv for more information • Bit to check in ParamPresenceMask - **16**
TRMessageTlv	• Transfer Route MT Message • See transferRouteMessageTlv for more information • Bit to check in ParamPresenceMask - **17**
MMTlv	• Message mode • See messageModeTlv for more information • Bit to check in ParamPresenceMask - **18**
ETWSTlv	• ETWS Message • See sMSEtwsMessageTlv for more information • Bit to check in ParamPresenceMask - **19**
ETWSPLMNTlv	• ETWS PLMN Information • See eTWSPLMNInfoTlv for more information • Bit to check in ParamPresenceMask - **20**
SMSCTlv	• SMSC Address • See sMSCAddressTlv for more information • Bit to check in ParamPresenceMask - **21**
IMSTlv	• SMS on IMS • See sMSOnIMSTlv for more information • Bit to check in ParamPresenceMask - **22**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1423.2 Field Documentation

8.1423.2.1 eTWSPLMNInfoTlv unpack_sms_SetNewSMSCallback_ind_t::ETWSPLMNTlv

8.1423.2.2 sMSEtwsMessageTlv unpack_sms_SetNewSMSCallback_ind_t::ETWSTlv

8.1423.2.3 sMSOnIMSTlv unpack_sms_SetNewSMSCallback_ind_t::IMSTlv

8.1423.2.4 messageModeTlv unpack_sms_SetNewSMSCallback_ind_t::MMTlv

8.1423.2.5 newMTMessageTlv unpack_sms_SetNewSMSCallback_ind_t::NewMMTlv

8.1423.2.6 swi_uint256_t unpack_sms_SetNewSMSCallback_ind_t::ParamPresenceMask

8.1423.2.7 sMSCAddressTlv unpack_sms_SetNewSMSCallback_ind_t::SMSCTlv

8.1423.2.8 transferRouteMessageTlv unpack_sms_SetNewSMSCallback_ind_t::TRMessageTlv

8.1424 unpack_sms_SetNewSMSCallback_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1424.1 Detailed Description

This structure contains unpack set new SMS callback.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1424.2 Field Documentation

8.1424.2.1 swi_uint256_t unpack_sms_SetNewSMSCallback_t::ParamPresenceMask

8.1425 unpack_sms_SetSMSCAddress_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1425.1 Detailed Description

This structure contains unpack Set SMS Address parameter.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1425.2 Field Documentation

8.1425.2.1 swi_uint256_t unpack_sms_SetSMSCAddress_t::ParamPresenceMask

8.1426 unpack_sms_SLQSDeleteSMS_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1426.1 Detailed Description

This structure contains unpack delete SMS parameters.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1426.2 Field Documentation

8.1426.2.1 swi_uint256_t unpack_sms_SLQSDeleteSMS_t::ParamPresenceMask

8.1427 unpack_sms_SLQSGetIndicationRegister_t Struct Reference

Data Fields

- sms_getIndicationReg * pGetIndicationRegInfo
- swi_uint256_t ParamPresenceMask

8.1427.1 Detailed Description

Structure containing Parameters that provides registration state of different WMS indications.

Parameters

pGetIndication-RegInfo	• Pointer to structure of getIndicationReg – See sms_getIndicationReg for more information – pRegTransLayerInfoEvt * Bit to check in ParamPresenceMask - **16** – pRegTransNWRegInfoEvt * Bit to check in ParamPresenceMask - **17** – pRegCallStatInfoEvt * Bit to check in ParamPresenceMask - **18**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1427.2 Field Documentation

8.1427.2.1 swi_uint256_t unpack_sms_SLQSGetIndicationRegister_t::ParamPresenceMask

8.1427.2.2 sms_getIndicationReg∗ unpack_sms_SLQSGetIndicationRegister_t::pGetIndicationRegInfo

8.1428 unpack_sms_SLQSGetMessageWaiting_t Struct Reference

Data Fields

- sms_getMsgWaitingInfo ∗ pGetMsgWaitingInfoResp
- swi_uint256_t ParamPresenceMask

8.1428.1 Detailed Description

Structure contain Parameter that provide information about the message waiting information.

Parameters

pGetMsg-WaitingInfoResp	• Pointer to structure of getMsgWaitingInfoResp – See sms_getMsgWaitingInfo for more information • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1428.2 Field Documentation

8.1428.2.1 swi_uint256_t unpack_sms_SLQSGetMessageWaiting_t::ParamPresenceMask

8.1428.2.2 sms_getMsgWaitingInfo∗ unpack_sms_SLQSGetMessageWaiting_t::pGetMsgWaitingInfoResp

8.1429 unpack_sms_SLQSGetSMS_t Struct Reference

Data Fields

- uint32_t messageTag
- uint32_t messageFormat
- uint32_t messageSize
- uint8_t message [2048]
- swi_uint256_t ParamPresenceMask

8.1429.1 Detailed Description

This sturcture contains unpack get SMS parameters.

Parameters

messageTag	• Message tag – 0 - Read – 1 - Not read – 2 - Mobile originated and sent – 3 - Mobile originated but not yet sent

- Bit to check in ParamPresenceMask - **1**

Parameters

messageFormat	• Message format – 0 - CDMA (IS-637B) – 1 - 5 (Reserved) – 6 - GSM/WCDMA PP

- Bit to check in ParamPresenceMask - **1**

Parameters

messageSize	• Upon input the maximum number of bytes that can be written to the message array. • Upon successful output the actual number of bytes written to the message array. • Bit to check in ParamPresenceMask - **1**
message	• The message contents array
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1429.2 Field Documentation

8.1429.2.1 uint8_t unpack_sms_SLQSGetSMS_t::message[2048]

8.1429.2.2 uint32_t unpack_sms_SLQSGetSMS_t::messageFormat

8.1429.2.3 uint32_t unpack_sms_SLQSGetSMS_t::messageSize

8.1429.2.4 uint32_t unpack_sms_SLQSGetSMS_t::messageTag

8.1429.2.5 swi_uint256_t unpack_sms_SLQSGetSMS_t::ParamPresenceMask

8.1430 unpack_sms_SLQSGetSmsBroadcastConfig_t Struct Reference

Data Fields

- sms_qaQmi3GPPBroadcastCfgInfo * pBroadcastConfig
- sms_qaQmi3GPP2BroadcastCfgInfo * pCDMABroadcastConfig
- swi_uint256_t ParamPresenceMask

8.1430.1 Detailed Description

Structure contain parameters that Provides Information about the SMS BroadcastConfiguration

Parameters

pBroadcast-Config	• The data for 3GPP Broadcast Information(Optional). • Bit to check in ParamPresenceMask - **16**
pCDMA-BroadcastConfig	• The data for 3GPP2 Broadcast Information(Optional). • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1430.2 Field Documentation

8.1430.2.1 swi_uint256_t unpack_sms_SLQSGetSmsBroadcastConfig_t::ParamPresenceMask

8.1430.2.2 sms_qaQmi3GPPBroadcastCfgInfo* unpack_sms_SLQSGetSmsBroadcastConfig_t::pBroadcastConfig

8.1430.2.3 sms_qaQmi3GPP2BroadcastCfgInfo* unpack_sms_SLQSGetSmsBroadcastConfig_t::pCDMABroadcast-Config

8.1431 unpack_sms_SLQSGetSMSList_t Struct Reference

Data Fields

- uint32_t messageListSize
- qmiSmsMessageList messageList [255]
- swi_uint256_t ParamPresenceMask

8.1431.1 Detailed Description

This structure contains unpack get SMS list parameters.

Parameters

messageListSize	• Upon input the maximum number of elements that the message list array can contain. • Upon successful output the actual number of elements in the message list array. • Bit to check in ParamPresenceMask - **1**

messageList	• Message List • See qmiSmsMessageList for more information • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1431.2 Field Documentation

8.1431.2.1 qmiSmsMessageList unpack_sms_SLQSGetSMSList_t::messageList[255]

8.1431.2.2 uint32_t unpack_sms_SLQSGetSMSList_t::messageListSize

8.1431.2.3 swi_uint256_t unpack_sms_SLQSGetSMSList_t::ParamPresenceMask

8.1432 unpack_sms_SLQSGetTransLayerInfo_t Struct Reference

Data Fields

- sms_getTransLayerInfo * pGetTransLayerInfo
- swi_uint256_t ParamPresenceMask

8.1432.1 Detailed Description

Structure contain parameters that gives information about the transport layer.

Parameters

pGetTransLayer-Info	• Pointer to structure of getTransLayerInfo – See sms_getTransLayerInfo for more information – pGetTransLayerInfo->pRegInd * Bit to check in ParamPresenceMask - **16** – pGetTransLayerInfo->pTransLayerInfo * Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1432.2 Field Documentation

8.1432.2.1 swi_uint256_t unpack_sms_SLQSGetTransLayerInfo_t::ParamPresenceMask

8.1432.2.2 sms_getTransLayerInfo* unpack_sms_SLQSGetTransLayerInfo_t::pGetTransLayerInfo

8.1433 unpack_sms_SLQSGetTransNWRegInfo_t Struct Reference

Data Fields

- sms_getTransNWRegInfo * pGetTransNWRegInfo
- swi_uint256_t ParamPresenceMask

8.1433.1 Detailed Description

Structure containing parameters that provides transport layer network registration info.

Parameters

pGetTransNW-RegInfo	• Pointer to structure of getTransNWRegInfo – See sms_getTransNWRegInfo for more information – Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1433.2 Field Documentation

8.1433.2.1 swi_uint256_t unpack_sms_SLQSGetTransNWRegInfo_t::ParamPresenceMask

8.1433.2.2 sms_getTransNWRegInfo* unpack_sms_SLQSGetTransNWRegInfo_t::pGetTransNWRegInfo

8.1434 unpack_sms_SLQSModifySMSStatus_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1434.1 Detailed Description

This structure contains unpack modify SMS status parameters.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1434.2 Field Documentation

8.1434.2.1 swi_uint256_t unpack_sms_SLQSModifySMSStatus_t::ParamPresenceMask

8.1435 unpack_sms_SLQSNWRegInfoCallback_ind_t Struct Reference

Data Fields

- uint8_t NWRegStat
- swi_uint256_t ParamPresenceMask

8.1435.1 Detailed Description

Contains the parameters passed for indication about transport network registration change by the device.

Parameters

NWRegStat	• provides the transport network registration information • Values: – 0x00 - No Service – 0x01 - In Progress – 0x02 - Failed – 0x03 - Limited Service – 0x04 - Full Service • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

None

8.1435.2 Field Documentation

8.1435.2.1 uint8_t unpack_sms_SLQSNWRegInfoCallback_ind_t::NWRegStat

8.1435.2.2 swi_uint256_t unpack_sms_SLQSNWRegInfoCallback_ind_t::ParamPresenceMask

8.1436 unpack_sms_SLQSSendAsyncSMS_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1436.1 Detailed Description

This structure contains unpack SLQSSendAsyncSMS parameter.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1436.2 Field Documentation

8.1436.2.1 swi_uint256_t unpack_sms_SLQSSendAsyncSMS_t::ParamPresenceMask

8.1437 unpack_sms_SLQSSetIndicationRegister_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1437.1 Detailed Description

This structure contains unpack SLQSSetIndicationRegister parameter.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1437.2 Field Documentation

8.1437.2.1 swi_uint256_t unpack_sms_SLQSSetIndicationRegister_t::ParamPresenceMask

8.1438 unpack_sms_SLQSSetSmsBroadcastActivation_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1438.1 Detailed Description

This structure contains unpack SLQSSetSmsBroadcastActivation parameter.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1438.2 Field Documentation

8.1438.2.1 swi_uint256_t unpack_sms_SLQSSetSmsBroadcastActivation_t::ParamPresenceMask

8.1439 unpack_sms_SLQSSetSmsBroadcastConfig_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1439.1 Detailed Description

This structure contains unpack SLQSSetSmsBroadcastConfig parameters.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1439.2 Field Documentation

8.1439.2.1 swi_uint256_t unpack_sms_SLQSSetSmsBroadcastConfig_t::ParamPresenceMask

8.1440 unpack_sms_SLQSSetSmsStorage_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1440.1 Detailed Description

This structure contains unpack SLQSSetSmsStorage parameter.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1440.2 Field Documentation

8.1440.2.1 swi_uint256_t unpack_sms_SLQSSetSmsStorage_t::ParamPresenceMask

8.1441 unpack_sms_SLQSSmsGetMaxStorageSize_t Struct Reference

Data Fields

- sms_maxStorageSizeResp * pMaxStorageSizeResp
- swi_uint256_t ParamPresenceMask

8.1441.1 Detailed Description

Structure contain parameters that provides the maximum number of messages that can be stored in the specified memory storage. Also it provides the number of slots currently available

Parameters

pMaxStorage-SizeResp	• Response parameters for SmsSLQSGetMaxStorageSize – See sms_maxStorageSizeResp for more information • pMaxStorageSizeResp->maxStorageSize – Bit to check in ParamPresenceMask - **1** • pMaxStorageSizeResp->freeSlots – Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1441.2 Field Documentation

8.1441.2.1 swi_uint256_t unpack_sms_SLQSSmsGetMaxStorageSize_t::ParamPresenceMask

8.1441.2.2 sms_maxStorageSizeResp* unpack_sms_SLQSSmsGetMaxStorageSize_t::pMaxStorageSizeResp

8.1442 unpack_sms_SLQSSmsGetMessageProtocol_t Struct Reference

Data Fields

- sms_msgProtocolResp * pMessageProtocol
- swi_uint256_t ParamPresenceMask

8.1442.1 Detailed Description

Structure contain Parameters that get the message protocol currently in use for the WMS client.

Parameters

pMessage-Protocol	• Pointer to smsMsgprotocolResp – See sms_msgProtocolResp for more information • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1442.2 Field Documentation

8.1442.2.1 swi_uint256_t unpack_sms_SLQSSmsGetMessageProtocol_t::ParamPresenceMask

8.1442.2.2 sms_msgProtocolResp* unpack_sms_SLQSSmsGetMessageProtocol_t::pMessageProtocol

8.1443 unpack_sms_SLQSSmsSetRoutes_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1443.1 Detailed Description

This structure contains unpack SLQSSmsSetRoutes parameter.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1443.2 Field Documentation

8.1443.2.1 swi_uint256_t unpack_sms_SLQSSmsSetRoutes_t::ParamPresenceMask

8.1444 unpack_sms_SLQSSwiGetSMSStorage_t Struct Reference

Data Fields

- uint32_t ∗ pSmsStorage
- swi_uint256_t ParamPresenceMask

8.1444.1 Detailed Description

Structure contain Parameters that return current SMS configuration that is applied to all incoming and outgoing messages.

Parameters

pSmsStorage	• Values: – 0x01 - device's permanent memory – 0x02 - UICC • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1444.2 Field Documentation

8.1444.2.1 swi_uint256_t unpack_sms_SLQSSwiGetSMSStorage_t::ParamPresenceMask

8.1444.2.2 uint32_t∗ unpack_sms_SLQSSwiGetSMSStorage_t::pSmsStorage

8.1445 unpack_sms_SLQSTransLayerInfoCallback_ind_t Struct Reference

Data Fields

- uint8_t regInd
- sms_transLayerInfo ∗ pTransLayerInfo
- swi_uint256_t ParamPresenceMask

8.1445.1 Detailed Description

Contains the parameters passed for the indication about change in transport layer information

Parameters

regInd	• Indicates whether the transport layer is registered or not • Values: – 0x00 - Transport layer is not registered – 0x01 - Transport layer is registered • Bit to check in ParamPresenceMask - **1**

pTransLayerInfo	• Optional parameter • See sms_transLayerInfo for more information • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

None

8.1445.2 Field Documentation

8.1445.2.1 swi_uint256_t unpack_sms_SLQSTransLayerInfoCallback_ind_t::ParamPresenceMask

8.1445.2.2 sms_transLayerInfo* unpack_sms_SLQSTransLayerInfoCallback_ind_t::pTransLayerInfo

8.1445.2.3 uint8_t unpack_sms_SLQSTransLayerInfoCallback_ind_t::regInd

8.1446 unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t Struct Reference

Data Fields

- uint16_t sendStatus
- uint16_t messageID
- uint16_t causeCode
- uint8_t errorClass
- uint16_t RPCause
- uint8_t TPCause
- uint8_t msgDelFailureType
- uint8_t msgDelFailureCause
- uint8_t alphaIDLen
- uint8_t * pAlphaID
- uint32_t userData
- swi_uint256_t ParamPresenceMask

8.1446.1 Detailed Description

This structure contains SMS parameters for indication of RAW ASYNC SEND

Parameters

sendStatus	• Send Status • Values: – QMI_ERR_NONE - No error in the request – QMI_ERR_CAUSE_CODE - SMS cause code – QMI_ERR_MESSAGE_DELIVERY_FAILURE - Message could not be delivered – QMI_ERR_NO_MEMORY - Device could not allocate memory to formulate a response • Bit to check in ParamPresenceMask - **1**

messageID	• Unique ID assigned by WMS for non-retry messages. • Bit to check in ParamPresenceMask - **16**
causeCode	• WMS cause code • Bit to check in ParamPresenceMask - **17**
errorClass	• Error Class • Values: – 0x00 - ERROR_CLASS_TEMPORARY – 0x01 - ERROR_CLASS_PERMANENT • Bit to check in ParamPresenceMask - **18**
RPCause	• GW RP cause • Bit to check in ParamPresenceMask - **19**
TPCause	• GW TP Cause • Bit to check in ParamPresenceMask - **19**
msgDelFailure-Type	• Message delivery failure type • Values: – 0x00 - WMS_MESSAGE_DELIVERY_FAILURE_TEMPORARY – 0x01 - WMS_MESSAGE_DELIVERY_FAILURE_PERMANENT • Bit to check in ParamPresenceMask - **20**
msgDelFailure-Cause	• Message delivery failure cause • Values: – 0x00 - WMS_MESSAGE_BLOCKED_DUE_TO_CALL_CONTROL • Bit to check in ParamPresenceMask - **21**
alphaIDLen	• Number of sets of the pAlphaID • Bit to check in ParamPresenceMask - **22**
pAlphaID	• Alpha ID • Bit to check in ParamPresenceMask - **22**
userData	• Identifies the request associated with this indication. • Bit to check in ParamPresenceMask - **23**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1446.2 Field Documentation

8.1446.2.1 uint8_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::alphaIDLen

8.1446.2.2 uint16_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::causeCode

8.1446.2.3 uint8_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::errorClass

8.1446.2.4 uint16_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::messageID

8.1446.2.5 uint8_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::msgDelFailureCause

8.1446.2.6 uint8_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::msgDelFailureType

8.1446.2.7 uint8_t* unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::pAlphaID

8.1446.2.8 swi_uint256_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::ParamPresenceMask

8.1446.2.9 uint16_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::RPCause

8.1446.2.10 uint16_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::sendStatus

8.1446.2.11 uint8_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::TPCause

8.1446.2.12 uint32_t unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t::userData

8.1447 unpack_sms_SLQSWmsMemoryFullCallBack_ind_t Struct Reference

Data Fields

- uint8_t storageType
- uint8_t messageMode
- swi_uint256_t ParamPresenceMask

8.1447.1 Detailed Description

This structure contains unpack SMS memory full callback indication.

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV • Bit to check in ParamPresenceMask - **1**
messageMode	• 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS) • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1447.2 Field Documentation

8.1447.2.1 uint8_t unpack_sms_SLQSWmsMemoryFullCallBack_ind_t::messageMode

8.1447.2.2 swi_uint256_t unpack_sms_SLQSWmsMemoryFullCallBack_ind_t::ParamPresenceMask

8.1447.2.3 uint8_t unpack_sms_SLQSWmsMemoryFullCallBack_ind_t::storageType

8.1448 unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t Struct Reference

Data Fields

- uint8_t numInstances
- sms_messageWaitingInfoContent msgWaitInfo [0xFF]
- swi_uint256_t ParamPresenceMask

8.1448.1 Detailed Description

This structure holds information related to message waiting information indication

Parameters

numInstances	• Number of sets of the elements in structure sms_messageWaitingInfoContent • Bit to check in ParamPresenceMask - **1**
msgWaitInfo	• Pointer to structure of sms_messageWaitingInfoContent. – See sms_messageWaitingInfoContent for more information. • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1448.2 Field Documentation

8.1448.2.1 sms_messageWaitingInfoContent unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t::msgWaitInfo[0xFF]

8.1448.2.2 uint8_t unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t::numInstances

8.1448.2.3 swi_uint256_t unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t::ParamPresenceMask

8.1449 unpack_swidms_SLQSSwiDmsGetHWWatchdog_t Struct Reference

Data Fields

- swidms_SwiDmsGetHWWatchdog * pHWWatchdog
- swi_uint256_t ParamPresenceMask

8.1449.1 Detailed Description

This structure contains the get hw watchdog response

Parameters

pHWWatchdog	• See swidms_SwiDmsGetHWWatchdog for more information • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1449.2 Field Documentation

8.1449.2.1 swi_uint256_t unpack_swidms_SLQSSwiDmsGetHWWatchdog_t::ParamPresenceMask

8.1449.2.2 swidms_SwiDmsGetHWWatchdog* unpack_swidms_SLQSSwiDmsGetHWWatchdog_t::pHWWatchdog

8.1450 unpack_swidms_SLQSSwiDmsGetMTU_t Struct Reference

Data Fields

- swidms_mtuSize3gppTlv * pMTUSize3gpp
- swidms_hrpdMTUSizeTlv * pHrpdMTUSize
- swidms_ehrpdMTUSizeTlv * pEhrpdMTUSize
- swidms_usbMTUSizeTlv * pUsbMTUSize
- swi_uint256_t ParamPresenceMask

8.1450.1 Detailed Description

This structure contains the Get MTU Response parameter.

Parameters

pMTUSize3gpp	[Optional] • See swidms_mtuSize3gppTlv for more information • Bit to check in ParamPresenceMask - **16**
pHrpdMTUSize	[Optional] • See swidms_hrpdMTUSizeTlv for more information • Bit to check in ParamPresenceMask - **17**
pEhrpdMTUSize	[Optional] • See swidms_ehrpdMTUSizeTlv for more information • Bit to check in ParamPresenceMask - **18**
pUsbMTUSize	[Optional] • See swidms_usbMTUSizeTlv for more information • Bit to check in ParamPresenceMask - **19**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1450.2 Field Documentation

8.1450.2.1 swi_uint256_t unpack_swidms_SLQSSwiDmsGetMTU_t::ParamPresenceMask

8.1450.2.2 swidms_ehrpdMTUSizeTlv* unpack_swidms_SLQSSwiDmsGetMTU_t::pEhrpdMTUSize

8.1450.2.3 swidms_hrpdMTUSizeTlv* unpack_swidms_SLQSSwiDmsGetMTU_t::pHrpdMTUSize

8.1450.2.4 swidms_mtuSize3gppTlv* unpack_swidms_SLQSSwiDmsGetMTU_t::pMTUSize3gpp

8.1450.2.5 swidms_usbMTUSizeTlv* unpack_swidms_SLQSSwiDmsGetMTU_t::pUsbMTUSize

8.1451 unpack_swidms_SLQSSwiDmsGetSecureInfo_t Struct Reference

Data Fields

- uint8_t secureBootEnabled
- uint8_t memoryDumpAllowed
- uint8_t jtagAccessAllowed
- uint16_t TlvResult
- swi_uint256_t ParamPresenceMask

8.1451.1 Detailed Description

This structure contains secure boot config and other capabilities

Parameters

secureBootEnabled	• secure boot enabled or disabled 0- disabled 1- enabled • Bit to check in ParamPresenceMask - **1**
memoryDumpAllowed	• memory dump alloweed or disallowed 0- disallowed 1- allowed • Bit to check in ParamPresenceMask - **3**
jtagAccessAllowed	• Jtag access allowed or disallowed 0- disallowed 1- allowed • Bit to check in ParamPresenceMask - **4**
Tlvresult	• unpack Tlv result • Bit to check in ParamPresenceMask - **2**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1451.2 Field Documentation

8.1451.2.1 uint8_t unpack_swidms_SLQSSwiDmsGetSecureInfo_t::jtagAccessAllowed

8.1451.2.2 uint8_t unpack_swidms_SLQSSwiDmsGetSecureInfo_t::memoryDumpAllowed

8.1451.2.3 swi_uint256_t unpack_swidms_SLQSSwiDmsGetSecureInfo_t::ParamPresenceMask

8.1451.2.4 uint8_t unpack_swidms_SLQSSwiDmsGetSecureInfo_t::secureBootEnabled

8.1451.2.5 uint16_t unpack_swidms_SLQSSwiDmsGetSecureInfo_t::TlvResult

8.1452 unpack_swidms_SLQSSwiDmsGetUsbComp_t Struct Reference

Data Fields

- swidms_intfaceCfgTlv * pInterfaceCfg
- swidms_supportedIntBitmaskTlv * pSupportedBitmasks
- swi_uint256_t ParamPresenceMask

8.1452.1 Detailed Description

This structure contains the get usb composition response

Parameters

pInterfaceCfg	• See swidms_intfaceCfgTlv for more information • Bit to check in ParamPresenceMask - **1**
pSupported-Bitmasks	[Optional] • See swidms_supportedIntBitmaskTlv for more information • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1452.2 Field Documentation

8.1452.2.1 swi_uint256_t unpack_swidms_SLQSSwiDmsGetUsbComp_t::ParamPresenceMask

8.1452.2.2 swidms_intfaceCfgTlv* unpack_swidms_SLQSSwiDmsGetUsbComp_t::pInterfaceCfg

8.1452.2.3 swidms_supportedIntBitmaskTlv* unpack_swidms_SLQSSwiDmsGetUsbComp_t::pSupportedBitmasks

8.1453 unpack_swidms_SLQSSwiDmsGetUsbNetNum_t Struct Reference

Data Fields

- uint8_t usbNetNum
- swi_uint256_t ParamPresenceMask

8.1453.1 Detailed Description

This structure contains usb net numbers to get from remote endpoint for QMAP configuration

Parameters

usbNetNum	• value of usb net numbers on the device • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1453.2 Field Documentation

8.1453.2.1 swi_uint256_t unpack_swidms_SLQSSwiDmsGetUsbNetNum_t::ParamPresenceMask

8.1453.2.2 uint8_t unpack_swidms_SLQSSwiDmsGetUsbNetNum_t::usbNetNum

8.1454 unpack_swidms_SLQSSwiDmsSetHWWatchdog_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1454.1 Detailed Description

This structure is used to store unpack_swidms_SLQSSwiDmsSetHWWatchdog_t parameters.

Parameters

Tlvresult	• unpack Tlv result • Bit to check in ParamPresenceMask - **2**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1454.2 Field Documentation

8.1454.2.1 swi_uint256_t unpack_swidms_SLQSSwiDmsSetHWWatchdog_t::ParamPresenceMask

8.1454.2.2 uint16_t unpack_swidms_SLQSSwiDmsSetHWWatchdog_t::Tlvresult

8.1455 unpack_swidms_SLQSSwiDmsSetMTU_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1455.1 Detailed Description

This structure is used to store unpack_swidms_SLQSSwiDmsSetMTU_t parameters.

Parameters

Tlvresult	• unpack Tlv result • Bit to check in ParamPresenceMask - **2**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1455.2 Field Documentation

8.1455.2.1 swi_uint256_t unpack_swidms_SLQSSwiDmsSetMTU_t::ParamPresenceMask

8.1455.2.2 uint16_t unpack_swidms_SLQSSwiDmsSetMTU_t::Tlvresult

8.1456 unpack_swidms_SLQSSwiDmsSetUsbComp_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1456.1 Detailed Description

This structure is used to store unpack_swidms_SLQSSwiDmsSetUsbComp_t parameters.

Parameters

Tlvresult	• unpack Tlv result • Bit to check in ParamPresenceMask - **2**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1456.2 Field Documentation

8.1456.2.1 swi_uint256_t unpack_swidms_SLQSSwiDmsSetUsbComp_t::ParamPresenceMask

8.1456.2.2 uint16_t unpack_swidms_SLQSSwiDmsSetUsbComp_t::Tlvresult

8.1457 unpack_swiloc_SwiLocGetAutoStart_t Struct Reference

Data Fields

- uint8_t function
- int function_reported

- uint8_t fix_type
- int fix_type_reported
- uint8_t max_time
- int max_time_reported
- uint32_t max_dist
- int max_dist_reported
- uint32_t fix_rate
- int fix_rate_reported
- swi_uint256_t ParamPresenceMask

8.1457.1 Detailed Description

This structure contains SWI LOC Get Auto Start setting

Parameters

function	• Setting to indicate when modem should start an automatic GNSS fix – 0 - disabled – 1 - At bootup – 2 - When NMEA port is opened • Bit to check in ParamPresenceMask - **16**
function_reported	• 0 - not reported by modem • I - reported by modem
fix_type	• Type of GNSS fix: – 1 - Default Engine mode – 2 - MS-Based – 3 - MS-Assisted – 4 - Standalone • Bit to check in ParamPresenceMask - **17**
fix_type_reported	• 0 - not reported by modem • I - reported by modem
max_time	• Maximum time allowed for the receiver to get a fix in seconds • Valid range: 1-255 • Bit to check in ParamPresenceMask - **18**
max_time_reported	• 0 - not reported by modem • I - reported by modem
max_dist	• Maximum uncertainty of a fix measured by distance in meters • Valid range: 1 - 4294967280 • Bit to check in ParamPresenceMask - **19**

max_dist_-reported	• 0 - not reported by modem • l - reported by modem
fix_rate	• Time between fixes in seconds • Valid range: 1–65535 • Bit to check in ParamPresenceMask - **20**
fix_rate_-reported	• 0 - not reported by modem • l - reported by modem

8.1457.2 Field Documentation

8.1457.2.1 uint32_t unpack_swiloc_SwiLocGetAutoStart_t::fix_rate

8.1457.2.2 int unpack_swiloc_SwiLocGetAutoStart_t::fix_rate_reported

8.1457.2.3 uint8_t unpack_swiloc_SwiLocGetAutoStart_t::fix_type

8.1457.2.4 int unpack_swiloc_SwiLocGetAutoStart_t::fix_type_reported

8.1457.2.5 uint8_t unpack_swiloc_SwiLocGetAutoStart_t::function

8.1457.2.6 int unpack_swiloc_SwiLocGetAutoStart_t::function_reported

8.1457.2.7 uint32_t unpack_swiloc_SwiLocGetAutoStart_t::max_dist

8.1457.2.8 int unpack_swiloc_SwiLocGetAutoStart_t::max_dist_reported

8.1457.2.9 uint8_t unpack_swiloc_SwiLocGetAutoStart_t::max_time

8.1457.2.10 int unpack_swiloc_SwiLocGetAutoStart_t::max_time_reported

8.1457.2.11 swi_uint256_t unpack_swiloc_SwiLocGetAutoStart_t::ParamPresenceMask

8.1458 unpack_swioma_SLQSOMADMAlertCallback_ind_t Struct Reference

Data Fields

- uint32_t eventType
- unpack_omaDmFotaTlv_t SessionInfoFota
- unpack_omaDmConfigTlv_t SessionInfoConfig
- unpack_omaDmNotificationsTlv_t SessionInfoNotification
- swi_uint256_t ParamPresenceMask

8.1458.1 Detailed Description

Structure that contains OMA indication information based on eventType Strucutres for which the event is not valid will have values set to 0

Parameters

eventType	• 0x00 - SWIOMA-DM FOTA • 0x01 - SWIOMA-DM Config • 0x02 - SWIOMA-DM Notification • 0xff - indication missing event information.
SessionInfo-Fota[OUT]	• See unpack_omaDmFotaTlv_t for more information • Bit to check in ParamPresenceMask - **16**
SessionInfo-Config[OUT]	• See unpack_omaDmConfigTlv_t for more information • Bit to check in ParamPresenceMask - **17**
SessionInfo-Notification[OUT]	• See unpack_omaDmNotificationsTlv_t for more information • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1458.2 Field Documentation

8.1458.2.1 uint32_t unpack_swioma_SLQSOMADMAlertCallback_ind_t::eventType

8.1458.2.2 swi_uint256_t unpack_swioma_SLQSOMADMAlertCallback_ind_t::ParamPresenceMask

8.1458.2.3 unpack_omaDmConfigTlv_t unpack_swioma_SLQSOMADMAlertCallback_ind_t::SessionInfoConfig

8.1458.2.4 unpack_omaDmFotaTlv_t unpack_swioma_SLQSOMADMAlertCallback_ind_t::SessionInfoFota

8.1458.2.5 unpack_omaDmNotificationsTlv_t unpack_swioma_SLQSOMADMAlertCallback_ind_t::SessionInfo-Notification

8.1459 unpack_swioma_SLQSOMADMGetSessionInfo_t Struct Reference

Data Fields

- uint8_t Status
- uint16_t UpdateCompleteStatus
- uint8_t Severity
- uint16_t SourceLength
- uint8_t Source [255]
- uint16_t PkgNameLength
- uint8_t PkgName [255]
- uint16_t PkgDescLength
- uint8_t PkgDescription [255]
- uint16_t DateLength
- uint8_t Date [255]
- uint16_t TimeLength
- uint8_t Time [255]

- uint8_t SessionType
- uint8_t SessionState
- uint16_t RetryCount
- swi_uint256_t ParamPresenceMask

8.1459.1 Detailed Description

Structure that contains the session type for OMA get session info unpack command Also used as input parameter to specify the size of variable parameters. (ref. notes)

Parameters

Status	• 1 Byte parameter indicating status – 0x01 - No Firmware available – 0x02 - Query Firmware Download – 0x03 - Firmware Downloading – 0x04 - Firmware Downloaded – 0x05 - Query Firmware Update – 0x06 - Firmware Updating – 0x07 - Firmware Updated • Bit to check in ParamPresenceMask - **16**
UpdateCompleteStatus	• 2 byte parameter indicating Update Complete Status – See qaGobiApiTableSwiOMADMUpdateCompleteStatus.h Update Complete Status • Bit to check in ParamPresenceMask - **16**
Severity	• 1 byte parameter indicating severity – 0x01 - Mandatory – 0x02 - Optional • Bit to check in ParamPresenceMask - **16**
SourceLength	• 2 byte parameter indicating Length of Vendor Name String in Bytes. • Bit to check in ParamPresenceMask - **16**
Source	• Variable length parameter indicating Vendor Name in ASCII • See LITEQMI_MAX_SWIOMA_STR_LEN for more information • Bit to check in ParamPresenceMask - **16**
PkgNameLength	• 2 byte parameter indicating Length of Package Name String in Bytes. • Bit to check in ParamPresenceMask - **16**
PkgName	• Variable length parameter indicating Package Name in ASCII • See LITEQMI_MAX_SWIOMA_STR_LEN for more information • Bit to check in ParamPresenceMask - **16**

PkgDescLength	• 2 byte parameter indicating Length of Package Description String in Bytes. • Bit to check in ParamPresenceMask - **16**
PkgDescription	• Variable length parameter indicating Package Description in ASCII • See LITEQMI_MAX_SWIOMA_STR_LEN for more information • Bit to check in ParamPresenceMask - **16**
DateLength	• 2 byte parameter indicating Length of Package Description String in Bytes. • Bit to check in ParamPresenceMask - **16**
Date	• Variable length parameter indicating Package Description in ASCII • See LITEQMI_MAX_SWIOMA_STR_LEN for more information • Bit to check in ParamPresenceMask - **16**
TimeLength	• 2 byte parameter indicating Length of Time String in Bytes. • Bit to check in ParamPresenceMask - **16**
Time	• Variable length parameter indicating Time String in ASCII • See LITEQMI_MAX_SWIOMA_STR_LEN for more information • Bit to check in ParamPresenceMask - **16**
SessionType	• 1 byte parameter reflects the last session started for Sprint – 0x00 - No session since boot – 0x01 - Sprint CI-DC Session – 0x02 - Sprint CI-PRL Session – 0x03 - Sprint CI-FUMO Session – 0x04 - Sprint HFA-DC Session – 0x05 - Sprint HFA-PRL Session – 0x06 - Sprint HFA-FUMO Session – 0x07 - Sprint NI Session • Bit to check in ParamPresenceMask - **16**
SessionState	• 1 byte parameter indicating session state – 0x01 - idle – 0x02 - active – 0x03 - pending • Bit to check in ParamPresenceMask - **16**
RetryCount	• 1 byte parameter indicating retries left count – valid values 0 to 6 • Bit to check in ParamPresenceMask - **16**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1459.2 Field Documentation

8.1459.2.1 uint8_t unpack_swioma_SLQSOMADMGetSessionInfo_t::Date[255]

8.1459.2.2 uint16_t unpack_swioma_SLQSOMADMGetSessionInfo_t::DateLength

8.1459.2.3 swi_uint256_t unpack_swioma_SLQSOMADMGetSessionInfo_t::ParamPresenceMask

8.1459.2.4 uint16_t unpack_swioma_SLQSOMADMGetSessionInfo_t::PkgDescLength

8.1459.2.5 uint8_t unpack_swioma_SLQSOMADMGetSessionInfo_t::PkgDescription[255]

8.1459.2.6 uint8_t unpack_swioma_SLQSOMADMGetSessionInfo_t::PkgName[255]

8.1459.2.7 uint16_t unpack_swioma_SLQSOMADMGetSessionInfo_t::PkgNameLength

8.1459.2.8 uint16_t unpack_swioma_SLQSOMADMGetSessionInfo_t::RetryCount

8.1459.2.9 uint8_t unpack_swioma_SLQSOMADMGetSessionInfo_t::SessionState

8.1459.2.10 uint8_t unpack_swioma_SLQSOMADMGetSessionInfo_t::SessionType

8.1459.2.11 uint8_t unpack_swioma_SLQSOMADMGetSessionInfo_t::Severity

8.1459.2.12 uint8_t unpack_swioma_SLQSOMADMGetSessionInfo_t::Source[255]

8.1459.2.13 uint16_t unpack_swioma_SLQSOMADMGetSessionInfo_t::SourceLength

8.1459.2.14 uint8_t unpack_swioma_SLQSOMADMGetSessionInfo_t::Status

8.1459.2.15 uint8_t unpack_swioma_SLQSOMADMGetSessionInfo_t::Time[255]

8.1459.2.16 uint16_t unpack_swioma_SLQSOMADMGetSessionInfo_t::TimeLength

8.1459.2.17 uint16_t unpack_swioma_SLQSOMADMGetSessionInfo_t::UpdateCompleteStatus

8.1460 unpack_swioma_SLQSOMADMGetSettings_t Struct Reference

Data Fields

- uint32_t OMADMEnabled
- uint8_t FOTAdownload
- uint8_t FOTAUpdate
- uint8_t Autosdm
- uint8_t FwAutoCheck
- swi_uint256_t ParamPresenceMask

8.1460.1 Detailed Description

Structure containing the OMA DM settings retrieved from the device

Parameters

OMADMEnabled	[out] • Optional 4 byte parameter indicating OMADM service enabled – 0x00000001 - Client-initiated device configuration – 0x00000002 - Network-initiated device configuration – 0x00000010 - Client-initiated FUMO – 0x00000020 - Network-initiated FUMO • Bit to check in ParamPresenceMask - **16**
FOTAdownload	[out] • Optional 1 Byte parameter indicating support for FOTA Automatic download – 0x00 - Host permission required before downloading – 0x01 - Automatically start downloading, no host permission required – 0x02 - Automatically start downloading, while not roaming – 0x03 - Automatically reject download – 0x04 - Automatically reject download with “Enterprise Reject Policy • Bit to check in ParamPresenceMask - **17**
FOTAUpdate	[out] • Optional 1 byte parameter indicating FOTA Automatic update – 0x00 - User permission required before updating firmware – 0x01 - No user permission required before updating firmware – 0x02 - User permission required, auto update on power up • Bit to check in ParamPresenceMask - **18**
Autosdm	[out] • Optional 1 byte parameter indicating OMA Automatic UI Alert Response – 0x00 - Disabled – 0x01 - Enabled Accept – 0x02 - Enabled Reject • Bit to check in ParamPresenceMask - **19**
FwAutoCheck	[out] • Optional 1 byte parameter indicating OMA Automatic Check for Firmware Update on Power-Up Response – 0x00 - Disabled – 0x01 - Enabled • Bit to check in ParamPresenceMask - **20**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1460.2 Field Documentation

8.1460.2.1 uint8_t unpack_swioma_SLQSOMADMGetSettings_t::Autosdm

8.1460.2.2 uint8_t unpack_swioma_SLQSOMADMGetSettings_t::FOTAdownload

8.1460.2.3 uint8_t unpack_swioma_SLQSOMADMGetSettings_t::FOTAUpdate

8.1460.2.4 uint8_t unpack_swioma_SLQSOMADMGetSettings_t::FwAutoCheck

8.1460.2.5 uint32_t unpack_swioma_SLQSOMADMGetSettings_t::OMADMEnabled

8.1460.2.6 swi_uint256_t unpack_swioma_SLQSOMADMGetSettings_t::ParamPresenceMask

8.1461 unpack_swioma_SLQSOMADMStartSession_t Struct Reference

Data Fields

- uint32_t FwAvailability
- swi_uint256_t ParamPresenceMask

8.1461.1 Detailed Description

Structure that contains the responses for OMA start session command

Parameters

FwAvailability	[out] • OMA-DM CHECK FW Available • Values – 0x00000001 - FW Available. For CIDC and CIPRL, this value will be returned by the modem. CIDC and CIPRL are asynchronous OMADM sessions. – 0x00000002 - FW Not Available – 0x00000003 - FW Check Timed Out • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1461.2 Field Documentation

8.1461.2.1 uint32_t unpack_swioma_SLQSOMADMStartSession_t::FwAvailability

8.1461.2.2 swi_uint256_t unpack_swioma_SLQSOMADMStartSession_t::ParamPresenceMask

8.1462 unpack_uim_ChangePin_t Struct Reference

Data Fields

- uim_remainingRetries * pRemainingRetries
- uim_encryptedPIN1 * pEncryptedPIN1
- uint32_t * pIndicationToken
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1462.1 Detailed Description

This structure contains information of the response parameters associated with a set of PIN related API's.

Parameters

pRemaining-Retries(optional)	• See uim_remainingRetries for more information. • Bit to check in ParamPresenceMask - **16**
pEncryptedPI-N1(optional)	• See uim_encryptedPIN1 for more information. • Bit to check in ParamPresenceMask - **17**
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result is provided in a subsequent indication. • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1462.2 Field Documentation

8.1462.2.1 swi_uint256_t unpack_uim_ChangePin_t::ParamPresenceMask

8.1462.2.2 uim_encryptedPIN1∗ unpack_uim_ChangePin_t::pEncryptedPIN1

8.1462.2.3 uint32_t∗ unpack_uim_ChangePin_t::pIndicationToken

8.1462.2.4 uim_remainingRetries∗ unpack_uim_ChangePin_t::pRemainingRetries

8.1462.2.5 uint16_t unpack_uim_ChangePin_t::Tlvresult

8.1463 unpack_uim_GetCardStatus_t Struct Reference

Data Fields

- uim_cardStatus ∗ pCardStatus
- uim_hotSwapStatus ∗ pHotSwapStatus
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1463.1 Detailed Description

This structure contains information of the response parameters associated with a Get Card Status API.

Parameters

pCard-Status(optional)	• See uim_cardStatus for more information. • Bit to check in ParamPresenceMask - **16**

pHotSwap-Status(optional)	• See uim_hotSwapStatus for more information. • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1463.2 Field Documentation

8.1463.2.1 swi_uint256_t unpack_uim_GetCardStatus_t::ParamPresenceMask

8.1463.2.2 uim_cardStatus* unpack_uim_GetCardStatus_t::pCardStatus

8.1463.2.3 uim_hotSwapStatus* unpack_uim_GetCardStatus_t::pHotSwapStatus

8.1463.2.4 uint16_t unpack_uim_GetCardStatus_t::Tlvresult

8.1464 unpack_uim_GetCardStatusV2_t Struct Reference

Data Fields

- uim_cardStatus * pCardStatus
- uim_hotSwapStatus * pHotSwapStatus
- uim_validCardStatus * pValidCardStatus
- uim_simBusyStatus * pSimBusyStatus
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1464.1 Detailed Description

This structure contains information of the response parameters associated with a Get Card Status API.

Parameters

pCard-Status(optional)	• See uim_cardStatus for more information. • Bit to check in ParamPresenceMask - **16**
pHotSwap-Status(optional)	• See uim_hotSwapStatus for more information. • Bit to check in ParamPresenceMask - **17**
pValidCard-Status(optional)	• See uim_validCardStatus for more information. • Bit to check in ParamPresenceMask - **18**
pSimBusy-Status(optional)	• See uim_simBusyStatus for more information. • Bit to check in ParamPresenceMask - **21**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1464.2 Field Documentation

8.1464.2.1 swi_uint256_t unpack_uim_GetCardStatusV2_t::ParamPresenceMask

8.1464.2.2 uim_cardStatus* unpack_uim_GetCardStatusV2_t::pCardStatus

8.1464.2.3 uim_hotSwapStatus* unpack_uim_GetCardStatusV2_t::pHotSwapStatus

8.1464.2.4 uim_simBusyStatus* unpack_uim_GetCardStatusV2_t::pSimBusyStatus

8.1464.2.5 uim_validCardStatus* unpack_uim_GetCardStatusV2_t::pValidCardStatus

8.1464.2.6 uint16_t unpack_uim_GetCardStatusV2_t::Tlvresult

8.1465 unpack_uim_ReadTransparent_t Struct Reference

Data Fields

- uim_cardResult * pCardResult
- uim_readResult * pReadResult
- uint32_t * pIndicationToken
- uint8_t * pEncryptedData
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1465.1 Detailed Description

This structure contains information of the response parameters associated with a Read Transparent API.

Parameters

pCardResult	• See uim_cardResult for more information. • Bit to check in ParamPresenceMask - **16**
pReadResult	• See uim_readResult for more information. • Bit to check in ParamPresenceMask - **17**
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication. • Bit to check in ParamPresenceMask - **18**
pEncrypted-Data(optional)	• Encrypted Data. • Indicates whether the data from the card passed in read_result is encrypted. • Bit to check in ParamPresenceMask - **19**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1465.2 Field Documentation

8.1465.2.1 swi_uint256_t unpack_uim_ReadTransparent_t::ParamPresenceMask

8.1465.2.2 uim_cardResult∗ unpack_uim_ReadTransparent_t::pCardResult

8.1465.2.3 uint8_t∗ unpack_uim_ReadTransparent_t::pEncryptedData

8.1465.2.4 uint32_t∗ unpack_uim_ReadTransparent_t::pIndicationToken

8.1465.2.5 uim_readResult∗ unpack_uim_ReadTransparent_t::pReadResult

8.1465.2.6 uint16_t unpack_uim_ReadTransparent_t::Tlvresult

8.1466 unpack_uim_SetPinProtection_t Struct Reference

Data Fields

- uim_remainingRetries ∗ pRemainingRetries
- uim_encryptedPIN1 ∗ pEncryptedPIN1
- uint32_t ∗ pIndicationToken
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1466.1 Detailed Description

This structure contains information of the response parameters associated with a set of PIN related API's.

Parameters

pRemaining-Retries(optional)	• See uim_remainingRetries for more information. • Bit to check in ParamPresenceMask - **16**
pEncryptedPI-N1(optional)	• See uim_encryptedPIN1 for more information. • Bit to check in ParamPresenceMask - **17**
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result is provided in a subsequent indication. • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1466.2 Field Documentation

8.1466.2.1 swi_uint256_t unpack_uim_SetPinProtection_t::ParamPresenceMask

8.1466.2.2 uim_encryptedPIN1* unpack_uim_SetPinProtection_t::pEncryptedPIN1

8.1466.2.3 uint32_t* unpack_uim_SetPinProtection_t::pIndicationToken

8.1466.2.4 uim_remainingRetries* unpack_uim_SetPinProtection_t::pRemainingRetries

8.1466.2.5 uint16_t unpack_uim_SetPinProtection_t::Tlvresult

8.1467 unpack_uim_SetUimSlotStatusChangeCallback_ind_t Struct Reference

Data Fields

- slots_t slotsstatusChange
- uint8_t bNumberOfPhySlots
- swi_uint256_t ParamPresenceMask

8.1467.1 Detailed Description

Structure consist of card status params

Parameters

slotsstatus-Change	• See slot_t for more information • Bit to check in ParamPresenceMask - **16**
bNumberOfPhy-Slots	• Number of Physical Slot(s) • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1467.2 Field Documentation

8.1467.2.1 uint8_t unpack_uim_SetUimSlotStatusChangeCallback_ind_t::bNumberOfPhySlots

8.1467.2.2 swi_uint256_t unpack_uim_SetUimSlotStatusChangeCallback_ind_t::ParamPresenceMask

8.1467.2.3 slots_t unpack_uim_SetUimSlotStatusChangeCallback_ind_t::slotsstatusChange

8.1468 unpack_uim_SLQSUIMAuthenticate_t Struct Reference

Data Fields

- uim_cardResult * pCardResult
- uim_authenticateResult * pAuthenticateResult
- uint32_t * pIndicationToken

- swi_uint256_t ParamPresenceMask

8.1468.1 Detailed Description

This structure contains information of the response parameters associated with a SLQSUIMAuthenticate.

Parameters

pCardResult(optional)	• See uim_cardResult for more information. • Bit to check in ParamPresenceMask - **16**
pAuthenticateResult(optional)	• See uim_authenticateResult for more information. • Bit to check in ParamPresenceMask - **17**
pIndicationToken(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication. • Bit to check in ParamPresenceMask - **18**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1468.2 Field Documentation

8.1468.2.1 swi_uint256_t unpack_uim_SLQSUIMAuthenticate_t::ParamPresenceMask

8.1468.2.2 uim_authenticateResult* unpack_uim_SLQSUIMAuthenticate_t::pAuthenticateResult

8.1468.2.3 uim_cardResult* unpack_uim_SLQSUIMAuthenticate_t::pCardResult

8.1468.2.4 uint32_t* unpack_uim_SLQSUIMAuthenticate_t::pIndicationToken

8.1469 unpack_uim_SLQSUIMDepersonalization_t Struct Reference

Data Fields

- uim_remainingRetries * pRemainingRetries
- swi_uint256_t ParamPresenceMask

8.1469.1 Detailed Description

This structure contains information of the response parameters associated with a Depersonalization.

Parameters

pRemainingRetries(optional)	• See uim_remainingRetries for more information. • Bit to check in ParamPresenceMask - **16**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1469.2 Field Documentation

8.1469.2.1 swi_uint256_t unpack_uim_SLQSUIMDepersonalization_t::ParamPresenceMask

8.1469.2.2 uim_remainingRetries* unpack_uim_SLQSUIMDepersonalization_t::pRemainingRetries

8.1470 unpack_uim_SLQSUIMEventRegister_t Struct Reference

Data Fields

- uint32_t eventMask
- swi_uint256_t ParamPresenceMask

8.1470.1 Detailed Description

This structure contains unpack event register parameter.

Parameters

eventMask	- bit 0 - card status • bit 1 - SAP connection • bit 4 - physical slot status

- Bit to check in ParamPresenceMask - **16**

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1470.2 Field Documentation

8.1470.2.1 uint32_t unpack_uim_SLQSUIMEventRegister_t::eventMask

8.1470.2.2 swi_uint256_t unpack_uim_SLQSUIMEventRegister_t::ParamPresenceMask

8.1471 unpack_uim_SLQSUIMGetConfiguration_t Struct Reference

Data Fields

- uint8_t * pAutoSelection
- uim_personalizationStatus * pPersonalizationStatus
- uint8_t * pHaltSubscription
- swi_uint256_t ParamPresenceMask

8.1471.1 Detailed Description

This structure contains information of the response parameters associated with Get Configuration.

Parameters

pAuto-Selection(optional)	• Indicates whether the modem is configured to automatically select the provisioning sessions at powerup. • Valid values – 0 - Automatic provisioning is off – 1 - Automatic provisioning is on • Bit to check in ParamPresenceMask - **16**
p-Personalization-Status(optional)	• See uim_personalizationStatus for more information. • Bit to check in ParamPresenceMask - **17**
pHalt-Subscription(optional)	• Indicates if the modem is configured to publish the subscription after successful initialization. • Valid values – 0 - Modem proceeds with publishing the subscription – 1 - Modem does not publish the subscription • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1471.2 Field Documentation

8.1471.2.1 swi_uint256_t unpack_uim_SLQSUIMGetConfiguration_t::ParamPresenceMask

8.1471.2.2 uint8_t* unpack_uim_SLQSUIMGetConfiguration_t::pAutoSelection

8.1471.2.3 uint8_t* unpack_uim_SLQSUIMGetConfiguration_t::pHaltSubscription

8.1471.2.4 uim_personalizationStatus* unpack_uim_SLQSUIMGetConfiguration_t::pPersonalizationStatus

8.1472 unpack_uim_SLQSUIMGetFileAttributes_t Struct Reference

Data Fields

- uim_cardResult * pCardResult
- uim_fileAttributes * pFileAttributes
- uint32_t * pIndicationToken
- swi_uint256_t ParamPresenceMask

8.1472.1 Detailed Description

This structure contains information of the response parameters associated with a Get File Attributes

Parameters

pCard-Result(optional)	• See uim_cardResult for more information. • Bit to check in ParamPresenceMask - **16**
pFile-Attributes(optional)	• See uim_fileAttributes for more information. • Bit to check in ParamPresenceMask - **17**
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result must be provided in a subsequent indication. • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1472.2 Field Documentation

8.1472.2.1 swi_uint256_t unpack_uim_SLQSUIMGetFileAttributes_t::ParamPresenceMask

8.1472.2.2 uim_cardResult* unpack_uim_SLQSUIMGetFileAttributes_t::pCardResult

8.1472.2.3 uim_fileAttributes* unpack_uim_SLQSUIMGetFileAttributes_t::pFileAttributes

8.1472.2.4 uint32_t* unpack_uim_SLQSUIMGetFileAttributes_t::pIndicationToken

8.1473 unpack_uim_SLQSUIMGetSlotsStatus_t Struct Reference

Data Fields

- uint8_t * pNumberOfPhySlot
- slots_t * pUimSlotsStatus
- swi_uint256_t ParamPresenceMask

8.1473.1 Detailed Description

This structure contains information of the response parameters associated with a Get Slots Status API.

Parameters

pNumberOfPhy-Slot	• Number of sets of the Slot Status. • Bit to check in ParamPresenceMask - **16**
pUimSlotsStatus	• Slots Status See slots_t for more information.. • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1473.2 Field Documentation

8.1473.2.1 swi_uint256_t unpack_uim_SLQSUIMGetSlotsStatus_t::ParamPresenceMask

8.1473.2.2 uint8_t* unpack_uim_SLQSUIMGetSlotsStatus_t::pNumberOfPhySlot

8.1473.2.3 slots_t* unpack_uim_SLQSUIMGetSlotsStatus_t::pUimSlotsStatus

8.1474 unpack_uim_SLQSUIMRefreshCallback_Ind_t Struct Reference

Data Fields

- uint8_t TlvPresent
- uim_refreshevent refreshEvent
- swi_uint256_t ParamPresenceMask

8.1474.1 Detailed Description

This structure hold parameters about UIM refresh event indication.

Parameters

TlvPresent	• value is 1 if refresh event TLV is present in indication, otherwise 0
refreshEvent[OPTIONAL]	• see uim_refreshevent • Bit to check in ParamPresenceMask - **16**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1474.2 Field Documentation

8.1474.2.1 swi_uint256_t unpack_uim_SLQSUIMRefreshCallback_Ind_t::ParamPresenceMask

8.1474.2.2 uim_refreshevent unpack_uim_SLQSUIMRefreshCallback_Ind_t::refreshEvent

8.1474.2.3 uint8_t unpack_uim_SLQSUIMRefreshCallback_Ind_t::TlvPresent

8.1475 unpack_uim_SLQSUIMRefreshGetLastEvent_t Struct Reference

Data Fields

- uim_refreshevent * pRefreshEvent
- swi_uint256_t ParamPresenceMask

8.1475.1 Detailed Description

This structure contains information of the response parameters associated with a Refresh Get Last Event.

Parameters

refreshEvent(-Optional)	• See uim_refreshevent for more information. • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1475.2 Field Documentation

8.1475.2.1 swi_uint256_t unpack_uim_SLQSUIMRefreshGetLastEvent_t::ParamPresenceMask

8.1475.2.2 uim_refreshevent* unpack_uim_SLQSUIMRefreshGetLastEvent_t::pRefreshEvent

8.1476 unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t Struct Reference

Data Fields

- uim_cardStatus * pCardStatus
- swi_uint256_t ParamPresenceMask

8.1476.1 Detailed Description

This structure contains information about Status change callback.

Parameters

pCardStatus	Card Status • See uim_cardStatus for more information. • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1476.2 Field Documentation

8.1476.2.1 swi_uint256_t unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t::ParamPresenceMask

8.1476.2.2 uim_cardStatus* unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t::pCardStatus

8.1477 unpack_uim_UnblockPin_t Struct Reference

Data Fields

- uim_remainingRetries * pRemainingRetries
- uim_encryptedPIN1 * pEncryptedPIN1
- uint32_t * pIndicationToken
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1477.1 Detailed Description

This structure contains information of the response parameters associated with a set of PIN related API's.

Parameters

pRemaining-Retries(optional)	• See uim_remainingRetries for more information. • Bit to check in ParamPresenceMask - **16**
pEncryptedPI-N1(optional)	• See uim_encryptedPIN1 for more information. • Bit to check in ParamPresenceMask - **17**
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result is provided in a subsequent indication. • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1477.2 Field Documentation

8.1477.2.1 swi_uint256_t unpack_uim_UnblockPin_t::ParamPresenceMask

8.1477.2.2 uim_encryptedPIN1∗ unpack_uim_UnblockPin_t::pEncryptedPIN1

8.1477.2.3 uint32_t∗ unpack_uim_UnblockPin_t::pIndicationToken

8.1477.2.4 uim_remainingRetries∗ unpack_uim_UnblockPin_t::pRemainingRetries

8.1477.2.5 uint16_t unpack_uim_UnblockPin_t::Tlvresult

8.1478 unpack_uim_UnblockPinV2_t Struct Reference

Data Fields

- uim_remainingRetries ∗ pRemainingRetries
- uim_encryptedPIN1 ∗ pEncryptedPIN1
- uint32_t ∗ pIndicationToken
- uim_cardResult ∗ pCardResult
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1478.1 Detailed Description

This structure contains information of the response parameters associated with a set of PIN related API's.

Parameters

pRemaining-Retries(optional)	• See uim_remainingRetries for more information. • Bit to check in ParamPresenceMask - **16**
pEncryptedPI-N1(optional)	• See uim_encryptedPIN1 for more information. • Bit to check in ParamPresenceMask - **17**
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result is provided in a subsequent indication. • Bit to check in ParamPresenceMask - **18**
pCard-Result(optional)	• See uim_cardResult for more information. • Bit to check in ParamPresenceMask - **19**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1478.2 Field Documentation

8.1478.2.1 swi_uint256_t unpack_uim_UnblockPinV2_t::ParamPresenceMask

8.1478.2.2 uim_cardResult∗ unpack_uim_UnblockPinV2_t::pCardResult

8.1478.2.3 uim_encryptedPIN1∗ unpack_uim_UnblockPinV2_t::pEncryptedPIN1

8.1478.2.4 uint32_t∗ unpack_uim_UnblockPinV2_t::pIndicationToken

8.1478.2.5 uim_remainingRetries∗ unpack_uim_UnblockPinV2_t::pRemainingRetries

8.1478.2.6 uint16_t unpack_uim_UnblockPinV2_t::Tlvresult

8.1479 unpack_uim_VerifyPin_t Struct Reference

Data Fields

- uim_remainingRetries ∗ pRemainingRetries
- uim_encryptedPIN1 ∗ pEncryptedPIN1
- uint32_t ∗ pIndicationToken
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1479.1 Detailed Description

This structure contains information of the response parameters associated with a set of PIN related API's.

Parameters

pRemaining-Retries(optional)	• See uim_remainingRetries for more information. • Bit to check in ParamPresenceMask - **16**
pEncryptedPI-N1(optional)	• See uim_encryptedPIN1 for more information. • Bit to check in ParamPresenceMask - **17**
pIndication-Token(optional)	• Response in Indication. • When this TLV is present, it indicates that the result is provided in a subsequent indication. • Bit to check in ParamPresenceMask - **18**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1479.2 Field Documentation

8.1479.2.1 swi_uint256_t unpack_uim_VerifyPin_t::ParamPresenceMask

8.1479.2.2 uim_encryptedPIN1* unpack_uim_VerifyPin_t::pEncryptedPIN1

8.1479.2.3 uint32_t* unpack_uim_VerifyPin_t::pIndicationToken

8.1479.2.4 uim_remainingRetries* unpack_uim_VerifyPin_t::pRemainingRetries

8.1479.2.5 uint16_t unpack_uim_VerifyPin_t::Tlvresult

8.1480 unpack_voice_allCallStatusCallback_ind_t Struct Reference

Data Fields

- voice_arrCallInfo arrCallInfomation
- voice_arrRemotePartyNum * pArrRemotePartyNum
- voice_arrRemotePartyName * pArrRemotePartyName
- voice_arrAlertingType * pArrAlertingType
- voice_arrSvcOption * pArrSvcOption
- voice_arrCallEndReason * pArrCallEndReason
- voice_arrAlphaID * pArrAlphaID
- voice_arrConnectPartyNum * pArrConnectPartyNum
- voice_arrDiagInfo * pArrDiagInfo
- voice_arrCalledPartyNum * pArrCalledPartyNum
- voice_arrRedirPartyNum * pArrRedirPartyNum
- voice_arrAlertingPattern * pArrAlertingPattern
- swi_uint256_t ParamPresenceMask

8.1480.1 Detailed Description

This structure contains information about the indication parameters for all the calls originating or terminating from a particular device.

Parameters

arrCallInfo(mandatory)	• See voice_arrCallInfo for more information. • Bit to check in ParamPresenceMask - **1**
pArrRemotePartyNum(optional)	• See voice_arrRemotePartyNum for more information. • Bit to check in ParamPresenceMask - **16**
pArrRemotePartyName(optional)	• See voice_arrRemotePartyName for more information. • Bit to check in ParamPresenceMask - **17**
pArrAlertingType(optional)	• See voice_arrAlertingType for more information. • Bit to check in ParamPresenceMask - **18**
pArrSvcOption(optional)	• See voice_arrSvcOption for more information. • Bit to check in ParamPresenceMask - **19**
pArrCallEndReason(optional)	• See voice_arrCallEndReason for more information. • Bit to check in ParamPresenceMask - **20**
pArrAlphaID(optional)	• See voice_arrAlphaID for more information. • Bit to check in ParamPresenceMask - **21**
pArrConnectPartyNum(optional)	• See voice_arrConnectPartyNum for more information. • Bit to check in ParamPresenceMask - **22**
pArrDiagInfo(optional)	• See voice_arrDiagInfo for more information. • Bit to check in ParamPresenceMask - **23**
pArrCalledPartyNum(optional)	• See voice_arrCalledPartyNum for more information. • Bit to check in ParamPresenceMask - **24**
pArrRedirPartyNum(optional)	• See voice_arrRedirPartyNum for more information. • Bit to check in ParamPresenceMask - **25**
pArrAlertingPattern(optional)	• See voice_arrAlertingPattern for more information. • Bit to check in ParamPresenceMask - **26**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1480.2 Field Documentation

8.1480.2.1 voice_arrCallInfo unpack_voice_allCallStatusCallback_ind_t::arrCallInfomation

8.1480.2.2 swi_uint256_t unpack_voice_allCallStatusCallback_ind_t::ParamPresenceMask

8.1480.2.3 voice_arrAlertingPattern* unpack_voice_allCallStatusCallback_ind_t::pArrAlertingPattern

8.1480.2.4 voice_arrAlertingType* unpack_voice_allCallStatusCallback_ind_t::pArrAlertingType

8.1480.2.5 voice_arrAlphaID* unpack_voice_allCallStatusCallback_ind_t::pArrAlphaID

8.1480.2.6 voice_arrCalledPartyNum* unpack_voice_allCallStatusCallback_ind_t::pArrCalledPartyNum

8.1480.2.7 voice_arrCallEndReason* unpack_voice_allCallStatusCallback_ind_t::pArrCallEndReason

8.1480.2.8 voice_arrConnectPartyNum* unpack_voice_allCallStatusCallback_ind_t::pArrConnectPartyNum

8.1480.2.9 voice_arrDiagInfo* unpack_voice_allCallStatusCallback_ind_t::pArrDiagInfo

8.1480.2.10 voice_arrRedirPartyNum* unpack_voice_allCallStatusCallback_ind_t::pArrRedirPartyNum

8.1480.2.11 voice_arrRemotePartyName* unpack_voice_allCallStatusCallback_ind_t::pArrRemotePartyName

8.1480.2.12 voice_arrRemotePartyNum* unpack_voice_allCallStatusCallback_ind_t::pArrRemotePartyNum

8.1480.2.13 voice_arrSvcOption* unpack_voice_allCallStatusCallback_ind_t::pArrSvcOption

8.1481 unpack_voice_DTMFEventCallback_ind_t Struct Reference

Data Fields

- voice_DTMFInfo DTMFInformation
- uint8_t * pOnLength
- uint8_t * pOffLength
- swi_uint256_t ParamPresenceMask

8.1481.1 Detailed Description

This structure contains the parameters passed for DTMF event indication by the device.

Parameters

DTMF-Information(mandatory)	See voice_DTMFInfo for more information. • Bit to check in ParamPresenceMask - **1**
pOn-Length(optional)	• DTMF Pulse Width – 0x00 - DTMF_ONLENGTH_95MS - 95 ms – 0x01 - DTMF_ONLENGTH_150MS - 150 ms – 0x02 - DTMF_ONLENGTH_200MS - 200 ms – 0x03 - DTMF_ONLENGTH_250MS - 250 ms – 0x04 - DTMF_ONLENGTH_300MS - 300 ms – 0x05 - DTMF_ONLENGTH_350MS - 350 ms – 0x06 - DTMF_ONLENGTH_SMS - SMS Tx special pulse width • Bit to check in ParamPresenceMask - **16**
pOff-Length(optional)	• DTMF Interdigit Interval – 0x00 - DTMF_OFFLENGTH_60MS - 60 ms – 0x01 - DTMF_OFFLENGTH_100MS - 100 ms – 0x02 - DTMF_OFFLENGTH_150MS - 150 ms – 0x03 - DTMF_OFFLENGTH_200MS - 200 ms • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

None

8.1481.2 Field Documentation

8.1481.2.1 voice_DTMFInfo unpack_voice_DTMFEventCallback_ind_t::DTMFInformation

8.1481.2.2 swi_uint256_t unpack_voice_DTMFEventCallback_ind_t::ParamPresenceMask

8.1481.2.3 uint8_t* unpack_voice_DTMFEventCallback_ind_t::pOffLength

8.1481.2.4 uint8_t* unpack_voice_DTMFEventCallback_ind_t::pOnLength

8.1482 unpack_voice_OTASPStatusCallback_ind_t Struct Reference

Data Fields

- uint8_t callID
- uint8_t OTASPStatus
- swi_uint256_t ParamPresenceMask

8.1482.1 Detailed Description

This structure consist of OTASP or OTAPA event params

Parameters

callID	• Call identifier for the call. • Bit to check in ParamPresenceMask - **1**
OTASPStatus	• OTASP status for the OTASP call. Values: – 0x00 - OTASP_STATUS_SPL_UNLOCKED.SPL unlocked; only for user-initiated OTASP – 0x01 - OTASP_STATUS_SPRC_RETRIES_EXCEEDED. SPC retries exceeded; only for user-initiated OTASP – 0x02 - OTASP_STATUS_AKEY_EXCHANGED.A-key exchanged; only for user-initiated OTASP – 0x03 - OTASP_STATUS_SSD_UPDATED. SSD updated; for both user-initiated OTASP and network-initiated OTASP (OTAPA) – 0x04 - OTASP_STATUS_NAM_DOWNLOADED - NAM downloaded; only for user-initiated OTASP – 0x05 - OTASP_STATUS_MDN_DOWNLOADED - MDN downloaded; only for user-initiated OTASP – 0x06 - OTASP_STATUS_IMSI_DOWNLOADED - IMSI downloaded; only for user-initiated OTASP – 0x07 - OTASP_STATUS_PRL_DOWNLOADED - PRL downloaded; only for user-initiated OTASP – 0x08 - OTASP_STATUS_COMMITTED - Commit successful; only for user-initiated OTASP – 0x09 - OTASP_STATUS_OTAPA_STARTED - OTAPA started; only for network-initiated OTASP(OTAPA) – 0x0A - OTASP_STATUS_OTAPA_STOPPED - OTAPA stopped; only for network-initiated OTASP(OTAPA) – 0x0B - OTASP_STATUS_OTAPA_ABORTED - OTAPA aborted; only for network-initiated OTASP(OTAPA) – 0x0C - OTASP_STATUS_OTAPA_COMMITTED - OTAPA committed; only for network-initiated OTASP(OTAPA) • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1482.2 Field Documentation

8.1482.2.1 uint8_t unpack_voice_OTASPStatusCallback_ind_t::callID

8.1482.2.2 uint8_t unpack_voice_OTASPStatusCallback_ind_t::OTASPStatus

8.1482.2.3 swi_uint256_t unpack_voice_OTASPStatusCallback_ind_t::ParamPresenceMask

8.1483 unpack_voice_SLQSOriginateUSSD_t Struct Reference

Data Fields

- uint16_t * pfailureCause
- voice_alphaIDInfo * pAlphaIDInfo
- struct voice_USSInfo * pUSSDInfo
- uint8_t * pCcResultType

- uint8_t * pCallId
- voice_ccSUPSType * pCCSuppsType
- swi_uint256_t ParamPresenceMask

8.1483.1 Detailed Description

This structure contains the parameters of USS response.

Parameters

pfailureCause

- Failure Cause.
- 0 - QMI_FAILURE_CAUSE_OFFLINE - Phone is offline
- 20 - QMI_FAILURE_CAUSE_CDMA_LOCK - Phone is CDMA locked until a power cycle; CDMA only
- 21 - QMI_FAILURE_CAUSE_NO_SRV - Phone has no service
- 22 - QMI_FAILURE_CAUSE_FADE - Call has ended abnormally
- 23 - QMI_FAILURE_CAUSE_INTERCEPT - Received intercept from the base station; originating only; CDMA only
- 24 - QMI_FAILURE_CAUSE_REORDER - Received reorder from the base station; originating only; CDMA only
- 25 - QMI_FAILURE_CAUSE_REL_NORMAL - Received release from the base station; no reason was given
- 26 - QMI_FAILURE_CAUSE_REL_SO_REJ - Received release from the base station; SO reject; CDMA only
- 27 - QMI_FAILURE_CAUSE_INCOM_CALL - Received incoming call from the base station
- 28 - QMI_FAILURE_CAUSE_ALERT_STOP - Received alert stop from the base station; incoming only; CDMA only
- 29 - QMI_FAILURE_CAUSE_CLIENT_END - Client ended the call
- 30 - QMI_FAILURE_CAUSE_ACTIVATION - Received end activation; OTASP call only; CDMA only
- 31 - QMI_FAILURE_CAUSE_MC_ABORT - MC aborted the origination/conversation; CDMA only
- 32 - QMI_FAILURE_CAUSE_MAX_ACCESS_PROBE - Maximum access probes were transmitted; CDMA only
- 33 - QMI_FAILURE_CAUSE_PSIST_N - Persistence test failure; FEATURE_JCDMA only; CDMA only
- 34 - QMI_FAILURE_CAUSE_UIM_NOT_PRESENT - R-UIM is not present
- 35 - QMI_FAILURE_CAUSE_ACC_IN_PROG - Access attempt is already in progress
- 36 - QMI_FAILURE_CAUSE_ACC_FAIL - Access failure for a reason other than the above
- 37 - QMI_FAILURE_CAUSE_RETRY_ORDER - Received retry order; originating only; IS 2000; CDMA only
- 38 - QMI_FAILURE_CAUSE_CCS_NOT_SUPPORTED_BYBS - Concurrent service is not supported by the base station
- 39 - QMI_FAILURE_CAUSE_NO_RESPONSE_FROM_BS - No response was received from the base station
- 40 - QMI_FAILURE_CAUSE_REJECTED_BY_BS - Call was rejected by the base station; CDMA only
- 41 - QMI_FAILURE_CAUSE_INCOMPATIBLE - Concurrent services requested were not compatible; CDMA only
- 42 - QMI_FAILURE_CAUSE_ACCESS_BLOCK - Access is blocked by the base station; CDMA only
- 43 - QMI_FAILURE_CAUSE_ALREADY_IN_TC - Corresponds to CM_CALL_ORIGERR_ALREADY_IN_TC
- 44 - QMI_FAILURE_CAUSE_EMERGENCY_FLASHED - Call is ended because an emergency call was flashed over this call; CDMA only
- 45 - QMI_FAILURE_CAUSE_USER_CALL_ORIGDURING_GPS - Used if CM is ending a GPS call in preference of a user call
- 46 - QMI_FAILURE_CAUSE_USER_CALL_ORIGDURING_SMS - Used if CM is ending an SMS call in preference of a user call
- 47 - QMI_FAILURE_CAUSE_USER_CALL_ORIGDURING_DATA - Used if CM is ending a data call in preference of an emergency call
- 48 - QMI_FAILURE_CAUSE_REDIR_OR_HANDOFF - Call was rejected because of a redirection or handoff
- 49 - QMI_FAILURE_CAUSE_ACCESS_BLOCK_ALL - Access is blocked by the base station for all mobiles; KDDI-specific; CDMA only
- 50 - QMI_FAILURE_CAUSE_OTASP_SPC_ERR - To support OTASP SPC Error indication
- 51 - QMI_FAILURE_CAUSE_IS707B_MAX_ACC - Maximum access probes for an IS-707B

AlphaIdentifier	• see voice_alphaIDInfo definition • Bit to check in ParamPresenceMask - **17**
pUSSDInfo	• USS Data from Network (See structure voice_USSInfo) • Bit to check in ParamPresenceMask - **18**
pCcResultType	• CC result code • Bit to check in ParamPresenceMask - **19**
pCallId	• Bit to check in ParamPresenceMask - **20** • NULL pointer - Invalid data.
pCCSuppsType	• See structure 'voice_ccSUPSType' definition • Bit to check in ParamPresenceMask - **21**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1483.2 Field Documentation

8.1483.2.1 voice_alphaIDInfo* unpack_voice_SLQSOriginateUSSD_t::pAlphaIDInfo

8.1483.2.2 swi_uint256_t unpack_voice_SLQSOriginateUSSD_t::ParamPresenceMask

8.1483.2.3 uint8_t* unpack_voice_SLQSOriginateUSSD_t::pCallId

8.1483.2.4 uint8_t* unpack_voice_SLQSOriginateUSSD_t::pCcResultType

8.1483.2.5 voice_ccSUPSType* unpack_voice_SLQSOriginateUSSD_t::pCCSuppsType

8.1483.2.6 uint16_t* unpack_voice_SLQSOriginateUSSD_t::pfailureCause

8.1483.2.7 struct voice_USSInfo* unpack_voice_SLQSOriginateUSSD_t::pUSSDInfo

8.1484 unpack_voice_SLQSVoiceAnswerCall_t Struct Reference

Data Fields

- uint8_t * pCallId
- swi_uint256_t ParamPresenceMask

8.1484.1 Detailed Description

Contains the parameters passed for pack voice Answer Call.

Parameters

pCallId	• Unique call identifier for the call that must be answered. • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1484.2 Field Documentation

8.1484.2.1 swi_uint256_t unpack_voice_SLQSVoiceAnswerCall_t::ParamPresenceMask

8.1484.2.2 uint8_t* unpack_voice_SLQSVoiceAnswerCall_t::pCallId

8.1485 unpack_voice_SLQSVoiceBurstDTMF_t Struct Reference

Data Fields

- uint8_t * pCallID
- swi_uint256_t ParamPresenceMask

8.1485.1 Detailed Description

This structure contains Voice Burst DTMF Information for unpack.

Parameters

pCallID	• Call ID associated with call on which the DTMF information has to be sent. A burst DTMF request is sent to the current active/alerting call when pCallId is set to 0xFF. • This is IN/OUT parameter, value passed by user will be packed in request and value received from the device would be returned to the user. • If the call ID value received is 0, no value has been returned by the device • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1485.2 Field Documentation

8.1485.2.1 swi_uint256_t unpack_voice_SLQSVoiceBurstDTMF_t::ParamPresenceMask

8.1485.2.2 uint8_t* unpack_voice_SLQSVoiceBurstDTMF_t::pCallID

8.1486 unpack_voice_SLQSVoiceDialCall_t Struct Reference

Data Fields

- uint8_t * pCallID
- voice_alphaIDInfo * pAlphaIDInfo

- uint8_t * pCCResultType
- voice_ccSUPSType * pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1486.1 Detailed Description

This structure contains Voice Call Response Parameters

Parameters

pCallID(optional)	• Unique call identifier for the dialed call • Bit to check in ParamPresenceMask - **16**
pAlphaID-Info(optional)	• Pointer to structure of alphaIDInfo – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **17**
pCCResult-Type(optional)	• Call Control Result Type. – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service • Bit to check in ParamPresenceMask - **18**
pCCSUPS-Type(optional)	• Pointer to structure of ccSUPSType • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **19**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1486.2 Field Documentation

8.1486.2.1 voice_alphaIDInfo* unpack_voice_SLQSVoiceDialCall_t::pAlphaIDInfo

8.1486.2.2 swi_uint256_t unpack_voice_SLQSVoiceDialCall_t::ParamPresenceMask

8.1486.2.3 uint8_t* unpack_voice_SLQSVoiceDialCall_t::pCallID

8.1486.2.4 uint8_t* unpack_voice_SLQSVoiceDialCall_t::pCCResultType

8.1486.2.5 voice_ccSUPSType* unpack_voice_SLQSVoiceDialCall_t::pCCSUPSType

8.1487 unpack_voice_SLQSVoiceEndCall_t Struct Reference

Data Fields

- uint8_t * pCallId

- swi_uint256_t ParamPresenceMask

8.1487.1 Detailed Description

This structure contains unpack voice end call parameter.

Parameters

pCallId	• Unique call identifier for the call that must be ended • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1487.2 Field Documentation

8.1487.2.1 swi_uint256_t unpack_voice_SLQSVoiceEndCall_t::ParamPresenceMask

8.1487.2.2 uint8_t* unpack_voice_SLQSVoiceEndCall_t::pCallId

8.1488 unpack_voice_SLQSVoiceGetAllCallInfo_t Struct Reference

Data Fields

- voice_arrCallInfo * pArrCallInfo
- voice_arrRemotePartyNum * pArrRemotePartyNum
- voice_arrRemotePartyName * pArrRemotePartyName
- voice_arrAlertingType * pArrAlertingType
- voice_arrUUSInfo * pArrUUSInfo
- voice_arrSvcOption * pArrSvcOption
- uint8_t * pOTASPStatus
- uint8_t * pVoicePrivacy
- voice_arrCallEndReason * pArrCallEndReason
- voice_arrAlphaID * pArrAlphaID
- voice_arrConnectPartyNum * pArrConnectPartyNum
- voice_arrDiagInfo * pArrDiagInfo
- voice_arrCalledPartyNum * pArrCalledPartyNum
- voice_arrRedirPartyNum * pArrRedirPartyNum
- voice_arrAlertingPattern * pArrAlertingPattern
- swi_uint256_t ParamPresenceMask

8.1488.1 Detailed Description

This structure contains information about the response parameters with all the calls originating or terminating from a particular device.

Parameters

pArrCallInfo(optional)	• See voice_arrCallInfo for more information. • Bit to check in ParamPresenceMask - **16**
pArrRemotePartyNum(optional)	• See voice_arrRemotePartyNum for more information. • Bit to check in ParamPresenceMask - **17**
pArrRemotePartyName(optional)	• See voice_arrRemotePartyName for more information. • Bit to check in ParamPresenceMask - **18**
pArrAlertingType(optional)	• See voice_arrAlertingType for more information. • Bit to check in ParamPresenceMask - **19**
pArrUUSInfo(optional)	• See voice_arrUUSInfo for more information. • Bit to check in ParamPresenceMask - **20**
pArrSvcOption(optional)	• See voice_arrSvcOption for more information. • Bit to check in ParamPresenceMask - **21**

pOTASP-Status(optional)	• OTASP status for the OTASP call. • Applicable only for 3GPP2 devices. – 0x00 - OTASP_STATUS_SPL_UNLOCKED - SPL unlocked; only for user-initiated OTASP – 0x01 - OTASP_STATUS_SPRC_RETRIES_EXCEEDED - SPC retries exceeded; only for user-initiated OTASP – 0x02 - OTASP_STATUS_AKEY_EXCHANGED - A-key exchanged; only for user-initiated OTASP – 0x03 - OTASP_STATUS_SSD_UPDATED - SSD updated; for both user-initiated OTASP and network-initiated OTASP (OTAPA) – 0x04 - OTASP_STATUS_NAM_DOWNLOADED - NAM downloaded; only for user-initiated OTASP – 0x05 - OTASP_STATUS_MDN_DOWNLOADED - MDN downloaded; only for user-initiated OTASP – 0x06 - OTASP_STATUS_IMSI_DOWNLOADED - IMSI downloaded; only for user-initiated OTASP – 0x07 - OTASP_STATUS_PRL_DOWNLOADED - PRL downloaded; only for user-initiated OTASP – 0x08 - OTASP_STATUS_COMMITTED - Commit successful; only for user-initiated OTASP – 0x09 - OTASP_STATUS_OTAPA_STARTED - OTAPA started; only for network-initiated OTASP (OTAPA) – 0x0A - OTASP_STATUS_OTAPA_STOPPED - OTAPA stopped; only for network-initiated OTASP (OTAPA) – 0x0B - OTASP_STATUS_OTAPA_ABORTED - OTAPA aborted; only for network-initiated OTASP (OTAPA) – 0x0C - OTASP_STATUS_OTAPA_COMMITTED - OTAPA committed; only for network-initiated OTASP (OTAPA) – 0xFF - Not Available • Bit to check in ParamPresenceMask - **22**
pVoice-Privacy(optional)	• Voice Privacy. • Values. – 0x00 - VOICE_PRIVACY_STANDARD - Standard privacy – 0x01 - VOICE_PRIVACY_ENHANCED - Enhanced privacy – 0xFF - Not Available • Bit to check in ParamPresenceMask - **23**
pArrCallEnd-Reason(optional)	• See voice_arrCallEndReason for more information. • Bit to check in ParamPresenceMask - **24**
pArrAlphaI-D(optional)	• See voice_arrAlphaID for more information. • Bit to check in ParamPresenceMask - **25**
pArrConnect-Party-Num(optional)	• See voice_arrConnectPartyNum for more information. • Bit to check in ParamPresenceMask - **26**

pArrDiag-Info(optional)	• See voice_arrDiagInfo for more information. • Bit to check in ParamPresenceMask - **27**
pArrCalledParty-Num(optional)	• See voice_arrCalledPartyNum for more information. • Bit to check in ParamPresenceMask - **28**
pArrRedirParty-Num(optional)	• See voice_arrRedirPartyNum for more information. • Bit to check in ParamPresenceMask - **29**
pArrAlerting-Pattern(optional)	• See voice_arrAlertingPattern for more information. • Bit to check in ParamPresenceMask - **30**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1488.2 Field Documentation

8.1488.2.1 swi_uint256_t unpack_voice_SLQSVoiceGetAllCallInfo_t::ParamPresenceMask

8.1488.2.2 voice_arrAlertingPattern* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrAlertingPattern

8.1488.2.3 voice_arrAlertingType* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrAlertingType

8.1488.2.4 voice_arrAlphaID* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrAlphaID

8.1488.2.5 voice_arrCalledPartyNum* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrCalledPartyNum

8.1488.2.6 voice_arrCallEndReason* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrCallEndReason

8.1488.2.7 voice_arrCallInfo* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrCallInfo

8.1488.2.8 voice_arrConnectPartyNum* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrConnectPartyNum

8.1488.2.9 voice_arrDiagInfo* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrDiagInfo

8.1488.2.10 voice_arrRedirPartyNum* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrRedirPartyNum

8.1488.2.11 voice_arrRemotePartyName* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrRemotePartyName

8.1488.2.12 voice_arrRemotePartyNum* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrRemotePartyNum

8.1488.2.13 voice_arrSvcOption* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrSvcOption

8.1488.2.14 voice_arrUUSInfo* unpack_voice_SLQSVoiceGetAllCallInfo_t::pArrUUSInfo

8.1488.2.15 uint8_t* unpack_voice_SLQSVoiceGetAllCallInfo_t::pOTASPStatus

8.1488.2.16 uint8_t* unpack_voice_SLQSVoiceGetAllCallInfo_t::pVoicePrivacy

8.1489 unpack_voice_SLQSVoiceGetCallBarring_t Struct Reference

Data Fields

- uint8_t * pSvcClass
- uint16_t * pFailCause
- voice_alphaIDInfo * pAlphaIDInfo
- uint8_t * pCCResType
- uint8_t * pCallID
- voice_ccSUPSType * pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1489.1 Detailed Description

This structure contains Voice Get Call Barring Response Parameters

Parameters

pSvcClass	• Service class is a combination (sum) of information class constants (optional) • See qaGobiApiTableSupServiceInfoClasses.h for service classes. • Service Class is set to 0 if call waiting is not active for any of the information classes. • 0xFF,if Not Available • Bit to check in ParamPresenceMask - **16**
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available • Bit to check in ParamPresenceMask - **17**
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **18**

pCCResType	• Call Control Result Type (optional)
	  – 0x00 - CC_RESULT_TYPE_VOICE - Voice
	  – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service
	  – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service
	  – 0xFF - Not Available
	• Bit to check in ParamPresenceMask - **19**

pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid. • Bit to check in ParamPresenceMask - **20**

pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **21**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1489.2 Field Documentation

8.1489.2.1 voice_alphaIDInfo∗ unpack_voice_SLQSVoiceGetCallBarring_t::pAlphaIDInfo

8.1489.2.2 swi_uint256_t unpack_voice_SLQSVoiceGetCallBarring_t::ParamPresenceMask

8.1489.2.3 uint8_t∗ unpack_voice_SLQSVoiceGetCallBarring_t::pCallID

8.1489.2.4 uint8_t∗ unpack_voice_SLQSVoiceGetCallBarring_t::pCCResType

8.1489.2.5 voice_ccSUPSType∗ unpack_voice_SLQSVoiceGetCallBarring_t::pCCSUPSType

8.1489.2.6 uint16_t∗ unpack_voice_SLQSVoiceGetCallBarring_t::pFailCause

8.1489.2.7 uint8_t∗ unpack_voice_SLQSVoiceGetCallBarring_t::pSvcClass

8.1490 unpack_voice_SLQSVoiceGetCallForwardingStatus_t Struct Reference

Data Fields

- voice_getCallFWInfo ∗ pGetCallFWInfo
- uint16_t ∗ pFailCause
- voice_alphaIDInfo ∗ pAlphaIDInfo
- uint8_t ∗ pCCResType
- uint8_t ∗ pCallID
- voice_ccSUPSType ∗ pCCSUPSType
- voice_getCallFWExtInfo ∗ pGetCallFWExtInfo
- swi_uint256_t ParamPresenceMask

8.1490.1 Detailed Description

This structure contains Voice Get Call Forwarding Status Unpack Parameters

Parameters

pGetCallFWInfo	• Pointer to structure of getCallFWInfo (optional) – See voice_getCallFWInfo for more information • Bit to check in ParamPresenceMask - **16**

pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available • Bit to check in ParamPresenceMask - **17**
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **18**
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available • Bit to check in ParamPresenceMask - **19**
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid. • Bit to check in ParamPresenceMask - **20**
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **21**
pGetCallFWExt-Info	• Pointer to structure of getCallFWExtInfo (optional) – See voice_getCallFWExtInfo for more information • Bit to check in ParamPresenceMask - **22**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1490.2 Field Documentation

8.1490.2.1 voice_alphaIDInfo* unpack_voice_SLQSVoiceGetCallForwardingStatus_t::pAlphaIDInfo

8.1490.2.2 swi_uint256_t unpack_voice_SLQSVoiceGetCallForwardingStatus_t::ParamPresenceMask

8.1490.2.3 uint8_t* unpack_voice_SLQSVoiceGetCallForwardingStatus_t::pCallID

8.1490.2.4 uint8_t* unpack_voice_SLQSVoiceGetCallForwardingStatus_t::pCCResType

8.1490.2.5 voice_ccSUPSType* unpack_voice_SLQSVoiceGetCallForwardingStatus_t::pCCSUPSType

8.1490.2.6 uint16_t* unpack_voice_SLQSVoiceGetCallForwardingStatus_t::pFailCause

8.1490.2.7 voice_getCallFWExtInfo* unpack_voice_SLQSVoiceGetCallForwardingStatus_t::pGetCallFWExtInfo

8.1490.2.8 voice_getCallFWInfo* unpack_voice_SLQSVoiceGetCallForwardingStatus_t::pGetCallFWInfo

8.1491 unpack_voice_SLQSVoiceGetCallInfo_t Struct Reference

Data Fields

- voice_callInfo * pCallInfo
- voice_remotePartyNum * pRemotePartyNum
- uint16_t * pSrvOpt
- uint8_t * pVoicePrivacy
- uint8_t * pOTASPStatus
- voice_remotePartyName * pRemotePartyName
- voice_UUSInfo * pUUSInfo
- uint8_t * pAlertType
- voice_alphaIDInfo * pAlphaIDInfo
- voice_connectNumInfo * pConnectNumInfo
- voice_diagInfo * pDiagInfo
- uint32_t * pAlertingPattern
- swi_uint256_t ParamPresenceMask

8.1491.1 Detailed Description

This structure contains information of the unpack parameters associated with a call.

Parameters

pCallInfo(optional)	• See voice_callInfo for more information. • Bit to check in ParamPresenceMask - **16**
pRemotePartyNum(optional)	• See voice_remotePartyNum for more information. • Bit to check in ParamPresenceMask - **17**
pSrvOpt	• Service option(optional) • Applicable only for 3GPP2 devices. • See Table8 qaGobiApiTableServiceOptions.h for standard service option number assignments. • Bit to check in ParamPresenceMask - **18**
pVoicePrivacy	• Voice Privacy.(optional) • Applicable only for 3GPP2 devices. • Values. – 0x00 - VOICE_PRIVACY_STANDARD - Standard privacy – 0x01 - VOICE_PRIVACY_ENHANCED - Enhanced privacy – 0xFF - Not Available • Bit to check in ParamPresenceMask - **19**

pOTASPStatus	• OTASP status for the OTASP call.(optional) • Applicable only for 3GPP2 devices. – 0x00 - OTASP_STATUS_SPL_UNLOCKED - SPL unlocked; only for user-initiated OTASP – 0x01 - OTASP_STATUS_SPRC_RETRIES_EXCEEDED - SPC retries exceeded; only for user-initiated OTASP – 0x02 - OTASP_STATUS_AKEY_EXCHANGED - A-key exchanged; only for user-initiated OTASP – 0x03 - OTASP_STATUS_SSD_UPDATED - SSD updated; for both user-initiated OTASP and network-initiated OTASP (OTAPA) – 0x04 - OTASP_STATUS_NAM_DOWNLOADED - NAM downloaded; only for user-initiated OTASP – 0x05 - OTASP_STATUS_MDN_DOWNLOADED - MDN downloaded; only for user-initiated OTASP – 0x06 - OTASP_STATUS_IMSI_DOWNLOADED - IMSI downloaded; only for user-initiated OTASP – 0x07 - OTASP_STATUS_PRL_DOWNLOADED - PRL downloaded; only for user-initiated OTASP – 0x08 - OTASP_STATUS_COMMITTED - Commit successful; only for user-initiated OTASP – 0x09 - OTASP_STATUS_OTAPA_STARTED - OTAPA started; only for network-initiated OTASP (OTAPA) – 0x0A - OTASP_STATUS_OTAPA_STOPPED - OTAPA stopped; only for network-initiated OTASP (OTAPA) – 0x0B - OTASP_STATUS_OTAPA_ABORTED - OTAPA aborted; only for network-initiated OTASP (OTAPA) – 0x0C - OTASP_STATUS_OTAPA_COMMITTED - OTAPA committed; only for network-initiated OTASP (OTAPA) – 0xFF - Not Available • Bit to check in ParamPresenceMask - **20**
pRemoteParty-Name(optional)	• Applicable only for 3GPP devices. • See voice_remotePartyName for more information. • Bit to check in ParamPresenceMask - **21**
pUUS-Info(optional)	• Applicable only for 3GPP devices. • See voice_UUSInfo for more information. • Bit to check in ParamPresenceMask - **22**
pAlert-Type(optional)	• Alerting type. • Applicable only for 3GPP devices. – 0x00 - ALERTING_LOCAL - Local – 0x01 - ALERTING_REMOTE - Remote – 0xFF - Not Available • Bit to check in ParamPresenceMask - **23**

pAlphaID-Info(optional)	• Applicable only for 3GPP devices. • See voice_alphaIDInfo for more information. • Bit to check in ParamPresenceMask - **24**
pConnectNum-Info(optional)	• See voice_connectNumInfo for more information. • Bit to check in ParamPresenceMask - **25**
pDiag-Info(optional)	• See voice_diagInfo for more information. • Bit to check in ParamPresenceMask - **26**
pAlertingPattern	• Alerting pattern.(optional) – 0x00 - QMI_VOICE_ALERTING_PATTERN_1 - Pattern 1 – 0x01 - QMI_VOICE_ALERTING_PATTERN_2 - Pattern 2 – 0x02 - QMI_VOICE_ALERTING_PATTERN_3 - Pattern 3 – 0x04 - QMI_VOICE_ALERTING_PATTERN_5 - Pattern 5 – 0x05 - QMI_VOICE_ALERTING_PATTERN_6 - Pattern 6 – 0x06 - QMI_VOICE_ALERTING_PATTERN_7 - Pattern 7 – 0x07 - QMI_VOICE_ALERTING_PATTERN_8 - Pattern 8 – 0x08 - QMI_VOICE_ALERTING_PATTERN_9 - Pattern 9 – 0xFF - Not Available • Bit to check in ParamPresenceMask - **27**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1491.2 Field Documentation

8.1491.2.1 uint32_t* unpack_voice_SLQSVoiceGetCallInfo_t::pAlertingPattern

8.1491.2.2 uint8_t* unpack_voice_SLQSVoiceGetCallInfo_t::pAlertType

8.1491.2.3 voice_alphaIDInfo* unpack_voice_SLQSVoiceGetCallInfo_t::pAlphaIDInfo

8.1491.2.4 swi_uint256_t unpack_voice_SLQSVoiceGetCallInfo_t::ParamPresenceMask

8.1491.2.5 voice_callInfo* unpack_voice_SLQSVoiceGetCallInfo_t::pCallInfo

8.1491.2.6 voice_connectNumInfo* unpack_voice_SLQSVoiceGetCallInfo_t::pConnectNumInfo

8.1491.2.7 voice_diagInfo* unpack_voice_SLQSVoiceGetCallInfo_t::pDiagInfo

8.1491.2.8 uint8_t* unpack_voice_SLQSVoiceGetCallInfo_t::pOTASPStatus

8.1491.2.9 voice_remotePartyName* unpack_voice_SLQSVoiceGetCallInfo_t::pRemotePartyName

8.1491.2.10 voice_remotePartyNum* unpack_voice_SLQSVoiceGetCallInfo_t::pRemotePartyNum

8.1491.2.11 uint16_t* unpack_voice_SLQSVoiceGetCallInfo_t::pSrvOpt

8.1491.2.12 voice_UUSInfo* unpack_voice_SLQSVoiceGetCallInfo_t::pUUSInfo

8.1491.2.13 uint8_t* unpack_voice_SLQSVoiceGetCallInfo_t::pVoicePrivacy

8.1492 unpack_voice_SLQSVoiceGetCallWaiting_t Struct Reference

Data Fields

- uint8_t * pSvcClass
- uint16_t * pFailCause
- voice_alphaIDInfo * pAlphaIDInfo
- uint8_t * pCCResType
- uint8_t * pCallID
- voice_ccSUPSType * pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1492.1 Detailed Description

This structure contains Voice Get Call Waiting Unpack Parameters

Parameters

pSvcClass	• Service class is a combination (sum) of information class constants (optional) • See qaGobiApiTableSupServiceInfoClasses.h for service classes. • Service Class is set to 0 if call waiting is not active for any of the information classes. • 0xFF,if Not Available • Bit to check in ParamPresenceMask - **16**
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available • Bit to check in ParamPresenceMask - **17**
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **18**

pCCResType	• Call Control Result Type (optional)
	  – 0x00 - CC_RESULT_TYPE_VOICE - Voice
	  – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service
	  – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service
	  – 0xFF - Not Available
	• Bit to check in ParamPresenceMask - **19**

pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid. • Bit to check in ParamPresenceMask - **20**
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **21**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1492.2 Field Documentation

8.1492.2.1 voice_alphaIDInfo∗ unpack_voice_SLQSVoiceGetCallWaiting_t::pAlphaIDInfo

8.1492.2.2 swi_uint256_t unpack_voice_SLQSVoiceGetCallWaiting_t::ParamPresenceMask

8.1492.2.3 uint8_t∗ unpack_voice_SLQSVoiceGetCallWaiting_t::pCallID

8.1492.2.4 uint8_t∗ unpack_voice_SLQSVoiceGetCallWaiting_t::pCCResType

8.1492.2.5 voice_ccSUPSType∗ unpack_voice_SLQSVoiceGetCallWaiting_t::pCCSUPSType

8.1492.2.6 uint16_t∗ unpack_voice_SLQSVoiceGetCallWaiting_t::pFailCause

8.1492.2.7 uint8_t∗ unpack_voice_SLQSVoiceGetCallWaiting_t::pSvcClass

8.1493 unpack_voice_SLQSVoiceGetCLIP_t Struct Reference

Data Fields

- voice_CLIPResp ∗ pCLIPResp
- uint16_t ∗ pFailCause
- voice_alphaIDInfo ∗ pAlphaIDInfo
- uint8_t ∗ pCCResType
- uint8_t ∗ pCallID
- voice_ccSUPSType ∗ pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1493.1 Detailed Description

This structure contains Voice Get Calling Line Identification Presentation(CLIP) Response Parameters

Parameters

pCLIPResp	• Pointer to structure of CLIPResp (optional) – See voice_CLIPResp for more information • Bit to check in ParamPresenceMask - **16**
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available • Bit to check in ParamPresenceMask - **17**
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **18**
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available • Bit to check in ParamPresenceMask - **19**
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid. • Bit to check in ParamPresenceMask - **20**
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **21**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1493.2 Field Documentation

8.1493.2.1 voice_alphaIDInfo* unpack_voice_SLQSVoiceGetCLIP_t::pAlphaIDInfo

8.1493.2.2 swi_uint256_t unpack_voice_SLQSVoiceGetCLIP_t::ParamPresenceMask

8.1493.2.3 uint8_t* unpack_voice_SLQSVoiceGetCLIP_t::pCallID

8.1493.2.4 uint8_t* unpack_voice_SLQSVoiceGetCLIP_t::pCCResType

8.1493.2.5 voice_ccSUPSType* unpack_voice_SLQSVoiceGetCLIP_t::pCCSUPSType

8.1493.2.6 voice_CLIPResp∗ unpack_voice_SLQSVoiceGetCLIP_t::pCLIPResp

8.1493.2.7 uint16_t∗ unpack_voice_SLQSVoiceGetCLIP_t::pFailCause

8.1494 unpack_voice_SLQSVoiceGetCLIR_t Struct Reference

Data Fields

- voice_CLIRResp ∗ pCLIRResp
- uint16_t ∗ pFailCause
- voice_alphaIDInfo ∗ pAlphaIDInfo
- uint8_t ∗ pCCResType
- uint8_t ∗ pCallID
- voice_ccSUPSType ∗ pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1494.1 Detailed Description

This structure contains Voice Get Calling Line Identification Restriction (CLIR) Response Parameters

Parameters

pCLIRResp	• Pointer to structure of CLIRResp (optional) – See voice_CLIRResp for more information • Bit to check in ParamPresenceMask - **16**
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available • Bit to check in ParamPresenceMask - **17**
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **18**

pCCResType	• Call Control Result Type (optional)
	  – 0x00 - CC_RESULT_TYPE_VOICE - Voice
	  – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service
	  – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service
	  – 0xFF - Not Available
	• Bit to check in ParamPresenceMask - **19**

pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid. • Bit to check in ParamPresenceMask - **20**

pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **21**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1494.2 Field Documentation

8.1494.2.1 voice_alphaIDInfo∗ unpack_voice_SLQSVoiceGetCLIR_t::pAlphaIDInfo

8.1494.2.2 swi_uint256_t unpack_voice_SLQSVoiceGetCLIR_t::ParamPresenceMask

8.1494.2.3 uint8_t∗ unpack_voice_SLQSVoiceGetCLIR_t::pCallID

8.1494.2.4 uint8_t∗ unpack_voice_SLQSVoiceGetCLIR_t::pCCResType

8.1494.2.5 voice_ccSUPSType∗ unpack_voice_SLQSVoiceGetCLIR_t::pCCSUPSType

8.1494.2.6 voice_CLIRResp∗ unpack_voice_SLQSVoiceGetCLIR_t::pCLIRResp

8.1494.2.7 uint16_t∗ unpack_voice_SLQSVoiceGetCLIR_t::pFailCause

8.1495 unpack_voice_SLQSVoiceGetCNAP_t Struct Reference

Data Fields

- voice_CNAPResp ∗ pCNAPResp
- uint16_t ∗ pFailCause
- voice_alphaIDInfo ∗ pAlphaIDInfo
- uint8_t ∗ pCCResType
- uint8_t ∗ pCallID
- voice_ccSUPSType ∗ pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1495.1 Detailed Description

This structure contains Voice Get Calling Name Presentation(CNAP) Response Parameters

Parameters

pCNAPResp	• Pointer to structure of CNAPResp (optional) – See voice_CNAPResp for more information • Bit to check in ParamPresenceMask - **16**

pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available • Bit to check in ParamPresenceMask - **17**
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **18**
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available • Bit to check in ParamPresenceMask - **19**
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid. • Bit to check in ParamPresenceMask - **20**
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **21**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1495.2 Field Documentation

8.1495.2.1 voice_alphaIDInfo* unpack_voice_SLQSVoiceGetCNAP_t::pAlphaIDInfo

8.1495.2.2 swi_uint256_t unpack_voice_SLQSVoiceGetCNAP_t::ParamPresenceMask

8.1495.2.3 uint8_t* unpack_voice_SLQSVoiceGetCNAP_t::pCallID

8.1495.2.4 uint8_t* unpack_voice_SLQSVoiceGetCNAP_t::pCCResType

8.1495.2.5 voice_ccSUPSType* unpack_voice_SLQSVoiceGetCNAP_t::pCCSUPSType

8.1495.2.6 voice_CNAPResp* unpack_voice_SLQSVoiceGetCNAP_t::pCNAPResp

8.1495.2.7 uint16_t* unpack_voice_SLQSVoiceGetCNAP_t::pFailCause

8.1496 unpack_voice_SLQSVoiceGetCOLP_t Struct Reference

Data Fields

- voice_COLPResp * pCOLPResp
- uint16_t * pFailCause
- voice_alphaIDInfo * pAlphaIDInfo
- uint8_t * pCCResType
- uint8_t * pCallID
- voice_ccSUPSType * pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1496.1 Detailed Description

This structure contains Voice Get Connected Line Identification Presentation(COLP) Response Parameters

Parameters

pCOLPResp	• Pointer to structure of COLPResp (optional) – See voice_COLPResp for more information • Bit to check in ParamPresenceMask - **16**
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available • Bit to check in ParamPresenceMask - **17**
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **18**
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available • Bit to check in ParamPresenceMask - **19**
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid. • Bit to check in ParamPresenceMask - **20**
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **21**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1496.2 Field Documentation

8.1496.2.1 voice_alphaIDInfo* unpack_voice_SLQSVoiceGetCOLP_t::pAlphaIDInfo

8.1496.2.2 swi_uint256_t unpack_voice_SLQSVoiceGetCOLP_t::ParamPresenceMask

8.1496.2.3 uint8_t* unpack_voice_SLQSVoiceGetCOLP_t::pCallID

8.1496.2.4 uint8_t* unpack_voice_SLQSVoiceGetCOLP_t::pCCResType

8.1496.2.5 voice_ccSUPSType* unpack_voice_SLQSVoiceGetCOLP_t::pCCSUPSType

8.1496.2.6 voice_COLPResp* unpack_voice_SLQSVoiceGetCOLP_t::pCOLPResp

8.1496.2.7 uint16_t* unpack_voice_SLQSVoiceGetCOLP_t::pFailCause

8.1497 unpack_voice_SLQSVoiceGetCOLR_t Struct Reference

Data Fields

- voice_COLRResp * pCOLRResp
- uint16_t * pFailCause
- voice_alphaIDInfo * pAlphaIDInfo
- uint8_t * pCCResType
- uint8_t * pCallID
- voice_ccSUPSType * pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1497.1 Detailed Description

This structure contains Voice Get Connected Line Identification Restriction(COLR) Response Parameters

Parameters

pCOLRResp	• Pointer to structure of COLRResp (optional) – See voice_COLRResp for more information • Bit to check in ParamPresenceMask - **16**
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available • Bit to check in ParamPresenceMask - **17**

pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **18**

pCCResType	• Call Control Result Type (optional)
	  – 0x00 - CC_RESULT_TYPE_VOICE - Voice
	  – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service
	  – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service
	  – 0xFF - Not Available
	• Bit to check in ParamPresenceMask - **19**

pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid. • Bit to check in ParamPresenceMask - **20**
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **21**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1497.2 Field Documentation

8.1497.2.1 voice_alphaIDInfo∗ unpack_voice_SLQSVoiceGetCOLR_t::pAlphaIDInfo

8.1497.2.2 swi_uint256_t unpack_voice_SLQSVoiceGetCOLR_t::ParamPresenceMask

8.1497.2.3 uint8_t∗ unpack_voice_SLQSVoiceGetCOLR_t::pCallID

8.1497.2.4 uint8_t∗ unpack_voice_SLQSVoiceGetCOLR_t::pCCResType

8.1497.2.5 voice_ccSUPSType∗ unpack_voice_SLQSVoiceGetCOLR_t::pCCSUPSType

8.1497.2.6 voice_COLRResp∗ unpack_voice_SLQSVoiceGetCOLR_t::pCOLRResp

8.1497.2.7 uint16_t∗ unpack_voice_SLQSVoiceGetCOLR_t::pFailCause

8.1498 unpack_voice_SLQSVoiceGetConfig_t Struct Reference

Data Fields

- uint8_t ∗ pAutoAnswerStat
- voice_airTimer ∗ pAirTimerCnt
- voice_roamTimer ∗ pRoamTimerCnt

- uint8_t * pCurrTTYMode
- voice_prefVoiceSO * pCurPrefVoiceSO
- voice_curAMRConfig * pCurAMRConfig
- uint8_t * pCurVoicePrivacyPref
- uint8_t * pCurVoiceDomainPref
- swi_uint256_t ParamPresenceMask

8.1498.1 Detailed Description

This structure contains Voice Get Configuration Response Parameters.

Parameters

pAutoAnswerStat(optional)	• Auto Answer Status • Value returned is read from NV_AUTO_ANSWER_I. – 0x00 - Disabled – 0x01 - Enabled – 0xFF - Not Available • Bit to check in ParamPresenceMask - **16**
pAirTimerCnt(optional)	• Air Timer Count • Value returned is read from NV_AIR_CNT_I. • See voice_airTimer for more information • Bit to check in ParamPresenceMask - **17**
pRoamTimerCnt(optional)	• Roam Timer Count • Value returned is read from NV_ROAM_CNT_I. • See voice_roamTimer for more information • Bit to check in ParamPresenceMask - **18**
pCurrTTYMode(optional)	• Current TTY Mode • Value returned is read from NV_TTY_I. – 0x00 - TTY_MODE_FULL - Full – 0x01 - TTY_MODE_VCO - Voice carry over – 0x02 - TTY_MODE_HCO - Hearing carry over – 0x03 - TTY_MODE_OFF - Off – 0xFF - Not Available • Bit to check in ParamPresenceMask - **19**
pCurPrefVoiceSO(optional)	• Current Preferred Voice SO • Value returned is read from NV_PREF_VOICE_SO_I. • See voice_prefVoiceSO for more information • Bit to check in ParamPresenceMask - **20**

pCurAMR-Config(optional)	• Current Adaptive Multi-Rate Configuration. • Values returned are read from NV_GSM_ARM_CALL_CONFIG_I and NV_UMTS_AMR_CODEC_PREFERENCE_CONFIG_I. • See voice_curAMRConfig for more information • Bit to check in ParamPresenceMask - **21**
pCurVoice-Privacy-Pref(optional)	• Current Voice Privacy Preference • Value returned is read from NV_VOICE_PRIV_I. – 0x00 - Standard privacy – 0x01 - Enhanced privacy – 0xFF - Not Available • Bit to check in ParamPresenceMask - **22**
pCurVoice-Domain-Pref(optional)	• Current Voice Domain Preference. – 0x00 - Circuit-switched (CS) only – 0x01 - Packet-switched (PS) only – 0x02 - CS is preferred; PS is secondary – 0x03 - PS is preferred; CS is secondary – 0xFF - Not Available • Bit to check in ParamPresenceMask - **23**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1498.2 Field Documentation

8.1498.2.1 voice_airTimer* unpack_voice_SLQSVoiceGetConfig_t::pAirTimerCnt

8.1498.2.2 swi_uint256_t unpack_voice_SLQSVoiceGetConfig_t::ParamPresenceMask

8.1498.2.3 uint8_t* unpack_voice_SLQSVoiceGetConfig_t::pAutoAnswerStat

8.1498.2.4 voice_curAMRConfig* unpack_voice_SLQSVoiceGetConfig_t::pCurAMRConfig

8.1498.2.5 voice_prefVoiceSO* unpack_voice_SLQSVoiceGetConfig_t::pCurPrefVoiceSO

8.1498.2.6 uint8_t* unpack_voice_SLQSVoiceGetConfig_t::pCurrTTYMode

8.1498.2.7 uint8_t* unpack_voice_SLQSVoiceGetConfig_t::pCurVoiceDomainPref

8.1498.2.8 uint8_t* unpack_voice_SLQSVoiceGetConfig_t::pCurVoicePrivacyPref

8.1498.2.9 voice_roamTimer* unpack_voice_SLQSVoiceGetConfig_t::pRoamTimerCnt

8.1499 unpack_voice_SLQSVoiceManageCalls_t Struct Reference

Data Fields

- uint16_t * pFailCause
- swi_uint256_t ParamPresenceMask

8.1499.1 Detailed Description

This structure contains Failure cause Information. Populated when API Fails.

Parameters

pFailCause	• Supplementary service failure causes (optional, supply NULL if not required). • See Table8 qaGobiApiTableVoiceCallEndReasons.h for supplementary services failure cause – 0xFFFF is the value when the information is not received from device • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1499.2 Field Documentation

8.1499.2.1 swi_uint256_t unpack_voice_SLQSVoiceManageCalls_t::ParamPresenceMask

8.1499.2.2 uint16_t* unpack_voice_SLQSVoiceManageCalls_t::pFailCause

8.1500 unpack_voice_SLQSVoiceSendFlash_t Struct Reference

Data Fields

- uint8_t * pCallID
- swi_uint256_t ParamPresenceMask

8.1500.1 Detailed Description

This structure contains the flash information associated with a call.

Parameters

pCallID	• Unique call identifier associated with the current call. • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1500.2 Field Documentation

8.1500.2.1 swi_uint256_t unpack_voice_SLQSVoiceSendFlash_t::ParamPresenceMask

8.1500.2.2 uint8_t* unpack_voice_SLQSVoiceSendFlash_t::pCallID

8.1501 unpack_voice_SLQSVoiceSetCallBarringPassword_t Struct Reference

Data Fields

- uint16_t * pFailCause
- voice_alphaIDInfo * pAlphaIDInfo
- uint8_t * pCCResType
- uint8_t * pCallID
- voice_ccSUPSType * pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1501.1 Detailed Description

This structure contains Voice Set Call Barring Password Unpack Parameters

Parameters

pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available • Bit to check in ParamPresenceMask - **16**
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **17**
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available • Bit to check in ParamPresenceMask - **18**
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid. • Bit to check in ParamPresenceMask - **19**
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **20**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1501.2 Field Documentation

8.1501.2.1 voice_alphaIDInfo* unpack_voice_SLQSVoiceSetCallBarringPassword_t::pAlphaIDInfo

8.1501.2.2 swi_uint256_t unpack_voice_SLQSVoiceSetCallBarringPassword_t::ParamPresenceMask

8.1501.2.3 uint8_t* unpack_voice_SLQSVoiceSetCallBarringPassword_t::pCallID

8.1501.2.4 uint8_t* unpack_voice_SLQSVoiceSetCallBarringPassword_t::pCCResType

8.1501.2.5 voice_ccSUPSType* unpack_voice_SLQSVoiceSetCallBarringPassword_t::pCCSUPSType

8.1501.2.6 uint16_t* unpack_voice_SLQSVoiceSetCallBarringPassword_t::pFailCause

8.1502 unpack_voice_SLQSVoiceSetConfig_t Struct Reference

Data Fields

- uint8_t * pAutoAnsStatus
- uint8_t * pAirTimerStatus
- uint8_t * pRoamTimerStatus
- uint8_t * pTTYConfigStatus
- uint8_t * pPrefVoiceSOStatus
- uint8_t * pVoiceDomainPrefStatus
- swi_uint256_t ParamPresenceMask

8.1502.1 Detailed Description

This structure contains information about the Set Configuration Response Parameters.

Parameters

pAutoAnsStatus	• Auto Answer Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available. • Bit to check in ParamPresenceMask - **16**
pAirTimerStatus	• Air Timer Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available. • Bit to check in ParamPresenceMask - **17**

pRoamTimer-Status	• Roam Timer Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available. • Bit to check in ParamPresenceMask - **18**
pTTYConfig-Status	• TTY Config Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available. • Bit to check in ParamPresenceMask - **19**
pPrefVoiceSO-Status	• Preferred Voice SO Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available. • Bit to check in ParamPresenceMask - **20**
pVoiceDomain-PrefStatus	• Voice-Domain Preference Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available. • Bit to check in ParamPresenceMask - **21**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1502.2 Field Documentation

8.1502.2.1 uint8_t* unpack_voice_SLQSVoiceSetConfig_t::pAirTimerStatus

8.1502.2.2 swi_uint256_t unpack_voice_SLQSVoiceSetConfig_t::ParamPresenceMask

8.1502.2.3 uint8_t* unpack_voice_SLQSVoiceSetConfig_t::pAutoAnsStatus

8.1502.2.4 uint8_t* unpack_voice_SLQSVoiceSetConfig_t::pPrefVoiceSOStatus

8.1502.2.5 uint8_t* unpack_voice_SLQSVoiceSetConfig_t::pRoamTimerStatus

8.1502.2.6 uint8_t* unpack_voice_SLQSVoiceSetConfig_t::pTTYConfigStatus

8.1502.2.7 uint8_t* unpack_voice_SLQSVoiceSetConfig_t::pVoiceDomainPrefStatus

8.1503 unpack_voice_SLQSVoiceSetSUPSService_t Struct Reference

Data Fields

- uint16_t * pFailCause
- voice_alphaIDInfo * pAlphaIDInfo
- uint8_t * pCCResultType
- uint8_t * pCallID
- voice_ccSUPSType * pCCSUPSType
- swi_uint256_t ParamPresenceMask

8.1503.1 Detailed Description

This structure contains Supplementary Service response parameters related to different features and their activation, deactivation, registration and erasure (applicable only for 3GPP)

Parameters

pFailCause	• Supplementary service failure causes (optional, supply NULL if not required). – 0xFFFF is the value when the information is not received from device • Bit to check in ParamPresenceMask - **16**
pAlphaIDInfo	• Pointer to structure of alphaIDInfo. The parameter used to pass the alpha (if any) given by the SIM/R-UIM after call control (optional, supply NULL if not required) – See voice_alphaIDInfo for more information • Bit to check in ParamPresenceMask - **17**
pCCResultType	• Call control result types (optional, supply NULL if not required) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - if the device does not provide this information • Bit to check in ParamPresenceMask - **19**
pCallID	• Unique call identifier for the dialed call (optional, supply NULL if not required) – 0x00 - if the device does not provide this information • Bit to check in ParamPresenceMask - **18**
pCCSUPSType	• Data is present when pCCResultType is present and is other than Voice. (optional, supply NULL if not required) – See voice_ccSUPSType for more information • Bit to check in ParamPresenceMask - **20**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1503.2 Field Documentation

8.1503.2.1 voice_alphaIDInfo* unpack_voice_SLQSVoiceSetSUPSService_t::pAlphaIDInfo

8.1503.2.2 swi_uint256_t unpack_voice_SLQSVoiceSetSUPSService_t::ParamPresenceMask

8.1503.2.3 uint8_t* unpack_voice_SLQSVoiceSetSUPSService_t::pCallID

8.1503.2.4 uint8_t* unpack_voice_SLQSVoiceSetSUPSService_t::pCCResultType

8.1503.2.5 voice_ccSUPSType* unpack_voice_SLQSVoiceSetSUPSService_t::pCCSUPSType

8.1503.2.6 uint16_t* unpack_voice_SLQSVoiceSetSUPSService_t::pFailCause

8.1504 unpack_voice_SLQSVoiceStartContDTMF_t Struct Reference

Data Fields

- uint8_t * pCallID
- swi_uint256_t ParamPresenceMask

8.1504.1 Detailed Description

This structure contains parameters of continuous DTMF

Parameters

pCallID	• Call ID associated with call on which the DTMF information has to be sent. Start continuous DTMF request is sent to the current active/alerting call when pCallId is set to 0xFF. • This is IN/OUT parameter, value passed by user will be packed in request and value received from the device would be returned to the user. • If the call ID value received is 0, no value has been returned by the device • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1504.2 Field Documentation

8.1504.2.1 swi_uint256_t unpack_voice_SLQSVoiceStartContDTMF_t::ParamPresenceMask

8.1504.2.2 uint8_t* unpack_voice_SLQSVoiceStartContDTMF_t::pCallID

8.1505 unpack_voice_SLQSVoiceStopContDTMF_t Struct Reference

Data Fields

- uint8_t callID
- swi_uint256_t ParamPresenceMask

8.1505.1 Detailed Description

This structure contains parameters of stop continuous DTMF

Parameters

pCallID	• Call ID associated with call on which the DTMF information has to be sent. Stop continuous DTMF request is sent to the current active/alerting call when pCallId is set to 0xFF. • This is IN/OUT parameter, value passed by user will be packed in request and value received from the device would be returned to the user. • If the call ID value received is 0, no value has been returned by the device
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1505.2 Field Documentation

8.1505.2.1 uint8_t unpack_voice_SLQSVoiceStopContDTMF_t::callID

8.1505.2.2 swi_uint256_t unpack_voice_SLQSVoiceStopContDTMF_t::ParamPresenceMask

8.1506 unpack_voice_SLQSVoiceSUPSCallback_ind_t Struct Reference

Data Fields

- voice_SUPSInfo SUPSInformation
- uint8_t * pSvcClass
- uint8_t * pReason
- uint8_t * pCallFWNum
- uint8_t * pCallFWTimerVal
- struct voice_USSInfo * pUSSInfo
- uint8_t * pCallID
- voice_alphaIDInfo * pAlphaIDInfo
- uint8_t * pCallBarPasswd
- voice_newPwdData * pNewPwdData
- uint8_t * pDataSrc
- uint16_t * pFailCause
- voice_getCallFWInfo * pCallFwdInfo
- voice_CLIRResp * pCLIRstatus
- voice_CLIPResp * pCLIPstatus
- voice_COLPResp * pCOLPstatus
- voice_COLRResp * pCOLRstatus
- voice_CNAPResp * pCNAPstatus
- swi_uint256_t ParamPresenceMask

8.1506.1 Detailed Description

This structure contains the parameters passed for SUPS info indication by the device.

Parameters

SUPS-Information(mandatory)	See voice_SUPSInfo for more information. • Bit to check in ParamPresenceMask - **1**
pSvc-Class(optional)	• Service class is a combination (sum) of information class constants (optional) • See qaGobiApiTableSupServiceInfoClasses.h for service classes. • Bit to check in ParamPresenceMask - **16**
p-Reason(optional)	• See qaGobiApiTableCallControlReturnReasons.h for return reasons. • Bit to check in ParamPresenceMask - **17**
pCallFW-Num(optional)	• Call forwarding number to be registered with the network. • ASCII String, NULL terminated. • Bit to check in ParamPresenceMask - **18**
pCallFWTimer-Val(optional)	• Call Forwarding No Reply Timer. – Range: 5 to 30 in steps of 5. • Bit to check in ParamPresenceMask - **19**
pUSS-Info(optional)	• See voice_USSInfo for more information. • Bit to check in ParamPresenceMask - **20**
pCallID(optional)	• Call identifier of the voice call that has been modified to a supplementary service as a result of call control. • Bit to check in ParamPresenceMask - **21**
pAlphaID-Info(optional)	• See voice_alphaIDInfo for more information. • Bit to check in ParamPresenceMask - **22**

pCallBar-Passwd(optional)	• Password is required if call barring is provisioned using a password.
	  – Password consists of 4 ASCII digits.
	  – Range: 0000 to 9999.
	• This also serves as the old password in the register password scenario.
	• Bit to check in ParamPresenceMask - **23**

pNewPwd-Data(optional)	• See voice_newPwdData for more information. • Bit to check in ParamPresenceMask - **24**

pDataSrc(optional)	• Sups Data Source. • Used to distinguish between the supplementary service data sent to the network and the response received from the network. • If absent, the supplementary service data in this indication can be assumed as a request sent to the network. • Bit to check in ParamPresenceMask - **25**
pFailCause(optional)	• Supplementary services failure cause. • See qaGobiApiTableVoiceCallEndReasons.h for more information. • Bit to check in ParamPresenceMask - **26**
pCallFwdInfo(optional)	• See voice_getCallFWInfo for more information. • Bit to check in ParamPresenceMask - **27**
pCLIRstatus(optional)	• See voice_CLIRResp for more information. • Bit to check in ParamPresenceMask - **28**
pCLIPstatus(optional)	• See voice_CLIPResp for more information. • Bit to check in ParamPresenceMask - **29**
pCOLPstatus(optional)	• See voice_COLPResp for more information. • Bit to check in ParamPresenceMask - **30**
pCOLRstatus(optional)	• See voice_COLRResp for more information. • Bit to check in ParamPresenceMask - **31**
pCNAPstatus(optional)	• See voice_CNAPResp for more information. • Bit to check in ParamPresenceMask - **32**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

Note

None

8.1506.2 Field Documentation

8.1506.2.1 voice_alphaIDInfo* unpack_voice_SLQSVoiceSUPSCallback_ind_t::pAlphaIDInfo

8.1506.2.2 swi_uint256_t unpack_voice_SLQSVoiceSUPSCallback_ind_t::ParamPresenceMask

8.1506.2.3 uint8_t* unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCallBarPasswd

8.1506.2.4 **voice_getCallFWInfo**∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCallFwdInfo

8.1506.2.5 uint8_t∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCallFWNum

8.1506.2.6 uint8_t∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCallFWTimerVal

8.1506.2.7 uint8_t∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCallID

8.1506.2.8 **voice_CLIPResp**∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCLIPstatus

8.1506.2.9 **voice_CLIRResp**∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCLIRstatus

8.1506.2.10 **voice_CNAPResp**∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCNAPstatus

8.1506.2.11 **voice_COLPResp**∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCOLPstatus

8.1506.2.12 **voice_COLRResp**∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pCOLRstatus

8.1506.2.13 uint8_t∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pDataSrc

8.1506.2.14 uint16_t∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pFailCause

8.1506.2.15 **voice_newPwdData**∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pNewPwdData

8.1506.2.16 uint8_t∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pReason

8.1506.2.17 uint8_t∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pSvcClass

8.1506.2.18 struct **voice_USSInfo**∗ unpack_voice_SLQSVoiceSUPSCallback_ind_t::pUSSInfo

8.1506.2.19 **voice_SUPSInfo** unpack_voice_SLQSVoiceSUPSCallback_ind_t::SUPSInformation

8.1507 unpack_voice_SUPSNotificationCallback_ind_t Struct Reference

Data Fields

- uint8_t callID
- uint8_t notifType
- uint16_t ∗ pCUGIndex
- voice_ECTNum ∗ pECTNum
- swi_uint256_t ParamPresenceMask

8.1507.1 Detailed Description

Contains the parameters passed for SUPS notification indication by the device.

Parameters

callID	• Unique identifier of the call for which the notification is applicable. (mandatory) • Bit to check in ParamPresenceMask - **1**

notifType	• Notification type parameter (mandatory) – 0x01 - NOTIFICATION_TYPE_OUTGOING_CALL_IS_FORWARDED Originated MO call is being forwarded to another user – 0x02 - NOTIFICATION_TYPE_OUTGOING_CALL_IS_WAITING Originated MO call is waiting at the called user – 0x03 - NOTIFICATION_TYPE_OUTGOING_CUG_CALL Outgoing call is a CUG call – 0x04 - NOTIFICATION_TYPE_OUTGOING_CALLS_BARRED Outgoing calls are barred – 0x05 - NOTIFICATION_TYPE_OUTGOING_CALL_IS_DEFLECTED Outgoing call is deflected – 0x06 - NOTIFICATION_TYPE_INCOMING_CUG_CALL Incoming call is a CUG call – 0x07 - NOTIFICATION_TYPE_INCOMING_CALLS_BARRED Incoming calls are barred – 0x08 - NOTIFICATION_TYPE_INCOMING_FORWARDED_CALL Incoming call received is a forwarded call – 0x09 - NOTIFICATION_TYPE_INCOMING_DEFLECTED_CALL Incoming call is a deflected call – 0x0A - NOTIFICATION_TYPE_INCOMING_CALL_IS_FORWARDED Incoming call is forwarded to another user – 0x0B - NOTIFICATION_TYPE_UNCOND_CALL_FORWARD_ACTIVE Unconditional call forwarding is active – 0x0C - NOTIFICATION_TYPE_COND_CALL_FORWARD_ACTIVE Conditional call forwarding is active – 0x0D - NOTIFICATION_TYPE_CLIR_SUPPRESSION_REJECTED CLIR suppression is rejected – 0x0E - NOTIFICATION_TYPE_CALL_IS_ON_HOLD Call is put on hold at the remote party – 0x0F - NOTIFICATION_TYPE_CALL_IS_RETRIEVED Call is retrieved at the remote party from the hold state – 0x10 - NOTIFICATION_TYPE_CALL_IS_IN_MPTY Call is in a conference – 0x11 - NOTIFICATION_TYPE_INCOMING_CALL_IS_ECT Incoming call is an explicit call transfer • Bit to check in ParamPresenceMask - **1**
pCUGIndex	• The CUG Index used to indicate that the incoming/outgoing call is a CUG call. (optional, NULL when not present) Range: 0x00 to 0x7FFF. • Bit to check in ParamPresenceMask - **16**
pECTNum	• The ECT Number is used to indicate that the incoming call is an explicitly transferred call. (optional, NULL when not present) Refer ECTNum for details. • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

None

8.1507.2 Field Documentation

8.1507.2.1 uint8_t unpack_voice_SUPSNotificationCallback_ind_t::callID

8.1507.2.2 uint8_t unpack_voice_SUPSNotificationCallback_ind_t::notifType

8.1507.2.3 swi_uint256_t unpack_voice_SUPSNotificationCallback_ind_t::ParamPresenceMask

8.1507.2.4 uint16_t* unpack_voice_SUPSNotificationCallback_ind_t::pCUGIndex

8.1507.2.5 voice_ECTNum* unpack_voice_SUPSNotificationCallback_ind_t::pECTNum

8.1508 unpack_voice_USSDNotificationCallback_ind_t Struct Reference

Data Fields

- uint8_t notification_Type
- voice_USSDNotificationNetworkInfo USSDNotificationNetworkInfo
- swi_uint256_t ParamPresenceMask

8.1508.1 Detailed Description

Structure for storing the USSD notification indication parameters.

Parameters

notification_Type(mandatory)	Values: -0x01-FURTHER_USER_ACTION_NOT_REQUIRED -0x02-FURTHER_USER_ACTION_REQUIRED • Bit to check in ParamPresenceMask - **1**
USSDNotificationNetworkInfo(optional)	• USSD network info (See voice_USSDNotificationNetworkInfo) – Bit to check in ParamPresenceMask - **16**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1508.2 Field Documentation

8.1508.2.1 uint8_t unpack_voice_USSDNotificationCallback_ind_t::notification_Type

8.1508.2.2 swi_uint256_t unpack_voice_USSDNotificationCallback_ind_t::ParamPresenceMask

8.1508.2.3 voice_USSDNotificationNetworkInfo unpack_voice_USSDNotificationCallback_ind_t::USSDNotificationNetworkInfo

8.1509 unpack_voice_VoiceInfoRecCallback_ind_t Struct Reference

Data Fields

- uint8_t callID
- voice_signalInfo * pSignalInfo
- voice_callerIDInfo * pCallerIDInfo
- uint8_t * pDispInfo
- uint8_t * pExtDispInfo
- uint8_t * pCallerNameInfo
- uint8_t * pCallWaitInd
- voice_connectNumInfo * pConnectNumInfo
- voice_connectNumInfo * pCallingPartyInfo
- voice_calledPartyInfo * pCalledPartyInfo
- voice_redirNumInfo * pRedirNumInfo
- uint8_t * pCLIRCause
- voice_NSSAudioCtrl * pNSSAudioCtrl
- uint8_t * pNSSRelease
- voice_lineCtrlInfo * pLineCtrlInfo
- voice_extDispRecInfo * pExtDispRecInfo
- swi_uint256_t ParamPresenceMask

8.1509.1 Detailed Description

This structure contains Voice record Information

Parameters

callID	[Mandatory] • Call identifier for the call. • Bit to check in ParamPresenceMask - **1**
pSignalInfo[-Optional]	• Signal Information • See voice_signalInfo for more information • Bit to check in ParamPresenceMask - **16**
pCallerIDInfo[-Optional]	• Caller ID Information • See voice_callerIDInfo for more information • Bit to check in ParamPresenceMask - **17**
pDispInfo[-Optional]	• Display Information • Bit to check in ParamPresenceMask - **18**
pExtDispInfo[-Optional]	• Extended Display Information • Bit to check in ParamPresenceMask - **19**
pCallerName-Info[Optional]	• Caller Name Information • Bit to check in ParamPresenceMask - **20**

pCallWaitInd[-Optional]	• Call Waiting Indicator • Bit to check in ParamPresenceMask - **21**
pConnectNum-Info[Optional]	• Connected Number Information • see voice_connectNumInfo for more information • Bit to check in ParamPresenceMask - **22**
pCallingParty-Info[Optional]	• Calling Party Number Information • This structure is having exactly same elements as connectNumInfo • see voice_connectNumInfo for more information • Bit to check in ParamPresenceMask - **23**
pCalledParty-Info[Optional]	• Called Party Number Information • see voice_calledPartyInfo for more information • Bit to check in ParamPresenceMask - **24**
pRedirNumInfo[-Optional]	• Redirecting Number Information • see voice_redirNumInfo for more information • Bit to check in ParamPresenceMask - **25**
pCLIRCause[-Optional]	• National Supplementary Services - CLIR • see voice_NSSAudioCtrl for more information • Bit to check in ParamPresenceMask - **26**
pNSSAudioCtrl[-Optional]	• National Supplementary Services - Audio Control • Bit to check in ParamPresenceMask - **27**
pNSSRelease[-Optional]	• National Supplementary Services - Release • Bit to check in ParamPresenceMask - **28**
pLineCtrlInfo[-Optional]	• Line Control Information • see voice_lineCtrlInfo for more information • Bit to check in ParamPresenceMask - **29**
pExtDispRec-Info[Optional]	• Extended Display Record Information • see voice_extDispRecInfo for more information • Bit to check in ParamPresenceMask - **30**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1509.2 Field Documentation

8.1509.2.1 uint8_t unpack_voice_VoiceInfoRecCallback_ind_t::callID

8.1509.2.2 swi_uint256_t unpack_voice_VoiceInfoRecCallback_ind_t::ParamPresenceMask

8.1509.2.3 voice_calledPartyInfo* unpack_voice_VoiceInfoRecCallback_ind_t::pCalledPartyInfo

8.1509.2.4 voice_callerIDInfo* unpack_voice_VoiceInfoRecCallback_ind_t::pCallerIDInfo

8.1509.2.5 uint8_t* unpack_voice_VoiceInfoRecCallback_ind_t::pCallerNameInfo

8.1509.2.6 voice_connectNumInfo* unpack_voice_VoiceInfoRecCallback_ind_t::pCallingPartyInfo

8.1509.2.7 uint8_t* unpack_voice_VoiceInfoRecCallback_ind_t::pCallWaitInd

8.1509.2.8 uint8_t* unpack_voice_VoiceInfoRecCallback_ind_t::pCLIRCause

8.1509.2.9 voice_connectNumInfo* unpack_voice_VoiceInfoRecCallback_ind_t::pConnectNumInfo

8.1509.2.10 uint8_t* unpack_voice_VoiceInfoRecCallback_ind_t::pDispInfo

8.1509.2.11 uint8_t* unpack_voice_VoiceInfoRecCallback_ind_t::pExtDispInfo

8.1509.2.12 voice_extDispRecInfo* unpack_voice_VoiceInfoRecCallback_ind_t::pExtDispRecInfo

8.1509.2.13 voice_lineCtrlInfo* unpack_voice_VoiceInfoRecCallback_ind_t::pLineCtrlInfo

8.1509.2.14 voice_NSSAudioCtrl* unpack_voice_VoiceInfoRecCallback_ind_t::pNSSAudioCtrl

8.1509.2.15 uint8_t* unpack_voice_VoiceInfoRecCallback_ind_t::pNSSRelease

8.1509.2.16 voice_redirNumInfo* unpack_voice_VoiceInfoRecCallback_ind_t::pRedirNumInfo

8.1509.2.17 voice_signalInfo* unpack_voice_VoiceInfoRecCallback_ind_t::pSignalInfo

8.1510 unpack_voice_voicePrivacyChangeCallback_ind_t Struct Reference

Data Fields

- uint8_t callID
- uint8_t voicePrivacy
- swi_uint256_t ParamPresenceMask

8.1510.1 Detailed Description

Contains the parameters passed for voice privacy change indication

Parameters

callID	• Unique identifier of the call for which the voice privacy is applicable. (mandatory) • Bit to check in ParamPresenceMask - **1**

voicePrivacy	• Voice Privacy (mandatory) – 0x00 - VOICE_PRIVACY_STANDARD - Standard privacy – 0x01 - VOICE_PRIVACY_ENHANCED - Enhanced privacy • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

None

8.1510.2 Field Documentation

8.1510.2.1 uint8_t unpack_voice_voicePrivacyChangeCallback_ind_t::callID

8.1510.2.2 swi_uint256_t unpack_voice_voicePrivacyChangeCallback_ind_t::ParamPresenceMask

8.1510.2.3 uint8_t unpack_voice_voicePrivacyChangeCallback_ind_t::voicePrivacy

8.1511 unpack_wds_DHCPv4ClientLease_ind_t Struct Reference

Data Fields

- wds_DHCPProfileIdTlv ProfileIdTlv
- wds_DHCPLeaseStateTlv DHCPv4LeaseStateTlv
- wds_IPv4AdTlv IPv4AddrTlv
- wds_DHCPLeaseOptTlv DHCPv4LeaseOptTlv
- swi_uint256_t ParamPresenceMask

8.1511.1 Detailed Description

This structure contains DHCP IPv4 client lease information

Parameters

ProfileIdTlv	profile identifier information, see wds_DHCPProfileIdTlv for more details • Bit to check in ParamPresenceMask - **1**
DHCPv4Lease-StateTlv	lease state, see wds_DHCPLeaseStateTlv for more details • Bit to check in ParamPresenceMask - **2**
IPv4AddrTlv	IPv4 address, see wds_IPv4AdTlv for more details • Bit to check in ParamPresenceMask - **16**
DHCPv4Lease-OptTlv	DHCP lease option, see wds_DHCPLeaseOptTlv for more details • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1511.2 Field Documentation

8.1511.2.1 wds_DHCPLeaseOptTlv unpack_wds_DHCPv4ClientLease_ind_t::DHCPv4LeaseOptTlv

8.1511.2.2 wds_DHCPLeaseStateTlv unpack_wds_DHCPv4ClientLease_ind_t::DHCPv4LeaseStateTlv

8.1511.2.3 wds_IPv4AdTlv unpack_wds_DHCPv4ClientLease_ind_t::IPv4AddrTlv

8.1511.2.4 swi_uint256_t unpack_wds_DHCPv4ClientLease_ind_t::ParamPresenceMask

8.1511.2.5 wds_DHCPProfileIdTlv unpack_wds_DHCPv4ClientLease_ind_t::ProfileIdTlv

8.1512 unpack_wds_GetAutoconnect_t Struct Reference

Data Fields

- uint32_t * psetting
- swi_uint256_t ParamPresenceMask

8.1512.1 Detailed Description

auto connect data session setting parameter.

Parameters

pSetting	• NDIS auto connect setting – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1512.2 Field Documentation

8.1512.2.1 swi_uint256_t unpack_wds_GetAutoconnect_t::ParamPresenceMask

8.1512.2.2 uint32_t* unpack_wds_GetAutoconnect_t::psetting

8.1513 unpack_wds_GetByteTotals_t Struct Reference

Data Fields

- uint64_t * pTXTotalBytes
- uint64_t * pRXTotalBytes
- swi_uint256_t ParamPresenceMask

8.1513.1 Detailed Description

This structure contains unpack get byte totals information.

Parameters

pTXTotalBytes	• Bytes transmitted without error • Bit to check in ParamPresenceMask - **25**
pRXTotalBytes	• Bytes received without error • Bit to check in ParamPresenceMask - **26**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1513.2 Field Documentation

8.1513.2.1 swi_uint256_t unpack_wds_GetByteTotals_t::ParamPresenceMask

8.1513.2.2 uint64_t* unpack_wds_GetByteTotals_t::pRXTotalBytes

8.1513.2.3 uint64_t* unpack_wds_GetByteTotals_t::pTXTotalBytes

8.1514 unpack_wds_GetConnectionRate_t Struct Reference

Data Fields

- uint32_t currentChannelTXRate
- uint32_t currentChannelRXRate
- uint32_t maxChannelTXRate
- uint32_t maxChannelRXRate
- swi_uint256_t ParamPresenceMask

8.1514.1 Detailed Description

This structure contains unpack get connection rate information.

Parameters

currentChannel-TXRate	• Current channel Tx rate (in bps) • Bit to check in ParamPresenceMask - **1**
currentChannel-RXRate	• Current channel Rx rate (in bps) • Bit to check in ParamPresenceMask - **1**
maxChannelTX-Rate	• Maximum Tx rate (bps) that may be assigned to device by serving system. • Bit to check in ParamPresenceMask - **1**
maxChannelRX-Rate	• Maximum Rx rate (bps) that may be assigned to device by serving system. • Bit to check in ParamPresenceMask - **1**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1514.2 Field Documentation

8.1514.2.1 uint32_t unpack_wds_GetConnectionRate_t::currentChannelRXRate

8.1514.2.2 uint32_t unpack_wds_GetConnectionRate_t::currentChannelTXRate

8.1514.2.3 uint32_t unpack_wds_GetConnectionRate_t::maxChannelRXRate

8.1514.2.4 uint32_t unpack_wds_GetConnectionRate_t::maxChannelTXRate

8.1514.2.5 swi_uint256_t unpack_wds_GetConnectionRate_t::ParamPresenceMask

8.1515 unpack_wds_GetDataBearerTechnology_t Struct Reference

Data Fields

- uint32_t * pDataBearer
- swi_uint256_t ParamPresenceMask

8.1515.1 Detailed Description

This structure contains unpack get data bearer technology information.

Parameters

pDataBearer[OUT]	• Data bearer technology – 0x01 - CDMA2000 1x – 0x02 - CDMA 1xEV-DO Rev 0 – 0x03 - GSM – 0x04 - UMTS – 0x05 - CDMA2000 HRPD (1xEV-DO Rev A) – 0x06 - EDGE – 0x07 - HSDPA AND WCDMA – 0x08 - WCDMA AND HSUPA – 0x09 - HSDPA AND HSUPA – 0x0A - LTE – 0x0B - CDMA2000 EHRPD – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA – 0x10 - HSDPA+ and 64QAM – 0x11 - HSDPA+, 64QAM and HSUPA – 0x12 - TDSCDMA – 0x13 - TDSCDMA and HSDPA – 0xFF - Unknown • Bit to check in ParamPresenceMask - **1**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1515.2 Field Documentation

8.1515.2.1 swi_uint256_t unpack_wds_GetDataBearerTechnology_t::ParamPresenceMask

8.1515.2.2 uint32_t* unpack_wds_GetDataBearerTechnology_t::pDataBearer

8.1516 unpack_wds_GetDefaultProfile_t Struct Reference

Data Fields

- uint32_t pdptype
- uint32_t ipaddr
- uint32_t pridns
- uint32_t secdns
- uint16_t ipaddrv6
- uint16_t pridnsv6
- uint16_t secdnsv6
- uint32_t auth
- uint8_t namesize
- int8_t name [255]
- uint8_t apnsize
- int8_t apnname [255]

- uint8_t usersize
- int8_t username [255]
- swi_uint256_t ParamPresenceMask

8.1516.1 Detailed Description

Reads the default profile settings from the device. The default profile is used to establish an auto connect data session.

Parameters

pdptype	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6 • Bit to check in ParamPresenceMask - **17**
ipaddr	• Preferred IPv4 address to be assigned to device • Bit to check in ParamPresenceMask - **30**
pridns	• Primary DNS IPv4 address preference • Bit to check in ParamPresenceMask - **21**
secdns	• Secondary DNS IPv4 address preference • Bit to check in ParamPresenceMask - **22**
ipaddrv6	• Preferred IPv6 address to be assigned to device • Bit to check in ParamPresenceMask - **143**
pridnsv6	• Primary DNS Pv6 address preference • Bit to check in ParamPresenceMask - **143**
secdnsv6	• Secondary DNS IPv6 address preference • Bit to check in ParamPresenceMask - **143**

auth	• Bitmap that indicates authentication algorithm preference – 0x00000001 - PAP preference * 0 - Never performed * 1 - May be performed – 0x00000002 - CHAP preference * 0 - Never performed * 1 - May be performed – All other bits are reserved and must be set to 0 – If more than 1 bit is set, then device decides which authentication procedure is performed while setting up data session e.g. the device may have a policy to select the most secure authentication mechanism. • Bit to check in ParamPresenceMask - **29**
namesize	• Maximum number of characters (including NULL terminator) that profile name array can contain. • Bit to check in ParamPresenceMask - **16**
name	• Profile name • Bit to check in ParamPresenceMask - **16**
apnsize	• Maximum number of characters (including NULL terminator) that APN name array can contain • Bit to check in ParamPresenceMask - **20**
apnname	• Access point name. NULL-terminated string parameter that is a logical name used to select GGSN and external packet data network. • If value is NULL or omitted, then subscription default value will be requested. • Bit to check in ParamPresenceMask - **20**
usersize	• Maximum number of characters (including NULL terminator) that username array can contain. • Bit to check in ParamPresenceMask - **27**
username	• Username used during network authentication • Bit to check in ParamPresenceMask - **27**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1516.2 Field Documentation

8.1516.2.1 int8_t unpack_wds_GetDefaultProfile_t::apnname[255]

8.1516.2.2 uint8_t unpack_wds_GetDefaultProfile_t::apnsize

8.1516.2.3 uint32_t unpack_wds_GetDefaultProfile_t::auth

8.1516.2.4 uint32_t unpack_wds_GetDefaultProfile_t::ipaddr

8.1516.2.5 uint16_t unpack_wds_GetDefaultProfile_t::ipaddrv6

8.1516.2.6 int8_t unpack_wds_GetDefaultProfile_t::name[255]

8.1516.2.7 uint8_t unpack_wds_GetDefaultProfile_t::namesize

8.1516.2.8 swi_uint256_t unpack_wds_GetDefaultProfile_t::ParamPresenceMask

8.1516.2.9 uint32_t unpack_wds_GetDefaultProfile_t::pdptype

8.1516.2.10 uint32_t unpack_wds_GetDefaultProfile_t::pridns

8.1516.2.11 uint16_t unpack_wds_GetDefaultProfile_t::pridnsv6

8.1516.2.12 uint32_t unpack_wds_GetDefaultProfile_t::secdns

8.1516.2.13 uint16_t unpack_wds_GetDefaultProfile_t::secdnsv6

8.1516.2.14 int8_t unpack_wds_GetDefaultProfile_t::username[255]

8.1516.2.15 uint8_t unpack_wds_GetDefaultProfile_t::usersize

8.1517 unpack_wds_GetDefaultProfileNum_t Struct Reference

Data Fields

- uint8_t index
- swi_uint256_t ParamPresenceMask

8.1517.1 Detailed Description

This structure contains unpack Get Default Profile Number information.

Parameters

index	profile index • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1517.2 Field Documentation

8.1517.2.1 uint8_t unpack_wds_GetDefaultProfileNum_t::index

8.1517.2.2 swi_uint256_t unpack_wds_GetDefaultProfileNum_t::ParamPresenceMask

8.1518 unpack_wds_GetDormancyState_t Struct Reference

Data Fields

- uint32_t dormancyState
- swi_uint256_t ParamPresenceMask

8.1518.1 Detailed Description

This structure contains unpack get dormancy state information.

Parameters

dormancyState	• Dormancy state of current packet data session – 1 - Traffic channel dormant – 2 - Traffic channel active • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1518.2 Field Documentation

8.1518.2.1 uint32_t unpack_wds_GetDormancyState_t::dormancyState

8.1518.2.2 swi_uint256_t unpack_wds_GetDormancyState_t::ParamPresenceMask

8.1519 unpack_wds_GetLastMobileIPError_t Struct Reference

Data Fields

- uint32_t error
- swi_uint256_t ParamPresenceMask

8.1519.1 Detailed Description

structure to store last mobile IP error.

Parameters

error	• Status of last MIP call (or attempt) – Zero - Success – NonZero - Error code See qaGobiApiTableCallEndReasons.h for Mobile IP Error codes • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1519.2 Field Documentation

8.1519.2.1 uint32_t unpack_wds_GetLastMobileIPError_t::error

8.1519.2.2 swi_uint256_t unpack_wds_GetLastMobileIPError_t::ParamPresenceMask

8.1520 unpack_wds_GetMobileIP_t Struct Reference

Data Fields

- uint32_t mipMode
- swi_uint256_t ParamPresenceMask

8.1520.1 Detailed Description

This structure contains unpack get mobile IP information.

Parameters

mipMode	• Mobile IP setting – 0 - Mobile IP off (simple IP only) – 1 - Mobile IP preferred – 2 - Mobile IP only • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1520.2 Field Documentation

8.1520.2.1 uint32_t unpack_wds_GetMobileIP_t::mipMode

8.1520.2.2 swi_uint256_t unpack_wds_GetMobileIP_t::ParamPresenceMask

8.1521 unpack_wds_GetMobileIPProfile_t Struct Reference

Data Fields

- uint8_t enabled
- uint32_t address
- uint32_t primaryHA
- uint32_t secondaryHA
- uint8_t revTunneling
- uint8_t naiSize
- int8_t NAI [255]
- uint32_t HASPI
- uint32_t AAASPI
- uint32_t HAState
- uint32_t AAAState
- swi_uint256_t ParamPresenceMask

8.1521.1 Detailed Description

This structure contains unpack get mobile IP profile information.

Parameters

enabled	• Profile enabled: – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **16**
address	• Home IPv4 address: • Bit to check in ParamPresenceMask - **17**
primaryHA	• Primary home agent IPv4 address • Bit to check in ParamPresenceMask - **18**
secondaryHA	• Secondary home agent IPv4 address • Bit to check in ParamPresenceMask - **19**
revTunneling	• Reverse tunneling enabled – 0 - Disabled – 1 - Enabled • Bit to check in ParamPresenceMask - **20**
naiSize	• The maximum number of characters (including NULL terminator) that the NAI array can contain. • Bit to check in ParamPresenceMask - **21**
NAI	• Network access identifier string • Bit to check in ParamPresenceMask - **21**
HASPI	• Home agent security parameter index • Bit to check in ParamPresenceMask - **22**
AAASPI	• AAA server security parameter index • Bit to check in ParamPresenceMask - **23**
HAState	• Home agent key state – 0 - Unset – 1 - Set, default value – 2 - Set, modified from default – 3 - 0xFFFFFFFF - Unknown • Bit to check in ParamPresenceMask - **26**

AAAState	• AAA key state – 0 - Unset – 1 - Set, default value – 2 - Set, modified from default – 3 - 0xFFFFFFFF - Unknown • Bit to check in ParamPresenceMask - **27**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1521.2 Field Documentation

8.1521.2.1 uint32_t unpack_wds_GetMobileIPProfile_t::AAASPI

8.1521.2.2 uint32_t unpack_wds_GetMobileIPProfile_t::AAAState

8.1521.2.3 uint32_t unpack_wds_GetMobileIPProfile_t::address

8.1521.2.4 uint8_t unpack_wds_GetMobileIPProfile_t::enabled

8.1521.2.5 uint32_t unpack_wds_GetMobileIPProfile_t::HASPI

8.1521.2.6 uint32_t unpack_wds_GetMobileIPProfile_t::HAState

8.1521.2.7 int8_t unpack_wds_GetMobileIPProfile_t::NAI[255]

8.1521.2.8 uint8_t unpack_wds_GetMobileIPProfile_t::naiSize

8.1521.2.9 swi_uint256_t unpack_wds_GetMobileIPProfile_t::ParamPresenceMask

8.1521.2.10 uint32_t unpack_wds_GetMobileIPProfile_t::primaryHA

8.1521.2.11 uint8_t unpack_wds_GetMobileIPProfile_t::revTunneling

8.1521.2.12 uint32_t unpack_wds_GetMobileIPProfile_t::secondaryHA

8.1522 unpack_wds_GetPacketStatistics_t Struct Reference

Data Fields

- uint32_t * pTXPacketSuccesses
- uint32_t * pRXPacketSuccesses
- uint32_t * pTXPacketErrors
- uint32_t * pRXPacketErrors
- uint32_t * pTXPacketOverflows
- uint32_t * pRXPacketOverflows
- uint64_t * pTXOkBytesCount
- uint64_t * pRXOkBytesCount
- uint64_t * pTXOKBytesLastCall
- uint64_t * pRXOKBytesLastCall
- uint32_t * pTXDroppedCount

- uint32_t * pRXDroppedCount
- swi_uint256_t ParamPresenceMask

8.1522.1 Detailed Description

This structure contains unpack get packet statistics information.

Parameters

pTXPacket-Successes	• No of transmitted Packets without error. • Bit to check in ParamPresenceMask - **16**
pRXPacket-Successes	• No of received Packets without error. • Bit to check in ParamPresenceMask - **17**
pTXPacketErrors	• Number of outgoing packets with framing errors. • Bit to check in ParamPresenceMask - **18**
pRXPacket-Errors	• Number of incoming packets with framing errors. • Bit to check in ParamPresenceMask - **19**
pTXPacket-Overflows	• Number of packets dropped because Tx buffer overflowed (out of memory). • Bit to check in ParamPresenceMask - **20**
pRXPacket-Overflows	• Number of packets dropped because Rx buffer overflowed (out of memory). • Bit to check in ParamPresenceMask - **21**
pTXOkBytes-Count	• Number of bytes transmitted without error. • Bit to check in ParamPresenceMask - **25**
pRXOkBytes-Count	• Number of bytes received without error. • Bit to check in ParamPresenceMask - **26**
pTXOKBytes-LastCall	• Number of bytes transmitted without error during the last data call (0 if no call was made earlier). Returned only if not in a call, and when the previous call was made using RmNet (for any devices that support • Bit to check in ParamPresenceMask - **27**
pRXOKBytes-LastCall	• Number of bytes received without error during the last data call (0 if no call was made earlier). Returned only if not in a call, and when the previous call was made using RmNet (for any devices that support • Bit to check in ParamPresenceMask - **28**

pTXDropped-Count	• Number of outgoing packets dropped. • Bit to check in ParamPresenceMask - **29**
pRXDropped-Count	• Number of incoming packets dropped. • Bit to check in ParamPresenceMask - **30**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1522.2 Field Documentation

8.1522.2.1 swi_uint256_t unpack_wds_GetPacketStatistics_t::ParamPresenceMask

8.1522.2.2 uint32_t* unpack_wds_GetPacketStatistics_t::pRXDroppedCount

8.1522.2.3 uint64_t* unpack_wds_GetPacketStatistics_t::pRXOkBytesCount

8.1522.2.4 uint64_t* unpack_wds_GetPacketStatistics_t::pRXOKBytesLastCall

8.1522.2.5 uint32_t* unpack_wds_GetPacketStatistics_t::pRXPacketErrors

8.1522.2.6 uint32_t* unpack_wds_GetPacketStatistics_t::pRXPacketOverflows

8.1522.2.7 uint32_t* unpack_wds_GetPacketStatistics_t::pRXPacketSuccesses

8.1522.2.8 uint32_t* unpack_wds_GetPacketStatistics_t::pTXDroppedCount

8.1522.2.9 uint64_t* unpack_wds_GetPacketStatistics_t::pTXOkBytesCount

8.1522.2.10 uint64_t* unpack_wds_GetPacketStatistics_t::pTXOKBytesLastCall

8.1522.2.11 uint32_t* unpack_wds_GetPacketStatistics_t::pTXPacketErrors

8.1522.2.12 uint32_t* unpack_wds_GetPacketStatistics_t::pTXPacketOverflows

8.1522.2.13 uint32_t* unpack_wds_GetPacketStatistics_t::pTXPacketSuccesses

8.1523 unpack_wds_GetPacketStatus_t Struct Reference

Data Fields

- uint32_t tXPacketSuccesses
- uint32_t rXPacketSuccesses
- uint32_t tXPacketErrors
- uint32_t rXPacketErrors
- uint32_t tXPacketOverflows
- uint32_t rXPacketOverflows
- uint64_t tXOkBytesCount
- uint64_t rXOkBytesCount
- uint64_t tXOKBytesLastCall

- uint64_t rXOKBytesLastCall
- uint32_t tXDroppedCount
- uint32_t rXDroppedCount
- swi_uint256_t ParamPresenceMask

8.1523.1 Detailed Description

Returns the packet data transfer statistics since the start of the current packet data.

Parameters

tXPacket-Successes	• No. of packets transmitted without error • Bit to check in ParamPresenceMask - **16**
rXPacket-Successes	• No. of packets received without error • Bit to check in ParamPresenceMask - **17**
tXPacketErrors	• No. of outgoing packets with framing errors • Bit to check in ParamPresenceMask - **18**
rXPacketErrors	• No. of incoming packets with framing errors • Bit to check in ParamPresenceMask - **19**
txPacket-Overflows	• Number of packets dropped because Tx buffer overflowed • Bit to check in ParamPresenceMask - **20**
rxPacket-Overflows	• Number of packets dropped because Rx buffer overflowed • Bit to check in ParamPresenceMask - **21**
txOkBytesCount	• No of bytes transmitted without error. • Bit to check in ParamPresenceMask - **25**
rxOkBytesCount	• No of bytes received without error. • Bit to check in ParamPresenceMask - **26**
txOKBytesLast-Call	• No of bytes transmitted without error during the last data call (0 if no call was made earlier). Returned only if not in a call, and when the previous call was made using RmNet (for any devices that support • Bit to check in ParamPresenceMask - **27**
rxOKBytesLast-Call	• Number of bytes received without error during the last data call (0 if no call was made earlier). Returned only if not in a call, and when the previous call was made using RmNet (for any devices that support • Bit to check in ParamPresenceMask - **28**

txDroppedCount	• Number of outgoing packets dropped. • Bit to check in ParamPresenceMask - **29**
rxDroppedCount	• Number of incoming packets dropped. • Bit to check in ParamPresenceMask - **30**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1523.2 Field Documentation

8.1523.2.1 swi_uint256_t unpack_wds_GetPacketStatus_t::ParamPresenceMask

8.1523.2.2 uint32_t unpack_wds_GetPacketStatus_t::rXDroppedCount

8.1523.2.3 uint64_t unpack_wds_GetPacketStatus_t::rXOkBytesCount

8.1523.2.4 uint64_t unpack_wds_GetPacketStatus_t::rXOKBytesLastCall

8.1523.2.5 uint32_t unpack_wds_GetPacketStatus_t::rXPacketErrors

8.1523.2.6 uint32_t unpack_wds_GetPacketStatus_t::rXPacketOverflows

8.1523.2.7 uint32_t unpack_wds_GetPacketStatus_t::rXPacketSuccesses

8.1523.2.8 uint32_t unpack_wds_GetPacketStatus_t::tXDroppedCount

8.1523.2.9 uint64_t unpack_wds_GetPacketStatus_t::tXOkBytesCount

8.1523.2.10 uint64_t unpack_wds_GetPacketStatus_t::tXOKBytesLastCall

8.1523.2.11 uint32_t unpack_wds_GetPacketStatus_t::tXPacketErrors

8.1523.2.12 uint32_t unpack_wds_GetPacketStatus_t::tXPacketOverflows

8.1523.2.13 uint32_t unpack_wds_GetPacketStatus_t::tXPacketSuccesses

8.1524 unpack_wds_GetSessionDuration_t Struct Reference

Data Fields

- uint64_t callDuration
- swi_uint256_t ParamPresenceMask

8.1524.1 Detailed Description

This structure contains unpack get session duration information.

Parameters

callDuration	• Duration of the current packet session in milliseconds • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1524.2 Field Documentation

8.1524.2.1 uint64_t unpack_wds_GetSessionDuration_t::callDuration

8.1524.2.2 swi_uint256_t unpack_wds_GetSessionDuration_t::ParamPresenceMask

8.1525 unpack_wds_GetSessionState_t Struct Reference

Data Fields

- uint32_t connectionStatus
- swi_uint256_t ParamPresenceMask

8.1525.1 Detailed Description

This structure contains unpack get session state information.

Parameters

connection-Status	- state of the current packet data session. • 1 - Disconnected. • 2 - Connected. • 3 - Suspended. • 4 - Authenticating. • Bit to check in ParamPresenceMask - **1**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1525.2 Field Documentation

8.1525.2.1 uint32_t unpack_wds_GetSessionState_t::connectionStatus

8.1525.2.2 swi_uint256_t unpack_wds_GetSessionState_t::ParamPresenceMask

8.1526 unpack_wds_RMSetTransferStatistics_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1526.1 Detailed Description

This structure contains unpack fetch current data system transfer statistics information.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1526.2 Field Documentation

8.1526.2.1 swi_uint256_t unpack_wds_RMSetTransferStatistics_t::ParamPresenceMask

8.1527 unpack_wds_SetMobileIPProfile_t Struct Reference

Data Fields

- swi_uint256_t ParamPresenceMask

8.1527.1 Detailed Description

This structure contains set mobile IP profile information.

Parameters

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1527.2 Field Documentation

8.1527.2.1 swi_uint256_t unpack_wds_SetMobileIPProfile_t::ParamPresenceMask

8.1528 unpack_wds_SLQSCreateProfile_t Struct Reference

Data Fields

- PackCreateProfileOut * pCreateProfileOut
- uint8_t * pProfileID
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1528.1 Detailed Description

This structure contains unpack create profile information.

Parameters

pCreateProfile-Out	• SLQS Create profile Information • See PackCreateProfileOut

pProfileID	• SLQS profile identifier information
TIvresult	• TLV present flag, TURE if presented, otherwise FALSE
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1528.2 Field Documentation

8.1528.2.1 swi_uint256_t unpack_wds_SLQSCreateProfile_t::ParamPresenceMask

8.1528.2.2 PackCreateProfileOut* unpack_wds_SLQSCreateProfile_t::pCreateProfileOut

8.1528.2.3 uint8_t* unpack_wds_SLQSCreateProfile_t::pProfileID

8.1528.2.4 uint16_t unpack_wds_SLQSCreateProfile_t::TIvresult

8.1529 unpack_wds_SLQSDeleteProfile_t Struct Reference

Data Fields

- uint16_t extendedErrorCode
- swi_uint256_t ParamPresenceMask

8.1529.1 Detailed Description

This structure contains unpack delete profile information.

Parameters

extendedError-Code[OUT]	• The extended error code received from DS Profile subsystem of type eWDS_ERR_PROFILE_-REG_xxx. • Error code will only will be present if error code eQCWWAN_ERR_QMI_EXTENDED_INTERN-AL is returned by device. • See qm_wds_ds_profile_extended_err_codes enum in qmerrno.h for received error description. • Bit to check in ParamPresenceMask - **224**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1529.2 Field Documentation

8.1529.2.1 uint16_t unpack_wds_SLQSDeleteProfile_t::extendedErrorCode

8.1529.2.2 swi_uint256_t unpack_wds_SLQSDeleteProfile_t::ParamPresenceMask

8.1530 unpack_wds_SLQSDUNCallInfoCallBack_ind_t Struct Reference

Data Fields

- wds_ConnStatusTlv CSTlv
- wds_LastMdmCallEndRsnTlv LMCERTlv
- wds_TXBytesOKTlv TXBOTlv
- wds_RXBytesOKTlv RXBOTlv
- wds_DormStatTlv DSTlv
- wds_DataBearTechTlv DBTTlv
- wds_ChannelRateTlv CRTlv
- swi_uint256_t ParamPresenceMask

8.1530.1 Detailed Description

Structure used to store Reg Mgr Config Indication Parameters.

Parameters

CSTlv	• Connection status tlv • See wds_ConnStatusTlv for more information • Bit to check in ParamPresenceMask - **16**
LMCERTlv	• last modem call end reason tlv • see wds_LastMdmCallEndRsnTlv for more information • Bit to check in ParamPresenceMask - **17**
TXBOTlv	• Tx bytes OK tlv • see wds_TXBytesOKTlv for more information • Bit to check in ParamPresenceMask - **18**
RXBOTlv	• Rx bytes OK tlv • see wds_RXBytesOKTlv for more information • Bit to check in ParamPresenceMask - **19**
DSTlv	• Dormancy status tlv • see wds_DormStatTlv for more information • Bit to check in ParamPresenceMask - **20**
DBTTlv	• Data bear technology tlv • see wds_DataBearTechTlv for more information • Bit to check in ParamPresenceMask - **21**
CRTlv	• Channel rate Tlv • see wds_ChannelRateTlv for more information • Bit to check in ParamPresenceMask - **22**

ParamPresence-Mask	• bitmask representation to indicate valid parameters.

Note

: None

8.1530.2 Field Documentation

8.1530.2.1 wds_ChannelRateTlv unpack_wds_SLQSDUNCallInfoCallBack_ind_t::CRTlv

8.1530.2.2 wds_ConnStatusTlv unpack_wds_SLQSDUNCallInfoCallBack_ind_t::CSTlv

8.1530.2.3 wds_DataBearTechTlv unpack_wds_SLQSDUNCallInfoCallBack_ind_t::DBTTlv

8.1530.2.4 wds_DormStatTlv unpack_wds_SLQSDUNCallInfoCallBack_ind_t::DSTlv

8.1530.2.5 wds_LastMdmCallEndRsnTlv unpack_wds_SLQSDUNCallInfoCallBack_ind_t::LMCERTlv

8.1530.2.6 swi_uint256_t unpack_wds_SLQSDUNCallInfoCallBack_ind_t::ParamPresenceMask

8.1530.2.7 wds_RXBytesOKTlv unpack_wds_SLQSDUNCallInfoCallBack_ind_t::RXBOTlv

8.1530.2.8 wds_TXBytesOKTlv unpack_wds_SLQSDUNCallInfoCallBack_ind_t::TXBOTlv

8.1531 unpack_wds_SLQSGet3GPPConfigItem_t Struct Reference

Data Fields

- uint16_t LTEAttachProfile
- uint16_t profileList [5]
- uint8_t defaultPDNEnabled
- uint8_t _3gppRelease
- uint16_t LTEAttachProfileList [24]
- uint16_t LTEAttachProfileListLen
- swi_uint256_t ParamPresenceMask

8.1531.1 Detailed Description

This structure contains unpack get 3GPP configure item information.

Parameters

	LTEAttachProfile	• LTE Attach Profile – points to a single WORD Value indicating the attached LTE Profile – Optional parameter with possible values 1-16 (EM/MC73xx or earlier) • This setting is deprecated on MC/EM74xx • Bit to check in ParamPresenceMask - **16**

	profileList	Profile List • an array of 4 profile configurations • Each element points to a single WORD value indicating profile • Optional parameter with possible values – 1 - 16 (MC/EM73xx and before) – 1 - 24 (MC/EM74xx and onwards) • function SLQSGet3GPPConfigItem() returns a default value 255 if no 3gpp configuration is present • Bit to check in ParamPresenceMask - **17** • Note: the 5th entry is currently ignored, please set it to zero
`out`	*defaultPDN-Enabled*	• 0 - disabled • 1 - enabled • Bit to check in ParamPresenceMask - **18**
`out`	*_3gppRelease*	3GPP release • 0 - Release_99 • 1 - Release_5 • 2 - Release_6 • 3 - Release_7 • 4 - Release_8 • 5 - Release_9 (In 9x30 and toworads) • 6 - Release_10 (In 9x30 and toworads) • 7 - Release_11 (In 9x30 and toworads) • Bit to check in ParamPresenceMask - **19**
`out`	*LTEAttach-ProfileList*	• pointer to WORD array indiciating LTE Attach Profile List – Optional parameter – possible values: 1-24 – This setting is only supported for MC/EM74xx onwards – Please provide attach profiles in order of decreasing priority in this list. • Bit to check in ParamPresenceMask - **20**
`in,out`	*LTEAttach-ProfileListLen*	• Number of element in pLTEAttachProfileList – valid range: 1-24 – This setting is only supported for MC/EM74xx onwards • Bit to check in ParamPresenceMask - **20**
	ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1531.2 Field Documentation

8.1531.2.1 uint8_t unpack_wds_SLQSGet3GPPConfigItem_t::_3gppRelease

8.1531.2.2 uint8_t unpack_wds_SLQSGet3GPPConfigItem_t::defaultPDNEnabled

8.1531.2.3 uint16_t unpack_wds_SLQSGet3GPPConfigItem_t::LTEAttachProfile

8.1531.2.4 uint16_t unpack_wds_SLQSGet3GPPConfigItem_t::LTEAttachProfileList[24]

8.1531.2.5 uint16_t unpack_wds_SLQSGet3GPPConfigItem_t::LTEAttachProfileListLen

8.1531.2.6 swi_uint256_t unpack_wds_SLQSGet3GPPConfigItem_t::ParamPresenceMask

8.1531.2.7 uint16_t unpack_wds_SLQSGet3GPPConfigItem_t::profileList[5]

8.1532 unpack_wds_SLQSGetCurrDataSystemStat_t Struct Reference

Data Fields

- uint8_t prefNetwork
- uint8_t networkInfoLen
- currNetworkInfo currNetworkInfo [255]
- swi_uint256_t ParamPresenceMask

8.1532.1 Detailed Description

Data System Status

Parameters

prefNetwork	• Preferred Network • Values: – 0 - 3GPP – 1 - 3GPP2 • Bit to check in ParamPresenceMask - **16**
networkInfoLen	• As input parameter size assigned to next parameter i.e. network information • As output the actual number of network information elements returned by the device • Bit to check in ParamPresenceMask - **16**
currNetworkInfo	• Network information • See currNetworkInfo for more details • Bit to check in ParamPresenceMask - **16**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1532.2 Field Documentation

8.1532.2.1 currNetworkInfo unpack_wds_SLQSGetCurrDataSystemStat_t::currNetworkInfo[255]

8.1532.2.2 uint8_t unpack_wds_SLQSGetCurrDataSystemStat_t::networkInfoLen

8.1532.2.3 swi_uint256_t unpack_wds_SLQSGetCurrDataSystemStat_t::ParamPresenceMask

8.1532.2.4 uint8_t unpack_wds_SLQSGetCurrDataSystemStat_t::prefNetwork

8.1533 unpack_wds_SLQSGetCurrentChannelRate_t Struct Reference

Data Fields

- uint32_t current_channel_tx_rate
- uint32_t current_channel_rx_rate
- uint32_t max_channel_tx_rate
- uint32_t max_channel_rx_rate
- swi_uint256_t ParamPresenceMask

8.1533.1 Detailed Description

This structure contains unpack get current channel rate information.

Parameters

current_channel_tx_rate	• Current Channel Tx Rate. • Instantaneous channel Tx rate in bits per second. • In 9x15, this is the total current channel rate for all PDNs combined. • In 9x30 and later, this is the channel rate for a specific PDN. • Bit to check in ParamPresenceMask - **1**
current_channel_rx_rate	• Current Channel Rx Rate. • Instantaneous channel Rx rate in bits per second. • In 9x15, this is the total current channel rate for all PDNs combined. • In 9x30 and later, this is the channel rate for a specific PDN • Bit to check in ParamPresenceMask - **1**
max_channel_tx_rate	• Max Channel Tx Rate. • Maximum total Tx rate that modem is able to support in current serving system in bits per second. • In 9x15, this is a default hard coded value for the current serving system. • Bit to check in ParamPresenceMask - **1**
max_channel_rx_rate	• Max Channel Rx Rate. • Maximum total Rx rate that modem is able to support in current serving system in bits per second. • In 9x15, this is a default hard coded value for the current serving system. • Bit to check in ParamPresenceMask - **1**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1533.2 Field Documentation

8.1533.2.1 uint32_t unpack_wds_SLQSGetCurrentChannelRate_t::current_channel_rx_rate

8.1533.2.2 uint32_t unpack_wds_SLQSGetCurrentChannelRate_t::current_channel_tx_rate

8.1533.2.3 uint32_t unpack_wds_SLQSGetCurrentChannelRate_t::max_channel_rx_rate

8.1533.2.4 uint32_t unpack_wds_SLQSGetCurrentChannelRate_t::max_channel_tx_rate

8.1533.2.5 swi_uint256_t unpack_wds_SLQSGetCurrentChannelRate_t::ParamPresenceMask

8.1534 unpack_wds_SLQSGetDataBearerTechnology_t Struct Reference

Data Fields

- uint8_t dataBearerMask
- qmiWDSDataBearerTechnology curDataBearerTechnology
- qmiWDSDataBearerTechnology lastCallDataBearerTechnology
- swi_uint256_t ParamPresenceMask

8.1534.1 Detailed Description

Structure to hold the data bearer technology values

Parameters

dataBearerMask[OUT]	• This bit mask indicates if data bearer information for the current and/or last call has been received from the device. If a bit is set, then the information is available in the corresponding structure i.e. the one provided by the caller. Refer to liteQmiDataBearerMasks for bit-mask positions. • Bit to check in ParamPresenceMask - **1**
curDataBearerTechnology[OUT]	• current data bearer technology value. • See qmiWDSDataBearerTechnology • Bit to check in ParamPresenceMask - **1**
lastCallDataBearerTechnology[OUT]	• last call data bearer technology value. • See qmiWDSDataBearerTechnology – NULL if the parameter is not required • Bit to check in ParamPresenceMask - **16**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1534.2 Field Documentation

8.1534.2.1 qmiWDSDataBearerTechnology unpack_wds_SLQSGetDataBearerTechnology_t::curDataBearerTechnology

8.1534.2.2 uint8_t unpack_wds_SLQSGetDataBearerTechnology_t::dataBearerMask

8.1534.2.3 qmiWDSDataBearerTechnology unpack_wds_SLQSGetDataBearerTechnology_t::lastCallDataBearer-Technology

8.1534.2.4 swi_uint256_t unpack_wds_SLQSGetDataBearerTechnology_t::ParamPresenceMask

8.1535 unpack_wds_SLQSGetDUNCallInfo_t Struct Reference

Data Fields

- connectionStatus connectionStatus
- uint16_t callEndReason
- uint64_t txOKBytesCount
- uint64_t rxOKBytesCount
- uint8_t dormancyStatus
- uint8_t dataBearerTech
- dunchannelRate channelRate
- uint64_t lastCallTXOKBytesCnt
- uint64_t lastCallRXOKBytesCnt
- uint64_t mdmCallDurationActive
- uint8_t lastCallDataBearerTech
- swi_uint256_t ParamPresenceMask

8.1535.1 Detailed Description

This structure contains the DUN Call Info response parameters

Parameters

connection-Status	• See connectionStatus for more information • Bit to check in ParamPresenceMask - **16**
callEndReason	• Last modem call end reason • See qaGobiApiTableCallEndReasons.h for Call End Reason • Only valid if the last call made was DUN, else zero is returned • Bit to check in ParamPresenceMask - **17**
txOKBytesCount	• Number of bytes transmitted without error • Returned only if a data call is up • Bit to check in ParamPresenceMask - **18**
rxOKBytesCount	• Number of bytes received without error • Returned only if a data call is up • Bit to check in ParamPresenceMask - **19**

dormancyStatus	• Current traffic channel status • Returned if a data call is up – 0x01 - Traffic channel dormant – 0x02 - Traffic channel active • Bit to check in ParamPresenceMask - **20**
dataBearerTech	• Current data bearer technology • Returned only if a data call is up – 0x01 - cdma2000 1X – 0x02 - cdma2000 HRPD (1xEV-DO) – 0x03 - GSM – 0x04 - UMTS – 0x05 - cdma200 HRPD (1xEV-DO RevA) – 0x06 - EDGE – 0x07 - HSDPA and WCDMA – 0x08 - WCDMA and HSUPA – 0x09 - HSDPA and HSUPA – 0x0A - LTE – 0x0B - cdma2000 EHRPD – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA – 0x10 - HSDPA+ and 64QAM – 0x11 - HSDPA+, 64QAM and HSUPA – 0x12 - TDSCDMA – 0x13 - TDSCDMA and HSDPA • Bit to check in ParamPresenceMask - **21**
channelRate	• See dunchannelRate for more information • Bit to check in ParamPresenceMask - **22**
lastCallTXOK-BytesCnt	• Number of bytes transmitted without error during the last data call (0 if no call was made). • Return only if not in a call and the previous call was made using DUN. • Bit to check in ParamPresenceMask - **23**
lastCallRXOK-BytesCnt	• Number of bytes transmitted without error during the last data call (0 if no call was made). • Return only if not in a call and the previous call was made using DUN. • Bit to check in ParamPresenceMask - **24**

mdmCall-DurationActive	• Duration that the call is active in milliseconds • If the modem connection status is connected, this represents the active duration of the current DUN call • If the modem connection status is disconnected, this represents the duration of the last DUN call since the device was powered up (0 if no call has been made or if the last call was not DUN) • Bit to check in ParamPresenceMask - **25**
lastCallData-BearerTech	• Last Call Data Bearer Technology • Returned only if not in a call and when the previous call was made using DUN – 0x01 - cdma2000 1X – 0x02 - cdma2000 HRPD (1xEV-DO) – 0x03 - GSM – 0x04 - UMTS – 0x05 - cdma200 HRPD (1xEV-DO Rev A) – 0x06 - EDGE – 0x07 - HSDPA and WCDMA – 0x08 - WCDMA and HSUPA – 0x09 - HSDPA and HSUPA – 0x0A - LTE – 0x0B - cdma2000 EHRPD – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA – 0x10 - HSDPA+ and 64QAM – 0x11 - HSDPA+, 64QAM and HSUPA – 0x12 - TDSCDMA – 0x13 - TDSCDMA and HSDPA • Bit to check in ParamPresenceMask - **32**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1535.2 Field Documentation

8.1535.2.1 uint16_t unpack_wds_SLQSGetDUNCallInfo_t::callEndReason

8.1535.2.2 dunchannelRate unpack_wds_SLQSGetDUNCallInfo_t::channelRate

8.1535.2.3 connectionStatus unpack_wds_SLQSGetDUNCallInfo_t::connectionStatus

8.1535.2.4 uint8_t unpack_wds_SLQSGetDUNCallInfo_t::dataBearerTech

8.1535.2.5 uint8_t unpack_wds_SLQSGetDUNCallInfo_t::dormancyStatus

8.1535.2.6 uint8_t unpack_wds_SLQSGetDUNCallInfo_t::lastCallDataBearerTech

8.1535.2.7 uint64_t unpack_wds_SLQSGetDUNCallInfo_t::lastCallRXOKBytesCnt

8.1535.2.8 uint64_t unpack_wds_SLQSGetDUNCallInfo_t::lastCallTXOKBytesCnt

8.1535.2.9 uint64_t unpack_wds_SLQSGetDUNCallInfo_t::mdmCallDurationActive

8.1535.2.10 swi_uint256_t unpack_wds_SLQSGetDUNCallInfo_t::ParamPresenceMask

8.1535.2.11 uint64_t unpack_wds_SLQSGetDUNCallInfo_t::rxOKBytesCount

8.1535.2.12 uint64_t unpack_wds_SLQSGetDUNCallInfo_t::txOKBytesCount

8.1536 unpack_wds_SLQSGetProfileSettings_t Struct Reference

Data Fields

- UnPackGetProfileSettingOut * pProfileSettings
- uint8_t ProfileType
- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1536.1 Detailed Description

This structure contains the profile setting information of parameter pOutput for API unpack_wds_SLQSGetProfileSettings

Parameters

pProfileSettings	- Profile Settings
ProfileType	- Profile Type • 0 - Profile 3GPP • 1 - Profile 3GPP2
Tlvresult	- unpack Tlv Result.
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1536.2 Field Documentation

8.1536.2.1 swi_uint256_t unpack_wds_SLQSGetProfileSettings_t::ParamPresenceMask

8.1536.2.2 UnPackGetProfileSettingOut* unpack_wds_SLQSGetProfileSettings_t::pProfileSettings

8.1536.2.3 uint8_t unpack_wds_SLQSGetProfileSettings_t::ProfileType

8.1536.2.4 uint16_t unpack_wds_SLQSGetProfileSettings_t::Tlvresult

8.1537 unpack_wds_SLQSGetRuntimeSettings_t Struct Reference

Data Fields

- uint32_t IPv4
- uint8_t ProfileName [128]
- uint32_t PDPType

- uint8_t APNName [128]
- uint32_t PrimaryDNSV4
- uint32_t SecondaryDNSV4
- LibPackUMTSQoS UMTSGrantedQoS
- struct wds_GPRSQoS GPRSGrantedQoS
- uint8_t Username [128]
- uint32_t Authentication
- struct wds_ProfileIdentifier ProfileID
- uint32_t GWAddressV4
- uint32_t SubnetMaskV4
- uint8_t PCSCFAddrPCO
- struct wds_PCSCFIPv4ServerAddressList ServerAddrList
- struct wds_PCSCFFQDNAddressList PCSCFFQDNAddrList
- uint16_t PrimaryDNSV6 [8]
- uint16_t SecondaryDNSV6 [8]
- uint32_t Mtu
- struct wds_DomainNameList DomainList
- uint8_t IPFamilyPreference
- uint8_t IMCNflag
- uint16_t Technology
- struct wds_IPV6AddressInfo IPV6AddrInfo
- struct wds_IPV6GWAddressInfo IPV6GWAddrInfo
- swi_uint256_t ParamPresenceMask

8.1537.1 Detailed Description

This structure contains unpack get runtime settings information.

Parameters

IPv4	ipv4 address • Bit to check in ParamPresenceMask - **30**
ProfileName	profile name • Bit to check in ParamPresenceMask - **16**
PDPType	PDP type • Bit to check in ParamPresenceMask - **17**
APNName	APN name • Bit to check in ParamPresenceMask - **20**
PrimaryDNSV4	primary dns IPV4 • Bit to check in ParamPresenceMask - **21**
SecondaryDNS-V4	secondary dns IPV4 • Bit to check in ParamPresenceMask - **22**
UMTSGranted-QoS	UMTS Granted Qos • Bit to check in ParamPresenceMask - **23**
GPRSGranted-QoS	GPRS Granted QoS • Bit to check in ParamPresenceMask - **25**

Username	username for authentication process • Bit to check in ParamPresenceMask - **27**
Authentication	authentication for authentication process • Bit to check in ParamPresenceMask - **29**
ProfielID	profile ID • Bit to check in ParamPresenceMask - **31**
GWAddressV4	Gateway IPv4 • Bit to check in ParamPresenceMask - **32**
SubnetMaskV4	Subnet mask IPV4 • Bit to check in ParamPresenceMask - **33**
PCSCFAddrPCO	PCSCF address PCO • Bit to check in ParamPresenceMask - **34**
ServerAddrList	PCSCF server address list IPV4 • Bit to check in ParamPresenceMask - **35**
PCSCFFQDNAddrList	PCSCF FQDN address list IPV4 • Bit to check in ParamPresenceMask - **36**
PrimaryDNSV6	Primary DNS IPV6 • Bit to check in ParamPresenceMask - **39**
SecondryDNSV6	Secondry DNS IPV6 • Bit to check in ParamPresenceMask - **40**
Mtu	actual (runtime) Maximum Transfer Unit • Bit to check in ParamPresenceMask - **41**
DomainList	domain list • Bit to check in ParamPresenceMask - **42**
IPFamilyPreference	ip family preference, it could be IPV4 or IPV6 • Bit to check in ParamPresenceMask - **43**
IMCNflag	IM control flag, value: TRUE or FALSE • Bit to check in ParamPresenceMask - **44**
Technology	technology on which current packet data session is in progress • Values: – 32767 - CDMA – 32764 - UMTS – 30592 - EPC – 30584 - modem link local • Bit to check in ParamPresenceMask - **45**
IPV6AddrInfo	address information IPV6 • Bit to check in ParamPresenceMask - **37**

IPV6GWAddr-Info	gateway address information IPV6 • Bit to check in ParamPresenceMask - **38**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1537.2 Field Documentation

8.1537.2.1 uint8_t unpack_wds_SLQSGetRuntimeSettings_t::APNName[128]

8.1537.2.2 uint32_t unpack_wds_SLQSGetRuntimeSettings_t::Authentication

8.1537.2.3 struct wds_DomainNameList unpack_wds_SLQSGetRuntimeSettings_t::DomainList

8.1537.2.4 struct wds_GPRSQoS unpack_wds_SLQSGetRuntimeSettings_t::GPRSGrantedQoS

8.1537.2.5 uint32_t unpack_wds_SLQSGetRuntimeSettings_t::GWAddressV4

8.1537.2.6 uint8_t unpack_wds_SLQSGetRuntimeSettings_t::IMCNflag

8.1537.2.7 uint8_t unpack_wds_SLQSGetRuntimeSettings_t::IPFamilyPreference

8.1537.2.8 uint32_t unpack_wds_SLQSGetRuntimeSettings_t::IPv4

8.1537.2.9 struct wds_IPV6AddressInfo unpack_wds_SLQSGetRuntimeSettings_t::IPV6AddrInfo

8.1537.2.10 struct wds_IPV6GWAddressInfo unpack_wds_SLQSGetRuntimeSettings_t::IPV6GWAddrInfo

8.1537.2.11 uint32_t unpack_wds_SLQSGetRuntimeSettings_t::Mtu

8.1537.2.12 swi_uint256_t unpack_wds_SLQSGetRuntimeSettings_t::ParamPresenceMask

8.1537.2.13 uint8_t unpack_wds_SLQSGetRuntimeSettings_t::PCSCFAddrPCO

8.1537.2.14 struct wds_PCSCFFQDNAddressList unpack_wds_SLQSGetRuntimeSettings_t::PCSCFFQDNAddrList

8.1537.2.15 uint32_t unpack_wds_SLQSGetRuntimeSettings_t::PDPType

8.1537.2.16 uint32_t unpack_wds_SLQSGetRuntimeSettings_t::PrimaryDNSV4

8.1537.2.17 uint16_t unpack_wds_SLQSGetRuntimeSettings_t::PrimaryDNSV6[8]

8.1537.2.18 struct wds_ProfileIdentifier unpack_wds_SLQSGetRuntimeSettings_t::ProfileID

8.1537.2.19 uint8_t unpack_wds_SLQSGetRuntimeSettings_t::ProfileName[128]

8.1537.2.20 uint32_t unpack_wds_SLQSGetRuntimeSettings_t::SecondaryDNSV4

8.1537.2.21 uint16_t unpack_wds_SLQSGetRuntimeSettings_t::SecondaryDNSV6[8]

8.1537.2.22 struct wds_PCSCFIPv4ServerAddressList unpack_wds_SLQSGetRuntimeSettings_t::ServerAddrList

8.1537.2.23 uint32_t unpack_wds_SLQSGetRuntimeSettings_t::SubnetMaskV4

8.1537.2.24 uint16_t unpack_wds_SLQSGetRuntimeSettings_t::Technology

8.1537.2.25 LibPackUMTSQoS unpack_wds_SLQSGetRuntimeSettings_t::UMTSGrantedQoS

8.1537.2.26 uint8_t unpack_wds_SLQSGetRuntimeSettings_t::Username[128]

8.1538 unpack_wds_SLQSModifyProfile_t Struct Reference

Data Fields

- uint16_t * pExtErrorCode
- swi_uint256_t ParamPresenceMask

8.1538.1 Detailed Description

This structure contains out parameters for unpack_wds_SLQSModifyProfile

Parameters

pExtErrorCode	• The extended error code received from DS Profile subsystem of type eWDS_ERR_PROFILE_-REG_xxx. • Error code will only will be present if error code eQCWWAN_ERR_QMI_EXTENDED_INTERN-AL is returned by device. • See qm_wds_ds_profile_extended_err_codes enum in qmerrno.h for received error description. • Bit to check in ParamPresenceMask - **224**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1538.2 Field Documentation

8.1538.2.1 swi_uint256_t unpack_wds_SLQSModifyProfile_t::ParamPresenceMask

8.1538.2.2 uint16_t* unpack_wds_SLQSModifyProfile_t::pExtErrorCode

8.1539 unpack_wds_SLQSSetIPFamilyPreference_t Struct Reference

Data Fields

- uint16_t Tlvresult
- swi_uint256_t ParamPresenceMask

8.1539.1 Detailed Description

This structure contains unpack Set IP family preference information

Parameters

Tlvresult	unpack result
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1539.2 Field Documentation

8.1539.2.1 swi_uint256_t unpack_wds_SLQSSetIPFamilyPreference_t::ParamPresenceMask

8.1539.2.2 uint16_t unpack_wds_SLQSSetIPFamilyPreference_t::Tlvresult

8.1540 unpack_wds_SLQSSetPacketSrvStatusCallback_t Struct Reference

Data Fields

- uint8_t conn_status
- uint8_t reconfigReqd
- uint16_t sessionEndReason
- uint16_t verboseSessnEndReasonType
- uint16_t verboseSessnEndReason
- uint8_t ipFamily
- uint16_t techName
- uint8_t bearerID
- swi_uint256_t ParamPresenceMask

8.1540.1 Detailed Description

This structure contains unpack set packet service status callback information.

Parameters

conn_status	connection status. • Current link status. Values: – 1 - DISCONNECTED – 2 - CONNECTED – 3 - SUSPENDED – 4 - AUTHENTICATING • Bit to check in ParamPresenceMask - **1**
reconfigReqd	Indicates whether the network interface on the host needs to be reconfigured. • Values: – 0 - No need to reconfigure. – 1 - Reconfiguration required.

- Bit to check in ParamPresenceMask - **1**

Parameters

sessionEndReason	Call End Reason • See qaGobiApiTableCallEndReasons.h for Call End Reason • Bit to check in ParamPresenceMask - **16**
verboseSessnEndReasonType	Verbose call end reason type • Call end reason type. Values: – 0 - Unspecified – 1 - Mobile IP – 2 - Internal – 3 - Call Manager defined – 6 - 3GPP Specification defined – 7 - PPP – 8 - EHRPD – 9 - IPv6 • Bit to check in ParamPresenceMask - **17**
verboseSessnEndReason	Reason the call ended (verbose) • See qaGobiApiTableCallEndReasons.h for Call End Reason • Bit to check in ParamPresenceMask - **17**
ipFamily	IP family of the packet data connection. • Values – 4 - IPv4 – 6 - IPv6 • Bit to check in ParamPresenceMask - **18**
techName	Technology name of the packet data connection. • Values – 32767 - CDMA – 32764 - UMTS – 30592 - EPC – 30590 - EMBMS – 30584 - Modem Link Local EPC is a logical interface to support LTE/eHRPD handoff. It is returned if the device supports IP session continuity. Modem Link Local is an interface for transferring data between entities on the AP and modem. • Bit to check in ParamPresenceMask - **19**
bearerID	• bearer ID (3GPP) or RLP ID (3GPP2) of the packet data connection. • Valid Values - 0 to 16 – Bit to check in ParamPresenceMask - **20**
ParamPresenceMask	• bitmask representation to indicate valid parameters.

8.1540.2 Field Documentation

8.1540.2.1 uint8_t unpack_wds_SLQSSetPacketSrvStatusCallback_t::bearerID

8.1540.2.2 uint8_t unpack_wds_SLQSSetPacketSrvStatusCallback_t::conn_status

8.1540.2.3 uint8_t unpack_wds_SLQSSetPacketSrvStatusCallback_t::ipFamily

8.1540.2.4 swi_uint256_t unpack_wds_SLQSSetPacketSrvStatusCallback_t::ParamPresenceMask

8.1540.2.5 uint8_t unpack_wds_SLQSSetPacketSrvStatusCallback_t::reconfigReqd

8.1540.2.6 uint16_t unpack_wds_SLQSSetPacketSrvStatusCallback_t::sessionEndReason

8.1540.2.7 uint16_t unpack_wds_SLQSSetPacketSrvStatusCallback_t::techName

8.1540.2.8 uint16_t unpack_wds_SLQSSetPacketSrvStatusCallback_t::verboseSessnEndReason

8.1540.2.9 uint16_t unpack_wds_SLQSSetPacketSrvStatusCallback_t::verboseSessnEndReasonType

8.1541 unpack_wds_SLQSSetWdsEventCallback_ind_t Struct Reference

Data Fields

- uint8_t xferStatAvail
- uint64_t tx_bytes
- uint64_t rx_bytes
- uint64_t tx_pkts
- uint64_t rx_pkts
- uint8_t mipstatAvail
- uint32_t mipStatus
- uint8_t dBTechAvail
- uint32_t dBTechnology
- uint8_t dormancyStatAvail
- uint32_t dormancyStatus
- uint8_t currDBTechAvail
- uint32_t ratMask
- uint32_t soMask
- uint8_t dataSysStatAvail
- uint8_t prefNetwork
- uint8_t netInfoLen
- wds_currNetworkInfo currNWInfo [255]
- uint8_t dBtechExtAvail
- uint32_t dBtechnologyExt
- uint32_t dBTechExtRatValue
- uint64_t dBTechExtSoMask
- swi_uint256_t ParamPresenceMask

8.1541.1 Detailed Description

This structure contains unpack set WDS event callback information.

Parameters

xferStatAvail	transfer statistic available
tx_bytes	• Number of bytes transmitted without error • Bit to check in ParamPresenceMask - **25**

rx_bytes	• Number of bytes received without error • Bit to check in ParamPresenceMask - **26**
tx_pkts	• Number of packets transmitted without error • Bit to check in ParamPresenceMask - **16**
rx_pkts	• Number of packets received without error. • Bit to check in ParamPresenceMask - **17**
mipstatAvail	Mobile IP status available • Bit to check in ParamPresenceMask - **27**
mipStatus	• Status of the last MIP call (or attempt). • Values – 0x00 - Success • Bit to check in ParamPresenceMask - **27**
dBTechAvail	Data Bearer technology available • Bit to check in ParamPresenceMask - **23**

dBTechnology	• Data Bearer technology
	  – Values
	  * 0x01 - cdma2000 ® 1X
	  * 0x02 - cdma2000 ® HRPD (1xEV-DO)
	  * 0x03 - GSM
	  * 0x04 - UMTS
	  * 0x05 - cdma2000 ® HRPD (1xEV-DO RevA)
	  * 0x06 - EDGE
	  * 0x07 - HSDPA and WCDMA
	  * 0x08 - WCDMA and HSUPA
	  * 0x09 - HSDPA and HSUPA
	  * 0x0A - LTE
	  * 0x0B - cdma2000 ® EHRPD
	  * 0x0C - HSDPA+ and WCDMA
	  * 0x0D - HSDPA+ and HSUPA
	  * 0x0E - DC_HSDPA+ and WCDMA
	  * 0x0F - DC_HSDAP+ and HSUPA
	  * 0x10 - HSDPA+ and 64QAM
	  * 0x11 - HSDPA+, 64QAM and HSUPA
	  * 0x12 - TDSCDMA
	  * 0x13 - TDSCDMA and HSDPA
	  * 0x14 - TDSCDMA and HSUPA
	  * -1 - Unknown
	• Bit to check in ParamPresenceMask - **23**

dormancyStat-Avail	Dormancy status available • Bit to check in ParamPresenceMask - **24**
dormancyStatus	• Dormancy status • Values – 1 - Traffic channel dormant – 2 - Traffic channel active • Bit to check in ParamPresenceMask - **24**
currDBTechAvail	• Current Data Bearer technology available • Bit to check in ParamPresenceMask - **29**
ratMask	• RAT mask to indicate type of technology • Values – 0x00 - DONT_CARE – 0x8000 - NULL_BEARER • CDMA RAT mask – 0x01 - CDMA_1X – 0x02 - EVDO_REV0 – 0x05 - HRPD – 0x0B - EHRPD • UMTS RAT mask – 0x03 - GPRS – 0x04 - WCDMA – 0x06 - EDGE – 0x07 - HSDPA and WCDMA – 0x08 - WCDMA and HSUPA – 0x09 - HSDPA and HSUPA – 0x0A - LTE – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA • Bit to check in ParamPresenceMask - **29**
soMask	• SO Mask • Bit to check in ParamPresenceMask - **29**
dataSysStatAvail	• Data System Status available • Bit to check in ParamPresenceMask - **36**

prefNetwork	• preferred network • Values – 0 - 3GPP – 1 - 3GPP2
currNWInfo	• Current Network Info • see wds_currNetworkInfo for more info
dBtechExtAvail	Data bearer technology extended available • Bit to check in ParamPresenceMask - **42**
dBtechnologyExt	• Data bearer technology Extended. • Values – WDS_BEARER_TECH_NETWORK_3GPP (0) - 3GPP – WDS_BEARER_TECH_NETWORK_3GPP2 (1) - 3GPP2 • Bit to check in ParamPresenceMask - **42**
dBTechExtRat-Value	• Data bearer technology Extended RAT Value • Values – WDS_BEARER_TECH_RAT_EX_NULL_BEARER (0x00) - NULL bearer – WDS_BEARER_TECH_RAT_EX_3GPP_WCDMA (0x01) - 3GPP WCDMA – WDS_BEARER_TECH_RAT_EX_3GPP_GERAN (0x02) - 3GPP GERAN – WDS_BEARER_TECH_RAT_EX_3GPP_LTE (0x03) - 3GPP LTE – WDS_BEARER_TECH_RAT_EX_3GPP_TDSCDMA (0x04) - 3GPP TDSCDMA – WDS_BEARER_TECH_RAT_EX_3GPP_WLAN (0x05) - 3GPP WLAN – WDS_BEARER_TECH_RAT_EX_3GPP_MAX (0x64) - 3GPP maximum – WDS_BEARER_TECH_RAT_EX_3GPP2_1X (0x65) - 3GPP2 1X – WDS_BEARER_TECH_RAT_EX_3GPP2_HRPD (0x66) - 3GPP2 HRPD – WDS_BEARER_TECH_RAT_EX_3GPP2_EHRPD (0x67) - 3GPP2 EHRPD – WDS_BEARER_TECH_RAT_EX_3GPP2_WLAN (0x68) - 3GPP2 WLAN – WDS_BEARER_TECH_RAT_EX_3GPP2_MAX (0xC8) - 3GPP2 maximum • Bit to check in ParamPresenceMask - **42**

dBTechExtSo-Mask	• Data bearer technology Extended SO Mask • Service Option (SO) mask to indicate the service option or type of application.An SO mask value of zero indicates that this field is ignored. • Values – 0x00 - SO mask unspecified – 3GPP SO mask * 0x01 - WCDMA * 0x02 - HSDPA * 0x04 - HSUPA * 0x08 - HSDPAPLUS * 0x10 - DC HSDPAPLUS * 0x20 - 64 QAM * 0x40 - HSPA * 0x80 - GPRS * 0x100 - EDGE * 0x200 - GSM * 0x400 - S2B * 0x800 - LTE limited service * 0x1000 - LTE FDD * 0x2000 - LTE TDD – 3GPP2 SO mask * 0x01000000 - 1X IS95 * 0x02000000 - 1X IS2000 * 0x04000000 - 1X IS2000 REL A * 0x08000000 - HDR REV0 DPA * 0x10000000 - HDR REVA DPA * 0x20000000 - HDR REVB DPA * 0x40000000 - HDR REVA MPA * 0x80000000 - HDR REVB MPA * 0x100000000 - HDR REVA EMPA * 0x200000000 - HDR REVB EMPA * 0x400000000 - HDR REVB MMPA * 0x800000000 - HDR EVDO FMC • Bit to check in ParamPresenceMask - **42**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1541.2 Field Documentation

8.1541.2.1 uint8_t unpack_wds_SLQSSetWdsEventCallback_ind_t::currDBTechAvail

8.1541.2.2 wds_currNetworkInfo unpack_wds_SLQSSetWdsEventCallback_ind_t::currNWInfo[255]

8.1541.2.3 uint8_t unpack_wds_SLQSSetWdsEventCallback_ind_t::dataSysStatAvail

8.1541.2.4 uint8_t unpack_wds_SLQSSetWdsEventCallback_ind_t::dBTechAvail

8.1541.2.5 uint8_t unpack_wds_SLQSSetWdsEventCallback_ind_t::dBtechExtAvail

8.1541.2.6 uint32_t unpack_wds_SLQSSetWdsEventCallback_ind_t::dBTechExtRatValue

8.1541.2.7 uint64_t unpack_wds_SLQSSetWdsEventCallback_ind_t::dBTechExtSoMask

8.1541.2.8 uint32_t unpack_wds_SLQSSetWdsEventCallback_ind_t::dBTechnology

8.1541.2.9 uint32_t unpack_wds_SLQSSetWdsEventCallback_ind_t::dBtechnologyExt

8.1541.2.10 uint8_t unpack_wds_SLQSSetWdsEventCallback_ind_t::dormancyStatAvail

8.1541.2.11 uint32_t unpack_wds_SLQSSetWdsEventCallback_ind_t::dormancyStatus

8.1541.2.12 uint8_t unpack_wds_SLQSSetWdsEventCallback_ind_t::mipstatAvail

8.1541.2.13 uint32_t unpack_wds_SLQSSetWdsEventCallback_ind_t::mipStatus

8.1541.2.14 uint8_t unpack_wds_SLQSSetWdsEventCallback_ind_t::netInfoLen

8.1541.2.15 swi_uint256_t unpack_wds_SLQSSetWdsEventCallback_ind_t::ParamPresenceMask

8.1541.2.16 uint8_t unpack_wds_SLQSSetWdsEventCallback_ind_t::prefNetwork

8.1541.2.17 uint32_t unpack_wds_SLQSSetWdsEventCallback_ind_t::ratMask

8.1541.2.18 uint64_t unpack_wds_SLQSSetWdsEventCallback_ind_t::rx_bytes

8.1541.2.19 uint64_t unpack_wds_SLQSSetWdsEventCallback_ind_t::rx_pkts

8.1541.2.20 uint32_t unpack_wds_SLQSSetWdsEventCallback_ind_t::soMask

8.1541.2.21 uint64_t unpack_wds_SLQSSetWdsEventCallback_ind_t::tx_bytes

8.1541.2.22 uint64_t unpack_wds_SLQSSetWdsEventCallback_ind_t::tx_pkts

8.1541.2.23 uint8_t unpack_wds_SLQSSetWdsEventCallback_ind_t::xferStatAvail

8.1542 unpack_wds_SLQSSGetDHCPv4ClientConfig_t Struct Reference

Data Fields

- wdsDhcpv4HwConfig * pHwConfig
- wdsDhcpv4OptionList * pRequestOptionList
- swi_uint256_t ParamPresenceMask

8.1542.1 Detailed Description

WDS SWI DHCPv4 Config Structure

Parameters

pHWConfig	• pointer to HW Config structure • See wdsDhcpv4HwConfig • Bit to check in ParamPresenceMask - **16**
pRequestOption-List	• pointer to Option List structure to be sent in DHCP request • See wdsDhcpv4OptionList • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1542.2 Field Documentation

8.1542.2.1 swi_uint256_t unpack_wds_SLQSSGetDHCPv4ClientConfig_t::ParamPresenceMask

8.1542.2.2 wdsDhcpv4HwConfig* unpack_wds_SLQSSGetDHCPv4ClientConfig_t::pHwConfig

8.1542.2.3 wdsDhcpv4OptionList* unpack_wds_SLQSSGetDHCPv4ClientConfig_t::pRequestOptionList

8.1543 unpack_wds_SLQSSGetLoopback_t Struct Reference

Data Fields

- uint8_t ByteLoopbackMode
- uint8_t ByteLoopbackMultiplier
- swi_uint256_t ParamPresenceMask

8.1543.1 Detailed Description

This structure contains unpack Get loopback information.

Parameters

ByteLoopback-Mode	• Loopback Mode.
	  – 0 - Disable
	  – 1 - Enable
	• Bit to check in ParamPresenceMask - **16**

ByteLoopback-Multiplier	• Loopback multiplier. Number of downlink bytes to send for each uplink byte. • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1543.2 Field Documentation

8.1543.2.1 uint8_t unpack_wds_SLQSSGetLoopback_t::ByteLoopbackMode

8.1543.2.2 uint8_t unpack_wds_SLQSSGetLoopback_t::ByteLoopbackMultiplier

8.1543.2.3 swi_uint256_t unpack_wds_SLQSSGetLoopback_t::ParamPresenceMask

8.1544 unpack_wds_SLQSStartDataSession_t Struct Reference

Data Fields

- uint32_t * psid
- uint32_t * pFailureReason
- uint32_t * pVerboseFailReasonType
- uint32_t * pVerboseFailureReason
- swi_uint256_t ParamPresenceMask

8.1544.1 Detailed Description

This structure contains unpack Start Data Session Information.

Parameters

psid	• Assigned session ID when starting a data session • Bit to check in ParamPresenceMask - **1**
pFailureReason	• Reason data session failed to be established • See qaGobiApiTableCallEndReasons.h for Call End Reason • Bit to check in ParamPresenceMask - **16**
pVerboseFail-ReasonType	• Parameter describing type of verbose failure reason • See qaGobiApiTableCallEndReasons.h for Call End Reason Type • Bit to check in ParamPresenceMask - **17**
pVerboseFailure-Reason	• Verbose reason explaining why call failed. Depends on verbFailReasonType parameter • See qaGobiApiTableCallEndReasons.h for Call End Reason • Bit to check in ParamPresenceMask - **17**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1544.2 Field Documentation

8.1544.2.1 swi_uint256_t unpack_wds_SLQSStartDataSession_t::ParamPresenceMask

8.1544.2.2 uint32_t* unpack_wds_SLQSStartDataSession_t::pFailureReason

8.1544.2.3 uint32_t* unpack_wds_SLQSStartDataSession_t::psid

8.1544.2.4 uint32_t* unpack_wds_SLQSStartDataSession_t::pVerboseFailReasonType

8.1544.2.5 uint32_t* unpack_wds_SLQSStartDataSession_t::pVerboseFailureReason

8.1545 unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t Struct Reference

Data Fields

- uint8_t contextId
- uint8_t bearerId
- int8_t apnName [100]
- uint32_t ipv4Address
- uint32_t ipv4GWAddress
- uint32_t prDNSIPv4Address
- uint32_t seDNSIPv4Address
- ipv6AddressInfo ipv6Address
- ipv6AddressInfo ipv6GWAddress
- uint16_t prDNSIPv6Address [8]
- uint16_t seDNSIPv6Address [8]
- uint32_t prPCSCFIPv4Address
- uint32_t sePCSCFIPv4Address
- uint16_t prPCSCFIPv6Address [8]
- uint16_t sePCSCFIPv6Address [8]
- swi_uint256_t ParamPresenceMask

8.1545.1 Detailed Description

This structure contains the unpack parameters retrieved by the API unpack_wds_SLQSWdsSwiPDPRuntime-Settings

Parameters

contextId	(optional) • Context Identifier • Bit to check in ParamPresenceMask - **16**
bearerId	(optional) • Bearer Identity • An EPS bearer identity uniquely identifies an EPS bearer for one UE accessing via E-UTRAN. The EPS Bearer Identity is allocated by the MME. • Bit to check in ParamPresenceMask - **17**
apnName	(optional) • APN name associated with the context id • Bit to check in ParamPresenceMask - **18**
ipv4Address	(optional) • IPv4 Address • Bit to check in ParamPresenceMask - **19**

ipv4GWAddress	(optional) • IPv4 Gateway Address • Bit to check in ParamPresenceMask - **20**
prDNSIPv4-Address	(optional) • Primary DNS IPv4 Address • Bit to check in ParamPresenceMask - **21**
seDNSIPv4-Address	(optional) • Secondary DNS IPv4 Address • Bit to check in ParamPresenceMask - **22**
ipv6Address	(optional) • IPv6 Address • Bit to check in ParamPresenceMask - **23**
ipv6GWAddress	(optional) • IPv6 Gateway Address • See ipv6AddressInfo for more information • Bit to check in ParamPresenceMask - **24**
prDNSIPv6-Address	(optional) • Primary IPv6 DNS Address(in network byte order) • This is an 8-element array of 16-bit numbers, each of which is in big-endian format • Bit to check in ParamPresenceMask - **25**
seDNSIPv6-Address	(optional) • Secondary IPv6 DNS Address(in network byte order) • This is an 8-element array of 16-bit numbers, each of which is in big-endian format • Bit to check in ParamPresenceMask - **26**
prPCSCFIPv4-Address	(optional) • Primary PCSCF IPv4 Address • Bit to check in ParamPresenceMask - **27**
sePCSCFIPv4-Address	(optional) • Secondary PCSCF IPv4 Address • Bit to check in ParamPresenceMask - **28**
prPCSCFIPv6-Address	(optional) • Primary PCSCF IPv6 Address • This is an 8-element array of 16-bit numbers, each of which is in big-endian format • Bit to check in ParamPresenceMask - **29**
sePCSCFIPv6-Address	(optional) • Secondary PCSCF IPv6 Address • This is an 8-element array of 16-bit numbers, each of which is in big-endian format • Bit to check in ParamPresenceMask - **30**
ParamPresence-Mask	• bitmask representation to indicate valid parameters.

8.1545.2 Field Documentation

8.1545.2.1 int8_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::apnName[100]

8.1545.2.2 uint8_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::bearerId

8.1545.2.3 uint8_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::contextId

8.1545.2.4 uint32_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::ipv4Address

8.1545.2.5 uint32_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::ipv4GWAddress

8.1545.2.6 ipv6AddressInfo unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::ipv6Address

8.1545.2.7 ipv6AddressInfo unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::ipv6GWAddress

8.1545.2.8 swi_uint256_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::ParamPresenceMask

8.1545.2.9 uint32_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::prDNSIPv4Address

8.1545.2.10 uint16_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::prDNSIPv6Address[8]

8.1545.2.11 uint32_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::prPCSCFIPv4Address

8.1545.2.12 uint16_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::prPCSCFIPv6Address[8]

8.1545.2.13 uint32_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::seDNSIPv4Address

8.1545.2.14 uint16_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::seDNSIPv6Address[8]

8.1545.2.15 uint32_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::sePCSCFIPv4Address

8.1545.2.16 uint16_t unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t::sePCSCFIPv6Address[8]

8.1546 UnPackGetProfileSettingOut Struct Reference

Data Fields

- UnpackQmiProfileInfo curProfile
- uint16_t * pExtErrCode

8.1546.1 Detailed Description

This structure contains the profile settings output

Parameters

curProfile	• Structure containing details of the current profile • See UnpackQmiProfileInfo

pExtErrCode	• pointer to a 2 byte extended error code • Error code will only will be present if error code eQCWWAN_ERR_QMI_EXTENDED_INTERNAL is returned by device. • See qm_wds_ds_profile_extended_err_codes enum in qmerrno.h for received error description. • Bit to check in ParamPresenceMask - **224**

8.1546.2 Field Documentation

8.1546.2.1 UnpackQmiProfileInfo UnPackGetProfileSettingOut::curProfile

8.1546.2.2 uint16_t* UnPackGetProfileSettingOut::pExtErrCode

8.1547 unpackWdsProfileParam Union Reference

Data Fields

- LibpackProfile3GPP SlqsProfile3GPP
- LibpackProfile3GPP2 SlqsProfile3GPP2

8.1547.1 Detailed Description

This union WdsProfileParam consists of Profile3GPP and Profile3GPP2 out of which one will be used to create profile.

Parameters

SlqsProfile3GPP	3GPP profile • See LibpackProfile3GPP
SlqsProfile3GPP2	3GPP2 profile • See LibpackProfile3GPP2

8.1547.2 Field Documentation

8.1547.2.1 LibpackProfile3GPP unpackWdsProfileParam::SlqsProfile3GPP

8.1547.2.2 LibpackProfile3GPP2 unpackWdsProfileParam::SlqsProfile3GPP2

8.1548 urlAddr Struct Reference

Data Fields

- CHAR address [256]
- BYTE TlvPresent

8.1548.1 Detailed Description

This structure contains LOC Get Server URL address field.

Parameters

address	• Uniform Resource Locator • Type - NULL terminated string • Maximum string length (including NULL terminator) 256
TlvPresent	• Tlv Present or not

8.1548.2 Field Documentation

8.1548.2.1 CHAR urlAddr::address[256]

8.1548.2.2 BYTE urlAddr::TlvPresent

8.1549 URLAddrInfo Struct Reference

Data Fields

- CHAR urlAddr [256]

8.1549.1 Detailed Description

This structure specifies information regarding the URL.

Parameters

urlAddr	• URL address. • Type - NULL-terminated string • Maximum string length (including NULL terminator) - 256

8.1549.2 Field Documentation

8.1549.2.1 CHAR URLAddrInfo::urlAddr[256]

8.1550 USBCompConfig Struct Reference

Data Fields

- BYTE * pUSBComp

8.1550.1 Detailed Description

This structure is used to store USB composition information

Parameters

pUSBComp[IN]	• Current USB Composition • Values: – 0..5 - Reserved (non-QMI) – 6 - DM NMEA AT QMI – 7 - DM NMEA AT QMI1 QMI2 QMI3 – 8 - DM NMEA AT MBIM – 9 - MBIM – 10 - NMEA MBIM – 11 - DM MBIM – 12 - DM NMEA MBIM 13-22 are combined compositions. One is for Win8 MBIM interfaces, another is for legacy QMI interfaces – 13 - 6 for QMI, 8 for MBIM – 14 - 6 for QMI, 9 for MBIM – 15 - 6 for QMI, 10 for MBIM – 16 - 6 for QMI, 11 for MBIM – 17 - 6 for QMI, 12 for MBIM – 18 - 7 for QMI, 8 for MBIM – 19 - 7 for QMI, 9 for MBIM – 20 - 7 for QMI, 10 for MBIM – 21 - 7 for QMI, 11 for MBIM – 22 - 7 for QMI, 12 for MBIM

8.1550.2 Field Documentation

8.1550.2.1 BYTE* USBCompConfig::pUSBComp

8.1551 USBCompParams Struct Reference

Data Fields

- BYTE * pUSBComp
- BYTE * pNumSupUSBComps
- BYTE * pSupUSBComps

8.1551.1 Detailed Description

This structure is used to store retrieved USB Composition

Parameters

pUSBComp[OUT]	• Current USB Composition(optional parameter) • Values: – 0..5 - Reserved (non-QMI) – 6 - DM NMEA AT QMI – 7 - DM NMEA AT QMI1 QMI2 QMI3 – 8 - DM NMEA AT MBIM – 9 - MBIM – 10 - NMEA MBIM – 11 - DM MBIM – 12 - DM NMEA MBIM 13-22 are combined compositions. One is for Win8 MBIM interfaces, another is for legacy QMI interfaces – 13 - 6 for QMI, 8 for MBIM – 14 - 6 for QMI, 9 for MBIM – 15 - 6 for QMI, 10 for MBIM – 16 - 6 for QMI, 11 for MBIM – 17 - 6 for QMI, 12 for MBIM – 18 - 7 for QMI, 8 for MBIM – 19 - 7 for QMI, 9 for MBIM – 20 - 7 for QMI, 10 for MBIM – 21 - 7 for QMI, 11 for MBIM – 22 - 7 for QMI, 12 for MBIM
pNumSupUSBComps[OUT]	• Number of supported USB compositions in the parameter to follow • Range - 0-255

pSupUSB-Comps[OUT]	• Optional parameter • List of supported USB compositions(1 Byte each - Max 255) • Total length is defined by pNumSupUSBComps parameter • Values: – 0..5 - Reserved (non-QMI) – 6 - DM NMEA AT QMI – 7 - DM NMEA AT QMI1 QMI2 QMI3 – 8 - DM NMEA AT MBIM – 9 - MBIM – 10 - NMEA MBIM – 11 - DM MBIM – 12 - DM NMEA MBIM 13-22 are combined compositions. One is for Win8 MBIM interfaces, another is for legacy QMI interfaces – 13 - 6 for QMI, 8 for MBIM – 14 - 6 for QMI, 9 for MBIM – 15 - 6 for QMI, 10 for MBIM – 16 - 6 for QMI, 11 for MBIM – 17 - 6 for QMI, 12 for MBIM – 18 - 7 for QMI, 8 for MBIM – 19 - 7 for QMI, 9 for MBIM – 20 - 7 for QMI, 10 for MBIM – 21 - 7 for QMI, 11 for MBIM – 22 - 7 for QMI, 12 for MBIM

8.1551.2 Field Documentation

8.1551.2.1 BYTE* USBCompParams::pNumSupUSBComps

8.1551.2.2 BYTE* USBCompParams::pSupUSBComps

8.1551.2.3 BYTE* USBCompParams::pUSBComp

8.1552 usbMTUSizeTlv Struct Reference

Data Fields

- BYTE TlvPresent
- WORD UsbMTUSize

8.1552.1 Detailed Description

This structure contains the parameters for USB MTU Size

Parameters

TlvPresent	• Tlv Present.

UsbMTUSize	USB MTU size • Size of USB MTU

8.1552.2 Field Documentation

8.1552.2.1 BYTE usbMTUSizeTlv::TlvPresent

8.1552.2.2 WORD usbMTUSizeTlv::UsbMTUSize

8.1553 USSDNoWaitIndicationInfo Struct Reference

Data Fields

- BYTE * pError
- BYTE * pFailureCause
- struct USSInfo * pUSSDData
- alphaIDInfo * pAlphaIdentifier

8.1553.1 Detailed Description

Contains the parameters passed for USSDNoWaitIndicationCallback by the device.

Parameters

pError	• Type of Error (if any)
pFailureCause	• Supplementary services failure cause
pUSSDData	• USS Data from Network. • See USSInfo for more details.

8.1553.2 Field Documentation

8.1553.2.1 alphaIDInfo* USSDNoWaitIndicationInfo::pAlphaIdentifier

8.1553.2.2 BYTE* USSDNoWaitIndicationInfo::pError

8.1553.2.3 BYTE* USSDNoWaitIndicationInfo::pFailureCause

8.1553.2.4 struct USSInfo* USSDNoWaitIndicationInfo::pUSSDData

8.1554 USSDRespFNetwork Struct Reference

Data Fields

- char * pTypeCode

- char * pRespData

8.1554.1 Detailed Description

This structure contains the response from the network

Parameters

pTypeCode	"0" USSD-Notify – text in pRespData "1" USSD-Request – text in pRespData "2" Session terminated by network "3" other local client (eg, SIM Toolkit) has responded "4" Operation not supported "5" Network timeout
pRespData	• points to a message string received from the network

8.1554.2 Field Documentation

8.1554.2.1 char* USSDRespFNetwork::pRespData

8.1554.2.2 char* USSDRespFNetwork::pTypeCode

8.1555 USSInfo Struct Reference

Data Fields

- BYTE ussDCS
- BYTE ussLen
- BYTE ussData [182]

8.1555.1 Detailed Description

This structure contains USS Information

Parameters

ussDCS	• 1 - ASCII coding scheme • 2 - 8-BIT coding scheme • 3 - UCS2
ussLen	• Range 1 to 182
ussData	• Data encoded as per the DCS

8.1555.2 Field Documentation

8.1555.2.1 BYTE USSInfo::ussData[182]

8.1555.2.2 BYTE USSInfo::ussDCS

8.1555.2.3 BYTE USSInfo::ussLen

8.1556 USSResp Struct Reference

Data Fields

- WORD * pfailureCause
- alphaIDInfo * pAlphaIDInfo
- struct USSInfo * pUSSDInfo
- BYTE * pCcResultType
- BYTE * pCallId
- ccSUPSType * pCCSuppsType

8.1556.1 Field Documentation

8.1556.1.1 alphaIDInfo* USSResp::pAlphaIDInfo

8.1556.1.2 BYTE* USSResp::pCallId

8.1556.1.3 BYTE* USSResp::pCcResultType

8.1556.1.4 ccSUPSType* USSResp::pCCSuppsType

8.1556.1.5 WORD* USSResp::pfailureCause

8.1556.1.6 struct USSInfo* USSResp::pUSSDInfo

8.1557 UUSInfo Struct Reference

Data Fields

- BYTE UUSType
- BYTE UUSDcs
- BYTE UUSDatalen
- BYTE UUSData [255]

8.1557.1 Detailed Description

This structure contains User to User Signaling Service Information.

Parameters

UUSType	• UUS type values are: – 0x00 - UUS_DATA – 0x01 - UUS_TYPE1_IMPLICIT – 0x02 - UUS_TYPE1_REQUIRED – 0x03 - UUS_TYPE1_NOT_REQUIRED – 0x04 - UUS_TYPE2_REQUIRED – 0x05 - UUS_TYPE2_NOT_REQUIRED – 0x06 - UUS_TYPE3_REQUIRED – 0x07 - UUS_TYPE3_NOT_REQUIRED – 0xFF - Not Available

UUSDcs	• UUS data coding scheme values are: – 0x01 - UUS_DCS_USP – 0x02 - UUS_DCS_OHLP – 0x03 - UUS_DCS_X244 – 0x04 - UUS_DCS_SMCF – 0x05 - UUS_DCS_IA5 – 0x06 - UUS_DCS_RV12RD – 0x07 - UUS_DCS_Q931UNCCM – 0xFF - Not Available
UUSDatalen	• Number of sets of the following elements. – UUSData • If zero(0) then no further information exists.
UUSData[MAX_-DESCRIPTION-_LENGTH]	• UUS data encoded as per coding scheme

8.1557.2 Field Documentation

8.1557.2.1 BYTE UUSInfo::UUSData[255]

8.1557.2.2 BYTE UUSInfo::UUSDatalen

8.1557.2.3 BYTE UUSInfo::UUSDcs

8.1557.2.4 BYTE UUSInfo::UUSType

8.1558 validCardStatus Struct Reference

Data Fields

- BYTE validCardLength
- BYTE validCard [255]

8.1558.1 Detailed Description

This structure contains Valid Card Status Information.

Parameters

validCardLength	• Number of sets of the following elements. i.e. validCard
validCard[MAX_-DESCRIPTION-_LENGTH]	• Indicates the status of the valid card. – 0 - Status of the card is unknown – 1 - Status of the card is valid

8.1558.2 Field Documentation

8.1558.2.1 BYTE validCardStatus::validCard[255]

8.1558.2.2 BYTE validCardStatus::validCardLength

8.1559 verifyUIMPIN Struct Reference

Data Fields

- BYTE pinID
- BYTE pinLen
- BYTE pinVal [255]

8.1559.1 Detailed Description

This structure contains the information about the pin parameters that need to be verified.

Parameters

pinID	• Indicates the PIN ID to be verified. – 1 - PIN1 (also called PIN) – 2 - PIN2 – 3 - Universal PIN – 4 - Hidden key
pinLen	• Length of the following elements i.e. pin value.
pinVal[MAX_DESCRIPTION_LENGTH]	• PIN value. • This value is a sequence of ASCII characters.

8.1559.2 Field Documentation

8.1559.2.1 BYTE verifyUIMPIN::pinID

8.1559.2.2 BYTE verifyUIMPIN::pinLen

8.1559.2.3 BYTE verifyUIMPIN::pinVal[255]

8.1560 voice_airTimer Struct Reference

Data Fields

- uint8_t namID
- uint32_t airTimerValue

8.1560.1 Detailed Description

This structure contains information about the Air Timer.

Parameters

namID	• Index of the NAM(Number Assignment Module) to be configured. • Range 0 to 3. • Some modems support only 1 or 2 NAMs. • 0xFF,if not available.
airTimerValue	• Time in minutes. • Cumulative air time is slammed. • 0xFFFFFFFF,if not available.

8.1560.2 Field Documentation

8.1560.2.1 uint32_t voice_airTimer::airTimerValue

8.1560.2.2 uint8_t voice_airTimer::namID

8.1561 voice_allCallsAlphaIDInfo Struct Reference

Data Fields

- uint8_t callID
- voice_alphaIDInfo AlphaIDInfo

8.1561.1 Detailed Description

This structure contains information for Alpha Identifier for All Calls

Parameters

callID	• Unique call identifier for the call.
AlphaIDInfo	• See voice_alphaIDInfo for more information.

8.1561.2 Field Documentation

8.1561.2.1 voice_alphaIDInfo voice_allCallsAlphaIDInfo::AlphaIDInfo

8.1561.2.2 uint8_t voice_allCallsAlphaIDInfo::callID

8.1562 voice_allCallsDiagInfo Struct Reference

Data Fields

- uint8_t callID
- voice_diagInfo DiagInfo

8.1562.1 Detailed Description

This structure contains Diagnostic Information for All Calls

Parameters

callID	• Unique call identifier for the call.
DiagInfo	• See voice_diagInfo for more information.

8.1562.2 Field Documentation

8.1562.2.1 uint8_t voice_allCallsDiagInfo::callID

8.1562.2.2 voice_diagInfo voice_allCallsDiagInfo::DiagInfo

8.1563 voice_allCallsUUSInfo Struct Reference

Data Fields

- uint8_t callID
- voice_UUSInfo uusInfo

8.1563.1 Detailed Description

This structure contains information for User to User Signaling Service for All Calls.

Parameters

callID	• Unique call identifier for the call.
uusInfo	• See voice_UUSInfo for more information.

8.1563.2 Field Documentation

8.1563.2.1 uint8_t voice_allCallsUUSInfo::callID

8.1563.2.2 voice_UUSInfo voice_allCallsUUSInfo::uusInfo

8.1564 voice_alphaIDInfo Struct Reference

Data Fields

- uint8_t alphaDcs
- uint8_t alphaLen
- uint8_t alphaText [255]

8.1564.1 Detailed Description

This structure contains information about the Alpha Identifier.

Parameters

alphaDcs	• Alpha coding scheme – 0x01 - GSM Default_Char – 0x02 - UCS2 – 0xFF - Not Available
alphaLen	• Number of sets of the following elements: – pAlpha_text • If zero(0) then no further information exists.
alphaText[MAX_VOICE_DESCRIPTION_LENGTH]	• Data encoded as per the alpha_dcs

8.1564.2 Field Documentation

8.1564.2.1 uint8_t voice_alphaIDInfo::alphaDcs

8.1564.2.2 uint8_t voice_alphaIDInfo::alphaLen

8.1564.2.3 uint8_t voice_alphaIDInfo::alphaText[255]

8.1565 voice_arrAlertingPattern Struct Reference

Data Fields

- uint8_t numInstances
- uint8_t callID [20]
- uint32_t alertingPattern [20]

8.1565.1 Detailed Description

This structure contains an array of Alerting Pattern.

Parameters

numInstances	• Number of callID, alertingPattern that follow. • If zero(0) then no further information exists.

callID[VOICE_MAX_NO_OF_CALLS]	• Array of Unique call identifier for the call.
alertingPattern[VOICE_MAX_NO_OF_CALLS]	• Array of Alerting pattern. – 0x00 - QMI_VOICE_ALERTING_PATTERN_1 - Pattern 1 – 0x01 - QMI_VOICE_ALERTING_PATTERN_2 - Pattern 2 – 0x02 - QMI_VOICE_ALERTING_PATTERN_3 - Pattern 3 – 0x04 - QMI_VOICE_ALERTING_PATTERN_5 - Pattern 5 – 0x05 - QMI_VOICE_ALERTING_PATTERN_6 - Pattern 6 – 0x06 - QMI_VOICE_ALERTING_PATTERN_7 - Pattern 7 – 0x07 - QMI_VOICE_ALERTING_PATTERN_8 - Pattern 8 – 0x08 - QMI_VOICE_ALERTING_PATTERN_9 - Pattern 9

8.1565.2 Field Documentation

8.1565.2.1 uint32_t voice_arrAlertingPattern::alertingPattern[20]

8.1565.2.2 uint8_t voice_arrAlertingPattern::callID[20]

8.1565.2.3 uint8_t voice_arrAlertingPattern::numInstances

8.1566 voice_arrAlertingType Struct Reference

Data Fields

- uint8_t numInstances
- uint8_t callID [20]
- uint8_t AlertingType [20]

8.1566.1 Detailed Description

This structure contains an array of Alerting Type.

Parameters

numInstances	• Number of callID, AlertingType that follow. • If zero(0) then no further information exists.
callID[VOICE_MAX_NO_OF_CALLS]	• Array of Unique call identifier for the call.
AlertingType[VOICE_MAX_NO_OF_CALLS]	• Array of Alerting type. – 0x00 - ALERTING_LOCAL - Local – 0x01 - ALERTING_REMOTE - Remote

8.1566.2 Field Documentation

8.1566.2.1 uint8_t voice_arrAlertingType::AlertingType[20]

8.1566.2.2 uint8_t voice_arrAlertingType::callID[20]

8.1566.2.3 uint8_t voice_arrAlertingType::numInstances

8.1567 voice_arrAlphaID Struct Reference

Data Fields

- uint8_t numInstances
- voice_allCallsAlphaIDInfo allCallsAlphaIDInfoArr [20]

8.1567.1 Detailed Description

This structure contains an array of Alpha ID Info

Parameters

numInstances	• Number of allCallsAlphaIDInfo that follow. • If zero(0) then no further information exists.
allCallsAlphaIDInfo[VOICE_MAX_NO_OF_CALLS]	• Array of allCallsAlphaIDInfo. • See voice_allCallsAlphaIDInfo for more information.

8.1567.2 Field Documentation

8.1567.2.1 voice_allCallsAlphaIDInfo voice_arrAlphaID::allCallsAlphaIDInfoArr[20]

8.1567.2.2 uint8_t voice_arrAlphaID::numInstances

8.1568 voice_arrCalledPartyNum Struct Reference

Data Fields

- uint8_t numInstances
- voice_peerNumberInfo CalledPartyNum [20]

8.1568.1 Detailed Description

This structure contains an array of Called Party Numbers consisting of information of all the numbers which have been called from the device.

Parameters

numInstances	• Number of calledPartyNum that follow. • If zero(0) then no further information exists.

CalledPartyNum[VOICE_MAX_NO_OF_CALLS]	• Array of CalledPartyNum. • See voice_peerNumberInfo for more information.

8.1568.2 Field Documentation

8.1568.2.1 voice_peerNumberInfo voice_arrCalledPartyNum::CalledPartyNum[20]

8.1568.2.2 uint8_t voice_arrCalledPartyNum::numInstances

8.1569 voice_arrCallEndReason Struct Reference

Data Fields

- uint8_t numInstances
- uint8_t callID [20]
- uint16_t callEndReason [20]

8.1569.1 Detailed Description

This structure contains an array of Call End Reasons.

Parameters

numInstances	• Number of callID, callEndReason that follow. • If zero(0) then no further information exists.
callID[VOICE_MAX_NO_OF_CALLS]	• Array of Unique call identifier for the call.
callEndReason[VOICE_MAX_NO_OF_CALLS]	• Array of Call End Reason . • See Table9 qaGobiApiTableVoiceCallEndReasons.h for a list of valid voice-related call end reasons

8.1569.2 Field Documentation

8.1569.2.1 uint16_t voice_arrCallEndReason::callEndReason[20]

8.1569.2.2 uint8_t voice_arrCallEndReason::callID[20]

8.1569.2.3 uint8_t voice_arrCallEndReason::numInstances

8.1570 voice_arrCallInfo Struct Reference

Data Fields

- uint8_t numInstances

- voice_getAllCallInformation getAllCallInfo [20]

8.1570.1 Detailed Description

This structure contains an array of Call Info

Parameters

numInstances	• Number of getAllCallInfo that follow. • If zero(0) then no further information exists.
getAllCallInfo[VOICE_MAX_NO_OF_CALLS]	• Array of CallInfo. • See voice_getAllCallInformation for more information.

8.1570.2 Field Documentation

8.1570.2.1 voice_getAllCallInformation voice_arrCallInfo::getAllCallInfo[20]

8.1570.2.2 uint8_t voice_arrCallInfo::numInstances

8.1571 voice_arrConnectPartyNum Struct Reference

Data Fields

- uint8_t numInstances
- voice_peerNumberInfo ConnectedPartyNum [20]

8.1571.1 Detailed Description

This structure contains an array of Connected Party Numbers consisting of information regarding all the devices connected.

Parameters

numInstances	• Number of ConnectedPartyNum that follow. • If zero(0) then no further information exists.
ConnectedPartyNum[VOICE_MAX_NO_OF_CALLS]	• Array of ConnectedPartyNum. • See voice_peerNumberInfo for more information.

8.1571.2 Field Documentation

8.1571.2.1 voice_peerNumberInfo voice_arrConnectPartyNum::ConnectedPartyNum[20]

8.1571.2.2 uint8_t voice_arrConnectPartyNum::numInstances

8.1572 voice_arrDiagInfo Struct Reference

Data Fields

- uint8_t numInstances
- voice_allCallsDiagInfo DiagInfo [20]

8.1572.1 Detailed Description

This structure contains an array of Diagnostic Information.

Parameters

numInstances	• Number of DiagInfo that follow. • If zero(0) then no further information exists.
DiagInfo[VOICE_MAX_NO_OF_CALLS]	• Array of DiagInfo. • See voice_allCallsDiagInfo for more information.

8.1572.2 Field Documentation

8.1572.2.1 voice_allCallsDiagInfo voice_arrDiagInfo::DiagInfo[20]

8.1572.2.2 uint8_t voice_arrDiagInfo::numInstances

8.1573 voice_arrRedirPartyNum Struct Reference

Data Fields

- uint8_t numInstances
- voice_peerNumberInfo RedirPartyNum [20]

8.1573.1 Detailed Description

This structure contains an array of Redirecting Party Numbers consisting of information of all the numbers which have been redirected from the device.

Parameters

numInstances	• Number of redirPartyNum that follow. • If zero(0) then no further information exists.
RedirPartyNum[VOICE_MAX_NO_OF_CALLS]	• Array of RedirPartyNum. • See voice_peerNumberInfo for more information.

8.1573.2 Field Documentation

8.1573.2.1 uint8_t voice_arrRedirPartyNum::numInstances

8.1573.2.2 voice_peerNumberInfo voice_arrRedirPartyNum::RedirPartyNum[20]

8.1574 voice_arrRemotePartyName Struct Reference

Data Fields

- uint8_t numInstances
- voice_getAllCallRmtPtyName GetAllCallRmtPtyName [20]

8.1574.1 Detailed Description

This structure contains an array of Remote Party Names

Parameters

numInstances	• Number of remotePartyName that follow. • If zero(0) then no further information exists.
GetAllCallRmtPtyName[MAX_NO_OF_CALLS]	• Array of remotePartyName. • See voice_getAllCallRmtPtyName for more information.

8.1574.2 Field Documentation

8.1574.2.1 voice_getAllCallRmtPtyName voice_arrRemotePartyName::GetAllCallRmtPtyName[20]

8.1574.2.2 uint8_t voice_arrRemotePartyName::numInstances

8.1575 voice_arrRemotePartyNum Struct Reference

Data Fields

- uint8_t numInstances
- voice_getAllCallRmtPtyNum RmtPtyNum [20]

8.1575.1 Detailed Description

This structure contains an array of Remote Party Numbers

Parameters

numInstances	• Number of remotePartyNum that follow. • If zero(0) then no further information exists.
RmtPtyNum[VOICE_MAX_NO_OF_CALLS]	• Array of remotePartyNum. • See voice_getAllCallRmtPtyNum for more information.

8.1575.2 Field Documentation

8.1575.2.1 uint8_t voice_arrRemotePartyNum::numInstances

8.1575.2.2 voice_getAllCallRmtPtyNum voice_arrRemotePartyNum::RmtPtyNum[20]

8.1576 voice_arrSvcOption Struct Reference

Data Fields

- uint8_t numInstances
- uint8_t callID [20]
- uint16_t srvOption [20]

8.1576.1 Detailed Description

This structure contains array an of Servicing option.

Parameters

numInstances	• Number of callID, srvOption that follow. • If zero(0) then no further information exists.
callID[VOICE_-MAX_NO_OF_-CALLS]	• Array of Unique call identifier for the call.
srvOption[VOIC-E_MAX_NO_O-F_CALLS]	• Array of Service option. • See Table9 qaGobiApiTableServiceOptions.h for standard service option number assignments.

8.1576.2 Field Documentation

8.1576.2.1 uint8_t voice_arrSvcOption::callID[20]

8.1576.2.2 uint8_t voice_arrSvcOption::numInstances

8.1576.2.3 uint16_t voice_arrSvcOption::srvOption[20]

8.1577 voice_arrUUSInfo Struct Reference

Data Fields

- uint8_t numInstances
- voice_allCallsUUSInfo AllCallsUUSInfo [20]

8.1577.1 Detailed Description

This structure contains an array of User to User Signaling Service Information

Parameters

numInstances	• Number of allCallsUUSInfo that follow. • If zero(0) then no further information exists.
AllCallsUUSInfo[VOICE_MAX_NO_OF_CALLS]	• Array of allCallsUUSInfo. • See voice_allCallsUUSInfo for more information.

8.1577.2 Field Documentation

8.1577.2.1 voice_allCallsUUSInfo voice_arrUUSInfo::AllCallsUUSInfo[20]

8.1577.2.2 uint8_t voice_arrUUSInfo::numInstances

8.1578 voice_burstDTMFInfo Struct Reference

Data Fields

- uint8_t * pCallID
- uint8_t digitCnt
- uint8_t pDigitBuff [255]

8.1578.1 Detailed Description

This structure contains Voice Burst DTMF Information

Parameters

pCallID	• Call ID associated with call on which the DTMF information has to be sent. A burst DTMF request is sent to the current active/alerting call when pCallId is set to 0xFF. • This is IN/OUT parameter, value passed by user will be packed in request and value received from the device would be returned to the user. • If the call ID value received is 0, no value has been returned by the device • NULL pointer - Invalid data.
digitCnt	• Length of DTMF digit buffer which follows
pDigitBuff[MAX_VOICE_DESCRIPTION_LENGTH]	• DTMF digit buffer in ASCII, NULL terminated

8.1578.2 Field Documentation

8.1578.2.1 uint8_t voice_burstDTMFInfo::digitCnt

8.1578.2.2 uint8_t* voice_burstDTMFInfo::pCallID

8.1578.2.3 uint8_t voice_burstDTMFInfo::pDigitBuff[255]

8.1579 voice_calledPartyInfo Struct Reference

Data Fields

- uint8_t PI
- uint8_t SI
- uint8_t numType
- uint8_t numPlan
- uint8_t numLen
- uint8_t number [255]

8.1579.1 Detailed Description

This structure contains Called party Number Information

Parameters

PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.
SI	• Number of sets of following elements – Caller Id
SI	• Number screening indicator. • Values: – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network
numType	• Number type. • Values: – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension

numPlan	• Number plan. • Values: – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
numLen	• Provides the length of number which follow.
number[255]	• number of numLen length, NULL terminated.

8.1579.2 Field Documentation

8.1579.2.1 uint8_t voice_calledPartyInfo::number[255]

8.1579.2.2 uint8_t voice_calledPartyInfo::numLen

8.1579.2.3 uint8_t voice_calledPartyInfo::numPlan

8.1579.2.4 uint8_t voice_calledPartyInfo::numType

8.1579.2.5 uint8_t voice_calledPartyInfo::PI

8.1579.2.6 uint8_t voice_calledPartyInfo::SI

8.1580 voice_calledPartySubAdd Struct Reference

Data Fields

- uint8_t extBit
- uint8_t subAddrType
- uint8_t oddEvenInd
- uint8_t subAddrLen
- uint8_t subAddr [255]

8.1580.1 Detailed Description

This structure contains information about the Called Sub Party Addresses.

Parameters

extBit	• Extension bit.
subAddrType	• Subaddress type. – 0x00 - NSAP – 0x01 - USER
oddEvenInd	• Even/odd indicator. – 0x00 - Even number of address signals – 0x01 - Odd number of address signals
subAddrLen	• Number of sets of the following elements: – SubAddress
subAddr[MAX_VOICE_DESCRIPTION_LENGTH]	• Array of the SubAddress in BCD number format.

8.1580.2 Field Documentation

8.1580.2.1 uint8_t voice_calledPartySubAdd::extBit

8.1580.2.2 uint8_t voice_calledPartySubAdd::oddEvenInd

8.1580.2.3 uint8_t voice_calledPartySubAdd::subAddr[255]

8.1580.2.4 uint8_t voice_calledPartySubAdd::subAddrLen

8.1580.2.5 uint8_t voice_calledPartySubAdd::subAddrType

8.1581 voice_callerIDInfo Struct Reference

Data Fields

- uint8_t PI
- uint8_t callerIDLen
- uint8_t callerID [255]

8.1581.1 Detailed Description

This structure contains Caller ID Information

Parameters

PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.

callerIDLen	• Number of sets of following elements – Caller Id
pCallerID	• Caller ID in ASCII string.

8.1581.2 Field Documentation

8.1581.2.1 uint8_t voice_callerIDInfo::callerID[255]

8.1581.2.2 uint8_t voice_callerIDInfo::callerIDLen

8.1581.2.3 uint8_t voice_callerIDInfo::PI

8.1582 voice_callFwdTypeAndPlan Struct Reference

Data Fields

- uint8_t numberType
- uint8_t numberPlan

8.1582.1 Detailed Description

This structure contains Supplementary Service request parameters related to different features and their activation, deactivation, registration and erasure (applicable only for 3GPP)

Parameters

numberType	• Call forwarding number type – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION Reserved extension
numberPlan	• Call forwarding number plan – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION Reserved extension

8.1582.2 Field Documentation

8.1582.2.1 uint8_t voice_callFwdTypeAndPlan::numberPlan

8.1582.2.2 uint8_t voice_callFwdTypeAndPlan::numberType

8.1583 voice_callFWExtInfo Struct Reference

Data Fields

- uint8_t SvcStatus
- uint8_t SvcClass
- uint8_t noReplyTimer
- uint8_t PI
- uint8_t SI
- uint8_t numType
- uint8_t numPlan
- uint8_t numLen
- uint8_t number [255]

8.1583.1 Detailed Description

This structure contains information for Get Call Forwarding Extended Information.

Parameters

SvcStatus	• Service status. Values: – 0x00 - SERVICE_STATUS_INACTIVE - Inactive – 0x01 - SERVICE_STATUS_ACTIVE - Active
SvcClass	• Service Class is a combination (sum) of information class constants • See qaGobiApiTableSupServiceInfoClasses.h for service classes.
noReplyTimer	• No reply timer value in seconds • A value of 0 indicates that no_reply_timer is ignored.
PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.
SI	• Number screening indicator. • Values: – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network

numType	• Number type. • Values: – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension
numPlan	• Number plan. • Values: – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
numLen	• Provides the length of number which follow.
number[255]	• number of numLen length, NULL terminated.

8.1583.2 Field Documentation

8.1583.2.1 uint8_t voice_callFWExtInfo::noReplyTimer

8.1583.2.2 uint8_t voice_callFWExtInfo::number[255]

8.1583.2.3 uint8_t voice_callFWExtInfo::numLen

8.1583.2.4 uint8_t voice_callFWExtInfo::numPlan

8.1583.2.5 uint8_t voice_callFWExtInfo::numType

8.1583.2.6 uint8_t voice_callFWExtInfo::PI

8.1583.2.7 uint8_t voice_callFWExtInfo::SI

8.1583.2.8 uint8_t voice_callFWExtInfo::SvcClass

8.1583.2.9 uint8_t voice_callFWExtInfo::SvcStatus

8.1584 voice_callFWInfo Struct Reference

Data Fields

- uint8_t SvcStatus
- uint8_t SvcClass
- uint8_t numLen
- uint8_t number [255]
- uint8_t noReplyTimer

8.1584.1 Detailed Description

This structure contains information for Get Call Forwarding Information.

Parameters

SvcStatus	• Service status. Values: – 0x00 - SERVICE_STATUS_INACTIVE - Inactive – 0x01 - SERVICE_STATUS_ACTIVE - Active
SvcClass	• Service Class is a combination (sum) of information class constants • See qaGobiApiTableSupServiceInfoClasses.h for service classes.
numLen	• Provides the length of number which follow.
number[255]	• number of numLen length, NULL terminated.
noReplyTimer	• No reply timer value in seconds • A value of 0 indicates that noReplyTimer is ignored.

8.1584.2 Field Documentation

8.1584.2.1 uint8_t voice_callFWInfo::noReplyTimer

8.1584.2.2 uint8_t voice_callFWInfo::number[255]

8.1584.2.3 uint8_t voice_callFWInfo::numLen

8.1584.2.4 uint8_t voice_callFWInfo::SvcClass

8.1584.2.5 uint8_t voice_callFWInfo::SvcStatus

8.1585 voice_callInfo Struct Reference

Data Fields

- uint8_t callID

- uint8_t callState
- uint8_t callType
- uint8_t direction
- uint8_t mode

8.1585.1 Detailed Description

This structure contains Information about call state changes. For example, when an incoming call is received, this structure is populated and indicate the incoming call information. When this incoming call is answered, the call status changes from INCOMING to CONVERSATION, which means a change in the call information and this structure is populated again with the changes and notified to/retrived by the user.

Parameters

callID	• Call identifier for the call queried for information. • If zero(0) then invalid.
callState	• Call state. – 0x01 - CALL_STATE_ORIGINATION - Origination – 0x02 - CALL_STATE_INCOMING - Incoming – 0x03 - CALL_STATE_CONVERSATION - Conversation – 0x04 - CALL_STATE_CC_IN_PROGRESS - Call is originating but waiting for call control to complete – 0x05 - CALL_STATE_ALERTING - Alerting – 0x06 - CALL_STATE_HOLD - Hold – 0x07 - CALL_STATE_WAITING - Waiting – 0x08 - CALL_STATE_DISCONNECTING - Disconnecting – 0x09 - CALL_STATE_END - End – 0x0A - CALL_STATE_SETUP - MT call is in Setup state in 3GPP – 0xFF - Not Available
callType	• Call type. – 0x00 - CALL_TYPE_VOICE - Voice – 0x02 - CALL_TYPE_VOICE_IP - Voice over IP – 0x06 - CALL_TYPE_OTAPA - OTAPA – 0x07 - CALL_TYPE_STD_OTASP - Standard OTASP – 0x08 - CALL_TYPE_NON_STD_OTASP - Nonstandard OTASP – 0x09 - CALL_TYPE_EMERGENCY - Emergency – 0xFF - Not Available
direction	• Direction. – 0x01 - CALL_DIRECTION_MO - MO call – 0x02 - CALL_DIRECTION_MT - MT call – 0xFF - Not Available

mode	• Mode. • If the mode field is "0x01 - CDMA",the optional Service Option, Voice Privacy, and OTASP Status (only for OTASP calls) TLVs are included in the response. – 0x01 - CALL_MODE_CDMA - CDMA – 0x02 - CALL_MODE_GSM - GSM – 0x03 - CALL_MODE_UMTS - UMTS – 0x04 - CALL_MODE_LTE - LTE – 0x05 - CALL_MODE_TDS - TD-SCDMA – 0xFF - Not Available

8.1585.2 Field Documentation

8.1585.2.1 uint8_t voice_callInfo::callID

8.1585.2.2 uint8_t voice_callInfo::callState

8.1585.2.3 uint8_t voice_callInfo::callType

8.1585.2.4 uint8_t voice_callInfo::direction

8.1585.2.5 uint8_t voice_callInfo::mode

8.1586 voice_callingPartyInfo Struct Reference

Data Fields

- uint8_t PI
- uint8_t SI
- uint8_t numType
- uint8_t numPlan
- uint8_t numLen
- uint8_t number [255]

8.1586.1 Detailed Description

This structure contains Calling party Number Information

Parameters

PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.
SI	• Number of sets of following elements – Caller Id

SI	• Number screening indicator. • Values: – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network
numType	• Number type. • Values: – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension
numPlan	• Number plan. • Values: – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
numLen	• Provides the length of number which follow.
number[255]	• number of numLen length, NULL terminated.

8.1586.2 Field Documentation

8.1586.2.1 uint8_t voice_callingPartyInfo::number[255]

8.1586.2.2 uint8_t voice_callingPartyInfo::numLen

8.1586.2.3 uint8_t voice_callingPartyInfo::numPlan

8.1586.2.4 uint8_t voice_callingPartyInfo::numType

8.1586.2.5 uint8_t voice_callingPartyInfo::PI

8.1586.2.6 uint8_t voice_callingPartyInfo::SI

8.1587 voice_ccSUPSType Struct Reference

Data Fields

- uint8_t svcType
- uint8_t reason

8.1587.1 Detailed Description

This structure contains information about the Call Control Supplementary Service Types

Parameters

svcType	• Service type. – 0x01 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_ACTIVATE - Activate – 0x02 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_DEACTIVATE - Deactivate – 0x03 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_REGISTER - Register – 0x04 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_ERASE - Erase – 0x05 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_INTERROGATE - Interrogate – 0x06 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_REGISTER_PASSWORD - Register password – 0x07 - VOICE_CC_SUPS_RESULT_SERVICE_TYPE_USSD - USSD – 0xFF - Not Available
reason	• Call control supplementary service result reason • Values: – See qaGobiApiTableCallControlReturnReasons.h for return reasons.

8.1587.2 Field Documentation

8.1587.2.1 uint8_t voice_ccSUPSType::reason

8.1587.2.2 uint8_t voice_ccSUPSType::svcType

8.1588 voice_CLIPResp Struct Reference

Data Fields

- uint8_t ActiveStatus
- uint8_t ProvisionStatus

8.1588.1 Detailed Description

This structure contains information about the Calling Line Identification Presentation (CLIP) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available
ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED - Provisioned – 0xFF - Not Available

8.1588.2 Field Documentation

8.1588.2.1 uint8_t voice_CLIPResp::ActiveStatus

8.1588.2.2 uint8_t voice_CLIPResp::ProvisionStatus

8.1589 voice_CLIRResp Struct Reference

Data Fields

- uint8_t ActiveStatus
- uint8_t ProvisionStatus

8.1589.1 Detailed Description

This structure contains information about the Calling Line Identification Restriction (CLIR) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available

ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED_PERMANENT - Permanently provisioned – 0x02 - PROVISION_STATUS_PRESENTATION_RESTRICTED - Restricted presentation – 0x03 - PROVISION_STATUS_PRESENTATION_ALLOWED - Allowed presentation – 0xFF - Not Available

8.1589.2 Field Documentation

8.1589.2.1 uint8_t voice_CLIRResp::ActiveStatus

8.1589.2.2 uint8_t voice_CLIRResp::ProvisionStatus

8.1590 voice_CNAPResp Struct Reference

Data Fields

- uint8_t ActiveStatus
- uint8_t ProvisionStatus

8.1590.1 Detailed Description

This structure contains information about the Calling Name Presentation (CNAP) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available
ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED - Provisioned – 0xFF - Not Available

8.1590.2 Field Documentation

8.1590.2.1 uint8_t voice_CNAPResp::ActiveStatus

8.1590.2.2 uint8_t voice_CNAPResp::ProvisionStatus

8.1591 voice_COLPResp Struct Reference

Data Fields

- uint8_t ActiveStatus
- uint8_t ProvisionStatus

8.1591.1 Detailed Description

This structure contains information about the Connected Line Identification Presentation (COLP) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available
ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED - Provisioned – 0xFF - Not Available

8.1591.2 Field Documentation

8.1591.2.1 uint8_t voice_COLPResp::ActiveStatus

8.1591.2.2 uint8_t voice_COLPResp::ProvisionStatus

8.1592 voice_COLRResp Struct Reference

Data Fields

- uint8_t ActiveStatus
- uint8_t ProvisionStatus

8.1592.1 Detailed Description

This structure contains information about the Connected Line Identification Restriction (COLR) supplementary service responses.

Parameters

ActiveStatus	• Active status. • Values: – 0x00 - ACTIVE_STATUS_INACTIVE - Inactive – 0x01 - ACTIVE_STATUS_ACTIVE - Active – 0xFF - Not Available
ProvisionStatus	• Provisioned status. • Values: – 0x00 - PROVISION_STATUS_NOT_PROVISIONED - Not provisioned – 0x01 - PROVISION_STATUS_PROVISIONED - Provisioned – 0xFF - Not Available

8.1592.2 Field Documentation

8.1592.2.1 uint8_t voice_COLRResp::ActiveStatus

8.1592.2.2 uint8_t voice_COLRResp::ProvisionStatus

8.1593 voice_connectNumInfo Struct Reference

Data Fields

- uint8_t numPresInd
- uint8_t screeningInd
- uint8_t numType
- uint8_t numPlan
- uint8_t callerIDLen
- uint8_t callerID [81]

8.1593.1 Detailed Description

This structure contains information about the numbers connected to a device. It contains information such as number type, eg International or Local.

Parameters

numPresInd	• Presentation indicator – 0x00 - PRESENTATION_ALLOWED - Allowed presentation – 0x01 - PRESENTATION_RESTRICTED - Restricted presentation – 0x02 - PRESENTATION_NUM_UNAVAILABLE - Unavailable presentation – 0x04 - PRESENTATION_PAYPHONE - Payphone presentation (GSM/UMTS specific) – 0xFF - Not Available

screeningInd	• Screening indicator. – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network – 0xFF - Not Available
numType	• Number type. – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension – 0xFF - Not Available
numPlan	• Number plan. – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension – 0xFF - Not Available
callerIDLen	• Provides the length of caller ID which follow. • If zero(0) then no further information exists.
callerID[MAX_VOICE_CALL_NO_LEN]	• callerID of numLen length, NULL terminated.

8.1593.2 Field Documentation

8.1593.2.1 uint8_t voice_connectNumInfo::callerID[81]

8.1593.2.2 uint8_t voice_connectNumInfo::callerIDLen

8.1593.2.3 uint8_t voice_connectNumInfo::numPlan

8.1593.2.4 uint8_t voice_connectNumInfo::numPresInd

8.1593.2.5 uint8_t voice_connectNumInfo::numType

8.1593.2.6 uint8_t voice_connectNumInfo::screeningInd

8.1594 voice_CUGInfo Struct Reference

Data Fields

- uint16_t CUGIndex
- uint8_t SuppPrefCUG
- uint8_t SuppOA

8.1594.1 Detailed Description

This structure contains Closed User Group Information

Parameters

CUGIndex	• Range 0x00... 0x7FFF
SuppPrefCUG	• Suppress preferential CUG – 0x00 - FALSE – 0x01 - TRUE
SuppOA	• Suppress OA subscription option – 0x00 - FALSE – 0x01 - TRUE

8.1594.2 Field Documentation

8.1594.2.1 uint16_t voice_CUGInfo::CUGIndex

8.1594.2.2 uint8_t voice_CUGInfo::SuppOA

8.1594.2.3 uint8_t voice_CUGInfo::SuppPrefCUG

8.1595 voice_curAMRConfig Struct Reference

Data Fields

- uint8_t gsmAmrStat
- uint8_t wcdmaAmrStat

8.1595.1 Detailed Description

This structure contains the Current Adaptive Multi Rate Configuration Information.

Parameters

gsmAmrStat	• GSM AMR Status – 0x00 - Disable – 0x01 - Enable – 0xFF - Not Available
wcdmaAmrStat	• WCDMA AMR Status • One or a combination of the following bitmask values: – Bit 0 - AMR codec advertised is not supported – Bit 1 - Controls WCDMA AMR wideband – Bit 2 - Controls GSM half rate AMR – Bit 3 - Controls GSM AMR wideband – Bit 4 - Controls GSM AMR narrowband • 0xFF, if not available

8.1595.2 Field Documentation

8.1595.2.1 uint8_t voice_curAMRConfig::gsmAmrStat

8.1595.2.2 uint8_t voice_curAMRConfig::wcdmaAmrStat

8.1596 voice_diagInfo Struct Reference

Data Fields

- uint8_t diagInfoLen
- uint8_t diagnosticInfo [255]

8.1596.1 Detailed Description

This structure contains Diagnostic Information

Parameters

diagInfoLen	• Provides the length of information which follow. • If zero(0) then no further information exists.
diagnosticInfo[MAX_VOICE_DESCRIPTION_LENGTH]	• Diagnostic information.

8.1596.2 Field Documentation

8.1596.2.1 uint8_t voice_diagInfo::diagInfoLen

8.1596.2.2 uint8_t voice_diagInfo::diagnosticInfo[255]

8.1597 voice_DTMFInfo Struct Reference

Data Fields

- uint8_t callID
- uint8_t DTMFEvent
- uint8_t digitCnt
- uint8_t digitBuff [255]

8.1597.1 Detailed Description

This structure contains information about the DTMF (Dual Tone Multi-Frequency).

Parameters

callID	• Call identifier for the current call.
DTMFEvent	• DTMF event – 0x00 - DTMF_EVENT_REV_BURST - Sends a CDMA-burst DTMF – 0x01 - DTMF_EVENT_REV_START_CONT - Starts a continuous DTMF tone – 0x03 - DTMF_EVENT_REV_STOP_CONT - Stops a continuous DTMF tone – 0x05 - DTMF_EVENT_FWD_BURST - Received a CDMA-burst DTMF message – 0x06 - DTMF_EVENT_FWD_START_CONT - Received a start-continuous DTMF tone order – 0x07 - DTMF_EVENT_FWD_STOP_CONT - Received a stop-continuous DTMF tone order
digitCnt	• Number of set of following element i.e. digitBuff.
digitBuff[MAX_VOICE_DESCRIPTION_LENGTH]	• DTMF digit buffer in ASCII string which is NULL terminated

8.1597.2 Field Documentation

8.1597.2.1 uint8_t voice_DTMFInfo::callID

8.1597.2.2 uint8_t voice_DTMFInfo::digitBuff[255]

8.1597.2.3 uint8_t voice_DTMFInfo::digitCnt

8.1597.2.4 uint8_t voice_DTMFInfo::DTMFEvent

8.1598 voice_DTMFLengths Struct Reference

Data Fields

- uint8_t DTMFPulseWidth
- uint8_t DTMFInterdigitInterval

8.1598.1 Detailed Description

This structure contains Voice Burst DTMF pulse length information

Parameters

DTMFPulse-Width	• DTMF pulse width. Values: – 0x00 - DTMF_ONLENGTH_95MS - 95 ms – 0x01 - DTMF_ONLENGTH_150MS - 150 ms – 0x02 - DTMF_ONLENGTH_200MS - 200 ms – 0x03 - DTMF_ONLENGTH_250MS - 250 ms – 0x04 - DTMF_ONLENGTH_300MS - 300 ms – 0x05 - DTMF_ONLENGTH_350MS - 350 ms – 0x06 - DTMF_ONLENGTH_SMS SMS Tx special pulse width
DTMFInterdigit-Interval	• DTMF interdigit interval Values: – 0x00 - DTMF_OFFLENGTH_60MS - 60 ms – 0x01 - DTMF_OFFLENGTH_100MS - 100 ms – 0x02 - DTMF_OFFLENGTH_150MS - 150 ms – 0x03 - DTMF_OFFLENGTH_200MS - 200 ms

8.1598.2 Field Documentation

8.1598.2.1 uint8_t voice_DTMFLengths::DTMFInterdigitInterval

8.1598.2.2 uint8_t voice_DTMFLengths::DTMFPulseWidth

8.1599 voice_ECTNum Struct Reference

Data Fields

- uint8_t ECTCallState
- uint8_t presentationInd
- uint8_t number [81]

8.1599.1 Detailed Description

Contains the parameters passed for Explicit Communication Transfer by the device.

Parameters

ECTCallState	• ECT call state: – 0x00 - ECT_CALL_STATE_NONE - None – 0x01 - ECT_CALL_STATE_ALERTING - Alerting – 0x02 - ECT_CALL_STATE_ACTIVE - Active

presentationInd	• Presentation indicator – 0x00 - presentationAllowedAddress – 0x01 - presentationRestricted – 0x02 - numberNotAvailable – 0x04 - presentationRestrictedAddress
number	• Number in ASCII characters terminated by NULL

8.1599.2 Field Documentation

8.1599.2.1 uint8_t voice_ECTNum::ECTCallState

8.1599.2.2 uint8_t voice_ECTNum::number[81]

8.1599.2.3 uint8_t voice_ECTNum::presentationInd

8.1600 voice_extDispRecInfo Struct Reference

Data Fields

- uint8_t dispType
- uint8_t extDispInfoLen
- uint8_t extDispInfo [255]

8.1600.1 Detailed Description

This structure contains Line Control Information

Parameters

dispType	• Values are per [S1, Table 3.7.5.16-1].
extDispInfoLen	• Number of sets of the following elements: – ext_display_info
extDispInfo	• Extended display information buffer containing the display record; refer to [S1, Section 3.7.5.16] for the format information of the buffer contents.

8.1600.2 Field Documentation

8.1600.2.1 uint8_t voice_extDispRecInfo::dispType

8.1600.2.2 uint8_t voice_extDispRecInfo::extDispInfo[255]

8.1600.2.3 uint8_t voice_extDispRecInfo::extDispInfoLen

8.1601 voice_getAllCallInformation Struct Reference

Data Fields

- voice_callInfo CallInfo
- uint8_t isEmpty
- uint8_t ALS

8.1601.1 Detailed Description

This structure contains information related to call state change.

Parameters

CallInfo	• See voice_callInfo for more information.
isEmpty	• Multiparty indicator. – 0x00 - False – 0x01 - True
ALS	• Alternate Line Service line indicator. • Feature for supporting two different phone numbers on the same mobile device. – 0x00 - ALS_LINE1 - Line 1 (default) – 0x01 - ALS_LINE2 - Line 2

8.1601.2 Field Documentation

8.1601.2.1 uint8_t voice_getAllCallInformation::ALS

8.1601.2.2 voice_callInfo voice_getAllCallInformation::CallInfo

8.1601.2.3 uint8_t voice_getAllCallInformation::isEmpty

8.1602 voice_getAllCallRmtPtyName Struct Reference

Data Fields

- uint8_t callID
- voice_remotePartyName RemotePartyName

8.1602.1 Detailed Description

This structure contains information for All Call Remote Party Names

Parameters

callID	• Unique call identifier for the call.
RemoteParty-Name	• See voice_remotePartyName for more information.

8.1602.2 Field Documentation

8.1602.2.1 uint8_t voice_getAllCallRmtPtyName::callID

8.1602.2.2 voice_remotePartyName voice_getAllCallRmtPtyName::RemotePartyName

8.1603 voice_getAllCallRmtPtyNum Struct Reference

Data Fields

- uint8_t callID
- voice_remotePartyNum RemotePartyNum

8.1603.1 Detailed Description

This structure contains information for All Call Remote Party Numbers

Parameters

callID	• Unique call identifier for the call.
RemoteParty-Num	• See voice_remotePartyNum for more information.

8.1603.2 Field Documentation

8.1603.2.1 uint8_t voice_getAllCallRmtPtyNum::callID

8.1603.2.2 voice_remotePartyNum voice_getAllCallRmtPtyNum::RemotePartyNum

8.1604 voice_getCallFWExtInfo Struct Reference

Data Fields

- uint8_t numInstances
- voice_callFWExtInfo CallFWExtInfo [20]

8.1604.1 Detailed Description

This structure contains an array of Call Forwarded Extended Information.

Parameters

numInstances	• Number of callFWExtInfo that follow. • If zero(0) then no further information exists.
CallFWExtInfo[VOICE_MAX_NO_OF_CALLS]	• Array of CallFWExtInfo. – See voice_callFWExtInfo for more information.

8.1604.2 Field Documentation

8.1604.2.1 voice_callFWExtInfo voice_getCallFWExtInfo::CallFWExtInfo[20]

8.1604.2.2 uint8_t voice_getCallFWExtInfo::numInstances

8.1605 voice_getCallFWInfo Struct Reference

Data Fields

- uint8_t numInstances
- voice_callFWInfo CallFWInfo [20]

8.1605.1 Detailed Description

This structure contains an array of Call Forwarded Information.

Parameters

numInstances	• Number of callFWInfo that follow. • If zero(0) then no further information exists.
CallFWInfo[VOICE_MAX_NO_OF_CALLS]	• Array of callFWInfo. – See voice_callFWInfo for more information.

8.1605.2 Field Documentation

8.1605.2.1 voice_callFWInfo voice_getCallFWInfo::CallFWInfo[20]

8.1605.2.2 uint8_t voice_getCallFWInfo::numInstances

8.1606 voice_lineCtrlInfo Struct Reference

Data Fields

- uint8_t polarityIncluded
- uint8_t toggleMode
- uint8_t revPolarity
- uint8_t pwrDenialTime

8.1606.1 Detailed Description

This structure contains Line Control Information

Parameters

polarityIncluded	• Included Polarity; Boolean Value
toggleMode	• Toggle mode; Boolean Value
revPolarity	• Reverse Polarity; Boolean Value
pwrDenialTime	• Power denial time; refer to [S1, Section 3.7.5.15 Line Control] for valid values

8.1606.2 Field Documentation

8.1606.2.1 uint8_t voice_lineCtrlInfo::polarityIncluded

8.1606.2.2 uint8_t voice_lineCtrlInfo::pwrDenialTime

8.1606.2.3 uint8_t voice_lineCtrlInfo::revPolarity

8.1606.2.4 uint8_t voice_lineCtrlInfo::toggleMode

8.1607 voice_newPwdData Struct Reference

Data Fields

- uint8_t newPwd [4]
- uint8_t newPwdAgain [4]

8.1607.1 Detailed Description

This structure contains New Password Data.

Parameters

newPwd[BARRING_PASSWORD_LENGTH]	• New password. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.
newPwdAgain[BARRING_PASSWORD_LENGTH]	• New password again. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.

8.1607.2 Field Documentation

8.1607.2.1 uint8_t voice_newPwdData::newPwd[4]

8.1607.2.2 uint8_t voice_newPwdData::newPwdAgain[4]

8.1608 voice_NSSAudioCtrl Struct Reference

Data Fields

- uint8_t upLink
- uint8_t downLink

8.1608.1 Detailed Description

This structure contains National Supplementary Services - Audio Control Information

Parameters

upLink	• Values as per[S24, 4.10 Reservation response].
downLink	• Values as per[S24, 4.10 Reservation response].

8.1608.2 Field Documentation

8.1608.2.1 uint8_t voice_NSSAudioCtrl::downLink

8.1608.2.2 uint8_t voice_NSSAudioCtrl::upLink

8.1609 voice_peerNumberInfo Struct Reference

Data Fields

- uint8_t callID
- uint8_t numPI
- uint8_t numSI
- uint8_t numType
- uint8_t numPlan
- uint8_t numLen
- uint8_t number [81]

8.1609.1 Detailed Description

This structure contains information for Connected Peer Numbers.

Parameters

callID	• Unique call identifier for the call.

numPI	• Number presentation indicator. – 0x00 - PRESENTATION_ALLOWED - Allowed presentation – 0x01 - PRESENTATION_RESTRICTED - Restricted presentation – 0x02 - PRESENTATION_NUM_UNAVAILABLE - Unavailable presentation – 0x04 - PRESENTATION_PAYPHONE - Payphone presentation (GSM/UMTS specific) – 0xFF - Not Available
numSI	• Number screening indicator. – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network
numType	• Number type. – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension
numPlan	• Number plan. – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
numLen	• Provides the length of number which follow.
number[MAX_VOICE_CALL_NO_LEN]	• number of numLen length, NULL terminated.

8.1609.2 Field Documentation

8.1609.2.1 uint8_t voice_peerNumberInfo::callID

8.1609.2.2 uint8_t voice_peerNumberInfo::number[81]

8.1609.2.3 uint8_t voice_peerNumberInfo::numLen

8.1609.2.4 uint8_t voice_peerNumberInfo::numPI

8.1609.2.5 uint8_t voice_peerNumberInfo::numPlan

8.1609.2.6 uint8_t voice_peerNumberInfo::numSI

8.1609.2.7 uint8_t voice_peerNumberInfo::numType

8.1610 voice_prefVoiceSO Struct Reference

Data Fields

- uint8_t namID
- uint8_t evrcCapability
- uint16_t homePageVoiceSO
- uint16_t homeOrigVoiceSO
- uint16_t roamOrigVoiceSO

8.1610.1 Detailed Description

This structure contains information about the Preferred Voice Service Options.

Parameters

namID	• Index of the NAM(Number Assignment Module) to be configured. • Range 0 to 3. • Some modems support only 1 or 2 NAMs. • 0xFF,if not available.

evrcCapability	• EVRC capability.
	• Values:
	  – 0x00 - Disable
	  – 0x01 - Enable
	  – 0xFF - Not Available

homePageVoiceSO	• Home page voice SO; most preferred CDMA SO to be requested from the network when receiving an incoming (MT) voice call within the home network. • Values: – 0x0000 - VOICE_SO_WILD - Any service option – 0x0001 - VOICE_SO_IS_96A - IS-96A – 0x0003 - VOICE_SO_EVRC - EVRC – 0x0011 - VOICE_SO_13K_IS733 - 13K_IS733 – 0x0038 - VOICE_SO_SELECTABLE_MODE_VOCODER - Selectable mode vocoder – 0x0044 - VOICE_SO_4GV_NARR0W_BAND - 4GV narrowband – 0x0046 - VOICE_SO_4GV_WIDE_BAND - 4GV wideband – 0x8000 - VOICE_SO_13K - 13K – 0x8001 - VOICE_SO_IS_96 - IS-96 – 0x8023 - VOICE_SO_WVRC - WVRC – 0xFFFF - Not Available
homeOrigVoiceSO	• Home origination voice SO; most preferred CDMA SO to be requested from the network when receiving an incoming (MT) voice call within the home network. • Values: – 0x0000 - VOICE_SO_WILD - Any service option – 0x0001 - VOICE_SO_IS_96A - IS-96A – 0x0003 - VOICE_SO_EVRC - EVRC – 0x0011 - VOICE_SO_13K_IS733 - 13K_IS733 – 0x0038 - VOICE_SO_SELECTABLE_MODE_VOCODER - Selectable mode vocoder – 0x0044 - VOICE_SO_4GV_NARR0W_BAND - 4GV narrowband – 0x0046 - VOICE_SO_4GV_WIDE_BAND - 4GV wideband – 0x8000 - VOICE_SO_13K - 13K – 0x8001 - VOICE_SO_IS_96 - IS-96 – 0x8023 - VOICE_SO_WVRC - WVRC – 0xFFFF - Not Available
roamOrigVoiceSO	• Roaming origination voice SO; most preferred CDMA SO to be requested from the network when receiving an incoming (MT) voice call within the home network. • Values: – 0x0000 - VOICE_SO_WILD - Any service option – 0x0001 - VOICE_SO_IS_96A - IS-96A – 0x0003 - VOICE_SO_EVRC - EVRC – 0x0011 - VOICE_SO_13K_IS733 - 13K_IS733 – 0x0038 - VOICE_SO_SELECTABLE_MODE_VOCODER - Selectable mode vocoder – 0x0044 - VOICE_SO_4GV_NARR0W_BAND - 4GV narrowband – 0x0046 - VOICE_SO_4GV_WIDE_BAND - 4GV wideband – 0x8000 - VOICE_SO_13K - 13K – 0x8001 - VOICE_SO_IS_96 - IS-96 – 0x8023 - VOICE_SO_WVRC - WVRC – 0xFFFF - Not Available

8.1610.2 Field Documentation

8.1610.2.1 uint8_t voice_prefVoiceSO::evrcCapability

8.1610.2.2 uint16_t voice_prefVoiceSO::homeOrigVoiceSO

8.1610.2.3 uint16_t voice_prefVoiceSO::homePageVoiceSO

8.1610.2.4 uint8_t voice_prefVoiceSO::namID

8.1610.2.5 uint16_t voice_prefVoiceSO::roamOrigVoiceSO

8.1611 voice_redirNumInfo Struct Reference

Data Fields

- uint8_t PI
- uint8_t SI
- uint8_t numType
- uint8_t numPlan
- uint8_t reason
- uint8_t numLen
- uint8_t number [255]

8.1611.1 Detailed Description

This structure contains Redirecting Number Information

Parameters

PI	• Presentation indicator; refer to [S1, Table 2.7.4.4-1] for valid values.
SI	• Number of sets of following elements – Caller Id
SI	• Number screening indicator. • Values: – 0x00 - QMI_VOICE_SI_USER_PROVIDED_NOT_SCREENED - Provided user is not screened – 0x01 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_PASSED - Provided user passed verification – 0x02 - QMI_VOICE_SI_USER_PROVIDED_VERIFIED_FAILED - Provided user failed verification – 0x03 - QMI_VOICE_SI_NETWORK_PROVIDED - Provided network

numType	• Number type. • Values: – 0x00 - QMI_VOICE_NUM_TYPE_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_TYPE_INTERNATIONAL - International – 0x02 - QMI_VOICE_NUM_TYPE_NATIONAL - National – 0x03 - QMI_VOICE_NUM_TYPE_NETWORK_SPECIFIC - Network-specific – 0x04 - QMI_VOICE_NUM_TYPE_SUBSCRIBER - Subscriber – 0x05 - QMI_VOICE_NUM_TYPE_RESERVED - Reserved – 0x06 - QMI_VOICE_NUM_TYPE_ABBREVIATED - Abbreviated – 0x07 - QMI_VOICE_NUM_TYPE_RESERVED_EXTENSION - Reserved extension
numPlan	• Number plan. • Values: – 0x00 - QMI_VOICE_NUM_PLAN_UNKNOWN - Unknown – 0x01 - QMI_VOICE_NUM_PLAN_ISDN - ISDN – 0x03 - QMI_VOICE_NUM_PLAN_DATA - Data – 0x04 - QMI_VOICE_NUM_PLAN_TELEX - Telex – 0x08 - QMI_VOICE_NUM_PLAN_NATIONAL - National – 0x09 - QMI_VOICE_NUM_PLAN_PRIVATE - Private – 0x0B - QMI_VOICE_NUM_PLAN_RESERVED_CTS - Reserved cordless telephony system – 0x0F - QMI_VOICE_NUM_PLAN_RESERVED_EXTENSION - Reserved extension
reason	-Redirecting reason; refer to [S1, Table 3.7.5.11-1] for valid values
numLen	• Provides the length of number which follow.
number[255]	• number of numLen length, NULL terminated.

8.1611.2 Field Documentation

8.1611.2.1 uint8_t voice_redirNumInfo::number[255]

8.1611.2.2 uint8_t voice_redirNumInfo::numLen

8.1611.2.3 uint8_t voice_redirNumInfo::numPlan

8.1611.2.4 uint8_t voice_redirNumInfo::numType

8.1611.2.5 uint8_t voice_redirNumInfo::PI

8.1611.2.6 uint8_t voice_redirNumInfo::reason

8.1611.2.7 uint8_t voice_redirNumInfo::SI

8.1612 voice_remotePartyName Struct Reference

Data Fields

- uint8_t namePI
- uint8_t codingScheme
- uint8_t nameLen
- uint8_t callerName [255]

8.1612.1 Detailed Description

This structure contains information about the names that are dialed from the device or from which a call is received on the device.

Parameters

namePI	• Name presentation indicator. – 0x00 - PRESENTATION_NAME_PRESENTATION_ALLOWED - Allowed presentation – 0x01 - PRESENTATION_NAME_PRESENTATION_RESTRICTED - Restricted presentation – 0x02 - PRESENTATION_NAME_UNAVAILABLE - Unavailable presentation – 0x03 - PRESENTATION_NAME_NAME_PRESENTATION_RESTRICTED - Restricted name presentation – 0xFF - Not Available
codingScheme	• Refer to Table10 qaGobiApiTableCodingScheme.h for coding schemes • 0xFF - Not Available
nameLen	• Provides the length of name which follow. • If zero(0) then no further information exists.
callerName[MAX_VOICE_DESCRIPTION_LENGTH]	• Name in ASCII, NULL ending.

8.1612.2 Field Documentation

8.1612.2.1 uint8_t voice_remotePartyName::callerName[255]

8.1612.2.2 uint8_t voice_remotePartyName::codingScheme

8.1612.2.3 uint8_t voice_remotePartyName::nameLen

8.1612.2.4 uint8_t voice_remotePartyName::namePI

8.1613 voice_remotePartyNum Struct Reference

Data Fields

- uint8_t presentationInd
- uint8_t numLen
- uint8_t remPartyNumber [81]

8.1613.1 Detailed Description

This structure contains information about the numbers that are dialed from the device or from which a call is received on the device.

Parameters

presentationInd	• Presentation indicator. – 0x00 - PRESENTATION_ALLOWED - Allowed presentation – 0x01 - PRESENTATION_RESTRICTED - Restricted presentation – 0x02 - PRESENTATION_NUM_UNAVAILABLE - Unavailable presentation – 0x04 - PRESENTATION_PAYPHONE - Payphone presentation (GSM/UMTS specific) – 0xFF - Not Available
numLen	• Provides the length of number which follow. • If zero(0) then no further information exists.
remPartyNumber[MAX_CALL_NO_LEN]	• Array of numbers in ASCII, NULL ending.

8.1613.2 Field Documentation

8.1613.2.1 uint8_t voice_remotePartyNum::numLen

8.1613.2.2 uint8_t voice_remotePartyNum::presentationInd

8.1613.2.3 uint8_t voice_remotePartyNum::remPartyNumber[81]

8.1614 voice_roamTimer Struct Reference

Data Fields

- uint8_t namID
- uint32_t roamTimerValue

8.1614.1 Detailed Description

This structure contains information about the Roam Timer.

Parameters

namID	• Index of the NAM(Number Assignment Module) to be configured. • Range 0 to 3. • Some modems support only 1 or 2 NAMs. • 0xFF,if not available.
roamTimerValue	• Time in minutes. • Cumulative air time is slammed. • 0xFFFFFFFF,if not available.

8.1614.2 Field Documentation

8.1614.2.1 uint8_t voice_roamTimer::namID

8.1614.2.2 uint32_t voice_roamTimer::roamTimerValue

8.1615 voice_signalInfo Struct Reference

Data Fields

- uint8_t signalType
- uint8_t alertPitch
- uint8_t signal

8.1615.1 Detailed Description

This structure contains Signal Information

Parameters

signalType	• Call identifier for the call.
alertPitch	• Signal Information
signal	• Caller ID Information

8.1615.2 Field Documentation

8.1615.2.1 uint8_t voice_signalInfo::alertPitch

8.1615.2.2 uint8_t voice_signalInfo::signal

8.1615.2.3 uint8_t voice_signalInfo::signalType

8.1616 voice_SUPSInfo Struct Reference

Data Fields

- uint8_t svcType
- uint8_t isModByCC

8.1616.1 Detailed Description

This structure contains information about the Supplementary Services.

Parameters

svcType	• Service type. – 0x01 - SERVICE_TYPE_ACTIVATE - Activate – 0x02 - SERVICE_TYPE_DEACTIVATE - Deactivate – 0x03 - SERVICE_TYPE_REGISTER - Register – 0x04 - SERVICE_TYPE_ERASE - Erase – 0x05 - SERVICE_TYPE_INTERROGATE - Interrogate – 0x06 - SERVICE_TYPE_REGISTER_PASSWORD - Register password – 0x07 - SERVICE_TYPE_USSD - USSD
isModByCC	• Indicates whether the supplementary service data is modified by the card (SIM/USIM) as part of the call control: – 0 - False – 1 - True

8.1616.2 Field Documentation

8.1616.2.1 uint8_t voice_SUPSInfo::isModByCC

8.1616.2.2 uint8_t voice_SUPSInfo::svcType

8.1617 voice_USSDNotificationNetworkInfo Struct Reference

Data Fields

- uint8_t tlvPresent
- struct voice_USSInfo networkInfo

8.1617.1 Detailed Description

Structure for storing the USS info present in USSDNotification callback.

Parameters

tlvPresent	Values: • 0 - Not present • 1 - Tlv is present

NetworkInfo	• USS Data from Network (See structure voice_USSInfo) • NULL pointer - Invalid data.

8.1617.2 Field Documentation

8.1617.2.1 struct voice_USSInfo voice_USSDNotificationNetworkInfo::networkInfo

8.1617.2.2 uint8_t voice_USSDNotificationNetworkInfo::tlvPresent

8.1618 voice_USSInfo Struct Reference

Data Fields

- uint8_t ussDCS
- uint8_t ussLen
- uint8_t ussData [182]

8.1618.1 Detailed Description

This structure contains USS Information

Parameters

ussDCS	• 1 - ASCII coding scheme • 2 - 8-BIT coding scheme • 3 - UCS2
ussLen	• Range 1 to 182
ussData	• Data encoded as per the DCS

8.1618.2 Field Documentation

8.1618.2.1 uint8_t voice_USSInfo::ussData[182]

8.1618.2.2 uint8_t voice_USSInfo::ussDCS

8.1618.2.3 uint8_t voice_USSInfo::ussLen

8.1619 voice_UUSInfo Struct Reference

Data Fields

- uint8_t UUSType
- uint8_t UUSDcs

- uint8_t UUSDatalen
- uint8_t UUSData [255]

8.1619.1 Detailed Description

This structure contains User to User Signaling Service Information.

Parameters

UUSType	• UUS type values are: – 0x00 - UUS_DATA – 0x01 - UUS_TYPE1_IMPLICIT – 0x02 - UUS_TYPE1_REQUIRED – 0x03 - UUS_TYPE1_NOT_REQUIRED – 0x04 - UUS_TYPE2_REQUIRED – 0x05 - UUS_TYPE2_NOT_REQUIRED – 0x06 - UUS_TYPE3_REQUIRED – 0x07 - UUS_TYPE3_NOT_REQUIRED – 0xFF - Not Available
UUSDcs	• UUS data coding scheme values are: – 0x01 - UUS_DCS_USP – 0x02 - UUS_DCS_OHLP – 0x03 - UUS_DCS_X244 – 0x04 - UUS_DCS_SMCF – 0x05 - UUS_DCS_IA5 – 0x06 - UUS_DCS_RV12RD – 0x07 - UUS_DCS_Q931UNCCM – 0xFF - Not Available
UUSDatalen	• Number of sets of the following elements. – UUSData • If zero(0) then no further information exists.
UUSData[MAX_VOICE_DESCRIPTION_LENGTH]	• UUS data encoded as per coding scheme

8.1619.2 Field Documentation

8.1619.2.1 uint8_t voice_UUSInfo::UUSData[255]

8.1619.2.2 uint8_t voice_UUSInfo::UUSDatalen

8.1619.2.3 uint8_t voice_UUSInfo::UUSDcs

8.1619.2.4 uint8_t voice_UUSInfo::UUSType

8.1620 voiceALSSelectLineInfo Struct Reference

Data Fields

- BYTE lineValue

8.1620.1 Detailed Description

This structure contains ALS Select Line Information Parameters.

Parameters

lineValue	• ALS Line Value. – 0x00 - ALS_LINE1 - Line 1 (default) – 0x01 - ALS_LINE2 - Line 2

8.1620.2 Field Documentation

8.1620.2.1 BYTE voiceALSSelectLineInfo::lineValue

8.1621 voiceALSSetLineSwitchInfo Struct Reference

Data Fields

- BYTE switchOption

8.1621.1 Detailed Description

This structure contains ALS Set Line Switching Information Parameters.

Parameters

switchOption	• Switch Option. – 0x00 - VOICE_LINE_SWITCHING_NOT_ALLOWED - Line switching is not allowed – 0x01 - VOICE_LINE_SWITCHING_ALLOWED - Line switching is allowed

8.1621.2 Field Documentation

8.1621.2.1 BYTE voiceALSSetLineSwitchInfo::switchOption

8.1622 voiceAnswerCall Struct Reference

Data Fields

- BYTE * pCallId

8.1622.1 Detailed Description

Contains the parameters passed for SLQSVoiceAnswerCall.

Parameters

pCallId[IN/OUT]	• Unique call identifier for the call that must be answered.

8.1622.2 Field Documentation

8.1622.2.1 BYTE* voiceAnswerCall::pCallId

8.1623 voiceBindSubscriptionInfo Struct Reference

Data Fields

- BYTE subsType

8.1623.1 Detailed Description

This structure contains Bind Subscription Information Parameters.

Parameters

subsType	• Subscription Type. – 0x00 - VOICE_SUBS_TYPE_PRIMARY - Primary – 0x01 - VOICE_SUBS_TYPE_SECONDARY - Secondary

8.1623.2 Field Documentation

8.1623.2.1 BYTE voiceBindSubscriptionInfo::subsType

8.1624 voiceBurstDTMFInfo Struct Reference

Data Fields

- burstDTMFInfo BurstDTMFInfo
- DTMFLengths * pBurstDTMFLengths

8.1624.1 Detailed Description

This structure contains parameters of burst Dual-Tone Multifrequency (DTMF)

Parameters

BurstDTMFInfo	• Burst DTMF Information – See burstDTMFInfo for more information

pBurstDTMF-Lengths	[optional] • DTMF Lengths – See DTMFLengths for more information

8.1624.2 Field Documentation

8.1624.2.1 burstDTMFInfo voiceBurstDTMFInfo::BurstDTMFInfo

8.1624.2.2 DTMFLengths* voiceBurstDTMFInfo::pBurstDTMFLengths

8.1625 voiceCallInfoReq Struct Reference

Data Fields

- BYTE callID

8.1625.1 Detailed Description

This structure contains information of the request parameters associated with a call.

Parameters

callID	• Call identifier for the call queried for information.

8.1625.2 Field Documentation

8.1625.2.1 BYTE voiceCallInfoReq::callID

8.1626 voiceCallInfoResp Struct Reference

Data Fields

- callInfo * pCallInfo
- remotePartyNum * pRemotePartyNum
- WORD * pSrvOpt
- BYTE * pVoicePrivacy
- BYTE * pOTASPStatus
- remotePartyName * pRemotePartyName
- UUSInfo * pUUSInfo
- BYTE * pAlertType
- alphaIDInfo * pAlphaIDInfo
- connectNumInfo * pConnectNumInfo
- diagInfo * pDiagInfo
- ULONG * pAlertingPattern

8.1626.1 Detailed Description

This structure contains information of the response parameters associated with a call.

Parameters

pCallInfo(optional)	• See callInfo for more information.
pRemotePartyNum(optional)	• See remotePartyNum for more information.
pSrvOpt	• Service option(optional) • Applicable only for 3GPP2 devices. • See Table8 qaGobiApiTableServiceOptions.h for standard service option number assignments.
pVoicePrivacy	• Voice Privacy.(optional) • Applicable only for 3GPP2 devices. • Values. – 0x00 - VOICE_PRIVACY_STANDARD - Standard privacy – 0x01 - VOICE_PRIVACY_ENHANCED - Enhanced privacy – 0xFF - Not Available
pOTASPStatus	• OTASP status for the OTASP call.(optional) • Applicable only for 3GPP2 devices. – 0x00 - OTASP_STATUS_SPL_UNLOCKED - SPL unlocked; only for user-initiated OTASP – 0x01 - OTASP_STATUS_SPRC_RETRIES_EXCEEDED - SPC retries exceeded; only for user-initiated OTASP – 0x02 - OTASP_STATUS_AKEY_EXCHANGED - A-key exchanged; only for user-initiated OTASP – 0x03 - OTASP_STATUS_SSD_UPDATED - SSD updated; for both user-initiated OTASP and network-initiated OTASP (OTAPA) – 0x04 - OTASP_STATUS_NAM_DOWNLOADED - NAM downloaded; only for user-initiated OTASP – 0x05 - OTASP_STATUS_MDN_DOWNLOADED - MDN downloaded; only for user-initiated OTASP – 0x06 - OTASP_STATUS_IMSI_DOWNLOADED - IMSI downloaded; only for user-initiated OTASP – 0x07 - OTASP_STATUS_PRL_DOWNLOADED - PRL downloaded; only for user-initiated OTASP – 0x08 - OTASP_STATUS_COMMITTED - Commit successful; only for user-initiated OTASP – 0x09 - OTASP_STATUS_OTAPA_STARTED - OTAPA started; only for network-initiated OTASP (OTAPA) – 0x0A - OTASP_STATUS_OTAPA_STOPPED - OTAPA stopped; only for network-initiated OTASP (OTAPA) – 0x0B - OTASP_STATUS_OTAPA_ABORTED - OTAPA aborted; only for network-initiated OTASP (OTAPA) – 0x0C - OTASP_STATUS_OTAPA_COMMITTED - OTAPA committed; only for network-initiated OTASP (OTAPA) – 0xFF - Not Available
pRemotePartyName(optional)	• Applicable only for 3GPP devices. • See remotePartyName for more information.

pUUS-Info(optional)	• Applicable only for 3GPP devices. • See UUSInfo for more information.
pAlert-Type(optional)	• Alerting type. • Applicable only for 3GPP devices. – 0x00 - ALERTING_LOCAL - Local – 0x01 - ALERTING_REMOTE - Remote – 0xFF - Not Available
pAlphaID-Info(optional)	• Applicable only for 3GPP devices. • See alphaIDInfo for more information.
pConnectNum-Info(optional)	• See connectNumInfo for more information.
pDiag-Info(optional)	• See diagInfo for more information.
pAlertingPattern	• Alerting pattern.(optional) – 0x00 - QMI_VOICE_ALERTING_PATTERN_1 - Pattern 1 – 0x01 - QMI_VOICE_ALERTING_PATTERN_2 - Pattern 2 – 0x02 - QMI_VOICE_ALERTING_PATTERN_3 - Pattern 3 – 0x04 - QMI_VOICE_ALERTING_PATTERN_5 - Pattern 5 – 0x05 - QMI_VOICE_ALERTING_PATTERN_6 - Pattern 6 – 0x06 - QMI_VOICE_ALERTING_PATTERN_7 - Pattern 7 – 0x07 - QMI_VOICE_ALERTING_PATTERN_8 - Pattern 8 – 0x08 - QMI_VOICE_ALERTING_PATTERN_9 - Pattern 9 – 0xFF - Not Available

8.1626.2 Field Documentation

8.1626.2.1 ULONG* voiceCallInfoResp::pAlertingPattern

8.1626.2.2 BYTE* voiceCallInfoResp::pAlertType

8.1626.2.3 alphaIDInfo* voiceCallInfoResp::pAlphaIDInfo

8.1626.2.4 callInfo* voiceCallInfoResp::pCallInfo

8.1626.2.5 connectNumInfo* voiceCallInfoResp::pConnectNumInfo

8.1626.2.6 diagInfo* voiceCallInfoResp::pDiagInfo

8.1626.2.7 BYTE* voiceCallInfoResp::pOTASPStatus

8.1626.2.8 remotePartyName* voiceCallInfoResp::pRemotePartyName

8.1626.2.9 remotePartyNum∗ voiceCallInfoResp::pRemotePartyNum

8.1626.2.10 WORD∗ voiceCallInfoResp::pSrvOpt

8.1626.2.11 UUSInfo∗ voiceCallInfoResp::pUUSInfo

8.1626.2.12 BYTE∗ voiceCallInfoResp::pVoicePrivacy

8.1627 voiceCallRequestParams Struct Reference

Data Fields

- BYTE callNumber [81]
- BYTE ∗ pCallType
- BYTE ∗ pCLIRType
- UUSInfo ∗ pUUSInFo
- CUGInfo ∗ pCUGInfo
- BYTE ∗ pEmergencyCategory
- calledPartySubAdd ∗ pCallPartySubAdd
- ULONG ∗ pSvcType

8.1627.1 Detailed Description

This structure contains Voice Call Request Parameters

Parameters

callNumber[81]	• Number to be dialed in ASCII string, NULL terminated. • Length Range [1 to 81]
pCall-Type(optional)	• the type of call to be dialed. CALL_TYPE_VOICE is automatically selected if this parameter is not provided. When CALL_TYPE_NON_STD_OTASP is selected, the call is sent as a nonstandard OTASP call regardless of the digit string Call type values are: – 0x00 - CALL_TYPE_VOICE - Voice (automatic selection) – 0x01 - CALL_TYPE_VOICE_FORCED - Avoid modem call classification – 0x08 - CALL_TYPE_NON_STD_OTASP - Nonstandard OTASP∗ – 0x09 - CALL_TYPE_EMERGENCY - Emergency
pCLIR-Type(optional)	• CLIR type values are: – 0x01 - CLIR_SUPPRESSION - Suppression – 0x02 - CLIR_INVOCATION - Invocation
pUUSIn-Fo(optional)	• Pointer to structure of UUSInfo – See UUSInfo for more information
pCUG-Info(optional)	• Pointer to structure of CUGInfo – See CUGInfo for more information

pEmergency-Category(optional)	• Bit mask of emergency number categories. This is only applicable when the call type is set to Emergency. – Bit 0 - VOICE_EMER_CAT_POLICE_BIT - Police – Bit 1 - VOICE_EMER_CAT_AMBULANCE_BIT - Ambulance – Bit 2 - VOICE_EMER_CAT_FIRE_BRIGADE_BIT- Fire brigade – Bit 3 - VOICE_EMER_CAT_MARINE_GUARD_BIT - Marine guard – Bit 4 - VOICE_EMER_CAT_MOUNTAIN_RESCUE_BIT - Mountain rescue – Bit 5 - VOICE_EMER_CAT_MANUAL_ECALL_BIT - Manual emergency call – Bit 6 - VOICE_EMER_CAT_AUTO_ECALL_BIT - Automatic emergency call – Bit 7 - VOICE_EMER_CAT_SPARE_BIT - Spare bit
pCallPartySub-Add(optional)	• Pointer to structure of calledPartySubAdd – See calledPartySubAdd for more information
pSvc-Type(optional)	• Service Type. – 0x01 - VOICE_DIAL_CALL_SRV_TYPE_AUTOMATIC - Automatic – 0x02 - VOICE_DIAL_CALL_SRV_TYPE_GSM - GSM – 0x03 - VOICE_DIAL_CALL_SRV_TYPE_WCDMA - WCDMA – 0x04 - VOICE_DIAL_CALL_SRV_TYPE_CDMA_AUTOMATIC - CDMA automatic – 0x05 - VOICE_DIAL_CALL_SRV_TYPE_GSM_WCDMA - GSM or WCDMA – 0x06 - VOICE_DIAL_CALL_SRV_TYPE_LTE -LTE

8.1627.2 Field Documentation

8.1627.2.1 BYTE voiceCallRequestParams::callNumber[81]

8.1627.2.2 calledPartySubAdd* voiceCallRequestParams::pCallPartySubAdd

8.1627.2.3 BYTE* voiceCallRequestParams::pCallType

8.1627.2.4 BYTE* voiceCallRequestParams::pCLIRType

8.1627.2.5 CUGInfo* voiceCallRequestParams::pCUGInfo

8.1627.2.6 BYTE* voiceCallRequestParams::pEmergencyCategory

8.1627.2.7 ULONG* voiceCallRequestParams::pSvcType

8.1627.2.8 UUSInfo* voiceCallRequestParams::pUUSInFo

8.1628 voiceCallResponseParams Struct Reference

Data Fields

- BYTE * pCallID
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCCResultType
- ccSUPSType * pCCSUPSType

8.1628.1 Detailed Description

This structure contains Voice Call Response Parameters

Parameters

pCallID(optional)	• Unique call identifier for the dialed call
pAlphaID-Info(optional)	• Pointer to structure of alphaIDInfo – See alphaIDInfo for more information
pCCResult-Type(optional)	• Call Control Result Type. – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service
pCCSUPS-Type(optional)	• Pointer to structure of ccSUPSType • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information

8.1628.2 Field Documentation

8.1628.2.1 alphaIDInfo∗ voiceCallResponseParams::pAlphaIDInfo

8.1628.2.2 BYTE∗ voiceCallResponseParams::pCallID

8.1628.2.3 BYTE∗ voiceCallResponseParams::pCCResultType

8.1628.2.4 ccSUPSType∗ voiceCallResponseParams::pCCSUPSType

8.1629 voiceContDTMFinfo Struct Reference

Data Fields

- BYTE ∗ pCallID
- BYTE DTMFdigit

8.1629.1 Detailed Description

This structure contains parameters of continuous DTMF

Parameters

pCallID[IN/OUT]	• Call ID associated with call on which the DTMF information has to be sent. Start continuous DTMF request is sent to the current active/alerting call when pCallId is set to 0xFF. • This is IN/OUT parameter, value passed by user will be packed in request and value received from the device would be returned to the user. • If the call ID value received is 0, no value has been returned by the device
DTMFdigit[IN]	• DTMF digit in ASCII.

8.1629.2 Field Documentation

8.1629.2.1 BYTE voiceContDTMFinfo::DTMFdigit

8.1629.2.2 BYTE* voiceContDTMFinfo::pCallID

8.1630 voiceDTMFEventInfo Struct Reference

Data Fields

- struct qmTlvResult results
- DTMFInfo DTMFInformation
- BYTE * pOnLength
- BYTE * pOffLength

8.1630.1 Detailed Description

This structure contains the parameters passed for SLQSVoiceSetDTMFEventCallBack by the device.

Parameters

DTMF-Information(mandatory)	• See DTMFInfo for more information.
pOn-Length(optional)	• DTMF Pulse Width – 0x00 - DTMF_ONLENGTH_95MS - 95 ms – 0x01 - DTMF_ONLENGTH_150MS - 150 ms – 0x02 - DTMF_ONLENGTH_200MS - 200 ms – 0x03 - DTMF_ONLENGTH_250MS - 250 ms – 0x04 - DTMF_ONLENGTH_300MS - 300 ms – 0x05 - DTMF_ONLENGTH_350MS - 350 ms – 0x06 - DTMF_ONLENGTH_SMS - SMS Tx special pulse width

pOff-Length(optional)	• DTMF Interdigit Interval – 0x00 - DTMF_OFFLENGTH_60MS - 60 ms – 0x01 - DTMF_OFFLENGTH_100MS - 100 ms – 0x02 - DTMF_OFFLENGTH_150MS - 150 ms – 0x03 - DTMF_OFFLENGTH_200MS - 200 ms

Note

None

8.1630.2 Field Documentation

8.1630.2.1 DTMFInfo voiceDTMFEventInfo::DTMFInformation

8.1630.2.2 BYTE* voiceDTMFEventInfo::pOffLength

8.1630.2.3 BYTE* voiceDTMFEventInfo::pOnLength

8.1630.2.4 struct qmTlvResult voiceDTMFEventInfo::results

8.1631 voiceFlashInfo Struct Reference

Data Fields

- BYTE * pCallID
- BYTE * pFlashPayLd
- BYTE * pFlashType

8.1631.1 Detailed Description

This structure contains the flash information associated with a call.

Parameters

pCallID[IN/OUT]	• Unique call identifier associated with the current call.
pFlashPayLd[IN](optional)	• Payload in ASCII to be sent in Flash. • Variable Length, NULL terminated.
pFlashType[IN](optional)	• Flash type. – 0 - Simple Flash (default) – 1 - Activate answer hold – 2 - Deactivate answer hold

8.1631.2 Field Documentation

8.1631.2.1 BYTE* voiceFlashInfo::pCallID

8.1631.2.2 BYTE* voiceFlashInfo::pFlashPayLd

8.1631.2.3 BYTE* voiceFlashInfo::pFlashType

8.1632 voiceGetAllCallInfo Struct Reference

Data Fields

- arrCallInfo * pArrCallInfo
- arrRemotePartyNum * pArrRemotePartyNum
- arrRemotePartyName * pArrRemotePartyName
- arrAlertingType * pArrAlertingType
- arrUUSInfo * pArrUUSInfo
- arrSvcOption * pArrSvcOption
- BYTE * pOTASPStatus
- BYTE * pVoicePrivacy
- arrCallEndReason * pArrCallEndReason
- arrAlphaID * pArrAlphaID
- arrConnectPartyNum * pArrConnectPartyNum
- arrDiagInfo * pArrDiagInfo
- arrCalledPartyNum * pArrCalledPartyNum
- arrRedirPartyNum * pArrRedirPartyNum
- arrAlertingPattern * pArrAlertingPattern

8.1632.1 Detailed Description

This structure contains information about the response parameters with all the calls originating or terminating from a particular device.

Parameters

pArrCallInfo(optional)	• See arrCallInfo for more information.
pArrRemotePartyNum(optional)	• See arrRemotePartyNum for more information.
pArrRemotePartyName(optional)	• See arrRemotePartyName for more information.
pArrAlertingType(optional)	• See arrAlertingType for more information.
pArrUUSInfo(optional)	• See arrUUSInfo for more information.
pArrSvcOption(optional)	• See arrSvcOption for more information.

pOTASP-Status(optional)	• OTASP status for the OTASP call. • Applicable only for 3GPP2 devices. – 0x00 - OTASP_STATUS_SPL_UNLOCKED - SPL unlocked; only for user-initiated OTASP – 0x01 - OTASP_STATUS_SPRC_RETRIES_EXCEEDED - SPC retries exceeded; only for user-initiated OTASP – 0x02 - OTASP_STATUS_AKEY_EXCHANGED - A-key exchanged; only for user-initiated OTASP – 0x03 - OTASP_STATUS_SSD_UPDATED - SSD updated; for both user-initiated OTASP and network-initiated OTASP (OTAPA) – 0x04 - OTASP_STATUS_NAM_DOWNLOADED - NAM downloaded; only for user-initiated OTASP – 0x05 - OTASP_STATUS_MDN_DOWNLOADED - MDN downloaded; only for user-initiated OTASP – 0x06 - OTASP_STATUS_IMSI_DOWNLOADED - IMSI downloaded; only for user-initiated OTASP – 0x07 - OTASP_STATUS_PRL_DOWNLOADED - PRL downloaded; only for user-initiated OTASP – 0x08 - OTASP_STATUS_COMMITTED - Commit successful; only for user-initiated OTASP – 0x09 - OTASP_STATUS_OTAPA_STARTED - OTAPA started; only for network-initiated OTASP (OTAPA) – 0x0A - OTASP_STATUS_OTAPA_STOPPED - OTAPA stopped; only for network-initiated OTASP (OTAPA) – 0x0B - OTASP_STATUS_OTAPA_ABORTED - OTAPA aborted; only for network-initiated OTASP (OTAPA) – 0x0C - OTASP_STATUS_OTAPA_COMMITTED - OTAPA committed; only for network-initiated OTASP (OTAPA) – 0xFF - Not Available
pVoice-Privacy(optional)	• Voice Privacy. • Values. – 0x00 - VOICE_PRIVACY_STANDARD - Standard privacy – 0x01 - VOICE_PRIVACY_ENHANCED - Enhanced privacy – 0xFF - Not Available
pArrCallEnd-Reason(optional)	• See arrCallEndReason for more information.
pArrAlphaI-D(optional)	• See arrAlphaID for more information.
pArrConnect-Party-Num(optional)	• See arrConnectPartyNum for more information.
pArrDiag-Info(optional)	• See arrDiagInfo for more information.
pArrCalledParty-Num(optional)	• See arrCalledPartyNum for more information.

pArrRedirParty-Num(optional)	• See arrRedirPartyNum for more information.
pArrAlerting-Pattern(optional)	• See arrAlertingPattern for more information.

8.1632.2 Field Documentation

8.1632.2.1 arrAlertingPattern∗ voiceGetAllCallInfo::pArrAlertingPattern

8.1632.2.2 arrAlertingType∗ voiceGetAllCallInfo::pArrAlertingType

8.1632.2.3 arrAlphaID∗ voiceGetAllCallInfo::pArrAlphaID

8.1632.2.4 arrCalledPartyNum∗ voiceGetAllCallInfo::pArrCalledPartyNum

8.1632.2.5 arrCallEndReason∗ voiceGetAllCallInfo::pArrCallEndReason

8.1632.2.6 arrCallInfo∗ voiceGetAllCallInfo::pArrCallInfo

8.1632.2.7 arrConnectPartyNum∗ voiceGetAllCallInfo::pArrConnectPartyNum

8.1632.2.8 arrDiagInfo∗ voiceGetAllCallInfo::pArrDiagInfo

8.1632.2.9 arrRedirPartyNum∗ voiceGetAllCallInfo::pArrRedirPartyNum

8.1632.2.10 arrRemotePartyName∗ voiceGetAllCallInfo::pArrRemotePartyName

8.1632.2.11 arrRemotePartyNum∗ voiceGetAllCallInfo::pArrRemotePartyNum

8.1632.2.12 arrSvcOption∗ voiceGetAllCallInfo::pArrSvcOption

8.1632.2.13 arrUUSInfo∗ voiceGetAllCallInfo::pArrUUSInfo

8.1632.2.14 BYTE∗ voiceGetAllCallInfo::pOTASPStatus

8.1632.2.15 BYTE∗ voiceGetAllCallInfo::pVoicePrivacy

8.1633 voiceGetCallBarringReq Struct Reference

Data Fields

- BYTE reason
- BYTE ∗ pSvcClass

8.1633.1 Detailed Description

This structure contains Voice Get Call Barring Request Parameters

Parameters

reason	• Call Barring Reason • Values: – 0x07 - QMI_VOICE_REASON_BARR_ALLOUTGOING - All outgoing – 0x08 - QMI_VOICE_REASON_BARR_OUTGOINGINT - Outgoing internal – 0x09 - QMI_VOICE_REASON_BARR_OUTGOINGINTEXTOHOME - Outgoing external to home – 0x0A - QMI_VOICE_REASON_BARR_ALLINCOMING - All incoming – 0x0B - QMI_VOICE_REASON_BARR_INCOMINGROAMING - Roaming incoming – 0x0C - QMI_VOICE_REASON_BARR_ALLBARRING - All calls are barred – 0x0D - QMI_VOICE_REASON_BARR_ALLOUTGOINGBARRING - All outgoing calls are barred – 0x0E - QMI_VOICE_REASON_BARR_ALLINCOMINGBARRING - All incoming calls are barred
pSvcClass[IN/OUT]	• Service class is a combination (sum) of information class constants (optional) • See qaGobiApiTableSupServiceInfoClasses.h for service classes. • Service Class is set to 0 if call waiting is not active for any of the information classes. • 0xFF,if Not Available

8.1633.2 Field Documentation

8.1633.2.1 BYTE* voiceGetCallBarringReq::pSvcClass

8.1633.2.2 BYTE voiceGetCallBarringReq::reason

8.1634 voiceGetCallBarringResp Struct Reference

Data Fields

- BYTE * pSvcClass
- WORD * pFailCause
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCCResType
- BYTE * pCallID
- ccSUPSType * pCCSUPSType

8.1634.1 Detailed Description

This structure contains Voice Get Call Barring Response Parameters

Parameters

pSvcClass[IN/OUT]	• Service class is a combination (sum) of information class constants (optional) • See qaGobiApiTableSupServiceInfoClasses.h for service classes. • Service Class is set to 0 if call waiting is not active for any of the information classes. • 0xFF,if Not Available

pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See alphaIDInfo for more information
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid.
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1634.2 Field Documentation

8.1634.2.1 alphaIDInfo* voiceGetCallBarringResp::pAlphaIDInfo

8.1634.2.2 BYTE* voiceGetCallBarringResp::pCallID

8.1634.2.3 BYTE* voiceGetCallBarringResp::pCCResType

8.1634.2.4 ccSUPSType* voiceGetCallBarringResp::pCCSUPSType

8.1634.2.5 WORD* voiceGetCallBarringResp::pFailCause

8.1634.2.6 BYTE* voiceGetCallBarringResp::pSvcClass

8.1635 voiceGetCallFWReq Struct Reference

Data Fields

- BYTE Reason
- BYTE * pSvcClass

8.1635.1 Detailed Description

This structure contains Voice Get Call Forwarding Status Request Parameters

Parameters

Reason	• Call Forwarding Reason • Values: – 0x01 - QMI_VOICE_REASON_FWDREASON_UNCONDITIONAL - Unconditional call forwarding – 0x02 - QMI_VOICE_REASON_FWDREASON_MOBILEBUSY - Forward when the mobile is busy – 0x03 - QMI_VOICE_REASON_FWDREASON_NOREPLY - Forward when there is no reply – 0x04 - QMI_VOICE_REASON_FWDREASON_UNREACHABLE - Forward when the call is unreachable – 0x05 - QMI_VOICE_REASON_FWDREASON_ALLFORWARDING - All forwarding – 0x06 - QMI_VOICE_REASON_FWDREASON_ALLCONDITIONAL - All conditional forwarding
pSvcClass(optional)	• Service Class is a combination (sum) of information class constants • See qaGobiApiTableSupServiceInfoClasses.h for service classes.

8.1635.2 Field Documentation

8.1635.2.1 BYTE* voiceGetCallFWReq::pSvcClass

8.1635.2.2 BYTE voiceGetCallFWReq::Reason

8.1636 voiceGetCallFWResp Struct Reference

Data Fields

- getCallFWInfo * pGetCallFWInfo
- WORD * pFailCause
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCCResType
- BYTE * pCallID
- ccSUPSType * pCCSUPSType
- getCallFWExtInfo * pGetCallFWExtInfo

8.1636.1 Detailed Description

This structure contains Voice Get Call Forwarding Status Response Parameters

Parameters

pGetCallFWInfo	• Pointer to structure of getCallFWInfo (optional) – See getCallFWInfo for more information

pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See alphaIDInfo for more information
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid.
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information
pGetCallFWExt-Info	• Pointer to structure of getCallFWExtInfo (optional) – See getCallFWExtInfo for more information

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1636.2 Field Documentation

8.1636.2.1 alphaIDInfo* voiceGetCallFWResp::pAlphaIDInfo

8.1636.2.2 BYTE* voiceGetCallFWResp::pCallID

8.1636.2.3 BYTE* voiceGetCallFWResp::pCCResType

8.1636.2.4 ccSUPSType* voiceGetCallFWResp::pCCSUPSType

8.1636.2.5 WORD* voiceGetCallFWResp::pFailCause

8.1636.2.6 getCallFWExtInfo* voiceGetCallFWResp::pGetCallFWExtInfo

8.1636.2.7 getCallFWInfo* voiceGetCallFWResp::pGetCallFWInfo

8.1637 voiceGetCallWaitInfo Struct Reference

Data Fields

- BYTE * pSvcClass
- WORD * pFailCause
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCCResType
- BYTE * pCallID
- ccSUPSType * pCCSUPSType

8.1637.1 Detailed Description

This structure contains Voice Get Call Waiting Response Parameters

Parameters

pSvcClass[IN/OUT]	• Service class is a combination (sum) of information class constants (optional) • See qaGobiApiTableSupServiceInfoClasses.h for service classes. • Service Class is set to 0 if call waiting is not active for any of the information classes. • 0xFF,if Not Available
pFailCause[OUT]	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available
pAlphaIDInfo[OUT]	• Pointer to structure of alphaIDInfo (optional) – See alphaIDInfo for more information

pCCResType[OUT]	• Call Control Result Type (optional)
	  – 0x00 - CC_RESULT_TYPE_VOICE - Voice
	  – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service
	  – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service
	  – 0xFF - Not Available

pCallID[OUT]	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid.
pCCSUPSType[OUT]	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1637.2 Field Documentation

8.1637.2.1 alphaIDInfo* voiceGetCallWaitInfo::pAlphaIDInfo

8.1637.2.2 BYTE* voiceGetCallWaitInfo::pCallID

8.1637.2.3 BYTE* voiceGetCallWaitInfo::pCCResType

8.1637.2.4 ccSUPSType* voiceGetCallWaitInfo::pCCSUPSType

8.1637.2.5 WORD* voiceGetCallWaitInfo::pFailCause

8.1637.2.6 BYTE* voiceGetCallWaitInfo::pSvcClass

8.1638 voiceGetCLIPResp Struct Reference

Data Fields

- CLIPResp * pCLIPResp
- WORD * pFailCause
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCCResType
- BYTE * pCallID
- ccSUPSType * pCCSUPSType

8.1638.1 Detailed Description

This structure contains Voice Get Calling Line Identification Presentation(CLIP) Response Parameters

Parameters

pCLIPResp	• Pointer to structure of CLIPResp (optional) – See CLIPResp for more information
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See alphaIDInfo for more information
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid.

pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1638.2 Field Documentation

8.1638.2.1 alphaIDInfo* voiceGetCLIPResp::pAlphaIDInfo

8.1638.2.2 BYTE* voiceGetCLIPResp::pCallID

8.1638.2.3 BYTE* voiceGetCLIPResp::pCCResType

8.1638.2.4 ccSUPSType* voiceGetCLIPResp::pCCSUPSType

8.1638.2.5 CLIPResp* voiceGetCLIPResp::pCLIPResp

8.1638.2.6 WORD* voiceGetCLIPResp::pFailCause

8.1639 voiceGetCLIRResp Struct Reference

Data Fields

- CLIRResp * pCLIRResp
- WORD * pFailCause
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCCResType
- BYTE * pCallID
- ccSUPSType * pCCSUPSType

8.1639.1 Detailed Description

This structure contains Voice Get Calling Line Identification Restriction (CLIR) Response Parameters

Parameters

pCLIRResp	• Pointer to structure of CLIRResp (optional) – See CLIRResp for more information
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See alphaIDInfo for more information

pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid.
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1639.2 Field Documentation

8.1639.2.1 alphaIDInfo∗ voiceGetCLIRResp::pAlphaIDInfo

8.1639.2.2 BYTE∗ voiceGetCLIRResp::pCallID

8.1639.2.3 BYTE∗ voiceGetCLIRResp::pCCResType

8.1639.2.4 ccSUPSType∗ voiceGetCLIRResp::pCCSUPSType

8.1639.2.5 CLIRResp∗ voiceGetCLIRResp::pCLIRResp

8.1639.2.6 WORD∗ voiceGetCLIRResp::pFailCause

8.1640 voiceGetCNAPResp Struct Reference

Data Fields

- CNAPResp ∗ pCNAPResp
- WORD ∗ pFailCause
- alphaIDInfo ∗ pAlphaIDInfo
- BYTE ∗ pCCResType
- BYTE ∗ pCallID
- ccSUPSType ∗ pCCSUPSType

8.1640.1 Detailed Description

This structure contains Voice Get Calling Name Presentation(CNAP) Response Parameters

Parameters

pCNAPResp	• Pointer to structure of CNAPResp (optional) – See CNAPResp for more information
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See alphaIDInfo for more information
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid.
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1640.2 Field Documentation

8.1640.2.1 alphaIDInfo* voiceGetCNAPResp::pAlphaIDInfo

8.1640.2.2 BYTE* voiceGetCNAPResp::pCallID

8.1640.2.3 BYTE* voiceGetCNAPResp::pCCResType

8.1640.2.4 ccSUPSType* voiceGetCNAPResp::pCCSUPSType

8.1640.2.5 CNAPResp* voiceGetCNAPResp::pCNAPResp

8.1640.2.6 WORD* voiceGetCNAPResp::pFailCause

8.1641 voiceGetCOLPResp Struct Reference

Data Fields

- COLPResp * pCOLPResp
- WORD * pFailCause
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCCResType
- BYTE * pCallID
- ccSUPSType * pCCSUPSType

8.1641.1 Detailed Description

This structure contains Voice Get Connected Line Identification Presentation(COLP) Response Parameters

Parameters

pCOLPResp	• Pointer to structure of COLPResp (optional) – See COLPResp for more information
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See alphaIDInfo for more information
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid.
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1641.2 Field Documentation

8.1641.2.1 alphaIDInfo* voiceGetCOLPResp::pAlphaIDInfo

8.1641.2.2 BYTE* voiceGetCOLPResp::pCallID

8.1641.2.3 BYTE* voiceGetCOLPResp::pCCResType

8.1641.2.4 ccSUPSType* voiceGetCOLPResp::pCCSUPSType

8.1641.2.5 COLPResp* voiceGetCOLPResp::pCOLPResp

8.1641.2.6 WORD* voiceGetCOLPResp::pFailCause

8.1642 voiceGetCOLRResp Struct Reference

Data Fields

- COLRResp * pCOLRResp
- WORD * pFailCause
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCCResType
- BYTE * pCallID
- ccSUPSType * pCCSUPSType

8.1642.1 Detailed Description

This structure contains Voice Get Connected Line Identification Restriction(COLR) Response Parameters

Parameters

pCOLRResp	• Pointer to structure of COLRResp (optional) – See COLRResp for more information
pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See alphaIDInfo for more information
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid.

pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1642.2 Field Documentation

8.1642.2.1 alphaIDInfo∗ voiceGetCOLRResp::pAlphaIDInfo

8.1642.2.2 BYTE∗ voiceGetCOLRResp::pCallID

8.1642.2.3 BYTE∗ voiceGetCOLRResp::pCCResType

8.1642.2.4 ccSUPSType∗ voiceGetCOLRResp::pCCSUPSType

8.1642.2.5 COLRResp∗ voiceGetCOLRResp::pCOLRResp

8.1642.2.6 WORD∗ voiceGetCOLRResp::pFailCause

8.1643 voiceGetConfigReq Struct Reference

Data Fields

- BYTE ∗ pAutoAnswer
- BYTE ∗ pAirTimer
- BYTE ∗ pRoamTimer
- BYTE ∗ pTTYMode
- BYTE ∗ pPrefVoiceSO
- BYTE ∗ pAMRStatus
- BYTE ∗ pPrefVoicePrivacy
- BYTE ∗ pNamID
- BYTE ∗ pVoiceDomainPref

8.1643.1 Detailed Description

This structure contains Voice Get Configuration Request Parameters

Parameters

pAuto-Answer(optional)	• Indicator to retrieve the Auto Answer Information. – 0x01 - Include auto answer information
pAir-Timer(optional)	• Indicator to retrieve the Air Timer Information. – 0x01 - Include air calls timer count information • Currently Not Supported.

pRoamTimer(optional)	• Indicator to retrieve the Roam Timer Information. – 0x01 - Include roam calls timer information • Currently Not Supported.
pTTYMode(optional)	• Indicator to retrieve the TTY Mode Information. – 0x01 - Include TTY configuration status information
pPrefVoiceSO(optional)	• Indicator to retrieve the Preferred Voice SO Information. – 0x01 - Include preferred voice configuration status information • Currently Not Supported.
pAMRStatus(optional)	• Indicator to retrieve the AMR Status Information. – 0x01 - Include AMR status information
pPrefVoicePrivacy(optional)	• Indicator to retrieve the Preferred Voice Privacy Information. – 0x01 - Include preferred voice privacy status information
pNamID(optional)	• Index of the Number Assignment Module Index (CDMA subscription) to be configured • Range: 0 to 3. • Some modems support only 1 or 2 NAMs. • The NAM Index is valid only when the request contains at least one of Air Timer, Roam Timer, and Preferred Voice SO. • If no nam_id value is specified in the request,the default value is 0.
pVoiceDomainPref(optional)	• Indicator to retrieve the Preferred Voice Domain Information. – 0x01 - Include voice domain preference information

Note

Using NULL for the pointers would make sure that the parameter is not returned.

8.1643.2 Field Documentation

8.1643.2.1 BYTE* voiceGetConfigReq::pAirTimer

8.1643.2.2 BYTE* voiceGetConfigReq::pAMRStatus

8.1643.2.3 BYTE* voiceGetConfigReq::pAutoAnswer

8.1643.2.4 BYTE* voiceGetConfigReq::pNamID

8.1643.2.5 BYTE* voiceGetConfigReq::pPrefVoicePrivacy

8.1643.2.6 BYTE* voiceGetConfigReq::pPrefVoiceSO

8.1643.2.7 BYTE* voiceGetConfigReq::pRoamTimer

8.1643.2.8 BYTE* voiceGetConfigReq::pTTYMode

8.1643.2.9 BYTE* voiceGetConfigReq::pVoiceDomainPref

8.1644 voiceGetConfigResp Struct Reference

Data Fields

- BYTE * pAutoAnswerStat
- airTimer * pAirTimerCnt
- roamTimer * pRoamTimerCnt
- BYTE * pCurrTTYMode
- prefVoiceSO * pCurPrefVoiceSO
- curAMRConfig * pCurAMRConfig
- BYTE * pCurVoicePrivacyPref
- BYTE * pCurVoiceDomainPref

8.1644.1 Detailed Description

This structure contains Voice Get Configuration Response Parameters.

Parameters

pAutoAnswer-Stat(optional)	• Auto Answer Status • Value returned is read from NV_AUTO_ANSWER_I. – 0x00 - Disabled – 0x01 - Enabled – 0xFF - Not Available
pAirTimer-Cnt(optional)	• Air Timer Count • Value returned is read from NV_AIR_CNT_I. • See airTimer for more information
pRoamTimer-Cnt(optional)	• Roam Timer Count • Value returned is read from NV_ROAM_CNT_I. • See roamTimer for more information
pCurrTTY-Mode(optional)	• Current TTY Mode • Value returned is read from NV_TTY_I. – 0x00 - TTY_MODE_FULL - Full – 0x01 - TTY_MODE_VCO - Voice carry over – 0x02 - TTY_MODE_HCO - Hearing carry over – 0x03 - TTY_MODE_OFF - Off – 0xFF - Not Available

pCurPrefVoiceSO(optional)	• Current Preferred Voice SO • Value returned is read from NV_PREF_VOICE_SO_I. • See prefVoiceSO for more information
pCurAMRConfig(optional)	• Current Adaptive Multi-Rate Configuration. • Values returned are read from NV_GSM_ARM_CALL_CONFIG_I and NV_UMTS_AMR_CODEC_PREFERENCE_CONFIG_I. • See curAMRConfig for more information
pCurVoicePrivacyPref(optional)	• Current Voice Privacy Preference • Value returned is read from NV_VOICE_PRIV_I. – 0x00 - Standard privacy – 0x01 - Enhanced privacy – 0xFF - Not Available
pCurVoiceDomainPref(optional)	• Current Voice Domain Preference. – 0x00 - Circuit-switched (CS) only – 0x01 - Packet-switched (PS) only – 0x02 - CS is preferred; PS is secondary – 0x03 - PS is preferred; CS is secondary – 0xFF - Not Available

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1644.2 Field Documentation

8.1644.2.1 airTimer* voiceGetConfigResp::pAirTimerCnt

8.1644.2.2 BYTE* voiceGetConfigResp::pAutoAnswerStat

8.1644.2.3 curAMRConfig* voiceGetConfigResp::pCurAMRConfig

8.1644.2.4 prefVoiceSO* voiceGetConfigResp::pCurPrefVoiceSO

8.1644.2.5 BYTE* voiceGetConfigResp::pCurrTTYMode

8.1644.2.6 BYTE* voiceGetConfigResp::pCurVoiceDomainPref

8.1644.2.7 BYTE* voiceGetConfigResp::pCurVoicePrivacyPref

8.1644.2.8 roamTimer* voiceGetConfigResp::pRoamTimerCnt

8.1645 voiceIndicationRegisterInfo Struct Reference

Data Fields

- BYTE * pRegDTMFEvents
- BYTE * pRegVoicePrivacyEvents
- BYTE * pSuppsNotifEvents

8.1645.1 Detailed Description

This structure contains parameters of Indication Register Information

Parameters

pRegDTMF-Events(optional)	• Registration Indication For DTMF Events. • When this registration is enabled, the device learns of DTMF events via the QMI_VOICE_DTMF_IND indication. – 0x00 - Disable – 0x01 - Enable
pRegVoice-Privacy-Events(optional)	• Registration Indication For Voice Privacy Events. • When this registration is enabled, the device learns of DTMF events via the QMI_VOICE_PRIVACY_IND indication. – 0x00 - Disable – 0x01 - Enable
pSuppsNotif-Events(optional)	• Registration Indication For Supplementary Service Notification Events. • When this registration is enabled, the device learns of DTMF events via the QMI_VOICE_SUPS_NOTIFICATION_IND indication. – 0x00 - Disable – 0x01 - Enable

Note

One of the optional parameter is mandatory to be present in the request.

8.1645.2 Field Documentation

8.1645.2.1 BYTE* voiceIndicationRegisterInfo::pRegDTMFEvents

8.1645.2.2 BYTE* voiceIndicationRegisterInfo::pRegVoicePrivacyEvents

8.1645.2.3 BYTE* voiceIndicationRegisterInfo::pSuppsNotifEvents

8.1646 voiceInfoRec Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE callID
- signalInfo * pSignalInfo

- callerIDInfo * pCallerIDInfo
- BYTE * pDispInfo
- BYTE * pExtDispInfo
- BYTE * pCallerNameInfo
- BYTE * pCallWaitInd
- connectNumInfo * pConnectNumInfo
- connectNumInfo * pCallingPartyInfo
- calledPartyInfo * pCalledPartyInfo
- redirNumInfo * pRedirNumInfo
- BYTE * pCLIRCause
- NSSAudioCtrl * pNSSAudioCtrl
- BYTE * pNSSRelease
- lineCtrlInfo * pLineCtrlInfo
- extDispRecInfo * pExtDispRecInfo

8.1646.1 Detailed Description

This structure contains Voice record Information

Parameters

callID	[Mandatory] • Call identifier for the call.
pSignalInfo[-Optional]	• Signal Information • See signalInfo for more information
pCallerIDInfo[-Optional]	• Caller ID Information • See callerIDInfo for more information
pDispInfo[-Optional]	• Display Information
pExtDispInfo[-Optional]	• Extended Display Information
pCallerName-Info[Optional]	• Caller Name Information
pCallWaitInd[-Optional]	• Call Waiting Indicator
pConnectNum-Info[Optional]	• Connected Number Information • see connectNumInfo for more information
pCallingParty-Info[Optional]	• Calling Party Number Information • This structure is having exactly same elements as connectNumInfo • see connectNumInfo for more information

pCalledPartyInfo[Optional]	• Called Party Number Information • see calledPartyInfo for more information
pRedirNumInfo[Optional]	• Redirecting Number Information • see redirNumInfo for more information
pCLIRCause[Optional]	• National Supplementary Services - CLIR • see NSSAudioCtrl for more information
pNSSAudioCtrl[Optional]	• National Supplementary Services - Audio Control
pNSSRelease[Optional]	• National Supplementary Services - Release
pLineCtrlInfo[Optional]	• Line Control Information • see lineCtrlInfo for more information
pExtDispRecInfo[Optional]	• Extended Display Record Information • see extDispRecInfo for more information

8.1646.2 Field Documentation

8.1646.2.1 BYTE voiceInfoRec::callID

8.1646.2.2 calledPartyInfo* voiceInfoRec::pCalledPartyInfo

8.1646.2.3 callerIDInfo* voiceInfoRec::pCallerIDInfo

8.1646.2.4 BYTE* voiceInfoRec::pCallerNameInfo

8.1646.2.5 connectNumInfo* voiceInfoRec::pCallingPartyInfo

8.1646.2.6 BYTE* voiceInfoRec::pCallWaitInd

8.1646.2.7 BYTE* voiceInfoRec::pCLIRCause

8.1646.2.8 connectNumInfo* voiceInfoRec::pConnectNumInfo

8.1646.2.9 BYTE* voiceInfoRec::pDispInfo

8.1646.2.10 BYTE* voiceInfoRec::pExtDispInfo

8.1646.2.11 extDispRecInfo* voiceInfoRec::pExtDispRecInfo

8.1646.2.12 lineCtrlInfo* voiceInfoRec::pLineCtrlInfo

8.1646.2.13 NSSAudioCtrl* voiceInfoRec::pNSSAudioCtrl

8.1646.2.14 BYTE* voiceInfoRec::pNSSRelease

8.1646.2.15 redirNumInfo* voiceInfoRec::pRedirNumInfo

8.1646.2.16 signalInfo* voiceInfoRec::pSignalInfo

8.1646.2.17 struct qmTlvResult voiceInfoRec::results

8.1647 voiceManageCallsReq Struct Reference

Data Fields

- BYTE SUPSType
- BYTE * pCallID

8.1647.1 Detailed Description

This structure contains Manage Calls Information.

Parameters

SUPSType	• Supplementary service type during the call. – 0x01 - SUPS_TYPE_RELEASE_HELD_OR_WAITING * Release is held or waiting – 0x02 - SUPS_TYPE_RELEASE_ACTIVE_ACCEPT_HELD_OR_WAITING * Release is active and accepting held or waiting – 0x03 - SUPS_TYPE_HOLD_ACTIVE_ACCEPT_WAITING_OR_HELD * Hold is active and accepting waiting or held – 0x04 - SUPS_TYPE_HOLD_ALL_EXCEPT_SPECIFIED_CALL * Hold all calls except a specified one – 0x05 - SUPS_TYPE_MAKE_CONFERENCE_CALL * Make a conference call – 0x06 - SUPS_TYPE_EXPLICIT_CALL_TRANSFER * Explicit call transfer – 0x07 - SUPS_TYPE_CCBS_ACTIVATION * Activate completion of calls to busy subscriber – 0x08 - SUPS_TYPE_END_ALL_CALLS * End all calls – 0x09 - SUPS_TYPE_RELEASE_SPECIFIED_CALL * Release a specified call
pCallID[Optional]	• Applicable only for SUPSType 0x04, 0x07, and 0x09

8.1647.2 Field Documentation

8.1647.2.1 BYTE* voiceManageCallsReq::pCallID

8.1647.2.2 BYTE voiceManageCallsReq::SUPSType

8.1648 voiceManageCallsResp Struct Reference

Data Fields

- WORD * pFailCause

8.1648.1 Detailed Description

This structure contains Failure cause Information. Populated when API Fails.

Parameters

pFailCause	• Supplementary service failure causes (optional, supply NULL if not required). • See Table8 qaGobiApiTableVoiceCallEndReasons.h for supplementary services failure cause – 0xFFFF is the value when the information is not received from device

8.1648.2 Field Documentation

8.1648.2.1 WORD* voiceManageCallsResp::pFailCause

8.1649 voiceOrigUSSDNoWaitInfo Struct Reference

Data Fields

- struct USSInfo USSInformation

8.1649.1 Detailed Description

This structure contains Orig USSD No Wait Information Parameters.

Parameters

USSInformation	• See USSInfo for more information.

8.1649.2 Field Documentation

8.1649.2.1 struct USSInfo voiceOrigUSSDNoWaitInfo::USSInformation

8.1650 voiceOTASPStatusInfo Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE callID
- BYTE OTASPStatus

8.1650.1 Detailed Description

This structure consist of OTASP or OTAPA event params

Parameters

callID	• Call identifier for the call.
OTASPStatus	• OTASP status for the OTASP call. Values: – 0x00 - OTASP_STATUS_SPL_UNLOCKED.SPL unlocked; only for user-initiated OTASP – 0x01 - OTASP_STATUS_SPRC_RETRIES_EXCEEDED. SPC retries exceeded; only for user-initiated OTASP – 0x02 - OTASP_STATUS_AKEY_EXCHANGED.A-key exchanged; only for user-initiated O-TASP – 0x03 - OTASP_STATUS_SSD_UPDATED. SSD updated; for both user-initiated OTASP and network-initiated OTASP (OTAPA) – 0x04 - OTASP_STATUS_NAM_DOWNLOADED - NAM downloaded; only for user-initiated OTASP – 0x05 - OTASP_STATUS_MDN_DOWNLOADED - MDN downloaded; only for user-initiated OTASP – 0x06 - OTASP_STATUS_IMSI_DOWNLOADED - IMSI downloaded; only for user-initiated OTASP – 0x07 - OTASP_STATUS_PRL_DOWNLOADED - PRL downloaded; only for user-initiated OTASP – 0x08 - OTASP_STATUS_COMMITTED - Commit successful; only for user-initiated OTASP – 0x09 - OTASP_STATUS_OTAPA_STARTED - OTAPA started; only for network-initiated OTASP(OTAPA) – 0x0A - OTASP_STATUS_OTAPA_STOPPED - OTAPA stopped; only for network-initiated OTASP(OTAPA) – 0x0B - OTASP_STATUS_OTAPA_ABORTED - OTAPA aborted; only for network-initiated OTASP(OTAPA) – 0x0C - OTASP_STATUS_OTAPA_COMMITTED - OTAPA committed; only for network-initiated OTASP(OTAPA)

8.1650.2 Field Documentation

8.1650.2.1 BYTE voiceOTASPStatusInfo::callID

8.1650.2.2 BYTE voiceOTASPStatusInfo::OTASPStatus

8.1650.2.3 struct qmTlvResult voiceOTASPStatusInfo::results

8.1651 voicePrivacyInfo Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE callID
- BYTE voicePrivacy

8.1651.1 Detailed Description

Contains the parameters passed for SLQSVoiceSetPrivacyChangeCallBack by the device.

Parameters

callID	• Unique identifier of the call for which the voice privacy is applicable. (mandatory)
voicePrivacy	• Voice Privacy (mandatory) – 0x00 - VOICE_PRIVACY_STANDARD - Standard privacy – 0x01 - VOICE_PRIVACY_ENHANCED - Enhanced privacy

Note

None

8.1651.2 Field Documentation

8.1651.2.1 BYTE voicePrivacyInfo::callID

8.1651.2.2 struct qmTlvResult voicePrivacyInfo::results

8.1651.2.3 BYTE voicePrivacyInfo::voicePrivacy

8.1652 voiceSetAllCallStatusCbkInfo Struct Reference

Data Fields

- struct qmTlvResult results
- arrCallInfo arrCallInfomation
- arrRemotePartyNum * pArrRemotePartyNum
- arrRemotePartyName * pArrRemotePartyName
- arrAlertingType * pArrAlertingType
- arrSvcOption * pArrSvcOption
- arrCallEndReason * pArrCallEndReason
- arrAlphaID * pArrAlphaID
- arrConnectPartyNum * pArrConnectPartyNum
- arrDiagInfo * pArrDiagInfo
- arrCalledPartyNum * pArrCalledPartyNum
- arrRedirPartyNum * pArrRedirPartyNum
- arrAlertingPattern * pArrAlertingPattern

8.1652.1 Detailed Description

This structure contains VoiceCall Information parameters. arrCallInfomation will be populated in case of change in the call information. Other paramters are optional therefore are populated based on device and technology type being used.

Parameters

arrCallInfomation	[mandatory] • Array of Call Information This must be populated if Indication is received See arrCallInfo for more information. – Applicable for both "3GPP/3GPP2"
pArrRemote-PartyNum	[optional] • Array of Remote Party Name.(NULL when not present) See arrRemotePartyNum for more information. – Applicable only for "3GPP/3GPP2"
pArrRemote-PartyName	[optional] • Array of Alerting Type.(NULL when not present) See arrRemotePartyName for more information. – Applicable only for "3GPP"
pArrAlertingType	[optional] • Array of Alerting Type(NULL when not present) See arrAlertingType for more information. – Applicable only for "3GPP"
pArrSvcOption	[optional] • Array of Service Option.(NULL when not present) See arrSvcOption for more information. – Applicable only for "3GPP"
pArrCallEnd-Reason	[optional] • Array of Call End Reason.(NULL when not present) See arrCallEndReason for more information. – Applicable only for "3GPP"
pArrAlphaID	[optional] • Array of Alpha Identifier(NULL when not present) See arrAlphaID for more information. – Applicable only for "3GPP"
pArrConnect-PartyNum	[optional] • Array of Connected Party Number.(NULL when not present) See arrConnectPartyNum for more information. – Applicable for both "3GPP/3GPP2"
pArrDiagInfo	[optional] • Array of Diagnostic Information.(NULL when not present) See arrDiagInfo for more information. – Applicable only for "3GPP"
pArrCalledParty-Num	[optional] • Array of Called Party Number.(NULL when not present) See arrCalledPartyNum for more information. – Applicable only for "3GPP"

pArrRedirParty-Num	[optional] • Array of Redirecting Party Number.(NULL when not present) See arrRedirPartyNum for more information. – Applicable only for "3GPP"
pArrAlerting-Pattern	[optional] • Array of Alerting Pattern.(NULL when not present) See arrAlertingPattern for more information. – Applicable only for "3GPP"

Note

Optional paramters would be NULL, if not received from the device.

8.1652.2 Field Documentation

8.1652.2.1 arrCallInfo voiceSetAllCallStatusCbkInfo::arrCallInfomation

8.1652.2.2 arrAlertingPattern* voiceSetAllCallStatusCbkInfo::pArrAlertingPattern

8.1652.2.3 arrAlertingType* voiceSetAllCallStatusCbkInfo::pArrAlertingType

8.1652.2.4 arrAlphaID* voiceSetAllCallStatusCbkInfo::pArrAlphaID

8.1652.2.5 arrCalledPartyNum* voiceSetAllCallStatusCbkInfo::pArrCalledPartyNum

8.1652.2.6 arrCallEndReason* voiceSetAllCallStatusCbkInfo::pArrCallEndReason

8.1652.2.7 arrConnectPartyNum* voiceSetAllCallStatusCbkInfo::pArrConnectPartyNum

8.1652.2.8 arrDiagInfo* voiceSetAllCallStatusCbkInfo::pArrDiagInfo

8.1652.2.9 arrRedirPartyNum* voiceSetAllCallStatusCbkInfo::pArrRedirPartyNum

8.1652.2.10 arrRemotePartyName* voiceSetAllCallStatusCbkInfo::pArrRemotePartyName

8.1652.2.11 arrRemotePartyNum* voiceSetAllCallStatusCbkInfo::pArrRemotePartyNum

8.1652.2.12 arrSvcOption* voiceSetAllCallStatusCbkInfo::pArrSvcOption

8.1652.2.13 struct qmTlvResult voiceSetAllCallStatusCbkInfo::results

8.1653 voiceSetCallBarringPwdInfo Struct Reference

Data Fields

- BYTE Reason
- BYTE oldPasswd [4]
- BYTE newPasswd [4]
- BYTE newPasswdAgain [4]

8.1653.1 Detailed Description

This structure contains Voice Set Call Barring Password Request Parameters

Parameters

Reason	• Call Barring Reason • Values: – 0x07 - QMI_VOICE_REASON_BARR_ALLOUTGOING - All outgoing – 0x08 - QMI_VOICE_REASON_BARR_OUTGOINGINT - Outgoing internal – 0x09 - QMI_VOICE_REASON_BARR_OUTGOINGINTEXTOHOME - Outgoing external to home – 0x0A - QMI_VOICE_REASON_BARR_ALLINCOMING - All incoming – 0x0B - QMI_VOICE_REASON_BARR_INCOMINGROAMING - Roaming incoming – 0x0C - QMI_VOICE_REASON_BARR_ALLBARRING - All calls are barred – 0x0D - QMI_VOICE_REASON_BARR_ALLOUTGOINGBARRING - All outgoing calls are barred – 0x0E - QMI_VOICE_REASON_BARR_ALLINCOMINGBARRING - All incoming calls are barred
oldPasswd[PASSWORD_LENGTH]	• Old password. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.
newPasswd[PASSWORD_LENGTH]	• New password. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.
newPasswdAgain[PASSWORD_LENGTH]	• New password Again. – Password consists of 4 ASCII digits. – Range: 0000 to 9999.

8.1653.2 Field Documentation

8.1653.2.1 BYTE voiceSetCallBarringPwdInfo::newPasswd[4]

8.1653.2.2 BYTE voiceSetCallBarringPwdInfo::newPasswdAgain[4]

8.1653.2.3 BYTE voiceSetCallBarringPwdInfo::oldPasswd[4]

8.1653.2.4 BYTE voiceSetCallBarringPwdInfo::Reason

8.1654 voiceSetCallBarringPwdResp Struct Reference

Data Fields

- WORD * pFailCause
- alphaIDInfo * pAlphaIDInfo

- BYTE * pCCResType
- BYTE * pCallID
- ccSUPSType * pCCSUPSType

8.1654.1 Detailed Description

This structure contains Voice Set Call Barring Password Response Parameters

Parameters

pFailCause	• Supplementary services failure cause (optional) • see qaGobiApiTableVoiceCallEndReasons.h for more information. • 0xFFFF,if Not Available
pAlphaIDInfo	• Pointer to structure of alphaIDInfo (optional) – See alphaIDInfo for more information
pCCResType	• Call Control Result Type (optional) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - Not Available
pCallID	• Call ID of the voice call that resulted from call control. (optional) • It is present when pCCResType is present and is Voice. • If zero(0) then invalid.
pCCSUPSType	• Supplementary service data that resulted from call control (optional) • Data is present when pCCResultType is present and is other than Voice. – See ccSUPSType for more information

Note

Using NULL for the pointers would make sure that the parameter is not returned or has default value.

8.1654.2 Field Documentation

8.1654.2.1 alphaIDInfo* voiceSetCallBarringPwdResp::pAlphaIDInfo

8.1654.2.2 BYTE* voiceSetCallBarringPwdResp::pCallID

8.1654.2.3 BYTE* voiceSetCallBarringPwdResp::pCCResType

8.1654.2.4 ccSUPSType* voiceSetCallBarringPwdResp::pCCSUPSType

8.1654.2.5 WORD* voiceSetCallBarringPwdResp::pFailCause

8.1655 voiceSetConfigReq Struct Reference

Data Fields

- BYTE * pAutoAnswer
- airTimer * pAirTimerConfig
- roamTimer * pRoamTimerConfig
- BYTE * pTTYMode
- prefVoiceSO * pPrefVoiceSO
- BYTE * pPrefVoiceDomain

8.1655.1 Detailed Description

This structure contains information about the Set Configuration Request Parameters.

Parameters

pAutoAnswer	• Value specified is written to NV_AUTO_ANSWER_I. (optional) • Values: – 0x00 - Disable – 0x01 - Enable
pAirTimerConfig	• Value specified is written to NV_AIR_CNT_I. (optional) • See airTimer for more information
pRoamTimer-Config	• Value specified is written to NV_ROAM_CNT_I. (optional) • See roamTimer for more information
pTTYMode	• Value specified is written to NV_TTY_I. (optional) • Values: – 0x00 - TTY_MODE_FULL - Full – 0x01 - TTY_MODE_VCO - Voice carry over – 0x02 - TTY_MODE_HCO - Hearing carry over – 0x03 - TTY_MODE_OFF - Off
pPrefVoiceSO	• Value specified is written to NV_PREF_VOICE_SO_I. (optional) • See prefVoiceSO for more information
pPrefVoice-Domain	• Preferred Voice-Domain. (optional) • Values: – 0x00 - VOICE_DOMAIN_PREF_CS_ONLY - Circuit-switched (CS) only – 0x01 - VOICE_DOMAIN_PREF_PS_ONLY - Packet-switched (PS) only – 0x02 - VOICE_DOMAIN_PREF_CS_PREF - CS is preferred, PS is secondary – 0x03 - VOICE_DOMAIN_PREF_PS_PREF - PS is preferred, CS is secondary

Note

One of the optional parameters must be present in the request.

8.1655.2 Field Documentation

8.1655.2.1 airTimer* voiceSetConfigReq::pAirTimerConfig

8.1655.2.2 BYTE* voiceSetConfigReq::pAutoAnswer

8.1655.2.3 BYTE* voiceSetConfigReq::pPrefVoiceDomain

8.1655.2.4 prefVoiceSO* voiceSetConfigReq::pPrefVoiceSO

8.1655.2.5 roamTimer* voiceSetConfigReq::pRoamTimerConfig

8.1655.2.6 BYTE* voiceSetConfigReq::pTTYMode

8.1656 voiceSetConfigResp Struct Reference

Data Fields

- BYTE * pAutoAnsStatus
- BYTE * pAirTimerStatus
- BYTE * pRoamTimerStatus
- BYTE * pTTYConfigStatus
- BYTE * pPrefVoiceSOStatus
- BYTE * pVoiceDomainPrefStatus

8.1656.1 Detailed Description

This structure contains information about the Set Configuration Response Parameters.

Parameters

pAutoAnsStatus	• Auto Answer Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available.
pAirTimerStatus	• Air Timer Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available.

pRoamTimer-Status	• Roam Timer Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available.
pTTYConfig-Status	• TTY Config Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available.
pPrefVoiceSO-Status	• Preferred Voice SO Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available.
pVoiceDomain-PrefStatus	• Voice-Domain Preference Status. (optional) • Values: – 0x00 - Information was written successfully – 0x01 - Information write failed – 0xFF - Not Available.

Note

Parameters which are mentioned as NULL will be ignored.

8.1656.2 Field Documentation

8.1656.2.1 BYTE* voiceSetConfigResp::pAirTimerStatus

8.1656.2.2 BYTE* voiceSetConfigResp::pAutoAnsStatus

8.1656.2.3 BYTE* voiceSetConfigResp::pPrefVoiceSOStatus

8.1656.2.4 BYTE* voiceSetConfigResp::pRoamTimerStatus

8.1656.2.5 BYTE* voiceSetConfigResp::pTTYConfigStatus

8.1656.2.6 BYTE* voiceSetConfigResp::pVoiceDomainPrefStatus

8.1657 voiceSetPrefPrivacy Struct Reference

Data Fields

- BYTE privacyPref

8.1657.1 Detailed Description

This structure contains the preferred voice privacy values.

Parameters

privacyPref	• Voice Privacy Preference – 0x00 - VOICE_PRIVACY_STANDARD - Standard privacy – 0x01 - VOICE_PRIVACY_ENHANCED - Enhanced privacy

8.1657.2 Field Documentation

8.1657.2.1 BYTE voiceSetPrefPrivacy::privacyPref

8.1658 voiceSetSUPSServiceReq Struct Reference

Data Fields

- BYTE voiceSvc
- BYTE reason
- BYTE * pServiceClass
- BYTE * pCallBarringPasswd
- BYTE * pCallForwardingNumber
- BYTE * pTimerVal
- callFwdTypeAndPlan * pCallFwdTypeAndPlan

8.1658.1 Detailed Description

This structure contains Supplementary Service request parameters related to different features and their activation, deactivation, registration and erasure (applicable only for 3GPP)

Parameters

voiceSvc	• Manages all call-independent supplementary services, such as activation, deactivation, registration, and erasure (mandatory) – 0x01 - VOICE_SERVICE_ACTIVATE – 0x02 - VOICE_SERVICE_DEACTIVATE – 0x03 - VOICE_SERVICE_REGISTER – 0x04 - VOICE_SERVICE_ERASE
reason	• supplementary service reason values (mandatory) – 0x01 - QMI_VOICE_REASON_FWD_UNCONDITIONAL Unconditional call forwarding – 0x02 - QMI_VOICE_REASON_FWD_MOBILEBUSY Forward when the mobile is busy – 0x03 - QMI_VOICE_REASON_FWD_NOREPLY Forward when there is no reply – 0x04 - QMI_VOICE_REASON_FWD_UNREACHABLE Forward when the call is unreachable – 0x05 - QMI_VOICE_REASON_FWD_ALLFORWARDING All forwarding – 0x06 - QMI_VOICE_REASON_FWD_ALLCONDITIONAL All conditional forwarding – 0x07 - QMI_VOICE_REASON_BARR_ALLOUTGOING All outgoing calls are barred – 0x08 - QMI_VOICE_REASON_BARR_OUTGOINGINT Outgoing internal calls are barred – 0x09 - QMI_VOICE_REASON_BARR_OUTGOINGINTEXTOHOME Outgoing calls external to home are barred – 0x0A - QMI_VOICE_REASON_BARR_ALLINCOMING All incoming calls are barred – 0x0B - QMI_VOICE_REASON_BARR_INCOMINGROAMING Roaming incoming calls are barred – 0x0C - QMI_VOICE_REASON_BARR_ALLBARRING All calls are barred – 0x0D - QMI_VOICE_REASON_BARR_ALLOUTGOINGBARRING All outgoing calls are barred – 0x0E - QMI_VOICE_REASON_BARR_ALLINCOMINGBARRING All incoming calls are barred – 0x0F - QMI_VOICE_REASON_CALLWAITING Call waiting
pServiceClass	• Service class is a combination (sum) of information class constants (optional) – See serviceClassInformation for more information
pCallBarring-Passwd	• Password is required if call barring is provisioned using a password. Password consists of 4 ASCII digits. Range: 0000 to 9999 (optional)

pCallForwarding-Number	• Call forwarding number to be registered with the network. This has to be included in the request only when the service is set to VOICE_SERVICE_REGISTER. NULL terminated ASCII string. (optional)
pTimerVal	• Call forwarding no reply timer value in seconds. This has to be included in the request only when the service is set to VOICE_SERVICE_REGISTER and the reason is QMI_VOICE_REASON_FWD_NOREPLY. (optional) – Range: 5 to 30 in steps of 5
pCallFwdType-AndPlan	• Information about call forwarding type and plan. This parameter is ignored when the Call Forwarding Number is not included (optional) – See callFwdTypeAndPlan for more information

8.1658.2 Field Documentation

8.1658.2.1 BYTE* voiceSetSUPSServiceReq::pCallBarringPasswd

8.1658.2.2 BYTE* voiceSetSUPSServiceReq::pCallForwardingNumber

8.1658.2.3 callFwdTypeAndPlan* voiceSetSUPSServiceReq::pCallFwdTypeAndPlan

8.1658.2.4 BYTE* voiceSetSUPSServiceReq::pServiceClass

8.1658.2.5 BYTE* voiceSetSUPSServiceReq::pTimerVal

8.1658.2.6 BYTE voiceSetSUPSServiceReq::reason

8.1658.2.7 BYTE voiceSetSUPSServiceReq::voiceSvc

8.1659 voiceSetSUPSServiceResp Struct Reference

Data Fields

- WORD * pFailCause
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCCResultType
- BYTE * pCallID
- ccSUPSType * pCCSUPSType

8.1659.1 Detailed Description

This structure contains Supplementary Service response parameters related to different features and their activation, deactivation, registration and erasure (applicable only for 3GPP)

Parameters

pFailCause	• Supplementary service failure causes (optional, supply NULL if not required). – 0xFFFF is the value when the information is not received from device

pAlphaIDInfo	• Pointer to structure of alphaIDInfo. The parameter used to pass the alpha (if any) given by the SIM/R-UIM after call control (optional, supply NULL if not required) – See alphaIDInfo for more information
pCCResultType	• Call control result types (optional, supply NULL if not required) – 0x00 - CC_RESULT_TYPE_VOICE - Voice – 0x01 - CC_RESULT_TYPE_SUPS - Supplementary service – 0x02 - CC_RESULT_TYPE_USSD - Unstructured supplementary service – 0xFF - if the device does not provide this information
pCallID	• Unique call identifier for the dialed call (optional, supply NULL if not required) – 0x00 - if the device does not provide this information
pCCSUPSType	• Data is present when pCCResultType is present and is other than Voice. (optional, supply NULL if not required) – See ccSUPSType for more information

8.1659.2 Field Documentation

8.1659.2.1 alphaIDInfo* voiceSetSUPSServiceResp::pAlphaIDInfo

8.1659.2.2 BYTE* voiceSetSUPSServiceResp::pCallID

8.1659.2.3 BYTE* voiceSetSUPSServiceResp::pCCResultType

8.1659.2.4 ccSUPSType* voiceSetSUPSServiceResp::pCCSUPSType

8.1659.2.5 WORD* voiceSetSUPSServiceResp::pFailCause

8.1660 voiceStopContDTMFinfo Struct Reference

Data Fields

- BYTE callID

8.1660.1 Detailed Description

This structure contains parameters of stop continuous DTMF

Parameters

pCallID[IN/OUT]	• Call ID associated with call on which the DTMF information has to be sent. Stop continuous DTMF request is sent to the current active/alerting call when pCallId is set to 0xFF. • This is IN/OUT parameter, value passed by user will be packed in request and value received from the device would be returned to the user. • If the call ID value received is 0, no value has been returned by the device

8.1660.2 Field Documentation

8.1660.2.1 BYTE voiceStopContDTMFinfo::callID

8.1661 voiceSUPSInfo Struct Reference

Data Fields

- struct qmTlvResult results
- SUPSInfo SUPSInformation
- BYTE * pSvcClass
- BYTE * pReason
- BYTE * pCallFWNum
- BYTE * pCallFWTimerVal
- struct USSInfo * pUSSInfo
- BYTE * pCallID
- alphaIDInfo * pAlphaIDInfo
- BYTE * pCallBarPasswd
- newPwdData * pNewPwdData
- BYTE * pDataSrc
- WORD * pFailCause
- getCallFWInfo * pCallFwdInfo
- CLIRResp * pCLIRstatus
- CLIPResp * pCLIPstatus
- COLPResp * pCOLPstatus
- COLRResp * pCOLRstatus
- CNAPResp * pCNAPstatus

8.1661.1 Detailed Description

This structure contains the parameters passed for SLQSVoiceSetSUPSCallBack by the device.

Parameters

SUPS-Information(mandatory)	• See SUPSInfo for more information.
pSvc-Class(optional)	• Service class is a combination (sum) of information class constants (optional) • See qaGobiApiTableSupServiceInfoClasses.h for service classes.
p-Reason(optional)	• See qaGobiApiTableCallControlReturnReasons.h for return reasons.

pCallFW-Num(optional)	• Call forwarding number to be registered with the network. • ASCII String, NULL terminated.
pCallFWTimer-Val(optional)	• Call Forwarding No Reply Timer. – Range: 5 to 30 in steps of 5.
pUSS-Info(optional)	• See USSInfo for more information.
pCallID(optional)	• Call identifier of the voice call that has been modified to a supplementary service as a result of call control.
pAlphaID-Info(optional)	• See alphaIDInfo for more information.
pCallBar-Passwd(optional)	• Password is required if call barring is provisioned using a password. – Password consists of 4 ASCII digits. – Range: 0000 to 9999. • This also serves as the old password in the register password scenario.
pNewPwd-Data(optional)	• See newPwdData for more information.
pData-Src(optional)	• Sups Data Source. • Used to distinguish between the supplementary service data sent to the network and the response received from the network. • If absent, the supplementary service data in this indication can be assumed as a request sent to the network.
pFail-Cause(optional)	• Supplementary services failure cause. • See qaGobiApiTableVoiceCallEndReasons.h for more information.
pCallFwd-Info(optional)	• See getCallFWInfo for more information.
pCLI-Rstatus(optional)	• See CLIRResp for more information.
pCLI-Pstatus(optional)	• See CLIPResp for more information.
pCOL-Pstatus(optional)	• See COLPResp for more information.
pCOL-Rstatus(optional)	• See COLRResp for more information.

pCNA-Pstatus(optional)	• See CNAPResp for more information.

Note

None

8.1661.2 Field Documentation

8.1661.2.1 alphaIDInfo* voiceSUPSInfo::pAlphaIDInfo

8.1661.2.2 BYTE* voiceSUPSInfo::pCallBarPasswd

8.1661.2.3 getCallFWInfo* voiceSUPSInfo::pCallFwdInfo

8.1661.2.4 BYTE* voiceSUPSInfo::pCallFWNum

8.1661.2.5 BYTE* voiceSUPSInfo::pCallFWTimerVal

8.1661.2.6 BYTE* voiceSUPSInfo::pCallID

8.1661.2.7 CLIPResp* voiceSUPSInfo::pCLIPstatus

8.1661.2.8 CLIRResp* voiceSUPSInfo::pCLIRstatus

8.1661.2.9 CNAPResp* voiceSUPSInfo::pCNAPstatus

8.1661.2.10 COLPResp* voiceSUPSInfo::pCOLPstatus

8.1661.2.11 COLRResp* voiceSUPSInfo::pCOLRstatus

8.1661.2.12 BYTE* voiceSUPSInfo::pDataSrc

8.1661.2.13 WORD* voiceSUPSInfo::pFailCause

8.1661.2.14 newPwdData* voiceSUPSInfo::pNewPwdData

8.1661.2.15 BYTE* voiceSUPSInfo::pReason

8.1661.2.16 BYTE* voiceSUPSInfo::pSvcClass

8.1661.2.17 struct USSInfo* voiceSUPSInfo::pUSSInfo

8.1661.2.18 struct qmTlvResult voiceSUPSInfo::results

8.1661.2.19 SUPSInfo voiceSUPSInfo::SUPSInformation

8.1662 voiceSUPSNotification Struct Reference

Data Fields

- struct qmTlvResult results
- BYTE callID

- BYTE notifType
- WORD * pCUGIndex
- ECTNum * pECTNum

8.1662.1 Detailed Description

Contains the parameters passed for SLQSVoiceSetSUPSNotificationCallback by the device.

Parameters

callID	• Unique identifier of the call for which the notification is applicable. (mandatory)
notifType	• Notification type parameter (mandatory) – 0x01 - NOTIFICATION_TYPE_OUTGOING_CALL_IS_FORWARDED Originated MO call is being forwarded to another user – 0x02 - NOTIFICATION_TYPE_OUTGOING_CALL_IS_WAITING Originated MO call is waiting at the called user – 0x03 - NOTIFICATION_TYPE_OUTGOING_CUG_CALL Outgoing call is a CUG call – 0x04 - NOTIFICATION_TYPE_OUTGOING_CALLS_BARRED Outgoing calls are barred – 0x05 - NOTIFICATION_TYPE_OUTGOING_CALL_IS_DEFLECTED Outgoing call is deflected – 0x06 - NOTIFICATION_TYPE_INCOMING_CUG_CALL Incoming call is a CUG call – 0x07 - NOTIFICATION_TYPE_INCOMING_CALLS_BARRED Incoming calls are barred – 0x08 - NOTIFICATION_TYPE_INCOMING_FORWARDED_CALL Incoming call received is a forwarded call – 0x09 - NOTIFICATION_TYPE_INCOMING_DEFLECTED_CALL Incoming call is a deflected call – 0x0A - NOTIFICATION_TYPE_INCOMING_CALL_IS_FORWARDED Incoming call is forwarded to another user – 0x0B - NOTIFICATION_TYPE_UNCOND_CALL_FORWARD_ACTIVE Unconditional call forwarding is active – 0x0C - NOTIFICATION_TYPE_COND_CALL_FORWARD_ACTIVE Conditional call forwarding is active – 0x0D - NOTIFICATION_TYPE_CLIR_SUPPRESSION_REJECTED CLIR suppression is rejected – 0x0E - NOTIFICATION_TYPE_CALL_IS_ON_HOLD Call is put on hold at the remote party – 0x0F - NOTIFICATION_TYPE_CALL_IS_RETRIEVED Call is retrieved at the remote party from the hold state – 0x10 - NOTIFICATION_TYPE_CALL_IS_IN_MPTY Call is in a conference – 0x11 - NOTIFICATION_TYPE_INCOMING_CALL_IS_ECT Incoming call is an explicit call transfer
pCUGIndex	• The CUG Index used to indicate that the incoming/outgoing call is a CUG call. (optional, NULL when not present) Range: 0x00 to 0x7FFF.

pECTNum	• The ECT Number is used to indicate that the incoming call is an explicitly transferred call. (optional, NULL when not present) Refer ECTNum for details.

Note

None

8.1662.2 Field Documentation

8.1662.2.1 BYTE voiceSUPSNotification::callID

8.1662.2.2 BYTE voiceSUPSNotification::notifType

8.1662.2.3 WORD* voiceSUPSNotification::pCUGIndex

8.1662.2.4 ECTNum* voiceSUPSNotification::pECTNum

8.1662.2.5 struct qmTlvResult voiceSUPSNotification::results

8.1663 wcdmaCellInfo Struct Reference

Data Fields

- WORD psc
- SHORT cpich_rscp
- SHORT cpich_ecno
- SHORT srxlev

8.1663.1 Detailed Description

This structure contains information about the WCDMA Cell.

Parameters

psc	• Primary scrambling code. • Range: 0 to 511.
cpich_rscp	• Absolute power level (in 1/10 dBm) of the common pilot channel as received by the UE. • Range: -120.0 dBm to -25.0 dBm
cpich_ecno	• CPICH Ec/No; ratio (in 1/10 dB) of the received energy per PN chip for the CPICH to the total received power spectral density at the UE antenna connector. • Range: -50.0 dB to 0.

srxlev	• Cell selection Rx level (Srxlev) value. • Range: -128 to 128. • This field is only valid when ue_in_idle is TRUE.

8.1663.2 Field Documentation

8.1663.2.1 SHORT wcdmaCellInfo::cpich_ecno

8.1663.2.2 SHORT wcdmaCellInfo::cpich_rscp

8.1663.2.3 WORD wcdmaCellInfo::psc

8.1663.2.4 SHORT wcdmaCellInfo::srxlev

8.1664 WCDMAECIOThresh Struct Reference

Data Fields

- BYTE WCDMAECIOThreshListLen
- WORD * pWCDMAECIOThreshList

8.1664.1 Detailed Description

This structure contains WCDMA ECIO threshold related parameters.

Parameters

WCDMAECIO-ThreshListLen	• Length of the WCDMA ECIO threshold list parameter to follow
pWCDMAECIO-ThreshList	• Array of ECIO thresholds (in units of 0.1 dB) • Maximum of 32 values • Range for ECIO values: -31.5 to 0 (in dB)

8.1664.2 Field Documentation

8.1664.2.1 WORD* WCDMAECIOThresh::pWCDMAECIOThreshList

8.1664.2.2 BYTE WCDMAECIOThresh::WCDMAECIOThreshListLen

8.1665 WCDMAInfoLTENeighborCell Struct Reference

Data Fields

- ULONG wcdmaRRCState
- BYTE umtsLTENbrCellLen
- umtsLTENbrCell UMTSLTENbrCell [255]

8.1665.1 Detailed Description

This structure contains information about the WCDMA - LTE Neighboring Cell Info Set.

Parameters

wcdmaRRC-State	• WCDMA RRC states. • Defined in 3GPP TS 25.331 • Values: – 0x00 - NAS_WCDMA_RRC_STATE_DISCONNECTED * WCDMA RRC State is IDLE – 0x01 - NAS_WCDMA_RRC_STATE_CELL_PCH * WCDMA RRC state is CELL_PCH – 0x02 - NAS_WCDMA_RRC_STATE_URA_PCH * WCDMA RRC state is URA_PCH – 0x03 - NAS_WCDMA_RRC_STATE_CELL_FACH * WCDMA RRC state is CELL_FACH – 0x04 - NAS_WCDMA_RRC_STATE_CELL_DCH * WCDMA RRC state is CELL_DCH
umtsLTENbr-CellLen	• Number of sets of UMTS LTE Neighbors.
UMTSLTENbr-Cell	• See umtsLTENbrCell for more information.

8.1665.2 Field Documentation

8.1665.2.1 umtsLTENbrCell WCDMAInfoLTENeighborCell::UMTSLTENbrCell[255]

8.1665.2.2 BYTE WCDMAInfoLTENeighborCell::umtsLTENbrCellLen

8.1665.2.3 ULONG WCDMAInfoLTENeighborCell::wcdmaRRCState

8.1666 wcdmaLongMsgDecodingParams Struct Reference

Data Fields

- BYTE * pMessage
- USHORT MessageLen
- BYTE * pSenderAddrLength
- CHAR * pSenderAddr
- BYTE * pTextMsgLength
- CHAR * pTextMsg
- BYTE * pScAddrLength
- CHAR * pScAddr
- sms_DateTime Time
- sms_DateTime Date
- BYTE * pReferenceNum
- BYTE * pTotalNum
- BYTE * pPartNum
- BOOL * pIsUDHPresent

8.1666.1 Detailed Description

Structure contains parameters which need to be decoded from message

Parameters

pMessage[IN]	• Message read off the device via SLQSGetSMS
MessageLen[IN]	• Message buffer length
pSenderAddr-Length[IN/OUT]	• Upon input, indicates the maximum number of ASCII characters (including NULL termination) that the pSenderAddr buffer can accommodate. A length with 24 will be much safe since this address filed can be up to 12 octets (24 bytes) Upon successful output, returns the length of destination address string.
pSenderAddr[O-UT]	• Note that a length with 24 bytes will be much safe. Returns NULL-terminated ASCII String containing destination address This field contains the Type of Address. To get the exact address, skip the first two bytes. e.g, 9085290100334, 90 is the Type of Address, indicates international format of phone number
pTextMsg-Length[IN/OUT]	• Upon input, specifies the number of characters the given text message buffer can accommodate. Upon successful output, returns the number of characters returns in the given text message buffer.
pTextMsg[OUT]	• Encoded PDU message
pScAddrLength[-IN/OUT]	• A length with 24 will be much safe since this address filed can be up to 12 octets (24 bytes) Returns NULL-terminated ASCII String containing destination address
pScAddr[OUT]	• Note that a length with 24 bytes will be much safe. Returns NULL-terminated ASCII String containing service center address. This SMSC field contains the Type of Address. To get the exact SMSC address, skip the first two bytes. e.g, 9085290100334, 90 is the Type of Address, indicates international format of phone number
Time[OUT]	• Time fecthed from message
Date[OUT]	• Date fecthed from message
pReference-Num[OUT]	• Reference number of the sms
pTotalNum[OUT]	• Total number of the concatenated message
pPartNum[OUT]	• Sequence number of the current message

pIsUDHPresent	• Is User Data Header Prensent in the PDU? If yes, it means it is a • concatenated SMS.

8.1666.2 Field Documentation

8.1666.2.1 sms_DateTime wcdmaLongMsgDecodingParams::Date

8.1666.2.2 USHORT wcdmaLongMsgDecodingParams::MessageLen

8.1666.2.3 BOOL* wcdmaLongMsgDecodingParams::pIsUDHPresent

8.1666.2.4 BYTE* wcdmaLongMsgDecodingParams::pMessage

8.1666.2.5 BYTE* wcdmaLongMsgDecodingParams::pPartNum

8.1666.2.6 BYTE* wcdmaLongMsgDecodingParams::pReferenceNum

8.1666.2.7 CHAR* wcdmaLongMsgDecodingParams::pScAddr

8.1666.2.8 BYTE* wcdmaLongMsgDecodingParams::pScAddrLength

8.1666.2.9 CHAR* wcdmaLongMsgDecodingParams::pSenderAddr

8.1666.2.10 BYTE* wcdmaLongMsgDecodingParams::pSenderAddrLength

8.1666.2.11 CHAR* wcdmaLongMsgDecodingParams::pTextMsg

8.1666.2.12 BYTE* wcdmaLongMsgDecodingParams::pTextMsgLength

8.1666.2.13 BYTE* wcdmaLongMsgDecodingParams::pTotalNum

8.1666.2.14 sms_DateTime wcdmaLongMsgDecodingParams::Time

8.1667 wcdmaMsgDecodingParams Struct Reference

Data Fields

- BYTE * pMessage
- USHORT MessageLen
- BYTE * pSenderAddrLength
- CHAR senderAddr [24+1]
- BYTE * pTextMsgLength
- CHAR textMsg [160+2]
- BYTE * pScAddrLength
- CHAR scAddr [24+1]
- sms_DateTime time
- sms_DateTime date

8.1667.1 Detailed Description

Structure contains parameters which need to be decoded from message

Parameters

pMessage[IN]	• Message read off the device via SLQSGetSMS
MessageLen	• Message buffer Length
pSenderAddr-Length[IN/OUT]	• Upon input, indicates the maximum number of ASCII characters (including NULL termination) that the pSenderAddr buffer can accommodate. A length with 24 will be much safe since this address filed can be up to 12 octets (24 bytes) Upon successful output, returns the length of destination address string.
senderAddr[OU-T]	• Note that a length with 24 bytes will be much safe. Returns NULL-terminated ASCII String containing destination address
pTextMsg-Length[IN/OUT]	• Upon input, specifies the number of characters the given text message buffer can accommodate. Upon successful output, returns the number of characters returns in the given text message buffer.
textMsg[OUT]	• Encoded PDU message
pScAddrLength[-IN/OUT]	• A length with 24 will be much safe since this address filed can be up to 12 octets (24 bytes) Returns NULL-terminated ASCII String containing destination address
scAddr[OUT]	• Note that a length with 24 bytes will be much safe. Returns NULL-terminated ASCII String containing service center address. This SMSC field contains the Type of Address. To get the exact SMSC address, skip the first two bytes. e.g, 9085290100334, 90 is the Type of Address, indicates international format of phone number
time[OUT]	• Time fecthed from message
date[OUT]	• Date fecthed from message

8.1667.2 Field Documentation

8.1667.2.1 sms_DateTime wcdmaMsgDecodingParams::date

8.1667.2.2 USHORT wcdmaMsgDecodingParams::MessageLen

8.1667.2.3 BYTE* wcdmaMsgDecodingParams::pMessage

8.1667.2.4 BYTE* wcdmaMsgDecodingParams::pScAddrLength

8.1667.2.5 BYTE* wcdmaMsgDecodingParams::pSenderAddrLength

8.1667.2.6 BYTE* wcdmaMsgDecodingParams::pTextMsgLength

8.1667.2.7 CHAR wcdmaMsgDecodingParams::scAddr[24+1]

8.1667.2.8 CHAR wcdmaMsgDecodingParams::senderAddr[24+1]

8.1667.2.9 CHAR wcdmaMsgDecodingParams::textMsg[160+2]

8.1667.2.10 sms_DateTime wcdmaMsgDecodingParams::time

8.1668 wcdmaMsgEncodingParams Struct Reference

Data Fields

- ULONG messageSize
- CHAR * pDestAddr
- CHAR * pTextMsg
- CHAR PDUMessage [400]
- BYTE alphabet

8.1668.1 Detailed Description

Structure contains parameters which need to encoded with message

Parameters

messageSize	• The length of the message contents in bytes
pDestAddr[IN]	• Gives NULL-terminated ASCII String containing destination address
pTextMsg[IN]	• Text message to be encoded, maximum limit is 160 charaters
PDUMessage[OUT]	• Encoded PDU message
alphabet[IN]	• Encoding method to generate the PDU – 0 - 7 bit encoding – 4 - 8 bit encoding – 8 - 16 bit UCS2 encoding – others value will be treated as default 7 bit encoding

8.1668.2 Field Documentation

8.1668.2.1 BYTE wcdmaMsgEncodingParams::alphabet

8.1668.2.2 ULONG wcdmaMsgEncodingParams::messageSize

8.1668.2.3 CHAR* wcdmaMsgEncodingParams::pDestAddr

8.1668.2.4 CHAR wcdmaMsgEncodingParams::PDUMessage[400]

8.1668.2.5 CHAR* wcdmaMsgEncodingParams::pTextMsg

8.1669 WCDMARSSIThresh Struct Reference

Data Fields

- BYTE WCDMARSSIThreshListLen
- WORD * pWCDMARSSIThreshList

8.1669.1 Detailed Description

This structure contains WCDMA RSSI threshold related parameters.

Parameters

WCDMARSSI-ThreshListLen	• Length of the WCDMA RSSI threshold list parameter to follow
pWCDMARSSI-ThreshList	• Array of RSSI thresholds (in units of 0.1 dBm) • Maximum of 32 values. • Range for RSSI values: -121 to 0 (in dBm)

8.1669.2 Field Documentation

8.1669.2.1 WORD* WCDMARSSIThresh::pWCDMARSSIThreshList

8.1669.2.2 BYTE WCDMARSSIThresh::WCDMARSSIThreshListLen

8.1670 WCDMASysInfo Struct Reference

Data Fields

- sysInfoCommon sysInfoWCDMA
- BYTE lacValid
- WORD lac
- BYTE cellIdValid
- ULONG cellId
- BYTE regRejectInfoValid
- BYTE rejectSrvDomain
- BYTE rejCause
- BYTE networkIdValid
- BYTE MCC [3]
- BYTE MNC [3]
- BYTE hsCallStatusValid
- BYTE hsCallStatus
- BYTE hsIndValid
- BYTE hsInd
- BYTE pscValid
- WORD psc

8.1670.1 Detailed Description

Structure for storing the WCDMA System Information.

Parameters

sysInfoWCDMA	• See sysInfoCommon for more information.
lacValid	• Indicates whether the location area code is valid.. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
lac	• Location area code. • Only applies to 3GPP. – 0xFFFF - Not Available
cellIdValid	• Indicates whether the cell ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
cellId	• Cell ID. – 0xFFFFFFFF - Not Available
regRejectInfo-Valid	• Indicates whether the registration reject information is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
rejectSrvDomain	• Type of service domain in which the registration is rejected. – 0x00 - SYS_SRV_DOMAIN_NO_SRV - No service – 0x01 - Circuit-switched only – 0x02 - Packet-switched only – 0x03 - Circuit-switched and packet-switched – 0x04 - Camped – 0xFF - Not Available
rejCause	• Reject cause values sent are specified in [3GPP TS 24.008, Section 10.5.3.6]. – 0xFF - Not Available

networkIdValid	• Indicates whether the network ID is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
MCC[PLMN_LENGTH]	• Mobile Country Code. • MCC digits in ASCII characters
MNC[PLMN_LENGTH]	• Mobile Network Code. • MNC digits in ASCII characters • An unused byte is set to 0xFF. • In case of two-digit MNC values, the third (unused) digit is set to 0xFF. For example, 15 (a two-digit MNC) is reported using the byte stream 0x31 0x35 0xFF.
hsCallStatusValid	• Indicates whether the high-speed call status is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
hsCallStatus	• Call status on high speed. • Only applicable for WCDMA. – 0x00 - HSDPA and HSUPA are unsupported – 0x01 - HSDPA is supported – 0x02 - HSUPA is supported – 0x03 - HSDPA and HSUPA are supported – 0x04 - HSDPA+ is supported – 0x05 - HSDPA+ and HSUPA are supported – 0x06 - Dual-cell HSDPA+ is supported – 0x07 - Dual-cell HSDPA+ and HSUPA are supported – 0xFF - Not Available
hsIndValid	• Indicates whether high-speed service indication is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available

hsInd	• High-speed service indication • Only applicable for WCDMA. – 0x00 - HSDPA and HSUPA are unsupported – 0x01 - HSDPA is supported – 0x02 - HSUPA is supported – 0x03 - HSDPA and HSUPA are supported – 0x04 - HSDPA+ is supported – 0x05 - HSDPA+ and HSUPA are supported – 0x06 - Dual-cell HSDPA+ is supported – 0x07 - Dual-cell HSDPA+ and HSUPA are supported – 0xFF - Not Available
pscValid	• Indicates whether primary scrambling code is valid. – 0x00 - Invalid – 0x01 - Valid – 0xFF - Not Available
psc	• Primary scrambling code. – 0xFFFF - Not Available

8.1670.2 Field Documentation

8.1670.2.1 ULONG WCDMASysInfo::cellId

8.1670.2.2 BYTE WCDMASysInfo::cellIdValid

8.1670.2.3 BYTE WCDMASysInfo::hsCallStatus

8.1670.2.4 BYTE WCDMASysInfo::hsCallStatusValid

8.1670.2.5 BYTE WCDMASysInfo::hsInd

8.1670.2.6 BYTE WCDMASysInfo::hsIndValid

8.1670.2.7 WORD WCDMASysInfo::lac

8.1670.2.8 BYTE WCDMASysInfo::lacValid

8.1670.2.9 BYTE WCDMASysInfo::MCC[3]

8.1670.2.10 BYTE WCDMASysInfo::MNC[3]

8.1670.2.11 BYTE WCDMASysInfo::networkIdValid

8.1670.2.12 WORD WCDMASysInfo::psc

8.1670.2.13 BYTE WCDMASysInfo::pscValid

8.1670.2.14 BYTE WCDMASysInfo::regRejectInfoValid

8.1670.2.15 BYTE WCDMASysInfo::rejCause

8.1670.2.16 BYTE WCDMASysInfo::rejectSrvDomain

8.1670.2.17 sysInfoCommon WCDMASysInfo::sysInfoWCDMA

8.1671 wcdmaUARFCN Struct Reference

Data Fields

- BYTE status
- ULONG uarfcn

8.1671.1 Detailed Description

This structure contains the parameters for WCDMA UARFCN.

Parameters

status	• 0 - Disable • 1 - Enable
uarfcn	• UARFCN to which UE is locked

8.1671.2 Field Documentation

8.1671.2.1 BYTE wcdmaUARFCN::status

8.1671.2.2 ULONG wcdmaUARFCN::uarfcn

8.1672 wds_channelRate Struct Reference

Data Fields

- uint32_t CurrChanTxRate
- uint32_t CurrChanRxRate

8.1672.1 Detailed Description

This structure contains Channel Rate

Parameters

CurrChanTxRate	• Max channel Tx rate in bits per second
CurrChanRx-Rate	• Max channel Rx rate in bits per second

8.1672.2 Field Documentation

8.1672.2.1 uint32_t wds_channelRate::CurrChanRxRate

8.1672.2.2 uint32_t wds_channelRate::CurrChanTxRate

8.1673 wds_ChannelRateTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- wds_channelRate ChannelRate

8.1673.1 Detailed Description

This structure stores information about channel rate TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
ChannelRate	• see wds_channelRate for more info

8.1673.2 Field Documentation

8.1673.2.1 wds_channelRate wds_ChannelRateTlv::ChannelRate

8.1673.2.2 uint8_t wds_ChannelRateTlv::TlvPresent

8.1674 wds_ConnStatusTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t MDMConnStatus

8.1674.1 Detailed Description

This structure stores information about modem connection status TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
MDMConn-Status	-Modem connecton status • 0x01 - disconnected • 0x02 - connected

8.1674.2 Field Documentation

8.1674.2.1 uint8_t wds_ConnStatusTlv::MDMConnStatus

8.1674.2.2 uint8_t wds_ConnStatusTlv::TlvPresent

8.1675 wds_currNetworkInfo Struct Reference

Data Fields

- uint8_t NetworkType
- uint32_t RATMask
- uint32_t SOMask

8.1675.1 Detailed Description

Network information structure

Parameters

NetworkType	• Values: – 0 - 3GPP – 1 - 3GPP2
RATMask	• RAT mask to indicate type of technology • Values – 0x00 - DONT_CARE – 0x8000 - NULL_BEARER • CDMA RAT mask – 0x01 - CDMA_1X – 0x02 - EVDO_REV0 – 0x05 - HRPD – 0x0B - EHRPD • UMTS RAT mask – 0x03 - GPRS – 0x04 - WCDMA – 0x06 - EDGE – 0x07 - HSDPA and WCDMA – 0x08 - WCDMA and HSUPA – 0x09 - HSDPA and HSUPA – 0x0A - LTE – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA
SOMask	• SO Mask

8.1675.2 Field Documentation

8.1675.2.1 uint8_t wds_currNetworkInfo::NetworkType

8.1675.2.2 uint32_t wds_currNetworkInfo::RATMask

8.1675.2.3 uint32_t wds_currNetworkInfo::SOMask

8.1676 wds_DataBearTechTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t DataBearerTech

8.1676.1 Detailed Description

This structure hold parameters about data bearer technology TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
DataBearerTech	• Data bear technology – 0x01 - cdma2000 1X – 0x02 - cdma2000 HRPD (1xEV-DO) – 0x03 - GSM – 0x04 - UMTS – 0x05 - cdma200 HRPD (1xEV-DO RevA) – 0x06 - EDGE – 0x07 - HSDPA and WCDMA – 0x08 - WCDMA and HSUPA – 0x09 - HSDPA and HSUPA – 0x0A - LTE – 0x0B - cdma2000 EHRPD – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA – 0x10 - HSDPA+ and 64QAM – 0x11 - HSDPA+, 64QAM and HSUPA – 0x12 - TDSCDMA – 0x13 - TDSCDMA and HSDPA – 0xFF - Unknown

8.1676.2 Field Documentation

8.1676.2.1 uint8_t wds_DataBearTechTlv::DataBearerTech

8.1676.2.2 uint8_t wds_DataBearTechTlv::TlvPresent

8.1677 wds_DataULongLongTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t ullData

8.1677.1 Detailed Description

This structure contains Data unsigned long long TLV data.

Parameters

TlvPresent	a flag indicates whether TLV presented or not
ullData	unsigend long long data in 64bit

8.1677.2 Field Documentation

8.1677.2.1 uint8_t wds_DataULongLongTlv::TlvPresent

8.1677.2.2 uint64_t wds_DataULongLongTlv::ullData

8.1678 wds_DataULongTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t ulData

8.1678.1 Detailed Description

This structure contains Data unsigned long TLV data.

Parameters

TlvPresent	a flag indicates whether TLV presented or not
ulData	unsigend long data in 32bit

8.1678.2 Field Documentation

8.1678.2.1 uint8_t wds_DataULongTlv::TlvPresent

8.1678.2.2 uint32_t wds_DataULongTlv::ulData

8.1679 wds_DHCPLeaseOptTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t numOpt

- wds_DHCPOpt optList [30]
- uint8_t optListData [2048]

8.1679.1 Detailed Description

DHCP lease option information

Parameters

TlvPresent	a flag indicates whether TLV presented or not
numOpt	number of sets of wds_DHCPOpt
optList	option list
optListData	option list data

8.1679.2 Field Documentation

8.1679.2.1 uint8_t wds_DHCPLeaseOptTlv::numOpt

8.1679.2.2 wds_DHCPOpt wds_DHCPLeaseOptTlv::optList[30]

8.1679.2.3 uint8_t wds_DHCPLeaseOptTlv::optListData[2048]

8.1679.2.4 uint8_t wds_DHCPLeaseOptTlv::TlvPresent

8.1680 wds_DHCPLeaseStateTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t leaseState

8.1680.1 Detailed Description

DHCP lease state information

Parameters

TlvPresent	a flag indicates whether TLV presented or not
leaseState	lease state • 0 - active, newly acquired • 1 - active, renewed • 2 - active, renewing • 3 - active, rebinding • 4 - inactive, expired • 5 - inactive, renew refused • 6 - inactive, rebind refused • 7 - inactive, other

8.1680.2 Field Documentation

8.1680.2.1 uint8_t wds_DHCPLeaseStateTlv::leaseState

8.1680.2.2 uint8_t wds_DHCPLeaseStateTlv::TlvPresent

8.1681 wds_DHCPOpt Struct Reference

Data Fields

- uint8_t optCode
- uint8_t optValLen
- uint8_t * pOptVal

8.1681.1 Detailed Description

DHCP option code information

Parameters

optCode	option code • values: – 0 - 255
optValLen	length of option code • values: – 0 - 255
pOptVal	option value

8.1681.2 Field Documentation

8.1681.2.1 uint8_t wds_DHCPOpt::optCode

8.1681.2.2 uint8_t wds_DHCPOpt::optValLen

8.1681.2.3 uint8_t* wds_DHCPOpt::pOptVal

8.1682 wds_DHCPProfileIdTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t profileType
- uint8_t profileId

8.1682.1 Detailed Description

DHCP profile id TLV information

Parameters

TlvPresent	a flag indicates whether TLV presented or not
profileType	identifying the type of the profile • 0 - 3GPP

profileId	index identifying the profile • 1-24 valid for 3GPP profile type (9x30 and onwards)

8.1682.2 Field Documentation

8.1682.2.1 uint8_t wds_DHCPProfileIdTlv::profileId

8.1682.2.2 uint8_t wds_DHCPProfileIdTlv::profileType

8.1682.2.3 uint8_t wds_DHCPProfileIdTlv::TlvPresent

8.1683 wds_DHCPv4HWConfig Struct Reference

Data Fields

- uint8_t hwType
- uint8_t chaddrLen
- uint8_t chaddr [16]

8.1683.1 Detailed Description

WDS SWI DHCPv4 HW Config Structure.

Parameters

hwType	• HW Type 1 - Ethernet 20 - Serial
chaddrlen	• chaddrlen
chaddr	• chaddr. Max size 16 bytes

8.1683.2 Field Documentation

8.1683.2.1 uint8_t wds_DHCPv4HWConfig::chaddr[16]

8.1683.2.2 uint8_t wds_DHCPv4HWConfig::chaddrLen

8.1683.2.3 uint8_t wds_DHCPv4HWConfig::hwType

8.1684 wds_DHCPv4Option Struct Reference

Data Fields

- uint8_t optCode
- uint8_t optValLen
- uint8_t optVal [255]

8.1684.1 Detailed Description

WDS SWI DHCPv4 Option Structure

Parameters

optCode	• Option code – 0 - 255
optValLen	• Option value length – 0 - 255
optVal	• Option value

8.1684.2 Field Documentation

8.1684.2.1 uint8_t wds_DHCPv4Option::optCode

8.1684.2.2 uint8_t wds_DHCPv4Option::optVal[255]

8.1684.2.3 uint8_t wds_DHCPv4Option::optValLen

8.1685 wds_DHCPv4OptionList Struct Reference

Data Fields

- uint8_t numOpt
- wds_DHCPv4Option * pOptList

8.1685.1 Detailed Description

WDS SWI DHCPv4 Option List Structure

Parameters

numOpt	• number of options – 0 - 255
pOptList	• pointer to list of DHCP Options

8.1685.2 Field Documentation

8.1685.2.1 uint8_t wds_DHCPv4OptionList::numOpt

8.1685.2.2 wds_DHCPv4Option* wds_DHCPv4OptionList::pOptList

8.1686 wds_DHCPv4ProfileId Struct Reference

Data Fields

- uint8_t profileType
- uint8_t profileId

8.1686.1 Detailed Description

WDS SWI DHCPv4 Profile Identifier Structure

Parameters

profileType	• 0 for 3GPP
profileId	• 1 to 24 for 3GPP profile

8.1686.2 Field Documentation

8.1686.2.1 uint8_t wds_DHCPv4ProfileId::profileId

8.1686.2.2 uint8_t wds_DHCPv4ProfileId::profileType

8.1687 wds_Domain Struct Reference

Data Fields

- uint16_t domainLen
- uint8_t domainName [256]

8.1687.1 Detailed Description

This structure contains the DomainName Information

Parameters

domainLen	• length of the recieved Domain name
domainName	• Domain name(Max 256 characters)

8.1687.2 Field Documentation

8.1687.2.1 uint16_t wds_Domain::domainLen

8.1687.2.2 uint8_t wds_Domain::domainName[256]

8.1688 wds_DomainNameList Struct Reference

Data Fields

- uint8_t numInstances
- struct wds_Domain domain [10]

8.1688.1 Detailed Description

This structure contains the DomainNameList Information

Parameters

numInstances	• Number of Domain name receieved
domain	• Domain name information(Max 10 Domain names)

Note

Data invalid when numInstances equal 0xff.

8.1688.2 Field Documentation

8.1688.2.1 struct wds_Domain wds_DomainNameList::domain[10]

8.1688.2.2 uint8_t wds_DomainNameList::numInstances

8.1689 wds_DormStatTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint8_t DormancyStat

8.1689.1 Detailed Description

This structure stores information about dormancy status TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
DormancyStat	-Dormancy status • 0x01 - Traffic channel dormant • 0x02 - Traffic channel active

8.1689.2 Field Documentation

8.1689.2.1 uint8_t wds_DormStatTlv::DormancyStat

8.1689.2.2 uint8_t wds_DormStatTlv::TlvPresent

8.1690 wds_GPRSQoS Struct Reference

Data Fields

- uint32_t precedenceClass
- uint32_t delayClass
- uint32_t reliabilityClass
- uint32_t peakThroughputClass
- uint32_t meanThroughputClass

8.1690.1 Detailed Description

This structure contains the GPRS Quality Of Service Information

Parameters

precedence-Class	• Precedence class
delayClass	• Delay class
reliabilityClass	• Reliability class
peak-Throughput-Class	• Peak throughput class
mean-Throughput-Class	• Mean throughput class

Note

Data invalid when all parameters are equal to 0xffffffff.

8.1690.2 Field Documentation

8.1690.2.1 uint32_t wds_GPRSQoS::delayClass

8.1690.2.2 uint32_t wds_GPRSQoS::meanThroughputClass

8.1690.2.3 uint32_t wds_GPRSQoS::peakThroughputClass

8.1690.2.4 uint32_t wds_GPRSQoS::precedenceClass

8.1690.2.5 uint32_t wds_GPRSQoS::reliabilityClass

8.1691 wds_IPv4AdTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint32_t IPv4Addr

8.1691.1 Detailed Description

IPv4 address TLV information

Parameters

TlvPresent	a flag indicates whether TLV presented or not
IPv4Addr	IPv4 address

8.1691.2 Field Documentation

8.1691.2.1 uint32_t wds_IPv4AdTlv::IPv4Addr

8.1691.2.2 uint8_t wds_IPv4AdTlv::TlvPresent

8.1692 wds_IPV6AddressInfo Struct Reference

Data Fields

- uint8_t IPV6PrefixLen
- uint16_t IPAddressV6 [8]

8.1692.1 Detailed Description

This structure contains the IPV6 Address Information

Parameters

IPV6PrefixLen	• Length of the received IPv6 address in no. of bits; can take value between 0 and 128 – 0xFF - Not Available
IPAddressV6	• IPv6 address(in network byte order); This is an 8-element array of 16 bit numbers, each of which is in big endian format.

8.1692.2 Field Documentation

8.1692.2.1 uint16_t wds_IPV6AddressInfo::IPAddressV6[8]

8.1692.2.2 uint8_t wds_IPV6AddressInfo::IPV6PrefixLen

8.1693 wds_IPV6GWAddressInfo Struct Reference

Data Fields

- uint8_t gwV6PrefixLen

- uint16_t gwAddressV6 [8]

8.1693.1 Detailed Description

This structure contains the IPV6 Gateway Address Information

Parameters

gwV6PrefixLen	• Length of the received IPv6 Gateway address in no. of bits; can take value between 0 and 128
IPAddressV6	• IPv6 Gateway address(in network byte order); This is an 8-element array of 16 bit numbers, each of which is in big endian format.

Note

Data invalid when IPV6PrefixLen equal 0xff.

8.1693.2 Field Documentation

8.1693.2.1 uint16_t wds_IPV6GWAddressInfo::gwAddressV6[8]

8.1693.2.2 uint8_t wds_IPV6GWAddressInfo::gwV6PrefixLen

8.1694 wds_LastMdmCallEndRsnTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint16_t CallEndReason

8.1694.1 Detailed Description

This structure stores information about modem last call end reason TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
CallEndReason	-Modem call end reason • See qaGobiApiTableCallEndReasons.h for Call End Reason

8.1694.2 Field Documentation

8.1694.2.1 uint16_t wds_LastMdmCallEndRsnTlv::CallEndReason

8.1694.2.2 uint8_t wds_LastMdmCallEndRsnTlv::TlvPresent

8.1695 wds_PCSCFFQDNAddress Struct Reference

Data Fields

- uint16_t fqdnLen
- uint8_t fqdnAddr [256]

8.1695.1 Detailed Description

This structure contains the PCSCFFQDNAddress Information

Parameters

fqdnLen	• length of the received FQDN address
fqdnAddr	• FQDN address(Max 256 characters)

8.1695.2 Field Documentation

8.1695.2.1 uint8_t wds_PCSCFFQDNAddress::fqdnAddr[256]

8.1695.2.2 uint16_t wds_PCSCFFQDNAddress::fqdnLen

8.1696 wds_PCSCFFQDNAddressList Struct Reference

Data Fields

- uint8_t numInstances
- struct wds_PCSCFFQDNAddress pcsfFQDNAddress [10]

8.1696.1 Detailed Description

This structure contains the PCSCFFQDNAddressList Information

Parameters

numInstances	• Number of FQDN addresses received
pcsfFQDN-Address	• FQDN address information(Max 10 addresses)

Note

Data invalid when numInstances equal 0xff.

8.1696.2 Field Documentation

8.1696.2.1 uint8_t wds_PCSCFFQDNAddressList::numInstances

8.1696.2.2 struct wds_PCSCFFQDNAddress wds_PCSCFFQDNAddressList::pcsfFQDNAddress[10]

8.1697 wds_PCSCFIPv4ServerAddressList Struct Reference

Data Fields

- uint8_t numInstances
- uint32_t pscsfIPv4Addr [64]

8.1697.1 Detailed Description

This structure contains the PCSCFIPv4ServerAddressList Information

Parameters

numInstances	• number of address following
pscsfIPv4Addr	• P-CSCF IPv4 server addresses(Max 16 address, 4 bytes each)

Note

Data invalid when numInstances equal 0xff and pscsfIPv4Addr equal to 0xffffffff.

8.1697.2 Field Documentation

8.1697.2.1 uint8_t wds_PCSCFIPv4ServerAddressList::numInstances

8.1697.2.2 uint32_t wds_PCSCFIPv4ServerAddressList::pscsfIPv4Addr[64]

8.1698 wds_ProfileIdentifier Struct Reference

Data Fields

- uint8_t profileType
- uint8_t profileIndex

8.1698.1 Detailed Description

This structure contains the Profile Identifier Information

Parameters

profileType	• Identifies the type of profile 0x00 = 3GPP
profileIndex	• Index of profile whose settings were loaded prior to session parameter negotiation for the current call. If this TLV is not present, data call parameters are based on device default settings for each parameter

Note

Data invalid when all parameters are equal to 0xff.

8.1698.2 Field Documentation

8.1698.2.1 uint8_t wds_ProfileIdentifier::profileIndex

8.1698.2.2 uint8_t wds_ProfileIdentifier::profileType

8.1699 wds_profileInfo Union Reference

Data Fields

- LibPackprofile_3GPP SlqsProfile3GPP
- LibPackprofile_3GPP2 SlqsProfile3GPP2

8.1699.1 Detailed Description

This union consist of profile_3GPP and profile_3GPP2 out of which one will be used to create profile.

Parameters

SlqsProfile3GPP	3GPP profile See LibPackprofile_3GPP
SlqsProfile3GP-P2	3GPP2 profile See LibPackprofile_3GPP2

8.1699.2 Field Documentation

8.1699.2.1 LibPackprofile_3GPP wds_profileInfo::SlqsProfile3GPP

8.1699.2.2 LibPackprofile_3GPP2 wds_profileInfo::SlqsProfile3GPP2

8.1700 wds_RXBytesOKTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t RxByteOKCnt

8.1700.1 Detailed Description

This structure stores information about Rx Bytes OK TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
RxByteOKCnt	-Number of bytes received without error

8.1700.2 Field Documentation

8.1700.2.1 uint64_t wds_RXBytesOKTlv::RxByteOKCnt

8.1700.2.2 uint8_t wds_RXBytesOKTlv::TlvPresent

8.1701 wds_transferStatInd Struct Reference

Data Fields

- uint8_t StatsPeriod
- uint32_t StatsMask

8.1701.1 Detailed Description

This structure contains the transfer statistic indication information

Parameters

StatsPeriod	Field Period between transfer statistic reports. • 0 - Do not report. • 1 - Other - Period between reports (in seconds).
StatsMask	requested statistic bit mask. • 0x00000040 - Tx bytes OK • 0x00000080 - Rx bytes OK

8.1701.2 Field Documentation

8.1701.2.1 uint32_t wds_transferStatInd::StatsMask

8.1701.2.2 uint8_t wds_transferStatInd::StatsPeriod

8.1702 wds_TrStatInd Struct Reference

Data Fields

- uint8_t statsPeriod
- uint32_t statsMask

8.1702.1 Detailed Description

This structure contains the information about the Transfer Statistics Indicator parameters.

Parameters

statsPeriod	• Period between transfer statistics reports. – 0 - Do not report – Other - Period between reports (seconds)

statsMask	• Requested statistic bit mask. – 0x00000001 - Tx packets OK – 0x00000002 - Rx packets OK – 0x00000004 - Tx packet errors – 0x00000008 - Rx packet errors – 0x00000010 - Tx overflows – 0x00000020 - Rx overflows – 0x00000040 - Tx bytes OK – 0x00000080 - Rx bytes OK • Each bit set causes the corresponding optional information to be sent in SLQSWdsEventReport-CallBack. • All unlisted bits are reserved for future use and must be set to zero.

8.1702.2 Field Documentation

8.1702.2.1 uint32_t wds_TrStatInd::statsMask

8.1702.2.2 uint8_t wds_TrStatInd::statsPeriod

8.1703 wds_TXBytesOKTlv Struct Reference

Data Fields

- uint8_t TlvPresent
- uint64_t TxByteOKCnt

8.1703.1 Detailed Description

This structure stores information about Tx Bytes OK TLV.

Parameters

TlvPresent	• value is 1 if this TLV is present in indication, otherwise 0
TxByteOKCnt	• Number of bytes transmitted without error

8.1703.2 Field Documentation

8.1703.2.1 uint8_t wds_TXBytesOKTlv::TlvPresent

8.1703.2.2 uint64_t wds_TXBytesOKTlv::TxByteOKCnt

8.1704 wds_UMTSMinQoS Struct Reference

Data Fields

- uint8_t trafficClass
- uint32_t maxUplinkBitrate
- uint32_t maxDownlinkBitrate
- uint32_t grntUplinkBitrate
- uint32_t grntDownlinkBitrate
- uint8_t qosDeliveryOrder
- uint32_t maxSDUSize
- uint8_t sduErrorRatio
- uint8_t resBerRatio
- uint8_t deliveryErrSDU
- uint32_t transferDelay
- uint32_t trafficPriority

8.1704.1 Detailed Description

This structure contains the UMTS Quality Of Service Information

Parameters

trafficClass	• 0x00 - Subscribed • 0x01 - Conversational • 0x02 - Streaming • 0x03 - Interactive • 0x04 - Background
maxUplinkBitrate	• Maximum uplink bit rate in bits/sec
maxDownlink-Bitrate	• Maximum downlink bit rate in bits/sec
grntUplinkBitrate	• Guaranteed uplink bit rate in bits/sec
grntDownlink-Bitrate	• Guaranteed downlink bit rate in bits/sec
qosDelivery-Order	- Qos delivery order • 0x00 - Subscribe • 0x01 - Delivery order on • 0x02 - Delivery order off
maxSDUSize	• Maximum SDU size

sduErrorRatio	- SDU error ratio • Target value for fraction of SDUs lost or detected as erroneous. • 0x00 - Subscribe • 0x01 - 1∗10^(-2) • 0x02 - 7∗10^(-3) • 0x03 - 1∗10^(-3) • 0x04 - 1∗10^(-4) • 0x05 - 1∗10^(-5) • 0x06 - 1∗10^(-6) • 0x07 - 1∗10^(-1)
resBerRatio	- Residual bit error ratio • Target value for undetected bit error ratio in in the delivered SDUs. • 0x00 - Subscribe • 0x01 - 5∗10^(-2) • 0x02 - 1∗10^(-2) • 0x03 - 5∗10^(-3) • 0x04 - 4∗10^(-3) • 0x05 - 1∗10^(-3) • 0x06 - 1∗10^(-4) • 0x07 - 1∗10^(-5) • 0x08 - 1∗10^(-6) • 0x09 - 1∗10^(-8)
deliveryErrSDU	- delivery of erroneous SDUs • Indicates whether SDUs detected as erroneous shall be delivered or not. • 0x00 - Subscribe • 0x01 - 5∗10^(-2) • 0x02 - 1∗10^(-2) • 0x03 - 5∗10^(-3) • 0x04 - 4∗10^(-3) • 0x05 - 1∗10^(-3) • 0x06 - 1∗10^(-4) • 0x07 - 1∗10^(-5) • 0x08 - 1∗10^(-6) • 0x09 - 1∗10^(-8)
transferDelay	- Transfer delay (ms) • Indicates the targeted time between a request to transfer an SDU at one SAP to its delivery at the other SAP in milliseconds.
trafficPriority	- Transfer handling priority • Specifies the relative importance for handling of SDUs that belong to the UMTS bearer, compared to the SDUs of other bearers.

8.1704.2 Field Documentation

8.1704.2.1 uint8_t wds_UMTSMinQoS::deliveryErrSDU

8.1704.2.2 uint32_t wds_UMTSMinQoS::grntDownlinkBitrate

8.1704.2.3 uint32_t wds_UMTSMinQoS::grntUplinkBitrate

8.1704.2.4 uint32_t wds_UMTSMinQoS::maxDownlinkBitrate

8.1704.2.5 uint32_t wds_UMTSMinQoS::maxSDUSize

8.1704.2.6 uint32_t wds_UMTSMinQoS::maxUplinkBitrate

8.1704.2.7 uint8_t wds_UMTSMinQoS::qosDeliveryOrder

8.1704.2.8 uint8_t wds_UMTSMinQoS::resBerRatio

8.1704.2.9 uint8_t wds_UMTSMinQoS::sduErrorRatio

8.1704.2.10 uint8_t wds_UMTSMinQoS::trafficClass

8.1704.2.11 uint32_t wds_UMTSMinQoS::trafficPriority

8.1704.2.12 uint32_t wds_UMTSMinQoS::transferDelay

8.1705 WdsByteTotals Struct Reference

Data Fields

- ULONG * pV4sessionId
- ULONG * pV6sessionId
- struct WdsByteTotalsElmnts ByteTotalsElmntsV4
- struct WdsByteTotalsElmnts ByteTotalsElmntsV6

8.1705.1 Detailed Description

WDS ByteTotals request data structure

Parameters

pV4sessionId	• The v4 session ID for which the byte totals are to be retrieved • provide a NULL pointer if not applicable
pV6sessionId	• The v6 session ID for which the byte totals are to be retrieved • provide a NULL pointer if not applicable
ByteTotals-ElmntsV4	• data structure to be populated with the byte totals for V4 session
ByteTotals-ElmntsV6	• data structure to be populated with the byte totals for V6 session

Note

At least one of pV4sessionId and pV6sessionId must point to a valid session ID.

8.1705.2 Field Documentation

8.1705.2.1 struct WdsByteTotalsElmnts WdsByteTotals::ByteTotalsElmntsV4

8.1705.2.2 struct WdsByteTotalsElmnts WdsByteTotals::ByteTotalsElmntsV6

8.1705.2.3 ULONG* WdsByteTotals::pV4sessionId

8.1705.2.4 ULONG* WdsByteTotals::pV6sessionId

8.1706 WdsByteTotalsElmnts Struct Reference

Data Fields

- ULONGLONG * pTXTotalBytes
- ULONGLONG * pRXTotalBytes

8.1706.1 Detailed Description

WDS Bytes Totals request data structure for individual session

Parameters

pTXTotalBytes	• No of transmitted bytes without error.
pRXTotalBytes	• No of received bytes without error.

8.1706.2 Field Documentation

8.1706.2.1 ULONGLONG* WdsByteTotalsElmnts::pRXTotalBytes

8.1706.2.2 ULONGLONG* WdsByteTotalsElmnts::pTXTotalBytes

8.1707 WdsClientLeaseChange Struct Reference

Data Fields

- BYTE * pEnableNotification

8.1707.1 Detailed Description

WDS SWI DHCPv4 Client Lease Change Structure

Parameters

pEnable-Notification	[IN] • Enable Notification or not

8.1707.2 Field Documentation

8.1707.2.1 BYTE* WdsClientLeaseChange::pEnableNotification

8.1708 WdsConnectionRate Struct Reference

Data Fields

- ULONG * pV4sessionId
- ULONG * pV6sessionId
- struct WdsConnectionRateElmnts ConnRateElmntsV4
- struct WdsConnectionRateElmnts ConnRateElmntsV6

8.1708.1 Detailed Description

WDS ConnectionRate request data structure

Parameters

pV4sessionId	• The v4 session ID for which the connection rate are to be retrieved • provide a NULL pointer if not applicable
pV6sessionId	• The v6 session ID for which the connection rate are to be retrieved • provide a NULL pointer if not applicable
ConnRate-ElmntsV4	• data structure to be populated with the connection rate for V4 session
ConnRate-ElmntsV6	• data structure to be populated with the connection rate for V6 session

Note

At least one of pV4sessionId and pV6sessionId must point to a valid session ID.

8.1708.2 Field Documentation

8.1708.2.1 struct WdsConnectionRateElmnts WdsConnectionRate::ConnRateElmntsV4

8.1708.2.2 struct WdsConnectionRateElmnts WdsConnectionRate::ConnRateElmntsV6

8.1708.2.3 ULONG* WdsConnectionRate::pV4sessionId

8.1708.2.4 ULONG* WdsConnectionRate::pV6sessionId

8.1709 WdsConnectionRateElmnts Struct Reference

Data Fields

- ULONG * pCurrentChannelTXRate
- ULONG * pCurrentChannelRXRate
- ULONG * pMaxChannelTXRate
- ULONG * pMaxChannelRXRate

8.1709.1 Detailed Description

WDS Connection rates request data structure for individual session

Parameters

pCurrentChannelTXRate[OUT]	• Instantaneous channel Tx rate in bits per second.
pCurrentChannelRXRate[OUT]	• Instantaneous channel Rx rate in bits per second.
pMaxChannelTXRate[OUT]	• Maximum Tx rate that can be assigned to the device by the • serving system in bits per second
pMaxChannelRXRate[OUT]	• Maximum Rx rate that can be assigned to the device by the • serving system in bits per second

8.1709.2 Field Documentation

8.1709.2.1 ULONG* WdsConnectionRateElmnts::pCurrentChannelRXRate

8.1709.2.2 ULONG* WdsConnectionRateElmnts::pCurrentChannelTXRate

8.1709.2.3 ULONG* WdsConnectionRateElmnts::pMaxChannelRXRate

8.1709.2.4 ULONG* WdsConnectionRateElmnts::pMaxChannelTXRate

8.1710 WdsDHCPv4ClientLeaseInd Struct Reference

Data Fields

- WdsDHCPv4ProfileId * pProfileId
- BYTE * pLeaseState
- ULONG * pIPv4Addr
- DHCPOptionList * pOptList

8.1710.1 Detailed Description

This structure contains DHCPv4 client lease status

Parameters

pProfileId	• Profile Type and Id
pLeaseState	• Values – 0 - active, newly acquired – 1 - active, renewed – 2 - active, renewing – 3 - active, rebinding – 4 - inactive, expired – 5 - inactive, renew refused – 6 - inactive, rebind refused – 7 - inactive, other
pIPv4Addr	• Values – IPv4 Address
pOptList	• Option list

8.1710.2 Field Documentation

8.1710.2.1 ULONG* WdsDHCPv4ClientLeaseInd::pIPv4Addr

8.1710.2.2 BYTE* WdsDHCPv4ClientLeaseInd::pLeaseState

8.1710.2.3 DHCPOptionList* WdsDHCPv4ClientLeaseInd::pOptList

8.1710.2.4 WdsDHCPv4ProfileId* WdsDHCPv4ClientLeaseInd::pProfileId

8.1711 WdsDHCPv4Config Struct Reference

Data Fields

- WdsDHCPv4ProfileId * pProfileId
- WdsDHCPv4HWConfig * pHwConfig
- WdsDHCPv4OptionList * pRequestOptionList

8.1711.1 Detailed Description

WDS SWI DHCPv4 Config Structure

Parameters

pProfileId	[IN] • pointer to Profile Id structure
pHWConfig	[IN/OUT] • pointer to HW Config structure

pRequestOption-List	[IN/OUT] • pointer to Option List structure to be sent in DHCP request

8.1711.2 Field Documentation

8.1711.2.1 WdsDHCPv4HWConfig* WdsDHCPv4Config::pHwConfig

8.1711.2.2 WdsDHCPv4ProfileId* WdsDHCPv4Config::pProfileId

8.1711.2.3 WdsDHCPv4OptionList* WdsDHCPv4Config::pRequestOptionList

8.1712 WdsDHCPv4HWConfig Struct Reference

Data Fields

- BYTE hwType
- BYTE chaddrLen
- BYTE chaddr [16]

8.1712.1 Detailed Description

WDS SWI DHCPv4 HW Config Structure.

Parameters

hwType	• HW Type 1 - Ethernet 20 - Serial
chaddrlen	• chaddrlen
chaddr	• chaddr. Max size 16 bytes

8.1712.2 Field Documentation

8.1712.2.1 BYTE WdsDHCPv4HWConfig::chaddr[16]

8.1712.2.2 BYTE WdsDHCPv4HWConfig::chaddrLen

8.1712.2.3 BYTE WdsDHCPv4HWConfig::hwType

8.1713 wdsDhcpv4HwConfig Struct Reference

Data Fields

- uint8_t hwType
- uint8_t chaddrLen
- uint8_t chaddr [16]

8.1713.1 Detailed Description

Structure contain DHCP V4 Hardware Configuration.

Parameters

hwType	DHCP HW Type, examples: • 0 - Ethernet • 20 - Serial
chaddrLen	Length of chaddr field, examples: • 6 for Ethernet MAC address
chaddr	Client hardware address

8.1713.2 Field Documentation

8.1713.2.1 uint8_t wdsDhcpv4HwConfig::chaddr[16]

8.1713.2.2 uint8_t wdsDhcpv4HwConfig::chaddrLen

8.1713.2.3 uint8_t wdsDhcpv4HwConfig::hwType

8.1714 WdsDHCPv4Option Struct Reference

Data Fields

- BYTE optCode
- BYTE optValLen
- BYTE optVal [255]

8.1714.1 Detailed Description

WDS SWI DHCPv4 Option Structure

Parameters

optCode	• Option code – 0 - 255
optValLen	• Option value length – 0 - 255
optVal	• Option value

8.1714.2 Field Documentation

8.1714.2.1 BYTE WdsDHCPv4Option::optCode

8.1714.2.2 BYTE WdsDHCPv4Option::optVal[255]

8.1714.2.3 BYTE WdsDHCPv4Option::optValLen

8.1715 wdsDhcpv4Option Struct Reference

Data Fields

- uint8_t optCode
- uint8_t optValLen
- uint8_t optVal [255]

8.1715.1 Detailed Description

This structure contains DHCP V4 Option information.

Parameters

optCode	Option code • 0 - 255
optValLen	Option value length • 0 - 255
optVal	Option Value

8.1715.2 Field Documentation

8.1715.2.1 uint8_t wdsDhcpv4Option::optCode

8.1715.2.2 uint8_t wdsDhcpv4Option::optVal[255]

8.1715.2.3 uint8_t wdsDhcpv4Option::optValLen

8.1716 WdsDHCPv4OptionList Struct Reference

Data Fields

- BYTE numOpt
- WdsDHCPv4Option * pOptList

8.1716.1 Detailed Description

WDS SWI DHCPv4 Option List Structure

Parameters

numOpt	• number of options – 0 - 255
pOptList	• pointer to list of DHCP Options

8.1716.2 Field Documentation

8.1716.2.1 BYTE WdsDHCPv4OptionList::numOpt

8.1716.2.2 WdsDHCPv4Option* WdsDHCPv4OptionList::pOptList

8.1717 wdsDhcpv4OptionList Struct Reference

Data Fields

- uint8_t numOpt
- wdsDhcpv4Option * pOptList

8.1717.1 Detailed Description

Structure contain DHCP V4 Option List

Parameters

numOpt	number of options • 0 - 255
pOptList	pointer to list of DHCP Options • See wdsDhcpv4Option

8.1717.2 Field Documentation

8.1717.2.1 uint8_t wdsDhcpv4OptionList::numOpt

8.1717.2.2 wdsDhcpv4Option* wdsDhcpv4OptionList::pOptList

8.1718 wdsDhcpv4ProfileId Struct Reference

Data Fields

- uint8_t profileType
- uint8_t profileId

8.1718.1 Detailed Description

This structure contains DHCP v4 ProfieIID Information.

Parameters

profileType	profile type • 0 - 3GPP
profileId	profile index • index identifiying the profile 1-24 valid for 3GPP profile type (EM74xx and onwards)

8.1718.2 Field Documentation

8.1718.2.1 uint8_t wdsDhcpv4ProfileId::profileId

8.1718.2.2 uint8_t wdsDhcpv4ProfileId::profileType

8.1719 WdsDHCPv4ProfileId Struct Reference

Data Fields

- BYTE profileType
- BYTE profileId

8.1719.1 Detailed Description

WDS SWI DHCPv4 Profile Identifier Structure

Parameters

profileType	• 0 for 3GPP
profileId	• 1 to 24 for 3GPP profile

8.1719.2 Field Documentation

8.1719.2.1 BYTE WdsDHCPv4ProfileId::profileId

8.1719.2.2 BYTE WdsDHCPv4ProfileId::profileType

8.1720 WDSGetLoopbackData Struct Reference

Data Fields

- BYTE ByteLoopbackMode
- BYTE ByteLoopbackMultiplier

8.1720.1 Detailed Description

This API to Queries Enable/disable Data Loopback Mode and set the value of loopback multiplier.

Parameters

pReq	[IN] • See WDSSetLoopbackData for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

WDS SWI Get Loopback Structure of Packet Data Connection Information.

Parameters

ByteLoopback-Mode	• Loopback Mode. – 0 - Disable – 1 - Enable
ByteLoopback-Multiplier	• Loopback multiplier. Number of downlink bytes to send for each uplink byte.

8.1720.2 Field Documentation

8.1720.2.1 BYTE WDSGetLoopbackData::ByteLoopbackMode

8.1720.2.2 BYTE WDSGetLoopbackData::ByteLoopbackMultiplier

8.1721 WdsIpAddressInfoReq Struct Reference

Data Fields

- ULONG * pv4sessionId
- ULONG * pv6sessionId
- QmiWdsIpAddressInfo ip

8.1721.1 Detailed Description

Parameters

pv4sessionId[OUT]	• IPv4 session id
pv6sessionId[OUT]	• IPv6 session id
ip[OUT]	• IP address information see QmiWdsIpAddressInfo for more details

8.1721.2 Field Documentation

8.1721.2.1 QmiWdsIpAddressInfo WdsIpAddressInfoReq::ip

8.1721.2.2 ULONG* WdsIpAddressInfoReq::pv4sessionId

8.1721.2.3 ULONG* WdsIpAddressInfoReq::pv6sessionId

8.1722 WdsPktStatisticsElmnts Struct Reference

Data Fields

- ULONG * pTXPacketSuccesses
- ULONG * pRXPacketSuccesses
- ULONG * pTXPacketErrors
- ULONG * pRXPacketErrors
- ULONG * pTXPacketOverflows
- ULONG * pRXPacketOverflows
- ULONGLONG * pTXOkBytesCount
- ULONGLONG * pRXOkBytesCount
- ULONGLONG * pTXOKBytesLastCall
- ULONGLONG * pRXOKBytesLastCall
- ULONG * pTXDroppedCount
- ULONG * pRXDroppedCount

8.1722.1 Detailed Description

WDS Pkt Statistics request data structure for individual session

Parameters

pTXPacket-Successes	• Number of transmitted Packets without error.
pRXPacket-Successes	• Number of received Packets without error.
pTXPacketErrors	• Number of outgoing packets with framing errors.
pRXPacket-Errors	• Number of incoming packets with framing errors.
pTXPacket-Overflows	• Number of packets dropped because Tx buffer overflowed (out of memory).
pRXPacket-Overflows	• Number of packets dropped because Rx buffer overflowed (out of memory).
pTXOkBytes-Count	• Number of bytes transmitted without error.
pRXOkBytes-Count	• Number of bytes received without error.
pTXOKBytes-LastCall	• Number of bytes transmitted without error during the last data call (0 if no call was made earlier). Returned only if not in a call, and when the previous call was made using RmNet (for any devices that support

pRXOKBytes-LastCall	• Number of bytes received without error during the last data call (0 if no call was made earlier). Returned only if not in a call, and when the previous call was made using RmNet (for any devices that support
pTXDropped-Count	• Number of outgoing packets dropped.
pRXDropped-Count	• Number of incoming packets dropped.

8.1722.2 Field Documentation

8.1722.2.1 ULONG* WdsPktStatisticsElmnts::pRXDroppedCount

8.1722.2.2 ULONGLONG* WdsPktStatisticsElmnts::pRXOkBytesCount

8.1722.2.3 ULONGLONG* WdsPktStatisticsElmnts::pRXOKBytesLastCall

8.1722.2.4 ULONG* WdsPktStatisticsElmnts::pRXPacketErrors

8.1722.2.5 ULONG* WdsPktStatisticsElmnts::pRXPacketOverflows

8.1722.2.6 ULONG* WdsPktStatisticsElmnts::pRXPacketSuccesses

8.1722.2.7 ULONG* WdsPktStatisticsElmnts::pTXDroppedCount

8.1722.2.8 ULONGLONG* WdsPktStatisticsElmnts::pTXOkBytesCount

8.1722.2.9 ULONGLONG* WdsPktStatisticsElmnts::pTXOKBytesLastCall

8.1722.2.10 ULONG* WdsPktStatisticsElmnts::pTXPacketErrors

8.1722.2.11 ULONG* WdsPktStatisticsElmnts::pTXPacketOverflows

8.1722.2.12 ULONG* WdsPktStatisticsElmnts::pTXPacketSuccesses

8.1723 WdsPktStatisticsReq Struct Reference

Data Fields

- ULONG * pStatMask

8.1723.1 Detailed Description

WDS PktStatistics request data structure

Parameters

pStatMask	• Packet Statistics Mask 0x00000001 - Tx packets OK 0x00000002 - Rx packets OK 0x00000004 - Tx packet errors 0x00000008 - Rx packet errors 0x00000010 - Tx overflows 0x00000020 - Rx overflows 0x00000040 - Tx bytes OK 0x00000080 - Rx bytes OK

8.1723.2 Field Documentation

8.1723.2.1 ULONG* WdsPktStatisticsReq::pStatMask

8.1724 WdsPktStatisticsResp Struct Reference

Data Fields

- ULONG * pV4sessionId
- ULONG * pV6sessionId
- struct WdsPktStatisticsElmnts PktStatElmntsV4
- struct WdsPktStatisticsElmnts PktStatElmntsV6

8.1724.1 Detailed Description

WDS PktStatistics response data structure

Parameters

pV4sessionId	• The v4 session ID for which the byte totals are to be retrieved • provide a NULL pointer if not applicable
pV6sessionId	• The v6 session ID for which the byte totals are to be retrieved • provide a NULL pointer if not applicable
PktStatElmntsV4	• data structure to be populated with the Pkt Statistics for V4 session
PktStatElmntsV6	• data structure to be populated with the Pkt Statistics for V6 session

Note

At least one of pV4sessionId and pV6sessionId must point to a valid session ID.

8.1724.2 Field Documentation

8.1724.2.1 struct WdsPktStatisticsElmnts WdsPktStatisticsResp::PktStatElmntsV4

8.1724.2.2 struct WdsPktStatisticsElmnts WdsPktStatisticsResp::PktStatElmntsV6

8.1724.2.3 ULONG* WdsPktStatisticsResp::pV4sessionId

8.1724.2.4 ULONG* WdsPktStatisticsResp::pV6sessionId

8.1725 WdsProfileParam Union Reference

Data Fields

- struct Profile3GPP SlqsProfile3GPP
- struct Profile3GPP2 SlqsProfile3GPP2

8.1725.1 Detailed Description

This union WdsProfileParam consist of Profile3GPP and Profile3GPP2 out of which one will be used to create profile.

Parameters

SlqsProfile3GPP	• 3GPP profile
SlqsProfile3GPP2	• 3GPP2 profile

8.1725.2 Field Documentation

8.1725.2.1 struct Profile3GPP WdsProfileParam::SlqsProfile3GPP

8.1725.2.2 struct Profile3GPP2 WdsProfileParam::SlqsProfile3GPP2

8.1726 WdsRunTimeSettings Struct Reference

Data Fields

- ULONG * v4sessionId
- ULONG * v6sessionId
- struct qmiWdsRunTimeSettings rts

8.1726.1 Detailed Description

WDS runtime settings request data structure

Parameters

v4sessionId	• The v4 session ID for which the runtime settings are to be retrieved • provide a NULL pointer if not applicable
v6sessionId	• The v6 session ID for which the runtime settings are to be retrieved • provide a NULL pointer if not applicable
qmiWdsRunTimeSettings	• data structure to be populated with the runtime settings

Note

At least one of v4sessionId and v6sessionId must point to a valid session ID.

8.1726.2 Field Documentation

8.1726.2.1 struct qmiWdsRunTimeSettings WdsRunTimeSettings::rts

8.1726.2.2 ULONG* WdsRunTimeSettings::v4sessionId

8.1726.2.3 ULONG* WdsRunTimeSettings::v6sessionId

8.1727 wdsSetEventReportReq Struct Reference

Data Fields

- BYTE * pCurrChannelRateInd
- TrStatInd * pTransferStatInd
- BYTE * pDataBearerTechInd
- BYTE * pDormancyStatusInd
- BYTE * pMIPStatusInd
- BYTE * pCurrDataBearerTechInd
- BYTE * pDataCallStatusChangeInd
- BYTE * pCurrPrefDataSysInd
- BYTE * pEVDOPageMonPerChangeInd
- BYTE * pDataSystemStatusChangeInd

8.1727.1 Detailed Description

This structure contains the information about the Set Event Report Request parameters.

Parameters

pCurrChannel-RateInd	(optional) • Current Channel Rate Indicator. – 0 - Do not report – 1 - Report channel rate when it changes
pTransferStatInd	(optional) • See TrStatInd for more information.
pDataBearer-TechInd	(optional) • Data Bearer Technology Indicator. – 0 - Do not report – 1 - Report radio interface used for data transfer when it changes
pDormancy-StatusInd	(optional) • Dormancy Status indicator. – 0 - Do not report – 1 - Report traffic channel state of interface used for data connection

pMIPStatusInd	(optional) • MIP Status Indicator. – 0 - Do not report – 1 - Report MIP status
pCurrDataBearerTechInd	(optional) • Current Data Bearer Technology Indicator. – 0 - Do not report – 1 - Report current data bearer technology when it changes
pDataCallStatusChangeInd	(optional) • Data Call Status Change Indicator. – 0 - Do not report – 1 - Report data call status change when it changes
pCurrPrefDataSysInd	(optional) • Current Preferred Data System Indicator. – 0 - Do not report – 1 - Report preferred data system when it changes
pEVDOPageMonPerChangeInd	(optional) • EV-DO Page Monitor Period Change Indicator. – 0 - Do not report – 1 - Report EV-DO page monitor period change event
pDataSystemStatusChangeInd	(optional) • Data System Status Change Indicator. – 0 - Do not report – 1 - Report data system status change event

Note

At least one parameter should be present.

8.1727.2 Field Documentation

8.1727.2.1 BYTE* wdsSetEventReportReq::pCurrChannelRateInd

8.1727.2.2 BYTE* wdsSetEventReportReq::pCurrDataBearerTechInd

8.1727.2.3 BYTE* wdsSetEventReportReq::pCurrPrefDataSysInd

8.1727.2.4 BYTE* wdsSetEventReportReq::pDataBearerTechInd

8.1727.2.5 BYTE* wdsSetEventReportReq::pDataCallStatusChangeInd

8.1727.2.6 BYTE* wdsSetEventReportReq::pDataSystemStatusChangeInd

8.1727.2.7 BYTE* wdsSetEventReportReq::pDormancyStatusInd

8.1727.2.8 BYTE* wdsSetEventReportReq::pEVDOPageMonPerChangeInd

8.1727.2.9 BYTE* wdsSetEventReportReq::pMIPStatusInd

8.1727.2.10 TrStatInd* wdsSetEventReportReq::pTransferStatInd

8.1728 WDSSetLoopbackData Struct Reference

Data Fields

- BYTE * pLoopbackMode
- BYTE * pLoopbackMultiplier

8.1728.1 Detailed Description

WDS SWI Set Loopback Structure of Set Loopback Information.

Parameters

pLoopbackMode	• Loopback Mode. – 0 - Disable – 1 - Enable
pLoopback-Multiplier	• Loopback multiplier. Number of downlink bytes to send for each uplink byte.

8.1728.2 Field Documentation

8.1728.2.1 BYTE* WDSSetLoopbackData::pLoopbackMode

8.1728.2.2 BYTE* WDSSetLoopbackData::pLoopbackMultiplier

8.1729 WDSSWICurrentChannelRates Struct Reference

Data Fields

- unsigned long current_channel_tx_rate
- unsigned long current_channel_rx_rate
- unsigned long max_channel_tx_rate
- unsigned long max_channel_rx_rate

8.1729.1 Detailed Description

WDS SWI Current Channel Rates Structure of Packet Data Connection Information.

Parameters

current_channel-_tx_rate	• Current Channel Tx Rate.
current_channel-_rx_rate	• Current Channel Rx Rate.

max_channel_tx_rate	• Max Channel Tx Rate.
max_channel_rx_rate	• Max Channel Rx Rate.

8.1729.2 Field Documentation

8.1729.2.1 unsigned long WDSSWICurrentChannelRates::current_channel_rx_rate

8.1729.2.2 unsigned long WDSSWICurrentChannelRates::current_channel_tx_rate

8.1729.2.3 unsigned long WDSSWICurrentChannelRates::max_channel_rx_rate

8.1729.2.4 unsigned long WDSSWICurrentChannelRates::max_channel_tx_rate

Chapter 9

File Documentation

9.1 apdoxypages.c File Reference

Contains the module declaration for the Doxygen output. Also contains the content of the main page and related pages.

Namespaces

- Tables

9.1.1 Detailed Description

Contains the module declaration for the Doxygen output. Also contains the content of the main page and related pages.

9.2 common.h File Reference

Data Structures

- struct pack_qmi_t
- struct unpack_qmi_t
- struct unpack_result_t

Macros

- #define SDU_HDR_LEN (3)
- #define MINREQBKLEN (2048)
- #define MSGID_AND_LEN (4)
- #define MSGID_DONT_CARE (0xffff)
- #define UNUSEDPARAM(x) (void)x
- #define DEAULT_LOC_TIMEOUT_IN_SEC 2
- #define SDK_VALIDATE_INPUT_PACK_PARAM(pCtx, pBuf, pLen)
- #define SDK_VALIDATE_INPUT_PACK_PARAM_AND_FILL_XID(pCtx, pBuf, pLen)
- #define SDK_VALIDATE_INPUT_UNPACK_PARAM(pResp, respLen, pOutput)
- #define SWI_INIT_UNPACK_RESULT_VALUE {0, SWI_UINT256_INT_VALUE}

Typedefs

- typedef void(∗ logger)(uint8_t lvl, const char ∗buff)

Enumerations

- enum eLOG_LEVEL {
  eLOG_INFO,
  eLOG_DEBUG,
  eLOG_WARN,
  eLOG_FATAL }
- enum eTimeout {
  eTIMEOUT_2_S = 2000,
  eTIMEOUT_5_S = 5000,
  eTIMEOUT_8_S = 8000,
  eTIMEOUT_10_S = 10000,
  eTIMEOUT_20_S = 20000,
  eTIMEOUT_30_S = 30000,
  eTIMEOUT_60_S = 60000,
  eTIMEOUT_300_S = 300000,
  eTIMEOUT_DEFAULT = eTIMEOUT_8_S }
- enum eQMI_SVC {
  eCTL,
  eWDS,
  eDMS,
  eNAS =3,
  eQOS,
  eSMS =5,
  ePDS =0x06,
  eVOICE =0x09,
  eCAT =0x0A,
  eUIM =0x0B,
  eLOC =0x10,
  eSAR =0x11,
  eIMS =0x12,
  eTMD =0x18,
  eIMSA =0x21,
  eRMS =225,
  eSWIOMA =240,
  eAUDIO =241,
  eSWIM2MCMD =243,
  eSWIM2MCMD_AVC2 =0xfd,
  eSWIOMAEXT =244,
  eSWIAUDIO = 245,
  eSWILOC =246,
  eSWIDMS =254 }
- enum msgtype {
  eREQ =0,
  eRSP =2,
  eIND =4 }

Functions

- uint16_t helper_get_xid (uint8_t ∗qmi_resp)
- uint16_t helper_get_error_code (uint8_t ∗qmi_resp)
- char ∗ helper_get_error_reason (uint16_t retVal)

- const char * helper_get_resp_ctx (uint8_t svc, uint8_t *pbuf, uint32_t len, unpack_qmi_t *pCtx)
- const char * helper_get_req_str (uint8_t svc, uint8_t *req, uint32_t len)
- unsigned unpack_result_code_only (uint8_t *pMdmResp)
- int helper_set_log_func (logger *func)
- void liteqmi_log (uint8_t lvl, const char *fmt,...)
- int helper_set_log_lvl (uint8_t lvl)
- void fill_sdu_hdr (pack_qmi_t *pCtx, uint8_t *pReqBuf)
- void fill_pack_ctx (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, uint8_t svc, int timeout)
- char * get_version ()
- char * liteqmi_GetVersion ()
- void liteqmi_helper_decode7bitAsciiEncString (uint8_t *encoded_str, uint8_t encoded_len, uint8_t *decoded_str)
- int helper_isBootLoader_DebugEnabled (const char *szPath, const char *pQsn)

Variables

- logger * glog
- uint8_t gloglvl

9.2.1 Macro Definition Documentation

9.2.1.1 #define DEAULT_LOC_TIMEOUT_IN_SEC 2

9.2.1.2 #define MINREQBKLEN (2048)

9.2.1.3 #define MSGID_AND_LEN (4)

9.2.1.4 #define MSGID_DONT_CARE (0xffff)

9.2.1.5 #define SDK_VALIDATE_INPUT_PACK_PARAM(*pCtx, pBuf, pLen*)

Value:

```
if ((pCtx == NULL) || (pBuf == NULL) || (pLen == NULL) ) \
        {\
        liteqmi_log(eLOG_DEBUG,"[  pack] %s parameter NULL\n",__func__); \
        return eQCWWAN_ERR_INVALID_ARG; \
        }
```

9.2.1.6 #define SDK_VALIDATE_INPUT_PACK_PARAM_AND_FILL_XID(*pCtx, pBuf, pLen*)

Value:

```
if ((pCtx == NULL) || (pBuf == NULL) || (pLen == NULL) ) \
        {\
        liteqmi_log(eLOG_DEBUG,"[  pack] %s parameter NULL\n",__func__); \
        return eQCWWAN_ERR_INVALID_ARG; \
        } \
    if (pCtx->xid == 0) \
       return eQCWWAN_ERR_INVALID_XID; \
    pBuf[0] = eREQ; \
    pBuf[1] = pCtx->xid & 0xff; \
    pBuf[2] = pCtx->xid >> 8;
```

9.2.1.7 #define SDK_VALIDATE_INPUT_UNPACK_PARAM(*pResp, respLen, pOutput*)

Value:

```
if ((pResp == NULL) || (respLen == 0) || (pOutput == NULL) ) \
        {\
        liteqmi_log(eLOG_DEBUG,"[ unpack] %s parameter NULL or invalid\n",
      __func__); \
        return eQCWWAN_ERR_INVALID_ARG; \
        }
```

9.2.1.8 #define SDU_HDR_LEN (3)

9.2.1.9 #define SWI_INIT_UNPACK_RESULT_VALUE {0, SWI_UINT256_INT_VALUE}

9.2.1.10 #define UNUSEDPARAM(*x*) (void)x

9.2.2 Typedef Documentation

9.2.2.1 typedef void(∗ logger)(uint8_t lvl, const char ∗buff)

9.2.3 Enumeration Type Documentation

9.2.3.1 enum eLOG_LEVEL

log levels

Enumerator

eLOG_INFO

eLOG_DEBUG

eLOG_WARN

eLOG_FATAL

9.2.3.2 enum eQMI_SVC

qmi service

Enumerator

eCTL

eWDS

eDMS

eNAS

eQOS

eSMS

ePDS

eVOICE

eCAT

eUIM

eLOC

eSAR

eIMS

eTMD

eIMSA

eRMS

eSWIOMA

eAUDIO

eSWIM2MCMD

eSWIM2MCMD_AVC2

eSWIOMAEXT

eSWIAUDIO

eSWILOC

eSWIDMS

9.2.3.3 enum eTimeout

eTimeout

Enumerator

eTIMEOUT_2_S

eTIMEOUT_5_S

eTIMEOUT_8_S

eTIMEOUT_10_S

eTIMEOUT_20_S

eTIMEOUT_30_S

eTIMEOUT_60_S

eTIMEOUT_300_S

eTIMEOUT_DEFAULT

9.2.3.4 enum msgtype

qmi message type

Enumerator

eREQ

eRSP

eIND

9.2.4 Function Documentation

9.2.4.1 void fill_pack_ctx (pack_qmi_t * *pCtx,* uint8_t * *pReqBuf,* uint16_t * *pLen,* uint8_t *svc,* int *timeout*)

9.2.4.2 void fill_sdu_hdr (pack_qmi_t * *pCtx,* uint8_t * *pReqBuf*)

9.2.4.3 char* get_version ( )

Returns

version string

9.2.4.4 uint16_t helper_get_error_code (uint8_t * *qmi_resp*)

9.2.4.5 char* helper_get_error_reason (uint16_t *retVal*)

9.2.4.6 const char* helper_get_req_str (uint8_t *svc,* uint8_t * *req,* uint32_t *len*)

extract msgid string from modem req

Parameters

in	*svc*	qmi service
in	*req*	qmi request
in	*len*	request length

Returns

qmi message string

9.2.4.7 const char* helper_get_resp_ctx (uint8_t *svc,* uint8_t * *pbuf,* uint32_t *len,* **unpack_qmi_t** * *pCtx*)

extract msgid/xid/type from modem reply

Parameters

in	*svc*	qmi service
in	*pbuf*	qmi response/indication
in	*len*	response/indication length
out	*pCtx*	unpacked context

Returns

qmi message string

9.2.4.8 uint16_t helper_get_xid (uint8_t * *qmi_resp*)

9.2.4.9 int helper_isBootLoader_DebugEnabled (const char * *szPath,* const char * *pQsn*)

Parameters

in	*szPath*	the full path of the provided bootloader or firmware file
in	*pQsn*	the QSN of a specific module user wants to check, it is a 4 bytes hex value without the prefix 0X. It can be retrieved by AT command AT!ENTERCND="<password>", AT!SECBOOTCFG?, the first parameter of the response of AT!SECBOOTCFG?.

Returns

values listed below

- -1 bootloader is not debug enabled
- 0 unbale to retrieve the bootloader debug info
- 1 bootloader is debug enabled for the provided QSN
- 4 either szPath or pQsn is invalid (NULL)
- 18 invalid file

9.2.4.10 int helper_set_log_func (logger * *func*)

set log function

9.2.4.11 int helper_set_log_lvl (uint8_t *lvl*)

set log level

9.2.4.12 char* liteqmi_GetVersion ( )

Returns

version string

9.2.4.13 void liteqmi_helper_decode7bitAsciiEncString (uint8_t * *encoded_str*, uint8_t *encoded_len*, uint8_t * *decoded_str*)

decode 7bit encoded string

Parameters

in	*encoded_str*	7 bit encoded ASCII
in	*encoded_len*	encoded length
out	*decoded_str*	decoded ASCII string

9.2.4.14 void liteqmi_log (uint8_t *lvl*, const char * *fmt*, ...)

9.2.4.15 unsigned unpack_result_code_only (uint8_t * *pMdmResp*)

common handler for unpacking response with TLV type 0x02 only

9.2.5 Variable Documentation

9.2.5.1 logger* glog

9.2.5.2 uint8_t gloglvl

9.3 dms.h File Reference

Data Structures

- struct unpack_dms_GetModelID_t
- struct unpack_dms_GetIMSI_t
- struct unpack_dms_GetFirmwareInfo_t
- struct unpack_dms_GetPower_t
- struct unpack_dms_GetSerialNumbers_t
- struct unpack_dms_GetHardwareRevision_t
- struct unpack_dms_SLQSGetBandCapability_t
- struct unpack_dms_GetDeviceCapabilities_t
- struct unpack_dms_GetFirmwareRevisions_t
- struct unpack_dms_GetFirmwareRevision_t
- struct unpack_dms_GetDeviceSerialNumbers_t
- struct unpack_dms_GetPRLVersion_t

- struct unpack_dms_GetNetworkTime_t
- struct unpack_dms_GetVoiceNumber_t
- struct unpack_dms_GetDeviceHardwareRev_t
- struct unpack_dms_GetFSN_t
- struct unpack_dms_GetDeviceCap_t
- struct pack_dms_SetPower_t
- struct unpack_dms_SetPower_t
- struct unpack_dms_GetBandCapability_t
- struct unpack_dms_GetUSBComp_t
- struct pack_dms_SetUSBComp_t
- struct unpack_dms_SetUSBComp_t
- struct pack_dms_SetCustFeature_t
- struct unpack_dms_SetCustFeature_t
- struct unpack_dms_GetCustFeature_t
- struct unpack_dms_SetFirmwarePreference_t
- struct unpack_dms_GetCrashAction_t
- struct pack_dms_SetCrashAction_t
- struct unpack_dms_SetCrashAction_t
- struct unpack_dms_GetDeviceMfr_t
- struct pack_dms_SetEventReport_t
- struct unpack_dms_SetEventReport_t
- struct dms_OperatingModeTlv
- struct dms_ActivationStatusTlv
- struct unpack_dms_SetEventReport_ind_t
- struct pack_dms_UIMGetICCID_t
- struct unpack_dms_UIMGetICCID_t
- struct pack_dms_SetCustFeaturesV2_t
- struct unpack_dms_SetCustFeaturesV2_t
- struct pack_dms_GetCustFeaturesV2_t
- struct DMSgetCustomInput
- struct DMScustSettingInfo
- struct DMScustSettingList
- struct DMSgetCustomFeatureV2
- struct unpack_dms_GetCustFeaturesV2_t
- struct unpack_dms_GetActivationState_t
- struct image_info_t
- struct unpack_dms_SLQSSwiGetFirmwareCurr_t
- struct pack_dms_SLQSSwiSetDyingGaspCfg_t
- struct unpack_dms_SLQSSwiSetDyingGaspCfg_t
- struct unpack_dms_SLQSSwiClearDyingGaspStatistics_t
- struct packgetDyingGaspStatistics
- struct unpack_dms_SLQSSwiGetDyingGaspStatistics_t
- struct packgetDyingGaspCfg
- struct unpack_dms_SLQSSwiGetDyingGaspCfg_t
- struct unpack_dms_SLQSDmsSwiGetResetInfo_t
- struct unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t
- struct pack_dms_SLQSDmsSwiIndicationRegister_t
- struct unpack_dms_SLQSDmsSwiIndicationRegister_t
- struct unpack_dms_SLQSSwiGetFwUpdateStatus_t
- struct unpack_dms_GetManufacturer_t
- struct unpack_dms_GetOfflineReason_t
- struct pack_dms_SetActivationStatusCallback_t
- struct unpack_dms_SetActivationStatusCallback_t
- struct pack_dms_UIMSetPINProtection_t
- struct unpack_dms_UIMSetPINProtection_t

- struct pack_dms_UIMUnblockPIN_t
- struct pack_dms_UIMVerifyPIN_t
- struct pack_dms_UIMChangePIN_t
- struct pack_dms_UIMGetControlKeyStatus_t
- struct unpack_dms_UIMGetControlKeyStatus_t
- struct unpack_dms_UIMGetPINStatus_t
- struct pack_dms_UIMSetControlKeyProtection_t
- struct unpack_dms_UIMSetControlKeyProtection_t
- struct pack_dms_UIMUnblockControlKey_t
- struct unpack_dms_UIMUnblockControlKey_t
- struct pack_dms_ResetToFactoryDefaults_t
- struct unpack_dms_ResetToFactoryDefaults_t
- struct pack_dms_ActivateAutomatic_t
- struct eriDataparams
- struct unpack_dms_SLQSGetERIFile_t
- struct unpack_dms_SLQSUIMGetState_t
- struct pack_dms_SLQSSwiGetCrashInfo_t
- struct crashInformation
- struct crashInfoParams
- struct unpack_dms_SLQSSwiGetCrashInfo_t
- struct unpack_dms_SLQSSwiGetHostDevInfo_t
- struct pack_dms_SLQSSwiSetHostDevInfo_t
- struct unpack_dms_SLQSSwiSetHostDevInfo_t
- struct unpack_dms_SLQSSwiGetOSInfo_t
- struct pack_dms_SLQSSwiSetOSInfo_t
- struct unpack_dms_SLQSSwiSetOSInfo_t
- struct unpack_dms_SLQSSwiGetSerialNoExt_t
- struct unpack_dms_SLQSDmsSwiGetPCInfo_t
- struct dms_PSMEnableStateTlv
- struct dms_PSMDurationThresholdTlv
- struct dms_PSMDurationDueToOOSTlv
- struct dms_PSMRandomizationWindowTlv
- struct dms_PSMActiveTimerTlv
- struct dms_PSMPeriodicUpdateTimerTlv
- struct dms_PSMEarlyWakeupTimeTlv
- struct unpack_dms_SLQSGetPowerSaveModeConfig_t
- struct pack_dms_SLQSSetPowerSaveModeConfig_t
- struct unpack_dms_SLQSSetPowerSaveModeConfig_t
- struct pack_dms_SetIndicationRegister_t
- struct unpack_dms_SetIndicationRegister_t
- struct dms_PSMEnableStateIndTlv
- struct dms_PSMActiveTimerIndTlv
- struct dms_PSMPeriodicUpdateTimerIndTlv
- struct unpack_dms_PSMCfgChange_ind_t
- struct pack_dms_SwiSetEventReport_t
- struct unpack_dms_SwiSetEventReport_t
- struct dms_TemperatureTlv
- struct dms_VoltageTlv
- struct dms_UimStatusTlv
- struct unpack_dms_SwiEventReportCallBack_ind_t
- struct pack_dms_SwiUimSelect_t
- struct unpack_dms_SwiUimSelect_t
- struct dms_UimAutoSwitchActSlotTlv
- struct unpack_dms_SLQSDmsSwiGetUimSelection_t

Macros

- #define DMS_UINT8_MAX_STRING_SZ 255
- #define DMS_MAX_CUST_ID_LEN 64
- #define DMS_MAX_CUST_VALUE_LEN 8
- #define DMS_IMGDETAILS_LEN 16
- #define DMS_MAX_FWUPDATE_LOG_STR_SZ 255
- #define DMS_MAX_FWUPDATE_REF_STR_SZ 15
- #define DMS_VALID_FSN_LEN 14
- #define DMS_MAX_RADIO_IFCS_SIZE 64
- #define DMS_SLQSFWINFO_MODELID_SZ 20
- #define DMS_SLQSFWINFO_BOOTVERSION_SZ 85
- #define DMS_SLQSFWINFO_APPVERSION_SZ 85
- #define DMS_SLQSFWINFO_SKU_SZ 15
- #define DMS_SLQSFWINFO_PACKAGEID_SZ 85
- #define DMS_SLQSFWINFO_CARRIER_SZ 20
- #define DMS_SLQSFWINFO_PRIVERSION_SZ 16
- #define DMS_SLQSFWINFO_CUR_CARR_NAME 17
- #define DMS_SLQSFWINFO_CUR_CARR_REV 13
- #define MAX_BUILD_ID_LEN 255
- #define UNIQUE_ID_LEN 16
- #define SLQS_MAX_DYING_GASP_CFG_SMS_CONTENT_LENGTH 160
- #define SLQS_MAX_DYING_GASP_CFG_SMS_NUMBER_LENGTH 20
- #define SPC_SIZE 6
- #define CK_MAX_SIZE 8
- #define ACT_CODE_MAX_SIZE 81
- #define ERI_DATA_MAX_SIZE 1024
- #define MEID_MAX_SIZE 8
- #define DMS_PM_ONLINE 0x00 /∗ Online ∗/
- #define DMS_PM_LOW 0x01 /∗ Low Power ∗/
- #define DMS_PM_FACTORY 0x02 /∗ Factory Test Mode ∗/
- #define DMS_PM_OFFLINE 0x03 /∗ Offline ∗/
- #define DMS_PM_RESET 0x04 /∗ Reset ∗/
- #define DMS_PM_SHUT_DOWN 0x05 /∗ Shut Down ∗/
- #define DMS_PM_PERSISTENT_LOW 0x06 /∗ Persistent Low Power ∗/
- #define DMS_SET_REPORT_ENABLE 1
- #define DMS_SET_REPORT_DISABLE 0
- #define DMS_SWI_SET_IND_ENABLE 1
- #define DMS_SWI_SET_IND_DISABLE 0
- #define DMS_SET_REG_IND_ENABLE 1
- #define DMS_SET_REG_IND_DISABLE 0
- #define DMS_SET_REG_IND_NO_CHANGE 2

Functions

- int pack_dms_GetIMSI (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, void ∗reqArg)
- int unpack_dms_GetIMSI (uint8_t ∗pResp, uint16_t respLen, unpack_dms_GetIMSI_t ∗pOutput)
- int pack_dms_GetModelID (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, void ∗reqArg)
- int unpack_dms_GetModelID (uint8_t ∗pResp, uint16_t respLen, unpack_dms_GetModelID_t ∗pOutput)
- int pack_dms_GetFirmwareInfo (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, void ∗reqArg)
- int unpack_dms_GetFirmwareInfo (uint8_t ∗pResp, uint16_t respLen, unpack_dms_GetFirmwareInfo_t ∗p-Output)
- int pack_dms_GetPower (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, void ∗reqArg)
- int unpack_dms_GetPower (uint8_t ∗pResp, uint16_t respLen, unpack_dms_GetPower_t ∗pOutput)

- int pack_dms_GetSerialNumbers (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetSerialNumbers (uint8_t *pResp, uint16_t respLen, unpack_dms_GetSerialNumbers_t *pOutput)
- int pack_dms_GetHardwareRevision (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetHardwareRevision (uint8_t *pResp, uint16_t respLen, unpack_dms_GetHardwareRevision_t *pOutput)
- int pack_dms_SLQSGetBandCapability (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_SLQSGetBandCapability (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSGetBandCapability_t *pOutput)
- int pack_dms_GetDeviceCapabilities (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetDeviceCapabilities (uint8_t *pResp, uint16_t respLen, unpack_dms_GetDeviceCapabilities_t *pOutput)
- int pack_dms_GetFirmwareRevisions (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetFirmwareRevisions (uint8_t *pResp, uint16_t respLen, unpack_dms_GetFirmwareRevisions_t *pOutput)
- int pack_dms_GetFirmwareRevision (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetFirmwareRevision (uint8_t *pResp, uint16_t respLen, unpack_dms_GetFirmwareRevision_t *pOutput)
- int pack_dms_GetDeviceSerialNumbers (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetDeviceSerialNumbers (uint8_t *pResp, uint16_t respLen, unpack_dms_GetDeviceSerialNumbers_t *pOutput)
- int pack_dms_GetPRLVersion (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetPRLVersion (uint8_t *pResp, uint16_t respLen, unpack_dms_GetPRLVersion_t *pOutput)
- int pack_dms_GetNetworkTime (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetNetworkTime (uint8_t *pResp, uint16_t respLen, unpack_dms_GetNetworkTime_t *pOutput)
- int pack_dms_GetVoiceNumber (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetVoiceNumber (uint8_t *pResp, uint16_t respLen, unpack_dms_GetVoiceNumber_t *pOutput)
- int pack_dms_GetDeviceHardwareRev (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetDeviceHardwareRev (uint8_t *pResp, uint16_t respLen, unpack_dms_GetDeviceHardwareRev_t *pOutput)
- int pack_dms_GetFSN (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetFSN (uint8_t *pResp, uint16_t respLen, unpack_dms_GetFSN_t *pOutput)
- int pack_dms_GetDeviceCap (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetDeviceCap (uint8_t *pResp, uint16_t respLen, unpack_dms_GetDeviceCap_t *pOutput)
- int pack_dms_SetPower (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SetPower_t *reqArg)
- int unpack_dms_SetPower (uint8_t *pResp, uint16_t respLen, unpack_dms_SetPower_t *pOutput)
- int pack_dms_GetBandCapability (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetBandCapability (uint8_t *pResp, uint16_t respLen, unpack_dms_GetBandCapability_t *pOutput)
- int pack_dms_GetUSBComp (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetUSBComp (uint8_t *pResp, uint16_t respLen, unpack_dms_GetUSBComp_t *pOutput)
- int pack_dms_SetUSBComp (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SetUSBComp_t *reqArg)
- int unpack_dms_SetUSBComp (uint8_t *pResp, uint16_t respLen, unpack_dms_SetUSBComp_t *pOutput)
- int pack_dms_SetCustFeature (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SetCustFeature_t *reqArg)
- int unpack_dms_SetCustFeature (uint8_t *pResp, uint16_t respLen, unpack_dms_SetCustFeature_t *pOutput)
- int pack_dms_GetCustFeature (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetCustFeature (uint8_t *pResp, uint16_t respLen, unpack_dms_GetCustFeature_t *pOutput)
- int pack_dms_SetFirmwarePreference (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)

- int unpack_dms_SetFirmwarePreference (uint8_t *pResp, uint16_t respLen, unpack_dms_SetFirmwarePreference_t *pOutput)
- int pack_dms_GetCrashAction (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetCrashAction (uint8_t *pResp, uint16_t respLen, unpack_dms_GetCrashAction_t *pOutput)
- int pack_dms_SetCrashAction (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SetCrashAction_t reqArg)
- int unpack_dms_SetCrashAction (uint8_t *pResp, uint16_t respLen, unpack_dms_SetCrashAction_t *pOutput)
- int pack_dms_GetDeviceMfr (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_GetDeviceMfr (uint8_t *pResp, uint16_t respLen, unpack_dms_GetDeviceMfr_t *pOutput)
- int pack_dms_SetEventReport (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SetEventReport_t *reqArg)
- int unpack_dms_SetEventReport (uint8_t *pResp, uint16_t respLen, unpack_dms_SetEventReport_t *pOutput)
- int unpack_dms_SetEventReport_ind (uint8_t *pResp, uint16_t respLen, unpack_dms_SetEventReport_ind_t *pOutput)
- int pack_dms_UIMGetICCID (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_UIMGetICCID_t *reqArg)
- int unpack_dms_UIMGetICCID (uint8_t *pResp, uint16_t respLen, unpack_dms_UIMGetICCID_t *pOutput)
- int pack_dms_SetCustFeaturesV2 (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SetCustFeaturesV2_t *reqArg)
- int unpack_dms_SetCustFeaturesV2 (uint8_t *pResp, uint16_t respLen, unpack_dms_SetCustFeaturesV2_t *pOutput)
- int pack_dms_GetCustFeaturesV2 (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_GetCustFeaturesV2_t *reqArg)
- int unpack_dms_GetCustFeaturesV2 (uint8_t *pResp, uint16_t respLen, unpack_dms_GetCustFeaturesV2_t *pOutput)
- int pack_dms_GetActivationState (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_GetActivationState (uint8_t *pResp, uint16_t respLen, unpack_dms_GetActivationState_t *pOutput)
- int pack_dms_SLQSSwiGetFirmwareCurr (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSSwiGetFirmwareCurr (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiGetFirmwareCurr_t *pOutput)
- int pack_dms_SLQSSwiSetDyingGaspCfg (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SLQSSwiSetDyingGaspCfg_t *reqArg)
- int unpack_dms_SLQSSwiSetDyingGaspCfg (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiSetDyingGaspCfg_t *pOutput)
- int pack_dms_SLQSSwiClearDyingGaspStatistics (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSSwiClearDyingGaspStatistics (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiClearDyingGaspStatistics_t *pOutput)
- int pack_dms_SLQSSwiGetDyingGaspStatistics (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSSwiGetDyingGaspStatistics (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiGetDyingGaspStatistics_t *pOutput)
- int pack_dms_SLQSSwiGetDyingGaspCfg (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSSwiGetDyingGaspCfg (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiGetDyingGaspCfg_t *pOutput)
- int pack_dms_SLQSDmsSwiGetResetInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSDmsSwiGetResetInfo (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSDmsSwiGetResetInfo_t *pOutput)
- int unpack_dms_SLQSDmsSwiGetResetInfo_Ind (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t *pOutput)
- int pack_dms_SLQSDmsSwiIndicationRegister (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SLQSDmsSwiIndicationRegister_t *reqArg)
- int unpack_dms_SLQSDmsSwiIndicationRegister (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSDmsSwiIndicationRegister_t *pOutput)

- int pack_dms_SLQSSwiGetFwUpdateStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSSwiGetFwUpdateStatus (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiGetFwUpdateStatus_t *pOutput)
- int pack_dms_GetManufacturer (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_GetManufacturer (uint8_t *pResp, uint16_t respLen, unpack_dms_GetManufacturer_t *pOutput)
- int pack_dms_GetOfflineReason (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_GetOfflineReason (uint8_t *pResp, uint16_t respLen, unpack_dms_GetOfflineReason_t *pOutput)
- int pack_dms_SetActivationStatusCallback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SetActivationStatusCallback_t *reqArg)
- int unpack_dms_SetActivationStatusCallback (uint8_t *pResp, uint16_t respLen, unpack_dms_SetActivationStatusCallback_t *pOutput)
- int pack_dms_UIMSetPINProtection (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_UIMSetPINProtection_t *pReq)
- int unpack_dms_UIMSetPINProtection (uint8_t *pResp, uint16_t respLen, unpack_dms_UIMSetPINProtection_t *pOutput)
- int pack_dms_UIMUnblockPIN (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_UIMUnblockPIN_t *pReq)
- int unpack_dms_UIMUnblockPIN (uint8_t *pResp, uint16_t respLen, unpack_dms_UIMSetPINProtection_t *pOutput)
- int pack_dms_UIMVerifyPIN (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_UIMVerifyPIN_t *pReq)
- int unpack_dms_UIMVerifyPIN (uint8_t *pResp, uint16_t respLen, unpack_dms_UIMSetPINProtection_t *pOutput)
- int pack_dms_UIMChangePIN (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_UIMChangePIN_t *pReq)
- int unpack_dms_UIMChangePIN (uint8_t *pResp, uint16_t respLen, unpack_dms_UIMSetPINProtection_t *pOutput)
- int pack_dms_UIMGetControlKeyStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_UIMGetControlKeyStatus_t *pReq)
- int unpack_dms_UIMGetControlKeyStatus (uint8_t *pResp, uint16_t respLen, unpack_dms_UIMGetControlKeyStatus_t *pOutput)
- int pack_dms_UIMGetPINStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_UIMGetPINStatus (uint8_t *pResp, uint16_t respLen, unpack_dms_UIMGetPINStatus_t *pOutput)
- int pack_dms_UIMSetControlKeyProtection (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_UIMSetControlKeyProtection_t *pReq)
- int unpack_dms_UIMSetControlKeyProtection (uint8_t *pResp, uint16_t respLen, unpack_dms_UIMSetControlKeyProtection_t *pOutput)
- int pack_dms_UIMUnblockControlKey (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_UIMUnblockControlKey_t *pReq)
- int unpack_dms_UIMUnblockControlKey (uint8_t *pResp, uint16_t respLen, unpack_dms_UIMUnblockControlKey_t *pOutput)
- int pack_dms_ResetToFactoryDefaults (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_ResetToFactoryDefaults_t *pReq)
- int unpack_dms_ResetToFactoryDefaults (uint8_t *pResp, uint16_t respLen, unpack_dms_ResetToFactoryDefaults_t *pOutput)
- int pack_dms_ValidateSPC (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_ResetToFactoryDefaults_t *pReq)
- int unpack_dms_ValidateSPC (uint8_t *pResp, uint16_t respLen, unpack_dms_ResetToFactoryDefaults_t *pOutput)
- int pack_dms_ActivateAutomatic (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_ActivateAutomatic_t *pReq)
- int unpack_dms_ActivateAutomatic (uint8_t *pResp, uint16_t respLen, unpack_dms_ResetToFactoryDefaults_t *pOutput)

- int pack_dms_SLQSGetERIFile (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSGetERIFile (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSGetERIFile_t *pOutput)
- int pack_dms_SLQSUIMGetState (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSUIMGetState (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSUIMGetState_t *pOutput)
- int pack_dms_SLQSSwiGetCrashInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SLQSSwiGetCrashInfo_t *pReq)
- int unpack_dms_SLQSSwiGetCrashInfo (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiGetCrashInfo_t *pOutput)
- int pack_dms_SLQSSwiGetHostDevInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSSwiGetHostDevInfo (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiGetHostDevInfo_t *pOutput)
- int pack_dms_SLQSSwiSetHostDevInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SLQSSwiSetHostDevInfo_t *pReq)
- int unpack_dms_SLQSSwiSetHostDevInfo (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiSetHostDevInfo_t *pOutput)
- int pack_dms_SLQSSwiGetOSInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSSwiGetOSInfo (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiGetOSInfo_t *pOutput)
- int pack_dms_SLQSSwiSetOSInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SLQSSwiSetOSInfo_t *pReq)
- int unpack_dms_SLQSSwiSetOSInfo (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiSetOSInfo_t *pOutput)
- int pack_dms_SLQSSwiGetSerialNoExt (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_dms_SLQSSwiGetSerialNoExt (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSwiGetSerialNoExt_t *pOutput)
- int pack_dms_SLQSDmsSwiGetPCInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_SLQSDmsSwiGetPCInfo (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSDmsSwiGetPCInfo_t *pOutput)
- int pack_dms_SLQSGetPowerSaveModeConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_SLQSGetPowerSaveModeConfig (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSGetPowerSaveModeConfig_t *pOutput)
- int pack_dms_SLQSSetPowerSaveModeConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SLQSSetPowerSaveModeConfig_t *reqArg)
- int unpack_dms_SLQSSetPowerSaveModeConfig (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSSetPowerSaveModeConfig_t *pOutput)
- int pack_dms_SetIndicationRegister (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SetIndicationRegister_t *reqArg)
- int unpack_dms_SetIndicationRegister (uint8_t *pResp, uint16_t respLen, unpack_dms_SetIndicationRegister_t *pOutput)
- int unpack_dms_PSMCfgChange_ind (uint8_t *pResp, uint16_t respLen, unpack_dms_PSMCfgChange_ind_t *pOutput)
- int pack_dms_SwiSetEventReport (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SwiSetEventReport_t *reqArg)
- int unpack_dms_SwiSetEventReport (uint8_t *pResp, uint16_t respLen, unpack_dms_SwiSetEventReport_t *pOutput)
- int unpack_dms_SwiEventReportCallBack_ind (uint8_t *pResp, uint16_t respLen, unpack_dms_SwiEventReportCallBack_ind_t *pOutput)
- int pack_dms_SwiUimSelect (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_dms_SwiUimSelect_t *reqArg)
- int unpack_dms_SwiUimSelect (uint8_t *pResp, uint16_t respLen, unpack_dms_SwiUimSelect_t *pOutput)
- int pack_dms_SLQSDmsSwiGetUimSelection (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_dms_SLQSDmsSwiGetUimSelection (uint8_t *pResp, uint16_t respLen, unpack_dms_SLQSDmsSwiGetUimSelection_t *pOutput)

9.3.1 Macro Definition Documentation

9.3.1.1 #define ACT_CODE_MAX_SIZE 81

9.3.1.2 #define CK_MAX_SIZE 8

9.3.1.3 #define DMS_IMGDETAILS_LEN 16

9.3.1.4 #define DMS_MAX_CUST_ID_LEN 64

9.3.1.5 #define DMS_MAX_CUST_VALUE_LEN 8

9.3.1.6 #define DMS_MAX_FWUPDATE_LOG_STR_SZ 255

9.3.1.7 #define DMS_MAX_FWUPDATE_REF_STR_SZ 15

9.3.1.8 #define DMS_MAX_RADIO_IFCS_SIZE 64

9.3.1.9 #define DMS_PM_FACTORY 0x02 /∗ Factory Test Mode ∗/

9.3.1.10 #define DMS_PM_LOW 0x01 /∗ Low Power ∗/

9.3.1.11 #define DMS_PM_OFFLINE 0x03 /∗ Offline ∗/

9.3.1.12 #define DMS_PM_ONLINE 0x00 /∗ Online ∗/

9.3.1.13 #define DMS_PM_PERSISTENT_LOW 0x06 /∗ Persistent Low Power ∗/

9.3.1.14 #define DMS_PM_RESET 0x04 /∗ Reset ∗/

9.3.1.15 #define DMS_PM_SHUT_DOWN 0x05 /∗ Shut Down ∗/

9.3.1.16 #define DMS_SET_REG_IND_DISABLE 0

9.3.1.17 #define DMS_SET_REG_IND_ENABLE 1

9.3.1.18 #define DMS_SET_REG_IND_NO_CHANGE 2

9.3.1.19 #define DMS_SET_REPORT_DISABLE 0

9.3.1.20 #define DMS_SET_REPORT_ENABLE 1

9.3.1.21 #define DMS_SLQSFWINFO_APPVERSION_SZ 85

9.3.1.22 #define DMS_SLQSFWINFO_BOOTVERSION_SZ 85

9.3.1.23 #define DMS_SLQSFWINFO_CARRIER_SZ 20

9.3.1.24 #define DMS_SLQSFWINFO_CUR_CARR_NAME 17

9.3.1.25 #define DMS_SLQSFWINFO_CUR_CARR_REV 13

9.3.1.26 #define DMS_SLQSFWINFO_MODELID_SZ 20

9.3.1.27 #define DMS_SLQSFWINFO_PACKAGEID_SZ 85

9.3.1.28 #define DMS_SLQSFWINFO_PRIVERSION_SZ 16

9.3.1.29 #define DMS_SLQSFWINFO_SKU_SZ 15

9.3.1.30 #define DMS_SWI_SET_IND_DISABLE 0

9.3.1.31 #define DMS_SWI_SET_IND_ENABLE 1

9.3.1.32 #define DMS_UINT8_MAX_STRING_SZ 255

9.3.1.33 #define DMS_VALID_FSN_LEN 14

9.3.1.34 #define ERI_DATA_MAX_SIZE 1024

9.3.1.35 #define MAX_BUILD_ID_LEN 255

9.3.1.36 #define MEID_MAX_SIZE 8

9.3.1.37 #define SLQS_MAX_DYING_GASP_CFG_SMS_CONTENT_LENGTH 160

9.3.1.38 #define SLQS_MAX_DYING_GASP_CFG_SMS_NUMBER_LENGTH 20

9.3.1.39 #define SPC_SIZE 6

9.3.1.40 #define UNIQUE_ID_LEN 16

9.3.2 Function Documentation

9.3.2.1 int pack_dms_ActivateAutomatic (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_ActivateAutomatic_t * *pReq*)

Requests the device to perform automatic service activation pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.2 int pack_dms_GetActivationState (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Get Activation State pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

This is only supported for 3GPP2 devices.

9.3.2.3 int pack_dms_GetBandCapability (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Band Capability pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.4 int pack_dms_GetCrashAction (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Crash Action pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.5 int pack_dms_GetCustFeature (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Custom Feature pack. This API is deprecated for EM74xx/MC74xx, please use pack_dms_GetCustFeatures-V2() instead for EM74xx/MC74xx.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.6 int pack_dms_GetCustFeaturesV2 (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_GetCustFeaturesV2_t * *reqArg*)

Get Custom Feature pack This function queries the modem for a list of supported features. This function is for firmware version 2.0 and newer. Currently supported Customization features:

- GPIOSARENABLE
- GPSSEL
- IMSWITCHHIDE
- IPV6ENABLE
- WAKEHOSTEN

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.7 int pack_dms_GetDeviceCap (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Device Capabilities pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.8 int pack_dms_GetDeviceCapabilities (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get device capability pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.9 int pack_dms_GetDeviceHardwareRev (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Hardware Revision of the device pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.10 int pack_dms_GetDeviceMfr (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Device Manufacture Name pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.11 int pack_dms_GetDeviceSerialNumbers (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Device Serial Number pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.12 int pack_dms_GetFirmwareInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get firmware info pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.13 int pack_dms_GetFirmwareRevision (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Firmware Revision pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.14 int pack_dms_GetFirmwareRevisions (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Firmware Revisions pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.15 int pack_dms_GetFSN (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get FSN pack. This API get the Factory Sequence Number of the device.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.16 int pack_dms_GetHardwareRevision (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get hardware revision of the device pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.17 int pack_dms_GetIMSI (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get IMSI pack. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_-xx_xx and all EM74xx firmware versions. Please use pack_uim_ReadTransparent()(EF ID: 3F00 7F20 6F07 for 2G card and 3F00 7FFF 6F07 for 3G card) instead for new firmware versions and new modules.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.18 int pack_dms_GetManufacturer (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

To get device manufacturer information pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.19 int pack_dms_GetModelID (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get model id pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.20 int pack_dms_GetNetworkTime (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Network Time pack Returns the current time of the device based on the value supported by the network.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.21 int pack_dms_GetOfflineReason (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

To get operating mode offline reason pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.22 int pack_dms_GetPower (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get operating mode of the device pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.23 int pack_dms_GetPRLVersion (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get PRL Versions pack. Return version of the active Preferred Roaming List (PRL) in use by the device.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.24 int pack_dms_GetSerialNumbers (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get serial numbers pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.25 int pack_dms_GetUSBComp (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, void * reqArg)

Get USB Comp pack This API queries the modem's USB interface configuration and supported configuration parameters.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.26 int pack_dms_GetVoiceNumber (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, void * reqArg)

Get Voice Number pack. Returns the voice number in use by the device.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.27 int pack_dms_ResetToFactoryDefaults (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_dms_ResetToFactoryDefaults_t * pReq)

Resets to default factory settings of the device pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.28 int pack_dms_SetActivationStatusCallback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SetActivationStatusCallback_t * *reqArg*)

Set activation status pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.29 int pack_dms_SetCrashAction (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SetCrashAction_t *reqArg*)

Set Crash Action pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.30 int pack_dms_SetCustFeature (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SetCustFeature_t * *reqArg*)

Set Custom Feature pack. This API is deprecated for EM74xx/MC74xx, please use pack_dms_SetCustFeatures-V2() instead for EM74xx/MC74xx.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.31 int pack_dms_SetCustFeaturesV2 (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SetCustFeaturesV2_t * *reqArg*)

Set Cust Features pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.32 int pack_dms_SetEventReport (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SetEventReport_t * *reqArg*)

Set Event Report pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.33 int pack_dms_SetFirmwarePreference (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Set Firmware Preference pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.34 int pack_dms_SetIndicationRegister (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SetIndicationRegister_t * *reqArg*)

Set Indication register pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.35 int pack_dms_SetPower (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SetPower_t * *reqArg*)

Set Power pack Sets the operating mode of the device.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.36 int pack_dms_SetUSBComp (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_dms_SetUSBComp_t * reqArg)

Set USB Comp pack This API is used to change the modem's USB interface configuration thus allowing a device to have multiple USB compositions. Devices will, by default, be configured to support a minimal set of interfaces to reduce end user modem installation time. Developers and some customers, however, require access to a custom set of interfaces. A reset is required for any change in the USB composition to take effect.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.37 int pack_dms_SLQSDmsSwiGetPCInfo (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, void * reqArg)

Get device power control status information pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.38 int pack_dms_SLQSDmsSwiGetResetInfo (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

To get reset info pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.39 int pack_dms_SLQSDmsSwiGetUimSelection (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get device UIM Selection information pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.40 int pack_dms_SLQSDmsSwiIndicationRegister (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SLQSDmsSwiIndicationRegister_t * *reqArg*)

Set the registration state for different indication pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

support EM/MC74xx onwards

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.41 int pack_dms_SLQSGetBandCapability (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get band capability of the device pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.42 int pack_dms_SLQSGetERIFile (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

To set UIM Get ERI file pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.43 int pack_dms_SLQSGetPowerSaveModeConfig (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Get Power Save Mode (PSM) configuration parameter pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter(NULL)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.44 int pack_dms_SLQSSetPowerSaveModeConfig (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SLQSSetPowerSaveModeConfig_t * *reqArg*)

Sets the Power Save Mode (PSM) configuration parameters pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.45 int pack_dms_SLQSSwiClearDyingGaspStatistics (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Clear Dying GASP Statistics pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.46 int pack_dms_SLQSSwiGetCrashInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SLQSSwiGetCrashInfo_t * *pReq*)

To Get the Crash Information from the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.47 int pack_dms_SLQSSwiGetDyingGaspCfg (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Get Dying GASP Config pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.48 int pack_dms_SLQSSwiGetDyingGaspStatistics (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Get Dying GASP Statistics pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.49 int pack_dms_SLQSSwiGetFirmwareCurr (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Get currently active image pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.50 int pack_dms_SLQSSwiGetFwUpdateStatus (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

To get Firmware Update status pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.51 int pack_dms_SLQSSwiGetHostDevInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

To get host dev information pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.52 int pack_dms_SLQSSwiGetOSInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

To Get Host OS Info pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.53 int pack_dms_SLQSSwiGetSerialNoExt (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

To get serial number extension pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.54 int pack_dms_SLQSSwiSetDyingGaspCfg (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SLQSSwiSetDyingGaspCfg_t * *reqArg*)

Set Dying GASP Config pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.55 int pack_dms_SLQSSwiSetHostDevInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SLQSSwiSetHostDevInfo_t * *pReq*)

To set Host Dev Info pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.56 int pack_dms_SLQSSwiSetOSInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SLQSSwiSetOSInfo_t * *pReq*)

To set Host OS Info pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.57 int pack_dms_SLQSUIMGetState (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Returns the UIM state pack. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9-X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API unpack_uim_GetCardStatus/ unpack_uim-_GetCardStatus for new firmware versions and new modules

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.58 int pack_dms_SwiSetEventReport (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SwiSetEventReport_t * *reqArg*)

Sets the DMS swi event report parameters pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.59 int pack_dms_SwiUimSelect (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_SwiUimSelect_t * *reqArg*)

Sets the DMS swi UIM Select parameters pack. A reset is required for any change in the UIM selection to take effect.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.60 int pack_dms_UIMChangePIN (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_UIMChangePIN_t * *pReq*)

To set UIM change PIN pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.61 int pack_dms_UIMGetControlKeyStatus (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_dms_UIMGetControlKeyStatus_t * pReq)

To set UIM Get Control Key Status pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.62 int pack_dms_UIMGetICCID (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_dms_UIMGetICCID_t * reqArg)

Packs the UIMGetICCID response message to a user-provided response structure. This API is deprecated on MC73xx/EM73xx modules. Since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use pack_uim_ReadTransparent()(EF ID: 3F00 2FE2) instead for new firmware versions and new modules.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.63 int pack_dms_UIMGetPINStatus (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

To set UIM Get PIN Status pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.64 int pack_dms_UIMSetControlKeyProtection (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_UIMSetControlKeyProtection_t * *pReq*)

To set UIM Set Control Key Protection pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.65 int pack_dms_UIMSetPINProtection (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_UIMSetPINProtection_t * *pReq*)

To set UIM PIN protection pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.66 int pack_dms_UIMUnblockControlKey (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_UIMUnblockControlKey_t * *pReq*)

To set UIM Unblock Control Key pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.67 int pack_dms_UIMUnblockPIN (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_UIMUnblockPIN_t * *pReq*)

To set UIM unblock PIN pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.68 int pack_dms_UIMVerifyPIN (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_dms_UIMVerifyPIN_t * *pReq*)

To set UIM verify PIN pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.69 int pack_dms_ValidateSPC (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_dms_ResetToFactoryDefaults_t * pReq)

Requests the device to perform automatic service activation pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
out	*pReq*	requeset parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.70 int unpack_dms_ActivateAutomatic (uint8_t * pResp, uint16_t respLen, unpack_dms_ResetToFactoryDefaults_t * pOutput)

Requests the device to perform automatic service activation unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.71 int unpack_dms_GetActivationState (uint8_t * pResp, uint16_t respLen, unpack_dms_GetActivationState_t * pOutput)

Get Activation State unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

This is only supported for 3GPP2 devices.

9.3.2.72 int unpack_dms_GetBandCapability (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetBandCapability_t * *pOutput*)

Get Band Capabilities unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.73 int unpack_dms_GetCrashAction (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetCrashAction_t * *pOutput*)

Get Crash Action unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.74 int unpack_dms_GetCustFeature (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetCustFeature_t * *pOutput*)

Get Custom Feature unpack. This API is deprecated for EM74xx/MC74xx, please use unpack_dms_GetCustFeaturesV2() instead for EM74xx/MC74xx.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.75 int unpack_dms_GetCustFeaturesV2 (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetCustFeaturesV2_t * *pOutput*)

Get Custom Feature unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.76 int unpack_dms_GetDeviceCap (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetDeviceCap_t * *pOutput*)

Get Device Capabilities unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.77 int unpack_dms_GetDeviceCapabilities (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetDeviceCapabilities_t * *pOutput*)

Get device capability unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.78 int unpack_dms_GetDeviceHardwareRev (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetDeviceHardwareRev_t * *pOutput*)

Get Hardware Revision of the device unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.79 int unpack_dms_GetDeviceMfr (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetDeviceMfr_t * *pOutput*)

Get Device Manufacture Name unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.80 int unpack_dms_GetDeviceSerialNumbers (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetDeviceSerialNumbers_t * *pOutput*)

Get Device Serial Number unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.81 int unpack_dms_GetFirmwareInfo (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_GetFirmwareInfo_t** * *pOutput*)

Get firmware info unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.82 int unpack_dms_GetFirmwareRevision (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_GetFirmwareRevision_t** * *pOutput*)

Get Firmware Revision unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.83 int unpack_dms_GetFirmwareRevisions (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetFirmwareRevisions_t * *pOutput*)

Get Firmware Revisions unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.84 int unpack_dms_GetFSN (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetFSN_t * *pOutput*)

Get FSN unpack This API get the Factory Sequence Number of the device.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.85 int unpack_dms_GetHardwareRevision (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetHardwareRevision_t * *pOutput*)

Get hardware revision of the device unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.86 int unpack_dms_GetIMSI (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_GetIMSI_t** * *pOutput*)

Get IMSI unpack. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx-_xx_xx and all EM74xx firmware versions. Please use unpack_uim_ReadTransparent()(EF ID: 3F00 7F20 6F07 for 2G card and 3F00 7FFF 6F07 for 3G card) instead for new firmware versions and new modules.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.87 int unpack_dms_GetManufacturer (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_GetManufacturer_t** * *pOutput*)

To get device manufacturer information unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.88 int unpack_dms_GetModelID (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_GetModelID_t** * *pOutput*)

Get model id unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.89 int unpack_dms_GetNetworkTime (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetNetworkTime_t * *pOutput*)

Get Network Time unpack. Returns the current time of the device based on the value supported by the network.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.90 int unpack_dms_GetOfflineReason (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetOfflineReason_t * *pOutput*)

To get operating mode offline reason unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.91 int unpack_dms_GetPower (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetPower_t * *pOutput*)

Get operating mode of the device unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.92 int unpack_dms_GetPRLVersion (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_GetPRLVersion_t** * *pOutput*)

Get PRL Versions unpack Return version of the active Preferred Roaming List (PRL) in use by the device.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.93 int unpack_dms_GetSerialNumbers (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_GetSerialNumbers_t** * *pOutput*)

Get serial numbers unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.94 int unpack_dms_GetUSBComp (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_GetUSBComp_t** * *pOutput*)

Get USB Comp unpack This API queries the modem's USB interface configuration and supported configuration parameters.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.95 int unpack_dms_GetVoiceNumber (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_GetVoiceNumber_t * *pOutput*)

Get Voice Number unpack Returns the voice number in use by the device.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.96 int unpack_dms_PSMCfgChange_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_PSMCfgChange_ind_t * *pOutput*)

PSM Configuration change Indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.97 int unpack_dms_ResetToFactoryDefaults (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_ResetToFactoryDefaults_t * *pOutput*)

Resets to default factory settings of the device unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.98 int unpack_dms_SetActivationStatusCallback (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SetActivationStatusCallback_t * *pOutput*)

Set Activation status unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.99 int unpack_dms_SetCrashAction (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SetCrashAction_t * *pOutput*)

Set Crash Action unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response. Not used

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.100 int unpack_dms_SetCustFeature (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SetCustFeature_t * *pOutput*)

Set Custom Feature unpack. This API is deprecated for EM74xx/MC74xx, please use unpack_dms_SetCustFeaturesV2() instead for EM74xx/MC74xx.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.101 int unpack_dms_SetCustFeaturesV2 (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SetCustFeaturesV2_t * *pOutput*)

Set Cust features unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.102 int unpack_dms_SetEventReport (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SetEventReport_t * *pOutput*)

Set Event Report unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.103 int unpack_dms_SetEventReport_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SetEventReport_ind_t * *pOutput*)

Event Report Indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.104 int unpack_dms_SetFirmwarePreference (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SetFirmwarePreference_t * *pOutput*)

Set Firmware Preference unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.105 int unpack_dms_SetIndicationRegister (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SetIndicationRegister_t * *pOutput*)

Set Indication register unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.106 int unpack_dms_SetPower (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SetPower_t** * *pOutput*)

Set Power unpack. Sets the operating mode of the device.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.107 int unpack_dms_SetUSBComp (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SetUSBComp_t** * *pOutput*)

Set USB Comp unpack This API is used to change the modem's USB interface configuration thus allowing a device to have multiple USB compositions. Devices will, by default, be configured to support a minimal set of interfaces to reduce end user modem installation time. Developers and some customers, however, require access to a custom set of interfaces. A reset is required for any change in the USB composition to take effect.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.108 int unpack_dms_SLQSDmsSwiGetPCInfo (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SLQSDmsSwiGetPCInfo_t** * *pOutput*)

Get device power control status information unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.109 int unpack_dms_SLQSDmsSwiGetResetInfo (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SLQSDmsSwiGetResetInfo_t** * *pOutput*)

To get reset info unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.110 int unpack_dms_SLQSDmsSwiGetResetInfo_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t** * *pOutput*)

DMS reset info Indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

support EM/MC74xx onwards

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.111 int unpack_dms_SLQSDmsSwiGetUimSelection (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SLQSDmsSwiGetUimSelection_t** * *pOutput*)

Get device UIM selection information unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.112 int unpack_dms_SLQSDmsSwiIndicationRegister (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSDmsSwiIndicationRegister_t * *pOutput*)

Set the registration state for different indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

support EM/MC74xx onwards

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.113 int unpack_dms_SLQSGetBandCapability (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSGetBandCapability_t * *pOutput*)

Get band capability of the device unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.114 int unpack_dms_SLQSGetERIFile (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SLQSGetERIFile_t** * *pOutput*)

To get UIM Get ERI file unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.115 int unpack_dms_SLQSGetPowerSaveModeConfig (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SLQSGetPowerSaveModeConfig_t** * *pOutput*)

Get Power Save Mode (PSM) configuration parameter unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.116 int unpack_dms_SLQSSetPowerSaveModeConfig (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SLQSSetPowerSaveModeConfig_t** * *pOutput*)

Sets the Power Save Mode (PSM) configuration parameters unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.117 int unpack_dms_SLQSSwiClearDyingGaspStatistics (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiClearDyingGaspStatistics_t * *pOutput*)

Clear Dying GASP Statistics unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.118 int unpack_dms_SLQSSwiGetCrashInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiGetCrashInfo_t * *pOutput*)

To Get the Crash Information from the device unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.119 int unpack_dms_SLQSSwiGetDyingGaspCfg (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiGetDyingGaspCfg_t * *pOutput*)

Get Dying GASP Config unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.120 int unpack_dms_SLQSSwiGetDyingGaspStatistics (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiGetDyingGaspStatistics_t * *pOutput*)

Get Dying GASP Statistics unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.121 int unpack_dms_SLQSSwiGetFirmwareCurr (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiGetFirmwareCurr_t * *pOutput*)

Get currently active image unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.122 int unpack_dms_SLQSSwiGetFwUpdateStatus (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiGetFwUpdateStatus_t * *pOutput*)

To get Firmware Update status unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.123 int unpack_dms_SLQSSwiGetHostDevInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiGetHostDevInfo_t * *pOutput*)

To get host dev information unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.124 int unpack_dms_SLQSSwiGetOSInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiGetOSInfo_t * *pOutput*)

To get Host OS Info unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.125 int unpack_dms_SLQSSwiGetSerialNoExt (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiGetSerialNoExt_t * *pOutput*)

To get serial number extension unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.126 int unpack_dms_SLQSSwiSetDyingGaspCfg (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiSetDyingGaspCfg_t * *pOutput*)

Set Dying GASP Config unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.127 int unpack_dms_SLQSSwiSetHostDevInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiSetHostDevInfo_t * *pOutput*)

To set Host Dev Info unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.128 int unpack_dms_SLQSSwiSetOSInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_SLQSSwiSetOSInfo_t * *pOutput*)

To set Host OS Info unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.129 int unpack_dms_SLQSUIMGetState (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SLQSUIMGetState_t** * *pOutput*)

Returns the UIM state unpack. This API is deprecated on MC73xx/EM73xx modules since firmware version SW-I9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API unpack_uim_GetCardStatus / unpack_-uim_GetCardStatus for new firmware versions and new modules

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.130 int unpack_dms_SwiEventReportCallBack_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SwiEventReportCallBack_ind_t** * *pOutput*)

unpack for DMS swi event report indication

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.131 int unpack_dms_SwiSetEventReport (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SwiSetEventReport_t** * *pOutput*)

Sets the swi event report parameters unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.132 int unpack_dms_SwiUimSelect (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_SwiUimSelect_t** * *pOutput*)

Sets the DMS swi UIM Select parameters unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.133 int unpack_dms_UIMChangePIN (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_UIMSetPINProtection_t** * *pOutput*)

To get UIM change PIN unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.134 int unpack_dms_UIMGetControlKeyStatus (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_UIMGetControlKeyStatus_t** * *pOutput*)

To get UIM Get ControlKeyStatus unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.135 int unpack_dms_UIMGetICCID (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_UIMGetICCID_t** * *pOutput*)

Unpacks the UIMGetICCID response message to a user-provided response structure.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.136 int unpack_dms_UIMGetPINStatus (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_UIMGetPINStatus_t** * *pOutput*)

To get UIM Get PIN Status unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.137 int unpack_dms_UIMSetControlKeyProtection (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_UIMSetControlKeyProtection_t** * *pOutput*)

To get UIM Set Control Key Protection unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.138 int unpack_dms_UIMSetPINProtection (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_UIMSetPINProtection_t * *pOutput*)

To get UIM Set PIN protection unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.139 int unpack_dms_UIMUnblockControlKey (uint8_t * *pResp*, uint16_t *respLen*, unpack_dms_UIMUnblockControlKey_t * *pOutput*)

To get UIM Unblock Control Key unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.140 int unpack_dms_UIMUnblockPIN (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_UIMSetPINProtection_t** * *pOutput*)

To get UIM unblock PIN unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.141 int unpack_dms_UIMVerifyPIN (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_UIMSetPINProtection_t** * *pOutput*)

To get UIM verify PIN unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.3.2.142 int unpack_dms_ValidateSPC (uint8_t * *pResp*, uint16_t *respLen*, **unpack_dms_ResetToFactoryDefaults_t** * *pOutput*)

Requests the device to perform automatic service activation unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.4 fms.h File Reference

Data Structures

- struct CarrierImage_t
- struct pack_fms_GetImagesPreference_t
- struct FMSImageElement
- struct FMSPrefImageList
- struct unpack_fms_GetImagesPreference_t
- struct pack_fms_GetStoredImages_t
- struct FMSImageIdElement
- struct FMSImageIDEntries
- struct FMSImageList
- struct unpack_fms_GetStoredImages_t
- struct pack_fms_SetImagesPreference_t
- struct unpack_fms_SetImagesPreference_t

Macros

- #define FMS_GOBI_MBN_IMG_ID_SIZE 16
- #define LITE_TOTAL_IMAGE_ID_STRING_SIZE 100
- #define FMS_GOBI_MBN_IMG_ID_STR_LEN LITE_TOTAL_IMAGE_ID_STRING_SIZE
- #define FMS_GOBI_MBN_BUILD_ID_STR_LEN LITE_TOTAL_IMAGE_ID_STRING_SIZE
- #define FMS_GOBI_LISTENTRIES_MAX 2
- #define FMS_MAX_IMAGE_PREFERENCE_IMAGE_SIZE 255
- #define FMS_MAX_IMAGE_ID_ELEMENT 50
- #define FMS_IMAGE_ID_MAX_ENTRIES 2
- #define FMS_FW_PRI_BUILD_MATCH_LEN 11
- #define FMS_IMAGE_ID_IMG_ID_LEN 16
- #define FMS_IMAGE_ID_BUILD_ID_LEN 32
- #define FMS_IMAGE_ID_PRI_IMGTYPE 0x01

Functions

- int pack_fms_GetImagesPreference (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_fms_GetImagesPreference_t *reqArg)
- int unpack_fms_GetImagesPreference (uint8_t *pResp, uint16_t respLen, unpack_fms_GetImagesPreference_t *pOutput)
- int pack_fms_GetStoredImages (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_fms_GetStoredImages_t *reqArg)
- int unpack_fms_GetStoredImages (uint8_t *pResp, uint16_t respLen, unpack_fms_GetStoredImages_t *pOutput)
- int pack_fms_SetImagesPreference (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_fms_SetImagesPreference_t *reqArg)
- int unpack_fms_SetImagesPreference (uint8_t *pResp, uint16_t respLen, unpack_fms_SetImagesPreference_t *pOutput)
- uint32_t GetValidFwPriCombinations (FMSImageList *pStoredImageList, uint32_t *pValidCombinationSize, CarrierImage_t *pValidCombinations)

9.4.1 Macro Definition Documentation

9.4.1.1 #define FMS_FW_PRI_BUILD_MATCH_LEN 11

9.4.1.2 #define FMS_GOBI_LISTENTRIES_MAX 2

9.4.1.3 #define FMS_GOBI_MBN_BUILD_ID_STR_LEN LITE_TOTAL_IMAGE_ID_STRING_SIZE

9.4.1.4 #define FMS_GOBI_MBN_IMG_ID_SIZE 16

9.4.1.5 #define FMS_GOBI_MBN_IMG_ID_STR_LEN LITE_TOTAL_IMAGE_ID_STRING_SIZE

9.4.1.6 #define FMS_IMAGE_ID_BUILD_ID_LEN 32

9.4.1.7 #define FMS_IMAGE_ID_IMG_ID_LEN 16

9.4.1.8 #define FMS_IMAGE_ID_MAX_ENTRIES 2

9.4.1.9 #define FMS_IMAGE_ID_PRI_IMGTYPE 0x01

9.4.1.10 #define FMS_MAX_IMAGE_ID_ELEMENT 50

9.4.1.11 #define FMS_MAX_IMAGE_PREFERENCE_IMAGE_SIZE 255

9.4.1.12 #define LITE_TOTAL_IMAGE_ID_STRING_SIZE 100

9.4.2 Function Documentation

9.4.2.1 uint32_t GetValidFwPriCombinations (FMSImageList * *pStoredImageList*, uint32_t * *pValidCombinationSize*, CarrierImage_t * *pValidCombinations*)

This API distills valid Firmware/PRI combinations from GetStoredImages result

Parameters

in	*pStoredImageList*	• image list returned from GetStoredImages • See FMSImageList
in,out	*pValidCombinationSize*	• number of combination passed in and returned
out	*pValidCombinations*	• valid combinations returned • See CarrierImage_t

Returns

- eQCWWAN_ERR_INVALID_ARG - Invalid parameters
- eQCWWAN_ERR_BUFFER_SZ - No enough element to store combinatons returned

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.4.2.2 int pack_fms_GetImagesPreference (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_fms_GetImagesPreference_t * reqArg)

Get Images Preference pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

9.4.2.3 int pack_fms_GetStoredImages (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_fms_GetStoredImages_t * reqArg)

Get Images Preference pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

9.4.2.4 int pack_fms_SetImagesPreference (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_fms_SetImagesPreference_t * reqArg)

Set Images Preference pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

9.4.2.5 int unpack_fms_GetImagesPreference (uint8_t * pResp, uint16_t respLen, unpack_fms_GetImagesPreference_t * pOutput)

Get Images Preference unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

9.4.2.6 int unpack_fms_GetStoredImages (uint8_t * pResp, uint16_t respLen, unpack_fms_GetStoredImages_t * pOutput)

Get Images Preference unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

9.4.2.7 int unpack_fms_SetImagesPreference (uint8_t * *pResp*, uint16_t *respLen*, unpack_fms_SetImagesPreference_t * *pOutput*)

Set Images Preference unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

9.5 loc.h File Reference

Data Structures

- struct loc_LocApplicationInfo
- struct loc_SV
- struct loc_SVInfo
- struct loc_GnssData
- struct loc_CellDb
- struct loc_ClkInfo
- struct loc_BdsSV
- struct loc_BdsSVInfo
- struct pack_loc_EventRegister_t
- struct unpack_loc_EventRegister_t
- struct pack_loc_SetExtPowerState_t
- struct unpack_loc_SetExtPowerState_t
- struct pack_loc_Start_t
- struct unpack_loc_Start_t
- struct pack_loc_Stop_t
- struct unpack_loc_Stop_t
- struct pack_loc_SetOperationMode_t
- struct unpack_loc_SetOperationMode_t
- struct pack_loc_Delete_Assist_Data_t
- struct unpack_loc_Delete_Assist_Data_t
- struct loc_precisionDilution
- struct loc_sensorDataUsage
- struct loc_svUsedforFix
- struct loc_gpsTime
- struct unpack_loc_PositionRpt_Ind_t
- struct unpack_loc_EngineState_Ind_t
- struct unpack_loc_SetExtPowerConfig_Ind_t
- struct unpack_loc_SLQSLOCGetBestAvailPos_t
- struct pack_loc_SLQSLOCGetBestAvailPos_t
- struct unpack_loc_BestAvailPos_Ind_t
- struct unpack_loc_SetOperationMode_Ind_t
- struct unpack_loc_DeleteAssistData_Ind_t
- struct loc_satelliteInfo

- struct unpack_loc_GnssSvInfo_Ind_t
- struct pack_loc_SLQSLOCInjectUTCTime_t
- struct altSrcInfo_t
- struct pack_loc_SLQSLOCInjectPosition_t
- struct pack_loc_SLQSLOCSetCradleMountConfig_t
- struct sensorData_t
- struct tempData_t
- struct pack_loc_SLQSLOCInjectSensorData_t
- struct unpack_loc_EventNMEA_Ind_t
- struct pack_loc_SLQSLOCGetServer_t
- struct loc_IPv4Info
- struct loc_IPv6Info
- struct loc_urlAddr
- struct unpack_loc_GetServer_Ind_t
- struct unpack_loc_CradleMountCallback_Ind_t
- struct unpack_loc_EventTimeSyncCallback_Ind_t
- struct unpack_loc_InjectTimeSyncDataCallback_Ind_t
- struct unpack_loc_InjectSensorDataCallback_Ind_t
- struct loc_accelAcceptReady
- struct loc_gyroAcceptReady
- struct loc_accelTempAcceptReady
- struct loc_gyroTempAcceptReady
- struct unpack_loc_SensorStreamingCallback_Ind_t
- struct unpack_loc_InjectUTCTimeCallback_Ind_t
- struct unpack_loc_InjectPositionCallback_Ind_t
- struct loc_IPv4Config
- struct loc_IPv6Config
- struct loc_URLAddrInfo
- struct pack_loc_SLQSLOCSetServer_t
- struct unpack_loc_SetServer_Ind_t
- struct unpack_loc_SLQSLOCGetOpMode_t
- struct unpack_loc_GetOpMode_Ind_t

Macros

- #define LOC_UINT8_MAX_STRING_SZ 255
- #define LOCEVENTMASKPOSITIONREPORT 0x00000001
- #define LOCEVENTMASKGNSSSVINFO 0x00000002
- #define LOCEVENTMASKNMEA 0x00000004
- #define LOCEVENTMASKNINOTIFYVERIFYREQ 0x00000008
- #define LOCEVENTMASKINJECTTIMEREQ 0x00000010
- #define LOCEVENTMASKINJECTPREDICTEDORBITSREQ 0x00000020
- #define LOCEVENTMASKINJECTPOSITIONREQ 0x00000040
- #define LOCEVENTMASKENGINESTATE 0x00000080
- #define LOCEVENTMASKFIXSESSIONSTATE 0x00000100
- #define LOCEVENTMASKWIFIREQ 0x00000200
- #define LOCEVENTMASKSENSORSTREAMINGREADYSTATUS 0x00000400
- #define LOCEVENTMASKTIMESYNCREQ 0x00000800
- #define LOCEVENTMASKSETSPISTREAMINGREPORT 0x00001000
- #define LOCEVENTMASKLOCATIONSERVERCONNECTIONREQ 0x00002000
- #define LOCEVENTMASKNIGEOFENCENOTIFICATION 0x00004000
- #define LOCEVENTMASKGEOFENCEGENALERT 0x00008000
- #define LOCEVENTMASKGEOFENCEBREACHNOTIFICATION 0x00010000
- #define LOCEVENTMASKPEDOMETERCONTROL 0x00020000

- #define LOCEVENTMASKMOTIONDATACONTROL 0x00040000
- #define LOCEVENTMASKBATCHFULLNOTIFICATION 0x00080000
- #define LOCEVENTMASKLIVEBATCHEDPOSITIONREPORT 0x00100000
- #define LOCEVENTMASKINJECTWIFIAPDATAREQ 0x00200000
- #define LOCEVENTMASKGEOFENCEBATCHBREACHNOTIFICATION 0x00400000
- #define LOCEVENTMASKVEHICLEDATAREADYSTATUS 0x00800000
- #define LOCEVENTMASKGNSSMEASUREMENTREPORT 0x01000000
- #define LOCEVENTMASKINVALIDVALUE 0xFFFFFFFF
- #define MAX_SENSOR_DATA_LEN 64
- #define MAX_TEMP_DATA_LEN 64
- #define MAX_LOC_NMEA_STR_LEN 201

Typedefs

- typedef unpack_loc_Delete_Assist_Data_t unpack_loc_DeleteAssistData_t
- typedef unpack_result_t unpack_loc_SLQSLOCInjectUTCTime_t
- typedef unpack_result_t unpack_loc_SLQSLOCInjectPosition_t
- typedef unpack_result_t unpack_loc_SLQSLOCSetCradleMountConfig_t
- typedef unpack_result_t unpack_loc_SLQSLOCInjectSensorData_t
- typedef unpack_result_t unpack_loc_SLQSLOCGetServer_t

Enumerations

- enum {
  eQMI_LOC_SESS_STATUS_SUCCESS =0,
  eQMI_LOC_SESS_STATUS_IN_PROGRESS =1,
  eQMI_LOC_SESS_STATUS_FAILURE =2,
  eQMI_LOC_SESS_STATUS_TIMEOUT =3 }

Functions

- int pack_loc_EventRegister (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_EventRegister_t *reqArg)
- int unpack_loc_EventRegister (uint8_t *pResp, uint16_t respLen, unpack_loc_EventRegister_t *pOutput)
- int pack_loc_SetExtPowerState (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_SetExtPowerState_t *reqArg)
- int unpack_loc_SetExtPowerState (uint8_t *pResp, uint16_t respLen, unpack_loc_SetExtPowerState_t *pOutput)
- int pack_loc_Start (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_Start_t *reqArg)
- int unpack_loc_Start (uint8_t *pResp, uint16_t respLen, unpack_loc_Start_t *pOutput)
- int pack_loc_Stop (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_Stop_t *reqArg)
- int unpack_loc_Stop (uint8_t *pResp, uint16_t respLen, unpack_loc_Stop_t *pOutput)
- int pack_loc_SetOperationMode (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_SetOperationMode_t *reqArg)
- int unpack_loc_SetOperationMode (uint8_t *pResp, uint16_t respLen, unpack_loc_SetOperationMode_t *pOutput)
- int pack_loc_DeleteAssistData (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_Delete_Assist_Data_t *reqArg)
- int unpack_loc_DeleteAssistData (uint8_t *pResp, uint16_t respLen, unpack_loc_Delete_Assist_Data_t *pOutput)
- int unpack_loc_PositionRpt_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_PositionRpt_Ind_t *pOutput)
- int unpack_loc_EngineState_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_EngineState_Ind_t *pOutput)

- int unpack_loc_SetExtPowerConfig_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_SetExtPowerConfig_Ind_t *pOutput)
- int pack_loc_SLQSLOCGetBestAvailPos (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_SLQSLOCGetBestAvailPos_t *reqArg)
- int unpack_loc_SLQSLOCGetBestAvailPos (uint8_t *pResp, uint16_t respLen, unpack_loc_SLQSLOCGetBestAvailPos_t *pOutput)
- int unpack_loc_BestAvailPos_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_BestAvailPos_Ind_t *pOutput)
- int unpack_loc_SetOperationMode_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_SetOperationMode_Ind_t *pOutput)
- int unpack_loc_DeleteAssistData_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_DeleteAssistData_Ind_t *pOutput)
- int unpack_loc_GnssSvInfo_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_GnssSvInfo_Ind_t *pOutput)
- int pack_loc_SLQSLOCInjectUTCTime (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_SLQSLOCInjectUTCTime_t *reqArg)
- int unpack_loc_SLQSLOCInjectUTCTime (uint8_t *pResp, uint16_t respLen, unpack_loc_SLQSLOCInjectUTCTime_t *pOutput)
- int pack_loc_SLQSLOCInjectPosition (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_SLQSLOCInjectPosition_t *reqArg)
- int unpack_loc_SLQSLOCInjectPosition (uint8_t *pResp, uint16_t respLen, unpack_loc_SLQSLOCInjectPosition_t *pOutput)
- int pack_loc_SLQSLOCSetCradleMountConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_SLQSLOCSetCradleMountConfig_t *reqArg)
- int unpack_loc_SLQSLOCSetCradleMountConfig (uint8_t *pResp, uint16_t respLen, unpack_loc_SLQSLOCSetCradleMountConfig_t *pOutput)
- int pack_loc_SLQSLOCInjectSensorData (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_SLQSLOCInjectSensorData_t *reqArg)
- int unpack_loc_SLQSLOCInjectSensorData (uint8_t *pResp, uint16_t respLen, unpack_loc_SLQSLOCInjectSensorData_t *pOutput)
- int unpack_loc_EventNMEA_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_EventNMEA_Ind_t *pOutput)
- int pack_loc_SLQSLOCGetServer (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_SLQSLOCGetServer_t *reqArg)
- int unpack_loc_SLQSLOCGetServer (uint8_t *pResp, uint16_t respLen, unpack_loc_SLQSLOCGetServer_t *pOutput)
- int unpack_loc_GetServer_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_GetServer_Ind_t *pOutput)
- int unpack_loc_CradleMountCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_CradleMountCallback_Ind_t *pOutput)
- int unpack_loc_EventTimeSyncCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_EventTimeSyncCallback_Ind_t *pOutput)
- int unpack_loc_InjectTimeSyncDataCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_InjectTimeSyncDataCallback_Ind_t *pOutput)
- int unpack_loc_InjectSensorDataCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_InjectSensorDataCallback_Ind_t *pOutput)
- int unpack_loc_SensorStreamingCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_SensorStreamingCallback_Ind_t *pOutput)
- int unpack_loc_InjectUTCTimeCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_InjectUTCTimeCallback_Ind_t *pOutput)
- int unpack_loc_InjectPositionCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_InjectPositionCallback_Ind_t *pOutput)
- int pack_loc_SLQSLOCSetServer (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_loc_SLQSLOCSetServer_t *reqArg)
- int unpack_loc_SLQSLOCSetServer (uint8_t *pResp, uint16_t respLen)
- int unpack_loc_SetServer_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_SetServer_Ind_t *pOutput)
- int pack_loc_SLQSLOCGetOpMode (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)

- int unpack_loc_SLQSLOCGetOpMode (uint8_t *pResp, uint16_t respLen, unpack_loc_SLQSLOCGetOpMode_t *pOutput)
- int unpack_loc_GetOpMode_Ind (uint8_t *pResp, uint16_t respLen, unpack_loc_GetOpMode_Ind_t *pOutput)

9.5.1 Macro Definition Documentation

9.5.1.1 #define LOC_UINT8_MAX_STRING_SZ 255

9.5.1.2 #define LOCEVENTMASKBATCHFULLNOTIFICATION 0x00080000

The control point must enable this mask to receive notification when a batch is full. The location engine sends this event to notify of Batch Full for ongoing batching session.

9.5.1.3 #define LOCEVENTMASKENGINESTATE 0x00000080

The control point must enable this mask to receive engine state report event indications.

9.5.1.4 #define LOCEVENTMASKFIXSESSIONSTATE 0x00000100

The control point must enable this mask to receive fix session status report event indications.

9.5.1.5 #define LOCEVENTMASKGEOFENCEBATCHBREACHNOTIFICATION 0x00400000

The control point must enable this mask to receive notifications when a Geofence is breached. These events are generated when a UE enters or leaves the perimeter of a Geofence. This breach notification is for multiple Geofences. Breaches from multiple Geofences are all batched and sent in the same notification.

9.5.1.6 #define LOCEVENTMASKGEOFENCEBREACHNOTIFICATION 0x00010000

The control point must enable this mask to receive notifications when a Geofence is breached. These events are generated when a UE enters or leaves the perimeter of a Geofence. This breach report is for a single Geofence.

9.5.1.7 #define LOCEVENTMASKGEOFENCEGENALERT 0x00008000

The control point must enable this mask to receive Geofence alerts. These alerts are generated to inform the client of the changes that may affect a Geofence, for example, if GPS is turned off or if the network is unavailable.

9.5.1.8 #define LOCEVENTMASKGNSSMEASUREMENTREPORT 0x01000000

The control point must enable this mask to receive system clock and satellite measurement report events (system clock, SV time, Doppler, etc.). Reports are generated only for the GNSS satellite constellations that are enabled using QMI_LOC_SET_GNSS_ CONSTELL_REPORT_CONFIG(Not yet supported).

9.5.1.9 #define LOCEVENTMASKGNSSSVINFO 0x00000002

The control point must enable this mask to receive satellite report event indications. These reports are sent at a 1 Hz rate.

9.5.1.10 #define LOCEVENTMASKINJECTPOSITIONREQ 0x00000040

The control point must enable this mask to receive position injection request event indications.

9.5.1.11 #define LOCEVENTMASKINJECTPREDICTEDORBITSREQ 0x00000020

The control point must enable this mask to receive predicted orbits request event indications.

9.5.1.12 #define LOCEVENTMASKINJECTTIMEREQ 0x00000010

The control point must enable this mask to receive time injection request event indications.

9.5.1.13 #define LOCEVENTMASKINJECTWIFIAPDATAREQ 0x00200000

The control point must enable this mask to receive Wi-Fi Access Point (AP) data inject request event indications.

9.5.1.14 #define LOCEVENTMASKINVALIDVALUE 0xFFFFFFFF

Invalid Event Mask

9.5.1.15 #define LOCEVENTMASKLIVEBATCHEDPOSITIONREPORT 0x00100000

The control point must enable this mask to receive position report indications along with an ongoing batching session. The location engine sends this event to notify the batched position report while a batching session is ongoing.

9.5.1.16 #define LOCEVENTMASKLOCATIONSERVERCONNECTIONREQ 0x00002000

The control point must enable this mask to receive location server requests. These requests are generated when the service wishes to establish a connection with a location server.

9.5.1.17 #define LOCEVENTMASKMOTIONDATACONTROL 0x00040000

The control point must enable this mask to register for motion data control requests from the location engine. The location engine sends this event to control the injection of motion data.

9.5.1.18 #define LOCEVENTMASKNIGEOFENCENOTIFICATION 0x00004000

The control point must enable this mask to receive notifications related to network-initiated Geofences. These events notify the client when a network-initiated Geofence is added, deleted, or edited.

9.5.1.19 #define LOCEVENTMASKNINOTIFYVERIFYREQ 0x00000008

The control point must enable this mask to receive NI Notify/Verify request event indications.

9.5.1.20 #define LOCEVENTMASKNMEA 0x00000004

The control point must enable this mask to receive NMEA reports for position and satellites in view. The report is at a 1 Hz rate.

9.5.1.21 #define LOCEVENTMASKPEDOMETERCONTROL 0x00020000

The control point must enable this mask to register for pedometer control requests from the location engine. The location engine sends this event to control the injection of pedometer reports.

9.5.1.22 #define LOCEVENTMASKPOSITIONREPORT 0x00000001

The control point must enable this mask to receive position report event indications.

9.5.1.23 #define LOCEVENTMASKSENSORSTREAMINGREADYSTATUS 0x00000400

The control point must enable this mask to receive notifications from the location engine indicating its readiness to accept data from the sensors (accelerometer, gyroscope, etc.).

9.5.1.24 #define LOCEVENTMASKSETSPISTREAMINGREPORT 0x00001000

The control point must enable this mask to receive Stationary Position Indicator (SPI) streaming report indications.

9.5.1.25 #define LOCEVENTMASKTIMESYNCREQ 0x00000800

The control point must enable this mask to receive time sync requests from the GPS engine. Time sync enables the GPS engine to synchronize its clock with the sensor processor's clock.

9.5.1.26 #define LOCEVENTMASKVEHICLEDATAREADYSTATUS 0x00800000

The control point must enable this mask to receive notifications from the location engine indicating its readiness to accept vehicle data (vehicle accelerometer, vehicle angular rate, vehicle odometry, etc.).

9.5.1.27 #define LOCEVENTMASKWIFIREQ 0x00000200

The control point must enable this mask to receive Wi-Fi position request event indications.

9.5.1.28 #define MAX_LOC_NMEA_STR_LEN 201

9.5.1.29 #define MAX_SENSOR_DATA_LEN 64

9.5.1.30 #define MAX_TEMP_DATA_LEN 64

9.5.2 Typedef Documentation

9.5.2.1 typedef unpack_loc_Delete_Assist_Data_t unpack_loc_DeleteAssistData_t

9.5.2.2 typedef unpack_result_t unpack_loc_SLQSLOCGetServer_t

9.5.2.3 typedef unpack_result_t unpack_loc_SLQSLOCInjectPosition_t

9.5.2.4 typedef unpack_result_t unpack_loc_SLQSLOCInjectSensorData_t

9.5.2.5 typedef unpack_result_t unpack_loc_SLQSLOCInjectUTCTime_t

9.5.2.6 typedef unpack_result_t unpack_loc_SLQSLOCSetCradleMountConfig_t

9.5.3 Enumeration Type Documentation

9.5.3.1 anonymous enum

Enumerator

eQMI_LOC_SESS_STATUS_SUCCESS

eQMI_LOC_SESS_STATUS_IN_PROGRESS

eQMI_LOC_SESS_STATUS_FAILURE

eQMI_LOC_SESS_STATUS_TIMEOUT

9.5.4 Function Documentation

9.5.4.1 int pack_loc_DeleteAssistData (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_Delete_Assist_Data_t * *reqArg*)

Delete Assistant Data pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.2 int pack_loc_EventRegister (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_EventRegister_t * *reqArg*)

Event Register pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.3 int pack_loc_SetExtPowerState (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_SetExtPowerState_t * *reqArg*)

Set Ext Power State pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.4 int pack_loc_SetOperationMode (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_SetOperationMode_t * *reqArg*)

Set Operation Mode pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.5 int pack_loc_SLQSLOCGetBestAvailPos (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_SLQSLOCGetBestAvailPos_t * *reqArg*)

Get Best Avail position pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.6 int pack_loc_SLQSLOCGetOpMode (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, void * *reqArg*)

Pack Get Operation mode.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.7 int pack_loc_SLQSLOCGetServer (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_SLQSLOCGetServer_t * *reqArg*)

Pack get server.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

The request is acknowledged through the response, but the SUCCESS/FAILURE status is sent through unpack_loc_GetServer_Ind callback If successful, the callback also contains the A-GPS server address.

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.8 int pack_loc_SLQSLOCInjectPosition (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_SLQSLOCInjectPosition_t * *reqArg*)

Pack inject position.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.9 int pack_loc_SLQSLOCInjectSensorData (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_SLQSLOCInjectSensorData_t * *reqArg*)

Pack inject sensor data.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.10 int pack_loc_SLQSLOCInjectUTCTime (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_SLQSLOCInjectUTCTime_t * *reqArg*)

Pack inject UTC time.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.11 int pack_loc_SLQSLOCSetCradleMountConfig (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_SLQSLOCSetCradleMountConfig_t * *reqArg*)

Pack set cradle mount configure.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.12 int pack_loc_SLQSLOCSetServer (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_SLQSLOCSetServer_t * *reqArg*)

Pack Set server.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

If multiple types of addresses are specified in the request, the IPv4 address takes precedence over the IPv6 address and the IPv6 address takes precedence over the URL address.The request is acknowledged through the response, but the SUCCESS/FAILURE status is sent through unpack_loc_SetServer_Ind callback

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.13 int pack_loc_Start (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_Start_t * *reqArg*)

LOC Start pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.14 int pack_loc_Stop (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_loc_Stop_t * *reqArg*)

Loc Stop pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.15 int unpack_loc_BestAvailPos_Ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_BestAvailPos_Ind_t * *pOutput*)

Loc Best Avial position Indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.16 int unpack_loc_CradleMountCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_CradleMountCallback_Ind_t * *pOutput*)

Unpack the Cradle Mount Indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.17 int unpack_loc_DeleteAssistData (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_Delete_Assist_Data_t * *pOutput*)

Delete Assistant Data unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.18 int unpack_loc_DeleteAssistData_Ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_DeleteAssistData_Ind_t * *pOutput*)

Unpack the status of delete the location engine assistance data

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.19 int unpack_loc_EngineState_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_EngineState_Ind_t** * *pOutput*)

Loc Engine State Indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.20 int unpack_loc_EventNMEA_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_EventNMEA_Ind_t** * *pOutput*)

Unpack the NMEA Event Indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.21 int unpack_loc_EventRegister (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_EventRegister_t** * *pOutput*)

Event Register unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.22 int unpack_loc_EventTimeSyncCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_EventTimeSyncCallback_Ind_t** * *pOutput*)

Unpack the Event Time Sync indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.23 int unpack_loc_GetOpMode_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_GetOpMode_Ind_t** * *pOutput*)

Unpack the Set Server Indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.24 int unpack_loc_GetServer_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_GetServer_Ind_t** * *pOutput*)

Unpack the Get Server Indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.25 int unpack_loc_GnssSvInfo_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_GnssSvInfo_Ind_t** * *pOutput*)

Unpack the GNSS SV Info Indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.26 int unpack_loc_InjectPositionCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_InjectPositionCallback_Ind_t** * *pOutput*)

Unpack the Inject position indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.27 int unpack_loc_InjectSensorDataCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_InjectSensorDataCallback_Ind_t** * *pOutput*)

Unpack the inject sensor data indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.28 int unpack_loc_InjectTimeSyncDataCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_InjectTimeSyncDataCallback_Ind_t** * *pOutput*)

Unpack the inject time sync data indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.29 int unpack_loc_InjectUTCTimeCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_InjectUTCTimeCallback_Ind_t** * *pOutput*)

Unpack the Inject UTC time indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.30 int unpack_loc_PositionRpt_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_PositionRpt_Ind_t** * *pOutput*)

Loc Position Report Indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.31 int unpack_loc_SensorStreamingCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SensorStreamingCallback_Ind_t * *pOutput*)

Unpack the Sensor streaming status indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.32 int unpack_loc_SetExtPowerConfig_Ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SetExtPowerConfig_Ind_t * *pOutput*)

Loc Set External Power Configure Indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.33 int unpack_loc_SetExtPowerState (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SetExtPowerState_t * *pOutput*)

Set Ext Power State unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.34 int unpack_loc_SetOperationMode (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_SetOperationMode_t** * *pOutput*)

Set Operation Mode unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.35 int unpack_loc_SetOperationMode_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_SetOperationMode_Ind_t** * *pOutput*)

Unpack the engine to use the specified operation mode.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.36 int unpack_loc_SetServer_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_loc_SetServer_Ind_t** * *pOutput*)

Unpack the Set Server Indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.37 int unpack_loc_SLQSLOCGetBestAvailPos (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SLQSLOCGetBestAvailPos_t * *pOutput*)

Get Best Avail position unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.38 int unpack_loc_SLQSLOCGetOpMode (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SLQSLOCGetOpMode_t * *pOutput*)

Get Operation mode unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.39 int unpack_loc_SLQSLOCGetServer (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SLQSLOCGetServer_t * *pOutput*)

Unpack get server.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.40 int unpack_loc_SLQSLOCInjectPosition (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SLQSLOCInjectPosition_t * *pOutput*)

Unpack inject position.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.41 int unpack_loc_SLQSLOCInjectSensorData (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SLQSLOCInjectSensorData_t * *pOutput*)

Unpack inject sensor data.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.42 int unpack_loc_SLQSLOCInjectUTCTime (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SLQSLOCInjectUTCTime_t * *pOutput*)

Unpack inject UTC time.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.43 int unpack_loc_SLQSLOCSetCradleMountConfig (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_SLQSLOCSetCradleMountConfig_t * *pOutput*)

Unpack set cradle mount configure.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.44 int unpack_loc_SLQSLOCSetServer (uint8_t * *pResp*, uint16_t *respLen*)

Unpack set server.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.45 int unpack_loc_Start (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_Start_t * *pOutput*)

Loc Start unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.5.4.46 int unpack_loc_Stop (uint8_t * *pResp*, uint16_t *respLen*, unpack_loc_Stop_t * *pOutput*)

Loc Stop unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6 nas.h File Reference

Data Structures

- struct unpack_nas_GetSignalStrengths_t
- struct unpack_nas_SLQSGetSysSelectionPref_t
- struct nas_netSelectionPref
- struct nas_acqOrderPref
- struct nas_CSGID
- struct pack_nas_SLQSSetSysSelectionPref_t
- struct nas_lteBandPrefExt
- struct nas_ciotAcqOrderPref
- struct nas_nr5gBandPref
- struct pack_nas_SLQSSetSysSelectionPrefExt_t
- struct pack_nas_SLQSSetBandPreference_t
- struct pack_nas_SLQSNasIndicationRegisterExt_t
- struct RFBandInfoElements
- struct unpack_nas_GetRFInfo_t
- struct cdmaSSInfo
- struct hdrSSInfo
- struct lteSSInfo
- struct tdscdmaSigInfoExt
- struct unpack_nas_SLQSNasGetSigInfo_t
- struct unpack_nas_SLQSNasSigInfoCallback_ind_t
- struct unpack_nas_GetHomeNetwork_t
- struct nas_SrvStatusInfo
- struct nas_GSMSrvStatusInfo
- struct nas_sysInfoCommon

- struct nas_CDMASysInfo
- struct nas_HDRSysInfo
- struct nas_GSMSysInfo
- struct nas_WCDMASysInfo
- struct nas_LTESysInfo
- struct nas_AddCDMASysInfo
- struct nas_AddSysInfo
- struct nas_CallBarringSysInfo
- struct nas_LteCiotOpModeTlv
- struct nas_NR5GSerStatTlv
- struct nas_NR5GSystemInfoTlv
- struct nas_NR5GCellStatusTlv
- struct unpack_nas_SLQSGetSysInfo_t
- struct unpack_nas_SLQSSysInfoCallback_ind_t
- struct unpack_nas_GetServingNetwork_t
- struct unpack_nas_GetServingNetworkCapabilities_t
- struct nas_QmiNas3GppNetworkInfo
- struct nas_QmiNas3GppNetworkRAT
- struct nas_QmisNasPcsDigit
- struct nas_QmisNasSlqsNasPCICellInfo
- struct nas_QmisNasSlqsNasPCIInfo
- struct nas_lteOpModeTlv
- struct unpack_nas_PerformNetworkScan_t
- struct unpack_nas_SLQSSwiGetLteCQI_t
- struct nas_CommInfo
- struct nas_LTEInfo
- struct unpack_nas_SLQSNasSwiModemStatus_t
- struct nas_servSystem
- struct nas_dataSrvCapabilities
- struct nas_currentPLMN
- struct nas_roamIndList
- struct nas_qaQmi3Gpp2TimeZone
- struct nas_detailSvcInfo
- struct nas_CDMASysInfoExt
- struct nas_callBarStatus
- struct unpack_nas_SLQSGetServingSystem_t
- struct nas_rxSignalStrengthListElement
- struct nas_ecioListElement
- struct nas_errorRateListElement
- struct nas_rsrqInformation
- struct nas_lteSnrinformation
- struct nas_lteRsrpinformation
- struct unpack_nas_SLQSGetSignalStrength_t
- struct nas_SLQSSignalStrengthsIndReq
- struct pack_nas_SLQSSetSignalStrengthsCallback_t
- struct nas_SLQSSignalStrengthsInformation
- struct nas_RejectReasonTlv
- struct nas_SignalStrengthTlv
- struct nas_RFInfoTlv
- struct nas_SLQSSignalStrengthsTlv
- struct unpack_nas_SetEventReportInd_t
- struct unpack_nas_GetCDMANetworkParameters_t
- struct unpack_nas_GetANAAAAuthenticationStatus_t
- struct unpack_nas_GetACCOLC_t
- struct pack_nas_SetACCOLC_t

- struct nas_CDMARSSIThresh
- struct nas_CDMAECIOThresh
- struct nas_HDRRSSIThresh
- struct nas_HDRECIOThresh
- struct nas_HDRSINRThreshold
- struct nas_HDRIOThresh
- struct nas_GSMRSSIThresh
- struct nas_WCDMARSSIThresh
- struct nas_WCDMAECIOThresh
- struct nas_LTERSSIThresh
- struct nas_LTESNRThreshold
- struct nas_LTERSRQThresh
- struct nas_LTERSRPThresh
- struct nas_LTESigRptConfig
- struct nas_TDSCDMARSCPThresh
- struct nas_TDSCDMARSSIThresh
- struct nas_TDSCDMAECIOThresh
- struct nas_TDSCDMASINRThresh
- struct pack_nas_SLQSNasConfigSigInfo2_t
- struct unpack_nas_SetDataCapabilitiesCallback_ind_t
- struct unpack_nas_GetNetworkPreference_t
- struct pack_nas_SetNetworkPreference_t
- struct unpack_nas_SetNetworkPreference_t
- struct unpack_nas_SetRoamingIndicatorCallback_ind_t
- struct NASServingSystemInfo
- struct unpack_nas_SetServingSystemCallback_ind_t
- struct NASPhyCaAggScellIndType
- struct NASPhyCaAggScellDlBw
- struct NASPhyCaAggScellInfo
- struct NASPhyCaAggPcellInfo
- struct NASPhyCaAggScellIndex
- struct NASPhyCaAggScellArray
- struct NasGetLTECphyCaInfo
- struct unpack_nas_SlqsGetLTECphyCAInfo_t
- struct NASEmergencyModeTlv
- struct NASModePreferenceTlv
- struct NASBandPreferenceTlv
- struct NASPRLPreferenceTlv
- struct NASRoamPreferenceTlv
- struct NASLTEBandPreferenceTlv
- struct NASNetSelPreferenceTlv
- struct NASServDomainPrefTlv
- struct NASGWAcqOrderPrefTlv
- struct NASAcqOrderPrefTlv
- struct NASRatDisabledMaskTlv
- struct NASCiotLteOpModePrefTlv
- struct NASLteM1BandPrefTlv
- struct NASLteNB1BandPrefTlv
- struct NASCiotAcqOrderPrefTlv
- struct NASNr5gBandPrefTlv
- struct NASQmiCbkNasSystemSelPrefInd
- struct unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t
- struct NASOTAMessageTlv
- struct NASLteNasReleaseInfoTlv
- struct NASTimeInfoTlv

- struct NASQmiCbkNasSwiOTAMessageInd
- struct unpack_nas_SLQSNasSwiOTAMessageCallback_ind_t
- struct nas_MNRInfo
- struct pack_nas_SLQSInitiateNetworkRegistration_t
- struct pack_nas_SLQSNasSwiIndicationRegister_t
- struct pack_nas_SLQSGetPLMNName_t
- struct unpack_nas_SLQSGetPLMNName_t
- struct nas_nmrCellInfo
- struct nas_GERANInfo
- struct nas_geranInstInfo
- struct nas_UMTSinstInfo
- struct nas_UMTSInfo
- struct nas_CDMAInfo
- struct nas_cellParams
- struct nas_LTEInfoIntrafreq
- struct nas_infoInterFreq
- struct nas_LTEInfoInterfreq
- struct nas_gsmCellInfo
- struct nas_lteGsmCellInfo
- struct nas_LTEInfoNeighboringGSM
- struct nas_wcdmaCellInfo
- struct nas_lteWcdmaCellInfo
- struct nas_LTEInfoNeighboringWCDMA
- struct nas_umtsLTENbrCell
- struct nas_WCDMAInfoLTENeighborCell
- struct unpack_nas_SLQSNasGetCellLocationInfo_t
- struct nas_timeInfo
- struct unpack_nas_SLQSGetNetworkTime_t
- struct nas_UniversalTime
- struct unpack_nas_SLQSNasNetworkTimeCallBack_ind_t
- struct nas_PhyCaAggScellIndType
- struct nas_PhyCaAggScellDlBw
- struct nas_PhyCaAggScellInfo
- struct nas_PhyCaAggPcellInfo
- struct nas_PhyCaAggScellIndex
- struct unpack_nas_SetNasLTECphyCaIndCallback_ind_t
- struct nas_RxSigInfo
- struct nas_SccRxInfo
- struct unpack_nas_SLQSSwiGetLteSccRxInfo_t
- struct unpack_nas_SLQSNasTimerCallback_ind_t
- struct pack_nas_InitiateDomainAttach_t
- struct pack_nas_SetCDMANetworkParameters_t
- struct unpack_nas_SLQSNasGetHDRColorCode_t
- struct pack_nas_SLQSNasGetTxRxInfo_t
- struct nas_rxInfo
- struct nas_txInfo
- struct unpack_nas_SLQSNasGetTxRxInfo_t
- struct nas_OperatorPLMNData
- struct nas_operatorPLMNList
- struct nas_serviceProviderName
- struct nas_PLMNNetworkNameData
- struct nas_PLMNNetworkName
- struct nas_operatorNameString
- struct unpack_nas_SLQSGetOperatorNameData_t
- struct pack_nas_SLQSNasGet3GPP2Subscription_t

- struct nas_namName
- struct nas_dirNum
- struct nas_sidNid
- struct nas_homeSIDNID
- struct nas_minBasedIMSI
- struct nas_trueIMSI
- struct nas_CDMAChannel
- struct unpack_nas_SLQSNasGet3GPP2Subscription_t
- struct nas_protocolSubtypeElement
- struct unpack_nas_SLQSSwiGetHDRPersonality_t
- struct unpack_nas_SLQSSwiGetHDRProtSubtype_t
- struct pack_nas_SLQSSwiPSDetach_t
- struct unpack_nas_SLQSGetErrorRate_t
- struct nas_DRCParams
- struct nas_PilotSetParams
- struct nas_PilotSetData
- struct unpack_nas_SLQSSwiGetHRPDStats_t
- struct nas_ActPilotPNElement
- struct nas_NetworkStat1x
- struct nas_NetworkStatEVDO
- struct nas_DeviceConfigDetail
- struct nas_DataStatusDetail
- struct unpack_nas_SLQSSwiNetworkDebug_t
- struct nas_RSSIThresh
- struct nas_ECIOThresh
- struct nas_HDRSINRThresh
- struct nas_LTESNRThresh
- struct nas_IOThresh
- struct nas_RSRQThresh
- struct nas_RSRPThresh
- struct nas_LTESigRptCfg
- struct nas_TDSCDMASINRCONFThresh
- struct pack_nas_SLQSConfigSigInfo_t
- struct unpack_nas_GetHomeNetwork3GPP2_t
- struct nas_wcdmaUARFCN
- struct nas_lteEARFCN
- struct nas_ltePCI
- struct pack_nas_SLQSNASSwiSetChannelLock_t
- struct unpack_nas_SLQSNASSwiGetChannelLock_t
- struct unpack_nas_SLQSNASGeteDRXParams_t
- struct pack_nas_SLQSNASGeteDRXParamsExt_t
- struct unpack_nas_SLQSNASGeteDRXParamsExt_t
- struct pack_nas_SLQSNASSeteDRXParams_t
- struct nas_HDRPersonality_Ind_Data
- struct unpack_nas_SLQSSwiHDRPersonalityCallback_Ind_t
- struct nas_RankIndicatorTlv
- struct unpack_nas_SLQSSwiRandIndicatorCallback_Ind_t
- struct nas_RFBandInfoElements
- struct nas_RfDedicatedBandInfoElements
- struct nas_RfBandInfoExtFormatElements
- struct nas_RfBandwidthInfoElements
- struct nas_RfBandInfoList
- struct nas_RfDedicatedBandInfo
- struct nas_RfBandInfoExtFormat
- struct nas_RfBandwidthInfo

- struct nas_LTEOperationMode
- struct unpack_nas_SLQSNasGetRFInfo_t
- struct nas_EmerModeTlv
- struct nas_ModePrefTlv
- struct nas_BandPrefTlv
- struct nas_PRLPrefTlv
- struct nas_RoamPrefTlv
- struct nas_LTEBandPrefTlv
- struct nas_NetSelPrefTlv
- struct nas_SrvDomainPrefTlv
- struct nas_GWAcqOrderPrefTlv
- struct nas_AcqOrderPrefTlv
- struct nas_RatDisabledMaskTlv
- struct nas_CiotLteOpModePrefTlv
- struct nas_LteM1BandPrefTlv
- struct nas_LteNb1BandPrefTlv
- struct nas_CiotAcqOrderPrefTlv
- struct nas_BandPrefInfoTlv
- struct unpack_nas_SLQSGetSysSelectionPrefExt_t
- struct pack_nas_PerformNetworkScanPCI_t
- struct nas_EdrxEnableType
- struct nas_EdrxCycleLength
- struct nas_EdrxPagingTimeWindow
- struct nas_EdrxRatType
- struct nas_EdrxCiotLteMode
- struct unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t
- struct nas_CsgId
- struct nas_PlmnID
- struct nas_LteOpMode
- struct unpack_nas_SLQSNasNetworkRejectCallback_Ind_t
- struct nas_ForbiddenNetworks3GPP
- struct unpack_nas_SLQSNASGetForbiddenNetworks_t

Macros

- #define NAS_OTA_MESSAGE_MAX_BUF_SIZE 2048
- #define NAS_MAX_NUM_NETWORKS 30
- #define NAS_MAX_DESCRIPTION_LENGTH 255
- #define NAS_PLMN_LENGTH 3
- #define NAS_MAX_SCC_RX_INFO_INSTANCES 255
- #define NAS_NAM_NAME_LENGTH 12
- #define NAS_IMSI_M_S1_LENGTH 7
- #define NAS_IMSI_M_S2_LENGTH 3
- #define NAS_SERVING_SYSTEM_INFO_MAX_RADIO_INTERFACE_LIST 255
- #define NAS_MAX_SLQS_NAS_PCI_INFO_PLMN_LENGTH 255
- #define NAS_MAX_SLQS_NAS_PCI_INFO_LENGTH 255
- #define NAS_MCC_MNC_INST_LENGTH 255
- #define LITE_NW_SCAN_LTE_OP_MODE_MAX_LENGTH 255
- #define NAS_MAX_PHY_CA_AGG_SCELL_ARRRY_SIZE 255

Typedefs

- typedef unpack_result_t unpack_nas_SLQSSetSysSelectionPref_t
- typedef unpack_result_t unpack_nas_SLQSSetSysSelectionPrefExt_t
- typedef unpack_result_t unpack_nas_SLQSSetBandPreference_t
- typedef unpack_result_t unpack_nas_SLQSNasIndicationRegisterExt_t
- typedef unpack_result_t unpack_nas_SLQSSetSignalStrengthsCallback_t
- typedef unpack_result_t unpack_nas_SetRFInfoCallback_t
- typedef unpack_result_t unpack_nas_SetLURejectCallback_t
- typedef unpack_result_t unpack_nas_SetACCOLC_t
- typedef unpack_result_t unpack_nas_SLQSNasConfigSigInfo2_t
- typedef unpack_result_t unpack_nas_SLQSInitiateNetworkRegistration_t
- typedef unpack_result_t unpack_nas_SLQSNasSwiIndicationRegister_t
- typedef unpack_result_t unpack_nas_InitiateDomainAttach_t
- typedef unpack_result_t unpack_nas_SetCDMANetworkParameters_t
- typedef unpack_result_t unpack_nas_SLQSSwiPSDetach_t
- typedef unpack_result_t unpack_nas_SLQSConfigSigInfo_t
- typedef unpack_result_t unpack_nas_SLQSNASSwiSetChannelLock_t
- typedef unpack_result_t unpack_nas_SLQSNASSeteDRXParams_t
- typedef nas_BandPrefInfoTlv nas_NR5gBandPrefTlv
- typedef nas_BandPrefInfoTlv nas_LTEBandPrefExtTlv

Enumerations

- enum LITEQMI_NAS_LTE_CPHY_SCELL_STATE {
  eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_DECONFIGURED =0x00,
  eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED =0x01,
  eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED =0x02 }
- enum LITEQMI_NAS_LTE_CPHY_CA_BW_NRB {
  eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_6 =0x00,
  eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_15 =0x01,
  eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_25 =0x02,
  eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_50 =0x03,
  eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_75 =0x04,
  eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_100 =0x05 }
- enum LITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND {

eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_1 = 120,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_2 = 121,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_3 = 122,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_4 = 123,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_5 = 124,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_6 = 125,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_7 = 126,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_8 = 127,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_9 = 128,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_10 = 129,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_11 = 130,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_12 = 131,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_13 = 132,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_14 = 133,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_17 = 134,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_33 = 135,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_34 = 136,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_35 = 137,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_36 = 138,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_37 = 139,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_38 = 140,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_39 = 141,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_40 = 142,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_18 = 143,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_19 = 144,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_20 = 145,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_21 = 146,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_24 = 147,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_25 = 148,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_41 = 149,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_42 = 150,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_43 = 151,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_23 = 152,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_26 = 153,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_32 = 154,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_125 = 155,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_126 = 156,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_127 = 157,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_28 = 158,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_29 = 159,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_30 = 160,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_66 = 161,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_250 = 162,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_46 = 163,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_27 = 164,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_31 = 165,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_71 = 166,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_47 = 167,
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_48 = 168 }

- enum NAS_LTE_CPHY_CA_BW_NRB_LITE {
  eNAS_LTE_CPHY_CA_BW_NRB_LITE_6 =0x00,
  eNAS_LTE_CPHY_CA_BW_NRB_LITE_15 =0x01,
  eNAS_LTE_CPHY_CA_BW_NRB_LITE_25 =0x02,
  eNAS_LTE_CPHY_CA_BW_NRB_LITE_50 =0x03,
  eNAS_LTE_CPHY_CA_BW_NRB_LITE_75 =0x04,
  eNAS_LTE_CPHY_CA_BW_NRB_LITE_100 =0x05 }

- enum NAS_LTE_CPHY_SCELL_STATE_LITE {

eNAS_LTE_CPHY_SCELL_STATE_DECONFIGURED_LITE =0x00,
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED_LITE =0x01,
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED_LITE =0x02 }

- enum LITE_TYPE_OF_SERVICE_DOMAIN {
  LITE_SYS_SRV_DOMAIN_NO_SRV = 0x00,
  LITE_SYS_SRV_DOMAIN_CS_ONLY = 0x01,
  LITE_SYS_SRV_DOMAIN_PS_ONLY = 0x02,
  LITE_SYS_SRV_DOMAIN_CS_PS = 0x03,
  LITE_SYS_SRV_DOMAIN_CAMPED = 0x04 }

Functions

- int unpack_nas_GetSignalStrengths (uint8_t *pResp, uint16_t respLen, unpack_nas_GetSignalStrengths_t *pOutput)
- int pack_nas_GetSignalStrengths (pack_qmi_t *pCtx, uint8_t *pReq, uint16_t *pLen)
- int pack_nas_SLQSGetSysSelectionPref (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSGetSysSelectionPref (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSGetSysSelectionPref_t *pOutput)
- int pack_nas_SLQSSetSysSelectionPref (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSSetSysSelectionPref_t *pReqParam)
- int unpack_nas_SLQSSetSysSelectionPref (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSetSysSelectionPref_t *pOutput)
- int pack_nas_SLQSSetSysSelectionPrefExt (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSSetSysSelectionPrefExt_t *pReqParam)
- int unpack_nas_SLQSSetSysSelectionPrefExt (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSetSysSelectionPrefExt_t *pOutput)
- int pack_nas_SLQSSetBandPreference (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSSetBandPreference_t *pReqParam)
- int unpack_nas_SLQSSetBandPreference (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSetBandPreference_t *pOutput)
- int pack_nas_SLQSNasIndicationRegisterExt (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSNasIndicationRegisterExt_t *pReqParam)
- int unpack_nas_SLQSNasIndicationRegisterExt (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasIndicationRegisterExt_t *pOutput)
- int pack_nas_GetRFInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_GetRFInfo (uint8_t *pResp, uint16_t respLen, unpack_nas_GetRFInfo_t *pOutput)
- int pack_nas_SLQSNasGetSigInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSNasGetSigInfo (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasGetSigInfo_t *pOutput)
- int unpack_valid_nas_SLQSNasGetSigInfo (uint8_t *pResp, uint8_t u8Info)
- int unpack_nas_SLQSNasSigInfoCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasSigInfoCallback_ind_t *pOutput)
- int unpack_nas_GetHomeNetwork (uint8_t *pResp, uint16_t respLen, unpack_nas_GetHomeNetwork_t *pOutput)
- int pack_nas_GetHomeNetwork (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int pack_nas_SLQSGetSysInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSGetSysInfo (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSGetSysInfo_t *pOutput)
- int unpack_nas_SLQSNasSysInfoCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSysInfoCallback_ind_t *pOutput)
- int pack_nas_GetServingNetwork (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_GetServingNetwork (uint8_t *pResp, uint16_t respLen, unpack_nas_GetServingNetwork_t *pOutput)
- int pack_nas_GetServingNetworkCapabilities (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_GetServingNetworkCapabilities (uint8_t *pResp, uint16_t respLen, unpack_nas_GetServingNetworkCapabilities_t *pOutput)

- int pack_nas_PerformNetworkScan (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_PerformNetworkScan (uint8_t *pResp, uint16_t respLen, unpack_nas_PerformNetwork-Scan_t *pOutput)
- int pack_nas_SLQSSwiGetLteCQI (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSSwiGetLteCQI (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSwiGetLteCQI_t *pOutput)
- int pack_nas_SLQSNasSwiModemStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSNasSwiModemStatus (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasSwi-ModemStatus_t *pOutput)
- int pack_nas_SLQSGetServingSystem (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSGetServingSystem (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSGetServing-System_t *pOutput)
- int unpack_valid_nas_SLQSGetServingSystem (uint8_t *pResp, uint8_t u8Info)
- int pack_nas_SLQSGetSignalStrength (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, uint16_t req-Mask)
- int unpack_nas_SLQSGetSignalStrength (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSGetSignal-Strength_t *pOutput)
- int unpack_valid_nas_SLQSGetSignalStrength (uint8_t *pResp, uint8_t u8Info)
- int pack_nas_SLQSSetSignalStrengthsCallback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack-_nas_SLQSSetSignalStrengthsCallback_t *pReqParam)
- int unpack_nas_SLQSSetSignalStrengthsCallback (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQS-SetSignalStrengthsCallback_t *pOutput)
- int pack_nas_SetRFInfoCallback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, uint8_t *pBenable)
- int unpack_nas_SetRFInfoCallback (uint8_t *pResp, uint16_t respLen, unpack_nas_SetRFInfoCallback_t *p-Output)
- int pack_nas_SetLURejectCallback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, uint8_t *p-Benable)
- int unpack_nas_SetLURejectCallback (uint8_t *pResp, uint16_t respLen, unpack_nas_SetLUReject-Callback_t *pOutput)
- int unpack_nas_SetEventReportInd (uint8_t *pResp, uint16_t respLen, unpack_nas_SetEventReportInd_t *pOutput)
- int pack_nas_GetCDMANetworkParameters (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_GetCDMANetworkParameters (uint8_t *pResp, uint16_t respLen, unpack_nas_GetCDMA-NetworkParameters_t *pOutput)
- int unpack_valid_nas_GetCDMANetworkParameters (uint8_t *pResp, uint8_t u8Info)
- int pack_nas_GetANAAAAuthenticationStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_GetANAAAAuthenticationStatus (uint8_t *pResp, uint16_t respLen, unpack_nas_GetANAA-AAuthenticationStatus_t *pOutput)
- int pack_nas_GetACCOLC (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_GetACCOLC (uint8_t *pResp, uint16_t respLen, unpack_nas_GetACCOLC_t *pOutput)
- int pack_nas_SetACCOLC (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SetACCOLC_t reqParam)
- int unpack_nas_SetACCOLC (uint8_t *pResp, uint16_t respLen, unpack_nas_SetACCOLC_t *pOutput)
- int pack_nas_SLQSNasConfigSigInfo2 (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_S-LQSNasConfigSigInfo2_t *pReqParam)
- int unpack_nas_SLQSNasConfigSigInfo2 (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasConfig-SigInfo2_t *pOutput)
- int unpack_nas_SetDataCapabilitiesCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SetData-CapabilitiesCallback_ind_t *pOutput)
- int pack_nas_GetNetworkPreference (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_GetNetworkPreference (uint8_t *pResp, uint16_t respLen, unpack_nas_GetNetwork-Preference_t *pOutput)
- int pack_nas_SetNetworkPreference (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_Set-NetworkPreference_t *reqArg)
- int unpack_nas_SetNetworkPreference (uint8_t *pResp, uint16_t respLen, unpack_nas_SetNetwork-Preference_t *pOutput)

- int unpack_nas_SetRoamingIndicatorCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SetRoamingIndicatorCallback_ind_t *pOutput)
- int unpack_nas_SetServingSystemCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SetServingSystemCallback_ind_t *pOutput)
- int pack_nas_SlqsGetLTECphyCAInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SlqsGetLTECphyCAInfo (uint8_t *pResp, uint16_t respLen, unpack_nas_SlqsGetLTECphyCAInfo_t *pOutput)
- int unpack_nas_SLQSSetSysSelectionPrefCallBack_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t *pOutput)
- int unpack_nas_SLQSNasSwiOTAMessageCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasSwiOTAMessageCallback_ind_t *pOutput)
- int pack_nas_SLQSInitiateNetworkRegistration (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSInitiateNetworkRegistration_t *pReqParam)
- int unpack_nas_SLQSInitiateNetworkRegistration (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSInitiateNetworkRegistration_t *pOutput)
- int pack_nas_SLQSNasSwiIndicationRegister (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSNasSwiIndicationRegister_t *pReqParam)
- int unpack_nas_SLQSNasSwiIndicationRegister (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasSwiIndicationRegister_t *pOutput)
- int pack_nas_SLQSGetPLMNName (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSGetPLMNName_t *reqArg)
- int unpack_nas_SLQSGetPLMNName (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSGetPLMNName_t *pOutput)
- int pack_nas_SLQSNasGetCellLocationInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSNasGetCellLocationInfo (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasGetCellLocationInfo_t *pOutput)
- int pack_nas_SLQSGetNetworkTime (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSGetNetworkTime (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSGetNetworkTime_t *pOutput)
- int unpack_nas_SLQSNasNetworkTimeCallBack_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasNetworkTimeCallBack_ind_t *pOutput)
- int unpack_nas_SetNasLTECphyCaIndCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SetNasLTECphyCaIndCallback_ind_t *pOutput)
- int pack_nas_SLQSSwiGetLteSccRxInfo (pack_qmi_t *pCtx, uint8_t *pReq, uint16_t *pLen)
- int unpack_nas_SLQSSwiGetLteSccRxInfo (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSwiGetLteSccRxInfo_t *pOutput)
- int unpack_nas_SLQSNasTimerCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasTimerCallback_ind_t *pOutput)
- int pack_nas_InitiateDomainAttach (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_InitiateDomainAttach_t *pReqParam)
- int unpack_nas_InitiateDomainAttach (uint8_t *pResp, uint16_t respLen, unpack_nas_InitiateDomainAttach_t *pOutput)
- int pack_nas_SetCDMANetworkParameters (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SetCDMANetworkParameters_t *pReqParam)
- int unpack_nas_SetCDMANetworkParameters (uint8_t *pResp, uint16_t respLen, unpack_nas_SetCDMANetworkParameters_t *pOutput)
- int pack_nas_SLQSNasGetHDRColorCode (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSNasGetHDRColorCode (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasGetHDRColorCode_t *pOutput)
- int pack_nas_SLQSNasGetTxRxInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSNasGetTxRxInfo_t *reqArg)
- int unpack_nas_SLQSNasGetTxRxInfo (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasGetTxRxInfo_t *pOutput)
- int pack_nas_SLQSGetOperatorNameData (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSGetOperatorNameData (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSGetOperatorNameData_t *pOutput)

- int pack_nas_SLQSNasGet3GPP2Subscription (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSNasGet3GPP2Subscription_t *reqArg)
- int unpack_nas_SLQSNasGet3GPP2Subscription (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasGet3GPP2Subscription_t *pOutput)
- int pack_nas_SLQSSwiGetHDRPersonality (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSSwiGetHDRPersonality (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSwiGetHDRPersonality_t *pOutput)
- int pack_nas_SLQSSwiGetHDRProtSubtype (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSSwiGetHDRProtSubtype (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSwiGetHDRProtSubtype_t *pOutput)
- int pack_nas_SLQSSwiPSDetach (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSSwiPSDetach_t *pReqParam)
- int unpack_nas_SLQSSwiPSDetach (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSwiPSDetach_t *pOutput)
- int pack_nas_SLQSGetErrorRate (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSGetErrorRate (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSGetErrorRate_t *pOutput)
- int pack_nas_SLQSSwiGetHRPDStats (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSSwiGetHRPDStats (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSwiGetHRPDStats_t *pOutput)
- int pack_nas_SLQSSwiNetworkDebug (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSSwiNetworkDebug (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSwiNetworkDebug_t *pOutput)
- int pack_nas_SLQSConfigSigInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSConfigSigInfo_t *pReqParam)
- int unpack_nas_SLQSConfigSigInfo (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSConfigSigInfo_t *pOutput)
- int pack_nas_GetHomeNetwork3GPP2 (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_GetHomeNetwork3GPP2 (uint8_t *pResp, uint16_t respLen, unpack_nas_GetHomeNetwork3GPP2_t *pOutput)
- int pack_nas_SLQSNASSwiSetChannelLock (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSNASSwiSetChannelLock_t *pReqParam)
- int unpack_nas_SLQSNASSwiSetChannelLock (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNASSwiSetChannelLock_t *pOutput)
- int pack_nas_SLQSNASSwiGetChannelLock (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSNASSwiGetChannelLock (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNASSwiGetChannelLock_t *pOutput)
- int pack_nas_SLQSNASGeteDRXParams (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSNASGeteDRXParams (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNASGeteDRXParams_t *pOutput)
- int pack_nas_SLQSNASGeteDRXParamsExt (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSNASGeteDRXParamsExt_t *pReqParam)
- int unpack_nas_SLQSNASGeteDRXParamsExt (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNASGeteDRXParamsExt_t *pOutput)
- int pack_nas_SLQSNASSeteDRXParams (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_SLQSNASSeteDRXParams_t *pReqParam)
- int unpack_nas_SLQSNASSeteDRXParams (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNASSeteDRXParams_t *pOutput)
- int unpack_nas_SLQSSwiHDRPersonalityCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSwiHDRPersonalityCallback_Ind_t *pOutput)
- int unpack_nas_SLQSSwiRandIndicatorCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSSwiRandIndicatorCallback_Ind_t *pOutput)
- int pack_nas_SLQSNasGetRFInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSNasGetRFInfo (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasGetRFInfo_t *pOutput)
- int pack_nas_SLQSGetSysSelectionPrefExt (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)

- int unpack_nas_SLQSGetSysSelectionPrefExt (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSGetSysSelectionPrefExt_t *pOutput)
- int pack_nas_PerformNetworkScanPCI (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_nas_PerformNetworkScanPCI_t *pReqParam)
- int unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t *pOutput)
- int unpack_nas_SLQSNasNetworkRejectCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNasNetworkRejectCallback_Ind_t *pOutput)
- int pack_nas_SLQSNASGetForbiddenNetworks (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_nas_SLQSNASGetForbiddenNetworks (uint8_t *pResp, uint16_t respLen, unpack_nas_SLQSNASGetForbiddenNetworks_t *pOutput)

9.6.1 Macro Definition Documentation

9.6.1.1 #define LITE_NW_SCAN_LTE_OP_MODE_MAX_LENGTH 255

9.6.1.2 #define NAS_IMSI_M_S1_LENGTH 7

9.6.1.3 #define NAS_IMSI_M_S2_LENGTH 3

9.6.1.4 #define NAS_MAX_DESCRIPTION_LENGTH 255

9.6.1.5 #define NAS_MAX_NUM_NETWORKS 30

9.6.1.6 #define NAS_MAX_PHY_CA_AGG_SCELL_ARRRY_SIZE 255

9.6.1.7 #define NAS_MAX_SCC_RX_INFO_INSTANCES 255

9.6.1.8 #define NAS_MAX_SLQS_NAS_PCI_INFO_LENGTH 255

9.6.1.9 #define NAS_MAX_SLQS_NAS_PCI_INFO_PLMN_LENGTH 255

9.6.1.10 #define NAS_MCC_MNC_INST_LENGTH 255

9.6.1.11 #define NAS_NAM_NAME_LENGTH 12

9.6.1.12 #define NAS_OTA_MESSAGE_MAX_BUF_SIZE 2048

9.6.1.13 #define NAS_PLMN_LENGTH 3

9.6.1.14 #define NAS_SERVING_SYSTEM_INFO_MAX_RADIO_INTERFACE_LIST 255

9.6.2 Typedef Documentation

9.6.2.1 typedef nas_BandPrefInfoTlv nas_LTEBandPrefExtTlv

Contain the LTE Band Preference Extended.

- See nas_BandPrefInfoTlv for more information.

9.6.2.2 typedef nas_BandPrefInfoTlv nas_NR5gBandPrefTlv

Contain the NR5G Band Preference.

- See nas_BandPrefInfoTlv for more information.

9.6.2.3 typedef unpack_result_t unpack_nas_InitiateDomainAttach_t

9.6.2.4 typedef unpack_result_t unpack_nas_SetACCOLC_t

9.6.2.5 typedef unpack_result_t unpack_nas_SetCDMANetworkParameters_t

9.6.2.6 typedef unpack_result_t unpack_nas_SetLURejectCallback_t

9.6.2.7 typedef unpack_result_t unpack_nas_SetRFInfoCallback_t

9.6.2.8 typedef unpack_result_t unpack_nas_SLQSConfigSigInfo_t

9.6.2.9 typedef unpack_result_t unpack_nas_SLQSInitiateNetworkRegistration_t

9.6.2.10 typedef unpack_result_t unpack_nas_SLQSNasConfigSigInfo2_t

9.6.2.11 typedef unpack_result_t unpack_nas_SLQSNasIndicationRegisterExt_t

9.6.2.12 typedef unpack_result_t unpack_nas_SLQSNASSeteDRXParams_t

9.6.2.13 typedef unpack_result_t unpack_nas_SLQSNasSwiIndicationRegister_t

9.6.2.14 typedef unpack_result_t unpack_nas_SLQSNASSwiSetChannelLock_t

9.6.2.15 typedef unpack_result_t unpack_nas_SLQSSetBandPreference_t

9.6.2.16 typedef unpack_result_t unpack_nas_SLQSSetSignalStrengthsCallback_t

9.6.2.17 typedef unpack_result_t unpack_nas_SLQSSetSysSelectionPref_t

9.6.2.18 typedef unpack_result_t unpack_nas_SLQSSetSysSelectionPrefExt_t

9.6.2.19 typedef unpack_result_t unpack_nas_SLQSSwiPSDetach_t

9.6.3 Enumeration Type Documentation

9.6.3.1 enum LITE_TYPE_OF_SERVICE_DOMAIN

Enumerator

LITE_SYS_SRV_DOMAIN_NO_SRV
LITE_SYS_SRV_DOMAIN_CS_ONLY
LITE_SYS_SRV_DOMAIN_PS_ONLY
LITE_SYS_SRV_DOMAIN_CS_PS
LITE_SYS_SRV_DOMAIN_CAMPED

9.6.3.2 enum LITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND

Enumerator

eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_1
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_2
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_3
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_4
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_5

eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_6
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_7
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_8
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_9
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_10
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_11
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_12
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_13
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_14
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_17
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_33
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_34
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_35
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_36
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_37
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_38
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_39
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_40
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_18
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_19
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_20
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_21
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_24
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_25
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_41
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_42
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_43
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_23
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_26
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_32
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_125
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_126
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_127
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_28
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_29
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_30
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_66
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_250
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_46
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_27
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_31
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_71
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_47
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_48

9.6.3.3 enum LITEQMI_NAS_LTE_CPHY_CA_BW_NRB

Enumerator

eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_6

eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_15

eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_25

eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_50

eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_75

eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_100

9.6.3.4 enum LITEQMI_NAS_LTE_CPHY_SCELL_STATE

Enumerator

eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_DECONFIGURED

eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED

eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED

9.6.3.5 enum NAS_LTE_CPHY_CA_BW_NRB_LITE

Enumerator

eNAS_LTE_CPHY_CA_BW_NRB_LITE_6

eNAS_LTE_CPHY_CA_BW_NRB_LITE_15

eNAS_LTE_CPHY_CA_BW_NRB_LITE_25

eNAS_LTE_CPHY_CA_BW_NRB_LITE_50

eNAS_LTE_CPHY_CA_BW_NRB_LITE_75

eNAS_LTE_CPHY_CA_BW_NRB_LITE_100

9.6.3.6 enum NAS_LTE_CPHY_SCELL_STATE_LITE

Enumerator

eNAS_LTE_CPHY_SCELL_STATE_DECONFIGURED_LITE

eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED_LITE

eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED_LITE

9.6.4 Function Documentation

9.6.4.1 int pack_nas_GetACCOLC (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Retrieves information about the access overload class (ACCOLC) pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.2 int pack_nas_GetANAAAAuthenticationStatus (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

AN-AAA authentication status of the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.3 int pack_nas_GetCDMANetworkParameters (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Get CDMA Network Parameters pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.4 int pack_nas_GetHomeNetwork (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

get home network pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.5 int pack_nas_GetHomeNetwork3GPP2 (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Get Home Network 3GPP2 Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.6 int pack_nas_GetNetworkPreference (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets the network registration preference pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

9.6.4.7 int pack_nas_GetRFInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

get rf info pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.8 int pack_nas_GetServingNetwork (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Pack provides information about the system that provides service to the device.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.9 int pack_nas_GetServingNetworkCapabilities (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Pack returns information regarding the data capabilities of the system that currently provides service to the device.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.10 int pack_nas_GetSignalStrengths (pack_qmi_t * pCtx, uint8_t * pReq, uint16_t * pLen)

get signal strengths pack. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15-C_05_xx_xx_xx and all EM74xx firmware versions. Please use pack_nas_SLQSNasGetSigInfo() for new firmware versions and new modules

Parameters

in,out	*pCtx*	qmi request context
out	*pReq*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.11 int pack_nas_InitiateDomainAttach (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_InitiateDomainAttach_t * *pReqParam*)

Initiates a domain attach/detach of the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.12 int pack_nas_PerformNetworkScan (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Pack performs scan for available networks and scans for RAT info as well.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.13 int pack_nas_PerformNetworkScanPCI (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_PerformNetworkScanPCI_t * *pReqParam*)

Pack performs scan for available networks and scans for LTE RAT info (specific Network or Scan Type).

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: MC75xx, EM75xx and WP76xx.

9.6.4.14 int pack_nas_SetACCOLC (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SetACCOLC_t *reqParam*)

Pack Sets the access overload class (ACCOLC)

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.15 int pack_nas_SetCDMANetworkParameters (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SetCDMANetworkParameters_t * *pReqParam*)

CDMA Network Parameters pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.16 int pack_nas_SetLURejectCallback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, uint8_t * *pBenable*)

Pack set registration reject Callback

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pBenable*	0/1 value to disable/enable indication respectively

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.17 int pack_nas_SetNetworkPreference (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SetNetworkPreference_t * *reqArg*)

Sets the network registration preference. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use pack_nas_SLQSSetSysSelection-Pref() for new firmware versions and new modules

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

9.6.4.18 int pack_nas_SetRFInfoCallback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, uint8_t * *pBenable*)

Pack Set RF Band Information callback.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pBenable*	0/1 value to disable/enable indication respectively

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.19 int pack_nas_SLQSConfigSigInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSConfigSigInfo_t * *pReqParam*)

Config Sig Info Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.20 int pack_nas_SLQSGetErrorRate (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Get Error Rate Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.21 int pack_nas_SlqsGetLTECphyCAInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Pack get carrier aggregation event information.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

9.6.4.22 int pack_nas_SLQSGetNetworkTime (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Pack Get Network Time.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.23 int pack_nas_SLQSGetOperatorNameData (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Operator Name Data Parameters pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.24 int pack_nas_SLQSGetPLMNName (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSGetPLMNName_t * *reqArg*)

Pack get operator name for specificed network.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.25 int pack_nas_SLQSGetServingSystem (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Pack queries information regarding the system that currently provides service.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.26 int pack_nas_SLQSGetSignalStrength (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, uint16_t *reqMask*)

Queries the current signal strength as measured by the device. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use pack_nas_SLQSNasGetSigInfo() for new firmware versions and new modules

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqMask*	request mask for fetching extra signal info

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.27 int pack_nas_SLQSGetSysInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Pack get system information.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.28 int pack_nas_SLQSGetSysSelectionPref (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Queries the different system selection preferences of the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.29 int pack_nas_SLQSGetSysSelectionPrefExt (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Queries the different system selection preferences of the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.30 int pack_nas_SLQSInitiateNetworkRegistration (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSInitiateNetworkRegistration_t * *pReqParam*)

Pack initiates a network registration.This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use pack_nas_SLQSSetSysSelectionPrefExt() instead for new firmware versions and new modules.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.31 int pack_nas_SLQSNasConfigSigInfo2 (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSNasConfigSigInfo2_t * *pReqParam*)

Pack sets the signal strength reporting thresholds

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.32 int pack_nas_SLQSNasGet3GPP2Subscription (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSNasGet3GPP2Subscription_t * *reqArg*)

3GPP2 Subscription Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.33 int pack_nas_SLQSNasGetCellLocationInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Pack retrieves cell location-related information.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.34 int pack_nas_SLQSNASGeteDRXParams (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Get eDRX Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.35 int pack_nas_SLQSNASGeteDRXParamsExt (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_nas_SLQSNASGeteDRXParamsExt_t * pReqParam)

Get eDRX Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.36 int pack_nas_SLQSNASGetForbiddenNetworks (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Get forbidden networks pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.37 int pack_nas_SLQSNasGetHDRColorCode (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

HDR Color Code Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.38 int pack_nas_SLQSNasGetRFInfo (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Gets radio band/channel information pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.39 int pack_nas_SLQSNasGetSigInfo (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

get sig info pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.40 int pack_nas_SLQSNasGetTxRxInfo (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_nas_SLQSNasGetTxRxInfo_t * reqArg)

Get Tx Rx Info Parameters pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.41 int pack_nas_SLQSNasIndicationRegisterExt (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_nas_SLQSNasIndicationRegisterExt_t * pReqParam)

Pack used to Registers/De-registers for different NAS (Network access service) indications.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

This function is used by a control point to register/deregister for different QMI_NAS indications. The control point's registration state variables, controlling registration for indications, are modified to reflect the settings indicated in the parameters that are present in the request message. At least one optional parameter must be present in the request.

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.42 int pack_nas_SLQSNASSeteDRXParams (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_nas_SLQSNASSeteDRXParams_t * pReqParam)

Set eDRX Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.43 int pack_nas_SLQSNASSwiGetChannelLock (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Get Channel Lock Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.44 int pack_nas_SLQSNasSwiIndicationRegister (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSNasSwiIndicationRegister_t * *pReqParam*)

Pack sets the registration state for different QMI_NAS SWI indications.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.45 int pack_nas_SLQSNasSwiModemStatus (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

This function requests the device to return the current status of modem.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.46 int pack_nas_SLQSNASSwiSetChannelLock (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSNASSwiSetChannelLock_t * *pReqParam*)

Set Channel Lock Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.47 int pack_nas_SLQSSetBandPreference (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSSetBandPreference_t * *pReqParam*)

Pack sets the different system selection preferences of the device.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.48 int pack_nas_SLQSSetSignalStrengthsCallback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSSetSignalStrengthsCallback_t * *pReqParam*)

Pack set signal strength thresholds callback.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request prarmeters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.49 int pack_nas_SLQSSetSysSelectionPref (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSSetSysSelectionPref_t * *pReqParam*)

Sets the different system selection preferences of the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.50 int pack_nas_SLQSSetSysSelectionPrefExt (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_nas_SLQSSetSysSelectionPrefExt_t * *pReqParam*)

Sets the different system selection preferences of the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.51 int pack_nas_SLQSSwiGetHDRPersonality (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

HDR Personality Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.52 int pack_nas_SLQSSwiGetHDRProtSubtype (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

HDR Protocol Sub type Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.53 int pack_nas_SLQSSwiGetHRPDStats (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

HRPD Stats Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.54 int pack_nas_SLQSSwiGetLteCQI (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Pack fetch CQI parameters for LTE data session.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.55 int pack_nas_SLQSSwiGetLteSccRxInfo (pack_qmi_t * pCtx, uint8_t * pReq, uint16_t * pLen)

get LTE Secondary carrier Rx signal level information pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReq*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.56 int pack_nas_SLQSSwiNetworkDebug (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Network Debug Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.57 int pack_nas_SLQSSwiPSDetach (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_nas_SLQSSwiPSDetach_t * pReqParam)

PS Connection Detach Parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request Parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.58 int unpack_nas_GetACCOLC (uint8_t * pResp, uint16_t respLen, unpack_nas_GetACCOLC_t * pOutput)

Retrieves information about the access overload class (ACCOLC) unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.59 int unpack_nas_GetANAAAAuthenticationStatus (uint8_t * pResp, uint16_t respLen, unpack_nas_GetANAAAAuthenticationStatus_t * pOutput)

AN-AAA authentication status of the device unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.60 int unpack_nas_GetCDMANetworkParameters (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_GetCDMANetworkParameters_t * *pOutput*)

Get CDMA Network Parameters unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	qmi output parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.61 int unpack_nas_GetHomeNetwork (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_GetHomeNetwork_t * *pOutput*)

Retrieves information about the home network of the device unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.62 int unpack_nas_GetHomeNetwork3GPP2 (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_GetHomeNetwork3GPP2_t * *pOutput*)

Get Home Network 3GPP2 Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.63 int unpack_nas_GetNetworkPreference (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_GetNetworkPreference_t * *pOutput*)

Gets the network registration preference unpack

Parameters

in	*pResp*	qmi resp from modem
in	*respLen*	qmi resp length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.64 int unpack_nas_GetRFInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_GetRFInfo_t * *pOutput*)

get rf info unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.65 int unpack_nas_GetServingNetwork (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_GetServingNetwork_t * *pOutput*)

Unpack provides information about the system that provides service to the device. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API unpack_nas_SLQSGetSysInfo() for new firmware versions and new modules

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.66 int unpack_nas_GetServingNetworkCapabilities (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_GetServingNetworkCapabilities_t** * *pOutput*)

Unpack returns information regarding the data capabilities of the system that currently provides service to the device.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.67 int unpack_nas_GetSignalStrengths (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_GetSignalStrengths_t** * *pOutput*)

Returns the available signal strengths (in dBm) as measured by the device in an array. This will also provides the corresponding radio interfaces in an array. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use unpack_nas_SLQSNasGetSigInfo() for new firmware versions and new modules

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.68 int unpack_nas_InitiateDomainAttach (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_InitiateDomainAttach_t** * *pOutput*)

Initiates a domain attach/detach of the device unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.69 int unpack_nas_PerformNetworkScan (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_PerformNetworkScan_t** * *pOutput*)

Unpack performs scan for available networks and scans for RAT info as well.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.70 int unpack_nas_SetACCOLC (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SetACCOLC_t** * *pOutput*)

Unpack Sets the access overload class (ACCOLC)

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.71 int unpack_nas_SetCDMANetworkParameters (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SetCDMANetworkParameters_t * *pOutput*)

CDMA Network Parameters unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.72 int unpack_nas_SetDataCapabilitiesCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SetDataCapabilitiesCallback_ind_t * *pOutput*)

Data Capabilities indication unpack

Parameters

in	*pResp*	qmi indication from modem
in	*respLen*	qmi indication length
out	*pOutput*	indication unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.73 int unpack_nas_SetEventReportInd (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SetEventReportInd_t * *pOutput*)

Unpack set event report indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.74 int unpack_nas_SetLURejectCallback (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SetLURejectCallback_t * *pOutput*)

Unpack set registration reject Callback

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.75 int unpack_nas_SetNasLTECphyCaIndCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SetNasLTECphyCaIndCallback_ind_t * *pOutput*)

Unpack set LTE PHY CA indication callback.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	sig info indication unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.76 int unpack_nas_SetNetworkPreference (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SetNetwork-Preference_t * *pOutput*)

Sets the network registration preference unpack

Parameters

in	*pResp*	qmi resp from modem
in	*respLen*	qmi resp length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.77 int unpack_nas_SetRFInfoCallback (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SetRFInfoCallback_t** * *pOutput*)

Unack Set RF Band Information callback.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.78 int unpack_nas_SetRoamingIndicatorCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SetRoamingIndicatorCallback_ind_t** * *pOutput*)

Roaming indication unpack

Parameters

in	*pResp*	qmi indication from modem
in	*respLen*	qmi indication length
out	*pOutput*	indication unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.79 int unpack_nas_SetServingSystemCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SetServingSystemCallback_ind_t** * *pOutput*)

Set Serving system indication unpack

Parameters

in	*pResp*	qmi indication from modem
in	*respLen*	qmi indication length
out	*pOutput*	indication unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.80 int unpack_nas_SLQSConfigSigInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSConfigSigInfo_t * *pOutput*)

Config Sig Info Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.81 int unpack_nas_SLQSGetErrorRate (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSGetErrorRate_t * *pOutput*)

Get Error Rate Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.82 int unpack_nas_SlqsGetLTECphyCAInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SlqsGetLTECphyCAInfo_t * *pOutput*)

Unack get carrier aggregation event information.

Parameters

in	*pResp*	qmi resp from modem
in	*respLen*	qmi resp length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.83 int unpack_nas_SLQSGetNetworkTime (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSGetNetwork-Time_t * *pOutput*)

Unpack get network time.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.84 int unpack_nas_SLQSGetOperatorNameData (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSGetOperatorNameData_t * *pOutput*)

Operator Name Data Parameters unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.85 int unpack_nas_SLQSGetPLMNName (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSGetPLMNName_t * *pOutput*)

unpack get operator name for specificed network.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.86 int unpack_nas_SLQSGetServingSystem (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSGetServingSystem_t * *pOutput*)

Unack queries information regarding the system that currently provides service.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.87 int unpack_nas_SLQSGetSignalStrength (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSGetSignalStrength_t * *pOutput*)

Unpack get signal strength.This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use unpack_nas_SLQSNasGetSigInfo() for new firmware versions and new modules

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.88 int unpack_nas_SLQSGetSysInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSGetSysInfo_t * *pOutput*)

Provides the system information. This API is preferred when trying to get the service status info and serving system info. The function unpack_nas_SLQSGetServingSystem_t() reports similar NAS information, but it is deprecated. Please refer to the header description of unpack_nas_SLQSGetServingSystem_t() for more information.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

This API queries current serving system information, including registration information and system property. The registration information for all RATs specified in the mode capability setting are included regardless of registration status. The RAT-specific system property are included only for RATs that are specified in the mode capability setting and which are not in either No Service or Power Save modes.

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.89 int unpack_nas_SLQSGetSysSelectionPref (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSGetSysSelectionPref_t * *pOutput*)

Queries the different system selection preferences of the device unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.90 int unpack_nas_SLQSGetSysSelectionPrefExt (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSGetSysSelectionPrefExt_t * *pOutput*)

Queries the different system selection preferences of the device unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.91 int unpack_nas_SLQSInitiateNetworkRegistration (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSInitiateNetworkRegistration_t * *pOutput*)

Unpack initiates a network registration.This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use unpack_nas_SLQSSetSysSelectionPrefExt() instead for new firmware versions and new modules.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.92 int unpack_nas_SLQSNasConfigSigInfo2 (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasConfigSigInfo2_t * *pOutput*)

Unpack sets the signal strength reporting thresholds

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.93 int unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t * *pOutput*)

unpack nas eDRX change Info indication

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.94 int unpack_nas_SLQSNasGet3GPP2Subscription (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SLQSNasGet3GPP2Subscription_t** * *pOutput*)

3GPP2 Subscription Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.95 int unpack_nas_SLQSNasGetCellLocationInfo (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SLQSNasGetCellLocationInfo_t** * *pOutput*)

Unpack retrieves cell location-related information.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.96 int unpack_nas_SLQSNASGeteDRXParams (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SLQSNASGeteDRXParams_t** * *pOutput*)

Get eDRX Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.97 int unpack_nas_SLQSNASGeteDRXParamsExt (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNASGeteDRXParamsExt_t * *pOutput*)

Get eDRX Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.98 int unpack_nas_SLQSNASGetForbiddenNetworks (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNASGetForbiddenNetworks_t * *pOutput*)

Get forbidden networks unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.99 int unpack_nas_SLQSNasGetHDRColorCode (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasGetHDRColorCode_t * *pOutput*)

HDR Color Code Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.100 int unpack_nas_SLQSNasGetRFInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasGetRFInfo_t * *pOutput*)

Gets radio band/channel information unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.101 int unpack_nas_SLQSNasGetSigInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasGetSigInfo_t * *pOutput*)

get sig info unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

This command queries the signal strength information for currently active RATs. Information is reported only if the corresponding RATs have signal strength values to be reported. If no signal strength information is available for any RAT, the response message contains only the mandatory response message

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.102 int unpack_nas_SLQSNasGetTxRxInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasGetTxRxInfo_t * *pOutput*)

Get Tx Rx Info Parameters unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.103 int unpack_nas_SLQSNasIndicationRegisterExt (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasIndicationRegisterExt_t * *pOutput*)

Unpack used to Registers/De-registers for different NAS (Network access service) indications.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.104 int unpack_nas_SLQSNasNetworkRejectCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasNetworkRejectCallback_Ind_t * *pOutput*)

unpack nas Network Reject Callback indication

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.105 int unpack_nas_SLQSNasNetworkTimeCallBack_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasNetworkTimeCallBack_ind_t * *pOutput*)

Unpack Network time callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	sig info indication unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.106 int unpack_nas_SLQSNASSeteDRXParams (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNASSeteDRXParams_t * *pOutput*)

Set eDRX Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.107 int unpack_nas_SLQSNasSigInfoCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasSigInfoCallback_ind_t * *pOutput*)

Unpack Signal Information callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	sig info indication unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.108 int unpack_nas_SLQSNASSwiGetChannelLock (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNASSwiGetChannelLock_t * *pOutput*)

Get Channel Lock Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.109 int unpack_nas_SLQSNasSwiIndicationRegister (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasSwiIndicationRegister_t * *pOutput*)

unpack sets the registration state for different QMI_NAS SWI indications.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.110 int unpack_nas_SLQSNasSwiModemStatus (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasSwiModemStatus_t * *pOutput*)

This function requests the device to return the current status of modem.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.111 int unpack_nas_SLQSNasSwiOTAMessageCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasSwiOTAMessageCallback_ind_t * *pOutput*)

OTA message indication unpack

Parameters

in	*pResp*	qmi indication from modem
in	*respLen*	qmi indication length
out	*pOutput*	indication unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.112 int unpack_nas_SLQSNASSwiSetChannelLock (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNASSwiSetChannelLock_t * *pOutput*)

Set Channel Lock Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.113 int unpack_nas_SLQSNasSysInfoCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSysInfoCallback_ind_t * *pOutput*)

Unpack system information callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.114 int unpack_nas_SLQSNasTimerCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSNasTimerCallback_ind_t * *pOutput*)

Unpack timer callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	network timer indication unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.115 int unpack_nas_SLQSSetBandPreference (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSetBandPreference_t * *pOutput*)

Unpack sets the different system selection preferences of the device.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

9.6.4.116 int unpack_nas_SLQSSetSignalStrengthsCallback (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSetSignalStrengthsCallback_t * *pOutput*)

Unpack set signal strength thresholds callback.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.117 int unpack_nas_SLQSSetSysSelectionPref (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSetSysSelectionPref_t * *pOutput*)

Sets the different system selection preferences of the device unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.118 int unpack_nas_SLQSSetSysSelectionPrefCallBack_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t * *pOutput*)

System Selection Preference indication unpack

Parameters

in	*pResp*	qmi indication from modem
in	*respLen*	qmi indication length
out	*pOutput*	indication unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.119 int unpack_nas_SLQSSetSysSelectionPrefExt (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSetSysSelectionPrefExt_t * *pOutput*)

Sets the different system selection preferences of the device unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.120 int unpack_nas_SLQSSwiGetHDRPersonality (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSwiGetHDRPersonality_t * *pOutput*)

HDR Personality Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.121 int unpack_nas_SLQSSwiGetHDRProtSubtype (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSwiGetHDRProtSubtype_t * *pOutput*)

HDR Protocol Sub type Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.122 int unpack_nas_SLQSSwiGetHRPDStats (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSwiGetHRPDStats_t * *pOutput*)

HRPD Stats Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.123 int unpack_nas_SLQSSwiGetLteCQI (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SLQSSwiGetLteCQI_t** * *pOutput*)

Unack fetch CQI parameters for LTE data session.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.124 int unpack_nas_SLQSSwiGetLteSccRxInfo (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SLQSSwiGetLteSccRxInfo_t** * *pOutput*)

get LTE Secondary carrier Rx signal level information unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.125 int unpack_nas_SLQSSwiHDRPersonalityCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_nas_SLQSSwiHDRPersonalityCallback_Ind_t** * *pOutput*)

unpack nas SWI Hdr Personality indication

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.126 int unpack_nas_SLQSSwiNetworkDebug (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSwiNetworkDebug_t * *pOutput*)

Network Debug Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.127 int unpack_nas_SLQSSwiPSDetach (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSwiPSDetach_t * *pOutput*)

PS Connection Detach Parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.128 int unpack_nas_SLQSSwiRandIndicatorCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_nas_SLQSSwiRandIndicatorCallback_Ind_t * *pOutput*)

unpack nas SWI Rank indicator indication

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.129 int unpack_valid_nas_GetCDMANetworkParameters (uint8_t * *pResp*, uint8_t *u8Info*)

valid CDMA Network Parameters

Parameters

in	*pResp*	qmi response from modem
in	*u8Info*	value to check unpack_nas_GetCDMANetworkParameters_t param valid. • 0 - SCI • 1 - SCM • 2 - RegHomeSID, RegForeignSID and RegForeignNID • 3 - ForceRev0 • 4 - CustomSCP, Protocol ,Broadcast and Application • 5 - Roaming

Returns

eQCWWAN_ERR_NONE on signal info valid, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.130 int unpack_valid_nas_SLQSGetServingSystem (uint8_t * *pResp*, uint8_t *u8Info*)

valid queries information regarding the system that currently provides service

Parameters

in	*pResp*	qmi response from modem
in	*u8Info*	value to check unpack_nas_SLQSGetServingSystem_t param valid. • 0 - RoamIndicatorVal • 1 - DataSrvCapabilities • 2 - CurrentPLMN • 3 - SystemID and NetworkID • 4 - BaseStationID, BaseStationLatitude and BasestationLongitude • 5 - RoamingIndicatorList • 6 - DefaultRoamInd • 7 - Gpp2TimeZone • 8 - CDMA_P_Rev • 9 - GppTimeZone • 10 - GppNetworkDSTAdjustment • 11 - Lac • 12 - CellID • 13 - ConcSvcInfo • 14 - PRLInd • 15 - DTMInd • 16 - DetailedSvcInfo • 17 - CDMASystemInfoExt • 18 - HdrPersonality • 19 - TrackAreaCode • 20 - CallBarStatus

Returns

eQCWWAN_ERR_NONE on signal info valid, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.131 int unpack_valid_nas_SLQSGetSignalStrength (uint8_t * *pResp*, uint8_t *u8Info*)

valid queries information regarding the system that currently provides service

Parameters

in	*pResp*	qmi response from modem
in	*u8Info*	value to check unpack_nas_SLQSGetSignalStrength_t param valid. • 0 - rxSignalStrengthList and rxSignalStrengthListLen • 1 - ecioList and ecioListLen • 2 - Io • 3 - sinr • 4 - errorRateListLen, errorRateList • 5 - rsrqInfo • 6 - ltesnr • 7 - ltersrp

Returns

eQCWWAN_ERR_NONE on signal info valid, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.6.4.132 int unpack_valid_nas_SLQSNasGetSigInfo (uint8_t * *pResp*, uint8_t *u8Info*)

valid get sig info

Parameters

in	*pResp*	qmi response from modem
in	*u8Info*	value to check unpack_nas_SLQSNasGetSigInfo_t param valid. • 0 - CDMASSInfo • 1 - HDRSSInfo. • 2 - GSMSSInfo. • 3 - WCDMASSInfo. • 4 - LTESSInfo.

Returns

eQCWWAN_ERR_NONE on signal info valid, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7 pds.h File Reference

Data Structures

- struct unpack_pds_GetPDSState_t
- struct pack_pds_SetPDSState_t
- struct unpack_pds_GetPDSDefaults_t
- struct pack_pds_SetPDSDefaults_t
- struct unpack_pds_GetPortAutomaticTracking_t
- struct pack_pds_SetPortAutomaticTracking_t
- struct pack_pds_StartPDSTrackingSessionExt_t
- struct pack_pds_PDSInjectTimeReference_t
- struct unpack_pds_GetXTRAAutomaticDownload_t
- struct pack_pds_SetXTRAAutomaticDownload_t
- struct unpack_pds_GetXTRANetwork_t
- struct pack_pds_SetXTRANetwork_t
- struct unpack_pds_GetXTRAValidity_t
- struct unpack_pds_GetServiceAutomaticTracking_t
- struct pack_pds_SetServiceAutomaticTracking_t
- struct pack_pds_ResetPDSData_t
- struct pack_pds_SLQSSetAGPSConfig_t
- struct pack_pds_SLQSPDSInjectAbsoluteTimeReference_t

- struct pack_pds_SLQSGetAGPSConfig_t
- struct unpack_pds_SLQSGetAGPSConfig_t
- struct pack_pds_SLQSPDSInjectPositionData_t
- struct unpack_pds_SLQSGetGPSStateInfo_t
- struct pack_pds_SLQSSetPositionMethodState_t
- struct pack_pds_SetEventReportCallback_t
- struct unpack_pds_SetEventReport_Ind_t
- struct unpack_pds_SetPdsState_Ind_t

Typedefs

- typedef unpack_result_t unpack_pds_SetPDSState_t
- typedef unpack_result_t unpack_pds_SetPDSDefaults_t
- typedef unpack_result_t unpack_pds_SetPortAutomaticTracking_t
- typedef unpack_result_t unpack_pds_StartPDSTrackingSessionExt_t
- typedef unpack_result_t unpack_pds_StopPDSTrackingSession_t
- typedef unpack_result_t unpack_pds_PDSInjectTimeReference_t
- typedef unpack_result_t unpack_pds_SetXTRAAutomaticDownload_t
- typedef unpack_result_t unpack_pds_SetXTRANetwork_t
- typedef unpack_result_t unpack_pds_ForceXTRADownload_t
- typedef unpack_result_t unpack_pds_SetServiceAutomaticTracking_t
- typedef unpack_result_t unpack_pds_ResetPDSData_t
- typedef unpack_result_t unpack_pds_SLQSSetAGPSConfig_t
- typedef unpack_result_t unpack_pds_SLQSPDSInjectAbsoluteTimeReference_t
- typedef unpack_result_t unpack_pds_SLQSPDSInjectPositionData_t
- typedef unpack_result_t unpack_pds_SLQSPDSDeterminePosition_t
- typedef unpack_result_t unpack_pds_SLQSSetPositionMethodState_t
- typedef unpack_result_t unpack_pds_SetEventReportCallback_t

Functions

- int pack_pds_GetPDSState (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen)
- int unpack_pds_GetPDSState (uint8_t ∗pResp, uint16_t respLen, unpack_pds_GetPDSState_t ∗pOutput)
- int pack_pds_SetPDSState (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_pds_SetPDSState_t ∗pReqParam)
- int unpack_pds_SetPDSState (uint8_t ∗pResp, uint16_t respLen, unpack_pds_SetPDSState_t ∗pOutput)
- int pack_pds_GetPDSDefaults (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen)
- int unpack_pds_GetPDSDefaults (uint8_t ∗pResp, uint16_t respLen, unpack_pds_GetPDSDefaults_t ∗pOutput)
- int pack_pds_SetPDSDefaults (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_pds_SetPDSDefaults_t ∗pReqParam)
- int unpack_pds_SetPDSDefaults (uint8_t ∗pResp, uint16_t respLen, unpack_pds_SetPDSDefaults_t ∗pOutput)
- int pack_pds_GetPortAutomaticTracking (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen)
- int unpack_pds_GetPortAutomaticTracking (uint8_t ∗pResp, uint16_t respLen, unpack_pds_GetPortAutomaticTracking_t ∗pOutput)
- int pack_pds_SetPortAutomaticTracking (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_pds_SetPortAutomaticTracking_t ∗pReqParam)
- int unpack_pds_SetPortAutomaticTracking (uint8_t ∗pResp, uint16_t respLen, unpack_pds_SetPortAutomaticTracking_t ∗pOutput)
- int pack_pds_StartPDSTrackingSessionExt (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_pds_StartPDSTrackingSessionExt_t ∗pReqParam)
- int unpack_pds_StartPDSTrackingSessionExt (uint8_t ∗pResp, uint16_t respLen, unpack_pds_StartPDSTrackingSessionExt_t ∗pOutput)

- int pack_pds_StopPDSTrackingSession (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_pds_StopPDSTrackingSession (uint8_t *pResp, uint16_t respLen, unpack_pds_StopPDSTrackingSession_t *pOutput)
- int pack_pds_PDSInjectTimeReference (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_pds_PDSInjectTimeReference_t *pReqParam)
- int unpack_pds_PDSInjectTimeReference (uint8_t *pResp, uint16_t respLen, unpack_pds_PDSInjectTimeReference_t *pOutput)
- int pack_pds_GetXTRAAutomaticDownload (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_pds_GetXTRAAutomaticDownload (uint8_t *pResp, uint16_t respLen, unpack_pds_GetXTRAAutomaticDownload_t *pOutput)
- int pack_pds_SetXTRAAutomaticDownload (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_pds_SetXTRAAutomaticDownload_t *pReqParam)
- int unpack_pds_SetXTRAAutomaticDownload (uint8_t *pResp, uint16_t respLen, unpack_pds_SetXTRAAutomaticDownload_t *pOutput)
- int pack_pds_GetXTRANetwork (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_pds_GetXTRANetwork (uint8_t *pResp, uint16_t respLen, unpack_pds_GetXTRANetwork_t *pOutput)
- int pack_pds_SetXTRANetwork (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_pds_SetXTRANetwork_t *pReqParam)
- int unpack_pds_SetXTRANetwork (uint8_t *pResp, uint16_t respLen, unpack_pds_SetXTRANetwork_t *pOutput)
- int pack_pds_GetXTRAValidity (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_pds_GetXTRAValidity (uint8_t *pResp, uint16_t respLen, unpack_pds_GetXTRAValidity_t *pOutput)
- int pack_pds_ForceXTRADownload (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_pds_ForceXTRADownload (uint8_t *pResp, uint16_t respLen, unpack_pds_ForceXTRADownload_t *pOutput)
- int pack_pds_GetServiceAutomaticTracking (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_pds_GetServiceAutomaticTracking (uint8_t *pResp, uint16_t respLen, unpack_pds_GetServiceAutomaticTracking_t *pOutput)
- int pack_pds_SetServiceAutomaticTracking (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_pds_SetServiceAutomaticTracking_t *pReqParam)
- int unpack_pds_SetServiceAutomaticTracking (uint8_t *pResp, uint16_t respLen, unpack_pds_SetServiceAutomaticTracking_t *pOutput)
- int pack_pds_ResetPDSData (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_pds_ResetPDSData_t *pReqParam)
- int unpack_pds_ResetPDSData (uint8_t *pResp, uint16_t respLen, unpack_pds_ResetPDSData_t *pOutput)
- int pack_pds_SLQSSetAGPSConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_pds_SLQSSetAGPSConfig_t *pReqParam)
- int unpack_pds_SLQSSetAGPSConfig (uint8_t *pResp, uint16_t respLen, unpack_pds_SLQSSetAGPSConfig_t *pOutput)
- int pack_pds_SLQSPDSInjectAbsoluteTimeReference (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_pds_SLQSPDSInjectAbsoluteTimeReference_t *pReqParam)
- int unpack_pds_SLQSPDSInjectAbsoluteTimeReference (uint8_t *pResp, uint16_t respLen, unpack_pds_SLQSPDSInjectAbsoluteTimeReference_t *pOutput)
- int pack_pds_SLQSGetAGPSConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_pds_SLQSGetAGPSConfig_t *pReqParam)
- int unpack_pds_SLQSGetAGPSConfig (uint8_t *pResp, uint16_t respLen, unpack_pds_SLQSGetAGPSConfig_t *pOutput)
- int pack_pds_SLQSPDSInjectPositionData (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_pds_SLQSPDSInjectPositionData_t *pReqParam)
- int unpack_pds_SLQSPDSInjectPositionData (uint8_t *pResp, uint16_t respLen, unpack_pds_SLQSPDSInjectPositionData_t *pOutput)
- int pack_pds_SLQSPDSDeterminePosition (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_pds_SLQSPDSDeterminePosition (uint8_t *pResp, uint16_t respLen, unpack_pds_SLQSPDSDeterminePosition_t *pOutput)

- int pack_pds_SLQSGetGPSStateInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_pds_SLQSGetGPSStateInfo (uint8_t *pResp, uint16_t respLen, unpack_pds_SLQSGetGPS-StateInfo_t *pOutput)
- int pack_pds_SLQSSetPositionMethodState (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_-pds_SLQSSetPositionMethodState_t *pReqParam)
- int unpack_pds_SLQSSetPositionMethodState (uint8_t *pResp, uint16_t respLen, unpack_pds_SLQSSet-PositionMethodState_t *pOutput)
- int pack_pds_SetEventReportCallback (pack_qmi_t *pCtx, uint8_t *pReq, uint16_t *pLen, pack_pds_Set-EventReportCallback_t *pReqParam)
- int unpack_pds_SetEventReportCallback (uint8_t *pResp, uint16_t respLen, unpack_pds_SetEventReport-Callback_t *pOutput)
- int unpack_pds_SetEventReport_Ind (uint8_t *pResp, uint16_t respLen, unpack_pds_SetEventReport_Ind_t *pOutput)
- int unpack_pds_SetPdsState_Ind (uint8_t *pResp, uint16_t respLen, unpack_pds_SetPdsState_Ind_t *p-Output)

9.7.1 Typedef Documentation

9.7.1.1 typedef unpack_result_t unpack_pds_ForceXTRADownload_t

9.7.1.2 typedef unpack_result_t unpack_pds_PDSInjectTimeReference_t

9.7.1.3 typedef unpack_result_t unpack_pds_ResetPDSData_t

9.7.1.4 typedef unpack_result_t unpack_pds_SetEventReportCallback_t

9.7.1.5 typedef unpack_result_t unpack_pds_SetPDSDefaults_t

9.7.1.6 typedef unpack_result_t unpack_pds_SetPDSState_t

9.7.1.7 typedef unpack_result_t unpack_pds_SetPortAutomaticTracking_t

9.7.1.8 typedef unpack_result_t unpack_pds_SetServiceAutomaticTracking_t

9.7.1.9 typedef unpack_result_t unpack_pds_SetXTRAAutomaticDownload_t

9.7.1.10 typedef unpack_result_t unpack_pds_SetXTRANetwork_t

9.7.1.11 typedef unpack_result_t unpack_pds_SLQSPDSDeterminePosition_t

9.7.1.12 typedef unpack_result_t unpack_pds_SLQSPDSInjectAbsoluteTimeReference_t

9.7.1.13 typedef unpack_result_t unpack_pds_SLQSPDSInjectPositionData_t

9.7.1.14 typedef unpack_result_t unpack_pds_SLQSSetAGPSConfig_t

9.7.1.15 typedef unpack_result_t unpack_pds_SLQSSetPositionMethodState_t

9.7.1.16 typedef unpack_result_t unpack_pds_StartPDSTrackingSessionExt_t

9.7.1.17 typedef unpack_result_t unpack_pds_StopPDSTrackingSession_t

9.7.2 Function Documentation

9.7.2.1 int pack_pds_ForceXTRADownload (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Forces the XTRA database to be downloaded to the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.2 int pack_pds_GetPDSDefaults (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Get the default tracking session configuration pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.3 int pack_pds_GetPDSState (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

Get current PDS state pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.4 int pack_pds_GetPortAutomaticTracking (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Returns the automatic tracking configuration for the NMEA COM port pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.5 int pack_pds_GetServiceAutomaticTracking (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

automatic tracking state for the service pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.6 int pack_pds_GetXTRAAutomaticDownload (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

XTRA automatic database download configuration pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.7 int pack_pds_GetXTRANetwork (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

XTRA WWAN network preference parameter pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.8 int pack_pds_GetXTRAValidity (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

XTRA database validity period parameter pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.9 int pack_pds_PDSInjectTimeReference (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_pds_PDSInjectTimeReference_t * pReqParam)

Inject system time parameters pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.10 int pack_pds_ResetPDSData (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_pds_ResetPDSData_t * pReqParam)

Resets the specified PDS data pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.11 int pack_pds_SetEventReportCallback (pack_qmi_t * pCtx, uint8_t * pReq, uint16_t * pLen, pack_pds_SetEventReportCallback_t * pReqParam)

Enables/disables the PDS Event report callback function pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReq*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.12 int pack_pds_SetPDSDefaults (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_pds_SetPDSDefaults_t * pReqParam)

Sets the default tracking session configuration pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.13 int pack_pds_SetPDSState (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_pds_SetPDSState_t * *pReqParam*)

Sets the PDS state pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.14 int pack_pds_SetPortAutomaticTracking (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_pds_SetPortAutomaticTracking_t * *pReqParam*)

Sets the automatic tracking configuration for the NMEA COM port pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.15 int pack_pds_SetServiceAutomaticTracking (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_pds_SetServiceAutomaticTracking_t * *pReqParam*)

Sets the automatic tracking state for the service pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.16 int pack_pds_SetXTRAAutomaticDownload (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_pds_SetXTRAAutomaticDownload_t * *pReqParam*)

Sets the XTRA automatic database download configuration pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.17 int pack_pds_SetXTRANetwork (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_pds_SetXTRANetwork_t * *pReqParam*)

Sets the XTRA WWAN network preference pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.18 int pack_pds_SLQSGetAGPSConfig (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_pds_SLQSGetAGPSConfig_t * *pReqParam*)

Gets the PDS AGPS (MS-based) configuration pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.19 int pack_pds_SLQSGetGPSStateInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Queries the MSM GPS server for receiver state information pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.20 int pack_pds_SLQSPDSDeterminePosition (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Requests the MSM GPS service to obtain the current position for manually controlled tracking sessions pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.21 int pack_pds_SLQSPDSInjectAbsoluteTimeReference (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_pds_SLQSPDSInjectAbsoluteTimeReference_t * pReqParam)

Injects a absolute time reference into the PDS engine pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.22 int pack_pds_SLQSPDSInjectPositionData (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_pds_SLQSPDSInjectPositionData_t * pReqParam)

Injects position data into the PDS engine pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.23 int pack_pds_SLQSSetAGPSConfig (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_pds_SLQSSetAGPSConfig_t * pReqParam)

Sets the PDS AGPS (MS-based) configuration pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.24 int pack_pds_SLQSSetPositionMethodState (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_pds_SLQSSetPositionMethodState_t * *pReqParam*)

Sets the state of positioning methods for the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.25 int pack_pds_StartPDSTrackingSessionExt (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_pds_StartPDSTrackingSessionExt_t * *pReqParam*)

Starts a PDS tracking session pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameters

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.26 int pack_pds_StopPDSTrackingSession (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Stops a PDS tracking session pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.27 int unpack_pds_ForceXTRADownload (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_ForceXTRADownload_t * *pOutput*)

Forces the XTRA database to be downloaded to the device unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.28 int unpack_pds_GetPDSDefaults (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_GetPDSDefaults_t * *pOutput*)

Get the default tracking session configuration unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.29 int unpack_pds_GetPDSState (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_GetPDSState_t * *pOutput*)

Get current PDS state unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.30 int unpack_pds_GetPortAutomaticTracking (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_GetPortAutomaticTracking_t * *pOutput*)

Returns the automatic tracking configuration for the NMEA COM port unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.31 int unpack_pds_GetServiceAutomaticTracking (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_GetServiceAutomaticTracking_t * *pOutput*)

automatic tracking state for the service unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.32 int unpack_pds_GetXTRAAutomaticDownload (uint8_t * *pResp*, uint16_t *respLen*, **unpack_pds_GetXTRAAutomaticDownload_t** * *pOutput*)

XTRA automatic database download configuration unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.33 int unpack_pds_GetXTRANetwork (uint8_t * *pResp*, uint16_t *respLen*, **unpack_pds_GetXTRANetwork_t** * *pOutput*)

XTRA WWAN network preference parameter unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.34 int unpack_pds_GetXTRAValidity (uint8_t * *pResp*, uint16_t *respLen*, **unpack_pds_GetXTRAValidity_t** * *pOutput*)

XTRA database validity period parameter unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.35 int unpack_pds_PDSInjectTimeReference (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_PDSInjectTime-Reference_t * *pOutput*)

Inject system time parameters unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.36 int unpack_pds_ResetPDSData (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_ResetPDSData_t * *pOutput*)

Resets the specified PDS data unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.37 int unpack_pds_SetEventReport_Ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SetEventReport_Ind_t * *pOutput*)

PDS Event Report Indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.38 int unpack_pds_SetEventReportCallback (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SetEventReportCallback_t * *pOutput*)

Enables/disables the PDS Event report callback function unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.39 int unpack_pds_SetPDSDefaults (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SetPDSDefaults_t * *pOutput*)

Sets the default tracking session configuration unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.40 int unpack_pds_SetPDSState (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SetPDSState_t * *pOutput*)

Sets the PDS state unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.41 int unpack_pds_SetPdsState_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_pds_SetPdsState_Ind_t** * *pOutput*)

PDS State Indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.42 int unpack_pds_SetPortAutomaticTracking (uint8_t * *pResp*, uint16_t *respLen*, **unpack_pds_SetPortAutomaticTracking_t** * *pOutput*)

Sets the automatic tracking configuration for the NMEA COM port unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.43 int unpack_pds_SetServiceAutomaticTracking (uint8_t * *pResp*, uint16_t *respLen*, **unpack_pds_SetServiceAutomaticTracking_t** * *pOutput*)

Sets the automatic tracking state for the service unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.44 int unpack_pds_SetXTRAAutomaticDownload (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SetXTRAAutomaticDownload_t * *pOutput*)

Sets the XTRA automatic database download configuration unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.45 int unpack_pds_SetXTRANetwork (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SetXTRANetwork_t * *pOutput*)

Sets the XTRA WWAN network preference unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.46 int unpack_pds_SLQSGetAGPSConfig (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SLQSGetAGPSConfig_t * *pOutput*)

Gets the PDS AGPS (MS-based) configuration unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.47 int unpack_pds_SLQSGetGPSStateInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SLQSGetGPSStateInfo_t * *pOutput*)

Queries the MSM GPS server for receiver state information unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.48 int unpack_pds_SLQSPDSDeterminePosition (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SLQSPDSDeterminePosition_t * *pOutput*)

Requests the MSM GPS service to obtain the current position for manually controlled tracking sessions unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.49 int unpack_pds_SLQSPDSInjectAbsoluteTimeReference (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SLQSPDSInjectAbsoluteTimeReference_t * *pOutput*)

Injects a absolute time reference into the PDS engine unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.50 int unpack_pds_SLQSPDSInjectPositionData (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SLQSPDSInjectPositionData_t * *pOutput*)

Injects position data into the PDS engine unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.51 int unpack_pds_SLQSSetAGPSConfig (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SLQSSetAGPSConfig_t * *pOutput*)

Sets the PDS AGPS (MS-based) configuration unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.52 int unpack_pds_SLQSSetPositionMethodState (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_SLQSSetPositionMethodState_t * *pOutput*)

Sets the state of positioning methods for the device unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.53 int unpack_pds_StartPDSTrackingSessionExt (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_StartPDSTrackingSessionExt_t * *pOutput*)

Starts a PDS tracking session unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.7.2.54 int unpack_pds_StopPDSTrackingSession (uint8_t * *pResp*, uint16_t *respLen*, unpack_pds_StopPDSTrackingSession_t * *pOutput*)

Stops a PDS tracking session unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.8 qaCbkCatEventReportInd.h File Reference

Data Structures

- struct CatEventIDDataTlv
- struct CatAlPhaIdentifierTlv
- struct CatEventListTlv

- struct CatRefreshTlv
- struct CatEndProactiveSessionTlv
- union currentCatEvent
- struct CatCommonEventTlv
- struct QmiCbkCatEventStatusReportInd

Macros

- #define QMI_MAX_CAT_EVENT_DATA_LENGTH 255
- #define QMI_CAN_COMMON_EVENT_TLV_NUMBER 11

Enumerations

- enum eQMI_CAT_EVENT_REPORT_IND_TLV {
  eTLV_CBK_DISPLAY_TEXT = 0x10,
  eTLV_CBK_GET_IN_KEY = 0x11,
  eTLV_CBK_GET_INPUT = 0x12,
  eTLV_CBK_SETUP_MENU = 0x13,
  eTLV_CBK_SELECT_ITEM = 0x14,
  eTLV_CBK_ALPHA_IDENTIFIER = 0x15,
  eTLV_CBK_SETUP_EVENT_LIST = 0x16,
  eTLV_CBK_SETUP_IDLE_MODE_TEXT = 0x17,
  eTLV_CBK_LANGUAGE_NOTIFICATION = 0x18,
  eTLV_CBK_REFRESH = 0x19,
  eTLV_CBK_END_PROACTIVE_SESSION = 0x1A }
- enum eQMI_CAT_EVENT_REPORT_IND_TLV_LENGTH {
  eTLV_SETUP_EVENT_LIST_LENGTH = 0x04,
  eTLV_REFRESH_LENGTH = 0x03,
  eTLV_END_PROACTIVE_SESSION_LENGTH = 0x01 }

Functions

- enum eQCWWANError UpkQmiCbkCatEventReportInd (BYTE *pMdmResp, struct QmiCbkCatEventStatus-ReportInd *pAipResp)

9.8.1 Macro Definition Documentation

9.8.1.1 #define QMI_CAN_COMMON_EVENT_TLV_NUMBER 11

9.8.1.2 #define QMI_MAX_CAT_EVENT_DATA_LENGTH 255

9.8.2 Enumeration Type Documentation

9.8.2.1 enum eQMI_CAT_EVENT_REPORT_IND_TLV

Enumerator

eTLV_CBK_DISPLAY_TEXT

eTLV_CBK_GET_IN_KEY

eTLV_CBK_GET_INPUT

eTLV_CBK_SETUP_MENU

eTLV_CBK_SELECT_ITEM

eTLV_CBK_ALPHA_IDENTIFIER

eTLV_CBK_SETUP_EVENT_LIST

eTLV_CBK_SETUP_IDLE_MODE_TEXT

eTLV_CBK_LANGUAGE_NOTIFICATION

eTLV_CBK_REFRESH

eTLV_CBK_END_PROACTIVE_SESSION

9.8.2.2 enum eQMI_CAT_EVENT_REPORT_IND_TLV_LENGTH

Enumerator

eTLV_SETUP_EVENT_LIST_LENGTH

eTLV_REFRESH_LENGTH

eTLV_END_PROACTIVE_SESSION_LENGTH

9.8.3 Function Documentation

9.8.3.1 enum eQCWWANError UpkQmiCbkCatEventReportInd (BYTE * *pMdmResp,* struct QmiCbkCatEventStatusReportInd * *pAipResp*)

9.9 qaCbkSwiOmaDmEventReportInd.h File Reference

Data Structures

- struct sessionInfoTlv
- struct sessionInfoTlvExt
- struct QmiCbkSwiOmaDmEventStatusReportInd
- struct QmiCbkSwiOmaDmEventStatusReportIndExt

Macros

- #define QMI_SWIOMA_DM_FOTA 0x00
- #define QMI_SWIOMA_DM_CONFIG 0x01
- #define QMI_SWIOMA_DM_NOT 0x02

Enumerations

- enum eQMI_SWIOMA_DM_EVENT_REPORT_IND {
  eTLV_IND_OMA_DM_FOTA = 0x10,
  eTLV_IND_OMA_DM_CONFIG = 0x11,
  eTLV_IND_OMA_DM_NOT = 0x12 }

Functions

- enum eQCWWANError UpkQmiCbkSwiOmaDmEventReportInd (BYTE *pMdmResp, struct QmiCbkSwiOmaDmEventStatusReportInd *pApiResp)
- package enum eQCWWANError UpkQmiCbkSwiOmaDmEventReportIndExt (BYTE *pMdmResp, struct QmiCbkSwiOmaDmEventStatusReportInd *pApiResp)

9.9.1 Macro Definition Documentation

9.9.1.1 #define QMI_SWIOMA_DM_CONFIG 0x01

9.9.1.2 #define QMI_SWIOMA_DM_FOTA 0x00

9.9.1.3 #define QMI_SWIOMA_DM_NOT 0x02

9.9.2 Enumeration Type Documentation

9.9.2.1 enum eQMI_SWIOMA_DM_EVENT_REPORT_IND

Enumerator

eTLV_IND_OMA_DM_FOTA

eTLV_IND_OMA_DM_CONFIG

eTLV_IND_OMA_DM_NOT

9.9.3 Function Documentation

9.9.3.1 enum eQCWWANError UpkQmiCbkSwiOmaDmEventReportInd (BYTE * *pMdmResp,* struct QmiCbkSwiOmaDmEventStatusReportInd * *pApiResp*)

9.9.3.2 package enum eQCWWANError UpkQmiCbkSwiOmaDmEventReportIndExt (BYTE * *pMdmResp,* struct QmiCbkSwiOmaDmEventStatusReportInd * *pApiResp*)

9.10 qaGobiApiAudio.h File Reference

Audio Service API function prototypes.

Data Structures

- struct GetAudioProfileReq
- struct GetAudioProfileResp
- struct SetAudioProfileReq
- struct GetAudioPathConfigReq
- struct TXPCMIIRFltr
- struct RXPCMIIRFltr
- struct RXAGCList
- struct RXAVCList
- struct TXAGCList
- struct GetAudioPathConfigResp
- struct SetAudioPathConfigReq
- struct GetAudioVolTLBConfigReq
- struct GetAudioVolTLBConfigResp
- struct SetAudioVolTLBConfigReq
- struct SetAudioVolTLBConfigResp

Functions

- ULONG SLQSGetAudioProfile (GetAudioProfileReq *pGetAudioProfileReq, GetAudioProfileResp *pGetAudioProfileResp)
- ULONG SLQSSetAudioProfile (SetAudioProfileReq *pSetAudioProfileReq)

- ULONG SLQSGetAudioPathConfig (GetAudioPathConfigReq *pGetAudioPathConfigReq, GetAudioPathConfigResp *pGetAudioPathConfigResp)
- ULONG SLQSSetAudioPathConfig (SetAudioPathConfigReq *pSetAudioPathConfigReq)
- ULONG SLQSGetAudioVolTLBConfig (GetAudioVolTLBConfigReq *pGetAudioVolTLBCfgReq, GetAudioVolTLBConfigResp *pGetAudioVolTLBCfgResp)
- ULONG SLQSSetAudioVolTLBConfig (SetAudioVolTLBConfigReq *pSetAudioVolTLBCfgReq, SetAudioVolTLBConfigResp *pSetAudioVolTLBCfgResp)

9.10.1 Detailed Description

Audio Service API function prototypes.

9.10.2 Function Documentation

9.10.2.1 ULONG SLQSGetAudioPathConfig (GetAudioPathConfigReq * *pGetAudioPathConfigReq*, GetAudioPathConfigResp * *pGetAudioPathConfigResp*)

This API gets the audio path configuration parameters.

Parameters

pGetAudioPathConfigReq[IN]	• See GetAudioPathConfigReq for more information
pGetAudioPathConfigResp[OUT]	• See GetAudioPathConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: SL9090
Timeout: 5 seconds

9.10.2.2 ULONG SLQSGetAudioProfile (GetAudioProfileReq * *pGetAudioProfileReq*, GetAudioProfileResp * *pGetAudioProfileResp*)

This API get the profile content of the requested audio generator.

Parameters

pGetAudioProfileReq[IN]	• See GetAudioProfileReq for more information
pGetAudioProfileResp[OUT]	• See GetAudioProfileResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: SL9090
Timeout: 5 seconds

9.10.2.3 ULONG SLQSGetAudioVolTLBConfig (GetAudioVolTLBConfigReq * *pGetAudioVolTLBCfgReq*, GetAudioVolTLBConfigResp * *pGetAudioVolTLBCfgResp*)

This API gets the audio path configuration parameters.

Parameters

pGetAudioVolTL-BCfgReq[IN]	• See GetAudioVolTLBConfigReq for more information
pGetAudioVolTL-BCfgResp[OUT]	• See GetAudioVolTLBConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: SL9090
Timeout: 5 seconds

9.10.2.4 ULONG SLQSSetAudioPathConfig (SetAudioPathConfigReq * *pSetAudioPathConfigReq*)

This API sets the audio path configuration parameters.

Parameters

pSetAudioPath-ConfigReq[IN]	• See SetAudioPathConfigReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: SL9090
Timeout: 5 seconds

9.10.2.5 ULONG SLQSSetAudioProfile (SetAudioProfileReq * *pSetAudioProfileReq*)

This API sets an audio profile.

Parameters

pSetAudio-ProfileReq[IN]	• See SetAudioProfileReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: SL9090
Timeout: 5 seconds

9.10.2.6 ULONG SLQSSetAudioVolTLBConfig (SetAudioVolTLBConfigReq * *pSetAudioVolTLBCfgReq*, SetAudioVolTLBConfigResp * *pSetAudioVolTLBCfgResp*)

This API sets the audio path configuration parameters.

Parameters

pSetAudioVolTL-BCfgReq[IN]	• See SetAudioVolTLBConfigReq for more information
pSetAudioVolTL-BCfgResp[OUT]	• See SetAudioVolTLBConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: SL9090
Timeout: 5 seconds

9.11 qaGobiApiCat.h File Reference

Card Application Toolkit API function headers.

Functions

- ULONG CATSendEnvelopeCommand (ULONG cmdID, ULONG dataLen, BYTE *pData)
- ULONG CATSendTerminalResponse (ULONG refID, ULONG dataLen, BYTE *pData)

9.11.1 Detailed Description

Card Application Toolkit API function headers.

9.11.2 Function Documentation

9.11.2.1 ULONG CATSendEnvelopeCommand (ULONG *cmdID*, ULONG *dataLen*, BYTE * *pData*)

Sends the envelope command to the device.

Parameters

cmdID	• Envelope command type – 0x01 - Menu Selection – 0x02 - Event DL User activity – 0x03 - Event DL Idle Screen Available – 0x04 - Event DL Language Selection
dataLen	• Length of pData in bytes
pData[IN]	• Encoded envelope data as defined in ETSI TS 102 223, section 7 [Smart Cards: Card Application Toolkit (CAT) - Release 4]

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 2 seconds

9.11.2.2 ULONG CATSendTerminalResponse (ULONG *refID,* ULONG *dataLen,* BYTE * *pData*)

Sends the terminal response to the device.

Parameters

refID	• Proactive command reference ID. The value should be the same as indicated in the CAT event callback data for the relevant proactive command.
dataLen	• Terminal response data length
pData[IN]	• Terminal response for the relevant proactive command encoded as per ETSI TS 102 223, section 6.8 [Smart Cards: Card Application Toolkit (CAT) - Release 4]

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 2 seconds

9.12 qaGobiApiCbk.h File Reference

Callback Service API function prototypes.

Data Structures

- struct qaQmiInterfaceInfo
- struct slqsSessionStateInfo
- struct slqsWdsEventInfo
- struct TransferStatsDataType
- struct SignalStrengthDataType
- struct SMSMTMessage
- struct SMSTransferRouteMTMessage
- struct SMSMessageMode
- struct SMSEtwsMessage
- struct SMSEtwsPlmn
- struct SMSCAddress
- struct SMSOnIMS
- struct SMSEventInfo_s
- struct CATEventDataType
- struct ServingSystemInfo
- struct RoamingInfo

- struct SLQSSignalStrengthsInformation
- struct SLQSSignalStrengthsIndReq
- struct ECTNum
- struct voiceSUPSNotification
- struct voiceSetAllCallStatusCbkInfo
- struct _transLayerInfoNotification
- struct _transNWRegInfoNotification
- struct UIMStatusChangeInfo
- struct voicePrivacyInfo
- struct voiceDTMFEventInfo
- struct voiceSUPSInfo
- struct LteCiotOpModeTlv
- struct NR5GSerStatTlv
- struct NR5GSystemInfoTlv
- struct NR5GCellStatusTlv
- struct nasSysInfo
- struct UniversalTime
- struct nasNetworkTime
- struct omaDmFotaTlv
- struct omaDmFotaTlvExt
- struct omaDmConfigTlvExt
- struct omaDmConfigTlv
- struct omaDmNotificationsTlv
- union sessionInfo
- union sessionInfoExt
- struct SMSMemoryInfo
- struct voiceOTASPStatusInfo
- struct signalInfo
- struct callerIDInfo
- struct callingPartyInfo
- struct calledPartyInfo
- struct redirNumInfo
- struct NSSAudioCtrl
- struct lineCtrlInfo
- struct extDispRecInfo
- struct voiceInfoRec
- struct msgWaitingInfo
- struct QosFlowInfoState
- struct QosFlowInfo
- struct QosEventInfo
- struct nasSigInfo
- struct _modemTempNotification
- struct _packetSrvStatus
- struct HDRPersonalityInd
- struct imsSIPConfigInfo
- struct imsRegMgrConfigInfo
- struct imsSMSConfigInfo
- struct imsUserConfigInfo
- struct imsVoIPConfigInfo
- struct USSDNoWaitIndicationInfo
- struct channelRate
- struct DUNCallInfoInd
- struct SMSAsyncRawSend_s
- struct LteNasReleaseInfo_s
- struct SwiOTAMsg_s

- struct DHCPOption
- struct DHCPOptionList
- struct WdsDHCPv4ClientLeaseInd
- struct SLQSSetDHCPv4ClientLeaseStatusCallbackParam
- struct QmiCbkLocCradleMountInd
- struct QmiCbkLocEventTimeSyncInd
- struct QmiCbkLocInjectTimeInd
- struct accelAcceptReady_s
- struct gyroAcceptReady_s
- struct accelTempAcceptReady_s
- struct gyroTempAcceptReady_s
- struct QmiCbkLocSensorStreamingInd
- struct QmiCbkLocInjectSensorDataInd
- struct precisionDilution_s
- struct gpsTime_s
- struct sensorDataUsage_s
- struct svUsedforFix_s
- struct QmiCbkLocPositionReportInd
- struct t_Sv
- struct t_sensor
- struct t_gpsTime
- struct QmiCbkLocBestAvailPosInd
- struct QmiCbkLocOpModeInd
- struct imsaRegStatusInfo
- struct imsaSvcStatusInfo
- struct imsaRatStatusInfo
- struct imsaPdpStatusInfo
- struct satelliteInfo
- struct gnssSvInfoNotification
- struct delAssistDataStatus
- struct QmiCbkNasLTECphyCaInfo
- struct RankIndicatorInd
- struct QmiCbkLocInjectUTCTimeInd
- struct QmiCbkLocInjectPositionInd
- struct UIMSlotStatusChangeInfo
- struct QmiCbkLocEngineStateInd
- struct _getResetInfoNotification
- struct _MitigationDevInfo
- struct QmiCbkTmdMitiLvlRptInd
- struct SLQSTmdMitigationLvlRptCallbackParam
- struct QmiCbkLocSetExtPowerConfigInd
- struct nasTimers
- struct CsgId
- struct PlmnID
- struct LteOpMode
- struct nasNetworkReject
- struct _SwiAvmsEventInd
- struct QmiCbkLocEventNMEAInd
- struct IPv4Info
- struct IPv6Info
- struct urlAddr
- struct QmiCbkLocGetServerInd
- struct SetLocGetServerCallbackPara
- struct dmsPsmCfgParamChange
- struct QmiCbkLocSetServerInd

- struct SetLocSetServerCallbackParam
- struct _modemUIMStatusNotification
- struct EdrxEnableType
- struct EdrxCycleLength
- struct EdrxPagingTimeWindow
- struct EdrxRatType
- struct EdrxCiotLteMode
- struct QmiCbkNasEdrxChangeInfo
- struct QmiCbkLocGetOpModeInd

Macros

- #define SIGSTRENGTH_THRESHOLD_ARR_SZ 5
- #define QMI_WMS_MAX_PAYLOAD_LENGTH 256
- #define QMI_ETWS_MAX_PAYLOAD_LENGTH 1254 /∗ Qualcomm defined max ∗/
- #define QMI_MAX_VOICE_NUMBER_LENGTH 81
- #define MAX_NO_OF_UUSINFO 20
- #define MAXUSSDLENGTH 182
- #define MAX_NO_OF_CALLS 20
- #define CBK_ENABLE_EVENT 0x01
- #define CBK_DISABLE_EVENT 0x00
- #define CBK_NOCHANGE 0xFF
- #define MAX_NO_OF_APPLICATIONS 10
- #define MAX_NO_OF_SLOTS 5
- #define MAX_NO_OF_FILES 255
- #define MAX_PATH_LENGTH 255
- #define EVENT_MASK_CARD 0x00000001
- #define EVENT_MASK_PHY_SLOT_STATUS 0x00000010
- #define EVENT_MASK_DEREGISTER_ALL 0x00000000
- #define REGISTER_EVENT 0x01
- #define DEREGISTER_EVENT 0x00
- #define FIRST_INSTANCE 0x00
- #define SECOND_INSTANCE 0x01
- #define THIRD_INSTANCE 0x02
- #define INVALID_INSTACNE 0x08
- #define REGISTER_SRV 0x01
- #define DEREGISTER_SRV 0x00
- #define WDS_SRV 0x01
- #define NAS_SRV 0x02
- #define PDS_SRV 0x04
- #define VOICE_SRV 0x08
- #define NUM_OF_SET 0xFF
- #define IPV4 4
- #define IPV6 6
- #define IPV4V6 7
- #define LOC_EVENT_MASK_ENG_STATE 0x00000080
- #define LOC_EVENT_MASK_TIME_SYNC 0x00000800
- #define LOC_EVENT_MASK_INJECT_TIME 0x00000010
- #define LOC_EVENT_MASK_SENSOR_STREAM 0x00000400
- #define LOC_EVENT_POSITION_REPORT 0x00000001
- #define LOC_EVENT_MASK_GNSS_SV_INFO 0x00000002
- #define LOC_EVENT_MASK_NMEA 0x00000004
- #define MAX_NMEA_STR_LEN 201
- #define DHCP_MAX_NUM_OPTIONS 30

- #define DHCP_OPTION_DATA_BUF_SIZE 2048 /∗ current max size of raw message in SDK process is 2048 ∗/
- #define MAX_MITIGATION_DEV_ID_LEN 255
- #define MAX_URL_ADDR_STR_LEN 256
- #define MAX_RADIO_INTERFACE_LIST 255
- #define USSD_DCS_ASCII 0x01 /∗ ASCII coding scheme ∗/
- #define USSD_DCS_8BIT 0x02 /∗ 8-bit coding scheme ∗/
- #define USSD_DCS_UCS2 0x03 /∗ UCS2 coding scheme ∗/

Typedefs

- typedef void(∗ tFNSLQSSessionState)(slqsSessionStateInfo ∗pSessionStateInfo)
- typedef void(∗ tFNSLQSWDSEvent)(slqsWdsEventInfo ∗pWdsEventInfo)
- typedef void(∗ tFNPower)(ULONG operatingMode)
- typedef void(∗ tFNActivationStatus)(ULONG activationStatus)
- typedef void(∗ tFNMobileIPStatus)(ULONG mipStatus)
- typedef void(∗ tFNRoamingIndicator)(ULONG roaming)
- typedef void(∗ tFNDataCapabilities)(BYTE dataCapsSize, BYTE ∗pDataCaps)
- typedef void(∗ tFNSignalStrength)(INT8 signalStrength, ULONG radioInterface)
- typedef void(∗ tFNRFInfo)(ULONG radioInterface, ULONG activeBandClass, ULONG activeChannel)
- typedef void(∗ tFNLUReject)(ULONG serviceDomain, ULONG rejectCause)
- typedef void(∗ tFNNewSMS)(ULONG storageType, ULONG messageIndex)
- typedef enum SMSEventType eSMSEventType
- typedef struct SMSMTMessage SMSMTMessageInfo
- typedef struct SMSTransferRouteMTMessage SMSTransferRouteMTMessageInfo
- typedef struct SMSMessageMode SMSMessageModeInfo
- typedef struct SMSEtwsMessage SMSEtwsMessageInfo
- typedef struct SMSEtwsPlmn SMSEtwsPlmnInfo
- typedef struct SMSCAddress SMSCAddressInfo
- typedef struct SMSOnIMS SMSOnIMSInfo
- typedef struct SMSEventInfo_s SMSEventInfo
- typedef void(∗ tFNSMSEvents)(SMSEventInfo ∗pSMSEventInfo)
- typedef void(∗ tFNNewNMEA)(LPCSTR pNMEA)
- typedef void(∗ tFNPDSState)(ULONG enabledStatus, ULONG trackingStatus)
- typedef void(∗ tFNCATEvent)(ULONG eventID, ULONG eventLen, BYTE ∗pEventData)
- typedef enum device_state_enum eDevState
- typedef void(∗ tFNDeviceStateChange)(eDevState device_state)
- typedef void(∗ tFNNet)(ULONG q_depth, BYTE isThrottle, BYTE instanceId)
- typedef void(∗ tFNFwDldCompletion)(ULONG fwdld_completion_status)
- typedef void(∗ tFNSLQSOMADMAlert)(ULONG eventType, BYTE ∗pEventFields)
- typedef void(∗ tFNOMADMState)(ULONG sessionState, ULONG failureReason)
- typedef void(∗ tFNServingSystem)(struct ServingSystemInfo ∗pServingSystem, struct RoamingInfo ∗pRoamingInfo)
- typedef void(∗ tFNBandPreference)(ULONGLONG band_pref)
- typedef void(∗ tFNUSSDRelease)(void)
- typedef void(∗ tFNUSSDNotification)(ULONG type, BYTE ∗pNetworkInfo)
- typedef void(∗ tFNSLQSSignalStrengths)(struct SLQSSignalStrengthsInformation sSLQSSignalStrengthsInfo)
- typedef void(∗ tFNSUPSNotification)(voiceSUPSNotification ∗pVoiceSUPSNotification)
- typedef void(∗ tFNSDKTerminated)(BYTE ∗psReason)
- typedef void(∗ tFNAllCallStatus)(voiceSetAllCallStatusCbkInfo ∗pVoiceSetAllCallStatusCbkInfo)
- typedef struct _transLayerInfoNotification transLayerNotification

- typedef void(∗ tFNtransLayerInfo)(transLayerNotification ∗pTransLayerNotification)
- typedef struct _transNWRegInfoNotification transNWRegInfoNotification
- typedef void(∗ tFNtransNWRegInfo)(transNWRegInfoNotification ∗pTransNWRegInfoNotification)
- typedef void(∗ tFNSysSelectionPref)(sysSelectPrefExtInfo ∗pSysSelectPrefInfo)
- typedef void(∗ tFNUIMRefresh)(UIMRefreshEvent ∗pUIMRefreshEvent)
- typedef void(∗ tFNUIMStatusChangeInfo)(UIMStatusChangeInfo ∗pUIMStatusChangeInfo)
- typedef void(∗ tFNPrivacyChange)(voicePrivacyInfo ∗pVoicePrivacyInfo)
- typedef void(∗ tFNDTMFEvent)(voiceDTMFEventInfo ∗pVoiceDTMFEventInfo)
- typedef void(∗ tFNSUPSInfo)(voiceSUPSInfo ∗pVoiceSUPSInfo)
- typedef void(∗ tFNSysInfo)(nasSysInfo ∗pNasSysInfo)
- typedef void(∗ tFNNetworkTime)(nasNetworkTime ∗pNasNetworkTime)
- typedef union sessionInfo sessionInformation
- typedef union sessionInfoExt sessionInformationExt
- typedef void(∗ tFNMemoryFull)(SMSMemoryInfo ∗pSMSMemoryFullInfo)
- typedef void(∗ tFNOTASPStatus)(voiceOTASPStatusInfo ∗pVoiceOTASPStatusInfo)
- typedef void(∗ tFNInfoRec)(voiceInfoRec ∗pVoiceInfoRec)
- typedef void(∗ tFNMessageWaiting)(msgWaitingInfo ∗pSMSMessageWaitingInfo)
- typedef void(∗ tFNSLQSQOSEvent)(BYTE instance, QosFlowInfo ∗pFlowInfo)
- typedef void(∗ tFNQosStatus)(BYTE instance, ULONG id, BYTE status, BYTE event, BYTE reason)
- typedef void(∗ tFNQosNWStatus)(BYTE status)
- typedef void(∗ tFNQosPriEvent)(WORD event)
- typedef void(∗ tFNSigInfo)(nasSigInfo ∗pNasSigInfo)
- typedef struct _modemTempNotification modemTempNotification
- typedef void(∗ tFNModemTempInfo)(modemTempNotification ∗pModemTempNotification)
- typedef struct _packetSrvStatus packetSrvStatus
- typedef void(∗ tFNPacketSrvState)(packetSrvStatus ∗pPacketSrvStatus)
- typedef void(∗ tFNHDRPersonaity)(HDRPersonalityInd ∗pHDRPers)
- typedef void(∗ tFNImsSIPConfig)(imsSIPConfigInfo ∗pImsSIPConfigInfo)
- typedef void(∗ tFNImsRegMgrConfig)(imsRegMgrConfigInfo ∗pImsRegMgrConfigInfo)
- typedef void(∗ tFNImsSMSConfig)(imsSMSConfigInfo ∗pImsSMSConfigInfo)
- typedef void(∗ tFNImsUserConfig)(imsUserConfigInfo ∗pImsUserConfigInfo)
- typedef void(∗ tFNImsVoIPConfig)(imsVoIPConfigInfo ∗pImsVoIPConfigInfo)
- typedef void(∗ tFNUSSDNoWaitIndication)(USSDNoWaitIndicationInfo ∗pNetworkInfo)
- typedef void(∗ tFNDUNCallInfo)(DUNCallInfoInd ∗pDUNCallInfo)
- typedef void(∗ tFNDataSysStatus)(CurrDataSysStat ∗pCurrDataSysStat)
- typedef struct SMSAsyncRawSend_s SMSAsyncRawSend
- typedef void(∗ tFNAsyncRawSend)(SMSAsyncRawSend ∗pSMSAsyncRawSend)
- typedef struct LteNasReleaseInfo_s LteNasReleaseInfo
- typedef struct SwiOTAMsg_s SwiOTAMsg
- typedef void(∗ tFNASwiOTAMsg)(SwiOTAMsg ∗pSwiOTAMsg)
- typedef void(∗ tFNNewGPS)(double dLongitude, double dLatitude, BYTE session_status, ULONG pos_src)
- typedef void(∗ tFNNewRMTransferStatistics)(QmiCbkWdsStatisticsIndState ∗pMsg)
- typedef void(∗ tFNDHCPv4ClientLeaseStatus)(BYTE instance, WdsDHCPv4ClientLeaseInd ∗pMsg)
- typedef void(∗ tFNSetCradleMount)(QmiCbkLocCradleMountInd ∗pSetLocCradleMount)
- typedef void(∗ tFNSetEventTimeSync)(QmiCbkLocEventTimeSyncInd ∗pSetLocEventTimeSync)
- typedef void(∗ tFNInjectTimeStatus)(QmiCbkLocInjectTimeInd ∗pLocInjectTime)
- typedef struct accelAcceptReady_s accelAcceptReady
- typedef struct gyroAcceptReady_s gyroAcceptReady
- typedef struct accelTempAcceptReady_s accelTempAcceptReady
- typedef struct gyroTempAcceptReady_s gyroTempAcceptReady
- typedef void(∗ tFNSensorStreaming)(QmiCbkLocSensorStreamingInd ∗pLocSensorStream)

- typedef void(∗ tFNInjectSensorData)(QmiCbkLocInjectSensorDataInd ∗pLocInjectSensorData)
- typedef struct precisionDilution_s precisionDilution
- typedef struct gpsTime_s gpsTime
- typedef struct sensorDataUsage_s sensorDataUsage
- typedef struct svUsedforFix_s svUsedforFix
- typedef void(∗ tFNEventPosition)(QmiCbkLocPositionReportInd ∗pLocPositionReport)
- typedef void(∗ tFNBestAvailPos)(QmiCbkLocBestAvailPosInd ∗pBestAvailPos)
- typedef void(∗ tFNOpMode)(QmiCbkLocOpModeInd ∗pLocOpmode)
- typedef void(∗ tFNImsaRegStatus)(imsaRegStatusInfo ∗pImsaRegStatusInfo)
- typedef void(∗ tFNImsaSvcStatus)(imsaSvcStatusInfo ∗pImsaSvcStatusInfo)
- typedef void(∗ tFNImsaRatStatus)(imsaRatStatusInfo ∗pImsaRatStatusInfo)
- typedef void(∗ tFNImsaPdpStatus)(imsaPdpStatusInfo ∗pImsaPdpStatusInfo)
- typedef void(∗ tFNGnssSvInfo)(gnssSvInfoNotification ∗pGnssSvInfoNotification)
- typedef void(∗ tFNDelAssistData)(delAssistDataStatus ∗pAssistDataNotification)
- typedef void(∗ tFNASwiLTECphyCaInfo)(QmiCbkNasLTECphyCaInfo ∗pQmiCbkNasLTECphyCaInfo)
- typedef void(∗ tFNRankIndicator)(RankIndicatorInd ∗pRankIndicatorInd)
- typedef void(∗ tFNInjectUTCTime)(QmiCbkLocInjectUTCTimeInd ∗pInjectUTCTimeNotification)
- typedef void(∗ tFNInjectPosition)(QmiCbkLocInjectPositionInd ∗pInjectPositionNotification)
- typedef void(∗ tFNCbkUimSlotStatusChangeInd)(UIMSlotStatusChangeInfo ∗pQmiCbkUimSlotStatus-ChangeInd)
- typedef void(∗ tFNSetEngineState)(QmiCbkLocEngineStateInd ∗pSetLocEngineState)
- typedef struct _getResetInfoNotification ResetInfoNotification
- typedef void(∗ tFNResetInfo)(ResetInfoNotification ∗pResetInfoNotification)
- typedef void(∗ tFNMitiLvlRpt)(QmiCbkTmdMitiLvlRptInd ∗pSetLocCradleMount)
- typedef void(∗ tFNSetExtPowerConfig)(QmiCbkLocSetExtPowerConfigInd ∗pSetExtConfigIndStatus)
- typedef void(∗ tFNNasTimer)(nasTimers ∗timers)
- typedef void(∗ tFNNetworkReject)(nasNetworkReject ∗pNetworkReject)
- typedef struct _SwiAvmsEventInd SwiAvmsEventInd
- typedef void(∗ tFNSwiAvmEventReport)(SwiAvmsEventInd ∗pEvent)
- typedef void(∗ tFNEventNmea)(QmiCbkLocEventNMEAInd ∗pNMEAEventData)
- typedef void(∗ tFNGetServer)(QmiCbkLocGetServerInd ∗pGetLocServerInfo)
- typedef void(∗ tFNPSMCfgParamChange)(dmsPsmCfgParamChange ∗pPSMCfgParamInd)
- typedef void(∗ tFNSetServer)(QmiCbkLocSetServerInd ∗pSetLocServerInfo)
- typedef struct _modemUIMStatusNotification modemUIMStatusNotification
- typedef void(∗ tFNUIMStatusInfo)(modemUIMStatusNotification ∗pmodemUIMStatusNotification)
- typedef void(∗ tFNNasEdrxChangeInfo)(QmiCbkNasEdrxChangeInfo ∗pQmiCbkNasEdrxChangeInfo)
- typedef void(∗ tFNGetOpMode)(QmiCbkLocGetOpModeInd ∗pLocGetOpMode)

Enumerations

- enum eQaQMIService {
  eQA_QMI_SVC_WDS = 0x01,
  eQA_QMI_SVC_NAS = 0x03,
  eQA_QMI_SVC_NA = 0xFF }
- enum SMSEventType {
  SMS_EVENT_MT_MESSAGE = 0x01,
  SMS_EVENT_TRANSFER_ROUTE_MT_MESSAGE = 0x02,
  SMS_EVENT_MESSAGE_MODE = 0x04,
  SMS_EVENT_ETWS = 0x08,
  SMS_EVENT_ETWS_PLMN = 0x10,
  SMS_EVENT_SMSC_ADDRESS = 0x20,
  SMS_EVENT_SMS_ON_IMS = 0x40 }

- enum device_state_enum {
  DEVICE_STATE_DISCONNECTED,
  DEVICE_STATE_READY,
  DEVICE_STATE_BOOT,
  DEVICE_STATE_SERIAL_ONLY }
- enum TYPE_OF_SERVICE_DOMAIN {
  SYS_SRV_DOMAIN_NO_SRV = 0x00,
  SYS_SRV_DOMAIN_CS_ONLY = 0x01,
  SYS_SRV_DOMAIN_PS_ONLY = 0x02,
  SYS_SRV_DOMAIN_CS_PS = 0x03,
  SYS_SRV_DOMAIN_CAMPED = 0x04 }

Functions

- ULONG SLQSSetSessionStateCallback (tFNSLQSSessionState pCallback)
- ULONG SLQSSetWdsEventCallback (tFNSLQSWDSEvent pCallback, BYTE interval, BYTE instanceid, BYTE ipfamily)
- ULONG SLQSSetWdsTransferStatisticCallback (tFNSLQSWDSEvent pXferStatsCb, BYTE interval, BYTE instanceid, BYTE ipfamily)
- ULONG iSLQSSetWdsFirstInstEventCallback (tFNSLQSWDSEvent pCallback)
- ULONG iSLQSSetWdsSecondInstEventCallback (tFNSLQSWDSEvent pCallback)
- ULONG iSLQSSetWdsThirdInstEventCallback (tFNSLQSWDSEvent pCallback)
- ULONG iSLQSSetWdsXferStatsFirstInstCallback (tFNSLQSWDSEvent pCallback)
- ULONG iSLQSSetWdsXferStatsSecondInstCallback (tFNSLQSWDSEvent pCallback)
- ULONG SetPowerCallback (tFNPower pCallback)
- ULONG SetActivationStatusCallback (tFNActivationStatus pCallback)
- ULONG SetMobileIPStatusCallback (tFNMobileIPStatus pCallback)
- ULONG SetRoamingIndicatorCallback (tFNRoamingIndicator pCallback)
- ULONG SetDataCapabilitiesCallback (tFNDataCapabilities pCallback)
- ULONG SetSignalStrengthCallback (tFNSignalStrength pCallback, BYTE thresholdsSize, INT8 *pThresholds)
- ULONG iSetSignalStrengthCallback (tFNSignalStrength pCallback)
- ULONG SetRFInfoCallback (tFNRFInfo pCallback)
- ULONG SetLURejectCallback (tFNLUReject pCallback)
- ULONG SetNewSMSCallback (tFNNewSMS pCallback)
- ULONG SLQSSetSMSEventCallback (tFNSMSEvents pCallback)
- ULONG SetNMEACallback (tFNNewNMEA pCallback)
- ULONG SetPDSStateCallback (tFNPDSState pCallback)
- ULONG SetCATEventCallback (tFNCATEvent pCallback, ULONG eventMask, ULONG *pErrorMask)
- ULONG iSetCATEventCallback (tFNCATEvent pCallback)
- ULONG SetDeviceStateChangeCbk (tFNDeviceStateChange pCallback)
- ULONG SetNetChangeCbk (BYTE instance, tFNNet pCallback, ULONG loMark, ULONG hiMark, ULONG period)
- ULONG SetFwDldCompletionCbk (tFNFwDldCompletion pCallback)
- ULONG SetSLQSOMADMAlertCallback (tFNSLQSOMADMAlert pCallback)
- ULONG SetSLQSOMADMAlertCallbackExt (tFNSLQSOMADMAlert pCallback)
- ULONG SetOMADMStateCallback (tFNOMADMState pCallback)
- ULONG SLQSSetServingSystemCallback (tFNServingSystem pCallback)
- ULONG SLQSSetBandPreferenceCbk (tFNBandPreference pCallback)
- ULONG SetUSSDReleaseCallback (tFNUSSDRelease pCallback)
- ULONG SetUSSDNotificationCallback (tFNUSSDNotification pCallback)
- ULONG SLQSSetSignalStrengthsCallback (tFNSLQSSignalStrengths pCallback, struct SLQSSignalStrengthsIndReq *pSLQSSignalStrengthsIndReq)
- ULONG iSLQSSetSignalStrengthsCallback (tFNSLQSSignalStrengths pCallback)
- ULONG SLQSVoiceSetSUPSNotificationCallback (tFNSUPSNotification pCallback)

- ULONG SLQSSetSDKTerminatedCallback (tFNSDKTerminated pCallback)
- ULONG SLQSVoiceSetAllCallStatusCallBack (tFNAllCallStatus pCallback)
- ULONG SLQSSetTransLayerInfoCallback (tFNtransLayerInfo pCallback)
- ULONG SLQSSetTransNWRegInfoCallback (tFNtransNWRegInfo pCallback)
- ULONG SLQSSetSysSelectionPrefCallBack (tFNSysSelectionPref pCallback)
- ULONG SLQSUIMSetRefreshCallBack (tFNUIMRefresh pCallback)
- ULONG SLQSUIMSetStatusChangeCallBack (tFNUIMStatusChangeInfo pCallback)
- ULONG SLQSVoiceSetPrivacyChangeCallBack (tFNPrivacyChange pCallback)
- ULONG SLQSVoiceSetDTMFEventCallBack (tFNDTMFEvent pCallback)
- ULONG SLQSVoiceSetSUPSCallBack (tFNSUPSInfo pCallback)
- ULONG SLQSNasSysInfoCallBack (tFNSysInfo pCallback)
- ULONG SLQSNasNetworkTimeCallBack (tFNNetworkTime pCallback)
- ULONG SLQSWmsMemoryFullCallBack (tFNMemoryFull pCallback)
- ULONG SLQSVoiceSetOTASPStatusCallBack (tFNOTASPStatus pCallback)
- ULONG SLQSVoiceInfoRecCallback (tFNInfoRec pCallback)
- ULONG SLQSWmsMessageWaitingCallBack (tFNMessageWaiting pCallback)
- ULONG SLQSSetQosEventCallback (BYTE instance, tFNSLQSQOSEvent pCallback)
- ULONG SLQSSetQosStatusCallback (BYTE instance, tFNQosStatus pCallback)
- ULONG SLQSSetQosNWStatusCallback (tFNQosNWStatus pCallback)
- ULONG SLQSSetQosPriEventCallback (tFNQosPriEvent pCallback)
- ULONG SLQSNasSigInfoCallBack (tFNSigInfo pCallback, sigInfo *pSigInfo)
- ULONG SLQSSetModemTempCallback (tFNModemTempInfo pCallback)
- ULONG SLQSSetPacketSrvStatusCallback (tFNPacketSrvState pCallback)
- ULONG SLQSSetSwiHDRPersCallback (tFNHDRPersonaity pCallback)
- ULONG SLQSSetSIPConfigCallback (tFNImsSIPConfig pCallback)
- ULONG SLQSSetRegMgrConfigCallback (tFNImsRegMgrConfig pCallback)
- ULONG SLQSSetIMSSMSConfigCallback (tFNImsSMSConfig pCallback)
- ULONG SLQSSetIMSUserConfigCallback (tFNImsUserConfig pCallback)
- ULONG SLQSSetIMSVoIPConfigCallback (tFNImsVoIPConfig pCallback)
- ULONG SetUSSDNoWaitIndicationCallback (tFNUSSDNoWaitIndication pCallback)
- ULONG SLQSSetDUNCallInfoCallback (BYTE StatsPeriod, tFNDUNCallInfo pCallback)
- ULONG iSLQSSetDUNCallInfoCallback (tFNDUNCallInfo pCallback)
- ULONG SLQSSetDataSystemStatusCallback (tFNDataSysStatus pCallback)
- ULONG SLQSWmsAsyncRawSendCallBack (tFNAsyncRawSend pCallback)
- ULONG SLQSNasSwiOTAMessageCallback (NasSwiIndReg *req, tFNASwiOTAMsg pCallback)
- ULONG SetGPSCallback (tFNNewGPS pCallback)
- ULONG SetRMTransferStatisticsCallback (tFNNewRMTransferStatistics pCallback)
- ULONG SLQSSetDHCPv4ClientLeaseStatusCallback (SLQSSetDHCPv4ClientLeaseStatusCallbackParam *pSLQSSetDHCPv4ClientLeaseStatusCallbackParam)
- ULONG SetLocCradleMountCallback (tFNSetCradleMount pCallback)
- ULONG SetLocEventTimeSyncCallback (tFNSetEventTimeSync pCallback)
- ULONG SetLocInjectTimeCallback (tFNInjectTimeStatus pCallback)
- ULONG SetLocSensorStreamingCallback (tFNSensorStreaming pCallback)
- ULONG SetLocInjectSensorDataCallback (tFNInjectSensorData pCallback)
- ULONG SetLocEventPositionCallback (tFNEventPosition pCallback)
- ULONG SetLocOpModeCallback (tFNOpMode pCallback)
- ULONG SLQSSetIMSARegStatusCallback (tFNImsaRegStatus pCallback)
- ULONG SLQSSetIMSASvcStatusCallback (tFNImsaSvcStatus pCallback)
- ULONG SLQSSetIMSARatStatusCallback (tFNImsaRatStatus pCallback)
- ULONG SLQSSetIMSAPdpStatusCallback (tFNImsaPdpStatus pCallback)
- ULONG SLQSNasSigInfo2CallBack (tFNSigInfo pCallback, setSignalStrengthInfo *pSigInfo2)
- ULONG SetLocGnssSvInfoCallback (tFNGnssSvInfo pCallback)
- ULONG SetLocDeleteAssistDataCallback (tFNDelAssistData pCallback)
- ULONG SetNasLTECphyCaIndCallback (tFNASwiLTECphyCaInfo pCallback)
- ULONG SetRankIndicatorCallback (tFNRankIndicator pCallback)

- ULONG SLQSSetLocInjectUTCTimeCallback (tFNInjectUTCTime pCallback)
- ULONG SLQSSetLocInjectPositionCallback (tFNInjectPosition pCallback)
- ULONG SetUimSlotStatusChangeCallback (tFNCbkUimSlotStatusChangeInd pCallback)
- ULONG SetLocEngineStateCallback (tFNSetEngineState pCallback)
- ULONG SLQSSetSwiGetResetInfoCallback (tFNResetInfo pCallback)
- ULONG SLQSTmdMitigationLvlRptCallback (SLQSTmdMitigationLvlRptCallbackParam *pSLQSTmdMitigationLvlRptCallbackParam)
- ULONG SetLocSetExtPowerConfigCallback (tFNSetExtPowerConfig pCallback)
- ULONG SetLocBestAvailPosCallback (tFNBestAvailPos pCallback)
- ULONG SLQSNasTimerCallback (tFNNasTimer pCallback)
- ULONG SLQSNasNetworkRejectCallback (tFNNetworkReject pCallback)
- ULONG SLQSSwiAVMSEventReportCallback (tFNSwiAvmEventReport pCallback)
- ULONG SetLocEventMaskNMEACallback (tFNEventNmea pCallback)
- ULONG SetLocGetServerCallback (SetLocGetServerCallbackPara *pSetLocGetServerCallbackPara)
- ULONG SetCfgParamChangeCallback (tFNPSMCfgParamChange pCallback)
- ULONG SetLocSetServerCallback (SetLocSetServerCallbackParam *pSetLocSetServerCallbackParam)
- ULONG SLQSSetUIMStatusCallback (tFNUIMStatusInfo pCallback)
- ULONG SLQSNasEdrxChangeInfoCallBack (tFNNasEdrxChangeInfo pCallback)
- ULONG SetLocGetOpModeCallback (tFNGetOpMode pCallback)

9.12.1 Detailed Description

Callback Service API function prototypes.

9.12.2 Macro Definition Documentation

9.12.2.1 #define CBK_DISABLE_EVENT 0x00

9.12.2.2 #define CBK_ENABLE_EVENT 0x01

9.12.2.3 #define CBK_NOCHANGE 0xFF

9.12.2.4 #define DEREGISTER_EVENT 0x00

9.12.2.5 #define DEREGISTER_SRV 0x00

9.12.2.6 #define DHCP_MAX_NUM_OPTIONS 30

9.12.2.7 #define DHCP_OPTION_DATA_BUF_SIZE 2048 /* current max size of raw message in SDK process is 2048 */

9.12.2.8 #define EVENT_MASK_CARD 0x00000001

9.12.2.9 #define EVENT_MASK_DEREGISTER_ALL 0x00000000

9.12.2.10 #define EVENT_MASK_PHY_SLOT_STATUS 0x00000010

9.12.2.11 #define FIRST_INSTANCE 0x00

9.12.2.12 #define INVALID_INSTACNE 0x08

9.12.2.13 #define IPV4 4

9.12.2.14 #define IPV4V6 7

9.12.2.15 #define IPV6 6

9.12.2.16 #define LOC_EVENT_MASK_ENG_STATE 0x00000080

9.12.2.17 #define LOC_EVENT_MASK_GNSS_SV_INFO 0x00000002

9.12.2.18 #define LOC_EVENT_MASK_INJECT_TIME 0x00000010

9.12.2.19 #define LOC_EVENT_MASK_NMEA 0x00000004

9.12.2.20 #define LOC_EVENT_MASK_SENSOR_STREAM 0x00000400

9.12.2.21 #define LOC_EVENT_MASK_TIME_SYNC 0x00000800

9.12.2.22 #define LOC_EVENT_POSITION_REPORT 0x00000001

9.12.2.23 #define MAX_MITIGATION_DEV_ID_LEN 255

9.12.2.24 #define MAX_NMEA_STR_LEN 201

9.12.2.25 #define MAX_NO_OF_APPLICATIONS 10

9.12.2.26 #define MAX_NO_OF_CALLS 20

9.12.2.27 #define MAX_NO_OF_FILES 255

9.12.2.28 #define MAX_NO_OF_SLOTS 5

9.12.2.29 #define MAX_NO_OF_UUSINFO 20

9.12.2.30 #define MAX_PATH_LENGTH 255

9.12.2.31 #define MAX_RADIO_INTERFACE_LIST 255

9.12.2.32 #define MAX_URL_ADDR_STR_LEN 256

9.12.2.33 #define MAXUSSDLENGTH 182

9.12.2.34 #define NAS_SRV 0x02

9.12.2.35 #define NUM_OF_SET 0xFF

9.12.2.36 #define PDS_SRV 0x04

9.12.2.37 #define QMI_ETWS_MAX_PAYLOAD_LENGTH 1254 /* Qualcomm defined max */

9.12.2.38 #define QMI_MAX_VOICE_NUMBER_LENGTH 81

9.12.2.39 #define QMI_WMS_MAX_PAYLOAD_LENGTH 256

9.12.2.40 #define REGISTER_EVENT 0x01

9.12.2.41 #define REGISTER_SRV 0x01

9.12.2.42 #define SECOND_INSTANCE 0x01

9.12.2.43 #define SIGSTRENGTH_THRESHOLD_ARR_SZ 5

9.12.2.44 #define THIRD_INSTANCE 0x02

9.12.2.45 #define USSD_DCS_8BIT 0x02 /∗ 8-bit coding scheme ∗/

9.12.2.46 #define USSD_DCS_ASCII 0x01 /∗ ASCII coding scheme ∗/

9.12.2.47 #define USSD_DCS_UCS2 0x03 /∗ UCS2 coding scheme ∗/

9.12.2.48 #define VOICE_SRV 0x08

9.12.2.49 #define WDS_SRV 0x01

9.12.3 Typedef Documentation

9.12.3.1 typedef struct accelAcceptReady_s accelAcceptReady

This structure contains Accelerometer Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

9.12.3.2 typedef struct accelTempAcceptReady_s accelTempAcceptReady

This structure contains Accelerometer Temperature Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

9.12.3.3 typedef enum device_state_enum eDevState

Device State enumeration

- See device_state_enum for more details

9.12.3.4 typedef enum SMSEventType eSMSEventType

This enumeration defines the different type of SMS events that are received

- See SMSEventType for more details

9.12.3.5 typedef struct gpsTime_s gpsTime

This structure contains GPS Time info.

Parameters

gpsWeek	• Current GPS week as calculated from midnight, Jan. 6, 1980. • Units - Weeks
gpsTimeOf-WeekMs	• Amount of time into the current GPS week. • Units - Milliseconds

9.12.3.6 typedef struct gyroAcceptReady_s gyroAcceptReady

This structure contains Gyroscope Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

9.12.3.7 typedef struct gyroTempAcceptReady_s gyroTempAcceptReady

This structure contains Gyroscope Temperature Accept Ready Info

Parameters

injectEnable	• GNSS location engine is ready to accept data from sensor. • Values • 0x01 - Ready to accept sensor data • 0x00 - Not ready to accept sensor data
samplesPer-Batch	• number of samples per batch the GNSS location engine is to receive. • samplingFrequency = samplesPerBatch ∗ batchesPerSecond • samplesPerBatch must be a nonzero positive value.
batchPerSec	• LTE NAS version minor • Number of sensor-data batches the GNSS location engine is to receive per second. • BatchesPerSecond must be a nonzero positive value.

9.12.3.8 typedef struct LteNasReleaseInfo_s LteNasReleaseInfo

This structure contains LTE Nas Release Infomation

Parameters

nas_release	• LTE NAS release
nas_major	• LTE NAS version major

nas_minor	• LTE NAS version minor

9.12.3.9 typedef struct _modemTempNotification modemTempNotification

Contains the parameters passed for SLQSSetModemTempCallback by the device.

Parameters

ModemTemp-State	• provides the temperature state of the modem • Values: – 0 - unknown – 1 - normal – 2 - high(warning) – 3 - high(critical) – 4 - low(critical)
Modem-Temperature	• provides the temperature of the modem

Note

None

9.12.3.10 typedef struct _modemUIMStatusNotification modemUIMStatusNotification

Contains the parameters passed for SLQSSetUIMStatusCallback by the device.

Parameters

ModemUIM-StatusInterface	• provides the temperature state of the modem • Values: – 0 - External UIM. – 1 - Embedded UIM. – 2 - Remote UIM.
ModemUIM-StatusEvent	• Values: – 0 - UIM card removed. – 1 - UIM card inserted.

Note

None

9.12.3.11 typedef struct _packetSrvStatus packetSrvStatus

Contains the parameters passed for SLQSSetPacketSrvStatusCallback by the device.

Parameters

pQmiInterface-Info	• See qaQmiInterfaceInfo for more information
connStatus	• Current Link Status – 1 - Disconnected – 2 - Connected – 3 - Suspended – 4 - Authenticating
reconfigReqd	• Indicates if the network interface on the host needs to be reconfigured – 0 - No need to reconfigure – 1 - Reconfiguration required
sessionEnd-Reason	• See qaGobiApiTableCallEndReasons.h for Call End Reason, 0xFFFF means invalid value
verboseSessn-EndReasonType	• Call End Reason Type – 0 - Unspecified – 1 - Mobile IP – 2 - Internal – 3 - Call Manager defined – 6 - 3GPP Specification defined – 7 - PPP – 8 - EHRPD – 9 - IPv6 – 0xFFFF - invalid value
verboseSessn-EndReason	• See qaGobiApiTableCallEndReasons.h for verbose Call End Reason. The values depend on verboseSessnEndReasonType parameter 0xFFFF means invalid value
ipFamily	• IP Family of the packet data connection – 4 - IPv4 – 6 - IPv6 – 0xFF - invalid value

techName	• Technology name of the packet data connection. – 32767 - CDMA – 32764 - UMTS – 30592 - EPC – 30590 - EMBMS – 30584 - Modem Link Local – 0xFFFF - invalid value EPC is a logical interface to support LTE/eHRPD handoff. Modem Link is an interface for transferring data between entities on the AP and modem.
bearerID	• Bearer ID (3GPP) or RLP ID (3GPP2) of the packet data connection 0xFF means invalid value

Note

Any parameter not returned by the device is returned as its maximum unsigned value by the callback.

9.12.3.12 typedef struct precisionDilution_s precisionDilution

This structure contains Dilution of precision associated with this position.

Parameters

PDOP	• Position dilution of precision. • Range - 1 (highest accuracy) to 50 (lowest accuracy) • PDOP = square root of (Square of HDOP + Square of VDOP2)
HDOP	• Horizontal dilution of precision. • Range - 1 (highest accuracy) to 50 (lowest accuracy)
VDOP	• Vertical dilution of precision. • Range- 1 (highest accuracy) to 50 (lowest accuracy)

9.12.3.13 typedef struct _getResetInfoNotification ResetInfoNotification

Contains the parameters passed for SLQSSetSwiGetResetInfoCallback by the device.

Parameters

type	• type of reset or power down, possible values listed below: – 0 - unknown – 1 - warm – 2 - hard – 3 - crash – 4 - power down

source	• entity which initiated the reset or power down, possible values listed below: – 0 - unknown – 1 - user requested – 2 - hardware switch – 3 - temperature critical – 4 - voltage critical – 5 - configuration update – 6 - LWM2M – 7 - OMA-DM – 8 - FOTA

Note

None

9.12.3.14 typedef struct sensorDataUsage_s sensorDataUsage

This structure contains Sensor Data Usage info.

Parameters

usageMask	• Specifies which sensors were used in calculating the position in the position report.

- Value
  - 0x00000001 - Accelerometer used
  - 0x00000002 - Gyroscope used

Parameters

aidingIndicator-Mask	

  - Specifies which results were aided by sensors.

- Value
  - 0x00000001 - AIDED_HEADING
  - 0x00000002 - AIDED_SPEED
  - 0x00000004 - AIDED_POSITION
  - 0x00000008 - AIDED_VELOCITY

9.12.3.15 typedef union sessionInfo sessionInformation

This union sessionInfo consist of omaDmFotaTlv, omaDmConfigTlv and omaDmNotificationsTlv, out of which one will be unpacked against pEventFields.

9.12.3.16 typedef union sessionInfoExt sessionInformationExt

This union sessionInfo consist of omaDmFotaTlv and omaDmConfigTlv, out of which one will be unpacked against pEventFields.

9.12.3.17 typedef struct SMSAsyncRawSend_s SMSAsyncRawSend

This structure contains SMS parameters

Parameters

sendStatus	• Send Status • Values: – QMI_ERR_NONE - No error in the request – QMI_ERR_CAUSE_CODE - SMS cause code – QMI_ERR_MESSAGE_DELIVERY_FAILURE - Message could not be delivered – QMI_ERR_NO_MEMORY - Device could not allocate memory to formulate a response
messageID	• Unique ID assigned by WMS for non-retry messages.
causeCode	• WMS cause code
errorClass	• Error Class • Values: – 0x00 - ERROR_CLASS_TEMPORARY – 0x01 - ERROR_CLASS_PERMANENT
RPCause	• GW RP cause
TPCause	• GW TP Cause
msgDelFailure-Type	• Message delivery failure type • Values: – 0x00 - WMS_MESSAGE_DELIVERY_FAILURE_TEMPORARY – 0x01 - WMS_MESSAGE_DELIVERY_FAILURE_PERMANENT
msgDelFailure-Cause	• Message delivery failure cause • Values: – 0x00 - WMS_MESSAGE_BLOCKED_DUE_TO_CALL_CONTROL
alphaIDLen	• Number of sets of the pAlphaID
pAlphaID	• Alpha ID

userData	• Identifies the request associated with this indication.

9.12.3.18 typedef struct SMSCAddress SMSCAddressInfo

This structure holds SMSC information

Parameters

length	• Number of sets of following element
data	• SMSC address

9.12.3.19 typedef struct SMSEtwsMessage SMSEtwsMessageInfo

This structure holds information related earthquake and Tsunami warning system

Parameters

notificationType	• Message mode 0x00 - Primary 0x01 - Secondary GSM 0x02 - Secondary UMTS
length	• Number of sets of following elements
data	• Raw message data

9.12.3.20 typedef struct SMSEtwsPlmn SMSEtwsPlmnInfo

This structure holds information related ETWS PLMN

Parameters

mobileCountry-Code	• 16 bit representation of MCC value range : 0 -999
mobileNetwork-Code	• 16 bit representation of MNC value range : 0 -999

9.12.3.21 typedef struct SMSEventInfo_s SMSEventInfo

This structure will hold the information related to received SMS events

Parameters

smsEventType	• Type of the SMS events that are received. This is a bit map of SMSEventType. Only the parameters (which follows) related to the events received would be filled, and the rest of the parameters would be NULL
pMTMessage-Info	• pointer to the SMSMTMessageInfo structure NULL, if this event is not present in the smsEventType parameter
pTransferRoute-MTMessageInfo	• pointer to the SMSTransferRouteMTMessageInfo structure . NULL, if this event is not present in the smsEventType parameter
pMessageMode-Info	• pointer to the SMSMessageModeInfo structure NULL, if this event is not present in the smsEventType parameter
pEtwsMessage-Info	• pointer to the SMSEtwsMessageInfo structure NULL, if this event is not present in the smsEventType parameter
pEtwsPlmnInfo	• pointer to the SMSEtwsPlmnInfo structure NULL, if this event is not present in the smsEventType parameter
pSMSCAddress-Info	• pointer to the SMSCAddressInfo structure NULL, if this event is not present in the smsEventType parameter
pSMSOnIMSInfo	• pointer to the SMSOnIMSInfo structure NULL, if this event is not present in the smsEventType parameter Note: None

9.12.3.22 typedef struct SMSMessageMode SMSMessageModeInfo

This structure holds information related to message mode

Parameters

messageMode	• Message mode 0x00 - CDMA 0x01 - GW

9.12.3.23 typedef struct SMSMTMessage SMSMTMessageInfo

This structure holds information related to MT SMS

Parameters

storageType	• SMS message storage type for the new message 0 - UIM 1 - NV

messageIndex	• Index of the new message

9.12.3.24 typedef struct SMSOnIMS SMSOnIMSInfo

This structure holds information related to message mode

Parameters

smsOnIMS	• Indicates whether the message is received from IMS 0x00 - Message is not received from IMS 0x01 - Message is received from IMS 0x02-0xFF - Reserved Note: In multiple modem solutions, this TLV may be used to help the client determine with which modem to communicate. This TLV may not be supported on all implementations.

9.12.3.25 typedef struct SMSTransferRouteMTMessage SMSTransferRouteMTMessageInfo

This structure holds information related to transfer route MT SMS

Parameters

ackIndicator	• Parameter to indicate if ACK must be sent by the control point 0x00 - Send ACK 0x01 - Do not send ACK
transactionID	• Transaction ID of the message
format	• Message format 0x00 - CDMA 0x02 - 0x05 - Reserved 0x06 - GW_PP 0x07 - GW_BC
length	• Length of the raw message. This length should not exceed the maximum WMS payload length of 256 bytes
data	• Raw message data

9.12.3.26 typedef struct svUsedforFix_s svUsedforFix

This structure contains SVs Used to Calculate the Fix.

Parameters

gnssSvUsedList-_len	• Number of sets of gnssSvUsedList
pGnssSvUsed-List	• Entry in the list contains the SV ID of a satellite used for calculating this position report. • Following information is associated with each SV ID: – GPS - 1 to 32 – SBAS - 33 to 64 – GLONASS - 65 to 96 – QZSS - 193 to 197 – BDS - 201 to 237

9.12.3.27 typedef struct _SwiAvmsEventInd SwiAvmsEventInd

9.12.3.28 typedef struct SwiOTAMsg_s SwiOTAMsg

This structure contains OTA message

Parameters

type	• message type – 0 - LTE ESM uplink – 1 - LTE ESM downlink – 2 - LTE EMM uplink – 3 - LTE EMM downlink – 4 - GSM/UMTS uplink – 5 - GSM/UMTS downlink
data_len	• OTA Message Content Length
data	• OTA Message Content
pLteNasRelInfo	• LTE NAS Release Info • see LteNasReleaseInfo for details
pTime	• Seconds in local time since Jan. 6th 1980 00:00:00 UTC

9.12.3.29 typedef void(∗ tFNActivationStatus)(ULONG activationStatus)

Activation status callback function.

Parameters

activationStatus	• Service Activation Code – 0 - Service not activated – 1 - Service activated – 2 - Activation connecting – 3 - Activation connected – 4 - OTASP security authenticated – 5 - OTASP NAM downloaded – 6 - OTASP MDN downloaded – 7 - OTASP IMSI downloaded – 8 - OTASP PRL downloaded – 9 - OTASP SPC downloaded – 10 - OTASP settings committed

9.12.3.30 typedef void(∗ tFNAllCallStatus)(voiceSetAllCallStatusCbkInfo ∗pVoiceSetAllCallStatusCbkInfo)

Voice Call Status Callback function. This function pointer will be executed to process received Indication.

Parameters

pVoiceSetAll-CallStatusCbk-Info	• Call back will populated memory pointed by this parameter when a call is originated, connected, or ended. See voiceSetAllCallStatusCbkInfo for more information.

9.12.3.31 typedef void(∗ tFNASwiLTECphyCaInfo)(QmiCbkNasLTECphyCaInfo ∗pQmiCbkNasLTECphyCaInfo)

LTE CPHY CA message callback function.

Parameters

pQmiCbkNasLT-ECphyCaInfo[O-UT]	• Events related to NAS, see QmiCbkNasLTECphyCaInfo for details.

9.12.3.32 typedef void(∗ tFNASwiOTAMsg)(SwiOTAMsg ∗pSwiOTAMsg)

OTA message callback function.

Parameters

pSwiOTAMsg[O-UT]	• Events related to NAS, see SwiOTAMsg for details

9.12.3.33 typedef void(∗ tFNAsyncRawSend)(SMSAsyncRawSend ∗pSMSAsyncRawSend)

SMS event related callback function.

Parameters

pSMSEventInfo[-OUT]	• Events related to SMS, see SMSEventInfo for details

9.12.3.34 typedef void(∗ tFNBandPreference)(ULONGLONG band_pref)

Band Preference Callback function

Parameters

pBandPref	- Bit mask representing the current band preference Bit position meanings: • 0 - BC0_A - Band Class 0, A-System • 1 - BC0_B - Band Class 0, B-System, Band Class 0 AB , GSM 850 Band • 2 - BC1 - Band Class 1, all blocks • 3 - BC2 - Band Class 2 place holder • 4 - BC3 - Band Class 3, A-System • 5 - BC4 - Band Class 4, all blocks • 6 - BC5 - Band Class 5, all blocks • 7 - GSM_DCS_1800 - GSM DCS band • 8 - GSM_EGSM_900 - GSM Extended GSM (E-GSM) band • 9 - GSM_PGSM_900 - GSM Primary GSM (P-GSM) band • 10 - BC6 - Band Class 6 • 11 - BC7 - Band Class 7 • 12 - BC8 - Band Class 8 • 13 - BC9 - Band Class 9 • 14 - BC10 - Band Class 10 • 15 - BC11 - Band Class 11 • 16 - GSM_450 - GSM 450 band • 17 - GSM_480 - GSM 480 band • 18 - GSM_750 - GSM 750 band • 19 - GSM_850 - GSM 850 band • 20 - GSM_RGSM_900 - GSM Railways GSM Band • 21 - GSM_PCS_1900 - GSM PCS band • 22 - WCDMA_I_IMT_2000 - WCDMA EUROPE JAPAN and CHINA IMT 2100 band • 23 - WCDMA_II_PCS_1900 - WCDMA US PCS 1900 band • 24 - WCDMA_III_1700 - WCDMA EUROPE and CHINA DCS 1800 band • 25 - WCDMA_IV_1700 - WCDMA US 1700 band • 26 - WCDMA_V_850 - WCDMA US 850 band • 27 - WCDMA_VI_800 - WCDMA JAPAN 800 band • 28 - BC12 - Band Class 12 • 29 - BC14 - Band Class 14 • 30 - RESERVED_2 - Reserved 2 • 31 - BC15 - Band Class 15 • 32 - 47 - Reserved • 48 - WCDMA_VII_2600 - WCDMA EUROPE 2600 band • 49 - WCDMA_VIII_900 - WCDMA EUROPE and JAPAN 900 band • 50 - WCDMA_IX_1700 - WCDMA JAPAN 1700 band • 51 to 55 - Reserved • 56 - BBC16 - Band Class 16 • 57 - BC17 - Band Class 17 • 58 - BC18 - Band Class 18 • 59 - BC19 - Band Class 19 • 60 to 64 - Reserved

Note

Timeout: NA To set the band preference the API SLQSSetBandPreference() should be used

9.12.3.35 typedef void(∗ tFNBestAvailPos)(QmiCbkLocBestAvailPosInd ∗pBestAvailPos)

Best available position callback function.

Parameters

pBestAvailPos[-OUT]	• Events related to LOC, see QmiCbkLocBestAvailPosInd for details

9.12.3.36 typedef void(∗ tFNCATEvent)(ULONG eventID, ULONG eventLen, BYTE ∗pEventData)

CAT event callback function.

Parameters

eventID	• Event ID – 16 - Display Text – 17 - Get In-Key – 18 - Get Input – 19 - Setup Menu – 20 - Select Item – 21 - Send SMS - Alpha Identifier – 22 - Setup Event List – 23 - Setup Idle Mode Text – 24 - Language Notification – 25 - Refresh – 26 - End Proactive Session
eventLen	• Length of pData (in bytes)
pEventData	• Data specific to the CAT event ID See currentCatEvent for details

Note

Technology Supported: UMTS

9.12.3.37 typedef void(∗ tFNCbkUimSlotStatusChangeInd)(UIMSlotStatusChangeInfo ∗pQmiCbkUimSlotStatusChangeInd)

Slot Status Change Notification callback.

Parameters

pQmiCbkUim-SlotStatus-ChangeInd	• See UIMSlotStatusChangeInfo for more information.

9.12.3.38 typedef void(∗ tFNDataCapabilities)(BYTE dataCapsSize, BYTE ∗pDataCaps)

Serving system data capabilities callback function.

Parameters

dataCapsSize	• Number of elements the data capability array contains
pDataCaps	• Data Capabilities Array. – 1 - GPRS – 2 - EDGE – 3 - HSDPA – 4 - HSUPA – 5 - WCDMA – 6 - CDMA 1xRTT – 7 - CDMA 1xEV-DO Rev 0 – 8 - CDMA 1xEV-DO Rev. A – 9 - GSM – 10 - EVDO Rev. B – 11 - LTE – 12 - HSDPA Plus – 13 - Dual Carrier HSDPA Plus

9.12.3.39 typedef void(∗ tFNDataSysStatus)(CurrDataSysStat ∗pCurrDataSysStat)

Data System Status callback.

Parameters

pCurrDataSys-Stat	• See CurrDataSysStat for more information.

9.12.3.40 typedef void(∗ tFNDelAssistData)(delAssistDataStatus ∗pAssistDataNotification)

Delete Assist Data Notification callback.

Parameters

pAssistData-Notification	• See delAssistDataStatus for more information.

9.12.3.41 typedef void(∗ tFNDeviceStateChange)(eDevState device_state)

Device State Change callback function prototype

Parameters

device_state	• the current state of the device

Note

Does not require communication with the device

9.12.3.42 typedef void(∗ tFNDHCPv4ClientLeaseStatus)(BYTE instance, WdsDHCPv4ClientLeaseInd ∗pMsg)

DHCPv4 client lease status message callback function.

Parameters

pMsg[OUT]	• Events related to DHCPv4 client lease, see WdsDHCPv4ClientLeaseInd for details

9.12.3.43 typedef void(∗ tFNDTMFEvent)(voiceDTMFEventInfo ∗pVoiceDTMFEventInfo)

Preferred DTMF event indication callback.

Parameters

pVoiceDTMF-EventInfo	• See voiceDTMFEventInfo for more information.

9.12.3.44 typedef void(∗ tFNDUNCallInfo)(DUNCallInfoInd ∗pDUNCallInfo)

DUN Call Info indication callback.

Parameters

pDUNCallInfo	• See DUNCallInfoInd for more information.

9.12.3.45 typedef void(∗ tFNEventNmea)(QmiCbkLocEventNMEAInd ∗pNMEAEventData)

Get LOC NMEA Event Data callback.

Parameters

pNMEAEvent-Data	• See QmiCbkLocEventNMEAInd for more information.

9.12.3.46 typedef void(∗ tFNEventPosition)(QmiCbkLocPositionReportInd ∗pLocPositionReport)

Position report callback function.

Parameters

pLocPosition-Report[OUT]	• Events related to LOC, see QmiCbkLocPositionReportInd for details

9.12.3.47 typedef void(∗ tFNFwDldCompletion)(ULONG fwdld_completion_status)

Firmware Download Completion callback function prototype

Parameters

error_code	• error code returned from firmware download operation, the possible return values are listed below: – eQCWWAN_ERR_NONE - indicates firmware download/switching is successful – eQCWWAN_ERR_SWIIM_FIRMWARE_NOT_DOWNLOADED - indicates no actual download takes place, this is the case of image switching stored on device – eQCWWAN_ERR_SWIIM_FW_ENTER_DOWNLOAD_MODE - indicates modem enters firmware download mode, firmware flashing is going to be started. – eQCWWAN_ERR_SWIIM_FW_FLASH_COMPLETE - indicates firmware flashing was complete, SDK is waiting for modem to reboot (can be more than one time), when modem is ready, SDK will send eQCWWAN_ERR_NONE to the host application.

Note

Does not require communication with the device

9.12.3.48 typedef void(∗ tFNGetOpMode)(QmiCbkLocGetOpModeInd ∗pLocGetOpMode)

LOC Get operating mode callback function.

Parameters

pLocGetOp-Mode[OUT]	• Events related to LOC, see QmiCbkLocGetOpModeInd for details

9.12.3.49 typedef void(∗ tFNGetServer)(QmiCbkLocGetServerInd ∗pGetLocServerInfo)

Get LOC Server Indication callback.

Parameters

pGetLocServer-Info	• See QmiCbkLocGetServerInd for more information.

9.12.3.50 typedef void(∗ tFNGnssSvInfo)(gnssSvInfoNotification ∗pGnssSvInfoNotification)

GNSS SVN Information Notification callback.

Parameters

pGnssSvInfo-Notification	• See gnssSvInfoNotification for more information.

9.12.3.51 typedef void(∗ tFNHDRPersonaity)(HDRPersonalityInd ∗pHDRPers)

HDR Personality indication callback.

Parameters

pHDRPers	• See HDRPersonalityInd for more information.

Note

Technology Supported: CDMA

9.12.3.52 typedef void(∗ tFNImsaPdpStatus)(imsaPdpStatusInfo ∗pImsaPdpStatusInfo)

IMSA PDP status indication callback.

Parameters

pImsaPdp-StatusInfo	• See imsaPdpStatusInfo for more information.

9.12.3.53 typedef void(∗ tFNImsaRatStatus)(imsaRatStatusInfo ∗pImsaRatStatusInfo)

IMSA RAT handover status indication callback.

Parameters

pImsaRatStatus-Info	• See imsaRatStatusInfo for more information.

9.12.3.54 typedef void(∗ tFNImsaRegStatus)(imsaRegStatusInfo ∗pImsaRegStatusInfo)

IMSA Registration Status indication callback.

Parameters

pImsaReg-StatusInfo	• See imsaRegStatusInfo for more information.

9.12.3.55 typedef void(* tFNImsaSvcStatus)(imsaSvcStatusInfo *pImsaSvcStatusInfo)

IMSA Service Status indication callback.

Parameters

pImsaSvcStatusInfo	• See imsaSvcStatusInfo for more information.

9.12.3.56 typedef void(* tFNImsRegMgrConfig)(imsRegMgrConfigInfo *pImsRegMgrConfigInfo)

IMS Reg Mgr Config indication callback.

Parameters

pImsRegMgrConfigInfo	• See imsRegMgrConfigInfo for more information.

9.12.3.57 typedef void(* tFNImsSIPConfig)(imsSIPConfigInfo *pImsSIPConfigInfo)

IMS SIP Config indication callback.

Parameters

pImsSIPConfigInfo	• See imsSIPConfigInfo for more information.

9.12.3.58 typedef void(* tFNImsSMSConfig)(imsSMSConfigInfo *pImsSMSConfigInfo)

IMS SMS Config indication callback.

Parameters

pImsSMSConfigInfo	• See imsSMSConfigInfo for more information.

9.12.3.59 typedef void(* tFNImsUserConfig)(imsUserConfigInfo *pImsUserConfigInfo)

IMS User Config indication callback.

Parameters

pImsUserConfigInfo	• See imsUserConfigInfo for more information.

9.12.3.60 typedef void(∗ tFNImsVoIPConfig)(imsVoIPConfigInfo ∗pImsVoIPConfigInfo)

IMS VoIP Config indication callback.

Parameters

pImsVoIPConfig-Info	• See imsVoIPConfigInfo for more information.

9.12.3.61 typedef void(∗ tFNInfoRec)(voiceInfoRec ∗pVoiceInfoRec)

Voice Information Record callback.

Parameters

pVoiceInfoRec	• See voiceInfoRec for more information.

Note

Technology Supported: CDMA
Device Supported: MC7750

9.12.3.62 typedef void(∗ tFNInjectPosition)(QmiCbkLocInjectPositionInd ∗pInjectPositionNotification)

Inject Position Notification callback.

Parameters

pInjectPosition-Notification	• See QmiCbkLocInjectPositionInd for more information.

9.12.3.63 typedef void(∗ tFNInjectSensorData)(QmiCbkLocInjectSensorDataInd ∗pLocInjectSensorData)

LOC Inject Sensor Data indication callback.

Parameters

pLocInject-SensorData	• See QmiCbkLocInjectSensorDataInd for more information.

9.12.3.64 typedef void(∗ tFNInjectTimeStatus)(QmiCbkLocInjectTimeInd ∗pLocInjectTime)

LOC Inject time status indication callback.

Parameters

pLocInjectTime	• See QmiCbkLocInjectTimeInd for more information.

9.12.3.65 typedef void(∗ tFNInjectUTCTime)(QmiCbkLocInjectUTCTimeInd ∗pInjectUTCTimeNotification)

Inject UTC Time Notification callback.

Parameters

pInjectUTCTime-Notification	• See QmiCbkLocInjectUTCTimeInd for more information.

9.12.3.66 typedef void(∗ tFNLUReject)(ULONG serviceDomain, ULONG rejectCause)

LU reject callback function.

Parameters

serviceDomain	• Service domain – 1 - Circuit Switched – 2 - Packet Switched – 3 - Circuit and Packet Switched

rejectCause	• Reject cause • Valid Values – 2 - IMSI unknown in HLR – 3 - Illegal MS – 4 - IMSI unknown in VLR – 5 - IMEI not accepted – 6 - Illegal ME – 7 - EPS services not allowed – 8 - EPS services and non-EPS services not allowed – 9 - UE identity cannot be derived by the network – 10 - Implicitly detached – 11 - PLMN not allowed – 12 - Location Area not allowed – 13 - Roaming not allowed in this location area – 14 - EPS services not allowed in this PLMN – 15 - No Suitable Cells In Location Area – 16 - MSC temporarily not reachable – 17 - Network failure – 18 - CS domain not available – 19 - ESM failure – 20 - MAC failure – 21 - Synch failure – 22 - Congestion – 23 - GSM authentication unacceptable – 24 - Security mode rejected, unspecified – 25 - Not authorized for this CSG – 26 - Non-EPS authentication unacceptable – 32 - Service option not supported – 33 - Requested service option not subscribed – 34 - Service option temporarily out of order – 38 - Call cannot be identified – 48 to 63 - retry upon entry into a new cell – 95 - Semantically incorrect message – 96 - Invalid mandatory information – 97 - Message type non-existent or not implemented – 98 - Message type not compatible with the protocol state – 99 - Information element non-existent or not implemented – 100 - Conditional IE error – 101 - Message not compatible with the protocol state – 111 - Protocol error, unspecified – Note - Any other value received by the mobile station shall be treated as 34, 'Service option temporarily out of order'. * Any other value received by the network shall be treated as 111, 'Protocol error, unspecified'. See 3GPP TS 24.008, Section 4.4.4.7 and Section 10.5.3.6 See qaGobiApiTableCallEndReasons.h for Call End reasons

Note

Technology Supported: UMTS

9.12.3.67 typedef void(∗ tFNMemoryFull)(SMSMemoryInfo ∗pSMSMemoryFullInfo)

SMS Memory related callback function.

Parameters

pSMSMemoryFullInfo[OUT]	• pointer to SMSMemoryInfo. • see SMSMemoryInfo for details.

9.12.3.68 typedef void(∗ tFNMessageWaiting)(msgWaitingInfo ∗pSMSMessageWaitingInfo)

SMS Memory related callback function.

Parameters

pSMSMessageWaitingInfo[OUT]	• pointer to msgWaitingInfo. • see msgWaitingInfo for details.

9.12.3.69 typedef void(∗ tFNMitiLvlRpt)(QmiCbkTmdMitiLvlRptInd ∗pSetLocCradleMount)

Set Loc cradle mount Indication callback.

Parameters

pSetLocCradleMount	• See QmiCbkTmdMitiLvlRptInd for more information.

9.12.3.70 typedef void(∗ tFNMobileIPStatus)(ULONG mipStatus)

Mobile IP status callback function.

Parameters

mipStatus	• Mobile IP Status – 0 - success – All others error codes as defined in RFC 2002 See qaGobiApiTableCallEndReasons.h for mobile IP error codes

9.12.3.71 typedef void(∗ tFNModemTempInfo)(modemTempNotification ∗pModemTempNotification)

Modem Temperature Information callback.

Parameters

pModemTemp-Notification	• See modemTempNotification for more information.

9.12.3.72 typedef void(∗ tFNNasEdrxChangeInfo)(QmiCbkNasEdrxChangeInfo ∗pQmiCbkNasEdrxChangeInfo)

Change in the eDRX value callback function.

Parameters

pQmiCbkNas-EdrxChange-Info[OUT]	• Events related to NAS, see QmiCbkNasEdrxChangeInfo for details.

9.12.3.73 typedef void(∗ tFNNasTimer)(nasTimers ∗timers)

Network timer Indication callback.

Parameters

timers	• See nasTimers for more information.

9.12.3.74 typedef void(∗ tFNNet)(ULONG q_depth, BYTE isThrottle, BYTE instanceId)

Transmit Queue Length Change callback function prototype

Parameters

q_depth	• transmit queue length
isThrottle	• 0: unthrottle • 1: throttle
instanceId	• qmi instance id

Note

Does not require communication with the device

9.12.3.75 typedef void(∗ tFNNetworkReject)(nasNetworkReject ∗pNetworkReject)

Network Reject Cause callback.

Parameters

pNasNetwork-Time	• See nasNetworkTime for more information.

9.12.3.76 typedef void(∗ tFNNetworkTime)(nasNetworkTime ∗pNasNetworkTime)

Network Time indication callback.

Parameters

pNasNetwork-Time	• See nasNetworkTime for more information.

9.12.3.77 typedef void(∗ tFNNewGPS)(double dLongitude, double dLatitude, BYTE session_status, ULONG pos_src)

Set Current Location Data.

Parameters

dLongitude[IN]	• Current Longitude Value
dLatitude[IN]	• Current Latitude Value
session_status[IN]	• Session Status – 0 - Success – 1 - In progress – 2 - General failure – 3 - Timeout – 4 - User ended the session – 5 - Bad parameter – 6 - Phone is offline – 7 - Engine is locked – 8 - E911 session in progress
pos_src[IN]	• position source • Bitmasks – 0x01 - GPS – 0x02 - Cell ID – 0x04 - GLONASS – 0x08 - Network – 0x10 - External positino injection – Others - unknown

9.12.3.78 typedef void(∗ tFNNewNMEA)(LPCSTR pNMEA)

New NMEA sentence callback function.

Parameters

pNMEA	• NULL-terminated string containing the position data in NMEA sentence format

9.12.3.79 typedef void(∗ tFNNewRMTransferStatistics)(QmiCbkWdsStatisticsIndState ∗pMsg)

PDS session state callback function.

Parameters

enabledStatus	• GPS enabled status – 0 - Disable – 1 - Enable
trackingStatus	• GPS tracking status – 0 - Unknown – 1 - Inactive – 2 - Active RM Transfer Statistics message callback function.
pMsg[OUT]	• Events related to NAS, see QmiCbkWdsStatisticsIndState for details

9.12.3.80 typedef void(∗ tFNNewSMS)(ULONG storageType, ULONG messageIndex)

New SMS message callback function.

Parameters

storageType	• SMS message storage type for the new message 0 - UIM 1 - NV
messageIndex	• Index of the new message

9.12.3.81 typedef void(∗ tFNOMADMState)(ULONG sessionState, ULONG failureReason)

OMA-DM state callback function

Parameters

sessionState	• Session state – 0x00 - Complete, information was updated – 0x01 - Complete, update information is unavailable – 0x02 - Failed – 0x03 - Retrying – 0x04 - Connecting – 0x05 - Connected – 0x06 - Authenticated – 0x07 - Mobile Directory Number (MDN) downloaded – 0x08 - Mobile Station Identifier (MSID) downloaded – 0x09 - PRL downloaded – 0x0A - Mobile IP (MIP) profile downloaded
failureReason	• Session failure reason (when state indicates failure) – 0x00 - Unknown – 0x01 - Network is unavailable – 0x02 - Server is unavailable – 0x03 - Authentication failed – 0x04 - Maximum retry exceeded – 0x05 - Session is cancelled

Note

Technology Supported: CDMA

9.12.3.82 typedef void(∗ tFNOpMode)(QmiCbkLocOpModeInd ∗pLocOpmode)

LOC operating mode callback function.

Parameters

pLocOpmode[OUT]	• Events related to LOC, see QmiCbkLocOpModeInd for details

9.12.3.83 typedef void(∗ tFNOTASPStatus)(voiceOTASPStatusInfo ∗pVoiceOTASPStatusInfo)

OTASP or OTAPA event Indication Callback function

Parameters

pVoiceOTASPStatusInfo	• OTASP Status Information. • See voiceOTASPStatusInfo for more information

Note

Technology Supported: CDMA

9.12.3.84 typedef void(∗ tFNPacketSrvState)(packetSrvStatus ∗pPacketSrvStatus)

Packet Service state callback function.

Parameters

pPacketSrv-Status	• See packetSrvStatus for more details

9.12.3.85 typedef void(∗ tFNPDSState)(ULONG enabledStatus, ULONG trackingStatus)

PDS session state callback function.

Parameters

enabledStatus	• GPS enabled status – 0 - Disable – 1 - Enable
trackingStatus	• GPS tracking status – 0 - Unknown – 1 - Inactive – 2 - Active

9.12.3.86 typedef void(∗ tFNPower)(ULONG operatingMode)

Power operating mode callback function.

Parameters

operatingMode	• Service Operating mode See Tables for Operating Modes

Note

Technology Supported: UMTS/CDMA
Device Supported: MC83x5, MC7700/50

9.12.3.87 typedef void(∗ tFNPrivacyChange)(voicePrivacyInfo ∗pVoicePrivacyInfo)

Preferred voice privacy indication callback.

Parameters

pVoicePrivacy-Info	• See voicePrivacyInfo for more information.

Note

Technology Supported: CDMA

9.12.3.88 typedef void(∗ tFNPSMCfgParamChange)(dmsPsmCfgParamChange ∗pPSMCfgParamInd)

Get PSM status Indication callback.

Parameters

pPSMCgfParam-Ind	• See dmsPsmCfgParamChange for more information.

9.12.3.89 typedef void(∗ tFNQosNWStatus)(BYTE status)

QOS Network status callback function.

Parameters

status	Network QoS support status • 0x00 - Current network does not support QoS • 0x01 - Current network supports QoS

9.12.3.90 typedef void(∗ tFNQosPriEvent)(WORD event)

QOS primary flow callback function.

Parameters

event	Event which causes this indication: • 0x0001 - Primary flow QoS modify operation success • 0x0002 - Primary flow QoS modify operation failure

9.12.3.91 typedef void(∗ tFNQosStatus)(BYTE instance, ULONG id, BYTE status, BYTE event, BYTE reason)

QOS Status callback function.

Parameters

instance	• QMI instance
id	• Index identifying the QoS flow whose status is being reported

status	Current QoS flow status: • 0x01 - QMI_QOS_STATUS_ACTIVATED • 0x02 - QMI_QOS_STATUS_SUSPENDED • 0x03 - QMI_QOS_STATUS_GONE
event	• 0x01 - QMI_QOS_ACTIVATED_EV • 0x02 - QMI_QOS_SUSPENDED_EV • 0x03 - QMI_QOS_GONE_EV • 0x04 - QMI_QOS_MODIFY_ACCEPTED_EV • 0x05 - QMI_QOS_MODIFY_REJECTED_EV • 0x06 - QMI_QOS_INFO_CODE_UPDATED_EV
reason	• 0x01 - QMI_QOS_INVALID_PARAMS • 0x02 - QMI_QOS_INTERNAL_CALL_ENDED • 0x03 - QMI_QOS_INTERNAL_ERROR • 0x04 - QMI_QOS_INSUFFICIENT_LOCAL_Resources • 0x05 - QMI_QOS_TIMED_OUT_OPERATION • 0x06 - QMI_QOS_INTERNAL_UNKNOWN_CAUSE_CODE • 0x07 - QMI_QOS_INTERNAL_MODIFY_IN_PROGRESS • 0x08 - QMI_QOS_NOT_SUPPORTED • 0x09 - QMI_QOS_NOT_AVAILABLE • 0x0A - QMI_QOS_NOT_GUARANTEED • 0x0B - QMI_QOS_INSUFFICIENT_NETWORK_RESOURCES • 0x0C - QMI_QOS_AWARE_SYSTEM • 0x0D - QMI_QOS_UNAWARE_SYSTEM • 0x0E - QOS_REJECTED_OPERATION • 0x0F - QMI_QOS_WILL_GRANT_WHEN_QOS_RESUMED • 0x10 - QMI_QOS_NETWORK_CALL_ENDED • 0x11 - QMI_QOS_NETWORK_SERVICE_NOT_AVAILABLE • 0x12 - QMI_QOS_NETWORK_L2_LINK_RELEASED • 0x13 - QMI_QOS_NETWORK_L2_LINK_REESTAB_REJ • 0x14 - QMI_QOS_NETWORK_L2_LINK_REESTAB_IND • 0x15 - QMI_QOS_NETWORK_UNKNOWN_CAUSE_CODE • 0x16 - QMI_NETWORK_BUSY

9.12.3.92 typedef void(∗ tFNRankIndicator)(RankIndicatorInd ∗pRankIndicatorInd)

Rank Indicator callback function.

Parameters

pRankIndicator-Ind[OUT]	• Events related to NAS, see RankIndicatorInd for details.

9.12.3.93 typedef void(∗ tFNResetInfo)(ResetInfoNotification ∗pResetInfoNotification)

Get Reset Info Indication callback.

Parameters

pResetInfo-Notification	• See ResetInfoNotification for more information.

9.12.3.94 typedef void(∗ tFNRFInfo)(ULONG radioInterface, ULONG activeBandClass, ULONG activeChannel)

RF information callback function.

Parameters

radioInterface	• Radio interface technology of the signal being measured See Tables for Radio Interface
activeBandClass	• Active band class See Tables for Active Band Class
activeChannel	• Active channel – 0 - Channel is not relevant to the reported technology

9.12.3.95 typedef void(∗ tFNRoamingIndicator)(ULONG roaming)

Roaming indicator callback function.

Parameters

roaming	• Roaming Indication – 0 - Roaming – 1 - Home – 2 - Roaming partner – >2 - Operator defined values

9.12.3.96 typedef void(∗ tFNSDKTerminated)(BYTE ∗psReason)

SDK terminated callback function prototype

Parameters

psReason	• sdk termination reason string

Note

Timeout: None
Does not require communication with the device

9.12.3.97 typedef void(∗ tFNSensorStreaming)(QmiCbkLocSensorStreamingInd ∗pLocSensorStream)

LOC Sensor Streaming indication callback.

Parameters

pLocSensor-Stream	• See QmiCbkLocSensorStreamingInd for more information.

9.12.3.98 typedef void(∗ tFNServingSystem)(struct ServingSystemInfo ∗pServingSystem,struct RoamingInfo ∗pRoamingInfo)

Serving System callback function

Parameters

pServingSystem	• ServingSystemInfo structure

9.12.3.99 typedef void(∗ tFNSetCradleMount)(QmiCbkLocCradleMountInd ∗pSetLocCradleMount)

Set Cradle Mount indication callback.

Parameters

pSetLocCradle-Mount	• See QmiCbkLocCradleMountInd for more information.

9.12.3.100 typedef void(∗ tFNSetEngineState)(QmiCbkLocEngineStateInd ∗pSetLocEngineState)

Set Engine State Indication callback.

Parameters

pSetLocEngine-State	• See QmiCbkLocEngineStateInd for more information.

9.12.3.101 typedef void(∗ tFNSetEventTimeSync)(QmiCbkLocEventTimeSyncInd ∗pSetLocEventTimeSync)

LOC event time sync indication callback.

Parameters

pSetLocEvent-TimeSync	• See QmiCbkLocEventTimeSyncInd for more information.

9.12.3.102 typedef void(∗ tFNSetExtPowerConfig)(QmiCbkLocSetExtPowerConfigInd ∗pSetExtConfigIndStatus)

Set Ext Power Config Indication callback.

Parameters

pSetExtConfig-IndStatus	• See QmiCbkLocSetExtPowerConfigInd for more information.

9.12.3.103 typedef void(∗ tFNSetServer)(QmiCbkLocSetServerInd ∗pSetLocServerInfo)

Set LOC Server Indication callback.

Parameters

pSetLocServer-Info	• See QmiCbkLocSetServerInd for more information.

9.12.3.104 typedef void(∗ tFNSigInfo)(nasSigInfo ∗pNasSigInfo)

Signal Strength Information indication callback.

Parameters

pNasSigInfo	• See nasSigInfo for more information.

9.12.3.105 typedef void(∗ tFNSignalStrength)(INT8 signalStrength, ULONG radioInterface)

Signal strength callback function.

Parameters

signalStrength	• Received signal strength (in dBm)
radioInterface	• Radio interface technology of the signal being measured See Tables for Radio Interface

9.12.3.106 typedef void(* tFNSLQSOMADMAlert)(ULONG eventType, BYTE *pEventFields)

SWIOMA-DM network-initiated alert callback function

Parameters

eventType	• 0x00 - SWIOMA-DM FOTA • 0x01 - SWIOMA-DM Config • 0x02 - SWIOMA-DM Notification
pEventFields	• Pointer to structure containing info for that session type • See sessionInfo for more details

9.12.3.107 typedef void(* tFNSLQSQOSEvent)(BYTE instance, QosFlowInfo *pFlowInfo)

QOS Event callback function.

Parameters

instance	• QMI instance
pFlowInfo	• See QosFlowInfo for more information

9.12.3.108 typedef void(* tFNSLQSSessionState)(slqsSessionStateInfo *pSessionStateInfo)

Session state callback function.

Parameters

pSessionStateInfo	• See slqsSessionStateInfo for more details

9.12.3.109 typedef void(* tFNSLQSSignalStrengths)(struct SLQSSignalStrengthsInformation sSLQSSignalStrengthsInfo)

Received Signal Strength Information callback function.

Parameters

sSLQSSignalStrengthsInfo	• See SLQSSignalStrengthsInformation for more information.

9.12.3.110 typedef void(* tFNSLQSWDSEvent)(slqsWdsEventInfo *pWdsEventInfo)

WDS Event callback function.

Parameters

pWdsEventInfo	• See slqsWdsEventInfo for more details

9.12.3.111 typedef void(∗ tFNSMSEvents)(SMSEventInfo ∗pSMSEventInfo)

SMS event related callback function.

Parameters

pSMSEventInfo[-OUT]	• Events related to SMS, see SMSEventInfo for details

9.12.3.112 typedef void(∗ tFNSUPSInfo)(voiceSUPSInfo ∗pVoiceSUPSInfo)

Preferred SUPS indication callback.

Parameters

pVoiceSUPSInfo	• See voiceSUPSInfo for more information.

Note

Technology Supported: GSM

9.12.3.113 typedef void(∗ tFNSUPSNotification)(voiceSUPSNotification ∗pVoiceSUPSNotification)

Supplementary service notification callback.

Parameters

pVoiceSUPS-Notification	• See voiceSUPSNotification for more information.

9.12.3.114 typedef void(∗ tFNSwiAvmEventReport)(SwiAvmsEventInd ∗pEvent)

AVMS Event Report indication callback.

Parameters

pEvent	• See SwiAvmsEventInd for more information.

9.12.3.115 typedef void(∗ tFNSysInfo)(nasSysInfo ∗pNasSysInfo)

System Information indication callback.

Parameters

pNasSysInfo	• See nasSysInfo for more information.

9.12.3.116 typedef void(∗ tFNSysSelectionPref)(sysSelectPrefExtInfo ∗pSysSelectPrefInfo)

System Selection Preference Callback function

Parameters

pSysSelectPrefInfo	• Current System Selection preferences for the device. • See sysSelectPrefExtInfo for more information

9.12.3.117 typedef void(∗ tFNtransLayerInfo)(transLayerNotification ∗pTransLayerNotification)

Transport Layer Information callback.

Parameters

transLayerNotification	• See transLayerNotification for more information.

9.12.3.118 typedef void(∗ tFNtransNWRegInfo)(transNWRegInfoNotification ∗pTransNWRegInfoNotification)

Transport Network Registration Information callback.

Parameters

pTransNWRegInfoNotification	• See transNWRegInfoNotification for more information.

9.12.3.119 typedef void(∗ tFNUIMRefresh)(UIMRefreshEvent ∗pUIMRefreshEvent)

UIM Refresh Callback function

Parameters

pUIMRefreshEvent	• Pointer to Refresh Event structure. • See UIMRefreshEvent for more information

9.12.3.120 typedef void(∗ tFNUIMStatusChangeInfo)(UIMStatusChangeInfo ∗pUIMStatusChangeInfo)

UIM Status Change Callback function

Parameters

pUIMStatus-ChangeInfo	• Pointer to UIM status change structure. • See UIMStatusChangeInfo for more information

9.12.3.121 typedef void(∗ tFNUIMStatusInfo)(modemUIMStatusNotification ∗pmodemUIMStatusNotification)

Modem UIM status Information callback.

Parameters

pmodemUIM-Status-Notification	• See modemUIMStatusNotification for more information.

9.12.3.122 typedef void(∗ tFNUSSDNotification)(ULONG type, BYTE ∗pNetworkInfo)

SetUSSDNotificationCallback function prototype

Parameters

type	- Notification type • 0x01 - No action required • 0x02 - Action required
pNetworkInfo	• USS information from the network (0 indicates that no info was received) – See USSInfo for more details

Note

Technology Supported: UMTS

9.12.3.123 typedef void(∗ tFNUSSDNoWaitIndication)(USSDNoWaitIndicationInfo ∗pNetworkInfo)

USSD No Wait indication callback.

Parameters

pNetworkInfo	• See USSDNoWaitIndicationInfo for more information.

9.12.3.124 typedef void(* tFNUSSDRelease)(void)

USSD releasecallback function prototype

Note

Technology Supported: UMTS

9.12.3.125 typedef struct _transLayerInfoNotification transLayerNotification

Contains the parameters passed for SLQSSetTransLayerInfoCallback by the device.

Parameters

regInd	• Indicates whether the transport layer is registered or not • Values: – 0x00 - Transport layer is not registered – 0x01 - Transport layer is registered
pTransLayerInfo	• Optional parameter • See transLayerInfo for more information

Note

None

9.12.3.126 typedef struct _transNWRegInfoNotification transNWRegInfoNotification

Contains the parameters passed for SLQSSetTransNWRegInfoCallback by the device.

Parameters

NWRegStat	• provides the transport network registration information • Values: – 0x00 - No Service – 0x01 - In Progress – 0x02 - Failed – 0x03 - Limited Service – 0x04 - Full Service

Note

None

9.12.4 Enumeration Type Documentation

9.12.4.1 enum device_state_enum

Device State enumeration

- See device_state_enum for more details

Enumerator

DEVICE_STATE_DISCONNECTED
DEVICE_STATE_READY
DEVICE_STATE_BOOT
DEVICE_STATE_SERIAL_ONLY

9.12.4.2 enum eQaQMIService

The QMI service information which is exposed to the application, only the services which are relevant to multiple PDP are listed in this enumeration as these are the only required services to be exposed.

Enumerator

eQA_QMI_SVC_WDS
eQA_QMI_SVC_NAS
eQA_QMI_SVC_NA

9.12.4.3 enum SMSEventType

This enumeration defines the different type of SMS events that are received

- See SMSEventType for more details

Enumerator

SMS_EVENT_MT_MESSAGE
SMS_EVENT_TRANSFER_ROUTE_MT_MESSAGE
SMS_EVENT_MESSAGE_MODE
SMS_EVENT_ETWS
SMS_EVENT_ETWS_PLMN
SMS_EVENT_SMSC_ADDRESS
SMS_EVENT_SMS_ON_IMS

9.12.4.4 enum TYPE_OF_SERVICE_DOMAIN

Enumerator

SYS_SRV_DOMAIN_NO_SRV
SYS_SRV_DOMAIN_CS_ONLY
SYS_SRV_DOMAIN_PS_ONLY
SYS_SRV_DOMAIN_CS_PS
SYS_SRV_DOMAIN_CAMPED

9.12.5 Function Documentation

9.12.5.1 ULONG iSetCATEventCallback (tFNCATEvent *pCallback*)

9.12.5.2 ULONG iSetSignalStrengthCallback (tFNSignalStrength *pCallback*)

9.12.5.3 ULONG iSLQSSetDUNCallInfoCallback (tFNDUNCallInfo *pCallback*)

9.12.5.4 ULONG iSLQSSetSignalStrengthsCallback (tFNSLQSSignalStrengths *pCallback*)

9.12.5.5 ULONG iSLQSSetWdsFirstInstEventCallback (tFNSLQSWDSEvent *pCallback*)

9.12.5.6 ULONG iSLQSSetWdsSecondInstEventCallback (tFNSLQSWDSEvent *pCallback*)

9.12.5.7 ULONG iSLQSSetWdsThirdInstEventCallback (tFNSLQSWDSEvent *pCallback*)

9.12.5.8 ULONG iSLQSSetWdsXferStatsFirstInstCallback (tFNSLQSWDSEvent *pCallback*)

9.12.5.9 ULONG iSLQSSetWdsXferStatsSecondInstCallback (tFNSLQSWDSEvent *pCallback*)

9.12.5.10 ULONG SetActivationStatusCallback (tFNActivationStatus *pCallback*)

Enables/disables the Activation Status callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.12.5.11 ULONG SetCATEventCallback (tFNCATEvent *pCallback,* ULONG *eventMask,* ULONG * *pErrorMask*)

Enables/disables the CAT event callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)
eventMask	• bitmask of CAT events to register for – 0x00000001 - Display Text – 0x00000002 - Get In-Key – 0x00000004 - Get Input – 0x00000008 - Setup Menu – 0x00000010 - Select Item – 0x00000020 - Send SMS - Alpha Identifier – 0x00000040 - Setup Event: User Activity – 0x00000080 - Setup Event: Idle Screen Notify – 0x00000100 - Setup Event: Language Sel Notify – 0x00000200 - Setup Idle Mode Text – 0x00000400 - Language Notification – 0x00000800 - Refresh – 0x00001000 - End Proactive Session
pErrorMask[OUT]	• error bitmask. Each bit set indicates the proactive command that caused the error – 0x00000001 - Display Text – 0x00000002 - Get In-Key – 0x00000004 - Get Input – 0x00000008 - Setup Menu – 0x00000010 - Select Item – 0x00000020 - Send SMS - Alpha Identifier – 0x00000040 - Setup Event: User Activity – 0x00000080 - Setup Event: Idle Screen Notify – 0x00000100 - Setup Event: Language Sel Notify – 0x00000200 - Setup Idle Mode Text – 0x00000400 - Language Notification – 0x00000800 - Refresh – 0x00001000 - End Proactive Session

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Technology Supported: UMTS
Timeout: 2 seconds

9.12.5.12 ULONG SetCfgParamChangeCallback (tFNPSMCfgParamChange *pCallback*)

Enables/disables PSM Configuration Change callback function.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable) • See tFNPSMCfgParamChange for more information.

9.12.5.13 ULONG SetDataCapabilitiesCallback (tFNDataCapabilities *pCallback*)

Enables/disables the data capabilities callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Does not require communication with the device

9.12.5.14 ULONG SetDeviceStateChangeCbk (tFNDeviceStateChange *pCallback*)

Used by the client application to register a Callback function for Device State Change (DSC) event notifications. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to be notified of DSC events • NULL to disable DSC event notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.12.5.15 ULONG SetFwDldCompletionCbk (tFNFwDldCompletion *pCallback*)

Used by the client application to register a Callback function for a Firmware Download Completion (FDC) event notification. The most recent successfully subscribed callback function will be the only function that is invoked when

the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable FDC event notification • NULL to disable FDC event notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: N/A

9.12.5.16 ULONG SetGPSCallback (tFNNewGPS *pCallback*)

Enables/disables the NMEA sentence callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.17 ULONG SetLocBestAvailPosCallback (tFNBestAvailPos *pCallback*)

Enables/disables Best Available Location callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.18 ULONG SetLocCradleMountCallback (tFNSetCradleMount *pCallback*)

Enables/disables the Cradle Mount callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.19 ULONG SetLocDeleteAssistDataCallback (tFNDelAssistData *pCallback*)

Enables/disables Delete Assist Data callback function. This API is used to receive the SUCCESS/FAILURE status of API SLQSLOCDelAssData().

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

9.12.5.20 ULONG SetLocEngineStateCallback (tFNSetEngineState *pCallback*)

Sends the GPS State Information event to the control point.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.21 ULONG SetLocEventMaskNMEACallback (tFNEventNmea *pCallback*)

Enables/disables NMEA Event callback function

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable) • See tFNEventNmea for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.22 ULONG SetLocEventPositionCallback (tFNEventPosition *pCallback*)

Enables/disables the Event Position Report callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.23 ULONG SetLocEventTimeSyncCallback (tFNSetEventTimeSync *pCallback*)

Enables/disables the Event Time Sync callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.24 ULONG SetLocGetOpModeCallback (tFNGetOpMode *pCallback*)

Enables/disables Get Operating Mode callback function. This API is used to receive the SUCCESS/FAILURE status of API SLQSLOCGetOpMode().

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

9.12.5.25 ULONG SetLocGetServerCallback (SetLocGetServerCallbackPara * *pSetLocGetServerCallbackPara*)

Enables/disables Get location server callback function

Parameters

pSetLocGet-ServerCallback-Para[IN]	• See SetLocGetServerCallbackPara for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.26 ULONG SetLocGnssSvInfoCallback (tFNGnssSvInfo *pCallback*)

Enables/disables the GNSS SV Info callback function. This API is used to send the satellite report to the application. The satellite reports are sent only to the application that invoked API SLQSLOCStart() that generated the satellite report.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.27 ULONG SetLocInjectSensorDataCallback (tFNInjectSensorData *pCallback*)

Enables/disables the Inject Sensor Data callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.28 ULONG SetLocInjectTimeCallback (tFNInjectTimeStatus *pCallback*)

Enables/disables the Inject Time Sync Data callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.29 ULONG SetLocOpModeCallback (tFNOpMode *pCallback*)

Enables/disables Set Operating Mode callback function. This API is used to receive the SUCCESS/FAILURE status of API SLQSLOCSetOpMode().

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

9.12.5.30 ULONG SetLocSensorStreamingCallback (tFNSensorStreaming *pCallback*)

Enables/disables the Event Sensor Streaming Ready Status callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.31 ULONG SetLocSetExtPowerConfigCallback (tFNSetExtPowerConfig *pCallback*)

Enables/disables the Set External Power Config Status callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.32 ULONG SetLocSetServerCallback (SetLocSetServerCallbackParam * *pSetLocSetServerCallbackParam*)

Set location server callback function

Parameters

req[IN]	• See LocSetServerReq for more information.

pCallback[IN]	• Callback function pointer (0 - Disable) • See tFNSetServer for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.33 ULONG SetLURejectCallback (tFNLUReject *pCallback*)

Enables/disables the LU reject callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.34 ULONG SetMobileIPStatusCallback (tFNMobileIPStatus *pCallback*)

Enables/disables the Mobile IP Status callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.12.5.35 ULONG SetNasLTECphyCaIndCallback (tFNASwiLTECphyCaInfo *pCallback*)

Enables/disables the LTE NAS CA Info callback function.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.36 ULONG SetNetChangeCbk (BYTE *instance,* tFNNet *pCallback,* ULONG *loMark,* ULONG *hiMark,* ULONG *period*)

Used by the client application to register a Callback function for USB Transmit Queue Length Change event notifications. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

instance[IN]	• PDP instance
pCallback[IN]	• a valid function pointer to be notified of the event • NULL to disable the event notification
loMark[IN]	• Transmit queue length smaller will trigger unthrottle event notification
hiMark[IN]	• Transmit queue length larger will trigger throttle event notification
period[IN]	• monitoring period in seconds, minimum 1 second

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.12.5.37 ULONG SetNewSMSCallback (tFNNewSMS *pCallback*)

Enables/disables the new SMS callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Timeout: 2 seconds

9.12.5.38 ULONG SetNMEACallback (tFNNewNMEA *pCallback*)

Enables/disables the NMEA sentence callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

This API is deprecated on all MC/EM74xx firmware versions. Please use SetLocEventPositionCallback()

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.39 ULONG SetOMADMStateCallback (tFNOMADMState *pCallback*)

Enables/disables the OMADM state callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

This API is deprecated on all MC/EM74xx firmware versions. Please use SetSLQSOMADMAlertCallback()

Parameters

pCallback[IN]	• a valid function pointer to enable OMADMState notification • NULL to disable OMADMState notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.12.5.40 ULONG SetPDSStateCallback (tFNPDSState *pCallback*)

Enables/disables the PDS service state callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.41 ULONG SetPowerCallback (tFNPower *pCallback*)

Enables/disables the Operating Mode callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.42 ULONG SetRankIndicatorCallback (tFNRankIndicator *pCallback*)

9.12.5.43 ULONG SetRFInfoCallback (tFNRFInfo *pCallback*)

Enables/disables the radio frequency information callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.44 ULONG SetRMTransferStatisticsCallback (tFNNewRMTransferStatistics *pCallback*)

Enables/disables the RM Transfer Statistics callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.45 ULONG SetRoamingIndicatorCallback (tFNRoamingIndicator *pCallback*)

Enables/disables the Roaming Indicator callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

This API is deprecated on all MC/EM74xx firmware versions. Please use SLQSNasSysInfoCallBack() instead

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.46 ULONG SetSignalStrengthCallback (tFNSignalStrength *pCallback,* BYTE *thresholdsSize,* INT8 * *pThresholds*)

Enables/disables the Signal Strength callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This API is deprecated on MC73xx/-EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSNasIndicationRegisterExt() for new firmware versions and new modules

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)
thresholdsSize	• Number of elements threshold array contains; a maximum of five thresholds is supported; • This parameter is not used when disabling the callback.
pThresholds[IN]	• Signal threshold array for each entry (in dBm). • This parameter is not used when disabling the callback.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
The signal strength callback function is called when a threshold in the threshold array is crossed.

9.12.5.47 ULONG SetSLQSOMADMAlertCallback (tFNSLQSOMADMAlert *pCallback*)

Enables/disables the SWIOMADM network-initiated alert callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable SLQSOMADMAlert notification • NULL to disable SLQSOMADMAlert notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.48 ULONG SetSLQSOMADMAlertCallbackExt (tFNSLQSOMADMAlert *pCallback*)

Enables/disables the SWIOMADM network-initiated alert callback function for SL9090 module. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable SLQSOMADMAlert notification • NULL to disable SLQSOMADMAlert notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Technology Supported: UMTS/CDMA
Device Supported: SL9090
Timeout: 2 seconds

9.12.5.49 ULONG SetUimSlotStatusChangeCallback (tFNCbkUimSlotStatusChangeInd *pCallback*)

Enables/disables Slot Status Change callback function.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.50 ULONG SetUSSDNotificationCallback (tFNUSSDNotification *pCallback*)

Enables/disables the USSDNotification callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable ServingSystem notification • NULL to disable ServingSystem notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Technology Supported: UMTS
Timeout: Does not require communication with device

9.12.5.51 ULONG SetUSSDNoWaitIndicationCallback (tFNUSSDNoWaitIndication *pCallback*)

SetUSSDNoWaitIndicationCallback

Parameters

pNetworkInfo	• Data from the network. • See USSDNoWaitIndicationInfo for more details.

Note

Technology Supported: UMTS
Device Supported: MC83x5

9.12.5.52 ULONG SetUSSDReleaseCallback (tFNUSSDRelease *pCallback*)

Enables/disables the USSD release callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable ServingSystem notification • NULL to disable ServingSystem notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Technology Supported: UMTS
Timeout: Does not require communication with the device

9.12.5.53 ULONG SLQSNasEdrxChangeInfoCallBack (tFNNasEdrxChangeInfo *pCallback*)

Enables/disables the eDRX Change Info callback function.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.54 ULONG SLQSNasNetworkRejectCallback (tFNNetworkReject *pCallback*)

9.12.5.55 ULONG SLQSNasNetworkTimeCallBack (tFNNetworkTime *pCallback*)

Enables/disables the Network Time callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
This callback is sent when the 3GPP or 3GPP2 network sends time information to the User Equipment.

9.12.5.56 ULONG SLQSNasSigInfo2CallBack (tFNSigInfo *pCallback,* setSignalStrengthInfo * *pSigInfo2*)

Enables/disables the Signal Info callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)
pSigInfo2[IN]	• Structure containing the threshold values beyond which signal information is to be reported • See setSignalStrengthInfo for more details

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
This callback is sent when the signal strength change occurs

9.12.5.57 ULONG SLQSNasSigInfoCallBack (tFNSigInfo *pCallback*, sigInfo * *pSigInfo*)

Enables/disables the Signal Info callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This callback is deprecated on MC73xx/-EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use callback SLQSNasSigInfo2CallBack() for new firmware versions and new modules

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)
pSigInfo[IN]	• Structure containing the threshold values beyond which signal information is to be reported • See sigInfo for more details

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
This callback is sent when the signal strength change occurs

9.12.5.58 ULONG SLQSNasSwiOTAMessageCallback (NasSwiIndReg * *req*, tFNASwiOTAMsg *pCallback*)

Enables/disables the SLQSNasSwiOTAMessageCallback callback function. To disable the callback, provide both req and pCallback as NULL pointer to the API

Parameters

req[IN]	• the request to which kind of message type should be enabled, see NasSwiIndReg for details
pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.59 ULONG SLQSNasSysInfoCallBack (tFNSysInfo *pCallback*)

Enables/disables the Sys Info callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
This callback provides current serving system information, including registration information and system property. The serving system information of the radio interfaces specified in mode_pref are included in the response message. When any value in the sys_info message changes, an indication message is sent. Indications contain all the values for all active RATs.

9.12.5.60 ULONG SLQSNasTimerCallback (tFNNasTimer *pCallback*)

Enables/disables Network Timer callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.61 ULONG SLQSSetBandPreferenceCbk (tFNBandPreference *pCallback*)

Enables/disables the Band Preference callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable Band Preference Indication notification • NULL to disable Band Preference notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Timeout: NA To set the band preference the API SLQSSetBandPreference() should be used

9.12.5.62 ULONG SLQSSetDataSystemStatusCallback (tFNDataSysStatus *pCallback*)

Enables/disables the Data System Status callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.12.5.63 ULONG SLQSSetDHCPv4ClientLeaseStatusCallback (SLQSSetDHCPv4ClientLeaseStatusCallbackParam * *pSLQSSetDHCPv4ClientLeaseStatusCallbackParam*)

Enables/disables the DHCP Client V4 Lease Status callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pSLQSSetDHCPv4ClientLeaseStatusCallbackParam[IN]	• See SLQSSetDHCPv4ClientLeaseStatusCallbackParam for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.64 ULONG SLQSSetDUNCallInfoCallback (BYTE *StatsPeriod,* tFNDUNCallInfo *pCallback*)

Enables/disables the DUN Call Info callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

StatsPeriod[IN]	• Period between reports(seconds) • 0 - Do not report • Only applicable to pTXOKBytesCount and pRXOKBytesCount parameters
pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.12.5.65 ULONG SLQSSetIMSAPdpStatusCallback (tFNImsaPdpStatus *pCallback*)

SLQSSetIMSAPdpStatusCallback

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.12.5.66 ULONG SLQSSetIMSARatStatusCallback (tFNImsaRatStatus *pCallback*)

SLQSSetIMSARatStatusCallback

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.12.5.67 ULONG SLQSSetIMSARegStatusCallback (tFNImsaRegStatus *pCallback*)

SLQSSetIMSARegStatusCallback

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.12.5.68 ULONG SLQSSetIMSASvcStatusCallback (tFNImsaSvcStatus *pCallback*)

SLQSSetIMSASvcStatusCallback

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.12.5.69 ULONG SLQSSetIMSSMSConfigCallback (tFNImsSMSConfig *pCallback*)

Enables/disables the SMS Config callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.70 ULONG SLQSSetIMSUserConfigCallback (tFNImsUserConfig *pCallback*)

Enables/disables the User Config callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.71 ULONG SLQSSetIMSVoIPConfigCallback (tFNImsVoIPConfig *pCallback*)

Enables/disables the VoIP Config callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.72 ULONG SLQSSetLocInjectPositionCallback (tFNInjectPosition *pCallback*)

Enables/disables Inject Position callback function. This API is used to receive the SUCCESS/FAILURE status of API SLQSLOCInjectPosition().

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

9.12.5.73 ULONG SLQSSetLocInjectUTCTimeCallback (tFNInjectUTCTime *pCallback*)

Enables/disables Inject UTC Time callback function. This API is used to receive the SUCCESS/FAILURE status of API SLQSLOCInjectUTCTime().

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

9.12.5.74 ULONG SLQSSetModemTempCallback (tFNModemTempInfo *pCallback*)

Enables/disables the Modem Temperature information callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.12.5.75 ULONG SLQSSetPacketSrvStatusCallback (tFNPacketSrvState *pCallback*)

Enables/disables the session state callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: none; does not require communication with the device

9.12.5.76 ULONG SLQSSetQosEventCallback (BYTE *instance,* tFNSLQSQOSEvent *pCallback*)

Enables/disables the QoS event callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This callback provide extra information regarding the QoS flow state

Parameters

in	*instance*	• QMI instance
in	*pCallback*	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

maximum number of tx/rx filters supported is 25 (pTxQFilter/pRxQFilter)

9.12.5.77 ULONG SLQSSetQosNWStatusCallback (tFNQosNWStatus *pCallback*)

Enables/disables the QoS event callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This callback provide extra information regarding the QoS Network supports status

Parameters

in	*pCallback[IN]*	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.12.5.78 ULONG SLQSSetQosPriEventCallback (tFNQosPriEvent *pCallback*)

Enables/disables the QoS event callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This callback provide extra information regarding the QoS Primary flow event

Parameters

in	*pCallback*	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS

9.12.5.79 ULONG SLQSSetQosStatusCallback (BYTE *instance,* tFNQosStatus *pCallback*)

Enables/disables the QoS event callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This callback provide extra information regarding the QoS status

Parameters

in	*instance*	• QMI instance
in	*pCallback[IN]*	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.12.5.80 ULONG SLQSSetRegMgrConfigCallback (tFNImsRegMgrConfig *pCallback*)

Enables/disables the Reg Mgr Config callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.81 ULONG SLQSSetSDKTerminatedCallback (tFNSDKTerminated *pCallback*)

Used by the client application to register a Callback function for SDK terminated event notifications. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to be notified of SWI events • NULL to disable SWI event notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: N/A
Device Supported: N/A
Timeout: N/A
The following signals will trigger this callback:

```
2 INT      4 ILL      5 TRAP     6 ABRT     7 BUS
8 FPE     11 SEGV    13 PIPE    15 TERM    31 SYS
```

9.12.5.82 ULONG SLQSSetServingSystemCallback (tFNServingSystem *pCallback*)

Enables/disables the Serving System callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

This API is deprecated on all MC/EM74xx firmware versions. Please use SLQSNasSysInfoCallBack()

Parameters

pCallback[IN]	• a valid function pointer to enable ServingSystem notification • NULL to disable ServingSystem notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.83 ULONG SLQSSetSessionStateCallback (tFNSLQSSessionState *pCallback*)

Enables/disables the session state callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This callback provide extra information regarding the multiple PDP interface

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: none; does not require communication with the device

9.12.5.84 ULONG SLQSSetSignalStrengthsCallback (tFNSLQSSignalStrengths *pCallback,* struct SLQSSignalStrengthsIndReq * *pSLQSSignalStrengthsIndReq*)

Enables/disables the Received Signal Strength Information callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This API is same as API SetSignalStrengthsCallback() except providing more information of signal such as ECIO, SNR etc. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSNasIndicationRegisterExt() for new firmware versions and new modules

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)
pSLQSSignal-StrengthsIndReq	• See SLQSSignalStrengthsIndReq for more information • This parameter is not used when disabling the callback.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
The signal strength callback function is called when a threshold in the threshold array is crossed.

9.12.5.85 ULONG SLQSSetSIPConfigCallback (tFNImsSIPConfig *pCallback*)

Enables/disables the SIP Config callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.86 ULONG SLQSSetSMSEventCallback (tFNSMSEvents *pCallback*)

Enables/disables the events related to SMS callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

9.12.5.87 ULONG SLQSSetSwiGetResetInfoCallback (tFNResetInfo *pCallback*)

Reset Info callback.

Parameters

pCallback	• See tFNResetInfo for more information.

9.12.5.88 ULONG SLQSSetSwiHDRPersCallback (tFNHDRPersonaity *pCallback*)

Enables/disables the HDR Personality callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 5 seconds

9.12.5.89 ULONG SLQSSetSysSelectionPrefCallBack (tFNSysSelectionPref *pCallback*)

Enables/disables the System Selection Preference callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable System Selection Preference Indication notification • NULL to disable Band Preference notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Timeout: 2 seconds
To set the system selection preferences the API SLQSSetSysSelectionPref() should be used

9.12.5.90 ULONG SLQSSetTransLayerInfoCallback (tFNtransLayerInfo *pCallback*)

Enables/disables the Transport Layer information callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.91 ULONG SLQSSetTransNWRegInfoCallback (tFNtransNWRegInfo *pCallback*)

Enables/disables the Transport Network Registration information callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.92 ULONG SLQSSetUIMStatusCallback (tFNUIMStatusInfo *pCallback*)

Enables/disables the Modem UIM status information callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.12.5.93 ULONG SLQSSetWdsEventCallback (tFNSLQSWDSEvent *pCallback,* BYTE *interval,* BYTE *instanceid,* BYTE *ipfamily*)

Enables/disables the WDS event callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This callback provide extra information regarding the multiple PDP interface. Transfer statistic are reported only when changed.

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)
interval	• Interval in seconds. • ignored when disabling, should be non-zero when enabling • period only affect transfer statistic attributes
instanceid	• PDP instance id 0 - First PDP instance 1 - Second PDP instance 2 - Third PDP instance
ipfamily	• 4 for an IPv4 data session • 6 for an IPv6 data session • 7 for an IPv4v6 data session

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds Currently 3 PDP instances are supported in device. user of this callback can subscribe by passing instanceid of particular instance. All PDP instance can be subscribed by passing instanceid sequentially.

9.12.5.94 ULONG SLQSSetWdsTransferStatisticCallback (tFNSLQSWDSEvent *pXferStatsCb,* BYTE *interval,* BYTE *instanceid,* BYTE *ipfamily*)

Enables/disables the WDS transfer statistic callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. This callback provide extra information regarding the multiple PDP interface. Transfer statistic are reported only when changed.

Parameters

pCallback[IN]	• Callback function pointer (0 - disable)
interval	• Interval in seconds. • ignored when disabling, should be non-zero when enabling • period only affect transfer statistic attributes
instanceid	• PDP instance id 0 - First PDP instance 1 - Second PDP instance 2 - Third PDP instance
ipfamily	• 4 for an IPv4 data session • 6 for an IPv6 data session • 7 for an IPv4v6 data session

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds Currently 3 PDP instances are supported in device. User of this callback can subscribe by passing instance id of particular instance. All PDP instance can be subscribed by passing instance id sequentially.

9.12.5.95 ULONG SLQSSwiAVMSEventReportCallback (tFNSwiAvmEventReport *pCallback*)

9.12.5.96 ULONG SLQSTmdMitigationLvlRptCallback (SLQSTmdMitigationLvlRptCallbackParam * *pSLQSTmdMitigationLvlRptCallbackParam*)

Thermal Mitigation callback.

Parameters

pSLQSTmd-MitigationLvlRpt-CallbackParam	• See SLQSTmdMitigationLvlRptCallbackParam for more information.

9.12.5.97 ULONG SLQSUIMSetRefreshCallBack (tFNUIMRefresh *pCallback*)

Enables/disables the UIM refresh callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable UIM Refresh Indication notification • NULL to disable Band Preference notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Timeout: 2 seconds
SLQSUIMRefreshRegister() API should be invoked prior to the invocation of the callback for the events to be registered.

9.12.5.98 ULONG SLQSUIMSetStatusChangeCallBack (tFNUIMStatusChangeInfo *pCallback*)

Enables/disables the UIM Status Change Callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable UIM Status Change Indication notification • NULL to disable Band Preference notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Timeout: 2 seconds

9.12.5.99 ULONG SLQSVoiceInfoRecCallback (tFNInfoRec *pCallback*)

Enables/disables the Voice information Record callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs. (Applicable only for 3GPP2)

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.12.5.100 ULONG SLQSVoiceSetAllCallStatusCallBack (tFNAllCallStatus *pCallback*)

Enables/disables Voice Call Status Callback function. User can subscribe this callback get the call state change notifications. eg:- Call originated, connected, or ended. Whenever there is a change in the call information, there will be a indication with the information.

Parameters

pCallback[IN]	• Callback function pointer (0 - Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.12.5.101 ULONG SLQSVoiceSetDTMFEventCallBack (tFNDTMFEvent *pCallback*)

Enables/disables the DTMF Event callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
This callback communicates that a DTMF event has been received.

9.12.5.102 ULONG SLQSVoiceSetOTASPStatusCallBack (tFNOTASPStatus *pCallback*)

Enables/disables OTASP(Over-The-Air Service Provisioning) or OTAPA(Over-The-Air Parameter Administration) event CallBack Function (applicable only for 3GPP2). The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• a valid function pointer to enable OTASP or OTAPA event Indication notification • NULL to disable OTASP or OTAPA event, Indication notification

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

Technology Supported: CDMA
Timeout: 10 seconds
This indication communicates the occurrence of an OTASP or OTAPA event. This indication is only applicable for 3GPP2 devices.

9.12.5.103 ULONG SLQSVoiceSetPrivacyChangeCallBack (tFNPrivacyChange *pCallback*)

Enables/disables the voice privacy change callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds
This callback communicates a change in the voice privacy of a call. This is applicable only in 3GPP2 devices.

9.12.5.104 ULONG SLQSVoiceSetSUPSCallBack (tFNSUPSInfo *pCallback*)

Enables/disables the SUPS callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: GSM
Timeout: 2 seconds
This callback notifies clients about the modem-originated supplementary service requests and the responses received from the network.

9.12.5.105 ULONG SLQSVoiceSetSUPSNotificationCallback (tFNSUPSNotification *pCallback*)

Enables/disables the supplementary service notification callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.106 ULONG SLQSWmsAsyncRawSendCallBack (tFNAsyncRawSend *pCallback*)

Enables/disables the SLQSWmsAsyncRawSendCallBack callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.12.5.107 ULONG SLQSWmsMemoryFullCallBack (tFNMemoryFull *pCallback*)

Enables/disables the event related to memory full status callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.12.5.108 ULONG SLQSWmsMessageWaitingCallBack (tFNMessageWaiting *pCallback*)

Enables/disables the event related to message waiting information callback function. The most recent successfully subscribed callback function will be the only function that is invoked when the corresponding event occurs.

Parameters

pCallback[IN]	• Callback function pointer (0-Disable)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.13 qaGobiApiDcs.h File Reference

Device Connectivity Service API function prototypes.

Data Structures

- struct DcsUsbPortNames
- struct QosMap
- struct NetStats

Macros

- #define LEN 10
- #define PORTNAM_LEN 32

Functions

- ULONG QCWWAN2kEnumerateDevices (BYTE ∗pDevicesSize, BYTE ∗pDevices)
- ULONG QCWWAN2kConnect (CHAR ∗pDeviceID, CHAR ∗pDeviceKey)
- ULONG QCWWANDisconnect ()
- ULONG QCWWAN2kGetConnectedDeviceID (ULONG deviceIDSize, CHAR ∗pDeviceID, ULONG deviceKeySize, CHAR ∗pDeviceKey)
- ULONG QCWWANEnumerateDevices (BYTE ∗pDevicesSize, BYTE ∗pDevices)
- ULONG QCWWANConnect (CHAR ∗pDeviceID, CHAR ∗pDeviceKey)
- ULONG SetSDKImagePath (LPCSTR pPath)

- ULONG SLQSGetUsbPortNames (struct DcsUsbPortNames ∗pUsbPortNames)
- ULONG SLQSStart_AVAgent (BYTE modem_index)
- ULONG SLQSStart (BYTE modem_index, CHAR ∗sn)
- ULONG SLQSKillSDKProcess ()
- ULONG SLQSGetDeviceMode (BYTE ∗pDeviceMode)
- ULONG SLQSStartSrv (BYTE action, BYTE mask)
- ULONG SLQSSetLoggingMask (BYTE mask)
- ULONG SLQSGetNetStatistic (struct NetStats ∗pNetStatistic, BYTE instance)
- ULONG GetQmapIsSupported (BYTE ∗pQmapsupport)
- ULONG SetQmapIPTable (struct QmuxIPTable ∗pQTable)
- ULONG SetQmapIPv6Table (QmuxIPv6Table ∗pQTable)

9.13.1 Detailed Description

Device Connectivity Service API function prototypes.

9.13.2 Macro Definition Documentation

9.13.2.1 #define LEN 10

9.13.2.2 #define PORTNAM_LEN 32

This structure contains the SLQSGetUsbPortNames Information

Parameters

AtCmdPort	[OUT] • Name of AT command port
NmeaPort	[OUT] • Name of NMEA port
DmPort	[OUT] • Name of DM port

Note

Technology Supported: UMTS/CDMA
Device Supported: MC83x5, MC7700/10/50
Timeout: 2 seconds
Port names are limited to 32 characters.

9.13.3 Function Documentation

9.13.3.1 ULONG GetQmapIsSupported (BYTE ∗ *pQmapsupport*)

Returns if the module supports QMAP feature.

Parameters

pQmapsupport[-OUT]	• value – 0 means module does not support QMAP, otherwise QMAP is supported

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.13.3.2 ULONG QCWWAN2kConnect (CHAR * *pDeviceID,* CHAR * *pDeviceKey*)

Connects the Connection Manager API to the first detected QC WWAN device. This function MUST be called after QCWWAN2kEnumerateDevices has been called.

Parameters

pDeviceID[IN]	• Device path pertaining to the device for which the API is being invoked e.g. /dev/qcqmi0.
pDeviceKey[IN]	• Device key pertaining to the device for which the API is being invoked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_ERR_NO_DEVICE otherwise

Note

Timeout: 2 seconds

9.13.3.3 ULONG QCWWAN2kEnumerateDevices (BYTE * *pDevicesSize,* BYTE * *pDevices*)

Enumerates the QC WWAN devices currently attached to the host. This API MUST be called before any other API.

Parameters

pDeviceSize[IN/-OUT]	• Upon input, maximum number of elements that the device array can contain. • Upon successful output, actual number of elements in the device array.
pDevices[IN/OU-T]	• Device array; array elements are structures with the following elements: CHAR deviceID[256] - Device path (e.g. /dev/qcqmi0) CHAR deviceKey[16] - Device key stored in the device (e.g. A1000004B01051)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_ERR_NO_DEVICE on otherwise

Note

Timeout: 2 seconds

9.13.3.4 ULONG QCWWAN2kGetConnectedDeviceID (ULONG *deviceIDSize*, CHAR * *pDeviceID*, ULONG *deviceKeySize*, CHAR * *pDeviceKey*)

Returns the device ID and device key of the currently connected QC WWAN device.

Parameters

deviceIDSize	• Maximum number of characters (including NULL terminator) that the device ID array can contain.
pDeviceID[OUT]	• Device path string
deviceKeySize	• Maximum number of characters (including NULL terminator) that the device key array can contain.
pDeviceKey[OUT]	• Device key string

Returns

eQCWWAN_ERR_NONE if device found, eQCWWAN_ERR_NO_DEVICE otherwise

Note

Timeout: 2 seconds

9.13.3.5 ULONG QCWWANConnect (CHAR * *pDeviceID*, CHAR * *pDeviceKey*)

Enumerates the QC WWAN devices currently attached to the host. This API MUST be called before any other API.

Parameters

pDeviceID[IN]	• Device path pertaining to the device for which the API is being invoked e.g. /dev/qcqmi0.
pDeviceKey[IN]	• Device key pertaining to the device for which the API is being invoked

Returns

eQCWWAN_ERR_NONE if device found, eQCWWAN_ERR_NO_DEVICE otherwise

Note

Timeout: 2 seconds
This API is deprecated; use QCWWAN2kConnect() instead

9.13.3.6 ULONG QCWWANDisconnect ( )

Disconnects the Connection Manager API from a previously connected QC device. This function de-registers all the callback functions that have been registered.

Parameters

none	

Returns

eQCWWAN_ERR_NONE

Note

Timeout: 2 seconds

9.13.3.7 ULONG QCWWANEnumerateDevices (BYTE * *pDevicesSize,* BYTE * *pDevices*)

Enumerates the QC WWAN devices currently attached to the host. This API is deprecated; use QCWWAN2kEnumerateDevices() instead.

Parameters

pDeviceSize[IN/OUT]	• Upon input, maximum number of elements that the device array can contain. • Upon successful output, actual number of elements in the device array.
pDevices[IN/OUT]	• Device array; array elements are structures with the following elements: CHAR deviceID[256] - Device path (e.g. /dev/qcqmi0) CHAR deviceKey[16] - Device key stored in the device

Returns

eQCWWAN_ERR_NONE

Note

Timeout: 2 seconds
This API must be called prior to any other APIs.

9.13.3.8 ULONG SetQmapIPTable (struct QmuxIPTable * *pQTable*)

Set the mux id associated with ip address to the SDK process, it will be propagated to driver by IOCTL

Parameters

pQTable[IN]	• See QmuxIPTable for more details

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.13.3.9 ULONG SetQmapIPv6Table (QmuxIPv6Table * *pQTable*)

Set the mux id associated with ipv6 address to the SDK process, it will be propagated to driver by IOCTL

Parameters

pQTable[IN]	• See QmuxIPv6Table for more details

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.13.3.10 ULONG SetSDKImagePath (LPCSTR *pPath*)

Set the location of the SLQS executable

Parameters

pPath[IN]	- Pointer to fully qualified path of SLQS executable (includes the executable file's name)

Returns

eQCWWAN_ERR_NONE

Note

Timeout: None

9.13.3.11 ULONG SLQSGetDeviceMode (BYTE * *pDeviceMode*)

Returns the Device Mode

Parameters

pDeviceMode[OUT]	• Pointer to SLQS Device Mode of type eDevState

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.13.3.12 ULONG SLQSGetNetStatistic (struct NetStats * *pNetStatistic,* BYTE *instance*)

Returns the usbnet statistics for a particular PDN.

Parameters

	pNetStatistic[OUT]	• Pointer to the structure NetStats which the value of every member is to be retrieved
in	*instance*	• PDP Instance id

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.13.3.13 ULONG SLQSGetUsbPortNames (struct DcsUsbPortNames * *pUsbPortNames*)

Returns the Usb Port Names currently in use.

Parameters

pUsbPortNames[OUT]	• Pointer to SLQS USB Port Names Information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.13.3.14 ULONG SLQSKillSDKProcess ( )

Kill the SDK process

Parameters

none	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: N/A
This API useful if the application was started with non-root privileges as subsequent attempt to start any application will fail because the SDK requires root permission to access /dev/qcqmi device special files.

9.13.3.15 ULONG SLQSSetLoggingMask (BYTE *mask*)

Limit Syslog messages according to the Mask provided by user

Parameters

mask	• Mask 0x01: disable all log • Mask 0xFF: enable all log

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.13.3.16 ULONG SLQSStart (BYTE *modem_index*, CHAR * *sn*)

Create the SDK process and IPC sockets for the Application and SDK processes to communicate over.

Parameters

in	*modem_index*	• 0: first modem detected • 1: second modem detected • 2: third modem detected • ... • 7: seventh modem detected
in	*sn*	This field is optional, it can be serial number or usb path for multiple modem feature, it can be retrieved from sytem command "dmesg" when specified, the modem_index will be mapping to sn or usb path Please set to NULL when not used

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: N/A

9.13.3.17 ULONG SLQSStart_AVAgent (BYTE *modem_index*)

Create IPC sockets for AirVantage Agent and SDK processes to communicate over

Parameters

none	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: N/A

9.13.3.18 ULONG SLQSStartSrv (BYTE *action,* BYTE *mask*)

Registers/deregisters for service with unsolicited notifications

Parameters

action,1	for register, 0 for deregister
mask	• Bit mask for unsolicited notifications – Bit0 - WDS – Bit1 - NAS – Bit2 - PDS – Bit3 - VOICE

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds API is useful to register for the services which supports unsolicited notifications. Registration/deregistration can be done by using parameter action if action is set then the mask (set bits) will be used for registering service and if action is "0" mask(set bits) will be used to deregister services. For example : bit mask 0x03 - Registers for services WDS and NAS if action is "1" and deregisters WDS and NAS if action is "0".

9.14 qaGobiApiDms.h File Reference

Device Management Service API function prototypes.

Data Structures

- struct serialNumbersInfo
- struct ERIFileparams
- struct custFeaturesInfo
- struct custFeaturesSetting
- struct dmsCurrentPRLInfo
- struct FactorySequenceNumber
- struct FirmwareUpdatStat
- struct USBCompParams
- struct USBCompConfig
- struct CrashInfo
- struct CrashInfoParams
- struct _SLQSSwiGetHostDevInfoParams
- struct _SLQSSwiSetHostDevInfoParams
- struct _SLQSSwiGetOSInfoParams
- struct _SLQSSwiSetOSInfoParams
- struct _SLQSSwiGetSerialNoExtParams
- struct setCustomSettingV2
- struct getCustomInput
- struct custSettingInfo
- struct custSettingList
- struct getCustomFeatureV2
- struct getDyingGaspCfg
- struct setDyingGaspCfg
- struct getDyingGaspStatistics
- struct dmsIndicationRegisterReq
- struct dmsSwiGetResetInfo
- struct BandCapabilityResp
- struct dmsSwiGetPCInfo
- struct PSMEnableStateTlv
- struct PSMDurationThresholdTlv
- struct PSMDurationDueToOOSTlv
- struct PSMRandomizationWindowTlv
- struct PSMActiveTimerTlv
- struct PSMPeriodicUpdateTimerTlv
- struct PSMEarlyWakeupTimeTlv
- struct PowerSaveModeConfigResp
- struct PowerSaveModeConfigReq
- struct SwiDmsUIMSelectReq
- struct UimAutoSwitchActSlotTlv
- struct dmsSwiGetUIMSelection

Macros

- #define MAX_FSN_LENGTH 255
- #define MAX_CUST_ID_LEN 64
- #define MAX_CUST_VALUE_LEN 8
- #define MAX_DYING_GASP_CFG_SMS_CONTENT_LENGTH 160
- #define MAX_DYING_GASP_CFG_SMS_NUMBER_LENGTH 20

Typedefs

- typedef struct serialNumbersInfo serialNumbersInfo
- typedef struct ERIFileparams ERIFileparams
- typedef struct custFeaturesInfo custFeaturesInfo
- typedef struct custFeaturesSetting custFeaturesSetting
- typedef struct dmsCurrentPRLInfo dmsCurrentPRLInfo
- typedef struct _SLQSSwiGetHostDevInfoParams SLQSSwiGetHostDevInfoParams
- typedef struct _SLQSSwiSetHostDevInfoParams SLQSSwiSetHostDevInfoParams
- typedef struct _SLQSSwiGetOSInfoParams SLQSSwiGetOSInfoParams
- typedef struct _SLQSSwiSetOSInfoParams SLQSSwiSetOSInfoParams
- typedef struct _SLQSSwiGetSerialNoExtParams SLQSSwiGetSerialNoExtParams

Functions

- ULONG GetManufacturer (BYTE stringSize, CHAR *pString)
- ULONG GetModelID (BYTE stringSize, CHAR *pString)
- ULONG GetFirmwareRevision (BYTE stringSize, CHAR *pString)
- ULONG GetFirmwareRevisions (BYTE amssSize, CHAR *pAMSSString, BYTE bootSize, CHAR *pBoot-String, BYTE priSize, CHAR *pPRIString)
- ULONG GetPRLVersion (WORD *pPRLVersion)
- ULONG GetIMSI (BYTE stringSize, CHAR *pString)
- ULONG GetSerialNumbers (BYTE esnSize, CHAR *pESNString, BYTE imeiSize, CHAR *pIMEIString, BY-TE meidSize, CHAR *pMEIDString)
- ULONG SLQSGetSerialNumbers (serialNumbersInfo *pSerialNumbersInfo)
- ULONG GetHardwareRevision (BYTE stringSize, CHAR *pString)
- ULONG GetNetworkTime (ULONGLONG *pTimeStamp, ULONG *pTimeSource)
- ULONG UIMSetPINProtection (ULONG id, ULONG bEnable, CHAR *pValue, ULONG *pVerifyRetriesLeft, ULONG *pUnblockRetriesLeft)
- ULONG UIMUnblockPIN (ULONG id, CHAR *pPUKValue, CHAR *pNewValue, ULONG *pVerifyRetriesLeft, ULONG *pUnblockRetriesLeft)
- ULONG UIMVerifyPIN (ULONG id, CHAR *pValue, ULONG *pVerifyRetriesLeft, ULONG *pUnblockRetries-Left)
- ULONG UIMChangePIN (ULONG id, CHAR *pOldValue, CHAR *pNewValue, ULONG *pVerifyRetriesLeft, ULONG *pUnblockRetriesLeft)
- ULONG GetVoiceNumber (BYTE voiceNumberSize, CHAR *pVoiceNumber, BYTE minSize, CHAR *pMIN)
- ULONG SetPower (ULONG powerMode)
- ULONG GetPower (ULONG *pPowerMode)
- ULONG UIMGetControlKeyStatus (ULONG id, ULONG *pStatus, ULONG *pVerifyRetriesLeft, ULONG *p-UnblockRetriesLeft)
- ULONG UIMGetICCID (BYTE stringSize, CHAR *pString)

- ULONG UIMGetPINStatus (ULONG id, ULONG *pStatus, ULONG *pVerifyRetriesLeft, ULONG *pUnblockRetriesLeft)
- ULONG GetOfflineReason (ULONG *pReasonMask, ULONG *pbPlatform)
- ULONG UIMSetControlKeyProtection (ULONG id, ULONG status, CHAR *pValue, ULONG *pVerifyRetriesLeft)
- ULONG UIMUnblockControlKey (ULONG id, CHAR *pValue, ULONG *pUnblockRetriesLeft)
- ULONG GetDeviceCapabilities (ULONG *pMaxTXChannelRate, ULONG *pMaxRXChannelRate, ULONG *pDataServiceCapability, ULONG *pSimCapability, ULONG *pRadioIfacesSize, BYTE *pRadioIfaces)
- ULONG ResetToFactoryDefaults (CHAR *pSPC)
- ULONG ValidateSPC (CHAR *pSPC)
- ULONG ActivateAutomatic (CHAR *pActivationCode)
- ULONG SLQSGetERIFile (ERIFileparams *pERIFileparams)
- ULONG GetActivationState (ULONG *pActivationState)
- ULONG SLQSUIMGetState (ULONG *pUIMState)
- ULONG SLQSGetBandCapability (ULONGLONG *pBandCapability)
- ULONG SLQSGetCustFeatures (custFeaturesInfo *pCustFeaturesInfo)
- ULONG SLQSSetCustFeatures (custFeaturesSetting *pCustFeaturesSetting)
- ULONG SLQSGetCurrentPRLInfo (dmsCurrentPRLInfo *pCurrentPRLInfo)
- ULONG SLQSSwiGetFSN (FactorySequenceNumber *pFSNumber)
- ULONG SLQSSwiGetFwUpdateStatus (FirmwareUpdatStat *pFirmwareUpdatStat)
- ULONG SLQSSwiGetUSBComp (USBCompParams *pUSBCompParams)
- ULONG SLQSSwiSetUSBComp (USBCompConfig *pUSBCompConfig)
- ULONG SLQSSwiGetCrashInfo (BYTE *pClear, CrashInfoParams *pCrashInfoParams)
- ULONG SLQSSwiGetCrashAction (BYTE *pDevCrashState)
- ULONG SLQSSwiSetCrashAction (BYTE crashActionParams)
- ULONG SLQSSwiGetHostDevInfo (SLQSSwiGetHostDevInfoParams *pGetHostDevInfoParams)
- ULONG SLQSSwiSetHostDevInfo (SLQSSwiSetHostDevInfoParams *pSetHostDevInfoParams)
- ULONG SLQSSwiGetOSInfo (SLQSSwiGetOSInfoParams *pParams)
- ULONG SLQSSwiSetOSInfo (SLQSSwiSetOSInfoParams *pParams)
- ULONG SLQSSwiGetSerialNoExt (SLQSSwiGetSerialNoExtParams *pParams)
- ULONG SLQSSetCustFeaturesV2 (setCustomSettingV2 *pSetCustSetting)
- ULONG SLQSGetCustFeaturesV2 (getCustomFeatureV2 *pGetCustomFeatureV2)
- ULONG SLQSSwiGetDyingGaspCfg (getDyingGaspCfg *pConfig)
- ULONG SLQSSwiSetDyingGaspCfg (setDyingGaspCfg *pConfig)
- ULONG SLQSSwiGetDyingGaspStatistics (getDyingGaspStatistics *pStatistics)
- ULONG SLQSSwiClearDyingGaspStatistics ()
- ULONG SLQSDmsSwiIndicationRegister (dmsIndicationRegisterReq *pIndicationRegisterReq)
- ULONG SLQSDmsSwiGetResetInfo (dmsSwiGetResetInfo *pGetResetInfoResp)
- ULONG SLQSGetBandCapabilities (BandCapabilityResp *pBandCapability)
- ULONG SLQSDmsSwiGetPCInfo (dmsSwiGetPCInfo *pGetPCInfoResp)
- ULONG SLQSGetPowerSaveModeConfig (PowerSaveModeConfigResp *pPSMConfigParam)
- ULONG SLQSSetPowerSaveModeConfig (PowerSaveModeConfigReq *pPSMConfigParamReq)
- ULONG SLQSSwiDmsUimSelect (SwiDmsUIMSelectReq *pReq)
- ULONG SLQSDmsSwiGetUimSelection (dmsSwiGetUIMSelection *pGetUIMSelectionResp)

9.14.1 Detailed Description

Device Management Service API function prototypes.

9.14.2 Macro Definition Documentation

9.14.2.1 #define MAX_CUST_ID_LEN 64

9.14.2.2 #define MAX_CUST_VALUE_LEN 8

9.14.2.3 #define MAX_DYING_GASP_CFG_SMS_CONTENT_LENGTH 160

9.14.2.4 #define MAX_DYING_GASP_CFG_SMS_NUMBER_LENGTH 20

9.14.2.5 #define MAX_FSN_LENGTH 255

9.14.3 Typedef Documentation

9.14.3.1 typedef struct **custFeaturesInfo custFeaturesInfo**

This structure contains current settings of custom features

Parameters

GpsEnable[OUT]	• describes if GPS is enabled or disabled • values: – 0x00 - GPS is disabled – 0x01 - GPS is enabled • function SLQSGetCustFeatures() returns a default value FFFFFFFF if no value is returned by the modem
pDisableIMSI[OUT]	• optional 1 byte parameter • describes if IMSI display is enabled or disabled • values: – 0x00 - Allow display of IMSI – 0x01 - Do not display IMSI • function SLQSGetCustFeatures() returns a default value FF if no value is returned by the modem
pIPFamSupport[OUT]	• optional 2 byte BitMask • bitmask representing the IP families supported • values: – 0x01 - IPv4 – 0x02 - IPv6 – 0x04 - IPv4v6 • function SLQSGetCustFeatures() returns a default value FFFF if no value is returned by the modem
pRMAutoConnect[OUT]	• optional 1 byte parameter • QMI Mode RM Net Auto Connect Support • values: – 0x00 - Not Supported – 0x01 - Supported • function SLQSGetCustFeatures() returns a default value FF if no value is returned by the modem

pGPSSel[OUT]	• optional 1 byte parameter • GPS Antenna Select • values: – 0x00 - Dedicated GPS Port – 0x01 - GPS Rx over AUX Port – 0x02 - GPS Rx over dedicated GPS port with no bias voltage applied • function SLQSGetCustFeatures() returns a default value FF if no value is returned by the modem
pSMSSupport[-OUT]	• optional 1 byte parameter • SMS support • values: – 0x00 - Not supported – 0x01 - supported • Used to determine whether or not to hide SMS from user • function SLQSGetCustFeatures() returns a default value FF if no value is returned by the modem. In this case assume, SMS is supported.
pIsVoice-Enabled[OUT]	• optional 1 byte parameter • Voice support • values: – 0x00 - Enable voice on both AT and QMI interface (default) – 0x01 - Reserved – 0x02 - Disable voice on both AT and QMI interface
pDHCPRelay-Enabled[OUT]	• optional 1 byte parameter • DHCP Relay support • values: – 0x00 - Disable DHCP relay – 0x01 - Enable DHCP relay
pGPSLPM[OUT]	• optional 1 byte parameter • GPSLPM support • values: – 0x00 - Enable GPS in Low Power Mode – 0x01 - Disable GPS in Low Power Mode

9.14.3.2 typedef struct custFeaturesSetting custFeaturesSetting

This structure contains settings to be used for custom features

Parameters

pGPSSel	• optional 1 byte parameter • GPS Antenna Select • values: – 0x00 - Dedicated GPS Port – 0x01 - GPS Rx over AUX Port – 0x02 - GPS Rx over dedicated GPS port with no bias voltage applied
pGPSEnable	• optional 4 byte parameter • GPS Enable/Disable • values: The value of 7 least significant bits: – 0 - Disabled – 1 - MT & MO enabled – 2 - MO enabled – 3 - MT enabled – 4 - MT & MO enabled if GPS_DISABLE pin is not asserted – 5 - MO GPS enabled if GPS_DISABLE pin is not asserted – 6 - MT GPS enabled if GPS_DISABLE pin is not asserted

Note

Only MC7750 3.5.x firmware supports above 0x04, 0x05 and 0x06 settings. To disable GLONASS, set the most significant bit - 0x80. This setting is only applicable if GPS is not Disabled.

Parameters

pIsVoiceEnabled	• optional 1 byte parameter • voice enabled/disabled • values: – 0 - Enable voice on both AT and QMI interface (default) – 1 - Reserved – 2 - Disable voice on both AT and QMI interface
pDHCPRelay-Enabled	• optional 1 byte parameter • DHCPRELAYENABLE support • values: – 0 - Disable DHCP relay – 1 - Enable DHCP relay
pGPSLPM	• optional 1 byte parameter • GPSLPM support • values: – 0 - Enable GPS in Low Power Mode – 1 - Disable GPS in Low Power Mode

9.14.3.3 typedef struct dmsCurrentPRLInfo dmsCurrentPRLInfo

This structure contains GetCurrentPRLInfo response parameter

Parameters

pPRLVersion[OUT]	- Optional • PRL version of device.
pPRLPreference	[OUT]- Optional • PRL Preference – 0 - Unset – 1 - Set

9.14.3.4 typedef struct ERIFileparams ERIFileparams

This structure contains Extended Roaming Indicator(ERI) file parameters

Parameters

pFileSize[IN/OUT]	• Upon input, the maximum number of bytes that file contents array can contain. • Upon successful output, actual number of bytes written to file contents array
pFile[OUT]	• ERI data read from persistent storage(Max size is 1024)

9.14.3.5 typedef struct serialNumbersInfo serialNumbersInfo

Returns all the serial numbers assigned to the device. These serial numbers include the ESN (Electronic serial number of the device), the IMEI (International Mobile Equipment Identity) and MEID (Mobile Equipment Identifier).

Parameters

esnSize	• The maximum number of characters (including NULL terminator) that the ESN string array can contain
pESNString[OUT]	• NULL-terminated ESN string. Empty string is returned when ESN is not supported/programmed
imeiSize	• The maximum number of characters (including NULL terminator) that the IMEI string array can contain
pIMEIString[OUT]	• NULL terminated IMEI string. Empty string is returned when IMEI is not supported/programmed
meidSize	• The maximum number of characters (including NULL terminator) that the MEID string array can contain

pMEIDString[OUT]	• NULL-terminated MEID string. Empty string is returned when MEID is not supported/programmed
imeiSvnSize	• The maximum number of characters (including NULL terminator) that the IMEI SVN string array can contain.
pImeiSvnString[OUT]	• NULL-terminated IMEI SVN string. Empty string is returned when IMEI SVN is not supported/programmed.

9.14.3.6 typedef struct _SLQSSwiGetHostDevInfoParams SLQSSwiGetHostDevInfoParams

This structure is used to Get Host Device Information

Parameters

bManSize[IN/OUT]	• Host Device Manufacturer String Size
pManString[OUT]	• Host Device Manufacturer Name(Optional parameter) • Null terminated ASCII String
bModelSize[IN/OUT]	• Host Device Model String Size
pModelString[OUT]	• Host Device Model String(Optional parameter) • Null terminated ASCII string.
bSWVerSize[IN/OUT]	• Host Device Software Version String Size
pSWVerString[OUT]	• Host Device Software Version String(Optional parameter) • Null terminated ASCII string
bPlasmaIDSize[IN/OUT]	• Host Device Plasma ID String Size
pPlasmaIDString[OUT]	• Host Device Plasma ID String(Optional parameter) • Null terminated alphanumeric ASCII String.

9.14.3.7 typedef struct _SLQSSwiGetOSInfoParams SLQSSwiGetOSInfoParams

This structure is used to Get OS Information

Parameters

bNameSize[IN/-OUT]	• Size of Operating System Name
pNameString[O-UT]	• Operating System Name(Optional parameter) • Null terminated ASCII string
bVersionSize[I-N/OUT]	• Operating System Version Size
pVersionString[-OUT]	• Operating System Version String(Optional parameter) • Null terminated ASCII string.

9.14.3.8 typedef struct _SLQSSwiGetSerialNoExtParams SLQSSwiGetSerialNoExtParams

This structure is used to store MEID Information

Parameters

meidLength[OU-T]	• String length of the of MEID received
pMeidString[OU-T]	• Optional parameter • Pointer to receive String containing the Mobile Equipment Identifier(MEID) of the device.

9.14.3.9 typedef struct _SLQSSwiSetHostDevInfoParams SLQSSwiSetHostDevInfoParams

This structure is used to Set Host Device Information

Parameters

bManSize[IN]	• Host Device Manufacturer String Size
pManString[IN]	• Host Device Manufacturer Name(Optional parameter) • Null terminated ASCII String
bModelSize[IN]	• Host Device Model String Size
pModelString[IN]	• Host Device Model String(Optional parameter) • Null terminated ASCII string.
bSWVerSize[IN]	• Host Device Software Version String Size

pSWVerString[IN]	• Host Device Software Version String(Optional parameter) • Null terminated ASCII string
bPlasmaIDSize[IN]	• Host Device Plasma ID String Size
pPlasmaIDString[IN]	• Host Device Plasma ID String(Optional parameter) • Null terminated alphanumeric ASCII String.

9.14.3.10 typedef struct _SLQSSwiSetOSInfoParams SLQSSwiSetOSInfoParams

This structure is used to Set OS Information

Parameters

bNameSize[IN]	• Size of Operating System Name
pNameString[IN]	• Operating System Name(Optional parameter) • Null terminated ASCII string
bVersionSize[IN]	• Operating System Version Size
pVersionString[IN]	• Operating System Version String(Optional parameter) • Null terminated ASCII string.

9.14.4 Function Documentation

9.14.4.1 ULONG ActivateAutomatic (CHAR * *pActivationCode*)

Requests the device to perform automatic service activation

Parameters

pActivationCode[IN]	• NULL-terminated string representing activation code (maximum string length of 12); specific carrier requirements may dictate actual activation code that is applicable, e.g., "*22899"

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Minutes

9.14.4.2 ULONG GetActivationState (ULONG * *pActivationState*)

Returns the device activation state. This API is only supported for 3GPP2 devices.

Parameters

pActivation-State[OUT]	• Service Activation Code 0 - Service not activated 1 - Service activated 2 - Activation connecting 3 - Activation connected 4 - OTASP security authenticated 5 - OTASP NAM downloaded 6 - OTASP MDN downloaded 7 - OTASP IMSI downloaded 8 - OTASP PRL downloaded 9 - OTASP SPC downloaded 10 - OTASP settings committed

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 Seconds

9.14.4.3 ULONG GetDeviceCapabilities (ULONG * *pMaxTXChannelRate,* ULONG * *pMaxRXChannelRate,* ULONG * *pDataServiceCapability,* ULONG * *pSimCapability,* ULONG * *pRadioIfacesSize,* BYTE * *pRadioIfaces*)

Gets the device capabilities

Parameters

pMaxTX-ChannelRate[O-UT]	• Maximum transmission rate (in bps) supported by the device • In multi-technology devices, this value will be the greatest rate among all supported technologies
pMaxRX-ChannelRate[O-UT]	• Maximum reception rate (in bps) supported by the device • In multi-technology devices, this value will be the greatest rate among all supported technologies

pDataService-Capability[OUT]	• CS/PS data service capability – 0 - No data services supported – 1 - Only Circuit Switched (CS) services supported – 2 - Only Packet Switched (PS) services supported – 3 - Simultaneous CS and PS – 4 - Non-simultaneous CS and PS
pSimCapability[-OUT]	• Device SIM capability – 0 - SIM not supported – 1 - SIM supported
pRadioIfaces-Size[IN/OUT]	• Upon input, the maximum number of elements that the radio interface array can contain • Upon successful output, actual number of elements in the radio interface array
pRadioIfaces[O-UT]	• Radio interface array. This is a structure of array containing the elements below. ULONG radioInterface – See qaGobiApiTableRadioInterfaces.h for Radio Interfaces

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.4 ULONG GetFirmwareRevision (BYTE *stringSize*, CHAR * *pString*)

Returns the device firmware revision

Parameters

stringSize	• The maximum number of characters (including NULL terminator) that the string array can contain
pString[OUT]	• NULL terminated string

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.5 ULONG GetFirmwareRevisions (BYTE *amssSize*, CHAR * *pAMSSString*, BYTE *bootSize*, CHAR * *pBootString*, BYTE *priSize*, CHAR * *pPRIString*)

Returns the device firmware revisions (AMSS, boot, and PRI)

Parameters

amssSize	• Maximum number of characters (including NULL terminator) that the AMSS string array can contain
pAMSSString[OUT]	• NULL-terminated AMSS revision string
bootSize	• Maximum number of characters (including NULL terminator) that the boot string array can contain
pBootString[OUT]	• NULL-terminated boot code revision string
priSize	• Maximum number of characters (including NULL terminator) that the PRI string array can contain
pPRIString[OUT]	• NULL-terminated PRI revision string

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.6 ULONG GetHardwareRevision (BYTE *stringSize*, CHAR * *pString*)

Returns the hardware revision of the device

Parameters

stringSize	• The maximum number of characters (including NULL terminator) that the string array can contain
pString[OUT]	• NULL terminated string

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.7 ULONG GetIMSI (BYTE *stringSize,* CHAR * *pString*)

Returns the device IMSI. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use SLQSUIMReadTransparent()(EF ID: 3F00 7F20 6F07 for 2G card and 3F00 7FFF 6F07 for 3G card) instead for new firmware versions and new modules.

Parameters

stringSize	• The maximum number of characters (including NULL terminator) that the string array can contain
pString[OUT]	• NULL terminated string

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.8 ULONG GetManufacturer (BYTE *stringSize,* CHAR * *pString*)

Returns the device manufacturer name

Parameters

stringSize	• The maximum number of characters (including NULL terminator) that the string array can contain.
pString[OUT]	• NULL terminated string

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.9 ULONG GetModelID (BYTE *stringSize*, CHAR * *pString*)

Returns the device model ID

Parameters

stringSize	• The maximum number of characters (including NULL terminator) that the string array can contain
pString[OUT]	• NULL terminated string

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.10 ULONG GetNetworkTime (ULONGLONG * *pTimeStamp*, ULONG * *pTimeSource*)

Returns the current time of the device based on the value supported by the network.

Parameters

pTimeStamp[OUT]	• Count of 1.25 ms that have elapsed from the start of GPS time (Jan 6, 1980)
pTimeSource[OUT]	• Source of timestamp 0 - 32 kHz device clock 1 - CDMA network 2 - cdma2000 1xEV-DO network

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
The source of the timestamp provided specifies how the timestamp was determined. The first network time that is available will be returned. If no network time is available, the timestamp is taken from the 32 kHz slow-clock of the device.

9.14.4.11 ULONG GetOfflineReason (ULONG * *pReasonMask,* ULONG * *pbPlatform*)

Returns reason why the operating mode of the device is currently offline.

Parameters

pReasonMask[OUT]	• Optional parameter • Bitmask of offline reasons – 0x00000001 - Host image configuration issue – 0x00000002 - PRI image configuration issue – 0x00000004 - PRI version incompatible – 0x00000008 - PRI copy issue – All others - Reserved
pbPlatform[OUT]	• Optional parameter • Is the device offline due to a platform restriction? – 0 - No – 1 - Yes

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.14.4.12 ULONG GetPower (ULONG * *pPowerMode*)

Returns the operating mode of the device.

Parameters

pPowerMode[OUT]	• Selected operating mode – See qaGobiApiTablePowerModes.h for power modes

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.14.4.13 ULONG GetPRLVersion (WORD * *pPRLVersion*)

Returns the version of the active Preferred Roaming List (PRL) in use by the device.

Parameters

pPRLVersion[OUT]	• PRL version number

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.14 ULONG GetSerialNumbers (BYTE *esnSize*, CHAR * *pESNString*, BYTE *imeiSize*, CHAR * *pIMEIString*, BYTE *meidSize*, CHAR * *pMEIDString*)

Returns all the serial numbers assigned to the device. These serial numbers include the ESN (Electronic serial number of the device), the IMEI (International Mobile Equipment Identity) and MEID (Mobile Equipment Identifier).

Parameters

esnSize	• The maximum number of characters (including NULL terminator) that the ESN string array can contain
pESNString[OUT]	• NULL-terminated ESN string. Empty string is returned when ESN is not supported/programmed
imeiSize	• The maximum number of characters (including NULL terminator) that the IMEI string array can contain
pIMEIString[OUT]	• NULL terminated IMEI string. Empty string is returned when IMEI is not supported/programmed
meidSize	• The maximum number of characters (including NULL terminator) that the MEID string array can contain
pMEIDString[OUT]	• NULL-terminated MEID string. Empty string is returned when MEID is not supported/programmed

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

For CDMA devices that use a RUIM, the MEID of the RUIM (if present) will be returned. Use SLQSSwiGetSerialNoExt() to get MEID of CDMA modems. Timeout: 2 seconds

9.14.4.15 ULONG GetVoiceNumber (BYTE *voiceNumberSize*, CHAR * *pVoiceNumber*, BYTE *minSize*, CHAR * *pMIN*)

Returns the voice number in use by the device

Parameters

voiceNumberSize	• Maximum number of characters (including NULL terminator) that the voice number array can contain.
pVoiceNumber[OUT]	• Voice number string: MDN or MS ISDN

minSize	• Maximum number of characters (including NULL terminator) that the MIN array can contain.
pMIN[OUT]	• Optional Parameter • MIN string: Empty string returned when MIN is not supported/ programmed.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.16 ULONG ResetToFactoryDefaults (CHAR * *pSPC*)

Resets to default factory settings of the device

Parameters

pSPC[IN]	• NULL-terminated string representing a six-digit service programming code

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 minutes

9.14.4.17 ULONG SetPower (ULONG *powerMode*)

Sets the operating mode of the device.

Parameters

powerMode[IN]	• Selected operating mode – See qaGobiApiTablePowerModes.h for power modes

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.18 ULONG SLQSDmsSwiGetPCInfo (dmsSwiGetPCInfo * *pGetPCInfoResp*)

This function is used to get the device power control status information

Parameters

pGetPCInfoResp	• See dmsSwiGetPCInfo for more information of the input structure

9.14.4.19 ULONG SLQSDmsSwiGetResetInfo (dmsSwiGetResetInfo * *pGetResetInfoResp*)

This function is used to get reset info

Parameters

pGetResetInfo-Resp	• See dmsSwiGetResetInfo for more information of the input structure

9.14.4.20 ULONG SLQSDmsSwiGetUimSelection (dmsSwiGetUIMSelection * *pGetUIMSelectionResp*)

This command gets currently selected active UIM slot.

Parameters

pGetUIM-SelectionResp	• See dmsSwiGetUIMSelection for more information of the input structure

9.14.4.21 ULONG SLQSDmsSwiIndicationRegister (dmsIndicationRegisterReq * *pIndicationRegisterReq*)

This function used to set Swi Indication Register

Parameters

pConfig	• See dmsIndicationRegisterReq for more information of the inpurt structure

9.14.4.22 ULONG SLQSGetBandCapabilities (BandCapabilityResp * *pBandCapability*)

Returns the band capability of the device.

Parameters

pBand-Capability[OUT]	See BandCapabilityResp for more information of the inpurt structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.14.4.23 ULONG SLQSGetBandCapability (ULONGLONG * *pBandCapability*)

Returns the band capability of the device.

Parameters

pBandCapability[OUT]	Bitmask of bands supported by the device • Bit 0 - Band class 0, A-system • Bit 1 - Band class 0, B-system • Bit 2 - Band class 1, all blocks • Bit 3 - Band class 2 • Bit 4 - Band class 3, A-system • Bit 5 - Band class 4, all blocks • Bit 6 - Band class 5, all blocks • Bit 7 - GSM DCS band (1800) • Bit 8 - GSM Extended GSM (E-GSM) band (900) • Bit 9 - GSM Primary GSM (P-GSM) band (900) • Bit 10 - Band class 6 • Bit 11 - Band class 7 • Bit 12 - Band class 8 • Bit 13 - Band class 9 • Bit 14 - Band class 10 • Bit 15 - Band class 11 • Bit 16 - GSM 450 band • Bit 17 - GSM 480 band • Bit 18 - GSM 750 band • Bit 19 - GSM 850 band • Bit 20 - GSM railways GSM band (900) • Bit 21 - GSM PCS band (1900) • Bit 22 - WCDMA (Europe, Japan, and China) 2100 band • Bit 23 - WCDMA US PCS 1900 band • Bit 24 - WCDMA (Europe and China) DCS 1800 band • Bit 25 - WCDMA US 1700 band • Bit 26 - WCDMA US 850 band • Bit 27 - WCDMA Japan 800 band • Bit 28 - Band class 12 • Bit 29 - Band class 14 • Bit 30 - Reserved • Bit 31 - Band class 15 • Bits 32 through 47 - Reserved • Bit 48 - WCDMA Europe 2600 band • Bit 49 - WCDMA Europe and Japan 900 band • Bit 50 - WCDMA Japan 1700 band • Bits 51 through 55 - Reserved • Bit 56 - Band class 16 • Bit 57 - Band class 17 • Bit 58 - Band class 18 • Bit 59 - Band class 19 • Bit 60 - WCDMA Japan 850 band • Bit 61 - WCDMA 1500 band • Bits 62 and 63 - Reserved

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.14.4.24 ULONG SLQSGetCurrentPRLInfo (dmsCurrentPRLInfo * *pCurrentPRLInfo*)

This API get the currently active PRL information of the device.

Parameters

pCurrentPRLInfo	• Pointer to structure dmsCurrentPRLInfo • See dmsCurrentPRLInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 Secs

9.14.4.25 ULONG SLQSGetCustFeatures (custFeaturesInfo * *pCustFeaturesInfo*)

This API fetches the current settings of custom features. This API is deprecated for EM74xx/MC74xx, please use SLQSGetCustFeaturesV2() instead for EM74xx/MC74xx.

Parameters

pCustFeatures-Info	• Structure containing settings of custom features. • See custFeaturesInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.14.4.26 ULONG SLQSGetCustFeaturesV2 (getCustomFeatureV2 * *pGetCustomFeatureV2*)

This function queries the modem for a list of supported features. This function is for firmware version 2.0 and newer. Currently supported Customization features:

- GPIOSARENABLE
- GPSSEL
- IMSWITCHHIDE
- IPV6ENABLE
- WAKEHOSTEN

Parameters

pGetCustomFeatureV2	• See getCustomFeatureV2 for more information of the inpurt structure

9.14.4.27 ULONG SLQSGetERIFile (ERIFileparams * *pERIFileparams*)

Returns the Extended Roaming Indicator (ERI) file that is stored in EFS on the device at a predetermined location. See the carrier requirements for specific details.

Parameters

pERIFileparams	• Pointer to structure ERIFileparams • See ERIFileparams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 5 Seconds

9.14.4.28 ULONG SLQSGetPowerSaveModeConfig (PowerSaveModeConfigResp * *pPSMConfigParam*)

Returns the Power Save Mode (PSM) configuration parameters..

Parameters

pPSMConfig-Param[OUT]	See PowerSaveModeConfigResp for more information of the input structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.14.4.29 ULONG SLQSGetSerialNumbers (serialNumbersInfo * *pSerialNumbersInfo*)

Returns all the serial numbers assigned to the device. These serial numbers include the ESN (Electronic serial number of the device), the IMEI (International Mobile Equipment Identity), MEID (Mobile Equipment Identifier) and IMEI SVN (IMEI software version number).

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

For CDMA devices that use a RUIM, the MEID of the RUIM (if present) will be returned. Use SLQSSwiGet-SerialNoExt() to get MEID of CDMA modems. Timeout: 2 seconds

9.14.4.30 ULONG SLQSSetCustFeatures (custFeaturesSetting * *pCustFeaturesSetting*)

This API changes the settings of custom features, a reset is required for any settings that are changed to take effect. This API is deprecated for EM74xx/MC74xx, please use SLQSSetCustFeaturesV2() for EM74xx/MC74xx.

Parameters

pCustFeatures-Setting[IN]	• Structure containing settings of custom features. • See custFeaturesSetting for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.14.4.31 ULONG SLQSSetCustFeaturesV2 (setCustomSettingV2 * *pSetCustSetting*)

This function sets the modem for a list of supported features. This function is for firmware version 2.0 and newer. Currently supported customization features:

- GPIOSARENABLE
- GPSENABLE
- GPSSEL
- ISVOICEEN
- DHCPRELAYENABLE
- GPSLPM
- SUBNETMSKENABLE
- IMSWITCHHIDE
- IPV6ENABLE
- WAKEHOSTEN
- IPCHANNELRATEEN
- Other Custom Settings

Parameters

pSetCustSetting	• Optional parameter • See setCustomSettingV2 for more information

9.14.4.32 ULONG SLQSSetPowerSaveModeConfig (PowerSaveModeConfigReq * *pPSMConfigParamReq*)

Sets the Power Save Mode (PSM) configuration parameters.

Parameters

pPSMConfig-Param[OUT]	See PowerSaveModeConfigResp for more information of the input structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.14.4.33 ULONG SLQSSwiClearDyingGaspStatistics ( )

This function Clear Dying GASP Statistics.

9.14.4.34 ULONG SLQSSwiDmsUimSelect (SwiDmsUIMSelectReq * *pReq*)

This function used to set Swi UIM select. A reset is required for any change in the UIM selection to take effect.

Parameters

pReq[IN]	See SwiDmsUIMSelectReq for more information of the input structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.14.4.35 ULONG SLQSSwiGetCrashAction (BYTE * *pDevCrashState*)

This API queries the Crash State from the device.

Parameters

pDevCrash-State[OUT]	• Device Crash State • Values: – 0 - USB Memory Download Modem will reset after a crash and will stay in USB download mode with only ttyUSB0 enumerated. ramdump tool is to be used to recover the crash dump. Modem needs to be reset again to come back in ONLINE mode. – 1 - Reset Modem will reset and come back in ONLINE mode. Minimal crash data will be available and can be extracted with at!gcdump? AT command or SLQSSwiGetCrashInfo() SDK API – 2 - No action

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Please free two buffers after get crash report successfully

1. pCrashInfoParams->pCrashInfo->pCrashString
2. pCrashInfoParams->pCrashInfo->pGCDumpString Timeout: 5 Secs

9.14.4.36 ULONG SLQSSwiGetCrashInfo (BYTE * *pClear,* CrashInfoParams * *pCrashInfoParams*)

This API queries the Crash Information from the device.

Parameters

pClear[IN]	• request parameter Clear(Optional parameter) • Values: 0 - Do not clear crash data after response 1 - Clear crash data after response
pCrashInfo-Params[Out]	• Pointer to structure CrashInfoParams • See CrashInfoParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Timeout: 5 Secs

9.14.4.37 ULONG SLQSSwiGetDyingGaspCfg (getDyingGaspCfg * *pConfig*)

This function queries Dying GASP Config.

Parameters

pGetCustom-FeatureV2	• See getDyingGaspCfg for more information of the inpurt structure *

9.14.4.38 ULONG SLQSSwiGetDyingGaspStatistics (getDyingGaspStatistics * *pStatistics*)

This function queries Dying GASP Statistics.

Parameters

pStatistics	• See getDyingGaspStatistics for more information of the inpurt structure *

9.14.4.39 ULONG SLQSSwiGetFSN (FactorySequenceNumber * *pFSNumber*)

This API get the Factory Sequence Number of the device.

Parameters

pFSNumber	• Pointer to structure FactorySequenceNumber • See FactorySequenceNumber for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 5 Secs

9.14.4.40 ULONG SLQSSwiGetFwUpdateStatus (FirmwareUpdatStat * *pFirmwareUpdatStat*)

This API will be used to query last firmware update status. The firmware status is stored in RAM and can be retained over warm resets but not power off resets.

Parameters

pFirmware-UpdatStat	• Pointer to structure FirmwareUpdatStat • See FirmwareUpdatStat for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx
Timeout: 5 Secs

9.14.4.41 ULONG SLQSSwiGetHostDevInfo (SLQSSwiGetHostDevInfoParams * *pGetHostDevInfoParams*)

This API Get Host Information from the device.

Parameters

pGetHostDevInfoParams	• See SLQSSwiGetHostDevInfoParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Timeout: 2 Secs

9.14.4.42 ULONG SLQSSwiGetOSInfo (SLQSSwiGetOSInfoParams * *pParams*)

This API queries the device operating system info configured on the modem for OMA-DM reporting

Parameters

pParams	• - See SLQSSwiGetOSInfoParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Timeout: 2 Secs

9.14.4.43 ULONG SLQSSwiGetSerialNoExt (SLQSSwiGetSerialNoExtParams * *pParams*)

This API is used to get the MEID of the modem. For CDMA devices that use a RUIM, the MEID of the modem will always be returned.

Parameters

SLQSSwiGet-SerialNoExt-Params	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Timeout: 5 Secs

9.14.4.44 ULONG SLQSSwiGetUSBComp (USBCompParams * *pUSBCompParams*)

This API queries the modem's USB interface configuration and supported configuration parameters.

Parameters

pUSBComp-Params	• Pointer to structure USBCompParams • See USBCompParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Timeout: 5 Secs

9.14.4.45 ULONG SLQSSwiSetCrashAction (BYTE *crashActionParams*)

This API set the Crash Action to the device.

Parameters

crashAction-Params[IN]	• Crash Action • Values: – 0 - USB Memory Download Modem will reset after a crash and will stay in USB download mode with only ttyUSB0 enumerated. ramdump tool is to be used to recover the crash dump. Modem needs to be reset again to come back in ONLINE mode. – 1 - Reset Modem will reset and come back in ONLINE mode. Minimal crash data will be available and can be extracted with at!gcdump? AT command or SLQSSwiGetCrashInfo() SDK API – 2 - No action

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Timeout: 5 Secs

9.14.4.46 ULONG SLQSSwiSetDyingGaspCfg (setDyingGaspCfg * *pConfig*)

This function set Dying GASP Config.

Parameters

pConfig	• See setDyingGaspCfg for more information of the inpurt structure

9.14.4.47 ULONG SLQSSwiSetHostDevInfo (SLQSSwiSetHostDevInfoParams * *pSetHostDevInfoParams*)

This API Sets the host device info configured on the modem for OMA-DM reporting

Parameters

pSetHostDev-InfoParams	• See SLQSSwiSetHostDevInfoParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Timeout: 2 Secs

9.14.4.48 ULONG SLQSSwiSetOSInfo (SLQSSwiSetOSInfoParams * *pParams*)

This API Set OS Information to the device.

Parameters

pParams	• See SLQSSwiSetOSInfoParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Timeout: 2 Secs

9.14.4.49 ULONG SLQSSwiSetUSBComp (USBCompConfig * *pUSBCompConfig*)

This API is used to change the modem's USB interface configuration thus allowing a device to have multiple USB compositions. Devices will, by default, be configured to support a minimal set of interfaces to reduce end user modem installation time. Developers and some customers, however, require access to a custom set of interfaces. A reset is required for any change in the USB composition to take effect.

Parameters

pUSBCompConfig	• Pointer to structure USBCompConfig • See USBCompConfig for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Timeout: 5 Secs

9.14.4.50 ULONG SLQSUIMGetState (ULONG * *pUIMState*)

Returns the UIM state. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use API SLQSUIMGetCardStatus() for new firmware versions and new modules

Parameters

pUIMState[OUT]	• UIM state: – 0x00 - UIM initialization completed – 0x01 - UIM locked or failed – 0x02 - UIM not present – 0x03 - 0xFE - Reserved – 0xFF - UIM state currently unavailable

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.14.4.51 ULONG UIMChangePIN (ULONG *id*, CHAR * *pOldValue*, CHAR * *pNewValue*, ULONG * *pVerifyRetriesLeft*, ULONG * *pUnblockRetriesLeft*)

Changes the PIN value for a given PIN. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use API SLQSUIMChangePin() for new firmware versions and new modules

Parameters

id[IN]	• PIN ID – 1 (PIN1 / CHV1) – 2 (PIN2 / CHV2)
pOldValue[IN]	• Old PIN value of PIN to change
pNewValue[IN]	• New PIN value of PIN to change
pVerifyRetriesLeft[OUT]	• Optional Parameter • Upon operational failure, this will indicate number of retries left, after which PIN will be blocked. – 0xFFFFFFFF - Unknown

pUnblock-RetriesLeft[OUT]	• Optional Parameter • Upon operational failure, this will indicate number of unblock retries left, after which the PIN will be permanently blocked; i.e. UIM is unusable. – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.14.4.52 ULONG UIMGetControlKeyStatus (ULONG *id,* ULONG * *pStatus,* ULONG * *pVerifyRetriesLeft,* ULONG * *pUnblockRetriesLeft*)

Returns the status of the specified UIM facility control key. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Pleaes use SLQSUIMGetConfiguration instead for new firmware versions and new modules.

Parameters

id[IN]	• Facility ID – 0 - Network Personalization (PN) – 1 - Network Subset Personalization (PU) – 2 - Service Provider Personalization (PP) – 3 - Corporate Personalization (PC) – 4 - UIM Personalization (PF)
pStatus[OUT]	• Control key status – 0 - Deactivated – 1 - Activated – 2 - Blocked
pVerifyRetries-Left[OUT]	• The number of retries left, after which the control key will be blocked – 0xFFFFFFFF - Unknown
pUnblock-RetriesLeft[OUT]	• The number of unblock retries left, after which the control key will be permanently blocked – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.14.4.53 ULONG UIMGetICCID (BYTE *stringSize*, CHAR * *pString*)

Returns the UIM ICCID. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use SLQSUIMReadTransparent()(EF ID: 3F00 2FE2) instead for new firmware versions and new modules.

Parameters

stringSize	• The maximum number of characters (including NULL terminator) that the string array can contain.
pString[OUT]	• NULL terminated string

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.14.4.54 ULONG UIMGetPINStatus (ULONG *id*, ULONG * *pStatus*, ULONG * *pVerifyRetriesLeft*, ULONG * *pUnblockRetriesLeft*)

Gets the status of the SIM PINs. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use API SLQSUIMGetCardStatus() for new firmware versions and new modules

Parameters

id	• PIN ID – 1 (PIN1 / CHV1) – 2 (PIN2 / CHV2)

pStatus[OUT]	• PIN status(0xFFFFFFFF - Unknown) – 0 - PIN not initialized – 1 - PIN enabled, not verified – 2 - PIN enabled, verified – 3 - PIN disabled – 4 - PIN blocked – 5 - PIN permanently blocked
pVerifyRetries-Left[OUT]	• Upon operational failure, this will indicate number of retries left, after which PIN will be blocked. – 0xFFFFFFFF - Unknown
pUnblock-RetriesLeft[OUT]	• Upon operational failure, this will indicate number of unblock retries left, after which the PIN will be permanently blocked; i.e., UIM is unusable. – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.14.4.55 ULONG UIMSetControlKeyProtection (ULONG *id*, ULONG *status*, CHAR * *pValue*, ULONG * *pVerifyRetriesLeft*)

Changes the specified UIM facility control key. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use API SLQSUIMDepersonalization() for new firmware versions and new modules

Parameters

id[IN]	• Facility ID – 0 - Network Personalization (PN) – 1 - Network Subset Personalization (PU) – 2 - Service Provider Personalization (PP) – 3 - Corporate Personalization (PC) – 4 - UIM Personalization (PF)
status[IN]	• Control key status – 0 - Deactivated – 1 - Activated – 2 - Blocked

pValue[IN]	• Control key de-personalization string (maximum length of 8 characters)
pVerifyRetries-Left[OUT]	• Optional parameter • Upon operational failure, this will indicate number of retries left, after which the control key will be blocked – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.14.4.56 ULONG UIMSetPINProtection (ULONG *id*, ULONG *bEnable*, CHAR * *pValue*, ULONG * *pVerifyRetriesLeft*, ULONG * *pUnblockRetriesLeft*)

Enables or disables protection of SIM contents for a given PIN, This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use API SLQSUIMSetPinProtection() for new firmware versions and new modules

Parameters

id[IN]	• PIN ID – 1 (PIN1 / CHV1) – 2 (PIN2 / CHV2)
bEnable[IN]	• Enable/disable PIN protection, 0 = Disable
pValue[IN]	• PIN value of the PIN to be enabled/disabled
pVerifyRetries-Left[OUT]	• Optional parameter • Upon operational failure, this will indicate number of retries left, after which PIN will be blocked. – 0xFFFFFFFF - Unknown
pUnblock-RetriesLeft[OUT]	• Optional parameter • Upon operational failure, this will indicate number of unblock retries left, after which the PIN will be permanently blocked i.e. UIM is unusable. – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.14.4.57 ULONG UIMUnblockControlKey (ULONG *id*, CHAR * *pValue*, ULONG * *pUnblockRetriesLeft*)

Unblocks the specified UIM facility control key. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use API SLQSUIMDepersonalization() for new firmware versions and new modules

Parameters

id[IN]	• Facility ID – 0 - Network Personalization (PN) – 1 - Network Subset Personalization (PU) – 2 - Service Provider Personalization (PP) – 3 - Corporate Personalization (PC) – 4 - UIM Personalization (PF)
pValue[IN]	• Control key de-personalization string (maximum length of 8 characters)
pUnblock-RetriesLeft[OUT]	• Optional parameter • Upon operational failure, this will indicate number of unblock retries left, after which the control key will be blocked – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.14.4.58 ULONG UIMUnblockPIN (ULONG *id*, CHAR * *pPUKValue*, CHAR * *pNewValue*, ULONG * *pVerifyRetriesLeft*, ULONG * *pUnblockRetriesLeft*)

Unblocks a blocked SIM. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use API SLQSUIMUnblockPin() for new firmware versions and new modules

Parameters

id[IN]	• PIN ID – 1 (PIN1 / CHV1) – 2 (PIN2 / CHV2)
pPUKValue[IN]	• PUK value of PIN to unblock
pNewValue[IN]	• New PIN value of PIN to unblock
pVerifyRetries-Left[OUT]	• Optional Parameter • Upon operational failure, this will indicate number of retries left, after which the PIN will be blocked. – 0xFFFFFFFF - Unknown
pUnblock-RetriesLeft[OUT]	• Optional Parameter • Upon operational failure, this will indicate number of unblock retries left, after which the PIN will be permanently blocked; i.e. UIM is unusable – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.14.4.59 ULONG UIMVerifyPIN (ULONG *id*, CHAR * *pValue*, ULONG * *pVerifyRetriesLeft*, ULONG * *pUnblockRetriesLeft*)

Verifies a SIM PIN. This API is deprecated on MC73xx/EM73xx/WP76xx modules since firmware version SWI9-X15C_05_xx_xx_xx, all EM74xx and WP76xx firmware versions. Please use API SLQSUIMVerifyPin()() for new firmware versions and new modules

Parameters

id[IN]	• PIN ID – 1 (PIN1 / CHV1) – 2 (PIN2 / CHV2)
pValue[IN]	• Value of PIN to verify

pVerifyRetries-Left[OUT]	• Optional Parameter • Upon operational failure, this will indicate number of retries left, after which the PIN will be blocked. – 0xFFFFFFFF - Unknown
pUnblock-RetriesLeft[OUT]	• Optional Parameter • Upon operational failure, this will indicate number of unblock retries left, after which the PIN will be permanently blocked; i.e. UIM is unusable – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.14.4.60 ULONG ValidateSPC (CHAR * *pSPC*)

This function Validates Service Programming code of the device

Parameters

pSPC[IN]	• NULL-terminated string representing a six-digit service programming code

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Device Supported: MC83x5, MC7750
Timeout: 2 seconds

9.15 qaGobiApiFms.h File Reference

Firmware Management Service API function prototypes.

Data Structures

- struct fwinfo_s
- struct slqsfwinfo_s
- struct slqsfwpartno_s
- struct qmifwinfo_s
- struct ImageElement
- struct PrefImageList
- struct ImageIdElement
- struct ImageIDEntries
- struct ImageList
- struct sGetDeviceSeriesResult
- struct SWI_STRUCT_CarrierImage
- struct CurrImageInfo
- struct CurrentImgList

Macros

- #define SLQSFWINFO_MODELID_SZ 20
- #define SLQSFWINFO_BOOTVERSION_SZ 85
- #define SLQSFWINFO_APPVERSION_SZ 85
- #define SLQSFWINFO_SKU_SZ 15
- #define SLQSFWINFO_PACKAGEID_SZ 85
- #define SLQSFWINFO_CARRIER_SZ 20
- #define SLQSFWINFO_PRIVERSION_SZ 16
- #define SLQSFWINFO_CUR_CARR_NAME 17
- #define SLQSFWINFO_CUR_CARR_REV 13
- #define SLQSFWINFO_PART_NO_SZ 15
- #define GOBI_MBN_IMG_ID_SIZE 16
- #define TOTAL_IMAGE_ID_STRING_SIZE 100
- #define GOBI_MBN_IMG_ID_STR_LEN TOTAL_IMAGE_ID_STRING_SIZE
- #define GOBI_MBN_BUILD_ID_STR_LEN TOTAL_IMAGE_ID_STRING_SIZE
- #define GOBI_LISTENTRIES_MAX 2
- #define GOBI_SET_IMG_PREF_RSPLEN 40
- #define DEVICE_SHUTDOWN 5
- #define DEVICE_RESET 4
- #define DEVICE_OFFLINE 3
- #define FIRMWARE_UPDATE_SUCCESS 0x01
- #define FIRMWARE_UPDATE_FAIL 0x01
- #define PRI_UPDATE_FAIL 0x02
- #define FIRMWARE_UPGRADE_SUCCESS 0x00
- #define IMG_ID_LEN TOTAL_IMAGE_ID_STRING_SIZE
- #define BUILD_ID_LEN TOTAL_IMAGE_ID_STRING_SIZE
- #define G3K_FIRMWARE_DOWNLOAD 1
- #define SPKG_FIRMWARE_DOWNLOAD 2
- #define UNIQUE_ID_LEN 16
- #define BUILD_ID_MAX_LEN 255
- #define IMGDETAILS_LEN 16
- #define MAX_IMAGE_IDE_ELEMENTS 50

Enumerations

- enum eGobiImageTech {
  eGOBI_IMG_TECH_CDMA = 0,
  eGOBI_IMG_TECH_UMTS }

- enum eGobiImageCarrier {
  eGOBI_IMG_CAR_GENERIC = 1,
  eGOBI_IMG_CAR_FACTORY,
  eGOBI_IMG_CAR_NORF,
  eGOBI_IMG_CAR_VERIZON = 101,
  eGOBI_IMG_CAR_SPRINT,
  eGOBI_IMG_CAR_ALLTEL,
  eGOBI_IMG_CAR_BELL,
  eGOBI_IMG_CAR_TELUS,
  eGOBI_IMG_CAR_US,
  eGOBI_IMG_CAR_TELSTRA1,
  eGOBI_IMG_CAR_CHINA_UNICOM,
  eGOBI_IMG_CAR_TELCOM_NZ,
  eGOBI_IMG_CAR_SK_TELCOM1,
  eGOBI_IMG_CAR_RELIANCE1,
  eGOBI_IMG_CAR_TATA,
  eGOBI_IMG_CAR_METROPCS,
  eGOBI_IMG_CAR_LEAP,
  eGOBI_IMG_CAR_KDDI,
  eGOBI_IMG_CAR_IUSACELL,
  eGOBI_IMG_CAR_CHINA_TELECOM,
  eGOBI_IMG_CAR_OMH,
  eGOBI_IMG_CAR_GENERIC_CDMA,
  eGOBI_IMG_CAR_ATT = 201,
  eGOBI_IMG_CAR_VODAFONE,
  eGOBI_IMG_CAR_TMOBILE,
  eGOBI_IMG_CAR_ORANGE,
  eGOBI_IMG_CAR_TELEFONICA,
  eGOBI_IMG_CAR_TELCOM_ITALIA,
  eGOBI_IMG_CAR_3,
  eGOBI_IMG_CAR_O2,
  eGOBI_IMG_CAR_SFR,
  eGOBI_IMG_CAR_SWISSCOM,
  eGOBI_IMG_CAR_CHINA_MOBILE,
  eGOBI_IMG_CAR_TELSTRA2,
  eGOBI_IMG_CAR_SINGTEL_OPTUS,
  eGOBI_IMG_CAR_RELIANCE2,
  eGOBI_IMG_CAR_BHARTI,
  eGOBI_IMG_CAR_NTT_DOCOMO,
  eGOBI_IMG_CAR_EMOBILE,
  eGOBI_IMG_CAR_SOFTBANK,
  eGOBI_IMG_CAR_KT_FREETEL,
  eGOBI_IMG_CAR_SK_TELCOM2,
  eGOBI_IMG_CAR_TELENOR,
  eGOBI_IMG_CAR_NETCOM,
  eGOBI_IMG_CAR_TELIASONERA,
  eGOBI_IMG_CAR_AMX_TELCEL,
  eGOBI_IMG_CAR_BRASIL_VIVO,
  eGOBI_IMG_CAR_AERIS,
  eGOBI_IMG_CAR_ROGERS }

- enum eGobiImageRegion {

eGOBI_IMG_REG_NA = 0,
eGOBI_IMG_REG_LA,
eGOBI_IMG_REG_EU,
eGOBI_IMG_REG_ASIA,
eGOBI_IMG_REG_AUS,
eGOBI_IMG_REG_GLOBAL }

- enum eGobiImageGPS {
  eGOBI_IMG_GPS_NONE = 0,
  eGOBI_IMG_GPS_STAND_ALONE,
  eGOBI_IMG_GPS_ASSISTED,
  eGOBI_IMG_GPS_NO_XTRA }
- enum eGobiDeviceSeries {
  eGOBI_DEV_SERIES_UNKNOWN = -1,
  eGOBI_DEV_SERIES_NON_GOBI = 0,
  eGOBI_DEV_SERIES_G3K,
  eGOBI_DEV_SERIES_SIERRA_GOBI,
  eGOBI_DEV_SERIES_9X15,
  eGOBI_DEV_SERIES_9X30,
  eGOBI_DEV_SERIES_9X07_9X50,
  eGobi_DEV_SERIES_MC83 }

Functions

- ULONG GetImageStore (WORD imageStorePathSize, CHAR *pImageStorePath)
- ULONG SLQSGetFirmwareInfo (struct qmifwinfo_s *pinfo)
- ULONG SLQSGetImageInfoMC77xx (LPCSTR path, struct qmifwinfo_s *pinfo)
- ULONG SLQSGetImageInfoMC83xx (LPCSTR path, struct qmifwinfo_s *pinfo)
- ULONG SLQSGetImageInfo (LPCSTR path, struct qmifwinfo_s *pinfo)
- ULONG SLQSGetImagePartNumber (LPCSTR path, BYTE imgType, struct slqsfwpartno_s *pinfo)
- ULONG UpgradeFirmware2k (CHAR *pDestinationPath)
- ULONG GetImagesPreference (ULONG *pImageListSize, struct PrefImageList *pImageList)
- ULONG SetImagesPreference (ULONG imageListSize, BYTE *pImageList, ULONG bForceDownload, BYTE modemIndex, ULONG *pImageTypesSize, BYTE *pImageTypes)
- ULONG GetStoredImages (ULONG *pImageListSize, BYTE *pImageList)
- ULONG DeleteStoredImage (ULONG imageInfoSize, BYTE *pImageInfo)
- ULONG SLQSGetImageInfo_9x15 (LPCSTR path, BYTE imgType, struct slqsfwinfo_s *pinfo)
- ULONG SLQSUpgradeFirmware9x07 (CHAR *pDestinationPath)
- ULONG SLQSUpgradeFirmware9x15 (CHAR *pDestinationPath)
- ULONG SLQSGetBootVersionNumber (ULONG *bootversion)
- BOOL SLQSIsSpkgFormatRequired (void)
- void SLQSSetSpkgFormatRequired (BYTE isneeded)
- ULONG upgrade_mc77xx_fw (LPCSTR path)
- void eGetDeviceSeries (struct sGetDeviceSeriesResult *)
- ULONG SLQSSwiGetAllCarrierImages (ULONG *pNumOfItems, struct SWI_STRUCT_CarrierImage *pCarrierImages, char *pFolderPath)
- ULONG DownloadToSlot (CHAR *path, struct slqsfwinfo_s fwImgInfo, struct slqsfwinfo_s priImgInfo, BYTE slot, BYTE forceDownload)
- ULONG SLQSDownloadFirmwareToSlot (CHAR *pPath, BYTE slot_index, BYTE force_download)
- ULONG SLQSGetValidFwPriCombinations (struct ImageList *pStoredImageList, ULONG *pValidCombinationSize, struct SWI_STRUCT_CarrierImage *pValidCombinations)
- ULONG SLQSSetSIMBasedImageSwitching (void)
- void SLQSSetCrashStateCheckIgnore (BOOL ignore)
- ULONG SLQSSwiGetFirmwareCurr (CurrentImgList *pCurrentImgList)
- ULONG upgrade_9x07_9x50_fw (LPCSTR path)
- ULONG SetImagePath (CHAR *path, ULONG isMDM9x15, WORD imgMask, BYTE mdmProtocol)
- int SLQSIsBootloaderDebugEnabled (const char *szPath, const char *pQsn)

9.15.1 Detailed Description

Firmware Management Service API function prototypes.

9.15.2 Macro Definition Documentation

9.15.2.1 #define BUILD_ID_LEN TOTAL_IMAGE_ID_STRING_SIZE

9.15.2.2 #define BUILD_ID_MAX_LEN 255

9.15.2.3 #define DEVICE_OFFLINE 3

9.15.2.4 #define DEVICE_RESET 4

9.15.2.5 #define DEVICE_SHUTDOWN 5

9.15.2.6 #define FIRMWARE_UPDATE_FAIL 0x01

9.15.2.7 #define FIRMWARE_UPDATE_SUCCESS 0x01

9.15.2.8 #define FIRMWARE_UPGRADE_SUCCESS 0x00

9.15.2.9 #define G3K_FIRMWARE_DOWNLOAD 1

9.15.2.10 #define GOBI_LISTENTRIES_MAX 2

9.15.2.11 #define GOBI_MBN_BUILD_ID_STR_LEN TOTAL_IMAGE_ID_STRING_SIZE

9.15.2.12 #define GOBI_MBN_IMG_ID_SIZE 16

9.15.2.13 #define GOBI_MBN_IMG_ID_STR_LEN TOTAL_IMAGE_ID_STRING_SIZE

9.15.2.14 #define GOBI_SET_IMG_PREF_RSPLEN 40

9.15.2.15 #define IMG_ID_LEN TOTAL_IMAGE_ID_STRING_SIZE

9.15.2.16 #define IMGDETAILS_LEN 16

9.15.2.17 #define MAX_IMAGE_IDE_ELEMENTS 50

9.15.2.18 #define PRI_UPDATE_FAIL 0x02

9.15.2.19 #define SLQSFWINFO_APPVERSION_SZ 85

9.15.2.20 #define SLQSFWINFO_BOOTVERSION_SZ 85

9.15.2.21 #define SLQSFWINFO_CARRIER_SZ 20

9.15.2.22 #define SLQSFWINFO_CUR_CARR_NAME 17

9.15.2.23 #define SLQSFWINFO_CUR_CARR_REV 13

9.15.2.24 #define SLQSFWINFO_MODELID_SZ 20

9.15.2.25 #define SLQSFWINFO_PACKAGEID_SZ 85

9.15.2.26 #define SLQSFWINFO_PART_NO_SZ 15

9.15.2.27 #define SLQSFWINFO_PRIVERSION_SZ 16

9.15.2.28 #define SLQSFWINFO_SKU_SZ 15

9.15.2.29 #define SPKG_FIRMWARE_DOWNLOAD 2

9.15.2.30 #define TOTAL_IMAGE_ID_STRING_SIZE 100

9.15.2.31 #define UNIQUE_ID_LEN 16

9.15.3 Enumeration Type Documentation

9.15.3.1 enum eGobiDeviceSeries

enumeration which lists the Device Series

Enumerator

eGOBI_DEV_SERIES_UNKNOWN
eGOBI_DEV_SERIES_NON_GOBI
eGOBI_DEV_SERIES_G3K
eGOBI_DEV_SERIES_SIERRA_GOBI
eGOBI_DEV_SERIES_9X15
eGOBI_DEV_SERIES_9X30
eGOBI_DEV_SERIES_9X07_9X50
eGobi_DEV_SERIES_MC83

9.15.3.2 enum eGobiImageCarrier

enumeration which lists the carrier supported by the image

Enumerator

eGOBI_IMG_CAR_GENERIC
eGOBI_IMG_CAR_FACTORY
eGOBI_IMG_CAR_NORF
eGOBI_IMG_CAR_VERIZON
eGOBI_IMG_CAR_SPRINT
eGOBI_IMG_CAR_ALLTEL
eGOBI_IMG_CAR_BELL
eGOBI_IMG_CAR_TELUS
eGOBI_IMG_CAR_US
eGOBI_IMG_CAR_TELSTRA1
eGOBI_IMG_CAR_CHINA_UNICOM
eGOBI_IMG_CAR_TELCOM_NZ
eGOBI_IMG_CAR_SK_TELCOM1
eGOBI_IMG_CAR_RELIANCE1
eGOBI_IMG_CAR_TATA
eGOBI_IMG_CAR_METROPCS

eGOBI_IMG_CAR_LEAP

eGOBI_IMG_CAR_KDDI

eGOBI_IMG_CAR_IUSACELL

eGOBI_IMG_CAR_CHINA_TELECOM

eGOBI_IMG_CAR_OMH

eGOBI_IMG_CAR_GENERIC_CDMA

eGOBI_IMG_CAR_ATT

eGOBI_IMG_CAR_VODAFONE

eGOBI_IMG_CAR_TMOBILE

eGOBI_IMG_CAR_ORANGE

eGOBI_IMG_CAR_TELEFONICA

eGOBI_IMG_CAR_TELCOM_ITALIA

eGOBI_IMG_CAR_3

eGOBI_IMG_CAR_O2

eGOBI_IMG_CAR_SFR

eGOBI_IMG_CAR_SWISSCOM

eGOBI_IMG_CAR_CHINA_MOBILE

eGOBI_IMG_CAR_TELSTRA2

eGOBI_IMG_CAR_SINGTEL_OPTUS

eGOBI_IMG_CAR_RELIANCE2

eGOBI_IMG_CAR_BHARTI

eGOBI_IMG_CAR_NTT_DOCOMO

eGOBI_IMG_CAR_EMOBILE

eGOBI_IMG_CAR_SOFTBANK

eGOBI_IMG_CAR_KT_FREETEL

eGOBI_IMG_CAR_SK_TELCOM2

eGOBI_IMG_CAR_TELENOR

eGOBI_IMG_CAR_NETCOM

eGOBI_IMG_CAR_TELIASONERA

eGOBI_IMG_CAR_AMX_TELCEL

eGOBI_IMG_CAR_BRASIL_VIVO

eGOBI_IMG_CAR_AERIS

eGOBI_IMG_CAR_ROGERS

9.15.3.3 enum eGobiImageGPS

enumeration which lists the GPS type supported by the image

Enumerator

eGOBI_IMG_GPS_NONE

eGOBI_IMG_GPS_STAND_ALONE

eGOBI_IMG_GPS_ASSISTED

eGOBI_IMG_GPS_NO_XTRA

9.15.3.4 enum eGobiImageRegion

enumeration which lists the region supported by the image

Enumerator

eGOBI_IMG_REG_NA

eGOBI_IMG_REG_LA

eGOBI_IMG_REG_EU

eGOBI_IMG_REG_ASIA

eGOBI_IMG_REG_AUS

eGOBI_IMG_REG_GLOBAL

9.15.3.5 enum eGobiImageTech

enumeration which lists the technology supported by the image

Enumerator

eGOBI_IMG_TECH_CDMA

eGOBI_IMG_TECH_UMTS

9.15.4 Function Documentation

9.15.4.1 ULONG DeleteStoredImage (ULONG *imageInfoSize*, BYTE * *pImageInfo*)

Used to delete the specified image from the device. This API function is only relevant to devices with the ability to store multiple firmware images(see Device Supported section below).

Parameters

imageInfoSize[IN]	• The size in BYTEs of the image info array
pImageInfo[IN]	• The image info list array containing information about the image to be deleted. • See ImageElement

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: MC83x5/SL9090
Timeout: 2 Secs

9.15.4.2 ULONG DownloadToSlot (CHAR * *path*, struct slqsfwinfo_s *fwImgInfo*, struct slqsfwinfo_s *priImgInfo*, BYTE *slot*, BYTE *forceDownload*)

This API is dedicated for downloading a firmware image into a specific slot. it is used for EM74xx/MC74xx only

Parameters

path	• fully qualified path to firmware image to download
fwImgInfo	• See struct slqsfwinfo_s
priImgInfo	• See struct slqsfwinfo_s
slot	• slot id in the modem to store the firmware
forceDownload	• a flag to force download take place.

Returns

See qmerrno.h for eQCWWAN_xxx error values

Note

only EM74xx/MC74xx is supported

9.15.4.3 void eGetDeviceSeries (struct sGetDeviceSeriesResult *)

Name : eGetDeviceSeries

Parameters

none	

Returns

sGetDeviceSeriesResult

Note

Get Devie Series

9.15.4.4 ULONG GetImagesPreference (ULONG * *pImageListSize*, struct PrefImageList * *pImageList*)

restore original alignment from stack Gets the current images preference from the device.

Parameters

pImageListSize[-IN/OUT]	• Upon input, the size of structure ImageList ImageList • Upon successful output, the number of BYTEs copied to the image list array
pImageList[OUT]	• The caller must supply a pointer to a ImageList structure typecast as a BYTE pointer

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.15.4.5 ULONG GetImageStore (WORD *imageStorePathSize,* CHAR * *pImageStorePath*)

Returns the image store folder, i.e., the folder containing one or more carrier-specific image subfolders compatible with the currently connected QC WWAN device.

Parameters

imageStorePath-Size	• Maximum number of characters (including NULL terminator) that can be copied to the image store path array.
pImageStore-Path[OUT]	• The path to the image store

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.15.4.6 ULONG GetStoredImages (ULONG * *pImageListSize,* BYTE * *pImageList*)

restore original alignment from stack Gets the list of images stored on the device.

Parameters

pImageListSize[-IN/OUT]	• Upon input, the size of structure ImageList ImageList • Upon successful output, the number of BYTEs copied to the image list array

pImageList[OUT]	• The caller must supply a pointer to a ImageList structure typecast as a BYTE pointer

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: MC83x5/SL9090
Timeout: 2 seconds

9.15.4.7 ULONG SetImagePath (CHAR * *path,* ULONG *isMDM9x15,* WORD *imgMask,* BYTE *mdmProtocol*)

This API is used to set image path for firmware download

Parameters

path[IN]	• fully qualified path to firmware image to download.
isMDM9x15[IN]	• a flag indicates whether it is a MDM9x15 device
imgMask[IN]	• image mask to check CWE and NVU files are required or not
mdmProtocol[IN]	• which firmware download protocol should be used – 0 - SSDP protocol – 1 - Firehose protocol

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 12 seconds

9.15.4.8 ULONG SetImagesPreference (ULONG *imageListSize,* BYTE * *pImageList,* ULONG *bForceDownload,* BYTE *modemIndex,* ULONG * *pImageTypesSize,* BYTE * *pImageTypes*)

Sets the current images preference on the device. After this function successfully completes, the device must be reset for the selected image preference to be realized. Additionally, when the returned list of image types that require downloading is not empty, the device opens in QDL mode after the reset. At that point, the QDL portion of this API must be used to download the selected image preference to the device.

Parameters

imageListSize	• The size in BYTEs of the image list array
pImageList[IN]	• The image info list array containing Image Elements – See PrefImageList
bForce-Download[IN]	• Force device to download images from host? 0 - No Nonzero - Yes
modemIndex	• Desired storage index for downloaded modem image (optional, a value of 0xFF indicates unspecified)
pImageTypes-Size[IN/OUT]	• Upon input, maximum number of elements that download image types array can contain • Upon successful output, number of elements in download image types array
pImageTypes[O-UT]	-The download image types array.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.15.4.9 ULONG SLQSDownloadFirmwareToSlot (CHAR * *pPath,* BYTE *slot_index,* BYTE *force_download*)

This API is used to download firmware to a specific slot id of the modem. It is only applicable for EM74xx variant. This API encapsulates all steps involved in the firmware download process.Hence it is a blocking API call.

This API will not return until the entire process has been completed. This API will takes significant amount of time (in order of minutes, normally should be less than 10 minutes).

This API Performs the following steps:

1. Verifies arguments.
2. Retrieve and store the details of the firmware and the PRI file

3. Enable device state change callback.
4. Enable firmware download callback.
5. Set Image preference on the device and reset the device.
6. Wait for the firmware to download and device to become ready.
7. Check the firmware update status. If fail, return an error.
8. If update status is OK, check if current image preference and preferred image preference(from step 2) match
9. If match, firmware download is successful. otherwise, report FW_PREFERENCE_MISMATCH

   10.Disable callbacks and exit.

   The call to this API blocks until step 7 or 10. This could be a significant amount of time (in order of minutes). Also note that the device state change callback and firmware download callback are used internally

   within this API. Hence the user application's instance of these callbacks (if any) are cleared. The user must re-enable these callbacks after a call to this API in order to use them.

Parameters

pPath[IN]	• fully qualified path to firmware image to download.
slot_index[IN]	• slot id in the modem to store the firmware
force_download[IN]	• a flag to force download take place.

Returns

- eQCWWAN_ERR_NONE - Firmware download/Switch success.
- eQCWWAN_ERR_INVALID_ARG - The path input does not contain any image
- eQCWWAN_ERR_SWIIM_FW_UPDATE_FAIL - Firmware download/switch failed
- eQCWWAN_ERR_SWIIM_FW_PREFERENCE_MISMATCH - Download success but device offline due to image preference mismatch (ref. syslogs for cause)

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: NA

9.15.4.10 ULONG SLQSGetBootVersionNumber (ULONG * *bootversion*)

Gets the boot loader version number

Parameters

bootversion[OUT]	• boot loader version presented by a 4 byte integer

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: MC9090/SL9090
Timeout: 2 seconds

9.15.4.11 ULONG SLQSGetFirmwareInfo (struct qmifwinfo_s * *pinfo*)

Returns firmware image information from the connected device

Parameters

pinfo[OUT]	• firmware image information record

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values
struct qmifwinfo_s

Note

Timeout: 2 Seconds.

9.15.4.12 ULONG SLQSGetImageInfo (LPCSTR *path,* struct qmifwinfo_s * *pinfo*)

Returns firmware image information from a CWE file or mbn files stored on the host. For CWE, information is returned for the first CWE image found at the specified path. For MBN, the provided path must be located under the image store for the currently connected QC WWAN device. Note that as this API supports multiple firmware image types, it relies on the presence of a supported device. Otherwise, refer to SLQSGetImageInfoMC83xx and SLQSGetImageInfoMC77xx for APIs which do not rely on the presence of a supported device.

Parameters

path[IN]	• fully qualified path to folder containing CWE image or MBN images • should use a "/" at the end of the path.
pinfo[OUT]	• firmware image information record

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values
struct qmifwinfo_s

Note

Timeout: N/A

9.15.4.13 ULONG SLQSGetImageInfo_9x15 (LPCSTR *path*, BYTE *imgType*, struct slqsfwinfo_s * *pinfo*)

Returns firmware image information from a CWE file(s) stored on the host. It does not rely on the presence of a supported device.

Parameters

path[IN]	• fully qualified path to folder containing the image(s) • should use a "/" at the end of the path.
imgType[IN]	• 2 - Firmware Image(.cwe extension) • 3 - PRI Image (.nvu extension)
pinfo[OUT]	• firmware image information record

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values
struct qmifwinfo_s

Note

Device Supported: MC73xx
Timeout: N/A

9.15.4.14 ULONG SLQSGetImageInfoMC77xx (LPCSTR *path*, struct qmifwinfo_s * *pinfo*)

Returns firmware image information from a SPKGS CWE file stored on the host. The information is returned for the first SPKGS CWE image found at the specified path. This API executes independent of a MC77xx being connected to the target.

Parameters

path[IN]	• fully qualified path to folder containing SPKG CWE image • should use a "/" at the end of the path.
pinfo[OUT]	• firmware image information record

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values
struct qmifwinfo_s

Note

Device Supported: MC77xx
Timeout: N/A

9.15.4.15 ULONG SLQSGetImageInfoMC83xx (LPCSTR *path*, struct qmifwinfo_s * *pinfo*)

Returns firmware image information from an MBN file located on the host. This API executes independent of a MC83xx being connected to the target.

Parameters

path[IN]	• fully qualified path to folder containing MBN file • should use a "/" at the end of the path.
pinfo[OUT]	• firmware image information record

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values
struct qmifwinfo_s

Note

Device Supported: MC83xx/SL9090
Timeout: N/A

9.15.4.16 ULONG SLQSGetImagePartNumber (LPCSTR *path*, BYTE *imgType*, struct slqsfwpartno_s * *pinfo*)

Returns firmware image part number by a well defined cwe spkg format firmware file

Parameters

path[IN]	• fully qualified path to folder containing CWE image or MBN images • should use a "/" at the end of the path.
pinfo[OUT]	• firmware image part number

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values
struct slqsfwpartno_s

Note

Timeout: N/A

9.15.4.17 ULONG SLQSGetValidFwPriCombinations (struct ImageList * *pStoredImageList*, ULONG * *pValidCombinationSize*, struct SWI_STRUCT_CarrierImage * *pValidCombinations*)

This API distills valid Firmware/PRI combinations from GetStoredImages result

Parameters

in	*pStoredImage-List*	• image list returned from GetStoredImages
in,out	*pValid-CombinationSize*	• number of combination passed in and returned
out	*pValid-Combinations*	• valid combinations returned

Returns

- eQCWWAN_ERR_INVALID_ARG - Invalid parameters
- eQCWWAN_ERR_BUFFER_SZ - No enough element to store combinatons returned

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.15.4.18 int SLQSIsBootloaderDebugEnabled (const char * *szPath,* const char * *pQsn*)

This API is used to check if the bootloader is debug enabled or not for the specified QSN

Parameters

szPath[IN]	• the full path of the provided bootloader or firmware file
pQsn[IN]	• the QSN of a specific module user wants to check, it is a 4 bytes hex value without the prefix 0X. It can be retrieved by AT command AT!ENTERCND="<password>", AT!SECBOOTCFG?, the first parameter of the response of AT!SECBOOTCFG?.

Returns

values listed below

- -1 bootloader is not debug enabled
- 0 unbale to retrieve the bootloader debug info
- 1 bootloader is debug enabled for the provided QSN
- 4 either szPath or pQsn is invalid (NULL)
- 18 invalid file

9.15.4.19 BOOL SLQSIsSpkgFormatRequired (void)

Check if SPKG format download is required for SL9090/MC9090, it returns the value whcih was set by API SLQSSetSpkgFormatRequired()

Parameters

none	

Returns

return TRUE if required, otherwise, return FALSE

Note

Device Supported: MC9090/SL9090

9.15.4.20 void SLQSSetCrashStateCheckIgnore (BOOL *ignore*)

This API is used to set whether ignore crash state checking before proceed firmware download using the API UpgradeFirmware2k().

Parameters

in	*ignore*	• 0 - crash state checking applied (default value) • 1 - ignore crash state checking

Note

Device Supported: EM73xx/MC73xx, EM74xx/MC74xx

9.15.4.21 ULONG SLQSSetSIMBasedImageSwitching (void)

This API is used to enable the SIM-based Image Switching. The modem will reboot automatically to take effect of the enabing

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: EM74xx/MC74xx

9.15.4.22 void SLQSSetSpkgFormatRequired (BYTE *isneeded*)

Set if SPKG format download is required for SL9090/MC9090

Parameters

isneeded	[INPUT] user inputs the firmware download method preference • 1 - Gobi3K download method, use mbn files. This is default value • 2 - SPKG download method, use cwe file

Returns

None

Note

Device Supported: MC9090/SL9090

9.15.4.23 ULONG SLQSSwiGetAllCarrierImages (ULONG * *pNumOfItems*, struct SWI_STRUCT_CarrierImage * *pCarrierImages*, char * *pFolderPath*)

This API gets a list of all images stored on both the host and the device

Parameters

pNumOfItems	• Number of Images{IN/OUT]
pCarrierImages[-OUT]	• See SWI_STRUCT_CarrierImage
pFolderPath	• Path of Input folder [IN]

Returns

TRUE/FALSE

Note

In case pFolderPath is invalid, API does not return invalid path error as SLQSSwiGetAllCarrierImages get carrier images from device also.

9.15.4.24 ULONG SLQSSwiGetFirmwareCurr (CurrentImgList * *pCurrentImgList*)

This API gets the currently active images on the device.

Parameters

pCurrentImgList	• Pointer to structure CurrentImgList • See CurrentImgList for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx/EM74xx
Timeout: 5 Secs

9.15.4.25 ULONG SLQSUpgradeFirmware9x07 (CHAR * *pDestinationPath*)

This API is used to download firmware to a WP760x device.

This API Performs the following steps:

1. Verifies arguments.
2. Informs the SDK of the firmware upgrade path
3. Send the DM command to requests the device reset (device will reset after all open handles are released).

   Upon successful completion, the above steps will have been completed, however, the actual upgrade of the firmware will necessarily then follow.

Parameters

pDestination-Path[IN]	• fully qualified path to firmware image to download.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.15.4.26 ULONG SLQSUpgradeFirmware9x15 (CHAR * *pDestinationPath*)

This API is used to upgrade firmware on a MC73xx device. This API encapsulates all steps involved in the firmware download process. It is an alternative to any firmware download application. Hence it is a blocking API call. This API will not return until the entire process has been completed.

This API Performs the following steps:

1. Verifies arguments.
2. Retrieve and store the details of the firmware and the PRI file
3. Enable device state change callback.
4. Enable firmware download callback.
5. Set Image preference on the device and reset the device.
6. Wait for the firmware to download and device to become ready.
7. Check the firmware update status. If fail, return an error.
8. If update status is OK, check if current image preference and preferred image preference(from step 2) match
9. If match, firmware download is successful.
10. If do not match, repeat from step 5 once more.
11. Disable callbacks and exit.

    The call to this API blocks until step 7 or 11. This could be a significant amount of time (in order of minutes). Also note that the device state change callback and firmware download callback are used internally

    within this API. Hence the user application's instance of these callbacks (if any) are cleared. The user must re-enable these callbacks after a call to this API in order to use them.

Parameters

pDestination-Path[IN]	• fully qualified path to firmware image to download. The path must end with a forward slash.

Returns

- eQCWWAN_ERR_NONE - Firmware download/Switch success.
- eQCWWAN_ERR_INVALID_ARG - The path input does not contain any image
- eQCWWAN_ERR_SWIIM_FW_UPDATE_FAIL - Firmware download/switch failed
- eQCWWAN_ERR_SWIIM_FW_PREFERENCE_MISMATCH - Download success but device offline due to image preference mismatch (ref. syslogs for cause)

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: NA

9.15.4.27 ULONG upgrade_9x07_9x50_fw (LPCSTR *path*)

This API is used to download firmware to a 9x07 or 9x50 device.

Parameters

pDestination-Path[IN]	• fully qualified path to firmware image to download.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 12 seconds

9.15.4.28 ULONG upgrade_mc77xx_fw (LPCSTR *path*)

9.15.4.29 ULONG UpgradeFirmware2k (CHAR * *pDestinationPath*)

This API is used to download firmware to a MC77xx or Gobi 3000 device. For SL909/MC9090, SLQSSetSpkg-FormatRequired() needs to be called in advance to specify the download method, Gobi3K or SPKG download, please refer to the API SLQSSetSpkgFormatRequired() for more details of the input values. If SLQSSetSpkg-FormatRequired() is not called in advance, it will us Gobi3K firmware download method (MBN files) as the default download method.

This API Performs the following steps:

1. Verifies arguments.
2. Verify that device Crash State should be 1 (RESET State).
3. Informs the SDK of the firmware upgrade path
4. Updates the images preference on the currently connected device.
5. Requests the device reset (device will reset after all open handles are released).

   Upon successful completion, the above steps will have been completed, however, the actual upgrade of the firmware will necessarily then follow.

Parameters

pDestination-Path[IN]	• fully qualified path to firmware image to download. The path must end with a forward slash. For a Gobi 3000 device the path should specify the carrier image folder index i.e. "<path\to\carrier\image>/<carrier index>/" where <carrier index>=""> is a valid sub-directory entry. For 9x30 devices if pDestinationPath is not valid on host, it will use pseudo path for image switching.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 12 seconds

9.16 qaGobiApiIms.h File Reference

IMS Service API function prototypes.

Data Structures

- struct SetSIPConfigReq
- struct SetSIPConfigResp
- struct SetRegMgrConfigReq
- struct SetRegMgrConfigResp
- struct SetIMSSMSConfigReq
- struct SetIMSSMSConfigResp
- struct SetIMSUserConfigReq
- struct SetIMSUserConfigResp
- struct SetIMSVoIPConfigReq
- struct SetIMSVoIPConfigResp
- struct GetSIPConfigResp
- struct GetRegMgrConfigParams
- struct GetIMSSMSConfigParams
- struct GetIMSUserConfigParams
- struct GetIMSVoIPConfigResp
- struct imsCfgIndRegisterInfo

Functions

- ULONG SLQSSetSIPConfig (SetSIPConfigReq *pSetSIPConfigReq, SetSIPConfigResp *pSetSIPConfig-Resp)
- ULONG SLQSSetRegMgrConfig (SetRegMgrConfigReq *pSetRegMgrConfigReq, SetRegMgrConfigResp *pSetRegMgrConfigResp)
- ULONG SLQSSetIMSSMSConfig (SetIMSSMSConfigReq *pSetIMSSMSConfigReq, SetIMSSMSConfig-Resp *pSetIMSSMSConfigResp)

- ULONG SLQSSetIMSUserConfig (SetIMSUserConfigReq *pSetIMSUserConfigReq, SetIMSUserConfigResp *pSetIMSUserConfigResp)
- ULONG SLQSSetIMSVoIPConfig (SetIMSVoIPConfigReq *pSetIMSVoIPConfigReq, SetIMSVoIPConfigResp *pSetIMSVoIPConfigResp)
- ULONG SLQSGetSIPConfig (GetSIPConfigResp *pGetSIPConfigResp)
- ULONG SLQSGetRegMgrConfig (GetRegMgrConfigParams *pGetRegMgrConfigParams)
- ULONG SLQSGetIMSSMSConfig (GetIMSSMSConfigParams *pGetIMSSMSConfigParams)
- ULONG SLQSGetIMSUserConfig (GetIMSUserConfigParams *pGetIMSUserConfigParams)
- ULONG SLQSGetIMSVoIPConfig (GetIMSVoIPConfigResp *pGetIMSVoIPConfigResp)
- ULONG SLQSImsConfigIndicationRegister (imsCfgIndRegisterInfo *pImsCfgIndRegisterInfo)

9.16.1 Detailed Description

IMS Service API function prototypes.

9.16.2 Function Documentation

9.16.2.1 ULONG SLQSGetIMSSMSConfig (GetIMSSMSConfigParams * *pGetIMSSMSConfigParams*)

This API retrieves the SMS configuration parameters.

Parameters

pGetIMSSMSConfigParams[IN/OUT]	• See GetIMSSMSConfigParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.16.2.2 ULONG SLQSGetIMSUserConfig (GetIMSUserConfigParams * *pGetIMSUserConfigParams*)

This API retrieves the IMS User configuration parameters.

Parameters

pGetIMSUserConfigParams[IN/OUT]	• See GetIMSUserConfigParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.16.2.3 ULONG SLQSGetIMSVoIPConfig (GetIMSVoIPConfigResp * *pGetIMSVoIPConfigResp*)

This API retrieves the IMS VoIP configuration parameters.

Parameters

GetIMSVoIP-ConfigResp[OUT]	• See GetIMSVoIPConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.16.2.4 ULONG SLQSGetRegMgrConfig (GetRegMgrConfigParams * *pGetRegMgrConfigParams*)

This API retrieves the registration manager configuration parameters.

Parameters

pGetRegMgr-ConfigParams[IN/OUT]	• See GetRegMgrConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.16.2.5 ULONG SLQSGetSIPConfig (GetSIPConfigResp * *pGetSIPConfigResp*)

This API retrieves the Session Initiation Protocol(SIP) configuration parameters.

Parameters

pGetSIPConfig-Resp[OUT]	• See GetSIPConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.16.2.6 ULONG SLQSImsConfigIndicationRegister (imsCfgIndRegisterInfo * *pImsCfgIndRegisterInfo*)

Sets the registration state for different QMI_IMS indications for the requesting control point

Parameters

pImsCfgInd-RegisterInfo[IN]	• Structure containing Indication Register Information. – See imsCfgIndRegisterInfo for more informtaion.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 10 Secs

This API is used by a device to register/deregister for different QMI IMS indications. The device's registration state variables that control registration for indications will be modified to reflect the settings indicated in the request message. At least one optional parameter must be present in the request.

9.16.2.7 ULONG SLQSSetIMSSMSConfig (SetIMSSMSConfigReq * *pSetIMSSMSConfigReq,* SetIMSSMSConfigResp * *pSetIMSSMSConfigResp*)

This API sets the IMS SMS configuration parameters for the requesting control point.

Parameters

pSetIMSSMS-ConfigReq[IN]	• See SetIMSSMSConfigReq for more information
pSetIMSSMS-ConfigResp[OU-T]	• See SetIMSSMSConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.16.2.8 ULONG SLQSSetIMSUserConfig (SetIMSUserConfigReq * *pSetIMSUserConfigReq,* SetIMSUserConfigResp * *pSetIMSUserConfigResp*)

This API sets the IMS user configuration parameters for the requesting control point.

Parameters

pSetIMSUser-ConfigReq[IN]	• See SetIMSUserConfigReq for more information
pSetIMSUser-ConfigResp[OU-T]	• See SetIMSUserConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.16.2.9 ULONG SLQSSetIMSVoIPConfig (SetIMSVoIPConfigReq * *pSetIMSVoIPConfigReq*, SetIMSVoIPConfigResp * *pSetIMSVoIPConfigResp*)

This API sets the IMS Voice over Internet Protocol (VoIP) configuration parameters for the requesting control point.

Parameters

pSetIMSVoIP-ConfigReq[IN]	• See SetIMSVoIPConfigReq for more information
pSetIMSVoIP-ConfigResp[OUT]	• See SetIMSVoIPConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.16.2.10 ULONG SLQSSetRegMgrConfig (SetRegMgrConfigReq * *pSetRegMgrConfigReq*, SetRegMgrConfigResp * *pSetRegMgrConfigResp*)

This API sets the IMS registration manager configuration parameters for the requesting control point.

Parameters

pSetRegMgr-ConfigReq[IN]	• See SetRegMgrConfigReq for more information
pSetRegMgr-ConfigResp[OUT]	• See SetRegMgrConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.16.2.11 ULONG SLQSSetSIPConfig (SetSIPConfigReq * *pSetSIPConfigReq*, SetSIPConfigResp * *pSetSIPConfigResp*)

This API sets the IMS Session Initiation Protocol(SIP) configuration parameters for the requesting control point.

Parameters

pSetSIPConfig-Req[IN]	• See SetSIPConfigReq for more information
pSetSIPConfig-Resp[OUT]	• See SetSIPConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: NA
Device Supported: MC73xx, MC74xx and EM74xx
Timeout: 5 seconds

9.17 qaGobiApiImsa.h File Reference

IMSA Service API function prototypes.

Data Structures

- struct IMSAIndRegisterInfo
- struct SupportedMsgList
- struct IMSASupportedMsgInfo
- struct ReqFieldsList
- struct RespFieldsList

- struct IndFieldsList
- struct IMSASupportedFieldsResp
- struct IMSARegistrationStatus
- struct IMSAServiceStatus

Functions

- ULONG SLQSRegisterIMSAIndication (IMSAIndRegisterInfo *pImsaIndRegisterInfo)
- ULONG SLQSGetIMSASupportedMsg (IMSASupportedMsgInfo *pIMSASupportedMsgInfo)
- ULONG SLQSGetIMSASupportedFields (WORD messageID, IMSASupportedFieldsResp *pIMSASupportedFieldsResp)
- ULONG SLQSGetIMSARegStatus (IMSARegistrationStatus *pIMSARegistrationStatus)
- ULONG SLQSGetIMSAServiceStatus (IMSAServiceStatus *pIMSAServiceStatus)

9.17.1 Detailed Description

IMSA Service API function prototypes.

9.17.2 Function Documentation

9.17.2.1 ULONG SLQSGetIMSARegStatus (IMSARegistrationStatus * *pIMSARegistrationStatus*)

Queries the set of messages implemented by the currently running software.

Parameters

pIMSARegistrationStatus[OUT]	• Structure containing response parameters for registration status. – See IMSARegistrationStatus for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Secs

```
This API is used by a device to get the registration status for
various IMS services for the requesting control point.
```

9.17.2.2 ULONG SLQSGetIMSAServiceStatus (IMSAServiceStatus * *pIMSAServiceStatus*)

Gets the service status for various IMS services for the requesting control point.

Parameters

pIMSAServiceStatus[OUT]	• Structure containing response parameters for service status. – See IMSAServiceStatus for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Secs

```
This API is used by a device to Gets the service status for various
IMS services for the requesting control point.
```

9.17.2.3 ULONG SLQSGetIMSASupportedFields (WORD *messageID,* IMSASupportedFieldsResp * *pIMSASupportedFieldsResp*)

Queries the set of supported fields implemented by the currently running software.

Parameters

messageID[IN]	• Service Message ID.
pIMSA-Supported-FieldsResp[OUT]	• Structure containing Supported Fields Response. – See IMSASupportedFieldsResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Secs

```
This API is used by a device to query the fields supported for a
single command as implemented by the currently running software.
```

9.17.2.4 ULONG SLQSGetIMSASupportedMsg (IMSASupportedMsgInfo * *pIMSASupportedMsgInfo*)

Queries the set of messages implemented by the currently running software.

Parameters

pIMSA-SupportedMsg-Info[OUT]	• Structure containing Supported Messages Information. – See IMSASupportedMsgInfo for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Secs

```
This API is used by a device to query the set of messages implemented by
the currently running software
```

9.17.2.5 ULONG SLQSRegisterIMSAIndication (IMSAIndRegisterInfo * *pImsaIndRegisterInfo*)

Sets the registration state for different QMI_IMSA indications for the requesting control point

Parameters

pImsaInd-RegisterInfo[IN]	• Structure containing Indication Register Information. – See IMSAIndRegisterInfo for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Secs

```
This API is used by a device to register/deregister for different
QMI IMSA indications.
The device's registration state variables that control registration
for indications will be modified to reflect the settings indicated in the
request message.
At least one optional parameter must be present in the request.
```

9.18 qaGobiApiLoc.h File Reference

Location API function prototypes.

Data Structures

- struct LOCEventRegisterReqResp
- struct LOCExtPowerStateReqResp
- struct LocApplicationInfo
- struct LOCStartReq
- struct LOCStopReq

- struct SV
- struct SVInfo
- struct GnssData
- struct CellDb
- struct ClkInfo
- struct BdsSV
- struct BdsSVInfo
- struct LocDelAssDataReq
- struct SwiLocGetAutoStartResp
- struct SwiLocSetAutoStartReq
- struct altitudeSrcInfo
- struct LocInjectPositionReq
- struct LocSetCradleMountReq
- struct sensorData
- struct tempratureData
- struct LocInjectSensorDataReq
- struct LocGetServerReq
- struct IPv4Config
- struct IPv6Config
- struct URLAddrInfo
- struct LocSetServerReq

Macros

- #define MAX_SENSOR_DATA_LEN 64
- #define MAX_TEMP_DATA_LEN 64

Functions

- ULONG SLQSLOCEventRegister (LOCEventRegisterReqResp ∗pLOCEventRegisterReqResp)
- ULONG SLQSLOCSetExtPowerState (LOCExtPowerStateReqResp ∗pLOCExtPowerStateReqResp)
- ULONG SLQSLOCStart (LOCStartReq ∗pLOCStartReq)
- ULONG SLQSLOCStop (LOCStopReq ∗pLOCStopReq)
- ULONG SLQSLOCSetOpMode (ULONG mode)
- ULONG SLQSLOCDelAssData (LocDelAssDataReq request)
- ULONG SwiLocGetAutoStart (SwiLocGetAutoStartResp ∗resp)
- ULONG SwiLocSetAutoStart (SwiLocSetAutoStartReq ∗req)
- ULONG SLQSLOCInjectUTCTime (ULONGLONG timeMsec, ULONG timeUncMsec)
- ULONG SLQSLOCInjectPosition (LocInjectPositionReq ∗pLocInjectPositionReq)
- ULONG SLQSLOCSetCradleMountConfig (LocSetCradleMountReq ∗pLocSetCradleMountReq)
- ULONG SLQSLOCInjectSensorData (LocInjectSensorDataReq ∗pLocInjectSensorDataReq)
- ULONG SLQSLOCGetBestAvailPos (ULONG xid)
- ULONG SLQSLOCGetServer (LocGetServerReq ∗pLocGetServerReq)
- ULONG SLQSLOCSetServer (LocSetServerReq ∗pLocSetServerReq)
- ULONG SLQSLOCGetOpMode ()

9.18.1 Detailed Description

Location API function prototypes.

9.18.2 Macro Definition Documentation

9.18.2.1 #define MAX_SENSOR_DATA_LEN 64

9.18.2.2 #define MAX_TEMP_DATA_LEN 64

9.18.3 Function Documentation

9.18.3.1 ULONG SLQSLOCDelAssData (LocDelAssDataReq *request*)

Used by the control point to delete the location engine assistance data

Parameters

request[IN]	• request structure parameters should contain all NULL pointers to delete all assistance data. Otherwise, specify optional fields to be deleted. See LocDelAssDataReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.2 ULONG SLQSLOCEventRegister (LOCEventRegisterReqResp * *pLOCEventRegisterReqResp*)

Used by the control point to register for events from the location subsystem.

Parameters

pLOCEvent-RegisterReq-Resp[IN]	• See LOCEventRegisterReqResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.3 ULONG SLQSLOCGetBestAvailPos (ULONG *xid*)

Control point to get the best available position estimate from the location engine.

Parameters

xid[IN]	• Identifies the transaction. • The transaction ID is returned in the Get Best Available Position indication.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

- GPS engine should be started to get best available position.

9.18.3.4 ULONG SLQSLOCGetOpMode ( )

Used by the control point to Gets the current operation mode from the engine.

Parameters

N/A	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- Timeout: 5 seconds

9.18.3.5 ULONG SLQSLOCGetServer (LocGetServerReq * *pLocGetServerReq*)

Gets the A-GPS server address from the engine. The request is acknowledged through the response, but the SUCCESS/FAILURE status is sent through SetLocGetServerCallback callback If successful, the callback also contains the A-GPS server address

Parameters

pLocGetServer-Req[IN]	• See LocGetServerReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.6 ULONG SLQSLOCInjectPosition (LocInjectPositionReq * *pLocInjectPositionReq*)

Injects a position to the location engine.

Parameters

pLocInject-PositionReq[IN]	• See LocInjectPositionReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.7 ULONG SLQSLOCInjectSensorData (LocInjectSensorDataReq * *pLocInjectSensorDataReq*)

Control point to to inject sensor data into the GNSS location engine.

Parameters

pLocInject-SensorData-Req[IN]	• See LocInjectSensorDataReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.8 ULONG SLQSLOCInjectUTCTime (ULONGLONG *timeMsec*, ULONG *timeUncMsec*)

Injects UTC time in the location engine.

Parameters

timeMsec[IN]	• The UTC time since Jan. 1, 1970
timeUncMsec[IN]	• The time Uncertainty

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.9 ULONG SLQSLOCSetCradleMountConfig (LocSetCradleMountReq * *pLocSetCradleMountReq*)

Control point to set the current cradle mount configuration.

Parameters

pLocSetCradleMountReq[IN]	• See LocSetCradleMountReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.10 ULONG SLQSLOCSetExtPowerState (LOCExtPowerStateReqResp * *pLOCExtPowerStateReqResp*)

Used by the control point to set the current external power configuration.

Parameters

pLOCExtPowerStateReqResp[IN]	• See LOCExtPowerStateReqResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.11 ULONG SLQSLOCSetOpMode (ULONG *mode*)

Used by the control point to tells the engine to use the specified operation mode while making the position fixes

Parameters

mode[IN]	• Valid values: – eQMI_LOC_OPER_MODE_DEFAULT (1) - Use the default engine mode – eQMI_LOC_OPER_MODE_MSB (2) - Use the MS-based mode – eQMI_LOC_OPER_MODE_MSA (3) - Use the MS-assisted mode – eQMI_LOC_OPER_MODE_STANDALONE (4) - Use Standalone mode – eQMI_LOC_OPER_MODE_CELL_ID (5) - Use cell ID; this mode is only valid for GSM/UMTS networks – eQMI_LOC_OPER_MODE_WWAN (6) - Use WWAN measurements to calculate the position; if this mode is set, AFLT will be used for 1X networks and OTDOA will be used for LTE networks

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.12 ULONG SLQSLOCSetServer (LocSetServerReq * *pLocSetServerReq*)

Specifies the A-GPS server type and address.

Parameters

pLocSetServerReq[IN]	• See LocSetServerReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- Timeout: 5 seconds

  - If multiple types of addresses are specified in the request, the IPv4 address takes precedence over the IPv6 address and the IPv6 address takes precedence over the URL address.

9.18.3.13 ULONG SLQSLOCStart (LOCStartReq * *pLOCStartReq*)

Used by the control point to initiate a GPS session.

Parameters

pLOCStartReq-Req[IN]	• See LOCStartReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.14 ULONG SLQSLOCStop (LOCStopReq * *pLOCStopReq*)

Used by the control point to stop a GPS session.

Parameters

pLOCStopReq-Resp[IN]	• See LOCStopReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.18.3.15 ULONG SwiLocGetAutoStart (SwiLocGetAutoStartResp * *resp*)

Used by the control point to Get Loc Auto Start settings

Parameters

resp[OUT]	• See SwiLocGetAutoStartResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.18.3.16 ULONG SwiLocSetAutoStart (SwiLocSetAutoStartReq * *req*)

Used by the control point to Set Loc Auto Start settings

Parameters

req[IN]	• See SwiLocSetAutoStartReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.19 qaGobiApiNas.h File Reference

Network Access Service API function prototypes.

Data Structures

- struct RFBandInfoElements
- struct RfDedicatedBandInfoElements
- struct RfBandInfoExtFormatElements
- struct RfBandwidthInfoElements
- struct RfBandInfoList
- struct RfDedicatedBandInfo

- struct RfBandInfoExtFormat
- struct RfBandwidthInfo
- struct LTEOperationMode
- struct NasGetRFInfoResp
- struct servSystem
- struct dataSrvCapabilities
- struct currentPLMN
- struct roamIndList
- struct qaQmi3Gpp2TimeZone
- struct detailSvcInfo
- struct CDMASysInfoExt
- struct callBarStatus
- struct qaQmiServingSystemParam
- struct rxSignalStrengthListElement
- struct ecioListElement
- struct errorRateListElement
- struct rsrqInformation
- struct lteSnrinformation
- struct lteRsrpinformation
- struct slqsSignalStrengthInfo
- struct SlqsNas3GppNetworkInfo
- struct _SlqsNas3GppNetworkRAT_
- struct SlqsNasPcsDigit
- struct SlqsNasPCICellInfo
- struct SlqsNasPCIInfo
- struct lteOpModeTlv
- struct _slqsNetworkScanInfo
- struct netSelectionPref
- struct acqOrderPref
- struct CSGID
- struct _sysSelectPrefParams
- struct lteBandPrefExt
- struct ciotAcqOrderPref
- struct nr5gBandPref
- struct sysSelectPrefParamsExt
- struct _sysSelectPrefInfo
- struct AcqOrderPrefTlv
- struct RatDisabledMaskTlv
- struct CiotLteOpModePrefTlv
- struct LteM1BandPrefTlv
- struct LteNb1BandPrefTlv
- struct CiotAcqOrderPrefTlv
- struct BandPrefTlv
- struct _sysSelectPrefExtInfo
- struct SrvStatusInfo
- struct GSMSrvStatusInfo
- struct sysInfoCommon
- struct CDMASysInfo
- struct HDRSysInfo
- struct GSMSysInfo
- struct WCDMASysInfo
- struct LTESysInfo
- struct AddCDMASysInfo
- struct AddSysInfo
- struct CallBarringSysInfo

- struct nasGetSysInfoResp
- struct CommInfo
- struct LTEInfo
- struct swiModemStatusResp
- struct nasGetHDRColorCodeResp
- struct nasGetTxRxInfoReq
- struct rxInfo
- struct txInfo
- struct nasGetTxRxInfoResp
- struct CDMASSInfo
- struct HDRSSInfo
- struct LTESSInfo
- struct TDSCDMASigInfoExt
- struct nasGetSigInfoResp
- struct nasIndicationRegisterReq
- struct nasPLMNNameReq
- struct nasPLMNNameResp
- struct OperatorPLMNData
- struct operatorPLMNList
- struct serviceProviderName
- struct PLMNNetworkNameData
- struct PLMNNetworkName
- struct operatorNameString
- struct nasOperatorNameResp
- struct nasGet3GPP2SubscriptionInfoReq
- struct namName
- struct dirNum
- struct sidNid
- struct homeSIDNID
- struct minBasedIMSI
- struct trueIMSI
- struct CDMAChannel
- struct nasGet3GPP2SubscriptionInfoResp
- struct nmrCellInfo
- struct GERANInfo
- struct geranInstInfo
- struct UMTSinstInfo
- struct UMTSInfo
- struct CDMAInfo
- struct cellParams
- struct LTEInfoIntrafreq
- struct infoInterFreq
- struct LTEInfoInterfreq
- struct gsmCellInfo
- struct lteGsmCellInfo
- struct LTEInfoNeighboringGSM
- struct wcdmaCellInfo
- struct lteWcdmaCellInfo
- struct LTEInfoNeighboringWCDMA
- struct umtsLTENbrCell
- struct WCDMAInfoLTENeighborCell
- struct nasCellLocationInfoResp
- struct MNRInfo
- struct nasInitNetworkReg
- struct protocolSubtypeElement

- struct HDRPersonalityResp
- struct HDRProtSubtypResp
- struct PSDetachReq
- struct GetErrRateResp
- struct DRCParams
- struct PilotSetParams
- struct PilotSetData
- struct GetHRPDStatsResp
- struct ActPilotPNElement
- struct NetworkStat1x
- struct NetworkStatEVDO
- struct DeviceConfigDetail
- struct DataStatusDetail
- struct NetworkDebugResp
- struct LteCQIParm
- struct RSSIThresh
- struct ECIOThresh
- struct HDRSINRThresh
- struct LTESNRThresh
- struct IOThresh
- struct RSRQThresh
- struct RSRPThresh
- struct LTESigRptCfg
- struct TDSCDMASINRCONFThresh
- struct sigInfo
- struct NasSwiIndReg
- struct CDMARSSIThresh
- struct CDMAECIOThresh
- struct HDRRSSIThresh
- struct HDRECIOThresh
- struct HDRSINRThreshold
- struct HDRIOThresh
- struct GSMRSSIThresh
- struct WCDMARSSIThresh
- struct WCDMAECIOThresh
- struct LTERSSIThresh
- struct LTESNRThreshold
- struct LTERSRQThresh
- struct LTERSRPThresh
- struct LTESigRptConfig
- struct TDSCDMARSCPThresh
- struct TDSCDMARSSIThresh
- struct TDSCDMAECIOThresh
- struct TDSCDMASINRThresh
- struct setSignalStrengthInfo
- struct PhyCaAggScellIndType
- struct PhyCaAggScellDlBw
- struct PhyCaAggScellInfo
- struct PhyCaAggPcellInfo
- struct PhyCaAggScellIndex
- struct PhyCaAggScellArray
- struct nasGetLTECphyCaResp
- struct nasGetLTECphyCa
- struct wcdmaUARFCN
- struct lteEARFCN

- struct ltePCI
- struct nasSwiGetChannelLockResp
- struct nasSwiSetChannelLockReq
- struct timeInfo
- struct GetNetworkTimeResp
- struct RxSigInfo
- struct SccRxInfo
- struct LteSccRxInfoResp
- struct nasSeteDRXParamsReq
- struct nasGeteDRXParamsResp
- struct nasGeteDRXParamsReq
- struct _slqsNetworkScanInfoReq
- struct ForbiddenNetworks3GPP
- struct nasGetForbiddenNetworksResp

Macros

- #define SLQS_SS_INFO_LIST_MAX_ELEMENTS 18
- #define MAX_DESCRIPTION_LENGTH 255
- #define SLQS_SYSTEM_ID_SIZE 16
- #define PLMN_LENGTH 3
- #define MAX_SERV_SYSTEM_RADIO_INTERFACES 0x0A
- #define MAX_DATA_SRV_CAPABILITIES 0x20
- #define NAM_NAME_LENGTH 12
- #define IMSI_M_S1_LENGTH 7
- #define IMSI_M_S2_LENGTH 3
- #define MAX_PILOT_SETS 0xFF
- #define UATISIZE 16
- #define NAS_SIG_INFO_MAX_TDSCDMA_THRESHOLDS_LIST_SIZE 16
- #define NAS_SIG_INFO_MIN_dBm_FLOAT_VALUE -125.0
- #define NAS_SIG_INFO_MIN_dB_FLOAT_VALUE -10.0
- #define NAS_MAX_SCC_RX_INFO_INSTANCES 255
- #define NAS_MAX_SLQS_NAS_PCI_INFO_LENGTH 255
- #define NAS_MAX_SLQS_NAS_PCI_INFO_PLMN_LENGTH 255
- #define SLQS_NAS_MCC_MNC_INST_LENGTH 255
- #define SLQS_NAS_NW_SCAN_LTE_OP_MODE_MAX_LENGTH 255
- #define MAX_PHY_CA_AGG_SCELL_ARRRY_SIZE 255

Typedefs

- typedef struct _SlqsNas3GppNetworkRAT_ SlqsNas3GppNetworkRAT
- typedef struct _slqsNetworkScanInfo slqsNetworkScanInfo
- typedef struct _sysSelectPrefParams sysSelectPrefParams
- typedef struct _sysSelectPrefInfo sysSelectPrefInfo
- typedef BandPrefTlv NR5gBandPrefTlv
- typedef BandPrefTlv LTEBandPrefExtTlv
- typedef struct _sysSelectPrefExtInfo sysSelectPrefExtInfo
- typedef struct _slqsNetworkScanInfoReq slqsNetworkScanInfoReq

Enumerations

- enum _NAMS_RADIO_IF_TECHNOLOGY_ {
  eNAS_RADIO_IF_GSM = 0x04,
  eNAS_RADIO_IF_UMTS = 0x05,
  eNAS_RADIO_IF_LTE = 0x08,
  eNAS_RADIO_IF_TDSCDMA = 0x09 }

- enum NAS_LTE_CPHY_SCELL_STATE {
  eNAS_LTE_CPHY_SCELL_STATE_DECONFIGURED =0x00,
  eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED =0x01,
  eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED =0x02 }

- enum NAS_LTE_CPHY_CA_BW_NRB {
  eNAS_LTE_CPHY_CA_BW_NRB_6 =0x00,
  eNAS_LTE_CPHY_CA_BW_NRB_15 =0x01,
  eNAS_LTE_CPHY_CA_BW_NRB_25 =0x02,
  eNAS_LTE_CPHY_CA_BW_NRB_50 =0x03,
  eNAS_LTE_CPHY_CA_BW_NRB_75 =0x04,
  eNAS_LTE_CPHY_CA_BW_NRB_100 =0x05 }

- enum LTE_BAND_CLASS_E_UTRA_OPERATING_BAND {

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_1 = 120,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_2 = 121,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_3 = 122,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_4 = 123,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_5 = 124,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_6 = 125,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_7 = 126,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_8 = 127,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_9 = 128,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_10 = 129,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_11 = 130,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_12 = 131,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_13 = 132,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_14 = 133,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_17 = 134,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_33 = 135,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_34 = 136,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_35 = 137,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_36 = 138,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_37 = 139,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_38 = 140,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_39 = 141,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_40 = 142,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_18 = 143,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_19 = 144,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_20 = 145,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_21 = 146,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_24 = 147,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_25 = 148,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_41 = 149,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_42 = 150,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_43 = 151,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_23 = 152,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_26 = 153,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_32 = 154,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_125 = 155,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_126 = 156,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_127 = 157,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_28 = 158,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_29 = 159,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_30 = 160,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_66 = 161,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_250 = 162,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_46 = 163,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_27 = 164,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_31 = 165,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_71 = 166,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_47 = 167,
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_48 = 168 }

- enum eSYS_SRV_DOMAIN {
  eSYS_SRV_DOMAIN_NO_SRV = 0x00,
  eSYS_SRV_DOMAIN_CS_ONLY = 0x01,
  eSYS_SRV_DOMAIN_PS_ONLY = 0x02,
  eSYS_SRV_DOMAIN_CS_PS = 0x03,
  eSYS_SRV_DOMAIN_CAMPED = 0x04,
  eSYS_SRV_DOMAIN_UNKNOWN }

Functions

- ULONG GetSignalStrengths (ULONG *pArraySizes, INT8 *pSignalStrength, ULONG *pRadioInterface)
- ULONG PerformNetworkScan (BYTE *pInstanceSize, BYTE *pInstances)
- ULONG InitiateNetworkRegistration (ULONG regType, WORD mcc, WORD mnc, ULONG rat)
- ULONG GetServingNetwork (ULONG *pRegistrationState, ULONG *pCSDomain, ULONG *pPSDomain, ULONG *pRAN, BYTE *pRadioIfacesSize, BYTE *pRadioIfaces, ULONG *pRoaming, WORD *pMCC, WORD *pMNC, BYTE nameSize, CHAR *pName)
- ULONG GetHomeNetwork (WORD *pMCC, WORD *pMNC, BYTE nameSize, CHAR *pName, WORD *pSID, WORD *pNID)
- ULONG GetServingNetworkCapabilities (BYTE *pDataCapsSize, BYTE *pDataCaps)
- ULONG SetNetworkPreference (ULONG technologyPref, ULONG duration)
- ULONG GetNetworkPreference (ULONG *pTechnologyPref, ULONG *pDuration, ULONG *pPersistentTechnologyPref)
- ULONG GetRFInfo (BYTE *pInstanceSize, struct RFBandInfoElements *pRFBandInfo)
- ULONG SLQSNasGetRFInfo (NasGetRFInfoResp *pGetRFInfoResp)
- ULONG InitiateDomainAttach (ULONG action)
- ULONG GetACCOLC (BYTE *pACCOLC)
- ULONG SetACCOLC (CHAR *spc, BYTE accolc)
- ULONG SetCDMANetworkParameters (CHAR *pSPC, BYTE *pForceRev0, BYTE *pCustomSCP, ULONG *pProtocol, ULONG *pBroadcast, ULONG *pApplication, ULONG *pRoaming)
- ULONG GetCDMANetworkParameters (BYTE *pSCI, BYTE *pSCM, BYTE *pRegHomeSID, BYTE *pRegForeignSID, BYTE *pRegForeignNID, BYTE *pForceRev0, BYTE *pCustomSCP, ULONG *pProtocol, ULONG *pBroadcast, ULONG *pApplication, ULONG *pRoaming)
- ULONG GetANAAAAuthenticationStatus (ULONG *pStatus)
- ULONG SLQSGetServingSystem (qaQmiServingSystemParam *pServingSystem)
- ULONG SLQSSetBandPreference (ULONGLONG bandpreference)
- ULONG SLQSNasIndicationRegister (BYTE systemSelectionInd, BYTE DDTMInd, BYTE servingSystemInd)
- ULONG SLQSGetSignalStrength (struct slqsSignalStrengthInfo *pSignalInfo)
- ULONG SLQSPerformNetworkScan (slqsNetworkScanInfo *pNetworkInfo)
- ULONG SLQSSetSysSelectionPref (sysSelectPrefParams *pSysSelectPrefParams)
- ULONG SLQSSetSysSelectionPrefExt (sysSelectPrefParamsExt *pSysSelectPrefParamsExt)
- ULONG SLQSGetSysSelectionPref (sysSelectPrefInfo *pSysSelectPrefInfo)
- ULONG SLQSGetSysSelectionPrefExt (sysSelectPrefExtInfo *pSysSelectPrefExtInfo)
- ULONG SLQSNasGetSysInfo (nasGetSysInfoResp *pGetSysInfoResp)
- ULONG SLQSNasSwiModemStatus (swiModemStatusResp *pModemStatusResp)
- ULONG SLQSNasGetHDRColorCode (nasGetHDRColorCodeResp *pGetHDRColorCodeResp)
- ULONG SLQSNasGetTxRxInfo (nasGetTxRxInfoReq *pGetTxRxInfoReq, nasGetTxRxInfoResp *pGetTxRxInfoResp)
- ULONG SLQSNasGetSigInfo (nasGetSigInfoResp *pGetSigInfoResp)
- ULONG SLQSNasIndicationRegisterExt (nasIndicationRegisterReq *pIndicationRegisterReq)
- ULONG SLQSGetPLMNName (nasPLMNNameReq *pPLMNNameReq, nasPLMNNameResp *pPLMNNameResp)
- ULONG SLQSGetOperatorNameData (nasOperatorNameResp *pOperatorNameData)
- ULONG SLQSNasGet3GPP2Subscription (nasGet3GPP2SubscriptionInfoReq *pGet3GPP2SubsInfoReq, nasGet3GPP2SubscriptionInfoResp *pGet3GPP2SubsInfoResp)
- ULONG SLQSNasGetCellLocationInfo (nasCellLocationInfoResp *pNasCellLocationInfoResp)
- ULONG SLQSInitiateNetworkRegistration (nasInitNetworkReg *pNasInitNetRegistrationReg)
- ULONG SLQSSwiGetHDRPersonality (HDRPersonalityResp *pHDRPersonalityResp)
- ULONG SLQSSwiGetHDRProtSubtype (HDRProtSubtypResp *pHDRProtSubtypResp)
- ULONG SLQSSwiPSDetach (PSDetachReq *pPSDetachReq)
- ULONG SLQSGetErrorRate (GetErrRateResp *pGetErrRateResp)
- ULONG SLQSSwiGetHRPDStats (GetHRPDStatsResp *pGetHRPDStatsResp)
- ULONG SLQSSwiNetworkDebug (NetworkDebugResp *pNetworkDebugResp)
- ULONG SLQSSwiGetLteCQI (LteCQIParm *pLteCQIResp)

- ULONG SLQSConfigSigInfo (sigInfo *pSigInfo)
- ULONG SLQSNasSwiIndicationRegister (NasSwiIndReg *pIndRegReq)
- ULONG GetHomeNetwork3GPP2 (WORD *pMCC, WORD *pMNC, BYTE nameSize, CHAR *pName, WORD *pSID, WORD *pNID, WORD *pNw2MCC, WORD *pNw2MNC, BYTE *pNw2DescDisp, BYTE *pNw2DescEnc, BYTE *pNw2DescLen, BYTE *pNw2Name)
- ULONG SLQSNasConfigSigInfo2 (setSignalStrengthInfo *pSetSignalStrengthInfo)
- ULONG SLQSNASGetLTECPHYCaInfo (nasGetLTECphyCa *pLTECPhyCa)
- ULONG SLQSNasIndicationRegisterLTECphyCa (BYTE *bStatus)
- ULONG SLQSNASSwiGetChannelLock (nasSwiGetChannelLockResp *pNasSwiGetChannelLockResp)
- ULONG SLQSNASSwiSetChannelLock (nasSwiSetChannelLockReq *pNasSwiSetChannelLockReq)
- ULONG SLQSGetNetworkTime (GetNetworkTimeResp *pGetNetworkTimeResp)
- ULONG SLQSSwiGetLteSccRxInfo (LteSccRxInfoResp *pLteSccRxInfoResp)
- ULONG SLQSNASSeteDRXParams (nasSeteDRXParamsReq *pNasSeteDRXParamsReq)
- ULONG SLQSNASGeteDRXParams (nasGeteDRXParamsResp *pNasGeteDRXParamsResp)
- ULONG SLQSNASGeteDRXParamsExt (nasGeteDRXParamsReq *pNasGeteDRXParamsReq, nasGeteDRXParamsResp *pNasGeteDRXParamsResp)
- ULONG SLQSPerformNetworkScanPCI (slqsNetworkScanInfoReq *pScanInfoReq, slqsNetworkScanInfo *pNetworkInfo)
- ULONG SLQSNASGetForbiddenNetworks (nasGetForbiddenNetworksResp *pNasGetForbiddenNetworksResp)

9.19.1 Detailed Description

Network Access Service API function prototypes.

9.19.2 Macro Definition Documentation

9.19.2.1 #define IMSI_M_S1_LENGTH 7

9.19.2.2 #define IMSI_M_S2_LENGTH 3

9.19.2.3 #define MAX_DATA_SRV_CAPABILITIES 0x20

9.19.2.4 #define MAX_DESCRIPTION_LENGTH 255

9.19.2.5 #define MAX_PHY_CA_AGG_SCELL_ARRRY_SIZE 255

9.19.2.6 #define MAX_PILOT_SETS 0xFF

9.19.2.7 #define MAX_SERV_SYSTEM_RADIO_INTERFACES 0x0A

9.19.2.8 #define NAM_NAME_LENGTH 12

9.19.2.9 #define NAS_MAX_SCC_RX_INFO_INSTANCES 255

9.19.2.10 #define NAS_MAX_SLQS_NAS_PCI_INFO_LENGTH 255

9.19.2.11 #define NAS_MAX_SLQS_NAS_PCI_INFO_PLMN_LENGTH 255

9.19.2.12 #define NAS_SIG_INFO_MAX_TDSCDMA_THRESHOLDS_LIST_SIZE 16

9.19.2.13 #define NAS_SIG_INFO_MIN_dB_FLOAT_VALUE -10.0

9.19.2.14 #define NAS_SIG_INFO_MIN_dBm_FLOAT_VALUE -125.0

9.19.2.15 #define PLMN_LENGTH 3

9.19.2.16 #define SLQS_NAS_MCC_MNC_INST_LENGTH 255

9.19.2.17 #define SLQS_NAS_NW_SCAN_LTE_OP_MODE_MAX_LENGTH 255

9.19.2.18 #define SLQS_SS_INFO_LIST_MAX_ELEMENTS 18

9.19.2.19 #define SLQS_SYSTEM_ID_SIZE 16

9.19.2.20 #define UATISIZE 16

9.19.3 Typedef Documentation

9.19.3.1 typedef BandPrefTlv LTEBandPrefExtTlv

Contain the LTE Band Preference Extended.

- See BandPrefTlv for more information.

9.19.3.2 typedef BandPrefTlv NR5gBandPrefTlv

Contain the NR5G Band Preference.

- See BandPrefTlv for more information.

9.19.3.3 typedef struct _SlqsNas3GppNetworkRAT_ SlqsNas3GppNetworkRAT

Contain the 3GPP radio access technology information.

Parameters

MCC	• Mobile Country Code
MNC	• Mobile Network Code
RAT	• Radio Access Technology – 0x04 - GERAN – 0x05 - UMTS – 0x08 - LTE – 0x09 - TD-SCDMA

9.19.3.4 typedef struct _slqsNetworkScanInfo slqsNetworkScanInfo

Contain the network scan information.

Parameters

pNetworkInfoInstances[IN/OUT]	• Upon input, maximum number of elements that the network info instance array can contain. • Upon successful output, the actual number of elements in the network info instance array.
pNetworkInfo[OUT]	• Network info instance array – See SlqsNas3GppNetworkInfo for more information
pRATInstances[IN/OUT]	• Upon input, maximum number of elements that the RAT info instance array can contain. • Upon successful output, the actual number of elements in the RAT info instance array.
pRATInfo[OUT]	• RAT info instance array – See SlqsNas3GppNetworkRAT for more information
pPCSDigitInstances[IN/OUT]	• Upon input, maximum number of elements that the PCS Digit info instance array can contain. • Upon successful output, the actual number of elements in the PCS Digit info instance array.
pPCSDigitInfo[OUT]	• PCS Digit info instance array – See SlqsNasPcsDigit for more information
pScanResult[OUT]	• status of network scan • 0x00 - scan successful • 0x01 - scan was aborted • 0x02 - scan did not complete due to a radio link failure recovery in progress
pPCIInfo[OUT]	• PCI Information. • See SlqsNasPCIInfo for more information.
has_PCIInfo[Out]	• PCI Information Availability. – false : Unavailable. – true : Available.
pLteOpModeTlv[OUT]	• LTE Operational Mode. • See lteOpModeTlv for more information.

9.19.3.5 typedef struct _slqsNetworkScanInfoReq slqsNetworkScanInfoReq

Contain the network scan request information.

Parameters

pNetworkType	• Optional parameter NetworkType. • Bit 0 - GSM • Bit 1 - UMTS • Bit 2 - LTE • Bit 3 - TD-SCDMA
pScanType[IN]	• Optional parameter Scan Type. • 0x00 - PLMN (default) • 0x01 - Closed subscriber group • 0x02 - Mode preference • 0x03 - Physical cell ID

pCiotOpMode-Pref[IN]	• CIOT LTE Operational Mode Preference
	• Bitmask representing the Cellular Internet of Things (CIoT) LTE operational mode preference.
	• Values:
	  – Bit 0 (0x01) - QMI_NAS_CIOT_LTE_OP_MODE_PREF_WB - LTE wideband (legacy LTE)
	  – Bit 1 (0x02) - QMI_NAS_CIOT_LTE_OP_MODE_PREF_M1 - LTE M1
	  – Bit 2 (0x04) - QMI_NAS_CIOT_LTE_OP_MODE_PREF_NB1 - LTE NB1
	  – All unlisted bits are reserved for future use and the service point ignores them if used.

pLteM1Band-Pref[IN]	• Bitmask representing the LTE M1 band preferencet. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127

pLteNb1Band-Pref[IN]	• Bitmask representing the LTE NB1 band preference. • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – Bit 61 - E-UTRA Operating Band 126 – Bit 62 - E-UTRA Operating Band 127

9.19.3.6 typedef struct _sysSelectPrefExtInfo sysSelectPrefExtInfo

Structure for storing the current preferred system selection settings for the device.

Parameters

pSysSelectPrefInfo	• See sysSelectPrefInfo for more information
pAcqOrderPref	• Optional parameter • Acquisition Order Preference • See AcqOrderPrefTlv for more information
pRatDisabledMask	• Optional parameter • See RatDisabledMaskTlv for more information
pCiotLteOpModePref	• Optional parameter • See CiotLteOpModePrefTlv for more information
pLteM1BandPref	• Optional parameter • See LteM1BandPrefTlv for more information
pLteNb1BandPref	• Optional parameter • See LteNb1BandPrefTlv for more information
pCiotAcqOrderPref	• Optional parameter indicating CIOT Acquisition Order Preference • See CiotAcqOrderPrefTlv for more information
pNr5gBandPref	• Optional parameter indicating NR5G Band Preference • See NR5gBandPrefTlv for more information
pLTEBandPrefExt	• Optional parameter indicating LTE Band Preference Extended • See LTEBandPrefExtTlv for more information

Note

None

9.19.3.7 typedef struct _sysSelectPrefInfo sysSelectPrefInfo

Structure for storing the current preferred system selection settings for the device.

Parameters

pEmerMode	• Optional parameter specifying the emergency Mode • Values: – 0 - OFF (normal) – 1 - ON (Emergency) • function SLQSGetSysSelectionPref() returns a default value FF if no value is returned by the device.
pModePref	• Optional parameter • Bit Mask indicating the radio technology mode preference • Bit values: – Bit 0 - cdma2000 1x – Bit 1 - cdma2000 HRPD(1xEV-DO) – Bit 2 - GSM – Bit 3 - UMTS – Bit 4 - LTE – Bit 5 - TD-SCDMA – Bit 6 - NR5G • function SLQSGetSysSelectionPref() returns a default value FF if no value is returned by the device.

pBandPref	• Optional parameter • Bit mask representing the band preference • Bit values: – Bit 0 - Band Class 0, A-System – Bit 1 - Band Class 0, B-System, Band Class 0 AB, GSM 850 Band – Bit 2 - Band Class 1, all blocks – Bit 3 - Band Class 2 place holder – Bit 4 - Band Class 3, A-System – Bit 5 - Band Class 4, all blocks – Bit 6 - Band Class 5, all blocks – Bit 7 - GSM_DCS_1800 band – Bit 8 - GSM Extended GSM (E-GSM) 900 band – Bit 9 - GSM Primary GSM (P-GSM) 900 band – Bit 10 - Band Class 6 – Bit 11 - Band Class 7 – Bit 12 - Band Class 8 – Bit 13 - Band Class 9 – Bit 14 - Band Class 10 – Bit 15 - Band Class 11 – Bit 16 - GSM 450 band – Bit 17 - GSM 480 band – Bit 18 - GSM 750 band – Bit 19 - GSM 850 band – Bit 20 - GSM Railways GSM 900 Band – Bit 21 - GSM PCS 1900 band – Bit 22 - WCDMA Europe, Japan, and China IMT 2100 band – Bit 23 - WCDMA U.S. PCS 1900 band – Bit 24 - WCDMA Europe and China DCS 1800 band – Bit 25 - WCDMA U.S. 1700 band – Bit 26 - WCDMA U.S. 850 band – Bit 27 - WCDMA Japan 800 band – Bit 28 - Band Class 12 – Bit 29 - Band Class 14 – Bit 30 - Reserved – Bit 31 - Band Class 15 – Bit 32 to 47 - Reserved – Bit 48 - WCDMA Europe 2600 band – Bit 49 - WCDMA Europe and Japan 900 band – Bit 50 - WCDMA Japan 1700 band – Bit 51 to 55 - Reserved – Bit 56 - Band Class 16 – Bit 57 - Band Class 17 – Bit 58 - Band Class 18 – Bit 59 - Band Class 19 – Bit 60 to 64 - Reserved • function SLQSGetSysSelectionPref() returns a default value FFFFFFFFFFFFFFFF if no value is returned by the device.

pPRLPref	• Optional parameter indicating the CDMA PRL Preference • Values: – 0x0001 - Acquire available system only on the A side – 0x0002 - Acquire available system only on the B side – 0x3FFF - Acquire any available systems • function SLQSGetSysSelectionPref() returns a default value FFFF if no value is returned by the device.
pRoamPref	• Optional parameter indicating the roaming Preference • Values: – 0x01 - Acquire only systems for which the roaming indicator is off – 0x02 - Acquire a system as long as its roaming indicator is not off – 0x03 - Acquire only systems for which the roaming indicator is off or solid on, i.e. not flashing; CDMA only – 0xFF - Acquire systems, regardless of their roaming indicator • function SLQSGetSysSelectionPref() returns a default value FFFF if no value is returned by the device.

pLTEBandPref	• Optional parameter • Bit mask representing the LTE band preference • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – All other bits are reserved • function SLQSGetSysSelectionPref() returns a default value FFFFFFFFFFFFFFFF if no value is returned by the device.

pNetSelPref	• Optional parameter indicating network selection preference • Values: – 0x00 - Automatic network selection – 0x01 - Manual network selection • function SLQSGetSysSelectionPref() returns a default value FF if no value is returned by the device.
pSrvDomainPref	• Optional parameter indicating Service domain preference • Values: – 0x00 - Circuit switched only – 0x01 - Packet switched only – 0x02 - Circuit switched and packet switched – 0x03 - Packet switched attach – 0x04 - Packet switched detach • function SLQSGetSysSelectionPref() returns a default value FFFFFFFF if no value is returned by the device.
pGWAcqOrder-Pref	• Optional parameter indicating GSM/WCDMA Acquisition order Preference • Values: – 0x00 - Automatic – 0x01 - GSM then WCDMA – 0x02 - WCDMA then GSM • function SLQSGetSysSelectionPref() returns a default value FFFFFFFF if no value is returned by the device.

Note

None

9.19.3.8 typedef struct _sysSelectPrefParams sysSelectPrefParams

Contain the system selection preferences.

Parameters

pEmerMode	• Optional parameter specifying the emergency Mode • Values: – 0 - OFF (normal) – 1 - ON (Emergency)
pModePref	• Optional parameter • Bit Mask indicating the radio technology mode preference • Bit values: – Bit 0 - cdma2000 1x – Bit 1 - cdma2000 HRPD(1xEV-DO) – Bit 2 - GSM – Bit 3 - UMTS – Bit 4 - LTE – Bit 5 - TD-SCDMA – Bit 6 - NR5G

pBandPref	• Optional parameter • Bit mask representing the band preference • Bit values: – Bit 0 - Band Class 0, A-System – Bit 1 - Band Class 0, B-System, Band Class 0 AB, GSM 850 Band – Bit 2 - Band Class 1, all blocks – Bit 3 - Band Class 2 place holder – Bit 4 - Band Class 3, A-System – Bit 5 - Band Class 4, all blocks – Bit 6 - Band Class 5, all blocks – Bit 7 - GSM_DCS_1800 band – Bit 8 - GSM Extended GSM (E-GSM) 900 band – Bit 9 - GSM Primary GSM (P-GSM) 900 band – Bit 10 - Band Class 6 – Bit 11 - Band Class 7 – Bit 12 - Band Class 8 – Bit 13 - Band Class 9 – Bit 14 - Band Class 10 – Bit 15 - Band Class 11 – Bit 16 - GSM 450 band – Bit 17 - GSM 480 band – Bit 18 - GSM 750 band – Bit 19 - GSM 850 band – Bit 20 - GSM Railways GSM 900 Band – Bit 21 - GSM PCS 1900 band – Bit 22 - WCDMA Europe, Japan, and China IMT 2100 band – Bit 23 - WCDMA U.S. PCS 1900 band – Bit 24 - WCDMA Europe and China DCS 1800 band – Bit 25 - WCDMA U.S. 1700 band – Bit 26 - WCDMA U.S. 850 band – Bit 27 - WCDMA Japan 800 band – Bit 28 - Band Class 12 – Bit 29 - Band Class 14 – Bit 30 - Reserved – Bit 31 - Band Class 15 – Bit 32 to 47 - Reserved – Bit 48 - WCDMA Europe 2600 band – Bit 49 - WCDMA Europe and Japan 900 band – Bit 50 - WCDMA Japan 1700 band – Bit 51 to 55 - Reserved – Bit 56 - Band Class 16 – Bit 57 - Band Class 17 – Bit 58 - Band Class 18 – Bit 59 - Band Class 19 – Bit 60 to 64 - Reserved

pPRLPref	• Optional parameter indicating the CDMA PRL Preference • Values: – 0x0001 - Acquire available system only on the A side – 0x0002 - Acquire available system only on the B side – 0x3FFF - Acquire any available systems
pRoamPref	• Optional parameter indicating the roaming Preference • Values: – 0x01 - Acquire only systems for which the roaming indicator is off – 0x02 - Acquire a system as long as its roaming indicator is not off – 0x03 - Acquire only systems for which the roaming indicator is off or solid on, i.e. not flashing; CDMA only – 0xFF - Acquire systems, regardless of their roaming indicator

pLTEBandPref	• Optional parameter • Bit mask representing the LTE band preference • Bit Values – Bit 0 - E-UTRA Operating Band 1 – Bit 1 - E-UTRA Operating Band 2 – Bit 2 - E-UTRA Operating Band 3 – Bit 3 - E-UTRA Operating Band 4 – Bit 4 - E-UTRA Operating Band 5 – Bit 5 - E-UTRA Operating Band 6 – Bit 6 - E-UTRA Operating Band 7 – Bit 7 - E-UTRA Operating Band 8 – Bit 8 - E-UTRA Operating Band 9 – Bit 9 - E-UTRA Operating Band 10 – Bit 10 - E-UTRA Operating Band 11 – Bit 11 - E-UTRA Operating Band 12 – Bit 12 - E-UTRA Operating Band 13 – Bit 13 - E-UTRA Operating Band 14 – Bit 16 - E-UTRA Operating Band 17 – Bit 17 - E-UTRA Operating Band 18 – Bit 18 - E-UTRA Operating Band 19 – Bit 19 - E-UTRA Operating Band 20 – Bit 20 - E-UTRA Operating Band 21 – Bit 22 - E-UTRA Operating Band 23 – Bit 23 - E-UTRA Operating Band 24 – Bit 24 - E-UTRA Operating Band 25 – Bit 25 - E-UTRA Operating Band 26 – Bit 27 - E-UTRA Operating Band 28 – Bit 28 - E-UTRA Operating Band 29 – Bit 29 - E-UTRA Operating Band 32 – Bit 32 - E-UTRA Operating Band 33 – Bit 33 - E-UTRA Operating Band 34 – Bit 34 - E-UTRA Operating Band 35 – Bit 35 - E-UTRA Operating Band 36 – Bit 36 - E-UTRA Operating Band 37 – Bit 37 - E-UTRA Operating Band 38 – Bit 38 - E-UTRA Operating Band 39 – Bit 39 - E-UTRA Operating Band 40 – Bit 40 - E-UTRA Operating Band 41 – Bit 41 - E-UTRA Operating Band 42 – Bit 42 - E-UTRA Operating Band 43 – Bit 60 - E-UTRA Operating Band 125 – All other bits are reserved

pNetSelPref	- netSelectionPref • Optional parameter for specifying Network Selection Preference • Modem selects networks based on this parameter(if present). • Either of pNetSelPref or pCSGID can be set. • see netSelectionPref for more information
pChgDuration	• Optional parameter specifying the duration of the change • At least one system selection setting to be set if pChgDuration is populated. • Values: – 0x00 - Power cycle - Remains active until the next device power cycle – 0x01 - Permanent - Remains active through power cycles until changed by client – Device will use "0x01 - permanent" as default if this parameter is omitted
pMNCIncPCS-DigStat	• Optional parameter indicating if MNC includes PCS digit • pNetSelPref is expected if MNC includes PCS digit is set to 1. • Values: – TRUE - MNC is a 3 digit value; e.g., a reported value of 90 corresponds to an MNC value of 090 – FALSE - MNC is a 2-digit value; e.g., a reported value of 90 corresponds to an MNC value of 90
pSrvDomainPref	• Optional parameter indicating Service domain preference • Values: – 0x00 - Circuit switched only – 0x01 - Packet switched only – 0x02 - Circuit switched and packet switched – 0x03 - Packet switched attach – 0x04 - Packet switched detach
pGWAcqOrder-Pref	• Optional parameter indicating GSM/WCDMA Acquisition order Preference • Values: – 0x00 - Automatic – 0x01 - GSM then WCDMA – 0x02 - WCDMA then GSM
pTdscdmaBand-Pref	• Optional parameter indicating bitmask representing the TD-SCDMA band preference to be set. • Values: – 0x01 - TD-SCDMA Band A – 0x02 - TD-SCDMA Band B – 0x04 - TD-SCDMA Band C – 0x08 - TD-SCDMA Band D – 0x10 - TD-SCDMA Band E – 0x20 - TD-SCDMA Band F – All other bits are reserved

pAcqOrderPref	- acqOrderPref • Optional parameter for specifying Acquisition Order Preference • see acqOrderPref for more information
pSrvReg-Restriction	• Optional parameter indicating Network Selection Registration Restriction Preference • Values: – 0x00 - Device follows the normal registration process – 0x01 - Device camps on the network according to its provisioning, but does not register – 0x02 - Device selects the network for limited service – All other values are reserved.
pCSGID	- CSGID • Optional parameter for specifying CSG ID • Either of pNetSelPref or pCSGID can be set. • see CSGID for more information
pRAT	• Optional parameter Radio Access Technology order Preference • Values: – 0x04 - GSM – 0x05 - UMTS – 0x08 - LTE – 0x09 - TDSCDMA – 0x0A - LTE-M1 – 0x0B - LTE-NB1 – 0x0C - NR5G

9.19.4 Enumeration Type Documentation

9.19.4.1 enum _NAMS_RADIO_IF_TECHNOLOGY_

Enumerator

eNAS_RADIO_IF_GSM

eNAS_RADIO_IF_UMTS

eNAS_RADIO_IF_LTE

eNAS_RADIO_IF_TDSCDMA

9.19.4.2 enum eSYS_SRV_DOMAIN

Enumerator

eSYS_SRV_DOMAIN_NO_SRV

eSYS_SRV_DOMAIN_CS_ONLY

eSYS_SRV_DOMAIN_PS_ONLY

eSYS_SRV_DOMAIN_CS_PS

eSYS_SRV_DOMAIN_CAMPED

eSYS_SRV_DOMAIN_UNKNOWN

9.19.4.3 enum LTE_BAND_CLASS_E_UTRA_OPERATING_BAND

Enumerator

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_1
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_2
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_3
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_4
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_5
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_6
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_7
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_8
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_9
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_10
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_11
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_12
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_13
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_14
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_17
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_33
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_34
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_35
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_36
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_37
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_38
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_39
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_40
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_18
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_19
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_20
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_21
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_24
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_25
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_41
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_42
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_43
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_23
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_26
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_32
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_125
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_126
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_127
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_28
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_29
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_30
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_66

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_250

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_46

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_27

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_31

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_71

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_47

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_48

9.19.4.4 enum NAS_LTE_CPHY_CA_BW_NRB

Enumerator

eNAS_LTE_CPHY_CA_BW_NRB_6

eNAS_LTE_CPHY_CA_BW_NRB_15

eNAS_LTE_CPHY_CA_BW_NRB_25

eNAS_LTE_CPHY_CA_BW_NRB_50

eNAS_LTE_CPHY_CA_BW_NRB_75

eNAS_LTE_CPHY_CA_BW_NRB_100

9.19.4.5 enum NAS_LTE_CPHY_SCELL_STATE

Enumerator

eNAS_LTE_CPHY_SCELL_STATE_DECONFIGURED

eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED

eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED

9.19.5 Function Documentation

9.19.5.1 ULONG GetACCOLC (BYTE * *pACCOLC*)

Retrieves information about the access overload class (ACCOLC)

Parameters

pACCOLC[OUT]	• ACCOLC : Valid range is 0 to 15

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.19.5.2 ULONG GetANAAAAuthenticationStatus (ULONG * *pStatus*)

AN-AAA authentication status of the device.

Parameters

pStatus[OUT]	• Status of last AN-AAA authentication attempt – 0 - Failure – 1 - Success – 2 - Not Requested

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.19.5.3 ULONG GetCDMANetworkParameters (BYTE * *pSCI*, BYTE * *pSCM*, BYTE * *pRegHomeSID*, BYTE * *pRegForeignSID*, BYTE * *pRegForeignNID*, BYTE * *pForceRev0*, BYTE * *pCustomSCP*, ULONG * *pProtocol*, ULONG * *pBroadcast*, ULONG * *pApplication*, ULONG * *pRoaming*)

Gets the current CDMA network parameters

Parameters

pSCI[OUT]	• Slot cycle index – 0xFF-Unknown
pSCM[OUT]	• Station class mark – 0xFF-Unknown
pRegHomeSID[OUT]	• Register on home SID – 0 - Disabled – 1 - Enabled – 0xFF - Unknown
pRegForeignSID[OUT]	• Register on foreign SID – 0 - Disabled – 1 - Enabled – 0xFF - Unknown

pRegForeignNID[OUT]	• Register on foreign NID – 0 - Disabled – 1 - Enabled – 0xFF - Unknown
pForceRev0[OUT]	• Force CDMA 1x-EV-DO Rev. 0 mode – 0 - Disabled – 1 - Enabled – 0xFF - Unknown
pCustomSCP[OUT]	• Use a custom config for CDMA 1x-EV-DO SCP – 0 - Disabled – 1 - Enabled – 0xFF - Unknown
pProtocol[OUT]	• Protocol mask for custom SCP config – 0x00000001 - Subtype 2 Physical Layer – 0x00000002 - Enhanced CCMAC – 0x00000004 - Enhanced ACMAC – 0x00000008 - Enhanced FTCMAC – 0x00000010 - Subtype 3 RTCMAC – 0x00000020 - Subsystem 1 RTCMAC – 0x00000040 - Enhanced Idle – 0x00000080 - Generic Multimode Capable Disc Port – 0xFFFFFFFF - Unknown
pBroadcast[OUT]	• Broadcast mask for custom SCP config – 0x00000001 - Generic broadcast enabled – 0xFFFFFFFF - Unknown
pApplication[OUT]	• Application mask for custom SCP config – 0x00000001 - SN Multiflow Packet Application – 0x00000002 - SN Enhanced Multiflow Packet Application – 0xFFFFFFFF - Unknown
pRoaming[OUT]	• Roaming preference – 0 - Automatic – 1 - Home Only – 2 - Affiliated Roaming Only – 3 - Home and Affiliated Roaming – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 5 seconds

9.19.5.4 ULONG GetHomeNetwork (WORD * *pMCC,* WORD * *pMNC,* BYTE *nameSize,* CHAR * *pName,* WORD * *pSID,* WORD * *pNID*)

Retrieves information about the home network of the device. For 3GPP2 home network information use GetHomeNetwork3GPP2.

Parameters

pMCC[OUT]	• Mobile country code (UMTS only).
pMNC[OUT]	• Mobile network code (UMTS only).
nameSize	• Maximum number of characters (including NULL terminator) that 8 network name array can contain (UMTS only).
pName[OUT]	• Network name or description represented as a NULL terminated string (empty string returned when unknown) (UMTS only).
pSID[OUT]	• Home network system ID – 0xFFFF - Unknown. – Only applies to cdma2000
pNID[OUT]	• Home network ID – 0xFFFF - Unknown. – Only applies to cdma2000

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.5 ULONG GetHomeNetwork3GPP2 (WORD * *pMCC,* WORD * *pMNC,* BYTE *nameSize,* CHAR * *pName,* WORD * *pSID,* WORD * *pNID,* WORD * *pNw2MCC,* WORD * *pNw2MNC,* BYTE * *pNw2DescDisp,* BYTE * *pNw2DescEnc,* BYTE * *pNw2DescLen,* BYTE * *pNw2Name*)

Retrieves information about the home network of the device. It will extract 3GPP2 Network Information also.

Parameters

pMCC[OUT]	• Mobile country code (UMTS only).
pMNC[OUT]	• Mobile network code (UMTS only).
nameSize	• Maximum number of characters (including NULL terminator) that 8 network name array can contain (UMTS only).
pName[OUT]	• Network name or description represented as a NULL terminated string (empty string returned when unknown) (UMTS only).
pSID[OUT]	• Home network system ID – 0xFFFF - Unknown. – Only applies to cdma2000
pNID[OUT]	• Home network ID – 0xFFFF - Unknown. – Only applies to cdma2000
pNw2MCC[OUT]	• Mobile country code (3GPP2 only). • Range : 0 to 999
pNw2MNC[OUT]	• Mobile network code (3GPP2 only). • Range : 0 to 999
pNw2DescDisp[-OUT]	• Network Name Display (3GPP2 only). -Valid Value – 0x00 - Do not display – 0x01 - Display – 0xFF - Unknown

pNw2DescDisp[-OUT]	• Encoding of the network description (3GPP2 only). • Valid Value – 0x00 - Octet, unspecified – 0x02 - 7-bit ASCII – 0x04 - Unicode – 0x09 - GSM 7-bit default
nw2DescLen[OUT]	• Network Description Length (3GPP2 only).
pNw2Name[OUT]	• Network Name (3GPP2 only).

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.6 ULONG GetNetworkPreference (ULONG * *pTechnologyPref,* ULONG * *pDuration,* ULONG * *pPersistentTechnologyPref*)

Returns the network registration preference. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSGetSysSelectionPref() for new firmware versions and new modules

Parameters

pTechnologyPref[OUT]	• Bitmask representing the radio technology preference set. • No bits set indicates to the device to automatically determine the technology to use • Values: – Bit 0 - Technology is 3GPP2 – Bit 1 - Technology is 3GPP • Any combination of the following may be returned: – Bit 2 - Analog - AMPS if 3GPP2, GSM if 3GPP – Bit 3 - Digital - CDMA if 3GPP2, WCDMA if 3GPP – Bit 4 - HDR – Bit 5 - LTE – Bits 6 to 15 - Reserved

pDuration[OUT]	• Duration of active preference – 0 - Permanent – 1 - Power cycle – 2 - Until the end of the next call or a power cycle – 3 - Until the end of the next call, a specified time, or a power cycle – 4 to 6 - Until the end of the next call
pPersistent-TechnologyPref[-OUT]	• Bit field representing persistent radio technology preference – Same representation as the pTechnologyPref parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.7 ULONG GetRFInfo (BYTE * *pInstanceSize,* struct RFBandInfoElements * *pRFBandInfo*)

Sets the RFInfoList

Parameters

pInstanceSize[IN/OUT]	• Upon input, maximum number of elements that the RF info instances array can contain. • Upon successful output, actual number of elements in RF info instances array.
pInstances[OUT]	• RF info instances array – See RFBandInfoElements for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.8 ULONG GetServingNetwork (ULONG * *pRegistrationState*, ULONG * *pCSDomain*, ULONG * *pPSDomain*, ULONG * *pRAN*, BYTE * *pRadioIfacesSize*, BYTE * *pRadioIfaces*, ULONG * *pRoaming*, WORD * *pMCC*, WORD * *pMNC*, BYTE *nameSize*, CHAR * *pName*)

Provides information about the system that provides service to the device. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSNasGetSysInfo() for new firmware versions and new modules

Parameters

pRegistrationState[OUT]	• Registration state: – 0 - Not registered – 1 - Registered – 2 - Searching/Not Registered – 3 - Registration Denied – 4 - Unknown
pCSDomain[OUT]	• Circuit switch domain status: – 0 - Unknown/Not Applicable – 1 - Attached – 2 - Detached
pPSDomain[OUT]	• Packet switch domain status – 0 - Unknown/Not Applicable – 1 - Attached – 2 - Detached
pRAN[OUT]	• Type of radio access network on which mobile is registered: – 0 - Unknown – 1 - cdma2000 network – 2 - UMTS network
pRadioIfacesSize[IN/OUT]	• Upon input, maximum number of elements that the radio interface array contain. • Upon successful output, actual number of elements in the radio interface array.
pRadioIfaces[OUT]	• An array of Radio Interface Technology – See qaGobiApiTableRadioInterfaces.h for the Radio Interface Technologies
pRoaming[OUT]	• Roaming indicator
pMCC[OUT]	• Mobile country code
pMNC[OUT]	• Mobile network code

nameSize	• Maximum number of characters (including NULL terminator) that network name array can contain; applicable only for UMTS networks
pName[OUT]	• Network name or description represented as a NULL terminated string; empty string is returned when unknown; applicable only for UMTS networks

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.9 ULONG GetServingNetworkCapabilities (BYTE * *pDataCapsSize,* BYTE * *pDataCaps*)

Returns information regarding the data capabilities of the system that currently provides service to the device.

Parameters

pDataCapsSize[IN/OUT]	• Upon input, the maximum number of elements the data capabilities array can contain. • Upon output, the actual number of elements in the data capabilities array.
pDataCaps[OUT]	• Data capabilities array of unsigned long type – 1 - GPRS – 2 - EDGE – 3 - HSDPA – 4 - HSUPA – 5 - WCDMA – 6 - CDMA 1xRTT – 7 - CDMA 1xEV-DO Rev 0 – 8 - CDMA 1xEV-DO Rev. A – 9 - GSM – 10 - EVDO Rev. B – 11 - LTE – 12 - HSDPA Plus – 13 - Dual Carrier HSDPA Plus

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.10 ULONG GetSignalStrengths (ULONG * *pArraySizes,* INT8 * *pSignalStrength,* ULONG * *pRadioInterface*)

Returns the available signal strengths (in dBm) as measured by the device in an array. The API also provides the corresponding radio radio interfaces in an array. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSNasGetSigInfo() for new firmware versions and new modules

Parameters

pArraySizes[IN/-OUT]	• Upon input maximum number of elements that each array can contain. • Upon successful output actual number of elements in the array.
pSignal-Strength[OUT]	• Received signal strength array (in dBm)
pRadio-Interface[OUT]	• Radio interface technology array of the signal being measured – See qaGobiApiTableRadioInterfaces.h for Radio Interface info

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.11 ULONG InitiateDomainAttach (ULONG *action*)

Initiates a domain attach/detach of the device. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSSetSysSelectionPref() for new firmware versions and new modules

Parameters

action[IN]	• Domain action to attempt 1 - Attach 2 - Detach

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 seconds

9.19.5.12 ULONG InitiateNetworkRegistration (ULONG *regType*, WORD *mcc*, WORD *mnc*, ULONG *rat*)

Initiates the network registration process. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSSetSysSelectionPref() and SLQSSetBandPreference() for new firmware versions and new modules

Parameters

regType	• Registration type – 1 - Automatic – 2 - Manual
mcc	• Mobile country code
mnc	• Mobile network code
rat	• Radio access technology – 4 - GSM – 5 - UMTS

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 seconds

9.19.5.13 ULONG PerformNetworkScan (BYTE * *pInstanceSize*, BYTE * *pInstances*)

Performs scan for available networks.

Parameters

pInstanceSize[IN/OUT]	• Upon input, maximum number of elements that the network info instance array can contain. • Upon successful output, the actual number of elements in the network info instance array.
pInstances[OUT]	• Network info instance array – See QmiNas3GppNetworkInfo

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 5 minutes

9.19.5.14 ULONG SetACCOLC (CHAR * *spc*, BYTE *accolc*)

Sets the access overload class (ACCOLC)

Parameters

spc[IN]	• service programming code NULL-terminated string of six digit
ACCOLC[IN]	• ACCOLC : Valid range is 0 to 15

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 5 seconds

9.19.5.15 ULONG SetCDMANetworkParameters (CHAR * *pSPC*, BYTE * *pForceRev0*, BYTE * *pCustomSCP*, ULONG * *pProtocol*, ULONG * *pBroadcast*, ULONG * *pApplication*, ULONG * *pRoaming*)

Sets the CDMA network parameters. Currently the modified settings will not be utilized until the device has been reset. For this reason, the recommended approach when using SetCDMANetworkParameters is for the application to perform the following steps:

1 - Call SetCDMANetworkParameters() 2 - Call SetPower(5) 3 - Call QCWWANDisconnect() 4 - Reconnect after the device power cycles

Parameters

pSPC[IN]	• Six digit service programming code (not necessary when only the roaming field is being set)
pForceRev0[IN]	• (Optional)Force CDMA 1x-EV-DO Rev. 0 mode – 0 - Disabled – 1 - Enabled Note: Enabled can only be specified if pCustomSCP state is set to Disabled
pCustomSCP[IN]	• (Optional)Use a custom config for CDMA 1x-EV-DO SCP – 0 - Disabled – 1 - Enabled Note: Enabled can only be specified if pForceRev0 is set to Disabled
pProtocol[IN]	• Protocol mask for custom SCP config – 0x00000001 - Subtype 2 Physical Layer – 0x00000002 - Enhanced CCMAC – 0x00000004 - Enhanced ACMAC – 0x00000008 - Enhanced FTCMAC – 0x00000010 - Subtype 3 RTCMAC – 0x00000020 - Subsystem 1 RTCMAC – 0x00000040 - Enhanced Idle – 0x00000080 - Generic Multimode Capable Disc Port – 0xFFFFFFFF - Unknown
pBroadcast[IN]	• Broadcast mask for custom SCP config – 0x00000001 - Generic broadcast enabled – 0xFFFFFFFF - Unknown
pApplication[IN]	• Application mask for custom SCP config – 0x00000001 - SN Multiflow Packet Application – 0x00000002 - SN Enhanced Multiflow Packet Application – 0xFFFFFFFF - Unknown
pRoaming[IN]	• Roaming preference – 0 - Automatic – 1 - Home Only – 2 - Affiliated Roaming Only – 3 - Home and Affiliated Roaming – 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 5 seconds

9.19.5.16 ULONG SetNetworkPreference (ULONG *technologyPref,* ULONG *duration*)

Sets the network registration preference. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSSetSysSelectionPref() for new firmware versions and new modules

Parameters

technologyPref[IN]	• 2 Byte Bitmask representing radio technology preference – No bits set indicates device to automatically determine the technology to use. – Type of technology * Bit 0 - Technology is 3GPP2 * Bit 1 - Technology is 3GPP – Technology-specific protocol bitmask * Bit 2 - Analog · AMPS if 3GPP2, GSM if 3GPP * Bit 3 - Digital · CDMA if 3GPP2, WCDMA if 3GPP * Bit 4 - HDR * Bit 5 - LTE * All other bits are reserved.
duration[IN]	• Duration of active preference – 0 - Persistent – 1 - Power cycle

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.17 ULONG SLQSConfigSigInfo (sigInfo * *pSigInfo*)

Sets the signal reporting thresholds. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use SLQSNasConfigSigInfo2() instead for new firmware versions and new modules.

Parameters

pSigInfo[IN]	• See sigInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.19.5.18 ULONG SLQSGetErrorRate (GetErrRateResp * *pGetErrRateResp*)

This API retrieves current error rate information

Parameters

pGetErrRate-Resp[OUT]	• See GetErrRateResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.19.5.19 ULONG SLQSGetNetworkTime (GetNetworkTimeResp * *pGetNetworkTimeResp*)

This API retrieves the last known network time information from the UE.

Parameters

pGetNetwork-TimeResp[OUT]	• See GetNetworkTimeResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.19.5.20 ULONG SLQSGetOperatorNameData (nasOperatorNameResp * *pOperatorNameData*)

Get the operator name data from the network. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSGetPLMNName() for new firmware versions and new modules

Parameters

pOperatorNameData[OUT]	• See nasOperatorNameResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 10 seconds

9.19.5.21 ULONG SLQSGetPLMNName (nasPLMNNameReq * *pPLMNNameReq,* nasPLMNNameResp * *pPLMNNameResp*)

Get the operator name data from the network.

Parameters

pPLMNNameReq[IN]	• See nasPLMNNameReq for more information
pPLMNNameResp[OUT]	• See nasPLMNNameResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 10 seconds

9.19.5.22 ULONG SLQSGetServingSystem (qaQmiServingSystemParam * *pServingSystem*)

Provides information about the system that provides service to the device. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSNasGetSysInfo() for new firmware versions and new modules. Also report available radio interface technology. If there are more than one radio interface, please choose the right interface(usually the first pair).

- See SLQSSetSysSelectionPref

Parameters

pServing-System[OUT]	• serving system parameters obtained from the system

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

Note

Timeout: 2 seconds

9.19.5.23 ULONG SLQSGetSignalStrength (struct slqsSignalStrengthInfo * *pSignalInfo*)

Queries the current signal strength as measured by the device. This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSNasGetSigInfo() for new firmware versions and new modules

Parameters

pSignalInfo[IN/-OUT]	• See slqsSignalStrengthInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.24 ULONG SLQSGetSysSelectionPref (sysSelectPrefInfo * *pSysSelectPrefInfo*)

Queries the different system selection preferences of the device.

Parameters

pSysSelectPrefInfo[OUT]	• See sysSelectPrefInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.25 ULONG SLQSGetSysSelectionPrefExt (sysSelectPrefExtInfo * *pSysSelectPrefExtInfo*)

Queries the different system selection preferences of the device.

Parameters

pSysSelectPrefExtInfo[OUT]	• See sysSelectPrefExtInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.26 ULONG SLQSInitiateNetworkRegistration (nasInitNetworkReg * *pNasInitNetRegistrationReg*)

Initiates the network registration process.This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use SLQSSetSysSelectionPrefExt() instead for new firmware versions and new modules.

Parameters

pNasInitNetRegistrationReq[IN]	• Pointer to structure nasInitNetworkReq – See nasInitNetworkReg for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 seconds

9.19.5.27 ULONG SLQSNasConfigSigInfo2 (setSignalStrengthInfo * *pSetSignalStrengthInfo*)

Sets the signal strength reporting thresholds

Parameters

pSetSignalStrengthInfo[IN]	• See setSignalStrengthInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds
Mixture of threshold and delta values can be provided in the request. But for each type and RAT,only one of threshold list or delta value is to be provided.

9.19.5.28 ULONG SLQSNasGet3GPP2Subscription (nasGet3GPP2SubscriptionInfoReq * *pGet3GPP2SubsInfoReq*, nasGet3GPP2SubscriptionInfoResp * *pGet3GPP2SubsInfoResp*)

This API retrieves 3GPP2 subscription-related information.

Parameters

pGet3GPP2SubsInfoReq[IN]	• See nasGet3GPP2SubscriptionInfoReq for more information
pGet3GPP2SubsInfoResp[OUT]	• See nasGet3GPP2SubscriptionInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds
This command retrieves 3GPP2 subscription-related information. The QMI_ERR_INTERNAL error is returned when no information can be retrieved from the modem.

9.19.5.29 ULONG SLQSNasGetCellLocationInfo (nasCellLocationInfoResp * *pNasCellLocationInfoResp*)

This API retrieves cell location-related information

Parameters

pNasCell-LocationInfo-Resp[OUT]	• See nasCellLocationInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
This API retrieves cell location-related information, depending on current serving system.

9.19.5.30 ULONG SLQSNASGeteDRXParams (nasGeteDRXParamsResp * *pNasGeteDRXParamsResp*)

This API Retrieves the eDRX (extended discontinuous reception) parameters for the device.

Parameters

pNasGeteDRX-ParamsResp[IN]	• See nasGeteDRXParamsResp for more information.

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

Note

Timeout: 5 seconds

9.19.5.31 ULONG SLQSNASGeteDRXParamsExt (nasGeteDRXParamsReq * *pNasGeteDRXParamsReq*, nasGeteDRXParamsResp * *pNasGeteDRXParamsResp*)

This API Retrieves the eDRX (extended discontinuous reception) parameters for the device.

Parameters

pNasGeteDRX-ParamsResp[IN]	• See nasGeteDRXParamsResp for more information.

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

Note

Timeout: 5 seconds

9.19.5.32 ULONG SLQSNASGetForbiddenNetworks (nasGetForbiddenNetworksResp * *pNasGetForbiddenNetworksResp*)

This API queries the list of forbidden networks from the device.

Parameters

pNasGet-Forbidden-NetworksResp[I-N]	• See nasGetForbiddenNetworksResp for more information.

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

Note

Timeout: 5 seconds

9.19.5.33 ULONG SLQSNasGetHDRColorCode (nasGetHDRColorCodeResp * *pGetHDRColorCodeResp*)

This API retrieves the current HDR color code value.

Parameters

pGetHDRColor-CodeResp[OUT]	• See nasGetHDRColorCodeResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.34 ULONG SLQSNASGetLTECPHYCaInfo (nasGetLTECphyCa * *pLTECPhyCa*)

This API Get LTE CPHY Carrier Info

Parameters

pLTECPhyCa[IN]	• See nasGetLTECphyCa for more information.

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

9.19.5.35 ULONG SLQSNasGetRFInfo (NasGetRFInfoResp * *pGetRFInfoResp*)

Gets radio band/channel information regarding the system currently providing service.

Parameters

pGetRFInfoResp[IN/OUT]	• See NasGetRFInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.36 ULONG SLQSNasGetSigInfo (nasGetSigInfoResp * *pGetSigInfoResp*)

This API queries information regarding the signal strength.

Parameters

pGetSigInfo-Resp[OUT]	• See nasGetSigInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
This command queries the signal strength information for currently active RATs. Information is reported only if the corresponding RATs have signal strength values to be reported. If no signal strength information is available for any RAT, the response message contains only the mandatory response message

9.19.5.37 ULONG SLQSNasGetSysInfo (nasGetSysInfoResp * *pGetSysInfoResp*)

Provides the system information. This API is preferred when trying to get the service status info and serving system info. The API SLQSGetServingSystem() reports similar NAS information, but it is deprecated. Please refer to the header description of API SLQSGetServingSystem() for more information.

Parameters

pGetSysInfo-Resp[OUT]	• See nasGetSysInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
This API queries current serving system information, including registration information and system property. The registration information for all RATs specified in the mode capability setting are included regardless of registration status. The RAT-specific system property are included only for RATs that are specified in the mode capability setting and which are not in either No Service or Power Save modes.

9.19.5.38 ULONG SLQSNasGetTxRxInfo (nasGetTxRxInfoReq * *pGetTxRxInfoReq,* nasGetTxRxInfoResp * *pGetTxRxInfoResp*)

This API retrieves the detailed Tx/Rx information.

Parameters

pGetTxRxInfo-Req[IN]	• See nasGetTxRxInfoReq for more information
pGetTxRxInfo-Resp[OUT]	• See nasGetTxRxInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
This command retrieves Tx/Rx information for a radio interface. The Rx chain are included in the response message only if they are enabled.

9.19.5.39 ULONG SLQSNasIndicationRegister (BYTE *systemSelectionInd,* BYTE *DDTMInd,* BYTE *servingSystemInd*)

Register/De-register from NAS (Network access service) broadcast indications. Some callbacks would not be invoked if the indications are not registered. The details are provided in the parameter description.

Parameters

system-SelectionInd[IN]	• system selection preference indication registration. The following callbacks would not be invoked if the indication is disabled. tFNRoamingIndicator tFNDataCapabilities and tFNServingSystem – 0x00 - for disable – 0x01 - for enable – 0xFF - No change - Specifying this parameter indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device
DDTMInd[IN]	• DDTM (Data Dedicated Transmission Mode) indication registration. – 0x00 - for disable – 0x01 - for enable – 0xFF - No change - Specifying this parameter indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device
servingSystem-Ind[IN]	• Serving system indication registration. The following callbacks would not be invoked if the indication is disabled. tFNBandPreference – 0x00 - for disable – 0x01 - for enable – 0xFF - No change - Specifying this parameter indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

Note

Timeout: 2 seconds

9.19.5.40 ULONG SLQSNasIndicationRegisterExt (nasIndicationRegisterReq * *pIndicationRegisterReq*)

This API Registers/De-registers for different NAS (Network access service) indications.

Parameters

pIndication-RegisterReq[IN]	• See nasIndicationRegisterReq for more information

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

Note

Timeout: 2 seconds
This API is used by a control point to register/deregister for different QMI_NAS indications. The control point's registration state variables, controlling registration for indications, are modified to reflect the settings indicated in the parameters that are present in the request message. At least one optional parameter must be present in the request.

9.19.5.41 ULONG SLQSNasIndicationRegisterLTECphyCa (BYTE * *bStatus*)

This API Registers/De-registers for NAS CPHY Carrier Info.

Parameters

bStatus[IN]	• Values – 0 - De-register. – 1 - Register.

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

9.19.5.42 ULONG SLQSNASSeteDRXParams (nasSeteDRXParamsReq * *pNasSeteDRXParamsReq*)

This API sets the eDRX (extended discontinuous reception) parameters for the device.

Parameters

pNasSeteDRX-ParamsReq[IN]	• See nasSeteDRXParamsReq for more information.

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

Note

Timeout: 5 seconds

9.19.5.43 ULONG SLQSNASSwiGetChannelLock (nasSwiGetChannelLockResp * *pNasSwiGetChannelLockResp*)

This API queries the channel or cell which the UE is locked into.

Parameters

pNasSwiGet-ChannelLock[O-UT]	• See nasSwiGetChannelLockResp for more information.

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

9.19.5.44 ULONG SLQSNasSwiIndicationRegister (NasSwiIndReg * *pIndRegReq*)

sets the registration state for different QMI_NAS SWI indications

Parameters

pIndRegReq[IN]	• See NasSwiIndReg for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.45 ULONG SLQSNasSwiModemStatus (swiModemStatusResp * *pModemStatusResp*)

This API requests the device to return the current status of modem.

Parameters

pModemStatusResp[OUT]	• See swiModemStatusResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.46 ULONG SLQSNASSwiSetChannelLock (nasSwiSetChannelLockReq * *pNasSwiSetChannelLockReq*)

This API allows the host to lock the UE to a specific channel or cell.

Parameters

pNasSwiSetChannelLockReq[IN]	• See nasSwiSetChannelLockReq for more information.

Returns

eQCWWAN_ERR_sNONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

Note

The settings are persistent across reboots.

9.19.5.47 ULONG SLQSPerformNetworkScan (slqsNetworkScanInfo * *pNetworkInfo*)

Performs scan for available networks and scans for RAT info as well.

Parameters

pNetworkInfo[IN/OUT]	• See slqsNetworkScanInfo for more information • Valid pointers to the following structure members are mandatory – pNetworkInfoInstances – pNetworkInfo

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 5 minutes

9.19.5.48 ULONG SLQSPerformNetworkScanPCI (slqsNetworkScanInfoReq * *pScanInfoReq,* slqsNetworkScanInfo * *pNetworkInfo*)

Performs scan for available networks and scans for LTE RAT info(specific Network or Scan Type).

Parameters

pScanInfoReq[IN/OUT]	• See slqsNetworkScanInfoReq for more information
pNetworkInfo[IN/OUT]	• See slqsNetworkScanInfo for more information • Valid pointers to the following structure members are mandatory – pNetworkInfoInstances – pNetworkInfo

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Device Supported: MC75xx, EM75xx and WP76xx.
Timeout: 300 minutes

9.19.5.49 ULONG SLQSSetBandPreference (ULONGLONG *bandpreference*)

Provides information about the band preference.

Parameters

bandpreference[-IN]	• Bit mask representing the band preference to be set. • Bit position meanings: – 0 - BC0_A - Band Class 0, A-System – 1 - BC0_B - Band Class 0, B-System, Band Class 0 AB , GSM 850 Band – 2 - BC1 - Band Class 1, all blocks – 3 - BC2 - Band Class 2 place holder – 4 - BC3 - Band Class 3, A-System – 5 - BC4 - Band Class 4, all blocks – 6 - BC5 - Band Class 5, all blocks – 7 - GSM_DCS_1800 - GSM DCS band – 8 - GSM_EGSM_900 - GSM Extended GSM (E-GSM) band – 9 - GSM_PGSM_900 - GSM Primary GSM (P-GSM) band – 10 - BC6 - Band Class 6 – 11 - BC7 - Band Class 7 – 12 - BC8 - Band Class 8 – 13 - BC9 - Band Class 9 – 14 - BC10 - Band Class 10 – 15 - BC11 - Band Class 11 – 16 - GSM_450 - GSM 450 band – 17 - GSM_480 - GSM 480 band – 18 - GSM_750 - GSM 750 band – 19 - GSM_850 - GSM 850 band – 20 - GSM_RGSM_900 - GSM Railways GSM Band – 21 - GSM_PCS_1900 - GSM PCS band – 22 - WCDMA_I_IMT_2000 - WCDMA EUROPE JAPAN and CHINA IMT 2100 band – 23 - WCDMA_II_PCS_1900 - WCDMA US PCS 1900 band – 24 - WCDMA_III_1700 - WCDMA EUROPE and CHINA DCS 1800 band – 25 - WCDMA_IV_1700 - WCDMA US 1700 band – 26 - WCDMA_V_850 - WCDMA US 850 band – 27 - WCDMA_VI_800 - WCDMA JAPAN 800 band – 28 - BC12 - Band Class 12 – 29 - BC14 - Band Class 14 – 30 - RESERVED_2 - Reserved 2 – 31 - BC15 - Band Class 15 – 32 - 47 - Reserved – 48 - WCDMA_VII_2600 - WCDMA EUROPE 2600 band – 49 - WCDMA_VIII_900 - WCDMA EUROPE and JAPAN 900 band – 50 - WCDMA_IX_1700 - WCDMA JAPAN 1700 band – 51 to 55 - Reserved – 56 - BBC16 - Band Class 16 – 57 - BC17 - Band Class 17 – 58 - BC18 - Band Class 18 – 59 - BC19 - Band Class 19 – 60 to 64 - Reserved

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise.

See Also

See qmerrno.h for eQCWWAN_xxx error values.

Note

Timeout: 2 seconds

9.19.5.50 ULONG SLQSSetSysSelectionPref (sysSelectPrefParams * *pSysSelectPrefParams*)

Sets the different system selection preferences of the device.

Parameters

pSysSelectPrefParams[IN]	• See sysSelectPrefParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.51 ULONG SLQSSetSysSelectionPrefExt (sysSelectPrefParamsExt * *pSysSelectPrefParamsExt*)

Sets the different system selection preferences of the device.

Parameters

pSysSelectPrefParamsExt[IN]	• See sysSelectPrefParamsExt for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.19.5.52 ULONG SLQSSwiGetHDRPersonality (HDRPersonalityResp * *pHDRPersonalityResp*)

This API retrieves HDR Personality related information

Parameters

pHDR-Personality-Resp[OUT]	• See HDRPersonalityResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 5 seconds

9.19.5.53 ULONG SLQSSwiGetHDRProtSubtype (HDRProtSubtypResp * *pHDRProtSubtypResp*)

This API retrieves HDR Prototype Subtype related information

Parameters

pHDRProt-SubtypResp[OU-T]	• See HDRProtSubtypResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 5 seconds

9.19.5.54 ULONG SLQSSwiGetHRPDStats (GetHRPDStatsResp * *pGetHRPDStatsResp*)

This API retrieves currently acquired HRPD system statistics

Parameters

pGetHRPD-StatsResp[OUT]	• See GetHRPDStatsResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.19.5.55 ULONG SLQSSwiGetLteCQI (LteCQIParm * *pLteCQIResp*)

This API Fetch CQI parameters for LTE data session

Parameters

pLteCQIParm[OUT]	• See LteCQIParm for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.19.5.56 ULONG SLQSSwiGetLteSccRxInfo (LteSccRxInfoResp * *pLteSccRxInfoResp*)

This API retrieves the LTE Secondary carrier Rx signal level information.

Parameters

pGetLteSccRxInforesp[OUT]	• See GetLteSccRxInforesp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.19.5.57 ULONG SLQSSwiNetworkDebug (NetworkDebugResp * *pNetworkDebugResp*)

This API retrieves device and network status details

Parameters

pNetworkDebug-Resp[OUT]	• See NetworkDebugResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.19.5.58 ULONG SLQSSwiPSDetach (PSDetachReq * *pPSDetachReq*)

This API detaches PS connection.

Parameters

pPSDetachReq[-IN]	• See PSDetachReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 5 seconds

9.20 qaGobiApiOmadm.h File Reference

Open Mobile Alliance Device Management Service API function prototypes.

Functions

- ULONG OMADMStartSession (ULONG sessionType)
- ULONG OMADMCancelSession ()

- ULONG OMADMGetSessionInfo (ULONG *pSessionState, ULONG *pSessionType, ULONG *pFailureReason, BYTE *pRetryCount, WORD *pSessionPause, WORD *pTimeRemaining)
- ULONG OMADMGetPendingNIA (ULONG *pSessionType, USHORT *pSessionID)

9.20.1 Detailed Description

Open Mobile Alliance Device Management Service API function prototypes.

9.20.2 Function Documentation

9.20.2.1 ULONG OMADMCancelSession ( )

Cancels an ongoing OMA-DM session.

Parameters

None	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.20.2.2 ULONG OMADMGetPendingNIA (ULONG * *pSessionType,* USHORT * *pSessionID*)

Returns information about the pending network-initiated alert

Parameters

SessionType[OUT]	• Session Type – 0x04 - Network-initiated PRL update – 0x05 - Network-initiated device configure
SessionID[OUT]	• Session Id – Unique session ID for NIA request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.20.2.3 ULONG OMADMGetSessionInfo (ULONG * *pSessionState,* ULONG * *pSessionType,* ULONG * *pFailureReason,* BYTE * *pRetryCount,* WORD * *pSessionPause,* WORD * *pTimeRemaining*)

Returns information related to the current (or previous if no session is active) OMA-DM session.

Parameters

SessionState[OUT]	• Session state – 0x00 - Complete, information was updated – 0x01 - Complete, update information is unavailable – 0x02 - Failed – 0x03 - Retrying – 0x04 - Connecting – 0x05 - Connected – 0x06 - Authenticated – 0x07 - Mobile Directory Number (MDN) downloaded – 0x08 - Mobile Station Identifier (MSID) downloaded – 0x09 - PRL downloaded – 0x0A - Mobile IP (MIP) profile downloaded
sessionType[OUT]	• Session State – 0x00 - Client-initiated device configure – 0x01 - Client-initiated PRL update – 0x02 - Client-initiated hands-free activation – 0x03 - Device-initiated hands-free activation – 0x04 - Network-initiated PRL update – 0x05 - Network-initiated device configure
FailureReason[OUT]	• Session failure reason (when state indicates failure) – 0x00 - Unknown – 0x01 - Network is unavailable – 0x02 - Server is unavailable – 0x03 - Authentication failed – 0x04 - Maximum retry exceeded – 0x05 - Session is cancelled
RetryCount[OUT]	• Session retry count (when state indicates retrying)
SessionPause[OUT]	• Session pause timer (in seconds , when state indicates retrying)

Time-Remaining[OUT]	• Pause time remaining (in seconds , when state indicates retrying)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.20.2.4 ULONG OMADMStartSession (ULONG *sessionType*)

Starts an OMA-DM session.

Parameters

sessionType	• Session type – 0x00 - Client-initiated device configure – 0x01 - Client-initiated PRL update – 0x02 - Client-initiated hands-free activation

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.21 qaGobiApiPds.h File Reference

Position Determination Service API function prototypes.

Data Structures

- struct PDSPositionData
- struct GPSStateInfo
- struct PDSPosMethodStateReq

Macros

- #define DEFAULTBYTEVALUE 0xFF
- #define DEFAULTWORDVALUE 0xFFFF
- #define DEFAULTLONGVALUE 0xFFFFFFFF

Enumerations

- enum {
  eSetServiceAutomaticTrackingDisable =0,
  eSetServiceAutomaticTrackingEnable =1 }

Functions

- ULONG GetPDSState (ULONG *pEnabledStatus, ULONG *pTrackingStatus)
- ULONG SetPDSState (ULONG enable)
- ULONG StartPDSTrackingSessionExt (BYTE sessionControl, BYTE sessionType, BYTE sessionOperation, BYTE sessionServerOption, BYTE fixTimeout, ULONG fixInterval, ULONG fixCount, ULONG fixAccuracy)
- ULONG StopPDSTrackingSession ()
- ULONG PDSInjectTimeReference (ULONGLONG systemTime, USHORT systemDiscontinuities)
- ULONG GetPDSDefaults (ULONG *pOperation, BYTE *pTimeout, ULONG *pInterval, ULONG *pAccuracy)
- ULONG SetPDSDefaults (ULONG operation, BYTE timeout, ULONG interval, ULONG accuracy)
- ULONG GetXTRAAutomaticDownload (ULONG *pbEnabled, USHORT *pInterval)
- ULONG SetXTRAAutomaticDownload (ULONG bEnabled, USHORT interval)
- ULONG GetXTRANetwork (ULONG *pPreference)
- ULONG SetXTRANetwork (ULONG preference)
- ULONG GetXTRAValidity (USHORT *pGPSWeek, USHORT *pGPSWeekOffset, USHORT *pDuration)
- ULONG ForceXTRADownload ()
- ULONG GetServiceAutomaticTracking (ULONG *pbAuto)
- ULONG SetServiceAutomaticTracking (ULONG bAuto)
- ULONG GetPortAutomaticTracking (ULONG *pbAuto)
- ULONG SetPortAutomaticTracking (ULONG bAuto)
- ULONG ResetPDSData (ULONG *pGPSDataMask, ULONG *pCellDataMask)
- ULONG SLQSSetAGPSConfig (ULONG *pServerAddress, ULONG *pServerPort, BYTE *pServerURL, BYTE *pServerURLLength, BYTE *pNetworkMode)
- ULONG SLQSPDSInjectAbsoluteTimeReference (ULONGLONG timeMsec, ULONG timeUncMsec, BYTE timeBase, BYTE forceFlag)
- ULONG SLQSGetAGPSConfig (ULONG *pServerAddress, ULONG *pServerPort, BYTE *pServerURL, BYTE *pServerURLLength, BYTE *pNetworkMode)
- ULONG SLQSPDSInjectPositionData (struct PDSPositionData *pPositionData)
- ULONG SLQSPDSDeterminePosition ()
- ULONG SLQSGetGPSStateInfo (GPSStateInfo *pGPSStateInfo)
- ULONG SLQSSetPositionMethodState (PDSPosMethodStateReq *pPDSPosMethodStateReq)

9.21.1 Detailed Description

Position Determination Service API function prototypes.

9.21.2 Macro Definition Documentation

9.21.2.1 #define DEFAULTBYTEVALUE 0xFF

9.21.2.2 #define DEFAULTLONGVALUE 0xFFFFFFFF

9.21.2.3 #define DEFAULTWORDVALUE 0xFFFF

9.21.3 Enumeration Type Documentation

9.21.3.1 anonymous enum

Enumerator

eSetServiceAutomaticTrackingDisable

eSetServiceAutomaticTrackingEnable

9.21.4 Function Documentation

9.21.4.1 ULONG ForceXTRADownload ( )

Forces the XTRA database to be downloaded to the device.

Parameters

none	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.2 ULONG GetPDSDefaults (ULONG * *pOperation,* BYTE * *pTimeout,* ULONG * *pInterval,* ULONG * *pAccuracy*)

Returns the default tracking session configuration. The tracking session configuration is used when a tracking session is automatically started using SetServiceAutomaticTracking or due to the device detecting an application opening the NMEA port.

Parameters

pOperation[OUT]	• Current session operating mode – 0 - Standalone – 1 - MS based – 2 - MS assisted

pTimeout[OUT]	• Maximum amount of time (seconds) to work on each fix, maximum is 255
pInterval[OUT]	• Interval (seconds) between fix requests
pAccuracy[OUT]	• Preferred accuracy threshold (meters)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.3 ULONG GetPDSState (ULONG * *pEnabledStatus*, ULONG * *pTrackingStatus*)

Returns the current PDS state.

Parameters

pEnabled-Status[OUT]	• Current PDS state – 0 - disable – 1 - enable
pTracking-Status[OUT]	• Current PDS tracking session state • Values: – 0x00 - Unknown – 0x01 - Inactive – 0x02 - Active

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.21.4.4 ULONG GetPortAutomaticTracking (ULONG * *pbAuto*)

Returns the automatic tracking configuration for the NMEA COM port.

Parameters

pbAuto[OUT]	• Automatic tracking enabled for NMEA COM port – 0x00 - Disabled – 0x01 - Enabled

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.5 ULONG GetServiceAutomaticTracking (ULONG * *pbAuto*)

Returns the automatic tracking state for the service.

Parameters

pbAuto[OUT]	• Automatic tracking session started for service – 0x00 - Disabled – 0x01 - Enabled

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.6 ULONG GetXTRAAutomaticDownload (ULONG * *pbEnabled,* USHORT * *pInterval*)

Returns the XTRA automatic database download configuration.

Parameters

pbEnabled[OUT]	• Automatic XTRA download status – 0 - Disabled – 1 - Enabled
pInterval[OUT]	• Interval (hours) between XTRA downloads

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.7 ULONG GetXTRANetwork (ULONG * *pPreference*)

Returns the XTRA WWAN network preference. When automatic XTRA database downloading is enabled this preference determines which WWAN networks will be used to perform the XTRA database download.

Parameters

pPreference[OUT]	• XTRA WWAN network preference – 0x00 - None (any available network) – 0x01 - Home-only, only when on home systems – 0x02 - Roam-only, only when on non-home systems

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.8 ULONG GetXTRAValidity (USHORT * *pGPSWeek,* USHORT * *pGPSWeekOffset,* USHORT * *pDuration*)

Returns the XTRA database validity period. When automatic XTRA database downloading is enabled the validity period determines when the XTRA database will be updated through a new download.

Parameters

pGPSWeek[OUT]	• Starting GPS week of validity period
pGPSWeekOffset[OUT]	• Starting GPS week offset (minutes) of validity period
pDuration[OUT]	• Length of validity period (hours)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.9 ULONG PDSInjectTimeReference (ULONGLONG *systemTime,* USHORT *systemDiscontinuities*)

Injects a system time into the PDS engine.

Parameters

systemTime	• System time(milliseconds)
systemDiscontinuities	• Number of system time discontinuities

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.10 ULONG ResetPDSData (ULONG * *pGPSDataMask,* ULONG * *pCellDataMask*)

Resets the specified PDS data.

Parameters

pGPSDataMask[IN]	• Bitmask of GPS data to clear (optional) – 0x00000001 - EPH – 0x00000002 - ALM – 0x00000004 - POS – 0x00000008 - TIME – 0x00000010 - IONO – 0x00000020 - UTC – 0x00000040 - HEALTH – 0x00000080 - SVDIR – 0x00000100 - SVSTEER – 0x00000200 - SADATA – 0x00000400 - RTI – 0x00000800 - ALM_CORR – 0x00001000 - FREQ_BIAS_EST
pCellDataMask[IN]	• Bitmask of cell data to clear (optional) – 0x00000001 - POS – 0x00000002 - LATEST_GPS_POS – 0x00000004 - OTA_POS – 0x00000008 - EXT_REF_POS – 0x00000010 - TIMETAG – 0x00000020 - CELLID – 0x00000040 - CACHED_CELLID – 0x00000080 - LAST_SRV_CELL – 0x00000100 - CUR_SRV_CELL – 0x00000200 - NEIGHBOR_INFO

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.11 ULONG SetPDSDefaults (ULONG *operation*, BYTE *timeout*, ULONG *interval*, ULONG *accuracy*)

Sets the default tracking session configuration. The tracking session configuration is used when a tracking session is automatically started using SetServiceAutomaticTracking or due to the device detecting an application opening the NMEA port.

Parameters

operation	• Current session operating mode – 0 - Standalone – 1 - MS based – 2 - MS assisted
timeout	• Maximum amount of time (seconds) to work on each fix, maximum is 255
interval	• Interval (seconds) between fix requests
accuracy	• Preferred accuracy threshold (meters)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.12 ULONG SetPDSState (ULONG *enable*)

Sets the PDS state.

Parameters

enable[IN]	• Desired PDS state – Zero - disable – Non-Zero - enable

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Seconds

9.21.4.13 ULONG SetPortAutomaticTracking (ULONG *bAuto*)

Sets the automatic tracking configuration for the NMEA COM port.

Parameters

bAuto[IN]	• Enable automatic tracking for NMEA COM port – 0x00 - Disabled – 0x01 - Enabled

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.14 ULONG SetServiceAutomaticTracking (ULONG *bAuto*)

Sets the automatic tracking state for the service. Tracking session being started using the default session configuration. Auto-tracking continues to generate fixes indefinitely until requested to be disabled. In StartPDSTrackingSessionExt a tracking session get started using the specified session control method and input parameters. After completion of requested no. of position fixes or service times out to perform fix, tracking session ends and GPS service deactivates.

Parameters

bAuto[IN]	• Automatic tracking session started for service – 0x00 - Disabled – 0x01 - Enabled

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.15 ULONG SetXTRAAutomaticDownload (ULONG *bEnabled,* USHORT *interval*)

Sets the XTRA automatic database download configuration.

Parameters

bEnabled[IN]	• Automatic XTRA download status – 0 - Disabled – 1 - Enabled
interval[IN]	• Interval (hours) between XTRA downloads

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.16 ULONG SetXTRANetwork (ULONG *preference*)

Sets the XTRA WWAN network preference. When automatic XTRA database downloading is enabled this preference determines which WWAN networks will be used to perform the XTRA database download.

Parameters

preference[IN]	• XTRA WWAN network preference – 0x00 - None (any available network) – 0x01 - Home-only, only when on home systems – 0x02 - Roam-only, only when on non-home systems

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.17 ULONG SLQSGetAGPSConfig (ULONG * *pServerAddress*, ULONG * *pServerPort*, BYTE * *pServerURL*, BYTE * *pServerURLLength*, BYTE * *pNetworkMode*)

Gets the PDS AGPS (MS-based) configuration.

Parameters

pServerAddress[OUT]	• IPv4 address of AGPS server. "0" if not set
pServerPort[OUT]	• Port number of AGPS server. "0" if not set
pServerURL[OUT]	• URL of the AGPS server. "0" if not set
pServerURLLength[OUT]	• URL length of AGPS server. "0" if not set
pNetworkMode[IN]	• Network Mode of AGPS Server [optional - should be present in Multimode Systems] – 0x00 - UMTS – 0x01 - CDMA

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.18 ULONG SLQSGetGPSStateInfo (GPSStateInfo * *pGPSStateInfo*)

Queries the MSM GPS server for receiver state information

Parameters

pGPSStateInfo[OUT]	• contains the GPS State Info • See GPSStateInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Seconds

9.21.4.19 ULONG SLQSPDSDeterminePosition ( )

Requests the MSM GPS service to obtain the current position for manually controlled tracking sessions.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Seconds

9.21.4.20 ULONG SLQSPDSInjectAbsoluteTimeReference (ULONGLONG *timeMsec,* ULONG *timeUncMsec,* BYTE *timeBase,* BYTE *forceFlag*)

Injects a absolute time reference into the PDS engine.

Parameters

timeMsec[IN]	• Represents the number of milliseconds elapsed since either a GPS or UTC time base. If the time base is UTC, this value should NOT include leap seconds
timeUncMsec[IN]	• Time uncertainty in milliseconds
timeBase[IN]	• Time base – 0x00 - GPS (midnight, Jan 6, 1980) – 0x01 - UTC (midnight, Jan 1, 1970)
forceFlag[IN]	• Force acceptance of data

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.21 ULONG SLQSPDSInjectPositionData (struct PDSPositionData * *pPositionData*)

Injects position data into the PDS engine.

Parameters

pPositionData[IN]	• contains the position data to be injected to the PDS engine

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.22 ULONG SLQSSetAGPSConfig (ULONG * *pServerAddress*, ULONG * *pServerPort*, BYTE * *pServerURL*, BYTE * *pServerURLLength*, BYTE * *pNetworkMode*)

Sets the PDS AGPS (MS-based) configuration.

Parameters

pServerAddress[IN]	• IPv4 address of AGPS server [optional]
pServerPort[IN]	• Port number of AGPS server [optional - should be present when pServerAddress is present]
pServerURL[IN]	• URL of the AGPS server [optional]
pServerURLLength[IN]	• URL length of AGPS server [optional - should be present when pServerURL is present]
pNetworkMode[IN]	• Network Mode of AGPS Server [optional - should be present in Multimode Systems] – 0x00 - UMTS – 0x01 - CDMA

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.23 ULONG SLQSSetPositionMethodState (PDSPosMethodStateReq * *pPDSPosMethodStateReq*)

Sets the state of positioning methods for the device.

Parameters

pPDSPosMethodStateReq[IN]	• See PDSPosMethodStateReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Seconds

9.21.4.24 ULONG StartPDSTrackingSessionExt (BYTE *sessionControl,* BYTE *sessionType,* BYTE *sessionOperation,* BYTE *sessionServerOption,* BYTE *fixTimeout,* ULONG *fixInterval,* ULONG *fixCount,* ULONG *fixAccuracy*)

This function starts a PDS tracking session.

Parameters

sessionControl[IN]	• Control method: – 0x0 - Manual
sessionType[IN]	• Type: – 0x0 - New
sessionOperation[IN]	• Operating mode: – 0x00 - Standalone – 0x01 - MS-based
sessionServerOption[IN]	• Location server option: – 0x0 - Default
fixTimeout[IN]	• Maximum time to work on each fix (in seconds, max 255)
fixCount[IN]	• Count of position fix requests for this session (must be at least 1)
fixInterval[IN]	• interval between position fix requests (in seconds)

fixAccuracy[IN]	• Preferred accuracy threshold(in meters)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.21.4.25 ULONG StopPDSTrackingSession ( )

This function stops a PDS tracking session.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.22 qaGobiApiQos.h File Reference

Quality of Service API function prototypes.

Data Structures

- struct dataRate
- struct tokenBucket
- struct pktErrRate
- struct swiQosFlow
- struct IPv4Addr
- struct Tos
- struct IPv6Addr
- struct IPv6TrafCls
- struct Port
- struct swiQosFilter
- struct swiQosReq
- struct swiQosIds
- struct swiQosModifyReq
- struct swiQosGranted
- struct NWProfile
- struct sQosFlowStat
- struct sQosStat
- struct sApnExtraParams

Macros

- #define MAX_QOS_SPEC_PER_APN (10)
- #define MAX_QOS_FILTER_TLV 25

Functions

- ULONG SLQSQosReset (BYTE instance)
- ULONG SLQSQosReq (BYTE instance, swiQosReq *pQosReq, swiQosIds *pQosResp)
- ULONG SLQSQosRel (BYTE instance, swiQosIds *pQosIds)
- ULONG SLQSQosSuspend (BYTE instance, swiQosIds *pQosIds)
- ULONG SLQSQosResume (BYTE instance, swiQosIds *pQosIds)
- ULONG SLQSQosModify (BYTE instance, swiQosModifyReq *pReq)
- ULONG SLQSQosGetGranted (BYTE instance, ULONG id, swiQosGranted *pGranted)
- ULONG SLQSQosGetFlowStatus (BYTE instance, ULONG id, BYTE *pStatus)
- ULONG SLQSQosGetNetworkStatus (BYTE instance, BYTE *pStatus)
- ULONG SLQSQosGetNWProf (BYTE instance, BYTE *pSz, NWProfile *pProfile)
- ULONG SLQSQosSwiReadDataStats (BYTE instance, ULONG apnId, sQosStat *pQosStat)
- ULONG SLQSQosSwiReadApnExtraParams (BYTE instance, ULONG apnId, sApnExtraParams *pApnExtraParams)
- ULONG SetQosMuxID (BYTE instance)

9.22.1 Detailed Description

Quality of Service API function prototypes.

9.22.2 Macro Definition Documentation

9.22.2.1 #define MAX_QOS_FILTER_TLV 25

9.22.2.2 #define MAX_QOS_SPEC_PER_APN (10)

9.22.3 Function Documentation

9.22.3.1 ULONG SetQosMuxID (BYTE *instance*)

Bind MUX ID to Qos instance.

Parameters

in	*instance*	• QMI instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.22.3.2 ULONG SLQSQosGetFlowStatus (BYTE *instance*, ULONG *id*, BYTE * *pStatus*)

Get the status of a QoS flow.

Parameters

in	*instance*	• QMI instance
in	*id[IN]*	Qos identifier Index identifying the QoS flow that has been negotiated
out	*pStatus[OUT]*	Qos status Current QoS instance status: • 0x01 - QMI_QOS_STATUS_ACTIVATED • 0x02 - QMI_QOS_STATUS_SUSPENDED • 0x03 - QMI_QOS_STATUS_GONE

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

9.22.3.3 ULONG SLQSQosGetGranted (BYTE *instance*, ULONG *id*, swiQosGranted * *pGranted*)

Retrieve the QoS parameters that are in effect for the specified QoS 16 flow as a result of network negotiation

Parameters

in	*instance*	• QMI instance
in	*id[IN]*	• Qos identifier • Index identifying the QoS flow that has been negotiated
in	*pGranted[OUT]*	• Tx/Rx Qos granted flow • See swiQosGranted for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

9.22.3.4 ULONG SLQSQosGetNetworkStatus (BYTE *instance*, BYTE * *pStatus*)

Queries whether the device is currently on a network that supports QoS

Parameters

	instance[IN]	• QMI instance
out	*pStatus[OUT]*	Network QoS support status • 0 - No QoS support in network • 1 - Network supports QoS

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA

9.22.3.5 ULONG SLQSQosGetNWProf (BYTE *instance*, BYTE * *pSz*, NWProfile * *pProfile*)

Get network supported QoS profile information

Parameters

in	*instance*	• QMI instance
	in/out]	pSz Number of network supported QoS profiles for one technology
out	*pProfile*	Network supported QoS profiles

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

9.22.3.6 ULONG SLQSQosModify (BYTE *instance*, swiQosModifyReq * *pReq*)

Resume one or more existing QoS flows

Warning

NOT IMPLEMENTED

Parameters

in	*instance*	• QMI instance
	pReq[IN]	• See swiQosModifyReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

9.22.3.7 ULONG SLQSQosRel (BYTE *instance*, swiQosIds * *pQosIds*)

Release one or more existing QoS flows

Parameters

in	*instance*	• QMI instance
	pQosIds[IN]	• See swiQosIds for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

9.22.3.8 ULONG SLQSQosReq (BYTE *instance*, swiQosReq * *pQosReq*, swiQosIds * *pQosResp*)

Triggers QoS negotiation by providing QoS parameters

Parameters

instance[IN]	• QMI instance
pQoSReq[IN]	• See swiQosReq for more information
pQosResp[OUT]	• See swiQosIds for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS/CDMA
Device Supported: MC77XX
Timeout: 2 seconds
At least one pair of optional TLVs must be present; Tx QoS Flow Request and Tx QoS Filter Request TLVs must both be present if either one is present; Rx QoS Flow Request and Rx QoS Filter Request TLVs must both be present if either one is present

9.22.3.9 ULONG SLQSQosReset (BYTE *instance*)

Reset the QoS service state variables of the requesting control point

Parameters

in	*instance*	• QMI instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA, UMTS & LTE
Device Supported: MC7750
Timeout: 2 seconds

9.22.3.10 ULONG SLQSQosResume (BYTE *instance,* swiQosIds * *pQosIds*)

Resume one or more existing QoS flows

Parameters

in	*instance*	• QMI instance
	pQosIds[IN]	• See swiQosIds for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

9.22.3.11 ULONG SLQSQosSuspend (BYTE *instance*, swiQosIds * *pQosIds*)

Suspend one or more existing QoS flows

Parameters

in	*instance*	• QMI instance
	pQosIds[IN]	• See swiQosIds for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

9.22.3.12 ULONG SLQSQosSwiReadApnExtraParams (BYTE *instance*, ULONG *apnId*, sApnExtraParams * *pApnExtraParams*)

Queries extra APN parameters that are not reported by existing QCT QMI service

Parameters

in	*instance*	• QMI instance
in	*apnId*	• APN id
out	*pApnExtra-Params*	See sApnExtraParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.22.3.13 ULONG SLQSQosSwiReadDataStats (BYTE *instance*, ULONG *apnId*, sQosStat * *pQosStat*)

Get the current number of packets and bytes sent, dropped and received for each UL, DL bearer and a sum of them for UL and DL direction in the modem.

Parameters

in	*instance*	• QMI instance
in	*apnId*	• APN id
out	*pQosStat*	See sQosStat for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.23 qaGobiApiRms.h File Reference

Remote Management Service API function prototypes.

Functions

- ULONG GetSMSWake (ULONG *pEnabled, ULONG *pWakeMask)
- ULONG SetSMSWake (ULONG bEnable, ULONG wakeMask)

9.23.1 Detailed Description

Remote Management Service API function prototypes.

9.23.2 Function Documentation

9.23.2.1 ULONG GetSMSWake (ULONG * *pEnabled*, ULONG * *pWakeMask*)

Queries the state of the SMS wake functionality. When enabled SMS wake functionality results in incoming messages being searched for the configured mask. Upon detection of the mask the incoming message is deleted (i.e. not stored in memory) and the device attempts to wake the host (requires host platform support).

Parameters

pEnabled[OUT]	• SMS wake functionality enabled – 0 - Disabled – 1 - Enabled
pWakeMask[OUT]	• SMS wake mask to search for incoming messages (only relevant when enabled)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.23.2.2 ULONG SetSMSWake (ULONG *bEnable,* ULONG *wakeMask*)

Configures the SMS wake functionality. When enabled SMS wake functionality results in incoming messages being searched for the configured mask. Upon detection of the mask the incoming message is deleted (i.e. not stored in memory) and the device attempts to wake the host (requires host platform support).

Parameters

bEnable	• Enable SMS wake functionality – Zero - Disable – Non-Zero - Enable
wakeMask	• SMS wake mask to search for incoming messages (only relevant when enabling)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.24 qaGobiApiSar.h File Reference

Specific Absorption Rate API function prototypes.

Enumerations

- enum eQMISARRFState {
  QMI_SAR_RF_STATE_DEFAULT = 0,
  QMI_SAR_RF_STATE_1,
  QMI_SAR_RF_STATE_2,
  QMI_SAR_RF_STATE_3,
  QMI_SAR_RF_STATE_4,
  QMI_SAR_RF_STATE_5,
  QMI_SAR_RF_STATE_6,
  QMI_SAR_RF_STATE_7,
  QMI_SAR_RF_STATE_8 }

Functions

- ULONG SLQSGetRfSarState (ULONG *pSarRFState)
- ULONG SLQSSetRfSarState (ULONG RfSarState)

9.24.1 Detailed Description

Specific Absorption Rate API function prototypes.

9.24.2 Enumeration Type Documentation

9.24.2.1 enum eQMISARRFState

This enum contains the SAR RF States

Parameters

SAR	RF State • QMI_SAR_RF_STATE_DEFAULT = 0 • QMI_SAR_RF_STATE_1 • QMI_SAR_RF_STATE_2 • QMI_SAR_RF_STATE_3 • QMI_SAR_RF_STATE_4 • QMI_SAR_RF_STATE_5 • QMI_SAR_RF_STATE_6 • QMI_SAR_RF_STATE_7 • QMI_SAR_RF_STATE_8

Enumerator

QMI_SAR_RF_STATE_DEFAULT

QMI_SAR_RF_STATE_1

QMI_SAR_RF_STATE_2

QMI_SAR_RF_STATE_3

QMI_SAR_RF_STATE_4

QMI_SAR_RF_STATE_5

QMI_SAR_RF_STATE_6

QMI_SAR_RF_STATE_7

QMI_SAR_RF_STATE_8

9.24.3 Function Documentation

9.24.3.1 ULONG SLQSGetRfSarState (ULONG * *pSarRFState*)

Gets the specified RF SAR state.

Parameters

pSarRFState	• SAR RF State – QMI_SAR_RF_STATE_DEFAULT – QMI_SAR_RF_STATE_1 – QMI_SAR_RF_STATE_2 – QMI_SAR_RF_STATE_3 – QMI_SAR_RF_STATE_4 – QMI_SAR_RF_STATE_5 – QMI_SAR_RF_STATE_6 – QMI_SAR_RF_STATE_7 – QMI_SAR_RF_STATE_8

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.24.3.2 ULONG SLQSSetRfSarState (ULONG *RfSarState*)

Sets the specified RF SAR state.

Parameters

sar_rf_state	• SAR RF State – QMI_SAR_RF_STATE_DEFAULT – QMI_SAR_RF_STATE_1 – QMI_SAR_RF_STATE_2 – QMI_SAR_RF_STATE_3 – QMI_SAR_RF_STATE_4 – QMI_SAR_RF_STATE_5 – QMI_SAR_RF_STATE_6 – QMI_SAR_RF_STATE_7 – QMI_SAR_RF_STATE_8

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.25 qaGobiApiSms.h File Reference

Short Message Service API function prototypes.

Data Structures

- struct sms_DateTime
- struct sms_timestemp
- struct slqssendsmsparams_s
- struct BroadcastConfig
- struct _qaQmi3GPPBroadcastCfgInfo
- struct CDMABroadcastConfig
- struct _qaQmi3GPP2BroadcastCfgInfo
- struct cdmaMsgEncodingParams
- struct cdmaMsgDecodingParams
- struct cdmaMsgDecodingParamsExt
- struct wcdmaMsgEncodingParams
- struct wcdmaMsgDecodingParams
- struct wcdmaLongMsgDecodingParams
- struct _transLayerinfo
- struct _getTransLayerInfoResp
- struct _getTransNWRegInfoResp
- struct _getIndicationRegResp
- struct _setIndicationRegReq
- struct smsRouteEntry
- struct smsSetRoutesReq
- struct smsMsgprotocolResp
- struct smsMaxStorageSizeReq
- struct smsMaxStorageSizeResp
- struct messageWaitingInfoContent
- struct getMsgWaitingInfo
- struct slqssendasyncsmsparams_s

Macros

- #define CONFIG_LEN 0x05
- #define TIME_STAMP_BUF 0x08
- #define ABSOLUTE_VALIDITY 0x08
- #define TIME_DATE_BUF 0x09
- #define MAX_SMS_ROUTES 0x0A
- #define NUM_OF_SET 0xFF

- #define SMS_ASCII_STRING_SIZE 400
- #define MAXIMUM_SMS_MSG_LEN 160
- #define SMS_ASCII_STRING_ARRAY_SIZE SMS_ASCII_STRING_SIZE + 1
- #define SMS_MESSAGE_TIMESTEMP_SIZE 8
- #define MAX_SMSC_LENGTH 24
- #define SMS_DEFAULT_TIME_ZONE 0
- #define SMS_INVALID_TIME_STAMP_VALUE 0xff

Typedefs

- typedef struct _qaQmi3GPPBroadcastCfgInfo qaQmi3GPPBroadcastCfgInfo
- typedef struct _qaQmi3GPP2BroadcastCfgInfo qaQmi3GPP2BroadcastCfgInfo
- typedef struct _transLayerinfo transLayerInfo
- typedef struct _getTransLayerInfoResp getTransLayerInfoResp
- typedef struct _getTransNWRegInfoResp getTransNWRegInfoResp
- typedef struct _getIndicationRegResp getIndicationRegResp
- typedef struct _setIndicationRegReq setIndicationRegReq

Enumerations

- enum sEnumTimeStampenum {
  eTIMESTEMP_START = -1,
  eTIMESTEMP_YEAR = 0,
  eTIMESTEMP_MONTH = 1,
  eTIMESTEMP_DAY = 2,
  eTIMESTEMP_HOUR = 3,
  eTIMESTEMP_MINUTE = 4,
  eTIMESTEMP_SECOND = 5,
  eTIMESTEMP_TIMEZONE = 6,
  eTIMESTEMP_END = 7 }

Functions

- ULONG SLQSDeleteSMS (ULONG storageType, ULONG *pMessageIndex, ULONG *pMessageTag, BYTE *pMessageMode)
- ULONG SLQSGetSMS (ULONG storageType, ULONG messageIndex, ULONG *pMessageTag, ULONG *pMessageFormat, ULONG *pMessageSize, BYTE *pMessage, BYTE *pMessageMode)
- ULONG SendSMS (ULONG messageFormat, ULONG messageSize, BYTE *pMessage, ULONG *pMessageFailureCode, BYTE *pSmsOnIms)
- ULONG SLQSSendSMS (slqssendsmsparams_s *pSendSmsParams)
- ULONG GetSMSCAddress (BYTE addressSize, CHAR *pSMSCAddress, BYTE typeSize, CHAR *pSMSCType)
- ULONG SetSMSCAddress (CHAR *pSMSCAddress, CHAR *pSMSCType)
- ULONG SaveSMS (ULONG storageType, ULONG messageFormat, ULONG messageSize, BYTE *pMessage, ULONG *pMessageIndex)
- ULONG SLQSGetSMSList (ULONG storageType, ULONG *pRequestedTag, ULONG *pMessageListSize, BYTE *pMessageList, BYTE *pMessageMode)
- ULONG SLQSModifySMSStatus (ULONG storageType, ULONG messageIndex, ULONG messageTag, BYTE *pMessageMode)

- ULONG SLQSGetSmsBroadcastConfig (BYTE mode, qaQmi3GPPBroadcastCfgInfo *pBroadcastConfig, qaQmi3GPP2BroadcastCfgInfo *pCDMABroadcastConfig)
- ULONG SLQSSetSmsBroadcastConfig (BYTE mode, qaQmi3GPPBroadcastCfgInfo *pBroadcastConfig, qaQmi3GPP2BroadcastCfgInfo *pCDMABroadcastConfig)
- ULONG SLQSSetSmsBroadcastActivation (BYTE mode, BYTE broadcastActivate)
- ULONG SLQSCDMAEncodeMOTextMsg (struct cdmaMsgEncodingParams *pCdmaMsgEncodingParams)
- ULONG SLQSCDMADecodeMTTextMsg (struct cdmaMsgDecodingParams *pCdmaMsgDecodingParams)
- ULONG SLQSCDMADecodeMTTextMsgExt (struct cdmaMsgDecodingParamsExt *pCdmaMsgDecodingParamsExt)
- ULONG SLQSWCDMAEncodeMOTextMsg (struct wcdmaMsgEncodingParams *pWcdmaMsgEncodingParams)
- ULONG SLQSWCDMADecodeMTTextMsg (struct wcdmaMsgDecodingParams *pWcdmaMsgDecodingParams)
- ULONG SLQSWCDMADecodeLongTextMsg (struct wcdmaLongMsgDecodingParams *pWcdmaLongMsgDecodingParams)
- ULONG SLQSWCDMADecodeMTEncoding (BYTE *pMessage, USHORT MessageLen, BYTE *pEncoding)
- ULONG SLQSGetTransLayerInfo (getTransLayerInfoResp *pGetTransLayerInfoResp)
- ULONG SLQSGetTransNWRegInfo (getTransNWRegInfoResp *pGetTransNWRegInfoResp)
- ULONG SLQSGetIndicationRegister (getIndicationRegResp *pGetIndicationRegInfo)
- ULONG SLQSSetIndicationRegister (setIndicationRegReq *pSetIndicationRegReq)
- ULONG SLQSSmsSetRoutes (smsSetRoutesReq *pSetRoutesReq)
- ULONG SLQSSmsGetMessageProtocol (smsMsgprotocolResp *pMessageProtocol)
- ULONG SLQSSmsGetMaxStorageSize (smsMaxStorageSizeReq *pMaxStorageSizeReq, smsMaxStorageSizeResp *pMaxStorageSizeResp)
- ULONG SLQSGetMessageWaiting (getMsgWaitingInfo *pGetMsgWaitingInfoResp)
- ULONG SLQSSendAsyncSMS (slqssendasyncsmsparams_s *pSendSmsParams)
- ULONG SLQSSetSmsStorage (BYTE smsStorage)
- ULONG SLQSSwiGetSMSStorage (ULONG *pSmsStorage)
- ULONG SLQSSendLongSMS (ULONG messageFormat, ULONG messageSize, CHAR *pMessage, BYTE encodingScheme, ULONG *pMessageFailureCode, CHAR *pMobileNum, BYTE *pSmsOnIMS)

9.25.1 Detailed Description

Short Message Service API function prototypes.

9.25.2 Macro Definition Documentation

9.25.2.1 #define ABSOLUTE_VALIDITY 0x08

9.25.2.2 #define CONFIG_LEN 0x05

9.25.2.3 #define MAX_SMS_ROUTES 0x0A

9.25.2.4 #define MAX_SMSC_LENGTH 24

9.25.2.5 #define MAXIMUM_SMS_MSG_LEN 160

9.25.2.6 #define NUM_OF_SET 0xFF

9.25.2.7 #define SMS_ASCII_STRING_ARRAY_SIZE SMS_ASCII_STRING_SIZE + 1

9.25.2.8 #define SMS_ASCII_STRING_SIZE 400

9.25.2.9 #define SMS_DEFAULT_TIME_ZONE 0

9.25.2.10 #define SMS_INVALID_TIME_STAMP_VALUE 0xff

9.25.2.11 #define SMS_MESSAGE_TIMESTEMP_SIZE 8

9.25.2.12 #define TIME_DATE_BUF 0x09

9.25.2.13 #define TIME_STAMP_BUF 0x08

9.25.3 Typedef Documentation

9.25.3.1 typedef struct _getIndicationRegResp getIndicationRegResp

This structure contains Get Indication Register Response parameters

Parameters

pRegTrans-LayerInfoEvt	- • Optional 1 BYTE parameter indicating registration status of transport layer information events • Values: – 0x00 - Disabled – 0x01 - Enabled • function SLQSGetIndicationRegister() returns a default value 0xFF if this parameter is allocated memory in the structure and no response is received from the device.
pRegTransNW-RegInfoEvt	- • Optional 1 BYTEparameter indicating registration status of transport network registration information events • Values: – 0x00 - Disabled – 0x01 - Enabled • function SLQSGetIndicationRegister() returns a default value 0xFF if this parameter is allocated memory in the structure and no response is received from the device.
pRegCallStat-InfoEvt	- • Optional 1 BYTE parameter indicating registration status of call status information events • Values: – 0x00 - Disabled – 0x01 - Enabled • function SLQSGetIndicationRegister() returns a default value 0xFF if this parameter is allocated memory in the structure and no response is received from the device.

9.25.3.2 typedef struct _getTransLayerInfoResp getTransLayerInfoResp

This structure contains Get Transport Layer Info Response parameters

Parameters

pRegInd	- • Optional parameter indicating if transport layer is registered • Values: – 0x00 - Transport layer is not registered – 0x01 - Transport layer is registered • function SLQSGetTransLayerInfo() returns a default value 0xFF if no response is received from the device.
pTransLayerInfo	• Pointer to structure of transLayerInfo. – Optional parameter – See transLayerInfo for more information • function SLQSGetTransLayerInfo() returns a default value 0xFF for parameter values if no response is received from the device.

9.25.3.3 typedef struct _getTransNWRegInfoResp getTransNWRegInfoResp

This structure contains transport network registration info parameter

Parameters

pRegStatus	- • Optional 1 BYTE parameter indicating transport layer network registration status • Values: – 0x00 - No service – 0x01 - In progress – 0x02 - Failed – 0x03 - Limited Service – 0x04 - Full Service • function SLQSGetTransNWRegInfo() returns a default value 0xFF if no response is received from the device.

9.25.3.4 typedef struct _qaQmi3GPP2BroadcastCfgInfo qaQmi3GPP2BroadcastCfgInfo

This structure contains the 3GPP2 Broadcast Configuration Information parameters

Parameters

activated_ind	• Broadcast SMS – 0x00 - Deactivated – 0x01 - Activated
num_instances	• Number of sets (N) of parameters Following each set describes one entry in the broadcast configuration table. – serviceCategory – language – selected

broadcastConfig	• A CDMABroadcastConfig structure array. • Further defined by the structure CDMABroadcastConfig

9.25.3.5 typedef struct _qaQmi3GPPBroadcastCfgInfo qaQmi3GPPBroadcastCfgInfo

This structure contains the 3GPP Broadcast Configuration Information parameters

Parameters

activated_ind	• Broadcast SMS – 0x00 - Deactivated – 0x01 - Activated
num_instances	• Number of sets (N) of parameters Following each set describes one entry in the broadcast configuration table. – fromServiceId – toServiceId – selected
broadcastConfig	• A BroadcastConfig structure array. • Further defined by the structure BroadcastConfig

9.25.3.6 typedef struct _setIndicationRegReq setIndicationRegReq

This structure contains Indication Register request parameters

Parameters

pRegTrans-LayerInfoEvt	- • Optional 1 BYTE parameter indicating registration status of transport layer information events • Values: – 0x00 - Disabled – 0x01 - Enabled – NULL - No change - specifying NULL indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device
pRegTransNW-RegInfoEvt	- • Optional 1 BYTE parameter indicating registration status of transport network registration information events • Values: – 0x00 - Disabled – 0x01 - Enabled – NULL - No change - specifying NULL indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device

pRegCallStat-InfoEvt	- • Optional 1 BYTE parameter indicating registration status of call status information events • Values: – 0x00 - Disabled – 0x01 - Enabled – NULL - No change - specifying NULL indicates that the device will continue to use the existing setting (disable/enable) which has been previously set for the device

9.25.3.7 typedef struct _transLayerinfo transLayerInfo

This structure contains Transport Layer Information

Parameters

TransType	• Transport Type – 0x00 - IMS
TransCap	• Transport Capability • Values: – 0x00 - CDMA – 0x01 - GW

9.25.4 Enumeration Type Documentation

9.25.4.1 enum sEnumTimeStampenum

Enumerator

eTIMESTEMP_START

eTIMESTEMP_YEAR

eTIMESTEMP_MONTH

eTIMESTEMP_DAY

eTIMESTEMP_HOUR

eTIMESTEMP_MINUTE

eTIMESTEMP_SECOND

eTIMESTEMP_TIMEZONE

eTIMESTEMP_END

9.25.5 Function Documentation

9.25.5.1 ULONG GetSMSCAddress (BYTE *addressSize*, CHAR * *pSMSCAddress*, BYTE *typeSize*, CHAR * *pSMSCType*)

Gets the SMS center address.

Parameters

addressSize	• The maximum number of characters (including NULL terminator) that the SMS center address array can contain.
pSMSC-Address[0UT]	• The SMS center address represented as a NULL terminated string.
typeSize	• The maximum number of characters (including NULL terminator) that the SMS center address type array can contain.
pSMSCType[0U-T]	• The SMS center address type represented as a NULL terminated string.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 2 seconds

9.25.5.2 ULONG SaveSMS (ULONG *storageType*, ULONG *messageFormat*, ULONG *messageSize*, BYTE * *pMessage*, ULONG * *pMessageIndex*)

Saves an SMS message to device memory

Parameters

storageType[IN]	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
message-Format[IN]	• Message format – 0 - CDMA (IS-637B) – 1 - 5 (Reserved) – 6 - GSM/WCDMA PP
messageSize	• The length of the message contents in bytes
pMessage[IN]	• The message contents
pMessage-Index[OUT]	• The message index assigned by the device

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 10 seconds

9.25.5.3 ULONG SendSMS (ULONG *messageFormat*, ULONG *messageSize*, BYTE * *pMessage*, ULONG * *pMessageFailureCode*, BYTE * *pSmsOnIms*)

Sends an SMS message for immediate over-the-air transmission

Parameters

messageFormat[IN]	• Message format – 0 - CDMA (IS-637B) – 1 - 5 (Reserved) – 6 - GSM/WCDMA PP
messageSize[IN]	• The length of the message contents in bytes
pMessage[IN]	• The message contents in PDU format contains SMS header and payload message
pSmsOnIms[IN]	• (Optional) SMS on IMS • The message is to be sent on IMS. – 0x00 Message is not to be sent on IMS. – 0x01 Message is to be sent on IMS. – 0x02 to 0xFF Reserved.
pMessageFailureCode[OUT]	• (Optional) Message Failure Code • pointer to message failure code. If cause code is not provided, then value will be 0xFFFFFFFF

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 minutes

9.25.5.4 ULONG SetSMSCAddress (CHAR * *pSMSCAddress*, CHAR * *pSMSCType*)

Sets the SMS center address.

Parameters

pSMSC-Address[IN]	• The SMS center address represented as a NULL terminated string
pSMSCType[IN]	• The SMS center address type represented as a NULL terminated string (optional).

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 seconds

9.25.5.5 ULONG SLQSCDMADecodeMTTextMsg (struct cdmaMsgDecodingParams * *pCdmaMsgDecodingParams*)

Decodes text message to CDMA PDU message

Parameters

pMsgToBe-EncodedCDMA[-IN/OUT]	• Pointer to structure containing parameters needed for decoding

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: None

9.25.5.6 ULONG SLQSCDMADecodeMTTextMsgExt (struct cdmaMsgDecodingParamsExt * *pCdmaMsgDecodingParamsExt*)

Decodes text message to CDMA PDU message Ext

Parameters

pCdmaMsg-Decoding-ParamsExt[IN/O-UT]	• Pointer to structure containing parameters needed for decoding

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: None

9.25.5.7 ULONG SLQSCDMAEncodeMOTextMsg (struct cdmaMsgEncodingParams * *pCdmaMsgEncodingParams*)

Encodes text message to CDMA PDU message.

Parameters

pMsgToBe-EncodedCDMA[-IN/OUT]	• SLQS Runtime Settings Information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: None

9.25.5.8 ULONG SLQSDeleteSMS (ULONG *storageType,* ULONG * *pMessageIndex,* ULONG * *pMessageTag,* BYTE * *pMessageMode*)

Deletes one or more SMSs from device memory. If both of the optional parameters, messageIndex and messageTag, are NULL, all messages are deleted from the storage location specified in the mandatory storageType parameter. The optional index and tag parameters narrow the range of messages being deleted. If an index is specified, the single message with the index from the specified memory store will be deleted. If a tag is specified, all messages in the specified memory store whose tag matches that specified will be deleted.

There are three ways to use this message:

- Specify storageType only

  - Deletes all messages from memory storage
- Specify storageType and a tag
  - Deletes all messages from memory storage that match the given message tag
- Specify storageType and an index
  - Deletes only the message with the given index from memory storage

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
pMessageIndex[IN]	• (Optional) message index
pMessageTag[IN]	• (Optional) message tag – 0 - Read – 1 - Not read – 2 - Mobile originated and sent – 3 - Mobile originated but not yet sent
pMessageMode[IN]	• (Optional) messgae mode • 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 10 seconds

9.25.5.9 ULONG SLQSGetIndicationRegister (getIndicationRegResp * *pGetIndicationRegInfo*)

This API provides registration state of different WMS indications.

Parameters

pGetIndicationRegInfo	[OUT] • Pointer to structure of getIndicationRegResp – See getIndicationRegResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.25.5.10 ULONG SLQSGetMessageWaiting (getMsgWaitingInfo * *pGetMsgWaitingInfoResp*)

This API provides information about the message waiting information.

Parameters

pGetMsg-WaitingInfoResp	[OUT] • Pointer to structure of getMsgWaitingInfoResp – See getMsgWaitingInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.25.5.11 ULONG SLQSGetSMS (ULONG *storageType*, ULONG *messageIndex*, ULONG * *pMessageTag*, ULONG * *pMessageFormat*, ULONG * *pMessageSize*, BYTE * *pMessage*, BYTE * *pMessageMode*)

Returns an SMS from device memory.

Parameters

storageType	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
messageIndex	• Message index
pMessageTag[-OUT]	• Message tag – 0 - Read – 1 - Not read – 2 - Mobile originated and sent – 3 - Mobile originated but not yet sent

pMessage-Format[OUT]	• Message format – 0 - CDMA (IS-637B) – 1 - 5 (Reserved) – 6 - GSM/WCDMA PP
pMessageSize[IN/OUT]	• Upon input the maximum number of bytes that can be written to the message array. • Upon successful output the actual number of bytes written to the message array.
pMessage[OUT]	• The message contents array
pMessage-Mode[IN]	• (Optional) Message Mode • 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 seconds

9.25.5.12 ULONG SLQSGetSmsBroadcastConfig (BYTE *mode*, qaQmi3GPPBroadcastCfgInfo * *pBroadcastConfig*, qaQmi3GPP2BroadcastCfgInfo * *pCDMABroadcastConfig*)

Provides Information about the SMS BroadcastConfiguration

Parameters

mode[IN]	• Mode – 0x00 - CDMA, LTE (if network type is CDMA) – 0x01 - GW, LTE (if network type is UMTS)
pBroadcast-Config[OUT]	• The data for 3GPP Broadcast Information(Optional).
pCDMA-Broadcast-Config[OUT]	• The data for 3GPP2 Broadcast Information(Optional).

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 seconds

9.25.5.13 ULONG SLQSGetSMSList (ULONG *storageType*, ULONG * *pRequestedTag*, ULONG * *pMessageListSize*, BYTE * *pMessageList*, BYTE * *pMessageMode*)

Returns the list of SMS messages stored on the device.

Parameters

storageType[IN]	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
pRequestedTag[IN]	• (Optional) Message tag – 0 - Read – 1 - Not read – 2 - Mobile originated and sent – 3 - Mobile originated but not yet sent
pMessageListSize[IN/OUT]	• Upon input the maximum number of elements that the message list array can contain. • Upon successful output the actual number of elements in the message list array.
pMessageList[OUT]	• The message list array
pMessageMode[IN]	• (Optional) Message Mode • 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 seconds

9.25.5.14 ULONG SLQSGetTransLayerInfo (getTransLayerInfoResp * *pGetTransLayerInfoResp*)

This API provides information about the transport layer.

Parameters

pGetTransLayer-InfoResp	[OUT] • Pointer to structure of getTransLayerInfoResp – See getTransLayerInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.25.5.15 ULONG SLQSGetTransNWRegInfo (getTransNWRegInfoResp * *pGetTransNWRegInfoResp*)

This API provides transport layer network registration info.

Parameters

pGetTransNW-RegInfoResp	[OUT] • Pointer to structure of getTransNWRegInfoResp – See getTransNWRegInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.25.5.16 ULONG SLQSModifySMSStatus (ULONG *storageType*, ULONG *messageIndex*, ULONG *messageTag*, BYTE * *pMessageMode*)

Modifies the status of an SMS message saved in storage on the device.

Parameters

storageType[IN]	• SMS message storage type – 0 - UIM - Invalid in case of CDMA device that does not require SIM – 1 - NV
messageIndex[IN]	• Message index
messageTag[IN]	• Message tag – 0 - Read – 1 - Not read
pMessageMode[IN]	• (Optional) Message Mode • 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 seconds

9.25.5.17 ULONG SLQSSendAsyncSMS (slqssendasyncsmsparams_s * *pSendSmsParams*)

Sends an SMS message for immediate over-the-air transmission

Parameters

pSendSmsParams	• structure containing the SMS parameters. Refer slqssendasyncsmsparams_s

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 minutes

9.25.5.18 ULONG SLQSSendLongSMS (ULONG *messageFormat*, ULONG *messageSize*, CHAR * *pMessage*, BYTE *encodingScheme*, ULONG * *pMessageFailureCode*, CHAR * *pMobileNum*, BYTE * *pSmsOnIMS*)

Sends a long SMS message for immediate over-the-air transmission, a short SMS can be sent by this API as well, the input message is text string without any encoding

Parameters

messageFormat[IN]	• Message format – 0 - CDMA (IS-637B) – 1 - 5 (Reserved) – 6 - GSM/WCDMA PP
messageSize[IN]	• Message size of the input message text
pMessage[IN]	• Original message text
encodingScheme[IN]	• Encoding method to generate the PDU – 0 - 7 bit encoding – 4 - 8 bit encoding – 8 - 16 bit UCS2 encoding – others value will be treated as default 7 bit encoding
pMessageFailureCode[OUT]	• message failure code. If cause code is not provided, then value will be 0xFFFFFFFF
pMobileNum[IN]	• Mobile number of the receiver
pSmsOnIMS[IN]	• A flag indicates whether SMS was sent through IMS

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: 3GPP and 3GPP2, but 3GPP2 does not support multiple sms
Timeout: 5 minutes

9.25.5.19 ULONG SLQSSendSMS (slqssendsmsparams_s * *pSendSmsParams*)

Sends an SMS message for immediate over-the-air transmission

Parameters

pSendSms-Params	• structure containing the SMS parameters. Refer slqssendsmsparams_s

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 minutes

9.25.5.20 ULONG SLQSSetIndicationRegister (setIndicationRegReq * *pSetIndicationRegReq*)

This API sets the registration state of different WMS indications.

Parameters

pSetIndication-RegReq	[IN] • Pointer to structure of indicationRegReqParams – See setIndicationRegReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.25.5.21 ULONG SLQSSetSmsBroadcastActivation (BYTE *mode*, BYTE *broadcastActivate*)

Enables or disables the reception of broadcast SMS messages.

Parameters

Mode[IN]	• Mode • 0x00 - CDMA, LTE (if network type is CDMA) • 0x01 - GW, LTE (if network type is UMTS)
broadcast-Activate[IN]	• 0x00 - Disable broadcast • 0x01 - Activate broadcast

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 seconds

9.25.5.22 ULONG SLQSSetSmsBroadcastConfig (BYTE *mode*, qaQmi3GPPBroadcastCfgInfo * *pBroadcastConfig*, qaQmi3GPP2BroadcastCfgInfo * *pCDMABroadcastConfig*)

Sets the information about the SMS BroadcastConfiguration

Parameters

mode[IN]	• Mode – 0x00 - CDMA, LTE (if network type is CDMA) – 0x01 - GW, LTE (if network type is UMTS)
pBroadcast-Config[IN]	• The data for 3GPP Broadcast Information(Optional).
pCDMA-Broadcast-Config[IN]	• The data for 3GPP2 Broadcast Information(Optional).

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 seconds

9.25.5.23 ULONG SLQSSetSmsStorage (BYTE *smsStorage*)

Sets the SMS Storage on the device

Parameters

smsStorage[IN]	• SMS Storage – 0x01 - device's permanent memory – 0x02 - UICC

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: ALL
Timeout: 5 seconds

9.25.5.24 ULONG SLQSSmsGetMaxStorageSize (smsMaxStorageSizeReq * *pMaxStorageSizeReq*, smsMaxStorageSizeResp * *pMaxStorageSizeResp*)

This API provides the maximum number of messages that can be stored in the specified memory storage. Also it provides the number of slots currently available

Parameters

pMaxStorage-SizeReq[IN]	• Request parameters for SmsSLQSGetMaxStorageSize – See smsMaxStorageSizeReq for more information
pMaxStorage-SizeResp[OUT]	• Response parameters for SmsSLQSGetMaxStorageSize – See smsMaxStorageSizeResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.25.5.25 ULONG SLQSSmsGetMessageProtocol (smsMsgprotocolResp * *pMessageProtocol*)

This API queries the message protocol currently in use for the WMS client.

Parameters

pMessage-Protocol	[OUT} • Pointer to smsMsgprotocolResp – See smsMsgprotocolResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.25.5.26 ULONG SLQSSmsSetRoutes (smsSetRoutesReq * *pSetRoutesReq*)

This API sets the action performed on SMS message receipt for specified message routes. It also specifies the action performed on SMS receipt of status reports.

Parameters

pSetRoutesReq	[IN] • Pointer to structure of smsSetRoutesReq – See smsSetRoutesReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Secs

9.25.5.27 ULONG SLQSSwiGetSMSStorage (ULONG * *pSmsStorage*)

This API queries the device to return current SMS configuration that is applied to all incoming and outgoing messages.

Parameters

pSmsStorage[OUT]	• Values: – 0x01 - device's permanent memory – 0x02 - UICC

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Secs

9.25.5.28 ULONG SLQSWCDMADecodeLongTextMsg (struct wcdmaLongMsgDecodingParams * *pWcdmaLongMsgDecodingParams*)

Decodes WCDMA Long SMS PDU message, returns structure filled with decoded parameters

Parameters

pwcdmaMsg-Decoding-Params[IN/OUT]	• Pointer to parameters required for decoding

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: none

9.25.5.29 ULONG SLQSWCDMADecodeMTEncoding (BYTE * *pMessage,* USHORT *MessageLen,* BYTE * *pEncoding*)

Decodes WCDMA SMS PDU message to get encoding scheme

Parameters

pMessage[IN]	• Pointer to message for decoding
MessageLen[IN]	• Length of the message
pEncoding[OUT]	• Pointer to encoding scheme

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

9.25.5.30 ULONG SLQSWCDMADecodeMTTextMsg (struct wcdmaMsgDecodingParams * *pWcdmaMsgDecodingParams*)

Decodes WCDMA PDU message, returns structure filled with decoded parameters

Parameters

pwcdmaMsg-Decoding-Params[IN/OUT]	• Pointer to parameters required for decoding

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: none

9.25.5.31 ULONG SLQSWCDMAEncodeMOTextMsg (struct wcdmaMsgEncodingParams * *pWcdmaMsgEncodingParams*)

Returns the encoded WCDMA PDU message.

Parameters

pwcdmaMsg-Encoding-Params[IN/OUT]	• Pointer to parameters Required for encoding

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: None

9.26 qaGobiApiSwi.h File Reference

SWI API function prototypes.

Functions

- ULONG SLQSGetSdkVersion (CHAR **sdkversionpp)
- ULONG SLQSSendRawQMI (BYTE *pReqBuf, USHORT service, USHORT length, ULONG timeout, BYTE **ppInParm, USHORT *pParamLength)
- int SLQSGetPidof (CHAR *pProcName)

9.26.1 Detailed Description

SWI API function prototypes.

9.26.2 Function Documentation

9.26.2.1 int SLQSGetPidof (CHAR * *pProcName*)

Internal Wrapper function for enabling invocation of SLQS implementation pidof() function

Parameters

pProcName[IN]	• Process name whose PID is to be retrieved

Returns

pid if process exists else 0

See Also

NA

Note

NA

9.26.2.2 ULONG SLQSGetSdkVersion (CHAR ** *sdkversionpp*)

Returns the SDK version string

Parameters

ppString[OUT]	• pointer to pointer of NULL terminated string

Returns

eQCWWAN_ERR_NONE success eQCWWAN_ERR_INVALID_ARG provided pointer is NULL

Note

Technology Supported: N/A Timeout: 2 seconds

9.26.2.3 ULONG SLQSSendRawQMI (BYTE * *pReqBuf,* USHORT *service,* USHORT *length,* ULONG *timeout,* BYTE ** *ppInParm,* USHORT * *pParamLength*)

9.27 qaGobiApiSwiAudio.h File Reference

M2M Audio Service API function prototypes.

Data Structures

- struct GetM2MAudioProfileReq
- struct GetM2MAudioProfileResp
- struct SetM2MAudioProfileReq
- struct GetM2MAudioVolumeReq
- struct GetM2MAudioVolumeResp
- struct SetM2MAudioVolumeReq
- struct PCMparams
- struct SetM2MAudioAVCFGReq
- struct SetM2MAudioLPBKReq
- struct GetM2MSpkrGainReq
- struct GetM2MSpkrGainResp
- struct SetM2MSpkrGainReq
- struct GetM2MAVMuteReq
- struct GetM2MAVMuteResp
- struct SetM2MAVMuteReq

Macros

- #define MAX_LEN_IFACE_TABLE 255

Functions

- ULONG SLQSGetM2MAudioProfile (GetM2MAudioProfileReq *pGetM2MAudioProfileReq, GetM2MAudioProfileResp *pGetM2MAudioProfileResp)
- ULONG SLQSSetM2MAudioProfile (SetM2MAudioProfileReq *pSetM2MAudioProfileReq)
- ULONG SLQSGetM2MAudioVolume (GetM2MAudioVolumeReq *pGetM2MAudioVolumeReq, GetM2MAudioVolumeResp *pGetM2MAudioVolumeResp)
- ULONG SLQSSetM2MAudioVolume (SetM2MAudioVolumeReq *pSetM2MAudioVolumeReq)
- ULONG SLQSSetM2MAudioAVCFG (SetM2MAudioAVCFGReq *pSetM2MAudioAVCFGReq)
- ULONG SLQSSetM2MAudioLPBK (SetM2MAudioLPBKReq *pSetM2MAudioLPBKReq)
- ULONG SLQSSetM2MAudioNVDef ()
- ULONG SLQSGetM2MSpkrGain (GetM2MSpkrGainReq *pSpkrGainReq, GetM2MSpkrGainResp *pSpkrGainResp)
- ULONG SLQSSetM2MSpkrGain (SetM2MSpkrGainReq *pSpkrGainReq)
- ULONG SLQSGetM2MAVMute (GetM2MAVMuteReq *pGetM2MAVMuteReq, GetM2MAVMuteResp *pGetM2MAVMuteResp)
- ULONG SLQSSetM2MAVMute (SetM2MAVMuteReq *pSetM2MAVMuteReq)

9.27.1 Detailed Description

M2M Audio Service API function prototypes.

9.27.2 Macro Definition Documentation

9.27.2.1 #define MAX_LEN_IFACE_TABLE 255

9.27.3 Function Documentation

9.27.3.1 ULONG SLQSGetM2MAudioProfile (GetM2MAudioProfileReq * *pGetM2MAudioProfileReq*, GetM2MAudioProfileResp * *pGetM2MAudioProfileResp*)

This API gets the profile content.

Parameters

pGetM2MAudioProfileReq[OUT]	• See GetM2MAudioProfileReq for more information
pGetM2MAudioProfileResp[OUT]	• See GetM2MAudioProfileResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.2 ULONG SLQSGetM2MAudioVolume (GetM2MAudioVolumeReq * *pGetM2MAudioVolumeReq*, GetM2MAudioVolumeResp * *pGetM2MAudioVolumeResp*)

This API gets the Volume content.

Parameters

pGetM2MAudioVolumeReq[IN]	• See GetM2MAudioVolumeReq for more information
pGetM2MAudioVolumeResp[OUT]	• See GetM2MAudioVolumeResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.3 ULONG SLQSGetM2MAVMute (GetM2MAVMuteReq * *pGetM2MAVMuteReq*, GetM2MAVMuteResp * *pGetM2MAVMuteResp*)

This API Gets the AV Mute content.

Parameters

pGetM2MAV-MuteReq[IN]	• See GetM2MAVMuteReq for more information
pGetM2MAV-MuteResp[OUT]	• See GetM2MAVMuteResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.4 ULONG SLQSGetM2MSpkrGain (GetM2MSpkrGainReq * *pSpkrGainReq*, GetM2MSpkrGainResp * *pSpkrGainResp*)

This API Gets the SPKRGAIN content.

Parameters

pSpkrGainReq[I-N]	• See GetM2MSpkrGainReq for more information
pSpkrGain-Resp[OUT]	• See GetM2MSpkrGainResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.5 ULONG SLQSSetM2MAudioAVCFG (SetM2MAudioAVCFGReq * *pSetM2MAudioAVCFGReq*)

This API sets the AVCFG content.

Parameters

pSetM2MAudio-AVCFGReq[IN]	• See SetM2MAudioAVCFGReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.6 ULONG SLQSSetM2MAudioLPBK (SetM2MAudioLPBKReq * *pSetM2MAudioLPBKReq*)

This API sets the LPBK content.

Parameters

pSetM2MAudio-LPBKReq[IN]	• See SetM2MAudioLPBKReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.7 ULONG SLQSSetM2MAudioNVDef ( )

This API sets the NVDef content.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.8 ULONG SLQSSetM2MAudioProfile (SetM2MAudioProfileReq * *pSetM2MAudioProfileReq*)

This API sets the profile content.

Parameters

pSetM2MAudio-ProfileReq[IN]	• See SetM2MAudioProfileReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.9 ULONG SLQSSetM2MAudioVolume (SetM2MAudioVolumeReq * *pSetM2MAudioVolumeReq*)

This API sets the Volume content.

Parameters

pSetM2MAudio-VolumeReq[IN]	• See SetM2MAudioVolumeReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.10 ULONG SLQSSetM2MAVMute (SetM2MAVMuteReq * *pSetM2MAVMuteReq*)

This API Sets the AV Mute content.

Parameters

pSetM2MAV-MuteReq[IN]	• See SetM2MAVMuteReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.27.3.11 ULONG SLQSSetM2MSpkrGain (SetM2MSpkrGainReq * *pSpkrGainReq*)

This API Sets the SPKRGAIN content.

Parameters

pSpkrGainReq[IN]	• See GetM2MSpkrGainReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.28 qaGobiApiSwiAvms.h File Reference

SWI Open Mobile Alliance Device Management Service API function prototypes SWI AVMS QMI Service revision 1.14.

Data Structures

- struct _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp
- struct _QmiSwiAvmsEventReportConfigResp
- struct _QmiSwiAvmsEventReportNotificationResp
- struct _QmiSwiAvmsEventReportConnectionRequestResp
- struct _QmiSwiAvmsEventReportWAMSParamChangeResp
- struct _QmiSwiAvmsEventReportPackageIDResp

- struct _QmiSwiAvmsEventReportRegStatusResp
- struct _QmiSwiAvmsEventReportDataSessionStatusResp
- struct _QmiSwiAvmsEventReportSessionTypeResp
- struct _QmiSwiAvmsEventReportHTTPStatusResp
- struct _SLQSAVMSSettingsAPNInfo
- struct _SLQSAVMSSettingsConnectionRetryTimers
- struct _SLQSAVMSSettingsPeriodsInfo
- struct _SLQSAVMSSettings
- struct _SLQSAVMSSettings_v2
- struct _QmiSwiAvmsSetSettingsPeriodInfo
- struct _QmiSwiAvmsSetSettingsAPNInfo
- struct _QmiSwiAvmsSetSettingsConnectionRetryTimers
- struct _SLQSAVMSSetSettingsReqPara
- struct _SLQSAVMSSetSettingsReqPara_v2

Macros

- #define MAX_GET_SETTINGS_AVMS_APN_STRING_LENGTH 49
- #define MAX_GET_SETTINGS_AVMS_UNAME_STRING_LENGTH 29
- #define MAX_GET_SETTINGS_AVMS_PWD_STRING_LENGTH 29
- #define QMISWIAVMSSESSIONGETINFO_BINARYUPDATESESSIONINFO_VERSION_LENGTH 128
- #define QMISWIAVMSSESSIONGETINFO_BINARYUPDATESESSIONINFO_NAME_LENGTH 128
- #define QMISWIAVMSSESSIONGETINFO_BINARYUPDATESESSIONINFO_DESC_LENGTH 1024
- #define QMISWIAVMSSESSIONGETINFO_CONFIG_ALERT_MSG_LENGTH 200
- #define MAX_AVMS_RETRY_TIMER_NUMBER 8
- #define MAX_SWI_AVMS_SET_SETTING_APN_LENGTH 49
- #define MAX_SWI_AVMS_SET_SETTING_UNAME_LENGTH 29
- #define MAX_SWI_AVMS_SET_SETTING_PWD_LENGTH 29
- #define MAX_SWI_AVMS_SET_SETTING_CONNECTION_RETRY_TIMMERS 8

Typedefs

- typedef struct _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp
- typedef struct _QmiSwiAvmsEventReportConfigResp QmiSwiAvmsEventReportConfigResp
- typedef struct _QmiSwiAvmsEventReportNotificationResp QmiSwiAvmsEventReportNotificationResp
- typedef struct _QmiSwiAvmsEventReportConnectionRequestResp QmiSwiAvmsEventReportConnectionRequestResp
- typedef struct _QmiSwiAvmsEventReportWAMSParamChangeResp QmiSwiAvmsEventReportWAMSParamChangeResp
- typedef struct _QmiSwiAvmsEventReportPackageIDResp QmiSwiAvmsEventReportPackageIDResp
- typedef struct _QmiSwiAvmsEventReportRegStatusResp QmiSwiAvmsEventReportRegStatusResp
- typedef struct _QmiSwiAvmsEventReportDataSessionStatusResp QmiSwiAvmsEventReportDataSessionStatusResp
- typedef struct _QmiSwiAvmsEventReportSessionTypeResp QmiSwiAvmsEventReportSessionTypeResp
- typedef struct _QmiSwiAvmsEventReportHTTPStatusResp QmiSwiAvmsEventReportHTTPStatusResp
- typedef struct _SLQSAVMSSettingsAPNInfo SLQSAVMSSettingsAPNInfo

- typedef struct _SLQSAVMSSettingsConnectionRetryTimers SLQSAVMSSettingsConnectionRetryTimers
- typedef struct _SLQSAVMSSettingsPeriodsInfo SLQSAVMSSettingsPeriodsInfo
- typedef struct _SLQSAVMSSettings SLQSAVMSSettings
- typedef struct _SLQSAVMSSettings_v2 SLQSAVMSSettings_v2
- typedef struct _QmiSwiAvmsSetSettingsPeriodInfo QmiSwiAvmsSetSettingsPeriodInfo
- typedef struct _QmiSwiAvmsSetSettingsAPNInfo QmiSwiAvmsSetSettingsAPNInfo
- typedef struct _QmiSwiAvmsSetSettingsConnectionRetryTimers QmiSwiAvmsSetSettingsConnectionRetryTimers
- typedef struct _SLQSAVMSSetSettingsReqPara SLQSAVMSSetSettingsReq
- typedef struct _SLQSAVMSSetSettingsReqPara_v2 SLQSAVMSSetSettingsReq_v2

Functions

- ULONG SLQSAVMSStartSession (BYTE sessionType, ULONG *pSessionResponse)
- ULONG SLQSAVMSStopSession (BYTE sessiontype, BYTE *pSessionRep)
- ULONG SLQSAVMSGetSessionInfo (QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp *pBinaryUpdteSessionInfo, QmiSwiAvmsEventReportConfigResp *pAVMSConfig, QmiSwiAvmsEventReportNotificationResp *pNotif, QmiSwiAvmsEventReportPackageIDResp *pPackageID)
- ULONG SLQSAVMSSelection (BYTE selection, ULONG *pDeferTime, BYTE *pClientPerfOperationFlag, BYTE *pPackageID, WORD *pRejectReason)
- ULONG SLQSAVMSGetSettings (SLQSAVMSSettings *settings)
- ULONG SLQSAVMSGetSettings_v2 (SLQSAVMSSettings_v2 *settings)
- ULONG SLQSAVMSSetSettings (SLQSAVMSSetSettingsReq Request)
- ULONG SLQSAVMSSetSettings_v2 (SLQSAVMSSetSettingsReq_v2 Request)
- ULONG SLQSAVMSSetSettingsIgnoreAutoReboot (SLQSAVMSSetSettingsReq Request)
- ULONG SLQSAVMSSetEventReport ()

9.28.1 Detailed Description

SWI Open Mobile Alliance Device Management Service API function prototypes SWI AVMS QMI Service revision 1.14.

9.28.2 Macro Definition Documentation

9.28.2.1 #define MAX_AVMS_RETRY_TIMER_NUMBER 8

9.28.2.2 #define MAX_GET_SETTINGS_AVMS_APN_STRING_LENGTH 49

9.28.2.3 #define MAX_GET_SETTINGS_AVMS_PWD_STRING_LENGTH 29

9.28.2.4 #define MAX_GET_SETTINGS_AVMS_UNAME_STRING_LENGTH 29

9.28.2.5 #define MAX_SWI_AVMS_SET_SETTING_APN_LENGTH 49

9.28.2.6 #define MAX_SWI_AVMS_SET_SETTING_CONNECTION_RETRY_TIMMERS 8

9.28.2.7 #define MAX_SWI_AVMS_SET_SETTING_PWD_LENGTH 29

9.28.2.8 #define MAX_SWI_AVMS_SET_SETTING_UNAME_LENGTH 29

9.28.2.9 #define QMISWIAVMSSESSIONGETINFO_BINARYUPDATESESSIONINFO_DESC_LENGTH 1024

9.28.2.10 #define QMISWIAVMSSESSIONGETINFO_BINARYUPDATESESSIONINFO_NAME_LENGTH 128

9.28.2.11 #define QMISWIAVMSSESSIONGETINFO_BINARYUPDATESESSIONINFO_VERSION_LENGTH 128

9.28.2.12 #define QMISWIAVMSSESSIONGETINFO_CONFIG_ALERT_MSG_LENGTH 200

9.28.3 Typedef Documentation

9.28.3.1 typedef struct _QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp

Parameters

bBinaryType	: Type • 1 - Firmware. • 2 - User App. • 3 - Legato Framework.
bStat	: State • 0x01 - No binary update available. • 0x02 - Query binary Download. • 0x03 - Binary Downloading. • 0x04 - Binary downloaded. • 0x05 -Query Binary Update. • 0x06 - Binary updating. • 0x07 - Binary updated.
bUserInput-Request	Bit mask of available user inputs. • 0x00 - No user input required. Informational indication. • 0x01 - Accept. • 0x02 - Reject.
wUserInput-Timeout	Timeout for user input in minutes. A value of 0 means no time-out.
ulPkgDownload-Size	The size (in bytes) of the update package
ulPkgDownload-Complete	The number of bytes being downloaded. For downloading state, this value shall be $>$ 0 and incremented toward the pkg_dload_size. For other states, the value shall be 0 as it is meaningless.
wUpdate-CompeteStatus	Result code.This field should be looked at only when the AVMS session is complete.
bSerity	Serity. • 0x01 - Mandatory. • 0x02 - Optional.
wVersionLength	Length of FW Version string in bytes.
szVersion	FW Version string in ASCII.
wNameLength	Length Package Name string in bytes.
szName	Package Name in UCS2.
wDescription-Length	Length of description in bytes.
szDescription	Description of Update Package in USC2.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.2 typedef struct _QmiSwiAvmsEventReportConfigResp QmiSwiAvmsEventReportConfigResp

Parameters

bState	State. • 0x01 - AVMS Read Request. • 0x02 - AVMS Change Request. • 0x03 - AVMS Config Complete.
bUserInput-Request	Bit mask of available user inputs. • 0x00 - No user input required. Informational indication. • 0x01 - Accept. • 0x02 - Reject.
wUserInput-Timeout	Timeout for user input in seconds. A value of 0 means no time-out
wAlertMsg-Length	Length of Alert message string in bytes.
szAlertMsg	Alert message in UCS2.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.3 typedef struct _QmiSwiAvmsEventReportConnectionRequestResp QmiSwiAvmsEventReport-ConnectionRequestResp

Parameters

bUserInput-Request	Bit mask of available user inputs. • 0x00 - No user input required. Informational indication. • 0x01 - Accept. • 0x02 - Reject.
bUserInput-Request	Timeout for user input in minutes. A value of 0 means no time-out.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.4 typedef struct _QmiSwiAvmsEventReportDataSessionStatusResp QmiSwiAvmsEventReportData-SessionStatusResp

Parameters

bType	Notification type. • 0: Data session closed. • 1: Data session activated. • 2: Register made. -3: Data session error.
wErrorCode	LWM2M Session error code. • 0x0000: none
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.5 typedef struct _QmiSwiAvmsEventReportHTTPStatusResp QmiSwiAvmsEventReportHTTPStatus-Resp

Parameters

wHTTPStatus	See RFC 7231. • 100 - Continue • 101 - Switching Protocols • 200 - OK • 201 - Created • 202 - Accepted • 203 - Non-Authoritative Information • 204 - No Content • 205 - Reset Content • 206 - Partial Content • 300 - Multiple Choices • 301 - Moved Permanently • 302 - Found • 303 - See Other • 304 - Not Modified • 305 - Use Proxy • 307 - Temporary Redirect • 400 - Bad Request • 401 - Unauthorized • 402 - Payment Required • 403 - Forbidden • 404 - Not Found • 405 - Method Not Allowed • 406 - Not Acceptable • 407 - Proxy Authentication Required • 408 - Request Timeout • 409 - Conflict • 410 - Gone • 411 - Length Required • 412 - Precondition Failed • 413 - Payload Too Large • 414 - URI Too Long • 415 - Unsupported Media Type • 416 - Range Not Satisfiable • 417 - Expectation Failed • 426 - Upgrade Required • 500 - Internal Server Error • 501 - Not Implemented • 502 - Bad Gateway • 503 - Service Unavailable • 504 - Gateway Timeout • 505 - HTTP Version Not Supported
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.6 typedef struct _QmiSwiAvmsEventReportNotificationResp QmiSwiAvmsEventReportNotification-Resp

Parameters

bNotification	Notification. • 0x14 - Module starts sending data to server. • 0x15 - Authentication with the server. • 0x16 - session with the server is ended.
wSessionStatus	This field will set to the session status for notifications that occur at the end of a session, zero for all other notifications. • 0x0000: Successful: Session succeeded • 0x0001: Break: Session succeeded • 0x0002: Large Object Handled: Session succeeded • 0x0003: No status: Session succeeded • 0x0004: No more commands: Session succeeded • 0x0005: User cancel: Session cancelled • 0x0100-0x01FF: General errors • 0x0200-0x02FF: Syncml errors • 0x0300-0x03FF: Authentication errors • 0x0400-0x04FF: Protocol errors • 0x0500-0x05FF: Tree errors (DM Only) • 0x0600-0x06FF: Not applicable • 0x0700-0x07FF: Trigger errors • 0x0800-0x08FF: FUMO errors • 0x0900-0x09FF: Communication errors • 0x0A00-0x0AFF: Parsing errors • 0x0B00-0x0CFF: Not applicable • 0x7F00-0x7F12:Insignia errors • 0x7F13: Illegal text: Text received contains illegal characters • 0x7F14: Download failure: Failed to download FOTA image • 0x7F15: Empty session: Session ran successfully, but no information wasa updated • 0x7F16: Factory reset successful: Factory reset succeeded • 0x7F17: Factory reset fail: Factory reset failed
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.7 typedef struct _QmiSwiAvmsEventReportPackageIDResp QmiSwiAvmsEventReportPackageIDResp

Parameters

bPackageID	Package ID of the application binary that this AVMS_EVENT_ID notification is for.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.8 typedef struct _QmiSwiAvmsEventReportRegStatusResp QmiSwiAvmsEventReportRegStatusResp

Parameters

bRegStatus	LWM2M Registration status. • 0: Need Bootstrap. • 1: Bootstrap made. • 2: Register made. -3: Update made.
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.9 typedef struct _QmiSwiAvmsEventReportSessionTypeResp QmiSwiAvmsEventReportSessionTypeResp

Parameters

bType	Session Type. • 0: Bootstrap session. • 1. DM session
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.10 typedef struct _QmiSwiAvmsEventReportWAMSParamChangeResp QmiSwiAvmsEventReportWAMSParamChangeResp

Parameters

wWamsChangeMask	Mask of WAMS parameters changed. • By default set to 0xFF for all changes. • 0x01 - device_login • 0x02 - device_MD5_key • 0x04 - server_login • 0x08 - server_MD5_key • 0x10 - server_URL • 0x20 - Nonce • 0x40 - Application key
TlvPresent	Boolean indicating the presence of the TLV in the QMI response

9.28.3.11 typedef struct _QmiSwiAvmsSetSettingsAPNInfo QmiSwiAvmsSetSettingsAPNInfo

9.28.3.12 typedef struct _QmiSwiAvmsSetSettingsConnectionRetryTimers QmiSwiAvmsSetSettingsConnectionRetryTimers

9.28.3.13 typedef struct _QmiSwiAvmsSetSettingsPeriodInfo QmiSwiAvmsSetSettingsPeriodInfo

9.28.3.14 typedef struct _SLQSAVMSSetSettingsReqPara SLQSAVMSSetSettingsReq

Sets the AVMS settings requested (For AVC1 service).

Parameters

bAutoConnect[IN]	• Auto Connect to AirVantage server – 0x00 - FALSE – 0x01 - TRUE
bAutoReboot[IN]	• Automatic device reboot when the request is received from AirVantage server – 0x00 - FALSE – 0x01 - TRUE

bFwPromptdownload[IN]	• Start Firmware Download promptly/automatically – 0x00 - FALSE – 0x01 - TRUE
bFwPromptUpdate[IN]	• Start Firmware Download promptly/automatically – 0x00 - FALSE – 0x01 - TRUE
FwAutoSDM[Optional]	- OMA Automatic UI Alert Response • 0x00 - DISABLED • 0x01 - ENABLED ACCEPT • 0x02 - ENABLED REJECT
PollingTimer[Optional]	• 0-525600 (min) • 0:disabled
ConnectionRetryTimers[Optional]	• See QmiSwiAvmsSetSettingsConnectionRetryTimers for more information
APNInfo[Optional]	• See QmiSwiAvmsSetSettingsAPNInfo for more information
NotifStore[Optional]	• 0 : Disabled. • 1 : Enabeld.
PeroidInfo[Optional]	• See QmiSwiAvmsSetSettingsPeriodInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.28.3.15 typedef struct _SLQSAVMSSetSettingsReqPara_v2 SLQSAVMSSetSettingsReq_v2

Sets the AVMS settings requested (For AVC2 service).

Parameters

bAutoConnect[IN]	• Auto Connect to AirVantage server – 0x00 - FALSE – 0x01 - TRUE
bFwPromptdownload[IN]	• Start Firmware Download promptly/automatically – 0x00 - FALSE – 0x01 - TRUE
bFwPromptUpdate[IN]	• Start Firmware Download promptly/automatically – 0x00 - FALSE – 0x01 - TRUE
FwAutoSDM[Optional]	- OMA Automatic UI Alert Response • 0x00 - DISABLED • 0x01 - ENABLED ACCEPT • 0x02 - ENABLED REJECT
PollingTimer[Optional]	• 0-525600 (min) • 0:disabled
ConnectionRetryTimers[Optional]	• See QmiSwiAvmsSetSettingsConnectionRetryTimers for more information
APNInfo[Optional]	• See QmiSwiAvmsSetSettingsAPNInfo for more information
NotifStore[Optional]	• 0 : Disabled. • 1 : Enabeld.
PeroidInfo[Optional]	• See QmiSwiAvmsSetSettingsPeriodInfo for more information
bAutoReboot[Optional]	• Automatic device reboot when the request is received from AirVantage server – 0x00 - FALSE – 0x01 - TRUE

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Setting PromptFwDownload/PromptFwUpdate as TRUE implies AutoConnect to be also TRUE even if AutoConnect was set FALSE initially. Automatic firmware download/update selection trumps the connection setting flag.

9.28.3.16 typedef struct _SLQSAVMSSettings SLQSAVMSSettings

9.28.3.17 typedef struct _SLQSAVMSSettings_v2 SLQSAVMSSettings_v2

9.28.3.18 typedef struct _SLQSAVMSSettingsAPNInfo SLQSAVMSSettingsAPNInfo

9.28.3.19 typedef struct _SLQSAVMSSettingsConnectionRetryTimers SLQSAVMSSettingsConnectionRetryTimers

9.28.3.20 typedef struct _SLQSAVMSSettingsPeriodsInfo SLQSAVMSSettingsPeriodsInfo

9.28.4 Function Documentation

9.28.4.1 ULONG SLQSAVMSGetSessionInfo (QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp * *pBinaryUpdteSessionInfo*, QmiSwiAvmsEventReportConfigResp * *pAVMSConfig*, QmiSwiAvmsEventReportNotificationResp * *pNotif*, QmiSwiAvmsEventReportPackageIDResp * *pPackageID*)

Returns information related to the current AVMS session.

Parameters

pBinaryUpdteSessionInfo[OUT]	• See QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp for more information.
pAVMSConfig[OUT]	• See QmiSwiAvmsEventReportConfigResp for more information.
pNotif[OUT]	• See QmiSwiAvmsEventReportNotificationResp for more information.
pPackageID[OUT]	• See QmiSwiAvmsEventReportPackageIDResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.28.4.2 ULONG SLQSAVMSGetSettings (SLQSAVMSSettings * *settings*)

9.28.4.3 ULONG SLQSAVMSGetSettings_v2 (SLQSAVMSSettings_v2 * *settings*)

9.28.4.4 ULONG SLQSAVMSSelection (BYTE *selection*, ULONG * *pDeferTime*, BYTE * *pClientPerfOperationFlag*, BYTE * *pPackageID*, WORD * *pRejectReason*)

Sends the specified AVMS selection for the current network initiated session.

Parameters

selection[IN]	• AVMS User Selection. – 0x01 - Accept. – 0x02 - Reject. – 0x03 - Defer.
pDeferTime[IN]	• Defer time in minutes. A value of 0 will cause the prompt to be resent immediately.
pClientPerf-OperationFlag[IN]	• Client operation flag after accept. – 0 - if modem performs the operation (download or update). – 1 - if client performs the operation (download or update).
pPackageID[IN]	• Package ID (relevant to Application binary package) – Package ID of the application binary that the client is referring to for its selection. If this field is absent, the modem will assume the package of the most recent AVMS_EVENT_ID notification.
pRejectReason[IN]	• Reject reason.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.28.4.5 ULONG SLQSAVMSSetEventReport ( )

Sets AVMS Event Report.

Parameters

NULL	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.28.4.6 ULONG SLQSAVMSSetSettings (SLQSAVMSSetSettingsReq *Request*)

Sets AVMS settings requested (For AVC1 service).

Parameters

Request[IN]	• See SLQSAVMSSetSettingsReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.28.4.7 ULONG SLQSAVMSSetSettings_v2 (SLQSAVMSSetSettingsReq_v2 *Request*)

Sets AVMS settings requested (AVC2 service).

Parameters

Request[IN]	• See SLQSAVMSSetSettingsReq_v2 for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.28.4.8 ULONG SLQSAVMSSetSettingsIgnoreAutoReboot (SLQSAVMSSetSettingsReq *Request*)

Sets AVMS settings requested without Auto Reboot.

Parameters

Request[IN]	• See SLQSAVMSSetSettingsReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.28.4.9 ULONG SLQSAVMSStartSession (BYTE *sessionType,* ULONG * *pSessionResponse*)

Starts an AVMS session.

Parameters

sessionType[IN]	• Session type – 0x01 - FOTA, to check availability of FW Update. This field is mandatory in OMA-DM case but not necessary in LWM2M one. To keep compatibility, this shall be used in LWM2M without any specific treatment.
pSession-Response[OUT]	• Session Response – 0x01 -Available. – 0x02 -Not Available. – 0x03 -Check Timed Out

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.28.4.10 ULONG SLQSAVMSStopSession (BYTE *sessiontype,* BYTE * *pSessionRep*)

Stop an ongoing AVMS session.

Parameters

session[IN]	• Session – 0x01 - FOTA, to check availability of FW Update. – 0xFF - Cancel any active OMADM session.
pSessionRep[OUT]	• Session – 0x01 - FOTA session suspended. – 0xFF - Suspend ongoing FOTA session or stop any other active AVMS session.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.29 qaGobiApiSwiDms.h File Reference

SWI DMS API function prototypes.

Data Structures

- struct SwiDmsSLQSGetUsbNetNum
- struct MTUSizeReq
- struct mtuSize3gppTlv
- struct hrpdMTUSizeTlv
- struct ehrpdMTUSizeTlv
- struct usbMTUSizeTlv
- struct SwiDmsGetMTUResp
- struct intfaceCfgTlv
- struct supportedIntBitmaskTlv
- struct SwiDmsGetUsbCompResp
- struct setIntfaceCfgTlv
- struct SwiDmsGetHWWatchdog
- struct SwiDmsSetHWWatchdog
- struct SwiDmsGetSecureInfoResp

Functions

- ULONG SLQSSwiDmsGetUsbNetNum (SwiDmsSLQSGetUsbNetNum *pSwiDmsSLQSGetUsbNetNum)
- ULONG SLQSSwiDmsSetUsbNetNum (BYTE nUsbNetNum)
- ULONG SLQSSwiDmsSetMTU (MTUSizeReq *pMTUSizeReq)
- ULONG SLQSSwiDmsGetMTU (SwiDmsGetMTUResp *pSwiDMSGetMTUResp)
- ULONG SLQSSwiDmsGetUsbComp (SwiDmsGetUsbCompResp *pGetUsbCompResp)
- ULONG SLQSSwiDmsSetUsbComp (setIntfaceCfgTlv *pSetIntCfgReq)
- ULONG SLQSSwiDmsGetHWWatchdog (SwiDmsGetHWWatchdog *pGetHWWatchDogResp)
- ULONG SLQSSwiDmsSetHWWatchdog (SwiDmsSetHWWatchdog *pGetHWWatchDogResp)
- ULONG SLQSSwiDmsGetSecureInfo (SwiDmsGetSecureInfoResp *pSwiDMSGetSecureInfoResp)

9.29.1 Detailed Description

SWI DMS API function prototypes.

9.29.2 Function Documentation

9.29.2.1 ULONG SLQSSwiDmsGetHWWatchdog (SwiDmsGetHWWatchdog * *pGetHWWatchDogResp*)

This API is to get the hardware watch dog settings

Parameters

pGetHWWatch-DogResp[OUT]	See SLQSSwiDmsGetHWWatchdog for more information of the output structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds.

9.29.2.2 ULONG SLQSSwiDmsGetMTU (SwiDmsGetMTUResp * *pSwiDMSGetMTUResp*)

Returns the preferred MTU Size of the 3GPP, HRPD, EHRPD and USB descriptor Interfaces.

Parameters

pSwiDMSGetM-TUResp[OUT]	See SwiDmsGetMTUResp for more information of the input structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.29.2.3 ULONG SLQSSwiDmsGetSecureInfo (SwiDmsGetSecureInfoResp * *pSwiDMSGetSecureInfoResp*)

Returns the secure info about bootloader, memory dump etc.

Parameters

pSwiDMSGetSecureInfoResp[OUT]	See SwiDmsGetSecureInfoResp for more information of the input structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds

9.29.2.4 ULONG SLQSSwiDmsGetUsbComp (SwiDmsGetUsbCompResp * *pGetUsbCompResp*)

This API is to query the modem's USB interface configuraiton and supported interface bitmasks

Parameters

pGetUsbCompResp[OUT]	See SwiDmsGetUsbCompResp for more information of the output structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds.

9.29.2.5 ULONG SLQSSwiDmsGetUsbNetNum (SwiDmsSLQSGetUsbNetNum * *pSwiDmsSLQSGetUsbNetNum*)

Used by the control point to get the number of usb networks (QMAP configuration).

Parameters

pSwiDmsSLQS-GetUsbNet-Num[OUT]	• See SwiDmsSLQSGetUsbNetNum for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.29.2.6 ULONG SLQSSwiDmsSetHWWatchdog (SwiDmsSetHWWatchdog * *pGetHWWatchDogResp*)

This API is to get the hardware watch dog settings

Parameters

pGetHWWatch-DogResp[OUT]	See SwiDmsGetHWWatchdog for more information of the output structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds.

9.29.2.7 ULONG SLQSSwiDmsSetMTU (MTUSizeReq * *pMTUSizeReq*)

Sets the preferred MTU size for 3GPP, HRPD, EHRPD and USB Descriptor

Parameters

pMTUSizeReq[I-N]	See MTUSizeReq for more information of the input structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds. New MTU size effective after modem reboot.

9.29.2.8 ULONG SLQSSwiDmsSetUsbComp (setIntfaceCfgTlv * *pSetIntCfgReq*)

This API is to set the modem's USB interface configuraiton

Parameters

pSetIntCfgReq[IN]	See setIntfaceCfgTlv for more information of the input structure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 Seconds. This setting will be effective after modem reboot

9.29.2.9 ULONG SLQSSwiDmsSetUsbNetNum (BYTE *nUsbNetNum*)

Used by the control point to set the number of usb networks (QMAP configuration).

Parameters

nUsbNetNum[IN]	• value for usb net numbers • range is 0-8

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.30 qaGobiApiSwiOmadms.h File Reference

SWI Open Mobile Alliance Device Management Service API function prototypes SWI OMA-DM QMI Service revision 1.6.

Data Structures

- struct _SLQSOMADMSessionInfo
- struct _SLQSOMADMSettingsReqParams
- struct _SLQSOMADMSettings
- struct _SLQSOMADMSettingsReqParams3

Typedefs

- typedef struct _SLQSOMADMSessionInfo SLQSOMADMSessionInfo
- typedef struct _SLQSOMADMSettingsReqParams SLQSOMADMSettingsReqParams
- typedef struct _SLQSOMADMSettings SLQSOMADMSettings
- typedef struct _SLQSOMADMSettingsReqParams3 SLQSOMADMSettingsReqParams3

Functions

- ULONG SLQSOMADMStartSession (ULONG sessionType)
- ULONG SLQSOMADMCancelSession (ULONG session)
- ULONG SLQSOMADMGetSessionInfo (ULONG *pSessionType, SLQSOMADMSessionInfo *pResp)
- ULONG SLQSOMADMSendSelection (ULONG selection)
- ULONG SLQSOMADMGetSettings (ULONG *pbOMADMEnabled, ULONG *pbFOTAdownload, ULONG *pbFOTAUpdate)
- ULONG SLQSOMADMSetSettings (ULONG bFOTAdownload, ULONG bFOTAUpdate)
- ULONG SLQSOMADMSetSettings2 (SLQSOMADMSettingsReqParams *pSLQSOMADMSettingsReqParams)
- ULONG SLQSOMADMGetSettings2 (SLQSOMADMSettings *pSLQSOMADMSettings)
- ULONG SLQSOMADMStartSession2 (ULONG sessionType, ULONG *pFwAvailability)
- ULONG SLQSOMADMSendSelection2 (ULONG selection, ULONG *pDeferTime, ULONG *pRejectReason)
- ULONG SLQSOMADMSetSettings3 (SLQSOMADMSettingsReqParams3 *pSLQSOMADMSettingsReqParams3)

9.30.1 Detailed Description

SWI Open Mobile Alliance Device Management Service API function prototypes SWI OMA-DM QMI Service revision 1.6.

9.30.2 Typedef Documentation

9.30.2.1 typedef struct _SLQSOMADMSessionInfo SLQSOMADMSessionInfo

Structure containing the OMA DM Session Info returned by the device. Also used as input parameter to specify the size of variable parameters. (ref. notes)

Parameters

pStatus	• 1 Byte parameter indicating status(optional) – 0x01 - No Firmware available – 0x02 - Query Firmware Download – 0x03 - Firmware Downloading – 0x04 - Firmware Downloaded – 0x05 - Query Firmware Update – 0x06 - Firmware Updating – 0x07 - Firmware Updated
pUpdate-CompleteStatus	• 2 byte parameter indicating Update Complete Status(optional) – See qaGobiApiTableSwiOMADMUpdateCompleteStatus.h Update Complete Status

pSeverity	• 1 byte parameter indicating severity(optional) – 0x01 - Mandatory – 0x02 - Optional
pSourceLength	• 2 byte parameter indicating Length of Vendor Name String in Bytes.(optional)
pSource	• Variable length parameter indicating Vendor Name in ASCII(optional)
pPkgName-Length	• 2 byte parameter indicating Length of Package Name String in Bytes.(optional)
pPkgName	• Variable length parameter indicating Package Name in ASCII(optional)
pPkgDesc-Length	• 2 byte parameter indicating Length of Package Description String in Bytes.(optional)
pPkgDescription	• Variable length parameter indicating Package Description in ASCII(optional)
pDateLength	• 2 byte parameter indicating Length of Package Description String in Bytes.(optional)
pDate	• Variable length parameter indicating Package Description in ASCII
pTimeLength	• 2 byte parameter indicating Length of Time String in Bytes.(optional)
pTime	• Variable length parameter indicating Time String in ASCII(optional)
pSessionType	• 1 byte parameter reflects the last session started for Sprint(optional) – 0x00 - No session since boot – 0x01 - Sprint CI-DC Session – 0x02 - Sprint CI-PRL Session – 0x03 - Sprint CI-FUMO Session – 0x04 - Sprint HFA-DC Session – 0x05 - Sprint HFA-PRL Session – 0x06 - Sprint HFA-FUMO Session – 0x07 - Sprint NI Session
pSessionState	• 1 byte parameter indicating session state(optional) – 0x01 - idle – 0x02 - active – 0x03 - pending

pRetryCount	• 1 byte parameter indicating retries left count(optional) – valid values 0 to 6

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

As input parameter the members pSourceLength, pPkgNameLength pPkgDescLength, pDateLength, pTimeLength have to be specified. These should contain the initialized size of pSource, pPkgName, pPkgDescription, pDate, pTime respectively.

9.30.2.2 typedef struct _SLQSOMADMSettings SLQSOMADMSettings

Structure containing the OMA DM settings retrieved from the device

Parameters

pOMADMEnabled[OUT]	• 4 byte parameter indicating OMADM service enabled – 0x00000001 - Client-initiated device configuration – 0x00000002 - Network-initiated device configuration – 0x00000010 - Client-initiated FUMO – 0x00000020 - Network-initiated FUMO • function SLQSOMADMGetSettings2() returns a default value 0xFFFFFFFF in case this parameter is not returned by the modem.
pFOTAdownload[OUT]	• 1 Byte parameter indicating support for FOTA Automatic download – 0x00 - Host permission required before downloading – 0x01 - Automatically start downloading, no host permission required – 0x02 - Automatically start downloading, while not roaming – 0x03 - Automatically reject download – 0x04 - Automatically reject download with “Enterprise Reject Policy” • function SLQSOMADMGetSettings2() returns a default value 0xFF in case this parameter is not returned by the modem.
pFOTAUpdate[OUT]	• 1 byte parameter indicating FOTA Automatic update – 0x00 - User permission required before updating firmware – 0x01 - No user permission required before updating firmware – 0x02 - User permission required, auto update on power up • function SLQSOMADMGetSettings2() returns a default value 0xFF in case this parameter is not returned by the modem.

pAutosdm[OUT]	• 1 byte parameter indicating OMA Automatic UI Alert Response – 0x00 - Disabled – 0x01 - Enabled Accept – 0x02 - Enabled Reject • function SLQSOMADMGetSettings2() returns a default value 0xFF in case this parameter is not returned by the modem.
pFwAutoCheck[-OUT]	• Optional 1 byte parameter indicating OMA Automatic Check for Firmware Update on Power-Up Response – 0x00 - Disabled – 0x01 - Enabled • function SLQSOMADMGetSettings2() returns a default value 0xFF in case this parameter is not returned by the modem.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.30.2.3 typedef struct _SLQSOMADMSettingsReqParams SLQSOMADMSettingsReqParams

Structure containing the OMA DM settings to be set on the device

Parameters

FOTAdownload	• 1 Byte parameter indicating support for FOTA Automatic download – 0x00 - Firmware auto download FALSE – 0x01 - Firmware auto download TRUE
FOTAUpdate	• 1 byte parameter indicating FOTA Automatic update – 0x00 - Firmware auto update FALSE – 0x01 - Firmware auto update TRUE
pAutosdm[IN]	• Optional 1 byte parameter indicating OMA Automatic UI Alert Response – 0x00 - Disabled – 0x01 - Enabled Accept – 0x02 - Enabled Reject

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.30.2.4 typedef struct _SLQSOMADMSettingsReqParams3 SLQSOMADMSettingsReqParams3

Structure containing the OMA DM settings to be set on the device

Parameters

FOTAdownload	• 1 Byte parameter indicating support for FOTA Automatic download – 0x00 - Firmware auto download FALSE – 0x01 - Firmware auto download TRUE
FOTAUpdate	• 1 byte parameter indicating FOTA Automatic update – 0x00 - Firmware auto update FALSE – 0x01 - Firmware auto update TRUE
pAutosdm[IN]	• Optional 1 byte parameter indicating OMA Automatic UI Alert Response – 0x00 - Disabled – 0x01 - Enabled Accept – 0x02 - Enabled Reject
pFwAutoCheck[-IN]	• Optional 1 byte parameter indicating OMA Automatic Check for Firmware Update on Power-Up Response – 0x00 - Disabled – 0x01 - Enabled

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.30.3 Function Documentation

9.30.3.1 ULONG SLQSOMADMCancelSession (ULONG *session*)

Cancels an ongoing OMA-DM session.

Parameters

session[IN]	• Session – 0x01 - FOTA, to check availability of FW Update – 0xFF - Cancel any active OMADM session

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.30.3.2 ULONG SLQSOMADMGetSessionInfo (ULONG * *pSessionType,* SLQSOMADMSessionInfo * *pResp*)

Returns information related to the current (or previous if no session is active) OMA-DM session.

Parameters

SessionType[IN]	• Session type – 0x01 - FOTA – 0xFF - Any active OMADM session. If none active, then previous OMADM session
pResp[IN/OUT]	• See SLQSOMADMSessionInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.30.3.3 ULONG SLQSOMADMGetSettings (ULONG * *pbOMADMEnabled,* ULONG * *pbFOTAdownload,* ULONG * *pbFOTAUpdate*)

Returns the OMA-DM settings.

Parameters

pbOMADM-Enabled[OUT]	• Device OMADM service enabled – 0x00000001 - Client-initiated device configuration – 0x00000002 - Network-initiated device configuration – 0x00000010 - Client-initiated FUMO – 0x00000020 - Network-initiated FUMO

pbFOTAdownload[OUT]	• Firmware AutoDownload – 0x00 - Firmware auto download FALSE – 0x01 - Firmware autod ownload TRUE – 0x02 - Automatically start downloading, while not roaming – 0x03 - Automatically reject download – 0x04 - Automatically reject download with “Enterprise Reject Policy”
pbFOTAUpdate[OUT]	• Firmware AutoUpdate – 0x00 - Firmware auto update FALSE – 0x01 - Firmware auto update TRUE

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.30.3.4 ULONG SLQSOMADMGetSettings2 (SLQSOMADMSettings * *pSLQSOMADMSettings*)

Retrieves the OMA-DM settings from the device.

Parameters

SLQSOMADMSettingsReqParams	• See SLQSOMADMSettings for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.30.3.5 ULONG SLQSOMADMSendSelection (ULONG *selection*)

Sends the specified OMA-DM selection for the current network initiated session.

Parameters

selection[IN]	• OMA-DM NIA Selection – 0x01 - Accept – 0x02 - Reject – 0x03 - Defer

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.30.3.6 ULONG SLQSOMADMSendSelection2 (ULONG *selection,* ULONG * *pDeferTime,* ULONG * *pRejectReason*)

Sends the specified OMA-DM selection for the current network initiated session.

Parameters

selection[IN]	• OMA-DM NIA Selection – 0x01 - Accept – 0x02 - Reject – 0x03 - Defer
pDeferTime[IN]	• Defer time in minutes. A value of 0 will cause the prompt to be resent immediately. • This TLV is mandatory if selection is set to 0x03.
pRejectReason[IN]	• Reject Reason • This TLV is processed if selection is set to 0x02. If it is not present, the reject reason 0 is used as default.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.30.3.7 ULONG SLQSOMADMSetSettings (ULONG *bFOTAdownload,* ULONG *bFOTAUpdate*)

Sets the OMA-DM settings requested.

Parameters

bFOTAdownload[IN]	• Firmware Auto Download – 0x00 - Host permission required before downloading – 0x01 - Automatically start downloading, no host permission required – 0x02 - Automatically start downloading, while not roaming – 0x03 - Automatically reject download – 0x04 - Automatically reject download with “Enterprise Reject Policy”
bFOTAUpdate[IN]	• Firmware Auto Update – 0x00 - User permission required before updating firmware – 0x01 - No user permission required before updating firmware – 0x02 - User permission required, auto update on power up

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.30.3.8 ULONG SLQSOMADMSetSettings2 (SLQSOMADMSettingsReqParams * *pSLQSOMADMSettingsReqParams*)

Sets the settings related to OMADM. These settings are saved on the modem across power cycles.

Parameters

pSLQSOMADMSettingsReqParams[IN]	• See SLQSOMADMSettingsReqParams for more information

Note

Timeout: 20 seconds

9.30.3.9 ULONG SLQSOMADMSetSettings3 (SLQSOMADMSettingsReqParams3 * *pSLQSOMADMSettingsReqParams3*)

Sets the settings related to OMADM. These settings are saved on the modem across power cycles.

Parameters

SLQSOMADM-SettingsReq-ParamsExt[IN]	• See SLQSOMADMSettingsReqParamsExt for more information

Note

Timeout: 20 seconds

9.30.3.10 ULONG SLQSOMADMStartSession (ULONG *sessionType*)

Starts an OMA-DM session.

Parameters

sessionType[IN]	• Session type – 0x01 - FOTA, to check availability of FW Update – 0x02 - DM, to check availability of DM Update – 0x03 - PRL, to check availability of PRL Update

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.30.3.11 ULONG SLQSOMADMStartSession2 (ULONG *sessionType,* ULONG * *pFwAvailability*)

Starts an OMA-DM session.

Parameters

sessionType[IN]	• Session type – 0x01 - FOTA, to check availability of FW Update – 0x02 - DM, to check availability of DM Update – 0x03 - PRL, to check availability of PRL Update
pFwAvailability[-OUT]	• OMA-DM CHECK FW Available – 0x00000001 - FW Available. For CIDC and CIPRL, this value will be returned by the modem. CIDC and CIPRL are asynchronous OMADM sessions. – 0x00000002 - FW Not Available – 0x00000003 - FW Check Timed Out

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.31 qaGobiApiTableBandClasses.h File Reference

Network Access Service API Band Classes table.

9.31.1 Detailed Description

Network Access Service API Band Classes table.

9.31.2 Band Classes (Value - Description)

- 0 - CDMA Band Class 0
- 1 - CDMA Band Class 1
- 3 - CDMA Band Class 3
- 4 - CDMA Band Class 4
- 5 - CDMA Band Class 5
- 6 - CDMA Band Class 6
- 7 - CDMA Band Class 7
- 8 - CDMA Band Class 8
- 9 - CDMA Band Class 9
- 10 - CDMA Band Class 10
- 11 - CDMA Band Class 11
- 12 - CDMA Band Class 12
- 13 - CDMA Band Class 13
- 14 - CDMA Band Class 14
- 15 - CDMA Band Class 15
- 16 - CDMA Band Class 16
- 17 - CDMA Band Class 17
- 18 - CDMA Band Class 18
- 19 - CDMA Band Class 19
- 40 - GSM 450

- 41 - GSM 480
- 42 - GSM 750
- 43 - GSM 850
- 44 - GSM 900 (Extended)
- 45 - GSM 900 (Primary)
- 46 - GSM 900 (Railways)
- 47 - GSM 1800
- 48 - GSM 1900
- 80 - WCDMA 2100
- 81 - WCDMA PCS 1900
- 82 - WCDMA DCS 1800
- 83 - WCDMA 1700 (US)
- 84 - WCDMA 850
- 85 - WCDMA 800
- 86 - WCDMA 2600
- 87 - WCDMA 900
- 88 - WCDMA 1700 (Japan)
- 90 - WCDMA 1500 band (Japan)
- 91 - WCDMA 850 band (Japan)
- < Reserved 89, 92-109 for WCDMA band classes>
- 110 - WLAN US 2400 MHz
- 111 - WLAN JAPAN 2400 MHz
- 112 - WLAN EUROPEAN 2400 MHz
- 113 - WLAN FRANCE 2400 MHz
- 114 - WLAN SPAIN 2400 MHz
- 115 - WLAN US 5000 MHz band
- 116 - WLAN JAPAN 5000 MHz
- 117 - WLAN EUROPEAN 5000 MHz
- 118 - WLAN FRANCE 5000 MHz
- 119 - WLAN SPAIN 5000 MHz

9.31.2.1 LTE Bands

- 28 - LTE Band Class 28
- 39 - LTE Band Class 39
- 40 - LTE Band Class 40
- 41 - LTE Band Class 41
- 120 - FDD UL:1920-1980; DL:2110-2170; E-UTRA Operating Band 1
- 121 - FDD UL:1850-1910; DL:1930-1990; E-UTRA Operating Band 2
- 122 - FDD UL:1710-1785; DL:1805-1880; E-UTRA Operating Band 3
- 123 - FDD UL:1710-1755; DL:2110-2155; E-UTRA Operating Band 4
- 124 - FDD UL: 824- 849; DL: 869- 894; E-UTRA Operating Band 5
- 125 - FDD UL: 830- 840; DL: 875- 885; E-UTRA Operating Band 6
- 126 - FDD UL:2500-2570; DL:2620-2690; E-UTRA Operating Band 7
- 127 - FDD UL: 880- 915; DL: 925- 960; E-UTRA Operating Band 8
- 128 - FDD UL:1749.9-1784.9; DL:1844.9-1879.9; E-UTRA Operating Band 9
- 129 - FDD UL:1710-1770; DL:2110-2170; E-UTRA Operating Band 10
- 130 - FDD UL:1427.9-1452.9; DL:1475.9-1500.9; E-UTRA Operating Band 11
- 131 - FDD UL:698-716; DL:728-746; E-UTRA Operating Band 12
- 132 - FDD UL: 777- 787; DL: 746-756; E-UTRA Operating Band 13
- 133 - FDD UL: 788- 798; DL: 758-768; E-UTRA Operating Band 14
- 134 - FDD UL: 704-716; DL: 734-746; E-UTRA Operating Band 17
- 135 - TDD LTE UL: 1900-1920; DL: 1900-1920; E-UTRA Operating Band 33
- 136 - TDD LTE UL: 2010-2025; DL: 2010-2025; E-UTRA Operating Band 34
- 137 - TDD LTE UL: 1850-1910; DL: 1850-1910; E-UTRA Operating Band 35
- 138 - TDD LTE UL: 1930-1990; DL: 1930-1990; E-UTRA Operating Band 36
- 139 - TDD LTE UL: 1910-1930; DL: 1910-1930; E-UTRA Operating Band 37
- 140 - TDD LTE UL: 2570-2620; DL: 2570-2620; E-UTRA Operating Band 38
- 141 - TDD LTE UL: 1880-1920; DL: 1880-1920; E-UTRA Operating Band 39
- 142 - TDD LTE UL: 2300-2400; DL: 2300-2400; E-UTRA Operating Band 40
- 143 - FDD LTE UL: 815-830; DL: 860-875; E-UTRA Operating Band 18
- 144 - FDD LTE UL: 830-845; DL: 875-890; E-UTRA Operating Band 19
- 145 - FDD LTE UL: 832-862; DL: 791-821; E-UTRA Operating Band 20
- 146 - FDD LTE UL: 1447.9-1462.9; DL: 1495.9-1510.9; E-UTRA Operating Band 21
- 147 - FDD LTE UL: 1626.5-1660.5; DL: 1525-1559; E-UTRA Operating Band 24
- 148 - FDD LTE UL: 1850-19195; DL: 1930-1995; E-UTRA Operating Band 25
- 149 - TDD LTE UL: 2496-2690; DL: 2496-2690; E-UTRA Operating Band 41

- 150 - TDD LTE UL: 3400-3600; DL: 3400-3600; E-UTRA Operating Band 42
- 151 - TDD LTE UL: 3600-3800; DL: 3600-3800; E-UTRA Operating Band 43
- 152 - E-UTRA Operating Band 23
- 153 - E-UTRA Operating Band 26
- 154 - E-UTRA Operating Band 32
- 155 - E-UTRA Operating Band 125
- 156 - E-UTRA Operating Band 126
- 157 - E-UTRA Operating Band 127
- 158 - E-UTRA Operating Band 28
- 159 - E-UTRA Operating Band 29
- 160 - E-UTRA Operating Band 30
- 161 - E-UTRA Operating Band 66
- 162 - E-UTRA Operating Band 250
- 163 - E-UTRA Operating Band 46
- 164 - E-UTRA Operating Band 27
- 165 - E-UTRA Operating Band 31
- 166 - E-UTRA Operating Band 71
- 167 - E-UTRA Operating Band 47
- 168 - E-UTRA Operating Band 48
- 200 - TD-SCDMA Band A
- 201 - TD-SCDMA Band B
- 202 - TD-SCDMA Band C
- 203 - TD-SCDMA Band D
- 204 - TD-SCDMA Band E
- 205 - TD-SCDMA Band F
- 250 - NR5G Band 1
- 251 - NR5G Band 2

Copyright: © 2018 Sierra Wireless, Inc. all rights reserved

9.32 qaGobiApiTableCallControlReturnReasons.h File Reference

Call Control Return Reasons table.

9.32.1 Detailed Description

Call Control Return Reasons table.

9.32.2 S1

- 0x01 - QMI_VOICE_REASON_FWD_UNCONDITIONAL - Unconditional call forwarding
- 0x02 - QMI_VOICE_REASON_FWD_MOBILEBUSY - Forward when the mobile is busy
- 0x03 - QMI_VOICE_REASON_FWD_NOREPLY - Forward when there is no reply
- 0x04 - QMI_VOICE_REASON_FWD_UNREACHABLE - Forward when the call is unreachable
- 0x05 - QMI_VOICE_REASON_FWD_ALLFORWARDING - All forwarding
- 0x06 - QMI_VOICE_REASON_FWD_ALLCONDITIONAL - All conditional forwarding
- 0x07 - QMI_VOICE_REASON_BARR_ALLOUTGOING - All outgoing
- 0x08 - QMI_VOICE_REASON_BARR_OUTGOINGINT - Outgoing internal
- 0x09 - QMI_VOICE_REASON_BARR_OUTGOINGINTEXTOHOME - Outgoing external to home
- 0x0A - QMI_VOICE_REASON_BARR_ALLINCOMING - All incoming
- 0x0B - QMI_VOICE_REASON_BARR_INCOMINGROAMING - Roaming incoming
- 0x0C - QMI_VOICE_REASON_BARR_ALLBARRING - All calls are barred
- 0x0D - QMI_VOICE_REASON_BARR_ALLOUTGOINGBARRING - All outgoing calls are barred
- 0x0E - QMI_VOICE_REASON_BARR_ALLINCOMINGBARRING - All incoming calls are barred
- 0x0F - QMI_VOICE_REASON_CALLWAITING - Call waiting
- 0x10 - VOICE_CC_SUPS_RESULT_REASON_CLIP - CLIP
- 0x11 - VOICE_CC_SUPS_RESULT_REASON_CLIR - CLIR
- 0x12 - VOICE_CC_SUPS_RESULT_REASON_COLP - COLP
- 0x13 - VOICE_CC_SUPS_RESULT_REASON_COLR - COLR
- 0x14 - VOICE_CC_SUPS_RESULT_REASON_CNAP - CNAP
- 0xFF - Not Available

Copyright: © 2012 Sierra Wireless, Inc. all rights reserved

9.33 qaGobiApiTableCallEndReasons.h File Reference

Wireless Data Service Call End Reasons.

9.33.1 Detailed Description

Wireless Data Service Call End Reasons.

9.33.2 Call end reason codes (Code - Reason)

9.33.2.1 Technology-agnostic call end reasons

- 1 - Reason unspecified, check the verbose call end reason
- 2 - Client ended the call
- 3 - Device has no service
- 4 - Call ended abnormally
- 5 - Received release from base station; no reason given
- 6 - Access attempt already in progress; SD2.0 only
- 7 - Access failure for reason other than the above
- 8 - Call rejected because of redirection or handoff
- 9 - Call failed because close is in progress
- 10 - Authentication failed, 3GPP equivalent ESM(EPS Session Management) cause code value 29, User authentication failed
- 11 - Call ended because of internal call end. This error code is returned when data call is brought down due to some unknown error, such as not specific to any RAT
- 12 - Call ended because of internal error. This error code is returned when data call is brought down due to some unspecified internal error, such as NULL pointer
- 13 - Internal unknown cause code

9.33.2.2 EVDO CDMA 1xEV-DO

- 500 - Device is CDMA-locked until power cycle
- 501 - Received intercept from base station; origination only
- 502 - Received reorder from base station; origination only
- 503 - Received release from base station; service option reject
- 504 - Received incoming call from base station
- 505 - Received alert stop from base station; incoming only
- 506 - Received end activation; OTASP call only
- 507 - Max access probes transmitted
- 508 - Concurrent service is not supported by base station
- 509 - No response received from base station
- 510 - Call rejected by the base station; CDMA only
- 511 - Concurrent services requested were not compatible; CDMA only
- 512 - Corresponds to CM CALL ORIG ERR ALREADY IN TC
- 513 - Used if Call manager subsystem is ending a GPS call in favor of a user call
- 514 - Used if Call manager subsystem is ending a SMS call in favor of a user call
- 515 - CDMA Only; Device has no service

9.33.2.3 WCDMA/GSM call end reasons

- 1000 - Call origination request failed; WCDMA/GSM Only
- 1001 - Client rejected the incoming call; WCDMA/GSM Only
- 1002 - Device has no UMTS service; WCDMA/GSM Only
- 1003 - Network ended the call, look in cc call; WCDMA/GSM Only
- 1004 - LLC(Logical Link Control) or SNDCP(Sub Network Dependent Convergence Protocol) failure
- 1005 - Insufficient resources, 3GPP equivalent ESM(EPS Session Management) cause code value 26, Insufficient resources
- 1006 - Service option temporarily out of order, 3GPP equivalent ESM(EPS Session Management) cause code value 34, Service option temporarily out of order
- 1007 - PTI already used, 3GPP equivalent ESM(EPS Session Management) cause code value 35, PTI(-Procedure Transaction Identity) already in use
- 1008 - Regular PDP context deactivation, 3GPP equivalent ESM(EPS Session Management) cause code value 36, Regular deactivation
- 1009 - Network failure, 3GPP equivalent ESM(EPS Session Management) cause code value 38, Network failure
- 1010 - Reactivation requested, 3GPP equivalent ESM(EPS Session Management) cause code value 39, Reactivation requested
- 1011 - Protocol error, unspecified, 3GPP equivalent ESM(EPS Session Management) cause code value 111, Protocol error, unspecified
- 1012 - Operator determined barring, 3GPP equivalent ESM(EPS Session Management) cause code value 8, Operator Determined Barring
- 1013 - Unknown or missing Access Point Name (APN), 3GPP equivalent ESM(EPS Session Management) cause code value 27, Missing or unknown APN
- 1014 - Unknown PDP address or PDP type, 3GPP equivalent ESM(EPS Session Management) cause code value 28, Unknown PDN type
- 1015 - Activation rejected by GGSN, 3GPP equivalent ESM(EPS Session Management) cause code value 30, Requested rejected by Serving GW or PDN GW
- 1016 - Activation rejected, unspecified, 3GPP equivalent ESM(EPS Session Management) cause code value 31, Request rejected, unspecified
- 1017 - Service option not supported, 3GPP equivalent ESM(EPS Session Management) cause code value 32, Service option not supported
- 1018 - Requested service option not subscribed, 3GPP equivalent ESM(EPS Session Management) cause code value 33, Requested service option not subscribed
- 1019 - EPS Quality of Service (QoS) not accepted, 3GPP equivalent ESM(EPS Session Management) cause code value 37, EPS QoS not accepted
- 1020 - Semantic error in the TFT operation, 3GPP equivalent ESM(EPS Session Management) cause code value 41, Semantic error in the TFT operation
- 1021 - Syntactical error in the TFT operation, 3GPP equivalent ESM(EPS Session Management) cause code value 42, Syntactical error in the TFT operation
- 1022 - Unknown PDP context, 3GPP equivalent ESM(EPS Session Management) cause code value 43, Invalid EPS bearer identity

- 1023 - Semantic errors in packet filter(s), 3GPP equivalent ESM(EPS Session Management) cause code value 44, Semantic errors in packet filter(s)
- 1024 - Syntactical error in packet filter(s), 3GPP equivalent ESM(EPS Session Management) cause code value 45, Syntactical errors in packet filter(s)
- 1025 - PDP context without TFT already activated, 3GPP equivalent ESM(EPS Session Management) cause code value 46, Unused
- 1026 - Invalid transaction identifier value, 3GPP equivalent ESM(EPS Session Management) cause code value 81, Invalid PTI value
- 1027 - Semantically incorrect message, 3GPP equivalent ESM(EPS Session Management) cause code value 95, Semantically incorrect message
- 1028 - Invalid mandatory information, 3GPP equivalent ESM(EPS Session Management) cause code value 96, Invalid mandatory information
- 1029 - Message type non-existent or not implemented, 3GPP equivalent ESM(EPS Session Management) cause code value 97, Message type non-existent or not implemented
- 1030 - Message not compatible with state, 3GPP equivalent ESM(EPS Session Management) cause code value 98, Message type not compatible with the protocol state
- 1031 - Information element nonexistent or not implemented, 3GPP equivalent ESM(EPS Session Management) cause code value 99, Information element non-existent or not implemented
- 1032 - Conditional information element error, 3GPP equivalent ESM(EPS Session Management) cause code value 100, Conditional IE error
- 1033 - Message not compatible with protocol state, 3GPP equivalent ESM(EPS Session Management) cause code value 101, Message not compatible with the protocol state
- 1034 - APN restriction value incompatible with active PDP context, 3GPP equivalent ESM(EPS Session Management) cause code value 112, APN restriction value incompatible with
  - active EPS bearer context
- 1035 - No GPRS context present
- 1036 - Requested feature not supported, 3GPP equivalent ESM(EPS Session Management) cause code value 40, Feature not supported
- 1037 - Illegal MS, 3GPP equivalent EMM(EPS Mobility Management) cause code value 3, Illegal UE (MS)
- 1038 - Illegal ME, 3GPP equivalent EMM(EPS Mobility Management) cause code value 6, Illegal ME. This error code is sent to the MS if the ME used is not acceptable
  - to the network, e.g. blacklisted
- 1039 - GPRS and non GPRS services not allowed
- 1040 - GPRS services not allowed
- 1041 - MS identity not derived by the network, 3GPP equivalent EMM(EPS Mobility Management) cause code value 9, UE (MS) Identify cannot be derived by the network
- 1042 - Implicitly detached, 3GPP equivalent EMM(EPS Mobility Management) cause code value 10, Implicitly Detached
- 1043 - PLMN not allowed, 3GPP equivalent EMM(EPS Mobility Management) cause code value 11, PLMN not allowed
- 1044 - LA not allowed, this cause is sent to the MS if it requests location updating in a location area where the HPLMN determines that the MS, by subscription, is not allowed to operate.
- 1045 - GPRS services not allowed in PLMN

- 1046 - PDP duplicate
- 1047 - UE radio access technology change
- 1048 - app preempted
- 1049 - Congestion, This cause is sent if the service request or LOCATION UPDATING REQUEST message cannot be actioned because of congestion (e.g. congestion of the MSC or SGSN or GGSN or PDN Gateway; no channel; facility busy/congested etc.).
- 1050 - No PDP context activated
- 1051 - Access class DSAC rejection

9.33.2.4 EVDO CDMA 1xEV-DO

- 1500 - Abort connection setup due to the reception of a Connection Deny message with deny code set to either general or network busy.
- 1501 - Abort connection setup due to the reception of a Connection Deny message with deny code set to either billing or authentication failure.
- 1502 - Change HDR system due to redirection or PRL not preferred
- 1503 - Exit HDR due to redirection or PRL not preferred
- 1504 - No HDR session
- 1505 - Used if Call manager is ending an HDR call origination in favor of a GPS fix
- 1506 - Connection setup timeout
- 1507 - Call manager released HDR call so 1x call can continue

9.33.2.5 call end reason type

- 1 - Mobile IP
- 2 - Internal
- 3 - Call Manager defined
- 6 - 3GPP specification defined
- 7 - PPP
- 8 - EHRPD
- 9 - IPv6

9.33.2.6 Mobile IP call end reasons (Type=1)

- 64 - MIP(Mobile IP) FA(Foreign Agent) ERR REASON UNSPECIFIED, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration with unspecified reason
- 65 - MIP(Mobile IP) FA(Foreign Agent) ERR ADMINISTRATIVELY PROHIBITED, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent administratively prohibited MIP registration
- 66 - MIP(Mobile IP) FA(Foreign Agent) ERR INSUFFICIENT RESOURCES, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration due to insufficient resources

- 67 - MIP(Mobile IP) FA(Foreign Agent) ERR MOBILE NODE AUTHENTICATION FAILURE, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration because MN-AAA authenticator was wrong
- 68 - MIP(Mobile IP) FA(Foreign Agent) ERR HA AUTHENTICATION FAILURE, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration because of home agent authentication failure
- 69 - MIP(Mobile IP) FA(Foreign Agent) ERR REQUESTED LIFETIME TOO LONG, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration because requested lifetime is too long
- 70 - MIP(Mobile IP) FA(Foreign Agent) ERR MALFORMED REQUEST, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration due to malformed request
- 71 - MIP(Mobile IP) FA(Foreign Agent) ERR MALFORMED REPLY, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration due to malformed reply
- 72 - MIP(Mobile IP) FA(Foreign Agent) ERR ENCAPSULATION UNAVAILABLE, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration because requested encapsulation is unavailable
- 73 - MIP(Mobile IP) FA(Foreign Agent) ERR VJHC UNAVAILABLE, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration because VJ Header Compression is unavailable
- 74 - MIP(Mobile IP) FA(Foreign Agent) ERR REVERSE TUNNEL UNAVAILABLE, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration because reverse tunnel is unavailable
- 75 - MIP(Mobile IP) FA(Foreign Agent) ERR REVERSE TUNNEL IS MANDATORY AND T BIT NOT SET, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration because reverse tunnel is mandatory but not requested by device
- 79 - MIP(Mobile IP) FA(Foreign Agent) ERR DELIVERY STYLE NOT SUPPORTED, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration because delivery style is not supported
- 97 - MIP(Mobile IP) FA(Foreign Agent) ERR MISSING NAI, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration due to missing NAI
- 98 - MIP(Mobile IP) FA(Foreign Agent) ERR MISSING HA, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration due to missing Home Agent
- 99 - MIP(Mobile IP) FA(Foreign Agent) ERR MISSING HOME ADDR, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration due to missing Home Address
- 104 - MIP(Mobile IP) FA(Foreign Agent) ERR UNKNOWN CHALLENGE, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration due to unknown challenge
- 105 - MIP(Mobile IP) FA(Foreign Agent) ERR MISSING CHALLENGE, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration due to missing challenge
- 106 - MIP(Mobile IP) FA(Foreign Agent) ERR STALE CHALLENGE, this error code is returned when the data call bring up fails in MIP setup phase since foreign agent rejected MIP registration due to stale challenge
- 128 - MIP(Mobile IP) FA(Home Agent) ERR REASON UNSPECIFIED, this error code is returned when the data call bring up fails in MIP setup phase since home agent rejected MIP registration with unspecified reason

- 129 - MIP(Mobile IP) FA(Home Agent) ERR ADMINISTRATIVELY PROHIBITED, this error code is returned when the data call bring up fails in MIP setup phase since home agent administratively prohibited MIP registration
- 130 - MIP(Mobile IP) FA(Home Agent) ERR INSUFFICIENT RESOURCES, this error code is returned when the data call bring up fails in MIP setup phase since home agent rejected MIP registration due to insufficient resources
- 131 - MIP(Mobile IP) FA(Home Agent) ERR MOBILE NODE AUTHENTICATION FAILURE, this error code is returned when the data call bring up fails in MIP setup phase since home agent fails authentication because MN-HA authenticator was wrong
- 132 - MIP(Mobile IP) FA(Home Agent) ERR FA AUTHENTICATION FAILURE, this error code is returned when the data call bring up fails in MIP setup phase since home agent rejected MIP registration due to FA authentication failure
- 133 - MIP(Mobile IP) FA(Home Agent) ERR REGISTRATION ID MISMATCH, this error code is returned when the data call bring up fails in MIP setup phase since home agent rejected MIP registration due to registration id mismatch
- 134 - MIP(Mobile IP) FA(Home Agent) ERR MALFORMED REQUEST, this error code is returned when the data call bring up fails in MIP setup phase since home agent rejected MIP registration due to malformed request
- 136 - MIP(Mobile IP) FA(Home Agent) ERR UNKNOWN HA ADDR, this error code is returned when the data call bring up fails in MIP setup phase since home agent rejected MIP registration due to unknown Home Agent address. This code is returned by a home agent when the mobile node is performing dynamic home agent address resolution as described in RFC 3220 (IP Mobility Support for IPV4) Sections 3.6.1.1 and 3.6.1.2
- 137 - MIP(Mobile IP) FA(Home Agent) ERR REVERSE TUNNEL UNAVAILABLE, this error code is returned when the data call bring up fails in MIP setup phase since home agent rejected MIP registration because reverse tunnel is unavailable
- 138 - MIP(Mobile IP) FA(Home Agent) ERR REVERSE TUNNEL IS MANDATORY AND T BIT NOT SET, this error code is returned when the data call bring up fails in MIP setup phase since home agent rejected MIP registration because reverse tunnel is mandatory but not requested by device
- 139 - MIP(Mobile IP) FA(Home Agent) ERR ENCAPSULATION UNAVAILABLE, this error code is returned when the data call bring up fails in MIP setup phase since home agent rejected MIP registration due to encapsulation unavailable
- 65536 - MIP ERR REASON UNKNOWN

9.33.2.7 Internal call end reasons (Type=2)

- 200 - INTERNAL MIN, internal error table offset value, no meaningful message to the error.
- 201 - INTERNAL ERROR, this error code is returned when data call is brought down due to some unspecified internal error
- 202 - CALL ENDED
- 203 - INTERNAL UNKNOWN CAUSE CODE, this error code is returned when data call is brought down due to some unknown error
- 204 - UNKNOWN CAUSE CODE, this error code is returned when data call is brought down due to some unknown error
- 205 - CLOSE IN PROGRESS
- 206 - NETWORK INITIATED TERMINATION
- 207 - APP PREEMPTED

- 208 - ERR PDN IPV4 CALL DISALLOWED, this error code is returned when V4 PDN is in throttled state due to network providing only V6 address during the previous VSNCP bring up (subs_limited_to_v6). The time for which the IPv4 PDN is throttled is determined by the IPv4 throttling timers maintained in the profile
- 209 - ERR PDN IPV4 CALL THROTTLED, this error code is returned when V4 PDN is in throttled state due to previous VSNCP bring up failure(s). The time for which the IPv4 PDN is throttled is determined by the IPv4 throttling timers maintained in the profile
- 210 - ERR PDN IPV6 CALL DISALLOWED, this error code is returned when V6 PDN is in throttled state due to network providing only V4 address during the previous VSNCP bring up (subs_limited_to_v4). The time for which the IPv6 PDN is throttled is determined by the IPv6 throttling timers maintained in the profile
- 211 - ERR PDN IPV6 CALL THROTTLED, this error code is returned when V6 PDN is in throttled state due to previous VSNCP bring up failure(s). The time for which the IPv6 PDN is throttled is determined by the IPv6 throttling timers maintained in the profile
- 212 - MODEM RESTART
- 213 - PDP PPP NOT SUPPORTED
- 214 - UNPREFERRED RAT, this error code is returned when data call is brought down since the RAT on which the data call is attempted/connected is no longer the preferred RAT
- 215 - PHYS LINK CLOSE IN PROGRESS, this error code is returned when data call bring up is rejected because physical link is in the process of cleanup
- 216 - APN PENDING HANDOVER, this error code is returned when interface bring up is attempted for an APN that is yet to be handed over to target RAT
- 217 - PROFILE BEARER INCOMPATIBLE
- 218 - MMGSDI CARD EVT, this error code is returned when data call is brought down because card got refreshed/removed
- 219 - LPM OR PWR DOWN, this error code is returned when data call is brought down because device is going into lower power mode or powering down
- 220 - APN DISABLED, this error code is returned when APN is disabled in card
- 221 - MPIT EXPIRED, this error code is returned when data call is brought down because maximum PPP inactivity timer expired
- 222 - IPV6 ADDR TRANSFER FAILED
- 223 - TRAT SWAP FAILED
- 224 - EHRPD TO HRPD FALLBACK, this error code is returned when data call is brought down because device falls back from eHRPD to HRPD (not because of OOS on eHRPD but due to operator/spec driven eHRPD to HRPD fallback requirements)
- 225 - MANDATORY APN DISABLED, this error code is returned when any mandatory APN is disabled, and MinApnList Disallow call config item is set to TRUE in device
- 226 - MIP CONFIG FAILURE, this error code is returned when UE is in MIP Only config (QCMIP=2) but MIP config fails on call bring up due to incorrect provisioning
- 227 - INTERNAL_PDN_INACTIVITY_TIMER_EXPIRED, this error code is returned when PDN inactivity timer expired due to no data transmission in a configurable duration of time
- 228 - MAX_V4_CONNECTIONS, this error code is returned when IPv4 data call bring up is rejected because the UE already maintains the allotted maximum number of IPv4 data connections
- 229 - MAX_V6_CONNECTIONS, this error code is returned when IPv6 data call bring up is rejected because the UE already maintains the allotted maximum number of IPv6 data connections

- 230 - APN_MISMATCH, this error code is returned when New PDN bring up is rejected during interface selection because the UE has already allotted the available interfaces for other PDNs
- 231 - IP_VERSION_MISMATCH, this error code is returned when New call bring up is rejected because the existing data call IP type does not match the requested IP type
- 232 - DUN_CALL_DISALLOWED, this error code is returned when DUN call bring up is rejected because the UE is in eHRPD RAT
- 233 - INVALID_PROFILE, this error code is returned when Call bring up was requested with an invalid profile
- 234 - INTERNAL_EPC_NONEPC_TRANSITION, this error code is returned when Data call is rejected or brought down because the UE is in transition between EPC and non-EPC RAT
- 235 - INVALID_PROFILE_ID, this error code is returned when Call bring up was requested with an invalid profile ID
- 236 - INTERNAL_CALL_ALREADY_PRESENT, this error code is returned when a data call with the same policy is already connected or in the process of bring up on another RmNet instance
- 237 - IFACE_IN_USE, this error code is returned when the current IFACE is in use
- 238 - IP_PDP_MISMATCH, this error code is returned when a PPP call is attempted on a PDP profile
- 239 - APN_DISALLOWED_ON_ROAMING, this error code is returned when PDN connection to the APN is disallowed on the roaming network. The DS generates DS_SYS_EVENT_3GPP_ROAMING_DISALLOWED_INFO to inform clients of the APNs that must deregister and disconnect (if the PDN is up) while the UE is on the roaming network. Clients must deregister or disconnect if the APN name corresponding to the client is listed in this system event. Clients can register again if the APN name corresponding to the client is not listed in this system event.
- 240 - APN_PARAM_CHANGE, this error code is returned when Failure to reestablish the PDN with the changed parameters; when APN-related parameters are changed, the PDN associated with the parameters must be brought down and reestablished with the changed parameters
- 241 - IFACE_IN_USE_CFG_MATCH, this error code is returned when the IFACE is already in use with a matching configuration
- 242 - NULL_APN_DISALLOWED, this error code is returned when a PDN is attempted to be brought up with a NULL APN and when a NULL APN is not supported
- 243 - THERMAL_MITIGATION, this error code is returned when the thermal level increases and causes calls to be torn down when normal mode of operation is not allowed
- 244 - SUBS_ID_MISMATCH, this error code is returned when a new call bring up is rejected due to a mismatch between the subs_id in the profile and the subs_id in the ACL policy information
- 245 - DATA_SETTINGS_DISABLED, this error code is returned when the PDN connection to a given APN is disallowed because data is disabled from the device user interface (UI) settings
- 246 - DATA_ROAMING_SETTINGS_DISABLED, this error code is returned when the PDN Connection to a given APN is disallowed because data roaming is disabled from the device UI settings and the UE is roaming
- 247 - APN_FORMAT_INVALID, this error code is returned when the APN specified in the policy does not follow the format specified in the 3GPP Specification
- 248 - DDS_CALL_ABORT, this error code is returned when a DDS switch occurs; the data call is brought down with the DDS abort reason
- 249 - VALIDATION_FAILURE, this error code is returned when a data call is brought down due to an internal validation failure

9.33.2.8 Call Manager defined call end reasons (Type=3)

- 500 - CDMA LOCK, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to device in CDMA locked state
- 501 - INTERCEPT, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since it received an intercept order from the base station
- 502 - REORDER, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) due to receiving a reorder from base station
- 503 - REL SO REJ, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to receiving a release from base station with reason: SO Reject
- 504 - INCOM CALL, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since it received an incoming call from base station
- 505 - ALERT STOP, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to RL/FL fade (or) receiving call release from base stations
- 506 - ACTIVATION, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to channel acquisition failures. This indicates that device has failed acquiring all the channels in the PRL
- 507 - MAX ACCESS PROBE, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) due maximum access probes transmitted
- 508 - CCS NOT SUPPORTED BY BS, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since concurrent service is not supported by base station
- 509 - NO RESPONSE FROM BS, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since there is no response received from base station
- 510 - REJECTED BY BS, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) due to base station rejecting the call
- 511 - INCOMPATIBLE, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since concurrent services requested were not compatible
- 512 - ALREADY IN TC, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since traffic channel is already up for voice calls
- 513 - USER CAL ORIG DURING GPS
- 514 - USER CAL ORIG DURING SMS, this error code is returned when data call is brought down because traffic channel request got rejected since SMS is ongoing
- 515 - NO CDMA SRV, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since device does not have CDMA service
- 516 - MC ABORT, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since MC aborted the origination/conversation
- 517 - PSIST NG, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to persistence test failure
- 518 - UIM NOT PRESENT, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to RUIM not present
- 519 - RETRY ORDER, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) due to receiving a retry order from base station
- 520 - ACCESS BLOCK, this error code is returned when data call is brought down because traffic channel rejected/released due to Access blocked by base station

- 521 - ACCESS BLOCK ALL, this error code is returned when data call is brought down because traffic channel rejected due to Access blocked by the base station for all mobile devices
- 522 - IS707B MAX ACC, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) due maximum access probes for IS-707B call
- 523 - THERMAL EMERGENCY, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) to put device in thermal emergency
- 524 - CALL ORIG THROTTLED, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since call origination is throttled by DCTM module
- 535 - USER CALL ORIGINATE DURING VOICE CALL, this error code is returned when data call is brought down because traffic channel got released by CM(Call Manager) in favor of voice call or SMS when concurrent voice and data are not supported
- 1000 - CONFERENCE FAILED
- 1001 - INCOMING REJECTED
- 1002 - NO GATEWAY SERVICE
- 1003 - NO GPRS CONTEXT
- 1004 - ILLEGAL MS, This cause is sent to the MS when the network refuses service to the MS either because an identity of the MS is not acceptable to the network or because the MS does not pass the authentication check, i.e. the SRES received from the MS is different from that generated by the network
- 1005 - ILLEGAL ME, This cause is sent to the MS if the ME used is not acceptable to the network, e.g. blacklisted
- 1006 - GPRS SERVICES AND NON GPRS SERVICES NOT ALLOWED
- 1007 - GPRS SERVICES NOT ALLOWED
- 1008 - MS IDENTITY CANNOT BE DERIVED BY THE NETWORK
- 1009 - IMPLICITLY DETACHED, this error code is sent to the MS either if the network has implicitly detached the MS, e.g. some while after the Mobile reachable timer has expired, or if the GMM context data related to the subscription does not exist in the SGSN e.g. because of a SGSN restart.
- 1010 - PLMN NOT ALLOWED, this error code is sent to the MS if it requests location updating in a PLMN where the MS, by subscription or due to operator determined barring is not allowed to operate
- 1011 - LOCAL AREA NOT ALLOWED
- 1012 - GPRS SERVICES NOT ALLOWED IN THIS PLMN
- 1013 - PDP DUPLICATE
- 1014 - USER EQUIPMENT RADIO ACCESS TECHNOLOGY CHANGE
- 1015 - CONGESTION
- 1016 - NO PDP CONEXT ACTIVATED
- 1017 - ACCESS CLASS DSAC REJECTION
- 1018 - PDP ACTIVATE MAX RETRY FAILED
- 1019 - RAB FAILURE
- 1020 - EPS SERVICE NOT ALLOWED
- 1021 - TRACKING AREA NOT ALLOWED
- 1022 - ROAMING NOT ALLOWED IN THIS TRACKING AREA

- 1023 - NO SUITABLE CELLS IN TRACKING AREA
- 1024 - NOT AUTHORIZED FOR THIS CLOSED SUBSCRIBER GROUP
- 1025 - ESM UNKNOWN EPS BEARER CONTEXT
- 1026 - DRB RELEASED AT RRC
- 1027 - NAS SIG CONN RELEASED
- 1028 - EPS MOBILITY MANAGEMENT DETACHED
- 1029 - EPS MOBILITY MANAGEMENT ATTACH FAILED
- 1030 - EPS MOBILITY MANAGEMENT ATTACH STARTED
- 1031 - LTE NAS SERVICE REQ FAILED
- 1032 - ESM(EPS Session Management) ACTIVE DEDICATED BEARER REACTIVATED BY NW
- 1033 - ESM(EPS Session Management) LOWER LAYER FAILURE
- 1034 - ESM(EPS Session Management) SYNC UP WITH NW
- 1035 - ESM(EPS Session Management) NW ACTIVATED DED BEARER WITH ID OF DEF BEARER
- 1036 - ESM(EPS Session Management) BAD OTA MESSAGE
- 1037 - ESM DS REJECTED THE CALL
- 1038 - ESM(EPS Session Management) CONTEXT TRANSFERRED DUE TO IRAT
- 1039 - DS EXPLICIT DEACT
- 1040 - ESM(EPS Session Management) LOCAL CAUSE NONE
- 1041 - LTE NAS SERVICE REQ FAILED NO THROTTLE
- 1042 - ACL FAILURE, This error code should rarely triggered and reported to the application
- 1043 - LTE NAS SERVICE REQ FAILED DS DISALLOW
- 1044 - EMM(EPS Mobility Management) T3417 EXPIRED
- 1045 - EMM(EPS Mobility Management) T3417 EXT EXPIRED
- 1046 - LRRC(LTE Radio Resource Control) UL DATA CNF FAILURE TXN - Light Radio Resource Controller Uplink data confirmation failure
- 1047 - LRRC(LTE Radio Resource Control) UL DATA CNF FAILURE HO
- 1048 - LRRC(LTE Radio Resource Control) UL DATA CNF FAILURE CONN REL
- 1049 - LRRC(LTE Radio Resource Control) UL DATA CNF FAILURE RLF
- 1050 - LRRC(LTE Radio Resource Control) UL DATA CNF FAILURE CTRL NOT CONN
- 1051 - LRRC(LTE Radio Resource Control) CONN EST FAILURE
- 1052 - LRRC(LTE Radio Resource Control) CONN EST FAILURE ABORTED
- 1053 - LRRC(LTE Radio Resource Control) CONN EST FAILURE ACCESS BARRED
- 1054 - LRRC(LTE Radio Resource Control) CONN EST FAILURE CELL RESEL
- 1055 - LRRC(LTE Radio Resource Control) CONN EST FAILURE CONFIG FAILURE
- 1056 - LRRC(LTE Radio Resource Control) CONN EST FAILURE TIMER EXPIRED
- 1057 - LRRC(LTE Radio Resource Control) CONN EST FAILURE LINK FAILURE

- 1058 - LRRC(LTE Radio Resource Control) CONN EST FAILURE NOT CAMPED
- 1059 - LRRC(LTE Radio Resource Control) CONN EST FAILURE SI FAILURE
- 1060 - LRRC(LTE Radio Resource Control) CONN EST FAILURE CONN REJECT
- 1061 - LRRC(LTE Radio Resource Control) CONN REL NORMAL
- 1062 - LRRC(LTE Radio Resource Control) CONN REL RLF
- 1063 - LRRC(LTE Radio Resource Control) CONN REL CRE FAILURE
- 1064 - LRRC(LTE Radio Resource Control) CONN REL OOS DURING CRE
- 1065 - LRRC(LTE Radio Resource Control) CONN REL ABORTED
- 1066 - LRRC(LTE Radio Resource Control) CONN REL SIB READ ERROR
- 1067 - DETACH WITH REATTACH LTE NW DETACH
- 1068 - DETACH WITH OUT REATTACH LTE NW DETACH
- 1069 - ESM(EPS Session Management) PROC TIME OUT
- 1070 - MESSAGE EXCEED MAX L2 LIMIT
- 1500 - CD GEN OR BUSY, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to the reception of a Connection Deny message with a deny code of general or network busy
- 1501 - CD BILL OR AUTH, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to the reception of a Connection Deny message with a deny code of billing failure or authentication failure
- 1502 - CHG HDR, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since there is a change to HDR system due to redirection or PRL not preferred
- 1503 - EXIT HDR, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since device exited HDR due to redirection or PRL not preferred
- 1504 - HDR NO SESSION, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since device does not have a HDR session
- 1505 - HDR ORIG DURING GPS FIX, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since it is ending an HDR call origination in favor of a GPS fix
- 1506 - HDR CS TIMEOUT, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since connection setup on HDR system timed out
- 1507 - HDR RELEASED BY CM, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) when it wants to release a HDR call so a 1X call can continue
- 1508 - COLLOC ACQ FAIL, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) when device failed to acquire co-located HDR for origination
- 1509 - OTASP COMMIT IN PROG, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since an OTASP commit is in progress
- 1510 - NO HYBR HDR SRV, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since device has no Hybrid HDR service
- 1511 - HDR NO LOCK GRANTED, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since HDR module could not get the RF lock

- 1512 - HOLD OTHER IN PROG, this error code is returned when data call is brought down by CM(Call Manager) because DBM or SMS is in progress
- 1513 - HDR FADE, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since HDR module released the call due to fade
- 1514 - HDR ACC FAIL, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to HDR system Access Failure
- 2000 - CLIENT END, this error code is returned when client ends the data call
- 2001 - NO SRV, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since device has no service
- 2002 - FADE, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since device lost the system due to fade
- 2003 - REL NORMAL, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to receiving a release from base station with no reason
- 2004 - ACC IN PROG, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to Access attempt already in progress
- 2005 - ACC FAIL, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) due to Access Failure
- 2006 - REDIR OR HANDOFF, this error code is returned when data call is brought down because device is in the process of redirecting/handing off to a different target system
- 2500 - OFFLINE, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since device went offline
- 2501 - EMERGENCY MODE, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since device is operating in Emergency mode
- 2502 - PHONE IN USE, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since device is in use (e.g voice call)
- 2503 - INVALID MODE, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since the device's operational mode is different from the mode requested in the traffic channel bring up
- 2504 - INVALID SIM STATE, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since the SIM was marked by network as invalid for circuit and/or packet service domain
- 2505 - NO COLLOC HDR, this error code is returned when data call is brought down because traffic channel got rejected/released by CM(Call Manager) since there is no collocated HDR
- 2506 - CALL CONTROL REJECTED, this error code is returned when data call is brought down because traffic channel request got rejected by CM(Call Manager) since Call control module rejected the request

9.33.2.9 3GPP specification defined call end reasons (Type=6)

- 8 - OPERATOR DETERMINED BARRING, this reason code is posted by the MME(Mobility Management Entity) to indicate operator has barred the UE
- 25 - LLC SNDCP FAILURE, PDP context deactivation initiated by the MS or by the Network
- 26 - INSUFFICIENT RESOURCES, this reason is posted to indicate that the network cannot provide the requested service due to insufficient resources
- 27 - MISSING OR UNKNOWN APN, the APN was required and not specified or APN could not be resolved. In LTE mode of operation, this is a PDN throttling cause code, meaning the UE may endup throttling further requests to the same APN

- 28 - UNKNOWN PDN TYPE, the reason is posted by the network to indicate that the PDN type was not recognized
- 29 - AUTH FAILED, the reason is posted when authentication fails. In LTE mode of operation, this is a PDN throttling cause code, meaning the UE may end up throttling further requests to the same APN
- 30 - GGSN REJECT, the reason is posted when the request was rejected by Serving GW or PDN GW. In LTE mode of operation, this is a PDN throttling cause code, meaning the UE may end up throttling further requests to the same APN
- 31 - ACTIVATION REJECT, the reason is posted when the request is rejected by the network due to unspecified reasons
- 32 - OPTION NOT SUPPORTED, the reason is posted when UE requested a service not supported by the PLMN
- 33 - OPTION UNSUBSCRIBED, This cause is sent when the MS requests a service option for which it has no subscription
- 34 - OPTION TEMP OOO, service option temporarily out of order, this reason is posted when the network is temporarily out of resources to service the request
- 35 - PTI ALREADY USED, the reason is posted to indicate that PTI (Procedure Transaction Identifier) used in the request is already active via another UE requested procedure
- 36 - REGULAR DEACTIVATION, this reason is posted by the network to initiate a regular release of bearer resources
- 37 - EPS QOS NOT ACCEPTED, this reason is posted by the network to indicate that the QoS requested by the UE could not be accepted
- 38 - NETWORK FAILURE, this reason is posted when an error occurs in the network
- 39 - UMTS REACTIVATION REQ, this reason is posted by the network to request for bearer reactivation. This code may be posted during network congestion
- 40 - FEATURE NOT SUPPORTED, Unsuccessful MBMS context activation requested by the network
- 41 - TFT SEMANTIC ERROR, the reason is posted by the network to indicate semantic error(s) in specifying TFT operation included in the request
- 42 - TFT SYNTAX ERROR, the reason is posted by the network to indicate syntactic error(s) in specifying TFT operation included in the request
- 43 - UNKNOWN PDP CONTEXT, the reason is posted when the bearer identity (or linked bearer identity) in the request is invalid (or inactive)
- 44 - FILTER SEMANTIC ERROR, the reason is posted by the network to indicate semantic error(s) in specifying packet filter(s) associated with a TFT
- 45 - FILTER SYNTAX ERROR, the reason is posted by the network to indicate syntactic error(s) in specifying packet filter(s) associated with a TFT
- 46 - PDP WITHOUT ACTIVE TFT, the reason is posted by the network when UW requested more than one PDP connection without TFT
- 50 - IPV4 ONLY ALLOWED, 3GPP equivalent ESM(EPS Session Management) cause code value 50, PDN type IPv4 only allowed.
- 51 - IPV6 ONLY ALLOWED, 3GPP equivalent ESM(EPS Session Management) cause code value 51, PDN type IPv6 only allowed
- 52 - SINGLE ADDRESS BEARER ONLY, 3GPP equivalent ESM(EPS Session Management) cause code value 52, Single address bearers only allowed. The reason is posted when the network supports single address bearers only, meaning dual IP bearers are not supported

- 53 - ESM INFORMATION NOT RECEIVED, 3GPP equivalent ESM(EPS Session Management) cause code value 53, ESM information not received. The reason is posted by the network to indicate that the PDN connection request was rejected because ESM information was not received
- 54 - PND CONNECTION DOES NOT EXIST, 3GPP equivalent ESM(EPS Session Management) cause code value 54, PDN connection does not exist The reason is posted by the network during handover from a non-3GPP network to indicate that the MME does not have any information regarding the requested PDN connection
- 55 - MULTIPLE CONNECTION TO SAME PDN NOT ALLOWED, 3GPP equivalent ESM(EPS Session Management) cause code value 55, Multiple PDN connections for a given APN not allowed. The reason is posted by the network to indicate that the UE is already connected to the requested APN via another PDN/PDN connection
- 81 - INVALID TRANSACTION ID, the reason is posted by the network to indicate that the PTI used in the request is unassigned or reserved
- 95 - MESSAGE INCORRECT SEMANTIC, the reason is posted by the network to indicate receipt of an invalid message
- 96 - INVALID MANDATORY INFO, the reason is posted by the network to indicate receipt of a message with semantic error in a mandatory information element
- 97 - MESSAGE TYPE UNSUPPORTED, the reason is posted by the network to indicate receipt of a message that is either undefined or defined but not implemented by the equipment sending this ESM cause
- 98 - MSG TYPE NONCOMPATIBLE STATE, the reason is posted by the network to indicate receipt of a message type that cannot be handled in the current network protocol state
- 99 - UNKNOWN INFO ELEMENT, the reason is posted by the network to indicate receipt of a message that includes and information element that is either not defined or defined but not implemented by the equipment sending the ESM cause
- 100 - CONDITIONAL IE ERROR, the reason is posted by the network to indicate receipt of a message that includes a syntactically incorrect information element. This message is ignored by the network.
- 101 - MSG AND PROTOCOL STATE UNCOMPATIBLE, the reason is posted by the network to indicate receipt of a message that cannot be handled in the current network protocol state
- 111 - PROTOCOL ERROR, the reason is posted by the network to indicate a protocol error when no other error applies
- 112 - APN TYPE CONFLICT
- 113 - INVALID PROXY-CALL SESSION CONTROL FUNCTION ADDRESS

9.33.2.10 PPP call end reasons (Type=7)

- 1 - TIMEOUT, this error code is returned when the data call bring up fails in PPP setup due to timeout (For e.g: LCP Conf Ack not received from network)
- 2 - AUTH FAILURE, this error code is returned when the data call bring up fails in PPP setup due to authentication failure
- 3 - OPTION MISMATCH, this error code is returned when the data call bring up fails in PPP setup due option mismatch (e.g: Authentication is required, but not negotiated with network during LCP phase)
- 31 - PAP FAILURE, this error code is returned when the data call bring up fails in PPP setup due to PAP failure
- 32 - CHAP FAILURE, this error code is returned when the data call bring up fails in PPP setup due to CHAP failure
- 33 - CLOSE IN PROGRESS, this error code is returned when the data call bring up fails in PPP setup since PPP is in the process of cleaning the previous PPP session
- -1 - UNKNOWN, this error code is unused

9.33.2.11 EHRPD call end reasons (Type=8)

- 1 - SUBS LIMITED TO V4, this error code is returned when the V6 interface bring up fails because network provided only V4 address for the upcoming PDN
- 2 - SUBS LIMITED TO V6, this error code is returned when the V4 interface bring up fails because network provided only V6 address for the upcoming PDN
- 4 - VSNCP(Vendor Specific Network Control Protocol) TIMEOUT, this error code is returned when the data call bring up fails in VSNCP phase due to VSNCP timeout error
- 5 - VSNCP(Vendor Specific Network Control Protocol) FAILURE, this error code is returned when VSNCP configuration failed during call bring up
- 6 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I GEN ERROR, this error code is returned when the data call bring up fails in VSNCP phase due to general error
- 7 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I UNAUTH APN, this error code is returned when the data call bring up fails in VSNCP phase since network rejected VSNCP config request with reason requested APN is unauthorized
- 8 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I PDN LIMIT EXCEED, this error code is returned when the data call bring up fails in VSNCP phase since network rejected VSNCP config request with reason PDN limit exceeded
- 9 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I NO PDN GW, this error code is returned when the data call bring up fails in VSNCP phase since network rejected VSNCP config request with reason no PDN gateway
- 10 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I PDN GW UNREACH, this error code is returned when the data call bring up fails in VSNCP phase since network rejected VSNCP config request with reason PDN gateway unreachable
- 11 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I PDN GW REJ, this error code is returned when the data call bring up fails in VSNCP phase since network rejected VSNCP config request with reason PDN gateway reject
- 12 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I INSUFF PARAM, this error code is returned when the data call bring up fails in VSNCP phase since network rejected VSNCP config request with reason insufficient parameter
- 13 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I RESOURCE UNAVAIL, this error code is returned when the data call bring up fails in VSNCP phase since network rejected VSNCP config request with reason resource unavailable
- 14 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I ADMIN PROHIBIT, this error code is returned when the data call bring up fails in SNCP phase since network rejected VSNCP config request with reason admin prohibited
- 15 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I PDN ID IN USE, this error code is returned when the data call bring up fails in VSNCP phase because network rejected with reason PDN ID IN USE (or) All existing PDNs are brought down with this end reason because one of the PDN bring up got rejected by network with reason PDN ID IN USE
- 16 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I SUBSCR LIMITATION, this error code is returned when the data call bring up fails in VSNCP phase since network rejected VSNCP config request with reason subscriber limitation
- 17 - VSNCP(Vendor Specific Network Control Protocol) 3GPP2I PDN EXISTS FOR THIS APN, this error code is returned when the data call bring up fails in VSNCP phase since network rejected VSNCP config request with reason PDN exists for this APN

9.33.2.12 IPV6 call end reasons (Type=9)

- 1 - PREFIX UNAVAILABLE, this error code is returned when V6 data call is brought down because device failed to get the prefix from network
- 2 - IPV6 ERR HRPD IPV6 DISABLED, this error code is returned when V6 data call bring up is rejected because IPV6 is disabled in 1X/HRPD mode
- 3 - IPV6 DISABLED, this error code is returned when IPv6 data call bring up is rejected because NV1896 (IPV6 enable) is disabled

Copyright: © 2011-2013 Sierra Wireless, Inc. all rights reserved

9.34 qaGobiApiTableCarrierCodes.h File Reference

Carrier Codes table.

9.34.1 Detailed Description

Carrier Codes table.

9.34.2 Carrier Codes (Number - Carrier)

- 0 - no carrier specified
- 1 - Generic
- 2 - Telstra
- 4 - AT&T
- 5 - Verizon
- 11 - Sprint
- 12 - Telefonica
- 101 - Verizon
- 102 - Sprint
- 103 - Alltel
- 104 - Bell Mobility
- 105 - Telus
- 106 - U.S. Cellular
- 107 - Telstra
- 108 - China Unicom
- 109 - Telecom New Zealand
- 110 - SK Telecom
- 111 - Reliance Communications
- 112 - Tata Communications
- 113 - MetroPCS Communications

- 114 - Leap Wireless
- 115 - KDDI
- 116 - Grupo Iusacell
- 117 - China Telecom
- 118 - Open Mobile Handset
- 176 - Rogers
- 177 - NetIndex
- 178 - DNA
- 179 - Big Pond
- 201 - AT&T
- 202 - Vodafone
- 203 - T-Mobile
- 204 - Orange
- 205 - Telefonica
- 206 - Telecom Italia
- 207 - 3
- 208 - O2
- 209 - SFR
- 210 - Swisscom AG
- 211 - China Mobile
- 212 - Telstra
- 213 - Singapore Telecommunications
- 214 - Reliance Telecommunications
- 215 - Bharti Airtel
- 216 - NTT docomo
- 217 - E Mobile
- 218 - Softbank
- 219 - Korea Telecom Freetel
- 220 - SK Telecom
- 221 - Telenor
- 222 - NetCom Norway
- 223 - TeliaSonera
- 224 - América Móvil
- 225 - Brasil Vivo
- 0xFFFFFFFF - Unknown

Copyright: © 2011-2014 Sierra Wireless, Inc. all rights reserved

9.35 qaGobiApiTableCodingScheme.h File Reference

Data Coding Scheme.

Macros

- #define __GOBI_API_CODING_SCHEME_H__

9.35.1 Detailed Description

Data Coding Scheme.

9.35.2 S1

9.35.2.1 Use of bits 3..0\n\n

- Language using the GSM 7 bit default alphabet Bits 3..0
  indicate the language:
  0000 German
  0001 English
  0010 Italian
  0011 French
  0100 Spanish
  0101 Dutch
  0110 Swedish
  0111 Danish
  1000 Portuguese
  1001 Finnish
  1010 Norwegian
  1011 Greek
  1100 Turkish
  1101 Hungarian
  1110 Polish
  1111 Language unspecified

9.35.3 Coding Group Bits 7..4(0001)

9.35.3.1 use of bits 3..0

- 0000 GSM 7 bit default alphabet; message preceded by language indication.
  The first 3 characters of the message are a two-character representation of the language encoded according to ISO 639 [12], followed by a CR character. The CR character is then followed by 90 characters of text.
- 0001 UCS2; message preceded by language indication
  The message starts with a two GSM 7-bit default alphabet character representation of the language encoded according to ISO 639. This is padded

to the octet boundary with two bits set to 0 and then followed by 40 characters
of UCS2-encoded message.
An MS not supporting UCS2 coding will present the two character language
identifier followed by improperly interpreted user data.

9.35.4 Coding Group Bits 7..4(0010)

9.35.4.1 use of bits 3..0

- 0000 Czech
  0001 Hebrew
  0010 Arabic
  0011 Russian
  0100 Icelandic
  0101..1111 Reserved for other languages using the GSM 7 bit
  default alphabet, with unspecified handling at the MS

9.35.5 Coding Group Bits 7..4(0011)

9.35.5.1 use of bits 3..0

- 0000..1111 Reserved for other languages using the GSM 7 bit
  default alphabet, with unspecified handling at the MS

9.35.6 Coding Group Bits 7..4(01xx)

9.35.6.1 use of bits 3..0

- General Data Coding indication
  - Bits 5..0 indicate the following:
  - Bit 5, if set to 0, indicates the text is uncompressed
  - Bit 5, if set to 1, indicates the text is compressed using the compression algorithm defined in 3GPP TS 23.042
  - Bit 4, if set to 0, indicates that bits 1 to 0 are reserved and have no message class meaning
  - Bit 4, if set to 1, indicates that bits 1 to 0 have a message class meaning: Bit 1 Bit 0 Message Class:
    0 0 Class 0
    0 1 Class 1 Default meaning: ME-specific.
    1 0 Class 2 (U)SIM specific message.
    1 1 Class 3 Default meaning: TE-specific (see 3GPP TS 27.005)
    Bits 3 and 2 indicate the character set being used, as follows:
    Bit 3 Bit 2 Character set:
    0 0 GSM 7 bit default alphabet
    0 1 8 bit data
    1 0 UCS2 (16 bit) [10]
    1 1 Reserved

9.35.7 Coding Group Bits 7..4(1001)

9.35.7.1 Reserved coding groups

- Message with User Data Header (UDH) structure:
  Bit 1 Bit 0 Message Class:
  0 0 Class 0
  0 1 Class 1 Default meaning: ME-specific.
  1 0 Class 2 (U)SIM specific message.
  1 1 Class 3 Default meaning: TE-specific (see 3GPP TS 27.005 [8])
  Bits 3 and 2 indicate the alphabet being used, as follows:
  Bit 3 Bit 2 Alphabet:
  0 0 GSM 7 bit default alphabet
  0 1 8 bit data
  1 0 USC2 (16 bit) [10]
  1 1 Reserved

9.35.8 Coding Group Bits 7..4(1010..1101)

9.35.8.1 Reserved coding groups

9.35.9 Coding Group Bits 7..4(1110)

9.35.9.1 Defined by the WAP Forum

9.35.10 Coding Group Bits 7..4 (1111)

9.35.10.1 Data coding / message handling

- Bit 3 is reserved, set to 0.
  Bit 2 Message coding:
  0 GSM 7 bit default alphabet
  1 8 bit data
  Bit 1 Bit 0 Message Class:
  0 0 No message class.
  0 1 Class 1 user defined.
  1 0 Class 2 user defined.
  1 1 Class 3
  default meaning: TE specific(3GPP TS 27.005)
  Copyright: © 2012 Sierra Wireless, Inc. all rights reserved

9.35.11 Macro Definition Documentation

9.35.11.1 #define __GOBI_API_CODING_SCHEME_H__

9.36 qaGobiApiTableGpsCapabilityCodes.h File Reference

Position Determination Service API GPS Capability Codes.

9.36.1 Detailed Description

Position Determination Service API GPS Capability Codes.

9.36.2 GPS capability (Value - Capability)

- 0 - None
- 1 - Standalone
- 2 - Assisted (including XTRA and implying standalone is also supported)
- 3 - Assisted (without XTRA and implying standalone is also supported)
- 0xFFFFFFFF - Unknown

Copyright: © 2011 Sierra Wireless, Inc. all rights reserved

9.37 qaGobiApiTablePowerModes.h File Reference

Device Management Service API Power Modes table.

9.37.1 Detailed Description

Device Management Service API Power Modes table.

9.37.2 Power Modes (Value - Description)

- 0 - Online (default)
- 1 - Low power (airplane) mode
- 2 - Factory test mode
- 3 - Offline
- 4 - Resetting
- 5 - Power off
- 6 - Persistent low power (airplane) mode
- 7 - Mode - only low power

Valid transitions for Power Modes

- Online to Low Power, Persistent low power, Factory test, Offline or Shut Down
- Low power to online, Persistent low power, Offline, or Shut Down
- Persistent low power to Online, Low power, Offline or Shut down
- Factory test to online
- Offline to Reset

Copyright: © 2011 Sierra Wireless, Inc. all rights reserved

9.38 qaGobiApiTableRadioInterfaces.h File Reference

Network Access Service API Radio Interfaces table.

9.38.1 Detailed Description

Network Access Service API Radio Interfaces table.

9.38.2 Radio interface

9.38.2.1 Technology (Value - Radio Interface Technology)

- 0 - No service
- 1 - CDMA 1xRTT
- 2 - CDMA 1xEV-DO
- 3 - AMPS (Unsupported)
- 4 - GSM
- 5 - UMTS
- 6 - WLAN
- 7 - GPS
- 8 - LTE
- 9 - TD-SCDMA
- 10 - LTE-M1
- 11 - LTE-NB1
- 12 - NR5G

Copyright: © 2011 Sierra Wireless, Inc. all rights reserved

9.39 qaGobiApiTableRegionCodes.h File Reference

Region Codes table.

9.39.1 Detailed Description

Region Codes table.

9.39.2 Region Codes (Code - Region)

- 0 - North America
- 1 - Latin America
- 2 - Europe
- 3 - Asia

- 4 - Australia
- 5 - Global
- 0xFFFFFFFF - Unknown

Copyright: © 2011 Sierra Wireless, Inc. all rights reserved

9.40 qaGobiApiTableServiceOptions.h File Reference

Voice Service Options.

9.40.1 Detailed Description

Voice Service Options.

9.40.2 Service Option codes (Code - Reason)

9.40.2.1 Description

- 0x0001 - Basic variable rate voice service (8 kbps)
- 0x0002 - Mobile station loopback (8 kbps)
- 0x0003 - Enhanced variable rate voice service (8 kbps)
- 0x0004 - Asynchronous data service (9.6 kbps)
- 0x0005 - Group 3 facsimile (9.6 kbps)
- 0x0006 - Short message service (rate set 1)
- 0x0007 - Packet data service: Internet or ISO Protocol stack (9.6 kbps)
- 0x0008 - Packet data service: CDPD Protocol stack (9.6 kbps)
- 0x0009 - Mobile station loopback (13 kbps)
- 0x000A - transparent service
- 0x000B - III nontransparent service
- 0x000C - Asynchronous data service (14.4 or 9.6 kbps)
- 0x000D - Group 3 facsimile (14.4 or 9.6 kbps)
- 0x000E - Short message service (rate set 2)
- 0x000F - Packet data service: Internet or ISO Protocol stack (14.4 kbps)
- 0x0010 - Packet data service: CDPD Protocol stack (14.4 kbps)
- 0x0011 - High-rate voice service (13 kbps)
- 0x0012 - Over-the-air parameter administration (rate set 1)
- 0x0013 - Over-the-air parameter administration (rate set 2)
- 0x0014 - Group 3 analog facsimile (rate set 1)
- 0x0015 - Group 3 analog facsimile (rate set 2)
- 0x0016 - High-speed packet data service: Internet or ISO Protocol stack (RS1 forward, RS1 reverse)

- 0x0017 - High-speed packet data service: Internet or ISO Protocol stack (RS1 forward, RS2 reverse)
- 0x0018 - High-speed packet data service: Internet or ISO Protocol stack (RS2 forward, RS1 reverse)
- 0x0019 - High-speed packet data service: Internet or ISO Protocol stack (RS2 forward, RS2 reverse)
- 0x001A - High-speed packet data service: CDPD Protocol stack (RS1 forward, RS1 reverse)
- 0x001B - High-speed packet data service: CDPD Protocol stack (RS1 forward, RS2 reverse)
- 0x001C - High-speed packet data service: CDPD Protocol stack (RS2 forward, RS1 reverse)
- 0x001D - High-speed packet data service: CDPD Protocol stack (RS2 forward, RS2 reverse)
- 0x001E - RATE_SET_1 Supplemental channel loopback test for rate set 1
- 0x001F - RATE_SET_2 Supplemental channel loopback test for rate set 2
- 0x0020 - Test Data Service Option (TDSO)
- 0x0021 - cdma2000 high-speed packet data service, Internet or ISO Protocol stack
- 0x0022 - cdma2000 high-speed packet data service, CDPD Protocol
- 0x0023 - Location services, rate set 1 (9.6 kbps)
- 0x0024 - Location services, rate set 2 (14.4 kbps)
- 0x0025 - ISDN interworking service (64 kbps)
- 0x0026 - GSM voice
- 0x0027 - GSM circuit data
- 0x0028 - GSM packet data
- 0x0029 - GSM short message service
- 0x0036 - Markov Service Option (MSO)
- 0x0037 - Loopback Service Option (LSO)
- 0x0038 - Selectable mode vocoder
- 0x0039 - 32 kbps circuit video conferencing
- 0x003A - CONFERENCING 64 kbps circuit video conferencing
- 0x003B - HRPD packet data service, which when used in paging over the 1X air interface, a page response is not required
- 0x003C - Link Layer Assisted Robust Header Compression (LLA ROHC) - header removal
- 0x003D - LLA ROHC - Header Compression
- 0x003E - Source-controlled Variable-Rate Multimode Wideband (VMR-WB) speech codec rate set 2
- 0x003F - Source-controlled VMR-WB speech codec rate set 1
- 0x0040 - HRPD auxiliary packet data service instance
- 0x0041 - cdma2000/GPRS interworking
- 0x0042 - ISO_PROTOCOL_SO_66 cdma2000 high-speed packet data service, Internet or ISO Protocol stack
- 0x0043 - HRPD packet data IP service where higher layer protocol is IP or ROHC
- 0x0044 - Enhanced variable rate voice service (EVRC-B)
- 0x0045 - HRPD packet data service, which when used in paging over the 1X air interface, a page response is required

- 0x0046 - Enhanced variable rate voice service (EVRC-WB)
- 0x1004 - Asynchronous data service, Revision 1 (9.6 or 14.4 kbps)
- 0x1005 - Group 3 facsimile, Revision 1 (9.6 or 14.4 kbps)
- 0x1007 - Packet data service: Internet or ISO Protocol stack, Revision 1 (9.6 or 14.4 kbps)
- 0x1008 - Packet data service: CDPD Protocol stack, Revision 1 (9.6 or 14.4 kbps)
- 0x7FF8 - Identifies service reference identifier 0
- 0x7FF9 - Identifies service reference identifier 1
- 0x7FFA - Identifies service reference identifier 2
- 0x7FFB - Identifies service reference identifier 3
- 0x7FFC - Identifies service reference identifier 4
- 0x7FFD - Identifies service reference identifier 5
- 0x7FFE - Identifies service reference identifier 6
- 0x7FFF - Identifies service reference identifier 7

Copyright: © 2012 Sierra Wireless, Inc. all rights reserved

9.41 qaGobiApiTableSupServiceInfoClasses.h File Reference

Voice Supplementary Service Information Classes.

9.41.1 Detailed Description

Voice Supplementary Service Information Classes.

9.41.2 Supplementary Service Information Classes (Value - Service Class)

- 0X00 - CLASS_NONE
- 0X01 - CLASS_VOICE
- 0X02 - CLASS_DATA
- 0X04 - CLASS_FAX
- 0X08 - CLASS_SMS
- 0X10 - CLASS_DATACIRCUITSYNC
- 0X20 - CLASS_DATACIRCUITASYNC
- 0X40 - CLASS_PACKETACCESS
- 0X80 - CLASS_PADACCESS

Copyright: © 2012 Sierra Wireless, Inc. all rights reserved

9.42 qaGobiApiTableSwiAudio.h File Reference

Swi Audio related tables.

9.42.1 Detailed Description

Swi Audio related tables.

9.42.2 ACDB Device (Device ID - description)

- 0 - Vehicle HF
- 1 - Handset
- 2 - TTY
- 3 - USB
- 4 - NA

9.42.3 Physical Interface (Device ID - description - Interface parameters)

- 0 - PCM - Mode: 0-slave, 1-master, 2-Auxiliary PCM; Rate: 0-8k, 1-16k; Format: 0-linear, 1-u-law, 2-A-law; Padding: 0-disable, 1-enable; Bits-frame: 0-8BPF, 1-16BPF, 2-32BPF, 3-64BPF, 4-128BPF, 5-256BPF;
- 1 - I2S - None
- 2 - Analog(with internal codec) - None
- 3 - USB - None

Copyright: © 2013 Sierra Wireless, Inc. all rights reserved

9.43 qaGobiApiTableSwiOMADMSessionStatus.h File Reference

Session Status table.

9.43.1 Detailed Description

Session Status table.

9.43.2 OMA DM Session Status (Session Status - Meaning - Usage)

- 0x0000 - Successful - Session succeeded
- 0x0001 - Break - Session succeeded
- 0x0002 - Large Object Handled - Session succeeded
- 0x0003 - No status - Session succeeded
- 0x0004 - No more commands - Session succeeded
- 0x0005 - User cancel - Session cancelled
- 0x0100-0x01FF - General errors
- 0x0200-0x02FF - Syncml errors
- 0x0300-0x03FF - Authentication errors
- 0x0400-0x04FF - Protocol errors

- 0x0500-0x05FF - Tree errors (DM Only)
- 0x0600-0x06FF - Not applicable
- 0x0700-0x07FF - Trigger errors
- 0x0800-0x08FF - FUMO errors
- 0x0900-0x09FF - Communication errors
- 0x0A00-0x0AFF - Parsing errors
- 0x0B00-0x0CFF - Not applicable
- 0x7F00-0x7F12 - Insignia errors
- 0x7F13 - Illegal text - Text received contains illegal characters
- 0x7F14 - Download failure - Failed to download FOTA image
- 0x7F15 - Empty session - Session ran successfully, but no information was updated
- 0x7F16 - Factory reset successful - Factory reset succeeded
- 0x7F17 - Factory reset fail - Factory reset failed

Copyright: © 2017 Sierra Wireless, Inc. all rights reserved

9.44 qaGobiApiTableSwiOMADMUpdateCompleteStatus.h File Reference

Update Complete Status table.

9.44.1 Detailed Description

Update Complete Status table.

9.44.2 OMA DM Update Complete Status (Update Complete Status - Meaning - Usage)

- 200 - Successful - The request has succeeded
- 250-299 - Successful(vendor specified) - successful operation with vendor specified ResultCode
- 400 - Management Client Error - Management Client error - based on User or Device behavior
- 401 - User Cancelled - User chose not to accept the operation when prompted
- 402 - Corrupted Firmware Update Package - Corrupted firmware update package did not store correctly. Detected for example, by mismatch CRCs between actual and expected
- 403 - Firmware UpdatePackage(Device Mismatch) - Wrong firmware update package delivered to device based on current device characteristics
- 404 - Failed Firmware Update Package Validation - Failure to positively validate digital signature of firmware update package
- 405 - Firmware Update Package Not acceptable - firmware update package is not acceptable
- 406 - Alternate Download Authentication Failure - authentication required but authentication failure was encountered when downloading firmware update package
- 407 - Alternate Download Request Timeout - client has encountered a timeout when downloading firmware update package

- 408 - Not Implemented - the device does not support the requested operation
- 409 - Undefined Error - indicates failure not defined by any other error code
- 410 - Firmware Update Failed - firmware update operation failed in device
- 411 - Malformed or Bad URL - the URL provided for alternate download is bad
- 412 - Alternate Download Server Unavailable - the alternate download server is unavailable or does not respond
- 450 - Client Error (OMADM General) - Vendor defined client error
- 451 - Client Error (OMADM SyncML) - Vendor defined client error
- 452 - Client Error (OMADM Auth) - Vendor defined client error
- 453 - Client Error (OMADM Protocol)- Vendor defined client error
- 454 - Client Error (OMADM Tree) - Vendor defined client error
- 455 - Client Error (OMADM DStore) - Vendor defined client error
- 456 - Client Error (OMADM Trigger) - Vendor defined client error
- 457 - Client Error (OMADM Fumo) - Vendor defined client error
- 458 - Client Error (OMADM Comms) - Vendor defined client error
- 459 - Client Error (OMADM Parse) - Vendor defined client error
- 460 - Client Error (OMADM TNDS) - Vendor defined client error
- 461 - Client Error (OMADM SCM) - Vendor defined client error
- 462 - Client Error (OMADM Impl) - Vendor defined client error
- 463-499 - Client Error (Vendor Specified) - client error encountered for operation with vendor specified result code
- 500 - Alternate Download Server Error - Alternate download server error encountered
- 501 - Download fails due to device out of memory - The download fails due to insufficient memory in the device to save the firmware update package
- 502 - Firmware update fails due to device out of memory - The update fails because there isn't sufficient memory to update the device
- 503 - Download fails due to network issues - The download fails due to network/transport level errors
- 550-599 - Alternate Download Server Error (vendor specified)- Alternate download server error encountered for operation with vendor specified result code

Copyright: © 2013 Sierra Wireless, Inc. all rights reserved

9.45 qaGobiApiTableVoiceCallEndReasons.h File Reference

Voice Service Call and supplementary services end reasons.

9.45.1 Detailed Description

Voice Service Call and supplementary services end reasons.

9.45.2 Voice Call and supplementary services end reason codes (Code - Reason)

9.45.2.1 General

- 0 - Phone is offline
- 20 - Phone is CDMA locked until a power cycle; CDMA only
- 21 - Phone has no service, this is for backward compatibility
- 22 - Call has ended abnormally; CDMA only
- 23 - Received intercept from the base station; originating only; CDMA only
- 24 - Received reorder from the base station; originating only; CDMA only
- 25 - Received release from the base station; no reason was given
- 26 - Received release from the base station; SO reject; CDMA only
- 27 - Received incoming call from the base station
- 28 - Received alert stop from the base station; incoming only; CDMA only
- 29 - Client ended the call
- 30 - Received end activation; OTASP call only; CDMA only
- 31 - MC aborted the origination/conversation; CDMA only
- 32 - Maximum access probes were transmitted; CDMA only
- 33 - Persistence test failure; FEATURE_JCDMA only; CDMA only
- 34 - R-UIM is not present
- 35 - Access attempt is already in progress
- 36 - Access failure for a reason other than the above
- 37 - Received retry order; originating only; IS 2000; CDMA only
- 38 - BYBS Concurrent service is not supported by the base station
- 39 - No response was received from the base station
- 40 - Call was rejected by the base station; CDMA only
- 41 - Concurrent services requested were not compatible; CDMA only
- 42 - Access is blocked by the base station; CDMA only
- 43 - Corresponds to CM_CALL_ORIG_ ERR_ALREADY_IN_TC
- 44 - Call is ended because an emergency call is flashed over this call; CDMA only
- 45 - Used if CM is ending a GPS call in preference of a user call
- 46 - Used if CM is ending an SMS call in preference of a user call
- 47 - Used if CM is ending a data call in preference of an emergency call
- 48 - Call was rejected because of a redirection or handoff
- 49 - Access is blocked by the base station for all mobiles; KDDI-specific; CDMA only
- 50 - To support OTASP SPC Error indication
- 51 - Maximum access probes for an IS-707B call; CDMA only

- 52 - Base station reject order
- 53 - Base station retry order
- 54 - Timer T42 is expired
- 55 - Timer T40 is expired
- 56 - Service initialization failure - Traffic Channel Initialization
- 57 - Timer T50m is expired - Traffic Channel Initialization
- 58 - Timer T51m is expired - Traffic Channel Initialization
- 59 - Acknowledgement timeout due to 12 retransmissions
- 60 - Bad forward link or timer T5M is expired
- 61 - Transceiver Resource Manager request failed
- 62 - Timer T41 is expired
- 100 - WCDMA/GSM/TDS only; call end LL cause, Received a reason for ending the call from the lower layer
- 101 - WCDMA/GSM only; Call origination request failed
- 102 - WCDMA/GSM only; client rejected an incoming call
- 103 - WCDMA/GSM only; client rejected a setup indication
- 104 - WCDMA/GSM only; network ended the call
- 105 - WCDMA/GSM only
- 106 - GWM/WCDMA only; phone has no service
- 107 - 1X only; phone has no service
- 108 - Full service is unavailable
- 109 - Indicates resources are not available to handle a new MO/MT PS call

9.45.2.2 service Errors

- 110 - Unknown subscriber
- 111 - Illegal subscriber
- 112 - Bearer service not provisioned
- 113 - Tele service not provisioned
- 114 - Illegal equipment
- 115 - Call barred
- 116 - Illegal ss operation
- 117 - Ss error status
- 118 - Ss not available
- 119 - Ss subscription violation
- 120 - Ss incompatibility
- 121 - Facility not supported
- 122 - Absent subscriber

- 123 - Short term denial
- 124 - Long term denial
- 125 - System failure
- 126 - Data missing
- 127 - Unexpected data value
- 128 - Pwd registration failure
- 129 - Negative pwd check
- 130 - Num of pwd attempts violation
- 131 - Position method failure
- 132 - Unknown alphabet
- 133 - Ussd busy
- 134 - Rejected by user
- 135 - Rejected by network
- 136 - Deflection to served subscriber
- 137 - Special service code
- 138 - Invalid deflected to number
- 139 - Mpty participants exceeded
- 140 - Resources not available

9.45.2.3 control cause values

- 141 - Unassigned number
- 142 - No route to destination
- 143 - Channel unacceptable
- 144 - Operator determined barring
- 145 - Normal call clearing
- 146 - User busy sEE [s3, aNNEX h]
- 147 - No user responding sEE [s3, aNNEX h]
- 148 - User alerting no answer
- 149 - Call rejected sEE [s3, aNNEX h]
- 150 - Number changed sEE [s3, aNNEX h]
- 151 - Preemption sEE [s3, aNNEX h]
- 152 - Destination out of order
- 153 - Invalid number format
- 154 - Facility rejected
- 155 - Resp to status enquiry
- 156 - Normal unspecified

- 157 - No circuit or channel available
- 158 - Network out of order
- 159 - Temporary failure
- 160 - Switching equipment congestion
- 161 - Access information discarded
- 162 - Requested circuit or channel not available
- 163 - Resources unavailable or unspecified
- 164 - Qos unavailable
- 165 - Requested facility not subscribed
- 166 - Incoming calls barred within cug
- 167 - Bearer capability not auth
- 168 - Bearer capability unavailable
- 169 - Service option not available
- 170 - Acm limit exceeded
- 171 - Bearer service not implemented
- 172 - Requested facility not implemented
- 173 - Only digital information bearer available
- 174 - Service or option not implemented
- 175 - Invalid transaction identifier
- 176 - USER NOT MEMBER OF CUG
- 177 - Incompatible destination
- 178 - Invalid transit nw selection
- 179 - Semantically incorrect message
- 180 - Invalid mandatory information
- 181 - Message type non implemented
- 182 - Message type not compatible with protocol statE
- 183 - Information element non existent
- 184 - Conditonal ie error
- 185 - Message not compatible with protocol state
- 186 - Recovery on timer expired
- 187 - Protocol error unspecified
- 188 - Interworking unspecified
- 189 - Outgoing calls barred within cug
- 190 - No cug selection
- 191 - Unknown cug index
- 192 - Cug index incompatible

- 193 - Cug call failure unspecified
- 194 - Clir not subscribed
- 195 - Ccbs possible sEE
- 196 - Ccbs not possible

9.45.2.4 reject causes

- 197 - Imsi unknown in hlr
- 198 - Illegal ms
- 199 - Imsi unknown in vlr
- 200 - Imei not accepted
- 201 - Illegal me sEE
- 202 - Plmn not allowed
- 203 - Location area not allowed
- 204 - Roaming not allowed in this location area
- 205 - No suitable cells in location area
- 206 - Network failure sEE
- 207 - mac failure sEE
- 208 - Synch failure
- 209 - Network congestion
- 210 - GSM authentication unacceptable
- 211 - Service not subscribed
- 212 - Service temporarily out of order
- 213 - Call cannot be identified
- 214 - Incorrect semantics in message
- 215 - Mandatory information invalid
- 216 - Call failed due to other access stratum failures
- 217 - SIM is invalid
- 218 - Invalid call state
- 219 - Access class is blocked
- 220 - No resources are in the protocol stack to allow the call
- 221 - Invalid user data was received

9.45.2.5 reject causes

- 222 - Timer T3230 is expired
- 223 - No cell is available
- 224 - Abort message was received
- 225 - Radio link was lost due to other lower layer causes

9.45.2.6 reject causes

- 226 - Timer T303 is expired
- 227 - CNM MM release is pending

9.45.2.7 stratum reject causes

- 228 - Access stratum RR release indication
- 229 - Access stratum random access failure
- 230 - RRC_REL_IND Access stratum RRC release indication
- 231 - Access stratum close session indication
- 232 - Access stratum open session failure
- 233 - Access stratum low level failure
- 234 - Access stratum low level failure redial is not allowed
- 235 - Access stratum low level immediate retry
- 236 - Access stratum abort radio is unavailable

9.45.2.8 reject causes

- 237 - Service option is not supported

9.45.2.9 IP end reasons

- 300 - Received SIP 400 bad request;waiting for INVITE response
- 301 - Received SIP 400 bad request;waiting for INVITE response
- 302 - Received SIP 404 not found; call failed; called party does not exist
- 303 - Received SIP 415 unsupported media type; call failed; called party does not support media
- 304 - Received SIP 480 temporarily unavailable; call failed; called party is not in the LTE area
- 305 - No network response; call failed
- 306 - No network response; unable to put call on hold
- 307 - Moved to eHRPD; call failed or dropped; not in the LTE area
- 308 - Upgrade/downgrade rejected (200 OK with the current call SDP)
- 309 - Received 403 call forbidden; waiting for INVITE response
- 310 - Generic timeout; did not receive a response from the server or other end
- 311 - Reported on the MO side for generic internal software errors; user can try again if the call still exists
- 312 - Reported on the MT side if the upgrade timer has been cancelled or cannot complete the request for some reason after notifying the user of a re-invite request
- 313 - Call origination is rejected due to a Service-Specific Access Control (SSAC) barring
- 314 - Phone was put in thermal emergency
- 315 - 1XCSFB call ended because of a soft failure
- 316 - 1XCSFB call ended because of a hard failure

Copyright: © 2012 Sierra Wireless, Inc. all rights reserved

9.46 qaGobiApiTmd.h File Reference

Thermal Mitigation Device API function prototypes.

Data Structures

- struct mitigationDevList
- struct TmdGetMitigationDevListResp
- struct TmdGetMitigationLvlReq
- struct TmdGetMitigationLvlResp
- struct TmdRegNotMitigationLvlReq
- struct TmdDeRegNotMitigationLvlReq
- struct TmdMitigationLvlIndReq

Macros

- #define MAX_MITIGATION_DEV_LIST_LEN 255
- #define MAX_MITIGATION_DEV_ID_LEN 255

Functions

- ULONG SLQSTmdGetMitigationDevList (TmdGetMitigationDevListResp *pTmdGetMitigationDevListResp)
- ULONG SLQSTmdGetMitigationLvl (TmdGetMitigationLvlReq *pTmdGetMitigationLvlReq, TmdGetMitigationLvlResp *pTmdGetMitigationLvlResp)
- ULONG SLQSTmdRegNotMitigationLvl (TmdRegNotMitigationLvlReq *pTmdRegNotMitigationLvlReq)
- ULONG SLQSTmdDeRegNotMitigationLvl (TmdDeRegNotMitigationLvlReq *pTmdDeRegNotMitigationLvlReq)

9.46.1 Detailed Description

Thermal Mitigation Device API function prototypes.

9.46.2 Macro Definition Documentation

9.46.2.1 #define MAX_MITIGATION_DEV_ID_LEN 255

9.46.2.2 #define MAX_MITIGATION_DEV_LIST_LEN 255

9.46.3 Function Documentation

9.46.3.1 ULONG SLQSTmdDeRegNotMitigationLvl (TmdDeRegNotMitigationLvlReq * *pTmdDeRegNotMitigationLvlReq*)

Deregisters the notification for mitigation device level changes.

Parameters

pTmdDeRegNotMitigationLvlReq[IN]	• See TmdDeRegNotMitigationLvlReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.46.3.2 ULONG SLQSTmdGetMitigationDevList (TmdGetMitigationDevListResp * *pTmdGetMitigationDevListResp*)

Used by the control point to gets the list of mitigation devices from the remote endpoint.

Parameters

pTmdGetMitigationDevListResp[OUT]	• See TmdGetMitigationDevListResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.46.3.3 ULONG SLQSTmdGetMitigationLvl (TmdGetMitigationLvlReq * *pTmdGetMitigationLvlReq*, TmdGetMitigationLvlResp * *pTmdGetMitigationLvlResp*)

Gets the thermal mitigation level for the mitigation device

Parameters

pTmdGetMitigationLvlReq[IN]	• See TmdGetMitigationLvlReq for more information
pTmdGetMitigationLvlResp[OUT]	• See TmdGetMitigationLvlResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.46.3.4 ULONG SLQSTmdRegNotMitigationLvl (TmdRegNotMitigationLvlReq * *pTmdRegNotMitigationLvlReq*)

Registers for notification of mitigation device level changes.

Parameters

pTmdRegNot-MitigationLvl-Req[IN]	• See TmdRegNotMitigationLvlReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.47 qaGobiApiUim.h File Reference

Uim Service API function prototypes.

Data Structures

- struct UIMPowerDownReq
- struct fileInfo
- struct UIMRefreshEvent
- struct appStatus
- struct slotInfo
- struct cardStatus
- struct hotSwapStatus
- struct validCardStatus
- struct simBusyStatus
- struct UIMGetCardStatusResp
- struct UIMGetCardStatusRespV2
- struct cardResult
- struct UIMSessionInformation
- struct setPINProtection
- struct UIMSetPinProtectionReq
- struct remainingRetries
- struct encryptedPIN1
- struct UIMPinResp
- struct UIMPinRespV2
- struct verifyUIMPIN
- struct UIMVerifyPinReq
- struct changeUIMPIN
- struct UIMChangePinReq
- struct unblockUIMPIN
- struct UIMUnblockPinReq
- struct UIMEventRegisterReqResp
- struct UIMRefreshOKReq
- struct registerRefresh
- struct UIMRefreshRegisterReq
- struct UIMRefreshCompleteReq
- struct UIMRefreshGetLastEventResp
- struct UIMRefreshGetLastEventReq
- struct UIMGetFileAttributesReq
- struct fileAttributes

- struct UIMGetFileAttributesResp
- struct depersonalizationInformation
- struct UIMDepersonalizationReq
- struct UIMDepersonalizationResp
- struct authenticationData
- struct UIMAuthenticateReq
- struct authenticateResult
- struct UIMAuthenticateResp
- struct readResult
- struct readTransparentInfo
- struct UIMReadTransparentReq
- struct UIMReadTransparentResp
- struct UIMPowerUpReq
- struct UIMSlotStatus
- struct UIMSlotsStatus
- struct UIMGetSlotsStatusResp
- struct UIMSwitchSlotReq
- struct personalizationStatus
- struct UIMGetConfigurationReq
- struct UIMGetConfigurationResp

Macros

- #define MAX_DESCRIPTION_LENGTH 255
- #define MAX_CONTENT_LENGTH 1024
- #define MAX_NO_OF_APPLICATIONS 10
- #define MAX_NO_OF_SLOTS 5
- #define MAX_PUK_LENGTH 8
- #define MAX_PATH_LENGTH 255
- #define MAX_ICCID_LENGTH 255
- #define MAX_SLOTS_STATUS 255
- #define MAX_ACTIVE_PERS_FEATURES 12

Functions

- ULONG SLQSUIMReset ()
- ULONG SLQSUIMPowerDown (UIMPowerDownReq *pUIMPowerDownReq)
- ULONG SLQSUIMGetCardStatus (UIMGetCardStatusResp *pUIMGetCardStatusResp)
- ULONG SLQSUIMGetCardStatusV2 (UIMGetCardStatusRespV2 *pUIMGetCardStatusResp)
- ULONG SLQSUIMSetPinProtection (UIMSetPinProtectionReq *pUIMSetPinProtectionReq, UIMPinResp *pUIMSetPinProtectionResp)
- ULONG SLQSUIMVerifyPin (UIMVerifyPinReq *pUIMVerifyPinReq, UIMPinResp *pUIMVerifyPinResp)
- ULONG SLQSUIMChangePin (UIMChangePinReq *pUIMChangePinReq, UIMPinResp *pUIMChangePinResp)
- ULONG SLQSUIMUnblockPin (UIMUnblockPinReq *pUIMUnblockPinReq, UIMPinResp *pUIMUnblockPinResp)
- ULONG SLQSUIMUnblockPinV2 (UIMUnblockPinReq *pUIMUnblockPinReq, UIMPinRespV2 *pUIMUnblockPinResp)
- ULONG SLQSUIMEventRegister (UIMEventRegisterReqResp *pUIMEventRegisterReqResp)
- ULONG SLQSUIMRefreshOK (UIMRefreshOKReq *pUIMRefreshOKReq)
- ULONG SLQSUIMRefreshRegister (UIMRefreshRegisterReq *pUIMRefreshRegisterReq)
- ULONG SLQSUIMRefreshComplete (UIMRefreshCompleteReq *pUIMRefreshCompleteReq)
- ULONG SLQSUIMRefreshGetLastEvent (UIMRefreshGetLastEventReq *pUIMRefreshGetLastEventReq, UIMRefreshGetLastEventResp *pUIMRefreshGetLastEventResp)

- ULONG SLQSUIMGetFileAttributes (UIMGetFileAttributesReq *pUIMGetFileAttributesReq, UIMGetFileAttributesResp *pUIMGetFileAttributesResp)
- ULONG SLQSUIMDepersonalization (UIMDepersonalizationReq *pUIMDepersonilizationReq, UIMDepersonalizationResp *pUIMDepersonilizationResp)
- ULONG SLQSUIMAuthenticate (UIMAuthenticateReq *pUIMAuthenticateReq, UIMAuthenticateResp *pUIMAuthenticateResp)
- ULONG SLQSUIMReadTransparent (UIMReadTransparentReq *pUIMReadTransparentReq, UIMReadTransparentResp *pUIMReadTransparentResp)
- ULONG SLQSUIMPowerUp (UIMPowerUpReq *pUIMPowerUpReq)
- ULONG SLQSUIMGetSlotsStatus (UIMGetSlotsStatusResp *pResp)
- ULONG SLQSUIMSwitchSlot (UIMSwitchSlotReq *pReq)
- ULONG SLQSUIMGetConfiguration (UIMGetConfigurationReq *pUIMGetConfigurationReq, UIMGetConfigurationResp *pUIMGetConfigurationResp)

9.47.1 Detailed Description

Uim Service API function prototypes.

9.47.2 Macro Definition Documentation

9.47.2.1 #define MAX_ACTIVE_PERS_FEATURES 12

9.47.2.2 #define MAX_CONTENT_LENGTH 1024

9.47.2.3 #define MAX_DESCRIPTION_LENGTH 255

9.47.2.4 #define MAX_ICCID_LENGTH 255

9.47.2.5 #define MAX_NO_OF_APPLICATIONS 10

9.47.2.6 #define MAX_NO_OF_SLOTS 5

9.47.2.7 #define MAX_PATH_LENGTH 255

9.47.2.8 #define MAX_PUK_LENGTH 8

9.47.2.9 #define MAX_SLOTS_STATUS 255

9.47.3 Function Documentation

9.47.3.1 ULONG SLQSUIMAuthenticate (UIMAuthenticateReq * *pUIMAuthenticateReq,* UIMAuthenticateResp * *pUIMAuthenticateResp*)

This API executes the authentication algorithm on the card.

Parameters

pUIMAuthenticateReq[IN]	• See UIMAuthenticateReq for more information.
pUIMAuthenticateResp[OUT]	• See UIMAuthenticateResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This API executes a security command on the card that depends on
the card type.
The response contains the status code received from the card
(SW1 and SW2) when the card responded to the read request.
The client can pass a token in the request to receive the result
in a subsequent SLQSUIMAuthenticateCallback
```

9.47.3.2 ULONG SLQSUIMChangePin (UIMChangePinReq * *pUIMChangePinReq*, UIMPinResp * *pUIMChangePinResp*)

This API changes the value of the specified PIN.

Parameters

pUIMChange-PinReq[IN]	• See UIMChangePinReq for more information.
pUIMChange-PinResp[OUT]	• See UIMPinResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This API changes the value of the specified PIN.
The application must pass both the new and the old values of the
PIN to complete the operation
The same PIN can be used by multiple sessions (i.e., the PIN is
shared between GSM and RUIM in an ICC card).
The PIN is automatically set for all the sessions when the API
is executed.
The client can pass a token in the request to receive the result
in a subsequent SLQSUIMChangePinCallback.
```

9.47.3.3 ULONG SLQSUIMDepersonalization (UIMDepersonalizationReq * *pUIMDepersonilizationReq*, UIMDepersonalizationResp * *pUIMDepersonilizationResp*)

This API de-activates or unblocks the personalization on the phone.

Parameters

pUIM-Depersonilization-Req[IN]	• See UIMDepersonalizationReq for more information.
pUIM-Depersonilization-Resp[OUT]	• See UIMDepersonalizationResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This API deactivates or unblocks the personalization on the phone.
Each feature can be deactivated/unblocked independently of the
other features.
```

9.47.3.4 ULONG SLQSUIMEventRegister (UIMEventRegisterReqResp * *pUIMEventRegisterReqResp*)

This API Registers for event notifications from the card.

Parameters

pUIMEvent-RegisterReq-Resp[IN/OUT]	• See UIMEventRegisterReqResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This function registers for event notifications from the card.
The client must verify the mask in the response to determine
which events were registered successfully. Events not supported
correctly are not registered. The client can deregister from
all event notifications by passing "0x00000000" bitmask in the
request.
```

9.47.3.5 ULONG SLQSUIMGetCardStatus (UIMGetCardStatusResp * *pUIMGetCardStatusResp*)

This API retrieves the current status of the card.

Parameters

pUIMGetCardStatusResp[OUT]	• See UIMGetCardStatusResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This function retrieves the current status of the card(activated)
and the status of all applications available on the card.
The function also returns support information for the hot-swap
feature and the status of the switch used to detect a card
removal/insertion.

Please use \ref SLQSUIMGetSlotsStatus to retrieves active and
inactivate SIMs status.
```

9.47.3.6 ULONG SLQSUIMGetCardStatusV2 (UIMGetCardStatusRespV2 * *pUIMGetCardStatusResp*)

This API retrieves the current status of the card -V2.

Parameters

pUIMGetCardStatusResp[OUT]	• See UIMGetCardStatusResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This function retrieves the current status of the card(activated)
and the status of all applications available on the card.
The function also returns support information for the hot-swap
feature and the status of the switch used to detect a card
removal/insertion.

Please use \ref SLQSUIMGetSlotsStatus to retrieves active and
inactivate SIMs status.
```

9.47.3.7 ULONG SLQSUIMGetConfiguration (UIMGetConfigurationReq * *pUIMGetConfigurationReq*, UIMGetConfigurationResp * *pUIMGetConfigurationResp*)

This API Gets the modem configuration for the UIM module.

Parameters

pUIMGet-Configuration-Req[IN]	• See UIMGetConfigurationReq for more information.
pUIMGet-Configuration-Resp[OUT]	• See UIMGetConfigurationResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

9.47.3.8 ULONG SLQSUIMGetFileAttributes (UIMGetFileAttributesReq * *pUIMGetFileAttributesReq*, UIMGetFileAttributesResp * *pUIMGetFileAttributesResp*)

This API retrieves the file attributes for any Elementary File(EF) or Dedicated File(DF) in the card and provides access by the path.

Parameters

pUIMGetFile-AttributesReq[I-N]	• See UIMGetFileAttributesReq for more information.
pUIMGetFile-AttributesResp[-OUT]	• See UIMGetFileAttributesResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This API retrieves the file attributes for any Elementary File(EF)
or Dedicated File(DF) in the card and provides access by the path.
The response contains the status code received from the card
```

```
(SW1 and SW2) when the card responded to the select request.
The client can pass a token in the request to receive the result
in a subsequent SLQSUIMGetFileAttributesCallback.
```

9.47.3.9 ULONG SLQSUIMGetSlotsStatus (UIMGetSlotsStatusResp * *pResp*)

This API Retrieves the current of the physical and logical slots.

Parameters

pResp[OUT]	• See UIMGetSlotsStatusResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

9.47.3.10 ULONG SLQSUIMPowerDown (UIMPowerDownReq * *pUIMPowerDownReq*)

This API powers down the SIM card.

Parameters

pUIMPower-DownReq[IN]	• See UIMPowerDownReq for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This function powers down the card.
This is usually performed when the phone is switched off or when
it is set to Airplane mode.
```

9.47.3.11 ULONG SLQSUIMPowerUp (UIMPowerUpReq * *pUIMPowerUpReq*)

This API powers up the SIM card.

Parameters

pUIMPowerUp-Req[IN]	• See UIMPowerUpReq for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This function powers up the card.
This is usually performed when the phone is switched off or when
it is set to Airplane mode.
```

9.47.3.12 ULONG SLQSUIMReadTransparent (UIMReadTransparentReq * *pUIMReadTransparentReq*, UIMReadTransparentResp * *pUIMReadTransparentResp*)

This API executes the Read Transparent algorithm on the card.

Parameters

pUIMRead-Transparent-Req[IN]	• See UIMReadTransparentReq for more information.
pUIMRead-Transparent-Resp[OUT]	• See UIMReadTransparentResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This API Provides read access to any transparent file in the
card and provides access by the path.
The response contains the status code received from the card
(SW1 and SW2) when the card responded to the read request.
The client can pass a token in the request to receive the result
in a subsequent QMI_UIM_READ_TRANSPARENT_IND indication.
```

9.47.3.13 ULONG SLQSUIMRefreshComplete (UIMRefreshCompleteReq * *pUIMRefreshCompleteReq*)

This API invoked when the client has finished the Refresh procedure.

Parameters

pUIMRefresh-CompleteReq[I-N]	• See UIMRefreshCompleteReq for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This function is invoked when the client has finished the Refresh
procedure (has reread all the cached files) and communicates this
to the modem. This function enables the terminal response to be
sent to the card
```

9.47.3.14 ULONG SLQSUIMRefreshGetLastEvent (UIMRefreshGetLastEventReq * *pUIMRefreshGetLastEventReq*, UIMRefreshGetLastEventResp * *pUIMRefreshGetLastEventResp*)

This API provides the ability to retrieve the last refresh event.

Parameters

pUIMRefresh-GetLastEvent-Req[IN]	• See UIMRefreshGetLastEventReq for more information.
pUIMRefresh-GetLastEvent-Resp[OUT]	• See UIMRefreshGetLastEventResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This function provides the ability to retrieve the last refresh
event. The event information is usually passed in as an indication
from the QMI to the application and is saved by the application at
that time. If the event information is not saved, the client can
retrieve the last refresh event.
Details regarding the Refresh procedure (i.e., the stages and
actions that an application must complete) are described in
document: 80-VM566-1(NAA Refresh High Level Guide )
```

9.47.3.15 ULONG SLQSUIMRefreshOK (UIMRefreshOKReq * *pUIMRefreshOKReq*)

This API Enables the client to indicate whether it is OK to start the Refresh procedure.

Parameters

pUIMRefreshO-KReq[IN]	• Consist of parameters for SLQSUIMRefreshOK. Please see /ref UIMRefreshOKReq for details.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This function enables the client to indicate whether it is OK to
start the Refresh procedure. This command is used only after a
refresh event is received, which indicates the need to vote.
```

9.47.3.16 ULONG SLQSUIMRefreshRegister (UIMRefreshRegisterReq * *pUIMRefreshRegisterReq*)

This API Registers for file change notifications triggered by the card.

Parameters

pUIMRefresh-RegisterReq[IN]	• See UIMRefreshRegisterReq for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This function registers for file change notifications triggered
by the card. The client can specify a list of files. The client
is notified only when one of the files is modified by the Refresh
procedure. This function can be invoked multiple times for each
session type. If the function is invoked twice with the same session
type, the new values overwrite the previous values. The client can
also use this function to stop receiving indications of the refresh.
This API should be invoked prior to the invocation of the
SLQSUIMSetRefreshCallBack for the events to be registered.
```

9.47.3.17 ULONG SLQSUIMReset ( )

This API resets the issuing control points state kept by the service.

Parameters

None	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
The list of events to which the client is registered is emptied.
The client must register again using the SLQSUIMEventReg API
to start receiving the events again. This would mean that the
callback registrations would be reset after this API.
```

9.47.3.18 ULONG SLQSUIMSetPinProtection (UIMSetPinProtectionReq * *pUIMSetPinProtectionReq,* UIMPinResp * *pUIMSetPinProtectionResp*)

This API enables or disables the protection of the UIM contents by a specific PIN.

Parameters

pUIMSetPinProtectionReq[IN]	• See UIMSetPinProtectionReq for more information.
pUIMSetPinProtectionResp[OUT]	• See UIMPinResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This API enables or disables the protection of UIM contents by a
specific PIN.
The same PIN can be used by multiple sessions (i.e., the PIN is
shared between GSM and RUIM in an ICC card).
The PIN is automatically set for all the sessions when the API
is executed.
The client can pass a token in the request to receive the result
in a subsequent SLQSUIMSetPinProtectionCallback indication.
```

9.47.3.19 ULONG SLQSUIMSwitchSlot (UIMSwitchSlotReq * *pReq*)

This API Switches the binding between a logical slot and a physical slot.

Parameters

pReq[IN]	• See UIMSwitchSlotReq for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
Please wait at least one second before this API call again.
```

9.47.3.20 ULONG SLQSUIMUnblockPin (UIMUnblockPinReq * *pUIMUnblockPinReq*, UIMPinResp * *pUIMUnblockPinResp*)

This API unblocks a blocked PIN using the PUK code.

Parameters

pUIMUnblock-PinReq[IN]	• See UIMUnblockPinReq for more information.
pUIMUnblock-PinResp[OUT]	• See UIMPinResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This API unblocks a blocked PIN using the PUK code.
The client must pass PUK1 to unblock PIN1 or PUK2 to unblock PIN2.
The same PIN can be used by multiple sessions (i.e., the PIN is
shared between GSM and RUIM in an ICC card).
The PIN is automatically set for all the sessions when the API
is executed.
The client can pass a token in the request to receive the result
in a subsequent SLQSUIMUnblockPinCallback.
```

9.47.3.21 ULONG SLQSUIMUnblockPinV2 (UIMUnblockPinReq * *pUIMUnblockPinReq*, UIMPinRespV2 * *pUIMUnblockPinResp*)

This API unblocks a blocked PIN using the PUK code -V2.

Parameters

pUIMUnblock-PinReq[IN]	• See UIMUnblockPinReq for more information.
pUIMUnblock-PinResp[OUT]	• See UIMPinResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This API unblocks a blocked PIN using the PUK code.
The client must pass PUK1 to unblock PIN1 or PUK2 to unblock PIN2.
The same PIN can be used by multiple sessions (i.e., the PIN is
shared between GSM and RUIM in an ICC card).
The PIN is automatically set for all the sessions when the API
is executed.
The client can pass a token in the request to receive the result
in a subsequent SLQSUIMUnblockPinCallback.
```

9.47.3.22 ULONG SLQSUIMVerifyPin (UIMVerifyPinReq * *pUIMVerifyPinReq*, UIMPinResp * *pUIMVerifyPinResp*)

This API verifies the PIN before the card content is accessed.

Parameters

pUIMVerifyPin-Req[IN]	• See UIMVerifyPinReq for more information.
pUIMVerifyPin-Resp[OUT]	• See UIMPinResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs

```
This API verifies the PIN before the card content is accessed.
The same PIN can be used by multiple sessions (i.e., the PIN is
shared between GSM and RUIM in an ICC card).
The PIN is automatically set for all the sessions when the API
is executed.
The client can pass a token in the request to receive the result
in a subsequent SLQSUIMVerifyPinCallback.
```

9.48 qaGobiApiVoice.h File Reference

Voice Service API function prototypes.

Data Structures

- struct USSInfo
- struct UUSInfo
- struct CUGInfo
- struct calledPartySubAdd
- struct voiceCallRequestParams
- struct alphaIDInfo
- struct ccSUPSType
- struct voiceCallResponseParams
- struct callFwdTypeAndPlan
- struct voiceSetSUPSServiceReq
- struct voiceSetSUPSServiceResp
- struct airTimer
- struct roamTimer
- struct prefVoiceSO
- struct voiceSetConfigReq
- struct voiceSetConfigResp
- struct voiceAnswerCall
- struct CLIRResp
- struct voiceGetCLIRResp
- struct CLIPResp
- struct voiceGetCLIPResp
- struct voiceGetCallWaitInfo
- struct voiceGetCallBarringReq
- struct voiceGetCallBarringResp
- struct voiceGetCallFWReq
- struct callFWInfo
- struct callFWExtInfo
- struct getCallFWInfo
- struct getCallFWExtInfo
- struct voiceGetCallFWResp
- struct voiceSetCallBarringPwdInfo
- struct voiceSetCallBarringPwdResp
- struct callInfo
- struct remotePartyNum
- struct remotePartyName
- struct connectNumInfo
- struct diagInfo
- struct voiceCallInfoReq

- struct voiceCallInfoResp
- struct getAllCallInformation
- struct getAllCallRmtPtyNum
- struct getAllCallRmtPtyName
- struct allCallsUUSInfo
- struct allCallsAlphaIDInfo
- struct allCallsDiagInfo
- struct peerNumberInfo
- struct arrCallInfo
- struct arrRemotePartyNum
- struct arrRemotePartyName
- struct arrAlertingType
- struct arrUUSInfo
- struct arrSvcOption
- struct arrCallEndReason
- struct arrAlphaID
- struct arrConnectPartyNum
- struct arrDiagInfo
- struct arrCalledPartyNum
- struct arrRedirPartyNum
- struct arrAlertingPattern
- struct voiceGetAllCallInfo
- struct voiceManageCallsReq
- struct voiceManageCallsResp
- struct burstDTMFInfo
- struct DTMFLengths
- struct voiceBurstDTMFInfo
- struct voiceContDTMFinfo
- struct voiceStopContDTMFinfo
- struct voiceFlashInfo
- struct voiceSetPrefPrivacy
- struct voiceIndicationRegisterInfo
- struct DTMFInfo
- struct SUPSInfo
- struct newPwdData
- struct COLPResp
- struct COLRResp
- struct CNAPResp
- struct voiceGetConfigReq
- struct curAMRConfig
- struct voiceGetConfigResp
- struct voiceOrigUSSDNoWaitInfo
- struct voiceBindSubscriptionInfo
- struct voiceALSSetLineSwitchInfo
- struct voiceALSSelectLineInfo
- struct voiceGetCOLPResp
- struct voiceGetCOLRResp
- struct voiceGetCNAPResp
- struct USSResp
- struct USSDRespFNetwork

Macros

- #define MAXUSSDLENGTH 182
- #define MAX_CALL_NO_LEN 81
- #define MAX_DESCRIPTION_LENGTH 255
- #define PASSWORD_LENGTH 4
- #define MAX_NO_OF_CALLS 20

Enumerations

- enum serviceClassInformation {
  VOICE_SUPS_SRV_CLASS_NONE = 0x00,
  VOICE_SUPS_SRV_CLASS_VOICE = 0x01,
  VOICE_SUPS_SRV_CLASS_DATA = 0x02,
  VOICE_SUPS_SRV_CLASS_FAX = 0x04,
  VOICE_SUPS_SRV_CLASS_SMS = 0x08,
  VOICE_SUPS_SRV_CLASS_DATACIRCUITSYNC = 0x10,
  VOICE_SUPS_SRV_CLASS_DATACIRCUITASYNC = 0x20,
  VOICE_SUPS_SRV_CLASS_PACKETACCESS = 0x40,
  VOICE_SUPS_SRV_CLASS_PADACCESS = 0x80 }

Functions

- ULONG OriginateUSSD (BYTE *pInfo)
- ULONG AnswerUSSD (BYTE *pInfo)
- ULONG CancelUSSD ()
- ULONG SLQSVoiceDialCall (voiceCallRequestParams *pCallRequestParams, voiceCallResponseParams *pCallResponseParams)
- ULONG SLQSVoiceEndCall (BYTE *pCallId)
- ULONG SLQSVoiceSetSUPSService (voiceSetSUPSServiceReq *pVoiceSetSUPSServiceReq, voiceSetSUPSServiceResp *pVoiceSetSUPSServiceResp)
- ULONG SLQSVoiceSetConfig (voiceSetConfigReq *pVoiceSetConfigReq, voiceSetConfigResp *pVoiceSetConfigResp)
- ULONG SLQSVoiceAnswerCall (voiceAnswerCall *pVoiceAnswerCall)
- ULONG SLQSVoiceGetCLIR (voiceGetCLIRResp *pVoiceGetCLIRResp)
- ULONG SLQSVoiceGetCLIP (voiceGetCLIPResp *pVoiceGetCLIPResp)
- ULONG SLQSVoiceGetCallWaiting (voiceGetCallWaitInfo *pVoiceGetCallWaitInfo)
- ULONG SLQSVoiceGetCallBarring (voiceGetCallBarringReq *pVoiceGetCallBarringReq, voiceGetCallBarringResp *pVoiceGetCallBarringResp)
- ULONG SLQSVoiceGetCallForwardingStatus (voiceGetCallFWReq *pVoiceGetCallFWReq, voiceGetCallFWResp *pVoiceGetCallFWResp)
- ULONG SLQSVoiceSetCallBarringPassword (voiceSetCallBarringPwdInfo *pVoiceSetCallBarringPwdInfo, voiceSetCallBarringPwdResp *pSetCallBarringPwdResp)
- ULONG SLQSVoiceGetCallInfo (voiceCallInfoReq *pGetCallInfoReq, voiceCallInfoResp *pGetCallInfoResp)
- ULONG SLQSVoiceGetAllCallInfo (voiceGetAllCallInfo *pGetAllCallInfo)
- ULONG SLQSVoiceManageCalls (voiceManageCallsReq *pVoiceManageCallsReq, voiceManageCallsResp *pVoiceManageCallsResp)
- ULONG SLQSVoiceBurstDTMF (voiceBurstDTMFInfo *pBurstDTMFInfo)
- ULONG SLQSVoiceStartContDTMF (voiceContDTMFinfo *pContDTMFInfo)
- ULONG SLQSVoiceStopContDTMF (voiceStopContDTMFinfo *pVoiceStopContDTMFinfo)
- ULONG SLQSVoiceSendFlash (voiceFlashInfo *pFlashInfo)
- ULONG SLQSVoiceSetPreferredPrivacy (voiceSetPrefPrivacy *pSetPrefPrivacy)
- ULONG SLQSVoiceIndicationRegister (voiceIndicationRegisterInfo *pVoiceIndicationRegisterInfo)
- ULONG SLQSVoiceGetConfig (voiceGetConfigReq *pVoiceGetConfigReq, voiceGetConfigResp *pVoiceGetConfigResp)

- ULONG SLQSVoiceOrigUSSDNoWait (voiceOrigUSSDNoWaitInfo *pVoiceOrigUSSDNoWaitInfo)
- ULONG SLQSVoiceBindSubscription (voiceBindSubscriptionInfo *pVoiceBindSubscriptionInfo)
- ULONG SLQSVoiceALSSetLineSwitching (voiceALSSetLineSwitchInfo *pVoiceALSSetLineSwitchInfo)
- ULONG SLQSVoiceALSSelectLine (voiceALSSelectLineInfo *pVoiceALSSelectLineInfo)
- ULONG SLQSVoiceGetCOLP (voiceGetCOLPResp *pVoiceGetCOLPResp)
- ULONG SLQSVoiceGetCOLR (voiceGetCOLRResp *pVoiceGetCOLRResp)
- ULONG SLQSVoiceGetCNAP (voiceGetCNAPResp *pVoiceGetCNAPResp)
- ULONG SLQSOriginateUSSD (struct USSInfo *pReq, struct USSResp *pResp)

9.48.1 Detailed Description

Voice Service API function prototypes.

9.48.2 Macro Definition Documentation

9.48.2.1 #define MAX_CALL_NO_LEN 81

9.48.2.2 #define MAX_DESCRIPTION_LENGTH 255

9.48.2.3 #define MAX_NO_OF_CALLS 20

9.48.2.4 #define MAXUSSDLENGTH 182

9.48.2.5 #define PASSWORD_LENGTH 4

9.48.3 Enumeration Type Documentation

9.48.3.1 enum serviceClassInformation

Service Class information

Enumerator

VOICE_SUPS_SRV_CLASS_NONE

VOICE_SUPS_SRV_CLASS_VOICE

VOICE_SUPS_SRV_CLASS_DATA

VOICE_SUPS_SRV_CLASS_FAX

VOICE_SUPS_SRV_CLASS_SMS

VOICE_SUPS_SRV_CLASS_DATACIRCUITSYNC

VOICE_SUPS_SRV_CLASS_DATACIRCUITASYNC

VOICE_SUPS_SRV_CLASS_PACKETACCESS

VOICE_SUPS_SRV_CLASS_PADACCESS

9.48.4 Function Documentation

9.48.4.1 ULONG AnswerUSSD (BYTE * *pInfo*)

Responds to a USSD request from the network.

Parameters

pInfo[IN]	• USS information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 5 mins

9.48.4.2 ULONG CancelUSSD ( )

Cancels an in-progress USSD operation.

Parameters

None	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs

9.48.4.3 ULONG OriginateUSSD (BYTE * *pInfo*)

Initiates a USSD operation.

Parameters

pInfo[IN]	• USS information • See USSInfo for more details

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 5 mins

9.48.4.4 ULONG SLQSOriginateUSSD (struct USSInfo * *pReq*, struct USSResp * *pResp*)

Initiates a USSD session.

Parameters

pReq	[IN] • USS information • See USSInfo for more details
pResp	[OUT] • USS information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Device Supported: MC83x5
Timeout: 5 mins

9.48.4.5 ULONG SLQSVoiceALSSelectLine (voiceALSSelectLineInfo * *pVoiceALSSelectLineInfo*)

This API allows the user to select the preferred line.

Parameters

pVoiceALSSelectLineInfo[IN]	• See voiceALSSelectLineInfo for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
This API allows the user to select the preferred line, and the status is updated on the card. The API is supported only for specific SIM/USIMs that support alternate line service. This command is applicable only in 3GPP devices. A No Effect error is returned if the update on the card fails.

9.48.4.6 ULONG SLQSVoiceALSSetLineSwitching (voiceALSSetLineSwitchInfo * *pVoiceALSSetLineSwitchInfo*)

This API sets the line switch setting on the card.

Parameters

pVoiceALSSetLineSwitchInfo[IN]	• See voiceALSSetLineSwitchInfo for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
This API sets a line to be switchable or unswitchable, and the switch status is updated on the card. The API is supported only for specific SIM/USIMs that support alternate line service. This command is applicable only in 3GPP devices. A No Effect error is returned if the update on the card fails.

9.48.4.7 ULONG SLQSVoiceAnswerCall (voiceAnswerCall * *pVoiceAnswerCall*)

Answers an incoming voice call.

Parameters

pVoiceAnswerCall[IN/OUT]	• Pointer to structure of voiceAnswerCall – See voiceAnswerCall for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 10 Secs
This API is used to answer an incoming voice call when the incoming voice call is the only call present at that time. If there are other calls while an incoming call (waiting call) is received, API "SLQSVoiceSendFlash" can be used case of 3GPP2(CDMA) and API "SLQSVoiceManageCalls" in the case of 3GPP(UMTS). If the result indicates success, the device has started the requested operation and it does not mean that the call has been answered. "SLQSVoiceSetAllCallStatusCallback" can be subscribed to check the call Information/State.

9.48.4.8 ULONG SLQSVoiceBindSubscription (voiceBindSubscriptionInfo * *pVoiceBindSubscriptionInfo*)

This API binds a subscription type to a specific voice client ID.

Parameters

pVoiceBindSubscriptionInfo[IN]	• See voiceBindSubscriptionInfo for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs
Some versions of the modem support the Dual SIM feature. With this feature the modem can register with two different cellular networks simultaneously. Each network registration is associated with a different subscription, e.g., phone number, such that the modem appears to the network to be two different users. By default, the Voice client is bound to the primary subscription. This command allows the Voice client to change this binding. After receiving a successful response to this command, all future commands sent by the client will affect the newly bound subscription only.

9.48.4.9 ULONG SLQSVoiceBurstDTMF (voiceBurstDTMFInfo * *pBurstDTMFInfo*)

Sends a burst Dual-Tone Multi frequency (DTMF) (applicable only for 3GPP2)

Parameters

pBurstDTMFInfo[IN/OUT]	• Structure containing parameters of burst DTMF. • See voiceBurstDTMFInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 30 Secs
Applicable only for 3GPP2. This API sends a burst DTMF. If API result indicates success, this means the device has started the requested operation. It does not mean that the burst DTMF request has been sent to the network. A burst DTMF request is sent to the current active/alerting call when CallId is set to 0xFF. This API is applicable only in 3GPP2.

9.48.4.10 ULONG SLQSVoiceDialCall (voiceCallRequestParams * *pCallRequestParams*, voiceCallResponseParams * *pCallResponseParams*)

Originates a voice call (MO call).

Parameters

pCallRequestParams[IN]	• Pointer to structure of voiceCallRequestParams – See voiceCallRequestParams for more information
pCallResponseParams[OUT]	• Pointer to structure of voiceCallResponseParams – See voiceCallResponseParams for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs
This API originates a voice call (MO). If the function returns success with a call_id, the device has started the requested operation. It does not mean that the call has been connected. SLQSVoiceSetAllCallStatusCallback() callback can be subscribed to learn if the call was successful.

9.48.4.11 ULONG SLQSVoiceEndCall (BYTE * *pCallId*)

This message ends a voice call

Parameters

pCallId	[IN/OUT] • Unique call identifier for the call that must be ended

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs
If the function returns success, the device has started the requested operation. It does not mean that the call has been ended. The application should always process the SLQSVoiceSetAllCallStatusCallback() callback to learn if the call was ended.

9.48.4.12 ULONG SLQSVoiceGetAllCallInfo (voiceGetAllCallInfo * *pGetAllCallInfo*)

This API queries the information associated with all the calls originating or terminating from a particular device.

Parameters

pGetAllCallInfo[-OUT]	• See voiceGetAllCallInfo for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs
This command is used by the control point to get information of all the calls to and fro from the device in progress. The information keeps on updating constantly, as the state of a call changes example,from incoming to conversation to terminated.
This API requires a firmware with at least voice 2.0 support.

9.48.4.13 ULONG SLQSVoiceGetCallBarring (voiceGetCallBarringReq * *pVoiceGetCallBarringReq,* voiceGetCallBarringResp * *pVoiceGetCallBarringResp*)

Queries the status of Call Barring Supplementary Service (applicable only for 3GPP).

Parameters

pVoiceGetCall-BarringReq[IN]	• Pointer to structure of voiceGetCallBarringReq – See voiceGetCallBarringReq for more information
pVoiceGetCall-BarringResp[O-UT]	• Pointer to structure of voiceGetCallBarringResp – See voiceGetCallBarringResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
This API queries the status of the call barring supplementary service, i.e., to find whether the call barring supplementary service is active and, if active, for which service classes it is active. The request is a blocking request, i.e., the response is sent only after confirmation is received from the network. The maximum time it takes for the response to be sent is approximately 30 sec. This API is applicable only in 3GPP devices.

9.48.4.14 ULONG SLQSVoiceGetCallForwardingStatus (voiceGetCallFWReq * *pVoiceGetCallFWReq,* voiceGetCallFWResp * *pVoiceGetCallFWResp*)

Queries the status of Call Forwarding Supplementary Service.

Parameters

pVoiceGetCallFWReq[IN]	• Pointer to structure of voiceGetCallFWReq – See voiceGetCallFWReq for more information
pVoiceGetCallFWResp[OUT]	• Pointer to structure of voiceGetCallFWResp – See voiceGetCallFWResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
This API queries the status of the call forwarding supplementary service, i.e., to find whether the call forwarding supplementary service is active and, if active, for which service classes and call forwarding number it is active. The request is a blocking request, i.e., the response is sent only after confirmation is received from the network. The maximum time it takes for the response to be sent is approximately 30 sec. This API is applicable only in 3GPP devices.

9.48.4.15 ULONG SLQSVoiceGetCallInfo (voiceCallInfoReq * *pGetCallInfoReq,* voiceCallInfoResp * *pGetCallInfoResp*)

This API queries the information associated with a call and gives information about a particular call whose call Id is sent in as request.

Parameters

pGetCallInfo-Req[IN]	• See voiceCallInfoReq for more information.
pGetCallInfo-Resp[OUT]	• See voiceCallInfoResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs
If no voice call is in progress or an invalid call_id is sent in the request, an error is returned as the response.
This API requires a firmware with atleast voice 2.0 support.

9.48.4.16 ULONG SLQSVoiceGetCallWaiting (voiceGetCallWaitInfo * *pVoiceGetCallWaitInfo*)

Queries the status of Call Waiting Supplementary Service (applicable only for 3GPP).

Parameters

pVoiceGetCall-WaitInfo[IN/OUT]	• Pointer to structure of voiceGetCallWaitInfo – See voiceGetCallWaitInfo for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
This API queries the status of the call waiting supplementary service, i.e., to find whether the call waiting supplementary service is active. The request is a blocking request, i.e., the response is sent only after confirmation is received from the network. The maximum time it takes for the response to be sent is approximately 30 sec. This API is applicable only in 3GPP devices.

9.48.4.17 ULONG SLQSVoiceGetCLIP (voiceGetCLIPResp * *pVoiceGetCLIPResp*)

Queries the status of the Calling Line Identification Presentation (CLIP) supplementary service (applicable only for 3GPP).

Parameters

pVoiceGetCLIP-Resp[OUT]	• Pointer to structure of voiceGetCLIPResp – See voiceGetCLIPResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
This API queries the status of the CLIP supplementary service. The active_status field is only applicable when provision_status is PROVISIONED, i.e., there is not any case where provision_status is NOT_PROVISIONED and active_status is ACTIVE. The request is a blocking request, i.e., the response is sent only after confirmation is received from the network. The maximum time it takes for the response to be sent is approximately 30 sec. This API is applicable only in 3GPP devices.

9.48.4.18 ULONG SLQSVoiceGetCLIR (voiceGetCLIRResp * *pVoiceGetCLIRResp*)

Queries the status of the Calling Line Identification Restriction (CLIR) supplementary service (applicable only for 3GPP).

Parameters

pVoiceGetCLIR-Resp[OUT]	• Pointer to structure of voiceGetCLIRResp – See voiceGetCLIRResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
This API queries the status of the CLIR supplementary service. The active_status field is only applicable when provision_status is PROVISIONED, i.e., there is not any case where provision_status is NOT_PROVISIONED and active_status is ACTIVE. The request is a blocking request, i.e., the response is sent only after confirmation is received from the network. The maximum time it takes for the response to be sent is approximately 30 sec. This API is applicable only in 3GPP devices.

9.48.4.19 ULONG SLQSVoiceGetCNAP (voiceGetCNAPResp * *pVoiceGetCNAPResp*)

Queries the status of the Calling Name Presentation(CNAP) supplementary service (applicable only for 3GPP).

Parameters

pVoiceGetCNAPResp[OUT]	• Pointer to structure of voiceGetCNAPResp – See voiceGetCNAPResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs

This API queries the status of the CNAP supplementary service. A response indicates whether CNAP is active/inactive and provisioned/not provisioned in the network. The active_status field is only applicable when provision_status is PROVISIONED, i.e., there is not any case where provision_status is NOT_PROVISIONED and active_status is ACTIVE. This API is applicable only in 3GPP devices.

9.48.4.20 ULONG SLQSVoiceGetCOLP (voiceGetCOLPResp * *pVoiceGetCOLPResp*)

Queries the status of the Connected Line Identification Presentation (COLP) supplementary service (applicable only for 3GPP).

Parameters

pVoiceGetCOLPResp[OUT]	• Pointer to structure of voiceGetCOLPResp – See voiceGetCOLPResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs

This API queries the status of the COLP supplementary service. A response indicates whether COLP is active/inactive and provisioned/not provisioned in the network. The active_status field is only applicable when provision_status is PROVISIONED, i.e., there is not any case where provision_status is NOT_PROVISIONED and active_status is ACTIVE. This API is applicable only in 3GPP devices.

9.48.4.21 ULONG SLQSVoiceGetCOLR (voiceGetCOLRResp * *pVoiceGetCOLRResp*)

Queries the status of the Connected Line Identification Restriction (COLR) supplementary service (applicable only for 3GPP).

Parameters

pVoiceGetCOLRResp[OUT]	• Pointer to structure of voiceGetCOLRResp – See voiceGetCOLRResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs

This API queries the status of the COLR supplementary service. A response indicates whether COLR is active/inactive and provisioned/not provisioned in the network. The active_status field is only applicable when provision_status is PROVISIONED, i.e., there is not any case where provision_status is NOT_PROVISIONED and active_status is ACTIVE. This API is applicable only in 3GPP devices.

9.48.4.22 ULONG SLQSVoiceGetConfig (voiceGetConfigReq * *pVoiceGetConfigReq*, voiceGetConfigResp * *pVoiceGetConfigResp*)

This API retrieves various configuration parameters that control the modem behavior related to circuit switched services.

Parameters

pVoiceGetConfigReq	• Structure containing Get Config request parameters. – See voiceGetConfigReq for more information.
pVoiceGetConfigResp	• Structure containing Get Config response parameters. – See voiceGetConfigResp for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs
Any invalid value in a request message causes the service point to reject the message without retrieving any configuration information.

9.48.4.23 ULONG SLQSVoiceIndicationRegister (voiceIndicationRegisterInfo * *pVoiceIndicationRegisterInfo*)

Sets the registration state for different QMI_VOICE indications for the requesting control point

Parameters

pVoice-Indication-RegisterInfo[IN]	• Structure containing Indication Register Information. – See voiceIndicationRegisterInfo for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 10 Secs

```
This API is used by a device to register/deregister for different
QMI VOICE indications.
The device's registration state variables that control registration
for indications will be modified to reflect the settings indicated in the
request message.
At least one optional parameter must be present in the request.
```

9.48.4.24 ULONG SLQSVoiceManageCalls (voiceManageCallsReq * *pVoiceManageCallsReq,* voiceManageCallsResp * *pVoiceManageCallsResp*)

Manages the calls by using the supplementary service applicable during the call. In cases of successful API completion if the state of any call is changed, it is indicated using CallBack SLQSVoiceSetAllCallStatusCallBack. If there are other calls while an incoming voice call (waiting call) is received, this API is used to answer the call. This API is applicable only in "3GPP devices".

Parameters

pVoiceManage-CallsReq[IN]	• Request structure of to manage calls.
pVoiceManage-CallsResp[OUT]	• Response Structure to manage Calls

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 10 Secs
Applicable only for "3GPP"

9.48.4.25 ULONG SLQSVoiceOrigUSSDNoWait (voiceOrigUSSDNoWaitInfo * *pVoiceOrigUSSDNoWaitInfo*)

This API initiates a USSD operation such that the response for this request is returned immediately and the data is returned via an indication.

Parameters

pVoiceOrigUSSDNoWaitInfo[IN]	• See voiceOrigUSSDNoWaitInfo for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
This API starts a new USSD operation. The response to the request is sent immediately. The response result is sent to the client via the SLQSVoiceOrigUSSDNoWaitCallback. This command is applicable only in 3GPP devices.

9.48.4.26 ULONG SLQSVoiceSendFlash (voiceFlashInfo * *pFlashInfo*)

This API sends a simple flash message. Applicable only for 3GPP2 devices.

Parameters

pFlashInfo[IN/OUT]	• See voiceFlashInfo for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 10 Secs
If success, it only means the device has started the requested operation and not that the Flash has been sent. If the optional parameter Flash Type is not set, the default flash type is assumed to be a simple flash. If the parameter Flash Type is set to 1 the call ID corresponding to it is either an incoming or waiting call's call ID. If the parameter Flash Type is set to 2 the call ID corresponding to it is a held call's call ID. A Flash request is sent to the appropriate call when call_id is set to 0xFF.

9.48.4.27 ULONG SLQSVoiceSetCallBarringPassword (voiceSetCallBarringPwdInfo * *pVoiceSetCallBarringPwdInfo*, voiceSetCallBarringPwdResp * *pSetCallBarringPwdResp*)

Sets a Call Barring Password (applicable only for 3GPP).

Parameters

pVoiceSetCallBarringPwdInfo[IN]	• Pointer to structure of voiceSetCallBarringPwdInfo – See voiceSetCallBarringPwdInfo for more information
pSetCallBarringPwdResp[OUT]	• Pointer to structure of voiceSetCallBarringPwdResp – See voiceSetCallBarringPwdResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
This API changes the call barring supplementary service password. The request is a blocking request, i.e., the response is sent only after confirmation is received from the network. The maximum time it takes for the response to be sent is approximately 30 sec. This API is applicable only in 3GPP devices.

9.48.4.28 ULONG SLQSVoiceSetConfig (voiceSetConfigReq * *pVoiceSetConfigReq*, voiceSetConfigResp * *pVoiceSetConfigResp*)

This message sets various configuration parameters that control the modem behavior related to circuit-switched services.

Parameters

pVoiceSetConfigReq[IN]	• Pointer to structure of voiceSetConfigReq – See voiceSetConfigReq for more information
pVoiceSetConfigResp[OUT]	• Pointer to structure of voiceSetConfigResp – See voiceSetConfigResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs
Any invalid value in a request message causes the device to reject the message without updating any configuration information. In the case of a successful update of all requested information, a QMI_ERR_NONE error is returned. In the case where a subset of information failed to be written, a QMI_ERR_INTERNAL error is returned with corresponding optional information requested in the request message.

9.48.4.29 ULONG SLQSVoiceSetPreferredPrivacy (voiceSetPrefPrivacy * *pSetPrefPrivacy*)

This API sets the voice privacy preference. Applicable only for 3GPP2 devices.

Parameters

pSetPrefPrivacy[IN]	• See voiceSetPrefPrivacy for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Device Supported: SL9090
Timeout: 10 Secs

9.48.4.30 ULONG SLQSVoiceSetSUPSService (voiceSetSUPSServiceReq * *pVoiceSetSUPSServiceReq,* voiceSetSUPSServiceResp * *pVoiceSetSUPSServiceResp*)

This API manages call-independent supplementary services, e.g., activation of call forwarding (to forward incoming calls to a third party), activation of call barring (to request the network to block some of the call attempts), and activation of call waiting (to be notified of an incoming call even when the user is engaged in an active or held call).

Parameters

pVoiceSetSUPSServiceReq	[IN] • Pointer to structure of voiceSetSUPSServiceReq – See voiceSetSUPSServiceReq for more information
pVoiceSetSUPSServiceResp	[OUT] • Pointer to structure of voiceSetSUPSServiceResp – See voiceSetSUPSServiceResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Timeout: 30 Secs
Some of the call-independent services are provided by the network operator as part of the service agreement. If they are not provided by default, the user has to explicitly request them. This API provides the facility to the control point for sending the explicit request to the network for enabling/disabling

9.48.4.31 ULONG SLQSVoiceStartContDTMF (voiceContDTMFinfo * *pContDTMFInfo*)

Starts a continuous DTMF.

Parameters

pContDTMF-Info[IN/OUT]	• Structure containing Continuous DTMF Information. – See voiceContDTMFinfo for more Information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs
This API starts a continuous DTMF. If the API results indicates success, it means that the device has started the requested operation. It does not mean that the start continuous DTMF request has been sent to the network. A start continuous DTMF request is sent to the current active/alerting call when CallId is set to 0xFF.

9.48.4.32 ULONG SLQSVoiceStopContDTMF (voiceStopContDTMFinfo * *pVoiceStopContDTMFinfo*)

Stops a continuous DTMF.

Parameters

pVoiceStopCont-DTMFinfo	• Structure containing Continuous Stop DTMF Information. – See voiceStopContDTMFinfo for more information. • Start continuous DTMF request is sent to the current active/alerting call when CallId is set to 0xFF. • This is IN/OUT params, value passed by user will packed in request and before unpacking response this will be assigned with an invalid callID value "0". It change to a valid value if received as part of response otherwise Invalid value will be present.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 30 Secs
This API starts a continuous DTMF. If the API results indicates success, it means that the device has started the requested operation. It does not mean that the start continuous DTMF request has been sent to the network. A stop continuous DTMF request is sent to the current active/alerting call when CallId is set to 0xFF.

9.49 qaGobiApiWds.h File Reference

Wireless Data Service API function prototypes.

Data Structures

- struct dataBearerTechnology
- struct dataBearers
- struct QmiWdsIpAddressInfo
- struct WdsIpAddressInfoReq
- struct UMTSQoS
- struct ProfileIdentifier
- struct GPRSQoS
- struct PCSCFIPv4ServerAddressList
- struct PCSCFFQDNAddress
- struct PCSCFFQDNAddressList
- struct Domain
- struct DomainNameList
- struct IPV6AddressInfo
- struct IPV6GWAddressInfo
- struct qmiWdsRunTimeSettings
- struct WdsRunTimeSettings
- struct ssdatasession_params
- struct SLQSDeleteProfileParams
- struct Profile3GPP
- struct Profile3GPP2
- union WdsProfileParam
- struct CreateProfileIn
- struct UMTSMinQoS
- struct GPRSRequestedQoS
- struct TFTIDParams
- struct UMTSReqQoSSigInd
- struct QosClassID
- struct CreateProfileOut
- struct slqsautoconnect
- struct ModifyProfileIn
- struct ModifyProfileOut
- struct _slqs3GPPConfigItem
- struct _GetProfileSettingIn

- struct _GetProfileSettingOut
- struct TrStatInd
- struct wdsSetEventReportReq
- struct swiPDPRuntimeSettingsReq
- struct swiPDPRuntimeSettingsResp
- struct WdsConnectionRateElmnts
- struct WdsConnectionRate
- struct WdsByteTotalsElmnts
- struct WdsByteTotals
- struct GetInstIDResp
- struct GetSessionIDResp
- struct TransferStatInd
- struct getDUNCallInfoReq
- struct ConnectionStatus
- struct ChannelRate
- struct getDUNCallInfoResp
- struct WdsPktStatisticsElmnts
- struct WdsPktStatisticsResp
- struct WdsPktStatisticsReq
- struct CurrNetworkInfo
- struct CurrDataSysStat
- struct swiRMTrasnferStaticsReq
- struct DataULongTlv
- struct DataULongLongTlv
- struct QmiCbkWdsStatisticsIndState
- struct DataBearerTech
- struct DataBearerTechExt
- struct WDSSWICurrentChannelRates
- struct WDSSetLoopbackData
- struct WDSGetLoopbackData
- struct WdsDHCPv4ProfileId
- struct WdsDHCPv4HWConfig
- struct WdsDHCPv4Option
- struct WdsDHCPv4OptionList
- struct WdsDHCPv4Config
- struct WdsClientLeaseChange

Macros

- #define IPV6_ADDRESS_ARRAY_SIZE 8

Typedefs

- typedef struct dataBearerTechnology QmiWDSDataBearerTechnology
- typedef struct dataBearers QmiWDSDataBearers
- typedef union WdsProfileParam QmiProfileInfo
- typedef struct _slqs3GPPConfigItem slqs3GPPConfigItem
- typedef struct _GetProfileSettingIn GetProfileSettingIn
- typedef struct _GetProfileSettingOut GetProfileSettingOut

Enumerations

- enum qmiDataBearerMasks {
  QMI_WDS_CURRENT_CALL_DB_MASK = 0x01,
  QMI_WDS_LAST_CALL_DB_MASK = 0x02 }
- enum pdpidx {
  WDSPDP1IDX,
  WDSPDP2IDX,
  WDSPDP3IDX,
  WDSPDP4IDX,
  WDSPDP5IDX,
  WDSPDP6IDX,
  WDSPDP7IDX,
  WDSPDP8IDX,
  WDSNUMPDPS }

Functions

- ULONG SetMobileIP (ULONG mode)
- ULONG GetMobileIP (ULONG *pMode)
- ULONG SetMobileIPParameters (CHAR *pSPC, ULONG *pMode, BYTE *pRetryLimit, BYTE *pRetryInterval, BYTE *pReRegPeriod, BYTE *pReRegTraffic, BYTE *pHAAuthenticator, BYTE *pHA2002bis)
- ULONG SetAutoconnect (ULONG setting)
- ULONG GetAutoconnect (ULONG *pSetting)
- ULONG SetDefaultProfile (ULONG profileType, ULONG *pPDPType, ULONG *pIPAddress, ULONG *pPrimaryDNS, ULONG *pSecondaryDNS, ULONG *pAuthentication, CHAR *pName, CHAR *pAPNName, CHAR *pUsername, CHAR *pPassword)
- ULONG SetDefaultProfileLTE (ULONG profileType, ULONG *pPDPType, ULONG *pIPAddressv4, ULONG *pPrimaryDNSv4, ULONG *pSecondaryDNSv4, USHORT *pIPAddressv6, USHORT *PrimaryDNSv6, USHORT *pSecondaryDNSv6, ULONG *pAuthentication, CHAR *pName, CHAR *pAPNName, CHAR *pUsername, CHAR *pPassword)
- ULONG SetDefaultProfileLTEV2 (ULONG profileType, ULONG *pPDPType, ULONG *pIPAddressv4, ULONG *pPrimaryDNSv4, ULONG *pSecondaryDNSv4, USHORT *pIPAddressv6, USHORT *PrimaryDNSv6, USHORT *pSecondaryDNSv6, ULONG *pAuthentication, CHAR *pName, CHAR *pAPNName, CHAR *pUsername, CHAR *pPassword)
- ULONG GetDefaultProfile (ULONG profileType, ULONG *pPDPType, ULONG *pIPAddress, ULONG *pPrimaryDNS, ULONG *pSecondaryDNS, ULONG *pAuthentication, BYTE nameSize, CHAR *pName, BYTE apnSize, CHAR *pAPNName, BYTE userSize, CHAR *pUsername)
- ULONG GetDefaultProfileLTE (ULONG profileType, ULONG *pPDPType, ULONG *pIPAddressv4, ULONG *pPrimaryDNSv4, ULONG *pSecondaryDNSv4, USHORT *pIPAddressv6, USHORT *pPrimaryDNSv6, USHORT *pSecondaryDNSv6, ULONG *pAuthentication, BYTE nameSize, CHAR *pName, BYTE apnSize, CHAR *pAPNName, BYTE userSize, CHAR *pUsername)
- ULONG GetSessionState (ULONG *pState, BYTE instance)
- ULONG GetPacketStatus (ULONG *pTXPacketSuccesses, ULONG *pRXPacketSuccesses, ULONG *pTXPacketErrors, ULONG *pRXPacketErrors, ULONG *pTXPacketOverflows, ULONG *pRXPacketOverflows, BYTE instance)
- ULONG GetByteTotals (ULONGLONG *pTXTotalBytes, ULONGLONG *pRXTotalBytes, BYTE instance)
- ULONG GetDormancyState (ULONG *pDormancyState, BYTE instance)
- ULONG GetDataBearerTechnology (ULONG *pDataBearer, BYTE instance)
- ULONG SLQSGetDataBearerTechnology (QmiWDSDataBearers *pDataBearers, BYTE instance)
- ULONG GetSessionDuration (ULONGLONG *pDuration, BYTE instance)
- ULONG GetIPAddressLTE (WdsIpAddressInfoReq *)
- ULONG GetConnectionRate (ULONG *pCurrentChannelTXRate, ULONG *pCurrentChannelRXRate, ULONG *pMaxChannelTXRate, ULONG *pMaxChannelRXRate, BYTE instance)
- ULONG GetMobileIPProfile (BYTE index, BYTE *pEnabled, ULONG *pAddress, ULONG *pPrimaryHA, ULONG *pSecondaryHA, BYTE *pRevTunneling, BYTE naiSize, CHAR *pNAI, ULONG *pHASPI, ULONG *pAAASPI, ULONG *pHAState, ULONG *pAAAState)

- ULONG GetLastMobileIPError (ULONG *pError)
- ULONG iSLQSMISetIPFamilyPreference (BYTE IPFamilyPreference, BYTE instance)
- BOOL WDS_IsGobiDevice ()
- ULONG SetActiveMobileIPProfile (CHAR *pSPC, BYTE index)
- ULONG SetMobileIPProfile (CHAR *pSPC, BYTE index, BYTE *pEnabled, ULONG *pAddress, ULONG *pPrimaryHA, ULONG *pSecondaryHA, BYTE *pRevTunneling, CHAR *pNAI, ULONG *pHASPI, ULONG *pAAASPI, CHAR *pMNHA, CHAR *pMNAAA)
- ULONG SLQSGetRuntimeSettings (struct WdsRunTimeSettings *pRunTimeSettings)
- ULONG SLQSSetProfile (ULONG profileType, BYTE profileId, ULONG *pPDPType, ULONG *pIPAddress, ULONG *pPrimaryDNS, ULONG *pSecondaryDNS, ULONG *pAuthentication, CHAR *pName, CHAR *pAPNName, CHAR *pUsername, CHAR *pPassword)
- ULONG SLQSGetProfile (ULONG profileType, BYTE profileId, ULONG *pPDPType, ULONG *pIPAddress, ULONG *pPrimaryDNS, ULONG *pSecondaryDNS, ULONG *pAuthentication, BYTE nameSize, CHAR *pName, BYTE apnSize, CHAR *pAPNName, BYTE userSize, CHAR *pUsername, WORD *pExtendedErrorCode)
- ULONG SLQSStartStopDataSession (struct ssdatasession_params *pin)
- ULONG SLQSDeleteProfile (struct SLQSDeleteProfileParams *pProfileToDelete, WORD *pExtendedErrorCode)
- ULONG SLQSCreateProfile (struct CreateProfileIn *pReq, struct CreateProfileOut *pResp)
- ULONG SLQSAutoConnect (struct slqsautoconnect *pacreq)
- ULONG SLQSModifyProfile (struct ModifyProfileIn *pReq, struct ModifyProfileOut *pResp)
- ULONG SLQSSet3GPPConfigItem (slqs3GPPConfigItem *pSLQS3GPPConfigItem)
- ULONG SLQSGet3GPPConfigItem (slqs3GPPConfigItem *pSLQS3GPPConfigItem)
- ULONG SLQSGetProfileSettings (GetProfileSettingIn *pReq, GetProfileSettingOut *pResp)
- ULONG SLQSWdsSetEventReport (wdsSetEventReportReq *pSetEventReportReq)
- ULONG SLQSWdsSwiPDPRuntimeSettings (swiPDPRuntimeSettingsReq *pPDPRuntimeSettingsReq, swiPDPRuntimeSettingsResp *pPDPRuntimeSettingsResp)
- ULONG iGetConnectionRate (ULONG *pv4sessionId, ULONG *pv6sessionId, struct WdsConnectionRateElmnts *pConnectionRateElmnt)
- ULONG SLQSGetConnectionRate (struct WdsConnectionRate *pConnectionRate)
- ULONG iGetByteTotals (ULONG *pv4sessionId, ULONG *pv6sessionId, struct WdsByteTotalsElmnts *pByteTotalsElmnt)
- ULONG SLQSGetByteTotals (struct WdsByteTotals *pByteTotals)
- ULONG SLQSWdsGoDormant (void)
- ULONG SLQSWdsGoActive (void)
- ULONG SLQSGetSessionState (ULONG *pStateV4, ULONG *pStateV6, BYTE instance)
- ULONG SLQSGetDUNCallInfo (getDUNCallInfoReq *pGetDUNCallInfoReq, getDUNCallInfoResp *pGetDUNCallInfoResp)
- ULONG GetPacketStatistics (struct WdsPktStatisticsReq *pStatMask, struct WdsPktStatisticsElmnts *pPktStatisticsElmnt, BYTE instance)
- ULONG iGetPacketStatistics (ULONG *pV4sessionId, ULONG *pV6sessionId, struct WdsPktStatisticsReq *pStatMask, struct WdsPktStatisticsElmnts *pPktStatisticsElmnt)
- ULONG SLQSGetPacketStatistics (struct WdsPktStatisticsReq *pStatMask, struct WdsPktStatisticsResp *pPktStatistics)
- ULONG SLQSGetCurrDataSystemStat (CurrDataSysStat *pCurrDataSysStat)
- ULONG RMSetTransferStatistics (swiRMTrasnferStaticsReq *pSwiRMTrasnferStaticsReq)
- ULONG SLQSResetPacketStatics ()
- ULONG SLQSGetDataBearerTechnologyExt (DataBearerTechExt *pDataBearerTech, BYTE instance)
- ULONG SLQSGetCurrentChannelRate (WDSSWICurrentChannelRates *pRates, BYTE instance)
- ULONG SLQSSSetLoopback (WDSSetLoopbackData *pReq)
- ULONG SLQSSGetLoopback (WDSGetLoopbackData *data)
- ULONG GetDefaultProfileNum (BYTE profile_type, BYTE profile_family, BYTE *pProfile_no)
- ULONG SetDefaultProfileNum (BYTE profile_type, BYTE profile_family, BYTE profile_index)
- ULONG SLQSSSetDHCPv4ClientConfig (WdsDHCPv4Config *pReq)
- ULONG SLQSSGetDHCPv4ClientConfig (WdsDHCPv4Config *pReqResp)
- ULONG SetMuxID (BYTE instance)

9.49.1 Detailed Description

Wireless Data Service API function prototypes.

9.49.2 Macro Definition Documentation

9.49.2.1 #define IPV6_ADDRESS_ARRAY_SIZE 8

9.49.3 Typedef Documentation

9.49.3.1 typedef struct _GetProfileSettingIn GetProfileSettingIn

This structure contains the input parameters for SLQSGetProfileSettings

Parameters

ProfileType	• Identifies the technology type of the profile – 0x00 - 3GPP – 0x01 - 3GPP2
ProfileID	• index identifying the profile

9.49.3.2 typedef struct _GetProfileSettingOut GetProfileSettingOut

This structure contains the profile settings retrieved by the API SLQSGetProfileSettings

Parameters

curProfile	• Structure containing details of the profile • See QmiProfileInfo for more details
pExtErrCode	• pointer to a 2 byte extended error code • Error code will only will be present if error code eQCWWAN_ERR_QMI_EXTENDED_INTERNAL is returned by device. • See qm_wds_ds_profile_extended_err_codes enum in qmerrno.h for received error description.

9.49.3.3 typedef union WdsProfileParam QmiProfileInfo

This union WdsProfileParam consist of Profile3GPP and Profile3GPP2 out of which one will be used to create profile.

Parameters

SlqsProfile3GPP	• 3GPP profile

SlqsProfile3GPP2	• 3GPP2 profile

9.49.3.4 typedef struct dataBearers QmiWDSDataBearers

Structure to hold the data bearer technology values

Parameters

dataBearerMask[OUT]	• This bit mask indicates if data bearer information for the current and/or last call has been received from the device. If a bit is set, then the information is available in the corresponding structure i.e. the one provided by the caller. Refer to qmiDataBearerMasks for bit-mask positions.
pCurDataBearerTechnology[OUT]	• current data bearer technology value. – NULL if the parameter is not required
pLastCallDataBearerTechnology[OUT]	• last call data bearer technology value. – NULL if the parameter is not required

9.49.3.5 typedef struct dataBearerTechnology QmiWDSDataBearerTechnology

Structure to hold the current data bearer technology values

Parameters

pCurrentNetwork[OUT]	• current selected network – 0 - UNKNOWN – 1 - 3GPP2 – 2 - 3GPP

pRatMask[OUT]	• Radio Access Technology (RAT) mask to indicate the type of technology (RAT mask value of zero indicates that this field is ignored) – 0x8000 - NULL Bearer – 0x0000 - DO_NOT_CARE – CDMA RAT mask * 0x01 - CDMA_1X * 0x02 - EVDO_REV0 * 0x04 - EVDO_REVA * 0x08 - EVDO_REVB * 0x10 - EHRPD * 0x20 - FMC – UMTS RAT mask * 0x01 - WCDMA * 0x02 - GPRS * 0x04 - HSDPA * 0x08 - HSUPA * 0x10 - EDGE * 0x20 - LTE * 0x40 - HSDPA+ * 0x80 - DC_HSDPA+ * 0x100 - 64_QAM * 0x200 - TDSCDMA
pSoMask[OUT]	• Service Option (SO) mask to indicate the SO or type of application (SO mask value of zero indicates that this field is ignored) – 0x00 - DO_NOT_CARE – CDMA 1X SO mask * 0x01 - CDMA_1X_IS95 * 0x02 - CDMA_1X_IS2000 * 0x04 - CDMA_1X_IS2000_REL_A – CDMA EV-DO Rev 0 SO mask * 0x01 - DPA – CDMA EV-DO Rev A SO mask * 0x01 - EVDO_REVA_DPA * 0x02 - EVDO_REVA_MFPA * 0x04 - EVDO_REVA_EMPA * 0x08 - EVDO_REVA_EMPA_EHRPD – CDMA EV-DO Rev B SO mask * 0x01 - DPA * 0x02 - MFPA * 0x04 - EMPA * 0x08 - EMPA_EHRPD * 0x10 - MMPA * 0x20 - MMPA_EHRPD

9.49.3.6 typedef struct _slqs3GPPConfigItem slqs3GPPConfigItem

This structure contains the 3gpp Configuration Item information.

Parameters

pLTEAttach-Profile	• LTE Attach Profile – points to a single WORD Value indicating the attached LTE Profile – Optional parameter with possible values 1-16 (EM/MC73xx or earlier) – function SLQSGet3GPPConfigItem() returns a default value 255 if no LTE Attach Profile is configured • This setting is deprecated on MC/EM74xx
pProfileList	• Profile List – an array of 4 profile configurations – Each element points to a single WORD value indicating profile – Optional parameter with possible values * 1 - 16 (MC/EM73xx and before) * 1 - 24 (MC/EM74xx and onwards) – function SLQSGet3GPPConfigItem() returns a default value 255 if no 3gpp configuration is present
pDefaultPDN-Enabled	• Always Connect Default PDN – A single BYTE value indicating the status of Always connect default PDN * 0 - disabled * 1 - enabled – Optional parameter – function SLQSGet3GPPConfigItem() returns a default value 255 if no 3gpp configuration is present
p3gppRelease	• 3gpp release – A single BYTE value indicating the 3gpp release * 0 - Release 99 * 1 - Release 5 * 2 - Release 6 * 3 - Release 7 * 4 - Release 8 – In 9x30 and onwards * 5 - Release 9 * 6 - Release 10 * 7 - Release 11 – Optional parameter – function SLQSGet3GPPConfigItem() returns a default value 255 if no 3gpp configuration is present

pLTEAttach-ProfileList	• pointer to WORD array indicating LTE Attach Profile List – Optional parameter – possible values: 1-24 – This setting is only supported for MC/EM74xx onwards – The new equivalent option for "pLTEAttachProfile" on 74xx modems is "pLTEAttachProfile-List". Please provide attach profiles in order of decreasing priority in this list.
LTEAttach-ProfileListLen	• Number of element in pLTEAttachProfileList – valid range: 1-24 * This setting is only supported for MC/EM74xx onwards

9.49.4 Enumeration Type Documentation

9.49.4.1 enum pdpidx

Enumerator

WDSPDP1IDX
WDSPDP2IDX
WDSPDP3IDX
WDSPDP4IDX
WDSPDP5IDX
WDSPDP6IDX
WDSPDP7IDX
WDSPDP8IDX
WDSNUMPDPS

9.49.4.2 enum qmiDataBearerMasks

Bit mask values to indicate the presence of data bearer information for the current and last data calls

Enumerator

QMI_WDS_CURRENT_CALL_DB_MASK
QMI_WDS_LAST_CALL_DB_MASK

9.49.5 Function Documentation

9.49.5.1 ULONG GetAutoconnect (ULONG * *pSetting*)

Returns the current auto connect data session setting.

Parameters

pSetting[OUT]	• NDIS auto connect setting – 0 - Disabled – 1 - Enabled

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.2 ULONG GetByteTotals (ULONGLONG * *pTXTotalBytes,* ULONGLONG * *pRXTotalBytes,* BYTE *instance*)

Returns the Rx/Tx byte counts since the start of the last packet data session for IPV4 session only.

Parameters

pTXTotalBytes[-OUT]	• Bytes transmitted without error
pRXTotalBytes[-OUT]	• Bytes received without error
instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds, Rx/Tx byte counts for IPV4 only

9.49.5.3 ULONG GetConnectionRate (ULONG * *pCurrentChannelTXRate,* ULONG * *pCurrentChannelRXRate,* ULONG * *pMaxChannelTXRate,* ULONG * *pMaxChannelRXRate,* BYTE *instance*)

Returns connection rate information for the packet data connection. This API is not applicable when multiple data session is up. For multiple PDN, please use API SLQSGetConnectionRate()

Parameters

pCurrent-ChannelTX-Rate[OUT]	• Current channel Tx rate (in bps)
pCurrent-ChannelRX-Rate[OUT]	• Current channel Rx rate (in bps)

pMaxChannelTXRate[OUT]	• Maximum Tx rate (bps) that may be assigned to device by serving system.
pMaxChannelRXRate[OUT]	• Maximum Rx rate (bps) that may be assigned to device by serving system.
instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.4 ULONG GetDataBearerTechnology (ULONG * *pDataBearer,* BYTE *instance*)

Retrieves the current data bearer technology (only valid when connected). This API is deprecated on MC73xx/EM73xx modules since firmware version SWI9X15C_05_xx_xx_xx and all EM74xx firmware versions. Please use API SLQSGetDataBearerTechnologyExt() for new firmware versions and new modules.

Parameters

pDataBearer[OUT]	• Data bearer technology – 0x01 - CDMA2000 1x – 0x02 - CDMA 1xEV-DO Rev 0 – 0x03 - GSM – 0x04 - UMTS – 0x05 - CDMA2000 HRPD (1xEV-DO Rev A) – 0x06 - EDGE – 0x07 - HSDPA AND WCDMA – 0x08 - WCDMA AND HSUPA – 0x09 - HSDPA AND HSUPA – 0x0A - LTE – 0x0B - CDMA2000 EHRPD – 0x0C - HSDPA+ and WCDMA – 0x0D - HSDPA+ and HSUPA – 0x0E - DC_HSDPA+ and WCDMA – 0x0F - DC_HSDPA+ and HSUPA – 0x10 - HSDPA+ and 64QAM – 0x11 - HSDPA+, 64QAM and HSUPA – 0x12 - TDSCDMA – 0x13 - TDSCDMA and HSDPA – 0xFF - Unknown

instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

The QMI command of this API is deprecated. Use SLQSGetDataBearerTechnologyExt() for new modules (chipset 9x15, 9x30). Version Introduced: Major-1, Minor-12 Version Deprecated: Major-1, Minor-40 Timeout: 2 seconds

9.49.5.5 ULONG GetDefaultProfile (ULONG *profileType*, ULONG * *pPDPType*, ULONG * *pIPAddress*, ULONG * *pPrimaryDNS*, ULONG * *pSecondaryDNS*, ULONG * *pAuthentication*, BYTE *nameSize*, CHAR * *pName*, BYTE *apnSize*, CHAR * *pAPNName*, BYTE *userSize*, CHAR * *pUsername*)

Reads the default profile settings from the device. The default profile is used to establish an auto connect data session.

Parameters

profileType	• Type of profile – 0 - UMTS
pPDPType[OUT]	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6
pIPAddress[OUT]	• Preferred IPv4 address to be assigned to device
pPrimaryDNS[OUT]	• Primary DNS Ipv4 address preference
pSecondaryDNS[OUT]	• Secondary DNS Ipv4 address preference

pAuthentication[-OUT]	• Bitmap that indicates authentication algorithm preference – 0x00000001 - PAP preference * 0 - Never performed * 1 - May be performed – 0x00000002 - CHAP preference * 0 - Never performed * 1 - May be performed – All other bits are reserved and must be set to 0 – If more than 1 bit is set, then device decides which authentication procedure is performed while setting up data session e.g. the device may have a policy to select the most secure authentication mechanism.
nameSize	• Maximum number of characters (including NULL terminator) that profile name array can contain.
pName[OUT]	• Profile name
apnSize	• Maximum number of characters (including NULL terminator) that APN name array can contain
pAPNName[OUT]	• Access point name. NULL-terminated string parameter that is a logical name used to select GGSN and external packet data network. • If value is NULL or omitted, then subscription default value will be requested.
userSize	• Maximum number of characters (including NULL terminator) that username array can contain.
pUsername[OUT]	• Username used during network authentication

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.6 ULONG GetDefaultProfileLTE (ULONG *profileType*, ULONG * *pPDPType*, ULONG * *pIPAddressv4*, ULONG * *pPrimaryDNSv4*, ULONG * *pSecondaryDNSv4*, USHORT * *pIPAddressv6*, USHORT * *pPrimaryDNSv6*, USHORT * *pSecondaryDNSv6*, ULONG * *pAuthentication*, BYTE *nameSize*, CHAR * *pName*, BYTE *apnSize*, CHAR * *pAPNName*, BYTE *userSize*, CHAR * *pUsername*)

Reads the default profile settings from the device. The default profile is used to establish an auto connect data session.

Parameters

profileType	• Type of profile – 0 - UMTS
pPDPType[OUT]	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6
pIPAddressv4[-OUT]	• Preferred IPv4 addr to be assigned to device
pPrimaryDN-Sv4[OUT]	• Primary DNS Ipv4 address preference
pSecondaryDN-Sv4[OUT]	• Secondary DNS Ipv4 address preference
pIPAddressv6[-OUT]	• Preferred IPv6 addr to be assigned to device Space for storing 8 element array for the IPv6 addresses is allocated by the application. The IP Address will be retrieved in the big endian format. For example User buffer contents: [<U0>..<U7>] IPv6 address: 1234:2A01:....:5678 U0 corresponds to 1234 U1 corresponds to 2A01 – ----------— – -— – ----------— – -— U7 corresponds to 5678
pPrimaryDN-Sv6[OUT]	• Primary DNS Ipv6 address preference
pSecondaryDN-Sv6[OUT]	• Secondary DNS Ipv6 address preference
pAuthentication[-OUT]	• Bitmap that indicates authentication algorithm preference – 0x00000001 - PAP preference * 0 - Never performed * 1 - May be performed – 0x00000002 - CHAP preference * 0 - Never performed * 1 - May be performed – All other bits are reserved and must be set to 0 – If more than 1 bit is set, then device decides which authentication procedure is performed while setting up data session e.g. the device may have a policy to select the most secure authentication mechanism.

nameSize	• Maximum number of characters (including NULL terminator) that Profile name array can contain
pName[OUT]	• Profile name
apnSize	• Maximum number of characters (including NULL terminator) that APN name array can contain
pAPNName[IN]	• Access point name. NULL-terminated string parameter that is a logical name used to select GGSN and external packet data network. • If value is NULL or omitted, then subscription default value will be requested.
userSize	• Maximum number of characters including NULL terminator) that username array can contain.
pUsername[OUT]	• Username used during network authentication

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: LTE
Timeout: 2 seconds

9.49.5.7 ULONG GetDefaultProfileNum (BYTE *profile_type*, BYTE *profile_family*, BYTE * *pProfile_no*)

This API to Get default profile number

Parameters

profile_type	[IN] • 0 - 3GPP • 1 - 3GPP2
profile_family	[IN] • 0 - Embedded • 1 - Tethered
pProfile_no	[OUT]

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.8 ULONG GetDormancyState (ULONG * *pDormancyState,* BYTE *instance*)

Returns the dormancy state of the current packet data session when connected.

Parameters

pDormancy-State[OUT]	• Dormancy state of current packet data session – 1 - Traffic channel dormant – 2 - Traffic channel active
instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.9 ULONG GetIPAddressLTE (WdsIpAddressInfoReq *)

Returns the current packet data session IP address(es)

- Parameter values default to their data type's maximum unsigned value unless explicitly stated otherwise.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: LTE
Timeout: 2 seconds.

9.49.5.10 ULONG GetLastMobileIPError (ULONG * *pError*)

Returns the last mobile IP error.

Parameters

pError[OUT]	• Status of last MIP call (or attempt) – Zero - Success – NonZero - Error code See qaGobiApiTableCallEndReasons.h for Mobile IP Error codes

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Device Supported: MC83x5
Timeout: 2 seconds

9.49.5.11 ULONG GetMobileIP (ULONG * *pMode*)

Returns the current mobile IP setting.

Parameters

mode[OUT]	• Mobile IP setting – 0 - Mobile IP off (simple IP only) – 1 - Mobile IP preferred – 2 - Mobile IP only

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.49.5.12 ULONG GetMobileIPProfile (BYTE *index*, BYTE * *pEnabled*, ULONG * *pAddress*, ULONG * *pPrimaryHA*, ULONG * *pSecondaryHA*, BYTE * *pRevTunneling*, BYTE *naiSize*, CHAR * *pNAI*, ULONG * *pHASPI*, ULONG * *pAAASPI*, ULONG * *pHAState*, ULONG * *pAAAState*)

Returns the specified mobile IP profile settings.

Parameters

index	• Mobile IP profile ID
pEnabled[OUT]	• Profile enabled: – 0 - Disabled – 1 - Enabled – 0xFF - Unknown
pAddress[OUT]	• Home IPv4 address: – 0xFFFFFFFF - Unknown
pPrimaryHA[OUT]	• Primary home agent IPv4 address – 0xFFFFFFFF - Unknown
pSecondaryHA[OUT]	• Secondary home agent IPv4 address – 0xFFFFFFFF - Unknown
pRevTunneling[OUT]	• Reverse tunneling enabled – 0 - Disabled – 1 - Enabled – 0xFF - Unknown
naiSize	• The maximum number of characters (including NULL terminator) that the NAI array can contain.
pNAI[OUT]	• Network access identifier string
pHASPI[OUT]	• Home agent security parameter index
pAAASPI[OUT]	• AAA server security parameter index – 0xFFFFFFFF - Unknown
pHAState[OUT]	• Home agent key state – 0 - Unset – 1 - Set, default value – 2 - Set, modified from default – 3 - 0xFFFFFFFF - Unknown

pAAAState[OUT]	• AAA key state – 0 - Unset – 1 - Set, default value – 2 - Set, modified from default – 3 - 0xFFFFFFFF - Unknown

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.49.5.13 ULONG GetPacketStatistics (struct WdsPktStatisticsReq * *pStatMask,* struct WdsPktStatisticsElmnts * *pPktStatisticsElmnt,* BYTE *instance*)

Returns the current packet transfer counter values from the device. Since the start of the last packet data session.

Parameters

pStatMask[IN]	• See WdsPktStatisticsReq for more information
pPktStatistics-Elmnt[OUT]	• See WdsPktStatisticsElmnts for more information
instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.49.5.14 ULONG GetPacketStatus (ULONG * *pTXPacketSuccesses,* ULONG * *pRXPacketSuccesses,* ULONG * *pTXPacketErrors,* ULONG * *pRXPacketErrors,* ULONG * *pTXPacketOverflows,* ULONG * *pRXPacketOverflows,* BYTE *instance*)

Returns the packet data transfer statistics since the start of the current packet data.

Parameters

pTXPacket-Successes[OUT]	• Number of packets transmitted without error
pRXPacket-Successes[OUT]	• Number of packets received without error
pTXPacket-Errors[OUT]	• Number of outgoing packets with framing errors
pRXPacket-Errors[OUT]	• Number of incoming packets with framing errors
pTXPacket-Overflows[OUT]	• Number of packets dropped because Tx buffer overflowed
pRXPacket-Overflows[OUT]	• Number of packets dropped because Rx buffer overflowed
instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.15 ULONG GetSessionDuration (ULONGLONG * *pDuration,* BYTE *instance*)

Returns the duration of the current packet data session.

Parameters

pDuration[OUT]	• Duration of the current packet session in milliseconds
instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS/CDMA
Device Supported: MC83x5, MC7700/50
Timeout: 2 seconds

9.49.5.16 ULONG GetSessionState (ULONG * *pState,* BYTE *instance*)

Returns the state of the current packet data session.

Parameters

pState[OUT]	• Current link status – 1 - DISCONNECTED – 2 - CONNECTED – 3 - SUSPENDED (not supported) – 4 - AUTHENTICATING
instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.17 ULONG iGetByteTotals (ULONG * *pv4sessionId,* ULONG * *pv6sessionId,* struct WdsByteTotalsElmnts * *pByteTotalsElmnt*)

9.49.5.18 ULONG iGetConnectionRate (ULONG * *pv4sessionId,* ULONG * *pv6sessionId,* struct WdsConnectionRateElmnts * *pConnectionRateElmnt*)

9.49.5.19 ULONG iGetPacketStatistics (ULONG * *pV4sessionId,* ULONG * *pV6sessionId,* struct WdsPktStatisticsReq * *pStatMask,* struct WdsPktStatisticsElmnts * *pPktStatisticsElmnt*)

9.49.5.20 ULONG iSLQSMISetIPFamilyPreference (BYTE *IPFamilyPreference,* BYTE *instance*)

9.49.5.21 ULONG RMSetTransferStatistics (swiRMTrasnferStaticsReq * *pSwiRMTrasnferStaticsReq*)

This API request the device to fetch current data system transfer Statistics.

Parameters

pswiRMTrasnfer-StaticsReq[IN]	• See swiRMTrasnferStaticsReq for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.22 ULONG SetActiveMobileIPProfile (CHAR * *pSPC,* BYTE *index*)

Sets active mobile IP profile.

Parameters

pSPC[IN]	• NULL-terminated string representing six digit service programming code
index[IN]	• Index of the profile to be set as the active profile

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.49.5.23 ULONG SetAutoconnect (ULONG *setting*)

Sets the auto connect data session setting.

Parameters

setting[IN]	• NDIS autoconnect setting – 0 - Disabled – 1 - Enabled

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

When enabling, timeout is 5 minutes,
When disabling, timeout is 5 seconds

9.49.5.24 ULONG SetDefaultProfile (ULONG *profileType*, ULONG * *pPDPType*, ULONG * *pIPAddress*, ULONG * *pPrimaryDNS*, ULONG * *pSecondaryDNS*, ULONG * *pAuthentication*, CHAR * *pName*, CHAR * *pAPNName*, CHAR * *pUsername*, CHAR * *pPassword*)

Writes the default profile settings to the device. The default profile is used to establish an autoconnect data session.

Parameters

profileType	• Type of profile – 0 - UMTS
pPDPType[IN]	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile (optional) – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6
pIPAddress[IN]	• Preferred IPv4 addr to be assigned to device (optional)
pPrimaryDNS[IN]	• Primary DNS Ipv4 address preference (optional)
pSecondaryDNS[IN]	• Secondary DNS Ipv4 address preference (optional)
pAuthentication[IN]	• Bitmap that indicates authentication algorithm preference (optional) – 0x00000001 - PAP preference * 0 - Never performed * 1 - May be performed – 0x00000002 - CHAP preference * 0 - Never performed * 1 - May be performed – All other bits are reserved and must be set to 0 – If more than 1 bit is set, then device decides which authentication procedure is performed while setting up data session e.g. the device may have a policy to select the most secure authentication mechanism.

pName[IN]	• profile Name (optional)
pAPNName[IN]	• Access point name. NULL-terminated string parameter that is a logical name used to select GGSN and external packet data network (optional) • If value is NULL or omitted, then subscription default value will be requested.
pUsername[IN]	• Username used during network authentication (optional)
pPassword[IN]	• Password used during network authentication (optional)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout is 2 seconds.

9.49.5.25 ULONG SetDefaultProfileLTE (ULONG *profileType*, ULONG * *pPDPType*, ULONG * *pIPAddressv4*, ULONG * *pPrimaryDNSv4*, ULONG * *pSecondaryDNSv4*, USHORT * *pIPAddressv6*, USHORT * *PrimaryDNSv6*, USHORT * *pSecondaryDNSv6*, ULONG * *pAuthentication*, CHAR * *pName*, CHAR * *pAPNName*, CHAR * *pUsername*, CHAR * *pPassword*)

Writes the default profile settings to the device. The default profile is used to establish an auto connect data session.

Parameters

profileType	• Type of profile – 0 - UMTS
pPDPType[IN]	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile (optional) – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6
pIPAddressv4[IN]	• Preferred IPv4 address to be assigned to device (optional)
pPrimaryDNSv4[IN]	• Primary DNS Ipv4 address preference (optional)

pSecondaryDNSv4[IN]	• Secondary DNS Ipv4 address preference (optional)
pIPAddressv6[IN]	• Preferred IPv6 address to be assigned to device (optional)
pPrimaryDNSv6[IN]	• Primary DNS Ipv6 address preference (optional)
pSecondaryDNSv6[IN]	• Secondary DNS Ipv6 address preference (optional)
pAuthentication[IN]	• Bitmap that indicates authentication algorithm preference (optional) – 0x00000001 - PAP preference * 0 - Never performed * 1 - May be performed – 0x00000002 - CHAP preference * 0 - Never performed * 1 - May be performed – All other bits are reserved and must be set to 0 – If more than 1 bit is set, then device decides which authentication procedure is performed while setting up data session e.g.the device may have a policy to select the most secure authentication mechanism.
pName[IN]	• profile Name (optional)
pAPNName[IN]	• Access point name. NULL-terminated string parameter that is a logical name used to select GGSN and external packet data network (optional) • If value is NULL or omitted, then subscription default value will be requested
pUsername[IN]	• Username used during network authentication (optional)
pPassword[IN]	• Password used during network authentication (optional)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Deprecated, please use SetDefaultProfileLTEV2 instead
Technology Supported: LTE
Timeout: 2 seconds

9.49.5.26 ULONG SetDefaultProfileLTEV2 (ULONG *profileType*, ULONG * *pPDPType*, ULONG * *pIPAddressv4*, ULONG * *pPrimaryDNSv4*, ULONG * *pSecondaryDNSv4*, USHORT * *pIPAddressv6*, USHORT * *PrimaryDNSv6*, USHORT * *pSecondaryDNSv6*, ULONG * *pAuthentication*, CHAR * *pName*, CHAR * *pAPNName*, CHAR * *pUsername*, CHAR * *pPassword*)

Writes the default profile settings to the device. The default profile is used to establish an auto connect data session.

Parameters

profileType	• Type of profile – 0 - UMTS
pPDPType[IN]	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile (optional) – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6
pIPAddressv4[IN]	• Preferred IPv4 address to be assigned to device (optional)
pPrimaryDNSv4[IN]	• Primary DNS Ipv4 address preference (optional)
pSecondaryDNSv4[IN]	• Secondary DNS Ipv4 address preference (optional)
pIPAddressv6[IN]	• Preferred IPv6 addr to be assigned to device (optional)
pPrimaryDNSv6[IN]	• Primary DNS Ipv6 address preference (optional)
pSecondaryDNSv6[IN]	• Secondary DNS Ipv6 address preference (optional)
pAuthentication[IN]	• Bitmap that indicates authentication algorithm preference (optional) – 0x00000001 - PAP preference * 0 - Never performed * 1 - May be performed – 0x00000002 - CHAP preference * 0 - Never performed * 1 - May be performed – All other bits are reserved and must be set to 0 – If more than 1 bit is set, then device decides which authentication procedure is performed while setting up data session e.g.the device may have a policy to select the most secure authentication mechanism.
pName[IN]	• profile Name (optional)

pAPNName[IN]	• Access point name. NULL-terminated string parameter that is a logical name used to select GGSN and external packet data network (optional) • If value is NULL or omitted, then subscription default value will be requested
pUsername[IN]	• Username used during network authentication (optional)
pPassword[IN]	• Password used during network authentication (optional)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: LTE
Timeout: 2 seconds
Replaces deprecated Function SetDefaultProfileLTE

9.49.5.27 ULONG SetDefaultProfileNum (BYTE *profile_type,* BYTE *profile_family,* BYTE *profile_index*)

This API to Set default profile number

Parameters

profile_type	[IN] • 0 - 3GPP • 1 - 3GPP2
profile_family	[IN] • 0 - Embedded • 1 - Tethered
profile_index	[IN]

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.28 ULONG SetMobileIP (ULONG *mode*)

Sets the current mobile IP setting.

Parameters

mode[IN]	• Mobile IP setting – 0 - Mobile IP off (simple IP only) – 1 - Mobile IP preferred – 2 - Mobile IP only

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.49.5.29 ULONG SetMobileIPParameters (CHAR * *pSPC,* ULONG * *pMode,* BYTE * *pRetryLimit,* BYTE * *pRetryInterval,* BYTE * *pReRegPeriod,* BYTE * *pReRegTraffic,* BYTE * *pHAAuthenticator,* BYTE * *pHA2002bis*)

Sets the specified mobile IP parameters.

Parameters

pSPC[IN]	• NULL-terminated string representing six digit service programming code.
pMode[IN]	• Mode to be set (optional) – 0 - Mobile IP off (simple IP only) – 1 - Mobile IP preferred – 2 - Mobile IP only
pRetryLimit[IN]	• Registration retry attempt limit (optional)
pRetryInterval[IN]	• Registration retry attempt interval used to determine the time between registration attempts (optional)
pReRegPeriod[IN]	• Period (in minutes) to attempt re-registration before current registration expires (optional)
pReRegTraffic[IN]	• Re-registration only if traffic since last attempt (optional) – Zero - Disabled – NonZero - Enabled

pHA-Authenticator[IN]	• MH-HA authenticator calculator (optional) – Zero - Disabled – NonZero - Enabled
pHA2002bis[IN]	• MH-HA RFC 2002bis authentication instead of RFC2002 (optional) – Zero - Disabled – NonZero - Enabled

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Device Supported: None
Timeout: 2 seconds

9.49.5.30 ULONG SetMobileIPProfile (CHAR * *pSPC*, BYTE *index*, BYTE * *pEnabled*, ULONG * *pAddress*, ULONG * *pPrimaryHA*, ULONG * *pSecondaryHA*, BYTE * *pRevTunneling*, CHAR * *pNAI*, ULONG * *pHASPI*, ULONG * *pAAASPI*, CHAR * *pMNHA*, CHAR * *pMNAAA*)

Sets the mobile IP parameters.

Parameters

pSPC[IN]	• Six digit service programming code string
index[IN]	• Index of the profile to modify
pEnabled[IN]	• (Optional) Enable profile? 0 - Disabled Nonzero - Enabled
pAddress[IN]	• (Optional) Home IPv4 address
pPrimaryHA[IN]	• (Optional) Primary home agent IPv4 address
pSecondaryHA[IN]	• (Optional) Secondary home agent IPv4 address
pRevTunneling[IN]	• (Optional) Enable reverse tunneling? 0 - Disabled Nonzero - Enabled

pNAI[IN]	• (Optional) Network access identifier string
pHASPI[IN]	• (Optional) Home agent security parameter index
pAAASPI[IN]	• (Optional) AAA server security parameter index
pMNHA[IN]	• (Optional) MN-HA key string
pMNAAA[IN]	• (Optional) MN-AAA key string

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA
Timeout: 2 seconds

9.49.5.31 ULONG SetMuxID (BYTE *instance*)

This API is used for QMAP feature, it binds the MUX id before starting a data session or registering a WDS indcation, it is mandatory to do this for QMAP feature.

Parameters

instance	[IN] • QMI Instance ID, value 0-8, it will be mapped to mux id 0x80-0x88 by this API

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.32 ULONG SLQSAutoConnect (struct slqsautoconnect * *pacreq*)

Returns auto connect settings

Parameters

slqsautoconnect[-IN]	• SLQS auto connect settings

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: CDMA/UMTS
Device Supported: MC83x5, MC7700
Timeout: 2 seconds

9.49.5.33 ULONG SLQSCreateProfile (struct CreateProfileIn * *pReq,* struct CreateProfileOut * *pResp*)

Create a new profile with the specified parameters. Note that some firmware versions do not support the optional Profile ID parameter. In this case an error will be returned and the caller can subsequently create a profile by specifying a NULL pointer for the Profile ID parameter. The Profile ID pertaining to the newly created profile is returned in the response structure (pResp).

Parameters

pReq[IN]	• SLQS Create profile Information
pResp[OUT]	• SLQS profile identifier information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS
Device Supported: MC83x5, MC7700
Timeout: 2 seconds

9.49.5.34 ULONG SLQSDeleteProfile (struct SLQSDeleteProfileParams * *pProfileToDelete,* WORD * *pExtendedErrorCode*)

Deletes a configured profile stored on the device. The deletion of a profile does not affect profile index assignments.

Parameters

pProfileToDelete[IN]	• Information about the profile to be deleted. • See SLQSDeleteProfileParams for more details.
pExtendedErrorCode[OUT]	• The extended error code received from DS Profile subsystem of type eWDS_ERR_PROFILE_REG_xxx. • Error code will only will be present if error code eQCWWAN_ERR_QMI_EXTENDED_INTERNAL is returned by device. • See qm_wds_ds_profile_extended_err_codes enum in qmerrno.h for received error description.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values.

Note

Timeout: 2 seconds

9.49.5.35 ULONG SLQSGet3GPPConfigItem (slqs3GPPConfigItem * *pSLQS3GPPConfigItem*)

Reads the 3gpp configuration item.

Parameters

pSLQS3GPPConfigItem[OUT]	• See slqs3GPPConfigItem for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS/LTE
Timeout: 2 seconds

9.49.5.36 ULONG SLQSGetByteTotals (struct WdsByteTotals * *pByteTotals*)

This API request the device to fetch ByteTotals for IPV4 and IPV6.

Parameters

pByteTotals[IN/-OUT]	• See WdsByteTotals for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.37 ULONG SLQSGetConnectionRate (struct WdsConnectionRate * *pConnectionRate*)

This API request the device to fetch ConnectionRate. It can be used for both mono and multiple PDN use case.

Parameters

pConnection-Rate[IN/OUT]	• See WdsConnectionRate for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS/CDMA
Device Supported: MC77XX
Timeout: 2 seconds

9.49.5.38 ULONG SLQSGetCurrDataSystemStat (CurrDataSysStat * *pCurrDataSysStat*)

This API request the device to fetch current data system status.

Parameters

pCurrDataSys-Stat[IN/OUT]	• See CurrDataSysStat for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 5 seconds\n
```

9.49.5.39 ULONG SLQSGetCurrentChannelRate (WDSSWICurrentChannelRates * *pRates*, BYTE *instance*)

This API Queries current bitrate of a packet data connection.

Parameters

pRates	[IN] • See WDSSWICurrentChannelRates for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

This feature depends on custom feature setting IPCHANNELRATEEN which can be set via SLQSSetCustFeaturesV2

Timeout: 2 seconds

9.49.5.40 ULONG SLQSGetDataBearerTechnology (QmiWDSDataBearers * *pDataBearers*, BYTE *instance*)

Retrieves the data bearer technology values for current and/or last data calls. The device must be in a data call for this function to execute successfully.

Parameters

qmiWDSDataBearers[OUT]	• Indicates the current and the last call data bearer technology. Should not be NULL, on input.
instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS/CDMA
Device Supported: MC7750,GOBI,MC7700
Timeout: 2 seconds

9.49.5.41 ULONG SLQSGetDataBearerTechnologyExt (DataBearerTechExt * *pDataBearerTech*, BYTE *instance*)

This API Get Data Bearer Technology. This is a new API to replace API GetDataBearerTechnology(). see the description of GetDataBearerTechnology() to get more information

Parameters

pDataBearer-Tech	[IN] • See DataBearerTechExt for more information
instance	[IN] • PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.42 ULONG SLQSGetDUNCallInfo (getDUNCallInfoReq * *pGetDUNCallInfoReq*, getDUNCallInfoResp * *pGetDUNCallInfoResp*)

This API queries the current modem connection status.

Parameters

pGetDUNCall-InfoReq[IN]	• See getDUNCallInfoReq for more information
pGetDUNCall-InfoResp[OUT]	• See getDUNCallInfoResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 seconds

9.49.5.43 ULONG SLQSGetPacketStatistics (struct WdsPktStatisticsReq * *pStatMask*, struct WdsPktStatisticsResp * *pPktStatistics*)

This API request the device to fetch current packet transfer counter values from the device

Parameters

pStatMask[IN]	– See WdsPktStatisticsReq for more information
pPktStatistics[OUT]	– See WdsPktStatisticsResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 5 seconds\n
```

9.49.5.44 ULONG SLQSGetProfile (ULONG *profileType*, BYTE *profileId*, ULONG * *pPDPType*, ULONG * *pIPAddress*, ULONG * *pPrimaryDNS*, ULONG * *pSecondaryDNS*, ULONG * *pAuthentication*, BYTE *nameSize*, CHAR * *pName*, BYTE *apnSize*, CHAR * *pAPNName*, BYTE *userSize*, CHAR * *pUsername*, WORD * *pExtendedErrorCode*)

Reads the profile settings from the device for the specified profile id.

Parameters

profileType	• Type of profile – 0 - UMTS
profileId	• Index of the configured profile for which settings are read – Value between 1 - 16 (EM/MC73xx or earlier) – Value between 1 - 24 (EM/MC74xx onwards)
pPDPType[OUT]	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6
pIPAddress[OUT]	• Preferred IPv4 address to be assigned to device
pPrimaryDNS[OUT]	• Primary DNS Ipv4 address preference

pSecondaryDNS[OUT]	• Secondary DNS Ipv4 address preference
pAuthentication[OUT]	• Bitmap that indicates authentication algorithm preference – 0x00000001 - PAP preference * 0 - Never performed * 1 - May be performed – 0x00000002 - CHAP preference * 0 - Never performed * 1 - May be performed – All other bits are reserved and must be set to 0 – If more than 1 bit is set, then device decides which authentication procedure is performed while setting up data session e.g. the device may have a policy to select the most secure authentication mechanism.
nameSize	• Maximum number of characters (including NULL terminator) that profile name array can contain.
pName[OUT]	• Profile name
apnSize	• Maximum number of characters (including NULL terminator) that APN name array can contain
pAPNName[OUT]	• Access point name. NULL-terminated string parameter that is a logical name used to select GGSN and external packet data network. • If value is NULL or omitted, then subscription default value will be requested.
userSize	• Maximum number of characters (including NULL terminator) that username array can contain.
pUsername[OUT]	• Username used during network authentication
pExtendedErrorCode	• The extended error code received from DS Profile subsystem of type eWDS_ERR_PROFILE_REG_xxx. • Error code will only will be present if error code eQCWWAN_ERR_QMI_EXTENDED_INTERNAL is returned by device. • See qm_wds_ds_profile_extended_err_codes enum in qmerrno.h for received error description.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.45 ULONG SLQSGetProfileSettings (GetProfileSettingIn * *pReq*, GetProfileSettingOut * *pResp*)

Retrieves a profile(3GPP/3GPP2) with the specified parameters.

Parameters

pReq[IN]	• details of the profile to be fetched • See GetProfileSettingIn for more information
pResp[OUT]	• The profile settings and/or extended error code returned by the device based on input parameters. • See GetProfileSettingOut for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.46 ULONG SLQSGetRuntimeSettings (struct WdsRunTimeSettings * *pRunTimeSettings*)

Returns the packet data session settings currently in use.

Parameters

pRunTime-Settings[OUT]	• SLQS Runtime Settings Information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.47 ULONG SLQSGetSessionState (ULONG * *pStateV4,* ULONG * *pStateV6,* BYTE *instance*)

Returns the state of the current packet data session.

Parameters

pStateV4[OUT]	• Current link status for IPV4 Session – 1 - DISCONNECTED – 2 - CONNECTED – 3 - SUSPENDED (not supported) – 4 - AUTHENTICATING
pStateV6[OUT]	• Current link status for IPV6 Session – 1 - DISCONNECTED – 2 - CONNECTED – 3 - SUSPENDED (not supported) – 4 - AUTHENTICATING
instance	• PDP instance

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.48 ULONG SLQSModifyProfile (struct ModifyProfileIn * *pReq,* struct ModifyProfileOut * *pResp*)

Modify a profile(3GPP/3GPP2) with the specified parameters.

Parameters

pReq[IN]	• Contains parameters which can be modified
pResp[OUT]	• Contains parameters which indicates modification success or failure

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds

9.49.5.49 ULONG SLQSResetPacketStatics ( )

This API request the device to reset packet data transfer statistics.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.50 ULONG SLQSSet3GPPConfigItem (slqs3GPPConfigItem * *pSLQS3GPPConfigItem*)

Sets the 3gpp configuration item.

Parameters

pSLQS3GPP-ConfigItem[IN]	• See slqs3GPPConfigItem for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS/LTE
Timeout: 2 seconds

9.49.5.51 ULONG SLQSSetProfile (ULONG *profileType*, BYTE *profileId*, ULONG * *pPDPType*, ULONG * *pIPAddress*, ULONG * *pPrimaryDNS*, ULONG * *pSecondaryDNS*, ULONG * *pAuthentication*, CHAR * *pName*, CHAR * *pAPNName*, CHAR * *pUsername*, CHAR * *pPassword*)

Writes the profile settings for the specified profile Id.

Parameters

profileType	• Type of profile – 0 - UMTS
profileId	• Profile number to be modified – Value between 1 - 16 (EM/MC73xx or earlier) – Value between 1 - 24 (EM/MC74xx onwards)
pPDPType[IN]	• Packet Data Protocol (PDP) type specifies the type of data payload exchanged over the air link when the packet data session is established with this profile (optional) – 0 - PDP-IP (IPv4) – 1 - PDP-PPP – 2 - PDP-IPv6 – 3 - PDP-IPv4v6
pIPAddress[IN]	• Preferred IPv4 address to be assigned to device (optional)
pPrimaryDNS[IN]	• Primary DNS Ipv4 address preference (optional)
pSecondaryDNS[IN]	• Secondary DNS Ipv4 address preference (optional)
pAuthentication[IN]	• Bitmap that indicates authentication algorithm preference (optional) – 0x00000001 - PAP preference * 0 - Never performed * 1 - May be performed – 0x00000002 - CHAP preference * 0 - Never performed * 1 - May be performed – All other bits are reserved and must be set to 0 – If more than 1 bit is set, then device decides which authentication procedure is performed while setting up data session e.g. the device may have a policy to select the most secure authentication mechanism.
pName[IN]	• profile Name (optional)
pAPNName[IN]	• Access point name. NULL-terminated string parameter that is a logical name used to select GGSN and external packet data network (optional) • If value is NULL or omitted, then subscription default value will be requested.
pUsername[IN]	• Username used during network authentication (optional)

pPassword[IN]	• Password used during network authentication (optional)

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout is 2 seconds.

9.49.5.52 ULONG SLQSSGetDHCPv4ClientConfig (WdsDHCPv4Config * *pReqResp*)

This API gets the DHCP Client V4 Configuration.

Parameters

pReq	[IN] • See WdsDHCPv4Config for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.53 ULONG SLQSSGetLoopback (WDSGetLoopbackData * *data*)

This API to Get the value of loopback mode and multiplier.

Parameters

pReq	[IN] • See WDSGetLoopbackData for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.54 ULONG SLQSSSetDHCPv4ClientConfig (WdsDHCPv4Config * *pReq*)

This API sets the DHCP Client V4 Configuration.

Parameters

pReq	[IN] • See WdsDHCPv4Config for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.55 ULONG SLQSSSetLoopback (WDSSetLoopbackData * *pReq*)

This API to Enable/disable Data Loopback Mode and set the value of loopback multiplier.

Parameters

pReq	[IN] • See WDSSetLoopbackData for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

```
Timeout: 2 seconds\n
```

9.49.5.56 ULONG SLQSSStartStopDataSession (struct ssdatasession_params * *pin*)

Starts or stops a 3GPP/3GPP2 data session on a preconfigured profile. To set the IP family for the data session, execute SLQSSetIPFamilyPreference prior to calling this API.

Parameters

pin[IN]	• ssdatasession_params structure • See ssdatasession_params for more details

Returns

eQCWWAN_ERR_NONE on success, for IPV4V6 data call, the following return values ar treated as success as well, fail otherwise.

- eQCWWAN_ERR_SWICM_V4DWN_V6DWN
- eQCWWAN_ERR_SWICM_V4DWN_V6UP
- eQCWWAN_ERR_SWICM_V4UP_V6DWN
- eQCWWAN_ERR_SWICM_V4UP_V6UP

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 5 Minutes
Use SLQSSetProfile to configure 3GPP profiles

9.49.5.57 ULONG SLQSWdsGoActive (void)

Forces the device to immediately reestablish the traffic channel on the serving radio interface

Parameters

None	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

This channel can go dormant any time after it has been reactivated. There is no assurance that the channel remains active for any guaranteed period. Timeout: 5 seconds

9.49.5.58 ULONG SLQSWdsGoDormant (void)

Forces the device to immediately drop the traffic channel on the serving radio interface

Parameters

None	

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

This channel can be reactivated as soon as data is sent over the network interface. There is no assurance that the channel remains dormant for any guaranteed period. Timeout: 5 seconds

9.49.5.59 ULONG SLQSWdsSetEventReport (wdsSetEventReportReq * *pSetEventReportReq*)

This API sets the wireless data connection state reporting conditions for the requesting control point.

Parameters

pSetEventReportReq[IN]	• See wdsSetEventReportReq for more information.

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 2 seconds
The control point event reporting state variables are modified to reflect the settings indicated in the request message. The service maintains a set of state variables for each control point. Relevant wireless data connection state changes are communicated to the registered WDS control point via the SLQSWdsSetEventReportCallBack. The AT command equivalents to this command are AT+CMER, AT+CIND, and AT+CIEV

9.49.5.60 ULONG SLQSWdsSwiPDPRuntimeSettings (swiPDPRuntimeSettingsReq * *pPDPRuntimeSettingsReq,* swiPDPRuntimeSettingsResp * *pPDPRuntimeSettingsResp*)

This API requests the device to return the active PDP context associated with a context id.

Parameters

pPDPRuntimeSettingsReq[IN]	• See swiPDPRuntimeSettingsReq for more information
pPDPRuntimeSettingsResp[OUT]	• See swiPDPRuntimeSettingsResp for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

Note

Technology Supported: UMTS/CDMA
Device Supported: MC77XX
Timeout: 2 seconds
The AT command equivalent to this command is AT+CGCONTRDP

9.49.5.61 BOOL WDS_IsGobiDevice ( )

9.50 qaNasGetRFBandInfo.h File Reference

Data Structures

- struct QmiNasGetRFBandInfoResp

Enumerations

- enum eQMI_NAS_GET_RF_INFO_RESP {
  eTLV_RF_BAND_INFO = 0x01,
  eTLV_RF_DEDICATED_BAND_INFO = 0x10,
  eTLV_RF_EXT_FORMAT_BAND_INFO = 0x11,
  eTLV_RF_BANDWIDTH_INFO = 0x12,
  eTLV_LTE_OPERATIONAL_MODE = 0x13 }

Functions

- enum eQCWWANError PkQmiNasGetRFBandInfo (WORD *pMlength, BYTE *pBuffer)
- enum eQCWWANError UpkQmiNasGetRFBandInfo (BYTE *pMdmResp, struct QmiNasGetRFBandInfoResp *pApiResp)

9.50.1 Enumeration Type Documentation

9.50.1.1 enum eQMI_NAS_GET_RF_INFO_RESP

Enumerator

eTLV_RF_BAND_INFO

eTLV_RF_DEDICATED_BAND_INFO

eTLV_RF_EXT_FORMAT_BAND_INFO

eTLV_RF_BANDWIDTH_INFO

eTLV_LTE_OPERATIONAL_MODE

9.50.2 Function Documentation

9.50.2.1 enum eQCWWANError PkQmiNasGetRFBandInfo (WORD * *pMlength*, BYTE * *pBuffer*)

9.50.2.2 enum eQCWWANError UpkQmiNasGetRFBandInfo (BYTE * *pMdmResp*, struct QmiNasGetRFBandInfoResp * *pApiResp*)

9.51 qaNasPerformNetworkScan.h File Reference

Data Structures

- struct QmiNas3GppNetworkInfo
- struct QmiNasPerformNetworkScanResp

Macros

- #define QMI_NAS_NETSTATUS_MASK 0x03
- #define QMI_NAS_MAX_INSTANCES 20
- #define INDEX_ZERO 0
- #define ROAMING_INDEX 2
- #define FORBIDDEN_INDEX 4
- #define PREFERRED_INDEX 6
- #define MAX_DESCRIPTION_LENGTH 255

Enumerations

- enum eQMI_NAS_PERFORM_NETWORK_SCAN_RESP { eTLV_3GPP_NETWORK_INFO = 0x10 }

Functions

- enum eQCWWANError PkQmiNasPerformNetworkScan (WORD ∗pMlength, BYTE ∗pParamField)
- enum eQCWWANError UpkQmiNasPerformNetworkScan (BYTE ∗pMdmResp, struct QmiNasPerformNetworkScanResp ∗pAipResp)

9.51.1 Macro Definition Documentation

9.51.1.1 #define FORBIDDEN_INDEX 4

9.51.1.2 #define INDEX_ZERO 0

9.51.1.3 #define MAX_DESCRIPTION_LENGTH 255

9.51.1.4 #define PREFERRED_INDEX 6

9.51.1.5 #define QMI_NAS_MAX_INSTANCES 20

9.51.1.6 #define QMI_NAS_NETSTATUS_MASK 0x03

9.51.1.7 #define ROAMING_INDEX 2

9.51.2 Enumeration Type Documentation

9.51.2.1 enum eQMI_NAS_PERFORM_NETWORK_SCAN_RESP

Enumerator

eTLV_3GPP_NETWORK_INFO

9.51.3 Function Documentation

9.51.3.1 enum eQCWWANError PkQmiNasPerformNetworkScan (WORD * *pMlength,* BYTE * *pParamField*)

9.51.3.2 enum eQCWWANError UpkQmiNasPerformNetworkScan (BYTE * *pMdmResp,* struct QmiNasPerformNetworkScanResp * *pAipResp*)

9.52 qmerrno.h File Reference

Enumerations

- enum eQCWWANError {
  eQCWWAN_ERR_ENUM_BEGIN = -1,
  eQCWWAN_ERR_NONE,
  eQCWWAN_ERR_GENERAL,
  eQCWWAN_ERR_INTERNAL,
  eQCWWAN_ERR_MEMORY,
  eQCWWAN_ERR_INVALID_ARG,
  eQCWWAN_ERR_BUFFER_SZ,
  eQCWWAN_ERR_NO_DEVICE,
  eQCWWAN_ERR_INVALID_DEVID,
  eQCWWAN_ERR_NO_CONNECTION,
  eQCWWAN_ERR_QMI_IFACE,
  eQCWWAN_ERR_QMI_CONNECT,
  eQCWWAN_ERR_QMI_REQ_SCH,
  eQCWWAN_ERR_QMI_REQ,
  eQCWWAN_ERR_QMI_RSP,
  eQCWWAN_ERR_QMI_REQ_TO,
  eQCWWAN_ERR_QMI_RSP_TO,
  eQCWWAN_ERR_MALFORMED_QMI_RSP,
  eQCWWAN_ERR_INVALID_QMI_RSP,
  eQCWWAN_ERR_INVALID_FILE,
  eQCWWAN_ERR_FILE_OPEN,
  eQCWWAN_ERR_FILE_COPY,
  eQCWWAN_ERR_OFFLINE = 27,
  eQCWWAN_ERR_RESET,
  eQCWWAN_ERR_NO_SIGNAL,
  eQCWWAN_ERR_MULTIPLE_DEVICES,
  eQCWWAN_ERR_DRIVER,
  eQCWWAN_ERR_NO_CANCELABLE_OP,
  eQCWWAN_ERR_CANCEL_OP,
  eQCWWAN_ERR_API_MUTEX_TIMEOUT,
  eQCWWAN_ERR_PDU_GENERATION,
  eQCWWAN_ERR_INVALID_XID,
  eQCWWAN_ERR_MULTIPLE_SMS_UNSUPPORTED,
  eQCWWAN_ERR_ENUM_END,
  eQCWWAN_ERR_QMI_OFFSET = 1000,
  eQCWWAN_ERR_QMI_MALFORMED_MSG = 1001,
  eQCWWAN_ERR_QMI_NO_MEMORY,
  eQCWWAN_ERR_QMI_INTERNAL,
  eQCWWAN_ERR_QMI_ABORTED,
  eQCWWAN_ERR_QMI_CLIENT_IDS_EXHAUSTED,
  eQCWWAN_ERR_QMI_UNABORTABLE_TRANSACTION,
  eQCWWAN_ERR_QMI_INVALID_CLIENT_ID,
  eQCWWAN_ERR_QMI_NO_THRESHOLDS,
  eQCWWAN_ERR_QMI_INVALID_HANDLE,
  eQCWWAN_ERR_QMI_INVALID_PROFILE,
  eQCWWAN_ERR_QMI_INVALID_PINID,
  eQCWWAN_ERR_QMI_INCORRECT_PIN,
  eQCWWAN_ERR_QMI_NO_NETWORK_FOUND,
  eQCWWAN_ERR_QMI_CALL_FAILED,
  eQCWWAN_ERR_QMI_OUT_OF_CALL,
  eQCWWAN_ERR_QMI_NOT_PROVISIONED,
  eQCWWAN_ERR_QMI_MISSING_ARG,
  eQCWWAN_ERR_QMI_ARG_TOO_LONG = 1019,
  eQCWWAN_ERR_QMI_INVALID_TX_ID = 1022,
  eQCWWAN_ERR_QMI_DEVICE_IN_USE,
  eQCWWAN_ERR_QMI_OP_NETWORK_UNSUPPORTED,
  eQCWWAN_ERR_QMI_OP_DEVICE_UNSUPPORTED,
  eQCWWAN_ERR_QMI_NO_EFFECT,
  eQCWWAN_ERR_QMI_NO_FREE_PROFILE,
  eQCWWAN_ERR_QMI_INVALID_PDP_TYPE,
  eQCWWAN_ERR_QMI_INVALID_TECH_PREF,
  eQCWWAN_ERR_QMI_INVALID_PROFILE_TYPE,

eQCWWAN_ERR_QMI_WIDTH = 0xFFFF }

- enum qm_wds_ds_profile_extended_err_codes {
  eWDS_ERR_PROFILE_REG_RESULT_FAIL = 1,
  eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_HNDL,
  eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_OP,
  eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_PROFILE_TYPE,
  eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_PROFILE_NUM,
  eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_IDENT,
  eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL,
  eWDS_ERR_PROFILE_REG_RESULT_ERR_LIB_NOT_INITED,
  eWDS_ERR_PROFILE_REG_RESULT_ERR_LEN_INVALID,
  eWDS_ERR_PROFILE_REG_RESULT_LIST_END,
  eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_SUBS_ID,
  eWDS_ERR_PROFILE_REG_INVAL_PROFILE_FAMILY,
  eWDS_ERR_PROFILE_REG_3GPP_INVAL_PROFILE_FAMILY = 1001,
  eWDS_ERR_PROFILE_REG_3GPP_ACCESS_ERR,
  eWDS_ERR_PROFILE_REG_3GPP_CONTEXT_NOT_DEFINED,
  eWDS_ERR_PROFILE_REG_3GPP_VALID_FLAG_NOT_SET,
  eWDS_ERR_PROFILE_REG_3GPP_READ_ONLY_FLAG_SET,
  eWDS_ERR_PROFILE_REG_3GPP_ERR_OUT_OF_PROFILES,
  eWDS_ERR_PROFILE_REG_3GPP2_ERR_INVALID_IDENT_FOR_PROFILE = 1101,
  eWDS_ERR_PROFILE_REG_END }

9.52.1 Enumeration Type Documentation

9.52.1.1 enum eQCWWANError

QMI Error Code Enumeration

Enumerator

eQCWWAN_ERR_ENUM_BEGIN

eQCWWAN_ERR_NONE 00 - Success

eQCWWAN_ERR_GENERAL 01 - General error

eQCWWAN_ERR_INTERNAL 02 - Internal error

eQCWWAN_ERR_MEMORY 03 - Memory error

eQCWWAN_ERR_INVALID_ARG 04 - Invalid argument

eQCWWAN_ERR_BUFFER_SZ 05 - Buffer too small

eQCWWAN_ERR_NO_DEVICE 06 - Unable to detect WWAN device

eQCWWAN_ERR_INVALID_DEVID 07 - Invalid WWAN device ID

eQCWWAN_ERR_NO_CONNECTION 08 - No connection to WWAN device

eQCWWAN_ERR_QMI_IFACE 09 - Unable to obtain QMI interace

eQCWWAN_ERR_QMI_CONNECT 10 - Unable to connect to QMI interface

eQCWWAN_ERR_QMI_REQ_SCH 11 - Unable to schedule QMI request

eQCWWAN_ERR_QMI_REQ 12 - Error sending QMI request

eQCWWAN_ERR_QMI_RSP 13 - Error receiving QMI response

eQCWWAN_ERR_QMI_REQ_TO 14 - Timeout while sending QMI request

eQCWWAN_ERR_QMI_RSP_TO 15 - Timeout while receiving QMI response

eQCWWAN_ERR_MALFORMED_QMI_RSP 16 - Malformed QMI response received

eQCWWAN_ERR_INVALID_QMI_RSP 17 - Invalid QMI response received

eQCWWAN_ERR_INVALID_FILE 18 - Invalid file path

eQCWWAN_ERR_FILE_OPEN 19 - Unable to open file

eQCWWAN_ERR_FILE_COPY 20 - Unable to copy file

eQCWWAN_ERR_OFFLINE 27 - Unable to set WWAN device offline

eQCWWAN_ERR_RESET 28 - Unable to reset WWAN device

eQCWWAN_ERR_NO_SIGNAL 29 - No available signal

eQCWWAN_ERR_MULTIPLE_DEVICES 30 - Multiple WWAN devices detected

eQCWWAN_ERR_DRIVER 31 - Error interfacing to driver

eQCWWAN_ERR_NO_CANCELABLE_OP 32 - No cancelable operation is pending

eQCWWAN_ERR_CANCEL_OP 33- Error canceling outstanding operation

eQCWWAN_ERR_API_MUTEX_TIMEOUT 34- api mutex lock timeout

eQCWWAN_ERR_PDU_GENERATION 35- PDU generation error

eQCWWAN_ERR_INVALID_XID 36- Invalid transaction id

eQCWWAN_ERR_MULTIPLE_SMS_UNSUPPORTED 37- Unsupported multiple SMS

eQCWWAN_ERR_ENUM_END End of SLQS SDK specific error codes

eQCWWAN_ERR_QMI_OFFSET 1000 - This is not an error code but the offset from which mapped QMI error codes start from

eQCWWAN_ERR_QMI_MALFORMED_MSG 1001 - Malformed or Corrupted QMI msg

eQCWWAN_ERR_QMI_NO_MEMORY 1002 - Device could not allocate memory for QMI Resp

eQCWWAN_ERR_QMI_INTERNAL 1003 - Unexpected error occurred during processing

eQCWWAN_ERR_QMI_ABORTED 1004 - Processing aborted

eQCWWAN_ERR_QMI_CLIENT_IDS_EXHAUSTED 1005 - QMI client IDs have been exhausted

eQCWWAN_ERR_QMI_UNABORTABLE_TRANSACTION 1006 - Unable to abort QMI transaction

eQCWWAN_ERR_QMI_INVALID_CLIENT_ID 1007 - Invalid QMI client ID

eQCWWAN_ERR_QMI_NO_THRESHOLDS 1008 - No thresholds were provided

eQCWWAN_ERR_QMI_INVALID_HANDLE 1009 - Invalid Handle provided in the QMI request

eQCWWAN_ERR_QMI_INVALID_PROFILE 1010 - Profile specified is invalid

eQCWWAN_ERR_QMI_INVALID_PINID 1011 - Invalid PIN ID specified

eQCWWAN_ERR_QMI_INCORRECT_PIN 1012 - Incorrect PIN ID specified

eQCWWAN_ERR_QMI_NO_NETWORK_FOUND 1013 - No network found

eQCWWAN_ERR_QMI_CALL_FAILED 1014 - Call failed

eQCWWAN_ERR_QMI_OUT_OF_CALL 1015 - Device is not in a call

eQCWWAN_ERR_QMI_NOT_PROVISIONED 1016 - Requested information element not provisioned on device

eQCWWAN_ERR_QMI_MISSING_ARG 1017 - Mandatory QMI TLV not provided

eQCWWAN_ERR_QMI_ARG_TOO_LONG 1019 - Arg passed in QMI TLV larger than available storage in device

eQCWWAN_ERR_QMI_INVALID_TX_ID 1022 - Invalid TX ID specified

eQCWWAN_ERR_QMI_DEVICE_IN_USE 1023 - Device currently in a call

eQCWWAN_ERR_QMI_OP_NETWORK_UNSUPPORTED 1024 - The selected operation is not supported by the network

eQCWWAN_ERR_QMI_OP_DEVICE_UNSUPPORTED 1025 - The selected operation is not supported by the device

eQCWWAN_ERR_QMI_NO_EFFECT 1026 - Requested operation would have no effect

eQCWWAN_ERR_QMI_NO_FREE_PROFILE 1027 - No space for a profile is available

eQCWWAN_ERR_QMI_INVALID_PDP_TYPE 1028 - Invalid PDP type specified

eQCWWAN_ERR_QMI_INVALID_TECH_PREF 1029 - Invalid technology preference specified

eQCWWAN_ERR_QMI_INVALID_PROFILE_TYPE 1030 - Invalid profile type specified

eQCWWAN_ERR_QMI_INVALID_SERVICE_TYPE 1031 - Invalid service type specified

eQCWWAN_ERR_QMI_INVALID_REGISTER_ACTION 1032 - Invalid register action specified

eQCWWAN_ERR_QMI_INVALID_PS_ATTACH_ACTION 1033 - Invalid PS attach/detach action specified

eQCWWAN_ERR_QMI_AUTHENTICATION_FAILED 1034 - Authentication of supplied information element failed

eQCWWAN_ERR_QMI_PIN_BLOCKED 1035 - PIN is blocked; an unblock operation needs to be issued

eQCWWAN_ERR_QMI_PIN_PERM_BLOCKED 1036 - PIN is permanently blocked; the UIM is unusable

eQCWWAN_ERR_QMI_SIM_NOT_INITIALIZED 1037 - UIM initialization has not completed

eQCWWAN_ERR_QMI_MAX_QOS_REQUESTS_IN_USE 1038 - Max QOS requests are used

eQCWWAN_ERR_QMI_INCORRECT_FLOW_FILTER 1039 - The Flow filter is incorrect

eQCWWAN_ERR_QMI_NETWORK_QOS_UNAWARE 1040 - Network unaware of the QOS requested

eQCWWAN_ERR_QMI_INVALID_ID 1041 - Invalid QOS ID

eQCWWAN_ERR_QMI_INVALID_QOS_ID 1041 - Invalid QOS ID

eQCWWAN_ERR_QMI_REQUESTED_NUM_UNSUPPORTED 1042 - The request number is not supported

eQCWWAN_ERR_QMI_INTERFACE_NOT_FOUND 1043 - Unable to find the interface

eQCWWAN_ERR_QMI_FLOW_SUSPENDED 1044- Flow suspended

eQCWWAN_ERR_QMI_INVALID_DATA_FORMAT 1045 - Data format is invalid

eQCWWAN_ERR_QMI_GENERAL 1046 - General error

eQCWWAN_ERR_QMI_UNKNOWN 1047 - Unknown error

eQCWWAN_ERR_QMI_INVALID_ARG 1048 - A specified argument is invalid

eQCWWAN_ERR_QMI_INVALID_INDEX 1049 - A specified index is invalid

eQCWWAN_ERR_QMI_NO_ENTRY 1050 - No information element exists at specified memory designation

eQCWWAN_ERR_QMI_DEVICE_STORAGE_FULL 1051 - The memory storage specified in the request is full

eQCWWAN_ERR_QMI_DEVICE_NOT_READY 1052 - Device not in a ready state

eQCWWAN_ERR_QMI_NETWORK_NOT_READY 1053 - Network not in a ready state

eQCWWAN_ERR_QMI_CAUSE_CODE 1054 - Error provided in SMS cause code

eQCWWAN_ERR_QMI_MESSAGE_NOT_SENT 1055 - The message could not be sent

eQCWWAN_ERR_QMI_MESSAGE_DELIVERY_FAILURE 1056 - The message could not be delivered

eQCWWAN_ERR_QMI_INVALID_MESSAGE_ID 1057 - The message ID specified for the message is invalid

eQCWWAN_ERR_QMI_ENCODING 1058 - The message is not encoded properly

eQCWWAN_ERR_QMI_AUTHENTICATION_LOCK 1059 - Maximum number of authentication failures has been reached

eQCWWAN_ERR_QMI_INVALID_TRANSITION 1060 - Operating mode transition from the current mode is invalid

eQCWWAN_ERR_QMI_NOT_A_MCAST_IFACE 1061 - The intercace is not muticast

eQCWWAN_ERR_QMI_MAX_MCAST_REQUESTS_IN_USE 1062 - Maximum requests in use

eQCWWAN_ERR_QMI_INVALID_MCAST_HANDLE 1063 - Invalid muticast handle

eQCWWAN_ERR_QMI_INVALID_IP_FAMILY_PREF 1064 - Invalid IP family preference

eQCWWAN_ERR_QMI_SESSION_INACTIVE 1065 - No tracking session has been started

eQCWWAN_ERR_QMI_SESSION_INVALID 1066 - Current session does not allow this operation

eQCWWAN_ERR_QMI_SESSION_OWNERSHIP 1067 - Current tracking session not started by this QMI control point

eQCWWAN_ERR_QMI_INSUFFICIENT_RESOURCES 1068 - Device GPS service resources insufficient for request

eQCWWAN_ERR_QMI_DISABLED 1069 - Support for QMI message is disabled

eQCWWAN_ERR_QMI_INVALID_OPERATION 1070 - Invalid operation specified

eQCWWAN_ERR_QMI_INVALID_QMI_CMD 1071 - Invalid/unknown QMI command specified

eQCWWAN_ERR_QMI_TPDU_TYPE 1072 - Message contains TPDU type that cannot be read as raw message

eQCWWAN_ERR_QMI_SMSC_ADDR 1073 - The SMSC address specified is invalid

eQCWWAN_ERR_QMI_INFO_UNAVAILABLE 1074 - Information element is unavailable at this point

eQCWWAN_ERR_QMI_SEGMENT_TOO_LONG 1075 - Segment size too large

eQCWWAN_ERR_QMI_SEGMENT_ORDER 1076 - Segment order is incorrect

eQCWWAN_ERR_QMI_BUNDLING_NOT_SUPPORTED 1077 - Bundling not supported

eQCWWAN_ERR_QMI_OP_PARTIAL_FAILURE 1078 - The operation failed partially

eQCWWAN_ERR_QMI_POLICY_MISMATCH 1079 - Policy mismatch

eQCWWAN_ERR_QMI_SIM_FILE_NOT_FOUND 1080 - SIM file not found

eQCWWAN_ERR_QMI_EXTENDED_INTERNAL 1081 - Extended internal error

eQCWWAN_ERR_QMI_ACCESS_DENIED 1082 - Access to a required entity is not available

eQCWWAN_ERR_QMI_HARDWARE_RESTRICTED 1083 - Selected operating mode is invalid with current hardware setting

eQCWWAN_ERR_QMI_ACK_NOT_SENT 1084 - ACK not sent

eQCWWAN_ERR_QMI_INJECT_TIMEOUT 1084 - Inject a timeout for the request

eQCWWAN_ERR_QMI_INCOMPATIBLE_STATE 1090 - Incompatible state

eQCWWAN_ERR_QMI_FDN_RESTRICT 1091 - FDN Restrict

eQCWWAN_ERR_QMI_SUPS_FAILURE_CAUSE 1092 - SUPS failure cause

eQCWWAN_ERR_QMI_NO_RADIO 1093 - No Radio

eQCWWAN_ERR_QMI_NOT_SUPPORTED 1094 - Not Supported

eQCWWAN_ERR_QMI_NO_SUBSCRIPTION 1095 - No Subscription

eQCWWAN_ERR_QMI_CARD_CALL_CONTROL_FAILED 1096 - Card call control failed

eQCWWAN_ERR_QMI_NETWORK_ABORTED 1097 - Network Aborted

eQCWWAN_ERR_QMI_MSG_BLOCKED 1098 - Open Error

eQCWWAN_ERR_QMI_MAX Error - End of QMI specific defines

eQCWWAN_ERR_SWICM_START **Vendor defines - Connection Manager error codes**

eQCWWAN_ERR_SWICM_NOT_IMPLEMENTED 0xE001 - The API is yet to be implemented

eQCWWAN_ERR_SWICM_QMI_SVC_NOT_SUPPORTED 0xE002 - The service is not supported

eQCWWAN_ERR_SWICM_QMI_CLNT_NOT_SUPPORTED 0xE003 - The client is not supported

eQCWWAN_ERR_SWICM_TIMEOUT 0xE004 - API Timeout

eQCWWAN_ERR_SWICM_SOCKET_IN_USE 0xE005 - The communication socket is in use

eQCWWAN_ERR_SWICM_AM_VERS_ERROR 0xE006 - SLQS API and SDK version mismatch

eQCWWAN_ERR_SWICM_FAILED_TO_KILL_SDK_PROCESS 0xE007 - Failed to kill SDK process

eQCWWAN_ERR_SWICM_CALL_IN_PROGRESS 0xE008 - Call in progress

eQCWWAN_ERR_SWICM_V4DWN_V6DWN 0xE009 - IPV4 and IPV6 is down

eQCWWAN_ERR_SWICM_V4DWN_V6UP 0xE00A - IPV4 is down and IPV6 is up

eQCWWAN_ERR_SWICM_V4UP_V6DWN 0xE00B - IPV4 is up and IPV6 is down

eQCWWAN_ERR_SWICM_V4UP_V6UP 0xE00C - IPV4 and IPV6 is up

eQCWWAN_ERR_SWICM_INVALID_SESSION_ID 0xE00D - Invalid V4 Session ID

eQCWWAN_ERR_SWICM_INVALID_V4_SESSION_ID 0xE00E - Invalid V4 Session ID

eQCWWAN_ERR_SWICM_INVALID_V6_SESSION_ID 0xE00F - Invalid V6 Session ID

eQCWWAN_ERR_SWICM_SM_NO_AVAILABLE_SESSIONS 0xE010 - No available Session Manager slots for additional data sessions

eQCWWAN_ERR_SWICM_END 0xE011 - End of connection manager specific codes

eQCWWAN_ERR_SWISMS_START **Vendor defines - SMS Error codes**

eQCWWAN_ERR_SWISMS_MSG_LEN_TOO_LONG 0xE101 - SMS message length is long

eQCWWAN_ERR_SWISMS_MSG_CORRUPTED 0xE102 - The SMS message is corrupted (encoding wrong)

eQCWWAN_ERR_SWISMS_SMSC_NUM_CORRUPTED 0xE103 - The SMS number is corrupted (incorrect number)

eQCWWAN_ERR_SWISMS_BEARER_DATA_NOT_FOUND 0xE104 - The SMS bearer data is not available

eQCWWAN_ERR_SWISM_END

eQCWWAN_ERR_SWIIM_START **Vendor defines - Image Management error codes**

eQCWWAN_ERR_SWIIM_INVALID_PATH 0xE801 - Invalid directory path

eQCWWAN_ERR_SWIIM_OPENING_DIR 0xE802 - Unable to open the directory

eQCWWAN_ERR_SWIIM_FILE_NOT_FOUND 0xE803 - No Firmware image present in the path

eQCWWAN_ERR_SWIIM_OPENING_FILE 0xE804 - Unable to open the file

eQCWWAN_ERR_SWIIM_CORRUPTED_FW_IMAGE 0xE805 - Firmware image is corrupted

eQCWWAN_ERR_SWIIM_FIRMWARE_NOT_DOWNLOADED 0xE806 - No Firmware image download needed

eQCWWAN_ERR_SWIIM_FW_UPDATE_FAIL 0xE807 - Firmware update failed

eQCWWAN_ERR_SWIIM_FW_PREFERENCE_MISMATCH 0xE808 - Update success but pri/fw preference mismatch

eQCWWAN_ERR_SWIIM_FW_UPDATE_SUCCESS 0xE809 - Update successful

eQCWWAN_ERR_SWIIM_FW_ENTER_DOWNLOAD_MODE 0xE80A - Enter Download Mode

eQCWWAN_ERR_SWIIM_FW_FLASH_COMPLETE 0xE80B - File transfer to modem complete

eQCWWAN_ERR_SWIIM_FW_WAIT_FOR_REBOOT 0xE80C - Wait for modem to reboot

eQCWWAN_ERR_SWIIM_INVALID_CRASH_STATE 0xE80D - Invalid Crash State for Firmware Download

eQCWWAN_ERR_SWIIM_FW_SAME_AS_CURRENT_ACTIVE_IMAGE 0xE80E - Same as current active image

eQCWWAN_ERR_SWIIM_FW_INVALID_SLOT_INDEX 0xE80F - invalid slot index

eQCWWAN_ERR_SWIIM_FW_SECBOOT_IMAGE_NOT_SIGNED 0xE810 - image not signed

eQCWWAN_ERR_SWIIM_FW_SECBOOT_INVALID_CERT_CHAIN 0xE811 - invalid certificate chain

eQCWWAN_ERR_SWIIM_FW_TOO_MANY_FILES 0xE812 - too many files

eQCWWAN_ERR_SWIIM_END

eQCWWAN_ERR_SWIDCS_START **Vendor defines - Device Connectivity error codes**

eQCWWAN_ERR_SWIDCS_IOCTL_ERR 0xE901 - IO Control error

eQCWWAN_ERR_SWIDCS_FILEIO_ERR 0xE902 - file open/read/write error

eQCWWAN_ERR_SWIDCS_DEVNODE_NOT_FOUND 0xE903 - The device is not found

eQCWWAN_ERR_SWIDCS_APP_DISCONNECTED 0xE904 - Application is disconnected from SDK

eQCWWAN_ERR_SWIDCS_END

eQCWWAN_ERR_QMI_CAT_START **QMI errors related to CAT**

eQCWWAN_ERR_QMI_EVENT_REG_FAILED 62441 - CAT event registration failed

eQCWWAN_ERR_QMI_INVALID_TERMINAL_RSP 62442 - Invalid terminal response

eQCWWAN_ERR_QMI_INVALID_ENVELOPE_CMD 62443 - Invalid envelope command

eQCWWAN_ERR_QMI_CARD_BUSY_RSP 62444 - Card busy response for envelope command

eQCWWAN_ERR_QMI_ENVELOPE_CMD_FAILURE 62445 - Envelope command failure

eQCWWAN_ERR_QMI_CAT_END

eQCWWAN_ERR_NULL_TLV

eQCWWAN_ERR_QMI_WIDTH 0xFFFF - Not an error, represent the end of QMI errors

9.52.1.2 enum qm_wds_ds_profile_extended_err_codes

WDS DS profile extented error codes

Enumerator

eWDS_ERR_PROFILE_REG_RESULT_FAIL 1 - General Failure

eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_HNDL 2 - The request contains an invalid profile handle

eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_OP 3 - An invalid operation was requested.

eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_PROFILE_TYPE 4 - The request contains an invalid technology type

eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_PROFILE_NUM 5 - The request contains an invalid profile number

eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_IDENT 6 - The request contains an invalid profile identifier

eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL 7 - The request contains an invalid argument other than profile number and profile identifier received.

eWDS_ERR_PROFILE_REG_RESULT_ERR_LIB_NOT_INITED 8 - Profile registry has not been initialized yet

eWDS_ERR_PROFILE_REG_RESULT_ERR_LEN_INVALID 9 - The request contains a parameter with invalid length.

eWDS_ERR_PROFILE_REG_RESULT_LIST_END 10 - End of the profile list was reached while searching for the requested profile.

eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_SUBS_ID 11 - The request contains an invalid subscrition identifier.

eWDS_ERR_PROFILE_REG_INVAL_PROFILE_FAMILY 12 - The request contains an invalid profile family.

eWDS_ERR_PROFILE_REG_3GPP_INVAL_PROFILE_FAMILY 1001 - The request contains an invalid 3GPP profile family.

eWDS_ERR_PROFILE_REG_3GPP_ACCESS_ERR 1002 - An error was encountered while accessing the 3GPP profiles.

eWDS_ERR_PROFILE_REG_3GPP_CONTEXT_NOT_DEFINED 1003 - The given 3GPP profile doesn't have a valid context.

eWDS_ERR_PROFILE_REG_3GPP_VALID_FLAG_NOT_SET 1004 - The given 3GPP profile is marked invalid.

eWDS_ERR_PROFILE_REG_3GPP_READ_ONLY_FLAG_SET 1005 - The given 3GPP profile is marked read-only.

eWDS_ERR_PROFILE_REG_3GPP_ERR_OUT_OF_PROFILES 1006 - Creation of a new 3GPP profile failed because the limit of 16 profiles has already been reached.

eWDS_ERR_PROFILE_REG_3GPP2_ERR_INVALID_IDENT_FOR_PROFILE 1101 - An invalid profile identifier was received as part of the 3GPP2 profile modification request.

eWDS_ERR_PROFILE_REG_END

9.53 qos.h File Reference

Data Structures

- struct unpack_qos_SLQSQosGetNetworkStatus_t
- struct pack_qos_SLQSQosSwiReadApnExtraParams_t
- struct unpack_qos_SLQSQosSwiReadApnExtraParams_t

- struct pack_qos_SLQSQosSwiReadDataStats_t
- struct unpack_QosFlowStat_t
- struct unpack_qos_SLQSQosSwiReadDataStats_t
- struct unpack_qos_SLQSSetQosNWStatusCallback_ind_t
- struct unpack_qos_SLQSSetQosStatusCallback_ind_t
- struct unpack_qos_SLQSSetQosPriEventCallback_ind_t
- struct pack_qos_SLQSSetQosEventCallback_t
- struct unpack_qos_SLQSSetQosEventCallback_t
- struct unpack_qos_QosFlowInfoState_t
- struct unpack_qos_dataRate_t
- struct unpack_qos_tokenBucket_t
- struct unpack_qos_pktErrRate_t
- struct unpack_qos_swiQosFlow_t
- struct unpack_qos_IPv4Addr_t
- struct unpack_qos_Tos_t
- struct unpack_qos_IPv6Addr_t
- struct unpack_qos_IPv6TrafCls_t
- struct unpack_qos_Port_t
- struct unpack_qos_swiQosFilter_t
- struct unpack_qos_QosFlowInfo_t
- struct unpack_qos_SLQSSetQosEventCallback_ind_t
- struct qos_BindDataPortPeripheralEndPointID_t
- struct qos_BindDataPortMuxID_t
- struct qos_BindDataPortSIODataPort_t
- struct pack_qos_BindDataPort_t
- struct unpack_qos_BindDataPort_t

Macros

- #define LITEQMI_MAX_QOS_FLOW_PER_APN_STATS 10
- #define LITEQMI_MAX_QOS_FILTERS 25
- #define LITEQMI_MAX_QOS_FLOWS 8

Functions

- int pack_qos_SLQSQosGetNetworkStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_qos_SLQSQosGetNetworkStatus (uint8_t *pResp, uint16_t respLen, unpack_qos_SLQSQosGetNetworkStatus_t *pOutput)
- int pack_qos_SLQSQosSwiReadApnExtraParams (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_qos_SLQSQosSwiReadApnExtraParams_t reqParam)
- int unpack_qos_SLQSQosSwiReadApnExtraParams (uint8_t *pResp, uint16_t respLen, unpack_qos_SLQSQosSwiReadApnExtraParams_t *pOutput)
- int pack_qos_SLQSQosSwiReadDataStats (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_qos_SLQSQosSwiReadDataStats_t reqParam)
- int unpack_qos_SLQSQosSwiReadDataStats (uint8_t *pResp, uint16_t respLen, unpack_qos_SLQSQosSwiReadDataStats_t *pOutput)
- int unpack_qos_SLQSSetQosNWStatusCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_qos_SLQSSetQosNWStatusCallback_ind_t *pOutput)
- int unpack_qos_SLQSSetQosStatusCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_qos_SLQSSetQosStatusCallback_ind_t *pOutput)
- int unpack_qos_SLQSSetQosPriEventCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_qos_SLQSSetQosPriEventCallback_ind_t *pOutput)
- int pack_qos_SLQSSetQosEventCallback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_qos_SLQSSetQosEventCallback_t reqParam)

- int unpack_qos_SLQSSetQosEventCallback (uint8_t ∗pResp, uint16_t respLen, unpack_qos_SLQSSetQosEventCallback_t ∗pOutput)
- int unpack_qos_SLQSSetQosEventCallback_ind (uint8_t ∗pResp, uint16_t respLen, unpack_qos_SLQSSetQosEventCallback_ind_t ∗pOutput)
- int pack_qos_BindDataPort (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_qos_BindDataPort_t req)
- int unpack_qos_BindDataPort (uint8_t ∗pResp, uint16_t respLen, unpack_qos_BindDataPort_t ∗pOutput)

9.53.1 Macro Definition Documentation

9.53.1.1 #define LITEQMI_MAX_QOS_FILTERS 25

9.53.1.2 #define LITEQMI_MAX_QOS_FLOW_PER_APN_STATS 10

9.53.1.3 #define LITEQMI_MAX_QOS_FLOWS 8

9.53.2 Function Documentation

9.53.2.1 int pack_qos_BindDataPort (pack_qmi_t ∗ *pCtx,* uint8_t ∗ *pReqBuf,* uint16_t ∗ *pLen,* pack_qos_BindDataPort_t *req*)

Function to pack command to Binds a control point to a data port. This maps to PkQmiQosBindDataPort

Parameters

out	*pCtx*	• See pack_qmi_t for more information
in,out	*pReqBuf*	• Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
in,out	*pLen*	• On input, size of pReqBuf • On ouptut, number of bytes actually packed
in	*req*	• See pack_qos_BindDataPort_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- Timeout: 2 seconds

9.53.2.2 int pack_qos_SLQSQosGetNetworkStatus (pack_qmi_t ∗ *pCtx,* uint8_t ∗ *pReqBuf,* uint16_t ∗ *pLen*)

Function to pack command to retrieve QoS status of the network. This maps to SLQSQosGetNetworkStatus

Parameters

out	*pCtx*	• See pack_qmi_t for more information
in,out	*pReqBuf*	• Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
in,out	*pLen*	• On input, size of pReqBuf • On ouptut, number of bytes actually packed

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- Timeout: 2 seconds
- Technology Supported: CDMA
- PDN Specific: No

9.53.2.3 int pack_qos_SLQSQosSwiReadApnExtraParams (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_qos_SLQSQosSwiReadApnExtraParams_t *reqParam*)

Function to pack QMI command to query extra APN parameters This maps to SLQSQosSwiReadApnExtraParams

Parameters

out	*pCtx*	• See pack_qmi_t for more information
in,out	*pReqBuf*	• Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
in,out	*pLen*	• On input, size of pReqBuf • On ouptut, number of bytes actually packed
in	*reqParam*	• See pack_qos_SLQSQosSwiReadApnExtraParams_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- Timeout: 2 seconds
  - PDN Specific: Yes

9.53.2.4 int pack_qos_SLQSQosSwiReadDataStats (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_qos_SLQSQosSwiReadDataStats_t *reqParam*)

Function to pack QMI command to query APN data statistics This maps to SLQSQosSwiReadDataStats

Parameters

out	*pCtx*	• See pack_qmi_t for more information
in,out	*pReqBuf*	• Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
in,out	*pLen*	• On input, size of pReqBuf • On ouptut, number of bytes actually packed
in	*reqParam*	• See pack_qos_SLQSQosSwiReadDataStats_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- Timeout: 2 seconds
  - PDN Specific: Yes

9.53.2.5 int pack_qos_SLQSSetQosEventCallback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_qos_SLQSSetQosEventCallback_t *reqParam*)

Function to pack QMI command to enable QoS event indications This maps to SLQSSetQosEventCallback

Parameters

out	*pCtx*	• See pack_qmi_t for more information

in,out	*pReqBuf*	• Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
in,out	*pLen*	• On input, size of pReqBuf • On ouptut, number of bytes actually packed
in	*reqParam*	• See pack_qos_SLQSSetQosEventCallback_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- Timeout: 2 seconds
  - PDN Specific: Yes

9.53.2.6 int unpack_qos_BindDataPort (uint8_t * *pResp*, uint16_t *respLen*, **unpack_qos_BindDataPort_t** * *pOutput*)

Function to unpack the response to Binds a control point to a data port. This maps to UpkQmiQosBindDataPort

Parameters

in	*pResp*	• Response from modem
in	*respLen*	• Length of pResp from modem
out	*pOutput*	• See unpack_qos_BindDataPort_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.53.2.7 int unpack_qos_SLQSQosGetNetworkStatus (uint8_t * *pResp*, uint16_t *respLen*, **unpack_qos_SLQSQosGetNetworkStatus_t** * *pOutput*)

Function to unpack the response to get NW QoS status command This maps to SLQSQosGetNetworkStatus

Parameters

in	*pResp*	• Response from modem
in	*respLen*	• Length of pResp from modem
out	*pOutput*	• See unpack_qos_SLQSQosGetNetworkStatus_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.53.2.8 int unpack_qos_SLQSQosSwiReadApnExtraParams (uint8_t * *pResp*, uint16_t *respLen*, unpack_qos_SLQSQosSwiReadApnExtraParams_t * *pOutput*)

Function to unpack the response to get NW QoS status command This maps to SLQSQosSwiReadApnExtraParams

Parameters

in	*pResp*	• Response from modem
in	*respLen*	• Length of pResp from modem
out	*pOutput*	• See unpack_qos_SLQSQosSwiReadApnExtraParams_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.53.2.9 int unpack_qos_SLQSQosSwiReadDataStats (uint8_t * *pResp*, uint16_t *respLen*, unpack_qos_SLQSQosSwiReadDataStats_t * *pOutput*)

Function to unpack APN data statistics response This maps to SLQSQosSwiReadDataStats

Parameters

in	*pResp*	• Response from modem

in	*respLen*	• Length of pResp from modem
out	*pOutput*	• See unpack_qos_SLQSQosSwiReadDataStats_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.53.2.10 int unpack_qos_SLQSSetQosEventCallback (uint8_t * *pResp*, uint16_t *respLen*, unpack_qos_SLQSSetQosEventCallback_t * *pOutput*)

Function to unpack enable QoS event indications command's response This maps to SLQSSetQosEventCallback

Parameters

in	*pResp*	• Response from modem
in	*respLen*	• Length of pResp from modem
out	*pOutput*	• See unpack_qos_SLQSSetQosEventCallback_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.53.2.11 int unpack_qos_SLQSSetQosEventCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_qos_SLQSSetQosEventCallback_ind_t * *pOutput*)

Function to unpack QoS event indications This maps to SLQSSetQosEventCallback

Parameters

in	*pResp*	• Response from modem
in	*respLen*	• Length of pResp from modem

out	*pOutput*	• See unpack_qos_SLQSSetQosEventCallback_ind_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- This is a broadcast notification that is sent to the registered QoS service
- No explicit function to register for this indication is needed
- Please use eQMI_QOS_NETWORK_STATUS_IND indication to identify this event from QOS service read function

9.53.2.12 int unpack_qos_SLQSSetQosNWStatusCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_qos_SLQSSetQosNWStatusCallback_ind_t * *pOutput*)

Function to unpack QoS NW status indication. This maps to SLQSSetQosNWStatusCallback

Parameters

in	*pResp*	• Response from modem
in	*respLen*	• Length of pResp from modem
out	*pOutput*	• See unpack_qos_SLQSSetQosNWStatusCallback_ind_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- Technology Supported: CDMA
- This is a broadcast notification that is sent to the registered QoS service
- No explicit function to register for this indication is needed
- Please use eQMI_QOS_NETWORK_STATUS_IND indication to identify this event from QOS service read function

9.53.2.13 int unpack_qos_SLQSSetQosPriEventCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_qos_SLQSSetQosPriEventCallback_ind_t * *pOutput*)

Function to unpack QoS primary flow events. This maps to SLQSSetQosPriEventCallback

Parameters

in	*pResp*	• Response from modem
in	*respLen*	• Length of pResp from modem
out	*pOutput*	• See unpack_qos_SLQSSetQosPriEventCallback_ind_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- This is a broadcast notification that is sent to the registered QoS service
- No explicit function to register for this indication is needed
- Please use eQMI_QOS_PRIMARY_QOS_EVENT_IND indication to identify this event from QOS service read function
- This is only generated when the primary flow is modified by the host

9.53.2.14 int unpack_qos_SLQSSetQosStatusCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_qos_SLQSSetQosStatusCallback_ind_t * *pOutput*)

Function to unpack QoS status indications. This maps to SLQSSetQosStatusCallback

Parameters

in	*pResp*	• Response from modem
in	*respLen*	• Length of pResp from modem
out	*pOutput*	• See unpack_qos_SLQSSetQosStatusCallback_ind_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- This is a broadcast notification that is sent to the registered QoS service
- No explicit function to register for this indication is needed
- Please use eQMI_QOS_FLOW_STATUS_IND indication to identify this event from QOS service read function

9.54 rms.h File Reference

Data Structures

- struct unpack_rms_GetSMSWake_t
- struct pack_rms_SetSMSWake_t
- struct unpack_rms_SetSMSWake_t

Macros

- #define __LITEQMI_RMS_H__

Functions

- int pack_rms_GetSMSWake (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen)
- int unpack_rms_GetSMSWake (uint8_t ∗pResp, uint16_t respLen, unpack_rms_GetSMSWake_t ∗pOutput)
- int pack_rms_SetSMSWake (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_rms_SetSMSWake_t ∗reqArg)
- int unpack_rms_SetSMSWake (uint8_t ∗pResp, uint16_t respLen, unpack_rms_SetSMSWake_t ∗pOutput)

9.54.1 Macro Definition Documentation

9.54.1.1 #define __LITEQMI_RMS_H__

9.54.2 Function Documentation

9.54.2.1 int pack_rms_GetSMSWake (pack_qmi_t ∗ *pCtx*, uint8_t ∗ *pReqBuf*, uint16_t ∗ *pLen*)

Get SMS Wake pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.54.2.2 int pack_rms_SetSMSWake (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_rms_SetSMSWake_t * *reqArg*)

Set SMS Wake pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.54.2.3 int unpack_rms_GetSMSWake (uint8_t * *pResp*, uint16_t *respLen*, unpack_rms_GetSMSWake_t * *pOutput*)

Get SMS Wake unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.54.2.4 int unpack_rms_SetSMSWake (uint8_t * *pResp*, uint16_t *respLen*, unpack_rms_SetSMSWake_t * *pOutput*)

Set SMS Wake unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.55 sar.h File Reference

Data Structures

- struct unpack_sar_SLQSGetRfSarState_t
- struct pack_sar_SLQSSetRfSarState_t

Typedefs

- typedef unpack_result_t unpack_sar_SLQSSetRfSarState_t

Functions

- int pack_sar_SLQSGetRfSarState (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen)
- int unpack_sar_SLQSGetRfSarState (uint8_t ∗pResp, uint16_t respLen, unpack_sar_SLQSGetRfSarState_t ∗pOutput)
- int pack_sar_SLQSSetRfSarState (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_sar_SLQSSetRfSarState_t ∗reqArg)
- int unpack_sar_SLQSSetRfSarState (uint8_t ∗pResp, uint16_t respLen, unpack_sar_SLQSSetRfSarState_t ∗pOutput)

9.55.1 Typedef Documentation

9.55.1.1 typedef unpack_result_t unpack_sar_SLQSSetRfSarState_t

9.55.2 Function Documentation

9.55.2.1 int pack_sar_SLQSGetRfSarState (pack_qmi_t ∗ *pCtx,* uint8_t ∗ *pReqBuf,* uint16_t ∗ *pLen*)

Gets the specified RF SAR state pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.55.2.2 int pack_sar_SLQSSetRfSarState (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_sar_SLQSSetRfSarState_t * reqArg)

Sets the specified RF SAR state pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.55.2.3 int unpack_sar_SLQSGetRfSarState (uint8_t * pResp, uint16_t respLen, unpack_sar_SLQSGetRfSarState_t * pOutput)

Gets the specified RF SAR state unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.55.2.4 int unpack_sar_SLQSSetRfSarState (uint8_t * pResp, uint16_t respLen, unpack_sar_SLQSSetRfSarState_t * pOutput)

Sets the specified RF SAR state unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56 sms.h File Reference

Data Structures

- struct pack_sms_SLQSGetSMS_t
- struct unpack_sms_SLQSGetSMS_t
- struct pack_sms_SLQSGetSMSList_t
- struct qmiSmsMessageList
- struct unpack_sms_SLQSGetSMSList_t
- struct pack_sms_SLQSModifySMSStatus_t
- struct unpack_sms_SLQSModifySMSStatus_t
- struct pack_sms_SLQSDeleteSMS_t
- struct unpack_sms_SLQSDeleteSMS_t
- struct pack_sms_SendSMS_t
- struct unpack_sms_SendSMS_t
- struct pack_sms_SetNewSMSCallback_t
- struct unpack_sms_SetNewSMSCallback_t
- struct sMSMTMessageInfo
- struct newMTMessageTlv
- struct sMSTransferRouteMTMessageInfo
- struct transferRouteMessageTlv
- struct sMSMessageModeInfo
- struct messageModeTlv
- struct sMSEtwsMessageInfo
- struct sMSEtwsMessageTlv
- struct sMSEtwsPlmnInfo
- struct eTWSPLMNInfoTlv
- struct sMSCAddressInfo
- struct sMSCAddressTlv
- struct sMSOnIMSInfo
- struct sMSOnIMSTlv
- struct unpack_sms_SetNewSMSCallback_ind_t
- struct unpack_sms_SLQSWmsMemoryFullCallBack_ind_t
- struct unpack_sms_GetSMSCAddress_t
- struct pack_sms_SetSMSCAddress_t
- struct unpack_sms_SetSMSCAddress_t
- struct pack_sms_SaveSMS_t
- struct unpack_sms_SaveSMS_t
- struct sms_BroadcastConfig
- struct sms_qaQmi3GPPBroadcastCfgInfo
- struct sms_CDMABroadcastConfig
- struct sms_qaQmi3GPP2BroadcastCfgInfo
- struct unpack_sms_SLQSGetSmsBroadcastConfig_t
- struct pack_sms_SLQSGetSmsBroadcastConfig_t
- struct pack_sms_SLQSSetSmsBroadcastConfig_t
- struct unpack_sms_SLQSSetSmsBroadcastConfig_t
- struct pack_sms_SLQSSetSmsBroadcastActivation_t
- struct unpack_sms_SLQSSetSmsBroadcastActivation_t
- struct sms_transLayerInfo
- struct sms_getTransLayerInfo

- struct unpack_sms_SLQSGetTransLayerInfo_t
- struct sms_getTransNWRegInfo
- struct unpack_sms_SLQSGetTransNWRegInfo_t
- struct sms_getIndicationReg
- struct unpack_sms_SLQSGetIndicationRegister_t
- struct sms_setIndicationReg
- struct pack_sms_SLQSSetIndicationRegister_t
- struct unpack_sms_SLQSSetIndicationRegister_t
- struct sms_routeEntry
- struct sms_setRoutesReq
- struct pack_sms_SLQSSmsSetRoutes_t
- struct unpack_sms_SLQSSmsSetRoutes_t
- struct sms_msgProtocolResp
- struct unpack_sms_SLQSSmsGetMessageProtocol_t
- struct sms_maxStorageSizeReq
- struct sms_maxStorageSizeResp
- struct pack_sms_SLQSSmsGetMaxStorageSize_t
- struct unpack_sms_SLQSSmsGetMaxStorageSize_t
- struct sms_messageWaitingInfoContent
- struct sms_getMsgWaitingInfo
- struct unpack_sms_SLQSGetMessageWaiting_t
- struct sms_sendAsyncsmsParams
- struct pack_sms_SLQSSendAsyncSMS_t
- struct unpack_sms_SLQSSendAsyncSMS_t
- struct pack_sms_SLQSSetSmsStorage_t
- struct unpack_sms_SLQSSetSmsStorage_t
- struct unpack_sms_SLQSSwiGetSMSStorage_t
- struct unpack_sms_SLQSTransLayerInfoCallback_ind_t
- struct unpack_sms_SLQSNWRegInfoCallback_ind_t
- struct unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t
- struct unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t

Macros

- #define MAX_SMS_MESSAGE_SIZE 2048
- #define MAX_SMS_LIST_SIZE 255
- #define MAX_MS_TRANSFER_ROUTE_MSG 256
- #define MAX_MSE_TWS_MSG 1254
- #define MAX_MSC_ADDRESS_SIZE 256
- #define MAX_CDMA_ENC_MO_TXT_MSG_SIZE 255
- #define SMSC_TYPE_LEN 0x03
- #define SMS_CONFIG_LEN 0x05
- #define SMS_MAX_SMS_ROUTES 0x0A
- #define SMS_NUM_OF_SET 0xFF

Enumerations

- enum eqmiCbkSetStatus {
  LITEQMI_QMI_CBK_PARAM_RESET = 0,
  LITEQMI_QMI_CBK_PARAM_SET = 1,
  LITEQMI_QMI_CBK_PARAM_NOCHANGE }

Functions

- int pack_sms_SLQSGetSMS (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSGetSMS_t *reqParam)
- int unpack_sms_SLQSGetSMS (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSGetSMS_t *pOutput)
- int pack_sms_SLQSGetSMSList (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSGetSMSList_t *reqParam)
- int unpack_sms_SLQSGetSMSList (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSGetSMSList_t *pOutput)
- int pack_sms_SLQSModifySMSStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSModifySMSStatus_t *reqParam)
- int unpack_sms_SLQSModifySMSStatus (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSModifySMSStatus_t *pOutput)
- int pack_sms_SLQSDeleteSMS (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSDeleteSMS_t *reqParam)
- int unpack_sms_SLQSDeleteSMS (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSDeleteSMS_t *pOutput)
- int pack_sms_SendSMS (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SendSMS_t *reqParam)
- int unpack_sms_SendSMS (uint8_t *pResp, uint16_t respLen, unpack_sms_SendSMS_t *pOutput)
- int pack_sms_SetNewSMSCallback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SetNewSMSCallback_t reqParam)
- int unpack_sms_SetNewSMSCallback (uint8_t *pResp, uint16_t respLen, unpack_sms_SetNewSMSCallback_t *Output)
- int unpack_sms_SetNewSMSCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_sms_SetNewSMSCallback_ind_t *pOutput)
- int unpack_sms_SLQSWmsMemoryFullCallBack_ind (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSWmsMemoryFullCallBack_ind_t *pOutput)
- int pack_sms_GetSMSCAddress (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_sms_GetSMSCAddress (uint8_t *pResp, uint16_t respLen, unpack_sms_GetSMSCAddress_t *pOutput)
- int pack_sms_SetSMSCAddress (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SetSMSCAddress_t *reqParam)
- int unpack_sms_SetSMSCAddress (uint8_t *pResp, uint16_t respLen, unpack_sms_SetSMSCAddress_t *pOutput)
- int pack_sms_SaveSMS (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SaveSMS_t *reqParam)
- int unpack_sms_SaveSMS (uint8_t *pResp, uint16_t respLen, unpack_sms_SaveSMS_t *pOutput)
- int pack_sms_SLQSGetSmsBroadcastConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSGetSmsBroadcastConfig_t *reqParam)
- int unpack_sms_SLQSGetSmsBroadcastConfig (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSGetSmsBroadcastConfig_t *pOutput)
- int pack_sms_SLQSSetSmsBroadcastConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSSetSmsBroadcastConfig_t *reqParam)
- int unpack_sms_SLQSSetSmsBroadcastConfig (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSSetSmsBroadcastConfig_t *pOutput)
- int pack_sms_SLQSSetSmsBroadcastActivation (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSSetSmsBroadcastActivation_t *reqParam)
- int unpack_sms_SLQSSetSmsBroadcastActivation (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSSetSmsBroadcastActivation_t *pOutput)
- int pack_sms_SLQSGetTransLayerInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_sms_SLQSGetTransLayerInfo (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSGetTransLayerInfo_t *pOutput)
- int pack_sms_SLQSGetTransNWRegInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_sms_SLQSGetTransNWRegInfo (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSGetTransNWRegInfo_t *pOutput)

- int pack_sms_SLQSGetIndicationRegister (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_sms_SLQSGetIndicationRegister (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSGetIndicationRegister_t *pOutput)
- int pack_sms_SLQSSetIndicationRegister (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSSetIndicationRegister_t *reqParam)
- int unpack_sms_SLQSSetIndicationRegister (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSSetIndicationRegister_t *pOutput)
- int pack_sms_SLQSSmsSetRoutes (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSSmsSetRoutes_t *reqParam)
- int unpack_sms_SLQSSmsSetRoutes (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSSmsSetRoutes_t *pOutput)
- int pack_sms_SLQSSmsGetMessageProtocol (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_sms_SLQSSmsGetMessageProtocol (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSSmsGetMessageProtocol_t *pOutput)
- int pack_sms_SLQSSmsGetMaxStorageSize (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSSmsGetMaxStorageSize_t *reqParam)
- int unpack_sms_SLQSSmsGetMaxStorageSize (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSSmsGetMaxStorageSize_t *pOutput)
- int pack_sms_SLQSGetMessageWaiting (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_sms_SLQSGetMessageWaiting (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSGetMessageWaiting_t *pOutput)
- int pack_sms_SLQSSendAsyncSMS (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSSendAsyncSMS_t *reqParam)
- int unpack_sms_SLQSSendAsyncSMS (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSSendAsyncSMS_t *pOutput)
- int pack_sms_SLQSSetSmsStorage (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_sms_SLQSSetSmsStorage_t *reqParam)
- int unpack_sms_SLQSSetSmsStorage (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSSetSmsStorage_t *pOutput)
- int pack_sms_SLQSSwiGetSMSStorage (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_sms_SLQSSwiGetSMSStorage (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSSwiGetSMSStorage_t *pOutput)
- int unpack_sms_SLQSTransLayerInfoCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSTransLayerInfoCallback_ind_t *pOutput)
- int unpack_sms_SLQSNWRegInfoCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSNWRegInfoCallback_ind_t *pOutput)
- int unpack_sms_SLQSWmsMessageWaitingCallBack_ind (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t *pOutput)
- int unpack_sms_SLQSWmsAsyncRawSendCallBack_ind (uint8_t *pResp, uint16_t respLen, unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t *pOutput)

9.56.1 Macro Definition Documentation

9.56.1.1 #define MAX_CDMA_ENC_MO_TXT_MSG_SIZE 255

9.56.1.2 #define MAX_MS_TRANSFER_ROUTE_MSG 256

9.56.1.3 #define MAX_MSC_ADDRESS_SIZE 256

9.56.1.4 #define MAX_MSE_TWS_MSG 1254

9.56.1.5 #define MAX_SMS_LIST_SIZE 255

9.56.1.6 #define MAX_SMS_MESSAGE_SIZE 2048

9.56.1.7 #define SMS_CONFIG_LEN 0x05

9.56.1.8 #define SMS_MAX_SMS_ROUTES 0x0A

9.56.1.9 #define SMS_NUM_OF_SET 0xFF

9.56.1.10 #define SMSC_TYPE_LEN 0x03

9.56.2 Enumeration Type Documentation

9.56.2.1 enum eqmiCbkSetStatus

Enumerator

LITEQMI_QMI_CBK_PARAM_RESET

LITEQMI_QMI_CBK_PARAM_SET

LITEQMI_QMI_CBK_PARAM_NOCHANGE

9.56.3 Function Documentation

9.56.3.1 int pack_sms_GetSMSCAddress (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets the SMS center address pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.2 int pack_sms_SaveSMS (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SaveSMS_t * *reqParam*)

Saves an SMS message to device memory pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.3 int pack_sms_SendSMS (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SendSMS_t * *reqParam*)

send sms list pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.4 int pack_sms_SetNewSMSCallback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SetNewSMSCallback_t *reqParam*)

set new sms callback pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.5 int pack_sms_SetSMSCAddress (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SetSMSCAddress_t * *reqParam*)

Set the SMS center address pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.6 int pack_sms_SLQSDeleteSMS (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SLQSDeleteSMS_t * *reqParam*)

delete sms pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.7 int pack_sms_SLQSGetIndicationRegister (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets registration state of different WMS indications pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.8 int pack_sms_SLQSGetMessageWaiting (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets the message waiting information pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.9 int pack_sms_SLQSGetSMS (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SLQSGetSMS_t * *reqParam*)

get sms pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.10 int pack_sms_SLQSGetSmsBroadcastConfig (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SLQSGetSmsBroadcastConfig_t * *reqParam*)

Provides Information about the SMS BroadcastConfiguration pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.11 int pack_sms_SLQSGetSMSList (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SLQSGetSMSList_t * *reqParam*)

get sms list pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.12 int pack_sms_SLQSGetTransLayerInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets information about the transport layer pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.13 int pack_sms_SLQSGetTransNWRegInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets transport layer network registration info pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.14 int pack_sms_SLQSModifySMSStatus (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SLQSModifySMSStatus_t * *reqParam*)

modify sms status pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.15 int pack_sms_SLQSSendAsyncSMS (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SLQSSendAsyncSMS_t * *reqParam*)

Sends an SMS message for immediate over-the-air transmission pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.16 int pack_sms_SLQSSetIndicationRegister (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SLQSSetIndicationRegister_t * *reqParam*)

Sets the registration state of different WMS indications pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.17 int pack_sms_SLQSSetSmsBroadcastActivation (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_sms_SLQSSetSmsBroadcastActivation_t * reqParam)

Enables or disables the reception of broadcast SMS messages pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.18 int pack_sms_SLQSSetSmsBroadcastConfig (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_sms_SLQSSetSmsBroadcastConfig_t * reqParam)

Sets the information about the SMS BroadcastConfiguration pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.19 int pack_sms_SLQSSetSmsStorage (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_sms_SLQSSetSmsStorage_t * reqParam)

Sets the SMS Storage on the device pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.20 int pack_sms_SLQSSmsGetMaxStorageSize (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SLQSSmsGetMaxStorageSize_t * *reqParam*)

Get the maximum number of messages that can be stored in the specified memory storage. Also it provides the number of slots currently available pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.21 int pack_sms_SLQSSmsGetMessageProtocol (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets the message protocol currently in use for the WMS client pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.22 int pack_sms_SLQSSmsSetRoutes (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_sms_SLQSSmsSetRoutes_t * *reqParam*)

Sets the action performed on SMS message receipt for specified message routes. It also specifies the action performed on SMS receipt of status reports pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
	reqParam	packed request

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.23 int pack_sms_SLQSSwiGetSMSStorage (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets the current SMS configuration that is applied to all incoming and outgoing messages pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.24 int unpack_sms_GetSMSCAddress (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_GetSMSCAddress_t * *pOutput*)

Gets the SMS center address unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.25 int unpack_sms_SaveSMS (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SaveSMS_t * *pOutput*)

Saves an SMS message to device memory unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.26 int unpack_sms_SendSMS (uint8_t * *pResp*, uint16_t *respLen*, **unpack_sms_SendSMS_t** * *pOutput*)

send sms unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.27 int unpack_sms_SetNewSMSCallback (uint8_t * *pResp*, uint16_t *respLen*, **unpack_sms_SetNewSMSCallback_t** * *Output*)

set new sms callback unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*Output*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.28 int unpack_sms_SetNewSMSCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_sms_SetNewSMSCallback_ind_t** * *pOutput*)

set new sms callback indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.29 int unpack_sms_SetSMSCAddress (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SetSMSCAddress_t * *pOutput*)

Set the SMS center address unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.30 int unpack_sms_SLQSDeleteSMS (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSDeleteSMS_t * *pOutput*)

delete sms unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.31 int unpack_sms_SLQSGetIndicationRegister (uint8_t * *pResp*, uint16_t *respLen*, **unpack_sms_SLQSGetIndicationRegister_t** * *pOutput*)

Gets registration state of different WMS indications unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.32 int unpack_sms_SLQSGetMessageWaiting (uint8_t * *pResp*, uint16_t *respLen*, **unpack_sms_SLQSGetMessageWaiting_t** * *pOutput*)

Gets the message waiting information unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.33 int unpack_sms_SLQSGetSMS (uint8_t * *pResp*, uint16_t *respLen*, **unpack_sms_SLQSGetSMS_t** * *pOutput*)

get sms unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.34 int unpack_sms_SLQSGetSmsBroadcastConfig (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSGetSmsBroadcastConfig_t * *pOutput*)

Provides Information about the SMS BroadcastConfiguration unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.35 int unpack_sms_SLQSGetSMSList (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSGetSMSList_t * *pOutput*)

get sms list unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.36 int unpack_sms_SLQSGetTransLayerInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSGetTransLayerInfo_t * *pOutput*)

Gets information about the transport layer unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.37 int unpack_sms_SLQSGetTransNWRegInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSGetTransNWRegInfo_t * *pOutput*)

Gets transport layer network registration info unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.38 int unpack_sms_SLQSModifySMSStatus (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSModifySMS-Status_t * *pOutput*)

modify sms status unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.39 int unpack_sms_SLQSNWRegInfoCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSNWRegInfoCallback_ind_t * *pOutput*)

Unpack indication about change in transport layer info

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.40 int unpack_sms_SLQSSendAsyncSMS (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSSendAsyncSMS_t * *pOutput*)

Sends an SMS message for immediate over-the-air transmission unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.41 int unpack_sms_SLQSSetIndicationRegister (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSSetIndicationRegister_t * *pOutput*)

Sets the registration state of different WMS indications unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.42 int unpack_sms_SLQSSetSmsBroadcastActivation (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSSetSmsBroadcastActivation_t * *pOutput*)

Enables or disables the reception of broadcast SMS messages unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.43 int unpack_sms_SLQSSetSmsBroadcastConfig (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSSetSmsBroadcastConfig_t * *pOutput*)

Sets the information about the SMS BroadcastConfiguration unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.44 int unpack_sms_SLQSSetSmsStorage (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSSetSmsStorage_t * *pOutput*)

Sets the SMS Storage on the device unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.45 int unpack_sms_SLQSSmsGetMaxStorageSize (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSSmsGetMaxStorageSize_t * *pOutput*)

Get the maximum number of messages that can be stored in the specified memory storage. Also it provides the number of slots currently available unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.46 int unpack_sms_SLQSSmsGetMessageProtocol (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSSmsGetMessageProtocol_t * *pOutput*)

Gets the message protocol currently in use for the WMS client unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.47 int unpack_sms_SLQSSmsSetRoutes (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSSmsSetRoutes_t * *pOutput*)

Sets the action performed on SMS message receipt for specified message routes. It also specifies the action performed on SMS receipt of status reports unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.48 int unpack_sms_SLQSSwiGetSMSStorage (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSSwiGetSMSStorage_t * *pOutput*)

Gets the current SMS configuration that is applied to all incoming and outgoing messages unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.49 int unpack_sms_SLQSTransLayerInfoCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSTransLayerInfoCallback_ind_t * *pOutput*)

Unpack indication about change in transport layer info

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.50 int unpack_sms_SLQSWmsAsyncRawSendCallBack_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t * *pOutput*)

Unpack indication for sms async raw send

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.51 int unpack_sms_SLQSWmsMemoryFullCallBack_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSWmsMemoryFullCallBack_ind_t * *pOutput*)

sms full callback indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.56.3.52 int unpack_sms_SLQSWmsMessageWaitingCallBack_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t * *pOutput*)

Unpack indication for message waiting information

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.57 SwiDataTypes.h File Reference

SWI data types.

Data Structures

- struct qmTlvResult

Macros

- #define SWI_API

- #define QMI_NO_LTE_FW_SUPPORT 0
- #define QMI_TLV_PLACEHOLDER 0x8F
- #define UNUSEDPARAM(x) (void)x
- #define MEMSET_STATIC_OUTPUT_STRUCT(OUTPUT_PARA, STRUCT_OF_OUTPUT_PARA) memset(OUTPUT_PARA,0,sizeof(STRUCT_OF_OUTPUT_PARA));\

Typedefs

- typedef unsigned int ULONG
- typedef unsigned long long ULONGLONG
- typedef signed char INT8
- typedef unsigned char BYTE
- typedef char CHAR
- typedef unsigned short WORD
- typedef unsigned short USHORT
- typedef const char * LPCSTR
- typedef int BOOL
- typedef signed short SHORT
- typedef signed int INT32
- typedef float FLOAT
- typedef unsigned short qmuint16
- typedef unsigned long qmulong

9.57.1 Detailed Description

SWI data types.

9.57.2 Macro Definition Documentation

9.57.2.1 #define MEMSET_STATIC_OUTPUT_STRUCT(*OUTPUT_PARA, STRUCT_OF_OUTPUT_PARA*) memset(OUTPUT_PARA,0,sizeof(STRUCT_OF_OUTPUT_PARA));\

Macro used to memset unpack output paramter. To prevent output parameter is not inititalized.

9.57.2.2 #define QMI_NO_LTE_FW_SUPPORT 0

9.57.2.3 #define QMI_TLV_PLACEHOLDER 0x8F

9.57.2.4 #define SWI_API

9.57.2.5 #define UNUSEDPARAM(*x*) (void)x

Macro used to avoid “unused variable” compiler warnings generated due to the inclusion of the "-Wextra" flag in our make files.

9.57.3 Typedef Documentation

9.57.3.1 typedef int BOOL

9.57.3.2 typedef unsigned char BYTE

9.57.3.3 typedef char CHAR

9.57.3.4 typedef float FLOAT

9.57.3.5 typedef signed int INT32

9.57.3.6 typedef signed char INT8

9.57.3.7 typedef const char* LPCSTR

9.57.3.8 typedef unsigned short qmuint16

9.57.3.9 typedef unsigned long qmulong

9.57.3.10 typedef signed short SHORT

9.57.3.11 typedef unsigned int ULONG

9.57.3.12 typedef unsigned long long ULONGLONG

9.57.3.13 typedef unsigned short USHORT

9.57.3.14 typedef unsigned short WORD

9.58 swidms.h File Reference

Data Structures

- struct unpack_swidms_SLQSSwiDmsGetUsbNetNum_t
- struct pack_swidms_SLQSSwiDmsSetUsbNetNum_t
- struct pack_swidms_SLQSSwiDmsSetMTU_t
- struct unpack_swidms_SLQSSwiDmsSetMTU_t
- struct swidms_mtuSize3gppTlv
- struct swidms_hrpdMTUSizeTlv
- struct swidms_ehrpdMTUSizeTlv
- struct swidms_usbMTUSizeTlv
- struct unpack_swidms_SLQSSwiDmsGetMTU_t
- struct swidms_intfaceCfgTlv
- struct swidms_supportedIntBitmaskTlv
- struct unpack_swidms_SLQSSwiDmsGetUsbComp_t
- struct pack_swidms_SLQSSwiDmsSetUsbComp_t
- struct unpack_swidms_SLQSSwiDmsSetUsbComp_t
- struct swidms_SwiDmsGetHWWatchdog
- struct unpack_swidms_SLQSSwiDmsGetHWWatchdog_t
- struct pack_swidms_SLQSSwiDmsSetHWWatchdog_t
- struct unpack_swidms_SLQSSwiDmsSetHWWatchdog_t
- struct unpack_swidms_SLQSSwiDmsGetSecureInfo_t

Typedefs

- typedef unpack_result_t unpack_swidms_SLQSSwiDmsSetUsbNetNum_t

Functions

- int pack_swidms_SLQSSwiDmsGetUsbNetNum (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_swidms_SLQSSwiDmsGetUsbNetNum (uint8_t *pResp, uint16_t respLen, unpack_swidms_SLQSSwiDmsGetUsbNetNum_t *pOutput)
- int pack_swidms_SLQSSwiDmsSetUsbNetNum (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_swidms_SLQSSwiDmsSetUsbNetNum_t *pReqParam)
- int unpack_swidms_SLQSSwiDmsSetUsbNetNum (uint8_t *pResp, uint16_t respLen, unpack_swidms_SLQSSwiDmsSetUsbNetNum_t *pOutput)
- int pack_swidms_SLQSSwiDmsSetMTU (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_swidms_SLQSSwiDmsSetMTU_t *reqArg)
- int unpack_swidms_SLQSSwiDmsSetMTU (uint8_t *pResp, uint16_t respLen, unpack_swidms_SLQSSwiDmsSetMTU_t *pOutput)
- int pack_swidms_SLQSSwiDmsGetMTU (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_swidms_SLQSSwiDmsGetMTU (uint8_t *pResp, uint16_t respLen, unpack_swidms_SLQSSwiDmsGetMTU_t *pOutput)
- int pack_swidms_SLQSSwiDmsGetUsbComp (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_swidms_SLQSSwiDmsGetUsbComp (uint8_t *pResp, uint16_t respLen, unpack_swidms_SLQSSwiDmsGetUsbComp_t *pOutput)
- int pack_swidms_SLQSSwiDmsSetUsbComp (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_swidms_SLQSSwiDmsSetUsbComp_t *reqArg)
- int unpack_swidms_SLQSSwiDmsSetUsbComp (uint8_t *pResp, uint16_t respLen, unpack_swidms_SLQSSwiDmsSetUsbComp_t *pOutput)
- int pack_swidms_SLQSSwiDmsGetHWWatchdog (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_swidms_SLQSSwiDmsGetHWWatchdog (uint8_t *pResp, uint16_t respLen, unpack_swidms_SLQSSwiDmsGetHWWatchdog_t *pOutput)
- int pack_swidms_SLQSSwiDmsSetHWWatchdog (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_swidms_SLQSSwiDmsSetHWWatchdog_t *reqArg)
- int unpack_swidms_SLQSSwiDmsSetHWWatchdog (uint8_t *pResp, uint16_t respLen, unpack_swidms_SLQSSwiDmsSetHWWatchdog_t *pOutput)
- int pack_swidms_SLQSSwiDmsGetSecureInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_swidms_SLQSSwiDmsGetSecureInfo (uint8_t *pResp, uint16_t respLen, unpack_swidms_SLQSSwiDmsGetSecureInfo_t *pOutput)

9.58.1 Typedef Documentation

9.58.1.1 typedef unpack_result_t unpack_swidms_SLQSSwiDmsSetUsbNetNum_t

9.58.2 Function Documentation

9.58.2.1 int pack_swidms_SLQSSwiDmsGetHWWatchdog (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets the hardware watchdog settings pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.2 int pack_swidms_SLQSSwiDmsGetMTU (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Get the preferred MTU Size of the 3GPP, HRPD, EHRPD and USB descriptor Interfaces pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.3 int pack_swidms_SLQSSwiDmsGetSecureInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

pack function to get secure boot config and other capabilities

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.4 int pack_swidms_SLQSSwiDmsGetUsbComp (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets the usb interface composition pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.5 int pack_swidms_SLQSSwiDmsGetUsbNetNum (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

pack function to get usb net numbers for QMAP configuration

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.6 int pack_swidms_SLQSSwiDmsSetHWWatchdog (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_swidms_SLQSSwiDmsSetHWWatchdog_t * reqArg)

Sets the usb interface config value pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values.

9.58.2.7 int pack_swidms_SLQSSwiDmsSetMTU (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_swidms_SLQSSwiDmsSetMTU_t * reqArg)

Sets the preferred MTU size for 3GPP, HRPD, EHRPD Interfaces pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.8 int pack_swidms_SLQSSwiDmsSetUsbComp (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_swidms_SLQSSwiDmsSetUsbComp_t * *reqArg*)

Sets the usb interface config value pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values. This setting will be effective after modem reboot

9.58.2.9 int pack_swidms_SLQSSwiDmsSetUsbNetNum (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_swidms_SLQSSwiDmsSetUsbNetNum_t * *pReqParam*)

pack function to set usb net numbers for QMAP configuration

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request params

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.10 int unpack_swidms_SLQSSwiDmsGetHWWatchdog (uint8_t * *pResp*, uint16_t *respLen*, unpack_swidms_SLQSSwiDmsGetHWWatchdog_t * *pOutput*)

Gets the hardware watchdog settings unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.11 int unpack_swidms_SLQSSwiDmsGetMTU (uint8_t * *pResp*, uint16_t *respLen*, unpack_swidms_SLQSSwiDmsGetMTU_t * *pOutput*)

Get the MTU Size of the 3GPP, HRPD, EHRPD and USB descriptor Interfaces unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.12 int unpack_swidms_SLQSSwiDmsGetSecureInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_swidms_SLQSSwiDmsGetSecureInfo_t * *pOutput*)

unpack function to get secure boot config

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.13 int unpack_swidms_SLQSSwiDmsGetUsbComp (uint8_t * *pResp*, uint16_t *respLen*, unpack_swidms_SLQSSwiDmsGetUsbComp_t * *pOutput*)

Gets the usb interface composition unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.14 int unpack_swidms_SLQSSwiDmsGetUsbNetNum (uint8_t * *pResp*, uint16_t *respLen*, unpack_swidms_SLQSSwiDmsGetUsbNetNum_t * *pOutput*)

unpack function to get usb net numbers for QMAP configuration

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.15 int unpack_swidms_SLQSSwiDmsSetHWWatchdog (uint8_t * *pResp*, uint16_t *respLen*, unpack_swidms_SLQSSwiDmsSetHWWatchdog_t * *pOutput*)

Sets the hardware watchdog settings value unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values. This setting will be effective after modem reboot

9.58.2.16 int unpack_swidms_SLQSSwiDmsSetMTU (uint8_t * *pResp*, uint16_t *respLen*, unpack_swidms_SLQSSwiDmsSetMTU_t * *pOutput*)

Sets preferred MTU size for 3GPP, HRPD, EHRPD Interfaces unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.58.2.17 int unpack_swidms_SLQSSwiDmsSetUsbComp (uint8_t * *pResp*, uint16_t *respLen*, unpack_swidms_SLQSSwiDmsSetUsbComp_t * *pOutput*)

Sets the usb interface config value unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values. This setting will be effective after modem reboot

9.58.2.18 int unpack_swidms_SLQSSwiDmsSetUsbNetNum (uint8_t * *pResp*, uint16_t *respLen*, unpack_swidms_SLQSSwiDmsSetUsbNetNum_t * *pOutput*)

unpack function to set usb net numbers for QMAP configuration

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.59 swiloc.h File Reference

Data Structures

- struct unpack_swiloc_SwiLocGetAutoStart_t
- struct pack_swiloc_SwiLocSetAutoStart_t

Typedefs

- typedef unpack_result_t unpack_swiloc_SwiLocSetAutoStart_t

Functions

- int pack_swiloc_SwiLocGetAutoStart (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen)
- int unpack_swiloc_SwiLocGetAutoStart (uint8_t ∗pResp, uint16_t respLen, unpack_swiloc_SwiLocGetAutoStart_t ∗pOutput)
- int pack_swiloc_SwiLocSetAutoStart (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_swiloc_SwiLocSetAutoStart_t ∗reqArg)
- int unpack_swiloc_SwiLocSetAutoStart (uint8_t ∗pResp, uint16_t respLen, unpack_swiloc_SwiLocSetAutoStart_t ∗pOutput)

9.59.1 Typedef Documentation

9.59.1.1 typedef unpack_result_t unpack_swiloc_SwiLocSetAutoStart_t

9.59.2 Function Documentation

9.59.2.1 int pack_swiloc_SwiLocGetAutoStart (pack_qmi_t ∗ *pCtx,* uint8_t ∗ *pReqBuf,* uint16_t ∗ *pLen*)

Get Auto Start pack

Parameters

in	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.59.2.2 int pack_swiloc_SwiLocSetAutoStart (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_swiloc_SwiLocSetAutoStart_t * *reqArg*)

Set Auto Start pack

Parameters

in	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.59.2.3 int unpack_swiloc_SwiLocGetAutoStart (uint8_t * *pResp*, uint16_t *respLen*, unpack_swiloc_SwiLocGetAutoStart_t * *pOutput*)

Get Auto Start unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.59.2.4 int unpack_swiloc_SwiLocSetAutoStart (uint8_t * *pResp*, uint16_t *respLen*, unpack_swiloc_SwiLocSetAutoStart_t * *pOutput*)

Set Auto Start unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.60 swioma.h File Reference

Data Structures

- struct pack_swioma_SLQSOMADMStartSession_t
- struct unpack_swioma_SLQSOMADMStartSession_t
- struct pack_swioma_SLQSOMADMCancelSession_t
- struct unpack_swioma_SLQSOMADMGetSettings_t
- struct pack_swioma_SLQSOMADMSetSettings_t
- struct pack_swioma_SLQSOMADMSendSelection_t
- struct pack_swioma_SLQSOMADMGetSessionInfo_t
- struct unpack_swioma_SLQSOMADMGetSessionInfo_t
- struct unpack_omaDmFotaTlv_t
- struct unpack_omaDmConfigTlv_t
- struct unpack_omaDmNotificationsTlv_t
- struct unpack_swioma_SLQSOMADMAlertCallback_ind_t

Macros

- #define LITEQMI_MAX_SWIOMA_STR_LEN 255

Typedefs

- typedef unpack_result_t unpack_swioma_SLQSOMADMCancelSession_t
- typedef unpack_result_t unpack_swioma_SLQSOMADMSetSettings_t
- typedef unpack_result_t unpack_swioma_SLQSOMADMSendSelection_t
- typedef unpack_result_t unpack_swioma_SLQSOMADMAlertCallback_t

Functions

- int pack_swioma_SLQSOMADMStartSession (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_swioma_SLQSOMADMStartSession_t reqParam)
- int unpack_swioma_SLQSOMADMStartSession (uint8_t ∗pResp, uint16_t respLen, unpack_swioma_SLQSOMADMStartSession_t ∗pOutput)
- int pack_swioma_SLQSOMADMCancelSession (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_swioma_SLQSOMADMCancelSession_t reqParam)
- int unpack_swioma_SLQSOMADMCancelSession (uint8_t ∗pResp, uint16_t respLen, unpack_swioma_SLQSOMADMCancelSession_t ∗pOutput)
- int pack_swioma_SLQSOMADMGetSettings (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen)
- int unpack_swioma_SLQSOMADMGetSettings (uint8_t ∗pResp, uint16_t respLen, unpack_swioma_SLQSOMADMGetSettings_t ∗pOutput)
- int pack_swioma_SLQSOMADMSetSettings (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_swioma_SLQSOMADMSetSettings_t reqParam)
- int unpack_swioma_SLQSOMADMSetSettings (uint8_t ∗pResp, uint16_t respLen, unpack_swioma_SLQSOMADMSetSettings_t ∗pOutput)
- int pack_swioma_SLQSOMADMSendSelection (pack_qmi_t ∗pCtx, uint8_t ∗pReqBuf, uint16_t ∗pLen, pack_swioma_SLQSOMADMSendSelection_t reqParam)
- int unpack_swioma_SLQSOMADMSendSelection (uint8_t ∗pResp, uint16_t respLen, unpack_swioma_SLQSOMADMSendSelection_t ∗pOutput)

- int pack_swioma_SLQSOMADMGetSessionInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_swioma_SLQSOMADMGetSessionInfo_t reqParam)
- int unpack_swioma_SLQSOMADMGetSessionInfo (uint8_t *pResp, uint16_t respLen, unpack_swioma_SLQSOMADMGetSessionInfo_t *pOutput)
- int pack_swioma_SLQSOMADMAlertCallback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_swioma_SLQSOMADMAlertCallback (uint8_t *pResp, uint16_t respLen, unpack_swioma_SLQSOMADMAlertCallback_t *pOutput)
- int unpack_swioma_SLQSOMADMAlertCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_swioma_SLQSOMADMAlertCallback_ind_t *pOutput)

9.60.1 Macro Definition Documentation

9.60.1.1 #define LITEQMI_MAX_SWIOMA_STR_LEN 255

9.60.2 Typedef Documentation

9.60.2.1 typedef unpack_result_t unpack_swioma_SLQSOMADMAlertCallback_t

9.60.2.2 typedef unpack_result_t unpack_swioma_SLQSOMADMCancelSession_t

9.60.2.3 typedef unpack_result_t unpack_swioma_SLQSOMADMSendSelection_t

9.60.2.4 typedef unpack_result_t unpack_swioma_SLQSOMADMSetSettings_t

9.60.3 Function Documentation

9.60.3.1 int pack_swioma_SLQSOMADMAlertCallback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Function to pack QMI command to enable the SWIOMADM network-initiated alert callback function. This maps to SetSLQSOMADMAlertCallback

Parameters

pCtx	[out] • See pack_qmi_t for more information
pReqBuf	[in,out] • Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
pLen	[in,out] • On input, size of pReqBuf • On ouptut, number of bytes actually packed

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.60.3.2 int pack_swioma_SLQSOMADMCancelSession (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_swioma_SLQSOMADMCancelSession_t *reqParam*)

Function to pack cancel OMA-DM session command This maps to SLQSOMADMCancelSession

Parameters

pCtx	[out] • See pack_qmi_t for more information
pReqBuf	[in,out] • Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
pLen	[in,out] • On input, size of pReqBuf • On output, number of bytes actually packed
reqParam	[in] • See pack_swioma_SLQSOMADMCancelSession_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.60.3.3 int pack_swioma_SLQSOMADMGetSessionInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_swioma_SLQSOMADMGetSessionInfo_t *reqParam*)

Function to pack QMI command to return information related to the current (or previous if no session is active) OMA-DM session. This maps to SLQSOMADMGetSessionInfo

Parameters

pCtx	[out] • See pack_qmi_t for more information
pReqBuf	[in,out] • Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
pLen	[in,out] • On input, size of pReqBuf • On ouptut, number of bytes actually packed
reqParam	[in] • See pack_swioma_SLQSOMADMGetSessionInfo_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.60.3.4 int pack_swioma_SLQSOMADMGetSettings (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Function to pack command to retrieve the OMA-DM settings from the device. This maps to SLQSOMADMGetSettings2

Parameters

pCtx	[out] • See pack_qmi_t for more information
pReqBuf	[in,out] • Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
pLen	[in,out] • On input, size of pReqBuf • On output, number of bytes actually packed

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.60.3.5 int pack_swioma_SLQSOMADMSendSelection (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_swioma_SLQSOMADMSendSelection_t *reqParam*)

Function to pack OMA-DM send selection command This maps to SLQSOMADMSendSelection2

Parameters

pCtx	[out] • See pack_qmi_t for more information

pReqBuf	[in,out] • Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
pLen	[in,out] • On input, size of pReqBuf • On ouptut, number of bytes actually packed
reqParam	[in] • See pack_swioma_SLQSOMADMSendSelection_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.60.3.6 int pack_swioma_SLQSOMADMSetSettings (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_swioma_SLQSOMADMSetSettings_t *reqParam*)

Function to pack OMA-DM set settings command This maps to SLQSOMADMSetSettings3

Parameters

pCtx	[out] • See pack_qmi_t for more information
pReqBuf	[in,out] • Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
pLen	[in,out] • On input, size of pReqBuf • On ouptut, number of bytes actually packed
reqParam	[in] • See pack_swioma_SLQSOMADMSetSettings_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.60.3.7 int pack_swioma_SLQSOMADMStartSession (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_swioma_SLQSOMADMStartSession_t *reqParam*)

Function to pack Start OMA-DM session command This maps to SLQSOMADMStartSession2

Parameters

pCtx	[out] • See pack_qmi_t for more information
pReqBuf	[in,out] • Buffer for packed QMI command to be provided by the host application • Minimum expected size is 2048 bytes
pLen	[in,out] • On input, size of pReqBuf • On ouptut, number of bytes actually packed
reqParam	[in] • See pack_swioma_SLQSOMADMStartSession_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

Timeout: 20 seconds

9.60.3.8 int unpack_swioma_SLQSOMADMAlertCallback (uint8_t * *pResp*, uint16_t *respLen*, unpack_swioma_SLQSOMADMAlertCallback_t * *pOutput*)

Function to unpack response of QMI command to enable the SWIOMADM network-initiated alert callback function. This maps to SetSLQSOMADMAlertCallback

Parameters

pResp	[in] • Response from modem
respLen	[in] • Length of pResp from modem
pOutput	[out] • response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

- Please use eQMI_SWIOMA_EVENT_IND indication to identify this event from SWIOMA service read function

9.60.3.9 int unpack_swioma_SLQSOMADMAlertCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_swioma_SLQSOMADMAlertCallback_ind_t * *pOutput*)

Function to unpack SWIOMADM alert indications This maps to SetSLQSOMADMAlertCallback

Parameters

pResp	[in] • Response from modem
respLen	[in] • Length of pResp from modem
pOutput	[out] • See unpack_swioma_SLQSOMADMAlertCallback_ind_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.60.3.10 int unpack_swioma_SLQSOMADMCancelSession (uint8_t * *pResp*, uint16_t *respLen*, unpack_swioma_SLQSOMADMCancelSession_t * *pOutput*)

Function to pack cancel OMA-DM session command This maps to SLQSOMADMCancelSession

Parameters

pResp	[in] • Response from modem
respLen	[in] • Length of pResp from modem
pOutput	[out] • response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.60.3.11 int unpack_swioma_SLQSOMADMGetSessionInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_swioma_SLQSOMADMGetSessionInfo_t * *pOutput*)

Function to unpack information related to the current (or previous if no session is active) OMA-DM session. This maps to SLQSOMADMGetSessionInfo

Parameters

pResp	[in] • Response from modem
respLen	[in] • Length of pResp from modem
pOutput	[out] • See unpack_swioma_SLQSOMADMGetSessionInfo_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.60.3.12 int unpack_swioma_SLQSOMADMGetSettings (uint8_t * *pResp*, uint16_t *respLen*, unpack_swioma_SLQSOMADMGetSettings_t * *pOutput*)

Function to unpack OMA-DM get settings response from modem This maps to SLQSOMADMGetSettings2

Parameters

pResp	[in] • Response from modem
respLen	[in] • Length of pResp from modem
pOutput	[out] • See unpack_swioma_SLQSOMADMGetSettings_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.60.3.13 int unpack_swioma_SLQSOMADMSendSelection (uint8_t * *pResp*, uint16_t *respLen*, unpack_swioma_SLQSOMADMSendSelection_t * *pOutput*)

Function to unpack OMA-DM send selection command This maps to SLQSOMADMSendSelection2

Parameters

pResp	[in] • Response from modem
respLen	[in] • Length of pResp from modem
pOutput	[out] • response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.60.3.14 int unpack_swioma_SLQSOMADMSetSettings (uint8_t * *pResp*, uint16_t *respLen*, unpack_swioma_SLQSOMADMSetSettings_t * *pOutput*)

Function to unpack OMA-DM set settings command This maps to SLQSOMADMSetSettings3

Parameters

pResp	[in] • Response from modem
respLen	[in] • Length of pResp from modem
pOutput	[out] • response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.60.3.15 int unpack_swioma_SLQSOMADMStartSession (uint8_t * *pResp*, uint16_t *respLen*, unpack_swioma_SLQSOMADMStartSession_t * *pOutput*)

Function to unpack Start OMA-DM session response from modem This maps to SLQSOMADMStartSession2

Parameters

pResp	[in] • Response from modem
respLen	[in] • Length of pResp from modem
pOutput	[out] • See unpack_swioma_SLQSOMADMStartSession_t for more information

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.61 switype_256bit.h File Reference

Data Structures

- struct swi_uint256_t

Macros

- #define SWI_UINT256_WORD_COUNT 16
- #define SWI_UINT256_BITS_PER_WORD 16
- #define SWI_UINT256_WORD_OFFSET(val) ((val) / SWI_UINT256_BITS_PER_WORD)
- #define SWI_UINT256_BIT_OFFSET(val) ((val) % SWI_UINT256_BITS_PER_WORD)
- #define SWI_UINT256_INT_VALUE {{0}}

Functions

- void swi_uint256_set_bit (swi_uint256_t *pMask, uint8_t bit)
- void swi_uint256_clear_bit (swi_uint256_t *pMask, uint8_t bit)
- uint8_t swi_uint256_get_bit (swi_uint256_t Mask, uint8_t bit)
- void swi_uint256_print_mask (swi_uint256_t mask)

9.61.1 Macro Definition Documentation

9.61.1.1 #define SWI_UINT256_BIT_OFFSET(*val*) ((val) % SWI_UINT256_BITS_PER_WORD)

9.61.1.2 #define SWI_UINT256_BITS_PER_WORD 16

9.61.1.3 #define SWI_UINT256_INT_VALUE {{0}}

9.61.1.4 #define SWI_UINT256_WORD_COUNT 16

9.61.1.5 #define SWI_UINT256_WORD_OFFSET(*val*) ((val) / SWI_UINT256_BITS_PER_WORD)

9.61.2 Function Documentation

9.61.2.1 void swi_uint256_clear_bit (swi_uint256_t * *pMask,* uint8_t *bit*)

Clear relevant bit in provided mask

Parameters

in	*pMask*	Pointer to bitmask
in	*bit*	Bit to clear

9.61.2.2 uint8_t swi_uint256_get_bit (swi_uint256_t *Mask,* uint8_t *bit*)

Get relevant bit from provided mask

Parameters

in	*Mask*	Bit mask
in	*bit*	Bit to extract

Returns

Bit value

- 0 - bit is not set
- 1 - bit is set

9.61.2.3 void swi_uint256_print_mask (swi_uint256_t *mask*)

Print the log mask to syslog. Use only for debugging

Parameters

in	*mask*	Bit mask

9.61.2.4 void swi_uint256_set_bit (swi_uint256_t * *pMask,* uint8_t *bit*)

Set relevant bit in provided mask

Parameters

in	*pMask*	Pointer to bit mask
in	*bit*	Bit to set

9.62 SWIWWANCMAPI.h File Reference

9.63 uim.h File Reference

Data Structures

- struct uim_appStatus
- struct uim_slotInfo
- struct uim_cardStatus
- struct uim_hotSwapStatus
- struct uim_validCardStatus
- struct uim_simBusyStatus
- struct unpack_uim_GetCardStatus_t
- struct unpack_uim_GetCardStatusV2_t
- struct uim_encryptedPIN1
- struct uim_remainingRetries
- struct uim_sessionInformation
- struct uim_verifyUIMPIN
- struct uim_unblockUIMPIN
- struct uim_cardResult
- struct uim_setPINProtection
- struct uim_changeUIMPIN
- struct uim_fileInfo
- struct uim_UIMSessionInformation
- struct uim_readTransparentInfo
- struct uim_readResult
- struct pack_uim_VerifyPin_t
- struct unpack_uim_VerifyPin_t
- struct pack_uim_UnblockPin_t
- struct unpack_uim_UnblockPin_t
- struct unpack_uim_UnblockPinV2_t
- struct pack_uim_SetPinProtection_t
- struct unpack_uim_SetPinProtection_t
- struct pack_uim_ChangePin_t
- struct unpack_uim_ChangePin_t
- struct pack_uim_ReadTransparent_t
- struct unpack_uim_ReadTransparent_t
- struct pack_uim_SLQSUIMEventRegister_t
- struct unpack_uim_SLQSUIMEventRegister_t
- struct appStats
- struct slotInf
- struct unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t
- struct slot_t
- struct slots_t
- struct unpack_uim_SLQSUIMGetSlotsStatus_t
- struct pack_uim_SLQSUIMSwitchSlot_t
- struct unpack_uim_SetUimSlotStatusChangeCallback_ind_t
- struct pack_uim_SLQSUIMPowerUp_t
- struct pack_uim_SLQSUIMPowerDown_t
- struct pack_uim_SLQSUIMRefreshOK_t
- struct uim_registerRefresh
- struct pack_uim_SLQSUIMRefreshRegister_t
- struct pack_uim_SLQSUIMRefreshComplete_t
- struct uim_refreshevent
- struct pack_uim_SLQSUIMRefreshGetLastEvent_t
- struct unpack_uim_SLQSUIMRefreshGetLastEvent_t

- struct pack_uim_SLQSUIMGetFileAttributes_t
- struct uim_fileAttributes
- struct unpack_uim_SLQSUIMGetFileAttributes_t
- struct uim_depersonalizationInformation
- struct pack_uim_SLQSUIMDepersonalization_t
- struct unpack_uim_SLQSUIMDepersonalization_t
- struct uim_authenticationData
- struct pack_uim_SLQSUIMAuthenticate_t
- struct uim_authenticateResult
- struct unpack_uim_SLQSUIMAuthenticate_t
- struct uim_personalizationStatus
- struct pack_uim_SLQSUIMGetConfiguration_t
- struct unpack_uim_SLQSUIMGetConfiguration_t
- struct unpack_uim_SLQSUIMRefreshCallback_Ind_t

Macros

- #define UIM_UINT8_MAX_STRING_SZ 255
- #define UIM_MAX_DESCRIPTION_LENGTH 255
- #define UIM_MAX_NO_OF_SLOTS 5
- #define UIM_MAX_NO_OF_APPLICATIONS 10
- #define MAX_NO_OF_SLOTS 5
- #define MAX_NO_OF_APPLICATIONS 10
- #define MAX_DESCRIPTION_LENGTH 255
- #define MAX_SLOTS_STATUS 255
- #define MAX_ICCID_LENGTH 255
- #define UIM_MAX_CONTENT_LENGTH 1024
- #define UIM_MAX_ACTIVE_PERS_FEATURES 12

Typedefs

- typedef unpack_result_t unpack_uim_SLQSUIMSwitchSlot_t
- typedef unpack_result_t unpack_uim_SLQSUIMPowerUp_t
- typedef unpack_result_t unpack_uim_SLQSUIMPowerDown_t
- typedef unpack_result_t unpack_uim_SLQSUIMReset_t
- typedef unpack_result_t unpack_uim_SLQSUIMRefreshOK_t
- typedef unpack_result_t unpack_uim_SLQSUIMRefreshRegister_t
- typedef unpack_result_t unpack_uim_SLQSUIMRefreshComplete_t

Functions

- int pack_uim_GetCardStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, void *reqArg)
- int unpack_uim_GetCardStatus (uint8_t *pResp, uint16_t respLen, unpack_uim_GetCardStatus_t *pOutput)
- int unpack_uim_GetCardStatusV2 (uint8_t *pResp, uint16_t respLen, unpack_uim_GetCardStatusV2_t *pOutput)
- int pack_uim_VerifyPin (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_VerifyPin_t *reqArg)
- int unpack_uim_VerifyPin (uint8_t *pResp, uint16_t respLen, unpack_uim_VerifyPin_t *pOutput)
- int pack_uim_UnblockPin (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_UnblockPin_t *reqArg)
- int unpack_uim_UnblockPin (uint8_t *pResp, uint16_t respLen, unpack_uim_UnblockPin_t *pOutput)
- int unpack_uim_UnblockPinV2 (uint8_t *pResp, uint16_t respLen, unpack_uim_UnblockPinV2_t *pOutput)

- int pack_uim_SetPinProtection (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SetPinProtection_t *reqArg)
- int unpack_uim_SetPinProtection (uint8_t *pResp, uint16_t respLen, unpack_uim_SetPinProtection_t *pOutput)
- int pack_uim_ChangePin (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_ChangePin_t *reqArg)
- int unpack_uim_ChangePin (uint8_t *pResp, uint16_t respLen, unpack_uim_ChangePin_t *pOutput)
- int pack_uim_ReadTransparent (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_ReadTransparent_t *reqArg)
- int unpack_uim_ReadTransparent (uint8_t *pResp, uint16_t respLen, unpack_uim_ReadTransparent_t *pOutput)
- int pack_uim_SLQSUIMEventRegister (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMEventRegister_t *reqArg)
- int unpack_uim_SLQSUIMEventRegister (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMEventRegister_t *pOutput)
- int unpack_uim_SLQSUIMSetStatusChangeCallBack_ind (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t *pOutput)
- int pack_uim_SLQSUIMGetSlotsStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_uim_SLQSUIMGetSlotsStatus (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMGetSlotsStatus_t *pOutput)
- int pack_uim_SLQSUIMSwitchSlot (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMSwitchSlot_t *reqArg)
- int unpack_uim_SLQSUIMSwitchSlot (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMSwitchSlot_t *pOutput)
- int unpack_uim_SetUimSlotStatusChangeCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_uim_SetUimSlotStatusChangeCallback_ind_t *pOutput)
- int pack_uim_SLQSUIMPowerUp (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMPowerUp_t *reqArg)
- int unpack_uim_SLQSUIMPowerUp (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMPowerUp_t *pOutput)
- int pack_uim_SLQSUIMPowerDown (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMPowerDown_t *reqArg)
- int unpack_uim_SLQSUIMPowerDown (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMPowerDown_t *pOutput)
- int pack_uim_SLQSUIMReset (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_uim_SLQSUIMReset (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMReset_t *pOutput)
- int pack_uim_SLQSUIMRefreshOK (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMRefreshOK_t *reqArg)
- int unpack_uim_SLQSUIMRefreshOK (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMRefreshOK_t *pOutput)
- int pack_uim_SLQSUIMRefreshRegister (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMRefreshRegister_t *reqArg)
- int unpack_uim_SLQSUIMRefreshRegister (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMRefreshRegister_t *pOutput)
- int pack_uim_SLQSUIMRefreshComplete (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMRefreshComplete_t *reqArg)
- int unpack_uim_SLQSUIMRefreshComplete (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMRefreshComplete_t *pOutput)
- int pack_uim_SLQSUIMRefreshGetLastEvent (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMRefreshGetLastEvent_t *reqArg)
- int unpack_uim_SLQSUIMRefreshGetLastEvent (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMRefreshGetLastEvent_t *pOutput)
- int pack_uim_SLQSUIMGetFileAttributes (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMGetFileAttributes_t *reqArg)
- int unpack_uim_SLQSUIMGetFileAttributes (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMGetFileAttributes_t *pOutput)

- int pack_uim_SLQSUIMDepersonalization (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMDepersonalization_t *reqArg)
- int unpack_uim_SLQSUIMDepersonalization (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMDepersonalization_t *pOutput)
- int pack_uim_SLQSUIMAuthenticate (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMAuthenticate_t *reqArg)
- int unpack_uim_SLQSUIMAuthenticate (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMAuthenticate_t *pOutput)
- int pack_uim_SLQSUIMGetConfiguration (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_uim_SLQSUIMGetConfiguration_t *reqArg)
- int unpack_uim_SLQSUIMGetConfiguration (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMGetConfiguration_t *pOutput)
- int unpack_uim_SLQSUIMRefreshCallback_Ind (uint8_t *pResp, uint16_t respLen, unpack_uim_SLQSUIMRefreshCallback_Ind_t *pOutput)

9.63.1 Macro Definition Documentation

9.63.1.1 #define MAX_DESCRIPTION_LENGTH 255

9.63.1.2 #define MAX_ICCID_LENGTH 255

9.63.1.3 #define MAX_NO_OF_APPLICATIONS 10

9.63.1.4 #define MAX_NO_OF_SLOTS 5

9.63.1.5 #define MAX_SLOTS_STATUS 255

9.63.1.6 #define UIM_MAX_ACTIVE_PERS_FEATURES 12

9.63.1.7 #define UIM_MAX_CONTENT_LENGTH 1024

9.63.1.8 #define UIM_MAX_DESCRIPTION_LENGTH 255

9.63.1.9 #define UIM_MAX_NO_OF_APPLICATIONS 10

9.63.1.10 #define UIM_MAX_NO_OF_SLOTS 5

9.63.1.11 #define UIM_UINT8_MAX_STRING_SZ 255

9.63.2 Typedef Documentation

9.63.2.1 typedef unpack_result_t unpack_uim_SLQSUIMPowerDown_t

9.63.2.2 typedef unpack_result_t unpack_uim_SLQSUIMPowerUp_t

9.63.2.3 typedef unpack_result_t unpack_uim_SLQSUIMRefreshComplete_t

9.63.2.4 typedef unpack_result_t unpack_uim_SLQSUIMRefreshOK_t

9.63.2.5 typedef unpack_result_t unpack_uim_SLQSUIMRefreshRegister_t

9.63.2.6 typedef unpack_result_t unpack_uim_SLQSUIMReset_t

9.63.2.7 typedef unpack_result_t unpack_uim_SLQSUIMSwitchSlot_t

9.63.3 Function Documentation

9.63.3.1 int pack_uim_ChangePin (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_uim_ChangePin_t * reqArg)

Change Pin pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.2 int pack_uim_GetCardStatus (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, void * reqArg)

Get Card Status pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.3 int pack_uim_ReadTransparent (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_uim_ReadTransparent_t * reqArg)

SLQS ReadTransparent pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.4 int pack_uim_SetPinProtection (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SetPinProtection_t * *reqArg*)

Set Pin Protection pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.5 int pack_uim_SLQSUIMAuthenticate (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMAuthenticate_t * *reqArg*)

Send a security command to the card pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.6 int pack_uim_SLQSUIMDepersonalization (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMDepersonalization_t * *reqArg*)

De-activates or unblocks the personalization on the phone pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.7 int pack_uim_SLQSUIMEventRegister (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMEventRegister_t * *reqArg*)

UIM Status Change callback enable pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.8 int pack_uim_SLQSUIMGetConfiguration (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMGetConfiguration_t * *reqArg*)

Gets the modem configuration for the UIM module pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.9 int pack_uim_SLQSUIMGetFileAttributes (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMGetFileAttributes_t * *reqArg*)

Retrieves the file attributes for any EF(Elementary File) or DF(Dedicated File) in the card and provides access by the path pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.10 int pack_uim_SLQSUIMGetSlotsStatus (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Pack get slots status.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.11 int pack_uim_SLQSUIMPowerDown (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMPowerDown_t * *reqArg*)

Powers down the card pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.12 int pack_uim_SLQSUIMPowerUp (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMPowerUp_t * *reqArg*)

Powers up the card pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.13 int pack_uim_SLQSUIMRefreshComplete (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMRefreshComplete_t * *reqArg*)

Enables the terminal response to be sent to the card When the client finished Refresh procedure pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.14 int pack_uim_SLQSUIMRefreshGetLastEvent (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMRefreshGetLastEvent_t * *reqArg*)

Retrieve the last refresh event pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.15 int pack_uim_SLQSUIMRefreshOK (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMRefreshOK_t * *reqArg*)

Enables the client to indicate whether it is OK to start the Refresh procedure pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.16 int pack_uim_SLQSUIMRefreshRegister (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMRefreshRegister_t * *reqArg*)

Registers for file change notifications triggered by the card pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.17 int pack_uim_SLQSUIMReset (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Resets the issuing control points state kept by the service pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.18 int pack_uim_SLQSUIMSwitchSlot (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_SLQSUIMSwitchSlot_t * *reqArg*)

switch slot pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.19 int pack_uim_UnblockPin (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_UnblockPin_t * *reqArg*)

Unblock Pin pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.20 int pack_uim_VerifyPin (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_uim_VerifyPin_t * *reqArg*)

Verify Pin Status pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.21 int unpack_uim_ChangePin (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_ChangePin_t * *pOutput*)

Change Pin unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.22 int unpack_uim_GetCardStatus (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_GetCardStatus_t * *pOutput*)

Get Card Status unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.23 int unpack_uim_GetCardStatusV2 (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_GetCardStatusV2_t** * *pOutput*)

Get Card Status unpack V2

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.24 int unpack_uim_ReadTransparent (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_ReadTransparent_t** * *pOutput*)

SLQS ReadTransparent unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.25 int unpack_uim_SetPinProtection (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_SetPinProtection_t** * *pOutput*)

Set Pin Protection unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.26 int unpack_uim_SetUimSlotStatusChangeCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SetUimSlotStatusChangeCallback_ind_t * *pOutput*)

UIM Slot Status Change indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

use pack_uim_SLQSUIMEventRegister to subscribe

9.63.3.27 int unpack_uim_SLQSUIMAuthenticate (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIM-Authenticate_t * *pOutput*)

Unpack the status code received from the card when card responded to the read request

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.28 int unpack_uim_SLQSUIMDepersonalization (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIMDepersonalization_t * *pOutput*)

De-activates or unblocks the personalization on the phone unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.29 int unpack_uim_SLQSUIMEventRegister (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIMEvent-Register_t * *pOutput*)

UIM Status Change callback enable unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.30 int unpack_uim_SLQSUIMGetConfiguration (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIMGetConfiguration_t * *pOutput*)

Gets the modem configuration for the UIM module unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.31 int unpack_uim_SLQSUIMGetFileAttributes (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIMGetFileAttributes_t * *pOutput*)

Retrieves the file attributes for any EF(Elementary File) or DF(Dedicated File) in the card and provides access by the path unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.32 int unpack_uim_SLQSUIMGetSlotsStatus (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIMGetSlotsStatus_t * *pOutput*)

get slot status unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.33 int unpack_uim_SLQSUIMPowerDown (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIMPowerDown_t * *pOutput*)

Powers down the card unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.34 int unpack_uim_SLQSUIMPowerUp (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_SLQSUIMPowerUp_t** * *pOutput*)

Powers up the card unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.35 int unpack_uim_SLQSUIMRefreshCallback_Ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_SLQSUIMRefreshCallback_Ind_t** * *pOutput*)

Unpack UIM refresh event indication.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.36 int unpack_uim_SLQSUIMRefreshComplete (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_SLQSUIMRefreshComplete_t** * *pOutput*)

Enables the terminal response to be sent to the card When the client finished Refresh procedure unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.37 int unpack_uim_SLQSUIMRefreshGetLastEvent (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIMRefreshGetLastEvent_t * *pOutput*)

Retrieve the last refresh event unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.38 int unpack_uim_SLQSUIMRefreshOK (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIMRefreshOK_t * *pOutput*)

Enables the client to indicate whether it is OK to start the Refresh procedure unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.39 int unpack_uim_SLQSUIMRefreshRegister (uint8_t * *pResp*, uint16_t *respLen*, unpack_uim_SLQSUIMRefreshRegister_t * *pOutput*)

Registers for file change notifications triggered by the card unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.40 int unpack_uim_SLQSUIMReset (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_SLQSUIMReset_t** * *pOutput*)

Resets the issuing control points state kept by the service unpack.

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.41 int unpack_uim_SLQSUIMSetStatusChangeCallBack_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t** * *pOutput*)

UIM Status Change indication unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

use pack_uim_SLQSUIMEventRegister to subscribe

9.63.3.42 int unpack_uim_SLQSUIMSwitchSlot (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_SLQSUIMSwitchSlot_t** * *pOutput*)

switch slot unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.43 int unpack_uim_UnblockPin (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_UnblockPin_t** * *pOutput*)

Unblock Pin unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.44 int unpack_uim_UnblockPinV2 (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_UnblockPinV2_t** * *pOutput*)

Unblock Pin unpack V2

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.63.3.45 int unpack_uim_VerifyPin (uint8_t * *pResp*, uint16_t *respLen*, **unpack_uim_VerifyPin_t** * *pOutput*)

Verify Pin unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64 voice.h File Reference

Data Structures

- struct voice_USSInfo
- struct pack_voice_OriginateUSSD_t
- struct pack_voice_AnswerUSSD_t
- struct voice_UUSInfo
- struct voice_CUGInfo
- struct voice_calledPartySubAdd
- struct pack_voice_SLQSVoiceDialCall_t
- struct voice_alphaIDInfo
- struct voice_ccSUPSType
- struct unpack_voice_SLQSVoiceDialCall_t
- struct pack_voice_SLQSVoiceEndCall_t
- struct unpack_voice_SLQSVoiceEndCall_t
- struct voice_callFwdTypeAndPlan
- struct pack_voice_SLQSVoiceSetSUPSService_t
- struct unpack_voice_SLQSVoiceSetSUPSService_t
- struct voice_airTimer
- struct voice_roamTimer
- struct voice_prefVoiceSO
- struct pack_voice_SLQSVoiceSetConfig_t
- struct unpack_voice_SLQSVoiceSetConfig_t
- struct pack_voice_SLQSVoiceAnswerCall_t
- struct unpack_voice_SLQSVoiceAnswerCall_t
- struct voice_CLIRResp
- struct unpack_voice_SLQSVoiceGetCLIR_t
- struct voice_CLIPResp
- struct unpack_voice_SLQSVoiceGetCLIP_t
- struct pack_voice_SLQSVoiceGetCallWaiting_t
- struct unpack_voice_SLQSVoiceGetCallWaiting_t
- struct pack_voice_SLQSVoiceGetCallBarring_t
- struct unpack_voice_SLQSVoiceGetCallBarring_t
- struct pack_voice_SLQSVoiceGetCallForwardingStatus_t
- struct voice_callFWInfo
- struct voice_callFWExtInfo
- struct voice_getCallFWInfo
- struct voice_getCallFWExtInfo
- struct unpack_voice_SLQSVoiceGetCallForwardingStatus_t

- struct pack_voice_SLQSVoiceSetCallBarringPassword_t
- struct unpack_voice_SLQSVoiceSetCallBarringPassword_t
- struct pack_voice_SLQSVoiceGetCallInfo_t
- struct voice_callInfo
- struct voice_remotePartyNum
- struct voice_remotePartyName
- struct voice_connectNumInfo
- struct voice_diagInfo
- struct unpack_voice_SLQSVoiceGetCallInfo_t
- struct voice_getAllCallInformation
- struct voice_getAllCallRmtPtyNum
- struct voice_getAllCallRmtPtyName
- struct voice_allCallsUUSInfo
- struct voice_allCallsAlphaIDInfo
- struct voice_allCallsDiagInfo
- struct voice_peerNumberInfo
- struct voice_arrCallInfo
- struct voice_arrRemotePartyNum
- struct voice_arrRemotePartyName
- struct voice_arrAlertingType
- struct voice_arrUUSInfo
- struct voice_arrSvcOption
- struct voice_arrCallEndReason
- struct voice_arrAlphaID
- struct voice_arrConnectPartyNum
- struct voice_arrDiagInfo
- struct voice_arrCalledPartyNum
- struct voice_arrRedirPartyNum
- struct voice_arrAlertingPattern
- struct unpack_voice_SLQSVoiceGetAllCallInfo_t
- struct pack_voice_SLQSVoiceManageCalls_t
- struct unpack_voice_SLQSVoiceManageCalls_t
- struct voice_burstDTMFInfo
- struct voice_DTMFLengths
- struct pack_voice_SLQSVoiceBurstDTMF_t
- struct unpack_voice_SLQSVoiceBurstDTMF_t
- struct pack_voice_SLQSVoiceStartContDTMF_t
- struct unpack_voice_SLQSVoiceStartContDTMF_t
- struct pack_voice_SLQSVoiceStopContDTMF_t
- struct unpack_voice_SLQSVoiceStopContDTMF_t
- struct pack_voice_SLQSVoiceSendFlash_t
- struct unpack_voice_SLQSVoiceSendFlash_t
- struct pack_voice_SLQSVoiceSetPreferredPrivacy_t
- struct pack_voice_SLQSVoiceIndicationRegister_t
- struct pack_voice_SLQSVoiceGetConfig_t
- struct voice_curAMRConfig
- struct unpack_voice_SLQSVoiceGetConfig_t
- struct pack_voice_SLQSVoiceOrigUSSDNoWait_t
- struct pack_voice_SLQSVoiceBindSubscription_t
- struct pack_voice_SLQSVoiceALSSetLineSwitching_t
- struct pack_voice_SLQSVoiceALSSelectLine_t
- struct voice_COLPResp
- struct unpack_voice_SLQSVoiceGetCOLP_t
- struct voice_COLRResp
- struct unpack_voice_SLQSVoiceGetCOLR_t

- struct voice_CNAPResp
- struct unpack_voice_SLQSVoiceGetCNAP_t
- struct pack_voice_SLQSOriginateUSSD_t
- struct unpack_voice_SLQSOriginateUSSD_t
- struct voice_USSDNotificationNetworkInfo
- struct unpack_voice_USSDNotificationCallback_ind_t
- struct voice_SUPSInfo
- struct voice_newPwdData
- struct unpack_voice_SLQSVoiceSUPSCallback_ind_t
- struct unpack_voice_allCallStatusCallback_ind_t
- struct unpack_voice_voicePrivacyChangeCallback_ind_t
- struct voice_DTMFInfo
- struct unpack_voice_DTMFEventCallback_ind_t
- struct voice_ECTNum
- struct unpack_voice_SUPSNotificationCallback_ind_t
- struct unpack_voice_OTASPStatusCallback_ind_t
- struct voice_signalInfo
- struct voice_callerIDInfo
- struct voice_callingPartyInfo
- struct voice_calledPartyInfo
- struct voice_redirNumInfo
- struct voice_NSSAudioCtrl
- struct voice_lineCtrlInfo
- struct voice_extDispRecInfo
- struct unpack_voice_VoiceInfoRecCallback_ind_t

Macros

- #define MAXVOICEUSSDLENGTH 182
- #define MAX_VOICE_CALL_NO_LEN 81
- #define MAX_VOICE_DESCRIPTION_LENGTH 255
- #define VOICE_MAX_NO_OF_CALLS 20
- #define BARRING_PASSWORD_LENGTH 4

Typedefs

- typedef unpack_result_t unpack_voice_OriginateUSSD_t
- typedef unpack_result_t unpack_voice_AnswerUSSD_t
- typedef unpack_result_t unpack_voice_CancelUSSD_t
- typedef unpack_result_t unpack_voice_SLQSVoiceSetPreferredPrivacy_t
- typedef unpack_result_t unpack_voice_SLQSVoiceIndicationRegister_t
- typedef unpack_result_t unpack_voice_SLQSVoiceOrigUSSDNoWait_t
- typedef unpack_result_t unpack_voice_SLQSVoiceBindSubscription_t
- typedef unpack_result_t unpack_voice_SLQSVoiceALSSetLineSwitching_t
- typedef unpack_result_t unpack_voice_SLQSVoiceALSSelectLine_t

Enumerations

- enum liteServiceClassInformation {
  LITE_VOICE_SUPS_SRV_CLASS_NONE = 0x00,
  LITE_VOICE_SUPS_SRV_CLASS_VOICE = 0x01,
  LITE_VOICE_SUPS_SRV_CLASS_DATA = 0x02,
  LITE_VOICE_SUPS_SRV_CLASS_FAX = 0x04,
  LITE_VOICE_SUPS_SRV_CLASS_SMS = 0x08,
  LITE_VOICE_SUPS_SRV_CLASS_DATACIRCUITSYNC = 0x10,
  LITE_VOICE_SUPS_SRV_CLASS_DATACIRCUITASYNC = 0x20,
  LITE_VOICE_SUPS_SRV_CLASS_PACKETACCESS = 0x40,
  LITE_VOICE_SUPS_SRV_CLASS_PADACCESS = 0x80 }

Functions

- int pack_voice_OriginateUSSD (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_OriginateUSSD_t *reqArg)
- int unpack_voice_OriginateUSSD (uint8_t *pResp, uint16_t respLen, unpack_voice_OriginateUSSD_t *pOutput)
- int pack_voice_AnswerUSSD (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_AnswerUSSD_t *reqArg)
- int unpack_voice_AnswerUSSD (uint8_t *pResp, uint16_t respLen, unpack_voice_AnswerUSSD_t *pOutput)
- int pack_voice_CancelUSSD (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_voice_CancelUSSD (uint8_t *pResp, uint16_t respLen, unpack_voice_CancelUSSD_t *pOutput)
- int pack_voice_SLQSVoiceDialCall (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceDialCall_t *pReq)
- int unpack_voice_SLQSVoiceDialCall (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceDialCall_t *pOutput)
- int pack_voice_SLQSVoiceEndCall (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceEndCall_t *pReq)
- int unpack_voice_SLQSVoiceEndCall (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceEndCall_t *pOutput)
- int pack_voice_SLQSVoiceSetSUPSService (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceSetSUPSService_t *pReq)
- int unpack_voice_SLQSVoiceSetSUPSService (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceSetSUPSService_t *pOutput)
- int pack_voice_SLQSVoiceSetConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceSetConfig_t *pReq)
- int unpack_voice_SLQSVoiceSetConfig (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceSetConfig_t *pOutput)
- int pack_voice_SLQSVoiceAnswerCall (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceAnswerCall_t *pReq)
- int unpack_voice_SLQSVoiceAnswerCall (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceAnswerCall_t *pOutput)
- int pack_voice_SLQSVoiceGetCLIR (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_voice_SLQSVoiceGetCLIR (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetCLIR_t *pOutput)
- int pack_voice_SLQSVoiceGetCLIP (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_voice_SLQSVoiceGetCLIP (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetCLIP_t *pOutput)
- int pack_voice_SLQSVoiceGetCallWaiting (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceGetCallWaiting_t *pReq)
- int unpack_voice_SLQSVoiceGetCallWaiting (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetCallWaiting_t *pOutput)
- int pack_voice_SLQSVoiceGetCallBarring (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceGetCallBarring_t *pReq)

- int unpack_voice_SLQSVoiceGetCallBarring (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetCallBarring_t *pOutput)
- int pack_voice_SLQSVoiceGetCallForwardingStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceGetCallForwardingStatus_t *pReq)
- int unpack_voice_SLQSVoiceGetCallForwardingStatus (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetCallForwardingStatus_t *pOutput)
- int pack_voice_SLQSVoiceSetCallBarringPassword (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceSetCallBarringPassword_t *pReq)
- int unpack_voice_SLQSVoiceSetCallBarringPassword (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceSetCallBarringPassword_t *pOutput)
- int pack_voice_SLQSVoiceGetCallInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceGetCallInfo_t *pReq)
- int unpack_voice_SLQSVoiceGetCallInfo (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetCallInfo_t *pOutput)
- int pack_voice_SLQSVoiceGetAllCallInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_voice_SLQSVoiceGetAllCallInfo (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetAllCallInfo_t *pOutput)
- int pack_voice_SLQSVoiceManageCalls (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceManageCalls_t *pReq)
- int unpack_voice_SLQSVoiceManageCalls (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceManageCalls_t *pOutput)
- int pack_voice_SLQSVoiceBurstDTMF (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceBurstDTMF_t *pReq)
- int unpack_voice_SLQSVoiceBurstDTMF (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceBurstDTMF_t *pOutput)
- int pack_voice_SLQSVoiceStartContDTMF (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceStartContDTMF_t *pReq)
- int unpack_voice_SLQSVoiceStartContDTMF (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceStartContDTMF_t *pOutput)
- int pack_voice_SLQSVoiceStopContDTMF (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceStopContDTMF_t *pReq)
- int unpack_voice_SLQSVoiceStopContDTMF (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceStopContDTMF_t *pOutput)
- int pack_voice_SLQSVoiceSendFlash (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceSendFlash_t *pReq)
- int unpack_voice_SLQSVoiceSendFlash (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceSendFlash_t *pOutput)
- int pack_voice_SLQSVoiceSetPreferredPrivacy (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceSetPreferredPrivacy_t *reqArg)
- int unpack_voice_SLQSVoiceSetPreferredPrivacy (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceSetPreferredPrivacy_t *pOutput)
- int pack_voice_SLQSVoiceIndicationRegister (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceIndicationRegister_t *reqArg)
- int unpack_voice_SLQSVoiceIndicationRegister (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceIndicationRegister_t *pOutput)
- int pack_voice_SLQSVoiceGetConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceGetConfig_t *reqArg)
- int unpack_voice_SLQSVoiceGetConfig (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetConfig_t *pOutput)
- int pack_voice_SLQSVoiceOrigUSSDNoWait (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceOrigUSSDNoWait_t *reqArg)
- int unpack_voice_SLQSVoiceOrigUSSDNoWait (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceOrigUSSDNoWait_t *pOutput)
- int pack_voice_SLQSVoiceBindSubscription (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceBindSubscription_t *reqArg)
- int unpack_voice_SLQSVoiceBindSubscription (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceBindSubscription_t *pOutput)

- int pack_voice_SLQSVoiceALSSetLineSwitching (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceALSSetLineSwitching_t *reqArg)
- int unpack_voice_SLQSVoiceALSSetLineSwitching (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceALSSetLineSwitching_t *pOutput)
- int pack_voice_SLQSVoiceALSSelectLine (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSVoiceALSSelectLine_t *reqArg)
- int unpack_voice_SLQSVoiceALSSelectLine (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceALSSelectLine_t *pOutput)
- int pack_voice_SLQSVoiceGetCOLP (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_voice_SLQSVoiceGetCOLP (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetCOLP_t *pOutput)
- int pack_voice_SLQSVoiceGetCOLR (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_voice_SLQSVoiceGetCOLR (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetCOLR_t *pOutput)
- int pack_voice_SLQSVoiceGetCNAP (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_voice_SLQSVoiceGetCNAP (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceGetCNAP_t *pOutput)
- int pack_voice_SLQSOriginateUSSD (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_voice_SLQSOriginateUSSD_t *reqArg)
- int unpack_voice_SLQSOriginateUSSD (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSOriginateUSSD_t *pOutput)
- int unpack_voice_USSDNotificationCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_voice_USSDNotificationCallback_ind_t *pOutput)
- int unpack_voice_SLQSVoiceSUPSCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_voice_SLQSVoiceSUPSCallback_ind_t *pOutput)
- int unpack_voice_allCallStatusCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_voice_allCallStatusCallback_ind_t *pOutput)
- int unpack_voice_voicePrivacyChangeCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_voice_voicePrivacyChangeCallback_ind_t *pOutput)
- int unpack_voice_DTMFEventCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_voice_DTMFEventCallback_ind_t *pOutput)
- int unpack_voice_SUPSNotificationCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_voice_SUPSNotificationCallback_ind_t *pOutput)
- int unpack_voice_OTASPStatusCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_voice_OTASPStatusCallback_ind_t *pOutput)
- int unpack_voice_VoiceInfoRecCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_voice_VoiceInfoRecCallback_ind_t *pOutput)

9.64.1 Detailed Description

9.64.2 S1

- 3GPP Mobile Radio Interface Layer 3 Specification : Core Network Protocols; Stage 3 (Release 7)
- 3GPP TS 24.008 V7.0.0 (2005-06)

9.64.3 Macro Definition Documentation

9.64.3.1 #define BARRING_PASSWORD_LENGTH 4

9.64.3.2 #define MAX_VOICE_CALL_NO_LEN 81

9.64.3.3 #define MAX_VOICE_DESCRIPTION_LENGTH 255

9.64.3.4 #define MAXVOICEUSSDLENGTH 182

9.64.3.5 #define VOICE_MAX_NO_OF_CALLS 20

9.64.4 Typedef Documentation

9.64.4.1 typedef unpack_result_t unpack_voice_AnswerUSSD_t

9.64.4.2 typedef unpack_result_t unpack_voice_CancelUSSD_t

9.64.4.3 typedef unpack_result_t unpack_voice_OriginateUSSD_t

9.64.4.4 typedef unpack_result_t unpack_voice_SLQSVoiceALSSelectLine_t

9.64.4.5 typedef unpack_result_t unpack_voice_SLQSVoiceALSSetLineSwitching_t

9.64.4.6 typedef unpack_result_t unpack_voice_SLQSVoiceBindSubscription_t

9.64.4.7 typedef unpack_result_t unpack_voice_SLQSVoiceIndicationRegister_t

9.64.4.8 typedef unpack_result_t unpack_voice_SLQSVoiceOrigUSSDNoWait_t

9.64.4.9 typedef unpack_result_t unpack_voice_SLQSVoiceSetPreferredPrivacy_t

9.64.5 Enumeration Type Documentation

9.64.5.1 enum liteServiceClassInformation

Service Class information

Enumerator

LITE_VOICE_SUPS_SRV_CLASS_NONE

LITE_VOICE_SUPS_SRV_CLASS_VOICE

LITE_VOICE_SUPS_SRV_CLASS_DATA

LITE_VOICE_SUPS_SRV_CLASS_FAX

LITE_VOICE_SUPS_SRV_CLASS_SMS

LITE_VOICE_SUPS_SRV_CLASS_DATACIRCUITSYNC

LITE_VOICE_SUPS_SRV_CLASS_DATACIRCUITASYNC

LITE_VOICE_SUPS_SRV_CLASS_PACKETACCESS

LITE_VOICE_SUPS_SRV_CLASS_PADACCESS

9.64.6 Function Documentation

9.64.6.1 int pack_voice_AnswerUSSD (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_AnswerUSSD_t * *reqArg*)

Responds to a USSD request from the network pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.2 int pack_voice_CancelUSSD (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Cancels an in-progress USSD operation pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.3 int pack_voice_OriginateUSSD (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_OriginateUSSD_t * *reqArg*)

Initiates a USSD operation pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.4 int pack_voice_SLQSOriginateUSSD (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSOriginateUSSD_t * *reqArg*)

Initiates a USSD session pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.5 int pack_voice_SLQSVoiceALSSelectLine (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceALSSelectLine_t * *reqArg*)

allows the user to select the preferred line pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.6 int pack_voice_SLQSVoiceALSSetLineSwitching (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceALSSetLineSwitching_t * *reqArg*)

sets the line switch setting on the card pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.7 int pack_voice_SLQSVoiceAnswerCall (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_voice_SLQSVoiceAnswerCall_t * pReq)

Answers an incoming voice call pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.8 int pack_voice_SLQSVoiceBindSubscription (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_voice_SLQSVoiceBindSubscription_t * reqArg)

binds a subscription type to a specific voice client ID pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.9 int pack_voice_SLQSVoiceBurstDTMF (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_voice_SLQSVoiceBurstDTMF_t * pReq)

Sends a burst Dual-Tone Multi frequency (DTMF) pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.10 int pack_voice_SLQSVoiceDialCall (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceDialCall_t * *pReq*)

Originates a voice call (MO call) pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.11 int pack_voice_SLQSVoiceEndCall (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceEndCall_t * *pReq*)

Ends a voice call pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.12 int pack_voice_SLQSVoiceGetAllCallInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

information associated with all the calls originating or terminating pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.13 int pack_voice_SLQSVoiceGetCallBarring (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceGetCallBarring_t * *pReq*)

Status of Call Barring Supplementary Service pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.14 int pack_voice_SLQSVoiceGetCallForwardingStatus (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceGetCallForwardingStatus_t * *pReq*)

Status of Call Forwarding Supplementary Service pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.15 int pack_voice_SLQSVoiceGetCallInfo (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_voice_SLQSVoiceGetCallInfo_t * pReq)

information associated with a call pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.16 int pack_voice_SLQSVoiceGetCallWaiting (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_voice_SLQSVoiceGetCallWaiting_t * pReq)

Status of Call Waiting Supplementary Service pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.17 int pack_voice_SLQSVoiceGetCLIP (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen)

status of the Calling Line Identification Presentation (CLIP) pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.18 int pack_voice_SLQSVoiceGetCLIR (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

status of the Calling Line Identification Restriction (CLIR) pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.19 int pack_voice_SLQSVoiceGetCNAP (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

status of the Calling Name Presentation(CNAP) pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.20 int pack_voice_SLQSVoiceGetCOLP (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

status of the Connected Line Identification Presentation pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.21 int pack_voice_SLQSVoiceGetCOLR (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

status of the Connected Line Identification Restriction pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.22 int pack_voice_SLQSVoiceGetConfig (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceGetConfig_t * *reqArg*)

retrieves various configuration parameters that control the modem behavior pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.23 int pack_voice_SLQSVoiceIndicationRegister (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceIndicationRegister_t * *reqArg*)

Sets the registration state for different QMI_VOICE indications pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.24 int pack_voice_SLQSVoiceManageCalls (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceManageCalls_t * *pReq*)

Manages the calls by using the supplementary service pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.25 int pack_voice_SLQSVoiceOrigUSSDNoWait (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceOrigUSSDNoWait_t * *reqArg*)

initiates a USSD operation No Wait pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.26 int pack_voice_SLQSVoiceSendFlash (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceSendFlash_t * *pReq*)

sends a simple flash message pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.27 int pack_voice_SLQSVoiceSetCallBarringPassword (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceSetCallBarringPassword_t * *pReq*)

Sets a Call Barring Password pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.28 int pack_voice_SLQSVoiceSetConfig (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceSetConfig_t * *pReq*)

configuration parameters that control the modem behavior pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.29 int pack_voice_SLQSVoiceSetPreferredPrivacy (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_voice_SLQSVoiceSetPreferredPrivacy_t * reqArg)

sets the voice privacy preference pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.30 int pack_voice_SLQSVoiceSetSUPSService (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_voice_SLQSVoiceSetSUPSService_t * pReq)

call-independent supplementary services pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.31 int pack_voice_SLQSVoiceStartContDTMF (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_voice_SLQSVoiceStartContDTMF_t * pReq)

Starts a continuous DTMF pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.32 int pack_voice_SLQSVoiceStopContDTMF (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_voice_SLQSVoiceStopContDTMF_t * *pReq*)

Stops a continuous DTMF pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.33 int unpack_voice_allCallStatusCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_allCallStatusCallback_ind_t * *pOutput*)

Unpack all call status callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	all call status callback unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.34 int unpack_voice_AnswerUSSD (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_AnswerUSSD_t * *pOutput*)

Responds to a USSD request from the network unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.35 int unpack_voice_CancelUSSD (uint8_t * *pResp*, uint16_t *respLen*, **unpack_voice_CancelUSSD_t** * *pOutput*)

Cancels an in-progress USSD operation unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.36 int unpack_voice_DTMFEventCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_voice_DTMFEventCallback_ind_t** * *pOutput*)

Unpack DTMF event callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	DTMF event callback unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.37 int unpack_voice_OriginateUSSD (uint8_t * *pResp*, uint16_t *respLen*, **unpack_voice_OriginateUSSD_t** * *pOutput*)

Initiates a USSD operation unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.38 int unpack_voice_OTASPStatusCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_OTASPStatusCallback_ind_t * *pOutput*)

Unpack voice OTASP status callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	voice OTASP status callback unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.39 int unpack_voice_SLQSOriginateUSSD (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSOriginateUSSD_t * *pOutput*)

Initiates a USSD session unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.40 int unpack_voice_SLQSVoiceALSSelectLine (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceALSSelectLine_t * *pOutput*)

allows the user to select the preferred line unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.41 int unpack_voice_SLQSVoiceALSSetLineSwitching (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceALSSetLineSwitching_t * *pOutput*)

sets the line switch setting on the card unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.42 int unpack_voice_SLQSVoiceAnswerCall (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceAnswerCall_t * *pOutput*)

Answers an incoming voice call unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.43 int unpack_voice_SLQSVoiceBindSubscription (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceBindSubscription_t * *pOutput*)

binds a subscription type to a specific voice client ID unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.44 int unpack_voice_SLQSVoiceBurstDTMF (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceBurstDTMF_t * *pOutput*)

Sends a burst Dual-Tone Multi frequency (DTMF) unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.45 int unpack_voice_SLQSVoiceDialCall (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceDialCall_t * *pOutput*)

Originates a voice call (MO call) unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.46 int unpack_voice_SLQSVoiceEndCall (uint8_t * *pResp*, uint16_t *respLen*, **unpack_voice_SLQSVoiceEndCall_t** * *pOutput*)

Ends a voice call unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.47 int unpack_voice_SLQSVoiceGetAllCallInfo (uint8_t * *pResp*, uint16_t *respLen*, **unpack_voice_SLQSVoiceGetAllCallInfo_t** * *pOutput*)

information associated with all the calls originating or terminating unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.48 int unpack_voice_SLQSVoiceGetCallBarring (uint8_t * *pResp*, uint16_t *respLen*, **unpack_voice_SLQSVoiceGetCallBarring_t** * *pOutput*)

Status of Call Barring Supplementary Service unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.49 int unpack_voice_SLQSVoiceGetCallForwardingStatus (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceGetCallForwardingStatus_t * *pOutput*)

Status of Call Forwarding Supplementary Service unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.50 int unpack_voice_SLQSVoiceGetCallInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceGetCallInfo_t * *pOutput*)

information associated with a call unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.51 int unpack_voice_SLQSVoiceGetCallWaiting (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceGetCallWaiting_t * *pOutput*)

Status of Call Waiting Supplementary Service unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.52 int unpack_voice_SLQSVoiceGetCLIP (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceGetCLIP_t * *pOutput*)

status of the Calling Line Identification Presentation (CLIP) unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.53 int unpack_voice_SLQSVoiceGetCLIR (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceGetCLIR_t * *pOutput*)

status of the Calling Line Identification Restriction (CLIR) unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.54 int unpack_voice_SLQSVoiceGetCNAP (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceGetCNAP_t * *pOutput*)

status of the Calling Name Presentation(CNAP) unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.55 int unpack_voice_SLQSVoiceGetCOLP (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceGetCOLP_t * *pOutput*)

status of the Connected Line Identification Presentation unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.56 int unpack_voice_SLQSVoiceGetCOLR (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceGetCOLR_t * *pOutput*)

status of the Connected Line Identification Restriction unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.57 int unpack_voice_SLQSVoiceGetConfig (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceGetConfig_t * *pOutput*)

retrieves various configuration parameters that control the modem behavior unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.58 int unpack_voice_SLQSVoiceIndicationRegister (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceIndicationRegister_t * *pOutput*)

Sets the registration state for different QMI_VOICE indications unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.59 int unpack_voice_SLQSVoiceManageCalls (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceManageCalls_t * *pOutput*)

Manages the calls by using the supplementary service unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.60 int unpack_voice_SLQSVoiceOrigUSSDNoWait (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceOrigUSSDNoWait_t * *pOutput*)

initiates a USSD operation No Wait unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.61 int unpack_voice_SLQSVoiceSendFlash (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceSendFlash_t * *pOutput*)

sends a simple flash message unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.62 int unpack_voice_SLQSVoiceSetCallBarringPassword (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceSetCallBarringPassword_t * *pOutput*)

Sets a Call Barring Password unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.63 int unpack_voice_SLQSVoiceSetConfig (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceSetConfig_t * *pOutput*)

configuration parameters that control the modem behavior unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.64 int unpack_voice_SLQSVoiceSetPreferredPrivacy (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceSetPreferredPrivacy_t * *pOutput*)

sets the voice privacy preference unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.65 int unpack_voice_SLQSVoiceSetSUPSService (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceSetSUPSService_t * *pOutput*)

call-independent supplementary services unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.66 int unpack_voice_SLQSVoiceStartContDTMF (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceStartContDTMF_t * *pOutput*)

Starts a continuous DTMF unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.67 int unpack_voice_SLQSVoiceStopContDTMF (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceStopContDTMF_t * *pOutput*)

Stops a continuous DTMF unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

Note

return eQCWWAN_ERR_NULL_TLV then callID value is invalid.

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.68 int unpack_voice_SLQSVoiceSUPSCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SLQSVoiceSUPSCallback_ind_t * *pOutput*)

Unpack voice sups callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	voice susp callback unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.69 int unpack_voice_SUPSNotificationCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_SUPSNotificationCallback_ind_t * *pOutput*)

Unpack SUPS notification callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	SUPS notification callback unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.70 int unpack_voice_USSDNotificationCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_voice_USSDNotificationCallback_ind_t** * *pOutput*)

Unpack USSD notification callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	USSD notification unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.71 int unpack_voice_VoiceInfoRecCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_voice_VoiceInfoRecCallback_ind_t** * *pOutput*)

Unpack SUPS notification callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	SUPS notification callback unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.64.6.72 int unpack_voice_voicePrivacyChangeCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, unpack_voice_voicePrivacyChangeCallback_ind_t * *pOutput*)

Unpack voice privacy change callback indication.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	voice privacy change callback unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65 wds.h File Reference

Data Structures

- struct LibPackQosClassID
- struct LibPackTFTIDParams
- struct LibPackGPRSRequestedQoS
- struct LibPackUMTSQoS
- struct LibPackUMTSReqQoSSigInd
- struct pack_wds_SLQSStartDataSession_t
- struct unpack_wds_SLQSStartDataSession_t
- struct unpack_wds_SLQSSetPacketSrvStatusCallback_t
- struct pack_wds_SLQSStopDataSession_t
- struct wds_ProfileIdentifier
- struct wds_GPRSQoS
- struct wds_PCSCFIPv4ServerAddressList
- struct wds_PCSCFFQDNAddress
- struct wds_PCSCFFQDNAddressList
- struct wds_Domain
- struct wds_DomainNameList
- struct wds_IPV6AddressInfo
- struct wds_IPV6GWAddressInfo
- struct unpack_wds_SLQSGetRuntimeSettings_t
- struct wds_currNetworkInfo
- struct unpack_wds_SLQSSetWdsEventCallback_ind_t
- struct pack_wds_SLQSSetWdsEventCallback_t
- struct pack_wds_SLQSGetRuntimeSettings_t
- struct wds_UMTSMinQoS
- struct LibPackprofile_3GPP
- struct LibPackprofile_3GPP2
- union wds_profileInfo
- struct pack_wds_SLQSCreateProfile_t
- struct PackCreateProfileOut
- struct unpack_wds_SLQSCreateProfile_t
- struct pack_wds_SLQSModifyProfile_t

- struct unpack_wds_SLQSModifyProfile_t
- struct pack_wds_SLQSGetProfileSettings_t
- struct LibpackProfile3GPP
- struct LibpackProfile3GPP2
- union unpackWdsProfileParam
- struct UnPackGetProfileSettingOut
- struct unpack_wds_SLQSGetProfileSettings_t
- struct unpack_wds_GetSessionState_t
- struct pack_wds_GetDefaultProfile_t
- struct unpack_wds_GetDefaultProfile_t
- struct unpack_wds_GetConnectionRate_t
- struct pack_wds_GetPacketStatus_t
- struct unpack_wds_GetPacketStatus_t
- struct unpack_wds_GetSessionDuration_t
- struct pack_wds_GetSessionDuration_t
- struct unpack_wds_GetDormancyState_t
- struct pack_wds_GetDormancyState_t
- struct pack_wds_SLQSDeleteProfile_t
- struct unpack_wds_SLQSDeleteProfile_t
- struct pack_wds_SetDefaultProfile_t
- struct unpack_wds_SLQSGet3GPPConfigItem_t
- struct pack_wds_SLQSSet3GPPConfigItem_t
- struct unpack_wds_GetMobileIP_t
- struct pack_wds_GetMobileIP_t
- struct pack_wds_GetMobileIPProfile_t
- struct unpack_wds_GetMobileIPProfile_t
- struct currNetworkInfo
- struct unpack_wds_SLQSGetCurrDataSystemStat_t
- struct pack_wds_SLQSGetCurrDataSystemStat_t
- struct unpack_wds_GetLastMobileIPError_t
- struct pack_wds_GetLastMobileIPError_t
- struct rmTrasnferStaticsReq
- struct pack_wds_RMSetTransferStatistics_t
- struct unpack_wds_RMSetTransferStatistics_t
- struct pack_wds_SetMobileIPProfile_t
- struct unpack_wds_SetMobileIPProfile_t
- struct pack_wds_SLQSWdsSwiPDPRuntimeSettings_t
- struct ipv6AddressInfo
- struct unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t
- struct wds_transferStatInd
- struct pack_wds_SLQSGetDUNCallInfo_t
- struct connectionStatus
- struct dunchannelRate
- struct unpack_wds_SLQSGetDUNCallInfo_t
- struct qmiWDSDataBearerTechnology
- struct unpack_wds_SLQSGetDataBearerTechnology_t
- struct pack_wds_SLQSGetDataBearerTechnology_t
- struct pack_wds_SLQSSetIPFamilyPreference_t
- struct unpack_wds_SLQSSetIPFamilyPreference_t
- struct pack_wds_SetDefaultProfileNum_t
- struct pack_wds_GetDefaultProfileNum_t
- struct unpack_wds_GetDefaultProfileNum_t
- struct wdsDhcpv4ProfileId
- struct wdsDhcpv4HwConfig
- struct wdsDhcpv4Option

- struct wdsDhcpv4OptionList
- struct pack_wds_SLQSSGetDHCPv4ClientConfig_t
- struct unpack_wds_SLQSSGetDHCPv4ClientConfig_t
- struct pack_wds_GetPacketStatistics_t
- struct unpack_wds_GetPacketStatistics_t
- struct unpack_wds_GetByteTotals_t
- struct unpack_wds_SLQSGetCurrentChannelRate_t
- struct unpack_wds_SLQSSGetLoopback_t
- struct pack_wds_SLQSSSetLoopback_t
- struct wds_DataULongTlv
- struct wds_DataULongLongTlv
- struct unpack_RMTransferStatistics_ind_t
- struct pack_wds_DHCPv4ClientLeaseChange_t
- struct wds_DHCPProfileIdTlv
- struct wds_DHCPLeaseStateTlv
- struct wds_IPv4AdTlv
- struct wds_DHCPOpt
- struct wds_DHCPLeaseOptTlv
- struct unpack_wds_DHCPv4ClientLease_ind_t
- struct pack_wds_SetMobileIP_t
- struct pack_wds_SetMobileIPParameters_t
- struct pack_wds_SetAutoconnect_t
- struct unpack_wds_GetAutoconnect_t
- struct wds_TrStatInd
- struct pack_wds_SLQSWdsSetEventReport_t
- struct wds_DHCPv4ProfileId
- struct wds_DHCPv4HWConfig
- struct wds_DHCPv4Option
- struct wds_DHCPv4OptionList
- struct pack_wds_SLQSSSetDHCPv4ClientConfig_t
- struct unpack_wds_GetDataBearerTechnology_t
- struct wds_ConnStatusTlv
- struct wds_LastMdmCallEndRsnTlv
- struct wds_TXBytesOKTlv
- struct wds_RXBytesOKTlv
- struct wds_DormStatTlv
- struct wds_DataBearTechTlv
- struct wds_channelRate
- struct wds_ChannelRateTlv
- struct unpack_wds_SLQSDUNCallInfoCallBack_ind_t

Macros

- #define IPV6_ADDRESS_ARRAY_SIZE 8
- #define MAX_WDS_3GPP_CONF_LTE_ATTACH_PROFILE_LIST_SIZE 24
- #define PACK_WDS_IPV4 4
- #define PACK_WDS_IPV6 6
- #define BYT_STAT_STAT_MASK 0X000000C0
- #define WDS_DHCP_MAX_NUM_OPTIONS 30
- #define WDS_DHCP_OPTION_DATA_BUF_SIZE 2048 /∗ current max size of raw message in SDK process is 2048 ∗/
- #define WDS_TFTID_SOURCE_IP_SIZE 8
- #define WDS_PROFILE_3GPP 0
- #define WDS_PROFILE_3GPP2 1

Typedefs

- typedef unpack_result_t unpack_wds_SLQSStopDataSession_t
- typedef unpack_result_t unpack_wds_SLQSSetWdsEventCallback_t
- typedef union unpackWdsProfileParam UnpackQmiProfileInfo
- typedef unpack_result_t unpack_wds_SetDefaultProfile_t
- typedef unpack_result_t unpack_wds_SLQSSet3GPPConfigItem_t
- typedef unpack_result_t unpack_wds_SetDefaultProfileNum_t
- typedef unpack_result_t unpack_wds_SLQSSSetLoopback_t
- typedef struct unpack_RMTransferStatistics_ind_t unpack_wds_RMTransferStatistics_ind_t
- typedef unpack_result_t unpack_wds_DHCPv4ClientLeaseChange_t
- typedef unpack_result_t unpack_wds_SetMobileIP_t
- typedef unpack_result_t unpack_wds_SetMobileIPParameters_t
- typedef unpack_result_t unpack_wds_SetAutoconnect_t
- typedef unpack_result_t unpack_wds_SLQSWdsSetEventReport_t
- typedef unpack_result_t unpack_wds_SLQSWdsGoDormant_t
- typedef unpack_result_t unpack_wds_SLQSWdsGoActive_t
- typedef unpack_result_t unpack_wds_SLQSResetPacketStatics_t
- typedef unpack_result_t unpack_wds_SLQSSSetDHCPv4ClientConfig_t
- typedef unpack_result_t unpack_wds_SetMuxID_t

Enumerations

- enum liteQmiDataBearerMasks { QMI_LITE_WDS_CURRENT_CALL_DB_MASK = 0x01, QMI_LITE_WDS_LAST_CALL_DB_MASK = 0x02 }

Functions

- int pack_wds_SLQSStartDataSession (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSStartDataSession_t *reqArg)
- int unpack_wds_SLQSStartDataSession (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSStartDataSession_t *pOutput)
- int unpack_wds_SLQSSetPacketSrvStatusCallback (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSSetPacketSrvStatusCallback_t *pOutput)
- int pack_wds_SLQSStopDataSession (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSStopDataSession_t *reqArg)
- int unpack_wds_SLQSStopDataSession (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSStopDataSession_t *pOutput)
- int unpack_wds_SLQSGetRuntimeSettings (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSGetRuntimeSettings_t *pOutput)
- int unpack_wds_SLQSSetWdsEventCallback_ind (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSSetWdsEventCallback_ind_t *pOutput)
- int unpack_wds_SLQSSetWdsEventCallback (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSSetWdsEventCallback_t *pOutput)
- int pack_wds_SLQSSetWdsEventCallback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSSetWdsEventCallback_t *reqArg)
- int pack_wds_SLQSGetRuntimeSettings (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSGetRuntimeSettings_t *reqArg)
- int pack_wds_SLQSCreateProfile (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSCreateProfile_t *reqArg)
- int unpack_wds_SLQSCreateProfile (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSCreateProfile_t *pOutput)

- int pack_wds_SLQSModifyProfile (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSModifyProfile_t *reqArg)
- int unpack_wds_SLQSModifyProfile (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSModifyProfile_t *pOutput)
- int pack_wds_SLQSGetProfileSettings (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSGetProfileSettings_t *reqArg)
- int unpack_wds_SLQSGetProfileSettings (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSGetProfileSettings_t *pOutput)
- int pack_wds_GetSessionState (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_GetSessionState (uint8_t *pResp, uint16_t respLen, unpack_wds_GetSessionState_t *pOutput)
- int pack_wds_GetDefaultProfile (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_GetDefaultProfile_t *reqParam)
- int unpack_wds_GetDefaultProfile (uint8_t *pResp, uint16_t respLen, unpack_wds_GetDefaultProfile_t *pOutput)
- int pack_wds_GetConnectionRate (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_GetConnectionRate (uint8_t *pResp, uint16_t respLen, unpack_wds_GetConnectionRate_t *pOutput)
- int pack_wds_GetPacketStatus (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_GetPacketStatus_t *reqParam)
- int unpack_wds_GetPacketStatus (uint8_t *pResp, uint16_t respLen, unpack_wds_GetPacketStatus_t *pOutput)
- int pack_wds_GetSessionDuration (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_GetSessionDuration_t *reqParam)
- int unpack_wds_GetSessionDuration (uint8_t *pResp, uint16_t respLen, unpack_wds_GetSessionDuration_t *pOutput)
- int pack_wds_GetDormancyState (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_GetDormancyState_t *reqParam)
- int unpack_wds_GetDormancyState (uint8_t *pResp, uint16_t respLen, unpack_wds_GetDormancyState_t *pOutput)
- int pack_wds_SLQSDeleteProfile (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSDeleteProfile_t *reqParam)
- int unpack_wds_SLQSDeleteProfile (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSDeleteProfile_t *pOutput)
- int pack_wds_SetDefaultProfile (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SetDefaultProfile_t *reqParam)
- int unpack_wds_SetDefaultProfile (uint8_t *pResp, uint16_t respLen, unpack_wds_SetDefaultProfile_t *pOutput)
- int pack_wds_SLQSGet3GPPConfigItem (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_SLQSGet3GPPConfigItem (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSGet3GPPConfigItem_t *pOutput)
- int pack_wds_SLQSSet3GPPConfigItem (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSSet3GPPConfigItem_t *reqParam)
- int unpack_wds_SLQSSet3GPPConfigItem (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSSet3GPPConfigItem_t *pOutput)
- int pack_wds_GetMobileIP (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_GetMobileIP_t *pReqParam)
- int unpack_wds_GetMobileIP (uint8_t *pResp, uint16_t respLen, unpack_wds_GetMobileIP_t *pOutput)
- int pack_wds_GetMobileIPProfile (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_GetMobileIPProfile_t *reqParam)
- int unpack_wds_GetMobileIPProfile (uint8_t *pResp, uint16_t respLen, unpack_wds_GetMobileIPProfile_t *pOutput)
- int pack_wds_SLQSGetCurrDataSystemStat (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSGetCurrDataSystemStat_t *pReqParam)
- int unpack_wds_SLQSGetCurrDataSystemStat (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSGetCurrDataSystemStat_t *pOutput)

- int pack_wds_GetLastMobileIPError (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_GetLastMobileIPError_t *pReqParam)
- int unpack_wds_GetLastMobileIPError (uint8_t *pResp, uint16_t respLen, unpack_wds_GetLastMobileIPError_t *pOutput)
- int pack_wds_RMSetTransferStatistics (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_RMSetTransferStatistics_t *reqParam)
- int unpack_wds_RMSetTransferStatistics (uint8_t *pResp, uint16_t respLen, unpack_wds_RMSetTransferStatistics_t *pOutput)
- int pack_wds_SetMobileIPProfile (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SetMobileIPProfile_t *reqParam)
- int unpack_wds_SetMobileIPProfile (uint8_t *pResp, uint16_t respLen, unpack_wds_SetMobileIPProfile_t *pOutput)
- int pack_wds_SLQSWdsSwiPDPRuntimeSettings (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSWdsSwiPDPRuntimeSettings_t *reqParam)
- int unpack_wds_SLQSWdsSwiPDPRuntimeSettings (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t *pOutput)
- int pack_wds_SLQSGetDUNCallInfo (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSGetDUNCallInfo_t *reqParam)
- int unpack_wds_SLQSGetDUNCallInfo (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSGetDUNCallInfo_t *pOutput)
- int pack_wds_SLQSGetDataBearerTechnology (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSGetDataBearerTechnology_t *pReqParam)
- int unpack_wds_SLQSGetDataBearerTechnology (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSGetDataBearerTechnology_t *pOutput)
- int pack_wds_SLQSSetIPFamilyPreference (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSSetIPFamilyPreference_t *pReqParam)
- int unpack_wds_SLQSSetIPFamilyPreference (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSSetIPFamilyPreference_t *pOutput)
- int pack_wds_SetDefaultProfileNum (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SetDefaultProfileNum_t *pReqParam)
- int unpack_wds_SetDefaultProfileNum (uint8_t *pResp, uint16_t respLen, unpack_wds_SetDefaultProfileNum_t *pOutput)
- int pack_wds_GetDefaultProfileNum (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_GetDefaultProfileNum_t *pReqParam)
- int unpack_wds_GetDefaultProfileNum (uint8_t *pResp, uint16_t respLen, unpack_wds_GetDefaultProfileNum_t *pOutput)
- int pack_wds_SLQSSGetDHCPv4ClientConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSSGetDHCPv4ClientConfig_t *pReq)
- int unpack_wds_SLQSSGetDHCPv4ClientConfig (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSSGetDHCPv4ClientConfig_t *pOutput)
- int pack_wds_GetPacketStatistics (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_GetPacketStatistics_t *pReq)
- int unpack_wds_GetPacketStatistics (uint8_t *pResp, uint16_t respLen, unpack_wds_GetPacketStatistics_t *pOutput)
- int pack_wds_GetByteTotals (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_GetByteTotals (uint8_t *pResp, uint16_t respLen, unpack_wds_GetByteTotals_t *pOutput)
- int pack_wds_SLQSGetCurrentChannelRate (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_SLQSGetCurrentChannelRate (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSGetCurrentChannelRate_t *pOutput)
- int pack_wds_SLQSSGetLoopback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_SLQSSGetLoopback (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSSGetLoopback_t *pOutput)
- int pack_wds_SLQSSSetLoopback (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSSSetLoopback_t *reqArg)
- int unpack_wds_SLQSSSetLoopback (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSSSetLoopback_t *pOutput)

- int unpack_wds_RMTransferStatistics_ind (uint8_t *pResp, uint16_t respLen, unpack_RMTransferStatistics_ind_t *pOutput)
- int pack_wds_DHCPv4ClientLeaseChange (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_DHCPv4ClientLeaseChange_t *reqArg)
- int unpack_wds_DHCPv4ClientLeaseChange (uint8_t *pResp, uint16_t respLen, unpack_wds_DHCPv4ClientLeaseChange_t *pOutput)
- int unpack_wds_DHCPv4ClientLease_ind (uint8_t *pResp, uint16_t respLen, unpack_wds_DHCPv4ClientLease_ind_t *pOutput)
- int pack_wds_SetMobileIP (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SetMobileIP_t *reqArg)
- int unpack_wds_SetMobileIP (uint8_t *pResp, uint16_t respLen, unpack_wds_SetMobileIP_t *pOutput)
- int pack_wds_SetMobileIPParameters (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SetMobileIPParameters_t *reqArg)
- int unpack_wds_SetMobileIPParameters (uint8_t *pResp, uint16_t respLen, unpack_wds_SetMobileIPParameters_t *pOutput)
- int pack_wds_SetAutoconnect (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SetAutoconnect_t *reqArg)
- int unpack_wds_SetAutoconnect (uint8_t *pResp, uint16_t respLen, unpack_wds_SetAutoconnect_t *pOutput)
- int pack_wds_GetAutoconnect (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_GetAutoconnect (uint8_t *pResp, uint16_t respLen, unpack_wds_GetAutoconnect_t *pOutput)
- int pack_wds_SLQSWdsSetEventReport (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSWdsSetEventReport_t *reqArg)
- int unpack_wds_SLQSWdsSetEventReport (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSWdsSetEventReport_t *pOutput)
- int pack_wds_SLQSWdsGoDormant (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_SLQSWdsGoDormant (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSWdsGoDormant_t *pOutput)
- int pack_wds_SLQSWdsGoActive (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_SLQSWdsGoActive (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSWdsGoActive_t *pOutput)
- int pack_wds_SLQSResetPacketStatics (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_SLQSResetPacketStatics (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSResetPacketStatics_t *pOutput)
- int pack_wds_SLQSSSetDHCPv4ClientConfig (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, pack_wds_SLQSSSetDHCPv4ClientConfig_t *reqArg)
- int unpack_wds_SLQSSSetDHCPv4ClientConfig (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSSSetDHCPv4ClientConfig_t *pOutput)
- int pack_wds_GetDataBearerTechnology (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen)
- int unpack_wds_GetDataBearerTechnology (uint8_t *pResp, uint16_t respLen, unpack_wds_GetDataBearerTechnology_t *pOutput)
- int pack_wds_SetMuxID (pack_qmi_t *pCtx, uint8_t *pReqBuf, uint16_t *pLen, uint8_t *pMuxID)
- int unpack_wds_SetMuxID (uint8_t *pResp, uint16_t respLen, unpack_wds_SetMuxID_t *pOutput)
- int unpack_wds_SLQSDUNCallInfoCallBack_ind (uint8_t *pResp, uint16_t respLen, unpack_wds_SLQSDUNCallInfoCallBack_ind_t *pOutput)

9.65.1 Detailed Description

9.65.2 SO Mask

- SO mask to indicate the service option or type of application.
  - An SO mask value of zero indicates that this field is ignored.
  - Values:

    - 0x00 - DONT_CARE
  - CDMA 1X SO mask:
    - 0x01 - CDMA_1X_IS95
    - 0x02 - CDMA_1X_IS2000
    - 0x04 - CDMA_1X_IS2000_REL_A
  - CDMA EV-DO Rev 0 SO mask:
    - 0x01 - DPA
  - CDMA EV-DO Rev A SO mask:
    - 0x01 - DPA
    - 0x02 - MFPA
    - 0x04 - EMPA
    - 0x08 - EMPA_EHRPD
  - CDMA EV-DO Rev B SO mask:
    - 0x01 - DPA
    - 0x02 - MFPA
    - 0x04 - EMPA
    - 0x08 - EMPA_EHRPD
    - 0x10 - MMPA
    - 0x20 - MMPA_EHRPD

9.65.3 RAT Mask

- RAT mask to indicate the type of technology. A RAT mask value of zero indicates that this field is ignored. Values:
  - 0x00 - DONT_CARE
  - 0x8000 - NULL_BEARER
- CDMA RAT mask:
  - 0x01 - CDMA_1X
  - 0x02 - EVDO_REV0
  - 0x04 - EVDO_REVA
  - 0x08 - EVDO_REVB
  - 0x10 - EHRPD
  - 0x20 - FMC
- UMTS RAT mask:
  - 0x01 - WCDMA
  - 0x02 - GPRS
  - 0x04 - HSDPA
  - 0x08 - HSUPA
  - 0x10 - EDGE
  - 0x20 - LTE
  - 0x40 - HSDPA+
  - 0x80 - DC_HSDPA+
  - 0x100 - 64_QAM
  - 0x200 - TD-SCDMA

9.65.4 Macro Definition Documentation

9.65.4.1 #define BYT_STAT_STAT_MASK 0X000000C0

9.65.4.2 #define IPV6_ADDRESS_ARRAY_SIZE 8

9.65.4.3 #define MAX_WDS_3GPP_CONF_LTE_ATTACH_PROFILE_LIST_SIZE 24

9.65.4.4 #define PACK_WDS_IPV4 4

9.65.4.5 #define PACK_WDS_IPV6 6

9.65.4.6 #define WDS_DHCP_MAX_NUM_OPTIONS 30

9.65.4.7 #define WDS_DHCP_OPTION_DATA_BUF_SIZE 2048 /∗ current max size of raw message in SDK process is 2048 ∗/

9.65.4.8 #define WDS_PROFILE_3GPP 0

9.65.4.9 #define WDS_PROFILE_3GPP2 1

9.65.4.10 #define WDS_TFTID_SOURCE_IP_SIZE 8

9.65.5 Typedef Documentation

9.65.5.1 typedef unpack_result_t unpack_wds_DHCPv4ClientLeaseChange_t

9.65.5.2 typedef struct unpack_RMTransferStatistics_ind_t unpack_wds_RMTransferStatistics_ind_t

9.65.5.3 typedef unpack_result_t unpack_wds_SetAutoconnect_t

9.65.5.4 typedef unpack_result_t unpack_wds_SetDefaultProfile_t

9.65.5.5 typedef unpack_result_t unpack_wds_SetDefaultProfileNum_t

9.65.5.6 typedef unpack_result_t unpack_wds_SetMobileIP_t

9.65.5.7 typedef unpack_result_t unpack_wds_SetMobileIPParameters_t

9.65.5.8 typedef unpack_result_t unpack_wds_SetMuxID_t

9.65.5.9 typedef unpack_result_t unpack_wds_SLQSResetPacketStatics_t

9.65.5.10 typedef unpack_result_t unpack_wds_SLQSSet3GPPConfigItem_t

9.65.5.11 typedef unpack_result_t unpack_wds_SLQSSetWdsEventCallback_t

9.65.5.12 typedef unpack_result_t unpack_wds_SLQSSSetDHCPv4ClientConfig_t

9.65.5.13 typedef unpack_result_t unpack_wds_SLQSSSetLoopback_t

9.65.5.14 typedef unpack_result_t unpack_wds_SLQSStopDataSession_t

9.65.5.15 typedef unpack_result_t unpack_wds_SLQSWdsGoActive_t

9.65.5.16 typedef unpack_result_t unpack_wds_SLQSWdsGoDormant_t

9.65.5.17 typedef unpack_result_t unpack_wds_SLQSWdsSetEventReport_t

9.65.5.18 typedef union unpackWdsProfileParam UnpackQmiProfileInfo

This union WdsProfileParam consists of Profile3GPP and Profile3GPP2 out of which one will be used to create profile.

Parameters

SlqsProfile3GPP	3GPP profile • See LibpackProfile3GPP
SlqsProfile3GPP2	3GPP2 profile • See LibpackProfile3GPP2

9.65.6 Enumeration Type Documentation

9.65.6.1 enum liteQmiDataBearerMasks

Bit mask values to indicate the presence of data bearer information for the current and last data calls

Enumerator

QMI_LITE_WDS_CURRENT_CALL_DB_MASK

QMI_LITE_WDS_LAST_CALL_DB_MASK

9.65.7 Function Documentation

9.65.7.1 int pack_wds_DHCPv4ClientLeaseChange (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_DHCPv4ClientLeaseChange_t * *reqArg*)

DHCPv4 lease state changes pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.2 int pack_wds_GetAutoconnect (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets auto connect data session setting pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.3 int pack_wds_GetByteTotals (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

get Rx/Tx byte counts since the start of the last packet data session pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.4 int pack_wds_GetConnectionRate (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

get connection rate pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: No

9.65.7.5 int pack_wds_GetDataBearerTechnology (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

get current data bearer technology pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.6 int pack_wds_GetDefaultProfile (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_GetDefaultProfile_t * *reqParam*)

get default profile pack.

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.7 int pack_wds_GetDefaultProfileNum (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_wds_GetDefaultProfileNum_t * pReqParam)

get default profile number pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.8 int pack_wds_GetDormancyState (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_wds_GetDormancyState_t * reqParam)

get dormancy state pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: No

9.65.7.9 int pack_wds_GetLastMobileIPError (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_wds_GetLastMobileIPError_t * pReqParam)

get current data system pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: No

9.65.7.10 int pack_wds_GetMobileIP (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_GetMobileIP_t * *pReqParam*)

get mobile ip mode pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: No

9.65.7.11 int pack_wds_GetMobileIPProfile (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_GetMobileIPProfile_t * *reqParam*)

get mobile ip profile pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.12 int pack_wds_GetPacketStatistics (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_GetPacketStatistics_t * *pReq*)

gets current packet transfer counter values pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.13 int pack_wds_GetPacketStatus (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_GetPacketStatus_t * *reqParam*)

get packet status pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.14 int pack_wds_GetSessionDuration (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_GetSessionDuration_t * *reqParam*)

get session duration pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: No

9.65.7.15 int pack_wds_GetSessionState (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

get session state pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.16 int pack_wds_RMSetTransferStatistics (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_RMSetTransferStatistics_t * *reqParam*)

RM set transfer statistics pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Note

PDN Specific: No

9.65.7.17 int pack_wds_SetAutoconnect (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SetAutoconnect_t * *reqArg*)

Auto connect data session parameters pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.18 int pack_wds_SetDefaultProfile (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SetDefaultProfile_t * *reqParam*)

set default profile pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.19 int pack_wds_SetDefaultProfileNum (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_wds_SetDefaultProfileNum_t * pReqParam)

set default profile number pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.20 int pack_wds_SetMobileIP (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_wds_SetMobileIP_t * reqArg)

Sets the current mobile IP setting pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.21 int pack_wds_SetMobileIPParameters (pack_qmi_t * pCtx, uint8_t * pReqBuf, uint16_t * pLen, pack_wds_SetMobileIPParameters_t * reqArg)

Sets the specified mobile IP parameters pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.22 int pack_wds_SetMobileIPProfile (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SetMobileIPProfile_t * *reqParam*)

set mobile ip profile pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.23 int pack_wds_SetMuxID (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, uint8_t * *pMuxID*)

Set MUX ID pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pMuxID*	MUX ID. • 0x80 to 0x88

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.24 int pack_wds_SLQSCreateProfile (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSCreateProfile_t * *reqArg*)

Create Profile pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.25 int pack_wds_SLQSDeleteProfile (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSDeleteProfile_t * *reqParam*)

delete stored profile pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.26 int pack_wds_SLQSGet3GPPConfigItem (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

get 3Gpp config items pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.27 int pack_wds_SLQSGetCurrDataSystemStat (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSGetCurrDataSystemStat_t * *pReqParam*)

get current data system pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.28 int pack_wds_SLQSGetCurrentChannelRate (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

get current Tx/Rx channel bitrate of the current packet data pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.29 int pack_wds_SLQSGetDataBearerTechnology (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSGetDataBearerTechnology_t * *pReqParam*)

get data bearer technology pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.30 int pack_wds_SLQSGetDUNCallInfo (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSGetDUNCallInfo_t * *reqParam*)

get dun call info pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.31 int pack_wds_SLQSGetProfileSettings (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSGetProfileSettings_t * *reqArg*)

Get Profile Settings pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.32 int pack_wds_SLQSGetRuntimeSettings (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSGetRuntimeSettings_t * *reqArg*)

get runtime settings pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.33 int pack_wds_SLQSModifyProfile (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSModifyProfile_t * *reqArg*)

Modify Profile pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.34 int pack_wds_SLQSResetPacketStatics (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Reset packet data transfer statistics pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.35 int pack_wds_SLQSSet3GPPConfigItem (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSSet3GPPConfigItem_t * *reqParam*)

set 3Gpp config items pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.36 int pack_wds_SLQSSetIPFamilyPreference (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSSetIPFamilyPreference_t * *pReqParam*)

Set IP Family Preference pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.37 int pack_wds_SLQSSetWdsEventCallback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSSetWdsEventCallback_t * *reqArg*)

set event callback pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: No

9.65.7.38 int pack_wds_SLQSSGetDHCPv4ClientConfig (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSSGetDHCPv4ClientConfig_t * *pReq*)

get DHCPv4 Client Config pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*pReq*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.39 int pack_wds_SLQSSGetLoopback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

get the value of loopback mode and multiplier pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.40 int pack_wds_SLQSSSetDHCPv4ClientConfig (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSSSetDHCPv4ClientConfig_t * *reqArg*)

Gets the DHCP Client V4 Configuration pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

see qmerrno.h for eQCWWAN_xxx error values

9.65.7.41 int pack_wds_SLQSSSetLoopback (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSSSetLoopback_t * *reqArg*)

Enable/disable Data Loopback Mode and set the value of loopback multiplier pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.42 int pack_wds_SLQSStartDataSession (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSStartDataSession_t * *reqArg*)

Start data session

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.43 int pack_wds_SLQSStopDataSession (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSStopDataSession_t * *reqArg*)

stop data session pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.44 int pack_wds_SLQSWdsGoActive (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets the device into Active state pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.45 int pack_wds_SLQSWdsGoDormant (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*)

Gets the device into dormant state pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.46 int pack_wds_SLQSWdsSetEventReport (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSWdsSetEventReport_t * *reqArg*)

Sets the event report parameters pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqArg*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.47 int pack_wds_SLQSWdsSwiPDPRuntimeSettings (pack_qmi_t * *pCtx*, uint8_t * *pReqBuf*, uint16_t * *pLen*, pack_wds_SLQSWdsSwiPDPRuntimeSettings_t * *reqParam*)

swi pdp runtime settings pack

Parameters

in,out	*pCtx*	qmi request context
out	*pReqBuf*	qmi request buffer
out	*pLen*	qmi request length
in	*reqParam*	request parameter

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Note

PDN Specific: Yes

9.65.7.48 int unpack_wds_DHCPv4ClientLease_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_DHCPv4ClientLease_ind_t** * *pOutput*)

DHCP lease state has changed indication unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.49 int unpack_wds_DHCPv4ClientLeaseChange (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_DHCPv4ClientLeaseChange_t** * *pOutput*)

DHCPv4 lease state changes unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.50 int unpack_wds_GetAutoconnect (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_GetAutoconnect_t** * *pOutput*)

Gets auto connect data session setting unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.51 int unpack_wds_GetByteTotals (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_GetByteTotals_t** * *pOutput*)

get Rx/Tx byte counts since the start of the last packet data session unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.52 int unpack_wds_GetConnectionRate (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_GetConnectionRate_t** * *pOutput*)

get connection rate unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.53 int unpack_wds_GetDataBearerTechnology (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_GetDataBearerTechnology_t** * *pOutput*)

get current data bearer technology unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.54 int unpack_wds_GetDefaultProfile (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_GetDefaultProfile_t * *pOutput*)

get default profile unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.55 int unpack_wds_GetDefaultProfileNum (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_GetDefaultProfileNum_t * *pOutput*)

get default profile number unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.56 int unpack_wds_GetDormancyState (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_GetDormancyState_t * *pOutput*)

get dormancy state unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.57 int unpack_wds_GetLastMobileIPError (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_GetLastMobileIP-Error_t * *pOutput*)

get current data system unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.58 int unpack_wds_GetMobileIP (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_GetMobileIP_t * *pOutput*)

get mobile ip mode unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.59 int unpack_wds_GetMobileIPProfile (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_GetMobileIPProfile_t * *pOutput*)

get mobile ip profile unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.60 int unpack_wds_GetPacketStatistics (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_GetPacketStatistics_t * *pOutput*)

gets current packet transfer counter values unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.61 int unpack_wds_GetPacketStatus (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_GetPacketStatus_t * *pOutput*)

get packet status unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.62 int unpack_wds_GetSessionDuration (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_GetSessionDuration_t * *pOutput*)

get session duration unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.63 int unpack_wds_GetSessionState (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_GetSessionState_t** * *pOutput*)

get session state unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.64 int unpack_wds_RMSetTransferStatistics (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_RMSetTransferStatistics_t** * *pOutput*)

RM set transfer statistics unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.65 int unpack_wds_RMTransferStatistics_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_RMTransferStatistics_ind_t** * *pOutput*)

RM transfer statistics indication unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.66 int unpack_wds_SetAutoconnect (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SetAutoconnect_t * *pOutput*)

Auto connect data session parameters unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.67 int unpack_wds_SetDefaultProfile (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SetDefaultProfile_t * *pOutput*)

set default profile unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.68 int unpack_wds_SetDefaultProfileNum (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SetDefaultProfileNum_t * *pOutput*)

set default profile number unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.69 int unpack_wds_SetMobileIP (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SetMobileIP_t** * *pOutput*)

Sets the current mobile IP setting unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.70 int unpack_wds_SetMobileIPParameters (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SetMobileIP-Parameters_t** * *pOutput*)

Sets the specified mobile IP parameters unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.71 int unpack_wds_SetMobileIPProfile (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SetMobileIPProfile_t** * *pOutput*)

set mobile ip profile unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.72 int unpack_wds_SetMuxID (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SetMuxID_t** * *pOutput*)

Set MUX ID unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.73 int unpack_wds_SLQSCreateProfile (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SLQSCreateProfile_t** * *pOutput*)

Create Profile unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response structure to fill

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.74 int unpack_wds_SLQSDeleteProfile (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SLQSDeleteProfile_t** * *pOutput*)

delete stored profile unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.75 int unpack_wds_SLQSDUNCallInfoCallBack_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SLQSDUNCallInfoCallBack_ind_t** * *pOutput*)

unpack DUN call info indication

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.76 int unpack_wds_SLQSGet3GPPConfigItem (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SLQSGet3GPPConfigItem_t** * *pOutput*)

get 3GPP config items unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.77 int unpack_wds_SLQSGetCurrDataSystemStat (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SLQSGetCurrDataSystemStat_t** * *pOutput*)

get current data system unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.78 int unpack_wds_SLQSGetCurrentChannelRate (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSGetCurrentChannelRate_t * *pOutput*)

get current Tx/Rx channel bitrate of the current packet data unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.79 int unpack_wds_SLQSGetDataBearerTechnology (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSGetDataBearerTechnology_t * *pOutput*)

get data bearer technology unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.80 int unpack_wds_SLQSGetDUNCallInfo (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSGetDUNCallInfo_t * *pOutput*)

get dun call info unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.81 int unpack_wds_SLQSGetProfileSettings (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSGetProfileSettings_t * *pOutput*)

get session state unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response structure to fill

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.82 int unpack_wds_SLQSGetRuntimeSettings (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSGetRuntimeSettings_t * *pOutput*)

get runtime settings unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.83 int unpack_wds_SLQSModifyProfile (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSModifyProfile_t * *pOutput*)

Modify Profile unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response structure to fill

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.84 int unpack_wds_SLQSResetPacketStatics (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSResetPacketStatics_t * *pOutput*)

Reset packet data transfer statistics unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.85 int unpack_wds_SLQSSet3GPPConfigItem (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSSet3GPPConfigItem_t * *pOutput*)

set 3GPP config items unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

9.65.7.86 int unpack_wds_SLQSSetIPFamilyPreference (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSSetIPFamilyPreference_t * *pOutput*)

Set IP Family Preference unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.87 int unpack_wds_SLQSSetPacketSrvStatusCallback (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SLQSSetPacketSrvStatusCallback_t** * *pOutput*)

set packet srv status callback unpack

Parameters

in	*pResp*	qmi response
in	*respLen*	length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.88 int unpack_wds_SLQSSetWdsEventCallback (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SLQSSetWdsEventCallback_t** * *pOutput*)

set event callback unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.89 int unpack_wds_SLQSSetWdsEventCallback_ind (uint8_t * *pResp*, uint16_t *respLen*, **unpack_wds_SLQSSetWdsEventCallback_ind_t** * *pOutput*)

set event callback unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.90 int unpack_wds_SLQSSGetDHCPv4ClientConfig (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSSGetDHCPv4ClientConfig_t * *pOutput*)

get DHCPv4 Client Config unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.91 int unpack_wds_SLQSSGetLoopback (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSSGetLoopback_t * *pOutput*)

get the value of loopback mode and multiplier unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.92 int unpack_wds_SLQSSSetDHCPv4ClientConfig (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSSSetDHCPv4ClientConfig_t * *pOutput*)

Gets the DHCP Client V4 Configuration unpack.

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.93 int unpack_wds_SLQSSSetLoopback (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSSSetLoopback_t * *pOutput*)

Enable/disable Data Loopback Mode and set the value of loopback multiplier unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.94 int unpack_wds_SLQSStartDataSession (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSStartDataSession_t * *pOutput*)

start data session unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.95 int unpack_wds_SLQSStopDataSession (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSStopDataSession_t * *pOutput*)

stop data session unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.96 int unpack_wds_SLQSWdsGoActive (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSWdsGoActive_t * *pOutput*)

Gets the device into Active state unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.97 int unpack_wds_SLQSWdsGoDormant (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSWdsGoDormant_t * *pOutput*)

Gets the device into dormant state unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.98 int unpack_wds_SLQSWdsSetEventReport (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSWdsSetEventReport_t * *pOutput*)

Sets the event report parameters unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	unpacked response

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

9.65.7.99 int unpack_wds_SLQSWdsSwiPDPRuntimeSettings (uint8_t * *pResp*, uint16_t *respLen*, unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t * *pOutput*)

get current data system unpack

Parameters

in	*pResp*	qmi response from modem
in	*respLen*	qmi response length
out	*pOutput*	response unpacked

Returns

eQCWWAN_ERR_NONE on success, eQCWWAN_xxx error value otherwise

See Also

See qmerrno.h for eQCWWAN_xxx error values

Index

_3gppRelease
    unpack_wds_SLQSGet3GPPConfigItem_t, 1535
_GetProfileSettingIn, 70
    ProfileID, 70
    ProfileType, 70
_GetProfileSettingOut, 70
    curProfile, 71
    pExtErrCode, 71
_MitigationDevInfo, 73
    deviceID, 73
    deviceIdLen, 73
_QmiSwiAvmsEventReportBinaryUpdateSessionInfo-Resp, 78
    bBinaryType, 79
    bSerity, 79
    bState, 79
    bUserInputRequest, 79
    szDescription, 79
    szName, 80
    szVersion, 80
    TlvPresent, 80
    ulPkgDownloadComplete, 80
    ulPkgDownloadSize, 80
    wDescriptionLength, 80
    wNameLength, 80
    wUpdateCompeteStatus, 80
    wUserInputTimeout, 80
    wVersionLength, 80
_QmiSwiAvmsEventReportConfigResp, 80
    bState, 81
    bUserInputRequest, 81
    szAlertMsg, 81
    TlvPresent, 81
    wAlertMsgLength, 81
    wUserInputTimeout, 81
_QmiSwiAvmsEventReportConnectionRequestResp, 81
    bUserInputRequest, 81
    TlvPresent, 81
    wUserInputTimeout, 81
_QmiSwiAvmsEventReportDataSessionStatusResp, 81
    bType, 82
    TlvPresent, 82
    wErrorCode, 82
_QmiSwiAvmsEventReportHTTPStatusResp, 82
    TlvPresent, 83
    wHTTPStatus, 83
_QmiSwiAvmsEventReportNotificationResp, 84
    bNotification, 84
    TlvPresent, 84
    wSessionStatus, 85
_QmiSwiAvmsEventReportPackageIDResp, 85
    bPackageID, 85
    TlvPresent, 85
_QmiSwiAvmsEventReportRegStatusResp, 85
    bRegStatus, 85
    TlvPresent, 85
_QmiSwiAvmsEventReportSessionTypeResp, 85
    bType, 86
    TlvPresent, 86
_QmiSwiAvmsEventReportWAMSParamChangeResp, 86
    TlvPresent, 86
    wWamsChangeMask, 86
_QmiSwiAvmsSetSettingsAPNInfo, 86
    bAPNLength, 87
    bPWDLength, 87
    bUnameLength, 87
    szAPN, 87
    szPWD, 87
    szUname, 87
_QmiSwiAvmsSetSettingsConnectionRetryTimers, 87
    Timers, 87
_QmiSwiAvmsSetSettingsPeriodInfo, 87
    ulMax, 87
    ulMin, 87
_SLQSAVMSSetSettingsReqPara, 90
    pAPNInfo, 92
    pAutoConnect, 92
    pAutoReboot, 92
    pConnectionRetryTimers, 92
    pFwAutoSDM, 92
    pFwPromptUpdate, 92
    pFwPromptdownload, 92
    pNotifStore, 92
    pPeroidInfo, 92
    pPollingTimer, 92
_SLQSAVMSSetSettingsReqPara_v2, 92
    pAPNInfo, 93
    pAutoConnect, 93
    pAutoReboot, 93
    pConnectionRetryTimers, 94
    pFwPromptUpdate, 94
    pFwPromptdownload, 94
    pNotifStore, 94
    pPeroidInfo, 94
    pPollingTimer, 94
_SLQSAVMSSettings, 94

pAPNInfo, 94
pAutoConnect, 94
pAutoReboot, 94
pConnectionRetryTimers, 94
pFwAutoSDM, 94
pFwPromptUpdate, 94
pFwPromptdownload, 94
pNotificationStore, 94
pOMADMEnabled, 94
pPeroidsInfo, 94
pPollingTimer, 94
_SLQSAVMSSettingsAPNInfo, 95
bAPNLength, 96
bPWDLength, 96
bUnameLength, 96
pAPN, 96
pPWD, 96
pUname, 96
_SLQSAVMSSettingsConnectionRetryTimers, 96
Timers, 96
_SLQSAVMSSettingsPeriodsInfo, 96
max, 96
min, 96
_SLQSAVMSSettings_v2, 95
pAPNInfo, 95
pAutoConnect, 95
pAutoReboot, 95
pConnectionRetryTimers, 95
pFwAutoSDM, 95
pFwPromptUpdate, 95
pFwPromptdownload, 95
pNotificationStore, 95
pOMADMEnabled, 95
pPeroidsInfo, 95
pPollingTimer, 95
_SLQSOMADMSessionInfo, 102
pDate, 104
pDateLength, 104
pPkgDescLength, 104
pPkgDescription, 104
pPkgName, 104
pPkgNameLength, 104
pRetryCount, 104
pSessionState, 104
pSessionType, 104
pSeverity, 104
pSource, 104
pSourceLength, 104
pStatus, 104
pTime, 104
pTimeLength, 104
pUpdateCompleteStatus, 104
_SLQSOMADMSettings, 104
pAutosdm, 106
pFOTAUpdate, 106
pFOTAdownload, 106
pFwAutoCheck, 106
pOMADMEnabled, 106
_SLQSOMADMSettingsReqParams, 106
FOTAUpdate, 107
FOTAdownload, 107
pAutosdm, 107
_SLQSOMADMSettingsReqParams3, 107
FOTAUpdate, 108
FOTAdownload, 108
pAutosdm, 108
pFwAutoCheck, 108
_SLQSSwiGetHostDevInfoParams, 108
bHostIDSize, 109
bManSize, 109
bModelSize, 109
bPlasmaIDSize, 109
bSWVerSize, 109
pHostID, 109
pManString, 109
pModelString, 109
pPlasmaIDString, 109
pSWVerString, 109
_SLQSSwiGetOSInfoParams, 109
bNameSize, 110
bVersionSize, 110
pNameString, 110
pVersionString, 110
_SLQSSwiGetSerialNoExtParams, 110
meidLength, 110
pMeidString, 110
_SLQSSwiSetHostDevInfoParams, 110
bHostIDSize, 111
bManSize, 111
bModelSize, 111
bPlasmaIDSize, 111
bSWVerSize, 111
pHostID, 111
pManString, 112
pModelString, 112
pPlasmaIDString, 112
pSWVerString, 112
_SLQSSwiSetOSInfoParams, 112
bNameSize, 112
bVersionSize, 112
pNameString, 112
pVersionString, 112
SlqsNas3GppNetworkRAT, 96
MCC, 97
MNC, 97
RAT, 97
_SwiAvmsEventInd, 112
BinaryUpdateSessionInfo, 113
Config, 113
ConnectionRequest, 113
DataSessionStatus, 113
HTTPStatus, 113
Notification, 113
PackageID, 113
RegStatus, 113
SessionType, 113

WAMSParaChanged, 113
_getIndicationRegResp, 69
pRegCallStatInfoEvt, 70
pRegTransLayerInfoEvt, 70
pRegTransNWRegInfoEvt, 70
_getResetInfoNotification, 71
source, 72
type, 72
_getTransLayerInfoResp, 72
pRegInd, 72
pTransLayerInfo, 72
_getTransNWRegInfoResp, 72
pRegStatus, 73
_modemTempNotification, 73
ModemTempState, 74
ModemTemperature, 74
_modemUIMStatusNotification, 74
ModemUIMStatusEvent, 75
ModemUIMStatusInterface, 75
_packetSrvStatus, 75
bearerID, 76
connStatus, 76
ipFamily, 76
pQmiInterfaceInfo, 76
reconfigReqd, 76
sessionEndReason, 76
techName, 77
verboseSessnEndReason, 77
verboseSessnEndReasonType, 77
_qaQmi3GPP2BroadcastCfgInfo, 77
activated_ind, 77
CDMABroadcastConfig, 77
num_instances, 77
_qaQmi3GPPBroadcastCfgInfo, 77
activated_ind, 78
broadcastConfig, 78
num_instances, 78
_setIndicationRegReq, 87
pRegCallStatInfoEvt, 88
pRegTransLayerInfoEvt, 88
pRegTransNWRegInfoEvt, 88
_slqs3GPPConfigItem, 88
LTEAttachProfileListLen, 90
p3gppRelease, 90
pDefaultPDNEnabled, 90
pLTEAttachProfile, 90
pLTEAttachProfileList, 90
pProfileList, 90
_slqsNetworkScanInfo, 97
has_PCIInfo, 98
pLteOpModeTlv, 98
pNetworkInfo, 98
pNetworkInfoInstances, 98
pPCIInfo, 98
pPCSDigitInfo, 98
pPCSDigitInstances, 98
pRATInfo, 98
pRATInstances, 99
pScanResult, 99
_slqsNetworkScanInfoReq, 99
pCiotOpModePref, 101
pLteM1BandPref, 101
pLteNB1BandPref, 102
pNetworkType, 102
pScanType, 102
_sysSelectPrefExtInfo, 113
pAcqOrderPref, 114
pCiotAcqOrderPref, 114
pCiotLteOpModePref, 114
pLTEBandPrefExt, 114
pLteM1BandPref, 114
pLteNb1BandPref, 114
pNr5gBandPref, 115
pRatDisabledMask, 115
pSysSelectPrefInfo, 115
_sysSelectPrefInfo, 115
pBandPref, 119
pEmerMode, 119
pGWAcqOrderPref, 119
pLTEBandPref, 119
pModePref, 119
pNetSelPref, 119
pPRLPref, 119
pRoamPref, 119
pSrvDomainPref, 119
_sysSelectPrefParams, 120
pAcqOrderPref, 125
pBandPref, 125
pCSGID, 125
pChgDuration, 125
pEmerMode, 125
pGWAcqOrderPref, 125
pLTEBandPref, 125
pMNCIncPCSDigStat, 125
pModePref, 125
pNetSelPref, 125
pPRLPref, 125
pRAT, 126
pRoamPref, 126
pSrvDomainPref, 126
pSrvRegRestriction, 126
pTdscdmaBandPref, 126
_transLayerInfoNotification, 126
pTransLayerInfo, 127
regInd, 127
results, 127
_transLayerinfo, 126
TransCap, 126
TransType, 126
_transNWRegInfoNotification, 127
NWRegStat, 128
results, 128

AAASPI
unpack_wds_GetMobileIPProfile_t, 1525
AAAState
unpack_wds_GetMobileIPProfile_t, 1525

ABSOLUTE_VALIDITY
qaGobiApiSms.h, 2171
ACT_CODE_MAX_SIZE
dms.h, 1733
ALS
getAllCallInformation, 290
voice_getAllCallInformation, 1602
AMSSString
unpack_dms_GetFirmwareRevision_t, 1221
unpack_dms_GetFirmwareRevisions_t, 1222
AOPTlv
NASQmiCbkNasSystemSelPrefInd, 667
APNName
unpack_wds_SLQSGetRuntimeSettings_t, 1545
AVMS (SWIAVMS), 65
absoluteValidity
cdmaMsgDecodingParams, 182
cdmaMsgDecodingParamsExt, 186
accelAcceptReady
qaGobiApiCbk.h, 1914
accelAcceptReady_s, 128
batchPerSec, 128
injectEnable, 128
samplesPerBatch, 128
accelTemp
pack_loc_SLQSLOCInjectSensorData_t, 737
accelTempAcceptReady
qaGobiApiCbk.h, 1914
accelTempAcceptReady_s, 128
batchPerSec, 129
injectEnable, 129
samplesPerBatch, 129
acceleroData
pack_loc_SLQSLOCInjectSensorData_t, 737
acceleroTimeSrc
pack_loc_SLQSLOCInjectSensorData_t, 737
AccessMac
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
accolc
pack_nas_SetACCOLC_t, 743
accuracy
pack_pds_SetPDSDefaults_t, 783
ackIndicator
SMSTransferRouteMTMessage, 1080
sMSTransferRouteMTMessageInfo, 1080
acqOrdeLen
acqOrderPref, 130
AcqOrderPrefTlv, 130
nas_acqOrderPref, 472
nas_AcqOrderPrefTlv, 473
AcqOrderLen
NASAcqOrderPrefTlv, 626
AcqOrderPref
NASAcqOrderPrefTlv, 626
acqOrderPref, 129
acqOrdeLen, 130
pAcqOrder, 130
AcqOrderPrefTlv, 130
acqOrdeLen, 130
pAcqOrder, 131
TlvPresent, 131
acroamsetting
pack_wds_SetAutoconnect_t, 847
slqsautoconnect, 1032
acsetting
pack_wds_SetAutoconnect_t, 847
slqsautoconnect, 1032
actCode
pack_dms_ActivateAutomatic_t, 706
ActPilotPNElement, 131
ActSetPilotPN, 131
ActSetPilotPNStrength, 131
ActSetCnt
nas_NetworkStat1x, 554
NetworkStat1x, 685
ActSetPilotPN
ActPilotPNElement, 131
nas_ActPilotPNElement, 473
ActSetPilotPNStrength
ActPilotPNElement, 131
nas_ActPilotPNElement, 473
action
pack_nas_InitiateDomainAttach_t, 742
slqsautoconnect, 1032
ssdatasession_params, 1086
ActivateAutomatic
qaGobiApiDms.h, 2011
activated_ind
_qaQmi3GPP2BroadcastCfgInfo, 77
_qaQmi3GPPBroadcastCfgInfo, 78
sms_qaQmi3GPP2BroadcastCfgInfo, 1058
sms_qaQmi3GPPBroadcastCfgInfo, 1059
activationState
pack_dms_SetActivationStatusCallback_t, 708
activationStatus
dms_ActivationStatusTlv, 246
ActivationStatusTlv
unpack_dms_SetEventReport_ind_t, 1237
activeBand
nas_RfBandInfoExtFormatElements, 585
RfBandInfoExtFormatElements, 968
activeBandClass
nas_RFBandInfoElements, 584
nas_RFInfoTlv, 590
RFBandInfoElements, 967
activeChannel
nas_RFBandInfoElements, 584
nas_RfBandInfoExtFormatElements, 585
nas_RFInfoTlv, 590
RFBandInfoElements, 967
RfBandInfoExtFormatElements, 968
activeInd
messageWaitingInfoContent, 466
sms_messageWaitingInfoContent, 1057
ActiveStatus

CLIPResp, 201
CLIRResp, 202
CNAPResp, 204
COLPResp, 205
COLRResp, 205
voice_CLIPResp, 1592
voice_CLIRResp, 1593
voice_CNAPResp, 1593
voice_COLPResp, 1594
voice_COLRResp, 1595
ActiveTechPref
unpack_nas_GetNetworkPreference_t, 1313
ActiveTimer
unpack_dms_PSMCfgChange_ind_t, 1234
activeTimer
dms_PSMActiveTimerTlv, 247
PSMActiveTimerTlv, 907
ActiveTimerInd
dms_PSMActiveTimerIndTlv, 247
AddCDMASysInfo, 131
geoSysIdx, 132
regPrd, 132
AddSysInfo, 132
cellBroadcastCap, 132
geoSysIdx, 132
addr
IPv4Addr, 367
IPv6Addr, 369
unpack_qos_IPv4Addr_t, 1398
unpack_qos_IPv6Addr_t, 1399
address
IPv4Info, 368
IPv6Info, 371
loc_IPv4Info, 413
loc_IPv6Info, 414
loc_urlAddr, 421
unpack_wds_GetMobileIPProfile_t, 1525
urlAddr, 1561
addressSize
unpack_sms_GetSMSCAddress_t, 1423
aid
uim_refreshevent, 1162
uim_sessionInformation, 1164
uim_UIMSessionInformation, 1168
UIMRefreshEvent, 1185
UIMSessionInformation, 1188
aidLength
appStats, 140
appStatus, 143
uim_appStatus, 1147
uim_refreshevent, 1162
uim_sessionInformation, 1164
uim_UIMSessionInformation, 1168
UIMRefreshEvent, 1185
UIMSessionInformation, 1188
aidVal
appStats, 140
appStatus, 143
uim_appStatus, 1147
aidingIndicatorMask
loc_sensorDataUsage, 419
sensorDataUsage_s, 991
t_sensor, 1124
airTimer, 132
airTimerValue, 133
namID, 133
airTimerValue
airTimer, 133
voice_airTimer, 1570
alertPitch
signalInfo, 1026
voice_signalInfo, 1614
alertingPattern
arrAlertingPattern, 144
voice_arrAlertingPattern, 1573
AlertingType
arrAlertingType, 145
voice_arrAlertingType, 1574
alertmsg
omaDmConfigTlv, 697
omaDmConfigTlvExt, 699
unpack_omaDmConfigTlv_t, 1380
alertmsglength
omaDmConfigTlv, 697
omaDmConfigTlvExt, 699
unpack_omaDmConfigTlv_t, 1380
allCallsAlphaIDInfo, 133
AlphaIDInfo, 133
callID, 133
allCallsAlphaIDInfoArr
arrAlphaID, 145
voice_arrAlphaID, 1574
allCallsDiagInfo, 133
callID, 134
DiagInfo, 134
AllCallsUUSInfo
arrUUSInfo, 151
voice_arrUUSInfo, 1580
allCallsUUSInfo, 134
callID, 134
uusInfo, 134
alphaDcs
alphaIDInfo, 135
voice_alphaIDInfo, 1572
AlphaID
CatAlPhaIdentifierTlv, 174
AlphaIDInfo
allCallsAlphaIDInfo, 133
voice_allCallsAlphaIDInfo, 1570
alphaIDInfo, 134
alphaDcs, 135
alphaLen, 135
alphaText, 135
alphaIDLen
SMSAsyncRawSend_s, 1066

unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t, 1440
AlphaIDLength
CatAlPhaIdentifierTlv, 174
alphaLen
alphaIDInfo, 135
voice_alphaIDInfo, 1572
alphaText
alphaIDInfo, 135
voice_alphaIDInfo, 1572
alphabet
wcdmaMsgEncodingParams, 1674
altSrcInfo_t, 136
coverage, 137
linkage, 137
source, 137
Altitude
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
altitudeAssumed
unpack_loc_GnssSvInfo_Ind_t, 1288
altitudeSrcInfo, 135
coverage, 136
linkage, 136
pack_loc_SLQSLOCInjectPosition_t, 735
source, 136
altitudeWrtEllipsoid
pack_loc_SLQSLOCInjectPosition_t, 735
altitudeWrtMeanSeaLevel
pack_loc_SLQSLOCInjectPosition_t, 735
ambr_dl
sApnExtraParams, 984
unpack_qos_SLQSQosSwiReadApnExtraParams_t, 1404
ambr_dl_ext
sApnExtraParams, 984
unpack_qos_SLQSQosSwiReadApnExtraParams_t, 1404
ambr_dl_ext2
sApnExtraParams, 984
unpack_qos_SLQSQosSwiReadApnExtraParams_t, 1404
ambr_ul
sApnExtraParams, 984
unpack_qos_SLQSQosSwiReadApnExtraParams_t, 1404
ambr_ul_ext
sApnExtraParams, 984
unpack_qos_SLQSQosSwiReadApnExtraParams_t, 1404
ambr_ul_ext2
sApnExtraParams, 984
unpack_qos_SLQSQosSwiReadApnExtraParams_t, 1404
amssSize
unpack_dms_GetFirmwareRevision_t, 1221
unpack_dms_GetFirmwareRevisions_t, 1222
AnswerUSSD
qaGobiApiVoice.h, 2287
apdoxypages.c, 1719
apnId
pack_qos_SLQSQosSwiReadApnExtraParams_t, 793
pack_qos_SLQSQosSwiReadDataStats_t, 793
sApnExtraParams, 984
sQosStat, 1082
unpack_qos_SLQSQosSwiReadApnExtraParams_t, 1404
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
apnName
unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t, 1559
apnname
unpack_wds_GetDefaultProfile_t, 1520
apnsize
unpack_wds_GetDefaultProfile_t, 1520
appNameLength
loc_LocApplicationInfo, 415
LocApplicationInfo, 423
appProviderLength
loc_LocApplicationInfo, 415
LocApplicationInfo, 423
appState
appStats, 140
appStatus, 143
uim_appStatus, 1147
appStats, 137
aidLength, 140
aidVal, 140
appState, 140
appType, 140
persoFeature, 140
persoRetries, 140
persoState, 140
persoUnblockRetries, 140
pin1Retries, 140
pin1State, 140
pin2Retries, 140
pin2State, 140
puk1Retries, 140
puk2Retries, 140
univPin, 140
AppStatus
slotInf, 1030
slotInfo, 1031
uim_slotInfo, 1167
appStatus, 140
aidLength, 143
aidVal, 143
appState, 143
appType, 143
persoFeature, 143
persoRetries, 143
persoState, 143
persoUnblockRetries, 143
pin1Retries, 143

pin1State, 143
pin2Retries, 143
pin2State, 143
puk1Retries, 143
puk2Retries, 143
univPin, 143
appType
appStats, 140
appStatus, 143
uim_appStatus, 1147
appVersionLength
loc_LocApplicationInfo, 415
LocApplicationInfo, 423
appVersionValid
loc_LocApplicationInfo, 415
LocApplicationInfo, 423
Application
unpack_nas_GetCDMANetworkParameters_t, 1308
appversion_str
slqsfwinfo_s, 1034
unpack_dms_GetFirmwareInfo_t, 1219
arfcn
GERANInfo, 288
gsmCellInfo, 328
nas_GERANInfo, 506
nas_gsmCellInfo, 508
arrAlertingPattern, 143
alertingPattern, 144
callID, 144
numInstances, 144
arrAlertingType, 144
AlertingType, 145
callID, 145
numInstances, 145
arrAlphaID, 145
allCallsAlphaIDInfoArr, 145
numInstances, 145
arrCallEndReason, 146
callEndReason, 147
callID, 147
numInstances, 147
arrCallInfo, 147
getAllCallInfo, 147
numInstances, 147
arrCallInfomation
unpack_voice_allCallStatusCallback_ind_t, 1470
voiceSetAllCallStatusCbkInfo, 1654
arrCalledPartyNum, 145
CalledPartyNum, 146
numInstances, 146
arrConnectPartyNum, 147
ConnectedPartyNum, 148
numInstances, 148
arrDiagInfo, 148
DiagInfo, 148
numInstances, 148
arrRedirPartyNum, 148
numInstances, 149
RedirPartyNum, 149
arrRemotePartyName, 149
GetAllCallRmtPtyName, 149
numInstances, 149
arrRemotePartyNum, 149
numInstances, 150
RmtPtyNum, 150
arrSvcOption, 150
callID, 150
numInstances, 150
srvOption, 150
arrUUSInfo, 151
AllCallsUUSInfo, 151
numInstances, 151
arrfileInfo
registerRefresh, 962
uim_refreshevent, 1162
uim_registerRefresh, 1163
UIMRefreshEvent, 1185
AtCmdPort
DcsUsbPortNames, 238
Audio Service (AUDIO), 59
auth
unpack_wds_GetDefaultProfile_t, 1520
authData
pack_uim_SLQSUIMAuthenticate_t, 815
UIMAuthenticateReq, 1171
AuthProt
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
authenticateResult, 151
content, 152
contentLen, 152
Authentication
unpack_wds_SLQSGetRuntimeSettings_t, 1545
authentication
pack_wds_SetDefaultProfile_t, 848
authenticationData, 152
context, 152
data, 153
dataLen, 153
Autosdm
unpack_swioma_SLQSOMADMGetSettings_t, 1453
avgPeriod
LTESigRptCfg, 457
LTESigRptConfig, 458
nas_LTESigRptCfg, 542
nas_LTESigRptConfig, 543
azimuth
loc_satelliteInfo, 418
satelliteInfo, 986

bAPNLength
_QmiSwiAvmsSetSettingsAPNInfo, 87
_SLQSAVMSSettingsAPNInfo, 96
bAltitudeAssumed
gnssSvInfoNotification, 321

bAuto
pack_pds_SetPortAutomaticTracking_t, 784
pack_pds_SetServiceAutomaticTracking_t, 784
bBinaryType
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 79
bEnable
pack_dms_UIMSetPINProtection_t, 722
pack_nas_SLQSSetSignalStrengthsCallback_t, 764
bEnabled
pack_pds_SetXTRAAutomaticDownload_t, 785
bForceDownload
pack_fms_SetImagesPreference_t, 725
bHostIDSize
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 111
bICCID
slot_t, 1028
UIMSlotStatus, 1190
bICCIDLength
slot_t, 1028
UIMSlotStatus, 1190
bLogicalSlot
pack_uim_SLQSUIMSwitchSlot_t, 821
slot_t, 1028
UIMSlotStatus, 1190
UIMSwitchSlotReq, 1192
bManSize
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 111
bModelSize
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 111
bNameSize
_SLQSSwiGetOSInfoParams, 110
_SLQSSwiSetOSInfoParams, 112
bNotification
_QmiSwiAvmsEventReportNotificationResp, 84
bNumberOfPhySlots
UIMSlotStatusChangeInfo, 1191
unpack_uim_SetUimSlotStatusChangeCallback_-ind_t, 1459
BOOL
SwiDataTypes.h, 2395
BPTlv
NASQmiCbkNasSystemSelPrefInd, 667
bPWDLength
_QmiSwiAvmsSetSettingsAPNInfo, 87
_SLQSAVMSSettingsAPNInfo, 96
bPackageID
_QmiSwiAvmsEventReportPackageIDResp, 85
bPlasmaIDSize
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 111
bRegStatus
_QmiSwiAvmsEventReportRegStatusResp, 85
bResetStatistics
rmTrasnferStaticsReq, 972
swiRMTrasnferStaticsReq, 1117
bSWVerSize
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 111
bSerity
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 79
bState
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 79
_QmiSwiAvmsEventReportConfigResp, 81
bType
_QmiSwiAvmsEventReportDataSessionStatus-Resp, 82
_QmiSwiAvmsEventReportSessionTypeResp, 86
BUILD_ID_LEN
qaGobiApiFms.h, 2046
BUILD_ID_MAX_LEN
qaGobiApiFms.h, 2046
bUnameLength
_QmiSwiAvmsSetSettingsAPNInfo, 87
_SLQSAVMSSettingsAPNInfo, 96
bUserInputRequest
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 79
_QmiSwiAvmsEventReportConfigResp, 81
_QmiSwiAvmsEventReportConnectionRequest-Resp, 81
bVersionSize
_SLQSSwiGetOSInfoParams, 110
_SLQSSwiSetOSInfoParams, 112
BYT_STAT_STAT_MASK
wds.h, 2477
BYTE
SwiDataTypes.h, 2395
band
LTEInfo, 442
nas_LTEInfo, 528
NASPhyCaAggScellArray, 658
PhyCaAggScellArray, 878
band1900
gsmCellInfo, 328
nas_gsmCellInfo, 508
band_pref
NASBandPreferenceTlv, 626
BandCapability
unpack_dms_GetBandCapability_t, 1208
bandCapability
BandCapabilityResp, 156
unpack_dms_SLQSGetBandCapability_t, 1251
BandCapabilityResp, 153
bandCapability, 156
pLteBandCapability, 156
pTdsBandCapability, 156
BandPref
nas_BandPrefTlv, 477
bandPref

pack_nas_SLQSSetBandPreference_t, 763
BandPrefTlv, 156
bits_129_192, 156
bits_193_256, 157
bits_1_64, 157
bits_65_128, 157
TlvPresent, 157
bandwidth
LTEInfo, 442
nas_LTEInfo, 528
nas_RfBandwidthInfoElements, 587
RfBandwidthInfoElements, 970
baseId
CDMAInfo, 180
CDMASysInfo, 193
nas_CDMAInfo, 480
nas_CDMASysInfo, 484
baseLat
CDMAInfo, 180
CDMASysInfo, 193
nas_CDMAInfo, 480
nas_CDMASysInfo, 484
baseLong
CDMAInfo, 180
CDMASysInfo, 193
nas_CDMAInfo, 480
nas_CDMASysInfo, 484
BasestationID
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1335
BasestationLatitude
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1335
BasestationLongitude
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1335
batchPerSec
accelAcceptReady_s, 128
accelTempAcceptReady_s, 129
gyroAcceptReady_s, 333
gyroTempAcceptReady_s, 334
loc_accelAcceptReady, 404
loc_accelTempAcceptReady, 405
loc_gyroAcceptReady, 411
loc_gyroTempAcceptReady, 412
BdsSV, 157
id, 157
mask, 157
BdsSVInfo, 157
len, 158
pSV, 158
BearerID
unpack_qos_QosFlowInfo_t, 1401
bearerID
_packetSrvStatus, 76
unpack_wds_SLQSSetPacketSrvStatusCallback_t, 1548
bearerId
sQosFlowStat, 1081
unpack_QosFlowStat_t, 1419
unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t, 1559
BinaryUpdateSessionInfo
_SwiAvmsEventInd, 113
bits_129_192
BandPrefTlv, 156
lteBandPrefExt, 437
nas_BandPrefInfoTlv, 475
nas_lteBandPrefExt, 522
nas_nr5gBandPref, 558
nr5gBandPref, 690
bits_193_256
BandPrefTlv, 157
lteBandPrefExt, 437
nas_BandPrefInfoTlv, 475
nas_lteBandPrefExt, 522
nas_nr5gBandPref, 558
nr5gBandPref, 690
bits_1_64
BandPrefTlv, 157
lteBandPrefExt, 437
nas_BandPrefInfoTlv, 475
nas_lteBandPrefExt, 522
nas_nr5gBandPref, 558
nr5gBandPref, 690
bits_65_128
BandPrefTlv, 157
lteBandPrefExt, 437
nas_BandPrefInfoTlv, 475
nas_lteBandPrefExt, 522
nas_nr5gBandPref, 558
nr5gBandPref, 690
bootSize
unpack_dms_GetFirmwareRevisions_t, 1222
BootString
unpack_dms_GetFirmwareRevisions_t, 1222
bootversion_str
slqsfwinfo_s, 1034
unpack_dms_GetFirmwareInfo_t, 1219
Broadcast
unpack_nas_GetCDMANetworkParameters_t, 1308
broadcastActivate
pack_sms_SLQSSetSmsBroadcastActivation_t, 802
BroadcastConfig, 158
fromServiceId, 158
selected, 158
toServiceId, 158
broadcastConfig
_qaQmi3GPPBroadcastCfgInfo, 78
sms_qaQmi3GPPBroadcastCfgInfo, 1059
bsInfoValid
CDMASysInfo, 193
nas_CDMASysInfo, 484
bsPRev

CDMASysInfo, 193
nas_CDMASysInfo, 484
bsPRevValid
CDMASysInfo, 193
nas_CDMASysInfo, 484
bsic
GERANInfo, 288
nas_GERANInfo, 506
bsicId
gsmCellInfo, 328
nas_gsmCellInfo, 508
bucketSz
tokenBucket, 1138
unpack_qos_tokenBucket_t, 1418
buildID
CurrImageInfo, 222
FMSImageIdElement, 283
image_info_t, 345
ImageIdElement, 347
buildIDLen
CurrImageInfo, 222
image_info_t, 345
buildIDLength
FMSImageIdElement, 283
ImageIdElement, 347
buildId
FMSImageElement, 282
ImageElement, 346
buildIdLength
FMSImageElement, 282
ImageElement, 346
BurstDTMFInfo
pack_voice_SLQSVoiceBurstDTMF_t, 827
voiceBurstDTMFInfo, 1620
burstDTMFInfo, 158
digitCnt, 159
pCallID, 159
pDigitBuff, 159
ByteLoopbackMode
unpack_wds_SLQSSGetLoopback_t, 1556
WDSGetLoopbackData, 1710
ByteLoopbackMultiplier
unpack_wds_SLQSSGetLoopback_t, 1556
WDSGetLoopbackData, 1710
ByteTotalsElmntsV4
WdsByteTotals, 1701
ByteTotalsElmntsV6
WdsByteTotals, 1701

CATEventDataType, 175
eventMask, 175
pErrorMask, 175
CATSendEnvelopeCommand
qaGobiApiCat.h, 1902
CATSendTerminalResponse
qaGobiApiCat.h, 1902
CBK_DISABLE_EVENT
qaGobiApiCbk.h, 1912
CBK_ENABLE_EVENT
qaGobiApiCbk.h, 1912
CBK_NOCHANGE
qaGobiApiCbk.h, 1912
CCETlv
QmiCbkCatEventStatusReportInd, 916
CDMA_P_Rev
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1335
CDMABroadcastConfig, 177
_qaQmi3GPP2BroadcastCfgInfo, 77
language, 178
selected, 178
serviceCategory, 178
sms_qaQmi3GPP2BroadcastCfgInfo, 1058
CDMAChannel, 178
priChA, 179
priChB, 179
secChA, 179
secChB, 179
CDMAECIOThresh, 179
CDMAECIOThreshListLen, 179
pCDMAECIOThreshList, 179
CDMAECIOThreshListLen
CDMAECIOThresh, 179
nas_CDMAECIOThresh, 479
CDMAInfo, 179
baseId, 180
baseLat, 180
baseLong, 180
nid, 180
refpn, 180
sid, 180
CDMARSSIThresh, 188
CDMARSSIThreshListLen, 189
pCDMARSSIThreshList, 189
CDMARSSIThreshListLen
CDMARSSIThresh, 189
nas_CDMARSSIThresh, 481
CDMASSInfo, 189
ecio, 190
rssi, 190
unpack_nas_SLQSNasGetSigInfo_t, 1359
CDMASysInfo, 190
baseId, 193
baseLat, 193
baseLong, 193
bsInfoValid, 193
bsPRev, 193
bsPRevValid, 193
ccsSupported, 193
ccsSupportedValid, 193
cdmaSysIdValid, 193
isSysPrlMatch, 193
isSysPrlMatchValid, 193
MCC, 193
MNC, 193
networkID, 193
networkIdValid, 193

pRevInUse, 193
pRevInUseValid, 194
packetZone, 193
packetZoneValid, 193
sysInfoCDMA, 194
systemID, 194
CDMASysInfoExt, 194
imsi_11_12, 194
MCC, 194
CDMASystemInfoExt
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1335
CHAR
SwiDataTypes.h, 2395
CK_MAX_SIZE
dms.h, 1733
CLIPResp, 200
ActiveStatus, 201
ProvisionStatus, 201
CLIRResp, 201
ActiveStatus, 202
ProvisionStatus, 202
CNAPResp, 203
ActiveStatus, 204
ProvisionStatus, 204
COLPResp, 204
ActiveStatus, 205
ProvisionStatus, 205
COLRResp, 205
ActiveStatus, 205
ProvisionStatus, 205
CONFIG_LEN
qaGobiApiSms.h, 2171
CQIValueCW0
LteCQIParm, 438
unpack_nas_SLQSSwiGetLteCQI_t, 1373
CQIValueCW1
LteCQIParm, 438
unpack_nas_SLQSSwiGetLteCQI_t, 1373
CRTlv
unpack_wds_SLQSDUNCallInfoCallBack_ind_t, 1534
CSDomain
unpack_nas_GetServingNetwork_t, 1316
CSGID, 215
id, 216
mcc, 216
mnc, 216
mncPcsDigits, 216
rat, 216
CSTlv
unpack_wds_SLQSDUNCallInfoCallBack_ind_t, 1534
CUGIndex
CUGInfo, 217
voice_CUGInfo, 1597
CUGInfo, 216
CUGIndex, 217
SuppOA, 217
SuppPrefCUG, 217
CallBacK registration (CBK), 47
CallBarStatus
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1335
callBarStatus, 160
csBarStatus, 161
psBarStatus, 161
CallBarringSysInfo, 159
csBarStatus, 160
psBarStatus, 160
callDuration
unpack_wds_GetSessionDuration_t, 1530
CallEndReason
DUNCallInfoInd, 265
wds_LastMdmCallEndRsnTlv, 1692
callEndReason
arrCallEndReason, 147
unpack_wds_SLQSGetDUNCallInfo_t, 1541
voice_arrCallEndReason, 1575
CallFWExtInfo
getCallFWExtInfo, 297
voice_getCallFWExtInfo, 1604
callFWExtInfo, 165
noReplyTimer, 166
numLen, 166
numPlan, 167
numType, 167
number, 166
PI, 167
SI, 167
SvcClass, 167
SvcStatus, 167
CallFWInfo
getCallFWInfo, 298
voice_getCallFWInfo, 1604
callFWInfo, 167
noReplyTimer, 167
numLen, 168
number, 167
SvcClass, 168
SvcStatus, 168
callFwdTypeAndPlan, 164
numberPlan, 165
numberType, 165
callID
allCallsAlphaIDInfo, 133
allCallsDiagInfo, 134
allCallsUUSInfo, 134
arrAlertingPattern, 144
arrAlertingType, 145
arrCallEndReason, 147
arrSvcOption, 150
callInfo, 169
DTMFInfo, 264
getAllCallRmtPtyName, 290
getAllCallRmtPtyNum, 291

pack_voice_SLQSVoiceGetCallInfo_t, 831
pack_voice_SLQSVoiceStopContDTMF_t, 842
peerNumberInfo, 875
unpack_voice_OTASPStatusCallback_ind_t, 1472
unpack_voice_SLQSVoiceStopContDTMF_t, 1505
unpack_voice_SUPSNotificationCallback_ind_t, 1510
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
unpack_voice_voicePrivacyChangeCallback_ind_t, 1514
voice_allCallsAlphaIDInfo, 1570
voice_allCallsDiagInfo, 1571
voice_allCallsUUSInfo, 1571
voice_arrAlertingPattern, 1573
voice_arrAlertingType, 1574
voice_arrCallEndReason, 1575
voice_arrSvcOption, 1579
voice_callInfo, 1589
voice_DTMFInfo, 1599
voice_getAllCallRmtPtyName, 1603
voice_getAllCallRmtPtyNum, 1603
voice_peerNumberInfo, 1607
voiceCallInfoReq, 1620
voiceInfoRec, 1648
voiceOTASPStatusInfo, 1651
voicePrivacyInfo, 1652
voiceStopContDTMFinfo, 1664
voiceSUPSNotification, 1668
callInfo, 168
callID, 169
callState, 169
callType, 169
direction, 169
mode, 169
callNumber
pack_voice_SLQSVoiceDialCall_t, 828
voiceCallRequestParams, 1624
callState
callInfo, 169
voice_callInfo, 1589
callType
callInfo, 169
voice_callInfo, 1589
calledPartyInfo, 161
numLen, 162
numPlan, 162
numType, 162
number, 162
PI, 162
SI, 162
CalledPartyNum
arrCalledPartyNum, 146
voice_arrCalledPartyNum, 1575
calledPartySubAdd, 162
extBit, 163
oddEvenInd, 163
subAddr, 163
subAddrLen, 163
subAddrType, 163
callerID
callerIDInfo, 164
connectNumInfo, 210
voice_callerIDInfo, 1584
voice_connectNumInfo, 1596
callerIDInfo, 163
callerID, 164
callerIDLen, 164
PI, 164
callerIDLen
callerIDInfo, 164
connectNumInfo, 210
voice_callerIDInfo, 1584
voice_connectNumInfo, 1596
callerName
remotePartyName, 964
voice_remotePartyName, 1612
Callinfo
getAllCallInformation, 290
voice_getAllCallInformation, 1602
callingPartyInfo, 169
numLen, 171
numPlan, 171
numType, 171
number, 171
PI, 171
SI, 171
campedCiotLteOpMode
LteCiotOpModeTlv, 437
nas_LteCiotOpModeTlv, 524
CancelUSSD
qaGobiApiVoice.h, 2288
Card Application Toolkit (CAT), 50
cardResult, 171
sw1, 171
sw2, 171
cardState
slotInf, 1030
slotInfo, 1031
uim_slotInfo, 1167
cardStatus, 171
index1xPri, 172
index1xSec, 172
indexGwPri, 172
indexGwSec, 172
numSlot, 172
SlotInfo, 172
Carrier
fwinfo_s, 287
carrier
CurrentImgList, 220
unpack_dms_SLQSSwiGetFirmwareCurr_t, 1257
carrier_str
slqsfwinfo_s, 1034
unpack_dms_GetFirmwareInfo_t, 1219
CarrierImage_t, 173
m_FwBuildId, 173

m_FwImageId, 173
m_PriBuildId, 174
m_PriImageId, 174
m_nCarrierId, 173
m_nFolderId, 174
m_nStorage, 174
CatAlPhaIdentifierTlv, 174
AlphaID, 174
AlphaIDLength, 174
ReferenceID, 174
CatAlphaIdtfr
currentCatEvent, 219
CatCommonEventTlv, 174
CatEvent, 174
EventID, 174
EventLength, 174
TlvPresent, 174
CatEndPS
currentCatEvent, 219
CatEndProactiveSessionTlv, 175
EndProactiveSession, 175
CatEvIDData
currentCatEvent, 219
CatEvent
CatCommonEventTlv, 174
CatEventIDDataTlv, 175
Data, 176
DataLength, 176
ReferenceID, 176
CatEventListTlv, 176
SetupEventList, 176
CatEventLst
currentCatEvent, 219
CatRefresh
currentCatEvent, 219
CatRefreshTlv, 176
RefreshMode, 177
RefreshStage, 177
causeCode
SMSAsyncRawSend_s, 1066
unpack_sms_SLQSWmsAsyncRawSendCallBack-_ind_t, 1440
ccSUPSType, 177
reason, 177
svcType, 177
ccsSupported
CDMASysInfo, 193
nas_CDMASysInfo, 484
ccsSupportedValid
CDMASysInfo, 193
nas_CDMASysInfo, 484
cdmaMsgDecodingParams, 180
absoluteValidity, 182
mcTimeStamp, 182
messageLength, 183
pAlertPriority, 183
pCallbkAddr, 183
pCallbkAddrLength, 183
pDisplayMode, 183
pLanguage, 183
pMessage, 183
pMessageID, 183
pPriority, 183
pPrivacy, 183
pReadAcknowledgementReq, 183
pRelativeValidity, 183
pSenderAddrLength, 183
pTextMsgLength, 183
pUserAcknowledgementReq, 183
senderAddr, 183
textMsg, 183
cdmaMsgDecodingParamsExt, 183
absoluteValidity, 186
mcTimeStamp, 186
messageLength, 186
pAlertPriority, 186
pCallbkAddr, 186
pCallbkAddrLength, 186
pDisplayMode, 186
pIsUDHPresent, 186
pLanguage, 186
pMessage, 186
pMessageID, 186
pPartNum, 186
pPriority, 186
pPrivacy, 186
pReadAcknowledgementReq, 186
pReferenceNum, 186
pRelativeValidity, 186
pSenderAddr, 186
pSenderAddrLength, 186
pTextMsg, 186
pTextMsgLength, 186
pTotalNum, 186
pUserAcknowledgementReq, 186
cdmaMsgEncodingParams, 187
messageId, 188
pCallbackAddr, 188
pDestAddr, 188
pEncodingAlphabet, 188
pMessage, 188
pMessageSize, 188
pPriority, 188
pRelValidity, 188
pTextMsg, 188
textMsgLength, 188
cdmaSSInfo, 189
ecio, 189
rssi, 189
cdmaSysIdValid
CDMASysInfo, 193
nas_CDMASysInfo, 484
cell_resel_priority
infoInterFreq, 365
nas_infoInterFreq, 520
cellBroadcastCap

AddSysInfo, 132
nas_AddSysInfo, 474
CellDb, 194
mask, 195
CellID
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1335
cellID
GERANInfo, 288
nas_GERANInfo, 506
nas_QmisNasSlqsNasPCICellInfo, 580
nas_UMTSInfo, 616
SlqsNasPCICellInfo, 1037
UMTSInfo, 1195
cellId
GSMSysInfo, 332
LTESysInfo, 463
nas_GSMSysInfo, 512
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 562
nas_WCDMASysInfo, 624
NR5GSystemInfoTlv, 694
WCDMASysInfo, 1678
cellIdValid
gsmCellInfo, 328
GSMSysInfo, 332
LTESysInfo, 463
nas_gsmCellInfo, 508
nas_GSMSysInfo, 512
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 562
nas_WCDMASysInfo, 625
NR5GSystemInfoTlv, 694
WCDMASysInfo, 1678
cellInterFreqParams
infoInterFreq, 365
nas_infoInterFreq, 520
cellIsTDD
nas_umtsLTENbrCell, 618
umtsLTENbrCell, 1197
CellParams
LTEInfoIntrafreq, 445
nas_LTEInfoIntrafreq, 531
cellParams, 195
pci, 196
rsrp, 196
rsrq, 196
rssi, 196
srxlev, 196
cellReselPriority
lteGsmCellInfo, 440
LTEInfoIntrafreq, 445
lteWcdmaCellInfo, 464
nas_lteGsmCellInfo, 526
nas_LTEInfoIntrafreq, 531
nas_lteWcdmaCellInfo, 548
cells_len
infoInterFreq, 365
lteGsmCellInfo, 440
nas_infoInterFreq, 520
nas_lteGsmCellInfo, 526
cellsLen
LTEInfoIntrafreq, 445
lteWcdmaCellInfo, 464
nas_LTEInfoIntrafreq, 531
nas_lteWcdmaCellInfo, 548
CfgValue
intfaceCfgTlv, 366
pack_swidms_SLQSSwiDmsSetUsbComp_t, 806
setIntfaceCfgTlv, 1009
swidms_intfaceCfgTlv, 1094
chaddr
wds_DHCPv4HWConfig, 1686
WdsDHCPv4HWConfig, 1705
wdsDhcpv4HwConfig, 1706
chaddrLen
wds_DHCPv4HWConfig, 1686
WdsDHCPv4HWConfig, 1705
wdsDhcpv4HwConfig, 1706
changePIN
pack_uim_ChangePin_t, 812
UIMChangePinReq, 1173
changeUIMPIN, 196
oldPINLen, 197
oldPINVal, 197
pinID, 197
pinLen, 197
pinVal, 197
ChannelRate, 197
CurrChanRxRate, 197
CurrChanTxRate, 197
DUNCallInfoInd, 265
MaxChanRxRate, 197
MaxChanTxRate, 197
wds_ChannelRateTlv, 1680
channelRate, 198
CurrChanRxRate, 198
CurrChanTxRate, 198
unpack_wds_SLQSGetDUNCallInfo_t, 1541
Chipset
DeviceConfigDetail, 242
nas_DeviceConfigDetail, 497
CiotAOPTlv
NASQmiCbkNasSystemSelPrefInd, 667
CiotAcqOrderLen
NASCiotAcqOrderPrefTlv, 628
ciotAcqOrderLen
ciotAcqOrderPref, 199
CiotAcqOrderPrefTlv, 200
nas_ciotAcqOrderPref, 487
nas_CiotAcqOrderPrefTlv, 488
CiotAcqOrderPref
NASCiotAcqOrderPrefTlv, 628
ciotAcqOrderPref, 198
ciotAcqOrderLen, 199
pCiotAcqOrder, 199

CiotAcqOrderPrefTlv, 199
ciotAcqOrderLen, 200
pCiotAcqOrder, 200
TlvPresent, 200
CiotLteOpModePref
NASCiotLteOpModePrefTlv, 629
ciotLteOpModePref
CiotLteOpModePrefTlv, 200
nas_CiotLteOpModePrefTlv, 488
CiotLteOpModePrefTlv, 200
ciotLteOpModePref, 200
TlvPresent, 200
CiotOpMPTlv
NASQmiCbkNasSystemSelPrefInd, 668
ckLen
depersonalizationInformation, 240
uim_depersonalizationInformation, 1153
ckVal
depersonalizationInformation, 240
uim_depersonalizationInformation, 1153
clear
pack_dms_SLQSSwiGetCrashInfo_t, 716
ClkInfo, 202
mask, 203
codingScheme
nas_PLMNNetworkNameData, 574
PLMNNetworkNameData, 887
remotePartyName, 964
voice_remotePartyName, 1612
CommInfo, 205
imsRegState, 207
modemMode, 207
psState, 207
systemMode, 207
temperature, 207
common.h
eAUDIO, 1723
eCAT, 1722
eCTL, 1722
eDMS, 1722
eIMS, 1722
eIMSA, 1723
eIND, 1723
eLOC, 1722
eLOG_DEBUG, 1722
eLOG_FATAL, 1722
eLOG_INFO, 1722
eLOG_WARN, 1722
eNAS, 1722
ePDS, 1722
eQOS, 1722
eREQ, 1723
eRMS, 1723
eRSP, 1723
eSAR, 1722
eSMS, 1722
eSWIAUDIO, 1723
eSWIDMS, 1723
eSWILOC, 1723
eSWIM2MCMD, 1723
eSWIM2MCMD_AVC2, 1723
eSWIOMA, 1723
eSWIOMAEXT, 1723
eTIMEOUT_10_S, 1723
eTIMEOUT_20_S, 1723
eTIMEOUT_2_S, 1723
eTIMEOUT_300_S, 1723
eTIMEOUT_30_S, 1723
eTIMEOUT_5_S, 1723
eTIMEOUT_60_S, 1723
eTIMEOUT_8_S, 1723
eTIMEOUT_DEFAULT, 1723
eTMD, 1722
eUIM, 1722
eVOICE, 1722
eWDS, 1722
common.h, 1719
eLOG_LEVEL, 1722
eQMI_SVC, 1722
eTimeout, 1723
fill_pack_ctx, 1723
fill_sdu_hdr, 1723
get_version, 1723
glog, 1725
gloglvl, 1725
helper_get_error_code, 1723
helper_get_error_reason, 1724
helper_get_req_str, 1724
helper_get_resp_ctx, 1724
helper_get_xid, 1724
helper_isBootLoader_DebugEnabled, 1724
helper_set_log_func, 1724
helper_set_log_lvl, 1725
liteqmi_GetVersion, 1725
liteqmi_helper_decode7bitAsciiEncString, 1725
liteqmi_log, 1725
logger, 1722
MINREQBKLEN, 1721
MSGID_AND_LEN, 1721
MSGID_DONT_CARE, 1721
msgtype, 1723
SDU_HDR_LEN, 1722
UNUSEDPARAM, 1722
unpack_result_code_only, 1725
commonInfo
swiModemStatusResp, 1104
unpack_nas_SLQSNasSwiModemStatus_t, 1367
ConcSvcInfo
unpack_nas_SLQSGetServingSystem_t, 1336
concSvcInfo
qaQmiServingSystemParam, 915
confidence
pack_loc_SLQSLOCSetCradleMountConfig_t, 739
Config
_SwiAvmsEventInd, 113
conn_status

unpack_wds_SLQSSetPacketSrvStatusCallback_-t, 1548
ConnRateElmntsV4
WdsConnectionRate, 1702
ConnRateElmntsV6
WdsConnectionRate, 1702
connStatus
_packetSrvStatus, 76
connectNumInfo, 208
callerID, 210
callerIDLen, 210
numPlan, 210
numPresInd, 210
numType, 210
screeningInd, 210
ConnectedPartyNum
arrConnectPartyNum, 148
voice_arrConnectPartyNum, 1576
ConnectionRequest
_SwiAvmsEventInd, 113
ConnectionStatus, 208
MDMCallDuration, 208
MDMConnStatus, 208
connectionStatus, 207
MDMCallDuration, 208
MDMConnStatus, 208
unpack_wds_GetSessionState_t, 1530
unpack_wds_SLQSGetDUNCallInfo_t, 1541
connetionState
imsaPdpStatusInfo, 350
content
authenticateResult, 152
readResult, 959
uim_authenticateResult, 1148
uim_readResult, 1160
contentLen
authenticateResult, 152
readResult, 959
uim_authenticateResult, 1148
uim_readResult, 1160
context
authenticationData, 152
uim_authenticationData, 1149
contextId
pack_wds_SLQSWdsSwiPDPRuntimeSettings_t, 867
swiPDPRuntimeSettingsReq, 1106
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
contextType
pack_wds_SLQSWdsSwiPDPRuntimeSettings_t, 867
swiPDPRuntimeSettingsReq, 1106
ControlMac
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
count
swidms_SwiDmsGetHWWatchdog, 1096
SwiDmsGetHWWatchdog, 1097
count0
nas_RankIndicatorTlv, 582
Count1
RankIndicatorInd, 958
count1
nas_RankIndicatorTlv, 582
Count2
RankIndicatorInd, 958
countryInitials
nas_PLMNNetworkNameData, 574
PLMNNetworkNameData, 887
coverage
altitudeSrcInfo, 136
altSrcInfo_t, 137
cphy_ca_dl_bandwidth
NASPhyCaAggScellArray, 658
PhyCaAggScellArray, 879
cphy_scell_info_list_len
NASPhyCaAggScellArray, 658
PhyCaAggScellArray, 879
cpich_ecno
nas_wcdmaCellInfo, 620
wcdmaCellInfo, 1669
cpich_rscp
nas_wcdmaCellInfo, 620
wcdmaCellInfo, 1669
cradleMountConfigStatus
QmiCbkLocCradleMountInd, 922
unpack_loc_CradleMountCallback_Ind_t, 1281
crashAction
pack_dms_SetCrashAction_t, 708
crashData
CrashInfo, 211
crashInformation, 213
crashId
CrashInfo, 211
crashInformation, 213
CrashInfo, 210
crashData, 211
crashId, 211
crashStrLen, 211
gcDumpStrLen, 211
numCrashes, 211
pCrashString, 211
pGCDumpString, 211
crashInfo
crashInfoParams, 212
crashInfoParam
unpack_dms_SLQSSwiGetCrashInfo_t, 1255
CrashInfoParams, 211
pCrashInfo, 212
pDevCrashStatus, 212
crashInfoParams, 212
crashInfo, 212
crashStatus, 212
crashInformation, 212
crashData, 213

crashId, 213
crashString, 213
crashStrlen, 213
gcdumpString, 213
gcdumpStrlen, 213
numCrashes, 213
crashStatus
crashInfoParams, 212
crashStrLen
CrashInfo, 211
crashString
crashInformation, 213
crashStrlen
crashInformation, 213
CreateProfileIn, 213
curProfile, 214
pProfileID, 214
pProfileType, 214
CreateProfileOut, 214
pExtErrorCode, 215
pProfileIndex, 215
pProfileType, 215
csAttachState
nas_servSystem, 600
NASServingSystemInfo, 670
ServingSystemInfo, 994
servSystem, 996
csBarStatus
CallBarringSysInfo, 160
callBarStatus, 161
nas_CallBarringSysInfo, 477
nas_callBarStatus, 478
CsgId, 215
csgId, 215
TlvPresent, 215
csgId
CsgId, 215
nas_CsgId, 490
cur_carr_name
slqsfwinfo_s, 1034
unpack_dms_GetFirmwareInfo_t, 1220
cur_carr_rev
slqsfwinfo_s, 1034
unpack_dms_GetFirmwareInfo_t, 1220
curAMRConfig, 217
gsmAmrStat, 218
wcdmaAmrStat, 218
curDataBearerTechnology
unpack_wds_SLQSGetDataBearerTechnology_t, 1538
curProfile
_GetProfileSettingOut, 71
CreateProfileIn, 214
ModifyProfileIn, 469
pack_wds_SLQSModifyProfile_t, 859
UnPackGetProfileSettingOut, 1560
CurrChanRxRate
ChannelRate, 197
channelRate, 198
dunchannelRate, 266
wds_channelRate, 1680
CurrChanTxRate
ChannelRate, 197
channelRate, 198
dunchannelRate, 266
wds_channelRate, 1680
currDBTechAvail
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1553
CurrDataSysStat, 218
pCurrNetworkInfo, 219
pNetworkInfoLen, 219
pPrefNetwork, 219
CurrImageInfo, 221
buildID, 222
buildIDLen, 222
imageType, 222
uniqueID, 222
currNWInfo
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1553
CurrNetworkInfo, 222
NetworkType, 223
RATMask, 224
SOMask, 224
currNetworkInfo, 224
NetworkType, 224
RATMask, 224
SOMask, 224
unpack_wds_SLQSGetCurrDataSystemStat_t, 1536
current_channel_rx_rate
unpack_wds_SLQSGetCurrentChannelRate_t, 1538
WDSSWICurrentChannelRates, 1718
current_channel_tx_rate
unpack_wds_SLQSGetCurrentChannelRate_t, 1538
WDSSWICurrentChannelRates, 1718
currentCatEvent, 219
CatAlphaIdtfr, 219
CatEndPS, 219
CatEvIDData, 219
CatEventLst, 219
CatRefresh, 219
CurrentCfgType
intfaceCfgTlv, 366
swidms_intfaceCfgTlv, 1094
currentChannelRXRate
unpack_wds_GetConnectionRate_t, 1517
currentChannelTXRate
unpack_wds_GetConnectionRate_t, 1517
currentDataBearer
pack_wds_SLQSSetWdsEventCallback_t, 862
CurrentImgList, 219
carrier, 220

fwvers, 220
numEntries, 220
pCurrImgInfo, 220
pkgver, 220
priver, 220
currentMitigationLvl
QmiCbkTmdMitiLvlRptInd, 942
currentNetwork
dataBearerTechnology, 234
qmiWDSDataBearerTechnology, 947
CurrentPLMN
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1336
currentPLMN, 220
MCC, 221
MNC, 221
netDescr, 221
netDescrLength, 221
cust_attr
custSettingInfo, 229
DMScustSettingInfo, 255
cust_id
custSettingInfo, 229
DMScustSettingInfo, 255
DMSgetCustomInput, 257
getCustomInput, 299
pack_dms_GetCustFeaturesV2_t, 707
pack_dms_SetCustFeaturesV2_t, 711
setCustomSettingV2, 1003
cust_value
custSettingInfo, 229
DMScustSettingInfo, 255
pack_dms_SetCustFeaturesV2_t, 711
setCustomSettingV2, 1003
custFeaturesInfo, 224
GpsEnable, 226
pDHCPRelayEnabled, 226
pDisableIMSI, 226
pGPSLPM, 226
pGPSSel, 226
pIPFamSupport, 226
pIsVoiceEnabled, 226
pRMAutoConnect, 226
pSMSSupport, 226
qaGobiApiDms.h, 2005
custFeaturesSetting, 227
pDHCPRelayEnabled, 228
pGPSEnable, 228
pGPSLPM, 228
pGPSSel, 228
pIsVoiceEnabled, 228
qaGobiApiDms.h, 2006
custSetting
custSettingList, 229
DMScustSettingList, 256
custSettingInfo, 228
cust_attr, 229
cust_id, 229
cust_value, 229
id_length, 229
value_length, 229
custSettingList, 229
custSetting, 229
list_type, 229
num_instances, 230
CustomSCP
unpack_nas_GetCDMANetworkParameters_t, 1308
CwtMute
GetM2MAudioProfileResp, 312
GetM2MAVMuteResp, 314
cycleLength
EdrxCycleLength, 269
nas_EdrxCycleLength, 500

DEVICE_STATE_BOOT
qaGobiApiCbk.h, 1954
DEVICE_STATE_DISCONNECTED
qaGobiApiCbk.h, 1954
DEVICE_STATE_READY
qaGobiApiCbk.h, 1954
DEVICE_STATE_SERIAL_ONLY
qaGobiApiCbk.h, 1954
DBTTlv
unpack_wds_SLQSDUNCallInfoCallBack_ind_t, 1534
dBTechAvail
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1553
dBTechExtRatValue
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
dBTechExtSoMask
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
dBTechnology
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
dBtechExtAvail
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1553
dBtechnologyExt
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
DEFAULTBYTEVALUE
qaGobiApiPds.h, 2145
DEFAULTLONGVALUE
qaGobiApiPds.h, 2145
DEFAULTWORDVALUE
qaGobiApiPds.h, 2145
DEREGISTER_EVENT
qaGobiApiCbk.h, 1912
DEREGISTER_SRV
qaGobiApiCbk.h, 1912
DEVICE_OFFLINE
qaGobiApiFms.h, 2046
DEVICE_RESET

qaGobiApiFms.h, 2046
DEVICE_SHUTDOWN
qaGobiApiFms.h, 2046
DHCPOption, 243
optCode, 243
optValLen, 243
pOptVal, 243
DHCPOptionList, 243
numOpt, 244
pOptions, 244
DHCPRelayEnabled
pack_dms_SetCustFeature_t, 710
unpack_dms_GetCustFeature_t, 1211
DHCPv4LeaseOptTlv
unpack_wds_DHCPv4ClientLease_ind_t, 1515
DHCPv4LeaseStateTlv
unpack_wds_DHCPv4ClientLease_ind_t, 1515
dLatitude
unpack_pds_SetEventReport_Ind_t, 1390
dLongitude
unpack_pds_SetEventReport_Ind_t, 1390
DMS_IMGDETAILS_LEN
dms.h, 1733
DMS_PM_FACTORY
dms.h, 1733
DMS_PM_LOW
dms.h, 1733
DMS_PM_OFFLINE
dms.h, 1733
DMS_PM_ONLINE
dms.h, 1733
DMS_PM_RESET
dms.h, 1733
DMS_PM_SHUT_DOWN
dms.h, 1733
DMS_VALID_FSN_LEN
dms.h, 1734
DMScustSettingInfo, 255
cust_attr, 255
cust_id, 255
cust_value, 255
id_length, 255
value_length, 255
DMScustSettingList, 256
custSetting, 256
list_type, 256
num_instances, 256
DMSgetCustomFeatureV2, 256
pCustSettingInfo, 257
pCustSettingList, 257
pGetCustomInput, 257
DMSgetCustomInput, 257
cust_id, 257
list_type, 257
DRCCover
DRCParams, 263
nas_DRCParams, 498
DRCParams, 263
DRCCover, 263
DRCValue, 263
DRCValue
DRCParams, 263
nas_DRCParams, 498
DSTlv
unpack_wds_SLQSDUNCallInfoCallBack_ind_t, 1534
DTMFEvent
DTMFInfo, 264
voice_DTMFInfo, 1599
DTMFInfo, 263
callID, 264
DTMFEvent, 264
digitBuff, 264
digitCnt, 264
DTMFInformation
unpack_voice_DTMFEventCallback_ind_t, 1471
voiceDTMFEventInfo, 1627
DTMFInterdigitInterval
DTMFLengths, 264
voice_DTMFLengths, 1600
DTMFLengths, 264
DTMFInterdigitInterval, 264
DTMFPulseWidth, 265
DTMFPulseWidth
DTMFLengths, 265
voice_DTMFLengths, 1600
DTMFdigit
pack_voice_SLQSVoiceStartContDTMF_t, 842
voiceContDTMFinfo, 1626
DTMInd
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1336
DUNCallInfoInd, 265
CallEndReason, 265
ChannelRate, 265
DataBearerTech, 265
DormancyStatus, 265
MdmConnStatus, 265
RXOKBytesCount, 265
TXOKBytesCount, 265
Data
CatEventIDDataTlv, 176
data
authenticationData, 153
sms_DateTime, 1052
sms_timestemp, 1064
SMSCAddress, 1066
sMSCAddressInfo, 1067
SMSEtwsMessage, 1068
sMSEtwsMessageInfo, 1069
SMSTransferRouteMTMessage, 1080
sMSTransferRouteMTMessageInfo, 1081
SwiOTAMsg_s, 1105
uim_authenticationData, 1149
data_buf
NASOTAMessageTlv, 656

data_len
NASOTAMessageTlv, 656
SwiOTAMsg_s, 1105
dataBearer
pack_wds_SLQSSetWdsEventCallback_t, 862
dataBearerMask
dataBearers, 230
unpack_wds_SLQSGetDataBearerTechnology_t, 1538
DataBearerTech, 230
DUNCallInfoInd, 265
ratValue, 232
soMask, 232
techType, 232
wds_DataBearTechTlv, 1682
dataBearerTech
unpack_wds_SLQSGetDUNCallInfo_t, 1541
DataBearerTechExt, 232
pBearerTech, 233
pLastBearerTech, 233
dataBearerTechExt
pack_wds_SLQSSetWdsEventCallback_t, 862
dataBearerTechnology, 233
currentNetwork, 234
ratMask, 235
soMask, 235
dataBearers, 230
dataBearerMask, 230
pCurDataBearerTechnology, 230
pLastCallDataBearerTechnology, 230
dataCapabilities
dataSrvCapabilities, 236
nas_dataSrvCapabilities, 493
dataCapabilitiesLen
dataSrvCapabilities, 236
nas_dataSrvCapabilities, 493
DataCaps
unpack_nas_GetServingNetwork_t, 1316
unpack_nas_GetServingNetworkCapabilities_t, 1318
dataCaps
unpack_nas_SetDataCapabilitiesCallback_ind_t, 1321
DataCapsLen
unpack_nas_GetServingNetwork_t, 1316
unpack_nas_GetServingNetworkCapabilities_t, 1318
dataCapsSize
unpack_nas_SetDataCapabilitiesCallback_ind_t, 1321
dataLen
authenticationData, 153
uim_authenticationData, 1149
DataLength
CatEventIDDataTlv, 176
DataRate
unpack_qos_swiQosFlow_t, 1416
dataRate, 235
dataRateMax, 235
guaranteedRate, 235
dataRateMax
dataRate, 235
unpack_qos_dataRate_t, 1398
dataServiceCaCapability
unpack_dms_GetDeviceCapabilities_t, 1214
DataServiceCapability
unpack_dms_GetDeviceCap_t, 1213
DataSessionStatus
_SwiAvmsEventInd, 113
DataSrvCapabilities
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1336
dataSrvCapabilities, 235
dataCapabilities, 236
dataCapabilitiesLen, 236
DataStatusDetail, 236
IPAddress, 237
LastErrCode, 237
dataSysStatAvail
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1553
dataSystemStatus
pack_wds_SLQSSetWdsEventCallback_t, 862
DataULongLongTlv, 238
TlvPresent, 238
ullData, 238
DataULongTlv, 238
TlvPresent, 238
ulData, 238
Date
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
wcdmaLongMsgDecodingParams, 1672
date
wcdmaMsgDecodingParams, 1673
DateLength
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
day
nas_timeInfo, 613
nas_UniversalTime, 619
timeInfo, 1134
UniversalTime, 1205
dayLtSavingAdj
nas_timeInfo, 613
timeInfo, 1134
dayOfWeek
nas_timeInfo, 613
nas_UniversalTime, 619
timeInfo, 1134
UniversalTime, 1205
daylightSavings
nas_qaQmi3Gpp2TimeZone, 577
qaQmi3Gpp2TimeZone, 911
DcsUsbPortNames, 238
AtCmdPort, 238

DmPort, 238
NmeaPort, 238
dedicatedBand
nas_RfDedicatedBandInfoElements, 589
RfDedicatedBandInfoElements, 972
defaultPDNEnabled
unpack_wds_SLQSGet3GPPConfigItem_t, 1535
DefaultRoamInd
unpack_nas_SLQSGetServingSystem_t, 1336
defaultRoamInd
qaQmiServingSystemParam, 915
delAssistDataStatus, 238
results, 239
status, 239
delayClass
GPRSQoS, 322
GPRSRequestedQoS, 323
LibPackGPRSRequestedQoS, 373
wds_GPRSQoS, 1690
DeleteStoredImage
qaGobiApiFms.h, 2049
deliveryErrSDU
LibPackUMTSQoS, 402
UMTSMinQoS, 1199
UMTSQoS, 1202
wds_UMTSMinQoS, 1699
depersonalizationInformation, 239
ckLen, 240
ckVal, 240
feature, 240
operation, 240
depersonilisationInfo
pack_uim_SLQSUIMDepersonalization_t, 816
UIMDepersonalizationReq, 1174
Description
SlqsNas3GppNetworkInfo, 1036
description
omaDmFotaTlv, 700
omaDmFotaTlvExt, 703
unpack_omaDmFotaTlv_t, 1382
descriptionlength
omaDmFotaTlv, 700
omaDmFotaTlvExt, 703
unpack_omaDmFotaTlv_t, 1382
Desription
nas_QmiNas3GppNetworkInfo, 578
destPortRangeEnd
LibPackTFTIDParams, 399
TFTIDParams, 1132
destPortRangeStart
LibPackTFTIDParams, 399
TFTIDParams, 1132
detailSvcInfo, 240
hdrHybrid, 241
hdrSrvStatus, 241
isSysForbidden, 241
srvCapability, 241
srvStatus, 242
DetailedSvcInfo
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1336
dev
qmifwinfo_s, 944
DevCrashState
unpack_dms_GetCrashAction_t, 1208
Device
SetM2MAudioAVCFGReq, 1011
Device Connectivity Service (DCS), 43
Device Management Service (DMS), 45
device_state_enum
qaGobiApiCbk.h, 1954
DeviceConfigDetail, 242
Chipset, 242
HWVersion, 242
QLIC, 243
Technology, 243
DeviceError
qmTlvResult, 952
deviceID
_MitigationDevInfo, 73
deviceIdLen
_MitigationDevInfo, 73
DeviceResult
qmTlvResult, 952
DiagInfo
allCallsDiagInfo, 134
arrDiagInfo, 148
voice_allCallsDiagInfo, 1571
voice_arrDiagInfo, 1577
diagInfo, 244
diagInfoLen, 244
diagnosticInfo, 244
diagInfoLen
diagInfo, 244
voice_diagInfo, 1598
diagnosticInfo
diagInfo, 244
voice_diagInfo, 1598
digitBuff
DTMFInfo, 264
voice_DTMFInfo, 1599
digitCnt
burstDTMFInfo, 159
DTMFInfo, 264
voice_burstDTMFInfo, 1580
voice_DTMFInfo, 1599
dirNum, 244
dirNum, 245
dirNumLen, 245
dirNum, 245
nas_dirNum, 497
dirNumLen
dirNum, 245
nas_dirNum, 497
direction
callInfo, 169

voice_callInfo, 1589
DisableIMSI
pack_dms_SetCustFeature_t, 710
unpack_dms_GetCustFeature_t, 1211
dispType
extDispRecInfo, 275
voice_extDispRecInfo, 1601
displayCondition
nas_serviceProviderName, 598
serviceProviderName, 993
dl_bw_value
nas_PhyCaAggPcellInfo, 566
nas_PhyCaAggScellDlBw, 566
nas_PhyCaAggScellInfo, 570
NASPhyCaAggPcellInfo, 657
NASPhyCaAggScellDlBw, 659
NASPhyCaAggScellInfo, 661
PhyCaAggPcellInfo, 877
PhyCaAggScellDlBw, 879
PhyCaAggScellInfo, 883
DmPort
DcsUsbPortNames, 238
dms.h, 1725
ACT_CODE_MAX_SIZE, 1733
CK_MAX_SIZE, 1733
DMS_IMGDETAILS_LEN, 1733
DMS_PM_FACTORY, 1733
DMS_PM_LOW, 1733
DMS_PM_OFFLINE, 1733
DMS_PM_ONLINE, 1733
DMS_PM_RESET, 1733
DMS_PM_SHUT_DOWN, 1733
DMS_VALID_FSN_LEN, 1734
ERI_DATA_MAX_SIZE, 1734
MAX_BUILD_ID_LEN, 1734
MEID_MAX_SIZE, 1734
pack_dms_ActivateAutomatic, 1734
pack_dms_GetActivationState, 1734
pack_dms_GetBandCapability, 1735
pack_dms_GetCrashAction, 1735
pack_dms_GetCustFeature, 1735
pack_dms_GetCustFeaturesV2, 1736
pack_dms_GetDeviceCap, 1736
pack_dms_GetDeviceCapabilities, 1737
pack_dms_GetDeviceHardwareRev, 1737
pack_dms_GetDeviceMfr, 1737
pack_dms_GetDeviceSerialNumbers, 1738
pack_dms_GetFSN, 1739
pack_dms_GetFirmwareInfo, 1738
pack_dms_GetFirmwareRevision, 1738
pack_dms_GetFirmwareRevisions, 1739
pack_dms_GetHardwareRevision, 1739
pack_dms_GetIMSI, 1740
pack_dms_GetManufacturer, 1740
pack_dms_GetModelID, 1740
pack_dms_GetNetworkTime, 1741
pack_dms_GetOfflineReason, 1741
pack_dms_GetPRLVersion, 1742
pack_dms_GetPower, 1741
pack_dms_GetSerialNumbers, 1742
pack_dms_GetUSBComp, 1742
pack_dms_GetVoiceNumber, 1743
pack_dms_ResetToFactoryDefaults, 1743
pack_dms_SLQSDmsSwiGetPCInfo, 1747
pack_dms_SLQSDmsSwiGetResetInfo, 1747
pack_dms_SLQSDmsSwiGetUimSelection, 1748
pack_dms_SLQSDmsSwiIndicationRegister, 1748
pack_dms_SLQSGetBandCapability, 1748
pack_dms_SLQSGetERIFile, 1749
pack_dms_SLQSGetPowerSaveModeConfig, 1749
pack_dms_SLQSSetPowerSaveModeConfig, 1749
pack_dms_SLQSSwiClearDyingGaspStatistics, 1750
pack_dms_SLQSSwiGetCrashInfo, 1750
pack_dms_SLQSSwiGetDyingGaspCfg, 1751
pack_dms_SLQSSwiGetDyingGaspStatistics, 1751
pack_dms_SLQSSwiGetFirmwareCurr, 1751
pack_dms_SLQSSwiGetFwUpdateStatus, 1752
pack_dms_SLQSSwiGetHostDevInfo, 1752
pack_dms_SLQSSwiGetOSInfo, 1752
pack_dms_SLQSSwiGetSerialNoExt, 1753
pack_dms_SLQSSwiSetDyingGaspCfg, 1753
pack_dms_SLQSSwiSetHostDevInfo, 1753
pack_dms_SLQSSwiSetOSInfo, 1754
pack_dms_SLQSUIMGetState, 1754
pack_dms_SetActivationStatusCallback, 1744
pack_dms_SetCrashAction, 1744
pack_dms_SetCustFeature, 1744
pack_dms_SetCustFeaturesV2, 1745
pack_dms_SetEventReport, 1745
pack_dms_SetFirmwarePreference, 1745
pack_dms_SetIndicationRegister, 1746
pack_dms_SetPower, 1746
pack_dms_SetUSBComp, 1746
pack_dms_SwiSetEventReport, 1754
pack_dms_SwiUimSelect, 1755
pack_dms_UIMChangePIN, 1755
pack_dms_UIMGetControlKeyStatus, 1755
pack_dms_UIMGetICCID, 1756
pack_dms_UIMGetPINStatus, 1756
pack_dms_UIMSetControlKeyProtection, 1757
pack_dms_UIMSetPINProtection, 1757
pack_dms_UIMUnblockControlKey, 1757
pack_dms_UIMUnblockPIN, 1758
pack_dms_UIMVerifyPIN, 1758
pack_dms_ValidateSPC, 1758
SPC_SIZE, 1734
UNIQUE_ID_LEN, 1734
unpack_dms_ActivateAutomatic, 1759
unpack_dms_GetActivationState, 1759
unpack_dms_GetBandCapability, 1760
unpack_dms_GetCrashAction, 1760
unpack_dms_GetCustFeature, 1760
unpack_dms_GetCustFeaturesV2, 1761
unpack_dms_GetDeviceCap, 1761

unpack_dms_GetDeviceCapabilities, 1761
unpack_dms_GetDeviceHardwareRev, 1762
unpack_dms_GetDeviceMfr, 1762
unpack_dms_GetDeviceSerialNumbers, 1762
unpack_dms_GetFSN, 1764
unpack_dms_GetFirmwareInfo, 1763
unpack_dms_GetFirmwareRevision, 1763
unpack_dms_GetFirmwareRevisions, 1763
unpack_dms_GetHardwareRevision, 1764
unpack_dms_GetIMSI, 1764
unpack_dms_GetManufacturer, 1765
unpack_dms_GetModelID, 1765
unpack_dms_GetNetworkTime, 1766
unpack_dms_GetOfflineReason, 1766
unpack_dms_GetPRLVersion, 1767
unpack_dms_GetPower, 1766
unpack_dms_GetSerialNumbers, 1767
unpack_dms_GetUSBComp, 1767
unpack_dms_GetVoiceNumber, 1768
unpack_dms_PSMCfgChange_ind, 1768
unpack_dms_ResetToFactoryDefaults, 1768
unpack_dms_SLQSDmsSwiGetPCInfo, 1772
unpack_dms_SLQSDmsSwiGetResetInfo, 1773
unpack_dms_SLQSDmsSwiGetResetInfo_Ind, 1773
unpack_dms_SLQSDmsSwiGetUimSelection, 1773
unpack_dms_SLQSDmsSwiIndicationRegister, 1774
unpack_dms_SLQSGetBandCapability, 1774
unpack_dms_SLQSGetERIFile, 1774
unpack_dms_SLQSGetPowerSaveModeConfig, 1775
unpack_dms_SLQSSetPowerSaveModeConfig, 1775
unpack_dms_SLQSSwiClearDyingGaspStatistics, 1776
unpack_dms_SLQSSwiGetCrashInfo, 1776
unpack_dms_SLQSSwiGetDyingGaspCfg, 1776
unpack_dms_SLQSSwiGetDyingGaspStatistics, 1777
unpack_dms_SLQSSwiGetFirmwareCurr, 1777
unpack_dms_SLQSSwiGetFwUpdateStatus, 1777
unpack_dms_SLQSSwiGetHostDevInfo, 1778
unpack_dms_SLQSSwiGetOSInfo, 1778
unpack_dms_SLQSSwiGetSerialNoExt, 1778
unpack_dms_SLQSSwiSetDyingGaspCfg, 1779
unpack_dms_SLQSSwiSetHostDevInfo, 1779
unpack_dms_SLQSSwiSetOSInfo, 1779
unpack_dms_SLQSUIMGetState, 1780
unpack_dms_SetActivationStatusCallback, 1769
unpack_dms_SetCrashAction, 1769
unpack_dms_SetCustFeature, 1769
unpack_dms_SetCustFeaturesV2, 1770
unpack_dms_SetEventReport, 1770
unpack_dms_SetEventReport_ind, 1770
unpack_dms_SetFirmwarePreference, 1771
unpack_dms_SetIndicationRegister, 1771
unpack_dms_SetPower, 1772
unpack_dms_SetUSBComp, 1772
unpack_dms_SwiEventReportCallBack_ind, 1780
unpack_dms_SwiSetEventReport, 1780
unpack_dms_SwiUimSelect, 1781
unpack_dms_UIMChangePIN, 1781
unpack_dms_UIMGetControlKeyStatus, 1781
unpack_dms_UIMGetICCID, 1782
unpack_dms_UIMGetPINStatus, 1782
unpack_dms_UIMSetControlKeyProtection, 1782
unpack_dms_UIMSetPINProtection, 1783
unpack_dms_UIMUnblockControlKey, 1783
unpack_dms_UIMUnblockPIN, 1783
unpack_dms_UIMVerifyPIN, 1784
unpack_dms_ValidateSPC, 1784
dms_ActivationStatusTlv, 245
activationStatus, 246
TlvPresent, 246
dms_OperatingModeTlv, 246
operatingMode, 246
TlvPresent, 246
dms_PSMActiveTimerIndTlv, 246
ActiveTimerInd, 247
TlvPresent, 247
dms_PSMActiveTimerTlv, 247
activeTimer, 247
TlvPresent, 247
dms_PSMDurationDueToOOSTlv, 247
durationDueToOOS, 248
TlvPresent, 248
dms_PSMDurationThresholdTlv, 248
durationThreshold, 248
TlvPresent, 248
dms_PSMEarlyWakeupTimeTlv, 248
earlyWakeupTime, 249
TlvPresent, 249
dms_PSMEnableStateIndTlv, 249
EnableStateInd, 249
TlvPresent, 249
dms_PSMEnableStateTlv, 249
enableState, 250
TlvPresent, 250
dms_PSMPeriodicUpdateTimerIndTlv, 250
PeriodicUpdateTimerInd, 250
TlvPresent, 250
dms_PSMPeriodicUpdateTimerTlv, 250
periodicUpdateTimer, 251
TlvPresent, 251
dms_PSMRandomizationWindowTlv, 251
randomizationWindow, 251
TlvPresent, 251
dms_TemperatureTlv, 251
TempStat, 252
Temperature, 252
TlvPresent, 252
dms_UimAutoSwitchActSlotTlv, 252
TlvPresent, 253
uimAutoSwitchActSlot, 253

dms_UimStatusTlv, 253
event, 253
intf, 253
TlvPresent, 253
dms_VoltageTlv, 253
TlvPresent, 254
VoltStat, 254
Voltage, 254
dmsCurrentPRLInfo, 254
pPRLPreference, 254
pPRLVersion, 255
qaGobiApiDms.h, 2007
dmsIndicationRegisterReq, 257
pSwiGetResetInd, 258
dmsPsmCfgParamChange, 258
pActiveTimer, 258
pEnableState, 258
pPeriodicUpdateTimer, 258
dmsSwiGetPCInfo, 259
opMode, 260
pLpmFlag, 260
pPersistentLpm, 260
pPowerOffMode, 260
pWdisable, 260
dmsSwiGetResetInfo, 260
source, 261
type, 261
dmsSwiGetUIMSelection, 261
pUimAutoSwitchActSlot, 261
uimSelect, 261
Domain, 262
domainLen, 262
domainName, 262
domain
DomainNameList, 262
wds_DomainNameList, 1689
domainLen
Domain, 262
wds_Domain, 1688
DomainList
unpack_wds_SLQSGetRuntimeSettings_t, 1545
domainName
Domain, 262
wds_Domain, 1688
DomainNameList, 262
domain, 262
numInstances, 262
DormancyStat
wds_DormStatTlv, 1689
dormancyStatAvail
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
dormancyState
unpack_wds_GetDormancyState_t, 1522
DormancyStatus
DUNCallInfoInd, 265
dormancyStatus
pack_wds_SLQSSetWdsEventCallback_t, 862
unpack_wds_SLQSGetDUNCallInfo_t, 1541
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
downLink
NSSAudioCtrl, 695
voice_NSSAudioCtrl, 1606
DownloadToSlot
qaGobiApiFms.h, 2049
dscp
QosMap, 958
dtmSupp
GSMSysInfo, 332
nas_GSMSysInfo, 512
dtmSuppValid
GSMSysInfo, 332
nas_GSMSysInfo, 512
dunchannelRate, 265
CurrChanRxRate, 266
CurrChanTxRate, 266
MaxChanRxRate, 266
MaxChanTxRate, 266
Duration
pack_nas_SetNetworkPreference_t, 746
unpack_nas_GetNetworkPreference_t, 1313
durationDueToOOS
dms_PSMDurationDueToOOSTlv, 248
PSMDurationDueToOOSTlv, 908
durationThreshold
dms_PSMDurationThresholdTlv, 248
PSMDurationThresholdTlv, 908

eAUDIO
common.h, 1723
eCAT
common.h, 1722
eCTL
common.h, 1722
eDMS
common.h, 1722
eGOBI_DEV_SERIES_9X07_9X50
qaGobiApiFms.h, 2047
eGOBI_DEV_SERIES_9X15
qaGobiApiFms.h, 2047
eGOBI_DEV_SERIES_9X30
qaGobiApiFms.h, 2047
eGOBI_DEV_SERIES_G3K
qaGobiApiFms.h, 2047
eGOBI_DEV_SERIES_NON_GOBI
qaGobiApiFms.h, 2047
eGOBI_DEV_SERIES_SIERRA_GOBI
qaGobiApiFms.h, 2047
eGOBI_DEV_SERIES_UNKNOWN
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_3
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_AERIS
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_ALLTEL
qaGobiApiFms.h, 2047

eGOBI_IMG_CAR_AMX_TELCEL
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_ATT
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_BELL
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_BHARTI
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_BRASIL_VIVO
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_CHINA_MOBILE
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_CHINA_TELECOM
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_CHINA_UNICOM
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_EMOBILE
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_FACTORY
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_GENERIC
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_GENERIC_CDMA
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_IUSACELL
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_KDDI
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_KT_FREETEL
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_LEAP
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_METROPCS
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_NETCOM
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_NORF
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_NTT_DOCOMO
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_O2
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_OMH
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_ORANGE
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_RELIANCE1
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_RELIANCE2
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_ROGERS
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_SFR
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_SINGTEL_OPTUS
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_SK_TELCOM1
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_SK_TELCOM2
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_SOFTBANK
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_SPRINT
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_SWISSCOM
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_TATA
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_TELCOM_ITALIA
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_TELCOM_NZ
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_TELEFONICA
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_TELENOR
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_TELIASONERA
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_TELSTRA1
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_TELSTRA2
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_TELUS
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_TMOBILE
qaGobiApiFms.h, 2048
eGOBI_IMG_CAR_US
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_VERIZON
qaGobiApiFms.h, 2047
eGOBI_IMG_CAR_VODAFONE
qaGobiApiFms.h, 2048
eGOBI_IMG_GPS_ASSISTED
qaGobiApiFms.h, 2048
eGOBI_IMG_GPS_NO_XTRA
qaGobiApiFms.h, 2048
eGOBI_IMG_GPS_NONE
qaGobiApiFms.h, 2048
eGOBI_IMG_GPS_STAND_ALONE
qaGobiApiFms.h, 2048
eGOBI_IMG_REG_ASIA
qaGobiApiFms.h, 2049
eGOBI_IMG_REG_AUS
qaGobiApiFms.h, 2049
eGOBI_IMG_REG_EU
qaGobiApiFms.h, 2049
eGOBI_IMG_REG_GLOBAL
qaGobiApiFms.h, 2049
eGOBI_IMG_REG_LA
qaGobiApiFms.h, 2049
eGOBI_IMG_REG_NA
qaGobiApiFms.h, 2049
eGOBI_IMG_TECH_CDMA
qaGobiApiFms.h, 2049
eGOBI_IMG_TECH_UMTS
qaGobiApiFms.h, 2049

eGobi_DEV_SERIES_MC83
qaGobiApiFms.h, 2047
eIMS
common.h, 1722
eIMSA
common.h, 1723
eIND
common.h, 1723
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_1
nas.h, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_10
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_11
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_12
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_125
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_126
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_127
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_13
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_14
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_17
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_18
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_19
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_2
nas.h, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_20
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_21
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_23
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_24
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_25
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_250
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_26
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_27
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_28
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_29
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_3
nas.h, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_30
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_31
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_32
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_33
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_34
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_35
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_36
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_37
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_38
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_39
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_4
nas.h, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_40
nas.h, 1825

eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_41
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_42
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_43
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_46
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_47
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_48
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_5
nas.h, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_6
nas.h, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_66
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_7
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_71
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_8
nas.h, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_9
nas.h, 1825
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_100
nas.h, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_15
nas.h, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_25
nas.h, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_50
nas.h, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_6
nas.h, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_75
nas.h, 1826
eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED
nas.h, 1826
eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED
nas.h, 1826
eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_DECONFIGURED
nas.h, 1826
eLOC
common.h, 1722
eLOG_DEBUG
common.h, 1722
eLOG_FATAL
common.h, 1722
eLOG_INFO
common.h, 1722
eLOG_WARN
common.h, 1722
eNAS
common.h, 1722
eNAS_LTE_CPHY_CA_BW_NRB_100
qaGobiApiNas.h, 2108
eNAS_LTE_CPHY_CA_BW_NRB_15
qaGobiApiNas.h, 2108
eNAS_LTE_CPHY_CA_BW_NRB_25
qaGobiApiNas.h, 2108
eNAS_LTE_CPHY_CA_BW_NRB_50
qaGobiApiNas.h, 2108
eNAS_LTE_CPHY_CA_BW_NRB_6
qaGobiApiNas.h, 2108
eNAS_LTE_CPHY_CA_BW_NRB_75
qaGobiApiNas.h, 2108
eNAS_LTE_CPHY_CA_BW_NRB_LITE_100
nas.h, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_15
nas.h, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_25
nas.h, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_50
nas.h, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_6
nas.h, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_75
nas.h, 1826
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED
qaGobiApiNas.h, 2108
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED_LITE
nas.h, 1826
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED
qaGobiApiNas.h, 2108
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED_LITE
nas.h, 1826
eNAS_LTE_CPHY_SCELL_STATE_DECONFIGURED
qaGobiApiNas.h, 2108
eNAS_LTE_CPHY_SCELL_STATE_DECONFIGURED_LITE
nas.h, 1826
eNAS_RADIO_IF_GSM
qaGobiApiNas.h, 2106

eNAS_RADIO_IF_LTE
qaGobiApiNas.h, 2106
eNAS_RADIO_IF_TDSCDMA
qaGobiApiNas.h, 2106
eNAS_RADIO_IF_UMTS
qaGobiApiNas.h, 2106
ePDS
common.h, 1722
eQA_QMI_SVC_NA
qaGobiApiCbk.h, 1954
eQA_QMI_SVC_NAS
qaGobiApiCbk.h, 1954
eQA_QMI_SVC_WDS
qaGobiApiCbk.h, 1954
eQCWWAN_ERR_API_MUTEX_TIMEOUT
qmerrno.h, 2354
eQCWWAN_ERR_BUFFER_SZ
qmerrno.h, 2353
eQCWWAN_ERR_CANCEL_OP
qmerrno.h, 2354
eQCWWAN_ERR_DRIVER
qmerrno.h, 2354
eQCWWAN_ERR_ENUM_BEGIN
qmerrno.h, 2353
eQCWWAN_ERR_ENUM_END
qmerrno.h, 2354
eQCWWAN_ERR_FILE_COPY
qmerrno.h, 2353
eQCWWAN_ERR_FILE_OPEN
qmerrno.h, 2353
eQCWWAN_ERR_GENERAL
qmerrno.h, 2353
eQCWWAN_ERR_INTERNAL
qmerrno.h, 2353
eQCWWAN_ERR_INVALID_ARG
qmerrno.h, 2353
eQCWWAN_ERR_INVALID_DEVID
qmerrno.h, 2353
eQCWWAN_ERR_INVALID_FILE
qmerrno.h, 2353
eQCWWAN_ERR_INVALID_QMI_RSP
qmerrno.h, 2353
eQCWWAN_ERR_INVALID_XID
qmerrno.h, 2354
eQCWWAN_ERR_MALFORMED_QMI_RSP
qmerrno.h, 2353
eQCWWAN_ERR_MEMORY
qmerrno.h, 2353
eQCWWAN_ERR_MULTIPLE_DEVICES
qmerrno.h, 2354
eQCWWAN_ERR_MULTIPLE_SMS_UNSUPPORTED
qmerrno.h, 2354
eQCWWAN_ERR_NO_CANCELABLE_OP
qmerrno.h, 2354
eQCWWAN_ERR_NO_CONNECTION
qmerrno.h, 2353
eQCWWAN_ERR_NO_DEVICE
qmerrno.h, 2353
eQCWWAN_ERR_NO_SIGNAL
qmerrno.h, 2354
eQCWWAN_ERR_NONE
qmerrno.h, 2353
eQCWWAN_ERR_NULL_TLV
qmerrno.h, 2357
eQCWWAN_ERR_OFFLINE
qmerrno.h, 2354
eQCWWAN_ERR_PDU_GENERATION
qmerrno.h, 2354
eQCWWAN_ERR_QMI_ABORTED
qmerrno.h, 2354
eQCWWAN_ERR_QMI_ACCESS_DENIED
qmerrno.h, 2356
eQCWWAN_ERR_QMI_ACK_NOT_SENT
qmerrno.h, 2356
eQCWWAN_ERR_QMI_ARG_TOO_LONG
qmerrno.h, 2354
eQCWWAN_ERR_QMI_AUTHENTICATION_FAILED
qmerrno.h, 2355
eQCWWAN_ERR_QMI_AUTHENTICATION_LOCK
qmerrno.h, 2355
eQCWWAN_ERR_QMI_BUNDLING_NOT_SUPPORTED
qmerrno.h, 2356
eQCWWAN_ERR_QMI_CALL_FAILED
qmerrno.h, 2354
eQCWWAN_ERR_QMI_CARD_BUSY_RSP
qmerrno.h, 2357
eQCWWAN_ERR_QMI_CARD_CALL_CONTROL_FAILED
qmerrno.h, 2356
eQCWWAN_ERR_QMI_CAT_END
qmerrno.h, 2357
eQCWWAN_ERR_QMI_CAT_START
qmerrno.h, 2357
eQCWWAN_ERR_QMI_CAUSE_CODE
qmerrno.h, 2355
eQCWWAN_ERR_QMI_CLIENT_IDS_EXHAUSTED
qmerrno.h, 2354
eQCWWAN_ERR_QMI_CONNECT
qmerrno.h, 2353
eQCWWAN_ERR_QMI_DEVICE_IN_USE
qmerrno.h, 2354
eQCWWAN_ERR_QMI_DEVICE_NOT_READY
qmerrno.h, 2355
eQCWWAN_ERR_QMI_DEVICE_STORAGE_FULL
qmerrno.h, 2355
eQCWWAN_ERR_QMI_DISABLED
qmerrno.h, 2355
eQCWWAN_ERR_QMI_ENCODING
qmerrno.h, 2355
eQCWWAN_ERR_QMI_ENVELOPE_CMD_FAILURE
qmerrno.h, 2357
eQCWWAN_ERR_QMI_EVENT_REG_FAILED
qmerrno.h, 2357
eQCWWAN_ERR_QMI_EXTENDED_INTERNAL
qmerrno.h, 2356

eQCWWAN_ERR_QMI_FDN_RESTRICT
qmerrno.h, 2356
eQCWWAN_ERR_QMI_FLOW_SUSPENDED
qmerrno.h, 2355
eQCWWAN_ERR_QMI_GENERAL
qmerrno.h, 2355
eQCWWAN_ERR_QMI_HARDWARE_RESTRICTED
qmerrno.h, 2356
eQCWWAN_ERR_QMI_IFACE
qmerrno.h, 2353
eQCWWAN_ERR_QMI_INCOMPATIBLE_STATE
qmerrno.h, 2356
eQCWWAN_ERR_QMI_INCORRECT_FLOW_FILTER
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INCORRECT_PIN
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INFO_UNAVAILABLE
qmerrno.h, 2356
eQCWWAN_ERR_QMI_INJECT_TIMEOUT
qmerrno.h, 2356
eQCWWAN_ERR_QMI_INSUFFICIENT_RESOURCES
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INTERFACE_NOT_FOUND
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INTERNAL
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INVALID_ARG
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_CLIENT_ID
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INVALID_DATA_FORMAT
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_ENVELOPE_CMD
qmerrno.h, 2357
eQCWWAN_ERR_QMI_INVALID_HANDLE
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INVALID_ID
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_INDEX
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_IP_FAMILY_PREF
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_MCAST_HANDLE
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_MESSAGE_ID
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_OPERATION
qmerrno.h, 2356
eQCWWAN_ERR_QMI_INVALID_PDP_TYPE
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INVALID_PINID
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INVALID_PROFILE
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INVALID_PROFILE_TYPE
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INVALID_PS_ATTACH_ACTION
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_QMI_CMD
qmerrno.h, 2356
eQCWWAN_ERR_QMI_INVALID_QOS_ID
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_REGISTER_ACTION
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_SERVICE_TYPE
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INVALID_TECH_PREF
qmerrno.h, 2354
eQCWWAN_ERR_QMI_INVALID_TERMINAL_RSP
qmerrno.h, 2357
eQCWWAN_ERR_QMI_INVALID_TRANSITION
qmerrno.h, 2355
eQCWWAN_ERR_QMI_INVALID_TX_ID
qmerrno.h, 2354
eQCWWAN_ERR_QMI_MALFORMED_MSG
qmerrno.h, 2354
eQCWWAN_ERR_QMI_MAX
qmerrno.h, 2356
eQCWWAN_ERR_QMI_MAX_MCAST_REQUESTS_IN_USE
qmerrno.h, 2355
eQCWWAN_ERR_QMI_MAX_QOS_REQUESTS_IN_USE
qmerrno.h, 2355
eQCWWAN_ERR_QMI_MESSAGE_DELIVERY_FAILURE
qmerrno.h, 2355
eQCWWAN_ERR_QMI_MESSAGE_NOT_SENT
qmerrno.h, 2355
eQCWWAN_ERR_QMI_MISSING_ARG
qmerrno.h, 2354
eQCWWAN_ERR_QMI_MSG_BLOCKED
qmerrno.h, 2356
eQCWWAN_ERR_QMI_NETWORK_ABORTED
qmerrno.h, 2356
eQCWWAN_ERR_QMI_NETWORK_NOT_READY
qmerrno.h, 2355
eQCWWAN_ERR_QMI_NETWORK_QOS_UNAWARE
qmerrno.h, 2355
eQCWWAN_ERR_QMI_NO_EFFECT
qmerrno.h, 2354
eQCWWAN_ERR_QMI_NO_ENTRY
qmerrno.h, 2355
eQCWWAN_ERR_QMI_NO_FREE_PROFILE
qmerrno.h, 2354
eQCWWAN_ERR_QMI_NO_MEMORY
qmerrno.h, 2354
eQCWWAN_ERR_QMI_NO_NETWORK_FOUND
qmerrno.h, 2354
eQCWWAN_ERR_QMI_NO_RADIO
qmerrno.h, 2356
eQCWWAN_ERR_QMI_NO_SUBSCRIPTION

qmerrno.h, 2356
eQCWWAN_ERR_QMI_NO_THRESHOLDS
qmerrno.h, 2354
eQCWWAN_ERR_QMI_NOT_A_MCAST_IFACE
qmerrno.h, 2355
eQCWWAN_ERR_QMI_NOT_PROVISIONED
qmerrno.h, 2354
eQCWWAN_ERR_QMI_NOT_SUPPORTED
qmerrno.h, 2356
eQCWWAN_ERR_QMI_OFFSET
qmerrno.h, 2354
eQCWWAN_ERR_QMI_OP_DEVICE_UNSUPPORTED
qmerrno.h, 2354
eQCWWAN_ERR_QMI_OP_NETWORK_UNSUPPORTED
qmerrno.h, 2354
eQCWWAN_ERR_QMI_OP_PARTIAL_FAILURE
qmerrno.h, 2356
eQCWWAN_ERR_QMI_OUT_OF_CALL
qmerrno.h, 2354
eQCWWAN_ERR_QMI_PIN_BLOCKED
qmerrno.h, 2355
eQCWWAN_ERR_QMI_PIN_PERM_BLOCKED
qmerrno.h, 2355
eQCWWAN_ERR_QMI_POLICY_MISMATCH
qmerrno.h, 2356
eQCWWAN_ERR_QMI_REQ
qmerrno.h, 2353
eQCWWAN_ERR_QMI_REQ_SCH
qmerrno.h, 2353
eQCWWAN_ERR_QMI_REQ_TO
qmerrno.h, 2353
eQCWWAN_ERR_QMI_REQUESTED_NUM_UNSUPPORTED
qmerrno.h, 2355
eQCWWAN_ERR_QMI_RSP
qmerrno.h, 2353
eQCWWAN_ERR_QMI_RSP_TO
qmerrno.h, 2353
eQCWWAN_ERR_QMI_SEGMENT_ORDER
qmerrno.h, 2356
eQCWWAN_ERR_QMI_SEGMENT_TOO_LONG
qmerrno.h, 2356
eQCWWAN_ERR_QMI_SESSION_INACTIVE
qmerrno.h, 2355
eQCWWAN_ERR_QMI_SESSION_INVALID
qmerrno.h, 2355
eQCWWAN_ERR_QMI_SESSION_OWNERSHIP
qmerrno.h, 2355
eQCWWAN_ERR_QMI_SIM_FILE_NOT_FOUND
qmerrno.h, 2356
eQCWWAN_ERR_QMI_SIM_NOT_INITIALIZED
qmerrno.h, 2355
eQCWWAN_ERR_QMI_SMSC_ADDR
qmerrno.h, 2356
eQCWWAN_ERR_QMI_SUPS_FAILURE_CAUSE
qmerrno.h, 2356
eQCWWAN_ERR_QMI_TPDU_TYPE
qmerrno.h, 2356
eQCWWAN_ERR_QMI_UNABORTABLE_TRANSACTION
qmerrno.h, 2354
eQCWWAN_ERR_QMI_UNKNOWN
qmerrno.h, 2355
eQCWWAN_ERR_QMI_WIDTH
qmerrno.h, 2357
eQCWWAN_ERR_RESET
qmerrno.h, 2354
eQCWWAN_ERR_SWICM_AM_VERS_ERROR
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_CALL_IN_PROGRESS
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_END
qmerrno.h, 2357
eQCWWAN_ERR_SWICM_FAILED_TO_KILL_SDK_PROCESS
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_INVALID_SESSION_ID
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_INVALID_V4_SESSION_ID
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_INVALID_V6_SESSION_ID
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_NOT_IMPLEMENTED
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_QMI_CLNT_NOT_SUPPORTED
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_QMI_SVC_NOT_SUPPORTED
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_SM_NO_AVAILABLE_SESSIONS
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_SOCKET_IN_USE
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_START
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_TIMEOUT
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_V4DWN_V6DWN
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_V4DWN_V6UP
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_V4UP_V6DWN
qmerrno.h, 2356
eQCWWAN_ERR_SWICM_V4UP_V6UP
qmerrno.h, 2356
eQCWWAN_ERR_SWIDCS_APP_DISCONNECTED
qmerrno.h, 2357
eQCWWAN_ERR_SWIDCS_DEVNODE_NOT_FOUND
qmerrno.h, 2357

eQCWWAN_ERR_SWIDCS_END
qmerrno.h, 2357
eQCWWAN_ERR_SWIDCS_FILEIO_ERR
qmerrno.h, 2357
eQCWWAN_ERR_SWIDCS_IOCTL_ERR
qmerrno.h, 2357
eQCWWAN_ERR_SWIDCS_START
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_CORRUPTED_FW_IMAGE
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_END
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FILE_NOT_FOUND
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FIRMWARE_NOT_DOWNLOADED
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_ENTER_DOWNLOAD_MODE
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_FLASH_COMPLETE
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_INVALID_SLOT_INDEX
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_PREFERENCE_MISMATCH
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_SAME_AS_CURRENT_ACTIVE_IMAGE
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_SECBOOT_IMAGE_NOT_SIGNED
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_SECBOOT_INVALID_CERT_CHAIN
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_TOO_MANY_FILES
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_UPDATE_FAIL
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_UPDATE_SUCCESS
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_FW_WAIT_FOR_REBOOT
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_INVALID_CRASH_STATE
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_INVALID_PATH
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_OPENING_DIR
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_OPENING_FILE
qmerrno.h, 2357
eQCWWAN_ERR_SWIIM_START
qmerrno.h, 2357
eQCWWAN_ERR_SWISM_END
qmerrno.h, 2357
eQCWWAN_ERR_SWISMS_BEARER_DATA_NOT_FOUND
qmerrno.h, 2357
eQCWWAN_ERR_SWISMS_MSG_CORRUPTED
qmerrno.h, 2357
eQCWWAN_ERR_SWISMS_MSG_LEN_TOO_LONG
qmerrno.h, 2357
eQCWWAN_ERR_SWISMS_SMSC_NUM_CORRUPTED
qmerrno.h, 2357
eQCWWAN_ERR_SWISMS_START
qmerrno.h, 2357
eQMI_LOC_SESS_STATUS_FAILURE
loc.h, 1795
eQMI_LOC_SESS_STATUS_IN_PROGRESS
loc.h, 1795
eQMI_LOC_SESS_STATUS_SUCCESS
loc.h, 1795
eQMI_LOC_SESS_STATUS_TIMEOUT
loc.h, 1795
eQOS
common.h, 1722
eREQ
common.h, 1723
eRMS
common.h, 1723
eRSP
common.h, 1723
eSAR
common.h, 1722
eSMS
common.h, 1722
eSWIAUDIO
common.h, 1723
eSWIDMS
common.h, 1723
eSWILOC
common.h, 1723
eSWIM2MCMD
common.h, 1723
eSWIM2MCMD_AVC2
common.h, 1723
eSWIOMA
common.h, 1723
eSWIOMAEXT
common.h, 1723
eSYS_SRV_DOMAIN_CAMPED
qaGobiApiNas.h, 2106
eSYS_SRV_DOMAIN_CS_ONLY
qaGobiApiNas.h, 2106
eSYS_SRV_DOMAIN_CS_PS
qaGobiApiNas.h, 2106
eSYS_SRV_DOMAIN_NO_SRV
qaGobiApiNas.h, 2106
eSYS_SRV_DOMAIN_PS_ONLY
qaGobiApiNas.h, 2106
eSYS_SRV_DOMAIN_UNKNOWN
qaGobiApiNas.h, 2106

eSetServiceAutomaticTrackingDisable
qaGobiApiPds.h, 2145
eSetServiceAutomaticTrackingEnable
qaGobiApiPds.h, 2145
eTIMEOUT_10_S
common.h, 1723
eTIMEOUT_20_S
common.h, 1723
eTIMEOUT_2_S
common.h, 1723
eTIMEOUT_300_S
common.h, 1723
eTIMEOUT_30_S
common.h, 1723
eTIMEOUT_5_S
common.h, 1723
eTIMEOUT_60_S
common.h, 1723
eTIMEOUT_8_S
common.h, 1723
eTIMEOUT_DEFAULT
common.h, 1723
eTIMESTEMP_DAY
qaGobiApiSms.h, 2175
eTIMESTEMP_END
qaGobiApiSms.h, 2175
eTIMESTEMP_HOUR
qaGobiApiSms.h, 2175
eTIMESTEMP_MINUTE
qaGobiApiSms.h, 2175
eTIMESTEMP_MONTH
qaGobiApiSms.h, 2175
eTIMESTEMP_SECOND
qaGobiApiSms.h, 2175
eTIMESTEMP_START
qaGobiApiSms.h, 2175
eTIMESTEMP_TIMEZONE
qaGobiApiSms.h, 2175
eTIMESTEMP_YEAR
qaGobiApiSms.h, 2175
eTLV_3GPP_NETWORK_INFO
qaNasPerformNetworkScan.h, 2350
eTLV_CBK_ALPHA_IDENTIFIER
qaCbkCatEventReportInd.h, 1896
eTLV_CBK_DISPLAY_TEXT
qaCbkCatEventReportInd.h, 1896
eTLV_CBK_END_PROACTIVE_SESSION
qaCbkCatEventReportInd.h, 1897
eTLV_CBK_GET_IN_KEY
qaCbkCatEventReportInd.h, 1896
eTLV_CBK_GET_INPUT
qaCbkCatEventReportInd.h, 1896
eTLV_CBK_LANGUAGE_NOTIFICATION
qaCbkCatEventReportInd.h, 1897
eTLV_CBK_REFRESH
qaCbkCatEventReportInd.h, 1897
eTLV_CBK_SELECT_ITEM
qaCbkCatEventReportInd.h, 1896
eTLV_CBK_SETUP_EVENT_LIST
qaCbkCatEventReportInd.h, 1896
eTLV_CBK_SETUP_IDLE_MODE_TEXT
qaCbkCatEventReportInd.h, 1897
eTLV_CBK_SETUP_MENU
qaCbkCatEventReportInd.h, 1896
eTLV_END_PROACTIVE_SESSION_LENGTH
qaCbkCatEventReportInd.h, 1897
eTLV_IND_OMA_DM_CONFIG
qaCbkSwiOmaDmEventReportInd.h, 1898
eTLV_IND_OMA_DM_FOTA
qaCbkSwiOmaDmEventReportInd.h, 1898
eTLV_IND_OMA_DM_NOT
qaCbkSwiOmaDmEventReportInd.h, 1898
eTLV_LTE_OPERATIONAL_MODE
qaNasGetRFBandInfo.h, 2349
eTLV_REFRESH_LENGTH
qaCbkCatEventReportInd.h, 1897
eTLV_RF_BAND_INFO
qaNasGetRFBandInfo.h, 2349
eTLV_RF_BANDWIDTH_INFO
qaNasGetRFBandInfo.h, 2349
eTLV_RF_DEDICATED_BAND_INFO
qaNasGetRFBandInfo.h, 2349
eTLV_RF_EXT_FORMAT_BAND_INFO
qaNasGetRFBandInfo.h, 2349
eTLV_SETUP_EVENT_LIST_LENGTH
qaCbkCatEventReportInd.h, 1897
eTMD
common.h, 1722
eUIM
common.h, 1722
eVOICE
common.h, 1722
eWDS
common.h, 1722
eWDS_ERR_PROFILE_REG_3GPP2_ERR_INVALID_IDENT_FOR_PROFILE
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_3GPP_ACCESS_ERR
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_3GPP_CONTEXT_NOT_DEFINED
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_3GPP_ERR_OUT_OF_PROFILES
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_3GPP_INVAL_PROFILE_FAMILY
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_3GPP_READ_ONLY_FLAG_SET
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_3GPP_VALID_FLAG_NOT_SET
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_END
qmerrno.h, 2358

eWDS_ERR_PROFILE_REG_INVAL_PROFILE_FAMILY
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_HNDL
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_IDENT
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_OP
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_PROFILE_NUM
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_PROFILE_TYPE
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_SUBS_ID
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_LEN_INVALID
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_LIB_NOT_INITED
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_FAIL
qmerrno.h, 2358
eWDS_ERR_PROFILE_REG_RESULT_LIST_END
qmerrno.h, 2358
ECIOThresListLen
ECIOThresh, 267
nas_ECIOThresh, 499
ECIOThresh, 267
ECIOThresListLen, 267
pECIOThresList, 267
ECTCallState
ECTNum, 268
voice_ECTNum, 1601
ECTNum, 267
ECTCallState, 268
number, 268
presentationInd, 268
eDevState
qaGobiApiCbk.h, 1915
eDevice
sGetDeviceSeriesResult, 1024
eGetDeviceSeries
qaGobiApiFms.h, 2050
eGobiDeviceSeries
qaGobiApiFms.h, 2047
eGobiImageCarrier
qaGobiApiFms.h, 2047
eGobiImageGPS
qaGobiApiFms.h, 2048
eGobiImageRegion
qaGobiApiFms.h, 2048
eGobiImageTech
qaGobiApiFms.h, 2049
eLOG_LEVEL
common.h, 1722
EMTlv
NASQmiCbkNasSystemSelPrefInd, 668
eQCWWANError
qmerrno.h, 2353
eQMI_SVC
common.h, 1722
eQMISARRFState
qaGobiApiSar.h, 2167
eQaQMIService
qaGobiApiCbk.h, 1954
ERI_DATA_MAX_SIZE
dms.h, 1734
ERIFileparams, 273
pFile, 273
pFileSize, 273
qaGobiApiDms.h, 2008
eSMSEventType
qaGobiApiCbk.h, 1915
ESNString
unpack_dms_GetDeviceSerialNumbers_t, 1218
eSYS_SRV_DOMAIN
qaGobiApiNas.h, 2106
ETWSPLMNInfo
eTWSPLMNInfoTlv, 275
eTWSPLMNInfoTlv, 274
ETWSPLMNInfo, 275
TlvPresent, 275
ETWSPLMNTlv
unpack_sms_SetNewSMSCallback_ind_t, 1426
ETWSTlv
unpack_sms_SetNewSMSCallback_ind_t, 1426
eTimeout
common.h, 1723
EVENT_MASK_CARD
qaGobiApiCbk.h, 1912
eValid
LibPackTFTIDParams, 399
TFTIDParams, 1132
EarMute
GetAudioProfileResp, 295
GetM2MAudioProfileResp, 312
GetM2MAVMuteResp, 314
SetAudioProfileReq, 1001
SetM2MAVMuteReq, 1014
earfcn
infoInterFreq, 365
LTEInfoIntrafreq, 445
ltePCI, 453
nas_infoInterFreq, 520
nas_LTEInfoIntrafreq, 531
nas_ltePCI, 539
nas_umtsLTENbrCell, 618

umtsLTENbrCell, 1197
earfcn0
lteEARFCN, 439
nas_lteEARFCN, 525
earfcn1
lteEARFCN, 439
nas_lteEARFCN, 525
earlyWakeupTime
dms_PSMEarlyWakeupTimeTlv, 249
PSMEarlyWakeupTimeTlv, 909
ecio
CDMASSInfo, 190
cdmaSSInfo, 189
ecioListElement, 266
HDRSSInfo, 341
hdrSSInfo, 340
nas_ecioListElement, 498
nas_rxInfo, 595
nas_UMTSInfo, 616
rxInfo, 979
TDSCDMASigInfoExt, 1127
tdscdmaSigInfoExt, 1126
UMTSInfo, 1195
ecioDelta
nas_SLQSSignalStrengthsIndReq, 602
SLQSSignalStrengthsIndReq, 1047
ecioInfo
nas_SLQSSignalStrengthsInformation, 604
SLQSSignalStrengthsInformation, 1049
ecioList
slqsSignalStrengthInfo, 1045
unpack_nas_SLQSGetSignalStrength_t, 1338
ecioListElement, 266
ecio, 266
radioIf, 267
ecioListLen
slqsSignalStrengthInfo, 1045
unpack_nas_SLQSGetSignalStrength_t, 1338
ecioThresholdList
nas_SLQSSignalStrengthsIndReq, 602
SLQSSignalStrengthsIndReq, 1047
ecioThresholdListLen
nas_SLQSSignalStrengthsIndReq, 602
SLQSSignalStrengthsIndReq, 1047
EdrxCiotLteMode, 268
lteOpMode, 269
TlvPresent, 269
edrxCiotLteModeTlv
unpack_nas_SLQSNasEdrxChangeInfoCallBack_-
Ind_t, 1351
EdrxCycleLength, 269
cycleLength, 269
TlvPresent, 269
edrxCycleLengthTlv
unpack_nas_SLQSNasEdrxChangeInfoCallBack_-
Ind_t, 1351
EdrxEnableType, 269
edrxEnabled, 270
TlvPresent, 270
edrxEnableTypeTlv
unpack_nas_SLQSNasEdrxChangeInfoCallBack_-
Ind_t, 1351
edrxEnabled
EdrxEnableType, 270
nas_EdrxEnableType, 501
EdrxPagingTimeWindow, 270
edrxPtw, 270
TlvPresent, 270
edrxPagingTimeWindowTlv
unpack_nas_SLQSNasEdrxChangeInfoCallBack_-
Ind_t, 1351
edrxPtw
EdrxPagingTimeWindow, 270
nas_EdrxPagingTimeWindow, 501
EdrxRatType, 270
edrxRatType, 271
TlvPresent, 271
edrxRatType
EdrxRatType, 271
nas_EdrxRatType, 502
edrxRatTypeTlv
unpack_nas_SLQSNasEdrxChangeInfoCallBack_-
Ind_t, 1351
egprsSupp
GSMSysInfo, 332
nas_GSMSysInfo, 512
egprsSuppValid
GSMSysInfo, 332
nas_GSMSysInfo, 512
ehrpdMTUSize
ehrpdMTUSizeTlv, 271
swidms_ehrpdMTUSizeTlv, 1092
ehrpdMTUSizeTlv, 271
ehrpdMTUSize, 271
TlvPresent, 271
elevation
loc_satelliteInfo, 418
satelliteInfo, 986
EmerMode
nas_EmerModeTlv, 503
NASEmergencyModeTlv, 629
emmConnState
LTEInfo, 442
nas_LTEInfo, 528
emmState
LTEInfo, 442
nas_LTEInfo, 528
emmSubState
LTEInfo, 442
nas_LTEInfo, 528
Enable
SetM2MAudioLPBKReq, 1012
enable
pack_pds_SetPDSState_t, 783
pack_qos_SLQSSetQosEventCallback_t, 794

pack_swidms_SLQSSwiDmsSetHWWatchdog_t, 805
swidms_SwiDmsGetHWWatchdog, 1096
SwiDmsGetHWWatchdog, 1097
SwiDmsSetHWWatchdog, 1099
EnableState
unpack_dms_PSMCfgChange_ind_t, 1234
enableState
dms_PSMEnableStateTlv, 250
PSMEnableStateTlv, 909
EnableStateInd
dms_PSMEnableStateIndTlv, 249
enabled
pack_rms_SetSMSWake_t, 794
unpack_rms_GetSMSWake_t, 1420
unpack_wds_GetMobileIPProfile_t, 1525
EnabledStatus
unpack_pds_SetPdsState_Ind_t, 1391
EncryptProt
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
EncryptedPIN1
pack_uim_ChangePin_t, 812
pack_uim_SetPinProtection_t, 814
pack_uim_UnblockPin_t, 822
encryptedPIN1, 272
pin1Len, 272
pin1Val, 272
EndPointType
qos_BindDataPortPeripheralEndPointID_t, 953
EndProactiveSession
CatEndProactiveSessionTlv, 175
EngineState
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
engineState
QmiCbkLocEngineStateInd, 923
unpack_loc_EngineState_Ind_t, 1283
entries
t_Sv, 1124
eqmiCbkSetStatus
sms.h, 2376
eriData
eriDataparams, 273
eriDataLen
eriDataparams, 273
eriDataparams, 272
eriData, 273
eriDataLen, 273
eriFile
unpack_dms_SLQSGetERIFile_t, 1252
error
unpack_wds_GetLastMobileIPError_t, 1522
errorClass
SMSAsyncRawSend_s, 1066
unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t, 1440
errorRate
errorRateListElement, 274
nas_errorRateListElement, 504
errorRateInfo
nas_SLQSSignalStrengthsInformation, 604
SLQSSignalStrengthsInformation, 1049
errorRateList
slqsSignalStrengthInfo, 1045
unpack_nas_SLQSGetSignalStrength_t, 1338
errorRateListElement, 273
errorRate, 274
radioIf, 274
errorRateListLen
slqsSignalStrengthInfo, 1045
unpack_nas_SLQSGetSignalStrength_t, 1338
errorState
slotInf, 1030
slotInfo, 1031
uim_slotInfo, 1167
esn
unpack_dms_GetSerialNumbers_t, 1230
esnSize
serialNumbersInfo, 992
unpack_dms_GetDeviceSerialNumbers_t, 1218
EspSpi
unpack_qos_swiQosFilter_t, 1412
EtwsMessageInfo
sMSEtwsMessageTlv, 1069
event
dms_UimStatusTlv, 253
unpack_qos_SLQSSetQosPriEventCallback_ind_t, 1408
unpack_qos_SLQSSetQosStatusCallback_ind_t, 1410
event_Index
QmiCbkCatEventStatusReportInd, 916
EventID
CatCommonEventTlv, 174
EventLength
CatCommonEventTlv, 174
eventMask
CATEventDataType, 175
pack_uim_SLQSUIMEventRegister_t, 816
UIMEventRegisterReqResp, 1175
unpack_uim_SLQSUIMEventRegister_t, 1461
eventRegister
LOCEventRegisterReqResp, 426
pack_loc_EventRegister_t, 729
eventType
unpack_swioma_SLQSOMADMAlertCallback_ind_t, 1449
evrcCapability
prefVoiceSO, 893
voice_prefVoiceSO, 1610
executingImage
FMSImageIDEntries, 284
ImageIDEntries, 348
exponent
pktErrRate, 884

unpack_qos_pktErrRate_t, 1400
extBit
calledPartySubAdd, 163
voice_calledPartySubAdd, 1583
extDispInfo
extDispRecInfo, 275
voice_extDispRecInfo, 1601
extDispInfoLen
extDispRecInfo, 275
voice_extDispRecInfo, 1601
extDispRecInfo, 275
dispType, 275
extDispInfo, 275
extDispInfoLen, 275
ExtErrorCode
PackCreateProfileOut, 868
extPowerState
LOCExtPowerStateReqResp, 426
pack_loc_SetExtPowerState_t, 729
extendedErrorCode
unpack_wds_SLQSDeleteProfile_t, 1532

FIRST_INSTANCE
qaGobiApiCbk.h, 1912
FLOAT
SwiDataTypes.h, 2395
FMSImageElement, 282
buildId, 282
buildIdLength, 282
imageId, 282
imageType, 282
FMSImageIDEntries, 283
executingImage, 284
imageIDElement, 284
imageIDSize, 284
imageType, 284
maxImages, 284
FMSImageIdElement, 282
buildID, 283
buildIDLength, 283
failureCount, 283
imageID, 283
storageIndex, 283
FMSImageList, 284
imageIDEntries, 285
listSize, 285
FMSPrefImageList, 285
listEntries, 285
listSize, 285
FORBIDDEN_INDEX
qaNasPerformNetworkScan.h, 2350
FOTAUpdate
_SLQSOMADMSettingsReqParams, 107
_SLQSOMADMSettingsReqParams3, 108
pack_swioma_SLQSOMADMSetSettings_t, 811
unpack_swioma_SLQSOMADMGetSettings_t, 1454
FOTAdownload
_SLQSOMADMSettingsReqParams, 107
_SLQSOMADMSettingsReqParams3, 108
pack_swioma_SLQSOMADMSetSettings_t, 811
unpack_swioma_SLQSOMADMGetSettings_t, 1453
FSNumber
FactorySequenceNumber, 276
facility
pack_dms_UIMGetControlKeyStatus_t, 720
pack_dms_UIMSetControlKeyProtection_t, 721
pack_dms_UIMUnblockControlKey_t, 722
facilityCk
pack_dms_UIMSetControlKeyProtection_t, 721
pack_dms_UIMUnblockControlKey_t, 723
facilityState
pack_dms_UIMSetControlKeyProtection_t, 721
unpack_dms_UIMGetControlKeyStatus_t, 1267
FactorySequenceNumber, 275
FSNumber, 276
failureCount
FMSImageIdElement, 283
ImageIdElement, 347
failureReason
ssdatasession_params, 1086
failureReasonv4
ssdatasession_params, 1086
failureReasonv6
ssdatasession_params, 1086
family
pack_wds_GetDefaultProfileNum_t, 843
pack_wds_SetDefaultProfileNum_t, 849
feature
depersonalizationInformation, 240
personalizationStatus, 876
uim_depersonalizationInformation, 1153
uim_personalizationStatus, 1159
fileAttributes, 276
fileID, 279
fileSize, 279
fileType, 279
rawLen, 279
rawValue, 279
recordCount, 279
recordSize, 279
secActivate, 279
secActivateMask, 279
secDeactivate, 279
secDeactivateMask, 279
secIncrease, 279
secIncreaseMask, 279
secRead, 279
secReadMask, 279
secWrite, 279
secWriteMask, 279
fileID
fileAttributes, 279
fileInfo, 280
uim_fileAttributes, 1157
uim_fileInfo, 1158

fileIndex
pack_uim_ReadTransparent_t, 813
pack_uim_SLQSUIMGetFileAttributes_t, 817
UIMGetFileAttributesReq, 1178
UIMReadTransparentReq, 1182
fileInfo, 279
fileID, 280
path, 280
pathLen, 280
fileSize
fileAttributes, 279
uim_fileAttributes, 1157
fileType
fileAttributes, 279
uim_fileAttributes, 1157
fill_pack_ctx
common.h, 1723
fill_sdu_hdr
common.h, 1723
filterId
LibPackTFTIDParams, 400
TFTIDParams, 1132
Firmware Management Service (FMS), 52
FirmwareID
fwinfo_s, 287
FirmwareUpdatStat, 280
pImgType, 281
pLogString, 281
pLogStringLen, 282
pRefData, 282
pRefString, 282
pRefStringLen, 282
ResCode, 282
fix_rate
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocGetAutoStartResp, 1102
SwiLocSetAutoStartReq, 1103
unpack_swiloc_SwiLocGetAutoStart_t, 1448
fix_rate_reported
SwiLocGetAutoStartResp, 1102
unpack_swiloc_SwiLocGetAutoStart_t, 1448
fix_type
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocGetAutoStartResp, 1102
SwiLocSetAutoStartReq, 1104
unpack_swiloc_SwiLocGetAutoStart_t, 1448
fix_type_reported
SwiLocGetAutoStartResp, 1102
unpack_swiloc_SwiLocGetAutoStart_t, 1448
fixAccuracy
pack_pds_StartPDSTrackingSessionExt_t, 791
fixCount
pack_pds_StartPDSTrackingSessionExt_t, 791
fixInterval
pack_pds_StartPDSTrackingSessionExt_t, 791
fixTimeout
pack_pds_StartPDSTrackingSessionExt_t, 791
flags
sensorData, 989
sensorData_t, 990
flowLabel
LibPackTFTIDParams, 400
TFTIDParams, 1132
fms.h, 1785
GetValidFwPriCombinations, 1786
pack_fms_GetImagesPreference, 1786
pack_fms_GetStoredImages, 1787
pack_fms_SetImagesPreference, 1787
unpack_fms_GetImagesPreference, 1787
unpack_fms_GetStoredImages, 1787
unpack_fms_SetImagesPreference, 1788
Forbidden
nas_QmiNas3GppNetworkInfo, 578
SlqsNas3GppNetworkInfo, 1036
ForbiddenNetworks3GPP, 285
forbiddenNwInstLen, 286
MCC, 286
MNC, 286
TlvPresent, 286
forbiddenNwInstLen
ForbiddenNetworks3GPP, 286
nas_ForbiddenNetworks3GPP, 505
forceFlag
pack_pds_SLQSPDSInjectAbsoluteTimeReference-_t, 786
ForceRev0
unpack_nas_GetCDMANetworkParameters_t, 1308
ForceXTRADownload
qaGobiApiPds.h, 2145
format
SMSTransferRouteMTMessage, 1080
sMSTransferRouteMTMessageInfo, 1081
ForwardMac
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
fqdnAddr
PCSCFFQDNAddress, 870
wds_PCSCFFQDNAddress, 1693
fqdnLen
PCSCFFQDNAddress, 870
wds_PCSCFFQDNAddress, 1693
freeSlots
sms_maxStorageSizeResp, 1056
smsMaxStorageSizeResp, 1073
freq
nas_PhyCaAggPcellInfo, 566
nas_PhyCaAggScellIndType, 567
nas_PhyCaAggScellInfo, 570
nas_QmisNasSlqsNasPCICellInfo, 580
NASPhyCaAggPcellInfo, 657
NASPhyCaAggScellArray, 658
NASPhyCaAggScellIndType, 660
NASPhyCaAggScellInfo, 661
PhyCaAggPcellInfo, 877
PhyCaAggScellArray, 879

PhyCaAggScellIndType, 880
PhyCaAggScellInfo, 883
SlqsNasPCICellInfo, 1037
freqsLen
LTEInfoInterfreq, 443
LTEInfoNeighboringGSM, 446
LTEInfoNeighboringWCDMA, 447
nas_LTEInfoInterfreq, 529
nas_LTEInfoNeighboringGSM, 532
nas_LTEInfoNeighboringWCDMA, 533
fromServiceId
BroadcastConfig, 158
sms_BroadcastConfig, 1051
fumoResultCode
omaDmFotaTlvExt, 703
function
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocGetAutoStartResp, 1102
SwiLocSetAutoStartReq, 1104
unpack_swiloc_SwiLocGetAutoStart_t, 1448
function_reported
SwiLocGetAutoStartResp, 1102
unpack_swiloc_SwiLocGetAutoStart_t, 1448
FwAutoCheck
unpack_swioma_SLQSOMADMGetSettings_t, 1454
FwAvailability
unpack_swioma_SLQSOMADMStartSession_t, 1454
fwdloadsize
omaDmFotaTlv, 700
unpack_omaDmFotaTlv_t, 1382
fwinfo_s, 286
Carrier, 287
FirmwareID, 287
GPSCapability, 287
Region, 287
Technology, 287
fwloadComplete
omaDmFotaTlv, 701
unpack_omaDmFotaTlv_t, 1382
fwvers
CurrentImgList, 220
unpack_dms_SLQSSwiGetFirmwareCurr_t, 1257

g
qmifwinfo_s, 944
gDlBitRate
LibPackQosClassID, 398
QosClassID, 954
GERANInfo, 287
arfcn, 288
bsic, 288
cellID, 288
insNmrCellInfo, 288
lac, 288
nmrInst, 288
plmn, 288
rxLev, 289
timingAdvance, 289
GPRSGrantedQoS
unpack_wds_SLQSGetRuntimeSettings_t, 1545
GPRSQoS, 321
delayClass, 322
meanThroughputClass, 322
peakThroughputClass, 322
precedenceClass, 322
reliabilityClass, 322
GPRSRequestedQoS, 322
delayClass, 323
meanThroughputClass, 323
peakThroughputClass, 323
precedenceClass, 323
reliabilityClass, 323
GPSCapability
fwinfo_s, 287
GPSLPM
pack_dms_SetCustFeature_t, 710
unpack_dms_GetCustFeature_t, 1211
GPSSel
pack_dms_SetCustFeature_t, 710
unpack_dms_GetCustFeature_t, 1211
GPSStateInfo, 323
Altitude, 326
EngineState, 326
glo_almanac_sv_msk, 326
glo_ephemeris_sv_msk, 326
glo_health_sv_msk, 326
glo_visible_sv_msk, 326
gps_almanac_sv_msk, 326
gps_ephemeris_sv_msk, 326
gps_health_sv_msk, 326
gps_visible_sv_msk, 326
HorizontalUncertainty, 326
Iono_valid, 326
Latitude, 326
Longitude, 326
sbas_almanac_sv_msk, 326
sbas_ephemeris_sv_msk, 326
sbas_health_sv_msk, 326
sbas_visible_sv_msk, 327
Time_uncert_ms, 327
TimeStmp_gps_week, 327
TimeStmp_tow_ms, 327
ValidMask, 327
VerticalUncertainty, 327
xtra_start_gps_minutes, 327
xtra_start_gps_week, 327
xtra_valid_duration_hours, 327
GSMRSSIThresh, 329
GSMRSSIThreshListLen, 329
pGSMRSSIThreshList, 329
GSMRSSIThreshListLen
GSMRSSIThresh, 329
nas_GSMRSSIThresh, 509
GSMSSInfo
unpack_nas_SLQSNasGetSigInfo_t, 1359

GSMSrvStatusInfo, 329
isPrefDataPath, 330
srvStatus, 330
trueSrvStatus, 330
GSMSysInfo, 330
cellId, 332
cellIdValid, 332
dtmSupp, 332
dtmSuppValid, 332
egprsSupp, 332
egprsSuppValid, 332
lac, 332
lacValid, 333
MCC, 333
MNC, 333
networkIdValid, 333
regRejectInfoValid, 333
rejCause, 333
rejectSrvDomain, 333
sysInfoGSM, 333
gUlBitRate
LibPackQosClassID, 398
QosClassID, 954
GWAOPTlv
NASQmiCbkNasSystemSelPrefInd, 668
GWAcqOrderPref
nas_GWAcqOrderPrefTlv, 513
NASGWAcqOrderPrefTlv, 643
GWAddressV4
unpack_wds_SLQSGetRuntimeSettings_t, 1545
gcDumpStrLen
CrashInfo, 211
gcdumpString
crashInformation, 213
gcdumpStrlen
crashInformation, 213
Generator
GetAudioProfileReq, 294
GetAudioVolTLBConfigReq, 296
GetM2MAudioProfileResp, 312
GetM2MAudioVolumeReq, 313
SetAudioProfileReq, 1001
SetAudioVolTLBConfigReq, 1002
SetM2MAudioVolumeReq, 1014
geoSysIdx
AddCDMASysInfo, 132
AddSysInfo, 132
nas_AddCDMASysInfo, 474
nas_AddSysInfo, 474
geranArfcn
geranInstInfo, 289
nas_geranInstInfo, 507
geranBsicBcc
geranInstInfo, 289
nas_geranInstInfo, 507
geranBsicNcc
geranInstInfo, 289
nas_geranInstInfo, 507
geranInst
nas_UMTSInfo, 616
UMTSInfo, 1196
GeranInstInfo
nas_UMTSInfo, 616
UMTSInfo, 1196
geranInstInfo, 289
geranArfcn, 289
geranBsicBcc, 289
geranBsicNcc, 289
geranRssi, 289
geranRssi
geranInstInfo, 289
nas_geranInstInfo, 507
get_version
common.h, 1723
GetACCOLC
qaGobiApiNas.h, 2108
GetANAAAAuthenticationStatus
qaGobiApiNas.h, 2108
GetActivationState
qaGobiApiDms.h, 2012
getAllCallInfo
arrCallInfo, 147
voice_arrCallInfo, 1576
getAllCallInformation, 289
ALS, 290
Callinfo, 290
isEmpty, 290
GetAllCallRmtPtyName
arrRemotePartyName, 149
voice_arrRemotePartyName, 1578
getAllCallRmtPtyName, 290
callID, 290
RemotePartyName, 290
getAllCallRmtPtyNum, 291
callID, 291
RemotePartyNum, 291
GetAudioPathConfigReq, 291
Item, 292
Profile, 292
GetAudioPathConfigResp, 292
pCodecSTGain, 293
pDTMFTXGain, 294
pECMode, 294
pMICGainSelect, 294
pNSEnable, 294
pRXAGCList, 294
pRXAVCAGCSwitch, 294
pRXAVCList, 294
pRXPCMIIRFltr, 294
pTXAGCList, 294
pTXAVCSwitch, 294
pTXGain, 294
pTXPCMIIRFltr, 294
GetAudioProfileReq, 294
Generator, 294
GetAudioProfileResp, 294

EarMute, 295
MicMute, 295
Profile, 295
Volume, 295
GetAudioVolTLBConfigReq, 296
Generator, 296
Item, 296
Profile, 296
Volume, 296
GetAudioVolTLBConfigResp, 296
ResCode, 297
GetAutoconnect
qaGobiApiWds.h, 2312
GetByteTotals
qaGobiApiWds.h, 2313
GetCDMANetworkParameters
qaGobiApiNas.h, 2109
getCallFWExtInfo, 297
CallFWExtInfo, 297
numInstances, 297
getCallFWInfo, 297
CallFWInfo, 298
numInstances, 298
GetConnectionRate
qaGobiApiWds.h, 2313
GetCustomFeatureV2
unpack_dms_GetCustFeaturesV2_t, 1212
getCustomFeatureV2, 298
pCustSettingInfo, 298
pCustSettingList, 298
pGetCustomInput, 298
getCustomInput, 299
cust_id, 299
list_type, 299
getDUNCallInfoReq, 299
Mask, 300
pReportChannelRate, 300
pReportConnStatus, 300
pReportDataBearerTech, 300
pReportDormStatus, 300
pTransferStatInd, 300
getDUNCallInfoResp, 301
pCallEndReason, 303
pChannelRate, 303
pConnectionStatus, 303
pDataBearerTech, 303
pDormancyStatus, 303
pLastCallDataBearerTech, 303
pLastCallRXOKBytesCnt, 303
pLastCallTXOKBytesCnt, 303
pMdmCallDurationActive, 303
pRXOKBytesCount, 303
pTXOKBytesCount, 303
GetDataBearerTechnology
qaGobiApiWds.h, 2314
GetDefaultProfile
qaGobiApiWds.h, 2315
GetDefaultProfileLTE
qaGobiApiWds.h, 2316
GetDefaultProfileNum
qaGobiApiWds.h, 2318
GetDeviceCapabilities
qaGobiApiDms.h, 2012
GetDormancyState
qaGobiApiWds.h, 2319
getDyingGaspCfg, 303
pDestSMSContent, 304
pDestSMSNum, 304
getDyingGaspStatistics, 304
pSMSAttemptedFlag, 304
pTimeStamp, 305
GetErrRateResp, 305
pCDMAFrameErrRate, 305
pGSMBER, 305
pHDRPackErrRate, 305
pWCDMABER, 305
GetFirmwareRevision
qaGobiApiDms.h, 2013
GetFirmwareRevisions
qaGobiApiDms.h, 2014
GetHRPDStatsResp, 306
pDRCParams, 306
pPilotSetData, 306
pUATI, 306
GetHardwareRevision
qaGobiApiDms.h, 2014
GetHomeNetwork
qaGobiApiNas.h, 2111
GetHomeNetwork3GPP2
qaGobiApiNas.h, 2112
GetIMSI
qaGobiApiDms.h, 2015
GetIMSSMSConfigParams, 306
pPhoneCtxtURI, 307
pPhoneCtxtURILen, 307
pSMSFormat, 307
pSMSOverIPNwInd, 307
pSettingResp, 307
GetIMSUserConfigParams, 307
pIMSDomain, 308
pIMSDomainLen, 308
pSettingResp, 308
GetIMSVoIPConfigResp, 308
pAmrMode, 310
pAmrOctetAligned, 310
pAmrWBMode, 310
pAmrWBOctetAligned, 310
pAmrWbEnable, 310
pMinSessionExpiryTimer, 310
pRTPRTCPInactTimer, 310
pRingBackTimer, 310
pRingingTimer, 310
pScrAmrEnable, 310
pScrAmrWbEnable, 310
pSessionExpiryTimer, 310
pSettingResp, 310

GetIPAddressLTE
qaGobiApiWds.h, 2319
GetImageStore
qaGobiApiFms.h, 2051
GetImagesPreference
qaGobiApiFms.h, 2050
getIndicationRegResp
qaGobiApiSms.h, 2172
GetInstIDResp, 310
pIPFamily, 310
pInstanceID, 310
GetLastMobileIPError
qaGobiApiWds.h, 2319
GetM2MAVMuteReq, 313
Profile, 313
GetM2MAVMuteResp, 314
CwtMute, 314
EarMute, 314
MicMute, 314
GetM2MAudioProfileReq, 311
pGenerator, 311
GetM2MAudioProfileResp, 311
CwtMute, 312
EarMute, 312
Generator, 312
MicMute, 312
Profile, 312
Volume, 312
GetM2MAudioVolumeReq, 312
Generator, 313
Profile, 313
GetM2MAudioVolumeResp, 313
Level, 313
GetM2MSpkrGainReq, 314
Profile, 315
GetM2MSpkrGainResp, 315
Value, 315
GetManufacturer
qaGobiApiDms.h, 2015
GetMobileIP
qaGobiApiWds.h, 2320
GetMobileIPProfile
qaGobiApiWds.h, 2320
GetModelID
qaGobiApiDms.h, 2016
getMsgWaitingInfo, 315
msgWaitInfo, 316
numInstances, 316
GetNetworkPreference
qaGobiApiNas.h, 2113
GetNetworkTime
qaGobiApiDms.h, 2016
GetNetworkTimeResp, 316
p3GPP2TimeInfo, 316
p3GPPTimeInfo, 316
GetOfflineReason
qaGobiApiDms.h, 2017
GetPDSDefaults
qaGobiApiPds.h, 2145
GetPDSState
qaGobiApiPds.h, 2146
GetPRLVersion
qaGobiApiDms.h, 2018
GetPacketStatistics
qaGobiApiWds.h, 2322
GetPacketStatus
qaGobiApiWds.h, 2322
GetPortAutomaticTracking
qaGobiApiPds.h, 2146
GetPower
qaGobiApiDms.h, 2018
GetProfileSettingIn
qaGobiApiWds.h, 2308
GetProfileSettingOut
qaGobiApiWds.h, 2308
GetQmapIsSupported
qaGobiApiDcs.h, 1994
GetRFInfo
qaGobiApiNas.h, 2114
GetRegMgrConfigParams, 316
pIMSTestMode, 317
pPCSCFPort, 317
pPriCSCFPortName, 317
pPriCSCFPortNameLen, 317
pSettingResp, 317
GetSIPConfigResp, 317
pSIPLocalPort, 318
pSettingResp, 318
pSigCompEnabled, 318
pSubscribeTimer, 318
pTimerSIPReg, 318
pTimerT1, 318
pTimerT2, 318
pTimerTf, 318
GetSMSCAddress
qaGobiApiSms.h, 2175
GetSMSWake
qaGobiApiRms.h, 2165
GetSerialNumbers
qaGobiApiDms.h, 2018
GetServiceAutomaticTracking
qaGobiApiPds.h, 2147
GetServingNetwork
qaGobiApiNas.h, 2114
GetServingNetworkCapabilities
qaGobiApiNas.h, 2116
GetSessionDuration
qaGobiApiWds.h, 2323
GetSessionIDResp, 317
pSessionIDv4, 317
pSessionIDv6, 317
GetSessionState
qaGobiApiWds.h, 2324
GetSignalStrengths
qaGobiApiNas.h, 2117
GetStoredImages

qaGobiApiFms.h, 2051
getTransLayerInfoResp
qaGobiApiSms.h, 2172
getTransNWRegInfoResp
qaGobiApiSms.h, 2173
GetValidFwPriCombinations
fms.h, 1786
GetVoiceNumber
qaGobiApiDms.h, 2019
GetXTRAAutomaticDownload
qaGobiApiPds.h, 2147
GetXTRANetwork
qaGobiApiPds.h, 2148
GetXTRAValidity
qaGobiApiPds.h, 2148
glo_almanac_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
glo_ephemeris_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
glo_health_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
glo_visible_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
GlobalCellID
nas_QmisNasSlqsNasPCICellInfo, 580
SlqsNasPCICellInfo, 1037
globalCellId
LTEInfoIntrafreq, 445
nas_LTEInfoIntrafreq, 531
glog
common.h, 1725
gloglvl
common.h, 1725
GnssData, 319
mask, 320
gnssSvId
loc_satelliteInfo, 418
satelliteInfo, 986
gnssSvInfoNotification, 320
bAltitudeAssumed, 321
pSatelliteInfo, 321
results, 321
gnssSvUsedList
loc_svUsedforFix, 421
svUsedforFix_s, 1090
gnssSvUsedList_len
loc_svUsedforFix, 421
svUsedforFix_s, 1090
Gpp2TimeZone
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1336
GppNetworkDSTAdjustment
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1336
GppTimeZone
qaQmiServingSystemParam, 915
unpack_nas_SLQSGetServingSystem_t, 1336
gps_almanac_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
gps_ephemeris_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
gps_health_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
gps_visible_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
GpsEnable
custFeaturesInfo, 226
pack_dms_SetCustFeature_t, 710
unpack_dms_GetCustFeature_t, 1211
gpsTime
qaGobiApiCbk.h, 1915
gpsTime_s, 327
gpsTimeOfWeekMs, 327
gpsWeek, 327
gpsTimeOfWeekMs
gpsTime_s, 327
loc_gpsTime, 410
t_gpsTime, 1123
gpsWeek
gpsTime_s, 327
loc_gpsTime, 410
t_gpsTime, 1123
grntDownlinkBitrate
LibPackUMTSQoS, 402
UMTSMinQoS, 1199
UMTSQoS, 1202
wds_UMTSMinQoS, 1699
grntUplinkBitrate
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
gsmAmrStat
curAMRConfig, 218
voice_curAMRConfig, 1598
GsmCellInfo
lteGsmCellInfo, 440
nas_lteGsmCellInfo, 526
gsmCellInfo, 327
arfcn, 328
band1900, 328
bsicId, 328
cellIdValid, 328
rssi, 328
srxlev, 328
gsmUmtsDl
NasSwiIndReg, 675
pack_nas_SLQSNasSwiIndicationRegister_t, 761

gsmUmtsUl
NasSwiIndReg, 675
pack_nas_SLQSNasSwiIndicationRegister_t, 761
guaranteedRate
dataRate, 235
unpack_qos_dataRate_t, 1398
gwAddressV6
IPV6GWAddressInfo, 371
wds_IPV6GWAddressInfo, 1692
gwV6PrefixLen
IPV6GWAddressInfo, 371
wds_IPV6GWAddressInfo, 1692
gyroAcceptReady
qaGobiApiCbk.h, 1915
gyroAcceptReady_s, 333
batchPerSec, 333
injectEnable, 333
samplesPerBatch, 334
gyroData
pack_loc_SLQSLOCInjectSensorData_t, 737
gyroTemp
pack_loc_SLQSLOCInjectSensorData_t, 737
gyroTempAcceptReady
qaGobiApiCbk.h, 1916
gyroTempAcceptReady_s, 334
batchPerSec, 334
injectEnable, 334
samplesPerBatch, 334
gyroTimeSrc
pack_loc_SLQSLOCInjectSensorData_t, 738

HASPI
unpack_wds_GetMobileIPProfile_t, 1525
HAState
unpack_wds_GetMobileIPProfile_t, 1525
HDOP
loc_precisionDilution, 416
precisionDilution_s, 890
HDRECIOThresh, 334
HDRECIOThreshListLen, 335
pHDRECIOThreshList, 335
HDRECIOThreshListLen
HDRECIOThresh, 335
nas_HDRECIOThresh, 514
HDRIOThresh, 335
HDRIOThreshListLen, 335
pHDRIOThreshList, 335
HDRIOThreshListLen
HDRIOThresh, 335
nas_HDRIOThresh, 514
HDRPersonalityInd, 335
pCurrentPersonality, 336
pPersonalityListLength, 336
pProtocolSubtypeElement, 336
HDRPersonalityResp, 336
pCurrentPersonality, 336
pPersonalityListLength, 336
pProtocolSubtypeElement, 336
HDRProtSubtypResp, 336
pAppSubType, 337
pCurrentPrsnlty, 337
pPersonalityListLength, 337
pProtoSubTypElmnt, 337
HDRRSSIThresh, 337
HDRRSSIThreshListLen, 338
pHDRRSSIThreshList, 338
HDRRSSIThreshListLen
HDRRSSIThresh, 338
nas_HDRRSSIThresh, 515
HDRSINRThresListLen
HDRSINRThresh, 338
nas_HDRSINRThresh, 516
HDRSINRThresh, 338
HDRSINRThresListLen, 338
pHDRSINRThresList, 338
HDRSINRThreshListLen
HDRSINRThreshold, 339
nas_HDRSINRThreshold, 517
HDRSINRThreshold, 338
HDRSINRThreshListLen, 339
pHDRSINRThreshList, 339
HDRSSInfo, 340
ecio, 341
io, 341
rssi, 341
sinr, 341
unpack_nas_SLQSNasGetSigInfo_t, 1359
HDRSysInfo, 341
hdrActiveProt, 343
hdrActiveProtValid, 343
hdrPersonality, 343
hdrPersonalityValid, 343
is856SysId, 343
is856SysIdValid, 343
isSysPrlMatch, 343
isSysPrlMatchValid, 343
sysInfoHDR, 343
HTTPStatus
_SwiAvmsEventInd, 113
HWVersion
DeviceConfigDetail, 242
nas_DeviceConfigDetail, 497
HardwareControlledMode
unpack_dms_GetPower_t, 1228
has_CycleLen
nasGeteDRXParamsResp, 633
has_EdrxEnable
nasGeteDRXParamsResp, 633
has_EdrxRAT
nasGeteDRXParamsResp, 633
has_LpmFlag
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1242
has_LteOpMode
nasGeteDRXParamsResp, 633
has_PCIInfo
_slqsNetworkScanInfo, 98
has_PagingTimeWindow

nasGeteDRXParamsResp, 633
has_PersistentLpm
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1242
has_PositionDataNMEA
unpack_pds_SetEventReport_Ind_t, 1390
has_PowerOffMode
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1242
has_SessionStatus
unpack_pds_SetEventReport_Ind_t, 1390
has_Wdisable
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1242
has_accelTemp
pack_loc_SLQSLOCInjectSensorData_t, 738
has_acceleroTimeSrc
pack_loc_SLQSLOCInjectSensorData_t, 738
has_accleroData
pack_loc_SLQSLOCInjectSensorData_t, 738
has_altitudeSrcInfo
pack_loc_SLQSLOCInjectPosition_t, 735
has_altitudeWrtEllipsoid
pack_loc_SLQSLOCInjectPosition_t, 735
has_altitudeWrtMeanSeaLevel
pack_loc_SLQSLOCInjectPosition_t, 735
has_confidence
pack_loc_SLQSLOCSetCradleMountConfig_t, 739
has_dLatitude
unpack_pds_SetEventReport_Ind_t, 1390
has_dLongitude
unpack_pds_SetEventReport_Ind_t, 1390
has_gyroData
pack_loc_SLQSLOCInjectSensorData_t, 738
has_gyroTemp
pack_loc_SLQSLOCInjectSensorData_t, 738
has_gyroTimeSrc
pack_loc_SLQSLOCInjectSensorData_t, 738
has_horConfidence
pack_loc_SLQSLOCInjectPosition_t, 735
has_horReliability
pack_loc_SLQSLOCInjectPosition_t, 735
has_horUncCircular
pack_loc_SLQSLOCInjectPosition_t, 735
has_latitude
pack_loc_SLQSLOCInjectPosition_t, 735
has_longitude
pack_loc_SLQSLOCInjectPosition_t, 735
has_opaqueId
pack_loc_SLQSLOCInjectSensorData_t, 738
has_posSrc
unpack_pds_SetEventReport_Ind_t, 1390
has_positionSrc
pack_loc_SLQSLOCInjectPosition_t, 735
has_rawHorConfidence
pack_loc_SLQSLOCInjectPosition_t, 735
has_rawHorUncCircular
pack_loc_SLQSLOCInjectPosition_t, 735
has_serverAddrTypeMask
pack_loc_SLQSLOCGetServer_t, 731
has_timestampAge
pack_loc_SLQSLOCInjectPosition_t, 735
has_timestampUtc
pack_loc_SLQSLOCInjectPosition_t, 735
has_vertConfidence
pack_loc_SLQSLOCInjectPosition_t, 735
has_vertRelicability
pack_loc_SLQSLOCInjectPosition_t, 735
has_vertUnc
pack_loc_SLQSLOCInjectPosition_t, 736
hdrActiveProt
HDRSysInfo, 343
nas_HDRSysInfo, 519
hdrActiveProtValid
HDRSysInfo, 343
nas_HDRSysInfo, 519
hdrHybrid
detailSvcInfo, 241
nas_detailSvcInfo, 496
HdrPersonality
unpack_nas_SLQSGetServingSystem_t, 1336
hdrPersonality
HDRSysInfo, 343
nas_HDRSysInfo, 519
NASServingSystemInfo, 670
qaQmiServingSystemParam, 915
ServingSystemInfo, 994
hdrPersonalityValid
HDRSysInfo, 343
nas_HDRSysInfo, 519
hdrSSInfo, 339
ecio, 340
io, 340
rssi, 340
sinr, 340
hdrSrvStatus
detailSvcInfo, 241
nas_detailSvcInfo, 496
healthStatus
loc_satelliteInfo, 418
satelliteInfo, 986
helper_get_error_code
common.h, 1723
helper_get_error_reason
common.h, 1724
helper_get_req_str
common.h, 1724
helper_get_resp_ctx
common.h, 1724
helper_get_xid
common.h, 1724
helper_isBootLoader_DebugEnabled
common.h, 1724
helper_set_log_func
common.h, 1724
helper_set_log_lvl
common.h, 1725
homeOrigVoiceSO
prefVoiceSO, 893

voice_prefVoiceSO, 1610
homePageVoiceSO
prefVoiceSO, 893
voice_prefVoiceSO, 1610
homeSIDNID, 343
numInstances, 344
SidNid, 344
horConfidence
pack_loc_SLQSLOCInjectPosition_t, 736
horReliability
pack_loc_SLQSLOCInjectPosition_t, 736
horUncCircular
pack_loc_SLQSLOCInjectPosition_t, 736
HorizontalUncertainty
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
hostID
pack_dms_SLQSSwiSetHostDevInfo_t, 717
unpack_dms_SLQSSwiGetHostDevInfo_t, 1260
hotSwap
hotSwapStatus, 344
uim_hotSwapStatus, 1158
hotSwapLength
hotSwapStatus, 344
uim_hotSwapStatus, 1158
hotSwapStatus, 344
hotSwap, 344
hotSwapLength, 344
hour
nas_timeInfo, 613
nas_UniversalTime, 619
timeInfo, 1134
UniversalTime, 1205
hrpdMTUSize
hrpdMTUSizeTlv, 345
swidms_hrpdMTUSizeTlv, 1092
hrpdMTUSizeTlv, 344
hrpdMTUSize, 345
TlvPresent, 345
hsCallStatus
nas_WCDMASysInfo, 625
WCDMASysInfo, 1678
hsCallStatusValid
nas_WCDMASysInfo, 625
WCDMASysInfo, 1678
hsInd
nas_WCDMASysInfo, 625
WCDMASysInfo, 1678
hsIndValid
nas_WCDMASysInfo, 625
WCDMASysInfo, 1678
hwType
wds_DHCPv4HWConfig, 1686
WdsDHCPv4HWConfig, 1705
wdsDhcpv4HwConfig, 1706
hwVer
unpack_dms_GetHardwareRevision_t, 1223

iFaceTab
PCMparams, 869
iFaceTabLen
PCMparams, 869
iGetByteTotals
qaGobiApiWds.h, 2324
iGetConnectionRate
qaGobiApiWds.h, 2324
iGetPacketStatistics
qaGobiApiWds.h, 2324
iLTEbandValue
nas_PhyCaAggPcellInfo, 566
nas_PhyCaAggScellInfo, 570
NASPhyCaAggPcellInfo, 657
NASPhyCaAggScellInfo, 661
PhyCaAggPcellInfo, 877
PhyCaAggScellInfo, 883
IMCNflag
unpack_wds_SLQSGetRuntimeSettings_t, 1545
IMEIString
unpack_dms_GetDeviceSerialNumbers_t, 1218
IMG_ID_LEN
qaGobiApiFms.h, 2046
IMGDETAILS_LEN
qaGobiApiFms.h, 2046
IMS Service (IMS), 61
IMSAIndRegisterInfo, 349
pPdpStatusConfig, 349
pRatHandoverStatusConfig, 349
pRegStatusConfig, 350
pServiceStatusConfig, 350
IMSARegistrationStatus, 351
pImsRegErrCode, 352
pImsRegStatus, 352
pNewImsRegStatus, 352
IMSAServiceStatus, 352
pSmsServiceRat, 354
pSmsServiceStatus, 354
pUtServiceRat, 354
pUtServiceStatus, 354
pVoipServiceRat, 354
pVoipServiceStatus, 354
pVsServiceRat, 354
pVsServiceStatus, 354
pVtServiceRat, 354
pVtServiceStatus, 355
IMSASupportedFieldsResp, 355
pIndFieldsList, 355
pReqFieldsList, 355
pRespFieldsList, 355
IMSASupportedMsgInfo, 355
pSupportedMsgList, 356
IMSI_M_S1_LENGTH
qaGobiApiNas.h, 2089
IMSI_M_S2_LENGTH
qaGobiApiNas.h, 2089
IMSInfo
sMSOnIMSTlv, 1077
IMSTlv

unpack_sms_SetNewSMSCallback_ind_t, 1426
INDEX_ZERO
qaNasPerformNetworkScan.h, 2350
INT32
SwiDataTypes.h, 2396
INT8
SwiDataTypes.h, 2396
INVALID_INSTACNE
qaGobiApiCbk.h, 1912
IOThresListLen
IOThresh, 367
nas_IOThresh, 521
IOThresh, 366
IOThresListLen, 367
pIOThresList, 367
IPAddress
DataStatusDetail, 237
nas_DataStatusDetail, 494
IPAddressV6
IPV6AddressInfo, 370
ipv6AddressInfo, 369
wds_IPV6AddressInfo, 1691
IPFamSupport
pack_dms_SetCustFeature_t, 710
unpack_dms_GetCustFeature_t, 1211
IPFamilyPreference
pack_wds_SLQSSetIPFamilyPreference_t, 861
unpack_wds_SLQSGetRuntimeSettings_t, 1545
IPSECSPI
LibPackTFTIDParams, 400
TFTIDParams, 1132
IPV4
qaGobiApiCbk.h, 1912
IPV4V6
qaGobiApiCbk.h, 1912
IPV6
qaGobiApiCbk.h, 1912
IPV6AddrInfo
unpack_wds_SLQSGetRuntimeSettings_t, 1545
IPV6AddressInfo, 369
IPAddressV6, 370
IPV6PrefixLen, 370
IPV6GWAddrInfo
unpack_wds_SLQSGetRuntimeSettings_t, 1545
IPV6GWAddressInfo, 370
gwAddressV6, 371
gwV6PrefixLen, 371
IPV6PrefixLen
IPV6AddressInfo, 370
ipv6AddressInfo, 369
wds_IPV6AddressInfo, 1691
IPv4
unpack_wds_SLQSGetRuntimeSettings_t, 1545
IPv4Addr, 367
addr, 367
IPv4Config, 368
loc_IPv4Config, 412
subnetMask, 367
wds_IPv4AdTlv, 1691
IPv4AddrTlv
unpack_wds_DHCPv4ClientLease_ind_t, 1515
IPv4Config, 367
IPv4Addr, 368
IPv4Port, 368
IPv4DstAddr
unpack_qos_swiQosFilter_t, 1412
IPv4Info, 368
address, 368
port, 368
TlvPresent, 368
IPv4Port
IPv4Config, 368
loc_IPv4Config, 412
IPv4SrcAddr
unpack_qos_swiQosFilter_t, 1412
IPv4Tos
unpack_qos_swiQosFilter_t, 1412
IPv6Addr, 368
addr, 369
IPv6Config, 370
loc_IPv6Config, 413
prefixLen, 369
IPv6Config, 370
IPv6Addr, 370
IPv6Port, 370
IPv6DstAddr
unpack_qos_swiQosFilter_t, 1412
IPv6Info, 371
address, 371
port, 372
TlvPresent, 372
IPv6Label
unpack_qos_swiQosFilter_t, 1412
IPv6Port
IPv6Config, 370
loc_IPv6Config, 413
IPv6SrcAddr
unpack_qos_swiQosFilter_t, 1412
IPv6TrafCls, 372
mask, 372
unpack_qos_swiQosFilter_t, 1412
val, 372
iSLQSMISetIPFamilyPreference
qaGobiApiWds.h, 2324
iSLQSSetDUNCallInfoCallback
qaGobiApiCbk.h, 1955
iSLQSSetSignalStrengthsCallback
qaGobiApiCbk.h, 1955
iSLQSSetWdsFirstInstEventCallback
qaGobiApiCbk.h, 1955
iSLQSSetWdsSecondInstEventCallback
qaGobiApiCbk.h, 1955
iSLQSSetWdsThirdInstEventCallback
qaGobiApiCbk.h, 1955
iSLQSSetWdsXferStatsFirstInstCallback
qaGobiApiCbk.h, 1955

iSLQSSetWdsXferStatsSecondInstCallback
qaGobiApiCbk.h, 1955
iSetCATEventCallback
qaGobiApiCbk.h, 1955
iSetSignalStrengthCallback
qaGobiApiCbk.h, 1955
Id
unpack_qos_swiQosFilter_t, 1412
id
BdsSV, 157
CSGID, 216
loc_BdsSV, 406
loc_SV, 420
nas_CSGID, 491
pack_dms_UIMChangePIN_t, 720
pack_dms_UIMSetPINProtection_t, 722
pack_dms_UIMUnblockPIN_t, 723
pack_dms_UIMVerifyPIN_t, 724
QosFlowInfoState, 957
SV, 1089
swiQosModifyReq, 1115
unpack_qos_QosFlowInfoState_t, 1402
unpack_qos_SLQSSetQosStatusCallback_ind_t, 1410
id_length
custSettingInfo, 229
DMScustSettingInfo, 255
IdleState
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
IfaceID
qos_BindDataPortPeripheralEndPointID_t, 953
image_info_t, 345
buildID, 345
buildIDLen, 345
imageType, 345
uniqueID, 345
ImageElement, 346
buildId, 346
buildIdLength, 346
imageId, 346
imageType, 346
imageID
FMSImageIdElement, 283
ImageIdElement, 347
imageIDElement
FMSImageIDEntries, 284
ImageIDEntries, 348
ImageIDEntries, 347
executingImage, 348
imageIDElement, 348
imageIDSize, 348
imageType, 348
maxImages, 348
imageIDEntries
FMSImageList, 285
ImageList, 348
imageIDSize
FMSImageIDEntries, 284
ImageIDEntries, 348
imageId
FMSImageElement, 282
ImageElement, 346
ImageIdElement, 346
buildID, 347
buildIDLength, 347
failureCount, 347
imageID, 347
storageIndex, 347
ImageList, 348
imageIDEntries, 348
listSize, 349
imageList
unpack_fms_GetStoredImages_t, 1273
ImageListSize
unpack_fms_GetImagesPreference_t, 1272
imageListSize
pack_fms_SetImagesPreference_t, 725
imageType
CurrImageInfo, 222
FMSImageElement, 282
FMSImageIDEntries, 284
image_info_t, 345
ImageElement, 346
ImageIDEntries, 348
ImageTypes
unpack_fms_SetImagesPreference_t, 1273
ImageTypesSize
unpack_fms_SetImagesPreference_t, 1273
imagelistSize
unpack_fms_GetStoredImages_t, 1273
imei_no
unpack_dms_GetSerialNumbers_t, 1230
imeiSize
serialNumbersInfo, 992
unpack_dms_GetDeviceSerialNumbers_t, 1218
imeiSvnSize
serialNumbersInfo, 992
unpack_dms_GetDeviceSerialNumbers_t, 1218
ImeiSvnString
unpack_dms_GetDeviceSerialNumbers_t, 1218
imeisv_svn
unpack_dms_GetSerialNumbers_t, 1230
imgType
unpack_dms_SLQSSwiGetFwUpdateStatus_t, 1259
imsCfgIndRegisterInfo, 357
pRegMgrConfigEvents, 358
pSIPConfigEvents, 358
pSMSConfigEvents, 358
pUserConfigEvents, 358
pVoIPConfigEvents, 358
imsRegMgrConfigInfo, 358
pCSCFPortName, 359
pIMSTestMode, 359
pPriCSCFPort, 359

imsRegState
CommInfo, 207
nas_CommInfo, 490
imsSIPConfigInfo, 359
pSIPLocalPort, 360
pSigCompEnabled, 360
pSubscribeTimer, 360
pTimerSIPReg, 360
pTimerT1, 360
pTimerT2, 360
pTimerTf, 360
imsSMSConfigInfo, 360
pPhoneCtxtURI, 360
pSMSFormat, 360
pSMSOverIPNwInd, 360
imsUserConfigInfo, 361
pIMSDomain, 361
imsVoIPConfigInfo, 361
pAmrMode, 363
pAmrOctetAligned, 363
pAmrWBMode, 363
pAmrWBOctetAligned, 363
pAmrWbEnable, 363
pMinSessionExpiryTimer, 363
pRTPRTCPInactTimer, 363
pRingBackTimer, 363
pRingingTimer, 363
pScrAmrEnable, 363
pScrAmrWbEnable, 363
pSessionExpiryTimer, 363
imsaPdpStatusInfo, 350
connetionState, 350
pFailErrorCode, 350
imsaRatStatusInfo, 350
pErrorCodeStr, 351
pRATStatus, 351
pSrcRAT, 351
pTgtRAT, 351
imsaRegStatusInfo, 352
pImsRegStatus, 352
pRegStatusErrorCode, 352
pbIMSRegistered, 352
imsaSvcStatusInfo, 356
pSMSSvcRAT, 356
pSMSSvcStatus, 356
pUTSvcRAT, 356
pUTSvcStatus, 356
pVOIPSvcRAT, 356
pVOIPSvcStatus, 357
pVTSvcRAT, 357
pVTSvcStatus, 357
imsi
unpack_dms_GetIMSI_t, 1224
imsi_11_12
CDMASysInfoExt, 194
nas_CDMASysInfoExt, 485
imsiM1112
minBasedIMSI, 467
nas_minBasedIMSI, 549
imsiMS1
minBasedIMSI, 467
nas_minBasedIMSI, 549
imsiMS2
minBasedIMSI, 467
nas_minBasedIMSI, 549
imsiT1112
nas_trueIMSI, 614
trueIMSI, 1141
imsiTS1
nas_trueIMSI, 614
trueIMSI, 1141
imsiTS2
nas_trueIMSI, 614
trueIMSI, 1141
imsiTaddrNum
nas_trueIMSI, 614
trueIMSI, 1141
InUse
nas_QmiNas3GppNetworkInfo, 578
SlqsNas3GppNetworkInfo, 1036
includes_pcs_digit
nas_QmisNasPcsDigit, 580
SlqsNasPcsDigit, 1039
IndFieldsList, 363
indicationFields, 364
indicationFieldsLen, 364
index
pack_wds_GetMobileIPProfile_t, 845
pack_wds_SetDefaultProfileNum_t, 849
pack_wds_SetMobileIPProfile_t, 852
swiQosFilter, 1110
swiQosFlow, 1113
swiQosReq, 1116
unpack_qos_swiQosFilter_t, 1412
unpack_qos_swiQosFlow_t, 1416
unpack_wds_GetDefaultProfileNum_t, 1521
index1xPri
cardStatus, 172
uim_cardStatus, 1151
index1xSec
cardStatus, 172
uim_cardStatus, 1151
indexGwPri
cardStatus, 172
uim_cardStatus, 1151
indexGwSec
cardStatus, 172
uim_cardStatus, 1151
indicationFields
IndFieldsList, 364
indicationFieldsLen
IndFieldsList, 364
Info
unpack_nas_SLQSNasSwiOTAMessageCallback-_ind_t, 1368

unpack_nas_SLQSSetSysSelectionPrefCallBack-_ind_t, 1369
infoInterFreq, 364
cell_resel_priority, 365
cellInterFreqParams, 365
cells_len, 365
earfcn, 365
threshXHigh, 365
threshXLow, 365
InfoInterfreq
LTEInfoInterfreq, 443
nas_LTEInfoInterfreq, 529
InitiateDomainAttach
qaGobiApiNas.h, 2117
InitiateNetworkRegistration
qaGobiApiNas.h, 2118
injectEnable
accelAcceptReady_s, 128
accelTempAcceptReady_s, 129
gyroAcceptReady_s, 333
gyroTempAcceptReady_s, 334
loc_accelAcceptReady, 404
loc_accelTempAcceptReady, 405
loc_gyroAcceptReady, 411
loc_gyroTempAcceptReady, 412
injectSensorDataStatus
QmiCbkLocInjectSensorDataInd, 928
unpack_loc_InjectSensorDataCallback_Ind_t, 1290
injectTimeSyncStatus
QmiCbkLocInjectTimeInd, 929
unpack_loc_InjectTimeSyncDataCallback_Ind_t, 1291
insNmrCellInfo
GERANInfo, 288
nas_GERANInfo, 506
instance
SLQSSetDHCPv4ClientLeaseStatusCallback-Param, 1043
instanceId
ssdatasession_params, 1086
instancesSize
unpack_nas_GetRFInfo_t, 1314
interval
pack_pds_SetPDSDefaults_t, 783
pack_pds_SetXTRAAutomaticDownload_t, 785
pack_wds_SLQSSetWdsEventCallback_t, 862
TransferStatsDataType, 1139
intf
dms_UimStatusTlv, 253
intfaceCfgTlv, 365
CfgValue, 366
CurrentCfgType, 366
TlvPresent, 366
Io
slqsSignalStrengthInfo, 1045
unpack_nas_SLQSGetSignalStrength_t, 1338
io
HDRSSInfo, 341
hdrSSInfo, 340
nas_SLQSSignalStrengthsInformation, 604
SLQSSignalStrengthsInformation, 1049
ioDelta
nas_SLQSSignalStrengthsIndReq, 603
SLQSSignalStrengthsIndReq, 1047
Iono_valid
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
ip
WdsIpAddressInfoReq, 1710
ipAddress
pack_wds_SetDefaultProfile_t, 849
ipFamily
_packetSrvStatus, 76
unpack_wds_SLQSSetPacketSrvStatusCallback_-t, 1549
ipVersion
LibPackTFTIDParams, 400
TFTIDParams, 1132
ipaddr
unpack_wds_GetDefaultProfile_t, 1520
ipaddrv6
unpack_wds_GetDefaultProfile_t, 1521
ipfamily
ssdatasession_params, 1086
ipv4Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
ipv4GWAddress
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
ipv6Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
ipv6AddressInfo, 369
IPAddressV6, 369
IPV6PrefixLen, 369
ipv6GWAddress
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
is856SysId
HDRSysInfo, 343
nas_HDRSysInfo, 519
is856SysIdValid
HDRSysInfo, 343
nas_HDRSysInfo, 519
is_DataRate_Available
unpack_qos_swiQosFlow_t, 1416
is_EspSpi_Available
unpack_qos_swiQosFilter_t, 1412
is_IPv4DstAddr_Available
unpack_qos_swiQosFilter_t, 1412
is_IPv4SrcAddr_Available
unpack_qos_swiQosFilter_t, 1412
is_IPv4Tos_Available
unpack_qos_swiQosFilter_t, 1412

is_IPv6DstAddr_Available
unpack_qos_swiQosFilter_t, 1412
is_IPv6Label_Available
unpack_qos_swiQosFilter_t, 1412
is_IPv6SrcAddr_Available
unpack_qos_swiQosFilter_t, 1412
is_IPv6TrafCls_Available
unpack_qos_swiQosFilter_t, 1412
is_Id_Available
unpack_qos_swiQosFilter_t, 1412
is_Jitter_Available
unpack_qos_swiQosFlow_t, 1416
is_Latency_Available
unpack_qos_swiQosFlow_t, 1416
is_LteBandCapability_Available
unpack_dms_SLQSGetBandCapability_t, 1251
is_LteQci_Available
unpack_qos_swiQosFlow_t, 1416
is_MaxAllowedPktSz_Available
unpack_qos_swiQosFlow_t, 1416
is_MinPolicedPktSz_Available
unpack_qos_swiQosFlow_t, 1416
is_NxtHdrProto_Available
unpack_qos_swiQosFilter_t, 1413
is_PktErrRate_Available
unpack_qos_swiQosFlow_t, 1416
is_Precedence_Available
unpack_qos_swiQosFilter_t, 1413
is_ProfileId3GPP2_Available
unpack_qos_swiQosFlow_t, 1416
is_RxQFlowGranted_Available
unpack_qos_QosFlowInfo_t, 1401
is_TCPDstPort_Available
unpack_qos_swiQosFilter_t, 1413
is_TCPSrcPort_Available
unpack_qos_swiQosFilter_t, 1413
is_TdsBandCapability_Available
unpack_dms_SLQSGetBandCapability_t, 1251
is_TokenBucket_Available
unpack_qos_swiQosFlow_t, 1416
is_TrafficClass_Available
unpack_qos_swiQosFlow_t, 1416
is_TranDstPort_Available
unpack_qos_swiQosFilter_t, 1413
is_TranSrcPort_Available
unpack_qos_swiQosFilter_t, 1413
is_TxQFlowGranted_Available
unpack_qos_QosFlowInfo_t, 1401
is_UDPDstPort_Available
unpack_qos_swiQosFilter_t, 1413
is_UDPSrcPort_Available
unpack_qos_swiQosFilter_t, 1413
is_val_3GPP2Pri_Available
unpack_qos_swiQosFlow_t, 1416
is_val_3GPPImCn_Available
unpack_qos_swiQosFlow_t, 1416
is_val_3GPPResResidualBER_Available
unpack_qos_swiQosFlow_t, 1416
is_val_3GPPSigInd_Available
unpack_qos_swiQosFlow_t, 1417
is_val_3GPPTraHdlPri_Available
unpack_qos_swiQosFlow_t, 1417
isEmpty
getAllCallInformation, 290
voice_getAllCallInformation, 1602
isInTraffic
nas_txInfo, 614
txInfo, 1143
isModByCC
SUPSInfo, 1088
voice_SUPSInfo, 1615
isNewFlow
QosFlowInfoState, 957
unpack_qos_QosFlowInfoState_t, 1402
isPrefDataPath
GSMSrvStatusInfo, 330
nas_GSMSrvStatusInfo, 510
nas_NR5GSerStatTlv, 559
nas_SrvStatusInfo, 606
NR5GSerStatTlv, 691
SrvStatusInfo, 1083
isRadioTuned
nas_rxInfo, 595
nas_RxSigInfo, 596
rxInfo, 979
RxSigInfo, 982
isSysForbidden
detailSvcInfo, 241
nas_detailSvcInfo, 496
nas_sysInfoCommon, 608
sysInfoCommon, 1119
isSysForbiddenValid
nas_sysInfoCommon, 608
sysInfoCommon, 1119
isSysPrlMatch
CDMASysInfo, 193
HDRSysInfo, 343
nas_CDMASysInfo, 484
nas_HDRSysInfo, 519
isSysPrlMatchValid
CDMASysInfo, 193
HDRSysInfo, 343
nas_CDMASysInfo, 484
nas_HDRSysInfo, 519
IsVoiceEnabled
pack_dms_SetCustFeature_t, 710
unpack_dms_GetCustFeature_t, 1211
Item
GetAudioPathConfigReq, 292
GetAudioVolTLBConfigReq, 296
SetAudioVolTLBConfigReq, 1002

Jitter
unpack_qos_swiQosFlow_t, 1417
jtagAccessAllowed
SwiDmsGetSecureInfoResp, 1098

unpack_swidms_SLQSSwiDmsGetSecureInfo_t, 1443

KeyExchange
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906

LITE_SYS_SRV_DOMAIN_CAMPED
nas.h, 1824
LITE_SYS_SRV_DOMAIN_CS_ONLY
nas.h, 1824
LITE_SYS_SRV_DOMAIN_CS_PS
nas.h, 1824
LITE_SYS_SRV_DOMAIN_NO_SRV
nas.h, 1824
LITE_SYS_SRV_DOMAIN_PS_ONLY
nas.h, 1824
LITE_VOICE_SUPS_SRV_CLASS_DATA
voice.h, 2443
LITE_VOICE_SUPS_SRV_CLASS_DATACIRCUITASYNC
voice.h, 2443
LITE_VOICE_SUPS_SRV_CLASS_DATACIRCUITSYNC
voice.h, 2443
LITE_VOICE_SUPS_SRV_CLASS_FAX
voice.h, 2443
LITE_VOICE_SUPS_SRV_CLASS_NONE
voice.h, 2443
LITE_VOICE_SUPS_SRV_CLASS_PACKETACCESS
voice.h, 2443
LITE_VOICE_SUPS_SRV_CLASS_PADACCESS
voice.h, 2443
LITE_VOICE_SUPS_SRV_CLASS_SMS
voice.h, 2443
LITE_VOICE_SUPS_SRV_CLASS_VOICE
voice.h, 2443
LITEQMI_QMI_CBK_PARAM_NOCHANGE
sms.h, 2376
LITEQMI_QMI_CBK_PARAM_RESET
sms.h, 2376
LITEQMI_QMI_CBK_PARAM_SET
sms.h, 2376
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_1
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_10
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_11
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_12
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_125
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_126
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_127
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_13
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_14
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_17
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_18
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_19
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_2
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_20
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_21
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_23
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_24
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_25
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_250
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_26
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_27
qaGobiApiNas.h, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_28
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_29
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_3
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_30
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_31

qaGobiApiNas.h, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-32
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-33
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-34
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-35
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-36
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-37
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-38
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-39
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_4
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-40
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-41
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-42
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-43
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-46
qaGobiApiNas.h, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-47
qaGobiApiNas.h, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-48
qaGobiApiNas.h, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_5
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_6
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-66
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_7
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_-71
qaGobiApiNas.h, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_8
qaGobiApiNas.h, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_9
qaGobiApiNas.h, 2107
LBPTlv
NASQmiCbkNasSystemSelPrefInd, 668
LEN
qaGobiApiDcs.h, 1994
LMCERTlv
unpack_wds_SLQSDUNCallInfoCallBack_ind_t, 1534
LOCEVENTMASKGNSSSVINFO
loc.h, 1792
LOCEVENTMASKNMEA
loc.h, 1793
LOCEVENTMASKWIFIREQ
loc.h, 1794
LOCEventRegisterReqResp, 424
eventRegister, 426
LOCExtPowerStateReqResp, 426
extPowerState, 426
LOCStartReq, 434
pApplicationInfo, 435
pConfigAltitudeAssumed, 435
pHorizontalAccuracyLvl, 435
pIntermediateReportState, 435
pMinIntervalTime, 435
pRecurrenceType, 435
SessionId, 435
LOCStopReq, 436
sessionId, 436
LPCSTR
SwiDataTypes.h, 2396
LTEAttachProfile
unpack_wds_SLQSGet3GPPConfigItem_t, 1535
LTEAttachProfileList
unpack_wds_SLQSGet3GPPConfigItem_t, 1536
LTEAttachProfileListLen
_slqs3GPPConfigItem, 90
pack_wds_SLQSSet3GPPConfigItem_t, 860
unpack_wds_SLQSGet3GPPConfigItem_t, 1536
LTEBandPref
nas_LTEBandPrefTlv, 523
NASLTEBandPreferenceTlv, 648
LTEBandPrefExtTlv
qaGobiApiNas.h, 2090
LTECphyCaInfo
unpack_nas_SlqsGetLTECphyCAInfo_t, 1327
LTEInfo, 440
band, 442
bandwidth, 442
emmConnState, 442
emmState, 442
emmSubState, 442
RXChan, 442

TXChan, 442
LTEInfoInterfreq, 443
freqsLen, 443
InfoInterfreq, 443
ueInIdle, 443
LTEInfoIntrafreq, 443
CellParams, 445
cellReselPriority, 445
cellsLen, 445
earfcn, 445
globalCellId, 445
plmn, 445
sIntraSearch, 445
sNonIntraSearch, 445
servingCellId, 445
tac, 445
threshServingLow, 445
ueInIdle, 445
LTEInfoNeighboringGSM, 445
freqsLen, 446
LteGsmCellInfo, 446
ueInIdle, 446
LTEInfoNeighboringWCDMA, 446
freqsLen, 447
LTEWCDMACellInfo, 447
ueInIdle, 447
LTEOperationMode, 451
pLTEOperationMode, 451
TlvPresent, 451
LTERSRPThresh, 454
LTERSRPThreshListLen, 454
pLTERSRPThreshList, 454
LTERSRPThreshListLen
LTERSRPThresh, 454
nas_LTERSRPThresh, 540
LTERSRQThresh, 455
LTERSRQThreshListLen, 455
pLTERSRQThreshList, 455
LTERSRQThreshListLen
LTERSRQThresh, 455
nas_LTERSRQThresh, 541
LTERSSIThresh, 455
LTERSSIThreshListLen, 456
pLTERSSIThreshList, 456
LTERSSIThreshListLen
LTERSSIThresh, 456
nas_LTERSSIThresh, 541
LTESNRThresListLen
LTESNRThresh, 459
nas_LTESNRThresh, 544
LTESNRThresh, 458
LTESNRThresListLen, 459
pLTESNRThresList, 459
LTESNRThreshListLen
LTESNRThreshold, 459
nas_LTESNRThreshold, 545
LTESNRThreshold, 459
LTESNRThreshListLen, 459
pLTESNRThreshList, 459
LTESSInfo, 460
rsrp, 461
rsrq, 461
rssi, 461
snr, 461
unpack_nas_SLQSNasGetSigInfo_t, 1359
LTESigRptCfg, 456
avgPeriod, 457
rptRate, 457
LTESigRptConfig, 457
avgPeriod, 458
rptRate, 458
LTESysInfo, 461
cellId, 463
cellIdValid, 463
lac, 463
lacValid, 463
MCC, 463
MNC, 463
networkIdValid, 463
regRejectInfoValid, 463
rejCause, 463
rejectSrvDomain, 463
sysInfoLTE, 463
tac, 463
tacValid, 464
LTEWCDMACellInfo
LTEInfoNeighboringWCDMA, 447
nas_LTEInfoNeighboringWCDMA, 533
Lac
qaQmiServingSystemParam, 916
unpack_nas_SLQSGetServingSystem_t, 1336
lac
GERANInfo, 288
GSMSysInfo, 332
LTESysInfo, 463
nas_GERANInfo, 506
nas_GSMSysInfo, 512
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 562
nas_UMTSInfo, 616
nas_WCDMASysInfo, 625
NR5GSystemInfoTlv, 694
UMTSInfo, 1196
WCDMASysInfo, 1678
lac1
nas_OperatorPLMNData, 564
OperatorPLMNData, 705
lac2
nas_OperatorPLMNData, 564
OperatorPLMNData, 705
lacValid
GSMSysInfo, 333
LTESysInfo, 463
nas_GSMSysInfo, 512
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 562

nas_WCDMASysInfo, 625
NR5GSystemInfoTlv, 694
WCDMASysInfo, 1678
language
CDMABroadcastConfig, 178
sms_CDMABroadcastConfig, 1052
lastCallDataBearerTech
unpack_wds_SLQSGetDUNCallInfo_t, 1541
lastCallDataBearerTechnology
unpack_wds_SLQSGetDataBearerTechnology_t, 1539
lastCallRXOKBytesCnt
unpack_wds_SLQSGetDUNCallInfo_t, 1541
lastCallTXOKBytesCnt
unpack_wds_SLQSGetDUNCallInfo_t, 1541
LastErrCode
DataStatusDetail, 237
nas_DataStatusDetail, 494
Latency
unpack_qos_swiQosFlow_t, 1417
Latitude
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
latitude
pack_loc_SLQSLOCInjectPosition_t, 736
leapSeconds
nas_qaQmi3Gpp2TimeZone, 577
qaQmi3Gpp2TimeZone, 911
leaseState
wds_DHCPLeaseStateTlv, 1684
len
BdsSVInfo, 158
loc_BdsSVInfo, 406
loc_SVInfo, 420
SVInfo, 1089
t_Sv, 1124
unpack_nas_GetSignalStrengths_t, 1318
length
readTransparentInfo, 960
SMSCAddress, 1067
sMSCAddressInfo, 1067
SMSEtwsMessage, 1068
sMSEtwsMessageInfo, 1069
SMSTransferRouteMTMessage, 1080
sMSTransferRouteMTMessageInfo, 1081
uim_readTransparentInfo, 1160
Level
GetM2MAudioVolumeResp, 313
SetM2MAudioVolumeReq, 1014
LibPackGPRSRequestedQoS, 372
delayClass, 373
meanThroughputClass, 373
peakThroughputClass, 373
precedenceClass, 373
reliabilityClass, 373
LibPackQosClassID, 397
gDlBitRate, 398
gUlBitRate, 398
maxDlBitRate, 398
maxUlBitRate, 398
QCI, 398
LibPackTFTIDParams, 398
destPortRangeEnd, 399
destPortRangeStart, 399
eValid, 399
filterId, 400
flowLabel, 400
IPSECSPI, 400
ipVersion, 400
nextHeader, 400
pSourceIP, 400
sourceIPMask, 400
srcPortRangeEnd, 400
srcPortRangeStart, 400
tosMask, 400
LibPackUMTSQoS, 400
deliveryErrSDU, 402
grntDownlinkBitrate, 402
grntUplinkBitrate, 402
maxDownlinkBitrate, 402
maxSDUSize, 402
maxUplinkBitrate, 402
qosDeliveryOrder, 402
resBerRatio, 402
sduErrorRatio, 402
trafficClass, 402
trafficPriority, 402
transferDelay, 402
LibPackUMTSReqQoSSigInd, 403
SigInd, 403
UMTSReqQoS, 403
LibPackprofile_3GPP, 386
pAPNClass, 390
pAPNDisabledFlag, 390
pAPNName, 390
pAPNnameSize, 391
pAddrAllocPref, 390
pAuthenticationPref, 391
pGPRSMinimumQoS, 391
pGPRSRequestedQos, 391
pIPv4AddrPref, 391
pIPv6AddPref, 391
pImCnFlag, 391
pPDNInactivTimeout, 391
pPDPtype, 391
pPassword, 391
pPasswordSize, 391
pPcscfAddrUsingDhcp, 391
pPcscfAddrUsingPCO, 391
pPdpAccessConFlag, 391
pPdpContext, 391
pPdpDataCompType, 391
pPdpHdrCompType, 391
pPriDNSIPv4AddPref, 391
pPriDNSIPv6addpref, 391
pPrimaryID, 391

pProfilename, 391
pProfilenameSize, 391
pQosClassID, 391
pSecDNSIPv4AddPref, 391
pSecDNSIPv6addpref, 391
pSecondaryFlag, 391
pSupportEmergencyCalls, 391
pTFTID1Params, 391
pTFTID2Params, 392
pUMTSMinQoS, 392
pUMTSMinQosSigInd, 392
pUMTSReqQoS, 392
pUMTSReqQoSSigInd, 392
pUsername, 392
pUsernameSize, 392
LibPackprofile_3GPP2, 392
pAPNClass3GPP2, 396
pAPNEnabled3GPP2, 396
pAllowLinger, 396
pApnString, 396
pApnStringSize, 396
pAppPriority, 396
pAppType, 396
pAuthPassword, 396
pAuthPassword_tSize, 396
pAuthProtocol, 396
pAuthRetryCount, 396
pAuthTimeout, 396
pDataMode, 396
pDataRate, 396
pIpcpAckTimeout, 396
pIpcpCreqRetryCount, 397
pIsPcscfAddressNedded, 397
pLcpAckTimeout, 397
pLcpCreqRetryCount, 397
pNegoDnsSrvrPref, 397
pPDNInactivTimeout3GPP2, 397
pPdnType, 397
pPppSessCloseTimer1x, 397
pPppSessCloseTimerDO, 397
pPriV6DnsAddress, 397
pPrimaryV4DnsAddress, 397
pRATType, 397
pSecV6DnsAddress, 397
pSecondaryV4DnsAddress, 397
pUserId, 397
pUserIdSize, 397
LibpackProfile3GPP, 373
pAPNClass, 379
pAPNDisabledFlag, 379
pAPNName, 379
pAPNnameSize, 379
pAddrAllocPref, 379
pAuthenticationPref, 379
pGPRSMinimumQoS, 379
pGPRSRequestedQos, 379
pIPv4AddrPref, 379
pIPv6AddPref, 379
pImCnFlag, 379
pPDNInactivTimeout, 379
pPDPtype, 379
pPassword, 379
pPasswordSize, 379
pPcscfAddrUsingDhcp, 379
pPcscfAddrUsingPCO, 379
pPdpAccessConFlag, 379
pPdpContext, 379
pPdpDataCompType, 379
pPdpHdrCompType, 379
pPriDNSIPv4AddPref, 379
pPriDNSIPv6addpref, 379
pPrimaryID, 379
pProfilename, 379
pProfilenameSize, 379
pQosClassID, 379
pSecDNSIPv4AddPref, 379
pSecDNSIPv6addpref, 380
pSecondaryFlag, 380
pSupportEmergencyCalls, 380
pTFTID1Params, 380
pTFTID2Params, 380
pUMTSMinQoS, 380
pUMTSMinQosSigInd, 380
pUMTSReqQoS, 380
pUMTSReqQoSSigInd, 380
pUsername, 380
pUsernameSize, 380
LibpackProfile3GPP2, 380
pAPNClass3GPP2, 385
pAPNEnabled3GPP2, 385
pAllowLinger, 385
pApnString, 385
pApnStringSize, 385
pAppPriority, 385
pAppType, 385
pAuthPassword, 385
pAuthPasswordSize, 385
pAuthProtocol, 385
pAuthRetryCount, 385
pAuthTimeout, 385
pDataMode, 385
pDataRate, 385
pIpcpAckTimeout, 385
pIpcpCreqRetryCount, 385
pIsPcscfAddressNedded, 385
pLcpAckTimeout, 385
pLcpCreqRetryCount, 385
pNegoDnsSrvrPref, 385
pPDNInactivTimeout3GPP2, 385
pPdnType, 385
pPppSessCloseTimer1x, 385
pPppSessCloseTimerDO, 386
pPriV6DnsAddress, 386
pPrimaryV4DnsAddress, 386
pRATType, 386
pSecV6DnsAddress, 386

pSecondaryV4DnsAddress, 386
pUserId, 386
pUserIdSize, 386
lineCtrlInfo, 403
polarityIncluded, 404
pwrDenialTime, 404
revPolarity, 404
toggleMode, 404
lineValue
pack_voice_SLQSVoiceALSSelectLine_t, 825
voiceALSSelectLineInfo, 1618
linkage
altitudeSrcInfo, 136
altSrcInfo_t, 137
list_type
custSettingList, 229
DMScustSettingList, 256
DMSgetCustomInput, 257
getCustomInput, 299
pack_dms_GetCustFeaturesV2_t, 707
listEntries
FMSPrefImageList, 285
PrefImageList, 891
listSize
FMSImageList, 285
FMSPrefImageList, 285
ImageList, 349
PrefImageList, 891
liteQmiDataBearerMasks
wds.h, 2478
liteServiceClassInformation
voice.h, 2443
liteqmi_GetVersion
common.h, 1725
liteqmi_helper_decode7bitAsciiEncString
common.h, 1725
liteqmi_log
common.h, 1725
loc.h
eQMI_LOC_SESS_STATUS_FAILURE, 1795
eQMI_LOC_SESS_STATUS_IN_PROGRESS, 1795
eQMI_LOC_SESS_STATUS_SUCCESS, 1795
eQMI_LOC_SESS_STATUS_TIMEOUT, 1795
loc.h, 1788
LOCEVENTMASKNMEA, 1793
LOCEVENTMASKWIFIREQ, 1794
MAX_TEMP_DATA_LEN, 1794
pack_loc_DeleteAssistData, 1795
pack_loc_EventRegister, 1795
pack_loc_SLQSLOCGetBestAvailPos, 1796
pack_loc_SLQSLOCGetOpMode, 1797
pack_loc_SLQSLOCGetServer, 1797
pack_loc_SLQSLOCInjectPosition, 1797
pack_loc_SLQSLOCInjectSensorData, 1798
pack_loc_SLQSLOCInjectUTCTime, 1798
pack_loc_SLQSLOCSetCradleMountConfig, 1799
pack_loc_SLQSLOCSetServer, 1799
pack_loc_SetExtPowerState, 1795
pack_loc_SetOperationMode, 1796
pack_loc_Start, 1799
pack_loc_Stop, 1800
unpack_loc_BestAvailPos_Ind, 1800
unpack_loc_CradleMountCallback_Ind, 1801
unpack_loc_DeleteAssistData, 1801
unpack_loc_DeleteAssistData_Ind, 1801
unpack_loc_DeleteAssistData_t, 1794
unpack_loc_EngineState_Ind, 1802
unpack_loc_EventNMEA_Ind, 1802
unpack_loc_EventRegister, 1802
unpack_loc_EventTimeSyncCallback_Ind, 1803
unpack_loc_GetOpMode_Ind, 1803
unpack_loc_GetServer_Ind, 1803
unpack_loc_GnssSvInfo_Ind, 1804
unpack_loc_InjectPositionCallback_Ind, 1804
unpack_loc_InjectSensorDataCallback_Ind, 1804
unpack_loc_InjectTimeSyncDataCallback_Ind, 1805
unpack_loc_InjectUTCTimeCallback_Ind, 1805
unpack_loc_PositionRpt_Ind, 1805
unpack_loc_SLQSLOCGetBestAvailPos, 1808
unpack_loc_SLQSLOCGetOpMode, 1808
unpack_loc_SLQSLOCGetServer, 1808
unpack_loc_SLQSLOCGetServer_t, 1794
unpack_loc_SLQSLOCInjectPosition, 1809
unpack_loc_SLQSLOCInjectPosition_t, 1794
unpack_loc_SLQSLOCInjectSensorData, 1809
unpack_loc_SLQSLOCInjectSensorData_t, 1794
unpack_loc_SLQSLOCInjectUTCTime, 1809
unpack_loc_SLQSLOCInjectUTCTime_t, 1794
unpack_loc_SLQSLOCSetCradleMountConfig, 1810
unpack_loc_SLQSLOCSetCradleMountConfig_t, 1794
unpack_loc_SLQSLOCSetServer, 1810
unpack_loc_SensorStreamingCallback_Ind, 1806
unpack_loc_SetExtPowerConfig_Ind, 1806
unpack_loc_SetExtPowerState, 1806
unpack_loc_SetOperationMode, 1807
unpack_loc_SetOperationMode_Ind, 1807
unpack_loc_SetServer_Ind, 1807
unpack_loc_Start, 1810
unpack_loc_Stop, 1811
loc_BdsSV, 405
id, 406
mask, 406
loc_BdsSVInfo, 406
len, 406
pSV, 406
loc_CellDb, 406
mask, 407
loc_ClkInfo, 407
mask, 408
loc_GnssData, 408
mask, 409
loc_IPv4Config, 412

IPv4Addr, 412
IPv4Port, 412
loc_IPv4Info, 412
address, 413
port, 413
TlvPresent, 413
loc_IPv6Config, 413
IPv6Addr, 413
IPv6Port, 413
loc_IPv6Info, 413
address, 414
port, 414
TlvPresent, 414
loc_LocApplicationInfo, 414
appNameLength, 415
appProviderLength, 415
appVersionLength, 415
appVersionValid, 415
pAppName, 415
pAppProvider, 415
pAppVersion, 415
loc_SV, 419
id, 420
mask, 420
system, 420
loc_SVInfo, 420
len, 420
pSV, 420
loc_URLAddrInfo, 421
urlAddr, 422
loc_accelAcceptReady, 404
batchPerSec, 404
injectEnable, 404
samplesPerBatch, 405
loc_accelTempAcceptReady, 405
batchPerSec, 405
injectEnable, 405
samplesPerBatch, 405
loc_gpsTime, 410
gpsTimeOfWeekMs, 410
gpsWeek, 410
loc_gyroAcceptReady, 410
batchPerSec, 411
injectEnable, 411
samplesPerBatch, 411
loc_gyroTempAcceptReady, 411
batchPerSec, 412
injectEnable, 412
samplesPerBatch, 412
loc_precisionDilution, 415
HDOP, 416
PDOP, 416
VDOP, 416
loc_satelliteInfo, 416
azimuth, 418
elevation, 418
gnssSvId, 418
healthStatus, 418
snr, 418
svInfoMask, 418
svListLen, 418
svStatus, 418
system, 418
validMask, 418
loc_sensorDataUsage, 418
aidingIndicatorMask, 419
usageMask, 419
loc_svUsedforFix, 420
gnssSvUsedList, 421
gnssSvUsedList_len, 421
loc_urlAddr, 421
address, 421
TlvPresent, 421
LocApplicationInfo, 422
appNameLength, 423
appProviderLength, 423
appVersionLength, 423
appVersionValid, 423
pAppName, 423
pAppProvider, 423
pAppVersion, 423
LocDelAssDataReq, 423
pBdsSVInfo, 424
pCellDb, 424
pClkInfo, 424
pGnssData, 424
pSVInfo, 424
LocGetServerReq, 426
pServerAddrTypeMask, 427
serverType, 427
LocInjectPositionReq, 427
pAltitudeSrcInfo, 430
pAltitudeWrtEllipsoid, 430
pAltitudeWrtMeanSeaLevel, 430
pHorConfidence, 430
pHorReliability, 431
pHorUncCircular, 431
pLatitude, 431
pLongitude, 431
pPositionSrc, 431
pRawHorConfidence, 431
pRawHorUncCircular, 431
pTimestampAge, 431
pTimestampUtc, 431
pVertConfidence, 431
pVertReliability, 431
pVertUnc, 431
LocInjectSensorDataReq, 431
pAcceleroData, 432
pAcceleroTempData, 432
pAcceleroTimeSrc, 432
pGyroData, 432
pGyroTempData, 432
pGyroTimeSrc, 432
pOpaqueIdentifier, 432
LocSetCradleMountReq, 432

pConfidence, 433
state, 433
LocSetServerReq, 433
pIPv4Config, 434
pIPv6Config, 434
pURLAddr, 434
serverType, 434
localTimeOffset
nas_qaQmi3Gpp2TimeZone, 577
qaQmi3Gpp2TimeZone, 911
Location Service(LOC), 63
logString
unpack_dms_SLQSSwiGetFwUpdateStatus_t, 1259
logger
common.h, 1722
longName
nas_PLMNNetworkNameData, 574
nasPLMNNameResp, 664
PLMNNetworkNameData, 887
unpack_nas_SLQSGetPLMNName_t, 1331
longNameCI
nasPLMNNameResp, 664
unpack_nas_SLQSGetPLMNName_t, 1331
longNameEn
nasPLMNNameResp, 664
unpack_nas_SLQSGetPLMNName_t, 1331
longNameLen
nas_PLMNNetworkNameData, 574
nasPLMNNameResp, 664
PLMNNetworkNameData, 887
unpack_nas_SLQSGetPLMNName_t, 1331
longNameSB
nasPLMNNameResp, 664
unpack_nas_SLQSGetPLMNName_t, 1331
longNameSpareBits
nas_PLMNNetworkNameData, 574
PLMNNetworkNameData, 887
Longitude
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
longitude
pack_loc_SLQSLOCInjectPosition_t, 736
loopbackMode
pack_wds_SLQSSSetLoopback_t, 863
loopbackMultiplier
pack_wds_SLQSSSetLoopback_t, 863
LpmFlag
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1243
LteBandCapability
unpack_dms_SLQSGetBandCapability_t, 1251
lteBandPrefExt, 436
bits_129_192, 437
bits_193_256, 437
bits_1_64, 437
bits_65_128, 437
LteCQIParm, 437
CQIValueCW0, 438
CQIValueCW1, 438
ValidityCW0, 438
ValidityCW1, 438
LteCiotOpModeTlv, 437
campedCiotLteOpMode, 437
TlvPresent, 437
lteEARFCN, 438
earfcn0, 439
earfcn1, 439
status, 439
lteEmmDl
NasSwiIndReg, 675
pack_nas_SLQSNasSwiIndicationRegister_t, 761
lteEmmUl
NasSwiIndReg, 675
pack_nas_SLQSNasSwiIndicationRegister_t, 761
lteEsmDl
NasSwiIndReg, 675
pack_nas_SLQSNasSwiIndicationRegister_t, 761
lteEsmUl
NasSwiIndReg, 675
pack_nas_SLQSNasSwiIndicationRegister_t, 761
LteGsmCellInfo
LTEInfoNeighboringGSM, 446
nas_LTEInfoNeighboringGSM, 532
lteGsmCellInfo, 439
cellReselPriority, 440
cells_len, 440
GsmCellInfo, 440
nccPermitted, 440
threshGsmHigh, 440
threshGsmLow, 440
LteM1BandPref
NASLteM1BandPrefTlv, 648
lteM1BandPref
LteM1BandPrefTlv, 448
nas_LteM1BandPrefTlv, 534
LteM1BandPrefTlv, 447
lteM1BandPref, 448
TlvPresent, 449
LteNB1BandPref
NASLteNB1BandPrefTlv, 649
LteNasReleaseInfo
qaGobiApiCbk.h, 1916
LteNasReleaseInfo_s, 449
nas_major, 449
nas_minor, 449
nas_release, 449
lteNb1BandPref
LteNb1BandPrefTlv, 451
nas_LteNb1BandPrefTlv, 536
LteNb1BandPrefTlv, 449
lteNb1BandPref, 451
TlvPresent, 451
LteOpMode, 451
lteOpMode, 452
TlvPresent, 452
lteOpMode

EdrxCiotLteMode, 269
LteOpMode, 452
lteOpModeTlv, 453
nas_EdrxCiotLteMode, 500
nas_LteOpMode, 538
nas_lteOpModeTlv, 539
lteOpModeLen
lteOpModeTlv, 453
nas_lteOpModeTlv, 539
lteOpModeTlv, 452
lteOpMode, 453
lteOpModeLen, 453
MCC, 453
MNC, 453
TlvPresent, 453
ltePCI, 453
earfcn, 453
pci, 454
status, 454
LteQci
unpack_qos_swiQosFlow_t, 1417
lteRsrpDelta
nas_SLQSSignalStrengthsIndReq, 603
SLQSSignalStrengthsIndReq, 1047
lteRsrpinfo
nas_SLQSSignalStrengthsInformation, 604
SLQSSignalStrengthsInformation, 1049
lteRsrpinformation, 454
rsrplevel, 454
lteSSInfo, 460
rsrp, 460
rsrq, 460
rssi, 460
snr, 460
LteSccRxInfoResp, 456
pSccRxInfo, 456
lteSnrDelta
nas_SLQSSignalStrengthsIndReq, 603
SLQSSignalStrengthsIndReq, 1047
lteSnrinfo
nas_SLQSSignalStrengthsInformation, 604
SLQSSignalStrengthsInformation, 1049
lteSnrinformation, 458
snrlevel, 458
lteWcdmaCellInfo, 464
cellReselPriority, 464
cellsLen, 464
threshXhigh, 464
threshXlow, 465
uarfcn, 465
WCDMACellInfo, 465
ltersrp
slqsSignalStrengthInfo, 1045
unpack_nas_SLQSGetSignalStrength_t, 1339
ltesnr
slqsSignalStrengthInfo, 1045
unpack_nas_SLQSGetSignalStrength_t, 1339

M1BandPTlv
NASQmiCbkNasSystemSelPrefInd, 668
m_FwBuildId
CarrierImage_t, 173
SWI_STRUCT_CarrierImage, 1091
m_FwImageId
CarrierImage_t, 173
SWI_STRUCT_CarrierImage, 1091
m_PriBuildId
CarrierImage_t, 174
SWI_STRUCT_CarrierImage, 1091
m_PriImageId
CarrierImage_t, 174
SWI_STRUCT_CarrierImage, 1091
m_nCarrierId
CarrierImage_t, 173
SWI_STRUCT_CarrierImage, 1091
m_nFolderId
CarrierImage_t, 174
SWI_STRUCT_CarrierImage, 1091
m_nStorage
CarrierImage_t, 174
SWI_STRUCT_CarrierImage, 1091
MACIndex
nas_NetworkStatEVDO, 556
NetworkStatEVDO, 687
MAX_BUILD_ID_LEN
dms.h, 1734
MAX_CALL_NO_LEN
qaGobiApiVoice.h, 2287
MAX_CONTENT_LENGTH
qaGobiApiUim.h, 2272
MAX_CUST_ID_LEN
qaGobiApiDms.h, 2005
MAX_FSN_LENGTH
qaGobiApiDms.h, 2005
MAX_ICCID_LENGTH
qaGobiApiUim.h, 2272
uim.h, 2420
MAX_MSE_TWS_MSG
sms.h, 2375
MAX_NMEA_STR_LEN
qaGobiApiCbk.h, 1913
MAX_NO_OF_CALLS
qaGobiApiCbk.h, 1913
qaGobiApiVoice.h, 2287
MAX_NO_OF_FILES
qaGobiApiCbk.h, 1913
MAX_NO_OF_SLOTS
qaGobiApiCbk.h, 1913
qaGobiApiUim.h, 2272
uim.h, 2420
MAX_NO_OF_UUSINFO
qaGobiApiCbk.h, 1913
MAX_PATH_LENGTH
qaGobiApiCbk.h, 1913
qaGobiApiUim.h, 2272
MAX_PILOT_SETS
qaGobiApiNas.h, 2089

MAX_PUK_LENGTH
qaGobiApiUim.h, 2272
MAX_SENSOR_DATA_LEN
loc.h, 1794
MAX_SLOTS_STATUS
qaGobiApiUim.h, 2272
uim.h, 2420
MAX_SMS_LIST_SIZE
sms.h, 2375
MAX_SMS_ROUTES
qaGobiApiSms.h, 2171
MAX_SMSC_LENGTH
qaGobiApiSms.h, 2171
MAX_TEMP_DATA_LEN
loc.h, 1794
qaGobiApiLoc.h, 2075
MAXUSSDLENGTH
qaGobiApiCbk.h, 1913
qaGobiApiVoice.h, 2287
MAXVOICEUSSDLENGTH
voice.h, 2442
MCC
SlqsNas3GppNetworkRAT, 97
CDMASysInfo, 193
CDMASysInfoExt, 194
currentPLMN, 221
ForbiddenNetworks3GPP, 286
GSMSysInfo, 333
lteOpModeTlv, 453
LTESysInfo, 463
nas_CDMASysInfo, 484
nas_CDMASysInfoExt, 485
nas_currentPLMN, 492
nas_ForbiddenNetworks3GPP, 505
nas_GSMSysInfo, 512
nas_lteOpModeTlv, 539
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 562
nas_QmiNas3GppNetworkInfo, 578
nas_QmiNas3GppNetworkRAT, 579
nas_QmisNasPcsDigit, 580
nas_WCDMASysInfo, 625
NR5GSystemInfoTlv, 694
SlqsNas3GppNetworkInfo, 1036
SlqsNasPcsDigit, 1039
unpack_nas_GetServingNetwork_t, 1316
WCDMASysInfo, 1678
MDMCallDuration
ConnectionStatus, 208
connectionStatus, 208
MDMConnStatus
ConnectionStatus, 208
connectionStatus, 208
wds_ConnStatusTlv, 1681
MEID_MAX_SIZE
dms.h, 1734
MEIDString
unpack_dms_GetDeviceSerialNumbers_t, 1218
MIN
unpack_dms_GetVoiceNumber_t, 1233
MINREQBKLEN
common.h, 1721
MMTlv
unpack_sms_SetNewSMSCallback_ind_t, 1426
MNC
SlqsNas3GppNetworkRAT, 97
CDMASysInfo, 193
currentPLMN, 221
ForbiddenNetworks3GPP, 286
GSMSysInfo, 333
lteOpModeTlv, 453
LTESysInfo, 463
nas_CDMASysInfo, 484
nas_currentPLMN, 492
nas_ForbiddenNetworks3GPP, 505
nas_GSMSysInfo, 512
nas_lteOpModeTlv, 539
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 562
nas_QmiNas3GppNetworkInfo, 578
nas_QmiNas3GppNetworkRAT, 579
nas_QmisNasPcsDigit, 580
nas_WCDMASysInfo, 625
NR5GSystemInfoTlv, 694
SlqsNas3GppNetworkInfo, 1036
SlqsNasPcsDigit, 1039
unpack_nas_GetServingNetwork_t, 1316
WCDMASysInfo, 1678
MNRInfo, 467
mcc, 468
mnc, 468
rat, 468
MPTlv
NASQmiCbkNasSystemSelPrefInd, 668
MSGID_AND_LEN
common.h, 1721
MSGID_DONT_CARE
common.h, 1721
MTMessageInfo
newMTMessageTlv, 687
MTUSize
MTUSizeReq, 471
pack_swidms_SLQSSwiDmsSetMTU_t, 805
MTUSize3gpp
mtuSize3gppTlv, 470
swidms_mtuSize3gppTlv, 1095
MTUSizeReq, 470
MTUSize, 471
manString
pack_dms_SLQSSwiSetHostDevInfo_t, 717
unpack_dms_SLQSSwiGetHostDevInfo_t, 1260
manufacturer
unpack_dms_GetManufacturer_t, 1224
Mask
getDUNCallInfoReq, 300
pack_wds_SLQSGetDUNCallInfo_t, 856

mask
BdsSV, 157
CellDb, 195
ClkInfo, 203
GnssData, 320
IPv6TrafCls, 372
loc_BdsSV, 406
loc_CellDb, 407
loc_ClkInfo, 408
loc_GnssData, 409
loc_SV, 420
SV, 1089
Tos, 1138
unpack_qos_IPv6TrafCls_t, 1399
unpack_qos_Tos_t, 1418
max
_SLQSAVMSSettingsPeriodsInfo, 96
max_channel_rx_rate
unpack_wds_SLQSGetCurrentChannelRate_t, 1538
WDSSWICurrentChannelRates, 1718
max_channel_tx_rate
unpack_wds_SLQSGetCurrentChannelRate_t, 1538
WDSSWICurrentChannelRates, 1718
max_dist
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocGetAutoStartResp, 1102
SwiLocSetAutoStartReq, 1104
unpack_swiloc_SwiLocGetAutoStart_t, 1448
max_dist_reported
SwiLocGetAutoStartResp, 1102
unpack_swiloc_SwiLocGetAutoStart_t, 1448
max_time
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocGetAutoStartResp, 1102
SwiLocSetAutoStartReq, 1104
unpack_swiloc_SwiLocGetAutoStart_t, 1448
max_time_reported
SwiLocGetAutoStartResp, 1102
unpack_swiloc_SwiLocGetAutoStart_t, 1448
MaxAllowedPktSz
unpack_qos_swiQosFlow_t, 1417
MaxChanRxRate
ChannelRate, 197
dunchannelRate, 266
MaxChanTxRate
ChannelRate, 197
dunchannelRate, 266
maxChannelRXRate
unpack_wds_GetConnectionRate_t, 1517
maxChannelTXRate
unpack_wds_GetConnectionRate_t, 1517
maxDlBitRate
LibPackQosClassID, 398
QosClassID, 954
maxDownlinkBitrate
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
maxImages
FMSImageIDEntries, 284
ImageIDEntries, 348
maxMitigationLevel
mitigationDevList, 467
MaxRXChannelRate
unpack_dms_GetDeviceCap_t, 1213
maxRxChannelRate
unpack_dms_GetDeviceCapabilities_t, 1215
maxSDUSize
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
maxStorageSize
sms_maxStorageSizeResp, 1056
smsMaxStorageSizeResp, 1073
MaxTXChannelRate
unpack_dms_GetDeviceCap_t, 1213
maxTxChannelRate
unpack_dms_GetDeviceCapabilities_t, 1215
maxUlBitRate
LibPackQosClassID, 398
QosClassID, 954
maxUplinkBitrate
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
mcTimeStamp
cdmaMsgDecodingParams, 182
cdmaMsgDecodingParamsExt, 186
mcc
CSGID, 216
MNRInfo, 468
nas_CSGID, 491
nas_MNRInfo, 550
nas_netSelectionPref, 552
nas_OperatorPLMNData, 564
nas_PlmnID, 572
nasPLMNNameReq, 662
netSelectionPref, 681
OperatorPLMNData, 705
pack_nas_SLQSGetPLMNName_t, 748
PlmnID, 885
unpack_nas_GetHomeNetwork_t, 1312
mccM
minBasedIMSI, 467
nas_minBasedIMSI, 549
mccT
nas_trueIMSI, 614
trueIMSI, 1141
mdmCallDurationActive
unpack_wds_SLQSGetDUNCallInfo_t, 1542
MdmConnStatus

DUNCallInfoInd, 265
meanThroughputClass
GPRSQoS, 322
GPRSRequestedQoS, 323
LibPackGPRSRequestedQoS, 373
wds_GPRSQoS, 1690
meid
unpack_dms_GetSerialNumbers_t, 1230
meidLength
_SLQSSwiGetSerialNoExtParams, 110
meidSize
serialNumbersInfo, 992
unpack_dms_GetDeviceSerialNumbers_t, 1218
meidString
unpack_dms_SLQSSwiGetSerialNoExt_t, 1262
memoryDumpAllowed
SwiDmsGetSecureInfoResp, 1098
unpack_swidms_SLQSSwiDmsGetSecureInfo_t, 1443
message
unpack_sms_SLQSGetSMS_t, 1429
message_type
NASOTAMessageTlv, 656
messageClass
sms_routeEntry, 1060
smsRouteEntry, 1078
messageFailureCode
slqssendsmsparams_s, 1042
unpack_sms_SendSMS_t, 1424
messageFormat
pack_sms_SaveSMS_t, 796
pack_sms_SendSMS_t, 796
slqssendasyncsmsparams_s, 1040
slqssendsmsparams_s, 1042
sms_sendAsyncsmsParams, 1062
unpack_sms_SLQSGetSMS_t, 1429
messageID
slqssendsmsparams_s, 1042
SMSAsyncRawSend_s, 1066
unpack_sms_SendSMS_t, 1424
unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t, 1440
messageId
cdmaMsgEncodingParams, 188
messageIndex
pack_sms_SLQSGetSMS_t, 799
pack_sms_SLQSModifySMSStatus_t, 801
qmiSmsMessageList, 946
SMSMTMessage, 1075
sMSMTMessageInfo, 1076
MessageLen
wcdmaLongMsgDecodingParams, 1672
wcdmaMsgDecodingParams, 1673
messageLength
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
messageList
unpack_sms_SLQSGetSMSList_t, 1431
messageListSize
unpack_sms_SLQSGetSMSList_t, 1431
messageMode
SMSMemoryInfo, 1073
SMSMessageMode, 1074
sMSMessageModeInfo, 1074
unpack_sms_SLQSWmsMemoryFullCallBack_ind_t, 1441
MessageModeInfo
messageModeTlv, 465
messageModeTlv, 465
MessageModeInfo, 465
TlvPresent, 465
messageSize
pack_sms_SaveSMS_t, 796
pack_sms_SendSMS_t, 796
slqssendasyncsmsparams_s, 1041
slqssendsmsparams_s, 1042
sms_sendAsyncsmsParams, 1062
unpack_sms_SLQSGetSMS_t, 1429
wcdmaMsgEncodingParams, 1674
messageTag
pack_sms_SLQSModifySMSStatus_t, 801
qmiSmsMessageList, 947
unpack_sms_SLQSGetSMS_t, 1429
messageType
sms_routeEntry, 1060
smsRouteEntry, 1078
messageWaitingInfoContent, 465
activeInd, 466
msgCount, 466
msgType, 466
MicMute
GetAudioProfileResp, 295
GetM2MAudioProfileResp, 312
GetM2MAVMuteResp, 314
SetAudioProfileReq, 1001
SetM2MAVMuteReq, 1014
min
_SLQSAVMSSettingsPeriodsInfo, 96
minBasedIMSI, 466
imsiM1112, 467
imsiMS1, 467
imsiMS2, 467
mccM, 467
MinPolicedPktSz
unpack_qos_swiQosFlow_t, 1417
minSize
unpack_dms_GetVoiceNumber_t, 1233
minute
nas_timeInfo, 613
nas_UniversalTime, 619
timeInfo, 1134
UniversalTime, 1205
mipMode
unpack_wds_GetMobileIP_t, 1523
mipStatus

unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
mipstatAvail
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
mitigationDevID
TmdDeRegNotMitigationLvlReq, 1134
TmdGetMitigationLvlReq, 1135
TmdMitigationLvlIndReq, 1137
TmdRegNotMitigationLvlReq, 1137
mitigationDevIDLen
TmdDeRegNotMitigationLvlReq, 1134
TmdGetMitigationLvlReq, 1135
TmdMitigationLvlIndReq, 1137
TmdRegNotMitigationLvlReq, 1137
mitigationDevId
mitigationDevList, 467
mitigationDevIdLen
mitigationDevList, 467
MitigationDevInfo
QmiCbkTmdMitiLvlRptInd, 942
mitigationDevList, 467
maxMitigationLevel, 467
mitigationDevId, 467
mitigationDevIdLen, 467
mnc
CSGID, 216
MNRInfo, 468
nas_CSGID, 491
nas_MNRInfo, 550
nas_netSelectionPref, 552
nas_OperatorPLMNData, 564
nas_PlmnID, 572
nasPLMNNameReq, 662
netSelectionPref, 681
OperatorPLMNData, 705
pack_nas_SLQSGetPLMNName_t, 748
PlmnID, 885
unpack_nas_GetHomeNetwork_t, 1312
mncPcsDigits
CSGID, 216
nas_CSGID, 491
mobileCountryCode
SMSEtwsPlmn, 1070
sMSEtwsPlmnInfo, 1070
mobileIP
pack_wds_SLQSSetWdsEventCallback_t, 862
mobileNetworkCode
SMSEtwsPlmn, 1070
sMSEtwsPlmnInfo, 1070
mode
callInfo, 169
pack_dms_SetEventReport_t, 711
pack_dms_SetPower_t, 713
pack_loc_SetOperationMode_t, 730
pack_sms_SLQSGetSmsBroadcastConfig_t, 799
pack_sms_SLQSSetSmsBroadcastActivation_t, 802
pack_sms_SLQSSetSmsBroadcastConfig_t, 803
pack_wds_SetMobileIP_t, 850
QmiCbkLocOpModeInd, 931
uim_refreshevent, 1162
UIMRefreshEvent, 1185
voice_callInfo, 1589
ModePref
nas_ModePrefTlv, 550
NASModePreferenceTlv, 650
modelString
pack_dms_SLQSSwiSetHostDevInfo_t, 717
unpack_dms_SLQSSwiGetHostDevInfo_t, 1260
modelid
unpack_dms_GetModelID_t, 1225
modelid_str
slqsfwinfo_s, 1034
unpack_dms_GetFirmwareInfo_t, 1220
modemMode
CommInfo, 207
nas_CommInfo, 490
modemTempNotification
qaGobiApiCbk.h, 1917
ModemTempState
_modemTempNotification, 74
ModemTemperature
_modemTempNotification, 74
ModemUIMStatusEvent
_modemUIMStatusNotification, 75
ModemUIMStatusInterface
_modemUIMStatusNotification, 75
modemUIMStatusNotification
qaGobiApiCbk.h, 1917
modemindex
pack_fms_SetImagesPreference_t, 725
ModifyProfileIn, 468
curProfile, 469
pProfileID, 469
pProfileType, 469
ModifyProfileOut, 469
pExtErrorCode, 469
month
nas_timeInfo, 613
nas_UniversalTime, 619
timeInfo, 1134
UniversalTime, 1205
msgCount
messageWaitingInfoContent, 466
sms_messageWaitingInfoContent, 1057
msgDelFailureCause
SMSAsyncRawSend_s, 1066
unpack_sms_SLQSWmsAsyncRawSendCallBack-_ind_t, 1440
msgDelFailureType
SMSAsyncRawSend_s, 1066
unpack_sms_SLQSWmsAsyncRawSendCallBack-_ind_t, 1440
msgProtocol
sms_msgProtocolResp, 1057

smsMsgprotocolResp, 1075
msgType
messageWaitingInfoContent, 466
sms_messageWaitingInfoContent, 1057
msgWaitInfo
getMsgWaitingInfo, 316
msgWaitingInfo, 470
sms_getMsgWaitingInfo, 1053
unpack_sms_SLQSWmsMessageWaitingCall-Back_ind_t, 1441
msgWaitingInfo, 469
msgWaitInfo, 470
numInstances, 470
results, 470
msgid
pack_qmi_t, 792
unpack_qmi_t, 1397
msgtype
common.h, 1723
Mtu
unpack_wds_SLQSGetRuntimeSettings_t, 1545
mtuSize3gppTlv, 470
MTUSize3gpp, 470
TlvPresent, 470
MultDisc
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
multiplier
pktErrRate, 884
unpack_qos_pktErrRate_t, 1400
MuxID
qos_BindDataPortMuxID_t, 952

NAI
unpack_wds_GetMobileIPProfile_t, 1525
NAM_NAME_LENGTH
qaGobiApiNas.h, 2089
NAS_NAM_NAME_LENGTH
nas.h, 1823
NAS_PLMN_LENGTH
nas.h, 1823
NAS_SRV
qaGobiApiCbk.h, 1913
NASAcqOrderPrefTlv, 626
AcqOrderLen, 626
AcqOrderPref, 626
TlvPresent, 626
NASBandPreferenceTlv, 626
band_pref, 626
TlvPresent, 626
NASCiotAcqOrderPrefTlv, 628
CiotAcqOrderLen, 628
CiotAcqOrderPref, 628
TlvPresent, 628
NASCiotLteOpModePrefTlv, 628
CiotLteOpModePref, 629
TlvPresent, 629
NASEmergencyModeTlv, 629
EmerMode, 629
TlvPresent, 629
NASGWAcqOrderPrefTlv, 643
GWAcqOrderPref, 643
TlvPresent, 643
NASLTEBandPreferenceTlv, 647
LTEBandPref, 648
TlvPresent, 648
NASLteM1BandPrefTlv, 648
LteM1BandPref, 648
TlvPresent, 648
NASLteNB1BandPrefTlv, 649
LteNB1BandPref, 649
TlvPresent, 649
NASLteNasReleaseInfoTlv, 648
nas_major, 649
nas_minor, 649
nas_release, 649
TlvPresent, 649
NASModePreferenceTlv, 649
ModePref, 650
TlvPresent, 650
NASNetSelPreferenceTlv, 650
NetSelPref, 650
TlvPresent, 650
NASNr5gBandPrefTlv, 654
Nr5gBandPrefbits1_64, 654
Nr5gBandPrefbits_129_192, 654
Nr5gBandPrefbits_193_256, 654
Nr5gBandPrefbits_65_128, 654
TlvPresent, 654
NASOTAMessageTlv, 655
data_buf, 656
data_len, 656
message_type, 656
TlvPresent, 656
NASPRLPreferenceTlv, 665
PRLPref, 665
TlvPresent, 665
NASPhyCaAggPcellInfo, 656
dl_bw_value, 657
freq, 657
iLTEbandValue, 657
pci, 657
TlvPresent, 657
NASPhyCaAggScellArray, 657
band, 658
cphy_ca_dl_bandwidth, 658
cphy_scell_info_list_len, 658
freq, 658
pci, 658
scell_idx, 658
scell_state, 658
TlvPresent, 659
NASPhyCaAggScellDlBw, 659
dl_bw_value, 659
TlvPresent, 659
NASPhyCaAggScellIndType, 660
freq, 660

pci, 660
scell_state, 660
TlvPresent, 660
NASPhyCaAggScellIndex, 659
scell_idx, 659
TlvPresent, 660
NASPhyCaAggScellInfo, 660
dl_bw_value, 661
freq, 661
iLTEbandValue, 661
pci, 661
scell_state, 661
TlvPresent, 661
NASQmiCbkNasSwiOTAMessageInd, 665
nasRelInfoTlv, 666
otaMsgTlv, 666
timeTlv, 666
NASQmiCbkNasSystemSelPrefInd, 666
AOPTlv, 667
BPTlv, 667
CiotAOPTlv, 667
CiotOpMPTlv, 668
EMTlv, 668
GWAOPTlv, 668
LBPTlv, 668
M1BandPTlv, 668
MPTlv, 668
NB1BandPTlv, 668
NR5gBandPTlv, 668
NSPTlv, 668
PRLPTlv, 668
RPTlv, 668
RatDMTlv, 668
SDPTlv, 668
NASRatDisabledMaskTlv, 668
RatDisabledMask, 668
TlvPresent, 668
NASRoamPreferenceTlv, 668
RoamPref, 669
TlvPresent, 669
NASServDomainPrefTlv, 669
SrvDomainPref, 669
TlvPresent, 669
NASServingSystemInfo, 669
csAttachState, 670
hdrPersonality, 670
psAttachState, 671
radioInterfaceList, 671
radioInterfaceNo, 671
registrationState, 671
selectedNetwork, 671
NASTimeInfoTlv, 679
time, 680
TlvPresent, 680
NB1BandPTlv
NASQmiCbkNasSystemSelPrefInd, 668
NMEAData
unpack_loc_EventNMEA_Ind_t, 1284
NR5GCellStatusTlv, 690
nr5gCellStatus, 691
TlvPresent, 691
NR5GSerStatTlv, 691
isPrefDataPath, 691
srvStatus, 691
TlvPresent, 692
trueSrvStatus, 692
NR5GSystemInfoTlv, 692
cellId, 694
cellIdValid, 694
lac, 694
lacValid, 694
MCC, 694
MNC, 694
nwIdValid, 694
regRejectInfoValid, 695
rejCause, 695
rejectSrvDomain, 695
roamStatus, 695
roamStatusValid, 695
srvCapValid, 695
srvDomain, 695
srvDomainValid, 695
srvcapability, 695
sysForbidden, 695
sysForbiddenValid, 695
tac, 695
tacValid, 695
TlvPresent, 695
NR5gBandPTlv
NASQmiCbkNasSystemSelPrefInd, 668
NR5gBandPrefTlv
qaGobiApiNas.h, 2090
NSPTlv
NASQmiCbkNasSystemSelPrefInd, 668
NSSAudioCtrl, 695
downLink, 695
upLink, 695
NUM_OF_SET
qaGobiApiCbk.h, 1913
qaGobiApiSms.h, 2171
nUsbNetNum
pack_swidms_SLQSSwiDmsSetUsbNetNum_t, 807
NWProfile, 696
pProfSz, 696
pProfValues, 696
tech, 696
NWQoSStatus
unpack_qos_SLQSQosGetNetworkStatus_t, 1403
NWRegStat
_transNWRegInfoNotification, 128
unpack_sms_SLQSNWRegInfoCallback_ind_t, 1433
naiSize
unpack_wds_GetMobileIPProfile_t, 1525
namID

airTimer, 133
nasGet3GPP2SubscriptionInfoReq, 629
pack_nas_SLQSNasGet3GPP2Subscription_t, 754
prefVoiceSO, 893
roamTimer, 974
voice_airTimer, 1570
voice_prefVoiceSO, 1610
voice_roamTimer, 1614
namName, 471
namName, 471
namNameLen, 471
namName, 471
nas_namName, 551
namNameLen
namName, 471
nas_namName, 551
Name
unpack_nas_GetServingNetwork_t, 1316
name
unpack_nas_GetHomeNetwork_t, 1312
unpack_wds_GetDefaultProfile_t, 1521
nameLen
remotePartyName, 964
voice_remotePartyName, 1612
namePI
remotePartyName, 964
voice_remotePartyName, 1612
nameSize
unpack_nas_GetHomeNetwork3GPP2_t, 1311
unpack_nas_GetServingNetwork_t, 1317
nameString
pack_dms_SLQSSwiSetOSInfo_t, 718
unpack_dms_SLQSSwiGetOSInfo_t, 1261
namelength
omaDmFotaTlv, 701
omaDmFotaTlvExt, 703
unpack_omaDmFotaTlv_t, 1382
namesize
unpack_wds_GetDefaultProfile_t, 1521
nas.h
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_1, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_10, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_11, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_12, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_125, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_126, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_127, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_13, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_14, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_17, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_18, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_19, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_2, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_20, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_21, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_23, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_24, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_25, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_250, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_26, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_27, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_28, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_29, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_3, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_30, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_31, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_32, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_33, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_34, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_35, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_36, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_37, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_38, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_39, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_4, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_40, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_41, 1825

eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_42, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_43, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_46, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_47, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_48, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_5, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_6, 1824
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_66, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_7, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_71, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_8, 1825
eLITEQMI_LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_9, 1825
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_100, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_15, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_25, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_50, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_6, 1826
eLITEQMI_NAS_LTE_CPHY_CA_BW_NRB_75, 1826
eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED, 1826
eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED, 1826
eLITEQMI_NAS_LTE_CPHY_SCELL_STATE_DECONFIGURED, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_100, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_15, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_25, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_50, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_6, 1826
eNAS_LTE_CPHY_CA_BW_NRB_LITE_75, 1826
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED_LITE, 1826
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED_LITE, 1826
eNAS_LTE_CPHY_SCELL_STATE_DECONFIGURED_LITE, 1826
LITE_SYS_SRV_DOMAIN_CAMPED, 1824
LITE_SYS_SRV_DOMAIN_CS_ONLY, 1824
LITE_SYS_SRV_DOMAIN_CS_PS, 1824
LITE_SYS_SRV_DOMAIN_NO_SRV, 1824
LITE_SYS_SRV_DOMAIN_PS_ONLY, 1824
nas.h, 1811
NAS_PLMN_LENGTH, 1823
nas_LTEBandPrefExtTlv, 1823
nas_NR5gBandPrefTlv, 1823
pack_nas_GetACCOLC, 1826
pack_nas_GetANAAAAuthenticationStatus, 1827
pack_nas_GetCDMANetworkParameters, 1827
pack_nas_GetHomeNetwork, 1827
pack_nas_GetHomeNetwork3GPP2, 1828
pack_nas_GetNetworkPreference, 1828
pack_nas_GetRFInfo, 1828
pack_nas_GetServingNetwork, 1828
pack_nas_GetServingNetworkCapabilities, 1829
pack_nas_GetSignalStrengths, 1829
pack_nas_InitiateDomainAttach, 1829
pack_nas_PerformNetworkScan, 1830
pack_nas_PerformNetworkScanPCI, 1830
pack_nas_SLQSConfigSigInfo, 1832
pack_nas_SLQSGetErrorRate, 1833
pack_nas_SLQSGetNetworkTime, 1833
pack_nas_SLQSGetOperatorNameData, 1834
pack_nas_SLQSGetPLMNName, 1834
pack_nas_SLQSGetServingSystem, 1834
pack_nas_SLQSGetSignalStrength, 1835
pack_nas_SLQSGetSysInfo, 1835
pack_nas_SLQSGetSysSelectionPref, 1835
pack_nas_SLQSGetSysSelectionPrefExt, 1836
pack_nas_SLQSInitiateNetworkRegistration, 1836
pack_nas_SLQSNASGetForbiddenNetworks, 1838
pack_nas_SLQSNASGeteDRXParams, 1837
pack_nas_SLQSNASGeteDRXParamsExt, 1838
pack_nas_SLQSNASSeteDRXParams, 1840
pack_nas_SLQSNASSwiGetChannelLock, 1841
pack_nas_SLQSNASSwiSetChannelLock, 1842
pack_nas_SLQSNasConfigSigInfo2, 1836
pack_nas_SLQSNasGet3GPP2Subscription, 1837
pack_nas_SLQSNasGetCellLocationInfo, 1837
pack_nas_SLQSNasGetHDRColorCode, 1838
pack_nas_SLQSNasGetRFInfo, 1839
pack_nas_SLQSNasGetSigInfo, 1839
pack_nas_SLQSNasGetTxRxInfo, 1839
pack_nas_SLQSNasIndicationRegisterExt, 1840
pack_nas_SLQSNasSwiIndicationRegister, 1841
pack_nas_SLQSNasSwiModemStatus, 1841
pack_nas_SLQSSetBandPreference, 1842
pack_nas_SLQSSetSignalStrengthsCallback, 1842
pack_nas_SLQSSetSysSelectionPref, 1843
pack_nas_SLQSSetSysSelectionPrefExt, 1843
pack_nas_SLQSSwiGetHDRPersonality, 1843
pack_nas_SLQSSwiGetHDRProtSubtype, 1844
pack_nas_SLQSSwiGetHRPDStats, 1844
pack_nas_SLQSSwiGetLteCQI, 1844
pack_nas_SLQSSwiGetLteSccRxInfo, 1845
pack_nas_SLQSSwiNetworkDebug, 1845

pack_nas_SLQSSwiPSDetach, 1845
pack_nas_SetACCOLC, 1831
pack_nas_SetCDMANetworkParameters, 1831
pack_nas_SetLURejectCallback, 1831
pack_nas_SetNetworkPreference, 1832
pack_nas_SetRFInfoCallback, 1832
pack_nas_SlqsGetLTECphyCAInfo, 1833
unpack_nas_GetACCOLC, 1846
unpack_nas_GetANAAAAuthenticationStatus, 1846
unpack_nas_GetCDMANetworkParameters, 1847
unpack_nas_GetHomeNetwork, 1847
unpack_nas_GetHomeNetwork3GPP2, 1847
unpack_nas_GetNetworkPreference, 1848
unpack_nas_GetRFInfo, 1848
unpack_nas_GetServingNetwork, 1848
unpack_nas_GetServingNetworkCapabilities, 1849
unpack_nas_GetSignalStrengths, 1849
unpack_nas_InitiateDomainAttach, 1849
unpack_nas_InitiateDomainAttach_t, 1823
unpack_nas_PerformNetworkScan, 1850
unpack_nas_SLQSConfigSigInfo, 1854
unpack_nas_SLQSConfigSigInfo_t, 1824
unpack_nas_SLQSGetErrorRate, 1854
unpack_nas_SLQSGetNetworkTime, 1855
unpack_nas_SLQSGetOperatorNameData, 1855
unpack_nas_SLQSGetPLMNName, 1855
unpack_nas_SLQSGetServingSystem, 1856
unpack_nas_SLQSGetSignalStrength, 1856
unpack_nas_SLQSGetSysInfo, 1856
unpack_nas_SLQSGetSysSelectionPref, 1857
unpack_nas_SLQSGetSysSelectionPrefExt, 1857
unpack_nas_SLQSInitiateNetworkRegistration, 1858
unpack_nas_SLQSInitiateNetworkRegistration_t, 1824
unpack_nas_SLQSNASGetForbiddenNetworks, 1860
unpack_nas_SLQSNASGeteDRXParams, 1859
unpack_nas_SLQSNASGeteDRXParamsExt, 1860
unpack_nas_SLQSNASSeteDRXParams, 1863
unpack_nas_SLQSNASSeteDRXParams_t, 1824
unpack_nas_SLQSNASSwiGetChannelLock, 1864
unpack_nas_SLQSNASSwiSetChannelLock, 1865
unpack_nas_SLQSNASSwiSetChannelLock_t, 1824
unpack_nas_SLQSNasConfigSigInfo2, 1858
unpack_nas_SLQSNasConfigSigInfo2_t, 1824
unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind, 1858
unpack_nas_SLQSNasGet3GPP2Subscription, 1859
unpack_nas_SLQSNasGetCellLocationInfo, 1859
unpack_nas_SLQSNasGetHDRColorCode, 1860
unpack_nas_SLQSNasGetRFInfo, 1861
unpack_nas_SLQSNasGetSigInfo, 1861
unpack_nas_SLQSNasGetTxRxInfo, 1861
unpack_nas_SLQSNasIndicationRegisterExt, 1862
unpack_nas_SLQSNasIndicationRegisterExt_t, 1824
unpack_nas_SLQSNasNetworkRejectCallback_Ind, 1862
unpack_nas_SLQSNasNetworkTimeCallBack_ind, 1862
unpack_nas_SLQSNasSigInfoCallback_ind, 1863
unpack_nas_SLQSNasSwiIndicationRegister, 1864
unpack_nas_SLQSNasSwiIndicationRegister_t, 1824
unpack_nas_SLQSNasSwiModemStatus, 1864
unpack_nas_SLQSNasSwiOTAMessageCallback_ind, 1865
unpack_nas_SLQSNasSysInfoCallback_ind, 1865
unpack_nas_SLQSNasTimerCallback_ind, 1866
unpack_nas_SLQSSetBandPreference, 1866
unpack_nas_SLQSSetBandPreference_t, 1824
unpack_nas_SLQSSetSignalStrengthsCallback, 1866
unpack_nas_SLQSSetSignalStrengthsCallback_t, 1824
unpack_nas_SLQSSetSysSelectionPref, 1867
unpack_nas_SLQSSetSysSelectionPref_t, 1824
unpack_nas_SLQSSetSysSelectionPrefCallBack_ind, 1867
unpack_nas_SLQSSetSysSelectionPrefExt, 1867
unpack_nas_SLQSSetSysSelectionPrefExt_t, 1824
unpack_nas_SLQSSwiGetHDRPersonality, 1868
unpack_nas_SLQSSwiGetHDRProtSubtype, 1868
unpack_nas_SLQSSwiGetHRPDStats, 1868
unpack_nas_SLQSSwiGetLteCQI, 1869
unpack_nas_SLQSSwiGetLteSccRxInfo, 1869
unpack_nas_SLQSSwiHDRPersonalityCallback_Ind, 1869
unpack_nas_SLQSSwiNetworkDebug, 1870
unpack_nas_SLQSSwiPSDetach, 1870
unpack_nas_SLQSSwiPSDetach_t, 1824
unpack_nas_SLQSSwiRandIndicatorCallback_Ind, 1870
unpack_nas_SetACCOLC, 1850
unpack_nas_SetACCOLC_t, 1824
unpack_nas_SetCDMANetworkParameters, 1850
unpack_nas_SetCDMANetworkParameters_t, 1824
unpack_nas_SetDataCapabilitiesCallback_ind, 1851
unpack_nas_SetEventReportInd, 1851
unpack_nas_SetLURejectCallback, 1852
unpack_nas_SetLURejectCallback_t, 1824
unpack_nas_SetNasLTECphyCaIndCallback_ind, 1852
unpack_nas_SetNetworkPreference, 1852
unpack_nas_SetRFInfoCallback, 1853
unpack_nas_SetRFInfoCallback_t, 1824

unpack_nas_SetRoamingIndicatorCallback_ind, 1853
unpack_nas_SetServingSystemCallback_ind, 1853
unpack_nas_SlqsGetLTECphyCAInfo, 1854
unpack_valid_nas_GetCDMANetworkParameters, 1871
unpack_valid_nas_SLQSGetServingSystem, 1871
unpack_valid_nas_SLQSGetSignalStrength, 1872
unpack_valid_nas_SLQSNasGetSigInfo, 1873
nas_AcqOrderPrefTlv, 472
acqOrdeLen, 473
pAcqOrder, 473
TlvPresent, 473
nas_ActPilotPNElement, 473
ActSetPilotPN, 473
ActSetPilotPNStrength, 473
nas_AddCDMASysInfo, 473
geoSysIdx, 474
regPrd, 474
nas_AddSysInfo, 474
cellBroadcastCap, 474
geoSysIdx, 474
nas_BandPrefInfoTlv, 474
bits_129_192, 475
bits_193_256, 475
bits_1_64, 475
bits_65_128, 475
TlvPresent, 475
nas_BandPrefTlv, 475
BandPref, 477
TlvPresent, 477
nas_CDMAChannel, 478
priChA, 479
priChB, 479
secChA, 479
secChB, 479
nas_CDMAECIOThresh, 479
CDMAECIOThreshListLen, 479
pCDMAECIOThreshList, 479
nas_CDMAInfo, 480
baseId, 480
baseLat, 480
baseLong, 480
nid, 480
refpn, 481
sid, 481
nas_CDMARSSIThresh, 481
CDMARSSIThreshListLen, 481
pCDMARSSIThreshList, 481
nas_CDMASysInfo, 481
baseId, 484
baseLat, 484
baseLong, 484
bsInfoValid, 484
bsPRev, 484
bsPRevValid, 484
ccsSupported, 484
ccsSupportedValid, 484
cdmaSysIdValid, 484
isSysPrlMatch, 484
isSysPrlMatchValid, 484
MCC, 484
MNC, 484
networkID, 484
networkIdValid, 484
pRevInUse, 485
pRevInUseValid, 485
packetZone, 485
packetZoneValid, 485
sysInfoCDMA, 485
systemID, 485
nas_CDMASysInfoExt, 485
imsi_11_12, 485
MCC, 485
nas_CSGID, 490
id, 491
mcc, 491
mnc, 491
mncPcsDigits, 491
rat, 491
nas_CallBarringSysInfo, 477
csBarStatus, 477
psBarStatus, 477
nas_CiotAcqOrderPrefTlv, 487
ciotAcqOrderLen, 488
pCiotAcqOrder, 488
TlvPresent, 488
nas_CiotLteOpModePrefTlv, 488
ciotLteOpModePref, 488
TlvPresent, 488
nas_CommInfo, 488
imsRegState, 490
modemMode, 490
psState, 490
systemMode, 490
temperature, 490
nas_CsgId, 490
csgId, 490
TlvPresent, 490
nas_DRCParams, 497
DRCCover, 498
DRCValue, 498
nas_DataStatusDetail, 493
IPAddress, 494
LastErrCode, 494
nas_DeviceConfigDetail, 496
Chipset, 497
HWVersion, 497
QLIC, 497
Technology, 497
nas_ECIOThresh, 499
ECIOThresListLen, 499
pECIOThresList, 499
nas_EdrxCiotLteMode, 499
lteOpMode, 500

TlvPresent, 500
nas_EdrxCycleLength, 500
cycleLength, 500
TlvPresent, 500
nas_EdrxEnableType, 500
edrxEnabled, 501
TlvPresent, 501
nas_EdrxPagingTimeWindow, 501
edrxPtw, 501
TlvPresent, 501
nas_EdrxRatType, 501
edrxRatType, 502
TlvPresent, 502
nas_EmerModeTlv, 502
EmerMode, 503
TlvPresent, 503
nas_ForbiddenNetworks3GPP, 504
forbiddenNwInstLen, 505
MCC, 505
MNC, 505
TlvPresent, 505
nas_GERANInfo, 505
arfcn, 506
bsic, 506
cellID, 506
insNmrCellInfo, 506
lac, 506
nmrInst, 506
plmn, 506
rxLev, 506
timingAdvance, 506
nas_GSMRSSIThresh, 508
GSMRSSIThreshListLen, 509
pGSMRSSIThreshList, 509
nas_GSMSrvStatusInfo, 509
isPrefDataPath, 510
srvStatus, 510
trueSrvStatus, 510
nas_GSMSysInfo, 510
cellId, 512
cellIdValid, 512
dtmSupp, 512
dtmSuppValid, 512
egprsSupp, 512
egprsSuppValid, 512
lac, 512
lacValid, 512
MCC, 512
MNC, 512
networkIdValid, 512
regRejectInfoValid, 512
rejCause, 512
rejectSrvDomain, 513
sysInfoGSM, 513
nas_GWAcqOrderPrefTlv, 513
GWAcqOrderPref, 513
TlvPresent, 513
nas_HDRECIOThresh, 513
HDRECIOThreshListLen, 514
pHDRECIOThreshList, 514
nas_HDRIOThresh, 514
HDRIOThreshListLen, 514
pHDRIOThreshList, 514
nas_HDRPersonality_Ind_Data, 514
pCurrentPersonality, 515
pPersonalityListLength, 515
pProtocolSubtypeElement, 515
nas_HDRRSSIThresh, 515
HDRRSSIThreshListLen, 515
pHDRRSSIThreshList, 515
nas_HDRSINRThresh, 516
HDRSINRThresListLen, 516
pHDRSINRThresList, 516
nas_HDRSINRThreshold, 516
HDRSINRThreshListLen, 517
pHDRSINRThreshList, 517
nas_HDRSysInfo, 517
hdrActiveProt, 519
hdrActiveProtValid, 519
hdrPersonality, 519
hdrPersonalityValid, 519
is856SysId, 519
is856SysIdValid, 519
isSysPrlMatch, 519
isSysPrlMatchValid, 519
sysInfoHDR, 519
nas_IOThresh, 521
IOThresListLen, 521
pIOThresList, 521
nas_LTEBandPrefExtTlv
nas.h, 1823
nas_LTEBandPrefTlv, 522
LTEBandPref, 523
TlvPresent, 524
nas_LTEInfo, 526
band, 528
bandwidth, 528
emmConnState, 528
emmState, 528
emmSubState, 528
RXChan, 528
TXChan, 528
nas_LTEInfoInterfreq, 529
freqsLen, 529
InfoInterfreq, 529
ueInIdle, 529
nas_LTEInfoIntrafreq, 529
CellParams, 531
cellReselPriority, 531
cellsLen, 531
earfcn, 531
globalCellId, 531
plmn, 531
sIntraSearch, 531
sNonIntraSearch, 531
servingCellId, 531

tac, 531
threshServingLow, 531
ueInIdle, 531
nas_LTEInfoNeighboringGSM, 531
freqsLen, 532
LteGsmCellInfo, 532
ueInIdle, 532
nas_LTEInfoNeighboringWCDMA, 532
freqsLen, 533
ueInIdle, 533
nas_LTEOperationMode, 537
pLTEOperationMode, 537
TlvPresent, 537
nas_LTERSRPThresh, 540
LTERSRPThreshListLen, 540
pLTERSRPThreshList, 540
nas_LTERSRQThresh, 540
LTERSRQThreshListLen, 541
pLTERSRQThreshList, 541
nas_LTERSSIThresh, 541
LTERSSIThreshListLen, 541
pLTERSSIThreshList, 541
nas_LTESNRThresh, 544
LTESNRThresListLen, 544
pLTESNRThresList, 544
nas_LTESNRThreshold, 544
LTESNRThreshListLen, 545
pLTESNRThreshList, 545
nas_LTESigRptCfg, 542
avgPeriod, 542
rptRate, 542
nas_LTESigRptConfig, 542
avgPeriod, 543
rptRate, 543
nas_LTESysInfo, 545
cellId, 547
cellIdValid, 547
lac, 547
lacValid, 547
MCC, 547
MNC, 547
networkIdValid, 547
regRejectInfoValid, 547
rejCause, 547
rejectSrvDomain, 547
sysInfoLTE, 547
tac, 547
tacValid, 547
nas_LteCiotOpModeTlv, 524
campedCiotLteOpMode, 524
TlvPresent, 524
nas_LteM1BandPrefTlv, 533
lteM1BandPref, 534
TlvPresent, 535
nas_LteNb1BandPrefTlv, 535
lteNb1BandPref, 536
TlvPresent, 537
nas_LteOpMode, 537
lteOpMode, 538
TlvPresent, 538
nas_MNRInfo, 549
mcc, 550
mnc, 550
rat, 550
nas_ModePrefTlv, 550
ModePref, 550
TlvPresent, 550
nas_NR5GCellStatusTlv, 558
nr5gCellStatus, 558
TlvPresent, 558
nas_NR5GSerStatTlv, 559
isPrefDataPath, 559
srvStatus, 559
TlvPresent, 559
trueSrvStatus, 559
nas_NR5GSystemInfoTlv, 560
cellId, 562
cellIdValid, 562
lac, 562
lacValid, 562
MCC, 562
MNC, 562
nwIdValid, 562
regRejectInfoValid, 563
rejCause, 563
rejectSrvDomain, 563
roamStatus, 563
roamStatusValid, 563
srvCapValid, 563
srvDomain, 563
srvDomainValid, 563
srvcapability, 563
sysForbidden, 563
sysForbiddenValid, 563
tac, 563
tacValid, 563
TlvPresent, 563
nas_NR5gBandPrefTlv
nas.h, 1823
nas_NetSelPrefTlv, 552
NetSelPref, 552
TlvPresent, 552
nas_NetworkStat1x, 552
ActSetCnt, 554
NeighborSetCnt, 554
pActPilotPNElements, 554
pNeighborSetPilotPN, 554
RX_EC_IO, 554
RX_PWR, 554
SO, 554
State, 554
TX_PWR, 554
nas_NetworkStatEVDO, 554
MACIndex, 556
PER, 556
pSectorID, 556

PilotEnergy, 556
RX_PWR, 556
SNR, 556
SectorIDLen, 556
State, 556
nas_OperatorPLMNData, 563
lac1, 564
lac2, 564
mcc, 564
mnc, 564
PLMNRecID, 564
nas_PLMNNetworkName, 572
numInstance, 572
PLMNNetName, 572
nas_PLMNNetworkNameData, 572
codingScheme, 574
countryInitials, 574
longName, 574
longNameLen, 574
longNameSpareBits, 574
shortName, 574
shortNameLen, 574
shortNameSpareBits, 574
nas_PRLPrefTlv, 574
PRLPref, 575
TlvPresent, 575
nas_PhyCaAggPcellInfo, 565
dl_bw_value, 566
freq, 566
iLTEbandValue, 566
pci, 566
TlvPresent, 566
nas_PhyCaAggScellDlBw, 566
dl_bw_value, 566
TlvPresent, 566
nas_PhyCaAggScellIndType, 567
freq, 567
pci, 567
scell_state, 567
TlvPresent, 567
nas_PhyCaAggScellIndex, 566
scell_idx, 567
TlvPresent, 567
nas_PhyCaAggScellInfo, 568
dl_bw_value, 570
freq, 570
iLTEbandValue, 570
pci, 570
scell_state, 570
TlvPresent, 570
nas_PilotSetData, 570
NumPilots, 570
pPilotSetInfo, 570
nas_PilotSetParams, 571
PilotPN, 571
PilotStrength, 571
PilotType, 571
nas_PlmnID, 571
mcc, 572
mnc, 572
pcsDigit, 572
TlvPresent, 572
nas_QmiNas3GppNetworkInfo, 577
Desription, 578
Forbidden, 578
InUse, 578
MCC, 578
MNC, 578
Preferred, 578
Roaming, 578
nas_QmiNas3GppNetworkRAT, 578
MCC, 579
MNC, 579
RAT, 579
nas_QmisNasPcsDigit, 579
includes_pcs_digit, 580
MCC, 580
MNC, 580
nas_QmisNasSlqsNasPCICellInfo, 580
cellID, 580
freq, 580
GlobalCellID, 580
nasQmisNasPcsDigit, 580
PlmnLen, 580
nas_QmisNasSlqsNasPCIInfo, 581
nasQmisNasSlqsNasPCICellInfo, 581
PCICellInfoLen, 581
rsrp, 581
rsrpRx0, 581
rsrpRx1, 581
rsrq, 582
rsrqRx0, 582
rsrqRx1, 582
nas_RFBandInfoElements, 583
activeBandClass, 584
activeChannel, 584
radioInterface, 584
nas_RFInfoTlv, 589
activeBandClass, 590
activeChannel, 590
radioInterface, 590
radioInterfaceSize, 590
TlvPresent, 590
nas_RSRPThresh, 591
pRSRPThresList, 592
RSRPThresListLen, 592
nas_RSRQThresh, 592
pRSRQThresList, 593
RSRQThresListLen, 593
nas_RSSIThresh, 593
pRSSIThresList, 594
RSSIThresListLen, 594
nas_RankIndicatorTlv, 582
count0, 582
count1, 582
TlvPresent, 582

nas_RatDisabledMaskTlv, 582
ratDisabledMask, 583
TlvPresent, 583
nas_RejectReasonTlv, 583
rejectCause, 583
serviceDomain, 583
TlvPresent, 583
nas_RfBandInfoExtFormat, 584
pInstancesSize, 585
pRfBandInfoExtFormatParam, 585
TlvPresent, 585
nas_RfBandInfoExtFormatElements, 585
activeBand, 585
activeChannel, 585
radioInterface, 585
nas_RfBandInfoList, 586
pInstanceSize, 586
pRFBandInfoParam, 586
nas_RfBandwidthInfo, 586
pInstancesSize, 587
pRfBandwidthInfoParam, 587
TlvPresent, 587
nas_RfBandwidthInfoElements, 587
bandwidth, 587
radioInterface, 587
nas_RfDedicatedBandInfo, 588
pInstancesSize, 588
pRfDedicatedBandInfoParam, 588
TlvPresent, 588
nas_RfDedicatedBandInfoElements, 588
dedicatedBand, 589
radioInterface, 589
nas_RoamPrefTlv, 591
RoamPref, 591
TlvPresent, 591
nas_RxSigInfo, 595
isRadioTuned, 596
rsrp, 596
rxChainIndex, 596
rxPower, 596
nas_SLQSSignalStrengthsIndReq, 601
ecioDelta, 602
ecioThresholdList, 602
ecioThresholdListLen, 602
ioDelta, 603
lteRsrpDelta, 603
lteSnrDelta, 603
rsrqDelta, 603
rxSignalStrengthDelta, 603
sinrDelta, 603
sinrThresholdList, 603
sinrThresholdListLen, 603
nas_SLQSSignalStrengthsInformation, 603
ecioInfo, 604
errorRateInfo, 604
io, 604
lteRsrpinfo, 604
lteSnrinfo, 604
rsrqInfo, 604
rxSignalStrengthInfo, 604
sinr, 604
nas_SLQSSignalStrengthsTlv, 604
sSLQSSignalStrengthsInfo, 605
TlvPresent, 605
nas_SccRxInfo, 597
numInstances, 598
rsrq, 598
sigInfo, 598
snr, 598
TlvPresent, 598
nas_SignalStrengthTlv, 601
radioInterface, 601
signalStrength, 601
TlvPresent, 601
nas_SrvDomainPrefTlv, 605
SrvDomainPref, 605
TlvPresent, 605
nas_SrvStatusInfo, 605
isPrefDataPath, 606
srvStatus, 606
nas_TDSCDMAECIOThresh, 609
nas_TDSCDMARSCPThresh, 609
nas_TDSCDMARSSIThresh, 610
nas_TDSCDMASINRCONFThresh, 610
nas_TDSCDMASINRThresh, 611
nas_UMTSInfo, 614
cellID, 616
ecio, 616
geranInst, 616
GeranInstInfo, 616
lac, 616
plmn, 616
psc, 616
rscp, 616
UMTSInstInfo, 616
uarfcn, 616
umtsInst, 616
nas_UMTSinstInfo, 616
umtsEcio, 617
umtsPsc, 617
umtsRscp, 617
umtsUarfcn, 617
nas_UniversalTime, 618
day, 619
dayOfWeek, 619
hour, 619
minute, 619
month, 619
second, 619
year, 619
nas_WCDMAECIOThresh, 620
nas_WCDMAInfoLTENeighborCell, 620
umtsLTENbrCellLen, 621
wcdmaRRCState, 621
nas_WCDMARSSIThresh, 621
nas_WCDMASysInfo, 622

cellId, 624
cellIdValid, 625
hsCallStatus, 625
hsCallStatusValid, 625
hsInd, 625
hsIndValid, 625
lac, 625
lacValid, 625
MCC, 625
MNC, 625
networkIdValid, 625
psc, 625
pscValid, 625
regRejectInfoValid, 625
rejCause, 625
rejectSrvDomain, 625
sysInfoWCDMA, 625
nas_acqOrderPref, 471
acqOrdeLen, 472
pAcqOrder, 472
nas_callBarStatus, 477
csBarStatus, 478
psBarStatus, 478
nas_cellParams, 485
pci, 486
rsrp, 486
rsrq, 486
rssi, 486
srxlev, 486
nas_ciotAcqOrderPref, 486
ciotAcqOrderLen, 487
pCiotAcqOrder, 487
nas_currentPLMN, 491
MCC, 492
MNC, 492
netDescr, 492
netDescrLength, 492
nas_dataSrvCapabilities, 492
dataCapabilities, 493
dataCapabilitiesLen, 493
nas_detailSvcInfo, 495
hdrHybrid, 496
hdrSrvStatus, 496
isSysForbidden, 496
srvCapability, 496
srvStatus, 496
nas_dirNum, 497
dirNum, 497
dirNumLen, 497
nas_ecioListElement, 498
ecio, 498
radioIf, 499
nas_errorRateListElement, 503
errorRate, 504
radioIf, 504
nas_geranInstInfo, 506
geranArfcn, 507
geranBsicBcc, 507
geranBsicNcc, 507
geranRssi, 507
nas_gsmCellInfo, 507
arfcn, 508
band1900, 508
bsicId, 508
cellIdValid, 508
rssi, 508
srxlev, 508
nas_homeSIDNID, 519
numInstances, 519
SidNid, 519
nas_infoInterFreq, 519
cell_resel_priority, 520
cellInterFreqParams, 520
cells_len, 520
earfcn, 520
threshXHigh, 520
threshXLow, 521
nas_lteBandPrefExt, 521
bits_129_192, 522
bits_193_256, 522
bits_1_64, 522
bits_65_128, 522
nas_lteEARFCN, 524
earfcn0, 525
earfcn1, 525
status, 525
nas_lteGsmCellInfo, 525
cellReselPriority, 526
cells_len, 526
GsmCellInfo, 526
nccPermitted, 526
threshGsmHigh, 526
threshGsmLow, 526
nas_lteOpModeTlv, 538
lteOpMode, 539
lteOpModeLen, 539
MCC, 539
MNC, 539
TlvPresent, 539
nas_ltePCI, 539
earfcn, 539
pci, 539
status, 539
nas_lteRsrpinformation, 539
rsrplevel, 540
nas_lteSnrinformation, 543
snrlevel, 544
nas_lteWcdmaCellInfo, 547
cellReselPriority, 548
cellsLen, 548
threshXhigh, 548
threshXlow, 548
uarfcn, 548
WCDMACellInfo, 548
nas_major
LteNasReleaseInfo_s, 449

NASLteNasReleaseInfoTlv, 649
nas_minBasedIMSI, 548
imsiM1112, 549
imsiMS1, 549
imsiMS2, 549
mccM, 549
nas_minor
LteNasReleaseInfo_s, 449
NASLteNasReleaseInfoTlv, 649
nas_namName, 550
namName, 551
namNameLen, 551
nas_netSelectionPref, 551
mcc, 552
mnc, 552
netReg, 552
nas_nmrCellInfo, 556
nmrArfcn, 557
nmrBsic, 557
nmrCellID, 557
nmrLac, 557
nmrPlmn, 557
nmrRxLev, 557
nas_nr5gBandPref, 557
bits_129_192, 558
bits_193_256, 558
bits_1_64, 558
bits_65_128, 558
nas_operatorNameString, 563
PLMNName, 563
nas_operatorPLMNList, 564
numInstance, 565
PLMNData, 565
nas_protocolSubtypeElement, 575
AccessMac, 576
AuthProt, 576
ControlMac, 576
EncryptProt, 576
ForwardMac, 576
IdleState, 576
KeyExchange, 576
MultDisc, 576
PhysicalLayer, 576
ReverseMac, 576
SecProt, 576
VirtStream, 576
nas_qaQmi3Gpp2TimeZone, 576
daylightSavings, 577
leapSeconds, 577
localTimeOffset, 577
nas_release
LteNasReleaseInfo_s, 449
NASLteNasReleaseInfoTlv, 649
nas_roamIndList, 590
numInstances, 590
radioInterface, 591
roamIndicator, 591
nas_rsrqInformation, 592
radioIf, 592
rsrq, 592
nas_rxInfo, 594
ecio, 595
isRadioTuned, 595
phase, 595
rscp, 595
rsrp, 595
rxPower, 595
nas_rxSignalStrengthListElement, 596
radioIf, 597
rxSignalStrength, 597
nas_servSystem, 599
csAttachState, 600
numRadioInterfaces, 600
psAttachState, 600
radioInterface, 600
regState, 600
selNetwork, 600
nas_serviceProviderName, 598
displayCondition, 598
spn, 598
spnLength, 598
nas_sidNid, 600
nid, 600
sid, 600
nas_sysInfoCommon, 606
isSysForbidden, 608
isSysForbiddenValid, 608
roamStatus, 608
roamStatusValid, 608
srvCapability, 608
srvCapabilityValid, 608
srvDomain, 608
srvDomainValid, 608
nas_timeInfo, 611
day, 613
dayLtSavingAdj, 613
dayOfWeek, 613
hour, 613
minute, 613
month, 613
radioInterface, 613
second, 613
timeZone, 613
TlvPresent, 613
year, 613
nas_trueIMSI, 613
imsiT1112, 614
imsiTS1, 614
imsiTS2, 614
imsiTaddrNum, 614
mccT, 614
nas_txInfo, 614
isInTraffic, 614
txPower, 614
nas_umtsLTENbrCell, 617
cellIsTDD, 618

earfcn, 618
pci, 618
rsrp, 618
rsrq, 618
srxlev, 618
nas_wcdmaCellInfo, 619
cpich_ecno, 620
cpich_rscp, 620
psc, 620
srxlev, 620
nas_wcdmaUARFCN, 625
status, 626
uarfcn, 626
nasCellLocationInfoResp, 627
pCDMAInfo, 627
pGERANInfo, 627
pLTEInfoInterfreq, 628
pLTEInfoIntrafreq, 628
pLTEInfoNeighboringGSM, 628
pLTEInfoNeighboringWCDMA, 628
pUMTSCellID, 628
pUMTSInfo, 628
pWCDMAInfoLTENeighborCell, 628
nasGet3GPP2SubscriptionInfoReq, 629
namID, 629
nasGet3GPP2SubscriptionInfoResp, 630
pCDMAChannel, 630
pDirNum, 630
pHomeSIDNID, 630
pMinBasedIMSI, 630
pNAMNameInfo, 630
pTrueIMSI, 630
nasGetForbiddenNetworksResp, 634
pForbiddenNetworks3GPP, 634
nasGetHDRColorCodeResp, 634
pColorCode, 634
nasGetLTECphyCa, 634
sPhyCaAggPcellInfo, 635
sPhyCaAggScellArray, 635
sPhyCaAggScellDlBw, 635
sPhyCaAggScellIndType, 635
sPhyCaAggScellIndex, 635
sPhyCaAggScellInfo, 635
NasGetLTECphyCaInfo, 635
PhyCaAggPcellInfo, 636
PhyCaAggScellArray, 636
PhyCaAggScellDlBw, 636
PhyCaAggScellIndType, 636
PhyCaAggScellIndex, 636
PhyCaAggScellInfo, 636
nasGetLTECphyCaResp, 636
pPhyCaAggPcellInfo, 636
pPhyCaAggScellArray, 636
pPhyCaAggScellDlBw, 636
pPhyCaAggScellIndType, 636
pPhyCaAggScellIndex, 636
pPhyCaAggScellInfo, 636
NasGetRFInfoResp, 637
pLTEOperationMode, 637
pRfBandInfoExtFormat, 637
pRfBandwidthInfo, 637
pRfDedicatedBandInfo, 637
rfbandInfoList, 637
nasGetSigInfoResp, 637
pCDMASSInfo, 638
pGSMSSInfo, 638
pHDRSSInfo, 638
pLTESSInfo, 638
pTDSCDMASigInfoExt, 638
pTDSCDMASigInfoRscp, 638
pWCDMASSInfo, 638
nasGetSysInfoResp, 638
pAddCDMASysInfo, 641
pAddGSMSysInfo, 641
pAddHDRSysInfo, 641
pAddLTESysInfo, 641
pAddWCDMASysInfo, 641
pCDMASrvStatusInfo, 641
pCDMASysInfo, 641
pCampedCiotLteOpMode, 641
pGSMCallBarringSysInfo, 641
pGSMCipherDomainSysInfo, 641
pGSMSrvStatusInfo, 641
pGSMSysInfo, 641
pHDRSrvStatusInfo, 641
pHDRSysInfo, 641
pLTESrvStatusInfo, 641
pLTESysInfo, 641
pLTEVoiceSupportSysInfo, 641
pWCDMACallBarringSysInfo, 641
pWCDMACipherDomainSysInfo, 641
pWCDMASrvStatusInfo, 641
pWCDMASysInfo, 641
nasGetTxRxInfoReq, 642
radio_if, 642
nasGetTxRxInfoResp, 642
pRXChain0Info, 642
pRXChain1Info, 643
pTXInfo, 643
nasGeteDRXParamsReq, 631
pEdrxRAT, 631
pLteOpMode, 631
nasGeteDRXParamsResp, 631
has_CycleLen, 633
has_EdrxEnable, 633
has_EdrxRAT, 633
has_LteOpMode, 633
has_PagingTimeWindow, 633
pCycleLen, 633
pEdrxEnable, 633
pEdrxRAT, 633
pLteOpMode, 634
pPagingTimeWindow, 634
nasIndicationRegisterReq, 643
pDDTMInd, 646
pDualStandByPrefInd, 646

pEdrxChangeInfoInd, 646
pErrorRateInd, 646
pHDRNewUATIAssInd, 646
pHDRSessionCloseInd, 646
pLTECphyCa, 646
pManagedRoamingInd, 646
pNetworkRejectInd, 646
pNetworkTimeInd, 646
pServingSystemInd, 646
pSignalStrengthInd, 646
pSubscriptionInfoInd, 646
pSuppressSysInfoInd, 646
pSysInfoInd, 646
pSystemSelectionInd, 646
nasInitNetworkReg, 646
pChangeDuration, 647
pMNRInfo, 647
pMncPcsDigitStatus, 647
regAction, 647
nasNetworkReject, 650
pCsgId, 653
pLteOpMode, 653
pPlmnId, 653
radioIf, 653
rejectCause, 653
results, 653
serviceDomain, 653
nasNetworkTime, 653
pDayltSavAdj, 654
pRadioInterface, 654
pTimeZone, 654
results, 654
universalTime, 654
nasOperatorNameResp, 655
pNITZInformation, 655
pOperatorNameString, 655
pOperatorPLMNList, 655
pPLMNNetworkName, 655
pSrvcProviderName, 655
nasPLMNNameReq, 661
mcc, 662
mnc, 662
pMncPcsStatus, 662
nasPLMNNameResp, 662
longName, 664
longNameCI, 664
longNameEn, 664
longNameLen, 664
longNameSB, 664
shortName, 664
shortNameCI, 664
shortNameEn, 664
shortNameLen, 664
shortNameSB, 664
spn, 664
spnEncoding, 664
spnLength, 665
nasQmisNasPcsDigit
nas_QmisNasSlqsNasPCICellInfo, 580
nasQmisNasSlqsNasPCICellInfo
nas_QmisNasSlqsNasPCIInfo, 581
nasRelInfoTlv
NASQmiCbkNasSwiOTAMessageInd, 666
nasSeteDRXParamsReq, 671
pCycleLen, 672
pEdrxCiotLteMode, 672
pEdrxEnable, 672
pEdrxRatType, 672
pPagingTimeWindow, 672
nasSigInfo, 672
pCDMASigInfo, 673
pGSMSigInfo, 673
pHDRSigInfo, 673
pLTESigInfo, 673
pRscp, 673
pTDSCDMASigInfoExt, 673
pWCDMASigInfo, 673
results, 673
nasSwiGetChannelLockResp, 673
pLteEARFCN, 674
pLtePCI, 674
pWcdmaUARFCN, 674
NasSwiIndReg, 674
gsmUmtsDl, 675
gsmUmtsUl, 675
lteEmmDl, 675
lteEmmUl, 675
lteEsmDl, 675
lteEsmUl, 675
pRankIndicatorInd, 675
pTimer, 675
nasSwiSetChannelLockReq, 675
pLteEARFCN, 676
pLtePCI, 676
pWcdmaUARFCN, 676
nasSysInfo, 676
pAddCDMASysInfo, 678
pAddGSMSysInfo, 678
pAddHDRSysInfo, 679
pAddLTESysInfo, 679
pAddWCDMASysInfo, 679
pCDMASrvStatusInfo, 679
pCDMASysInfo, 679
pGSMCallBarringSysInfo, 679
pGSMCipherDomainSysInfo, 679
pGSMSrvStatusInfo, 679
pGSMSysInfo, 679
pHDRSrvStatusInfo, 679
pHDRSysInfo, 679
pLTESrvStatusInfo, 679
pLTESysInfo, 679
pLTEVoiceSupportSysInfo, 679
pLteCiotOpModeTlv, 679
pNR5GCellStatus, 679
pNR5GSerStatTlv, 679
pNR5GSystemInfoTlv, 679

pSysInfoNoChange, 679
pWCDMACallBarringSysInfo, 679
pWCDMACipherDomainSysInfo, 679
pWCDMASrvStatusInfo, 679
pWCDMASysInfo, 679
results, 679
nasTimers, 680
results, 680
t3396_apn, 680
t3396_plmn_id, 680
t3396_val, 680
nccPermitted
lteGsmCellInfo, 440
nas_lteGsmCellInfo, 526
NeighborSetCnt
nas_NetworkStat1x, 554
NetworkStat1x, 685
netDescr
currentPLMN, 221
nas_currentPLMN, 492
netDescrLength
currentPLMN, 221
nas_currentPLMN, 492
netInfoLen
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
netReg
nas_netSelectionPref, 552
netSelectionPref, 681
NetSelPref
nas_NetSelPrefTlv, 552
NASNetSelPreferenceTlv, 650
netSelectionPref, 681
mcc, 681
mnc, 681
netReg, 681
NetStats, 681
rx_bytes, 682
rx_errors, 682
rx_overflows, 682
rx_packets, 682
tx_bytes, 682
tx_errors, 682
tx_overflows, 682
tx_packets, 682
Network Access Service (NAS), 46
NetworkDebugResp, 682
pDataStatusDetail, 683
pDeviceConfigDetail, 683
pNetworkStat1x, 683
pNetworkStatEVDO, 683
pObjectVer, 683
NetworkID
qaQmiServingSystemParam, 916
unpack_nas_SLQSGetServingSystem_t, 1336
networkID
CDMASysInfo, 193
nas_CDMASysInfo, 484
networkIdValid
CDMASysInfo, 193
GSMSysInfo, 333
LTESysInfo, 463
nas_CDMASysInfo, 484
nas_GSMSysInfo, 512
nas_LTESysInfo, 547
nas_WCDMASysInfo, 625
WCDMASysInfo, 1678
networkInfo
voice_USSDNotificationNetworkInfo, 1616
networkInfoLen
unpack_wds_SLQSGetCurrDataSystemStat_t, 1536
NetworkStat1x, 683
ActSetCnt, 685
NeighborSetCnt, 685
pActPilotPNElements, 685
pNeighborSetPilotPN, 685
RX_EC_IO, 685
RX_PWR, 685
SO, 685
State, 685
TX_PWR, 685
NetworkStatEVDO, 685
MACIndex, 687
PER, 687
pSectorID, 687
PilotEnergy, 687
RX_PWR, 687
SNR, 687
SectorIDLen, 687
State, 687
NetworkType
CurrNetworkInfo, 223
currNetworkInfo, 224
wds_currNetworkInfo, 1682
NewMMTlv
unpack_sms_SetNewSMSCallback_ind_t, 1426
newMTMessageTlv, 687
MTMessageInfo, 687
TlvPresent, 687
newPINLen
uim_unblockUIMPIN, 1169
unblockUIMPIN, 1204
newPINVal
uim_unblockUIMPIN, 1169
unblockUIMPIN, 1204
newPasswd
pack_voice_SLQSVoiceSetCallBarringPassword_t, 837
voiceSetCallBarringPwdInfo, 1655
newPasswdAgain
pack_voice_SLQSVoiceSetCallBarringPassword_t, 837
voiceSetCallBarringPwdInfo, 1655
newPin
pack_dms_UIMUnblockPIN_t, 723

newPwd
newPwdData, 688
voice_newPwdData, 1606
newPwdAgain
newPwdData, 688
voice_newPwdData, 1606
newPwdData, 687
newPwd, 688
newPwdAgain, 688
newValue
pack_dms_UIMChangePIN_t, 720
nextHeader
LibPackTFTIDParams, 400
TFTIDParams, 1132
nid
CDMAInfo, 180
nas_CDMAInfo, 480
nas_sidNid, 600
sidNid, 1024
unpack_nas_GetHomeNetwork_t, 1312
NmeaPort
DcsUsbPortNames, 238
nmrArfcn
nas_nmrCellInfo, 557
nmrCellInfo, 689
nmrBsic
nas_nmrCellInfo, 557
nmrCellInfo, 689
nmrCellID
nas_nmrCellInfo, 557
nmrCellInfo, 689
nmrCellInfo, 688
nmrArfcn, 689
nmrBsic, 689
nmrCellID, 689
nmrLac, 689
nmrPlmn, 689
nmrRxLev, 689
nmrInst
GERANInfo, 288
nas_GERANInfo, 506
nmrLac
nas_nmrCellInfo, 557
nmrCellInfo, 689
nmrPlmn
nas_nmrCellInfo, 557
nmrCellInfo, 689
nmrRxLev
nas_nmrCellInfo, 557
nmrCellInfo, 689
noReplyTimer
callFWExtInfo, 166
callFWInfo, 167
voice_callFWExtInfo, 1586
voice_callFWInfo, 1587
Non-service specific APIs (SWI), 57
notifType
unpack_voice_SUPSNotificationCallback_ind_t, 1510
voiceSUPSNotification, 1668
Notification
_SwiAvmsEventInd, 113
notification
omaDmNotificationsTlv, 704
unpack_omaDmNotificationsTlv_t, 1383
notification_Type
unpack_voice_USSDNotificationCallback_ind_t, 1510
notificationType
SMSEtwsMessage, 1068
sMSEtwsMessageInfo, 1069
notused
unpack_dms_SetCrashAction_t, 1236
nr5gBandPref, 689
bits_129_192, 690
bits_193_256, 690
bits_1_64, 690
bits_65_128, 690
Nr5gBandPrefbits1_64
NASNr5gBandPrefTlv, 654
Nr5gBandPrefbits_129_192
NASNr5gBandPrefTlv, 654
Nr5gBandPrefbits_193_256
NASNr5gBandPrefTlv, 654
Nr5gBandPrefbits_65_128
NASNr5gBandPrefTlv, 654
nr5gCellStatus
nas_NR5GCellStatusTlv, 558
NR5GCellStatusTlv, 691
num_instances
_qaQmi3GPP2BroadcastCfgInfo, 77
_qaQmi3GPPBroadcastCfgInfo, 78
custSettingList, 230
DMScustSettingList, 256
sms_qaQmi3GPP2BroadcastCfgInfo, 1058
sms_qaQmi3GPPBroadcastCfgInfo, 1059
numApp
slotInf, 1030
slotInfo, 1031
uim_slotInfo, 1167
numCrashes
CrashInfo, 211
crashInformation, 213
numEntries
CurrentImgList, 220
unpack_dms_SLQSSwiGetFirmwareCurr_t, 1257
numFeatures
personalizationStatus, 876
uim_personalizationStatus, 1159
numFiles
registerRefresh, 962
uim_registerRefresh, 1163
NumFlows
unpack_qos_SLQSSetQosEventCallback_ind_t, 1407

numInstance
nas_operatorPLMNList, 565
nas_PLMNNetworkName, 572
operatorPLMNList, 706
PLMNNetworkName, 886
numInstances
arrAlertingPattern, 144
arrAlertingType, 145
arrAlphaID, 145
arrCalledPartyNum, 146
arrCallEndReason, 147
arrCallInfo, 147
arrConnectPartyNum, 148
arrDiagInfo, 148
arrRedirPartyNum, 149
arrRemotePartyName, 149
arrRemotePartyNum, 150
arrSvcOption, 150
arrUUSInfo, 151
DomainNameList, 262
getCallFWExtInfo, 297
getCallFWInfo, 298
getMsgWaitingInfo, 316
homeSIDNID, 344
msgWaitingInfo, 470
nas_homeSIDNID, 519
nas_roamIndList, 590
nas_SccRxInfo, 598
PCSCFFQDNAddressList, 870
PCSCFIPv4ServerAddressList, 871
roamIndList, 973
SccRxInfo, 987
sms_getMsgWaitingInfo, 1054
unpack_sms_SLQSWmsMessageWaitingCall-Back_ind_t, 1441
voice_arrAlertingPattern, 1573
voice_arrAlertingType, 1574
voice_arrAlphaID, 1574
voice_arrCalledPartyNum, 1575
voice_arrCallEndReason, 1575
voice_arrCallInfo, 1576
voice_arrConnectPartyNum, 1576
voice_arrDiagInfo, 1577
voice_arrRedirPartyNum, 1577
voice_arrRemotePartyName, 1578
voice_arrRemotePartyNum, 1579
voice_arrSvcOption, 1579
voice_arrUUSInfo, 1580
voice_getCallFWExtInfo, 1604
voice_getCallFWInfo, 1604
wds_DomainNameList, 1689
wds_PCSCFFQDNAddressList, 1693
wds_PCSCFIPv4ServerAddressList, 1694
numLen
calledPartyInfo, 162
callFWExtInfo, 166
callFWInfo, 168
callingPartyInfo, 171
peerNumberInfo, 875
redirNumInfo, 961
remotePartyNum, 965
voice_calledPartyInfo, 1582
voice_callFWExtInfo, 1586
voice_callFWInfo, 1587
voice_callingPartyInfo, 1590
voice_peerNumberInfo, 1608
voice_redirNumInfo, 1611
voice_remotePartyNum, 1613
numOfFiles
uim_refreshevent, 1162
UIMRefreshEvent, 1185
numOfRoutes
sms_setRoutesReq, 1063
smsSetRoutesReq, 1079
numOpt
DHCPOptionList, 244
wds_DHCPLeaseOptTlv, 1684
wds_DHCPv4OptionList, 1687
WdsDHCPv4OptionList, 1708
wdsDhcpv4OptionList, 1708
numPI
peerNumberInfo, 875
voice_peerNumberInfo, 1608
NumPilots
nas_PilotSetData, 570
PilotSetData, 883
numPlan
calledPartyInfo, 162
callFWExtInfo, 167
callingPartyInfo, 171
connectNumInfo, 210
peerNumberInfo, 875
redirNumInfo, 961
voice_calledPartyInfo, 1582
voice_callFWExtInfo, 1586
voice_callingPartyInfo, 1590
voice_connectNumInfo, 1596
voice_peerNumberInfo, 1608
voice_redirNumInfo, 1611
numPresInd
connectNumInfo, 210
voice_connectNumInfo, 1596
numQosFlow
sQosStat, 1083
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
numRadioInterfaces
nas_servSystem, 600
servSystem, 996
NumRxFilters
unpack_qos_QosFlowInfo_t, 1401
numSI
peerNumberInfo, 875
voice_peerNumberInfo, 1608
numSlot
cardStatus, 172
uim_cardStatus, 1151

NumSupUSBComps
unpack_dms_GetUSBComp_t, 1232
NumTxFilters
unpack_qos_QosFlowInfo_t, 1402
numType
calledPartyInfo, 162
callFWExtInfo, 167
callingPartyInfo, 171
connectNumInfo, 210
peerNumberInfo, 876
redirNumInfo, 962
voice_calledPartyInfo, 1582
voice_callFWExtInfo, 1586
voice_callingPartyInfo, 1590
voice_connectNumInfo, 1597
voice_peerNumberInfo, 1608
voice_redirNumInfo, 1611
number
calledPartyInfo, 162
callFWExtInfo, 166
callFWInfo, 167
callingPartyInfo, 171
ECTNum, 268
peerNumberInfo, 875
redirNumInfo, 961
voice_calledPartyInfo, 1582
voice_callFWExtInfo, 1586
voice_callFWInfo, 1587
voice_callingPartyInfo, 1590
voice_ECTNum, 1601
voice_peerNumberInfo, 1608
voice_redirNumInfo, 1611
numberPlan
callFwdTypeAndPlan, 165
voice_callFwdTypeAndPlan, 1585
numberType
callFwdTypeAndPlan, 165
voice_callFwdTypeAndPlan, 1585
nwIdValid
nas_NR5GSystemInfoTlv, 562
NR5GSystemInfoTlv, 694
NxtHdrProto
unpack_qos_swiQosFilter_t, 1413

OKtoRefresh
pack_uim_SLQSUIMRefreshOK_t, 820
UIMRefreshOKReq, 1187
OMADMCancelSession
qaGobiApiOmadm.h, 2141
OMADMEnabled
unpack_swioma_SLQSOMADMGetSettings_t, 1454
OMADMGetPendingNIA
qaGobiApiOmadm.h, 2141
OMADMGetSessionInfo
qaGobiApiOmadm.h, 2142
OMADMStartSession
qaGobiApiOmadm.h, 2143
OTASPStatus
unpack_voice_OTASPStatusCallback_ind_t, 1472
voiceOTASPStatusInfo, 1651
oddEvenInd
calledPartySubAdd, 163
voice_calledPartySubAdd, 1583
OfflineReason
unpack_dms_GetPower_t, 1228
offset
readTransparentInfo, 960
uim_readTransparentInfo, 1160
oldPINLen
changeUIMPIN, 197
uim_changeUIMPIN, 1152
oldPINVal
changeUIMPIN, 197
uim_changeUIMPIN, 1152
oldPasswd
pack_voice_SLQSVoiceSetCallBarringPassword_t, 837
voiceSetCallBarringPwdInfo, 1655
oldValue
pack_dms_UIMChangePIN_t, 720
omaDmConfig
sessionInfo, 997
sessionInfoExt, 997
omaDmConfigTlv, 696
alertmsg, 697
alertmsglength, 697
state, 697
userInputReq, 697
userInputTimeout, 697
omaDmConfigTlvExt, 697
alertmsg, 699
alertmsglength, 699
state, 699
userInputReq, 699
userInputTimeout, 699
omaDmFota
sessionInfo, 997
sessionInfoExt, 997
omaDmFotaTlv, 699
description, 700
descriptionlength, 700
fwdloadsize, 700
fwloadComplete, 701
namelength, 701
package_name, 701
sessionType, 701
severity, 701
state, 701
updateCompleteStatus, 701
userInputReq, 701
userInputTimeout, 701
version, 701
versionlength, 701
omaDmFotaTlvExt, 701
description, 703
descriptionlength, 703

fumoResultCode, 703
namelength, 703
package_name, 703
packageSize, 703
receivedBytes, 703
reserved, 703
state, 703
userInputTimeout, 703
version, 703
versionlength, 703
omaDmNotifications
sessionInfo, 997
omaDmNotificationsTlv, 703
notification, 704
sessionStatus, 704
opMode
dmsSwiGetPCInfo, 260
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1243
opaqueId
pack_loc_SLQSLOCInjectSensorData_t, 738
Open Mobile Alliance Service (OMA), 53
operatingMode
dms_OperatingModeTlv, 246
OperatingModeTlv
unpack_dms_SetEventReport_ind_t, 1237
operation
depersonalizationInformation, 240
pack_pds_SetPDSDefaults_t, 783
uim_depersonalizationInformation, 1153
OperationMode
unpack_dms_GetPower_t, 1228
operatorNameString, 704
PLMNName, 704
OperatorPLMNData, 705
lac1, 705
lac2, 705
mcc, 705
mnc, 705
PLMNRecID, 705
operatorPLMNList, 705
numInstance, 706
PLMNData, 706
optCode
DHCPOption, 243
wds_DHCPOpt, 1685
wds_DHCPv4Option, 1687
WdsDHCPv4Option, 1706
wdsDhcpv4Option, 1707
optList
wds_DHCPLeaseOptTlv, 1684
optListData
wds_DHCPLeaseOptTlv, 1684
optVal
wds_DHCPv4Option, 1687
WdsDHCPv4Option, 1706
wdsDhcpv4Option, 1707
optValLen
DHCPOption, 243
wds_DHCPOpt, 1685
wds_DHCPv4Option, 1687
WdsDHCPv4Option, 1707
wdsDhcpv4Option, 1707
OriginateUSSD
qaGobiApiVoice.h, 2288
otaMsgTlv
NASQmiCbkNasSwiOTAMessageInd, 666

p1Status
unpack_dms_UIMGetPINStatus_t, 1269
p1UnblockRetriesLeft
unpack_dms_UIMGetPINStatus_t, 1269
p1VerifyRetriesLeft
unpack_dms_UIMGetPINStatus_t, 1269
p2Status
unpack_dms_UIMGetPINStatus_t, 1269
p2UnblockRetriesLeft
unpack_dms_UIMGetPINStatus_t, 1269
p2VerifyRetriesLeft
unpack_dms_UIMGetPINStatus_t, 1269
p3GPP2Pri
swiQosFlow, 1113
p3GPP2TimeInfo
GetNetworkTimeResp, 316
unpack_nas_SLQSGetNetworkTime_t, 1327
p3GPPImCn
swiQosFlow, 1113
p3GPPResResidualBER
swiQosFlow, 1113
p3GPPSigInd
swiQosFlow, 1113
p3GPPTimeInfo
GetNetworkTimeResp, 316
unpack_nas_SLQSGetNetworkTime_t, 1327
p3GPPTraHdlPri
swiQosFlow, 1113
p3GppNetworkInfoInstances
unpack_nas_PerformNetworkScan_t, 1320
p3GppNetworkInstanceSize
unpack_nas_PerformNetworkScan_t, 1320
p3gppRelease
_slqs3GPPConfigItem, 90
pack_wds_SLQSSet3GPPConfigItem_t, 860
pAAASPI
pack_wds_SetMobileIPProfile_t, 853
PACK_WDS_IPV4
wds.h, 2477
PACK_WDS_IPV6
wds.h, 2477
pAMRStatus
pack_voice_SLQSVoiceGetConfig_t, 833
voiceGetConfigReq, 1643
pAPN
_SLQSAVMSSettingsAPNInfo, 96
pAPNClass
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 390
Profile3GPP, 898

pAPNClass3GPP2
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 903
pAPNDisabledFlag
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 390
Profile3GPP, 898
pAPNEnabled3GPP2
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 903
pAPNInfo
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 93
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
pAPNName
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 390
Profile3GPP, 898
qmiWdsRunTimeSettings, 951
swiPDPRuntimeSettingsResp, 1108
pAPNnameSize
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
PASSWORD_LENGTH
qaGobiApiVoice.h, 2287
pAVRXAVCHeadroom
RXAVCList, 978
pAVRXAVCSens
RXAVCList, 978
pAccelAcceptReady
QmiCbkLocSensorStreamingInd, 937
unpack_loc_SensorStreamingCallback_Ind_t, 1299
pAccelSamplesAccepted
QmiCbkLocInjectSensorDataInd, 928
unpack_loc_InjectSensorDataCallback_Ind_t, 1290
pAccelTempAcceptReady
QmiCbkLocSensorStreamingInd, 937
unpack_loc_SensorStreamingCallback_Ind_t, 1299
pAccelTempSamplesAccepted
QmiCbkLocInjectSensorDataInd, 928
unpack_loc_InjectSensorDataCallback_Ind_t, 1290
pAcceleroData
LocInjectSensorDataReq, 432
pAcceleroTempData
LocInjectSensorDataReq, 432
pAcceleroTimeSrc
LocInjectSensorDataReq, 432
pAccolc
unpack_nas_GetACCOLC_t, 1306
pAccuracy
unpack_pds_GetPDSDefaults_t, 1384
pAcqOrder
acqOrderPref, 130
AcqOrderPrefTlv, 131
nas_acqOrderPref, 472
nas_AcqOrderPrefTlv, 473
pAcqOrderPref
_sysSelectPrefExtInfo, 114
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1349
pActPilotPNElements
nas_NetworkStat1x, 554
NetworkStat1x, 685
pActiveTimer
dmsPsmCfgParamChange, 258
pack_dms_SLQSSetPowerSaveModeConfig_t, 715
PowerSaveModeConfigReq, 889
PowerSaveModeConfigResp, 890
unpack_dms_SLQSGetPowerSaveModeConfig_t, 1253
pAddCDMASysInfo
nasGetSysInfoResp, 641
nasSysInfo, 678
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1378
pAddGSMSysInfo
nasGetSysInfoResp, 641
nasSysInfo, 678
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pAddHDRSysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pAddLTESysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pAddWCDMASysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pAddrAllocPref
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 390
Profile3GPP, 898
pAddress
pack_wds_SetMobileIPProfile_t, 853
pAirTimer
pack_voice_SLQSVoiceGetConfig_t, 833
voiceGetConfigReq, 1643

pAirTimerCnt
unpack_voice_SLQSVoiceGetConfig_t, 1498
voiceGetConfigResp, 1645
pAirTimerConfig
pack_voice_SLQSVoiceSetConfig_t, 839
voiceSetConfigReq, 1658
pAirTimerStatus
unpack_voice_SLQSVoiceSetConfig_t, 1502
voiceSetConfigResp, 1659
pAlertPriority
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pAlertType
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
voiceCallInfoResp, 1622
pAlertingPattern
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
voiceCallInfoResp, 1622
pAllowLinger
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 903
pAlphaID
SMSAsyncRawSend_s, 1066
unpack_sms_SLQSWmsAsyncRawSendCallBack-_ind_t, 1440
pAlphaIDInfo
unpack_voice_SLQSOriginateUSSD_t, 1475
unpack_voice_SLQSVoiceDialCall_t, 1477
unpack_voice_SLQSVoiceGetCallBarring_t, 1483
unpack_voice_SLQSVoiceGetCallForwarding-Status_t, 1484
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
unpack_voice_SLQSVoiceGetCallWaiting_t, 1489
unpack_voice_SLQSVoiceGetCLIP_t, 1490
unpack_voice_SLQSVoiceGetCLIR_t, 1492
unpack_voice_SLQSVoiceGetCNAP_t, 1493
unpack_voice_SLQSVoiceGetCOLP_t, 1495
unpack_voice_SLQSVoiceGetCOLR_t, 1496
unpack_voice_SLQSVoiceSetCallBarringPassword-_t, 1501
unpack_voice_SLQSVoiceSetSUPSService_t, 1504
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1507
USSResp, 1567
voiceCallInfoResp, 1622
voiceCallResponseParams, 1625
voiceGetCallBarringResp, 1632
voiceGetCallFWResp, 1634
voiceGetCallWaitInfo, 1635
voiceGetCLIPResp, 1637
voiceGetCLIRResp, 1638
voiceGetCNAPResp, 1639
voiceGetCOLPResp, 1640
voiceGetCOLRResp, 1642
voiceSetCallBarringPwdResp, 1656
voiceSetSUPSServiceResp, 1663
voiceSUPSInfo, 1666
pAlphaIdentifier
USSDNoWaitIndicationInfo, 1565
pAltitudeAssumed
QmiCbkLocPositionReportInd, 936
unpack_loc_PositionRpt_Ind_t, 1298
pAltitudeSrcInfo
LocInjectPositionReq, 430
pAltitudeWrtEllipsoid
LocInjectPositionReq, 430
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1279
unpack_loc_PositionRpt_Ind_t, 1298
pAltitudeWrtMeanSeaLevel
LocInjectPositionReq, 430
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1279
unpack_loc_PositionRpt_Ind_t, 1298
pAltitudeWrtSealevel
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
pAmrMode
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pAmrOctetAligned
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pAmrWBMode
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pAmrWBOctetAligned
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pAmrWbEnable
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pApnString
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 903
pApnStringSize
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 903
pApnname
pack_wds_SetDefaultProfile_t, 849
pAppName
loc_LocApplicationInfo, 415
LocApplicationInfo, 423

pAppPriority
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 903
pAppProvider
loc_LocApplicationInfo, 415
LocApplicationInfo, 423
pAppSubType
HDRProtSubtypResp, 337
unpack_nas_SLQSSwiGetHDRProtSubtype_t, 1371
pAppType
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 903
pAppVersion
loc_LocApplicationInfo, 415
LocApplicationInfo, 423
pApplication
pack_nas_SetCDMANetworkParameters_t, 745
pApplicationInfo
LOCStartReq, 435
pack_loc_Start_t, 741
pArrAlertingPattern
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrAlertingType
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrAlphaID
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrCallEndReason
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrCallInfo
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
pArrCalledPartyNum
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrConnectPartyNum
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrDiagInfo
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrRedirPartyNum
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrRemotePartyName
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrRemotePartyNum
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrSvcOption
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
voiceSetAllCallStatusCbkInfo, 1654
pArrUUSInfo
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
voiceGetAllCallInfo, 1630
pAuth
pack_wds_SLQSStartDataSession_t, 864
pAuthPassword
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 903
pAuthPassword_tSize
LibPackprofile_3GPP2, 396
pAuthPasswordSize
LibpackProfile3GPP2, 385
Profile3GPP2, 904
pAuthProtocol
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 904
pAuthRetryCount
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 904
pAuthStatus
unpack_nas_GetANAAAAuthenticationStatus_t, 1306
pAuthTimeout
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 904
pAuthenticateResult
UIMAuthenticateResp, 1172
unpack_uim_SLQSUIMAuthenticate_t, 1460
pAuthentication
qmiWdsRunTimeSettings, 951
ssdatasession_params, 1086

pAuthenticationPref
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pAutoAnsStatus
unpack_voice_SLQSVoiceSetConfig_t, 1502
voiceSetConfigResp, 1659
pAutoAnswer
pack_voice_SLQSVoiceGetConfig_t, 833
pack_voice_SLQSVoiceSetConfig_t, 839
voiceGetConfigReq, 1643
voiceSetConfigReq, 1658
pAutoAnswerStat
unpack_voice_SLQSVoiceGetConfig_t, 1498
voiceGetConfigResp, 1645
pAutoConnect
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 93
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
pAutoReboot
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 93
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
pAutoSelection
UIMGetConfigurationResp, 1177
unpack_uim_SLQSUIMGetConfiguration_t, 1462
pAutosdm
_SLQSOMADMSettings, 106
_SLQSOMADMSettingsReqParams, 107
_SLQSOMADMSettingsReqParams3, 108
pack_swioma_SLQSOMADMSetSettings_t, 811
pBandPref
_sysSelectPrefInfo, 119
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1349
pBdsSVInfo
LocDelAssDataReq, 424
pack_loc_Delete_Assist_Data_t, 726
pBearerID
QosFlowInfo, 956
pBearerId
swiPDPRuntimeSettingsResp, 1108
pBearerTech
DataBearerTechExt, 233
pBroadcast
pack_nas_SetCDMANetworkParameters_t, 745
pBroadcastConfig
pack_sms_SLQSSetSmsBroadcastConfig_t, 803
unpack_sms_SLQSGetSmsBroadcastConfig_t, 1430
pBurstDTMFLengths
pack_voice_SLQSVoiceBurstDTMF_t, 827
voiceBurstDTMFInfo, 1620
pCCResType
unpack_voice_SLQSVoiceGetCallBarring_t, 1483
unpack_voice_SLQSVoiceGetCallForwarding-Status_t, 1484
unpack_voice_SLQSVoiceGetCallWaiting_t, 1489
unpack_voice_SLQSVoiceGetCLIP_t, 1490
unpack_voice_SLQSVoiceGetCLIR_t, 1492
unpack_voice_SLQSVoiceGetCNAP_t, 1493
unpack_voice_SLQSVoiceGetCOLP_t, 1495
unpack_voice_SLQSVoiceGetCOLR_t, 1496
unpack_voice_SLQSVoiceSetCallBarringPassword-_t, 1501
voiceGetCallBarringResp, 1632
voiceGetCallFWResp, 1634
voiceGetCallWaitInfo, 1636
voiceGetCLIPResp, 1637
voiceGetCLIRResp, 1638
voiceGetCNAPResp, 1639
voiceGetCOLPResp, 1641
voiceGetCOLRResp, 1642
voiceSetCallBarringPwdResp, 1656
pCCResultType
unpack_voice_SLQSVoiceDialCall_t, 1477
unpack_voice_SLQSVoiceSetSUPSService_t, 1504
voiceCallResponseParams, 1625
voiceSetSUPSServiceResp, 1663
pCCSUPSType
unpack_voice_SLQSVoiceDialCall_t, 1477
unpack_voice_SLQSVoiceGetCallBarring_t, 1483
unpack_voice_SLQSVoiceGetCallForwarding-Status_t, 1484
unpack_voice_SLQSVoiceGetCallWaiting_t, 1489
unpack_voice_SLQSVoiceGetCLIP_t, 1490
unpack_voice_SLQSVoiceGetCLIR_t, 1492
unpack_voice_SLQSVoiceGetCNAP_t, 1493
unpack_voice_SLQSVoiceGetCOLP_t, 1495
unpack_voice_SLQSVoiceGetCOLR_t, 1496
unpack_voice_SLQSVoiceSetCallBarringPassword-_t, 1501
unpack_voice_SLQSVoiceSetSUPSService_t, 1504
voiceCallResponseParams, 1625
voiceGetCallBarringResp, 1632
voiceGetCallFWResp, 1634
voiceGetCallWaitInfo, 1636
voiceGetCLIPResp, 1637
voiceGetCLIRResp, 1638
voiceGetCNAPResp, 1639
voiceGetCOLPResp, 1641
voiceGetCOLRResp, 1642
voiceSetCallBarringPwdResp, 1656
voiceSetSUPSServiceResp, 1663
pCCSuppsType
unpack_voice_SLQSOriginateUSSD_t, 1475
USSResp, 1567
pCDMABroadcastConfig

pack_sms_SLQSSetSmsBroadcastConfig_t, 803
unpack_sms_SLQSGetSmsBroadcastConfig_t, 1430
pCDMAChannel
nasGet3GPP2SubscriptionInfoResp, 630
unpack_nas_SLQSNasGet3GPP2Subscription_t, 1352
pCDMAECIODelta
pack_nas_SLQSNasConfigSigInfo2_t, 752
setSignalStrengthInfo, 1021
pCDMAECIOThresh
pack_nas_SLQSNasConfigSigInfo2_t, 752
setSignalStrengthInfo, 1021
pCDMAECIOThreshList
CDMAECIOThresh, 179
nas_CDMAECIOThresh, 479
pCDMAFrameErrRate
GetErrRateResp, 305
unpack_nas_SLQSGetErrorRate_t, 1326
pCDMAInfo
nasCellLocationInfoResp, 627
unpack_nas_SLQSNasGetCellLocationInfo_t, 1354
pCDMARSSIDelta
pack_nas_SLQSNasConfigSigInfo2_t, 752
setSignalStrengthInfo, 1021
pCDMARSSIThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pCDMARSSIThreshList
CDMARSSIThresh, 189
nas_CDMARSSIThresh, 481
pCDMASSInfo
nasGetSigInfoResp, 638
pCDMASigInfo
nasSigInfo, 673
unpack_nas_SLQSNasSigInfoCallback_ind_t, 1365
pCDMASrvStatusInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pCDMASysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
PCICellInfo
SlqsNasPCIInfo, 1038
PCICellInfoLen
nas_QmisNasSlqsNasPCIInfo, 581
SlqsNasPCIInfo, 1038
pCLIPResp
unpack_voice_SLQSVoiceGetCLIP_t, 1490
voiceGetCLIPResp, 1637
pCLIPstatus
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
pCLIRCause
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pCLIRResp
unpack_voice_SLQSVoiceGetCLIR_t, 1492
voiceGetCLIRResp, 1638
pCLIRType
pack_voice_SLQSVoiceDialCall_t, 828
voiceCallRequestParams, 1624
pCLIRstatus
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
PCMparams, 869
iFaceTab, 869
iFaceTabLen, 869
pCNAPResp
unpack_voice_SLQSVoiceGetCNAP_t, 1493
voiceGetCNAPResp, 1639
pCNAPstatus
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
pCOLPResp
unpack_voice_SLQSVoiceGetCOLP_t, 1495
voiceGetCOLPResp, 1641
pCOLPstatus
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
pCOLRResp
unpack_voice_SLQSVoiceGetCOLR_t, 1496
voiceGetCOLRResp, 1642
pCOLRstatus
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
PCSCFAddrPCO
unpack_wds_SLQSGetRuntimeSettings_t, 1545
PCSCFFQDNAddrList
unpack_wds_SLQSGetRuntimeSettings_t, 1545
PCSCFFQDNAddress, 870
fqdnAddr, 870
fqdnLen, 870
PCSCFFQDNAddressList, 870
numInstances, 870
pcsfFQDNAddress, 870
PCSCFIPv4ServerAddressList, 871
numInstances, 871
pscsfIPv4Addr, 871
pCSCFPortName
imsRegMgrConfigInfo, 359
SetRegMgrConfigReq, 1016
pCSCFPortNameLen
SetRegMgrConfigReq, 1017

pCSGID
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
pCUGIndex
unpack_voice_SUPSNotificationCallback_ind_t, 1510
voiceSUPSNotification, 1668
pCUGInfo
pack_voice_SLQSVoiceDialCall_t, 828
voiceCallRequestParams, 1624
pCallBarPasswd
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1507
voiceSUPSInfo, 1666
pCallBarringPasswd
pack_voice_SLQSVoiceSetSUPSService_t, 841
voiceSetSUPSServiceReq, 1662
pCallEndReason
getDUNCallInfoResp, 303
pCallFWNum
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
pCallFWTimerVal
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
pCallForwardingNumber
pack_voice_SLQSVoiceSetSUPSService_t, 841
voiceSetSUPSServiceReq, 1662
pCallFwdInfo
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1507
voiceSUPSInfo, 1666
pCallFwdTypeAndPlan
pack_voice_SLQSVoiceSetSUPSService_t, 841
voiceSetSUPSServiceReq, 1662
pCallID
burstDTMFInfo, 159
pack_voice_SLQSVoiceManageCalls_t, 835
pack_voice_SLQSVoiceSendFlash_t, 836
pack_voice_SLQSVoiceStartContDTMF_t, 842
unpack_voice_SLQSVoiceBurstDTMF_t, 1476
unpack_voice_SLQSVoiceDialCall_t, 1477
unpack_voice_SLQSVoiceGetCallBarring_t, 1483
unpack_voice_SLQSVoiceGetCallForwarding-Status_t, 1484
unpack_voice_SLQSVoiceGetCallWaiting_t, 1489
unpack_voice_SLQSVoiceGetCLIP_t, 1490
unpack_voice_SLQSVoiceGetCLIR_t, 1492
unpack_voice_SLQSVoiceGetCNAP_t, 1493
unpack_voice_SLQSVoiceGetCOLP_t, 1495
unpack_voice_SLQSVoiceGetCOLR_t, 1496
unpack_voice_SLQSVoiceSendFlash_t, 1499
unpack_voice_SLQSVoiceSetCallBarringPassword-_t, 1501
unpack_voice_SLQSVoiceSetSUPSService_t, 1504
unpack_voice_SLQSVoiceStartContDTMF_t, 1504
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voice_burstDTMFInfo, 1580
voiceCallResponseParams, 1625
voiceContDTMFinfo, 1626
voiceFlashInfo, 1627
voiceGetCallBarringResp, 1632
voiceGetCallFWResp, 1634
voiceGetCallWaitInfo, 1636
voiceGetCLIPResp, 1637
voiceGetCLIRResp, 1638
voiceGetCNAPResp, 1639
voiceGetCOLPResp, 1640
voiceGetCOLRResp, 1642
voiceManageCallsReq, 1649
voiceSetCallBarringPwdResp, 1656
voiceSetSUPSServiceResp, 1663
voiceSUPSInfo, 1666
pCallId
pack_voice_SLQSVoiceAnswerCall_t, 826
pack_voice_SLQSVoiceEndCall_t, 829
unpack_voice_SLQSOriginateUSSD_t, 1475
unpack_voice_SLQSVoiceAnswerCall_t, 1476
unpack_voice_SLQSVoiceEndCall_t, 1478
USSResp, 1567
voiceAnswerCall, 1619
pCallInfo
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
voiceCallInfoResp, 1622
pCallPartySubAdd
pack_voice_SLQSVoiceDialCall_t, 828
voiceCallRequestParams, 1624
pCallType
pack_voice_SLQSVoiceDialCall_t, 828
voiceCallRequestParams, 1624
pCallWaitInd
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pCallback
SetLocGetServerCallbackPara, 1010
SetLocSetServerCallbackParam, 1010
SLQSSetDHCPv4ClientLeaseStatusCallback-Param, 1043
SLQSTmdMitigationLvlRptCallbackParam, 1049
pCallbackAddr
cdmaMsgEncodingParams, 188
pCallbkAddr
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pCallbkAddrLength
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pCalledPartyInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648

pCallerIDInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pCallerNameInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pCallingPartyInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pCampedCiotLteOpMode
nasGetSysInfoResp, 641
unpack_nas_SLQSGetSysInfo_t, 1342
pCardResult
UIMAuthenticateResp, 1172
UIMGetFileAttributesResp, 1179
UIMPinRespV2, 1181
UIMReadTransparentResp, 1183
unpack_uim_ReadTransparent_t, 1458
unpack_uim_SLQSUIMAuthenticate_t, 1460
unpack_uim_SLQSUIMGetFileAttributes_t, 1463
unpack_uim_UnblockPinV2_t, 1467
pCardStatus
UIMGetCardStatusResp, 1175
UIMGetCardStatusRespV2, 1176
unpack_uim_GetCardStatus_t, 1456
unpack_uim_GetCardStatusV2_t, 1457
unpack_uim_SLQSUIMSetStatusChangeCall-Back_ind_t, 1465
pCcResultType
unpack_voice_SLQSOriginateUSSD_t, 1475
USSResp, 1567
pCellDataMask
pack_pds_ResetPDSData_t, 781
pCellDb
LocDelAssDataReq, 424
pack_loc_Delete_Assist_Data_t, 726
pChangeDuration
nasInitNetworkReg, 647
pack_nas_SLQSInitiateNetworkRegistration_t, 749
pChannelRate
getDUNCallInfoResp, 303
pChgDuration
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
pCiotAcqOrder
ciotAcqOrderPref, 199
CiotAcqOrderPrefTlv, 200
nas_ciotAcqOrderPref, 487
nas_CiotAcqOrderPrefTlv, 488
pCiotAcqOrderPref
_sysSelectPrefExtInfo, 114
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
sysSelectPrefParamsExt, 1123
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1349
pCiotLteOpMode
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
sysSelectPrefParamsExt, 1123
pCiotLteOpModePref
_sysSelectPrefExtInfo, 114
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
sysSelectPrefParamsExt, 1123
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1349
pCiotOpModePref
_slqsNetworkScanInfoReq, 101
pack_nas_PerformNetworkScanPCI_t, 743
pClkInfo
LocDelAssDataReq, 424
pack_loc_Delete_Assist_Data_t, 726
pCodecSTGain
GetAudioPathConfigResp, 293
SetAudioPathConfigReq, 999
pColorCode
nasGetHDRColorCodeResp, 634
unpack_nas_SLQSNasGetHDRColorCode_t, 1357
pConfidence
LocSetCradleMountReq, 433
pConfigAltitudeAssumed
LOCStartReq, 435
pack_loc_Start_t, 741
pConfigurationMask
pack_uim_SLQSUIMGetConfiguration_t, 816
UIMGetConfigurationReq, 1177
pConnectNumInfo
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceCallInfoResp, 1622
voiceInfoRec, 1648
pConnectionRetryTimers
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 94
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
pConnectionStatus
getDUNCallInfoResp, 303
pContextId
swiPDPRuntimeSettingsResp, 1108
pCrashInfo
CrashInfoParams, 212
pCrashString
CrashInfo, 211
pCreateProfileOut
unpack_wds_SLQSCreateProfile_t, 1532
pCsgId
nasNetworkReject, 653
unpack_nas_SLQSNasNetworkRejectCallback_-Ind_t, 1363
pCurAMRConfig
unpack_voice_SLQSVoiceGetConfig_t, 1498
voiceGetConfigResp, 1645
pCurDataBearerTechnology
dataBearers, 230
pCurPrefVoiceSO
unpack_voice_SLQSVoiceGetConfig_t, 1498

voiceGetConfigResp, 1645
pCurProfile
pack_wds_SLQSCreateProfile_t, 854
pCurVoiceDomainPref
unpack_voice_SLQSVoiceGetConfig_t, 1498
voiceGetConfigResp, 1645
pCurVoicePrivacyPref
unpack_voice_SLQSVoiceGetConfig_t, 1498
voiceGetConfigResp, 1645
pCurrChannelRateInd
pack_wds_SLQSWdsSetEventReport_t, 866
wdsSetEventReportReq, 1716
pCurrDataBearerTechInd
pack_wds_SLQSWdsSetEventReport_t, 866
wdsSetEventReportReq, 1716
pCurrImgInfo
CurrentImgList, 220
unpack_dms_SLQSSwiGetFirmwareCurr_t, 1257
pCurrNetworkInfo
CurrDataSysStat, 219
pCurrPrefDataSysInd
pack_wds_SLQSWdsSetEventReport_t, 866
wdsSetEventReportReq, 1716
pCurrTTYMode
unpack_voice_SLQSVoiceGetConfig_t, 1498
voiceGetConfigResp, 1645
pCurrentChannelRXRate
WdsConnectionRateElmnts, 1703
pCurrentChannelTXRate
WdsConnectionRateElmnts, 1703
pCurrentPersonality
HDRPersonalityInd, 336
HDRPersonalityResp, 336
nas_HDRPersonality_Ind_Data, 515
unpack_nas_SLQSSwiGetHDRPersonality_t, 1370
pCurrentPrsnlty
HDRProtSubtypResp, 337
unpack_nas_SLQSSwiGetHDRProtSubtype_t, 1371
pCurrentmitigationLvl
TmdGetMitigationLvlResp, 1136
pCustSettingInfo
DMSgetCustomFeatureV2, 257
getCustomFeatureV2, 298
pCustSettingList
DMSgetCustomFeatureV2, 257
getCustomFeatureV2, 298
pCustomSCP
pack_nas_SetCDMANetworkParameters_t, 745
pCwtMute
SetM2MAudioProfileReq, 1013
SetM2MAVMuteReq, 1014
pCycleLen
nasGeteDRXParamsResp, 633
nasSeteDRXParamsReq, 672
pack_nas_SLQSNASSeteDRXParams_t, 760
unpack_nas_SLQSNASGeteDRXParams_t, 1355
unpack_nas_SLQSNASGeteDRXParamsExt_t, 1356
pDDTMInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 758
pDHCPRelayEnabled
custFeaturesInfo, 226
custFeaturesSetting, 228
PDOP
loc_precisionDilution, 416
precisionDilution_s, 890
PDPType
unpack_wds_SLQSGetRuntimeSettings_t, 1545
pDRCParams
GetHRPDStatsResp, 306
unpack_nas_SLQSSwiGetHRPDStats_t, 1372
PDS_SRV
qaGobiApiCbk.h, 1913
PDSInjectTimeReference
qaGobiApiPds.h, 2149
PDSPosMethodStateReq, 873
pWifiState, 874
pXtraDataState, 874
pXtraTimeState, 874
PDSPositionData, 871
pAltitudeWrtEllipsoid, 873
pAltitudeWrtSealevel, 873
pHorizontalConfidence, 873
pHorizontalUncCircular, 873
pLatitude, 873
pLongitude, 873
pPositionSource, 873
pTimeStamp, 873
pTimeType, 873
pVerticalConfidence, 873
pVerticalUnc, 873
pDTMFTXGain
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 999
PDUMessage
wcdmaMsgEncodingParams, 1674
pDataBearer
QosEventInfo, 955
slqsWdsEventInfo, 1050
unpack_wds_GetDataBearerTechnology_t, 1518
pDataBearerTech
getDUNCallInfoResp, 303
pDataBearerTechInd
pack_wds_SLQSWdsSetEventReport_t, 866
wdsSetEventReportReq, 1716
pDataCallStatusChangeInd
pack_wds_SLQSWdsSetEventReport_t, 866
wdsSetEventReportReq, 1716
pDataMode
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 904
pDataRate

LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 904
swiQosFlow, 1113
pDataSrc
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
pDataStatusDetail
NetworkDebugResp, 683
unpack_nas_SLQSSwiNetworkDebug_t, 1375
pDataSystemStatusChangeInd
pack_wds_SLQSWdsSetEventReport_t, 866
wdsSetEventReportReq, 1716
pDate
_SLQSOMADMSessionInfo, 104
pDateLength
_SLQSOMADMSessionInfo, 104
pDayltSavAdj
nasNetworkTime, 654
unpack_nas_SLQSNasNetworkTimeCallBack_ind_t, 1364
pDefaultPDNEnabled
_slqs3GPPConfigItem, 90
pack_wds_SLQSSet3GPPConfigItem_t, 860
pDeferTime
pack_swioma_SLQSOMADMSendSelection_t, 810
pDesription
QmiNas3GppNetworkInfo, 945
pDestAddr
cdmaMsgEncodingParams, 188
wcdmaMsgEncodingParams, 1674
pDestSMSContent
getDyingGaspCfg, 304
pack_dms_SLQSSwiSetDyingGaspCfg_t, 716
packgetDyingGaspCfg, 868
setDyingGaspCfg, 1004
pDestSMSNum
getDyingGaspCfg, 304
pack_dms_SLQSSwiSetDyingGaspCfg_t, 716
packgetDyingGaspCfg, 868
setDyingGaspCfg, 1004
pDetachAction
pack_nas_SLQSSwiPSDetach_t, 780
PSDetachReq, 907
pDevCrashStatus
CrashInfoParams, 212
pDeviceConfigDetail
NetworkDebugResp, 683
unpack_nas_SLQSSwiNetworkDebug_t, 1375
pDiagInfo
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
voiceCallInfoResp, 1622
pDigitBuff
burstDTMFInfo, 159
voice_burstDTMFInfo, 1580
pDirNum
nasGet3GPP2SubscriptionInfoResp, 630
unpack_nas_SLQSNasGet3GPP2Subscription_t, 1352
pDisableIMSI
custFeaturesInfo, 226
pDispInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pDisplayMode
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pDomainList
qmiWdsRunTimeSettings, 951
pDormancyStatus
getDUNCallInfoResp, 303
slqsWdsEventInfo, 1051
pDormancyStatusInd
pack_wds_SLQSWdsSetEventReport_t, 867
wdsSetEventReportReq, 1716
pDualStandByPrefInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 758
pDuration
unpack_pds_GetXTRAValidity_t, 1388
pDurationDueToOOS
PowerSaveModeConfigResp, 890
unpack_dms_SLQSGetPowerSaveModeConfig_t, 1253
pDurationThreshold
PowerSaveModeConfigResp, 890
unpack_dms_SLQSGetPowerSaveModeConfig_t, 1253
pECIOThresList
ECIOThresh, 267
nas_ECIOThresh, 499
pECIOThresh
pack_nas_SLQSConfigSigInfo_t, 747
sigInfo, 1025
pECMode
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pECTNum
unpack_voice_SUPSNotificationCallback_ind_t, 1510
voiceSUPSNotification, 1668
PER
nas_NetworkStatEVDO, 556
NetworkStatEVDO, 687
pESNString
serialNumbersInfo, 992
pEVDOPageMonPerChangeInd
pack_wds_SLQSWdsSetEventReport_t, 867
wdsSetEventReportReq, 1716
pEarMute
SetM2MAudioProfileReq, 1013
pEarlyWakeupTime
PowerSaveModeConfigResp, 890

unpack_dms_SLQSGetPowerSaveModeConfig_t, 1253
pEdrxChangeInfoInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 758
pEdrxCiotLteMode
nasSeteDRXParamsReq, 672
pack_nas_SLQSNASSeteDRXParams_t, 760
pEdrxEnable
nasGeteDRXParamsResp, 633
nasSeteDRXParamsReq, 672
pack_nas_SLQSNASSeteDRXParams_t, 760
unpack_nas_SLQSNASGeteDRXParams_t, 1355
unpack_nas_SLQSNASGeteDRXParamsExt_t, 1356
pEdrxRAT
nasGeteDRXParamsReq, 631
nasGeteDRXParamsResp, 633
pack_nas_SLQSNASGeteDRXParamsExt_t, 755
unpack_nas_SLQSNASGeteDRXParamsExt_t, 1356
pEdrxRatType
nasSeteDRXParamsReq, 672
pack_nas_SLQSNASSeteDRXParams_t, 760
pEhrpdMTUSize
SwiDmsGetMTUResp, 1098
unpack_swidms_SLQSSwiDmsGetMTU_t, 1443
pEmerMode
_sysSelectPrefInfo, 119
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pEmergencyCategory
pack_voice_SLQSVoiceDialCall_t, 828
voiceCallRequestParams, 1624
pEnableNotification
pack_wds_DHCPv4ClientLeaseChange_t, 843
WdsClientLeaseChange, 1702
pEnableState
dmsPsmCfgParamChange, 258
pEnabled
pack_wds_SetMobileIPProfile_t, 853
pEnabledStatus
unpack_pds_GetPDSState_t, 1385
pEncodingAlphabet
cdmaMsgEncodingParams, 188
pEncryptData
pack_uim_ReadTransparent_t, 813
UIMReadTransparentReq, 1183
pEncryptedData
UIMReadTransparentResp, 1183
unpack_uim_ReadTransparent_t, 1458
pEncryptedPIN1
pack_uim_VerifyPin_t, 823
UIMPinResp, 1180
UIMPinRespV2, 1181
UIMVerifyPinReq, 1194
unpack_uim_ChangePin_t, 1455
unpack_uim_SetPinProtection_t, 1459
unpack_uim_UnblockPin_t, 1466
unpack_uim_UnblockPinV2_t, 1467
unpack_uim_VerifyPin_t, 1468
pError
USSDNoWaitIndicationInfo, 1565
pErrorCodeStr
imsaRatStatusInfo, 351
pErrorMask
CATEventDataType, 175
pErrorRateInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 758
pEspSpi
swiQosFilter, 1110
pEtwsMessageInfo
SMSEventInfo_s, 1071
pEtwsPlmnInfo
SMSEventInfo_s, 1071
pExtDispInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pExtDispRecInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pExtErrCode
_GetProfileSettingOut, 71
UnPackGetProfileSettingOut, 1560
pExtErrorCode
CreateProfileOut, 215
ModifyProfileOut, 469
unpack_wds_SLQSModifyProfile_t, 1546
pFOTAUpdate
_SLQSOMADMSettings, 106
pFOTAdownload
_SLQSOMADMSettings, 106
pFailCause
unpack_voice_SLQSVoiceGetCallBarring_t, 1483
unpack_voice_SLQSVoiceGetCallForwarding-Status_t, 1484
unpack_voice_SLQSVoiceGetCallWaiting_t, 1489
unpack_voice_SLQSVoiceGetCLIP_t, 1491
unpack_voice_SLQSVoiceGetCLIR_t, 1492
unpack_voice_SLQSVoiceGetCNAP_t, 1493
unpack_voice_SLQSVoiceGetCOLP_t, 1495
unpack_voice_SLQSVoiceGetCOLR_t, 1496
unpack_voice_SLQSVoiceManageCalls_t, 1499
unpack_voice_SLQSVoiceSetCallBarringPassword-_t, 1501
unpack_voice_SLQSVoiceSetSUPSService_t, 1504
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceGetCallBarringResp, 1632
voiceGetCallFWResp, 1634

voiceGetCallWaitInfo, 1636
voiceGetCLIPResp, 1637
voiceGetCLIRResp, 1638
voiceGetCNAPResp, 1639
voiceGetCOLPResp, 1641
voiceGetCOLRResp, 1642
voiceManageCallsResp, 1650
voiceSetCallBarringPwdResp, 1656
voiceSetSUPSServiceResp, 1663
voiceSUPSInfo, 1666
pFailErrorCode
imsaPdpStatusInfo, 350
pFailureCause
USSDNoWaitIndicationInfo, 1565
pFailureReason
unpack_wds_SLQSStartDataSession_t, 1556
pFile
ERIFileparams, 273
pFileAttributes
UIMGetFileAttributesResp, 1179
unpack_uim_SLQSUIMGetFileAttributes_t, 1463
pFileSize
ERIFileparams, 273
pFixId
QmiCbkLocPositionReportInd, 936
unpack_loc_PositionRpt_Ind_t, 1298
pFlag
RXPCMIIRFltr, 981
TXPCMIIRFltr, 1144
pFlashPayLd
pack_voice_SLQSVoiceSendFlash_t, 836
voiceFlashInfo, 1628
pFlashType
pack_voice_SLQSVoiceSendFlash_t, 836
voiceFlashInfo, 1628
pFollowOnDC
slqssendasyncsmsparams_s, 1041
sms_sendAsyncsmsParams, 1062
pForbidden
QmiNas3GppNetworkInfo, 945
pForbiddenNetworks3GPP
nasGetForbiddenNetworksResp, 634
unpack_nas_SLQSNASGetForbiddenNetworks_t, 1357
pForceOnDC
slqssendasyncsmsparams_s, 1041
sms_sendAsyncsmsParams, 1062
pForceRev0
pack_nas_SetCDMANetworkParameters_t, 745
pFwAutoCheck
_SLQSOMADMSettings, 106
_SLQSOMADMSettingsReqParams3, 108
pack_swioma_SLQSOMADMSetSettings_t, 811
pFwAutoSDM
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 94
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
pFwPromptUpdate
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 94
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
pFwPromptdownload
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 94
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
pGCDumpString
CrashInfo, 211
pGERANInfo
nasCellLocationInfoResp, 627
unpack_nas_SLQSNasGetCellLocationInfo_t, 1354
pGPRSGrantedQoS
qmiWdsRunTimeSettings, 951
pGPRSMinimumQoS
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pGPRSRequestedQos
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pGPSDataMask
pack_pds_ResetPDSData_t, 782
pGPSEnable
custFeaturesSetting, 228
pGPSLPM
custFeaturesInfo, 226
custFeaturesSetting, 228
pGPSSel
custFeaturesInfo, 226
custFeaturesSetting, 228
pGPSWeek
unpack_pds_GetXTRAValidity_t, 1388
pGPSWeekOffset
unpack_pds_GetXTRAValidity_t, 1388
pGSMBER
GetErrRateResp, 305
unpack_nas_SLQSGetErrorRate_t, 1326
pGSMCallBarringSysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pGSMCipherDomainSysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pGSMRSSIDelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pGSMRSSIThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753

setSignalStrengthInfo, 1021
pGSMRSSIThreshList
GSMRSSIThresh, 329
nas_GSMRSSIThresh, 509
pGSMSSInfo
nasGetSigInfoResp, 638
pGSMSigInfo
nasSigInfo, 673
unpack_nas_SLQSNasSigInfoCallback_ind_t, 1365
pGSMSrvStatusInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pGSMSysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pGWAcqOrderPref
_sysSelectPrefInfo, 119
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pGWAddressV4
qmiWdsRunTimeSettings, 951
pGenerator
GetM2MAudioProfileReq, 311
SetM2MAudioProfileReq, 1013
pGetCallFWExtInfo
unpack_voice_SLQSVoiceGetCallForwarding-Status_t, 1485
voiceGetCallFWResp, 1634
pGetCallFWInfo
unpack_voice_SLQSVoiceGetCallForwarding-Status_t, 1485
voiceGetCallFWResp, 1634
pGetCustomInput
DMSgetCustomFeatureV2, 257
getCustomFeatureV2, 298
pGetDyingGaspCfg
unpack_dms_SLQSSwiGetDyingGaspCfg_t, 1256
pGetDyingGaspStatistics
unpack_dms_SLQSSwiGetDyingGaspStatistics_t, 1256
pGetIndicationRegInfo
unpack_sms_SLQSGetIndicationRegister_t, 1428
pGetMsgWaitingInfoResp
unpack_sms_SLQSGetMessageWaiting_t, 1428
pGetTransLayerInfo
unpack_sms_SLQSGetTransLayerInfo_t, 1431
pGetTransNWRegInfo
unpack_sms_SLQSGetTransNWRegInfo_t, 1432
pGnssData
LocDelAssDataReq, 424
pack_loc_Delete_Assist_Data_t, 726
pGpsTime
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1279
unpack_loc_PositionRpt_Ind_t, 1298
pGyroAcceptReady
QmiCbkLocSensorStreamingInd, 937
unpack_loc_SensorStreamingCallback_Ind_t, 1300
pGyroData
LocInjectSensorDataReq, 432
pGyroSamplesAccepted
QmiCbkLocInjectSensorDataInd, 928
unpack_loc_InjectSensorDataCallback_Ind_t, 1291
pGyroTempAcceptReady
QmiCbkLocSensorStreamingInd, 938
unpack_loc_SensorStreamingCallback_Ind_t, 1300
pGyroTempData
LocInjectSensorDataReq, 432
pGyroTempSamplesAccepted
QmiCbkLocInjectSensorDataInd, 928
unpack_loc_InjectSensorDataCallback_Ind_t, 1291
pGyroTimeSrc
LocInjectSensorDataReq, 432
pHA2002bis
pack_wds_SetMobileIPParameters_t, 851
pHAAuthenticator
pack_wds_SetMobileIPParameters_t, 851
pHASPI
pack_wds_SetMobileIPProfile_t, 853
pHDRECIODelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pHDRECIOThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pHDRECIOThreshList
HDRECIOThresh, 335
nas_HDRECIOThresh, 514
pHDRIODelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pHDRIOThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pHDRIOThreshList
HDRIOThresh, 335
nas_HDRIOThresh, 514
pHDRNewUATIAssInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 758
pHDRPackErrRate
GetErrRateResp, 305

unpack_nas_SLQSGetErrorRate_t, 1326
pHDRPersInd
unpack_nas_SLQSSwiHDRPersonalityCallback_-Ind_t, 1374
pHDRRSSIDelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pHDRRSSIThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pHDRRSSIThreshList
HDRRSSIThresh, 338
nas_HDRRSSIThresh, 515
pHDRSINRDelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pHDRSINRThresList
HDRSINRThresh, 338
nas_HDRSINRThresh, 516
pHDRSINRThresh
pack_nas_SLQSConfigSigInfo_t, 747
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
sigInfo, 1025
pHDRSINRThreshList
HDRSINRThreshold, 339
nas_HDRSINRThreshold, 517
pHDRSSInfo
nasGetSigInfoResp, 638
pHDRSessionCloseInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 758
pHDRSigInfo
nasSigInfo, 673
unpack_nas_SLQSNasSigInfoCallback_ind_t, 1365
pHDRSrvStatusInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pHDRSysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pHWWatchdog
unpack_swidms_SLQSSwiDmsGetHWWatchdog-_t, 1442
pHaltSubscription
UIMGetConfigurationResp, 1177
unpack_uim_SLQSUIMGetConfiguration_t, 1462
pHeading
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1279
unpack_loc_PositionRpt_Ind_t, 1298
pHeadingUnc
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1279
unpack_loc_PositionRpt_Ind_t, 1298
pHomeSIDNID
nasGet3GPP2SubscriptionInfoResp, 630
unpack_nas_SLQSNasGet3GPP2Subscription_t, 1352
pHorCirConf
QmiCbkLocBestAvailPosInd, 921
unpack_loc_BestAvailPos_Ind_t, 1279
pHorConfidence
LocInjectPositionReq, 430
QmiCbkLocPositionReportInd, 936
unpack_loc_PositionRpt_Ind_t, 1298
pHorEllpConf
QmiCbkLocBestAvailPosInd, 921
unpack_loc_BestAvailPos_Ind_t, 1279
pHorReliability
LocInjectPositionReq, 431
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1279
unpack_loc_PositionRpt_Ind_t, 1298
pHorUncCircular
LocInjectPositionReq, 431
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1279
unpack_loc_PositionRpt_Ind_t, 1298
pHorUncEllipseOrientAzimuth
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pHorUncEllipseSemiMajor
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pHorUncEllipseSemiMinor
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pHorizontalAccuracyLvl
LOCStartReq, 435
pack_loc_Start_t, 741
pHorizontalConfidence
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
pHorizontalUncCircular
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
pHostID
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 111
pHotSwapStatus

UIMGetCardStatusResp, 1175
UIMGetCardStatusRespV2, 1176
unpack_uim_GetCardStatus_t, 1456
unpack_uim_GetCardStatusV2_t, 1457
pHrpdMTUSize
SwiDmsGetMTUResp, 1098
unpack_swidms_SLQSSwiDmsGetMTU_t, 1443
pHwConfig
pack_wds_SLQSSSetDHCPv4ClientConfig_t, 863
unpack_wds_SLQSSGetDHCPv4ClientConfig_t, 1555
WdsDHCPv4Config, 1705
PI
calledPartyInfo, 162
callerIDInfo, 164
callFWExtInfo, 167
callingPartyInfo, 171
redirNumInfo, 962
voice_calledPartyInfo, 1582
voice_callerIDInfo, 1584
voice_callFWExtInfo, 1586
voice_callingPartyInfo, 1591
voice_redirNumInfo, 1611
PIFACEId
SetM2MAudioAVCFGReq, 1011
pIMCNflag
qmiWdsRunTimeSettings, 951
pIMEIString
serialNumbersInfo, 992
pIMSDomain
GetIMSUserConfigParams, 308
imsUserConfigInfo, 361
SetIMSUserConfigReq, 1005
pIMSDomainLen
GetIMSUserConfigParams, 308
SetIMSUserConfigReq, 1005
pIMSTestMode
GetRegMgrConfigParams, 317
imsRegMgrConfigInfo, 359
SetRegMgrConfigReq, 1017
pIOThresList
IOThresh, 367
nas_IOThresh, 521
pIOThresh
pack_nas_SLQSConfigSigInfo_t, 747
sigInfo, 1025
pIPAddressV4
QmiWdsIpAddressInfo, 948
qmiWdsRunTimeSettings, 951
pIPAddressV6
QmiWdsIpAddressInfo, 948
pIPFamSupport
custFeaturesInfo, 226
pIPFamily
GetInstIDResp, 310
pIPFamilyPreference
qmiWdsRunTimeSettings, 951
pIPV6AddrInfo
qmiWdsRunTimeSettings, 951
pIPV6GWAddrInfo
qmiWdsRunTimeSettings, 951
pIPv4Addr
WdsDHCPv4ClientLeaseInd, 1704
pIPv4AddrInfo
QmiCbkLocGetServerInd, 926
unpack_loc_GetServer_Ind_t, 1287
pIPv4AddrPref
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pIPv4Address
swiPDPRuntimeSettingsResp, 1108
pIPv4Config
LocSetServerReq, 434
pack_loc_SLQSLOCSetServer_t, 740
pIPv4DstAddr
swiQosFilter, 1110
pIPv4GWAddress
swiPDPRuntimeSettingsResp, 1108
pIPv4SrcAddr
swiQosFilter, 1110
pIPv6AddPref
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pIPv6AddrInfo
QmiCbkLocGetServerInd, 926
unpack_loc_GetServer_Ind_t, 1287
pIPv6Address
swiPDPRuntimeSettingsResp, 1108
pIPv6Config
LocSetServerReq, 434
pack_loc_SLQSLOCSetServer_t, 740
pIPv6DstAddr
swiQosFilter, 1110
pIPv6GWAddress
swiPDPRuntimeSettingsResp, 1108
pIPv6Label
swiQosFilter, 1110
pIPv6SrcAddr
swiQosFilter, 1110
pIPv6TrafCls
swiQosFilter, 1110
pIPv6prefixlen
QmiWdsIpAddressInfo, 948
pId
swiQosFilter, 1110
pIds
swiQosIds, 1114
pIgnoreHotSwapSwitch
pack_uim_SLQSUIMPowerUp_t, 818
UIMPowerUpReq, 1182
pImCnFlag
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898

pImageList
pack_fms_SetImagesPreference_t, 725
unpack_fms_GetImagesPreference_t, 1272
pImeiSvnString
serialNumbersInfo, 992
pImgType
FirmwareUpdatStat, 281
pImsRegErrCode
IMSARegistrationStatus, 352
pImsRegStatus
IMSARegistrationStatus, 352
imsaRegStatusInfo, 352
pInUse
QmiNas3GppNetworkInfo, 945
pIndFieldsList
IMSASupportedFieldsResp, 355
pIndicationToken
pack_uim_ChangePin_t, 812
pack_uim_ReadTransparent_t, 813
pack_uim_SetPinProtection_t, 814
pack_uim_SLQSUIMAuthenticate_t, 815
pack_uim_SLQSUIMGetFileAttributes_t, 817
pack_uim_UnblockPin_t, 822
pack_uim_VerifyPin_t, 823
UIMAuthenticateReq, 1171
UIMAuthenticateResp, 1172
UIMChangePinReq, 1173
UIMGetFileAttributesReq, 1178
UIMGetFileAttributesResp, 1179
UIMPinResp, 1180
UIMPinRespV2, 1181
UIMReadTransparentReq, 1183
UIMReadTransparentResp, 1183
UIMSetPinProtectionReq, 1189
UIMUnblockPinReq, 1193
UIMVerifyPinReq, 1194
unpack_uim_ChangePin_t, 1455
unpack_uim_ReadTransparent_t, 1458
unpack_uim_SetPinProtection_t, 1459
unpack_uim_SLQSUIMAuthenticate_t, 1460
unpack_uim_SLQSUIMGetFileAttributes_t, 1463
unpack_uim_UnblockPin_t, 1466
unpack_uim_UnblockPinV2_t, 1467
unpack_uim_VerifyPin_t, 1468
pInfo
pack_voice_AnswerUSSD_t, 824
pack_voice_OriginateUSSD_t, 824
pInstanceID
GetInstIDResp, 310
pInstanceSize
nas_RfBandInfoList, 586
QmiNasPerformNetworkScanResp, 946
RfBandInfoList, 969
pInstances
QmiNasPerformNetworkScanResp, 946
pInstancesSize
nas_RfBandInfoExtFormat, 585
nas_RfBandwidthInfo, 587
nas_RfDedicatedBandInfo, 588
QmiNasGetRFBandInfoResp, 945
RfBandInfoExtFormat, 968
RfBandwidthInfo, 970
RfDedicatedBandInfo, 971
pInterfaceCfg
SwiDmsGetUsbCompResp, 1099
unpack_swidms_SLQSSwiDmsGetUsbComp_t, 1444
pIntermediateReportState
LOCStartReq, 435
pack_loc_Start_t, 741
pInterval
unpack_pds_GetPDSDefaults_t, 1384
unpack_pds_GetXTRAAutomaticDownload_t, 1387
pIpcpAckTimeout
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 396
Profile3GPP2, 904
pIpcpCreqRetryCount
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pIsPcscfAddressNedded
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pIsUDHPresent
cdmaMsgDecodingParamsExt, 186
wcdmaLongMsgDecodingParams, 1672
pIsVoiceEnabled
custFeaturesInfo, 226
custFeaturesSetting, 228
pJitter
swiQosFlow, 1113
pKeyReferenceID
pack_uim_ChangePin_t, 812
pack_uim_SetPinProtection_t, 814
pack_uim_UnblockPin_t, 822
pack_uim_VerifyPin_t, 823
UIMChangePinReq, 1173
UIMSetPinProtectionReq, 1189
UIMUnblockPinReq, 1193
UIMVerifyPinReq, 1194
PLMN_LENGTH
qaGobiApiNas.h, 2089
PLMNData
nas_operatorPLMNList, 565
operatorPLMNList, 706
PLMNName
nas_operatorNameString, 563
operatorNameString, 704
PLMNNetName
nas_PLMNNetworkName, 572
PLMNNetworkName, 886
PLMNNetworkName, 885
numInstance, 886

PLMNNetName, 886
PLMNNetworkNameData, 886
codingScheme, 887
countryInitials, 887
longName, 887
longNameLen, 887
longNameSpareBits, 887
shortName, 887
shortNameLen, 887
shortNameSpareBits, 888
PLMNRecID
nas_OperatorPLMNData, 564
OperatorPLMNData, 705
pLTEAttachProfile
_slqs3GPPConfigItem, 90
pack_wds_SLQSSet3GPPConfigItem_t, 860
pLTEAttachProfileList
_slqs3GPPConfigItem, 90
pack_wds_SLQSSet3GPPConfigItem_t, 860
pLTEBandPref
_sysSelectPrefInfo, 119
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pLTEBandPrefExt
_sysSelectPrefExtInfo, 114
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
sysSelectPrefParamsExt, 1123
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pLTECphyCa
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 758
pLTEInfo
swiModemStatusResp, 1104
unpack_nas_SLQSNasSwiModemStatus_t, 1367
pLTEInfoInterfreq
nasCellLocationInfoResp, 628
unpack_nas_SLQSNasGetCellLocationInfo_t, 1354
pLTEInfoIntrafreq
nasCellLocationInfoResp, 628
unpack_nas_SLQSNasGetCellLocationInfo_t, 1354
pLTEInfoNeighboringGSM
nasCellLocationInfoResp, 628
unpack_nas_SLQSNasGetCellLocationInfo_t, 1354
pLTEInfoNeighboringWCDMA
nasCellLocationInfoResp, 628
unpack_nas_SLQSNasGetCellLocationInfo_t, 1354
pLTEOperationMode
LTEOperationMode, 451
nas_LTEOperationMode, 537
NasGetRFInfoResp, 637
QmiNasGetRFBandInfoResp, 946
unpack_nas_SLQSNasGetRFInfo_t, 1358
pLTERSRPDelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pLTERSRPThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pLTERSRPThreshList
LTERSRPThresh, 454
nas_LTERSRPThresh, 540
pLTERSRQDelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pLTERSRQThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pLTERSRQThreshList
LTERSRQThresh, 455
nas_LTERSRQThresh, 541
pLTERSSIDelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pLTERSSIThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pLTERSSIThreshList
LTERSSIThresh, 456
nas_LTERSSIThresh, 541
pLTESNRDelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pLTESNRThresList
LTESNRThresh, 459
nas_LTESNRThresh, 544
pLTESNRThresh
pack_nas_SLQSConfigSigInfo_t, 747
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
sigInfo, 1026
pLTESNRThreshList
LTESNRThreshold, 459
nas_LTESNRThreshold, 545
pLTESSInfo
nasGetSigInfoResp, 638
pLTESigInfo
nasSigInfo, 673
unpack_nas_SLQSNasSigInfoCallback_ind_t, 1365
pLTESigRptCfg
pack_nas_SLQSConfigSigInfo_t, 747
sigInfo, 1026
pLTESigRptConfig
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pLTESrvStatusInfo
nasGetSysInfoResp, 641

nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pLTESysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pLTEVoiceSupportSysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pLanguage
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pLastBearerTech
DataBearerTechExt, 233
pLastCallDataBearerTech
getDUNCallInfoResp, 303
pLastCallDataBearerTechnology
dataBearers, 230
pLastCallRXOKBytesCnt
getDUNCallInfoResp, 303
pLastCallTXOKBytesCnt
getDUNCallInfoResp, 303
pLatency
swiQosFlow, 1113
pLatitude
LocInjectPositionReq, 431
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pLcpAckTimeout
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pLcpCreqRetryCount
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pLeapSeconds
QmiCbkLocPositionReportInd, 936
unpack_loc_PositionRpt_Ind_t, 1298
pLeaseState
WdsDHCPv4ClientLeaseInd, 1704
pLineCtrlInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pLinktimer
pack_sms_SendSMS_t, 796
slqssendasyncsmsparams_s, 1041
slqssendsmsparams_s, 1042
sms_sendAsyncsmsParams, 1062
pLogString
FirmwareUpdatStat, 281
pLogStringLen
FirmwareUpdatStat, 282
pLongitude
LocInjectPositionReq, 431
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pLoopbackMode
WDSSetLoopbackData, 1717
pLoopbackMultiplier
WDSSetLoopbackData, 1717
pLpmFlag
dmsSwiGetPCInfo, 260
pLteBandCapability
BandCapabilityResp, 156
pLteCiotOpModeTlv
nasSysInfo, 679
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pLteEARFCN
nasSwiGetChannelLockResp, 674
nasSwiSetChannelLockReq, 676
pack_nas_SLQSNASSwiSetChannelLock_t, 762
unpack_nas_SLQSNASSwiGetChannelLock_t, 1366
pLteM1BandPref
_slqsNetworkScanInfoReq, 101
_sysSelectPrefExtInfo, 114
pack_nas_PerformNetworkScanPCI_t, 743
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
sysSelectPrefParamsExt, 1123
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pLteNB1BandPref
_slqsNetworkScanInfoReq, 102
pack_nas_PerformNetworkScanPCI_t, 743
pLteNasRelInfo
SwiOTAMsg_s, 1105
pLteNb1BandPref
_sysSelectPrefExtInfo, 114
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
sysSelectPrefParamsExt, 1123
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pLteOpMode
nasGeteDRXParamsReq, 631
nasGeteDRXParamsResp, 634
nasNetworkReject, 653
pack_nas_SLQSNASGeteDRXParamsExt_t, 755
unpack_nas_SLQSNASGeteDRXParamsExt_t, 1356
unpack_nas_SLQSNasNetworkRejectCallback_-Ind_t, 1363
pLteOpModeTlv
_slqsNetworkScanInfo, 98

unpack_nas_PerformNetworkScan_t, 1320
pLtePCI
nasSwiGetChannelLockResp, 674
nasSwiSetChannelLockReq, 676
pack_nas_SLQSNASSwiSetChannelLock_t, 762
unpack_nas_SLQSNASSwiGetChannelLock_t, 1366
pLteQci
swiQosFlow, 1113
pMCC
QmiNas3GppNetworkInfo, 945
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pMEIDString
serialNumbersInfo, 992
pMICGainSelect
GetAudioPathConfigResp, 294
pMIPStatusInd
pack_wds_SLQSWdsSetEventReport_t, 867
wdsSetEventReportReq, 1716
pMNAAA
pack_wds_SetMobileIPProfile_t, 853
pMNC
QmiNas3GppNetworkInfo, 945
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pMNCIncPCSDigStat
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
pMNHA
pack_wds_SetMobileIPProfile_t, 853
pMNRInfo
nasInitNetworkReg, 647
pack_nas_SLQSInitiateNetworkRegistration_t, 749
pMTMessageInfo
SMSEventInfo_s, 1071
pMTUSize3gpp
SwiDmsGetMTUResp, 1098
unpack_swidms_SLQSSwiDmsGetMTU_t, 1443
pMagneticDeviation
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pManString
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 112
pManagedRoamingInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 758
pMaxAllowedPktSz
swiQosFlow, 1113
pMaxChannelRXRate
WdsConnectionRateElmnts, 1703
pMaxChannelTXRate
WdsConnectionRateElmnts, 1703
pMaxStorageSizeReq
pack_sms_SLQSSmsGetMaxStorageSize_t, 804
pMaxStorageSizeResp
unpack_sms_SLQSSmsGetMaxStorageSize_t, 1436
pMdmCallDurationActive
getDUNCallInfoResp, 303
pMeidString
_SLQSSwiGetSerialNoExtParams, 110
pMessage
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
cdmaMsgEncodingParams, 188
pack_sms_SaveSMS_t, 796
pack_sms_SendSMS_t, 797
slqssendasyncsmsparams_s, 1041
slqssendsmsparams_s, 1042
sms_sendAsyncsmsParams, 1062
wcdmaLongMsgDecodingParams, 1672
wcdmaMsgDecodingParams, 1673
pMessageID
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pMessageIndex
pack_sms_SLQSDeleteSMS_t, 798
unpack_sms_SaveSMS_t, 1424
pMessageMode
pack_sms_SLQSDeleteSMS_t, 798
pack_sms_SLQSGetSMS_t, 799
pack_sms_SLQSGetSMSList_t, 800
pack_sms_SLQSModifySMSStatus_t, 801
sms_maxStorageSizeReq, 1055
smsMaxStorageSizeReq, 1072
pMessageModeInfo
SMSEventInfo_s, 1071
pMessageProtocol
unpack_sms_SLQSSmsGetMessageProtocol_t, 1436
pMessageSize
cdmaMsgEncodingParams, 188
pMessageTag
pack_sms_SLQSDeleteSMS_t, 798
pMicMute
SetM2MAudioProfileReq, 1013
pMinBasedIMSI
nasGet3GPP2SubscriptionInfoResp, 630
unpack_nas_SLQSNasGet3GPP2Subscription_t, 1352
pMinIntervalTime
LOCStartReq, 435
pack_loc_Start_t, 741
pMinPolicedPktSz
swiQosFlow, 1114
pMinSessionExpiryTimer
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pMitigationDevList
TmdGetMitigationDevListResp, 1135
pMitigationDevListLen
TmdGetMitigationDevListResp, 1135

pMncPcsDigitStatus
nasInitNetworkReg, 647
pack_nas_SLQSInitiateNetworkRegistration_t, 749
pMncPcsStatus
nasPLMNNameReq, 662
pack_nas_SLQSGetPLMNName_t, 748
pMode
pack_wds_SetMobileIPParameters_t, 851
QmiCbkLocGetOpModeInd, 925
unpack_loc_GetOpMode_Ind_t, 1286
pModePref
_sysSelectPrefInfo, 119
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pModelString
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 112
pMtu
qmiWdsRunTimeSettings, 951
pMuxID
pack_qos_BindDataPort_t, 793
pNAI
pack_wds_SetMobileIPProfile_t, 853
pNAMNameInfo
nasGet3GPP2SubscriptionInfoResp, 630
unpack_nas_SLQSNasGet3GPP2Subscription_t, 1352
pNID
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pNITZInformation
nasOperatorNameResp, 655
unpack_nas_SLQSGetOperatorNameData_t, 1328
pNMEAData
QmiCbkLocEventNMEAInd, 923
pNR5GCellStatus
nasSysInfo, 679
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pNR5GSerStatTlv
nasSysInfo, 679
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pNR5GSystemInfoTlv
nasSysInfo, 679
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pNSEnable
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pNSSAudioCtrl
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1648
pNSSRelease
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1649
pNamID
pack_voice_SLQSVoiceGetConfig_t, 833
voiceGetConfigReq, 1643
pName
pack_wds_SetDefaultProfile_t, 849
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pNameString
_SLQSSwiGetOSInfoParams, 110
_SLQSSwiSetOSInfoParams, 112
pNegoDnsSrvrPref
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pNeighborSetPilotPN
nas_NetworkStat1x, 554
NetworkStat1x, 685
pNetSelPref
_sysSelectPrefInfo, 119
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pNetworkInfo
_slqsNetworkScanInfo, 98
pNetworkInfoInstances
_slqsNetworkScanInfo, 98
pNetworkInfoLen
CurrDataSysStat, 219
pNetworkMode
pack_pds_SLQSGetAGPSConfig_t, 786
pack_pds_SLQSSetAGPSConfig_t, 789
pNetworkRejectInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 759
pNetworkStat1x
NetworkDebugResp, 683
unpack_nas_SLQSSwiNetworkDebug_t, 1375
pNetworkStatEVDO
NetworkDebugResp, 683
unpack_nas_SLQSSwiNetworkDebug_t, 1375
pNetworkTimeInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 759
pNetworkType
_slqsNetworkScanInfoReq, 102
pack_nas_PerformNetworkScanPCI_t, 743
pNewImsRegStatus
IMSARegistrationStatus, 352
pNewPwdData
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
pNotifStore
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 94
pNotificationStore
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95

pNr5gBandPref
_sysSelectPrefExtInfo, 115
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
sysSelectPrefParamsExt, 1123
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pNumSupUSBComps
USBCompParams, 1564
pNumberOfPhySlot
UIMGetSlotsStatusResp, 1179
unpack_uim_SLQSUIMGetSlotsStatus_t, 1464
pNw2DescDisp
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pNw2DescEnc
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pNw2DescLen
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pNw2MCC
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pNw2MNC
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pNw2Name
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pNxtHdrProto
swiQosFilter, 1110
pOMADMEnabled
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
_SLQSOMADMSettings, 106
PORTNAM_LEN
qaGobiApiDcs.h, 1994
pOTASPStatus
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
voiceCallInfoResp, 1622
voiceGetAllCallInfo, 1630
pObjectVer
NetworkDebugResp, 683
unpack_nas_SLQSSwiNetworkDebug_t, 1375
pOffLength
unpack_voice_DTMFEventCallback_ind_t, 1471
voiceDTMFEventInfo, 1627
pOnLength
unpack_voice_DTMFEventCallback_ind_t, 1471
voiceDTMFEventInfo, 1627
pOpaqueIdentifier
LocInjectSensorDataReq, 432
QmiCbkLocInjectSensorDataInd, 929
unpack_loc_InjectSensorDataCallback_Ind_t, 1291
pOperation
unpack_pds_GetPDSDefaults_t, 1384
pOperatorNameString
nasOperatorNameResp, 655
unpack_nas_SLQSGetOperatorNameData_t, 1328
pOperatorPLMNList
nasOperatorNameResp, 655
unpack_nas_SLQSGetOperatorNameData_t, 1328
pOptList
wds_DHCPv4OptionList, 1687
WdsDHCPv4ClientLeaseInd, 1704
WdsDHCPv4OptionList, 1708
wdsDhcpv4OptionList, 1708
pOptVal
DHCPOption, 243
wds_DHCPOpt, 1685
pOptions
DHCPOptionList, 244
pPCIInfo
_slqsNetworkScanInfo, 98
unpack_nas_PerformNetworkScan_t, 1320
pPCMParams
SetM2MAudioAVCFGReq, 1011
pPCSCFAddrPCO
qmiWdsRunTimeSettings, 951
pPCSCFFQDNAddrList
qmiWdsRunTimeSettings, 951
pPCSCFPort
GetRegMgrConfigParams, 317
pPCSDigitInfo
_slqsNetworkScanInfo, 98
pPCSDigitInstances
_slqsNetworkScanInfo, 98
pPCSInstance
unpack_nas_PerformNetworkScan_t, 1320
pPCSInstanceSize
unpack_nas_PerformNetworkScan_t, 1320
pPDNInactivTimeout
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pPDNInactivTimeout3GPP2
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pPDPType
qmiWdsRunTimeSettings, 951
pPDPtype
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 899
pPLMNNetworkName
nasOperatorNameResp, 655
unpack_nas_SLQSGetOperatorNameData_t, 1328
pPRLPref
_sysSelectPrefInfo, 119
_sysSelectPrefParams, 125
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 779
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pPRLPreference
dmsCurrentPRLInfo, 254
pPRLVersion
dmsCurrentPRLInfo, 255

pPWD
_SLQSAVMSSettingsAPNInfo, 96
pPacketsCountRX
QosEventInfo, 956
slqsWdsEventInfo, 1051
pPacketsCountTX
QosEventInfo, 956
slqsWdsEventInfo, 1051
pPagingTimeWindow
nasGeteDRXParamsResp, 634
nasSeteDRXParamsReq, 672
pack_nas_SLQSNASSeteDRXParams_t, 760
unpack_nas_SLQSNASGeteDRXParams_t, 1355
unpack_nas_SLQSNASGeteDRXParamsExt_t, 1356
pPartNum
cdmaMsgDecodingParamsExt, 186
wcdmaLongMsgDecodingParams, 1672
pPass
pack_wds_SLQSStartDataSession_t, 864
pPassword
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
pack_wds_SetDefaultProfile_t, 849
Profile3GPP, 898
ssdatasession_params, 1086
pPasswordSize
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pPcscfAddrUsingDhcp
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pPcscfAddrUsingPCO
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pPdnType
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pPdpAccessConFlag
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pPdpContext
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pPdpDataCompType
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pPdpHdrCompType
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 898
pPdpStatusConfig
IMSAIndRegisterInfo, 349
pPeriodicUpdateTimer
dmsPsmCfgParamChange, 258
pack_dms_SLQSSetPowerSaveModeConfig_t, 715
PowerSaveModeConfigReq, 889
PowerSaveModeConfigResp, 890
unpack_dms_SLQSGetPowerSaveModeConfig_t, 1253
pPeripheralEndPointID
pack_qos_BindDataPort_t, 793
pPeroidInfo
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 94
pPeroidsInfo
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
pPersistentLpm
dmsSwiGetPCInfo, 260
pPersonalityListLength
HDRPersonalityInd, 336
HDRPersonalityResp, 336
HDRProtSubtypResp, 337
nas_HDRPersonality_Ind_Data, 515
unpack_nas_SLQSSwiGetHDRPersonality_t, 1370
unpack_nas_SLQSSwiGetHDRProtSubtype_t, 1371
pPersonalizationStatus
UIMGetConfigurationResp, 1177
unpack_uim_SLQSUIMGetConfiguration_t, 1462
pPhoneCtxtURI
GetIMSSMSConfigParams, 307
imsSMSConfigInfo, 360
SetIMSSMSConfigReq, 1004
pPhoneCtxtURILen
GetIMSSMSConfigParams, 307
SetIMSSMSConfigReq, 1004
pPhyCaAggPcellInfo
nasGetLTECphyCaResp, 636
pPhyCaAggScellArray
nasGetLTECphyCaResp, 636
pPhyCaAggScellDlBw
nasGetLTECphyCaResp, 636
pPhyCaAggScellIndType
nasGetLTECphyCaResp, 636
pPhyCaAggScellIndex
nasGetLTECphyCaResp, 636
pPhyCaAggScellInfo
nasGetLTECphyCaResp, 636
pPilotSetData
GetHRPDStatsResp, 306
unpack_nas_SLQSSwiGetHRPDStats_t, 1372
pPilotSetInfo
nas_PilotSetData, 570
PilotSetData, 883
pPkgDescLength
_SLQSOMADMSessionInfo, 104

pPkgDescription
_SLQSOMADMSessionInfo, 104
pPkgName
_SLQSOMADMSessionInfo, 104
pPkgNameLength
_SLQSOMADMSessionInfo, 104
pPktErrRate
swiQosFlow, 1114
pPlasmaIDString
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 112
pPlmnId
nasNetworkReject, 653
unpack_nas_SLQSNasNetworkRejectCallback_-Ind_t, 1363
pPollingTimer
_SLQSAVMSSetSettingsReqPara, 92
_SLQSAVMSSetSettingsReqPara_v2, 94
_SLQSAVMSSettings, 94
_SLQSAVMSSettings_v2, 95
pPositionSource
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
pPositionSrc
LocInjectPositionReq, 431
pPowerOffMode
dmsSwiGetPCInfo, 260
pPppSessCloseTimer1x
LibpackProfile3GPP2, 385
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pPppSessCloseTimerDO
LibpackProfile3GPP2, 386
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pPrDNSIPv4Address
swiPDPRuntimeSettingsResp, 1108
pPrDNSIPv6Address
swiPDPRuntimeSettingsResp, 1108
pPrPCSCFIPv4Address
swiPDPRuntimeSettingsResp, 1108
pPrPCSCFIPv6Address
swiPDPRuntimeSettingsResp, 1108
pPrecedence
swiQosFilter, 1110
pPrecisionDilution
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pPrefNetwork
CurrDataSysStat, 219
pPrefVoiceDomain
pack_voice_SLQSVoiceSetConfig_t, 839
voiceSetConfigReq, 1658
pPrefVoicePrivacy
pack_voice_SLQSVoiceGetConfig_t, 833
voiceGetConfigReq, 1643
pPrefVoiceSO
pack_voice_SLQSVoiceGetConfig_t, 833
pack_voice_SLQSVoiceSetConfig_t, 839
voiceGetConfigReq, 1643
voiceSetConfigReq, 1658
pPrefVoiceSOStatus
unpack_voice_SLQSVoiceSetConfig_t, 1502
voiceSetConfigResp, 1659
pPreference
unpack_pds_GetXTRANetwork_t, 1387
pPreferred
QmiNas3GppNetworkInfo, 945
pPriCSCFPort
imsRegMgrConfigInfo, 359
SetRegMgrConfigReq, 1017
pPriCSCFPortName
GetRegMgrConfigParams, 317
pPriCSCFPortNameLen
GetRegMgrConfigParams, 317
pPriDNSIPv4AddPref
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 899
pPriDNSIPv6addpref
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 899
pPriV6DnsAddress
LibpackProfile3GPP2, 386
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pPrimaryDNSV4
qmiWdsRunTimeSettings, 951
pPrimaryDNSV6
qmiWdsRunTimeSettings, 951
pPrimaryHA
pack_wds_SetMobileIPProfile_t, 853
pPrimaryID
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 899
pPrimaryV4DnsAddress
LibpackProfile3GPP2, 386
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pPriority
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
cdmaMsgEncodingParams, 188
pPrivacy
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pProfSz
NWProfile, 696
pProfValues
NWProfile, 696
pProfileID
CreateProfileIn, 214

ModifyProfileIn, 469
qmiWdsRunTimeSettings, 951
unpack_wds_SLQSCreateProfile_t, 1532
pProfileId
pack_wds_SLQSCreateProfile_t, 854
pack_wds_SLQSModifyProfile_t, 859
pack_wds_SLQSSGetDHCPv4ClientConfig_t, 862
pack_wds_SLQSSSetDHCPv4ClientConfig_t, 863
WdsDHCPv4ClientLeaseInd, 1704
WdsDHCPv4Config, 1705
pProfileId3GPP
ssdatasession_params, 1086
pProfileId3GPP2
ssdatasession_params, 1086
swiQosFlow, 1114
pProfileIndex
CreateProfileOut, 215
pProfileList
_slqs3GPPConfigItem, 90
pack_wds_SLQSSet3GPPConfigItem_t, 860
pProfileName
qmiWdsRunTimeSettings, 951
pProfileSettings
unpack_wds_SLQSGetProfileSettings_t, 1542
pProfileType
CreateProfileIn, 214
CreateProfileOut, 215
ModifyProfileIn, 469
pack_wds_SLQSCreateProfile_t, 854
pack_wds_SLQSModifyProfile_t, 859
pProfilename
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 899
pProfilenameSize
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 899
pProtoSubTypElmnt
HDRProtSubtypResp, 337
unpack_nas_SLQSSwiGetHDRProtSubtype_t, 1371
pProtocol
pack_nas_SetCDMANetworkParameters_t, 745
pProtocolSubtypeElement
HDRPersonalityInd, 336
HDRPersonalityResp, 336
nas_HDRPersonality_Ind_Data, 515
unpack_nas_SLQSSwiGetHDRPersonality_t, 1370
pPsmEnableState
pack_dms_SLQSSetPowerSaveModeConfig_t, 715
PowerSaveModeConfigReq, 889
PowerSaveModeConfigResp, 890
unpack_dms_SLQSGetPowerSaveModeConfig_t, 1253
pQFlowState
QosFlowInfo, 956
pQmiInterfaceInfo
_packetSrvStatus, 76
slqsSessionStateInfo, 1043
slqsWdsEventInfo, 1051
pQosClassID
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 899
pRAT
_sysSelectPrefParams, 126
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 780
pRATINstance
unpack_nas_PerformNetworkScan_t, 1320
pRATInfo
_slqsNetworkScanInfo, 98
pRATInstanceSize
unpack_nas_PerformNetworkScan_t, 1320
pRATInstances
_slqsNetworkScanInfo, 99
pRATStatus
imsaRatStatusInfo, 351
pRATType
LibpackProfile3GPP2, 386
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
PREFERRED_INDEX
qaNasPerformNetworkScan.h, 2350
pRFBandInfoElements
QmiNasGetRFBandInfoResp, 946
pRFBandInfoParam
nas_RfBandInfoList, 586
RfBandInfoList, 969
PRI_UPDATE_FAIL
qaGobiApiFms.h, 2046
PRIString
unpack_dms_GetFirmwareRevision_t, 1221
unpack_dms_GetFirmwareRevisions_t, 1222
PRLInd
qaQmiServingSystemParam, 916
unpack_nas_SLQSGetServingSystem_t, 1336
PRLPTlv
NASQmiCbkNasSystemSelPrefInd, 668
PRLPref
nas_PRLPrefTlv, 575
NASPRLPreferenceTlv, 665
pRMAutoConnect
custFeaturesInfo, 226
pRSRPThresList
nas_RSRPThresh, 592
RSRPThresh, 975
pRSRPThresh
pack_nas_SLQSConfigSigInfo_t, 747
sigInfo, 1026
pRSRQThresList
nas_RSRQThresh, 593
RSRQThresh, 976
pRSRQThresh

pack_nas_SLQSConfigSigInfo_t, 747
sigInfo, 1026
pRSSIThresList
nas_RSSIThresh, 594
RSSIThresh, 977
pRSSIThresh
pack_nas_SLQSConfigSigInfo_t, 747
sigInfo, 1026
pRTPRTCPInactTimer
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pRXAGCList
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pRXAIG
RXAGCList, 978
pRXAVCAGCSwitch
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pRXAVCList
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pRXChain0Info
nasGetTxRxInfoResp, 642
unpack_nas_SLQSNasGetTxRxInfo_t, 1360
pRXChain1Info
nasGetTxRxInfoResp, 643
unpack_nas_SLQSNasGetTxRxInfo_t, 1360
pRXComprSlope
RXAGCList, 978
pRXComprThres
RXAGCList, 978
pRXDroppedCount
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pRXExpSlope
RXAGCList, 978
pRXExpThres
RXAGCList, 978
pRXOKBytesCount
getDUNCallInfoResp, 303
pRXOKBytesLastCall
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pRXOkBytesCount
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pRXPCMIIRFltr
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pRXPacketErrors
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pRXPacketOverflows
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pRXPacketSuccesses
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pRXStaticGain
RXAGCList, 978
pRXTotalBytes
unpack_wds_GetByteTotals_t, 1516
WdsByteTotalsElmnts, 1701
pRadioInterface
nasNetworkTime, 654
unpack_nas_SLQSNasNetworkTimeCallBack_ind_t, 1364
pRandomizationWindow
PowerSaveModeConfigResp, 890
unpack_dms_SLQSGetPowerSaveModeConfig_t, 1253
pRankIndicatorInd
NasSwiIndReg, 675
pack_nas_SLQSNasSwiIndicationRegister_t, 762
pRatDisabledMask
_sysSelectPrefExtInfo, 115
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pRatHandoverStatusConfig
IMSAIndRegisterInfo, 349
pRawHorConfidence
LocInjectPositionReq, 431
pRawHorUncCircular
LocInjectPositionReq, 431
pReRegPeriod
pack_wds_SetMobileIPParameters_t, 851
pReRegTraffic
pack_wds_SetMobileIPParameters_t, 851
pReadAcknowledgementReq
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pReadResult
UIMReadTransparentResp, 1183
unpack_uim_ReadTransparent_t, 1458
pReason
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
pReasonMask
unpack_dms_GetOfflineReason_t, 1227
pRecurrenceType
LOCStartReq, 435
pack_loc_Start_t, 741
pRedirNumInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1649
pRefData
FirmwareUpdatStat, 282
pRefString
FirmwareUpdatStat, 282
pRefStringLen
FirmwareUpdatStat, 282
pReferenceNum
cdmaMsgDecodingParamsExt, 186

wcdmaLongMsgDecodingParams, 1672
pRefreshEvent
UIMRefreshGetLastEventResp, 1186
unpack_uim_SLQSUIMRefreshGetLastEvent_t, 1465
pRegCallStatInfoEvt
_getIndicationRegResp, 70
_setIndicationRegReq, 88
sms_getIndicationReg, 1053
sms_setIndicationReg, 1063
pRegDTMFEvents
pack_voice_SLQSVoiceIndicationRegister_t, 834
voiceIndicationRegisterInfo, 1646
pRegInd
_getTransLayerInfoResp, 72
sms_getTransLayerInfo, 1054
pRegMgrConfigEvents
imsCfgIndRegisterInfo, 358
pRegStatus
_getTransNWRegInfoResp, 73
sms_getTransNWRegInfo, 1055
pRegStatusConfig
IMSAIndRegisterInfo, 350
pRegStatusErrorCode
imsaRegStatusInfo, 352
pRegTransLayerInfoEvt
_getIndicationRegResp, 70
_setIndicationRegReq, 88
sms_getIndicationReg, 1053
sms_setIndicationReg, 1063
pRegTransNWRegInfoEvt
_getIndicationRegResp, 70
_setIndicationRegReq, 88
sms_getIndicationReg, 1053
sms_setIndicationReg, 1063
pRegVoicePrivacyEvents
pack_voice_SLQSVoiceIndicationRegister_t, 834
voiceIndicationRegisterInfo, 1646
pRejectReason
pack_swioma_SLQSOMADMSendSelection_t, 810
pRelValidity
cdmaMsgEncodingParams, 188
pRelativeValidity
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pRemainingRetries
UIMDepersonalizationResp, 1174
UIMPinResp, 1180
UIMPinRespV2, 1181
unpack_uim_ChangePin_t, 1455
unpack_uim_SetPinProtection_t, 1459
unpack_uim_SLQSUIMDepersonalization_t, 1461
unpack_uim_UnblockPin_t, 1466
unpack_uim_UnblockPinV2_t, 1467
unpack_uim_VerifyPin_t, 1468
pRemotePartyName
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
voiceCallInfoResp, 1622
pRemotePartyNum
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
voiceCallInfoResp, 1622
pReportChannelRate
getDUNCallInfoReq, 300
pack_wds_SLQSGetDUNCallInfo_t, 856
pReportConnStatus
getDUNCallInfoReq, 300
pack_wds_SLQSGetDUNCallInfo_t, 856
pReportDataBearerTech
getDUNCallInfoReq, 300
pack_wds_SLQSGetDUNCallInfo_t, 856
pReportDormStatus
getDUNCallInfoReq, 300
pack_wds_SLQSGetDUNCallInfo_t, 856
pReq
SetLocGetServerCallbackPara, 1010
SetLocSetServerCallbackParam, 1011
SLQSTmdMitigationLvlRptCallbackParam, 1049
pReqFieldsList
IMSASupportedFieldsResp, 355
pReqMitigationLvl
TmdGetMitigationLvlResp, 1136
pReqSettings
pack_wds_SLQSGetRuntimeSettings_t, 858
pRequestOptionList
pack_wds_SLQSSSetDHCPv4ClientConfig_t, 863
unpack_wds_SLQSSGetDHCPv4ClientConfig_t, 1555
WdsDHCPv4Config, 1705
pRequestedTag
pack_sms_SLQSGetSMSList_t, 800
pRespData
USSDRespFNetwork, 1566
pRespFieldsList
IMSASupportedFieldsResp, 355
pRetryCount
_SLQSOMADMSessionInfo, 104
pRetryInterval
pack_wds_SetMobileIPParameters_t, 851
pRetryLimit
pack_wds_SetMobileIPParameters_t, 851
pRetryMessage
slqssendasyncsmsparams_s, 1041
sms_sendAsyncsmsParams, 1062
pRetryMessageId
slqssendasyncsmsparams_s, 1041
sms_sendAsyncsmsParams, 1062
pRevInUse
CDMASysInfo, 193
nas_CDMASysInfo, 485
pRevInUseValid
CDMASysInfo, 194
nas_CDMASysInfo, 485
pRevTunneling
pack_wds_SetMobileIPProfile_t, 853
pRfBandInfoExtFormat

NasGetRFInfoResp, 637
QmiNasGetRFBandInfoResp, 946
unpack_nas_SLQSNasGetRFInfo_t, 1358
pRfBandInfoExtFormatParam
nas_RfBandInfoExtFormat, 585
RfBandInfoExtFormat, 968
pRfBandwidthInfo
NasGetRFInfoResp, 637
QmiNasGetRFBandInfoResp, 946
unpack_nas_SLQSNasGetRFInfo_t, 1358
pRfBandwidthInfoParam
nas_RfBandwidthInfo, 587
RfBandwidthInfo, 970
pRfDedicatedBandInfo
NasGetRFInfoResp, 637
QmiNasGetRFBandInfoResp, 946
unpack_nas_SLQSNasGetRFInfo_t, 1358
pRfDedicatedBandInfoParam
nas_RfDedicatedBandInfo, 588
RfDedicatedBandInfo, 971
pRingBackTimer
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pRingingTimer
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pRoamPref
_sysSelectPrefInfo, 119
_sysSelectPrefParams, 126
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 780
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pRoamTimer
pack_voice_SLQSVoiceGetConfig_t, 833
voiceGetConfigReq, 1643
pRoamTimerCnt
unpack_voice_SLQSVoiceGetConfig_t, 1498
voiceGetConfigResp, 1645
pRoamTimerConfig
pack_voice_SLQSVoiceSetConfig_t, 839
voiceSetConfigReq, 1658
pRoamTimerStatus
unpack_voice_SLQSVoiceSetConfig_t, 1502
voiceSetConfigResp, 1659
pRoaming
pack_nas_SetCDMANetworkParameters_t, 745
QmiNas3GppNetworkInfo, 945
pRscp
nasSigInfo, 673
unpack_nas_SLQSNasSigInfoCallback_ind_t, 1365
pRxFilter
swiQosModifyReq, 1115
swiQosReq, 1116
pRxFlow
swiQosGranted, 1114
swiQosModifyReq, 1115
swiQosReq, 1116
pRxQFilter
QosFlowInfo, 957
pRxQFlowGranted
QosFlowInfo, 957
PSDetachReq, 907
pDetachAction, 907
PSDomain
unpack_nas_GetServingNetwork_t, 1317
pSID
unpack_nas_GetHomeNetwork3GPP2_t, 1311
pSIODataPort
pack_qos_BindDataPort_t, 793
pSIPConfigEvents
imsCfgIndRegisterInfo, 358
pSIPLocalPort
GetSIPConfigResp, 318
imsSIPConfigInfo, 360
SetSIPConfigReq, 1023
PSMActiveTimerTlv, 907
activeTimer, 907
TlvPresent, 907
PSMCfgChangeInfo
pack_dms_SetIndicationRegister_t, 712
PSMDurationDueToOOSTlv, 908
durationDueToOOS, 908
TlvPresent, 908
PSMDurationThresholdTlv, 908
durationThreshold, 908
TlvPresent, 908
PSMEarlyWakeupTimeTlv, 909
earlyWakeupTime, 909
TlvPresent, 909
PSMEnableStateTlv, 909
enableState, 909
TlvPresent, 909
PSMPeriodicUpdateTimerTlv, 910
periodicUpdateTimer, 910
TlvPresent, 910
PSMRandomizationWindowTlv, 910
randomizationWindow, 910
TlvPresent, 910
pSMSAttemptedFlag
getDyingGaspStatistics, 304
packgetDyingGaspStatistics, 869
pSMSCAddress
pack_sms_SetSMSCAddress_t, 797
unpack_sms_GetSMSCAddress_t, 1423
pSMSCAddressInfo
SMSEventInfo_s, 1071
pSMSCType
pack_sms_SetSMSCAddress_t, 797
unpack_sms_GetSMSCAddress_t, 1423
pSMSConfigEvents
imsCfgIndRegisterInfo, 358

pSMSFormat
GetIMSSMSConfigParams, 307
imsSMSConfigInfo, 360
SetIMSSMSConfigReq, 1004
pSMSOnIMSInfo
SMSEventInfo_s, 1072
pSMSOverIPNwInd
GetIMSSMSConfigParams, 307
imsSMSConfigInfo, 360
SetIMSSMSConfigReq, 1004
pSMSSupport
custFeaturesInfo, 226
pSMSSvcRAT
imsaSvcStatusInfo, 356
pSMSSvcStatus
imsaSvcStatusInfo, 356
PSMStatus
pack_dms_SetIndicationRegister_t, 712
pSPC
pack_nas_SetCDMANetworkParameters_t, 745
pack_wds_SetMobileIPParameters_t, 851
pSV
BdsSVInfo, 158
loc_BdsSVInfo, 406
loc_SVInfo, 420
SVInfo, 1090
pSVInfo
LocDelAssDataReq, 424
pack_loc_Delete_Assist_Data_t, 726
pSWVerString
_SLQSSwiGetHostDevInfoParams, 109
_SLQSSwiSetHostDevInfoParams, 112
pSarRFState
unpack_sar_SLQSGetRfSarState_t, 1422
pSatelliteInfo
gnssSvInfoNotification, 321
unpack_loc_GnssSvInfo_Ind_t, 1288
pScAddr
wcdmaLongMsgDecodingParams, 1672
pScAddrLength
wcdmaLongMsgDecodingParams, 1672
wcdmaMsgDecodingParams, 1673
pScanResult
_slqsNetworkScanInfo, 99
unpack_nas_PerformNetworkScan_t, 1320
pScanType
_slqsNetworkScanInfoReq, 102
pack_nas_PerformNetworkScanPCI_t, 743
pSccRxInfo
LteSccRxInfoResp, 456
unpack_nas_SLQSSwiGetLteSccRxInfo_t, 1373
pScrAmrEnable
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pScrAmrWbEnable
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pSeDNSIPv4Address
swiPDPRuntimeSettingsResp, 1108
pSeDNSIPv6Address
swiPDPRuntimeSettingsResp, 1108
pSePCSCFIPv4Address
swiPDPRuntimeSettingsResp, 1108
pSePCSCFIPv6Address
swiPDPRuntimeSettingsResp, 1108
pSecDNSIPv4AddPref
LibpackProfile3GPP, 379
LibPackprofile_3GPP, 391
Profile3GPP, 899
pSecDNSIPv6addpref
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 391
Profile3GPP, 899
pSecV6DnsAddress
LibpackProfile3GPP2, 386
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pSecondaryDNSV4
qmiWdsRunTimeSettings, 952
pSecondaryDNSV6
qmiWdsRunTimeSettings, 952
pSecondaryFlag
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 391
Profile3GPP, 899
pSecondaryHA
pack_wds_SetMobileIPProfile_t, 853
pSecondaryV4DnsAddress
LibpackProfile3GPP2, 386
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pSectorID
nas_NetworkStatEVDO, 556
NetworkStatEVDO, 687
pSendSmsParams
pack_sms_SLQSSendAsyncSMS_t, 801
pSenderAddr
cdmaMsgDecodingParamsExt, 186
wcdmaLongMsgDecodingParams, 1672
pSenderAddrLength
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
wcdmaLongMsgDecodingParams, 1672
wcdmaMsgDecodingParams, 1673
pSensorDataUsage
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pServerAddrList
qmiWdsRunTimeSettings, 952
pServerAddrTypeMask
LocGetServerReq, 427
pServerAddress

pack_pds_SLQSSetAGPSConfig_t, 789
unpack_pds_SLQSGetAGPSConfig_t, 1392
pServerPort
pack_pds_SLQSSetAGPSConfig_t, 789
unpack_pds_SLQSGetAGPSConfig_t, 1392
pServerURL
pack_pds_SLQSSetAGPSConfig_t, 789
unpack_pds_SLQSGetAGPSConfig_t, 1392
pServerURLLength
pack_pds_SLQSSetAGPSConfig_t, 789
unpack_pds_SLQSGetAGPSConfig_t, 1392
pServiceClass
pack_voice_SLQSVoiceSetSUPSService_t, 841
voiceSetSUPSServiceReq, 1662
pServiceOption
slqssendasyncsmsparams_s, 1041
sms_sendAsyncsmsParams, 1062
pServiceStatusConfig
IMSAIndRegisterInfo, 350
pServingSystemInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 759
pSessionExpiryTimer
GetIMSVoIPConfigResp, 310
imsVoIPConfigInfo, 363
SetIMSVoIPConfigReq, 1008
pSessionIDv4
GetSessionIDResp, 317
pSessionIDv6
GetSessionIDResp, 317
pSessionState
_SLQSOMADMSessionInfo, 104
pSessionType
_SLQSOMADMSessionInfo, 104
pSetIndicationRegReq
pack_sms_SLQSSetIndicationRegister_t, 802
pSetRoutesReq
pack_sms_SLQSSmsSetRoutes_t, 804
pSettingResp
GetIMSSMSConfigParams, 307
GetIMSUserConfigParams, 308
GetIMSVoIPConfigResp, 310
GetRegMgrConfigParams, 317
GetSIPConfigResp, 318
SetIMSSMSConfigResp, 1005
SetIMSUserConfigResp, 1006
SetIMSVoIPConfigResp, 1009
SetRegMgrConfigResp, 1017
SetSIPConfigResp, 1023
pSeverity
_SLQSOMADMSessionInfo, 104
pSigCompEnabled
GetSIPConfigResp, 318
imsSIPConfigInfo, 360
SetSIPConfigReq, 1023
pSigIndReq
pack_nas_SLQSSetSignalStrengthsCallback_t, 764
pSignalInfo
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
voiceInfoRec, 1649
pSignalStrengthInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 759
pSimBusyStatus
UIMGetCardStatusRespV2, 1176
unpack_uim_GetCardStatusV2_t, 1457
pSmsOnIms
slqssendasyncsmsparams_s, 1041
slqssendsmsparams_s, 1042
sms_sendAsyncsmsParams, 1062
pSmsServiceRat
IMSAServiceStatus, 354
pSmsServiceStatus
IMSAServiceStatus, 354
pSmsStorage
unpack_sms_SLQSSwiGetSMSStorage_t, 1437
pSource
_SLQSOMADMSessionInfo, 104
pSourceIP
LibPackTFTIDParams, 400
TFTIDParams, 1132
pSourceLength
_SLQSOMADMSessionInfo, 104
pSpeedHorizontal
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pSpeedUnc
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pSpeedVertical
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pSpeedVerticalUnc
QmiCbkLocBestAvailPosInd, 921
unpack_loc_BestAvailPos_Ind_t, 1280
pSrcRAT
imsaRatStatusInfo, 351
pSrvDomainPref
_sysSelectPrefInfo, 119
_sysSelectPrefParams, 126
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 780
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1350
pSrvOpt
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
voiceCallInfoResp, 1623
pSrvRegRestriction

_sysSelectPrefParams, 126
pack_nas_SLQSSetSysSelectionPref_t, 769
pack_nas_SLQSSetSysSelectionPrefExt_t, 780
pSrvcProviderName
nasOperatorNameResp, 655
unpack_nas_SLQSGetOperatorNameData_t, 1328
pStage0Val
RXPCMIIRFltr, 981
TXPCMIIRFltr, 1144
pStage1Val
RXPCMIIRFltr, 981
TXPCMIIRFltr, 1144
pStage2Val
RXPCMIIRFltr, 981
TXPCMIIRFltr, 1144
pStage3Val
RXPCMIIRFltr, 981
TXPCMIIRFltr, 1144
pStage4Val
RXPCMIIRFltr, 981
TXPCMIIRFltr, 1144
pStageCnt
RXPCMIIRFltr, 981
TXPCMIIRFltr, 1144
pStatMask
pack_wds_GetPacketStatistics_t, 845
WdsPktStatisticsReq, 1713
pStatus
_SLQSOMADMSessionInfo, 104
pSubnetMaskV4
qmiWdsRunTimeSettings, 952
pSubscribeTimer
GetSIPConfigResp, 318
imsSIPConfigInfo, 360
SetSIPConfigReq, 1023
pSubscriptionInfoInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 759
pSupUSBComps
USBCompParams, 1564
pSupportEmergencyCalls
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 391
Profile3GPP, 899
pSupportedBitmasks
SwiDmsGetUsbCompResp, 1099
unpack_swidms_SLQSSwiDmsGetUsbComp_t, 1444
pSupportedMsgList
IMSASupportedMsgInfo, 356
pSuppressSysInfoInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 759
pSuppsNotifEvents
pack_voice_SLQSVoiceIndicationRegister_t, 834
voiceIndicationRegisterInfo, 1646
pSvUsedforFix
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pSvcClass
pack_voice_SLQSVoiceGetCallBarring_t, 830
pack_voice_SLQSVoiceGetCallForwardingStatus-_t, 831
pack_voice_SLQSVoiceGetCallWaiting_t, 832
unpack_voice_SLQSVoiceGetCallBarring_t, 1483
unpack_voice_SLQSVoiceGetCallWaiting_t, 1489
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceGetCallBarringReq, 1631
voiceGetCallBarringResp, 1632
voiceGetCallFWReq, 1633
voiceGetCallWaitInfo, 1636
voiceSUPSInfo, 1666
pSvcType
pack_voice_SLQSVoiceDialCall_t, 829
voiceCallRequestParams, 1624
pSwiGetResetInd
dmsIndicationRegisterReq, 258
pSysInfoInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 759
pSysInfoNoChange
nasSysInfo, 679
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pSysSelectPrefInfo
_sysSelectPrefExtInfo, 115
pSysSelectPrefParams
sysSelectPrefParamsExt, 1123
pSystemSelectionInd
nasIndicationRegisterReq, 646
pack_nas_SLQSNasIndicationRegisterExt_t, 759
pTCPDstPort
swiQosFilter, 1110
pTCPSrcPort
swiQosFilter, 1110
pTDSCDMAECIODelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pTDSCDMAECIOThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pTDSCDMAECIOThreshList
nas_TDSCDMAECIOThresh, 609
TDSCDMAECIOThresh, 1124
pTDSCDMARSCPDelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pTDSCDMARSCPThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pTDSCDMARSCPThreshList
nas_TDSCDMARSCPThresh, 609
TDSCDMARSCPThresh, 1125
pTDSCDMARSSIDelta

pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1021
pTDSCDMARSSIThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1022
pTDSCDMARSSIThreshList
nas_TDSCDMARSSIThresh, 610
TDSCDMARSSIThresh, 1125
pTDSCDMASINRCONFThresh
sigInfo, 1026
pTDSCDMASINRDelta
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1022
pTDSCDMASINRThresh
pack_nas_SLQSNasConfigSigInfo2_t, 753
setSignalStrengthInfo, 1022
pTDSCDMASINRThreshList
nas_TDSCDMASINRThresh, 611
TDSCDMASINRThresh, 1128
pTDSCDMASigInfoExt
nasGetSigInfoResp, 638
nasSigInfo, 673
unpack_nas_SLQSNasSigInfoCallback_ind_t, 1365
pTDSCDMASigInfoRscp
nasGetSigInfoResp, 638
pTFTID1Params
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 391
Profile3GPP, 899
pTFTID2Params
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 392
Profile3GPP, 899
pTTYConfigStatus
unpack_voice_SLQSVoiceSetConfig_t, 1502
voiceSetConfigResp, 1659
pTTYMode
pack_voice_SLQSVoiceGetConfig_t, 833
pack_voice_SLQSVoiceSetConfig_t, 839
voiceGetConfigReq, 1644
voiceSetConfigReq, 1658
pTXAGCList
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pTXAIG
TXAGCList, 1142
pTXAVCSwitch
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pTXComprSlope
TXAGCList, 1142
pTXComprThres
TXAGCList, 1142
pTXDroppedCount
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pTXExpSlope
TXAGCList, 1142
pTXExpThres
TXAGCList, 1142
pTXGain
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pTXInfo
nasGetTxRxInfoResp, 643
unpack_nas_SLQSNasGetTxRxInfo_t, 1360
pTXOKBytesCount
getDUNCallInfoResp, 303
pTXOKBytesLastCall
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pTXOkBytesCount
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pTXPCMIIRFltr
GetAudioPathConfigResp, 294
SetAudioPathConfigReq, 1000
pTXPacketErrors
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pTXPacketOverflows
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pTXPacketSuccesses
unpack_wds_GetPacketStatistics_t, 1527
WdsPktStatisticsElmnts, 1712
pTXStaticGain
TXAGCList, 1142
pTXTotalBytes
unpack_wds_GetByteTotals_t, 1516
WdsByteTotalsElmnts, 1701
pTdsBandCapability
BandCapabilityResp, 156
pTdscdmaBandPref
_sysSelectPrefParams, 126
pack_nas_SLQSSetSysSelectionPref_t, 770
pack_nas_SLQSSetSysSelectionPrefExt_t, 780
pTech
pack_wds_SLQSStartDataSession_t, 864
pTechnology
qmiWdsRunTimeSettings, 952
ssdatasession_params, 1086
pTechnologyMask
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pTempReport
pack_dms_SwiSetEventReport_t, 718
pTextMsg
cdmaMsgDecodingParamsExt, 186
cdmaMsgEncodingParams, 188
wcdmaLongMsgDecodingParams, 1672
wcdmaMsgEncodingParams, 1675
pTextMsgLength

cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
wcdmaLongMsgDecodingParams, 1672
wcdmaMsgDecodingParams, 1673
pTgtRAT
imsaRatStatusInfo, 351
pTime
_SLQSOMADMSessionInfo, 104
SwiOTAMsg_s, 1105
pTimeLength
_SLQSOMADMSessionInfo, 104
pTimeSrc
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 936
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pTimeStamp
getDyingGaspStatistics, 305
pack_pds_SLQSPDSInjectPositionData_t, 788
packgetDyingGaspStatistics, 869
PDSPositionData, 873
pTimeType
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
pTimeUnc
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 937
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pTimeZone
nasNetworkTime, 654
unpack_nas_SLQSNasNetworkTimeCallBack_ind_t, 1364
pTimeout
unpack_pds_GetPDSDefaults_t, 1384
pTimer
NasSwiIndReg, 675
pack_nas_SLQSNasSwiIndicationRegister_t, 762
pTimerSIPReg
GetSIPConfigResp, 318
imsSIPConfigInfo, 360
SetSIPConfigReq, 1023
pTimerT1
GetSIPConfigResp, 318
imsSIPConfigInfo, 360
SetSIPConfigReq, 1023
pTimerT2
GetSIPConfigResp, 318
imsSIPConfigInfo, 360
SetSIPConfigReq, 1023
pTimerTf
GetSIPConfigResp, 318
imsSIPConfigInfo, 360
SetSIPConfigReq, 1023
pTimerVal
pack_voice_SLQSVoiceSetSUPSService_t, 841
voiceSetSUPSServiceReq, 1662
pTimestampAge
LocInjectPositionReq, 431
pTimestampUtc
LocInjectPositionReq, 431
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 937
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1298
pTokenBucket
swiQosFlow, 1114
pTos
swiQosFilter, 1110
pTotalBytesRX
QosEventInfo, 956
slqsWdsEventInfo, 1051
pTotalBytesTX
QosEventInfo, 956
slqsWdsEventInfo, 1051
pTotalNum
cdmaMsgDecodingParamsExt, 186
wcdmaLongMsgDecodingParams, 1672
pTrackingStatus
unpack_pds_GetPDSState_t, 1385
pTrafficClass
swiQosFlow, 1114
pTranDstPort
swiQosFilter, 1110
pTranSrcPort
swiQosFilter, 1110
pTransLayerInfo
_getTransLayerInfoResp, 72
_transLayerInfoNotification, 127
sms_getTransLayerInfo, 1054
unpack_sms_SLQSTransLayerInfoCallback_ind_t, 1438
pTransferRouteMTMessageInfo
SMSEventInfo_s, 1072
pTransferStatInd
getDUNCallInfoReq, 300
pack_wds_SLQSGetDUNCallInfo_t, 856
pack_wds_SLQSWdsSetEventReport_t, 867
wdsSetEventReportReq, 1717
pTransferStatusReport
sms_setRoutesReq, 1063
smsSetRoutesReq, 1079
pTrueIMSI
nasGet3GPP2SubscriptionInfoResp, 630
unpack_nas_SLQSNasGet3GPP2Subscription_t, 1352
pTxFilter
swiQosModifyReq, 1115
swiQosReq, 1116
pTxFlow
swiQosGranted, 1114
swiQosModifyReq, 1115
swiQosReq, 1116
pTxQFilter
QosFlowInfo, 957
pTxQFlowGranted

QosFlowInfo, 957
pTypeCode
USSDRespFNetwork, 1566
pUATI
GetHRPDStatsResp, 306
unpack_nas_SLQSSwiGetHRPDStats_t, 1372
pUDPDstPort
swiQosFilter, 1110
pUDPSrcPort
swiQosFilter, 1110
pUIMStatusReport
pack_dms_SwiSetEventReport_t, 718
pUMTSCellID
nasCellLocationInfoResp, 628
unpack_nas_SLQSNasGetCellLocationInfo_t, 1354
pUMTSGrantedQoS
qmiWdsRunTimeSettings, 952
pUMTSInfo
nasCellLocationInfoResp, 628
unpack_nas_SLQSNasGetCellLocationInfo_t, 1354
pUMTSMinQoS
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 392
Profile3GPP, 899
pUMTSMinQosSigInd
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 392
Profile3GPP, 899
pUMTSReqQoS
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 392
Profile3GPP, 899
pUMTSReqQoSSigInd
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 392
Profile3GPP, 899
pURL
QmiCbkLocGetServerInd, 926
unpack_loc_GetServer_Ind_t, 1287
pURLAddr
LocSetServerReq, 434
pack_loc_SLQSLOCSetServer_t, 740
pUSBComp
USBCompConfig, 1562
USBCompParams, 1564
pUSSDData
USSDNoWaitIndicationInfo, 1565
pUSSDInfo
unpack_voice_SLQSOriginateUSSD_t, 1475
USSResp, 1567
pUSSInfo
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
pUTSvcRAT
imsaSvcStatusInfo, 356
pUTSvcStatus
imsaSvcStatusInfo, 356
pUUSInFo
pack_voice_SLQSVoiceDialCall_t, 829
voiceCallRequestParams, 1624
pUUSInfo
unpack_voice_SLQSVoiceGetCallInfo_t, 1488
voiceCallInfoResp, 1623
pUimAutoSwitchActSlot
dmsSwiGetUIMSelection, 261
unpack_dms_SLQSDmsSwiGetUimSelection_t, 1246
pUimSlotsStatus
UIMGetSlotsStatusResp, 1179
unpack_uim_SLQSUIMGetSlotsStatus_t, 1464
pUname
_SLQSAVMSSettingsAPNInfo, 96
pUpdateCompleteStatus
_SLQSOMADMSessionInfo, 104
pUsbMTUSize
SwiDmsGetMTUResp, 1098
unpack_swidms_SLQSSwiDmsGetMTU_t, 1443
pUser
pack_wds_SLQSStartDataSession_t, 864
pUserAcknowledgementReq
cdmaMsgDecodingParams, 183
cdmaMsgDecodingParamsExt, 186
pUserConfigEvents
imsCfgIndRegisterInfo, 358
pUserData
slqssendasyncsmsparams_s, 1041
sms_sendAsyncsmsParams, 1062
pUserId
LibpackProfile3GPP2, 386
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pUserIdSize
LibpackProfile3GPP2, 386
LibPackprofile_3GPP2, 397
Profile3GPP2, 904
pUsername
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 392
pack_wds_SetDefaultProfile_t, 849
Profile3GPP, 899
qmiWdsRunTimeSettings, 952
ssdatasession_params, 1086
pUsernameSize
LibpackProfile3GPP, 380
LibPackprofile_3GPP, 392
Profile3GPP, 899
pUtServiceRat
IMSAServiceStatus, 354
pUtServiceStatus
IMSAServiceStatus, 354
pV4sessionId
WdsByteTotals, 1701
WdsConnectionRate, 1702

WdsPktStatisticsResp, 1713
pV6sessionId
WdsByteTotals, 1701
WdsConnectionRate, 1702
WdsPktStatisticsResp, 1713
pVOIPSvcRAT
imsaSvcStatusInfo, 356
pVOIPSvcStatus
imsaSvcStatusInfo, 357
pVTSvcRAT
imsaSvcStatusInfo, 357
pVTSvcStatus
imsaSvcStatusInfo, 357
pValidCardStatus
UIMGetCardStatusRespV2, 1176
unpack_uim_GetCardStatusV2_t, 1457
pVerboseFailReasonType
unpack_wds_SLQSStartDataSession_t, 1557
pVerboseFailureReason
unpack_wds_SLQSStartDataSession_t, 1557
pVersionString
_SLQSSwiGetOSInfoParams, 110
_SLQSSwiSetOSInfoParams, 112
pVertConfidence
LocInjectPositionReq, 431
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 937
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1299
pVertReliability
LocInjectPositionReq, 431
QmiCbkLocBestAvailPosInd, 921
QmiCbkLocPositionReportInd, 937
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1299
pVertUnc
LocInjectPositionReq, 431
QmiCbkLocBestAvailPosInd, 922
QmiCbkLocPositionReportInd, 937
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_PositionRpt_Ind_t, 1299
pVerticalConfidence
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
pVerticalUnc
pack_pds_SLQSPDSInjectPositionData_t, 788
PDSPositionData, 873
pVoIPConfigEvents
imsCfgIndRegisterInfo, 358
pVoiceDomainPref
pack_voice_SLQSVoiceGetConfig_t, 833
voiceGetConfigReq, 1644
pVoiceDomainPrefStatus
unpack_voice_SLQSVoiceSetConfig_t, 1502
voiceSetConfigResp, 1659
pVoicePrivacy
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
unpack_voice_SLQSVoiceGetCallInfo_t, 1488
voiceCallInfoResp, 1623
voiceGetAllCallInfo, 1630
pVoipServiceRat
IMSAServiceStatus, 354
pVoipServiceStatus
IMSAServiceStatus, 354
pVoltReport
pack_dms_SwiSetEventReport_t, 718
pVolume
SetM2MAudioProfileReq, 1013
pVsServiceRat
IMSAServiceStatus, 354
pVsServiceStatus
IMSAServiceStatus, 354
pVtServiceRat
IMSAServiceStatus, 354
pVtServiceStatus
IMSAServiceStatus, 355
pWCDMABER
GetErrRateResp, 305
unpack_nas_SLQSGetErrorRate_t, 1326
pWCDMACallBarringSysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pWCDMACipherDomainSysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pWCDMAECIODelta
pack_nas_SLQSNasConfigSigInfo2_t, 754
setSignalStrengthInfo, 1022
pWCDMAECIOThresh
pack_nas_SLQSNasConfigSigInfo2_t, 754
setSignalStrengthInfo, 1022
pWCDMAECIOThreshList
nas_WCDMAECIOThresh, 620
WCDMAECIOThresh, 1669
pWCDMAInfoLTENeighborCell
nasCellLocationInfoResp, 628
unpack_nas_SLQSNasGetCellLocationInfo_t, 1354
pWCDMARSSIDelta
pack_nas_SLQSNasConfigSigInfo2_t, 754
setSignalStrengthInfo, 1022
pWCDMARSSIThresh
pack_nas_SLQSNasConfigSigInfo2_t, 754
setSignalStrengthInfo, 1022
pWCDMARSSIThreshList
nas_WCDMARSSIThresh, 622
WCDMARSSIThresh, 1675
pWCDMASSInfo
nasGetSigInfoResp, 638
pWCDMASigInfo
nasSigInfo, 673

unpack_nas_SLQSNasSigInfoCallback_ind_t, 1366
pWCDMASrvStatusInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1343
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pWCDMASysInfo
nasGetSysInfoResp, 641
nasSysInfo, 679
unpack_nas_SLQSGetSysInfo_t, 1343
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
pWcdmaUARFCN
nasSwiGetChannelLockResp, 674
nasSwiSetChannelLockReq, 676
pack_nas_SLQSNASSwiSetChannelLock_t, 762
unpack_nas_SLQSNASSwiGetChannelLock_t, 1366
pWdisable
dmsSwiGetPCInfo, 260
pWifiState
pack_pds_SLQSSetPositionMethodState_t, 790
PDSPosMethodStateReq, 874
pXid
QmiCbkLocBestAvailPosInd, 922
unpack_loc_BestAvailPos_Ind_t, 1280
pXtraDataState
pack_pds_SLQSSetPositionMethodState_t, 790
PDSPosMethodStateReq, 874
pXtraTimeState
pack_pds_SLQSSetPositionMethodState_t, 790
PDSPosMethodStateReq, 874
pack_dms_ActivateAutomatic
dms.h, 1734
pack_dms_ActivateAutomatic_t, 706
actCode, 706
pack_dms_GetActivationState
dms.h, 1734
pack_dms_GetBandCapability
dms.h, 1735
pack_dms_GetCrashAction
dms.h, 1735
pack_dms_GetCustFeature
dms.h, 1735
pack_dms_GetCustFeaturesV2
dms.h, 1736
pack_dms_GetCustFeaturesV2_t, 706
cust_id, 707
list_type, 707
Tlvresult, 707
pack_dms_GetDeviceCap
dms.h, 1736
pack_dms_GetDeviceCapabilities
dms.h, 1737
pack_dms_GetDeviceHardwareRev
dms.h, 1737
pack_dms_GetDeviceMfr
dms.h, 1737
pack_dms_GetDeviceSerialNumbers
dms.h, 1738
pack_dms_GetFSN
dms.h, 1739
pack_dms_GetFirmwareInfo
dms.h, 1738
pack_dms_GetFirmwareRevision
dms.h, 1738
pack_dms_GetFirmwareRevisions
dms.h, 1739
pack_dms_GetHardwareRevision
dms.h, 1739
pack_dms_GetIMSI
dms.h, 1740
pack_dms_GetManufacturer
dms.h, 1740
pack_dms_GetModelID
dms.h, 1740
pack_dms_GetNetworkTime
dms.h, 1741
pack_dms_GetOfflineReason
dms.h, 1741
pack_dms_GetPRLVersion
dms.h, 1742
pack_dms_GetPower
dms.h, 1741
pack_dms_GetSerialNumbers
dms.h, 1742
pack_dms_GetUSBComp
dms.h, 1742
pack_dms_GetVoiceNumber
dms.h, 1743
pack_dms_ResetToFactoryDefaults
dms.h, 1743
pack_dms_ResetToFactoryDefaults_t, 707
spc, 707
pack_dms_SLQSDmsSwiGetPCInfo
dms.h, 1747
pack_dms_SLQSDmsSwiGetResetInfo
dms.h, 1747
pack_dms_SLQSDmsSwiGetUimSelection
dms.h, 1748
pack_dms_SLQSDmsSwiIndicationRegister
dms.h, 1748
pack_dms_SLQSDmsSwiIndicationRegister_t, 714
resetInfoInd, 715
pack_dms_SLQSGetBandCapability
dms.h, 1748
pack_dms_SLQSGetERIFile
dms.h, 1749
pack_dms_SLQSGetPowerSaveModeConfig
dms.h, 1749
pack_dms_SLQSSetPowerSaveModeConfig
dms.h, 1749
pack_dms_SLQSSetPowerSaveModeConfig_t, 715
pActiveTimer, 715
pPeriodicUpdateTimer, 715
pPsmEnableState, 715

pack_dms_SLQSSwiClearDyingGaspStatistics
dms.h, 1750
pack_dms_SLQSSwiGetCrashInfo
dms.h, 1750
pack_dms_SLQSSwiGetCrashInfo_t, 715
clear, 716
pack_dms_SLQSSwiGetDyingGaspCfg
dms.h, 1751
pack_dms_SLQSSwiGetDyingGaspStatistics
dms.h, 1751
pack_dms_SLQSSwiGetFirmwareCurr
dms.h, 1751
pack_dms_SLQSSwiGetFwUpdateStatus
dms.h, 1752
pack_dms_SLQSSwiGetHostDevInfo
dms.h, 1752
pack_dms_SLQSSwiGetOSInfo
dms.h, 1752
pack_dms_SLQSSwiGetSerialNoExt
dms.h, 1753
pack_dms_SLQSSwiSetDyingGaspCfg
dms.h, 1753
pack_dms_SLQSSwiSetDyingGaspCfg_t, 716
pDestSMSContent, 716
pDestSMSNum, 716
pack_dms_SLQSSwiSetHostDevInfo
dms.h, 1753
pack_dms_SLQSSwiSetHostDevInfo_t, 716
hostID, 717
manString, 717
modelString, 717
plasmaIDString, 717
swVerString, 717
pack_dms_SLQSSwiSetOSInfo
dms.h, 1754
pack_dms_SLQSSwiSetOSInfo_t, 717
nameString, 718
versionString, 718
pack_dms_SLQSUIMGetState
dms.h, 1754
pack_dms_SetActivationStatusCallback
dms.h, 1744
pack_dms_SetActivationStatusCallback_t, 707
activationState, 708
pack_dms_SetCrashAction
dms.h, 1744
pack_dms_SetCrashAction_t, 708
crashAction, 708
pack_dms_SetCustFeature
dms.h, 1744
pack_dms_SetCustFeature_t, 708
DHCPRelayEnabled, 710
DisableIMSI, 710
GPSLPM, 710
GPSSel, 710
GpsEnable, 710
IPFamSupport, 710
IsVoiceEnabled, 710
RMAutoConnect, 710
SMSSupport, 710
pack_dms_SetCustFeaturesV2
dms.h, 1745
pack_dms_SetCustFeaturesV2_t, 710
cust_id, 711
cust_value, 711
Tlvresult, 711
value_length, 711
pack_dms_SetEventReport
dms.h, 1745
pack_dms_SetEventReport_t, 711
mode, 711
pack_dms_SetFirmwarePreference
dms.h, 1745
pack_dms_SetIndicationRegister
dms.h, 1746
pack_dms_SetIndicationRegister_t, 712
PSMCfgChangeInfo, 712
PSMStatus, 712
RptIMSCapability, 712
pack_dms_SetPower
dms.h, 1746
pack_dms_SetPower_t, 712
mode, 713
Tlvresult, 713
pack_dms_SetUSBComp
dms.h, 1746
pack_dms_SetUSBComp_t, 713
Tlvresult, 714
USBComp, 714
pack_dms_SwiSetEventReport
dms.h, 1754
pack_dms_SwiSetEventReport_t, 718
pTempReport, 718
pUIMStatusReport, 718
pVoltReport, 718
pack_dms_SwiUimSelect
dms.h, 1755
pack_dms_SwiUimSelect_t, 719
uim_select, 719
pack_dms_UIMChangePIN
dms.h, 1755
pack_dms_UIMChangePIN_t, 719
id, 720
newValue, 720
oldValue, 720
pack_dms_UIMGetControlKeyStatus
dms.h, 1755
pack_dms_UIMGetControlKeyStatus_t, 720
facility, 720
pack_dms_UIMGetICCID
dms.h, 1756
pack_dms_UIMGetICCID_t, 720
ParamPresenceMask, 720
Tlvresult, 721
pack_dms_UIMGetPINStatus
dms.h, 1756

pack_dms_UIMSetControlKeyProtection
dms.h, 1757
pack_dms_UIMSetControlKeyProtection_t, 721
facility, 721
facilityCk, 721
facilityState, 721
pack_dms_UIMSetPINProtection
dms.h, 1757
pack_dms_UIMSetPINProtection_t, 721
bEnable, 722
id, 722
value, 722
pack_dms_UIMUnblockControlKey
dms.h, 1757
pack_dms_UIMUnblockControlKey_t, 722
facility, 722
facilityCk, 723
pack_dms_UIMUnblockPIN
dms.h, 1758
pack_dms_UIMUnblockPIN_t, 723
id, 723
newPin, 723
pukValue, 723
pack_dms_UIMVerifyPIN
dms.h, 1758
pack_dms_UIMVerifyPIN_t, 723
id, 724
value, 724
pack_dms_ValidateSPC
dms.h, 1758
pack_fms_GetImagesPreference
fms.h, 1786
pack_fms_GetImagesPreference_t, 724
Tlvresult, 724
pack_fms_GetStoredImages
fms.h, 1787
pack_fms_GetStoredImages_t, 724
Tlvresult, 725
pack_fms_SetImagesPreference
fms.h, 1787
pack_fms_SetImagesPreference_t, 725
bForceDownload, 725
imageListSize, 725
modemindex, 725
pImageList, 725
Tlvresult, 725
pack_loc_Delete_Assist_Data_t, 725
pBdsSVInfo, 726
pCellDb, 726
pClkInfo, 726
pGnssData, 726
pSVInfo, 726
Tlvresult, 726
pack_loc_DeleteAssistData
loc.h, 1795
pack_loc_EventRegister
loc.h, 1795
pack_loc_EventRegister_t, 726
eventRegister, 729
Tlvresult, 729
pack_loc_SLQSLOCGetBestAvailPos
loc.h, 1796
pack_loc_SLQSLOCGetBestAvailPos_t, 730
Tlvresult, 730
xid, 730
pack_loc_SLQSLOCGetOpMode
loc.h, 1797
pack_loc_SLQSLOCGetServer
loc.h, 1797
pack_loc_SLQSLOCGetServer_t, 731
has_serverAddrTypeMask, 731
serverAddrTypeMask, 731
serverType, 731
pack_loc_SLQSLOCInjectPosition
loc.h, 1797
pack_loc_SLQSLOCInjectPosition_t, 731
altitudeSrcInfo, 735
altitudeWrtEllipsoid, 735
altitudeWrtMeanSeaLevel, 735
has_altitudeSrcInfo, 735
has_altitudeWrtEllipsoid, 735
has_horConfidence, 735
has_horReliability, 735
has_horUncCircular, 735
has_latitude, 735
has_longitude, 735
has_positionSrc, 735
has_rawHorConfidence, 735
has_rawHorUncCircular, 735
has_timestampAge, 735
has_timestampUtc, 735
has_vertConfidence, 735
has_vertRelicability, 735
has_vertUnc, 736
horConfidence, 736
horReliability, 736
horUncCircular, 736
latitude, 736
longitude, 736
positionSrc, 736
rawHorConfidence, 736
rawHorUncCircular, 736
timestampAge, 736
timestampUtc, 736
vertConfidence, 736
vertReliability, 736
vertUnc, 736
pack_loc_SLQSLOCInjectSensorData
loc.h, 1798
pack_loc_SLQSLOCInjectSensorData_t, 736
accelTemp, 737
acceleroData, 737
acceleroTimeSrc, 737
gyroData, 737
gyroTemp, 737
gyroTimeSrc, 738

has_accelTemp, 738
has_acceleroTimeSrc, 738
has_accleroData, 738
has_gyroData, 738
has_gyroTemp, 738
has_gyroTimeSrc, 738
has_opaqueId, 738
opaqueId, 738
pack_loc_SLQSLOCInjectUTCTime
loc.h, 1798
pack_loc_SLQSLOCInjectUTCTime_t, 738
timeMsec, 738
timeUncMsec, 738
pack_loc_SLQSLOCSetCradleMountConfig
loc.h, 1799
pack_loc_SLQSLOCSetCradleMountConfig_t, 738
confidence, 739
has_confidence, 739
state, 739
pack_loc_SLQSLOCSetServer
loc.h, 1799
pack_loc_SLQSLOCSetServer_t, 739
pIPv4Config, 740
pIPv6Config, 740
pURLAddr, 740
serverType, 740
pack_loc_SetExtPowerState
loc.h, 1795
pack_loc_SetExtPowerState_t, 729
extPowerState, 729
Tlvresult, 729
pack_loc_SetOperationMode
loc.h, 1796
pack_loc_SetOperationMode_t, 729
mode, 730
Tlvresult, 730
pack_loc_Start
loc.h, 1799
pack_loc_Start_t, 740
pApplicationInfo, 741
pConfigAltitudeAssumed, 741
pHorizontalAccuracyLvl, 741
pIntermediateReportState, 741
pMinIntervalTime, 741
pRecurrenceType, 741
SessionId, 742
Tlvresult, 742
pack_loc_Stop
loc.h, 1800
pack_loc_Stop_t, 742
SessionId, 742
Tlvresult, 742
pack_nas_GetACCOLC
nas.h, 1826
pack_nas_GetANAAAAuthenticationStatus
nas.h, 1827
pack_nas_GetCDMANetworkParameters
nas.h, 1827
pack_nas_GetHomeNetwork
nas.h, 1827
pack_nas_GetHomeNetwork3GPP2
nas.h, 1828
pack_nas_GetNetworkPreference
nas.h, 1828
pack_nas_GetRFInfo
nas.h, 1828
pack_nas_GetServingNetwork
nas.h, 1828
pack_nas_GetServingNetworkCapabilities
nas.h, 1829
pack_nas_GetSignalStrengths
nas.h, 1829
pack_nas_InitiateDomainAttach
nas.h, 1829
pack_nas_InitiateDomainAttach_t, 742
action, 742
pack_nas_PerformNetworkScan
nas.h, 1830
pack_nas_PerformNetworkScanPCI
nas.h, 1830
pack_nas_PerformNetworkScanPCI_t, 743
pCiotOpModePref, 743
pLteM1BandPref, 743
pLteNB1BandPref, 743
pNetworkType, 743
pScanType, 743
pack_nas_SLQSConfigSigInfo
nas.h, 1832
pack_nas_SLQSConfigSigInfo_t, 746
pECIOThresh, 747
pIOThresh, 747
pLTESNRThresh, 747
pLTESigRptCfg, 747
pRSRPThresh, 747
pRSRQThresh, 747
pRSSIThresh, 747
pack_nas_SLQSGetErrorRate
nas.h, 1833
pack_nas_SLQSGetNetworkTime
nas.h, 1833
pack_nas_SLQSGetOperatorNameData
nas.h, 1834
pack_nas_SLQSGetPLMNName
nas.h, 1834
pack_nas_SLQSGetPLMNName_t, 747
mcc, 748
mnc, 748
pMncPcsStatus, 748
pack_nas_SLQSGetServingSystem
nas.h, 1834
pack_nas_SLQSGetSignalStrength
nas.h, 1835
pack_nas_SLQSGetSysInfo
nas.h, 1835
pack_nas_SLQSGetSysSelectionPref
nas.h, 1835

pack_nas_SLQSGetSysSelectionPrefExt
nas.h, 1836
pack_nas_SLQSInitiateNetworkRegistration
nas.h, 1836
pack_nas_SLQSInitiateNetworkRegistration_t, 748
pChangeDuration, 749
pMNRInfo, 749
pMncPcsDigitStatus, 749
regAction, 749
pack_nas_SLQSNASGetForbiddenNetworks
nas.h, 1838
pack_nas_SLQSNASGeteDRXParams
nas.h, 1837
pack_nas_SLQSNASGeteDRXParamsExt
nas.h, 1838
pack_nas_SLQSNASGeteDRXParamsExt_t, 754
pack_nas_SLQSNASSeteDRXParams
nas.h, 1840
pack_nas_SLQSNASSeteDRXParams_t, 759
pCycleLen, 760
pEdrxEnable, 760
pack_nas_SLQSNASSwiGetChannelLock
nas.h, 1841
pack_nas_SLQSNASSwiSetChannelLock
nas.h, 1842
pack_nas_SLQSNASSwiSetChannelLock_t, 762
pack_nas_SLQSNasConfigSigInfo2
nas.h, 1836
pack_nas_SLQSNasConfigSigInfo2_t, 749
pHDRIODelta, 753
pHDRIOThresh, 753
pLTESigRptConfig, 753
pack_nas_SLQSNasGet3GPP2Subscription
nas.h, 1837
pack_nas_SLQSNasGet3GPP2Subscription_t, 754
namID, 754
pack_nas_SLQSNasGetCellLocationInfo
nas.h, 1837
pack_nas_SLQSNasGetHDRColorCode
nas.h, 1838
pack_nas_SLQSNasGetRFInfo
nas.h, 1839
pack_nas_SLQSNasGetSigInfo
nas.h, 1839
pack_nas_SLQSNasGetTxRxInfo
nas.h, 1839
pack_nas_SLQSNasGetTxRxInfo_t, 755
radio_if, 756
pack_nas_SLQSNasIndicationRegisterExt
nas.h, 1840
pack_nas_SLQSNasIndicationRegisterExt_t, 756
pDDTMInd, 758
pDualStandByPrefInd, 758
pEdrxChangeInfoInd, 758
pErrorRateInd, 758
pHDRSessionCloseInd, 758
pLTECphyCa, 758
pManagedRoamingInd, 758
pNetworkRejectInd, 759
pNetworkTimeInd, 759
pServingSystemInd, 759
pSignalStrengthInd, 759
pSubscriptionInfoInd, 759
pSuppressSysInfoInd, 759
pSysInfoInd, 759
pSystemSelectionInd, 759
pack_nas_SLQSNasSwiIndicationRegister
nas.h, 1841
pack_nas_SLQSNasSwiIndicationRegister_t, 760
gsmUmtsDl, 761
gsmUmtsUl, 761
lteEmmDl, 761
lteEmmUl, 761
lteEsmDl, 761
lteEsmUl, 761
pRankIndicatorInd, 762
pTimer, 762
pack_nas_SLQSNasSwiModemStatus
nas.h, 1841
pack_nas_SLQSSetBandPreference
nas.h, 1842
pack_nas_SLQSSetBandPreference_t, 762
bandPref, 763
pack_nas_SLQSSetSignalStrengthsCallback
nas.h, 1842
pack_nas_SLQSSetSignalStrengthsCallback_t, 764
bEnable, 764
pSigIndReq, 764
pack_nas_SLQSSetSysSelectionPref
nas.h, 1843
pack_nas_SLQSSetSysSelectionPref_t, 764
pAcqOrderPref, 769
pBandPref, 769
pCSGID, 769
pChgDuration, 769
pEmerMode, 769
pGWAcqOrderPref, 769
pLTEBandPref, 769
pModePref, 769
pNetSelPref, 769
pPRLPref, 769
pRAT, 769
pRoamPref, 769
pSrvDomainPref, 769
pSrvRegRestriction, 769
pTdscdmaBandPref, 770
pack_nas_SLQSSetSysSelectionPrefExt
nas.h, 1843
pack_nas_SLQSSetSysSelectionPrefExt_t, 770
pAcqOrderPref, 779
pBandPref, 779
pCSGID, 779
pChgDuration, 779
pCiotAcqOrderPref, 779
pCiotLteOpMode, 779
pCiotLteOpModePref, 779

pEmerMode, 779
pGWAcqOrderPref, 779
pLTEBandPref, 779
pLteM1BandPref, 779
pLteNb1BandPref, 779
pModePref, 779
pNetSelPref, 779
pNr5gBandPref, 779
pPRLPref, 779
pRAT, 780
pRoamPref, 780
pSrvDomainPref, 780
pSrvRegRestriction, 780
pTdscdmaBandPref, 780
pack_nas_SLQSSwiGetHDRPersonality
nas.h, 1843
pack_nas_SLQSSwiGetHDRProtSubtype
nas.h, 1844
pack_nas_SLQSSwiGetHRPDStats
nas.h, 1844
pack_nas_SLQSSwiGetLteCQI
nas.h, 1844
pack_nas_SLQSSwiGetLteSccRxInfo
nas.h, 1845
pack_nas_SLQSSwiNetworkDebug
nas.h, 1845
pack_nas_SLQSSwiPSDetach
nas.h, 1845
pack_nas_SLQSSwiPSDetach_t, 780
pDetachAction, 780
pack_nas_SetACCOLC
nas.h, 1831
pack_nas_SetACCOLC_t, 743
accolc, 743
spc, 743
pack_nas_SetCDMANetworkParameters
nas.h, 1831
pack_nas_SetCDMANetworkParameters_t, 743
pApplication, 745
pBroadcast, 745
pCustomSCP, 745
pForceRev0, 745
pProtocol, 745
pRoaming, 745
pSPC, 745
pack_nas_SetLURejectCallback
nas.h, 1831
pack_nas_SetNetworkPreference
nas.h, 1832
pack_nas_SetNetworkPreference_t, 745
Duration, 746
TechnologyPref, 746
Tlvresult, 746
pack_nas_SetRFInfoCallback
nas.h, 1832
pack_nas_SlqsGetLTECphyCAInfo
nas.h, 1833
pack_pds_ForceXTRADownload
pds.h, 1876
pack_pds_GetPDSDefaults
pds.h, 1877
pack_pds_GetPDSState
pds.h, 1877
pack_pds_GetPortAutomaticTracking
pds.h, 1877
pack_pds_GetServiceAutomaticTracking
pds.h, 1878
pack_pds_GetXTRAAutomaticDownload
pds.h, 1878
pack_pds_GetXTRANetwork
pds.h, 1878
pack_pds_GetXTRAValidity
pds.h, 1879
pack_pds_PDSInjectTimeReference
pds.h, 1879
pack_pds_PDSInjectTimeReference_t, 780
systemDiscontinuities, 781
systemTime, 781
pack_pds_ResetPDSData
pds.h, 1879
pack_pds_ResetPDSData_t, 781
pCellDataMask, 781
pGPSDataMask, 782
pack_pds_SLQSGetAGPSConfig
pds.h, 1882
pack_pds_SLQSGetAGPSConfig_t, 785
pNetworkMode, 786
pack_pds_SLQSGetGPSStateInfo
pds.h, 1883
pack_pds_SLQSPDSDeterminePosition
pds.h, 1883
pack_pds_SLQSPDSInjectAbsoluteTimeReference
pds.h, 1883
pack_pds_SLQSPDSInjectAbsoluteTimeReference_t, 786
forceFlag, 786
timeBase, 786
timeMsec, 786
timeUncMsec, 787
pack_pds_SLQSPDSInjectPositionData
pds.h, 1884
pack_pds_SLQSPDSInjectPositionData_t, 787
pAltitudeWrtEllipsoid, 788
pAltitudeWrtSealevel, 788
pHorizontalConfidence, 788
pHorizontalUncCircular, 788
pLatitude, 788
pLongitude, 788
pPositionSource, 788
pTimeStamp, 788
pTimeType, 788
pVerticalConfidence, 788
pVerticalUnc, 788
pack_pds_SLQSSetAGPSConfig
pds.h, 1884
pack_pds_SLQSSetAGPSConfig_t, 789

pNetworkMode, 789
pServerAddress, 789
pServerPort, 789
pServerURL, 789
pack_pds_SLQSSetPositionMethodState
pds.h, 1885
pack_pds_SLQSSetPositionMethodState_t, 789
pWifiState, 790
pXtraDataState, 790
pXtraTimeState, 790
pack_pds_SetEventReportCallback
pds.h, 1880
pack_pds_SetEventReportCallback_t, 782
posDataNmea, 782
rptPosData, 782
pack_pds_SetPDSDefaults
pds.h, 1880
pack_pds_SetPDSDefaults_t, 782
accuracy, 783
interval, 783
operation, 783
timeout, 783
pack_pds_SetPDSState
pds.h, 1881
pack_pds_SetPDSState_t, 783
enable, 783
pack_pds_SetPortAutomaticTracking
pds.h, 1881
pack_pds_SetPortAutomaticTracking_t, 783
bAuto, 784
pack_pds_SetServiceAutomaticTracking
pds.h, 1881
pack_pds_SetServiceAutomaticTracking_t, 784
bAuto, 784
pack_pds_SetXTRAAutomaticDownload
pds.h, 1882
pack_pds_SetXTRAAutomaticDownload_t, 784
bEnabled, 785
interval, 785
pack_pds_SetXTRANetwork
pds.h, 1882
pack_pds_SetXTRANetwork_t, 785
preference, 785
pack_pds_StartPDSTrackingSessionExt
pds.h, 1885
pack_pds_StartPDSTrackingSessionExt_t, 790
fixAccuracy, 791
fixCount, 791
fixInterval, 791
fixTimeout, 791
sessionControl, 791
sessionOperation, 791
sessionServerOption, 791
sessionType, 791
pack_pds_StopPDSTrackingSession
pds.h, 1885
pack_qmi_t, 791
msgid, 792
svc, 792
timeout, 792
xid, 792
pack_qos_BindDataPort
qos.h, 2360
pack_qos_BindDataPort_t, 792
pMuxID, 793
pPeripheralEndPointID, 793
pSIODataPort, 793
pack_qos_SLQSQosGetNetworkStatus
qos.h, 2360
pack_qos_SLQSQosSwiReadApnExtraParams
qos.h, 2361
pack_qos_SLQSQosSwiReadApnExtraParams_t, 793
apnId, 793
pack_qos_SLQSQosSwiReadDataStats
qos.h, 2362
pack_qos_SLQSQosSwiReadDataStats_t, 793
apnId, 793
pack_qos_SLQSSetQosEventCallback
qos.h, 2362
pack_qos_SLQSSetQosEventCallback_t, 793
enable, 794
pack_rms_GetSMSWake
rms.h, 2368
pack_rms_SetSMSWake
rms.h, 2369
pack_rms_SetSMSWake_t, 794
enabled, 794
wake_mask, 794
pack_sar_SLQSGetRfSarState
sar.h, 2370
pack_sar_SLQSSetRfSarState
sar.h, 2370
pack_sar_SLQSSetRfSarState_t, 794
RfSarState, 795
pack_sms_GetSMSCAddress
sms.h, 2376
pack_sms_SLQSDeleteSMS
sms.h, 2378
pack_sms_SLQSDeleteSMS_t, 797
pMessageIndex, 798
pMessageMode, 798
pMessageTag, 798
storageType, 798
pack_sms_SLQSGetIndicationRegister
sms.h, 2378
pack_sms_SLQSGetMessageWaiting
sms.h, 2378
pack_sms_SLQSGetSMS
sms.h, 2379
pack_sms_SLQSGetSMS_t, 798
messageIndex, 799
pMessageMode, 799
storageType, 799
pack_sms_SLQSGetSMSList
sms.h, 2379
pack_sms_SLQSGetSMSList_t, 799

pMessageMode, 800
pRequestedTag, 800
storageType, 800
pack_sms_SLQSGetSmsBroadcastConfig
sms.h, 2379
pack_sms_SLQSGetSmsBroadcastConfig_t, 799
mode, 799
pack_sms_SLQSGetTransLayerInfo
sms.h, 2380
pack_sms_SLQSGetTransNWRegInfo
sms.h, 2380
pack_sms_SLQSModifySMSStatus
sms.h, 2380
pack_sms_SLQSModifySMSStatus_t, 800
messageIndex, 801
messageTag, 801
pMessageMode, 801
storageType, 801
pack_sms_SLQSSendAsyncSMS
sms.h, 2381
pack_sms_SLQSSendAsyncSMS_t, 801
pSendSmsParams, 801
pack_sms_SLQSSetIndicationRegister
sms.h, 2381
pack_sms_SLQSSetIndicationRegister_t, 801
pSetIndicationRegReq, 802
pack_sms_SLQSSetSmsBroadcastActivation
sms.h, 2381
pack_sms_SLQSSetSmsBroadcastActivation_t, 802
broadcastActivate, 802
mode, 802
pack_sms_SLQSSetSmsBroadcastConfig
sms.h, 2382
pack_sms_SLQSSetSmsBroadcastConfig_t, 802
mode, 803
pBroadcastConfig, 803
pCDMABroadcastConfig, 803
pack_sms_SLQSSetSmsStorage
sms.h, 2382
pack_sms_SLQSSetSmsStorage_t, 803
smsStorage, 803
pack_sms_SLQSSmsGetMaxStorageSize
sms.h, 2383
pack_sms_SLQSSmsGetMaxStorageSize_t, 804
pMaxStorageSizeReq, 804
pack_sms_SLQSSmsGetMessageProtocol
sms.h, 2383
pack_sms_SLQSSmsSetRoutes
sms.h, 2383
pack_sms_SLQSSmsSetRoutes_t, 804
pSetRoutesReq, 804
pack_sms_SLQSSwiGetSMSStorage
sms.h, 2384
pack_sms_SaveSMS
sms.h, 2376
pack_sms_SaveSMS_t, 795
messageFormat, 796
messageSize, 796
pMessage, 796
storageType, 796
pack_sms_SendSMS
sms.h, 2377
pack_sms_SendSMS_t, 796
messageFormat, 796
messageSize, 796
pLinktimer, 796
pMessage, 797
pack_sms_SetNewSMSCallback
sms.h, 2377
pack_sms_SetNewSMSCallback_t, 797
status, 797
pack_sms_SetSMSCAddress
sms.h, 2377
pack_sms_SetSMSCAddress_t, 797
pSMSCAddress, 797
pSMSCType, 797
pack_swidms_SLQSSwiDmsGetHWWatchdog
swidms.h, 2397
pack_swidms_SLQSSwiDmsGetMTU
swidms.h, 2398
pack_swidms_SLQSSwiDmsGetSecureInfo
swidms.h, 2398
pack_swidms_SLQSSwiDmsGetUsbComp
swidms.h, 2398
pack_swidms_SLQSSwiDmsGetUsbNetNum
swidms.h, 2399
pack_swidms_SLQSSwiDmsSetHWWatchdog
swidms.h, 2399
pack_swidms_SLQSSwiDmsSetHWWatchdog_t, 804
enable, 805
resetDelay, 805
timeout, 805
pack_swidms_SLQSSwiDmsSetMTU
swidms.h, 2399
pack_swidms_SLQSSwiDmsSetMTU_t, 805
MTUSize, 805
pack_swidms_SLQSSwiDmsSetUsbComp
swidms.h, 2400
pack_swidms_SLQSSwiDmsSetUsbComp_t, 805
CfgValue, 806
pack_swidms_SLQSSwiDmsSetUsbNetNum
swidms.h, 2400
pack_swidms_SLQSSwiDmsSetUsbNetNum_t, 806
nUsbNetNum, 807
pack_swiloc_SwiLocGetAutoStart
swiloc.h, 2404
pack_swiloc_SwiLocSetAutoStart
swiloc.h, 2404
pack_swiloc_SwiLocSetAutoStart_t, 807
fix_rate, 808
fix_type, 808
function, 808
max_dist, 808
max_time, 808
set_fix_rate, 808
set_fix_type, 808

set_function, 808
set_max_dist, 808
set_max_time, 808
pack_swioma_SLQSOMADMAlertCallback
swioma.h, 2407
pack_swioma_SLQSOMADMCancelSession
swioma.h, 2407
pack_swioma_SLQSOMADMCancelSession_t, 808
sessionType, 809
pack_swioma_SLQSOMADMGetSessionInfo
swioma.h, 2408
pack_swioma_SLQSOMADMGetSessionInfo_t, 809
SessionType, 809
pack_swioma_SLQSOMADMGetSettings
swioma.h, 2409
pack_swioma_SLQSOMADMSendSelection
swioma.h, 2409
pack_swioma_SLQSOMADMSendSelection_t, 809
pDeferTime, 810
pRejectReason, 810
selection, 810
pack_swioma_SLQSOMADMSetSettings
swioma.h, 2410
pack_swioma_SLQSOMADMSetSettings_t, 810
FOTAdownload, 811
pAutosdm, 811
pFwAutoCheck, 811
pack_swioma_SLQSOMADMStartSession
swioma.h, 2411
pack_swioma_SLQSOMADMStartSession_t, 811
sessionType, 811
pack_uim_ChangePin
uim.h, 2421
pack_uim_ChangePin_t, 811
changePIN, 812
EncryptedPIN1, 812
pIndicationToken, 812
pKeyReferenceID, 812
sessionInfo, 812
Tlvresult, 812
pack_uim_GetCardStatus
uim.h, 2421
pack_uim_ReadTransparent
uim.h, 2421
pack_uim_ReadTransparent_t, 812
fileIndex, 813
pEncryptData, 813
pIndicationToken, 813
readTransparent, 813
sessionInfo, 813
Tlvresult, 813
pack_uim_SLQSUIMAuthenticate
uim.h, 2422
pack_uim_SLQSUIMAuthenticate_t, 815
authData, 815
pIndicationToken, 815
sessionInfo, 815
pack_uim_SLQSUIMDepersonalization
uim.h, 2422
pack_uim_SLQSUIMDepersonalization_t, 815
depersonilisationInfo, 816
pack_uim_SLQSUIMEventRegister
uim.h, 2423
pack_uim_SLQSUIMEventRegister_t, 816
eventMask, 816
pack_uim_SLQSUIMGetConfiguration
uim.h, 2423
pack_uim_SLQSUIMGetConfiguration_t, 816
pConfigurationMask, 816
pack_uim_SLQSUIMGetFileAttributes
uim.h, 2423
pack_uim_SLQSUIMGetFileAttributes_t, 817
fileIndex, 817
pIndicationToken, 817
sessionInfo, 817
pack_uim_SLQSUIMGetSlotsStatus
uim.h, 2424
pack_uim_SLQSUIMPowerDown
uim.h, 2424
pack_uim_SLQSUIMPowerDown_t, 817
slot, 818
pack_uim_SLQSUIMPowerUp
uim.h, 2425
pack_uim_SLQSUIMPowerUp_t, 818
pIgnoreHotSwapSwitch, 818
slot, 818
pack_uim_SLQSUIMRefreshComplete
uim.h, 2425
pack_uim_SLQSUIMRefreshComplete_t, 818
refreshComplete, 819
sessionInfo, 819
pack_uim_SLQSUIMRefreshGetLastEvent
uim.h, 2425
pack_uim_SLQSUIMRefreshGetLastEvent_t, 819
sessionInfo, 819
pack_uim_SLQSUIMRefreshOK
uim.h, 2426
pack_uim_SLQSUIMRefreshOK_t, 819
OKtoRefresh, 820
sessionInfo, 820
pack_uim_SLQSUIMRefreshRegister
uim.h, 2426
pack_uim_SLQSUIMRefreshRegister_t, 820
regRefresh, 820
sessionInfo, 820
pack_uim_SLQSUIMReset
uim.h, 2426
pack_uim_SLQSUIMSwitchSlot
uim.h, 2427
pack_uim_SLQSUIMSwitchSlot_t, 820
bLogicalSlot, 821
ulPhysicalSlot, 821
pack_uim_SetPinProtection
uim.h, 2422
pack_uim_SetPinProtection_t, 814
EncryptedPIN1, 814

pIndicationToken, 814
pKeyReferenceID, 814
pinProtection, 814
sessionInfo, 814
Tlvresult, 814
pack_uim_UnblockPin
uim.h, 2427
pack_uim_UnblockPin_t, 821
EncryptedPIN1, 822
pIndicationToken, 822
pKeyReferenceID, 822
pinProtection, 822
sessionInfo, 822
Tlvresult, 822
pack_uim_VerifyPin
uim.h, 2427
pack_uim_VerifyPin_t, 822
pEncryptedPIN1, 823
pIndicationToken, 823
pKeyReferenceID, 823
sessionInfo, 823
Tlvresult, 823
verifyPIN, 823
pack_voice_AnswerUSSD
voice.h, 2443
pack_voice_AnswerUSSD_t, 823
pInfo, 824
pack_voice_CancelUSSD
voice.h, 2444
pack_voice_OriginateUSSD
voice.h, 2444
pack_voice_OriginateUSSD_t, 824
pInfo, 824
pack_voice_SLQSOriginateUSSD
voice.h, 2444
pack_voice_SLQSOriginateUSSD_t, 824
ussDCS, 825
ussData, 825
ussLen, 825
pack_voice_SLQSVoiceALSSelectLine
voice.h, 2445
pack_voice_SLQSVoiceALSSelectLine_t, 825
lineValue, 825
pack_voice_SLQSVoiceALSSetLineSwitching
voice.h, 2445
pack_voice_SLQSVoiceALSSetLineSwitching_t, 825
switchOption, 825
pack_voice_SLQSVoiceAnswerCall
voice.h, 2445
pack_voice_SLQSVoiceAnswerCall_t, 826
pCallId, 826
pack_voice_SLQSVoiceBindSubscription
voice.h, 2446
pack_voice_SLQSVoiceBindSubscription_t, 826
subsType, 826
pack_voice_SLQSVoiceBurstDTMF
voice.h, 2446
pack_voice_SLQSVoiceBurstDTMF_t, 826
pack_voice_SLQSVoiceDialCall
voice.h, 2447
pack_voice_SLQSVoiceDialCall_t, 827
callNumber, 828
pCLIRType, 828
pCUGInfo, 828
pCallPartySubAdd, 828
pCallType, 828
pEmergencyCategory, 828
pSvcType, 829
pUUSInFo, 829
pack_voice_SLQSVoiceEndCall
voice.h, 2447
pack_voice_SLQSVoiceEndCall_t, 829
pCallId, 829
pack_voice_SLQSVoiceGetAllCallInfo
voice.h, 2447
pack_voice_SLQSVoiceGetCLIP
voice.h, 2449
pack_voice_SLQSVoiceGetCLIR
voice.h, 2450
pack_voice_SLQSVoiceGetCNAP
voice.h, 2450
pack_voice_SLQSVoiceGetCOLP
voice.h, 2450
pack_voice_SLQSVoiceGetCOLR
voice.h, 2451
pack_voice_SLQSVoiceGetCallBarring
voice.h, 2448
pack_voice_SLQSVoiceGetCallBarring_t, 829
pSvcClass, 830
reason, 830
pack_voice_SLQSVoiceGetCallForwardingStatus
voice.h, 2448
pack_voice_SLQSVoiceGetCallForwardingStatus_t, 830
pSvcClass, 831
Reason, 831
pack_voice_SLQSVoiceGetCallInfo
voice.h, 2448
pack_voice_SLQSVoiceGetCallInfo_t, 831
callID, 831
pack_voice_SLQSVoiceGetCallWaiting
voice.h, 2449
pack_voice_SLQSVoiceGetCallWaiting_t, 831
pSvcClass, 832
pack_voice_SLQSVoiceGetConfig
voice.h, 2451
pack_voice_SLQSVoiceGetConfig_t, 832
pAMRStatus, 833
pAirTimer, 833
pAutoAnswer, 833
pNamID, 833
pPrefVoicePrivacy, 833
pPrefVoiceSO, 833
pRoamTimer, 833
pTTYMode, 833
pVoiceDomainPref, 833
pack_voice_SLQSVoiceIndicationRegister

voice.h, 2451
pack_voice_SLQSVoiceIndicationRegister_t, 834
pRegDTMFEvents, 834
pRegVoicePrivacyEvents, 834
pSuppsNotifEvents, 834
pack_voice_SLQSVoiceManageCalls
voice.h, 2452
pack_voice_SLQSVoiceManageCalls_t, 834
pCallID, 835
SUPSType, 835
pack_voice_SLQSVoiceOrigUSSDNoWait
voice.h, 2452
pack_voice_SLQSVoiceOrigUSSDNoWait_t, 835
pack_voice_SLQSVoiceSendFlash
voice.h, 2452
pack_voice_SLQSVoiceSendFlash_t, 836
pCallID, 836
pFlashPayLd, 836
pFlashType, 836
pack_voice_SLQSVoiceSetCallBarringPassword
voice.h, 2453
pack_voice_SLQSVoiceSetCallBarringPassword_t, 836
newPasswd, 837
newPasswdAgain, 837
oldPasswd, 837
Reason, 837
pack_voice_SLQSVoiceSetConfig
voice.h, 2453
pack_voice_SLQSVoiceSetConfig_t, 837
pAirTimerConfig, 839
pAutoAnswer, 839
pPrefVoiceDomain, 839
pPrefVoiceSO, 839
pRoamTimerConfig, 839
pTTYMode, 839
pack_voice_SLQSVoiceSetPreferredPrivacy
voice.h, 2453
pack_voice_SLQSVoiceSetPreferredPrivacy_t, 839
privacyPref, 839
pack_voice_SLQSVoiceSetSUPSService
voice.h, 2454
pack_voice_SLQSVoiceSetSUPSService_t, 839
pCallBarringPasswd, 841
pCallForwardingNumber, 841
pServiceClass, 841
pTimerVal, 841
reason, 841
voiceSvc, 841
pack_voice_SLQSVoiceStartContDTMF
voice.h, 2454
pack_voice_SLQSVoiceStartContDTMF_t, 841
DTMFdigit, 842
pCallID, 842
pack_voice_SLQSVoiceStopContDTMF
voice.h, 2455
pack_voice_SLQSVoiceStopContDTMF_t, 842
callID, 842
pack_wds_DHCPv4ClientLeaseChange
wds.h, 2478
pack_wds_DHCPv4ClientLeaseChange_t, 842
pEnableNotification, 843
pack_wds_GetAutoconnect
wds.h, 2478
pack_wds_GetByteTotals
wds.h, 2479
pack_wds_GetConnectionRate
wds.h, 2479
pack_wds_GetDataBearerTechnology
wds.h, 2480
pack_wds_GetDefaultProfile
wds.h, 2480
pack_wds_GetDefaultProfile_t, 843
profiletype, 843
pack_wds_GetDefaultProfileNum
wds.h, 2480
pack_wds_GetDefaultProfileNum_t, 843
family, 843
type, 843
pack_wds_GetDormancyState
wds.h, 2481
pack_wds_GetDormancyState_t, 844
pack_wds_GetLastMobileIPError
wds.h, 2481
pack_wds_GetLastMobileIPError_t, 844
pack_wds_GetMobileIP
wds.h, 2482
pack_wds_GetMobileIP_t, 844
pack_wds_GetMobileIPProfile
wds.h, 2482
pack_wds_GetMobileIPProfile_t, 844
index, 845
pack_wds_GetPacketStatistics
wds.h, 2483
pack_wds_GetPacketStatistics_t, 845
pStatMask, 845
pack_wds_GetPacketStatus
wds.h, 2483
pack_wds_GetPacketStatus_t, 845
statmask, 846
pack_wds_GetSessionDuration
wds.h, 2483
pack_wds_GetSessionDuration_t, 846
pack_wds_GetSessionState
wds.h, 2484
pack_wds_RMSetTransferStatistics
wds.h, 2484
pack_wds_RMSetTransferStatistics_t, 846
RmTrasnferStaticsReq, 846
pack_wds_SLQSCreateProfile
wds.h, 2488
pack_wds_SLQSCreateProfile_t, 853
pCurProfile, 854
pProfileId, 854
pProfileType, 854
pack_wds_SLQSDeleteProfile
wds.h, 2488

pack_wds_SLQSDeleteProfile_t, 854
profileIndex, 854
profileType, 854
pack_wds_SLQSGet3GPPConfigItem
wds.h, 2488
pack_wds_SLQSGetCurrDataSystemStat
wds.h, 2489
pack_wds_SLQSGetCurrDataSystemStat_t, 854
pack_wds_SLQSGetCurrentChannelRate
wds.h, 2489
pack_wds_SLQSGetDUNCallInfo
wds.h, 2490
pack_wds_SLQSGetDUNCallInfo_t, 855
Mask, 856
pReportChannelRate, 856
pReportConnStatus, 856
pReportDataBearerTech, 856
pReportDormStatus, 856
pTransferStatInd, 856
pack_wds_SLQSGetDataBearerTechnology
wds.h, 2490
pack_wds_SLQSGetDataBearerTechnology_t, 855
pack_wds_SLQSGetProfileSettings
wds.h, 2491
pack_wds_SLQSGetProfileSettings_t, 856
ProfileId, 857
ProfileType, 857
pack_wds_SLQSGetRuntimeSettings
wds.h, 2491
pack_wds_SLQSGetRuntimeSettings_t, 857
pReqSettings, 858
pack_wds_SLQSModifyProfile
wds.h, 2491
pack_wds_SLQSModifyProfile_t, 858
curProfile, 859
pProfileId, 859
pProfileType, 859
pack_wds_SLQSResetPacketStatics
wds.h, 2492
pack_wds_SLQSSGetDHCPv4ClientConfig
wds.h, 2493
pack_wds_SLQSSGetDHCPv4ClientConfig_t, 862
pProfileId, 862
pack_wds_SLQSSGetLoopback
wds.h, 2494
pack_wds_SLQSSSetDHCPv4ClientConfig
wds.h, 2494
pack_wds_SLQSSSetDHCPv4ClientConfig_t, 862
pHwConfig, 863
pProfileId, 863
pack_wds_SLQSSSetLoopback
wds.h, 2495
pack_wds_SLQSSSetLoopback_t, 863
loopbackMode, 863
loopbackMultiplier, 863
pack_wds_SLQSSet3GPPConfigItem
wds.h, 2492
pack_wds_SLQSSet3GPPConfigItem_t, 859
p3gppRelease, 860
pProfileList, 860
pack_wds_SLQSSetIPFamilyPreference
wds.h, 2493
pack_wds_SLQSSetIPFamilyPreference_t, 861
IPFamilyPreference, 861
pack_wds_SLQSSetWdsEventCallback
wds.h, 2493
pack_wds_SLQSSetWdsEventCallback_t, 861
currentDataBearer, 862
dataBearer, 862
dataBearerTechExt, 862
dataSystemStatus, 862
dormancyStatus, 862
interval, 862
mobileIP, 862
transferStats, 862
pack_wds_SLQSStartDataSession
wds.h, 2495
pack_wds_SLQSStartDataSession_t, 863
pAuth, 864
pPass, 864
pTech, 864
pUser, 864
pprofileid3gpp, 864
pprofileid3gpp2, 864
pack_wds_SLQSStopDataSession
wds.h, 2495
pack_wds_SLQSStopDataSession_t, 865
psid, 865
pack_wds_SLQSWdsGoActive
wds.h, 2496
pack_wds_SLQSWdsGoDormant
wds.h, 2496
pack_wds_SLQSWdsSetEventReport
wds.h, 2497
pack_wds_SLQSWdsSetEventReport_t, 865
pCurrChannelRateInd, 866
pCurrDataBearerTechInd, 866
pCurrPrefDataSysInd, 866
pDataBearerTechInd, 866
pDataCallStatusChangeInd, 866
pDataSystemStatusChangeInd, 866
pDormancyStatusInd, 867
pMIPStatusInd, 867
pTransferStatInd, 867
pack_wds_SLQSWdsSwiPDPRuntimeSettings
wds.h, 2497
pack_wds_SLQSWdsSwiPDPRuntimeSettings_t, 867
contextId, 867
contextType, 867
pack_wds_SetAutoconnect
wds.h, 2485
pack_wds_SetAutoconnect_t, 847
acroamsetting, 847
acsetting, 847
pack_wds_SetDefaultProfile
wds.h, 2485

pack_wds_SetDefaultProfile_t, 847
authentication, 848
ipAddress, 849
pApnname, 849
pName, 849
pPassword, 849
pUsername, 849
pdpType, 849
primaryDNS, 849
profileType, 849
secondaryDNS, 849
pack_wds_SetDefaultProfileNum
wds.h, 2485
pack_wds_SetDefaultProfileNum_t, 849
family, 849
index, 849
type, 849
pack_wds_SetMobileIP
wds.h, 2486
pack_wds_SetMobileIP_t, 850
mode, 850
pack_wds_SetMobileIPParameters
wds.h, 2486
pack_wds_SetMobileIPParameters_t, 850
pHA2002bis, 851
pHAAuthenticator, 851
pMode, 851
pReRegPeriod, 851
pReRegTraffic, 851
pRetryInterval, 851
pRetryLimit, 851
pSPC, 851
pack_wds_SetMobileIPProfile
wds.h, 2487
pack_wds_SetMobileIPProfile_t, 851
index, 852
pAAASPI, 853
pAddress, 853
pEnabled, 853
pHASPI, 853
pMNAAA, 853
pMNHA, 853
pNAI, 853
pPrimaryHA, 853
pRevTunneling, 853
pSecondaryHA, 853
spc, 853
pack_wds_SetMuxID
wds.h, 2487
PackCreateProfileOut, 867
ExtErrorCode, 868
ProfileIndex, 868
ProfileType, 868
package_name
omaDmFotaTlv, 701
omaDmFotaTlvExt, 703
unpack_omaDmFotaTlv_t, 1382
PackageID
_SwiAvmsEventInd, 113
packageSize
omaDmFotaTlvExt, 703
packageid_str
slqsfwinfo_s, 1034
unpack_dms_GetFirmwareInfo_t, 1220
packetSrvStatus
qaGobiApiCbk.h, 1917
packetZone
CDMASysInfo, 193
nas_CDMASysInfo, 485
packetZoneValid
CDMASysInfo, 193
nas_CDMASysInfo, 485
packgetDyingGaspCfg, 868
pDestSMSContent, 868
pDestSMSNum, 868
packgetDyingGaspStatistics, 868
pSMSAttemptedFlag, 869
pTimeStamp, 869
ParamPresenceMask
pack_dms_UIMGetICCID_t, 720
unpack_dms_GetActivationState_t, 1206
unpack_dms_GetBandCapability_t, 1208
unpack_dms_GetCrashAction_t, 1208
unpack_dms_GetCustFeature_t, 1211
unpack_dms_GetCustFeaturesV2_t, 1212
unpack_dms_GetDeviceCap_t, 1213
unpack_dms_GetDeviceCapabilities_t, 1215
unpack_dms_GetDeviceHardwareRev_t, 1215
unpack_dms_GetDeviceMfr_t, 1216
unpack_dms_GetDeviceSerialNumbers_t, 1218
unpack_dms_GetFirmwareInfo_t, 1220
unpack_dms_GetFirmwareRevision_t, 1221
unpack_dms_GetFirmwareRevisions_t, 1222
unpack_dms_GetFSN_t, 1223
unpack_dms_GetHardwareRevision_t, 1223
unpack_dms_GetIMSI_t, 1224
unpack_dms_GetManufacturer_t, 1224
unpack_dms_GetModelID_t, 1225
unpack_dms_GetNetworkTime_t, 1226
unpack_dms_GetOfflineReason_t, 1227
unpack_dms_GetPower_t, 1228
unpack_dms_GetPRLVersion_t, 1229
unpack_dms_GetSerialNumbers_t, 1230
unpack_dms_GetUSBComp_t, 1232
unpack_dms_GetVoiceNumber_t, 1233
unpack_dms_PSMCfgChange_ind_t, 1234
unpack_dms_ResetToFactoryDefaults_t, 1235
unpack_dms_SetActivationStatusCallback_t, 1235
unpack_dms_SetCrashAction_t, 1236
unpack_dms_SetCustFeature_t, 1236
unpack_dms_SetCustFeaturesV2_t, 1237
unpack_dms_SetEventReport_ind_t, 1238
unpack_dms_SetEventReport_t, 1238
unpack_dms_SetFirmwarePreference_t, 1239
unpack_dms_SetIndicationRegister_t, 1239
unpack_dms_SetPower_t, 1240

unpack_dms_SetUSBComp_t, 1240
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1243
unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t, 1244
unpack_dms_SLQSDmsSwiGetResetInfo_t, 1245
unpack_dms_SLQSDmsSwiGetUimSelection_t, 1246
unpack_dms_SLQSDmsSwiIndicationRegister_t, 1247
unpack_dms_SLQSGetBandCapability_t, 1251
unpack_dms_SLQSGetERIFile_t, 1252
unpack_dms_SLQSGetPowerSaveModeConfig_t, 1253
unpack_dms_SLQSSetPowerSaveModeConfig_t, 1254
unpack_dms_SLQSSwiClearDyingGaspStatistics_t, 1254
unpack_dms_SLQSSwiGetCrashInfo_t, 1255
unpack_dms_SLQSSwiGetDyingGaspCfg_t, 1256
unpack_dms_SLQSSwiGetDyingGaspStatistics_t, 1256
unpack_dms_SLQSSwiGetFirmwareCurr_t, 1257
unpack_dms_SLQSSwiGetFwUpdateStatus_t, 1259
unpack_dms_SLQSSwiGetHostDevInfo_t, 1260
unpack_dms_SLQSSwiGetOSInfo_t, 1261
unpack_dms_SLQSSwiGetSerialNoExt_t, 1262
unpack_dms_SLQSSwiSetDyingGaspCfg_t, 1262
unpack_dms_SLQSSwiSetHostDevInfo_t, 1263
unpack_dms_SLQSSwiSetOSInfo_t, 1263
unpack_dms_SLQSUIMGetState_t, 1264
unpack_dms_SwiEventReportCallBack_ind_t, 1265
unpack_dms_SwiSetEventReport_t, 1265
unpack_dms_SwiUimSelect_t, 1266
unpack_dms_UIMGetControlKeyStatus_t, 1267
unpack_dms_UIMGetICCID_t, 1267
unpack_dms_UIMGetPINStatus_t, 1269
unpack_dms_UIMSetControlKeyProtection_t, 1270
unpack_dms_UIMSetPINProtection_t, 1271
unpack_dms_UIMUnblockControlKey_t, 1271
unpack_fms_GetImagesPreference_t, 1272
unpack_fms_GetStoredImages_t, 1273
unpack_fms_SetImagesPreference_t, 1273
unpack_loc_BestAvailPos_Ind_t, 1279
unpack_loc_CradleMountCallback_Ind_t, 1281
unpack_loc_Delete_Assist_Data_t, 1281
unpack_loc_DeleteAssistData_Ind_t, 1282
unpack_loc_EngineState_Ind_t, 1283
unpack_loc_EventNMEA_Ind_t, 1284
unpack_loc_EventRegister_t, 1284
unpack_loc_EventTimeSyncCallback_Ind_t, 1284
unpack_loc_GetOpMode_Ind_t, 1286
unpack_loc_GetServer_Ind_t, 1287
unpack_loc_GnssSvInfo_Ind_t, 1288
unpack_loc_InjectPositionCallback_Ind_t, 1289
unpack_loc_InjectSensorDataCallback_Ind_t, 1291
unpack_loc_InjectTimeSyncDataCallback_Ind_t, 1291
unpack_loc_InjectUTCTimeCallback_Ind_t, 1292
unpack_loc_PositionRpt_Ind_t, 1298
unpack_loc_SensorStreamingCallback_Ind_t, 1299
unpack_loc_SetExtPowerConfig_Ind_t, 1300
unpack_loc_SetExtPowerState_t, 1301
unpack_loc_SetOperationMode_Ind_t, 1302
unpack_loc_SetOperationMode_t, 1302
unpack_loc_SetServer_Ind_t, 1303
unpack_loc_SLQSLOCGetBestAvailPos_t, 1304
unpack_loc_SLQSLOCGetOpMode_t, 1304
unpack_loc_Start_t, 1305
unpack_loc_Stop_t, 1305
unpack_nas_GetACCOLC_t, 1306
unpack_nas_GetANAAAAuthenticationStatus_t, 1306
unpack_nas_GetCDMANetworkParameters_t, 1308
unpack_nas_GetHomeNetwork3GPP2_t, 1311
unpack_nas_GetHomeNetwork_t, 1312
unpack_nas_GetNetworkPreference_t, 1313
unpack_nas_GetRFInfo_t, 1314
unpack_nas_GetServingNetwork_t, 1317
unpack_nas_GetServingNetworkCapabilities_t, 1318
unpack_nas_GetSignalStrengths_t, 1318
unpack_nas_PerformNetworkScan_t, 1320
unpack_nas_SetDataCapabilitiesCallback_ind_t, 1321
unpack_nas_SetEventReportInd_t, 1322
unpack_nas_SetNasLTECphyCaIndCallback_ind_t, 1323
unpack_nas_SetNetworkPreference_t, 1323
unpack_nas_SetRoamingIndicatorCallback_ind_t, 1324
unpack_nas_SetServingSystemCallback_ind_t, 1325
unpack_nas_SLQSGetErrorRate_t, 1326
unpack_nas_SlqsGetLTECphyCAInfo_t, 1327
unpack_nas_SLQSGetNetworkTime_t, 1327
unpack_nas_SLQSGetOperatorNameData_t, 1328
unpack_nas_SLQSGetPLMNName_t, 1331
unpack_nas_SLQSGetServingSystem_t, 1336
unpack_nas_SLQSGetSignalStrength_t, 1339
unpack_nas_SLQSGetSysInfo_t, 1342
unpack_nas_SLQSGetSysSelectionPref_t, 1347
unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t, 1351
unpack_nas_SLQSNasGet3GPP2Subscription_t, 1352
unpack_nas_SLQSNasGetCellLocationInfo_t, 1353
unpack_nas_SLQSNASGeteDRXParams_t, 1355
unpack_nas_SLQSNASGeteDRXParamsExt_t, 1356

unpack_nas_SLQSNASGetForbiddenNetworks_t, 1357
unpack_nas_SLQSNasGetHDRColorCode_t, 1357
unpack_nas_SLQSNasGetSigInfo_t, 1359
unpack_nas_SLQSNasGetTxRxInfo_t, 1360
unpack_nas_SLQSNasNetworkRejectCallback_-Ind_t, 1363
unpack_nas_SLQSNasNetworkTimeCallBack_ind-_t, 1364
unpack_nas_SLQSNasSigInfoCallback_ind_t, 1365
unpack_nas_SLQSNASSwiGetChannelLock_t, 1366
unpack_nas_SLQSNasSwiModemStatus_t, 1367
unpack_nas_SLQSNasSwiOTAMessageCallback-_ind_t, 1368
unpack_nas_SLQSNasTimerCallback_ind_t, 1368
unpack_nas_SLQSSetSysSelectionPrefCallBack-_ind_t, 1369
unpack_nas_SLQSSwiGetHDRPersonality_t, 1370
unpack_nas_SLQSSwiGetHDRProtSubtype_t, 1371
unpack_nas_SLQSSwiGetHRPDStats_t, 1372
unpack_nas_SLQSSwiGetLteCQI_t, 1373
unpack_nas_SLQSSwiGetLteSccRxInfo_t, 1373
unpack_nas_SLQSSwiHDRPersonalityCallback_-Ind_t, 1374
unpack_nas_SLQSSwiNetworkDebug_t, 1375
unpack_nas_SLQSSwiRandIndicatorCallback_-Ind_t, 1375
unpack_nas_SLQSSysInfoCallback_ind_t, 1379
unpack_pds_GetPDSDefaults_t, 1384
unpack_pds_GetPDSState_t, 1385
unpack_pds_GetPortAutomaticTracking_t, 1385
unpack_pds_GetServiceAutomaticTracking_t, 1386
unpack_pds_GetXTRAAutomaticDownload_t, 1387
unpack_pds_GetXTRANetwork_t, 1387
unpack_pds_GetXTRAValidity_t, 1388
unpack_pds_SetEventReport_Ind_t, 1390
unpack_pds_SetPdsState_Ind_t, 1391
unpack_pds_SLQSGetAGPSConfig_t, 1392
unpack_pds_SLQSGetGPSStateInfo_t, 1396
unpack_qos_BindDataPort_t, 1397
unpack_qos_SLQSQosGetNetworkStatus_t, 1403
unpack_qos_SLQSQosSwiReadApnExtraParams-_t, 1404
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
unpack_qos_SLQSSetQosEventCallback_ind_t, 1407
unpack_qos_SLQSSetQosEventCallback_t, 1407
unpack_qos_SLQSSetQosNWStatusCallback_ind-_t, 1408
unpack_qos_SLQSSetQosPriEventCallback_ind_-t, 1408
unpack_qos_SLQSSetQosStatusCallback_ind_t, 1410
unpack_result_t, 1419
unpack_rms_GetSMSWake_t, 1420
unpack_rms_SetSMSWake_t, 1421
unpack_RMTransferStatistics_ind_t, 1421
unpack_sar_SLQSGetRfSarState_t, 1422
unpack_sms_GetSMSCAddress_t, 1423
unpack_sms_SaveSMS_t, 1424
unpack_sms_SendSMS_t, 1424
unpack_sms_SetNewSMSCallback_ind_t, 1426
unpack_sms_SetNewSMSCallback_t, 1426
unpack_sms_SetSMSCAddress_t, 1427
unpack_sms_SLQSDeleteSMS_t, 1427
unpack_sms_SLQSGetIndicationRegister_t, 1428
unpack_sms_SLQSGetMessageWaiting_t, 1428
unpack_sms_SLQSGetSMS_t, 1429
unpack_sms_SLQSGetSmsBroadcastConfig_t, 1430
unpack_sms_SLQSGetSMSList_t, 1431
unpack_sms_SLQSGetTransLayerInfo_t, 1431
unpack_sms_SLQSGetTransNWRegInfo_t, 1432
unpack_sms_SLQSModifySMSStatus_t, 1432
unpack_sms_SLQSNWRegInfoCallback_ind_t, 1433
unpack_sms_SLQSSendAsyncSMS_t, 1433
unpack_sms_SLQSSetIndicationRegister_t, 1434
unpack_sms_SLQSSetSmsBroadcastActivation_t, 1434
unpack_sms_SLQSSetSmsBroadcastConfig_t, 1435
unpack_sms_SLQSSetSmsStorage_t, 1435
unpack_sms_SLQSSmsGetMaxStorageSize_t, 1435
unpack_sms_SLQSSmsGetMessageProtocol_t, 1436
unpack_sms_SLQSSmsSetRoutes_t, 1436
unpack_sms_SLQSSwiGetSMSStorage_t, 1437
unpack_sms_SLQSTransLayerInfoCallback_ind_t, 1438
unpack_sms_SLQSWmsAsyncRawSendCallBack-_ind_t, 1440
unpack_sms_SLQSWmsMemoryFullCallBack_ind-_t, 1441
unpack_sms_SLQSWmsMessageWaitingCall-Back_ind_t, 1441
unpack_swidms_SLQSSwiDmsGetHWWatchdog-_t, 1442
unpack_swidms_SLQSSwiDmsGetMTU_t, 1443
unpack_swidms_SLQSSwiDmsGetSecureInfo_t, 1443
unpack_swidms_SLQSSwiDmsGetUsbComp_t, 1444
unpack_swidms_SLQSSwiDmsGetUsbNetNum_t, 1445
unpack_swidms_SLQSSwiDmsSetHWWatchdog_-t, 1445
unpack_swidms_SLQSSwiDmsSetMTU_t, 1446
unpack_swidms_SLQSSwiDmsSetUsbComp_t, 1446

unpack_swiloc_SwiLocGetAutoStart_t, 1448
unpack_swioma_SLQSOMADMAlertCallback_ind_t, 1449
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
unpack_swioma_SLQSOMADMGetSettings_t, 1454
unpack_swioma_SLQSOMADMStartSession_t, 1454
unpack_uim_ChangePin_t, 1455
unpack_uim_GetCardStatus_t, 1456
unpack_uim_GetCardStatusV2_t, 1457
unpack_uim_ReadTransparent_t, 1458
unpack_uim_SetPinProtection_t, 1459
unpack_uim_SetUimSlotStatusChangeCallback_ind_t, 1459
unpack_uim_SLQSUIMAuthenticate_t, 1460
unpack_uim_SLQSUIMDepersonalization_t, 1461
unpack_uim_SLQSUIMEventRegister_t, 1461
unpack_uim_SLQSUIMGetConfiguration_t, 1462
unpack_uim_SLQSUIMGetFileAttributes_t, 1463
unpack_uim_SLQSUIMGetSlotsStatus_t, 1464
unpack_uim_SLQSUIMRefreshCallback_Ind_t, 1464
unpack_uim_SLQSUIMRefreshGetLastEvent_t, 1465
unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t, 1465
unpack_uim_UnblockPin_t, 1466
unpack_uim_UnblockPinV2_t, 1467
unpack_uim_VerifyPin_t, 1468
unpack_voice_allCallStatusCallback_ind_t, 1470
unpack_voice_DTMFEventCallback_ind_t, 1471
unpack_voice_OTASPStatusCallback_ind_t, 1472
unpack_voice_SLQSOriginateUSSD_t, 1475
unpack_voice_SLQSVoiceAnswerCall_t, 1476
unpack_voice_SLQSVoiceBurstDTMF_t, 1476
unpack_voice_SLQSVoiceDialCall_t, 1477
unpack_voice_SLQSVoiceEndCall_t, 1478
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1481
unpack_voice_SLQSVoiceGetCallBarring_t, 1483
unpack_voice_SLQSVoiceGetCallForwardingStatus_t, 1484
unpack_voice_SLQSVoiceGetCallInfo_t, 1487
unpack_voice_SLQSVoiceGetCallWaiting_t, 1489
unpack_voice_SLQSVoiceGetCLIP_t, 1490
unpack_voice_SLQSVoiceGetCLIR_t, 1492
unpack_voice_SLQSVoiceGetCNAP_t, 1493
unpack_voice_SLQSVoiceGetCOLP_t, 1495
unpack_voice_SLQSVoiceGetCOLR_t, 1496
unpack_voice_SLQSVoiceGetConfig_t, 1498
unpack_voice_SLQSVoiceManageCalls_t, 1499
unpack_voice_SLQSVoiceSendFlash_t, 1499
unpack_voice_SLQSVoiceSetCallBarringPassword_t, 1501
unpack_voice_SLQSVoiceSetConfig_t, 1502
unpack_voice_SLQSVoiceSetSUPSService_t, 1504
unpack_voice_SLQSVoiceStartContDTMF_t, 1504
unpack_voice_SLQSVoiceStopContDTMF_t, 1505
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1507
unpack_voice_SUPSNotificationCallback_ind_t, 1510
unpack_voice_USSDNotificationCallback_ind_t, 1510
unpack_voice_VoiceInfoRecCallback_ind_t, 1513
unpack_voice_voicePrivacyChangeCallback_ind_t, 1514
unpack_wds_DHCPv4ClientLease_ind_t, 1515
unpack_wds_GetAutoconnect_t, 1515
unpack_wds_GetByteTotals_t, 1516
unpack_wds_GetConnectionRate_t, 1517
unpack_wds_GetDataBearerTechnology_t, 1518
unpack_wds_GetDefaultProfile_t, 1521
unpack_wds_GetDefaultProfileNum_t, 1521
unpack_wds_GetDormancyState_t, 1522
unpack_wds_GetLastMobileIPError_t, 1523
unpack_wds_GetMobileIP_t, 1523
unpack_wds_GetMobileIPProfile_t, 1525
unpack_wds_GetPacketStatistics_t, 1527
unpack_wds_GetPacketStatus_t, 1529
unpack_wds_GetSessionDuration_t, 1530
unpack_wds_GetSessionState_t, 1530
unpack_wds_RMSetTransferStatistics_t, 1531
unpack_wds_SetMobileIPProfile_t, 1531
unpack_wds_SLQSCreateProfile_t, 1532
unpack_wds_SLQSDeleteProfile_t, 1532
unpack_wds_SLQSDUNCallInfoCallBack_ind_t, 1534
unpack_wds_SLQSGet3GPPConfigItem_t, 1536
unpack_wds_SLQSGetCurrDataSystemStat_t, 1536
unpack_wds_SLQSGetCurrentChannelRate_t, 1538
unpack_wds_SLQSGetDataBearerTechnology_t, 1539
unpack_wds_SLQSGetDUNCallInfo_t, 1542
unpack_wds_SLQSGetProfileSettings_t, 1542
unpack_wds_SLQSGetRuntimeSettings_t, 1545
unpack_wds_SLQSModifyProfile_t, 1546
unpack_wds_SLQSSetIPFamilyPreference_t, 1547
unpack_wds_SLQSSetPacketSrvStatusCallback_t, 1549
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
unpack_wds_SLQSSGetDHCPv4ClientConfig_t, 1555
unpack_wds_SLQSSGetLoopback_t, 1556
unpack_wds_SLQSStartDataSession_t, 1556
unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t, 1559
partno_str
slqsfwpartno_s, 1035
path

fileInfo, 280
uim_fileInfo, 1158
pathLen
fileInfo, 280
uim_fileInfo, 1158
pbAuto
unpack_pds_GetPortAutomaticTracking_t, 1386
unpack_pds_GetServiceAutomaticTracking_t, 1386
pbEnabled
unpack_pds_GetXTRAAutomaticDownload_t, 1387
pbIMSRegistered
imsaRegStatusInfo, 352
pbPlatform
unpack_dms_GetOfflineReason_t, 1227
pci
cellParams, 196
ltePCI, 454
nas_cellParams, 486
nas_ltePCI, 539
nas_PhyCaAggPcellInfo, 566
nas_PhyCaAggScellIndType, 567
nas_PhyCaAggScellInfo, 570
nas_umtsLTENbrCell, 618
NASPhyCaAggPcellInfo, 657
NASPhyCaAggScellArray, 658
NASPhyCaAggScellIndType, 660
NASPhyCaAggScellInfo, 661
PhyCaAggPcellInfo, 877
PhyCaAggScellArray, 879
PhyCaAggScellIndType, 880
PhyCaAggScellInfo, 883
umtsLTENbrCell, 1197
pcsDigit
nas_PlmnID, 572
PlmnID, 885
pcsfFQDNAddress
PCSCFFQDNAddressList, 870
wds_PCSCFFQDNAddressList, 1693
pdpType
pack_wds_SetDefaultProfile_t, 849
pdpidx
qaGobiApiWds.h, 2312
pdptype
unpack_wds_GetDefaultProfile_t, 1521
pds.h, 1873
pack_pds_ForceXTRADownload, 1876
pack_pds_GetPDSDefaults, 1877
pack_pds_GetPDSState, 1877
pack_pds_GetPortAutomaticTracking, 1877
pack_pds_GetServiceAutomaticTracking, 1878
pack_pds_GetXTRAAutomaticDownload, 1878
pack_pds_GetXTRANetwork, 1878
pack_pds_GetXTRAValidity, 1879
pack_pds_PDSInjectTimeReference, 1879
pack_pds_ResetPDSData, 1879
pack_pds_SLQSGetAGPSConfig, 1882
pack_pds_SLQSGetGPSStateInfo, 1883
pack_pds_SLQSPDSDeterminePosition, 1883
pack_pds_SLQSPDSInjectAbsoluteTimeReference, 1883
pack_pds_SLQSPDSInjectPositionData, 1884
pack_pds_SLQSSetAGPSConfig, 1884
pack_pds_SLQSSetPositionMethodState, 1885
pack_pds_SetEventReportCallback, 1880
pack_pds_SetPDSDefaults, 1880
pack_pds_SetPDSState, 1881
pack_pds_SetPortAutomaticTracking, 1881
pack_pds_SetServiceAutomaticTracking, 1881
pack_pds_SetXTRAAutomaticDownload, 1882
pack_pds_SetXTRANetwork, 1882
pack_pds_StartPDSTrackingSessionExt, 1885
pack_pds_StopPDSTrackingSession, 1885
unpack_pds_ForceXTRADownload, 1886
unpack_pds_ForceXTRADownload_t, 1876
unpack_pds_GetPDSDefaults, 1886
unpack_pds_GetPDSState, 1886
unpack_pds_GetPortAutomaticTracking, 1887
unpack_pds_GetServiceAutomaticTracking, 1887
unpack_pds_GetXTRAAutomaticDownload, 1887
unpack_pds_GetXTRANetwork, 1888
unpack_pds_GetXTRAValidity, 1888
unpack_pds_PDSInjectTimeReference, 1889
unpack_pds_PDSInjectTimeReference_t, 1876
unpack_pds_ResetPDSData, 1889
unpack_pds_ResetPDSData_t, 1876
unpack_pds_SLQSGetAGPSConfig, 1892
unpack_pds_SLQSGetGPSStateInfo, 1893
unpack_pds_SLQSPDSDeterminePosition, 1893
unpack_pds_SLQSPDSDeterminePosition_t, 1876
unpack_pds_SLQSPDSInjectAbsoluteTime-Reference, 1893
unpack_pds_SLQSPDSInjectAbsoluteTime-Reference_t, 1876
unpack_pds_SLQSPDSInjectPositionData, 1894
unpack_pds_SLQSPDSInjectPositionData_t, 1876
unpack_pds_SLQSSetAGPSConfig, 1894
unpack_pds_SLQSSetAGPSConfig_t, 1876
unpack_pds_SLQSSetPositionMethodState, 1894
unpack_pds_SLQSSetPositionMethodState_t, 1876
unpack_pds_SetEventReport_Ind, 1889
unpack_pds_SetEventReportCallback, 1890
unpack_pds_SetEventReportCallback_t, 1876
unpack_pds_SetPDSDefaults, 1890
unpack_pds_SetPDSDefaults_t, 1876
unpack_pds_SetPDSState, 1890
unpack_pds_SetPDSState_t, 1876
unpack_pds_SetPdsState_Ind, 1891
unpack_pds_SetPortAutomaticTracking, 1891
unpack_pds_SetPortAutomaticTracking_t, 1876
unpack_pds_SetServiceAutomaticTracking, 1891
unpack_pds_SetServiceAutomaticTracking_t, 1876
unpack_pds_SetXTRAAutomaticDownload, 1892
unpack_pds_SetXTRAAutomaticDownload_t, 1876

unpack_pds_SetXTRANetwork, 1892
unpack_pds_SetXTRANetwork_t, 1876
unpack_pds_StartPDSTrackingSessionExt, 1895
unpack_pds_StartPDSTrackingSessionExt_t, 1876
unpack_pds_StopPDSTrackingSession, 1895
unpack_pds_StopPDSTrackingSession_t, 1876
peakRate
tokenBucket, 1138
unpack_qos_tokenBucket_t, 1418
peakThroughputClass
GPRSQoS, 322
GPRSRequestedQoS, 323
LibPackGPRSRequestedQoS, 373
wds_GPRSQoS, 1690
peerNumberInfo, 874
callID, 875
numLen, 875
numPI, 875
numPlan, 875
numSI, 875
numType, 876
number, 875
PerformNetworkScan
qaGobiApiNas.h, 2118
PeriodicUpdateTimer
unpack_dms_PSMCfgChange_ind_t, 1234
periodicUpdateTimer
dms_PSMPeriodicUpdateTimerTlv, 251
PSMPeriodicUpdateTimerTlv, 910
PeriodicUpdateTimerInd
dms_PSMPeriodicUpdateTimerIndTlv, 250
PersistentLpm
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1243
PersistentTechPref
unpack_nas_GetNetworkPreference_t, 1313
persoFeature
appStats, 140
appStatus, 143
uim_appStatus, 1147
persoRetries
appStats, 140
appStatus, 143
uim_appStatus, 1147
persoState
appStats, 140
appStatus, 143
uim_appStatus, 1147
persoUnblockRetries
appStats, 140
appStatus, 143
uim_appStatus, 1147
personalizationStatus, 876
feature, 876
numFeatures, 876
unblockLeft, 876
verifyLeft, 876
pfailureCause
unpack_voice_SLQSOriginateUSSD_t, 1475
USSResp, 1567
phase
nas_rxInfo, 595
rxInfo, 979
PhyCaAggPcellInfo, 877
dl_bw_value, 877
freq, 877
iLTEbandValue, 877
NasGetLTECphyCaInfo, 636
pci, 877
TlvPresent, 877
PhyCaAggScellArray, 877
band, 878
cphy_ca_dl_bandwidth, 879
cphy_scell_info_list_len, 879
freq, 879
NasGetLTECphyCaInfo, 636
pci, 879
scell_idx, 879
scell_state, 879
TlvPresent, 879
PhyCaAggScellDlBw, 879
dl_bw_value, 879
NasGetLTECphyCaInfo, 636
TlvPresent, 879
PhyCaAggScellIndType, 880
freq, 880
NasGetLTECphyCaInfo, 636
pci, 880
scell_state, 880
TlvPresent, 881
PhyCaAggScellIndex, 879
NasGetLTECphyCaInfo, 636
scell_idx, 880
TlvPresent, 880
PhyCaAggScellInfo, 881
dl_bw_value, 883
freq, 883
iLTEbandValue, 883
NasGetLTECphyCaInfo, 636
pci, 883
scell_state, 883
TlvPresent, 883
PhysicalLayer
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
PilotEnergy
nas_NetworkStatEVDO, 556
NetworkStatEVDO, 687
PilotPN
nas_PilotSetParams, 571
PilotSetParams, 884
PilotSetData, 883
NumPilots, 883
pPilotSetInfo, 883
PilotSetParams, 884
PilotPN, 884
PilotStrength, 884

PilotType, 884
PilotStrength
nas_PilotSetParams, 571
PilotSetParams, 884
PilotType
nas_PilotSetParams, 571
PilotSetParams, 884
pin1Len
encryptedPIN1, 272
uim_encryptedPIN1, 1154
pin1Retries
appStats, 140
appStatus, 143
uim_appStatus, 1147
pin1State
appStats, 140
appStatus, 143
uim_appStatus, 1147
pin1Val
encryptedPIN1, 272
uim_encryptedPIN1, 1154
pin2Retries
appStats, 140
appStatus, 143
uim_appStatus, 1147
pin2State
appStats, 140
appStatus, 143
uim_appStatus, 1147
pinID
changeUIMPIN, 197
setPINProtection, 1016
uim_changeUIMPIN, 1152
uim_setPINProtection, 1165
uim_unblockUIMPIN, 1169
uim_verifyUIMPIN, 1170
unblockUIMPIN, 1204
verifyUIMPIN, 1569
pinLen
changeUIMPIN, 197
uim_changeUIMPIN, 1152
uim_verifyUIMPIN, 1170
verifyUIMPIN, 1569
pinLength
setPINProtection, 1016
uim_setPINProtection, 1165
pinOperation
setPINProtection, 1016
uim_setPINProtection, 1165
pinProtection
pack_uim_SetPinProtection_t, 814
pack_uim_UnblockPin_t, 822
UIMSetPinProtectionReq, 1189
pinVal
changeUIMPIN, 197
uim_changeUIMPIN, 1152
uim_verifyUIMPIN, 1170
verifyUIMPIN, 1569
pinValue
setPINProtection, 1016
uim_setPINProtection, 1165
PkQmiNasGetRFBandInfo
qaNasGetRFBandInfo.h, 2349
PkQmiNasPerformNetworkScan
qaNasPerformNetworkScan.h, 2351
PkgDescLength
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
PkgDescription
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
PkgName
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
PkgNameLength
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
pkgver
CurrentImgList, 220
unpack_dms_SLQSSwiGetFirmwareCurr_t, 1257
PktErrRate
unpack_qos_swiQosFlow_t, 1417
pktErrRate, 884
exponent, 884
multiplier, 884
PktStatElmntsV4
WdsPktStatisticsResp, 1713
PktStatElmntsV6
WdsPktStatisticsResp, 1713
plasmaIDString
pack_dms_SLQSSwiSetHostDevInfo_t, 717
unpack_dms_SLQSSwiGetHostDevInfo_t, 1260
plmn
GERANInfo, 288
LTEInfoIntrafreq, 445
nas_GERANInfo, 506
nas_LTEInfoIntrafreq, 531
nas_UMTSInfo, 616
UMTSInfo, 1196
PlmnID, 885
mcc, 885
mnc, 885
pcsDigit, 885
TlvPresent, 885
PlmnLen
nas_QmisNasSlqsNasPCICellInfo, 580
SlqsNasPCICellInfo, 1037
polarityIncluded
lineCtrlInfo, 404
voice_lineCtrlInfo, 1605
Port, 888
port, 888
range, 888
port
IPv4Info, 368
IPv6Info, 372

loc_IPv4Info, 413
loc_IPv6Info, 414
Port, 888
unpack_qos_Port_t, 1400
posDataNmea
pack_pds_SetEventReportCallback_t, 782
posSrc
unpack_pds_SetEventReport_Ind_t, 1390
Position Determination Service (PDS), 49
PositionDataNMEA
unpack_pds_SetEventReport_Ind_t, 1390
positionSrc
pack_loc_SLQSLOCInjectPosition_t, 736
PowerOffMode
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1243
PowerSaveModeConfigReq, 888
pActiveTimer, 889
pPeriodicUpdateTimer, 889
pPsmEnableState, 889
PowerSaveModeConfigResp, 889
pActiveTimer, 890
pDurationDueToOOS, 890
pDurationThreshold, 890
pEarlyWakeupTime, 890
pPeriodicUpdateTimer, 890
pPsmEnableState, 890
pRandomizationWindow, 890
pprofileid3gpp
pack_wds_SLQSStartDataSession_t, 864
pprofileid3gpp2
pack_wds_SLQSStartDataSession_t, 864
prDNSIPv4Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
prDNSIPv6Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
prPCSCFIPv4Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
prPCSCFIPv6Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
Precedence
unpack_qos_swiQosFilter_t, 1413
precedenceClass
GPRSQoS, 322
GPRSRequestedQoS, 323
LibPackGPRSRequestedQoS, 373
wds_GPRSQoS, 1690
precisionDilution
qaGobiApiCbk.h, 1919
precisionDilution_s, 890
HDOP, 890
PDOP, 890
VDOP, 890
PrefImageList, 891
listEntries, 891
listSize, 891
prefNetwork
unpack_wds_SLQSGetCurrDataSystemStat_t, 1537
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
prefVoiceSO, 891
evrcCapability, 893
homeOrigVoiceSO, 893
homePageVoiceSO, 893
namID, 893
roamOrigVoiceSO, 893
preference
pack_pds_SetXTRANetwork_t, 785
Preferred
nas_QmiNas3GppNetworkInfo, 578
SlqsNas3GppNetworkInfo, 1036
prefixLen
IPv6Addr, 369
unpack_qos_IPv6Addr_t, 1399
presentationInd
ECTNum, 268
remotePartyNum, 965
voice_ECTNum, 1601
voice_remotePartyNum, 1613
priChA
CDMAChannel, 179
nas_CDMAChannel, 479
priChB
CDMAChannel, 179
nas_CDMAChannel, 479
priSize
unpack_dms_GetFirmwareRevisions_t, 1222
pridns
unpack_wds_GetDefaultProfile_t, 1521
pridnsv6
unpack_wds_GetDefaultProfile_t, 1521
primaryDNS
pack_wds_SetDefaultProfile_t, 849
PrimaryDNSV4
unpack_wds_SLQSGetRuntimeSettings_t, 1545
PrimaryDNSV6
unpack_wds_SLQSGetRuntimeSettings_t, 1545
primaryHA
unpack_wds_GetMobileIPProfile_t, 1525
privacyPref
pack_voice_SLQSVoiceSetPreferredPrivacy_t, 839
voiceSetPrefPrivacy, 1660
priver
CurrentImgList, 220
unpack_dms_SLQSSwiGetFirmwareCurr_t, 1257
priversion_str
slqsfwinfo_s, 1034
unpack_dms_GetFirmwareInfo_t, 1220
Profile
GetAudioPathConfigReq, 292
GetAudioProfileResp, 295

GetAudioVolTLBConfigReq, 296
GetM2MAudioProfileResp, 312
GetM2MAudioVolumeReq, 313
GetM2MAVMuteReq, 313
GetM2MSpkrGainReq, 315
SetAudioPathConfigReq, 1000
SetAudioProfileReq, 1001
SetAudioVolTLBConfigReq, 1002
SetM2MAudioAVCFGReq, 1011
SetM2MAudioProfileReq, 1013
SetM2MAudioVolumeReq, 1014
SetM2MAVMuteReq, 1014
SetM2MSpkrGainReq, 1015
Profile3GPP, 893
pAPNClass, 898
pAPNDisabledFlag, 898
pAPNName, 898
pAPNnameSize, 898
pAddrAllocPref, 898
pAuthenticationPref, 898
pGPRSMinimumQoS, 898
pGPRSRequestedQos, 898
pIPv4AddrPref, 898
pIPv6AddPref, 898
pImCnFlag, 898
pPDNInactivTimeout, 898
pPDPtype, 899
pPassword, 898
pPasswordSize, 898
pPcscfAddrUsingDhcp, 898
pPcscfAddrUsingPCO, 898
pPdpAccessConFlag, 898
pPdpContext, 898
pPdpDataCompType, 898
pPdpHdrCompType, 898
pPriDNSIPv4AddPref, 899
pPriDNSIPv6addpref, 899
pPrimaryID, 899
pProfilename, 899
pProfilenameSize, 899
pQosClassID, 899
pSecDNSIPv4AddPref, 899
pSecDNSIPv6addpref, 899
pSecondaryFlag, 899
pSupportEmergencyCalls, 899
pTFTID1Params, 899
pTFTID2Params, 899
pUMTSMinQoS, 899
pUMTSMinQosSigInd, 899
pUMTSReqQoS, 899
pUMTSReqQoSSigInd, 899
pUsername, 899
pUsernameSize, 899
Profile3GPP2, 899
pAPNClass3GPP2, 903
pAPNEnabled3GPP2, 903
pAllowLinger, 903
pApnString, 903
pApnStringSize, 903
pAppPriority, 903
pAppType, 903
pAuthPassword, 903
pAuthPasswordSize, 904
pAuthProtocol, 904
pAuthRetryCount, 904
pAuthTimeout, 904
pDataMode, 904
pDataRate, 904
pIpcpAckTimeout, 904
pIpcpCreqRetryCount, 904
pIsPcscfAddressNedded, 904
pLcpAckTimeout, 904
pLcpCreqRetryCount, 904
pNegoDnsSrvrPref, 904
pPDNInactivTimeout3GPP2, 904
pPdnType, 904
pPppSessCloseTimer1x, 904
pPppSessCloseTimerDO, 904
pPriV6DnsAddress, 904
pPrimaryV4DnsAddress, 904
pRATType, 904
pSecV6DnsAddress, 904
pSecondaryV4DnsAddress, 904
pUserId, 904
pUserIdSize, 904
ProfileID
_GetProfileSettingIn, 70
unpack_wds_SLQSGetRuntimeSettings_t, 1545
ProfileId
pack_wds_SLQSGetProfileSettings_t, 857
profileId
wds_DHCPProfileIdTlv, 1686
wds_DHCPv4ProfileId, 1688
WdsDHCPv4ProfileId, 1709
wdsDhcpv4ProfileId, 1709
ProfileId3GPP2
unpack_qos_swiQosFlow_t, 1417
ProfileIdTlv
unpack_wds_DHCPv4ClientLease_ind_t, 1515
ProfileIdentifier, 904
profileIndex, 905
profileType, 905
ProfileIndex
PackCreateProfileOut, 868
profileIndex
pack_wds_SLQSDeleteProfile_t, 854
ProfileIdentifier, 905
SLQSDeleteProfileParams, 1033
wds_ProfileIdentifier, 1695
profileList
unpack_wds_SLQSGet3GPPConfigItem_t, 1536
ProfileName
unpack_wds_SLQSGetRuntimeSettings_t, 1545
ProfileType
_GetProfileSettingIn, 70
pack_wds_SLQSGetProfileSettings_t, 857

PackCreateProfileOut, 868
unpack_wds_SLQSGetProfileSettings_t, 1542
profileType
pack_wds_SetDefaultProfile_t, 849
pack_wds_SLQSDeleteProfile_t, 854
ProfileIdentifier, 905
SLQSDeleteProfileParams, 1033
wds_DHCPProfileIdTlv, 1686
wds_DHCPv4ProfileId, 1688
wds_ProfileIdentifier, 1695
WdsDHCPv4ProfileId, 1709
wdsDhcpv4ProfileId, 1709
profiletype
pack_wds_GetDefaultProfile_t, 843
Protocol
unpack_nas_GetCDMANetworkParameters_t, 1308
protocolSubtypeElement, 905
AccessMac, 906
AuthProt, 906
ControlMac, 906
EncryptProt, 906
ForwardMac, 906
IdleState, 906
KeyExchange, 906
MultDisc, 906
PhysicalLayer, 906
ReverseMac, 906
SecProt, 906
VirtStream, 907
ProvisionStatus
CLIPResp, 201
CLIRResp, 202
CNAPResp, 204
COLPResp, 205
COLRResp, 205
voice_CLIPResp, 1592
voice_CLIRResp, 1593
voice_CNAPResp, 1593
voice_COLPResp, 1594
voice_COLRResp, 1595
psAttachState
nas_servSystem, 600
NASServingSystemInfo, 671
ServingSystemInfo, 994
servSystem, 996
psBarStatus
CallBarringSysInfo, 160
callBarStatus, 161
nas_CallBarringSysInfo, 477
nas_callBarStatus, 478
psState
CommInfo, 207
nas_CommInfo, 490
psc
nas_UMTSInfo, 616
nas_wcdmaCellInfo, 620
nas_WCDMASysInfo, 625
UMTSInfo, 1196
wcdmaCellInfo, 1669
WCDMASysInfo, 1678
pscValid
nas_WCDMASysInfo, 625
WCDMASysInfo, 1678
pscsfIPv4Addr
PCSCFIPv4ServerAddressList, 871
wds_PCSCFIPv4ServerAddressList, 1694
psetting
unpack_wds_GetAutoconnect_t, 1515
psid
pack_wds_SLQSStopDataSession_t, 865
unpack_wds_SLQSStartDataSession_t, 1556
puk1Retries
appStats, 140
appStatus, 143
uim_appStatus, 1147
puk2Retries
appStats, 140
appStatus, 143
uim_appStatus, 1147
pukLen
uim_unblockUIMPIN, 1169
unblockUIMPIN, 1204
pukVal
uim_unblockUIMPIN, 1169
unblockUIMPIN, 1204
pukValue
pack_dms_UIMUnblockPIN_t, 723
pv4sessionId
WdsIpAddressInfoReq, 1710
pv6sessionId
WdsIpAddressInfoReq, 1710
pwrDenialTime
lineCtrlInfo, 404
voice_lineCtrlInfo, 1605

QMI_LITE_WDS_CURRENT_CALL_DB_MASK
wds.h, 2478
QMI_LITE_WDS_LAST_CALL_DB_MASK
wds.h, 2478
QMI_SAR_RF_STATE_1
qaGobiApiSar.h, 2167
QMI_SAR_RF_STATE_2
qaGobiApiSar.h, 2167
QMI_SAR_RF_STATE_3
qaGobiApiSar.h, 2167
QMI_SAR_RF_STATE_4
qaGobiApiSar.h, 2167
QMI_SAR_RF_STATE_5
qaGobiApiSar.h, 2167
QMI_SAR_RF_STATE_6
qaGobiApiSar.h, 2167
QMI_SAR_RF_STATE_7
qaGobiApiSar.h, 2167
QMI_SAR_RF_STATE_8
qaGobiApiSar.h, 2167
QMI_SAR_RF_STATE_DEFAULT

qaGobiApiSar.h, 2167
QMI_WDS_CURRENT_CALL_DB_MASK
qaGobiApiWds.h, 2312
QMI_WDS_LAST_CALL_DB_MASK
qaGobiApiWds.h, 2312
QCI
LibPackQosClassID, 398
QosClassID, 954
QCWWAN2kConnect
qaGobiApiDcs.h, 1995
QCWWAN2kEnumerateDevices
qaGobiApiDcs.h, 1995
QCWWAN2kGetConnectedDeviceID
qaGobiApiDcs.h, 1995
QCWWANConnect
qaGobiApiDcs.h, 1996
QCWWANDisconnect
qaGobiApiDcs.h, 1996
QCWWANEnumerateDevices
qaGobiApiDcs.h, 1997
QFlowState
unpack_qos_QosFlowInfo_t, 1402
QLIC
DeviceConfigDetail, 243
nas_DeviceConfigDetail, 497
qaCbkCatEventReportInd.h
eTLV_CBK_ALPHA_IDENTIFIER, 1896
eTLV_CBK_DISPLAY_TEXT, 1896
eTLV_CBK_END_PROACTIVE_SESSION, 1897
eTLV_CBK_GET_IN_KEY, 1896
eTLV_CBK_GET_INPUT, 1896
eTLV_CBK_LANGUAGE_NOTIFICATION, 1897
eTLV_CBK_REFRESH, 1897
eTLV_CBK_SELECT_ITEM, 1896
eTLV_CBK_SETUP_EVENT_LIST, 1896
eTLV_CBK_SETUP_IDLE_MODE_TEXT, 1897
eTLV_CBK_SETUP_MENU, 1896
eTLV_END_PROACTIVE_SESSION_LENGTH, 1897
eTLV_REFRESH_LENGTH, 1897
eTLV_SETUP_EVENT_LIST_LENGTH, 1897
qaCbkSwiOmaDmEventReportInd.h
eTLV_IND_OMA_DM_CONFIG, 1898
eTLV_IND_OMA_DM_FOTA, 1898
eTLV_IND_OMA_DM_NOT, 1898
qaGobiApiCbk.h
DEVICE_STATE_BOOT, 1954
DEVICE_STATE_DISCONNECTED, 1954
DEVICE_STATE_READY, 1954
DEVICE_STATE_SERIAL_ONLY, 1954
eQA_QMI_SVC_NA, 1954
eQA_QMI_SVC_NAS, 1954
eQA_QMI_SVC_WDS, 1954
SMS_EVENT_ETWS, 1954
SMS_EVENT_ETWS_PLMN, 1954
SMS_EVENT_MESSAGE_MODE, 1954
SMS_EVENT_MT_MESSAGE, 1954
SMS_EVENT_SMS_ON_IMS, 1954
SMS_EVENT_SMSC_ADDRESS, 1954
SMS_EVENT_TRANSFER_ROUTE_MT_MESSAGE, 1954
SYS_SRV_DOMAIN_CAMPED, 1954
SYS_SRV_DOMAIN_CS_ONLY, 1954
SYS_SRV_DOMAIN_CS_PS, 1954
SYS_SRV_DOMAIN_NO_SRV, 1954
SYS_SRV_DOMAIN_PS_ONLY, 1954
qaGobiApiFms.h
eGOBI_DEV_SERIES_9X07_9X50, 2047
eGOBI_DEV_SERIES_9X15, 2047
eGOBI_DEV_SERIES_9X30, 2047
eGOBI_DEV_SERIES_G3K, 2047
eGOBI_DEV_SERIES_NON_GOBI, 2047
eGOBI_DEV_SERIES_SIERRA_GOBI, 2047
eGOBI_DEV_SERIES_UNKNOWN, 2047
eGOBI_IMG_CAR_3, 2048
eGOBI_IMG_CAR_AERIS, 2048
eGOBI_IMG_CAR_ALLTEL, 2047
eGOBI_IMG_CAR_AMX_TELCEL, 2048
eGOBI_IMG_CAR_ATT, 2048
eGOBI_IMG_CAR_BELL, 2047
eGOBI_IMG_CAR_BHARTI, 2048
eGOBI_IMG_CAR_BRASIL_VIVO, 2048
eGOBI_IMG_CAR_CHINA_MOBILE, 2048
eGOBI_IMG_CAR_CHINA_TELECOM, 2048
eGOBI_IMG_CAR_CHINA_UNICOM, 2047
eGOBI_IMG_CAR_EMOBILE, 2048
eGOBI_IMG_CAR_FACTORY, 2047
eGOBI_IMG_CAR_GENERIC, 2047
eGOBI_IMG_CAR_GENERIC_CDMA, 2048
eGOBI_IMG_CAR_IUSACELL, 2048
eGOBI_IMG_CAR_KDDI, 2048
eGOBI_IMG_CAR_KT_FREETEL, 2048
eGOBI_IMG_CAR_LEAP, 2047
eGOBI_IMG_CAR_METROPCS, 2047
eGOBI_IMG_CAR_NETCOM, 2048
eGOBI_IMG_CAR_NORF, 2047
eGOBI_IMG_CAR_NTT_DOCOMO, 2048
eGOBI_IMG_CAR_O2, 2048
eGOBI_IMG_CAR_OMH, 2048
eGOBI_IMG_CAR_ORANGE, 2048
eGOBI_IMG_CAR_RELIANCE1, 2047
eGOBI_IMG_CAR_RELIANCE2, 2048
eGOBI_IMG_CAR_ROGERS, 2048
eGOBI_IMG_CAR_SFR, 2048
eGOBI_IMG_CAR_SINGTEL_OPTUS, 2048
eGOBI_IMG_CAR_SK_TELCOM1, 2047
eGOBI_IMG_CAR_SK_TELCOM2, 2048
eGOBI_IMG_CAR_SOFTBANK, 2048
eGOBI_IMG_CAR_SPRINT, 2047
eGOBI_IMG_CAR_SWISSCOM, 2048
eGOBI_IMG_CAR_TATA, 2047
eGOBI_IMG_CAR_TELCOM_ITALIA, 2048
eGOBI_IMG_CAR_TELCOM_NZ, 2047
eGOBI_IMG_CAR_TELEFONICA, 2048
eGOBI_IMG_CAR_TELENOR, 2048
eGOBI_IMG_CAR_TELIASONERA, 2048

eGOBI_IMG_CAR_TELSTRA1, 2047
eGOBI_IMG_CAR_TELSTRA2, 2048
eGOBI_IMG_CAR_TELUS, 2047
eGOBI_IMG_CAR_TMOBILE, 2048
eGOBI_IMG_CAR_US, 2047
eGOBI_IMG_CAR_VERIZON, 2047
eGOBI_IMG_CAR_VODAFONE, 2048
eGOBI_IMG_GPS_ASSISTED, 2048
eGOBI_IMG_GPS_NO_XTRA, 2048
eGOBI_IMG_GPS_NONE, 2048
eGOBI_IMG_GPS_STAND_ALONE, 2048
eGOBI_IMG_REG_ASIA, 2049
eGOBI_IMG_REG_AUS, 2049
eGOBI_IMG_REG_EU, 2049
eGOBI_IMG_REG_GLOBAL, 2049
eGOBI_IMG_REG_LA, 2049
eGOBI_IMG_REG_NA, 2049
eGOBI_IMG_TECH_CDMA, 2049
eGOBI_IMG_TECH_UMTS, 2049
eGobi_DEV_SERIES_MC83, 2047
qaGobiApiNas.h
eNAS_LTE_CPHY_CA_BW_NRB_100, 2108
eNAS_LTE_CPHY_CA_BW_NRB_15, 2108
eNAS_LTE_CPHY_CA_BW_NRB_25, 2108
eNAS_LTE_CPHY_CA_BW_NRB_50, 2108
eNAS_LTE_CPHY_CA_BW_NRB_6, 2108
eNAS_LTE_CPHY_CA_BW_NRB_75, 2108
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_ACTIVATED, 2108
eNAS_LTE_CPHY_SCELL_STATE_CONFIGURED_DEACTIVATED, 2108
eNAS_LTE_CPHY_SCELL_STATE_DECONFIGURED, 2108
eNAS_RADIO_IF_GSM, 2106
eNAS_RADIO_IF_LTE, 2106
eNAS_RADIO_IF_TDSCDMA, 2106
eNAS_RADIO_IF_UMTS, 2106
eSYS_SRV_DOMAIN_CAMPED, 2106
eSYS_SRV_DOMAIN_CS_ONLY, 2106
eSYS_SRV_DOMAIN_CS_PS, 2106
eSYS_SRV_DOMAIN_NO_SRV, 2106
eSYS_SRV_DOMAIN_PS_ONLY, 2106
eSYS_SRV_DOMAIN_UNKNOWN, 2106
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_1, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_10, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_11, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_12, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_125, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_126, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_127, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_13, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_14, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_17, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_18, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_19, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_2, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_20, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_21, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_23, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_24, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_25, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_250, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_26, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_27, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_28, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_29, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_3, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_30, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_31, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_32, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_33, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_34, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_35, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_36, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_37, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_38, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_39, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_4, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_40, 2107

LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_41, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_42, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_43, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_46, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_47, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_48, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_5, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_6, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_66, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_7, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_71, 2108
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_8, 2107
LTE_BAND_CLASS_E_UTRA_OPERATING_BAND_9, 2107
qaGobiApiPds.h
eSetServiceAutomaticTrackingDisable, 2145
eSetServiceAutomaticTrackingEnable, 2145
qaGobiApiSar.h
QMI_SAR_RF_STATE_1, 2167
QMI_SAR_RF_STATE_2, 2167
QMI_SAR_RF_STATE_3, 2167
QMI_SAR_RF_STATE_4, 2167
QMI_SAR_RF_STATE_5, 2167
QMI_SAR_RF_STATE_6, 2167
QMI_SAR_RF_STATE_7, 2167
QMI_SAR_RF_STATE_8, 2167
QMI_SAR_RF_STATE_DEFAULT, 2167
qaGobiApiSms.h
eTIMESTEMP_DAY, 2175
eTIMESTEMP_END, 2175
eTIMESTEMP_HOUR, 2175
eTIMESTEMP_MINUTE, 2175
eTIMESTEMP_MONTH, 2175
eTIMESTEMP_SECOND, 2175
eTIMESTEMP_START, 2175
eTIMESTEMP_TIMEZONE, 2175
eTIMESTEMP_YEAR, 2175
qaGobiApiVoice.h
VOICE_SUPS_SRV_CLASS_DATA, 2287
VOICE_SUPS_SRV_CLASS_DATACIRCUITASYNC, 2287
VOICE_SUPS_SRV_CLASS_DATACIRCUITSYNC, 2287
VOICE_SUPS_SRV_CLASS_FAX, 2287
VOICE_SUPS_SRV_CLASS_NONE, 2287
VOICE_SUPS_SRV_CLASS_PACKETACCESS, 2287
VOICE_SUPS_SRV_CLASS_PADACCESS, 2287
VOICE_SUPS_SRV_CLASS_SMS, 2287
VOICE_SUPS_SRV_CLASS_VOICE, 2287
qaGobiApiWds.h
QMI_WDS_CURRENT_CALL_DB_MASK, 2312
QMI_WDS_LAST_CALL_DB_MASK, 2312
WDSNUMPDPS, 2312
WDSPDP1IDX, 2312
WDSPDP2IDX, 2312
WDSPDP3IDX, 2312
WDSPDP4IDX, 2312
WDSPDP5IDX, 2312
WDSPDP6IDX, 2312
WDSPDP7IDX, 2312
WDSPDP8IDX, 2312
qaNasGetRFBandInfo.h
eTLV_LTE_OPERATIONAL_MODE, 2349
eTLV_RF_BAND_INFO, 2349
eTLV_RF_BANDWIDTH_INFO, 2349
eTLV_RF_DEDICATED_BAND_INFO, 2349
eTLV_RF_EXT_FORMAT_BAND_INFO, 2349
qaNasPerformNetworkScan.h
eTLV_3GPP_NETWORK_INFO, 2350
qaCbkCatEventReportInd.h, 1895
UpkQmiCbkCatEventReportInd, 1897
qaCbkSwiOmaDmEventReportInd.h, 1897
UpkQmiCbkSwiOmaDmEventReportInd, 1898
UpkQmiCbkSwiOmaDmEventReportIndExt, 1898
qaGobiApiAudio.h, 1898
SLQSGetAudioPathConfig, 1899
SLQSGetAudioProfile, 1899
SLQSGetAudioVolTLBConfig, 1900
SLQSSetAudioPathConfig, 1900
SLQSSetAudioProfile, 1901
SLQSSetAudioVolTLBConfig, 1901
qaGobiApiCat.h, 1902
CATSendEnvelopeCommand, 1902
CATSendTerminalResponse, 1902
qaGobiApiCbk.h, 1903
accelAcceptReady, 1914
accelTempAcceptReady, 1914
CBK_ENABLE_EVENT, 1912
CBK_NOCHANGE, 1912
DEREGISTER_EVENT, 1912
DEREGISTER_SRV, 1912
device_state_enum, 1954
eDevState, 1915
eQaQMIService, 1954
eSMSEventType, 1915
EVENT_MASK_CARD, 1912
FIRST_INSTANCE, 1912
gpsTime, 1915
gyroAcceptReady, 1915
gyroTempAcceptReady, 1916
INVALID_INSTACNE, 1912
IPV4, 1912

IPV4V6, 1912
IPV6, 1912
iSLQSSetDUNCallInfoCallback, 1955
iSLQSSetSignalStrengthsCallback, 1955
iSLQSSetWdsFirstInstEventCallback, 1955
iSLQSSetWdsSecondInstEventCallback, 1955
iSLQSSetWdsThirdInstEventCallback, 1955
iSLQSSetWdsXferStatsFirstInstCallback, 1955
iSLQSSetWdsXferStatsSecondInstCallback, 1955
iSetCATEventCallback, 1955
iSetSignalStrengthCallback, 1955
LteNasReleaseInfo, 1916
MAX_NO_OF_CALLS, 1913
MAX_NO_OF_FILES, 1913
MAX_NO_OF_SLOTS, 1913
MAX_PATH_LENGTH, 1913
MAXUSSDLENGTH, 1913
modemTempNotification, 1917
modemUIMStatusNotification, 1917
NAS_SRV, 1913
NUM_OF_SET, 1913
PDS_SRV, 1913
packetSrvStatus, 1917
precisionDilution, 1919
REGISTER_EVENT, 1913
REGISTER_SRV, 1913
ResetInfoNotification, 1919
SECOND_INSTANCE, 1913
SLQSNasEdrxChangeInfoCallBack, 1970
SLQSNasNetworkRejectCallback, 1971
SLQSNasNetworkTimeCallBack, 1971
SLQSNasSigInfo2CallBack, 1971
SLQSNasSigInfoCallBack, 1972
SLQSNasSwiOTAMessageCallback, 1972
SLQSNasSysInfoCallBack, 1973
SLQSNasTimerCallback, 1973
SLQSSetBandPreferenceCbk, 1973
SLQSSetDHCPv4ClientLeaseStatusCallback, 1974
SLQSSetDUNCallInfoCallback, 1975
SLQSSetDataSystemStatusCallback, 1974
SLQSSetIMSAPdpStatusCallback, 1975
SLQSSetIMSARatStatusCallback, 1975
SLQSSetIMSARegStatusCallback, 1976
SLQSSetIMSASvcStatusCallback, 1976
SLQSSetIMSSMSConfigCallback, 1977
SLQSSetIMSUserConfigCallback, 1977
SLQSSetIMSVoIPConfigCallback, 1978
SLQSSetLocInjectPositionCallback, 1978
SLQSSetLocInjectUTCTimeCallback, 1978
SLQSSetModemTempCallback, 1978
SLQSSetPacketSrvStatusCallback, 1979
SLQSSetQosEventCallback, 1979
SLQSSetQosNWStatusCallback, 1980
SLQSSetQosPriEventCallback, 1980
SLQSSetQosStatusCallback, 1980
SLQSSetRegMgrConfigCallback, 1981
SLQSSetSDKTerminatedCallback, 1981
SLQSSetSIPConfigCallback, 1983
SLQSSetSMSEventCallback, 1984
SLQSSetServingSystemCallback, 1982
SLQSSetSessionStateCallback, 1982
SLQSSetSignalStrengthsCallback, 1983
SLQSSetSwiGetResetInfoCallback, 1984
SLQSSetSwiHDRPersCallback, 1984
SLQSSetSysSelectionPrefCallBack, 1985
SLQSSetTransLayerInfoCallback, 1985
SLQSSetTransNWRegInfoCallback, 1985
SLQSSetUIMStatusCallback, 1986
SLQSSetWdsEventCallback, 1986
SLQSSetWdsTransferStatisticCallback, 1987
SLQSSwiAVMSEventReportCallback, 1988
SLQSTmdMitigationLvlRptCallback, 1988
SLQSUIMSetRefreshCallBack, 1988
SLQSUIMSetStatusChangeCallBack, 1988
SLQSVoiceInfoRecCallback, 1989
SLQSVoiceSetAllCallStatusCallBack, 1989
SLQSVoiceSetDTMFEventCallBack, 1990
SLQSVoiceSetOTASPStatusCallBack, 1990
SLQSVoiceSetPrivacyChangeCallBack, 1990
SLQSVoiceSetSUPSCallBack, 1991
SLQSVoiceSetSUPSNotificationCallback, 1991
SLQSWmsAsyncRawSendCallBack, 1992
SLQSWmsMemoryFullCallBack, 1992
SLQSWmsMessageWaitingCallBack, 1993
SMSAsyncRawSend, 1921
SMSCAddressInfo, 1922
SMSEtwsMessageInfo, 1922
SMSEtwsPlmnInfo, 1922
SMSEventInfo, 1922
SMSEventType, 1954
SMSMTMessageInfo, 1923
SMSMessageModeInfo, 1923
SMSOnIMSInfo, 1924
SMSTransferRouteMTMessageInfo, 1924
sensorDataUsage, 1920
sessionInformation, 1920
sessionInformationExt, 1920
SetActivationStatusCallback, 1955
SetCATEventCallback, 1955
SetCfgParamChangeCallback, 1956
SetDataCapabilitiesCallback, 1957
SetDeviceStateChangeCbk, 1957
SetFwDldCompletionCbk, 1957
SetGPSCallback, 1958
SetLURejectCallback, 1963
SetLocBestAvailPosCallback, 1958
SetLocCradleMountCallback, 1959
SetLocDeleteAssistDataCallback, 1959
SetLocEngineStateCallback, 1959
SetLocEventMaskNMEACallback, 1959
SetLocEventPositionCallback, 1960
SetLocEventTimeSyncCallback, 1960
SetLocGetOpModeCallback, 1960
SetLocGetServerCallback, 1960
SetLocGnssSvInfoCallback, 1961

SetLocInjectSensorDataCallback, 1961
SetLocInjectTimeCallback, 1961
SetLocOpModeCallback, 1962
SetLocSensorStreamingCallback, 1962
SetLocSetExtPowerConfigCallback, 1962
SetLocSetServerCallback, 1962
SetMobileIPStatusCallback, 1963
SetNMEACallback, 1965
SetNasLTECphyCaIndCallback, 1964
SetNetChangeCbk, 1964
SetNewSMSCallback, 1965
SetOMADMStateCallback, 1965
SetPDSStateCallback, 1966
SetPowerCallback, 1966
SetRFInfoCallback, 1966
SetRMTransferStatisticsCallback, 1967
SetRankIndicatorCallback, 1966
SetRoamingIndicatorCallback, 1967
SetSLQSOMADMAlertCallback, 1968
SetSLQSOMADMAlertCallbackExt, 1968
SetSignalStrengthCallback, 1968
SetUSSDNoWaitIndicationCallback, 1970
SetUSSDNotificationCallback, 1969
SetUSSDReleaseCallback, 1970
SetUimSlotStatusChangeCallback, 1969
svUsedforFix, 1924
SwiAvmsEventInd, 1925
SwiOTAMsg, 1925
tFNASwiLTECphyCaInfo, 1926
tFNASwiOTAMsg, 1926
tFNActivationStatus, 1925
tFNAllCallStatus, 1926
tFNAsyncRawSend, 1926
tFNBandPreference, 1927
tFNBestAvailPos, 1928
tFNCATEvent, 1929
tFNCbkUimSlotStatusChangeInd, 1929
tFNDHCPv4ClientLeaseStatus, 1931
tFNDTMFEvent, 1931
tFNDUNCallInfo, 1931
tFNDataCapabilities, 1929
tFNDataSysStatus, 1930
tFNDelAssistData, 1930
tFNDeviceStateChange, 1930
tFNEventNmea, 1931
tFNEventPosition, 1931
tFNFwDldCompletion, 1932
tFNGetOpMode, 1932
tFNGetServer, 1932
tFNGnssSvInfo, 1932
tFNHDRPersonaity, 1933
tFNImsRegMgrConfig, 1934
tFNImsSIPConfig, 1934
tFNImsSMSConfig, 1934
tFNImsUserConfig, 1934
tFNImsVoIPConfig, 1934
tFNImsaPdpStatus, 1933
tFNImsaRatStatus, 1933
tFNImsaRegStatus, 1933
tFNImsaSvcStatus, 1933
tFNInfoRec, 1935
tFNInjectPosition, 1935
tFNInjectSensorData, 1935
tFNInjectTimeStatus, 1935
tFNInjectUTCTime, 1936
tFNLUReject, 1936
tFNMemoryFull, 1938
tFNMessageWaiting, 1938
tFNMitiLvlRpt, 1938
tFNMobileIPStatus, 1938
tFNModemTempInfo, 1938
tFNNasEdrxChangeInfo, 1939
tFNNasTimer, 1939
tFNNet, 1939
tFNNetworkReject, 1939
tFNNetworkTime, 1940
tFNNewGPS, 1940
tFNNewNMEA, 1940
tFNNewRMTransferStatistics, 1941
tFNNewSMS, 1941
tFNOMADMState, 1941
tFNOTASPStatus, 1942
tFNOpMode, 1942
tFNPDSState, 1943
tFNPSMCfgParamChange, 1944
tFNPacketSrvState, 1943
tFNPower, 1943
tFNPrivacyChange, 1943
tFNQosNWStatus, 1944
tFNQosPriEvent, 1944
tFNQosStatus, 1944
tFNRFInfo, 1946
tFNRankIndicator, 1945
tFNResetInfo, 1945
tFNRoamingIndicator, 1946
tFNSDKTerminated, 1946
tFNSLQSOMADMAlert, 1948
tFNSLQSQOSEvent, 1949
tFNSLQSSessionState, 1949
tFNSLQSSignalStrengths, 1949
tFNSLQSWDSEvent, 1949
tFNSMSEvents, 1950
tFNSUPSInfo, 1950
tFNSUPSNotification, 1950
tFNSensorStreaming, 1947
tFNServingSystem, 1947
tFNSetCradleMount, 1947
tFNSetEngineState, 1947
tFNSetEventTimeSync, 1947
tFNSetExtPowerConfig, 1948
tFNSetServer, 1948
tFNSigInfo, 1948
tFNSignalStrength, 1948
tFNSwiAvmEventReport, 1950
tFNSysInfo, 1950
tFNSysSelectionPref, 1951

tFNUIMRefresh, 1951
tFNUIMStatusChangeInfo, 1951
tFNUIMStatusInfo, 1952
tFNUSSDNoWaitIndication, 1952
tFNUSSDNotification, 1952
tFNUSSDRelease, 1952
tFNtransLayerInfo, 1951
tFNtransNWRegInfo, 1951
THIRD_INSTANCE, 1914
transLayerNotification, 1953
transNWRegInfoNotification, 1953
USSD_DCS_8BIT, 1914
USSD_DCS_ASCII, 1914
USSD_DCS_UCS2, 1914
VOICE_SRV, 1914
WDS_SRV, 1914
qaGobiApiDcs.h, 1993
GetQmapIsSupported, 1994
LEN, 1994
PORTNAM_LEN, 1994
QCWWAN2kConnect, 1995
QCWWAN2kEnumerateDevices, 1995
QCWWAN2kGetConnectedDeviceID, 1995
QCWWANConnect, 1996
QCWWANDisconnect, 1996
QCWWANEnumerateDevices, 1997
SLQSGetDeviceMode, 1998
SLQSGetNetStatistic, 1998
SLQSGetUsbPortNames, 1999
SLQSKillSDKProcess, 1999
SLQSSetLoggingMask, 2000
SLQSStart, 2000
SLQSStart_AVAgent, 2001
SLQSStartSrv, 2001
SetQmapIPTable, 1997
SetQmapIPv6Table, 1997
SetSDKImagePath, 1998
qaGobiApiDms.h, 2002
ActivateAutomatic, 2011
custFeaturesInfo, 2005
custFeaturesSetting, 2006
dmsCurrentPRLInfo, 2007
ERIFileparams, 2008
GetActivationState, 2012
GetDeviceCapabilities, 2012
GetFirmwareRevision, 2013
GetFirmwareRevisions, 2014
GetHardwareRevision, 2014
GetIMSI, 2015
GetManufacturer, 2015
GetModelID, 2016
GetNetworkTime, 2016
GetOfflineReason, 2017
GetPRLVersion, 2018
GetPower, 2018
GetSerialNumbers, 2018
GetVoiceNumber, 2019
MAX_CUST_ID_LEN, 2005
MAX_FSN_LENGTH, 2005
ResetToFactoryDefaults, 2020
SLQSDmsSwiGetPCInfo, 2021
SLQSDmsSwiGetResetInfo, 2021
SLQSDmsSwiGetUimSelection, 2021
SLQSDmsSwiIndicationRegister, 2021
SLQSGetBandCapabilities, 2021
SLQSGetBandCapability, 2022
SLQSGetCurrentPRLInfo, 2024
SLQSGetCustFeatures, 2024
SLQSGetCustFeaturesV2, 2025
SLQSGetERIFile, 2025
SLQSGetPowerSaveModeConfig, 2025
SLQSGetSerialNumbers, 2026
SLQSSetCustFeatures, 2026
SLQSSetCustFeaturesV2, 2027
SLQSSetPowerSaveModeConfig, 2027
SLQSSwiClearDyingGaspStatistics, 2028
SLQSSwiDmsUimSelect, 2028
SLQSSwiGetCrashAction, 2028
SLQSSwiGetCrashInfo, 2029
SLQSSwiGetDyingGaspCfg, 2029
SLQSSwiGetDyingGaspStatistics, 2029
SLQSSwiGetFSN, 2030
SLQSSwiGetFwUpdateStatus, 2030
SLQSSwiGetHostDevInfo, 2031
SLQSSwiGetHostDevInfoParams, 2009
SLQSSwiGetOSInfo, 2031
SLQSSwiGetOSInfoParams, 2009
SLQSSwiGetSerialNoExt, 2031
SLQSSwiGetSerialNoExtParams, 2010
SLQSSwiGetUSBComp, 2032
SLQSSwiSetCrashAction, 2032
SLQSSwiSetDyingGaspCfg, 2033
SLQSSwiSetHostDevInfo, 2033
SLQSSwiSetHostDevInfoParams, 2010
SLQSSwiSetOSInfo, 2034
SLQSSwiSetOSInfoParams, 2011
SLQSSwiSetUSBComp, 2034
SLQSUIMGetState, 2034
serialNumbersInfo, 2008
SetPower, 2020
UIMChangePIN, 2035
UIMGetControlKeyStatus, 2036
UIMGetICCID, 2037
UIMGetPINStatus, 2037
UIMSetControlKeyProtection, 2038
UIMSetPINProtection, 2039
UIMUnblockControlKey, 2040
UIMUnblockPIN, 2040
UIMVerifyPIN, 2041
ValidateSPC, 2042
qaGobiApiFms.h, 2042
BUILD_ID_LEN, 2046
DEVICE_OFFLINE, 2046
DEVICE_RESET, 2046
DEVICE_SHUTDOWN, 2046
DeleteStoredImage, 2049

DownloadToSlot, 2049
eGetDeviceSeries, 2050
eGobiDeviceSeries, 2047
eGobiImageCarrier, 2047
eGobiImageGPS, 2048
eGobiImageRegion, 2048
eGobiImageTech, 2049
GetImageStore, 2051
GetImagesPreference, 2050
GetStoredImages, 2051
IMG_ID_LEN, 2046
IMGDETAILS_LEN, 2046
PRI_UPDATE_FAIL, 2046
SLQSDownloadFirmwareToSlot, 2053
SLQSGetBootVersionNumber, 2054
SLQSGetFirmwareInfo, 2055
SLQSGetImageInfo, 2055
SLQSGetImageInfo_9x15, 2056
SLQSGetImageInfoMC77xx, 2056
SLQSGetImageInfoMC83xx, 2057
SLQSGetImagePartNumber, 2057
SLQSGetValidFwPriCombinations, 2058
SLQSIsBootloaderDebugEnabled, 2058
SLQSIsSpkgFormatRequired, 2059
SLQSSetCrashStateCheckIgnore, 2059
SLQSSetSIMBasedImageSwitching, 2060
SLQSSetSpkgFormatRequired, 2060
SLQSSwiGetAllCarrierImages, 2060
SLQSSwiGetFirmwareCurr, 2061
SLQSUpgradeFirmware9x07, 2061
SLQSUpgradeFirmware9x15, 2062
SetImagePath, 2052
SetImagesPreference, 2052
UNIQUE_ID_LEN, 2047
upgrade_9x07_9x50_fw, 2063
upgrade_mc77xx_fw, 2063
UpgradeFirmware2k, 2063
qaGobiApiIms.h, 2064
SLQSGetIMSSMSConfig, 2065
SLQSGetIMSUserConfig, 2065
SLQSGetIMSVoIPConfig, 2066
SLQSGetRegMgrConfig, 2066
SLQSGetSIPConfig, 2067
SLQSImsConfigIndicationRegister, 2067
SLQSSetIMSSMSConfig, 2068
SLQSSetIMSUserConfig, 2068
SLQSSetIMSVoIPConfig, 2069
SLQSSetRegMgrConfig, 2069
SLQSSetSIPConfig, 2070
qaGobiApiImsa.h, 2070
SLQSGetIMSARegStatus, 2071
SLQSGetIMSAServiceStatus, 2071
SLQSGetIMSASupportedFields, 2072
SLQSGetIMSASupportedMsg, 2072
SLQSRegisterIMSAIndication, 2073
qaGobiApiLoc.h, 2073
SLQSLOCDelAssData, 2075
SLQSLOCEventRegister, 2075
SLQSLOCGetBestAvailPos, 2075
SLQSLOCGetOpMode, 2076
SLQSLOCGetServer, 2076
SLQSLOCInjectPosition, 2077
SLQSLOCInjectSensorData, 2077
SLQSLOCInjectUTCTime, 2077
SLQSLOCSetCradleMountConfig, 2078
SLQSLOCSetExtPowerState, 2078
SLQSLOCSetOpMode, 2079
SLQSLOCSetServer, 2079
SLQSLOCStart, 2080
SLQSLOCStop, 2080
SwiLocGetAutoStart, 2081
SwiLocSetAutoStart, 2081
qaGobiApiNas.h, 2081
eSYS_SRV_DOMAIN, 2106
GetACCOLC, 2108
GetANAAAAuthenticationStatus, 2108
GetCDMANetworkParameters, 2109
GetHomeNetwork, 2111
GetHomeNetwork3GPP2, 2112
GetNetworkPreference, 2113
GetRFInfo, 2114
GetServingNetwork, 2114
GetServingNetworkCapabilities, 2116
GetSignalStrengths, 2117
IMSI_M_S1_LENGTH, 2089
IMSI_M_S2_LENGTH, 2089
InitiateDomainAttach, 2117
InitiateNetworkRegistration, 2118
LTEBandPrefExtTlv, 2090
MAX_PILOT_SETS, 2089
NAM_NAME_LENGTH, 2089
NR5gBandPrefTlv, 2090
PLMN_LENGTH, 2089
PerformNetworkScan, 2118
SLQSConfigSigInfo, 2121
SLQSGetErrorRate, 2122
SLQSGetNetworkTime, 2122
SLQSGetOperatorNameData, 2123
SLQSGetPLMNName, 2123
SLQSGetServingSystem, 2124
SLQSGetSignalStrength, 2124
SLQSGetSysSelectionPref, 2124
SLQSGetSysSelectionPrefExt, 2125
SLQSInitiateNetworkRegistration, 2125
SLQSNASGetForbiddenNetworks, 2128
SLQSNASGetLTECPHYCaInfo, 2129
SLQSNASGeteDRXParams, 2127
SLQSNASGeteDRXParamsExt, 2127
SLQSNASSeteDRXParams, 2133
SLQSNASSwiGetChannelLock, 2133
SLQSNASSwiSetChannelLock, 2134
SLQSNasConfigSigInfo2, 2126
SLQSNasGet3GPP2Subscription, 2126
SLQSNasGetCellLocationInfo, 2127
SLQSNasGetHDRColorCode, 2128
SLQSNasGetRFInfo, 2129

SLQSNasGetSigInfo, 2129
SLQSNasGetSysInfo, 2130
SLQSNasGetTxRxInfo, 2130
SLQSNasIndicationRegister, 2131
SLQSNasIndicationRegisterExt, 2132
SLQSNasIndicationRegisterLTECphyCa, 2132
SLQSNasSwiIndicationRegister, 2133
SLQSNasSwiModemStatus, 2134
SLQSPerformNetworkScan, 2134
SLQSPerformNetworkScanPCI, 2135
SLQSSetBandPreference, 2135
SLQSSetSysSelectionPref, 2137
SLQSSetSysSelectionPrefExt, 2137
SLQSSwiGetHDRPersonality, 2137
SLQSSwiGetHDRProtSubtype, 2138
SLQSSwiGetHRPDStats, 2138
SLQSSwiGetLteCQI, 2139
SLQSSwiGetLteSccRxInfo, 2139
SLQSSwiNetworkDebug, 2139
SLQSSwiPSDetach, 2140
SetACCOLC, 2119
SetCDMANetworkParameters, 2119
SetNetworkPreference, 2121
SlqsNas3GppNetworkRAT, 2090
slqsNetworkScanInfo, 2090
slqsNetworkScanInfoReq, 2091
sysSelectPrefExtInfo, 2094
sysSelectPrefInfo, 2095
sysSelectPrefParams, 2100
UATISIZE, 2090
qaGobiApiOmadm.h, 2140
OMADMCancelSession, 2141
OMADMGetPendingNIA, 2141
OMADMGetSessionInfo, 2142
OMADMStartSession, 2143
qaGobiApiPds.h, 2143
DEFAULTBYTEVALUE, 2145
DEFAULTLONGVALUE, 2145
DEFAULTWORDVALUE, 2145
ForceXTRADownload, 2145
GetPDSDefaults, 2145
GetPDSState, 2146
GetPortAutomaticTracking, 2146
GetServiceAutomaticTracking, 2147
GetXTRAAutomaticDownload, 2147
GetXTRANetwork, 2148
GetXTRAValidity, 2148
PDSInjectTimeReference, 2149
ResetPDSData, 2149
SLQSGetAGPSConfig, 2153
SLQSGetGPSStateInfo, 2154
SLQSPDSDeterminePosition, 2154
SLQSPDSInjectAbsoluteTimeReference, 2155
SLQSPDSInjectPositionData, 2155
SLQSSetAGPSConfig, 2156
SLQSSetPositionMethodState, 2156
SetPDSDefaults, 2150
SetPDSState, 2151
SetPortAutomaticTracking, 2151
SetServiceAutomaticTracking, 2152
SetXTRAAutomaticDownload, 2152
SetXTRANetwork, 2153
StartPDSTrackingSessionExt, 2157
StopPDSTrackingSession, 2158
qaGobiApiQos.h, 2158
SLQSQosGetFlowStatus, 2159
SLQSQosGetGranted, 2160
SLQSQosGetNWProf, 2161
SLQSQosGetNetworkStatus, 2160
SLQSQosModify, 2161
SLQSQosRel, 2162
SLQSQosReq, 2162
SLQSQosReset, 2163
SLQSQosResume, 2163
SLQSQosSuspend, 2164
SLQSQosSwiReadApnExtraParams, 2164
SLQSQosSwiReadDataStats, 2164
SetQosMuxID, 2159
qaGobiApiRms.h, 2165
GetSMSWake, 2165
SetSMSWake, 2166
qaGobiApiSar.h, 2166
eQMISARRFState, 2167
SLQSGetRfSarState, 2168
SLQSSetRfSarState, 2168
qaGobiApiSms.h, 2169
ABSOLUTE_VALIDITY, 2171
CONFIG_LEN, 2171
getIndicationRegResp, 2172
GetSMSCAddress, 2175
getTransLayerInfoResp, 2172
getTransNWRegInfoResp, 2173
MAX_SMS_ROUTES, 2171
MAX_SMSC_LENGTH, 2171
NUM_OF_SET, 2171
qaQmi3GPP2BroadcastCfgInfo, 2173
qaQmi3GPPBroadcastCfgInfo, 2174
sEnumTimeStampenum, 2175
SLQSCDMADecodeMTTextMsg, 2178
SLQSCDMADecodeMTTextMsgExt, 2178
SLQSCDMAEncodeMOTextMsg, 2179
SLQSDeleteSMS, 2179
SLQSGetIndicationRegister, 2180
SLQSGetMessageWaiting, 2181
SLQSGetSMS, 2181
SLQSGetSMSList, 2183
SLQSGetSmsBroadcastConfig, 2182
SLQSGetTransLayerInfo, 2184
SLQSGetTransNWRegInfo, 2184
SLQSModifySMSStatus, 2184
SLQSSendAsyncSMS, 2185
SLQSSendLongSMS, 2185
SLQSSendSMS, 2186
SLQSSetIndicationRegister, 2187
SLQSSetSmsBroadcastActivation, 2187
SLQSSetSmsBroadcastConfig, 2188

SLQSSetSmsStorage, 2188
SLQSSmsGetMaxStorageSize, 2189
SLQSSmsGetMessageProtocol, 2189
SLQSSmsSetRoutes, 2190
SLQSSwiGetSMSStorage, 2190
SLQSWCDMADecodeLongTextMsg, 2191
SLQSWCDMADecodeMTEncoding, 2191
SLQSWCDMADecodeMTTextMsg, 2192
SLQSWCDMAEncodeMOTextMsg, 2192
SaveSMS, 2176
SendSMS, 2177
setIndicationRegReq, 2174
SetSMSCAddress, 2177
TIME_DATE_BUF, 2172
TIME_STAMP_BUF, 2172
transLayerInfo, 2175
qaGobiApiSwi.h, 2192
SLQSGetPidof, 2193
SLQSGetSdkVersion, 2193
SLQSSendRawQMI, 2193
qaGobiApiSwiAudio.h, 2194
SLQSGetM2MAVMute, 2196
SLQSGetM2MAudioProfile, 2195
SLQSGetM2MAudioVolume, 2195
SLQSGetM2MSpkrGain, 2196
SLQSSetM2MAVMute, 2198
SLQSSetM2MAudioAVCFG, 2196
SLQSSetM2MAudioLPBK, 2197
SLQSSetM2MAudioNVDef, 2197
SLQSSetM2MAudioProfile, 2198
SLQSSetM2MAudioVolume, 2198
SLQSSetM2MSpkrGain, 2199
qaGobiApiSwiAvms.h, 2199
QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 2202
QmiSwiAvmsEventReportConfigResp, 2203
QmiSwiAvmsEventReportConnectionRequest-Resp, 2203
QmiSwiAvmsEventReportDataSessionStatus-Resp, 2203
QmiSwiAvmsEventReportHTTPStatusResp, 2203
QmiSwiAvmsEventReportNotificationResp, 2204
QmiSwiAvmsEventReportPackageIDResp, 2205
QmiSwiAvmsEventReportRegStatusResp, 2205
QmiSwiAvmsEventReportSessionTypeResp, 2205
QmiSwiAvmsEventReportWAMSParamChange-Resp, 2206
QmiSwiAvmsSetSettingsAPNInfo, 2206
QmiSwiAvmsSetSettingsConnectionRetryTimers, 2206
QmiSwiAvmsSetSettingsPeriodInfo, 2206
SLQSAVMSGetSessionInfo, 2209
SLQSAVMSGetSettings, 2209
SLQSAVMSGetSettings_v2, 2209
SLQSAVMSSelection, 2210
SLQSAVMSSetEventReport, 2210
SLQSAVMSSetSettings, 2211
SLQSAVMSSetSettings_v2, 2211
SLQSAVMSSetSettingsIgnoreAutoReboot, 2211
SLQSAVMSSetSettingsReq, 2206
SLQSAVMSSetSettingsReq_v2, 2207
SLQSAVMSSettings, 2209
SLQSAVMSSettings_v2, 2209
SLQSAVMSSettingsAPNInfo, 2209
SLQSAVMSSettingsConnectionRetryTimers, 2209
SLQSAVMSSettingsPeriodsInfo, 2209
SLQSAVMSStartSession, 2212
SLQSAVMSStopSession, 2212
qaGobiApiSwiDms.h, 2213
SLQSSwiDmsGetHWWatchdog, 2214
SLQSSwiDmsGetMTU, 2214
SLQSSwiDmsGetSecureInfo, 2215
SLQSSwiDmsGetUsbComp, 2215
SLQSSwiDmsGetUsbNetNum, 2215
SLQSSwiDmsSetHWWatchdog, 2216
SLQSSwiDmsSetMTU, 2216
SLQSSwiDmsSetUsbComp, 2216
SLQSSwiDmsSetUsbNetNum, 2217
qaGobiApiSwiOmadms.h, 2217
SLQSOMADMCancelSession, 2222
SLQSOMADMGetSessionInfo, 2223
SLQSOMADMGetSettings, 2223
SLQSOMADMGetSettings2, 2224
SLQSOMADMSendSelection, 2224
SLQSOMADMSendSelection2, 2225
SLQSOMADMSessionInfo, 2218
SLQSOMADMSetSettings, 2225
SLQSOMADMSetSettings2, 2226
SLQSOMADMSetSettings3, 2226
SLQSOMADMSettings, 2220
SLQSOMADMSettingsReqParams, 2221
SLQSOMADMSettingsReqParams3, 2222
SLQSOMADMStartSession, 2227
SLQSOMADMStartSession2, 2227
qaGobiApiTableBandClasses.h, 2228
qaGobiApiTableCallControlReturnReasons.h, 2231
qaGobiApiTableCallEndReasons.h, 2232
qaGobiApiTableCarrierCodes.h, 2249
qaGobiApiTableCodingScheme.h, 2251
qaGobiApiTableGpsCapabilityCodes.h, 2253
qaGobiApiTablePowerModes.h, 2254
qaGobiApiTableRadioInterfaces.h, 2255
qaGobiApiTableRegionCodes.h, 2255
qaGobiApiTableServiceOptions.h, 2256
qaGobiApiTableSupServiceInfoClasses.h, 2258
qaGobiApiTableSwiAudio.h, 2258
qaGobiApiTableSwiOMADMSessionStatus.h, 2259
qaGobiApiTableSwiOMADMUpdateCompleteStatus.h, 2260
qaGobiApiTableVoiceCallEndReasons.h, 2261
qaGobiApiTmd.h, 2268
SLQSTmdDeRegNotMitigationLvl, 2268
SLQSTmdGetMitigationDevList, 2269
SLQSTmdGetMitigationLvl, 2269
SLQSTmdRegNotMitigationLvl, 2269
qaGobiApiUim.h, 2270

MAX_ICCID_LENGTH, 2272
MAX_NO_OF_SLOTS, 2272
MAX_PATH_LENGTH, 2272
MAX_PUK_LENGTH, 2272
MAX_SLOTS_STATUS, 2272
SLQSUIMAuthenticate, 2272
SLQSUIMChangePin, 2273
SLQSUIMDepersonalization, 2273
SLQSUIMEventRegister, 2274
SLQSUIMGetCardStatus, 2274
SLQSUIMGetCardStatusV2, 2275
SLQSUIMGetConfiguration, 2275
SLQSUIMGetFileAttributes, 2276
SLQSUIMGetSlotsStatus, 2277
SLQSUIMPowerDown, 2277
SLQSUIMPowerUp, 2277
SLQSUIMReadTransparent, 2278
SLQSUIMRefreshComplete, 2278
SLQSUIMRefreshGetLastEvent, 2279
SLQSUIMRefreshOK, 2279
SLQSUIMRefreshRegister, 2280
SLQSUIMReset, 2280
SLQSUIMSetPinProtection, 2281
SLQSUIMSwitchSlot, 2281
SLQSUIMUnblockPin, 2282
SLQSUIMUnblockPinV2, 2282
SLQSUIMVerifyPin, 2283
qaGobiApiVoice.h, 2284
AnswerUSSD, 2287
CancelUSSD, 2288
MAX_CALL_NO_LEN, 2287
MAX_NO_OF_CALLS, 2287
MAXUSSDLENGTH, 2287
OriginateUSSD, 2288
PASSWORD_LENGTH, 2287
SLQSOriginateUSSD, 2289
SLQSVoiceALSSelectLine, 2289
SLQSVoiceALSSetLineSwitching, 2290
SLQSVoiceAnswerCall, 2290
SLQSVoiceBindSubscription, 2291
SLQSVoiceBurstDTMF, 2291
SLQSVoiceDialCall, 2292
SLQSVoiceEndCall, 2292
SLQSVoiceGetAllCallInfo, 2293
SLQSVoiceGetCLIP, 2295
SLQSVoiceGetCLIR, 2296
SLQSVoiceGetCNAP, 2296
SLQSVoiceGetCOLP, 2297
SLQSVoiceGetCOLR, 2297
SLQSVoiceGetCallBarring, 2293
SLQSVoiceGetCallForwardingStatus, 2294
SLQSVoiceGetCallInfo, 2294
SLQSVoiceGetCallWaiting, 2295
SLQSVoiceGetConfig, 2298
SLQSVoiceIndicationRegister, 2299
SLQSVoiceManageCalls, 2299
SLQSVoiceOrigUSSDNoWait, 2300
SLQSVoiceSendFlash, 2300
SLQSVoiceSetCallBarringPassword, 2301
SLQSVoiceSetConfig, 2301
SLQSVoiceSetPreferredPrivacy, 2302
SLQSVoiceSetSUPSService, 2302
SLQSVoiceStartContDTMF, 2303
SLQSVoiceStopContDTMF, 2303
serviceClassInformation, 2287
qaGobiApiWds.h, 2304
GetAutoconnect, 2312
GetByteTotals, 2313
GetConnectionRate, 2313
GetDataBearerTechnology, 2314
GetDefaultProfile, 2315
GetDefaultProfileLTE, 2316
GetDefaultProfileNum, 2318
GetDormancyState, 2319
GetIPAddressLTE, 2319
GetLastMobileIPError, 2319
GetMobileIP, 2320
GetMobileIPProfile, 2320
GetPacketStatistics, 2322
GetPacketStatus, 2322
GetProfileSettingIn, 2308
GetProfileSettingOut, 2308
GetSessionDuration, 2323
GetSessionState, 2324
iGetByteTotals, 2324
iGetConnectionRate, 2324
iGetPacketStatistics, 2324
iSLQSMISetIPFamilyPreference, 2324
pdpidx, 2312
qmiDataBearerMasks, 2312
QmiProfileInfo, 2308
QmiWDSDataBearerTechnology, 2309
QmiWDSDataBearers, 2309
RMSetTransferStatistics, 2324
SLQSAutoConnect, 2333
SLQSCreateProfile, 2334
SLQSDeleteProfile, 2334
SLQSGet3GPPConfigItem, 2335
SLQSGetByteTotals, 2335
SLQSGetConnectionRate, 2336
SLQSGetCurrDataSystemStat, 2336
SLQSGetCurrentChannelRate, 2337
SLQSGetDUNCallInfo, 2338
SLQSGetDataBearerTechnology, 2337
SLQSGetDataBearerTechnologyExt, 2338
SLQSGetPacketStatistics, 2338
SLQSGetProfile, 2339
SLQSGetProfileSettings, 2341
SLQSGetRuntimeSettings, 2341
SLQSGetSessionState, 2341
SLQSModifyProfile, 2342
SLQSResetPacketStatics, 2343
SLQSSGetDHCPv4ClientConfig, 2345
SLQSSGetLoopback, 2345
SLQSSSetDHCPv4ClientConfig, 2346
SLQSSSetLoopback, 2346

SLQSSet3GPPConfigItem, 2343
SLQSSetProfile, 2343
SLQSStartStopDataSession, 2346
SLQSWdsGoActive, 2347
SLQSWdsGoDormant, 2347
SLQSWdsSetEventReport, 2348
SLQSWdsSwiPDPRuntimeSettings, 2348
SetActiveMobileIPProfile, 2325
SetAutoconnect, 2325
SetDefaultProfile, 2326
SetDefaultProfileLTE, 2327
SetDefaultProfileLTEV2, 2328
SetDefaultProfileNum, 2330
SetMobileIP, 2330
SetMobileIPParameters, 2331
SetMobileIPProfile, 2332
SetMuxID, 2333
slqs3GPPConfigItem, 2310
WDS_IsGobiDevice, 2349
qaNasGetRFBandInfo.h, 2349
PkQmiNasGetRFBandInfo, 2349
UpkQmiNasGetRFBandInfo, 2349
qaNasPerformNetworkScan.h, 2350
FORBIDDEN_INDEX, 2350
INDEX_ZERO, 2350
PREFERRED_INDEX, 2350
PkQmiNasPerformNetworkScan, 2351
ROAMING_INDEX, 2350
UpkQmiNasPerformNetworkScan, 2351
qaQmi3GPP2BroadcastCfgInfo
qaGobiApiSms.h, 2173
qaQmi3GPPBroadcastCfgInfo
qaGobiApiSms.h, 2174
qaQmi3Gpp2TimeZone, 911
daylightSavings, 911
leapSeconds, 911
localTimeOffset, 911
qaQmiInterfaceInfo, 911
qaQmiinstanceid, 912
qaQmisvctype, 912
v4sessionId, 912
v6sessionId, 912
qaQmiServingSystemParam, 912
BasestationID, 915
BasestationLatitude, 915
BasestationLongitude, 915
CDMA_P_Rev, 915
CDMASystemInfoExt, 915
CallBarStatus, 915
CellID, 915
concSvcInfo, 915
CurrentPLMN, 915
DTMInd, 915
DataSrvCapabilities, 915
defaultRoamInd, 915
DetailedSvcInfo, 915
Gpp2TimeZone, 915
GppNetworkDSTAdjustment, 915
GppTimeZone, 915
hdrPersonality, 915
Lac, 916
NetworkID, 916
PRLInd, 916
roamIndicatorVal, 916
RoamingIndicatorList, 916
ServingSystem, 916
SystemID, 916
trackAreaCode, 916
qaQmiinstanceid
qaQmiInterfaceInfo, 912
qaQmisvctype
qaQmiInterfaceInfo, 912
qm_wds_ds_profile_extended_err_codes
qmerrno.h, 2357
qmTlvResult, 952
DeviceError, 952
DeviceResult, 952
TlvPresenceMask, 952
TlvResultCode, 952
qmerrno.h
eQCWWAN_ERR_API_MUTEX_TIMEOUT, 2354
eQCWWAN_ERR_BUFFER_SZ, 2353
eQCWWAN_ERR_CANCEL_OP, 2354
eQCWWAN_ERR_DRIVER, 2354
eQCWWAN_ERR_ENUM_BEGIN, 2353
eQCWWAN_ERR_ENUM_END, 2354
eQCWWAN_ERR_FILE_COPY, 2353
eQCWWAN_ERR_FILE_OPEN, 2353
eQCWWAN_ERR_GENERAL, 2353
eQCWWAN_ERR_INTERNAL, 2353
eQCWWAN_ERR_INVALID_ARG, 2353
eQCWWAN_ERR_INVALID_DEVID, 2353
eQCWWAN_ERR_INVALID_FILE, 2353
eQCWWAN_ERR_INVALID_QMI_RSP, 2353
eQCWWAN_ERR_INVALID_XID, 2354
eQCWWAN_ERR_MALFORMED_QMI_RSP, 2353
eQCWWAN_ERR_MEMORY, 2353
eQCWWAN_ERR_MULTIPLE_DEVICES, 2354
eQCWWAN_ERR_MULTIPLE_SMS_UNSUPPORTED, 2354
eQCWWAN_ERR_NO_CANCELABLE_OP, 2354
eQCWWAN_ERR_NO_CONNECTION, 2353
eQCWWAN_ERR_NO_DEVICE, 2353
eQCWWAN_ERR_NO_SIGNAL, 2354
eQCWWAN_ERR_NONE, 2353
eQCWWAN_ERR_NULL_TLV, 2357
eQCWWAN_ERR_OFFLINE, 2354
eQCWWAN_ERR_PDU_GENERATION, 2354
eQCWWAN_ERR_QMI_ABORTED, 2354
eQCWWAN_ERR_QMI_ACCESS_DENIED, 2356
eQCWWAN_ERR_QMI_ACK_NOT_SENT, 2356
eQCWWAN_ERR_QMI_ARG_TOO_LONG, 2354
eQCWWAN_ERR_QMI_AUTHENTICATION_FAILED, 2355

eQCWWAN_ERR_QMI_AUTHENTICATION_LOCK, 2355
eQCWWAN_ERR_QMI_BUNDLING_NOT_SUPPORTED, 2356
eQCWWAN_ERR_QMI_CALL_FAILED, 2354
eQCWWAN_ERR_QMI_CARD_BUSY_RSP, 2357
eQCWWAN_ERR_QMI_CARD_CALL_CONTROL_FAILED, 2356
eQCWWAN_ERR_QMI_CAT_END, 2357
eQCWWAN_ERR_QMI_CAT_START, 2357
eQCWWAN_ERR_QMI_CAUSE_CODE, 2355
eQCWWAN_ERR_QMI_CLIENT_IDS_EXHAUSTED, 2354
eQCWWAN_ERR_QMI_CONNECT, 2353
eQCWWAN_ERR_QMI_DEVICE_IN_USE, 2354
eQCWWAN_ERR_QMI_DEVICE_NOT_READY, 2355
eQCWWAN_ERR_QMI_DEVICE_STORAGE_FULL, 2355
eQCWWAN_ERR_QMI_DISABLED, 2355
eQCWWAN_ERR_QMI_ENCODING, 2355
eQCWWAN_ERR_QMI_ENVELOPE_CMD_FAILURE, 2357
eQCWWAN_ERR_QMI_EVENT_REG_FAILED, 2357
eQCWWAN_ERR_QMI_EXTENDED_INTERNAL, 2356
eQCWWAN_ERR_QMI_FDN_RESTRICT, 2356
eQCWWAN_ERR_QMI_FLOW_SUSPENDED, 2355
eQCWWAN_ERR_QMI_GENERAL, 2355
eQCWWAN_ERR_QMI_HARDWARE_RESTRICTED, 2356
eQCWWAN_ERR_QMI_IFACE, 2353
eQCWWAN_ERR_QMI_INCOMPATIBLE_STATE, 2356
eQCWWAN_ERR_QMI_INCORRECT_FLOW_FILTER, 2355
eQCWWAN_ERR_QMI_INCORRECT_PIN, 2354
eQCWWAN_ERR_QMI_INFO_UNAVAILABLE, 2356
eQCWWAN_ERR_QMI_INJECT_TIMEOUT, 2356
eQCWWAN_ERR_QMI_INSUFFICIENT_RESOURCES, 2355
eQCWWAN_ERR_QMI_INTERFACE_NOT_FOUND, 2355
eQCWWAN_ERR_QMI_INTERNAL, 2354
eQCWWAN_ERR_QMI_INVALID_ARG, 2355
eQCWWAN_ERR_QMI_INVALID_CLIENT_ID, 2354
eQCWWAN_ERR_QMI_INVALID_DATA_FORMAT, 2355
eQCWWAN_ERR_QMI_INVALID_ENVELOPE_CMD, 2357
eQCWWAN_ERR_QMI_INVALID_HANDLE, 2354
eQCWWAN_ERR_QMI_INVALID_ID, 2355
eQCWWAN_ERR_QMI_INVALID_INDEX, 2355
eQCWWAN_ERR_QMI_INVALID_IP_FAMILY_PREF, 2355
eQCWWAN_ERR_QMI_INVALID_MCAST_HANDLE, 2355
eQCWWAN_ERR_QMI_INVALID_MESSAGE_ID, 2355
eQCWWAN_ERR_QMI_INVALID_OPERATION, 2356
eQCWWAN_ERR_QMI_INVALID_PDP_TYPE, 2354
eQCWWAN_ERR_QMI_INVALID_PINID, 2354
eQCWWAN_ERR_QMI_INVALID_PROFILE, 2354
eQCWWAN_ERR_QMI_INVALID_PROFILE_TYPE, 2354
eQCWWAN_ERR_QMI_INVALID_PS_ATTACH_ACTION, 2355
eQCWWAN_ERR_QMI_INVALID_QMI_CMD, 2356
eQCWWAN_ERR_QMI_INVALID_QOS_ID, 2355
eQCWWAN_ERR_QMI_INVALID_REGISTER_ACTION, 2355
eQCWWAN_ERR_QMI_INVALID_SERVICE_TYPE, 2354
eQCWWAN_ERR_QMI_INVALID_TECH_PREF, 2354
eQCWWAN_ERR_QMI_INVALID_TERMINAL_RSP, 2357
eQCWWAN_ERR_QMI_INVALID_TRANSITION, 2355
eQCWWAN_ERR_QMI_INVALID_TX_ID, 2354
eQCWWAN_ERR_QMI_MALFORMED_MSG, 2354
eQCWWAN_ERR_QMI_MAX, 2356
eQCWWAN_ERR_QMI_MAX_MCAST_REQUESTS_IN_USE, 2355
eQCWWAN_ERR_QMI_MAX_QOS_REQUESTS_IN_USE, 2355
eQCWWAN_ERR_QMI_MESSAGE_DELIVERY_FAILURE, 2355
eQCWWAN_ERR_QMI_MESSAGE_NOT_SENT, 2355
eQCWWAN_ERR_QMI_MISSING_ARG, 2354
eQCWWAN_ERR_QMI_MSG_BLOCKED, 2356
eQCWWAN_ERR_QMI_NETWORK_ABORTED, 2356
eQCWWAN_ERR_QMI_NETWORK_NOT_READY, 2355
eQCWWAN_ERR_QMI_NETWORK_QOS_UNAWARE, 2355
eQCWWAN_ERR_QMI_NO_EFFECT, 2354
eQCWWAN_ERR_QMI_NO_ENTRY, 2355
eQCWWAN_ERR_QMI_NO_FREE_PROFILE, 2354
eQCWWAN_ERR_QMI_NO_MEMORY, 2354
eQCWWAN_ERR_QMI_NO_NETWORK_FOUND, 2354
eQCWWAN_ERR_QMI_NO_RADIO, 2356

eQCWWAN_ERR_QMI_NO_SUBSCRIPTION, 2356
eQCWWAN_ERR_QMI_NO_THRESHOLDS, 2354
eQCWWAN_ERR_QMI_NOT_A_MCAST_IFACE, 2355
eQCWWAN_ERR_QMI_NOT_PROVISIONED, 2354
eQCWWAN_ERR_QMI_NOT_SUPPORTED, 2356
eQCWWAN_ERR_QMI_OFFSET, 2354
eQCWWAN_ERR_QMI_OP_DEVICE_UNSUPPORTED, 2354
eQCWWAN_ERR_QMI_OP_NETWORK_UNSUPPORTED, 2354
eQCWWAN_ERR_QMI_OP_PARTIAL_FAILURE, 2356
eQCWWAN_ERR_QMI_OUT_OF_CALL, 2354
eQCWWAN_ERR_QMI_PIN_BLOCKED, 2355
eQCWWAN_ERR_QMI_PIN_PERM_BLOCKED, 2355
eQCWWAN_ERR_QMI_POLICY_MISMATCH, 2356
eQCWWAN_ERR_QMI_REQ, 2353
eQCWWAN_ERR_QMI_REQ_SCH, 2353
eQCWWAN_ERR_QMI_REQ_TO, 2353
eQCWWAN_ERR_QMI_REQUESTED_NUM_UNSUPPORTED, 2355
eQCWWAN_ERR_QMI_RSP, 2353
eQCWWAN_ERR_QMI_RSP_TO, 2353
eQCWWAN_ERR_QMI_SEGMENT_ORDER, 2356
eQCWWAN_ERR_QMI_SEGMENT_TOO_LONG, 2356
eQCWWAN_ERR_QMI_SESSION_INACTIVE, 2355
eQCWWAN_ERR_QMI_SESSION_INVALID, 2355
eQCWWAN_ERR_QMI_SESSION_OWNERSHIP, 2355
eQCWWAN_ERR_QMI_SIM_FILE_NOT_FOUND, 2356
eQCWWAN_ERR_QMI_SIM_NOT_INITIALIZED, 2355
eQCWWAN_ERR_QMI_SMSC_ADDR, 2356
eQCWWAN_ERR_QMI_SUPS_FAILURE_CAUSE, 2356
eQCWWAN_ERR_QMI_TPDU_TYPE, 2356
eQCWWAN_ERR_QMI_UNABORTABLE_TRANSACTION, 2354
eQCWWAN_ERR_QMI_UNKNOWN, 2355
eQCWWAN_ERR_QMI_WIDTH, 2357
eQCWWAN_ERR_RESET, 2354
eQCWWAN_ERR_SWICM_AM_VERS_ERROR, 2356
eQCWWAN_ERR_SWICM_CALL_IN_PROGRESS, 2356
eQCWWAN_ERR_SWICM_END, 2357
eQCWWAN_ERR_SWICM_FAILED_TO_KILL_SDK_PROCESS, 2356
eQCWWAN_ERR_SWICM_INVALID_SESSION_ID, 2356
eQCWWAN_ERR_SWICM_INVALID_V4_SESSION_ID, 2356
eQCWWAN_ERR_SWICM_INVALID_V6_SESSION_ID, 2356
eQCWWAN_ERR_SWICM_NOT_IMPLEMENTED, 2356
eQCWWAN_ERR_SWICM_QMI_CLNT_NOT_SUPPORTED, 2356
eQCWWAN_ERR_SWICM_QMI_SVC_NOT_SUPPORTED, 2356
eQCWWAN_ERR_SWICM_SM_NO_AVAILABLE_SESSIONS, 2356
eQCWWAN_ERR_SWICM_SOCKET_IN_USE, 2356
eQCWWAN_ERR_SWICM_START, 2356
eQCWWAN_ERR_SWICM_TIMEOUT, 2356
eQCWWAN_ERR_SWICM_V4DWN_V6DWN, 2356
eQCWWAN_ERR_SWICM_V4DWN_V6UP, 2356
eQCWWAN_ERR_SWICM_V4UP_V6DWN, 2356
eQCWWAN_ERR_SWICM_V4UP_V6UP, 2356
eQCWWAN_ERR_SWIDCS_APP_DISCONNECTED, 2357
eQCWWAN_ERR_SWIDCS_DEVNODE_NOT_FOUND, 2357
eQCWWAN_ERR_SWIDCS_END, 2357
eQCWWAN_ERR_SWIDCS_FILEIO_ERR, 2357
eQCWWAN_ERR_SWIDCS_IOCTL_ERR, 2357
eQCWWAN_ERR_SWIDCS_START, 2357
eQCWWAN_ERR_SWIIM_CORRUPTED_FW_IMAGE, 2357
eQCWWAN_ERR_SWIIM_END, 2357
eQCWWAN_ERR_SWIIM_FILE_NOT_FOUND, 2357
eQCWWAN_ERR_SWIIM_FIRMWARE_NOT_DOWNLOADED, 2357
eQCWWAN_ERR_SWIIM_FW_ENTER_DOWNLOAD_MODE, 2357
eQCWWAN_ERR_SWIIM_FW_FLASH_COMPLETE, 2357
eQCWWAN_ERR_SWIIM_FW_INVALID_SLOT_INDEX, 2357
eQCWWAN_ERR_SWIIM_FW_PREFERENCE_MISMATCH, 2357
eQCWWAN_ERR_SWIIM_FW_SAME_AS_CURRENT_ACTIVE_IMAGE, 2357
eQCWWAN_ERR_SWIIM_FW_SECBOOT_IMAGE_NOT_SIGNED, 2357
eQCWWAN_ERR_SWIIM_FW_SECBOOT_INVALID_CERT_CHAIN, 2357
eQCWWAN_ERR_SWIIM_FW_TOO_MANY_FILES, 2357
eQCWWAN_ERR_SWIIM_FW_UPDATE_FAIL, 2357

eQCWWAN_ERR_SWIIM_FW_UPDATE_SUCCESS, 2357
eQCWWAN_ERR_SWIIM_FW_WAIT_FOR_REBOOT, 2357
eQCWWAN_ERR_SWIIM_INVALID_CRASH_STATE, 2357
eQCWWAN_ERR_SWIIM_INVALID_PATH, 2357
eQCWWAN_ERR_SWIIM_OPENING_DIR, 2357
eQCWWAN_ERR_SWIIM_OPENING_FILE, 2357
eQCWWAN_ERR_SWIIM_START, 2357
eQCWWAN_ERR_SWISM_END, 2357
eQCWWAN_ERR_SWISMS_BEARER_DATA_NOT_FOUND, 2357
eQCWWAN_ERR_SWISMS_MSG_CORRUPTED, 2357
eQCWWAN_ERR_SWISMS_MSG_LEN_TOO_LONG, 2357
eQCWWAN_ERR_SWISMS_SMSC_NUM_CORRUPTED, 2357
eQCWWAN_ERR_SWISMS_START, 2357
eWDS_ERR_PROFILE_REG_3GPP2_ERR_INVALID_IDENT_FOR_PROFILE, 2358
eWDS_ERR_PROFILE_REG_3GPP_ACCESS_ERR, 2358
eWDS_ERR_PROFILE_REG_3GPP_CONTEXT_NOT_DEFINED, 2358
eWDS_ERR_PROFILE_REG_3GPP_ERR_OUT_OF_PROFILES, 2358
eWDS_ERR_PROFILE_REG_3GPP_INVAL_PROFILE_FAMILY, 2358
eWDS_ERR_PROFILE_REG_3GPP_READ_ONLY_FLAG_SET, 2358
eWDS_ERR_PROFILE_REG_3GPP_VALID_FLAG_NOT_SET, 2358
eWDS_ERR_PROFILE_REG_END, 2358
eWDS_ERR_PROFILE_REG_INVAL_PROFILE_FAMILY, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_HNDL, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_IDENT, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_OP, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_PROFILE_NUM, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_PROFILE_TYPE, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_INVAL_SUBS_ID, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_LEN_INVALID, 2358
eWDS_ERR_PROFILE_REG_RESULT_ERR_LIB_NOT_INITED, 2358
eWDS_ERR_PROFILE_REG_RESULT_FAIL, 2358
eWDS_ERR_PROFILE_REG_RESULT_LIST_END, 2358
qmerrno.h, 2351
eQCWWANError, 2353
qm_wds_ds_profile_extended_err_codes, 2357
QmiCbkCatEventStatusReportInd, 916
CCETlv, 916
event_Index, 916
results, 916
QmiCbkLocBestAvailPosInd, 916
pAltitudeWrtEllipsoid, 921
pAltitudeWrtMeanSeaLevel, 921
pGpsTime, 921
pHeading, 921
pHeadingUnc, 921
pHorCirConf, 921
pHorEllpConf, 921
pHorReliability, 921
pHorUncCircular, 921
pHorUncEllipseOrientAzimuth, 921
pHorUncEllipseSemiMajor, 921
pHorUncEllipseSemiMinor, 921
pLatitude, 921
pLongitude, 921
pMagneticDeviation, 921
pPrecisionDilution, 921
pSensorDataUsage, 921
pSpeedHorizontal, 921
pSpeedUnc, 921
pSpeedVertical, 921
pSpeedVerticalUnc, 921
pSvUsedforFix, 921
pTechnologyMask, 921
pTimeSrc, 921
pTimeUnc, 921
pTimestampUtc, 921
pVertConfidence, 921
pVertReliability, 921
pVertUnc, 922
pXid, 922
results, 922
status, 922
QmiCbkLocCradleMountInd, 922
cradleMountConfigStatus, 922
results, 922
QmiCbkLocEngineStateInd, 922
engineState, 923
results, 923
QmiCbkLocEventNMEAInd, 923
pNMEAData, 923
results, 923
QmiCbkLocEventTimeSyncInd, 923
results, 924
timeSyncRefCounter, 924
QmiCbkLocGetOpModeInd, 924
pMode, 925
results, 925
status, 925

QmiCbkLocGetServerInd, 925
pIPv4AddrInfo, 926
pIPv6AddrInfo, 926
pURL, 926
results, 926
serverStatus, 926
serverType, 926
QmiCbkLocInjectPositionInd, 927
results, 927
status, 927
QmiCbkLocInjectSensorDataInd, 927
injectSensorDataStatus, 928
pAccelSamplesAccepted, 928
pAccelTempSamplesAccepted, 928
pGyroSamplesAccepted, 928
pGyroTempSamplesAccepted, 928
pOpaqueIdentifier, 929
results, 929
QmiCbkLocInjectTimeInd, 929
injectTimeSyncStatus, 929
results, 929
QmiCbkLocInjectUTCTimeInd, 929
results, 930
status, 930
QmiCbkLocOpModeInd, 930
mode, 931
results, 931
QmiCbkLocPositionReportInd, 931
pAltitudeAssumed, 936
pAltitudeWrtEllipsoid, 936
pAltitudeWrtMeanSeaLevel, 936
pFixId, 936
pGpsTime, 936
pHeading, 936
pHeadingUnc, 936
pHorConfidence, 936
pHorReliability, 936
pHorUncCircular, 936
pHorUncEllipseOrientAzimuth, 936
pHorUncEllipseSemiMajor, 936
pHorUncEllipseSemiMinor, 936
pLatitude, 936
pLeapSeconds, 936
pLongitude, 936
pMagneticDeviation, 936
pPrecisionDilution, 936
pSensorDataUsage, 936
pSpeedHorizontal, 936
pSpeedUnc, 936
pSpeedVertical, 936
pSvUsedforFix, 936
pTechnologyMask, 936
pTimeSrc, 936
pTimeUnc, 937
pTimestampUtc, 937
pVertConfidence, 937
pVertReliability, 937
pVertUnc, 937
results, 937
sessionId, 937
sessionStatus, 937
QmiCbkLocSensorStreamingInd, 937
pAccelAcceptReady, 937
pAccelTempAcceptReady, 937
pGyroAcceptReady, 937
pGyroTempAcceptReady, 938
results, 938
QmiCbkLocSetExtPowerConfigInd, 938
results, 938
status, 938
QmiCbkLocSetServerInd, 938
results, 939
serverStatus, 939
QmiCbkNasEdrxChangeInfo, 939
results, 940
sEdrxCiotLteMode, 940
sEdrxCycleLength, 940
sEdrxEnableType, 940
sEdrxPagingTimeWindow, 940
sEdrxRatType, 940
QmiCbkNasLTECphyCaInfo, 940
results, 941
sPhyCaAggPcellInfo, 941
sPhyCaAggScellDlBw, 941
sPhyCaAggScellIndType, 941
sPhyCaAggScellIndex, 941
sPhyCaAggScellInfo, 941
QmiCbkSwiOmaDmEventStatusReportInd, 941
results, 941
SITlv, 941
QmiCbkSwiOmaDmEventStatusReportIndExt, 941
SITlv, 941
QmiCbkTmdMitiLvlRptInd, 941
currentMitigationLvl, 942
MitigationDevInfo, 942
results, 942
QmiCbkWdsStatisticsIndState, 942
results, 943
RxDropConutTlv, 943
RxOkByteCountTlv, 943
RxOkConutTlv, 943
TxDropConutTlv, 943
TxOkByteCountTlv, 943
TxOkConutTlv, 943
qmiDataBearerMasks
qaGobiApiWds.h, 2312
QmiNas3GppNetworkInfo, 944
pDesription, 945
pForbidden, 945
pInUse, 945
pMCC, 945
pMNC, 945
pPreferred, 945
pRoaming, 945
QmiNasGetRFBandInfoResp, 945
pInstancesSize, 945

pLTEOperationMode, 946
pRFBandInfoElements, 946
pRfBandInfoExtFormat, 946
pRfBandwidthInfo, 946
pRfDedicatedBandInfo, 946
results, 946
QmiNasPerformNetworkScanResp, 946
pInstanceSize, 946
pInstances, 946
results, 946
QmiProfileInfo
qaGobiApiWds.h, 2308
qmiSmsMessageList, 946
messageIndex, 946
messageTag, 947
QmiSwiAvmsEventReportBinaryUpdateSessionInfo-Resp
qaGobiApiSwiAvms.h, 2202
QmiSwiAvmsEventReportConfigResp
qaGobiApiSwiAvms.h, 2203
QmiSwiAvmsEventReportConnectionRequestResp
qaGobiApiSwiAvms.h, 2203
QmiSwiAvmsEventReportDataSessionStatusResp
qaGobiApiSwiAvms.h, 2203
QmiSwiAvmsEventReportHTTPStatusResp
qaGobiApiSwiAvms.h, 2203
QmiSwiAvmsEventReportNotificationResp
qaGobiApiSwiAvms.h, 2204
QmiSwiAvmsEventReportPackageIDResp
qaGobiApiSwiAvms.h, 2205
QmiSwiAvmsEventReportRegStatusResp
qaGobiApiSwiAvms.h, 2205
QmiSwiAvmsEventReportSessionTypeResp
qaGobiApiSwiAvms.h, 2205
QmiSwiAvmsEventReportWAMSParamChangeResp
qaGobiApiSwiAvms.h, 2206
QmiSwiAvmsSetSettingsAPNInfo
qaGobiApiSwiAvms.h, 2206
QmiSwiAvmsSetSettingsConnectionRetryTimers
qaGobiApiSwiAvms.h, 2206
QmiSwiAvmsSetSettingsPeriodInfo
qaGobiApiSwiAvms.h, 2206
QmiWDSDataBearerTechnology
qaGobiApiWds.h, 2309
qmiWDSDataBearerTechnology, 947
currentNetwork, 947
ratMask, 947
soMask, 947
QmiWDSDataBearers
qaGobiApiWds.h, 2309
QmiWdsIpAddressInfo, 947
pIPAddressV4, 948
pIPAddressV6, 948
pIPv6prefixlen, 948
qmiWdsRunTimeSettings, 948
pAPNName, 951
pAuthentication, 951
pDomainList, 951
pGPRSGrantedQoS, 951
pGWAddressV4, 951
pIMCNflag, 951
pIPAddressV4, 951
pIPFamilyPreference, 951
pIPV6AddrInfo, 951
pIPV6GWAddrInfo, 951
pMtu, 951
pPCSCFAddrPCO, 951
pPCSCFFQDNAddrList, 951
pPDPType, 951
pPrimaryDNSV4, 951
pPrimaryDNSV6, 951
pProfileID, 951
pProfileName, 951
pSecondaryDNSV4, 952
pSecondaryDNSV6, 952
pServerAddrList, 952
pSubnetMaskV4, 952
pTechnology, 952
pUMTSGrantedQoS, 952
pUsername, 952
qmifwinfo_s, 943
dev, 944
g, 944
s, 944
qmuint16
SwiDataTypes.h, 2396
qmulong
SwiDataTypes.h, 2396
qos.h, 2358
pack_qos_BindDataPort, 2360
pack_qos_SLQSQosGetNetworkStatus, 2360
pack_qos_SLQSQosSwiReadApnExtraParams, 2361
pack_qos_SLQSQosSwiReadDataStats, 2362
pack_qos_SLQSSetQosEventCallback, 2362
unpack_qos_BindDataPort, 2363
unpack_qos_SLQSQosGetNetworkStatus, 2363
unpack_qos_SLQSQosSwiReadApnExtraParams, 2364
unpack_qos_SLQSQosSwiReadDataStats, 2364
unpack_qos_SLQSSetQosEventCallback, 2365
unpack_qos_SLQSSetQosEventCallback_ind, 2365
unpack_qos_SLQSSetQosNWStatusCallback_ind, 2366
unpack_qos_SLQSSetQosPriEventCallback_ind, 2366
unpack_qos_SLQSSetQosStatusCallback_ind, 2367
qos_BindDataPortMuxID_t, 952
MuxID, 952
qos_BindDataPortPeripheralEndPointID_t, 953
EndPointType, 953
IfaceID, 953
qos_BindDataPortSIODataPort_t, 953
SIODataPort, 953

qos_id
QosMap, 958
QosClassID, 953
gDlBitRate, 954
gUlBitRate, 954
maxDlBitRate, 954
maxUlBitRate, 954
QCI, 954
qosDeliveryOrder
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
QosEventInfo, 954
pDataBearer, 955
pPacketsCountRX, 956
pPacketsCountTX, 956
pTotalBytesRX, 956
pTotalBytesTX, 956
qosFlow
sQosStat, 1083
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
QosFlowInfo, 956
pBearerID, 956
pQFlowState, 956
pRxQFilter, 957
pRxQFlowGranted, 957
pTxQFilter, 957
pTxQFlowGranted, 957
unpack_qos_SLQSSetQosEventCallback_ind_t, 1407
QosFlowInfoState, 957
id, 957
isNewFlow, 957
state, 957
QosMap, 957
dscp, 958
qos_id, 958
state, 958
Quality of Service (QOS), 60

RAN
unpack_nas_GetServingNetwork_t, 1317
RAT
SlqsNas3GppNetworkRAT, 97
nas_QmiNas3GppNetworkRAT, 579
RATMask
CurrNetworkInfo, 224
currNetworkInfo, 224
wds_currNetworkInfo, 1682
REGISTER_EVENT
qaGobiApiCbk.h, 1913
REGISTER_SRV
qaGobiApiCbk.h, 1913
RFBandInfoElements, 966
activeBandClass, 967
activeChannel, 967
radioInterface, 967
unpack_nas_GetRFInfo_t, 1314
RFTlv
unpack_nas_SetEventReportInd_t, 1322
RMAutoConnect
pack_dms_SetCustFeature_t, 710
unpack_dms_GetCustFeature_t, 1211
RMSetTransferStatistics
qaGobiApiWds.h, 2324
ROAMING_INDEX
qaNasPerformNetworkScan.h, 2350
RPCause
SMSAsyncRawSend_s, 1066
unpack_sms_SLQSWmsAsyncRawSendCallBack-_ind_t, 1440
RPTlv
NASQmiCbkNasSystemSelPrefInd, 668
RRTlv
unpack_nas_SetEventReportInd_t, 1322
RSRPThresListLen
nas_RSRPThresh, 592
RSRPThresh, 975
RSRPThresh, 974
pRSRPThresList, 975
RSRPThresListLen, 975
RSRQThresListLen
nas_RSRQThresh, 593
RSRQThresh, 976
RSRQThresh, 975
pRSRQThresList, 976
RSRQThresListLen, 976
RSSIThresListLen
nas_RSSIThresh, 594
RSSIThresh, 977
RSSIThresh, 976
pRSSIThresList, 977
RSSIThresListLen, 977
RX_EC_IO
nas_NetworkStat1x, 554
NetworkStat1x, 685
RX_PWR
nas_NetworkStat1x, 554
nas_NetworkStatEVDO, 556
NetworkStat1x, 685
NetworkStatEVDO, 687
RXAGCList, 977
pRXAIG, 978
pRXComprSlope, 978
pRXComprThres, 978
pRXExpSlope, 978
pRXExpThres, 978
pRXStaticGain, 978
RXAVCList, 978
pAVRXAVCHeadroom, 978
pAVRXAVCSens, 978
RXBOTlv
unpack_wds_SLQSDUNCallInfoCallBack_ind_t, 1534
RXChan
LTEInfo, 442

nas_LTEInfo, 528
rXDroppedCount
unpack_wds_GetPacketStatus_t, 1529
RXOKBytesCount
DUNCallInfoInd, 265
rXOKBytesLastCall
unpack_wds_GetPacketStatus_t, 1529
rXOkBytesCount
unpack_wds_GetPacketStatus_t, 1529
RXPCMIIRFltr, 980
pFlag, 981
pStage0Val, 981
pStage1Val, 981
pStage2Val, 981
pStage3Val, 981
pStage4Val, 981
pStageCnt, 981
rXPacketErrors
unpack_wds_GetPacketStatus_t, 1529
rXPacketOverflows
unpack_wds_GetPacketStatus_t, 1529
rXPacketSuccesses
unpack_wds_GetPacketStatus_t, 1529
radio
unpack_nas_GetSignalStrengths_t, 1318
radio_if
nasGetTxRxInfoReq, 642
pack_nas_SLQSNasGetTxRxInfo_t, 756
radioIf
ecioListElement, 267
errorRateListElement, 274
nas_ecioListElement, 499
nas_errorRateListElement, 504
nas_rsrqInformation, 592
nas_rxSignalStrengthListElement, 597
nasNetworkReject, 653
rsrqInformation, 975
rxSignalStrengthListElement, 983
unpack_nas_SLQSNasNetworkRejectCallback_-Ind_t, 1363
RadioIfaces
unpack_dms_GetDeviceCap_t, 1213
unpack_dms_GetDeviceCapabilities_t, 1215
unpack_nas_GetServingNetwork_t, 1317
RadioIfacesSize
unpack_dms_GetDeviceCap_t, 1213
unpack_nas_GetServingNetwork_t, 1317
radioIfacesSize
unpack_dms_GetDeviceCapabilities_t, 1215
radioInterface
nas_RFBandInfoElements, 584
nas_RfBandInfoExtFormatElements, 585
nas_RfBandwidthInfoElements, 587
nas_RfDedicatedBandInfoElements, 589
nas_RFInfoTlv, 590
nas_roamIndList, 591
nas_servSystem, 600
nas_SignalStrengthTlv, 601
nas_timeInfo, 613
RFBandInfoElements, 967
RfBandInfoExtFormatElements, 968
RfBandwidthInfoElements, 970
RfDedicatedBandInfoElements, 972
roamIndList, 973
servSystem, 996
timeInfo, 1134
radioInterfaceList
NASServingSystemInfo, 671
ServingSystemInfo, 994
radioInterfaceNo
NASServingSystemInfo, 671
ServingSystemInfo, 995
radioInterfaceSize
nas_RFInfoTlv, 590
randomizationWindow
dms_PSMRandomizationWindowTlv, 251
PSMRandomizationWindowTlv, 910
range
Port, 888
unpack_qos_Port_t, 1400
RankIndicatorInd, 958
Count1, 958
Count2, 958
rankIndicatorTlv
unpack_nas_SLQSSwiRandIndicatorCallback_-Ind_t, 1375
rat
CSGID, 216
MNRInfo, 468
nas_CSGID, 491
nas_MNRInfo, 550
RatDMTlv
NASQmiCbkNasSystemSelPrefInd, 668
RatDisabledMask
NASRatDisabledMaskTlv, 668
ratDisabledMask
nas_RatDisabledMaskTlv, 583
RatDisabledMaskTlv, 959
RatDisabledMaskTlv, 958
ratDisabledMask, 959
TlvPresent, 959
ratMask
dataBearerTechnology, 235
qmiWDSDataBearerTechnology, 947
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
ratValue
DataBearerTech, 232
rawHorConfidence
pack_loc_SLQSLOCInjectPosition_t, 736
rawHorUncCircular
pack_loc_SLQSLOCInjectPosition_t, 736
rawLen
fileAttributes, 279
uim_fileAttributes, 1157
rawValue

fileAttributes, 279
uim_fileAttributes, 1157
rcv4
ssdatasession_params, 1086
rcv6
ssdatasession_params, 1086
readResult, 959
content, 959
contentLen, 959
readTransparent
pack_uim_ReadTransparent_t, 813
UIMReadTransparentReq, 1183
readTransparentInfo, 960
length, 960
offset, 960
Reason
pack_voice_SLQSVoiceGetCallForwardingStatus-_t, 831
pack_voice_SLQSVoiceSetCallBarringPassword_t, 837
voiceGetCallFWReq, 1633
voiceSetCallBarringPwdInfo, 1655
reason
ccSUPSType, 177
pack_voice_SLQSVoiceGetCallBarring_t, 830
pack_voice_SLQSVoiceSetSUPSService_t, 841
redirNumInfo, 962
unpack_qos_SLQSSetQosStatusCallback_ind_t, 1410
voice_ccSUPSType, 1591
voice_redirNumInfo, 1611
voiceGetCallBarringReq, 1631
voiceSetSUPSServiceReq, 1662
receiptAction
sms_routeEntry, 1060
smsRouteEntry, 1078
receivedBytes
omaDmFotaTlvExt, 703
reconfigReqd
_packetSrvStatus, 76
unpack_wds_SLQSSetPacketSrvStatusCallback_-t, 1549
reconfiguration_required
slqsSessionStateInfo, 1043
recordCount
fileAttributes, 279
uim_fileAttributes, 1157
recordSize
fileAttributes, 279
uim_fileAttributes, 1157
redirNumInfo, 960
numLen, 961
numPlan, 961
numType, 962
number, 961
PI, 962
reason, 962
SI, 962
RedirPartyNum
arrRedirPartyNum, 149
voice_arrRedirPartyNum, 1578
refData
unpack_dms_SLQSSwiGetFwUpdateStatus_t, 1259
refString
unpack_dms_SLQSSwiGetFwUpdateStatus_t, 1259
ReferenceID
CatAlPhaIdentifierTlv, 174
CatEventIDDataTlv, 176
refpn
CDMAInfo, 180
nas_CDMAInfo, 481
refreshComplete
pack_uim_SLQSUIMRefreshComplete_t, 819
UIMRefreshCompleteReq, 1184
refreshEvent
unpack_uim_SLQSUIMRefreshCallback_Ind_t, 1464
RefreshMode
CatRefreshTlv, 177
RefreshStage
CatRefreshTlv, 177
regAction
nasInitNetworkReg, 647
pack_nas_SLQSInitiateNetworkRegistration_t, 749
RegForeignNID
unpack_nas_GetCDMANetworkParameters_t, 1308
RegForeignSID
unpack_nas_GetCDMANetworkParameters_t, 1308
RegHomeSID
unpack_nas_GetCDMANetworkParameters_t, 1309
regInd
_transLayerInfoNotification, 127
unpack_sms_SLQSTransLayerInfoCallback_ind_t, 1438
regPrd
AddCDMASysInfo, 132
nas_AddCDMASysInfo, 474
regRefresh
pack_uim_SLQSUIMRefreshRegister_t, 820
UIMRefreshRegisterReq, 1187
regRejectInfoValid
GSMSysInfo, 333
LTESysInfo, 463
nas_GSMSysInfo, 512
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 563
nas_WCDMASysInfo, 625
NR5GSystemInfoTlv, 695
WCDMASysInfo, 1678
regState
nas_servSystem, 600

servSystem, 996
RegStatus
_SwiAvmsEventInd, 113
Region
fwinfo_s, 287
registerFlag
registerRefresh, 962
uim_registerRefresh, 1163
registerRefresh, 962
arrfileInfo, 962
numFiles, 962
registerFlag, 962
voteForInit, 963
RegistrationState
unpack_nas_GetServingNetwork_t, 1317
registrationState
NASServingSystemInfo, 671
ServingSystemInfo, 995
rejCause
GSMSysInfo, 333
LTESysInfo, 463
nas_GSMSysInfo, 512
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 563
nas_WCDMASysInfo, 625
NR5GSystemInfoTlv, 695
WCDMASysInfo, 1679
rejectCause
nas_RejectReasonTlv, 583
nasNetworkReject, 653
unpack_nas_SLQSNasNetworkRejectCallback_-Ind_t, 1363
rejectSrvDomain
GSMSysInfo, 333
LTESysInfo, 463
nas_GSMSysInfo, 513
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 563
nas_WCDMASysInfo, 625
NR5GSystemInfoTlv, 695
WCDMASysInfo, 1679
reliabilityClass
GPRSQoS, 322
GPRSRequestedQoS, 323
LibPackGPRSRequestedQoS, 373
wds_GPRSQoS, 1690
remPartyNumber
remotePartyNum, 965
voice_remotePartyNum, 1613
remainingRetries, 963
unblockLeft, 963
verifyLeft, 963
Remote Management Service (RMS), 51
RemotePartyName
getAllCallRmtPtyName, 290
voice_getAllCallRmtPtyName, 1603
remotePartyName, 963
callerName, 964
codingScheme, 964
nameLen, 964
namePI, 964
RemotePartyNum
getAllCallRmtPtyNum, 291
voice_getAllCallRmtPtyNum, 1603
remotePartyNum, 964
numLen, 965
presentationInd, 965
remPartyNumber, 965
ReqFieldsList, 965
requestFields, 965
requestFieldsLen, 965
requestFields
ReqFieldsList, 965
requestFieldsLen
ReqFieldsList, 965
resBerRatio
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
ResCode
FirmwareUpdatStat, 282
GetAudioVolTLBConfigResp, 297
SetAudioVolTLBConfigResp, 1002
unpack_dms_SLQSSwiGetFwUpdateStatus_t, 1259
reserved
omaDmFotaTlvExt, 703
resetDelay
pack_swidms_SLQSSwiDmsSetHWWatchdog_t, 805
swidms_SwiDmsGetHWWatchdog, 1096
SwiDmsGetHWWatchdog, 1097
SwiDmsSetHWWatchdog, 1100
resetInfoInd
pack_dms_SLQSDmsSwiIndicationRegister_t, 715
ResetInfoNotification
qaGobiApiCbk.h, 1919
ResetPDSData
qaGobiApiPds.h, 2149
ResetToFactoryDefaults
qaGobiApiDms.h, 2020
RespFieldsList, 966
responseFields, 966
responseFieldsLen, 966
responseFields
RespFieldsList, 966
responseFieldsLen
RespFieldsList, 966
results
_transLayerInfoNotification, 127
_transNWRegInfoNotification, 128
delAssistDataStatus, 239
gnssSvInfoNotification, 321
msgWaitingInfo, 470
nasNetworkReject, 653

nasNetworkTime, 654
nasSigInfo, 673
nasSysInfo, 679
nasTimers, 680
QmiCbkCatEventStatusReportInd, 916
QmiCbkLocBestAvailPosInd, 922
QmiCbkLocCradleMountInd, 922
QmiCbkLocEngineStateInd, 923
QmiCbkLocEventNMEAInd, 923
QmiCbkLocEventTimeSyncInd, 924
QmiCbkLocGetOpModeInd, 925
QmiCbkLocGetServerInd, 926
QmiCbkLocInjectPositionInd, 927
QmiCbkLocInjectSensorDataInd, 929
QmiCbkLocInjectTimeInd, 929
QmiCbkLocInjectUTCTimeInd, 930
QmiCbkLocOpModeInd, 931
QmiCbkLocPositionReportInd, 937
QmiCbkLocSensorStreamingInd, 938
QmiCbkLocSetExtPowerConfigInd, 938
QmiCbkLocSetServerInd, 939
QmiCbkNasEdrxChangeInfo, 940
QmiCbkNasLTECphyCaInfo, 941
QmiCbkSwiOmaDmEventStatusReportInd, 941
QmiCbkTmdMitiLvlRptInd, 942
QmiCbkWdsStatisticsIndState, 943
QmiNasGetRFBandInfoResp, 946
QmiNasPerformNetworkScanResp, 946
SMSAsyncRawSend_s, 1066
SMSMemoryInfo, 1073
UIMRefreshEvent, 1186
UIMSlotStatusChangeInfo, 1191
UIMStatusChangeInfo, 1192
voiceDTMFEventInfo, 1627
voiceInfoRec, 1649
voiceOTASPStatusInfo, 1651
voicePrivacyInfo, 1652
voiceSetAllCallStatusCbkInfo, 1654
voiceSUPSInfo, 1666
voiceSUPSNotification, 1668
RetryCount
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
revPolarity
lineCtrlInfo, 404
voice_lineCtrlInfo, 1605
revTunneling
unpack_wds_GetMobileIPProfile_t, 1525
ReverseMac
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
RfBandInfoExtFormat, 967
pInstancesSize, 968
pRfBandInfoExtFormatParam, 968
TlvPresent, 968
RfBandInfoExtFormatElements, 968
activeBand, 968
activeChannel, 968
radioInterface, 968
RfBandInfoList, 969
pInstanceSize, 969
pRFBandInfoParam, 969
RfBandwidthInfo, 969
pInstancesSize, 970
pRfBandwidthInfoParam, 970
TlvPresent, 970
RfBandwidthInfoElements, 970
bandwidth, 970
radioInterface, 970
RfDedicatedBandInfo, 970
pInstancesSize, 971
pRfDedicatedBandInfoParam, 971
TlvPresent, 971
RfDedicatedBandInfoElements, 971
dedicatedBand, 972
radioInterface, 972
RfSarState
pack_sar_SLQSSetRfSarState_t, 795
rfbandInfoList
NasGetRFInfoResp, 637
unpack_nas_SLQSNasGetRFInfo_t, 1358
RmTrasnferStaticsReq
pack_wds_RMSetTransferStatistics_t, 846
rmTrasnferStaticsReq, 972
bResetStatistics, 972
ulMask, 972
rms.h, 2368
pack_rms_GetSMSWake, 2368
pack_rms_SetSMSWake, 2369
unpack_rms_GetSMSWake, 2369
unpack_rms_SetSMSWake, 2369
RmtPtyNum
arrRemotePartyNum, 150
voice_arrRemotePartyNum, 1579
roamIndList, 972
numInstances, 973
radioInterface, 973
roamIndicator, 973
roamIndicator
nas_roamIndList, 591
roamIndList, 973
RoamIndicatorVal
unpack_nas_SLQSGetServingSystem_t, 1336
roamIndicatorVal
qaQmiServingSystemParam, 916
roamOrigVoiceSO
prefVoiceSO, 893
voice_prefVoiceSO, 1610
RoamPref
nas_RoamPrefTlv, 591
NASRoamPreferenceTlv, 669
roamStatus
nas_NR5GSystemInfoTlv, 563
nas_sysInfoCommon, 608
NR5GSystemInfoTlv, 695
sysInfoCommon, 1119

roamStatusValid
nas_NR5GSystemInfoTlv, 563
nas_sysInfoCommon, 608
NR5GSystemInfoTlv, 695
sysInfoCommon, 1119
roamTimer, 973
namID, 974
roamTimerValue, 974
roamTimerValue
roamTimer, 974
voice_roamTimer, 1614
Roaming
nas_QmiNas3GppNetworkInfo, 578
SlqsNas3GppNetworkInfo, 1036
unpack_nas_GetCDMANetworkParameters_t, 1309
unpack_nas_GetServingNetwork_t, 1317
roaming
unpack_nas_SetRoamingIndicatorCallback_ind_t, 1324
roaming_ind
RoamingInfo, 973
RoamingIndicatorList
qaQmiServingSystemParam, 916
unpack_nas_SLQSGetServingSystem_t, 1336
RoamingInfo, 973
roaming_ind, 973
TlvPresent, 973
routeList
sms_setRoutesReq, 1063
smsSetRoutesReq, 1079
routeStorage
sms_routeEntry, 1060
smsRouteEntry, 1078
RptIMSCapability
pack_dms_SetIndicationRegister_t, 712
rptPosData
pack_pds_SetEventReportCallback_t, 782
rptRate
LTESigRptCfg, 457
LTESigRptConfig, 458
nas_LTESigRptCfg, 542
nas_LTESigRptConfig, 543
rscp
nas_rxInfo, 595
nas_UMTSInfo, 616
rxInfo, 979
TDSCDMASigInfoExt, 1127
tdscdmaSigInfoExt, 1126
UMTSInfo, 1196
rsrp
cellParams, 196
LTESSInfo, 461
lteSSInfo, 460
nas_cellParams, 486
nas_QmisNasSlqsNasPCIInfo, 581
nas_rxInfo, 595
nas_RxSigInfo, 596
nas_umtsLTENbrCell, 618
rxInfo, 979
RxSigInfo, 982
SlqsNasPCIInfo, 1038
umtsLTENbrCell, 1197
rsrpRx0
nas_QmisNasSlqsNasPCIInfo, 581
SlqsNasPCIInfo, 1038
rsrpRx1
nas_QmisNasSlqsNasPCIInfo, 581
SlqsNasPCIInfo, 1038
rsrplevel
lteRsrpinformation, 454
nas_lteRsrpinformation, 540
rsrq
cellParams, 196
LTESSInfo, 461
lteSSInfo, 460
nas_cellParams, 486
nas_QmisNasSlqsNasPCIInfo, 582
nas_rsrqInformation, 592
nas_SccRxInfo, 598
nas_umtsLTENbrCell, 618
rsrqInformation, 975
SccRxInfo, 987
SlqsNasPCIInfo, 1038
umtsLTENbrCell, 1197
rsrqDelta
nas_SLQSSignalStrengthsIndReq, 603
SLQSSignalStrengthsIndReq, 1047
rsrqInfo
nas_SLQSSignalStrengthsInformation, 604
slqsSignalStrengthInfo, 1046
SLQSSignalStrengthsInformation, 1049
unpack_nas_SLQSGetSignalStrength_t, 1339
rsrqInformation, 975
radioIf, 975
rsrq, 975
rsrqRx0
nas_QmisNasSlqsNasPCIInfo, 582
SlqsNasPCIInfo, 1038
rsrqRx1
nas_QmisNasSlqsNasPCIInfo, 582
SlqsNasPCIInfo, 1038
rssi
CDMASSInfo, 190
cdmaSSInfo, 189
cellParams, 196
gsmCellInfo, 328
HDRSSInfo, 341
hdrSSInfo, 340
LTESSInfo, 461
lteSSInfo, 460
nas_cellParams, 486
nas_gsmCellInfo, 508
TDSCDMASigInfoExt, 1127
tdscdmaSigInfoExt, 1126
unpack_nas_GetSignalStrengths_t, 1318

rts
WdsRunTimeSettings, 1715
rx_bytes
NetStats, 682
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
rx_errors
NetStats, 682
rx_overflows
NetStats, 682
rx_packets
NetStats, 682
rx_pkts
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
RxByteOKCnt
wds_RXBytesOKTlv, 1695
rxChainIndex
nas_RxSigInfo, 596
RxSigInfo, 982
RxDropConutTlv
QmiCbkWdsStatisticsIndState, 943
unpack_RMTransferStatistics_ind_t, 1421
rxInfo, 978
ecio, 979
isRadioTuned, 979
phase, 979
rscp, 979
rsrp, 979
rxPower, 979
rxLev
GERANInfo, 289
nas_GERANInfo, 506
rxOKBytesCount
unpack_wds_SLQSGetDUNCallInfo_t, 1542
RxOkByteCountTlv
QmiCbkWdsStatisticsIndState, 943
unpack_RMTransferStatistics_ind_t, 1421
RxOkConutTlv
QmiCbkWdsStatisticsIndState, 943
unpack_RMTransferStatistics_ind_t, 1422
rxPower
nas_rxInfo, 595
nas_RxSigInfo, 596
rxInfo, 979
RxSigInfo, 982
RxQFilter
unpack_qos_QosFlowInfo_t, 1402
RxQFlowGranted
unpack_qos_QosFlowInfo_t, 1402
RxSigInfo, 981
isRadioTuned, 982
rsrp, 982
rxChainIndex, 982
rxPower, 982
rxSignalStrength
nas_rxSignalStrengthListElement, 597
rxSignalStrengthListElement, 983
rxSignalStrengthDelta
nas_SLQSSignalStrengthsIndReq, 603
SLQSSignalStrengthsIndReq, 1047
rxSignalStrengthInfo
nas_SLQSSignalStrengthsInformation, 604
SLQSSignalStrengthsInformation, 1049
rxSignalStrengthList
slqsSignalStrengthInfo, 1046
unpack_nas_SLQSGetSignalStrength_t, 1339
rxSignalStrengthListElement, 982
radioIf, 983
rxSignalStrength, 983
rxSignalStrengthListLen
slqsSignalStrengthInfo, 1046
unpack_nas_SLQSGetSignalStrength_t, 1339

s
qmifwinfo_s, 944
SMS_EVENT_ETWS
qaGobiApiCbk.h, 1954
SMS_EVENT_ETWS_PLMN
qaGobiApiCbk.h, 1954
SMS_EVENT_MESSAGE_MODE
qaGobiApiCbk.h, 1954
SMS_EVENT_MT_MESSAGE
qaGobiApiCbk.h, 1954
SMS_EVENT_SMS_ON_IMS
qaGobiApiCbk.h, 1954
SMS_EVENT_SMSC_ADDRESS
qaGobiApiCbk.h, 1954
SMS_EVENT_TRANSFER_ROUTE_MT_MESSAGE
qaGobiApiCbk.h, 1954
SYS_SRV_DOMAIN_CAMPED
qaGobiApiCbk.h, 1954
SYS_SRV_DOMAIN_CS_ONLY
qaGobiApiCbk.h, 1954
SYS_SRV_DOMAIN_CS_PS
qaGobiApiCbk.h, 1954
SYS_SRV_DOMAIN_NO_SRV
qaGobiApiCbk.h, 1954
SYS_SRV_DOMAIN_PS_ONLY
qaGobiApiCbk.h, 1954
sApnExtraParams, 983
ambr_dl, 984
ambr_dl_ext, 984
ambr_dl_ext2, 984
ambr_ul, 984
ambr_ul_ext, 984
ambr_ul_ext2, 984
apnId, 984
SCI
unpack_nas_GetCDMANetworkParameters_t, 1309
SCM
unpack_nas_GetCDMANetworkParameters_t, 1309
SDPTlv
NASQmiCbkNasSystemSelPrefInd, 668
SDU_HDR_LEN

common.h, 1722
SECOND_INSTANCE
qaGobiApiCbk.h, 1913
sEdrxCiotLteMode
QmiCbkNasEdrxChangeInfo, 940
sEdrxCycleLength
QmiCbkNasEdrxChangeInfo, 940
sEdrxEnableType
QmiCbkNasEdrxChangeInfo, 940
sEdrxPagingTimeWindow
QmiCbkNasEdrxChangeInfo, 940
sEdrxRatType
QmiCbkNasEdrxChangeInfo, 940
sEnumTimeStampenum
qaGobiApiSms.h, 2175
sGetDeviceSeriesResult, 1023
eDevice, 1024
uResult, 1024
SHORT
SwiDataTypes.h, 2396
SI
calledPartyInfo, 162
callFWExtInfo, 167
callingPartyInfo, 171
redirNumInfo, 962
voice_calledPartyInfo, 1582
voice_callFWExtInfo, 1586
voice_callingPartyInfo, 1591
voice_redirNumInfo, 1611
SIODataPort
qos_BindDataPortSIODataPort_t, 953
SITlv
QmiCbkSwiOmaDmEventStatusReportInd, 941
QmiCbkSwiOmaDmEventStatusReportIndExt, 941
sIntraSearch
LTEInfoIntrafreq, 445
nas_LTEInfoIntrafreq, 531
SLQSAVMSGetSessionInfo
qaGobiApiSwiAvms.h, 2209
SLQSAVMSGetSettings
qaGobiApiSwiAvms.h, 2209
SLQSAVMSGetSettings_v2
qaGobiApiSwiAvms.h, 2209
SLQSAVMSSelection
qaGobiApiSwiAvms.h, 2210
SLQSAVMSSetEventReport
qaGobiApiSwiAvms.h, 2210
SLQSAVMSSetSettings
qaGobiApiSwiAvms.h, 2211
SLQSAVMSSetSettings_v2
qaGobiApiSwiAvms.h, 2211
SLQSAVMSSetSettingsIgnoreAutoReboot
qaGobiApiSwiAvms.h, 2211
SLQSAVMSSetSettingsReq
qaGobiApiSwiAvms.h, 2206
SLQSAVMSSetSettingsReq_v2
qaGobiApiSwiAvms.h, 2207
SLQSAVMSSettings
qaGobiApiSwiAvms.h, 2209
SLQSAVMSSettings_v2
qaGobiApiSwiAvms.h, 2209
SLQSAVMSSettingsAPNInfo
qaGobiApiSwiAvms.h, 2209
SLQSAVMSSettingsConnectionRetryTimers
qaGobiApiSwiAvms.h, 2209
SLQSAVMSSettingsPeriodsInfo
qaGobiApiSwiAvms.h, 2209
SLQSAVMSStartSession
qaGobiApiSwiAvms.h, 2212
SLQSAVMSStopSession
qaGobiApiSwiAvms.h, 2212
SLQSAutoConnect
qaGobiApiWds.h, 2333
SLQSCDMADecodeMTTextMsg
qaGobiApiSms.h, 2178
SLQSCDMADecodeMTTextMsgExt
qaGobiApiSms.h, 2178
SLQSCDMAEncodeMOTextMsg
qaGobiApiSms.h, 2179
SLQSConfigSigInfo
qaGobiApiNas.h, 2121
SLQSCreateProfile
qaGobiApiWds.h, 2334
SLQSDeleteProfile
qaGobiApiWds.h, 2334
SLQSDeleteProfileParams, 1033
profileIndex, 1033
profileType, 1033
SLQSDeleteSMS
qaGobiApiSms.h, 2179
SLQSDmsSwiGetPCInfo
qaGobiApiDms.h, 2021
SLQSDmsSwiGetResetInfo
qaGobiApiDms.h, 2021
SLQSDmsSwiGetUimSelection
qaGobiApiDms.h, 2021
SLQSDmsSwiIndicationRegister
qaGobiApiDms.h, 2021
SLQSDownloadFirmwareToSlot
qaGobiApiFms.h, 2053
SLQSFWINFO_SKU_SZ
qaGobiApiFms.h, 2047
SLQSGet3GPPConfigItem
qaGobiApiWds.h, 2335
SLQSGetAGPSConfig
qaGobiApiPds.h, 2153
SLQSGetAudioPathConfig
qaGobiApiAudio.h, 1899
SLQSGetAudioProfile
qaGobiApiAudio.h, 1899
SLQSGetAudioVolTLBConfig
qaGobiApiAudio.h, 1900
SLQSGetBandCapabilities
qaGobiApiDms.h, 2021
SLQSGetBandCapability
qaGobiApiDms.h, 2022

SLQSGetBootVersionNumber
qaGobiApiFms.h, 2054
SLQSGetByteTotals
qaGobiApiWds.h, 2335
SLQSGetConnectionRate
qaGobiApiWds.h, 2336
SLQSGetCurrDataSystemStat
qaGobiApiWds.h, 2336
SLQSGetCurrentChannelRate
qaGobiApiWds.h, 2337
SLQSGetCurrentPRLInfo
qaGobiApiDms.h, 2024
SLQSGetCustFeatures
qaGobiApiDms.h, 2024
SLQSGetCustFeaturesV2
qaGobiApiDms.h, 2025
SLQSGetDUNCallInfo
qaGobiApiWds.h, 2338
SLQSGetDataBearerTechnology
qaGobiApiWds.h, 2337
SLQSGetDataBearerTechnologyExt
qaGobiApiWds.h, 2338
SLQSGetDeviceMode
qaGobiApiDcs.h, 1998
SLQSGetERIFile
qaGobiApiDms.h, 2025
SLQSGetErrorRate
qaGobiApiNas.h, 2122
SLQSGetFirmwareInfo
qaGobiApiFms.h, 2055
SLQSGetGPSStateInfo
qaGobiApiPds.h, 2154
SLQSGetIMSARegStatus
qaGobiApiImsa.h, 2071
SLQSGetIMSAServiceStatus
qaGobiApiImsa.h, 2071
SLQSGetIMSASupportedFields
qaGobiApiImsa.h, 2072
SLQSGetIMSASupportedMsg
qaGobiApiImsa.h, 2072
SLQSGetIMSSMSConfig
qaGobiApiIms.h, 2065
SLQSGetIMSUserConfig
qaGobiApiIms.h, 2065
SLQSGetIMSVoIPConfig
qaGobiApiIms.h, 2066
SLQSGetImageInfo
qaGobiApiFms.h, 2055
SLQSGetImageInfo_9x15
qaGobiApiFms.h, 2056
SLQSGetImageInfoMC77xx
qaGobiApiFms.h, 2056
SLQSGetImageInfoMC83xx
qaGobiApiFms.h, 2057
SLQSGetImagePartNumber
qaGobiApiFms.h, 2057
SLQSGetIndicationRegister
qaGobiApiSms.h, 2180
SLQSGetM2MAVMute
qaGobiApiSwiAudio.h, 2196
SLQSGetM2MAudioProfile
qaGobiApiSwiAudio.h, 2195
SLQSGetM2MAudioVolume
qaGobiApiSwiAudio.h, 2195
SLQSGetM2MSpkrGain
qaGobiApiSwiAudio.h, 2196
SLQSGetMessageWaiting
qaGobiApiSms.h, 2181
SLQSGetNetStatistic
qaGobiApiDcs.h, 1998
SLQSGetNetworkTime
qaGobiApiNas.h, 2122
SLQSGetOperatorNameData
qaGobiApiNas.h, 2123
SLQSGetPLMNName
qaGobiApiNas.h, 2123
SLQSGetPacketStatistics
qaGobiApiWds.h, 2338
SLQSGetPidof
qaGobiApiSwi.h, 2193
SLQSGetPowerSaveModeConfig
qaGobiApiDms.h, 2025
SLQSGetProfile
qaGobiApiWds.h, 2339
SLQSGetProfileSettings
qaGobiApiWds.h, 2341
SLQSGetRegMgrConfig
qaGobiApiIms.h, 2066
SLQSGetRfSarState
qaGobiApiSar.h, 2168
SLQSGetRuntimeSettings
qaGobiApiWds.h, 2341
SLQSGetSIPConfig
qaGobiApiIms.h, 2067
SLQSGetSMS
qaGobiApiSms.h, 2181
SLQSGetSMSList
qaGobiApiSms.h, 2183
SLQSGetSdkVersion
qaGobiApiSwi.h, 2193
SLQSGetSerialNumbers
qaGobiApiDms.h, 2026
SLQSGetServingSystem
qaGobiApiNas.h, 2124
SLQSGetSessionState
qaGobiApiWds.h, 2341
SLQSGetSignalStrength
qaGobiApiNas.h, 2124
SLQSGetSmsBroadcastConfig
qaGobiApiSms.h, 2182
SLQSGetSysSelectionPref
qaGobiApiNas.h, 2124
SLQSGetSysSelectionPrefExt
qaGobiApiNas.h, 2125
SLQSGetTransLayerInfo
qaGobiApiSms.h, 2184

SLQSGetTransNWRegInfo
qaGobiApiSms.h, 2184
SLQSGetUsbPortNames
qaGobiApiDcs.h, 1999
SLQSGetValidFwPriCombinations
qaGobiApiFms.h, 2058
SLQSImsConfigIndicationRegister
qaGobiApiIms.h, 2067
SLQSInitiateNetworkRegistration
qaGobiApiNas.h, 2125
SLQSIsBootloaderDebugEnabled
qaGobiApiFms.h, 2058
SLQSIsSpkgFormatRequired
qaGobiApiFms.h, 2059
SLQSKillSDKProcess
qaGobiApiDcs.h, 1999
SLQSLOCDelAssData
qaGobiApiLoc.h, 2075
SLQSLOCEventRegister
qaGobiApiLoc.h, 2075
SLQSLOCGetBestAvailPos
qaGobiApiLoc.h, 2075
SLQSLOCGetOpMode
qaGobiApiLoc.h, 2076
SLQSLOCGetServer
qaGobiApiLoc.h, 2076
SLQSLOCInjectPosition
qaGobiApiLoc.h, 2077
SLQSLOCInjectSensorData
qaGobiApiLoc.h, 2077
SLQSLOCInjectUTCTime
qaGobiApiLoc.h, 2077
SLQSLOCSetCradleMountConfig
qaGobiApiLoc.h, 2078
SLQSLOCSetExtPowerState
qaGobiApiLoc.h, 2078
SLQSLOCSetOpMode
qaGobiApiLoc.h, 2079
SLQSLOCSetServer
qaGobiApiLoc.h, 2079
SLQSLOCStart
qaGobiApiLoc.h, 2080
SLQSLOCStop
qaGobiApiLoc.h, 2080
SLQSModifyProfile
qaGobiApiWds.h, 2342
SLQSModifySMSStatus
qaGobiApiSms.h, 2184
SLQSNASGetForbiddenNetworks
qaGobiApiNas.h, 2128
SLQSNASGetLTECPHYCaInfo
qaGobiApiNas.h, 2129
SLQSNASGeteDRXParams
qaGobiApiNas.h, 2127
SLQSNASGeteDRXParamsExt
qaGobiApiNas.h, 2127
SLQSNASSeteDRXParams
qaGobiApiNas.h, 2133
SLQSNASSwiGetChannelLock
qaGobiApiNas.h, 2133
SLQSNASSwiSetChannelLock
qaGobiApiNas.h, 2134
SLQSNasConfigSigInfo2
qaGobiApiNas.h, 2126
SLQSNasEdrxChangeInfoCallBack
qaGobiApiCbk.h, 1970
SLQSNasGet3GPP2Subscription
qaGobiApiNas.h, 2126
SLQSNasGetCellLocationInfo
qaGobiApiNas.h, 2127
SLQSNasGetHDRColorCode
qaGobiApiNas.h, 2128
SLQSNasGetRFInfo
qaGobiApiNas.h, 2129
SLQSNasGetSigInfo
qaGobiApiNas.h, 2129
SLQSNasGetSysInfo
qaGobiApiNas.h, 2130
SLQSNasGetTxRxInfo
qaGobiApiNas.h, 2130
SLQSNasIndicationRegister
qaGobiApiNas.h, 2131
SLQSNasIndicationRegisterExt
qaGobiApiNas.h, 2132
SLQSNasIndicationRegisterLTECphyCa
qaGobiApiNas.h, 2132
SLQSNasNetworkRejectCallback
qaGobiApiCbk.h, 1971
SLQSNasNetworkTimeCallBack
qaGobiApiCbk.h, 1971
SLQSNasSigInfo2CallBack
qaGobiApiCbk.h, 1971
SLQSNasSigInfoCallBack
qaGobiApiCbk.h, 1972
SLQSNasSwiIndicationRegister
qaGobiApiNas.h, 2133
SLQSNasSwiModemStatus
qaGobiApiNas.h, 2134
SLQSNasSwiOTAMessageCallback
qaGobiApiCbk.h, 1972
SLQSNasSysInfoCallBack
qaGobiApiCbk.h, 1973
SLQSNasTimerCallback
qaGobiApiCbk.h, 1973
SLQSOMADMCancelSession
qaGobiApiSwiOmadms.h, 2222
SLQSOMADMGetSessionInfo
qaGobiApiSwiOmadms.h, 2223
SLQSOMADMGetSettings
qaGobiApiSwiOmadms.h, 2223
SLQSOMADMGetSettings2
qaGobiApiSwiOmadms.h, 2224
SLQSOMADMSendSelection
qaGobiApiSwiOmadms.h, 2224
SLQSOMADMSendSelection2
qaGobiApiSwiOmadms.h, 2225

SLQSOMADMSessionInfo
qaGobiApiSwiOmadms.h, 2218
SLQSOMADMSetSettings
qaGobiApiSwiOmadms.h, 2225
SLQSOMADMSetSettings2
qaGobiApiSwiOmadms.h, 2226
SLQSOMADMSetSettings3
qaGobiApiSwiOmadms.h, 2226
SLQSOMADMSettings
qaGobiApiSwiOmadms.h, 2220
SLQSOMADMSettingsReqParams
qaGobiApiSwiOmadms.h, 2221
SLQSOMADMSettingsReqParams3
qaGobiApiSwiOmadms.h, 2222
SLQSOMADMStartSession
qaGobiApiSwiOmadms.h, 2227
SLQSOMADMStartSession2
qaGobiApiSwiOmadms.h, 2227
SLQSOriginateUSSD
qaGobiApiVoice.h, 2289
SLQSPDSDeterminePosition
qaGobiApiPds.h, 2154
SLQSPDSInjectAbsoluteTimeReference
qaGobiApiPds.h, 2155
SLQSPDSInjectPositionData
qaGobiApiPds.h, 2155
SLQSPerformNetworkScan
qaGobiApiNas.h, 2134
SLQSPerformNetworkScanPCI
qaGobiApiNas.h, 2135
SLQSQosGetFlowStatus
qaGobiApiQos.h, 2159
SLQSQosGetGranted
qaGobiApiQos.h, 2160
SLQSQosGetNWProf
qaGobiApiQos.h, 2161
SLQSQosGetNetworkStatus
qaGobiApiQos.h, 2160
SLQSQosModify
qaGobiApiQos.h, 2161
SLQSQosRel
qaGobiApiQos.h, 2162
SLQSQosReq
qaGobiApiQos.h, 2162
SLQSQosReset
qaGobiApiQos.h, 2163
SLQSQosResume
qaGobiApiQos.h, 2163
SLQSQosSuspend
qaGobiApiQos.h, 2164
SLQSQosSwiReadApnExtraParams
qaGobiApiQos.h, 2164
SLQSQosSwiReadDataStats
qaGobiApiQos.h, 2164
SLQSRegisterIMSAIndication
qaGobiApiImsa.h, 2073
SLQSResetPacketStatics
qaGobiApiWds.h, 2343
SLQSSGetDHCPv4ClientConfig
qaGobiApiWds.h, 2345
SLQSSGetLoopback
qaGobiApiWds.h, 2345
SLQSSSTlv
unpack_nas_SetEventReportInd_t, 1322
SLQSSSetDHCPv4ClientConfig
qaGobiApiWds.h, 2346
SLQSSSetLoopback
qaGobiApiWds.h, 2346
SLQSSendAsyncSMS
qaGobiApiSms.h, 2185
SLQSSendLongSMS
qaGobiApiSms.h, 2185
SLQSSendRawQMI
qaGobiApiSwi.h, 2193
SLQSSendSMS
qaGobiApiSms.h, 2186
SLQSSet3GPPConfigItem
qaGobiApiWds.h, 2343
SLQSSetAGPSConfig
qaGobiApiPds.h, 2156
SLQSSetAudioPathConfig
qaGobiApiAudio.h, 1900
SLQSSetAudioProfile
qaGobiApiAudio.h, 1901
SLQSSetAudioVolTLBConfig
qaGobiApiAudio.h, 1901
SLQSSetBandPreference
qaGobiApiNas.h, 2135
SLQSSetBandPreferenceCbk
qaGobiApiCbk.h, 1973
SLQSSetCrashStateCheckIgnore
qaGobiApiFms.h, 2059
SLQSSetCustFeatures
qaGobiApiDms.h, 2026
SLQSSetCustFeaturesV2
qaGobiApiDms.h, 2027
SLQSSetDHCPv4ClientLeaseStatusCallback
qaGobiApiCbk.h, 1974
SLQSSetDHCPv4ClientLeaseStatusCallbackParam, 1043
instance, 1043
pCallback, 1043
SLQSSetDUNCallInfoCallback
qaGobiApiCbk.h, 1975
SLQSSetDataSystemStatusCallback
qaGobiApiCbk.h, 1974
SLQSSetIMSAPdpStatusCallback
qaGobiApiCbk.h, 1975
SLQSSetIMSARatStatusCallback
qaGobiApiCbk.h, 1975
SLQSSetIMSARegStatusCallback
qaGobiApiCbk.h, 1976
SLQSSetIMSASvcStatusCallback
qaGobiApiCbk.h, 1976
SLQSSetIMSSMSConfig
qaGobiApiIms.h, 2068

SLQSSetIMSSMSConfigCallback
qaGobiApiCbk.h, 1977
SLQSSetIMSUserConfig
qaGobiApiIms.h, 2068
SLQSSetIMSUserConfigCallback
qaGobiApiCbk.h, 1977
SLQSSetIMSVoIPConfig
qaGobiApiIms.h, 2069
SLQSSetIMSVoIPConfigCallback
qaGobiApiCbk.h, 1978
SLQSSetIndicationRegister
qaGobiApiSms.h, 2187
SLQSSetLocInjectPositionCallback
qaGobiApiCbk.h, 1978
SLQSSetLocInjectUTCTimeCallback
qaGobiApiCbk.h, 1978
SLQSSetLoggingMask
qaGobiApiDcs.h, 2000
SLQSSetM2MAVMute
qaGobiApiSwiAudio.h, 2198
SLQSSetM2MAudioAVCFG
qaGobiApiSwiAudio.h, 2196
SLQSSetM2MAudioLPBK
qaGobiApiSwiAudio.h, 2197
SLQSSetM2MAudioNVDef
qaGobiApiSwiAudio.h, 2197
SLQSSetM2MAudioProfile
qaGobiApiSwiAudio.h, 2198
SLQSSetM2MAudioVolume
qaGobiApiSwiAudio.h, 2198
SLQSSetM2MSpkrGain
qaGobiApiSwiAudio.h, 2199
SLQSSetModemTempCallback
qaGobiApiCbk.h, 1978
SLQSSetPacketSrvStatusCallback
qaGobiApiCbk.h, 1979
SLQSSetPositionMethodState
qaGobiApiPds.h, 2156
SLQSSetPowerSaveModeConfig
qaGobiApiDms.h, 2027
SLQSSetProfile
qaGobiApiWds.h, 2343
SLQSSetQosEventCallback
qaGobiApiCbk.h, 1979
SLQSSetQosNWStatusCallback
qaGobiApiCbk.h, 1980
SLQSSetQosPriEventCallback
qaGobiApiCbk.h, 1980
SLQSSetQosStatusCallback
qaGobiApiCbk.h, 1980
SLQSSetRegMgrConfig
qaGobiApiIms.h, 2069
SLQSSetRegMgrConfigCallback
qaGobiApiCbk.h, 1981
SLQSSetRfSarState
qaGobiApiSar.h, 2168
SLQSSetSDKTerminatedCallback
qaGobiApiCbk.h, 1981
SLQSSetSIMBasedImageSwitching
qaGobiApiFms.h, 2060
SLQSSetSIPConfig
qaGobiApiIms.h, 2070
SLQSSetSIPConfigCallback
qaGobiApiCbk.h, 1983
SLQSSetSMSEventCallback
qaGobiApiCbk.h, 1984
SLQSSetServingSystemCallback
qaGobiApiCbk.h, 1982
SLQSSetSessionStateCallback
qaGobiApiCbk.h, 1982
SLQSSetSignalStrengthsCallback
qaGobiApiCbk.h, 1983
SLQSSetSmsBroadcastActivation
qaGobiApiSms.h, 2187
SLQSSetSmsBroadcastConfig
qaGobiApiSms.h, 2188
SLQSSetSmsStorage
qaGobiApiSms.h, 2188
SLQSSetSpkgFormatRequired
qaGobiApiFms.h, 2060
SLQSSetSwiGetResetInfoCallback
qaGobiApiCbk.h, 1984
SLQSSetSwiHDRPersCallback
qaGobiApiCbk.h, 1984
SLQSSetSysSelectionPref
qaGobiApiNas.h, 2137
SLQSSetSysSelectionPrefCallBack
qaGobiApiCbk.h, 1985
SLQSSetSysSelectionPrefExt
qaGobiApiNas.h, 2137
SLQSSetTransLayerInfoCallback
qaGobiApiCbk.h, 1985
SLQSSetTransNWRegInfoCallback
qaGobiApiCbk.h, 1985
SLQSSetUIMStatusCallback
qaGobiApiCbk.h, 1986
SLQSSetWdsEventCallback
qaGobiApiCbk.h, 1986
SLQSSetWdsTransferStatisticCallback
qaGobiApiCbk.h, 1987
SLQSSignalStrengthsIndReq, 1046
ecioDelta, 1047
ecioThresholdList, 1047
ecioThresholdListLen, 1047
ioDelta, 1047
lteRsrpDelta, 1047
lteSnrDelta, 1047
rsrqDelta, 1047
rxSignalStrengthDelta, 1047
sinrDelta, 1047
sinrThresholdList, 1047
sinrThresholdListLen, 1047
SLQSSignalStrengthsInformation, 1048
ecioInfo, 1049
errorRateInfo, 1049
io, 1049

lteRsrpinfo, 1049
lteSnrinfo, 1049
rsrqInfo, 1049
rxSignalStrengthInfo, 1049
sinr, 1049
SLQSSmsGetMaxStorageSize
qaGobiApiSms.h, 2189
SLQSSmsGetMessageProtocol
qaGobiApiSms.h, 2189
SLQSSmsSetRoutes
qaGobiApiSms.h, 2190
SLQSStart
qaGobiApiDcs.h, 2000
SLQSStart_AVAgent
qaGobiApiDcs.h, 2001
SLQSStartSrv
qaGobiApiDcs.h, 2001
SLQSStartStopDataSession
qaGobiApiWds.h, 2346
SLQSSwiAVMSEventReportCallback
qaGobiApiCbk.h, 1988
SLQSSwiClearDyingGaspStatistics
qaGobiApiDms.h, 2028
SLQSSwiDmsGetHWWatchdog
qaGobiApiSwiDms.h, 2214
SLQSSwiDmsGetMTU
qaGobiApiSwiDms.h, 2214
SLQSSwiDmsGetSecureInfo
qaGobiApiSwiDms.h, 2215
SLQSSwiDmsGetUsbComp
qaGobiApiSwiDms.h, 2215
SLQSSwiDmsGetUsbNetNum
qaGobiApiSwiDms.h, 2215
SLQSSwiDmsSetHWWatchdog
qaGobiApiSwiDms.h, 2216
SLQSSwiDmsSetMTU
qaGobiApiSwiDms.h, 2216
SLQSSwiDmsSetUsbComp
qaGobiApiSwiDms.h, 2216
SLQSSwiDmsSetUsbNetNum
qaGobiApiSwiDms.h, 2217
SLQSSwiDmsUimSelect
qaGobiApiDms.h, 2028
SLQSSwiGetAllCarrierImages
qaGobiApiFms.h, 2060
SLQSSwiGetCrashAction
qaGobiApiDms.h, 2028
SLQSSwiGetCrashInfo
qaGobiApiDms.h, 2029
SLQSSwiGetDyingGaspCfg
qaGobiApiDms.h, 2029
SLQSSwiGetDyingGaspStatistics
qaGobiApiDms.h, 2029
SLQSSwiGetFSN
qaGobiApiDms.h, 2030
SLQSSwiGetFirmwareCurr
qaGobiApiFms.h, 2061
SLQSSwiGetFwUpdateStatus
qaGobiApiDms.h, 2030
SLQSSwiGetHDRPersonality
qaGobiApiNas.h, 2137
SLQSSwiGetHDRProtSubtype
qaGobiApiNas.h, 2138
SLQSSwiGetHRPDStats
qaGobiApiNas.h, 2138
SLQSSwiGetHostDevInfo
qaGobiApiDms.h, 2031
SLQSSwiGetHostDevInfoParams
qaGobiApiDms.h, 2009
SLQSSwiGetLteCQI
qaGobiApiNas.h, 2139
SLQSSwiGetLteSccRxInfo
qaGobiApiNas.h, 2139
SLQSSwiGetOSInfo
qaGobiApiDms.h, 2031
SLQSSwiGetOSInfoParams
qaGobiApiDms.h, 2009
SLQSSwiGetSMSStorage
qaGobiApiSms.h, 2190
SLQSSwiGetSerialNoExt
qaGobiApiDms.h, 2031
SLQSSwiGetSerialNoExtParams
qaGobiApiDms.h, 2010
SLQSSwiGetUSBComp
qaGobiApiDms.h, 2032
SLQSSwiNetworkDebug
qaGobiApiNas.h, 2139
SLQSSwiPSDetach
qaGobiApiNas.h, 2140
SLQSSwiSetCrashAction
qaGobiApiDms.h, 2032
SLQSSwiSetDyingGaspCfg
qaGobiApiDms.h, 2033
SLQSSwiSetHostDevInfo
qaGobiApiDms.h, 2033
SLQSSwiSetHostDevInfoParams
qaGobiApiDms.h, 2010
SLQSSwiSetOSInfo
qaGobiApiDms.h, 2034
SLQSSwiSetOSInfoParams
qaGobiApiDms.h, 2011
SLQSSwiSetUSBComp
qaGobiApiDms.h, 2034
SLQSTmdDeRegNotMitigationLvl
qaGobiApiTmd.h, 2268
SLQSTmdGetMitigationDevList
qaGobiApiTmd.h, 2269
SLQSTmdGetMitigationLvl
qaGobiApiTmd.h, 2269
SLQSTmdMitigationLvlRptCallback
qaGobiApiCbk.h, 1988
SLQSTmdMitigationLvlRptCallbackParam, 1049
pCallback, 1049
pReq, 1049
SLQSTmdRegNotMitigationLvl
qaGobiApiTmd.h, 2269

SLQSUIMAuthenticate
qaGobiApiUim.h, 2272
SLQSUIMChangePin
qaGobiApiUim.h, 2273
SLQSUIMDepersonalization
qaGobiApiUim.h, 2273
SLQSUIMEventRegister
qaGobiApiUim.h, 2274
SLQSUIMGetCardStatus
qaGobiApiUim.h, 2274
SLQSUIMGetCardStatusV2
qaGobiApiUim.h, 2275
SLQSUIMGetConfiguration
qaGobiApiUim.h, 2275
SLQSUIMGetFileAttributes
qaGobiApiUim.h, 2276
SLQSUIMGetSlotsStatus
qaGobiApiUim.h, 2277
SLQSUIMGetState
qaGobiApiDms.h, 2034
SLQSUIMPowerDown
qaGobiApiUim.h, 2277
SLQSUIMPowerUp
qaGobiApiUim.h, 2277
SLQSUIMReadTransparent
qaGobiApiUim.h, 2278
SLQSUIMRefreshComplete
qaGobiApiUim.h, 2278
SLQSUIMRefreshGetLastEvent
qaGobiApiUim.h, 2279
SLQSUIMRefreshOK
qaGobiApiUim.h, 2279
SLQSUIMRefreshRegister
qaGobiApiUim.h, 2280
SLQSUIMReset
qaGobiApiUim.h, 2280
SLQSUIMSetPinProtection
qaGobiApiUim.h, 2281
SLQSUIMSetRefreshCallBack
qaGobiApiCbk.h, 1988
SLQSUIMSetStatusChangeCallBack
qaGobiApiCbk.h, 1988
SLQSUIMSwitchSlot
qaGobiApiUim.h, 2281
SLQSUIMUnblockPin
qaGobiApiUim.h, 2282
SLQSUIMUnblockPinV2
qaGobiApiUim.h, 2282
SLQSUIMVerifyPin
qaGobiApiUim.h, 2283
SLQSUpgradeFirmware9x07
qaGobiApiFms.h, 2061
SLQSUpgradeFirmware9x15
qaGobiApiFms.h, 2062
SLQSVoiceALSSelectLine
qaGobiApiVoice.h, 2289
SLQSVoiceALSSetLineSwitching
qaGobiApiVoice.h, 2290
SLQSVoiceAnswerCall
qaGobiApiVoice.h, 2290
SLQSVoiceBindSubscription
qaGobiApiVoice.h, 2291
SLQSVoiceBurstDTMF
qaGobiApiVoice.h, 2291
SLQSVoiceDialCall
qaGobiApiVoice.h, 2292
SLQSVoiceEndCall
qaGobiApiVoice.h, 2292
SLQSVoiceGetAllCallInfo
qaGobiApiVoice.h, 2293
SLQSVoiceGetCLIP
qaGobiApiVoice.h, 2295
SLQSVoiceGetCLIR
qaGobiApiVoice.h, 2296
SLQSVoiceGetCNAP
qaGobiApiVoice.h, 2296
SLQSVoiceGetCOLP
qaGobiApiVoice.h, 2297
SLQSVoiceGetCOLR
qaGobiApiVoice.h, 2297
SLQSVoiceGetCallBarring
qaGobiApiVoice.h, 2293
SLQSVoiceGetCallForwardingStatus
qaGobiApiVoice.h, 2294
SLQSVoiceGetCallInfo
qaGobiApiVoice.h, 2294
SLQSVoiceGetCallWaiting
qaGobiApiVoice.h, 2295
SLQSVoiceGetConfig
qaGobiApiVoice.h, 2298
SLQSVoiceIndicationRegister
qaGobiApiVoice.h, 2299
SLQSVoiceInfoRecCallback
qaGobiApiCbk.h, 1989
SLQSVoiceManageCalls
qaGobiApiVoice.h, 2299
SLQSVoiceOrigUSSDNoWait
qaGobiApiVoice.h, 2300
SLQSVoiceSendFlash
qaGobiApiVoice.h, 2300
SLQSVoiceSetAllCallStatusCallBack
qaGobiApiCbk.h, 1989
SLQSVoiceSetCallBarringPassword
qaGobiApiVoice.h, 2301
SLQSVoiceSetConfig
qaGobiApiVoice.h, 2301
SLQSVoiceSetDTMFEventCallBack
qaGobiApiCbk.h, 1990
SLQSVoiceSetOTASPStatusCallBack
qaGobiApiCbk.h, 1990
SLQSVoiceSetPreferredPrivacy
qaGobiApiVoice.h, 2302
SLQSVoiceSetPrivacyChangeCallBack
qaGobiApiCbk.h, 1990
SLQSVoiceSetSUPSCallBack
qaGobiApiCbk.h, 1991

SLQSVoiceSetSUPSNotificationCallback
qaGobiApiCbk.h, 1991
SLQSVoiceSetSUPSService
qaGobiApiVoice.h, 2302
SLQSVoiceStartContDTMF
qaGobiApiVoice.h, 2303
SLQSVoiceStopContDTMF
qaGobiApiVoice.h, 2303
SLQSWCDMADecodeLongTextMsg
qaGobiApiSms.h, 2191
SLQSWCDMADecodeMTEncoding
qaGobiApiSms.h, 2191
SLQSWCDMADecodeMTTextMsg
qaGobiApiSms.h, 2192
SLQSWCDMAEncodeMOTextMsg
qaGobiApiSms.h, 2192
SLQSWdsGoActive
qaGobiApiWds.h, 2347
SLQSWdsGoDormant
qaGobiApiWds.h, 2347
SLQSWdsSetEventReport
qaGobiApiWds.h, 2348
SLQSWdsSwiPDPRuntimeSettings
qaGobiApiWds.h, 2348
SLQSWmsAsyncRawSendCallBack
qaGobiApiCbk.h, 1992
SLQSWmsMemoryFullCallBack
qaGobiApiCbk.h, 1992
SLQSWmsMessageWaitingCallBack
qaGobiApiCbk.h, 1993
SMS_CONFIG_LEN
sms.h, 2375
SMS_MAX_SMS_ROUTES
sms.h, 2376
SMS_NUM_OF_SET
sms.h, 2376
SMSAsyncRawSend
qaGobiApiCbk.h, 1921
SMSAsyncRawSend_s, 1064
alphaIDLen, 1066
causeCode, 1066
errorClass, 1066
messageID, 1066
msgDelFailureCause, 1066
msgDelFailureType, 1066
pAlphaID, 1066
RPCause, 1066
results, 1066
sendStatus, 1066
TPCause, 1066
userData, 1066
SMSC_TYPE_LEN
sms.h, 2376
SMSCAddress, 1066
data, 1066
length, 1067
SMSCAddressInfo
qaGobiApiCbk.h, 1922
sMSCAddressInfo, 1067
data, 1067
length, 1067
sMSCAddressTlv, 1067
SMSCInfo, 1067
TlvPresent, 1068
SMSCInfo
sMSCAddressTlv, 1067
SMSCTlv
unpack_sms_SetNewSMSCallback_ind_t, 1426
SMSEtwsMessage, 1068
data, 1068
length, 1068
notificationType, 1068
SMSEtwsMessageInfo
qaGobiApiCbk.h, 1922
sMSEtwsMessageInfo, 1068
data, 1069
length, 1069
notificationType, 1069
sMSEtwsMessageTlv, 1069
EtwsMessageInfo, 1069
TlvPresent, 1069
SMSEtwsPlmn, 1069
mobileCountryCode, 1070
mobileNetworkCode, 1070
SMSEtwsPlmnInfo
qaGobiApiCbk.h, 1922
sMSEtwsPlmnInfo, 1070
mobileCountryCode, 1070
mobileNetworkCode, 1070
SMSEventInfo
qaGobiApiCbk.h, 1922
SMSEventInfo_s, 1070
pEtwsMessageInfo, 1071
pEtwsPlmnInfo, 1071
pMTMessageInfo, 1071
pMessageModeInfo, 1071
pSMSCAddressInfo, 1071
pSMSOnIMSInfo, 1072
pTransferRouteMTMessageInfo, 1072
smsEventType, 1072
SMSEventType
qaGobiApiCbk.h, 1954
SMSMTMessage, 1075
messageIndex, 1075
storageType, 1075
SMSMTMessageInfo
qaGobiApiCbk.h, 1923
sMSMTMessageInfo, 1075
messageIndex, 1076
storageType, 1076
SMSMemoryInfo, 1073
messageMode, 1073
results, 1073
storageType, 1073
SMSMessageMode, 1073
messageMode, 1074

SMSMessageModeInfo
qaGobiApiCbk.h, 1923
sMSMessageModeInfo, 1074
messageMode, 1074
SMSOnIMS, 1076
smsOnIMS, 1076
SMSOnIMSInfo
qaGobiApiCbk.h, 1924
sMSOnIMSInfo, 1076
smsOnIMS, 1076
sMSOnIMSTlv, 1077
IMSInfo, 1077
TlvPresent, 1077
SMSSupport
pack_dms_SetCustFeature_t, 710
unpack_dms_GetCustFeature_t, 1211
SMSTransferRouteMTMessage, 1079
ackIndicator, 1080
data, 1080
format, 1080
length, 1080
transactionID, 1080
SMSTransferRouteMTMessageInfo
qaGobiApiCbk.h, 1924
sMSTransferRouteMTMessageInfo, 1080
ackIndicator, 1080
data, 1081
format, 1081
length, 1081
transactionID, 1081
SNR
nas_NetworkStatEVDO, 556
NetworkStatEVDO, 687
sNonIntraSearch
LTEInfoIntrafreq, 445
nas_LTEInfoIntrafreq, 531
SO
nas_NetworkStat1x, 554
NetworkStat1x, 685
SOMask
CurrNetworkInfo, 224
currNetworkInfo, 224
wds_currNetworkInfo, 1682
SPC_SIZE
dms.h, 1734
sPhyCaAggPcellInfo
nasGetLTECphyCa, 635
QmiCbkNasLTECphyCaInfo, 941
unpack_nas_SetNasLTECphyCaIndCallback_ind_t, 1323
sPhyCaAggScellArray
nasGetLTECphyCa, 635
sPhyCaAggScellDlBw
nasGetLTECphyCa, 635
QmiCbkNasLTECphyCaInfo, 941
unpack_nas_SetNasLTECphyCaIndCallback_ind_t, 1323
sPhyCaAggScellIndType
nasGetLTECphyCa, 635
QmiCbkNasLTECphyCaInfo, 941
unpack_nas_SetNasLTECphyCaIndCallback_ind_t, 1323
sPhyCaAggScellIndex
nasGetLTECphyCa, 635
QmiCbkNasLTECphyCaInfo, 941
unpack_nas_SetNasLTECphyCaIndCallback_ind_t, 1323
sPhyCaAggScellInfo
nasGetLTECphyCa, 635
QmiCbkNasLTECphyCaInfo, 941
unpack_nas_SetNasLTECphyCaIndCallback_ind_t, 1323
sQosFlowStat, 1081
bearerId, 1081
tx_bytes, 1081
tx_bytes_drp, 1081
tx_pkt, 1081
tx_pkt_drp, 1081
sQosStat, 1082
apnId, 1082
numQosFlow, 1083
qosFlow, 1083
total_rx_bytes, 1083
total_rx_pkt, 1083
total_tx_bytes, 1083
total_tx_bytes_drp, 1083
total_tx_pkt, 1083
total_tx_pkt_drp, 1083
SSInfo
unpack_nas_SetServingSystemCallback_ind_t, 1325
sSLQSSignalStrengthsInfo
nas_SLQSSignalStrengthsTlv, 605
SSTlv
unpack_nas_SetEventReportInd_t, 1322
SUPSInfo, 1087
isModByCC, 1088
svcType, 1088
SUPSInformation
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1508
voiceSUPSInfo, 1666
SUPSType
pack_voice_SLQSVoiceManageCalls_t, 835
voiceManageCallsReq, 1649
SV, 1088
id, 1089
mask, 1089
system, 1089
SVInfo, 1089
len, 1089
pSV, 1090
SWI Audio Service(SWIAUDIO), 62
SWI Open Mobile Alliance Service (SWIOMA), 55
SWI_API
SwiDataTypes.h, 2395

SWI_STRUCT_CarrierImage, 1090
m_FwBuildId, 1091
m_FwImageId, 1091
m_PriBuildId, 1091
m_PriImageId, 1091
m_nCarrierId, 1091
m_nFolderId, 1091
m_nStorage, 1091
SWIDMS, 66
SWIWWANCMAPI.h, 2416
samplesPerBatch
accelAcceptReady_s, 128
accelTempAcceptReady_s, 129
gyroAcceptReady_s, 334
gyroTempAcceptReady_s, 334
loc_accelAcceptReady, 405
loc_accelTempAcceptReady, 405
loc_gyroAcceptReady, 411
loc_gyroTempAcceptReady, 412
sar.h, 2370
pack_sar_SLQSGetRfSarState, 2370
pack_sar_SLQSSetRfSarState, 2370
unpack_sar_SLQSGetRfSarState, 2371
unpack_sar_SLQSSetRfSarState, 2371
unpack_sar_SLQSSetRfSarState_t, 2370
satelliteInfo, 984
azimuth, 986
elevation, 986
gnssSvId, 986
healthStatus, 986
snr, 986
svInfoMask, 986
svListLen, 986
svStatus, 986
system, 986
validMask, 986
SaveSMS
qaGobiApiSms.h, 2176
sbas_almanac_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
sbas_ephemeris_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
sbas_health_sv_msk
GPSStateInfo, 326
unpack_pds_SLQSGetGPSStateInfo_t, 1396
sbas_visible_sv_msk
GPSStateInfo, 327
unpack_pds_SLQSGetGPSStateInfo_t, 1396
scAddr
wcdmaMsgDecodingParams, 1674
SccRxInfo, 987
numInstances, 987
rsrq, 987
sigInfo, 987
snr, 987
TlvPresent, 987
scell_idx
nas_PhyCaAggScellIndex, 567
NASPhyCaAggScellArray, 658
NASPhyCaAggScellIndex, 659
PhyCaAggScellArray, 879
PhyCaAggScellIndex, 880
scell_state
nas_PhyCaAggScellIndType, 567
nas_PhyCaAggScellInfo, 570
NASPhyCaAggScellArray, 658
NASPhyCaAggScellIndType, 660
NASPhyCaAggScellInfo, 661
PhyCaAggScellArray, 879
PhyCaAggScellIndType, 880
PhyCaAggScellInfo, 883
screeningInd
connectNumInfo, 210
voice_connectNumInfo, 1597
sduErrorRatio
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
seDNSIPv4Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
seDNSIPv6Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
sePCSCFIPv4Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
sePCSCFIPv6Address
unpack_wds_SLQSWdsSwiPDPRuntimeSettings-_t, 1559
secActivate
fileAttributes, 279
uim_fileAttributes, 1157
secActivateMask
fileAttributes, 279
uim_fileAttributes, 1157
secChA
CDMAChannel, 179
nas_CDMAChannel, 479
secChB
CDMAChannel, 179
nas_CDMAChannel, 479
secDeactivate
fileAttributes, 279
uim_fileAttributes, 1157
secDeactivateMask
fileAttributes, 279
uim_fileAttributes, 1157
secIncrease
fileAttributes, 279
uim_fileAttributes, 1157
secIncreaseMask
fileAttributes, 279

uim_fileAttributes, 1157
SecProt
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 906
secRead
fileAttributes, 279
uim_fileAttributes, 1157
secReadMask
fileAttributes, 279
uim_fileAttributes, 1157
secWrite
fileAttributes, 279
uim_fileAttributes, 1157
secWriteMask
fileAttributes, 279
uim_fileAttributes, 1157
secdns
unpack_wds_GetDefaultProfile_t, 1521
secdnsv6
unpack_wds_GetDefaultProfile_t, 1521
second
nas_timeInfo, 613
nas_UniversalTime, 619
timeInfo, 1134
UniversalTime, 1205
secondaryDNS
pack_wds_SetDefaultProfile_t, 849
SecondaryDNSV4
unpack_wds_SLQSGetRuntimeSettings_t, 1545
SecondaryDNSV6
unpack_wds_SLQSGetRuntimeSettings_t, 1545
secondaryHA
unpack_wds_GetMobileIPProfile_t, 1525
SectorIDLen
nas_NetworkStatEVDO, 556
NetworkStatEVDO, 687
secureBootEnabled
SwiDmsGetSecureInfoResp, 1098
unpack_swidms_SLQSSwiDmsGetSecureInfo_t, 1444
selNetwork
nas_servSystem, 600
servSystem, 996
selected
BroadcastConfig, 158
CDMABroadcastConfig, 178
sms_BroadcastConfig, 1051
sms_CDMABroadcastConfig, 1052
selectedNetwork
NASServingSystemInfo, 671
ServingSystemInfo, 995
selection
pack_swioma_SLQSOMADMSendSelection_t, 810
SendSMS
qaGobiApiSms.h, 2177
sendStatus
SMSAsyncRawSend_s, 1066
unpack_sms_SLQSWmsAsyncRawSendCallBack-_ind_t, 1440
senderAddr
cdmaMsgDecodingParams, 183
wcdmaMsgDecodingParams, 1674
sensorData, 987
flags, 989
sensorDataLen, 989
timeOfFirstSample, 989
timeOffset, 989
xAxis, 989
yAxis, 989
zAxis, 989
sensorData_t, 989
flags, 990
sensorDataLen, 990
timeOfFirstSample, 990
timeOffset, 990
xAxis, 990
yAxis, 990
zAxis, 990
sensorDataLen
sensorData, 989
sensorData_t, 990
sensorDataUsage
qaGobiApiCbk.h, 1920
sensorDataUsage_s, 991
aidingIndicatorMask, 991
usageMask, 991
serialNumbersInfo, 991
esnSize, 992
imeiSize, 992
imeiSvnSize, 992
meidSize, 992
pESNString, 992
pIMEIString, 992
pImeiSvnString, 992
pMEIDString, 992
qaGobiApiDms.h, 2008
servSystem, 995
csAttachState, 996
numRadioInterfaces, 996
psAttachState, 996
radioInterface, 996
regState, 996
selNetwork, 996
ServerAddrList
unpack_wds_SLQSGetRuntimeSettings_t, 1545
serverAddrTypeMask
pack_loc_SLQSLOCGetServer_t, 731
serverStatus
QmiCbkLocGetServerInd, 926
QmiCbkLocSetServerInd, 939
unpack_loc_GetServer_Ind_t, 1288
unpack_loc_SetServer_Ind_t, 1303
serverType
LocGetServerReq, 427
LocSetServerReq, 434

pack_loc_SLQSLOCGetServer_t, 731
pack_loc_SLQSLOCSetServer_t, 740
QmiCbkLocGetServerInd, 926
unpack_loc_GetServer_Ind_t, 1288
serviceCategory
CDMABroadcastConfig, 178
sms_CDMABroadcastConfig, 1052
serviceClassInformation
qaGobiApiVoice.h, 2287
serviceDomain
nas_RejectReasonTlv, 583
nasNetworkReject, 653
unpack_nas_SLQSNasNetworkRejectCallback_-Ind_t, 1363
serviceProviderName, 993
displayCondition, 993
spn, 993
spnLength, 993
servingCellId
LTEInfoIntrafreq, 445
nas_LTEInfoIntrafreq, 531
ServingSystem
qaQmiServingSystemParam, 916
unpack_nas_SLQSGetServingSystem_t, 1336
ServingSystemInfo, 993
csAttachState, 994
hdrPersonality, 994
psAttachState, 994
radioInterfaceList, 994
radioInterfaceNo, 995
registrationState, 995
selectedNetwork, 995
sessionControl
pack_pds_StartPDSTrackingSessionExt_t, 791
sessionEndReason
_packetSrvStatus, 76
slqsSessionStateInfo, 1043
unpack_wds_SLQSSetPacketSrvStatusCallback_-t, 1549
SessionId
LOCStartReq, 435
pack_loc_Start_t, 742
pack_loc_Stop_t, 742
sessionId
LOCStopReq, 436
QmiCbkLocPositionReportInd, 937
ssdatasession_params, 1086
unpack_loc_PositionRpt_Ind_t, 1299
sessionInfo, 996
omaDmConfig, 997
omaDmFota, 997
omaDmNotifications, 997
pack_uim_ChangePin_t, 812
pack_uim_ReadTransparent_t, 813
pack_uim_SetPinProtection_t, 814
pack_uim_SLQSUIMAuthenticate_t, 815
pack_uim_SLQSUIMGetFileAttributes_t, 817
pack_uim_SLQSUIMRefreshComplete_t, 819
pack_uim_SLQSUIMRefreshGetLastEvent_t, 819
pack_uim_SLQSUIMRefreshOK_t, 820
pack_uim_SLQSUIMRefreshRegister_t, 820
pack_uim_UnblockPin_t, 822
pack_uim_VerifyPin_t, 823
sessionInfoTlv, 997
sessionInfoTlvExt, 998
UIMAuthenticateReq, 1171
UIMChangePinReq, 1173
UIMGetFileAttributesReq, 1178
UIMReadTransparentReq, 1183
UIMRefreshCompleteReq, 1184
UIMRefreshGetLastEventReq, 1186
UIMRefreshOKReq, 1187
UIMRefreshRegisterReq, 1187
UIMSetPinProtectionReq, 1189
UIMUnblockPinReq, 1193
UIMVerifyPinReq, 1194
SessionInfoConfig
unpack_swioma_SLQSOMADMAlertCallback_ind-_t, 1449
sessionInfoExt, 997
omaDmConfig, 997
omaDmFota, 997
SessionInfoFota
unpack_swioma_SLQSOMADMAlertCallback_ind-_t, 1449
SessionInfoNotification
unpack_swioma_SLQSOMADMAlertCallback_ind-_t, 1449
sessionInfoTlv, 997
sessionInfo, 997
sessionType, 997
TlvPresent, 997
sessionInfoTlvExt, 998
sessionInfo, 998
sessionType, 998
TlvPresent, 998
sessionInformation
qaGobiApiCbk.h, 1920
sessionInformationExt
qaGobiApiCbk.h, 1920
sessionOperation
pack_pds_StartPDSTrackingSessionExt_t, 791
sessionServerOption
pack_pds_StartPDSTrackingSessionExt_t, 791
SessionState
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
SessionStatus
unpack_pds_SetEventReport_Ind_t, 1390
sessionStatus
omaDmNotificationsTlv, 704
QmiCbkLocPositionReportInd, 937
unpack_loc_PositionRpt_Ind_t, 1299
unpack_omaDmNotificationsTlv_t, 1383
SessionType
_SwiAvmsEventInd, 113

pack_swioma_SLQSOMADMGetSessionInfo_t, 809
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
sessionType
omaDmFotaTlv, 701
pack_pds_StartPDSTrackingSessionExt_t, 791
pack_swioma_SLQSOMADMCancelSession_t, 809
pack_swioma_SLQSOMADMStartSession_t, 811
sessionInfoTlv, 997
sessionInfoTlvExt, 998
uim_refreshevent, 1162
uim_sessionInformation, 1164
uim_UIMSessionInformation, 1168
UIMRefreshEvent, 1186
UIMSessionInformation, 1188
unpack_omaDmFotaTlv_t, 1382
set_fix_rate
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocSetAutoStartReq, 1104
set_fix_type
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocSetAutoStartReq, 1104
set_function
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocSetAutoStartReq, 1104
set_max_dist
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocSetAutoStartReq, 1104
set_max_time
pack_swiloc_SwiLocSetAutoStart_t, 808
SwiLocSetAutoStartReq, 1104
SetACCOLC
qaGobiApiNas.h, 2119
SetActivationStatusCallback
qaGobiApiCbk.h, 1955
SetActiveMobileIPProfile
qaGobiApiWds.h, 2325
SetAudioPathConfigReq, 998
pCodecSTGain, 999
pDTMFTXGain, 999
pECMode, 1000
pNSEnable, 1000
pRXAGCList, 1000
pRXAVCAGCSwitch, 1000
pRXAVCList, 1000
pRXPCMIIRFltr, 1000
pTXAGCList, 1000
pTXAVCSwitch, 1000
pTXGain, 1000
pTXPCMIIRFltr, 1000
Profile, 1000
SetAudioProfileReq, 1000
EarMute, 1001
Generator, 1001
MicMute, 1001
Profile, 1001
Volume, 1001
SetAudioVolTLBConfigReq, 1001
Generator, 1002
Item, 1002
Profile, 1002
VolValue, 1002
Volume, 1002
SetAudioVolTLBConfigResp, 1002
ResCode, 1002
SetAutoconnect
qaGobiApiWds.h, 2325
SetCATEventCallback
qaGobiApiCbk.h, 1955
SetCDMANetworkParameters
qaGobiApiNas.h, 2119
SetCfgParamChangeCallback
qaGobiApiCbk.h, 1956
setCustomSettingV2, 1003
cust_id, 1003
cust_value, 1003
value_length, 1003
SetDataCapabilitiesCallback
qaGobiApiCbk.h, 1957
SetDefaultProfile
qaGobiApiWds.h, 2326
SetDefaultProfileLTE
qaGobiApiWds.h, 2327
SetDefaultProfileLTEV2
qaGobiApiWds.h, 2328
SetDefaultProfileNum
qaGobiApiWds.h, 2330
SetDeviceStateChangeCbk
qaGobiApiCbk.h, 1957
setDyingGaspCfg, 1003
pDestSMSContent, 1004
pDestSMSNum, 1004
SetFwDldCompletionCbk
qaGobiApiCbk.h, 1957
SetGPSCallback
qaGobiApiCbk.h, 1958
SetIMSSMSConfigReq, 1004
pPhoneCtxtURI, 1004
pPhoneCtxtURILen, 1004
pSMSFormat, 1004
pSMSOverIPNwInd, 1004
SetIMSSMSConfigResp, 1004
pSettingResp, 1005
SetIMSUserConfigReq, 1005
pIMSDomain, 1005
pIMSDomainLen, 1005
SetIMSUserConfigResp, 1005
pSettingResp, 1006
SetIMSVoIPConfigReq, 1006
pAmrMode, 1008
pAmrOctetAligned, 1008
pAmrWBMode, 1008
pAmrWBOctetAligned, 1008
pAmrWbEnable, 1008

pMinSessionExpiryTimer, 1008
pRTPRTCPInactTimer, 1008
pRingBackTimer, 1008
pRingingTimer, 1008
pScrAmrEnable, 1008
pScrAmrWbEnable, 1008
pSessionExpiryTimer, 1008
SetIMSVoIPConfigResp, 1008
pSettingResp, 1009
SetImagePath
qaGobiApiFms.h, 2052
SetImagesPreference
qaGobiApiFms.h, 2052
setIndicationRegReq
qaGobiApiSms.h, 2174
setIntfaceCfgTlv, 1009
CfgValue, 1009
SetLURejectCallback
qaGobiApiCbk.h, 1963
SetLocBestAvailPosCallback
qaGobiApiCbk.h, 1958
SetLocCradleMountCallback
qaGobiApiCbk.h, 1959
SetLocDeleteAssistDataCallback
qaGobiApiCbk.h, 1959
SetLocEngineStateCallback
qaGobiApiCbk.h, 1959
SetLocEventMaskNMEACallback
qaGobiApiCbk.h, 1959
SetLocEventPositionCallback
qaGobiApiCbk.h, 1960
SetLocEventTimeSyncCallback
qaGobiApiCbk.h, 1960
SetLocGetOpModeCallback
qaGobiApiCbk.h, 1960
SetLocGetServerCallback
qaGobiApiCbk.h, 1960
SetLocGetServerCallbackPara, 1010
pCallback, 1010
pReq, 1010
SetLocGnssSvInfoCallback
qaGobiApiCbk.h, 1961
SetLocInjectSensorDataCallback
qaGobiApiCbk.h, 1961
SetLocInjectTimeCallback
qaGobiApiCbk.h, 1961
SetLocOpModeCallback
qaGobiApiCbk.h, 1962
SetLocSensorStreamingCallback
qaGobiApiCbk.h, 1962
SetLocSetExtPowerConfigCallback
qaGobiApiCbk.h, 1962
SetLocSetServerCallback
qaGobiApiCbk.h, 1962
SetLocSetServerCallbackParam, 1010
pCallback, 1010
pReq, 1011
SetM2MAVMuteReq, 1014
EarMute, 1014
MicMute, 1014
pCwtMute, 1014
Profile, 1014
SetM2MAudioAVCFGReq, 1011
Device, 1011
PIFACEId, 1011
pPCMParams, 1011
Profile, 1011
SetM2MAudioLPBKReq, 1011
Enable, 1012
SetM2MAudioProfileReq, 1012
pCwtMute, 1013
pEarMute, 1013
pGenerator, 1013
pMicMute, 1013
pVolume, 1013
Profile, 1013
SetM2MAudioVolumeReq, 1013
Generator, 1014
Level, 1014
Profile, 1014
SetM2MSpkrGainReq, 1014
Profile, 1015
Value, 1015
SetMobileIP
qaGobiApiWds.h, 2330
SetMobileIPParameters
qaGobiApiWds.h, 2331
SetMobileIPProfile
qaGobiApiWds.h, 2332
SetMobileIPStatusCallback
qaGobiApiCbk.h, 1963
SetMuxID
qaGobiApiWds.h, 2333
SetNMEACallback
qaGobiApiCbk.h, 1965
SetNasLTECphyCaIndCallback
qaGobiApiCbk.h, 1964
SetNetChangeCbk
qaGobiApiCbk.h, 1964
SetNetworkPreference
qaGobiApiNas.h, 2121
SetNewSMSCallback
qaGobiApiCbk.h, 1965
SetOMADMStateCallback
qaGobiApiCbk.h, 1965
SetPDSDefaults
qaGobiApiPds.h, 2150
SetPDSState
qaGobiApiPds.h, 2151
SetPDSStateCallback
qaGobiApiCbk.h, 1966
setPINProtection, 1015
pinID, 1016
pinLength, 1016
pinOperation, 1016
pinValue, 1016

SetPortAutomaticTracking
qaGobiApiPds.h, 2151
SetPower
qaGobiApiDms.h, 2020
SetPowerCallback
qaGobiApiCbk.h, 1966
SetQmapIPTable
qaGobiApiDcs.h, 1997
SetQmapIPv6Table
qaGobiApiDcs.h, 1997
SetQosMuxID
qaGobiApiQos.h, 2159
SetRFInfoCallback
qaGobiApiCbk.h, 1966
SetRMTransferStatisticsCallback
qaGobiApiCbk.h, 1967
SetRankIndicatorCallback
qaGobiApiCbk.h, 1966
SetRegMgrConfigReq, 1016
pCSCFPortName, 1016
pCSCFPortNameLen, 1017
pIMSTestMode, 1017
pPriCSCFPort, 1017
SetRegMgrConfigResp, 1017
pSettingResp, 1017
SetRoamingIndicatorCallback
qaGobiApiCbk.h, 1967
SetSDKImagePath
qaGobiApiDcs.h, 1998
SetSIPConfigReq, 1022
pSIPLocalPort, 1023
pSigCompEnabled, 1023
pSubscribeTimer, 1023
pTimerSIPReg, 1023
pTimerT1, 1023
pTimerT2, 1023
pTimerTf, 1023
SetSIPConfigResp, 1023
pSettingResp, 1023
SetSLQSOMADMAlertCallback
qaGobiApiCbk.h, 1968
SetSLQSOMADMAlertCallbackExt
qaGobiApiCbk.h, 1968
SetSMSCAddress
qaGobiApiSms.h, 2177
SetSMSWake
qaGobiApiRms.h, 2166
SetServiceAutomaticTracking
qaGobiApiPds.h, 2152
SetSignalStrengthCallback
qaGobiApiCbk.h, 1968
setSignalStrengthInfo, 1017
pCDMAECIODelta, 1021
pCDMAECIOThresh, 1021
pCDMARSSIDelta, 1021
pCDMARSSIThresh, 1021
pGSMRSSIDelta, 1021
pGSMRSSIThresh, 1021
pHDRECIODelta, 1021
pHDRECIOThresh, 1021
pHDRIODelta, 1021
pHDRIOThresh, 1021
pHDRRSSIDelta, 1021
pHDRRSSIThresh, 1021
pHDRSINRDelta, 1021
pHDRSINRThresh, 1021
pLTERSRPDelta, 1021
pLTERSRPThresh, 1021
pLTERSRQDelta, 1021
pLTERSRQThresh, 1021
pLTERSSIDelta, 1021
pLTERSSIThresh, 1021
pLTESNRDelta, 1021
pLTESNRThresh, 1021
pLTESigRptConfig, 1021
pTDSCDMAECIODelta, 1021
pTDSCDMAECIOThresh, 1021
pTDSCDMARSCPDelta, 1021
pTDSCDMARSCPThresh, 1021
pTDSCDMARSSIDelta, 1021
pTDSCDMARSSIThresh, 1022
pTDSCDMASINRDelta, 1022
pTDSCDMASINRThresh, 1022
pWCDMAECIODelta, 1022
pWCDMAECIOThresh, 1022
pWCDMARSSIDelta, 1022
pWCDMARSSIThresh, 1022
SetUSSDNoWaitIndicationCallback
qaGobiApiCbk.h, 1970
SetUSSDNotificationCallback
qaGobiApiCbk.h, 1969
SetUSSDReleaseCallback
qaGobiApiCbk.h, 1970
SetUimSlotStatusChangeCallback
qaGobiApiCbk.h, 1969
SetXTRAAutomaticDownload
qaGobiApiPds.h, 2152
SetXTRANetwork
qaGobiApiPds.h, 2153
SetupEventList
CatEventListTlv, 176
Severity
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
severity
omaDmFotaTlv, 701
unpack_omaDmFotaTlv_t, 1382
Short Message Service (SMS), 48
shortName
nas_PLMNNetworkNameData, 574
nasPLMNNameResp, 664
PLMNNetworkNameData, 887
unpack_nas_SLQSGetPLMNName_t, 1331
shortNameCI
nasPLMNNameResp, 664
unpack_nas_SLQSGetPLMNName_t, 1331

shortNameEn
nasPLMNNameResp, 664
unpack_nas_SLQSGetPLMNName_t, 1331
shortNameLen
nas_PLMNNetworkNameData, 574
nasPLMNNameResp, 664
PLMNNetworkNameData, 887
unpack_nas_SLQSGetPLMNName_t, 1331
shortNameSB
nasPLMNNameResp, 664
unpack_nas_SLQSGetPLMNName_t, 1331
shortNameSpareBits
nas_PLMNNetworkNameData, 574
PLMNNetworkNameData, 888
sid
CDMAInfo, 180
nas_CDMAInfo, 481
nas_sidNid, 600
sidNid, 1024
unpack_nas_GetHomeNetwork_t, 1312
SidNid
homeSIDNID, 344
nas_homeSIDNID, 519
sidNid, 1024
nid, 1024
sid, 1024
SigInd
LibPackUMTSReqQoSSigInd, 403
UMTSReqQoSSigInd, 1203
sigInfo, 1024
nas_SccRxInfo, 598
pECIOThresh, 1025
pHDRSINRThresh, 1025
pIOThresh, 1025
pLTESNRThresh, 1026
pLTESigRptCfg, 1026
pRSRPThresh, 1026
pRSRQThresh, 1026
pRSSIThresh, 1026
pTDSCDMASINRCONFThresh, 1026
SccRxInfo, 987
signal
signalInfo, 1026
voice_signalInfo, 1614
signalInfo, 1026
alertPitch, 1026
signal, 1026
signalType, 1026
signalStrength
nas_SignalStrengthTlv, 601
SignalStrengthDataType, 1026
thresholds, 1027
thresholdsSize, 1027
signalStrengthReqMask
slqsSignalStrengthInfo, 1046
unpack_nas_SLQSGetSignalStrength_t, 1339
signalType
signalInfo, 1026
voice_signalInfo, 1614
simBusy
simBusyStatus, 1027
uim_simBusyStatus, 1166
simBusyLength
simBusyStatus, 1027
uim_simBusyStatus, 1166
simBusyStatus, 1027
simBusy, 1027
simBusyLength, 1027
SimCapability
unpack_dms_GetDeviceCap_t, 1213
simCapability
unpack_dms_GetDeviceCapabilities_t, 1215
sinr
HDRSSInfo, 341
hdrSSInfo, 340
nas_SLQSSignalStrengthsInformation, 604
slqsSignalStrengthInfo, 1046
SLQSSignalStrengthsInformation, 1049
TDSCDMASigInfoExt, 1127
tdscdmaSigInfoExt, 1126
unpack_nas_SLQSGetSignalStrength_t, 1339
sinrDelta
nas_SLQSSignalStrengthsIndReq, 603
SLQSSignalStrengthsIndReq, 1047
sinrThresholdList
nas_SLQSSignalStrengthsIndReq, 603
SLQSSignalStrengthsIndReq, 1047
sinrThresholdListLen
nas_SLQSSignalStrengthsIndReq, 603
SLQSSignalStrengthsIndReq, 1047
sku_str
slqsfwinfo_s, 1034
unpack_dms_GetFirmwareInfo_t, 1220
slot
pack_uim_SLQSUIMPowerDown_t, 818
pack_uim_SLQSUIMPowerUp_t, 818
UIMPowerDownReq, 1181
UIMPowerUpReq, 1182
slot_t, 1027
bICCID, 1028
bICCIDLength, 1028
bLogicalSlot, 1028
uPhyCardStatus, 1028
uPhySlotStatus, 1028
slotInf, 1028
AppStatus, 1030
cardState, 1030
errorState, 1030
numApp, 1030
upinRetries, 1030
upinState, 1030
upukRetries, 1030
SlotInfo
cardStatus, 172
uim_cardStatus, 1151
slotInfo, 1030

AppStatus, 1031
cardState, 1031
errorState, 1031
numApp, 1031
upinRetries, 1031
upinState, 1031
upukRetries, 1031
slots_t, 1031
uimSlotStatus, 1032
slotsstatusChange
UIMSlotStatusChangeInfo, 1191
unpack_uim_SetUimSlotStatusChangeCallback_-ind_t, 1459
slqs3GPPConfigItem
qaGobiApiWds.h, 2310
SlqsNas3GppNetworkInfo, 1035
Description, 1036
Forbidden, 1036
InUse, 1036
MCC, 1036
MNC, 1036
Preferred, 1036
Roaming, 1036
SlqsNas3GppNetworkRAT
qaGobiApiNas.h, 2090
SlqsNasPCICellInfo, 1036
cellID, 1037
freq, 1037
GlobalCellID, 1037
PlmnLen, 1037
slqsNasPcsDigit, 1037
SlqsNasPCIInfo, 1037
PCICellInfo, 1038
PCICellInfoLen, 1038
rsrp, 1038
rsrpRx0, 1038
rsrpRx1, 1038
rsrq, 1038
rsrqRx0, 1038
rsrqRx1, 1038
SlqsNasPcsDigit, 1038
includes_pcs_digit, 1039
MCC, 1039
MNC, 1039
slqsNasPcsDigit
SlqsNasPCICellInfo, 1037
slqsNetworkScanInfo
qaGobiApiNas.h, 2090
slqsNetworkScanInfoReq
qaGobiApiNas.h, 2091
SlqsProfile3GPP
unpackWdsProfileParam, 1560
wds_profileInfo, 1695
WdsProfileParam, 1714
SlqsProfile3GPP2
unpackWdsProfileParam, 1560
wds_profileInfo, 1695
WdsProfileParam, 1714
slqsSessionStateInfo, 1042
pQmiInterfaceInfo, 1043
reconfiguration_required, 1043
sessionEndReason, 1043
state, 1043
slqsSignalStrengthInfo, 1044
ecioList, 1045
ecioListLen, 1045
errorRateList, 1045
errorRateListLen, 1045
Io, 1045
ltersrp, 1045
ltesnr, 1045
rsrqInfo, 1046
rxSignalStrengthList, 1046
rxSignalStrengthListLen, 1046
signalStrengthReqMask, 1046
sinr, 1046
slqsWdsEventInfo, 1049
pDataBearer, 1050
pDormancyStatus, 1051
pPacketsCountRX, 1051
pPacketsCountTX, 1051
pQmiInterfaceInfo, 1051
pTotalBytesRX, 1051
pTotalBytesTX, 1051
slqsautoconnect, 1032
acroamsetting, 1032
acsetting, 1032
action, 1032
slqsfwinfo_s, 1033
appversion_str, 1034
bootversion_str, 1034
carrier_str, 1034
cur_carr_name, 1034
cur_carr_rev, 1034
modelid_str, 1034
packageid_str, 1034
priversion_str, 1034
sku_str, 1034
slqsfwpartno_s, 1034
partno_str, 1035
slqssendasyncsmsparams_s, 1039
messageFormat, 1040
messageSize, 1041
pFollowOnDC, 1041
pForceOnDC, 1041
pLinktimer, 1041
pMessage, 1041
pRetryMessage, 1041
pRetryMessageId, 1041
pServiceOption, 1041
pSmsOnIms, 1041
pUserData, 1041
slqssendsmsparams_s, 1041
messageFailureCode, 1042
messageFormat, 1042
messageID, 1042

messageSize, 1042
pLinktimer, 1042
pMessage, 1042
pSmsOnIms, 1042
sms.h
LITEQMI_QMI_CBK_PARAM_NOCHANGE, 2376
LITEQMI_QMI_CBK_PARAM_RESET, 2376
LITEQMI_QMI_CBK_PARAM_SET, 2376
sms.h, 2372
eqmiCbkSetStatus, 2376
MAX_MSE_TWS_MSG, 2375
MAX_SMS_LIST_SIZE, 2375
pack_sms_GetSMSCAddress, 2376
pack_sms_SLQSDeleteSMS, 2378
pack_sms_SLQSGetIndicationRegister, 2378
pack_sms_SLQSGetMessageWaiting, 2378
pack_sms_SLQSGetSMS, 2379
pack_sms_SLQSGetSMSList, 2379
pack_sms_SLQSGetSmsBroadcastConfig, 2379
pack_sms_SLQSGetTransLayerInfo, 2380
pack_sms_SLQSGetTransNWRegInfo, 2380
pack_sms_SLQSModifySMSStatus, 2380
pack_sms_SLQSSendAsyncSMS, 2381
pack_sms_SLQSSetIndicationRegister, 2381
pack_sms_SLQSSetSmsBroadcastActivation, 2381
pack_sms_SLQSSetSmsBroadcastConfig, 2382
pack_sms_SLQSSetSmsStorage, 2382
pack_sms_SLQSSmsGetMaxStorageSize, 2383
pack_sms_SLQSSmsGetMessageProtocol, 2383
pack_sms_SLQSSmsSetRoutes, 2383
pack_sms_SLQSSwiGetSMSStorage, 2384
pack_sms_SaveSMS, 2376
pack_sms_SendSMS, 2377
pack_sms_SetNewSMSCallback, 2377
pack_sms_SetSMSCAddress, 2377
SMS_CONFIG_LEN, 2375
SMS_MAX_SMS_ROUTES, 2376
SMS_NUM_OF_SET, 2376
SMSC_TYPE_LEN, 2376
unpack_sms_GetSMSCAddress, 2384
unpack_sms_SLQSDeleteSMS, 2386
unpack_sms_SLQSGetIndicationRegister, 2386
unpack_sms_SLQSGetMessageWaiting, 2387
unpack_sms_SLQSGetSMS, 2387
unpack_sms_SLQSGetSMSList, 2388
unpack_sms_SLQSGetSmsBroadcastConfig, 2387
unpack_sms_SLQSGetTransLayerInfo, 2388
unpack_sms_SLQSGetTransNWRegInfo, 2389
unpack_sms_SLQSModifySMSStatus, 2389
unpack_sms_SLQSNWRegInfoCallback_ind, 2389
unpack_sms_SLQSSendAsyncSMS, 2390
unpack_sms_SLQSSetIndicationRegister, 2390
unpack_sms_SLQSSetSmsBroadcastActivation, 2390
unpack_sms_SLQSSetSmsBroadcastConfig, 2391
unpack_sms_SLQSSetSmsStorage, 2391
unpack_sms_SLQSSmsGetMaxStorageSize, 2391
unpack_sms_SLQSSmsGetMessageProtocol, 2392
unpack_sms_SLQSSmsSetRoutes, 2392
unpack_sms_SLQSSwiGetSMSStorage, 2392
unpack_sms_SLQSTransLayerInfoCallback_ind, 2393
unpack_sms_SLQSWmsAsyncRawSendCallBack_ind, 2393
unpack_sms_SLQSWmsMemoryFullCallBack_ind, 2394
unpack_sms_SLQSWmsMessageWaitingCallBack_ind, 2394
unpack_sms_SaveSMS, 2384
unpack_sms_SendSMS, 2385
unpack_sms_SetNewSMSCallback, 2385
unpack_sms_SetNewSMSCallback_ind, 2385
unpack_sms_SetSMSCAddress, 2386
sms_BroadcastConfig, 1051
fromServiceId, 1051
selected, 1051
toServiceId, 1051
sms_CDMABroadcastConfig, 1051
language, 1052
selected, 1052
serviceCategory, 1052
sms_DateTime, 1052
data, 1052
sms_getIndicationReg, 1052
pRegCallStatInfoEvt, 1053
pRegTransLayerInfoEvt, 1053
pRegTransNWRegInfoEvt, 1053
sms_getMsgWaitingInfo, 1053
msgWaitInfo, 1053
numInstances, 1054
sms_getTransLayerInfo, 1054
pRegInd, 1054
pTransLayerInfo, 1054
sms_getTransNWRegInfo, 1054
pRegStatus, 1055
sms_maxStorageSizeReq, 1055
pMessageMode, 1055
storageType, 1055
sms_maxStorageSizeResp, 1055
freeSlots, 1056
maxStorageSize, 1056
sms_messageWaitingInfoContent, 1056
activeInd, 1057
msgCount, 1057
msgType, 1057
sms_msgProtocolResp, 1057
msgProtocol, 1057
sms_qaQmi3GPP2BroadcastCfgInfo, 1057
activated_ind, 1058
CDMABroadcastConfig, 1058
num_instances, 1058
sms_qaQmi3GPPBroadcastCfgInfo, 1058
activated_ind, 1059

broadcastConfig, 1059
num_instances, 1059
sms_routeEntry, 1059
messageClass, 1060
messageType, 1060
receiptAction, 1060
routeStorage, 1060
sms_sendAsyncsmsParams, 1060
messageFormat, 1062
messageSize, 1062
pFollowOnDC, 1062
pForceOnDC, 1062
pLinktimer, 1062
pMessage, 1062
pRetryMessage, 1062
pRetryMessageId, 1062
pServiceOption, 1062
pSmsOnIms, 1062
pUserData, 1062
sms_setIndicationReg, 1062
pRegCallStatInfoEvt, 1063
pRegTransLayerInfoEvt, 1063
pRegTransNWRegInfoEvt, 1063
sms_setRoutesReq, 1063
numOfRoutes, 1063
pTransferStatusReport, 1063
routeList, 1063
sms_timestemp, 1063
data, 1064
sms_transLayerInfo, 1064
TransCap, 1064
TransType, 1064
smsEventType
SMSEventInfo_s, 1072
smsMaxStorageSizeReq, 1072
pMessageMode, 1072
storageType, 1072
smsMaxStorageSizeResp, 1072
freeSlots, 1073
maxStorageSize, 1073
smsMsgprotocolResp, 1074
msgProtocol, 1075
smsOnIMS
SMSOnIMS, 1076
sMSOnIMSInfo, 1076
smsRouteEntry, 1077
messageClass, 1078
messageType, 1078
receiptAction, 1078
routeStorage, 1078
smsSetRoutesReq, 1078
numOfRoutes, 1079
pTransferStatusReport, 1079
routeList, 1079
smsStorage
pack_sms_SLQSSetSmsStorage_t, 803
snr
loc_satelliteInfo, 418
LTESSInfo, 461
lteSSInfo, 460
nas_SccRxInfo, 598
satelliteInfo, 986
SccRxInfo, 987
snrlevel
lteSnrinformation, 458
nas_lteSnrinformation, 544
soMask
DataBearerTech, 232
dataBearerTechnology, 235
qmiWDSDataBearerTechnology, 947
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
Source
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
source
_getResetInfoNotification, 72
altitudeSrcInfo, 136
altSrcInfo_t, 137
dmsSwiGetResetInfo, 261
unpack_dms_GetNetworkTime_t, 1226
unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t, 1244
unpack_dms_SLQSDmsSwiGetResetInfo_t, 1245
sourceIPMask
LibPackTFTIDParams, 400
TFTIDParams, 1132
SourceLength
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
spc
pack_dms_ResetToFactoryDefaults_t, 707
pack_nas_SetACCOLC_t, 743
pack_wds_SetMobileIPProfile_t, 853
Specific Absorption Rate (SAR), 54
spn
nas_serviceProviderName, 598
nasPLMNNameResp, 664
serviceProviderName, 993
unpack_nas_SLQSGetPLMNName_t, 1331
spnEncoding
nasPLMNNameResp, 664
unpack_nas_SLQSGetPLMNName_t, 1331
spnLength
nas_serviceProviderName, 598
nasPLMNNameResp, 665
serviceProviderName, 993
unpack_nas_SLQSGetPLMNName_t, 1332
srcPortRangeEnd
LibPackTFTIDParams, 400
TFTIDParams, 1132
srcPortRangeStart
LibPackTFTIDParams, 400
TFTIDParams, 1132
srvCapValid
nas_NR5GSystemInfoTlv, 563

NR5GSystemInfoTlv, 695
srvCapability
detailSvcInfo, 241
nas_detailSvcInfo, 496
nas_sysInfoCommon, 608
sysInfoCommon, 1119
srvCapabilityValid
nas_sysInfoCommon, 608
sysInfoCommon, 1119
srvDomain
nas_NR5GSystemInfoTlv, 563
nas_sysInfoCommon, 608
NR5GSystemInfoTlv, 695
sysInfoCommon, 1119
SrvDomainPref
nas_SrvDomainPrefTlv, 605
NASServDomainPrefTlv, 669
srvDomainValid
nas_NR5GSystemInfoTlv, 563
nas_sysInfoCommon, 608
NR5GSystemInfoTlv, 695
sysInfoCommon, 1119
srvOption
arrSvcOption, 150
voice_arrSvcOption, 1579
srvStatus
detailSvcInfo, 242
GSMSrvStatusInfo, 330
nas_detailSvcInfo, 496
nas_GSMSrvStatusInfo, 510
nas_NR5GSerStatTlv, 559
nas_SrvStatusInfo, 606
NR5GSerStatTlv, 691
SrvStatusInfo, 1083
SrvStatusInfo, 1083
isPrefDataPath, 1083
srvStatus, 1083
srvcapability
nas_NR5GSystemInfoTlv, 563
NR5GSystemInfoTlv, 695
srxlev
cellParams, 196
gsmCellInfo, 328
nas_cellParams, 486
nas_gsmCellInfo, 508
nas_umtsLTENbrCell, 618
nas_wcdmaCellInfo, 620
umtsLTENbrCell, 1198
wcdmaCellInfo, 1669
ssdatasession_params, 1084
action, 1086
failureReason, 1086
failureReasonv4, 1086
failureReasonv6, 1086
instanceId, 1086
ipfamily, 1086
pAuthentication, 1086
pPassword, 1086
pProfileId3GPP, 1086
pProfileId3GPP2, 1086
pTechnology, 1086
pUsername, 1086
rcv4, 1086
rcv6, 1086
sessionId, 1086
v4sessionId, 1086
v6sessionId, 1086
verbFailReason, 1086
verbFailReasonType, 1086
stage
uim_refreshevent, 1162
UIMRefreshEvent, 1186
StartPDSTrackingSessionExt
qaGobiApiPds.h, 2157
State
nas_NetworkStat1x, 554
nas_NetworkStatEVDO, 556
NetworkStat1x, 685
NetworkStatEVDO, 687
state
LocSetCradleMountReq, 433
omaDmConfigTlv, 697
omaDmConfigTlvExt, 699
omaDmFotaTlv, 701
omaDmFotaTlvExt, 703
pack_loc_SLQSLOCSetCradleMountConfig_t, 739
QosFlowInfoState, 957
QosMap, 958
slqsSessionStateInfo, 1043
unpack_dms_GetActivationState_t, 1206
unpack_dms_SLQSUIMGetState_t, 1264
unpack_omaDmConfigTlv_t, 1380
unpack_omaDmFotaTlv_t, 1382
unpack_qos_QosFlowInfoState_t, 1402
statmask
pack_wds_GetPacketStatus_t, 846
StatsMask
TransferStatInd, 1139
wds_transferStatInd, 1696
statsMask
TrStatInd, 1140
wds_TrStatInd, 1697
StatsPeriod
TransferStatInd, 1139
wds_transferStatInd, 1696
statsPeriod
TrStatInd, 1140
wds_TrStatInd, 1697
Status
unpack_loc_GetOpMode_Ind_t, 1286
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
status
delAssistDataStatus, 239
lteEARFCN, 439
ltePCI, 454

nas_lteEARFCN, 525
nas_ltePCI, 539
nas_wcdmaUARFCN, 626
pack_sms_SetNewSMSCallback_t, 797
QmiCbkLocBestAvailPosInd, 922
QmiCbkLocGetOpModeInd, 925
QmiCbkLocInjectPositionInd, 927
QmiCbkLocInjectUTCTimeInd, 930
QmiCbkLocSetExtPowerConfigInd, 938
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_DeleteAssistData_Ind_t, 1282
unpack_loc_InjectPositionCallback_Ind_t, 1289
unpack_loc_InjectUTCTimeCallback_Ind_t, 1292
unpack_loc_SetExtPowerConfig_Ind_t, 1300
unpack_loc_SetOperationMode_Ind_t, 1302
unpack_qos_SLQSSetQosNWStatusCallback_ind_t, 1408
unpack_qos_SLQSSetQosStatusCallback_ind_t, 1410
wcdmaUARFCN, 1679
statusChange
UIMStatusChangeInfo, 1192
StopPDSTrackingSession
qaGobiApiPds.h, 2158
storageIndex
FMSImageIdElement, 283
ImageIdElement, 347
storageType
pack_sms_SaveSMS_t, 796
pack_sms_SLQSDeleteSMS_t, 798
pack_sms_SLQSGetSMS_t, 799
pack_sms_SLQSGetSMSList_t, 800
pack_sms_SLQSModifySMSStatus_t, 801
sms_maxStorageSizeReq, 1055
smsMaxStorageSizeReq, 1072
SMSMemoryInfo, 1073
SMSMTMessage, 1075
sMSMTMessageInfo, 1076
unpack_sms_SLQSWmsMemoryFullCallBack_ind_t, 1441
String
unpack_dms_GetDeviceHardwareRev_t, 1215
unpack_dms_GetDeviceMfr_t, 1216
unpack_dms_GetFSN_t, 1223
unpack_dms_UIMGetICCID_t, 1267
stringSize
unpack_dms_GetDeviceHardwareRev_t, 1215
unpack_dms_GetDeviceMfr_t, 1216
unpack_dms_UIMGetICCID_t, 1267
subAddr
calledPartySubAdd, 163
voice_calledPartySubAdd, 1583
subAddrLen
calledPartySubAdd, 163
voice_calledPartySubAdd, 1583
subAddrType
calledPartySubAdd, 163
voice_calledPartySubAdd, 1583
subnetMask
IPv4Addr, 367
unpack_qos_IPv4Addr_t, 1398
SubnetMaskV4
unpack_wds_SLQSGetRuntimeSettings_t, 1545
subsType
pack_voice_SLQSVoiceBindSubscription_t, 826
voiceBindSubscriptionInfo, 1619
SupUSBComps
unpack_dms_GetUSBComp_t, 1232
SuppOA
CUGInfo, 217
voice_CUGInfo, 1597
SuppPrefCUG
CUGInfo, 217
voice_CUGInfo, 1597
supportedIntBitmaskTlv, 1086
TlvPresent, 1087
ValidBitmasks, 1087
supportedMsgLen
SupportedMsgList, 1087
SupportedMsgList, 1087
supportedMsgLen, 1087
supportedMsgs, 1087
supportedMsgs
SupportedMsgList, 1087
svInfoMask
loc_satelliteInfo, 418
satelliteInfo, 986
svListLen
loc_satelliteInfo, 418
satelliteInfo, 986
svStatus
loc_satelliteInfo, 418
satelliteInfo, 986
svUsedforFix
qaGobiApiCbk.h, 1924
svUsedforFix_s, 1090
gnssSvUsedList, 1090
gnssSvUsedList_len, 1090
svc
pack_qmi_t, 792
SvcClass
callFWExtInfo, 167
callFWInfo, 168
voice_callFWExtInfo, 1586
voice_callFWInfo, 1587
SvcStatus
callFWExtInfo, 167
callFWInfo, 168
voice_callFWExtInfo, 1586
voice_callFWInfo, 1587
svcType
ccSUPSType, 177
SUPSInfo, 1088
voice_ccSUPSType, 1591
voice_SUPSInfo, 1615
sw1

cardResult, 171
uim_cardResult, 1150
sw2
cardResult, 171
uim_cardResult, 1150
swVerString
pack_dms_SLQSSwiSetHostDevInfo_t, 717
unpack_dms_SLQSSwiGetHostDevInfo_t, 1260
swi_uint256_clear_bit
switype_256bit.h, 2416
swi_uint256_get_bit
switype_256bit.h, 2416
swi_uint256_print_mask
switype_256bit.h, 2416
swi_uint256_set_bit
switype_256bit.h, 2416
swi_uint256_t, 1091
word, 1092
SwiAvmsEventInd
qaGobiApiCbk.h, 1925
SwiDataTypes.h, 2394
BOOL, 2395
BYTE, 2395
CHAR, 2395
FLOAT, 2395
INT32, 2396
INT8, 2396
LPCSTR, 2396
qmuint16, 2396
qmulong, 2396
SHORT, 2396
SWI_API, 2395
ULONG, 2396
ULONGLONG, 2396
UNUSEDPARAM, 2395
USHORT, 2396
WORD, 2396
SwiDmsGetHWWatchdog, 1097
count, 1097
enable, 1097
resetDelay, 1097
timeout, 1097
SwiDmsGetMTUResp, 1097
pEhrpdMTUSize, 1098
pHrpdMTUSize, 1098
pMTUSize3gpp, 1098
pUsbMTUSize, 1098
SwiDmsGetSecureInfoResp, 1098
jtagAccessAllowed, 1098
memoryDumpAllowed, 1098
secureBootEnabled, 1098
SwiDmsGetUsbCompResp, 1099
pInterfaceCfg, 1099
pSupportedBitmasks, 1099
SwiDmsSLQSGetUsbNetNum, 1100
usbNetNum, 1100
SwiDmsSetHWWatchdog, 1099
enable, 1099
resetDelay, 1100
timeout, 1100
SwiDmsUIMSelectReq, 1100
uim_select, 1101
SwiLocGetAutoStart
qaGobiApiLoc.h, 2081
SwiLocGetAutoStartResp, 1101
fix_rate, 1102
fix_rate_reported, 1102
fix_type, 1102
fix_type_reported, 1102
function, 1102
function_reported, 1102
max_dist, 1102
max_dist_reported, 1102
max_time, 1102
max_time_reported, 1102
SwiLocSetAutoStart
qaGobiApiLoc.h, 2081
SwiLocSetAutoStartReq, 1102
fix_rate, 1103
fix_type, 1104
function, 1104
max_dist, 1104
max_time, 1104
set_fix_rate, 1104
set_fix_type, 1104
set_function, 1104
set_max_dist, 1104
set_max_time, 1104
swiModemStatusResp, 1104
commonInfo, 1104
pLTEInfo, 1104
SwiOTAMsg
qaGobiApiCbk.h, 1925
SwiOTAMsg_s, 1104
data, 1105
data_len, 1105
pLteNasRelInfo, 1105
pTime, 1105
type, 1105
swiPDPRuntimeSettingsReq, 1105
contextId, 1106
contextType, 1106
swiPDPRuntimeSettingsResp, 1106
pAPNName, 1108
pBearerId, 1108
pContextId, 1108
pIPv4Address, 1108
pIPv4GWAddress, 1108
pIPv6Address, 1108
pIPv6GWAddress, 1108
pPrDNSIPv4Address, 1108
pPrDNSIPv6Address, 1108
pPrPCSCFIPv4Address, 1108
pPrPCSCFIPv6Address, 1108
pSeDNSIPv4Address, 1108
pSeDNSIPv6Address, 1108

pSePCSCFIPv4Address, 1108
pSePCSCFIPv6Address, 1108
swiQosFilter, 1108
index, 1110
pEspSpi, 1110
pIPv4DstAddr, 1110
pIPv4SrcAddr, 1110
pIPv6DstAddr, 1110
pIPv6Label, 1110
pIPv6SrcAddr, 1110
pIPv6TrafCls, 1110
pId, 1110
pNxtHdrProto, 1110
pPrecedence, 1110
pTCPDstPort, 1110
pTCPSrcPort, 1110
pTos, 1110
pTranDstPort, 1110
pTranSrcPort, 1110
pUDPDstPort, 1110
pUDPSrcPort, 1110
version, 1111
swiQosFlow, 1111
index, 1113
p3GPP2Pri, 1113
p3GPPImCn, 1113
p3GPPResResidualBER, 1113
p3GPPSigInd, 1113
p3GPPTraHdlPri, 1113
pDataRate, 1113
pJitter, 1113
pLatency, 1113
pLteQci, 1113
pMaxAllowedPktSz, 1113
pMinPolicedPktSz, 1114
pPktErrRate, 1114
pProfileId3GPP2, 1114
pTokenBucket, 1114
pTrafficClass, 1114
swiQosGranted, 1114
pRxFlow, 1114
pTxFlow, 1114
swiQosIds, 1114
pIds, 1114
sz, 1115
swiQosModifyReq, 1115
id, 1115
pRxFilter, 1115
pRxFlow, 1115
pTxFilter, 1115
pTxFlow, 1115
swiQosReq, 1115
index, 1116
pRxFilter, 1116
pRxFlow, 1116
pTxFilter, 1116
pTxFlow, 1116
swiRMTrasnferStaticsReq, 1116
bResetStatistics, 1117
ulMask, 1117
swidms.h, 2396
pack_swidms_SLQSSwiDmsGetHWWatchdog, 2397
pack_swidms_SLQSSwiDmsGetMTU, 2398
pack_swidms_SLQSSwiDmsGetSecureInfo, 2398
pack_swidms_SLQSSwiDmsGetUsbComp, 2398
pack_swidms_SLQSSwiDmsGetUsbNetNum, 2399
pack_swidms_SLQSSwiDmsSetHWWatchdog, 2399
pack_swidms_SLQSSwiDmsSetMTU, 2399
pack_swidms_SLQSSwiDmsSetUsbComp, 2400
pack_swidms_SLQSSwiDmsSetUsbNetNum, 2400
unpack_swidms_SLQSSwiDmsGetHWWatchdog, 2400
unpack_swidms_SLQSSwiDmsGetMTU, 2401
unpack_swidms_SLQSSwiDmsGetSecureInfo, 2401
unpack_swidms_SLQSSwiDmsGetUsbComp, 2401
unpack_swidms_SLQSSwiDmsGetUsbNetNum, 2402
unpack_swidms_SLQSSwiDmsSetHWWatchdog, 2402
unpack_swidms_SLQSSwiDmsSetMTU, 2403
unpack_swidms_SLQSSwiDmsSetUsbComp, 2403
unpack_swidms_SLQSSwiDmsSetUsbNetNum, 2403
unpack_swidms_SLQSSwiDmsSetUsbNetNum_t, 2397
swidms_SwiDmsGetHWWatchdog, 1095
count, 1096
enable, 1096
resetDelay, 1096
timeout, 1096
swidms_ehrpdMTUSizeTlv, 1092
ehrpdMTUSize, 1092
TlvPresent, 1092
swidms_hrpdMTUSizeTlv, 1092
hrpdMTUSize, 1092
TlvPresent, 1093
swidms_intfaceCfgTlv, 1093
CfgValue, 1094
CurrentCfgType, 1094
TlvPresent, 1094
swidms_mtuSize3gppTlv, 1094
MTUSize3gpp, 1095
TlvPresent, 1095
swidms_supportedIntBitmaskTlv, 1095
TlvPresent, 1095
ValidBitmasks, 1095
swidms_usbMTUSizeTlv, 1096
TlvPresent, 1096
UsbMTUSize, 1096

swiloc.h, 2404
pack_swiloc_SwiLocGetAutoStart, 2404
pack_swiloc_SwiLocSetAutoStart, 2404
unpack_swiloc_SwiLocGetAutoStart, 2405
unpack_swiloc_SwiLocSetAutoStart, 2405
unpack_swiloc_SwiLocSetAutoStart_t, 2404
swioma.h, 2406
pack_swioma_SLQSOMADMAlertCallback, 2407
pack_swioma_SLQSOMADMCancelSession, 2407
pack_swioma_SLQSOMADMGetSessionInfo, 2408
pack_swioma_SLQSOMADMGetSettings, 2409
pack_swioma_SLQSOMADMSendSelection, 2409
pack_swioma_SLQSOMADMSetSettings, 2410
pack_swioma_SLQSOMADMStartSession, 2411
unpack_swioma_SLQSOMADMAlertCallback, 2411
unpack_swioma_SLQSOMADMAlertCallback_ind, 2412
unpack_swioma_SLQSOMADMAlertCallback_t, 2407
unpack_swioma_SLQSOMADMCancelSession, 2412
unpack_swioma_SLQSOMADMCancelSession_t, 2407
unpack_swioma_SLQSOMADMGetSessionInfo, 2413
unpack_swioma_SLQSOMADMGetSettings, 2413
unpack_swioma_SLQSOMADMSendSelection, 2414
unpack_swioma_SLQSOMADMSendSelection_t, 2407
unpack_swioma_SLQSOMADMSetSettings, 2414
unpack_swioma_SLQSOMADMSetSettings_t, 2407
unpack_swioma_SLQSOMADMStartSession, 2414
switchOption
pack_voice_SLQSVoiceALSSetLineSwitching_t, 825
voiceALSSetLineSwitchInfo, 1618
switype_256bit.h, 2415
swi_uint256_clear_bit, 2416
swi_uint256_get_bit, 2416
swi_uint256_print_mask, 2416
swi_uint256_set_bit, 2416
sysForbidden
nas_NR5GSystemInfoTlv, 563
NR5GSystemInfoTlv, 695
sysForbiddenValid
nas_NR5GSystemInfoTlv, 563
NR5GSystemInfoTlv, 695
sysInfoCDMA
CDMASysInfo, 194
nas_CDMASysInfo, 485
sysInfoCommon, 1117
isSysForbidden, 1119
isSysForbiddenValid, 1119
roamStatus, 1119
roamStatusValid, 1119
srvCapability, 1119
srvCapabilityValid, 1119
srvDomain, 1119
srvDomainValid, 1119
sysInfoGSM
GSMSysInfo, 333
nas_GSMSysInfo, 513
sysInfoHDR
HDRSysInfo, 343
nas_HDRSysInfo, 519
sysInfoLTE
LTESysInfo, 463
nas_LTESysInfo, 547
sysInfoWCDMA
nas_WCDMASysInfo, 625
WCDMASysInfo, 1679
sysSelectPrefExtInfo
qaGobiApiNas.h, 2094
sysSelectPrefInfo
qaGobiApiNas.h, 2095
sysSelectPrefParams
qaGobiApiNas.h, 2100
sysSelectPrefParamsExt, 1119
pCiotAcqOrderPref, 1123
pCiotLteOpMode, 1123
pCiotLteOpModePref, 1123
pLTEBandPrefExt, 1123
pLteM1BandPref, 1123
pLteNb1BandPref, 1123
pNr5gBandPref, 1123
pSysSelectPrefParams, 1123
system
loc_satelliteInfo, 418
loc_SV, 420
satelliteInfo, 986
SV, 1089
systemDiscontinuities
pack_pds_PDSInjectTimeReference_t, 781
SystemID
qaQmiServingSystemParam, 916
unpack_nas_SLQSGetServingSystem_t, 1336
systemID
CDMASysInfo, 194
nas_CDMASysInfo, 485
systemMode
CommInfo, 207
nas_CommInfo, 490
systemTime
pack_pds_PDSInjectTimeReference_t, 781
sz
swiQosIds, 1115
szAPN
_QmiSwiAvmsSetSettingsAPNInfo, 87
szAlertMsg
_QmiSwiAvmsEventReportConfigResp, 81
szDescription

_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 79
szName
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 80
szPWD
_QmiSwiAvmsSetSettingsAPNInfo, 87
szUname
_QmiSwiAvmsSetSettingsAPNInfo, 87
szVersion
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 80

t3396_apn
nasTimers, 680
unpack_nas_SLQSNasTimerCallback_ind_t, 1368
t3396_plmn_id
nasTimers, 680
unpack_nas_SLQSNasTimerCallback_ind_t, 1368
t3396_val
nasTimers, 680
unpack_nas_SLQSNasTimerCallback_ind_t, 1368
t_Sv, 1124
entries, 1124
len, 1124
t_gpsTime, 1123
gpsTimeOfWeekMs, 1123
gpsWeek, 1123
t_sensor, 1123
aidingIndicatorMask, 1124
usageMask, 1124
TCPDstPort
unpack_qos_swiQosFilter_t, 1413
TCPSrcPort
unpack_qos_swiQosFilter_t, 1413
TDSCDMAECIOThresh, 1124
TDSCDMAECIOThreshListLen
nas_TDSCDMAECIOThresh, 609
TDSCDMAECIOThresh, 1124
TDSCDMARSCPThresh, 1125
TDSCDMARSCPThreshListLen
nas_TDSCDMARSCPThresh, 609
TDSCDMARSCPThresh, 1125
TDSCDMARSSIThresh, 1125
TDSCDMARSSIThreshListLen
nas_TDSCDMARSSIThresh, 610
TDSCDMARSSIThresh, 1125
TDSCDMASINRCONFThresh, 1127
TDSCDMASINRThresh, 1128
TDSCDMASINRThreshListLen
nas_TDSCDMASINRThresh, 611
TDSCDMASINRThresh, 1128
TDSCDMASigInfoExt, 1126
ecio, 1127
rscp, 1127
rssi, 1127
sinr, 1127
tFNASwiLTECphyCallInfo
qaGobiApiCbk.h, 1926
tFNASwiOTAMsg
qaGobiApiCbk.h, 1926
tFNActivationStatus
qaGobiApiCbk.h, 1925
tFNAllCallStatus
qaGobiApiCbk.h, 1926
tFNAsyncRawSend
qaGobiApiCbk.h, 1926
tFNBandPreference
qaGobiApiCbk.h, 1927
tFNBestAvailPos
qaGobiApiCbk.h, 1928
tFNCATEvent
qaGobiApiCbk.h, 1929
tFNCbkUimSlotStatusChangeInd
qaGobiApiCbk.h, 1929
tFNDHCPv4ClientLeaseStatus
qaGobiApiCbk.h, 1931
tFNDTMFEvent
qaGobiApiCbk.h, 1931
tFNDUNCallInfo
qaGobiApiCbk.h, 1931
tFNDataCapabilities
qaGobiApiCbk.h, 1929
tFNDataSysStatus
qaGobiApiCbk.h, 1930
tFNDelAssistData
qaGobiApiCbk.h, 1930
tFNDeviceStateChange
qaGobiApiCbk.h, 1930
tFNEventNmea
qaGobiApiCbk.h, 1931
tFNEventPosition
qaGobiApiCbk.h, 1931
tFNFwDldCompletion
qaGobiApiCbk.h, 1932
tFNGetOpMode
qaGobiApiCbk.h, 1932
tFNGetServer
qaGobiApiCbk.h, 1932
tFNGnssSvInfo
qaGobiApiCbk.h, 1932
tFNHDRPersonaity
qaGobiApiCbk.h, 1933
tFNImsRegMgrConfig
qaGobiApiCbk.h, 1934
tFNImsSIPConfig
qaGobiApiCbk.h, 1934
tFNImsSMSConfig
qaGobiApiCbk.h, 1934
tFNImsUserConfig
qaGobiApiCbk.h, 1934
tFNImsVoIPConfig
qaGobiApiCbk.h, 1934
tFNImsaPdpStatus
qaGobiApiCbk.h, 1933
tFNImsaRatStatus
qaGobiApiCbk.h, 1933

tFNImsaRegStatus
qaGobiApiCbk.h, 1933
tFNImsaSvcStatus
qaGobiApiCbk.h, 1933
tFNInfoRec
qaGobiApiCbk.h, 1935
tFNInjectPosition
qaGobiApiCbk.h, 1935
tFNInjectSensorData
qaGobiApiCbk.h, 1935
tFNInjectTimeStatus
qaGobiApiCbk.h, 1935
tFNInjectUTCTime
qaGobiApiCbk.h, 1936
tFNLUReject
qaGobiApiCbk.h, 1936
tFNMemoryFull
qaGobiApiCbk.h, 1938
tFNMessageWaiting
qaGobiApiCbk.h, 1938
tFNMitiLvlRpt
qaGobiApiCbk.h, 1938
tFNMobileIPStatus
qaGobiApiCbk.h, 1938
tFNModemTempInfo
qaGobiApiCbk.h, 1938
tFNNasEdrxChangeInfo
qaGobiApiCbk.h, 1939
tFNNasTimer
qaGobiApiCbk.h, 1939
tFNNet
qaGobiApiCbk.h, 1939
tFNNetworkReject
qaGobiApiCbk.h, 1939
tFNNetworkTime
qaGobiApiCbk.h, 1940
tFNNewGPS
qaGobiApiCbk.h, 1940
tFNNewNMEA
qaGobiApiCbk.h, 1940
tFNNewRMTransferStatistics
qaGobiApiCbk.h, 1941
tFNNewSMS
qaGobiApiCbk.h, 1941
tFNOMADMState
qaGobiApiCbk.h, 1941
tFNOTASPStatus
qaGobiApiCbk.h, 1942
tFNOpMode
qaGobiApiCbk.h, 1942
tFNPDSState
qaGobiApiCbk.h, 1943
tFNPSMCfgParamChange
qaGobiApiCbk.h, 1944
tFNPacketSrvState
qaGobiApiCbk.h, 1943
tFNPower
qaGobiApiCbk.h, 1943
tFNPrivacyChange
qaGobiApiCbk.h, 1943
tFNQosNWStatus
qaGobiApiCbk.h, 1944
tFNQosPriEvent
qaGobiApiCbk.h, 1944
tFNQosStatus
qaGobiApiCbk.h, 1944
tFNRFInfo
qaGobiApiCbk.h, 1946
tFNRankIndicator
qaGobiApiCbk.h, 1945
tFNResetInfo
qaGobiApiCbk.h, 1945
tFNRoamingIndicator
qaGobiApiCbk.h, 1946
tFNSDKTerminated
qaGobiApiCbk.h, 1946
tFNSLQSOMADMAlert
qaGobiApiCbk.h, 1948
tFNSLQSQOSEvent
qaGobiApiCbk.h, 1949
tFNSLQSSessionState
qaGobiApiCbk.h, 1949
tFNSLQSSignalStrengths
qaGobiApiCbk.h, 1949
tFNSLQSWDSEvent
qaGobiApiCbk.h, 1949
tFNSMSEvents
qaGobiApiCbk.h, 1950
tFNSUPSInfo
qaGobiApiCbk.h, 1950
tFNSUPSNotification
qaGobiApiCbk.h, 1950
tFNSensorStreaming
qaGobiApiCbk.h, 1947
tFNServingSystem
qaGobiApiCbk.h, 1947
tFNSetCradleMount
qaGobiApiCbk.h, 1947
tFNSetEngineState
qaGobiApiCbk.h, 1947
tFNSetEventTimeSync
qaGobiApiCbk.h, 1947
tFNSetExtPowerConfig
qaGobiApiCbk.h, 1948
tFNSetServer
qaGobiApiCbk.h, 1948
tFNSigInfo
qaGobiApiCbk.h, 1948
tFNSignalStrength
qaGobiApiCbk.h, 1948
tFNSwiAvmEventReport
qaGobiApiCbk.h, 1950
tFNSysInfo
qaGobiApiCbk.h, 1950
tFNSysSelectionPref
qaGobiApiCbk.h, 1951

tFNUIMRefresh
qaGobiApiCbk.h, 1951
tFNUIMStatusChangeInfo
qaGobiApiCbk.h, 1951
tFNUIMStatusInfo
qaGobiApiCbk.h, 1952
tFNUSSDNoWaitIndication
qaGobiApiCbk.h, 1952
tFNUSSDNotification
qaGobiApiCbk.h, 1952
tFNUSSDRelease
qaGobiApiCbk.h, 1952
tFNtransLayerInfo
qaGobiApiCbk.h, 1951
tFNtransNWRegInfo
qaGobiApiCbk.h, 1951
TFTIDParams, 1130
destPortRangeEnd, 1132
destPortRangeStart, 1132
eValid, 1132
filterId, 1132
flowLabel, 1132
IPSECSPI, 1132
ipVersion, 1132
nextHeader, 1132
pSourceIP, 1132
sourceIPMask, 1132
srcPortRangeEnd, 1132
srcPortRangeStart, 1132
tosMask, 1132
THIRD_INSTANCE
qaGobiApiCbk.h, 1914
TIME_DATE_BUF
qaGobiApiSms.h, 2172
TIME_STAMP_BUF
qaGobiApiSms.h, 2172
TPCause
SMSAsyncRawSend_s, 1066
unpack_sms_SLQSWmsAsyncRawSendCallBack-_ind_t, 1440
TRMessageTlv
unpack_sms_SetNewSMSCallback_ind_t, 1426
TX_PWR
nas_NetworkStat1x, 554
NetworkStat1x, 685
TXAGCList, 1141
pTXAIG, 1142
pTXComprSlope, 1142
pTXComprThres, 1142
pTXExpSlope, 1142
pTXExpThres, 1142
pTXStaticGain, 1142
TXBOTlv
unpack_wds_SLQSDUNCallInfoCallBack_ind_t, 1534
TXChan
LTEInfo, 442
nas_LTEInfo, 528
tXDroppedCount
unpack_wds_GetPacketStatus_t, 1529
TXOKBytesCount
DUNCallInfoInd, 265
tXOKBytesLastCall
unpack_wds_GetPacketStatus_t, 1529
tXOkBytesCount
unpack_wds_GetPacketStatus_t, 1529
TXPCMIIRFltr, 1143
pFlag, 1144
pStage0Val, 1144
pStage1Val, 1144
pStage2Val, 1144
pStage3Val, 1144
pStage4Val, 1144
pStageCnt, 1144
tXPacketErrors
unpack_wds_GetPacketStatus_t, 1529
tXPacketOverflows
unpack_wds_GetPacketStatus_t, 1529
tXPacketSuccesses
unpack_wds_GetPacketStatus_t, 1529
Tables, 67
tac
LTEInfoIntrafreq, 445
LTESysInfo, 463
nas_LTEInfoIntrafreq, 531
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 563
NR5GSystemInfoTlv, 695
tacValid
LTESysInfo, 464
nas_LTESysInfo, 547
nas_NR5GSystemInfoTlv, 563
NR5GSystemInfoTlv, 695
TdsBandCapability
unpack_dms_SLQSGetBandCapability_t, 1251
tdscdmaSigInfoExt, 1126
ecio, 1126
rscp, 1126
rssi, 1126
sinr, 1126
tech
NWProfile, 696
techName
_packetSrvStatus, 77
unpack_wds_SLQSSetPacketSrvStatusCallback_-t, 1549
techType
DataBearerTech, 232
Technology
DeviceConfigDetail, 243
fwinfo_s, 287
nas_DeviceConfigDetail, 497
unpack_wds_SLQSGetRuntimeSettings_t, 1545
TechnologyPref
pack_nas_SetNetworkPreference_t, 746
tempData_t, 1128

temperature, 1129
temperatureDataLen, 1129
timeOfFirstSample, 1129
timeOffset, 1129
timeSource, 1129
TempStat
dms_TemperatureTlv, 252
TempTlv
unpack_dms_SwiEventReportCallBack_ind_t, 1265
Temperature
dms_TemperatureTlv, 252
temperature
CommInfo, 207
nas_CommInfo, 490
tempData_t, 1129
temprature Data, 1130
temperatureDataLen
tempData_t, 1129
temprature Data, 1130
temprature Data, 1129
temperature, 1130
temperatureDataLen, 1130
timeOfFirstSample, 1130
timeOffset, 1130
timeSource, 1130
textMsg
cdmaMsgDecodingParams, 183
wcdmaMsgDecodingParams, 1674
textMsgLength
cdmaMsgEncodingParams, 188
Thermal Mitigation Device(TMD), 64
threshGsmHigh
lteGsmCellInfo, 440
nas_lteGsmCellInfo, 526
threshGsmLow
lteGsmCellInfo, 440
nas_lteGsmCellInfo, 526
threshServingLow
LTEInfoIntrafreq, 445
nas_LTEInfoIntrafreq, 531
threshXHigh
infoInterFreq, 365
nas_infoInterFreq, 520
threshXLow
infoInterFreq, 365
nas_infoInterFreq, 521
threshXhigh
lteWcdmaCellInfo, 464
nas_lteWcdmaCellInfo, 548
threshXlow
lteWcdmaCellInfo, 465
nas_lteWcdmaCellInfo, 548
thresholds
SignalStrengthDataType, 1027
thresholdsSize
SignalStrengthDataType, 1027
Time
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
wcdmaLongMsgDecodingParams, 1672
time
NASTimeInfoTlv, 680
wcdmaMsgDecodingParams, 1674
Time_uncert_ms
GPSStateInfo, 327
unpack_pds_SLQSGetGPSStateInfo_t, 1396
timeBase
pack_pds_SLQSPDSInjectAbsoluteTimeReference_t, 786
timeInfo, 1132
day, 1134
dayLtSavingAdj, 1134
dayOfWeek, 1134
hour, 1134
minute, 1134
month, 1134
radioInterface, 1134
second, 1134
timeZone, 1134
TlvPresent, 1134
year, 1134
TimeLength
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
timeMsec
pack_loc_SLQSLOCInjectUTCTime_t, 738
pack_pds_SLQSPDSInjectAbsoluteTimeReference_t, 786
timeOfFirstSample
sensorData, 989
sensorData_t, 990
tempData_t, 1129
temprature Data, 1130
timeOffset
sensorData, 989
sensorData_t, 990
tempData_t, 1129
temprature Data, 1130
timeSource
tempData_t, 1129
temprature Data, 1130
TimeStmp_gps_week
GPSStateInfo, 327
unpack_pds_SLQSGetGPSStateInfo_t, 1396
TimeStmp_tow_ms
GPSStateInfo, 327
unpack_pds_SLQSGetGPSStateInfo_t, 1396
timeSyncRefCounter
QmiCbkLocEventTimeSyncInd, 924
unpack_loc_EventTimeSyncCallback_Ind_t, 1285
timeTlv
NASQmiCbkNasSwiOTAMessageInd, 666
timeUncMsec
pack_loc_SLQSLOCInjectUTCTime_t, 738

pack_pds_SLQSPDSInjectAbsoluteTimeReference_t, 787
timeZone
nas_timeInfo, 613
timeInfo, 1134
timeout
pack_pds_SetPDSDefaults_t, 783
pack_qmi_t, 792
pack_swidms_SLQSSwiDmsSetHWWatchdog_t, 805
swidms_SwiDmsGetHWWatchdog, 1096
SwiDmsGetHWWatchdog, 1097
SwiDmsSetHWWatchdog, 1100
Timers
_QmiSwiAvmsSetSettingsConnectionRetryTimers, 87
_SLQSAVMSSettingsConnectionRetryTimers, 96
timestamp
unpack_dms_GetNetworkTime_t, 1226
timestampAge
pack_loc_SLQSLOCInjectPosition_t, 736
timestampUtc
pack_loc_SLQSLOCInjectPosition_t, 736
timingAdvance
GERANInfo, 289
nas_GERANInfo, 506
TlvPresenceMask
qmTlvResult, 952
TlvPresent
_QmiSwiAvmsEventReportBinaryUpdateSessionInfoResp, 80
_QmiSwiAvmsEventReportConfigResp, 81
_QmiSwiAvmsEventReportConnectionRequestResp, 81
_QmiSwiAvmsEventReportDataSessionStatusResp, 82
_QmiSwiAvmsEventReportHTTPStatusResp, 83
_QmiSwiAvmsEventReportNotificationResp, 84
_QmiSwiAvmsEventReportPackageIDResp, 85
_QmiSwiAvmsEventReportRegStatusResp, 85
_QmiSwiAvmsEventReportSessionTypeResp, 86
_QmiSwiAvmsEventReportWAMSParamChangeResp, 86
AcqOrderPrefTlv, 131
BandPrefTlv, 157
CatCommonEventTlv, 174
CiotAcqOrderPrefTlv, 200
CiotLteOpModePrefTlv, 200
CsgId, 215
DataULongLongTlv, 238
DataULongTlv, 238
dms_ActivationStatusTlv, 246
dms_OperatingModeTlv, 246
dms_PSMActiveTimerIndTlv, 247
dms_PSMActiveTimerTlv, 247
dms_PSMDurationDueToOOSTlv, 248
dms_PSMDurationThresholdTlv, 248
dms_PSMEarlyWakeupTimeTlv, 249
dms_PSMEnableStateIndTlv, 249
dms_PSMEnableStateTlv, 250
dms_PSMPeriodicUpdateTimerIndTlv, 250
dms_PSMPeriodicUpdateTimerTlv, 251
dms_PSMRandomizationWindowTlv, 251
dms_TemperatureTlv, 252
dms_UimAutoSwitchActSlotTlv, 253
dms_UimStatusTlv, 253
dms_VoltageTlv, 254
EdrxCiotLteMode, 269
EdrxCycleLength, 269
EdrxEnableType, 270
EdrxPagingTimeWindow, 270
EdrxRatType, 271
ehrpdMTUSizeTlv, 271
eTWSPLMNInfoTlv, 275
ForbiddenNetworks3GPP, 286
hrpdMTUSizeTlv, 345
intfaceCfgTlv, 366
IPv4Info, 368
IPv6Info, 372
loc_IPv4Info, 413
loc_IPv6Info, 414
loc_urlAddr, 421
LteCiotOpModeTlv, 437
LteM1BandPrefTlv, 449
LteNb1BandPrefTlv, 451
LTEOperationMode, 451
LteOpMode, 452
lteOpModeTlv, 453
messageModeTlv, 465
mtuSize3gppTlv, 470
nas_AcqOrderPrefTlv, 473
nas_BandPrefInfoTlv, 475
nas_BandPrefTlv, 477
nas_CiotAcqOrderPrefTlv, 488
nas_CiotLteOpModePrefTlv, 488
nas_CsgId, 490
nas_EdrxCiotLteMode, 500
nas_EdrxCycleLength, 500
nas_EdrxEnableType, 501
nas_EdrxPagingTimeWindow, 501
nas_EdrxRatType, 502
nas_EmerModeTlv, 503
nas_ForbiddenNetworks3GPP, 505
nas_GWAcqOrderPrefTlv, 513
nas_LTEBandPrefTlv, 524
nas_LteCiotOpModeTlv, 524
nas_LteM1BandPrefTlv, 535
nas_LteNb1BandPrefTlv, 537
nas_LTEOperationMode, 537
nas_LteOpMode, 538
nas_lteOpModeTlv, 539
nas_ModePrefTlv, 550
nas_NetSelPrefTlv, 552
nas_NR5GCellStatusTlv, 558
nas_NR5GSerStatTlv, 559
nas_NR5GSystemInfoTlv, 563

nas_PhyCaAggPcellInfo, 566
nas_PhyCaAggScellDlBw, 566
nas_PhyCaAggScellIndex, 567
nas_PhyCaAggScellIndType, 567
nas_PhyCaAggScellInfo, 570
nas_PlmnID, 572
nas_PRLPrefTlv, 575
nas_RankIndicatorTlv, 582
nas_RatDisabledMaskTlv, 583
nas_RejectReasonTlv, 583
nas_RfBandInfoExtFormat, 585
nas_RfBandwidthInfo, 587
nas_RfDedicatedBandInfo, 588
nas_RFInfoTlv, 590
nas_RoamPrefTlv, 591
nas_SccRxInfo, 598
nas_SignalStrengthTlv, 601
nas_SLQSSignalStrengthsTlv, 605
nas_SrvDomainPrefTlv, 605
nas_timeInfo, 613
NASAcqOrderPrefTlv, 626
NASBandPreferenceTlv, 626
NASCiotAcqOrderPrefTlv, 628
NASCiotLteOpModePrefTlv, 629
NASEmergencyModeTlv, 629
NASGWAcqOrderPrefTlv, 643
NASLTEBandPreferenceTlv, 648
NASLteM1BandPrefTlv, 648
NASLteNasReleaseInfoTlv, 649
NASLteNB1BandPrefTlv, 649
NASModePreferenceTlv, 650
NASNetSelPreferenceTlv, 650
NASNr5gBandPrefTlv, 654
NASOTAMessageTlv, 656
NASPhyCaAggPcellInfo, 657
NASPhyCaAggScellArray, 659
NASPhyCaAggScellDlBw, 659
NASPhyCaAggScellIndex, 660
NASPhyCaAggScellIndType, 660
NASPhyCaAggScellInfo, 661
NASPRLPreferenceTlv, 665
NASRatDisabledMaskTlv, 668
NASRoamPreferenceTlv, 669
NASServDomainPrefTlv, 669
NASTimeInfoTlv, 680
newMTMessageTlv, 687
NR5GCellStatusTlv, 691
NR5GSerStatTlv, 692
NR5GSystemInfoTlv, 695
PhyCaAggPcellInfo, 877
PhyCaAggScellArray, 879
PhyCaAggScellDlBw, 879
PhyCaAggScellIndex, 880
PhyCaAggScellIndType, 881
PhyCaAggScellInfo, 883
PlmnID, 885
PSMActiveTimerTlv, 907
PSMDurationDueToOOSTlv, 908
PSMDurationThresholdTlv, 908
PSMEarlyWakeupTimeTlv, 909
PSMEnableStateTlv, 909
PSMPeriodicUpdateTimerTlv, 910
PSMRandomizationWindowTlv, 910
RatDisabledMaskTlv, 959
RfBandInfoExtFormat, 968
RfBandwidthInfo, 970
RfDedicatedBandInfo, 971
RoamingInfo, 973
SccRxInfo, 987
sessionInfoTlv, 997
sessionInfoTlvExt, 998
sMSCAddressTlv, 1068
sMSEtwsMessageTlv, 1069
sMSOnIMSTlv, 1077
supportedIntBitmaskTlv, 1087
swidms_ehrpdMTUSizeTlv, 1092
swidms_hrpdMTUSizeTlv, 1093
swidms_intfaceCfgTlv, 1094
swidms_mtuSize3gppTlv, 1095
swidms_supportedIntBitmaskTlv, 1095
swidms_usbMTUSizeTlv, 1096
timeInfo, 1134
transferRouteMessageTlv, 1139
UimAutoSwitchActSlotTlv, 1172
unpack_pds_SetPdsState_Ind_t, 1391
unpack_uim_SLQSUIMRefreshCallback_Ind_t, 1464
urlAddr, 1561
usbMTUSizeTlv, 1565
wds_ChannelRateTlv, 1680
wds_ConnStatusTlv, 1681
wds_DataBearTechTlv, 1682
wds_DataULongLongTlv, 1683
wds_DataULongTlv, 1683
wds_DHCPLeaseOptTlv, 1684
wds_DHCPLeaseStateTlv, 1684
wds_DHCPProfileIdTlv, 1686
wds_DormStatTlv, 1690
wds_IPv4AdTlv, 1691
wds_LastMdmCallEndRsnTlv, 1692
wds_RXBytesOKTlv, 1696
wds_TXBytesOKTlv, 1697
tlvPresent
voice_USSDNotificationNetworkInfo, 1616
TlvResult
unpack_swidms_SLQSSwiDmsGetSecureInfo_t, 1444
TlvResultCode
qmTlvResult, 952
Tlvresult
pack_dms_GetCustFeaturesV2_t, 707
pack_dms_SetCustFeaturesV2_t, 711
pack_dms_SetPower_t, 713
pack_dms_SetUSBComp_t, 714
pack_dms_UIMGetICCID_t, 721
pack_fms_GetImagesPreference_t, 724

pack_fms_GetStoredImages_t, 725
pack_fms_SetImagesPreference_t, 725
pack_loc_Delete_Assist_Data_t, 726
pack_loc_EventRegister_t, 729
pack_loc_SetExtPowerState_t, 729
pack_loc_SetOperationMode_t, 730
pack_loc_SLQSLOCGetBestAvailPos_t, 730
pack_loc_Start_t, 742
pack_loc_Stop_t, 742
pack_nas_SetNetworkPreference_t, 746
pack_uim_ChangePin_t, 812
pack_uim_ReadTransparent_t, 813
pack_uim_SetPinProtection_t, 814
pack_uim_UnblockPin_t, 822
pack_uim_VerifyPin_t, 823
unpack_dms_GetBandCapability_t, 1208
unpack_dms_GetCrashAction_t, 1209
unpack_dms_GetCustFeature_t, 1211
unpack_dms_GetCustFeaturesV2_t, 1212
unpack_dms_GetDeviceCap_t, 1213
unpack_dms_GetDeviceHardwareRev_t, 1215
unpack_dms_GetDeviceMfr_t, 1216
unpack_dms_GetDeviceSerialNumbers_t, 1218
unpack_dms_GetFirmwareInfo_t, 1220
unpack_dms_GetFirmwareRevision_t, 1221
unpack_dms_GetFirmwareRevisions_t, 1222
unpack_dms_GetFSN_t, 1223
unpack_dms_GetIMSI_t, 1224
unpack_dms_GetManufacturer_t, 1224
unpack_dms_GetModelID_t, 1225
unpack_dms_GetNetworkTime_t, 1226
unpack_dms_GetOfflineReason_t, 1227
unpack_dms_GetPower_t, 1228
unpack_dms_GetPRLVersion_t, 1229
unpack_dms_GetUSBComp_t, 1232
unpack_dms_GetVoiceNumber_t, 1233
unpack_dms_PSMCfgChange_ind_t, 1234
unpack_dms_ResetToFactoryDefaults_t, 1235
unpack_dms_SetActivationStatusCallback_t, 1235
unpack_dms_SetCustFeature_t, 1236
unpack_dms_SetCustFeaturesV2_t, 1237
unpack_dms_SetEventReport_ind_t, 1238
unpack_dms_SetEventReport_t, 1238
unpack_dms_SetFirmwarePreference_t, 1239
unpack_dms_SetIndicationRegister_t, 1239
unpack_dms_SetPower_t, 1240
unpack_dms_SetUSBComp_t, 1240
unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t, 1244
unpack_dms_SLQSDmsSwiGetResetInfo_t, 1245
unpack_dms_SLQSDmsSwiIndicationRegister_t, 1247
unpack_dms_SLQSGetERIFile_t, 1252
unpack_dms_SLQSSetPowerSaveModeConfig_t, 1254
unpack_dms_SLQSSwiClearDyingGaspStatistics_t, 1254
unpack_dms_SLQSSwiGetCrashInfo_t, 1255
unpack_dms_SLQSSwiGetDyingGaspCfg_t, 1256
unpack_dms_SLQSSwiGetDyingGaspStatistics_t, 1256
unpack_dms_SLQSSwiGetFwUpdateStatus_t, 1259
unpack_dms_SLQSSwiGetHostDevInfo_t, 1260
unpack_dms_SLQSSwiGetOSInfo_t, 1261
unpack_dms_SLQSSwiGetSerialNoExt_t, 1262
unpack_dms_SLQSSwiSetDyingGaspCfg_t, 1262
unpack_dms_SLQSSwiSetHostDevInfo_t, 1263
unpack_dms_SLQSSwiSetOSInfo_t, 1263
unpack_dms_SLQSUIMGetState_t, 1264
unpack_dms_SwiSetEventReport_t, 1265
unpack_dms_SwiUimSelect_t, 1266
unpack_dms_UIMGetControlKeyStatus_t, 1267
unpack_dms_UIMGetICCID_t, 1267
unpack_dms_UIMGetPINStatus_t, 1269
unpack_dms_UIMSetControlKeyProtection_t, 1270
unpack_dms_UIMSetPINProtection_t, 1271
unpack_dms_UIMUnblockControlKey_t, 1271
unpack_fms_GetImagesPreference_t, 1272
unpack_fms_GetStoredImages_t, 1273
unpack_fms_SetImagesPreference_t, 1273
unpack_loc_BestAvailPos_Ind_t, 1280
unpack_loc_Delete_Assist_Data_t, 1281
unpack_loc_DeleteAssistData_Ind_t, 1282
unpack_loc_EngineState_Ind_t, 1283
unpack_loc_EventNMEA_Ind_t, 1284
unpack_loc_EventRegister_t, 1284
unpack_loc_GetServer_Ind_t, 1288
unpack_loc_GnssSvInfo_Ind_t, 1288
unpack_loc_PositionRpt_Ind_t, 1299
unpack_loc_SetExtPowerConfig_Ind_t, 1300
unpack_loc_SetExtPowerState_t, 1301
unpack_loc_SetOperationMode_Ind_t, 1302
unpack_loc_SetOperationMode_t, 1302
unpack_loc_SetServer_Ind_t, 1303
unpack_loc_SLQSLOCGetBestAvailPos_t, 1304
unpack_loc_SLQSLOCGetOpMode_t, 1304
unpack_loc_Start_t, 1305
unpack_loc_Stop_t, 1305
unpack_nas_GetNetworkPreference_t, 1313
unpack_nas_SetNetworkPreference_t, 1324
unpack_nas_SetServingSystemCallback_ind_t, 1325
unpack_nas_SlqsGetLTECphyCAInfo_t, 1327
unpack_nas_SLQSNasGetRFInfo_t, 1358
unpack_nas_SLQSNasSwiOTAMessageCallback_ind_t, 1368
unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t, 1369
unpack_result_t, 1419
unpack_swidms_SLQSSwiDmsSetHWWatchdog_t, 1445
unpack_swidms_SLQSSwiDmsSetMTU_t, 1446
unpack_swidms_SLQSSwiDmsSetUsbComp_t, 1446
unpack_uim_ChangePin_t, 1455

unpack_uim_GetCardStatus_t, 1456
unpack_uim_GetCardStatusV2_t, 1457
unpack_uim_ReadTransparent_t, 1458
unpack_uim_SetPinProtection_t, 1459
unpack_uim_UnblockPin_t, 1466
unpack_uim_UnblockPinV2_t, 1467
unpack_uim_VerifyPin_t, 1468
unpack_wds_SLQSCreateProfile_t, 1532
unpack_wds_SLQSGetProfileSettings_t, 1542
unpack_wds_SLQSSetIPFamilyPreference_t, 1547
TmdDeRegNotMitigationLvlReq, 1134
mitigationDevID, 1134
mitigationDevIDLen, 1134
TmdGetMitigationDevListResp, 1134
pMitigationDevList, 1135
pMitigationDevListLen, 1135
TmdGetMitigationLvlReq, 1135
mitigationDevID, 1135
mitigationDevIDLen, 1135
TmdGetMitigationLvlResp, 1136
pCurrentmitigationLvl, 1136
pReqMitigationLvl, 1136
TmdMitigationLvlIndReq, 1136
mitigationDevID, 1137
mitigationDevIDLen, 1137
TmdRegNotMitigationLvlReq, 1137
mitigationDevID, 1137
mitigationDevIDLen, 1137
toServiceId
BroadcastConfig, 158
sms_BroadcastConfig, 1051
toggleMode
lineCtrlInfo, 404
voice_lineCtrlInfo, 1605
TokenBucket
unpack_qos_swiQosFlow_t, 1417
tokenBucket, 1137
bucketSz, 1138
peakRate, 1138
tokenRate, 1138
tokenRate
tokenBucket, 1138
unpack_qos_tokenBucket_t, 1418
Tos, 1138
mask, 1138
val, 1138
tosMask
LibPackTFTIDParams, 400
TFTIDParams, 1132
total_rx_bytes
sQosStat, 1083
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
total_rx_pkt
sQosStat, 1083
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
total_tx_bytes
sQosStat, 1083
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
total_tx_bytes_drp
sQosStat, 1083
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
total_tx_pkt
sQosStat, 1083
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
total_tx_pkt_drp
sQosStat, 1083
unpack_qos_SLQSQosSwiReadDataStats_t, 1406
TrStatInd, 1140
statsMask, 1140
statsPeriod, 1140
TrackAreaCode
unpack_nas_SLQSGetServingSystem_t, 1336
trackAreaCode
qaQmiServingSystemParam, 916
TrackingStatus
unpack_pds_SetPdsState_Ind_t, 1391
TrafficClass
unpack_qos_swiQosFlow_t, 1417
trafficClass
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
trafficPriority
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
TranDstPort
unpack_qos_swiQosFilter_t, 1413
TranSrcPort
unpack_qos_swiQosFilter_t, 1413
TransCap
_transLayerinfo, 126
sms_transLayerInfo, 1064
transLayerInfo
qaGobiApiSms.h, 2175
transLayerNotification
qaGobiApiCbk.h, 1953
transNWRegInfoNotification
qaGobiApiCbk.h, 1953
TransType
_transLayerinfo, 126
sms_transLayerInfo, 1064
transactionID
SMSTransferRouteMTMessage, 1080
sMSTransferRouteMTMessageInfo, 1081
transferDelay
LibPackUMTSQoS, 402
UMTSMinQoS, 1200
UMTSQoS, 1202
wds_UMTSMinQoS, 1700
TransferRouteMTMessageInfo
transferRouteMessageTlv, 1139
transferRouteMessageTlv, 1138

TlvPresent, 1139
TransferRouteMTMessageInfo, 1139
TransferStatInd, 1139
StatsMask, 1139
StatsPeriod, 1139
transferStats
pack_wds_SLQSSetWdsEventCallback_t, 862
TransferStatsDataType, 1139
interval, 1139
trueIMSI, 1140
imsiT1112, 1141
imsiTS1, 1141
imsiTS2, 1141
imsiTaddrNum, 1141
mccT, 1141
trueSrvStatus
GSMSrvStatusInfo, 330
nas_GSMSrvStatusInfo, 510
nas_NR5GSerStatTlv, 559
NR5GSerStatTlv, 692
tx_bytes
NetStats, 682
sQosFlowStat, 1081
unpack_QosFlowStat_t, 1419
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
tx_bytes_drp
sQosFlowStat, 1081
unpack_QosFlowStat_t, 1419
tx_errors
NetStats, 682
tx_overflows
NetStats, 682
tx_packets
NetStats, 682
tx_pkt
sQosFlowStat, 1081
unpack_QosFlowStat_t, 1419
tx_pkt_drp
sQosFlowStat, 1081
unpack_QosFlowStat_t, 1419
tx_pkts
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
TxByteOKCnt
wds_TXBytesOKTlv, 1697
TxDropConutTlv
QmiCbkWdsStatisticsIndState, 943
unpack_RMTransferStatistics_ind_t, 1422
txInfo, 1142
isInTraffic, 1143
txPower, 1143
txOKBytesCount
unpack_wds_SLQSGetDUNCallInfo_t, 1542
TxOkByteCountTlv
QmiCbkWdsStatisticsIndState, 943
unpack_RMTransferStatistics_ind_t, 1422
TxOkConutTlv
QmiCbkWdsStatisticsIndState, 943
unpack_RMTransferStatistics_ind_t, 1422
txPower
nas_txInfo, 614
txInfo, 1143
TxQFilter
unpack_qos_QosFlowInfo_t, 1402
TxQFlowGranted
unpack_qos_QosFlowInfo_t, 1402
type
_getResetInfoNotification, 72
dmsSwiGetResetInfo, 261
pack_wds_GetDefaultProfileNum_t, 843
pack_wds_SetDefaultProfileNum_t, 849
SwiOTAMsg_s, 1105
unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t, 1244
unpack_dms_SLQSDmsSwiGetResetInfo_t, 1245
unpack_qmi_t, 1397
typeSize
unpack_sms_GetSMSCAddress_t, 1423

u16PRLVersion
unpack_dms_GetPRLVersion_t, 1229
u8PRLPreference
unpack_dms_GetPRLVersion_t, 1229
UATISIZE
qaGobiApiNas.h, 2090
UDPDstPort
unpack_qos_swiQosFilter_t, 1413
UDPSrcPort
unpack_qos_swiQosFilter_t, 1413
UIMAuthenticateReq, 1171
authData, 1171
pIndicationToken, 1171
sessionInfo, 1171
UIMAuthenticateResp, 1171
pAuthenticateResult, 1172
pCardResult, 1172
pIndicationToken, 1172
UIMChangePIN
qaGobiApiDms.h, 2035
UIMChangePinReq, 1173
changePIN, 1173
pIndicationToken, 1173
pKeyReferenceID, 1173
sessionInfo, 1173
UIMDepersonalizationReq, 1173
depersonilisationInfo, 1174
UIMDepersonalizationResp, 1174
pRemainingRetries, 1174
UIMEventRegisterReqResp, 1174
eventMask, 1175
UIMGetCardStatusResp, 1175
pCardStatus, 1175
pHotSwapStatus, 1175
UIMGetCardStatusRespV2, 1175
pCardStatus, 1176
pHotSwapStatus, 1176

pSimBusyStatus, 1176
pValidCardStatus, 1176
UIMGetConfigurationReq, 1176
pConfigurationMask, 1177
UIMGetConfigurationResp, 1177
pAutoSelection, 1177
pHaltSubscription, 1177
pPersonalizationStatus, 1177
UIMGetControlKeyStatus
qaGobiApiDms.h, 2036
UIMGetFileAttributesReq, 1177
fileIndex, 1178
pIndicationToken, 1178
sessionInfo, 1178
UIMGetFileAttributesResp, 1178
pCardResult, 1179
pFileAttributes, 1179
pIndicationToken, 1179
UIMGetICCID
qaGobiApiDms.h, 2037
UIMGetPINStatus
qaGobiApiDms.h, 2037
UIMGetSlotsStatusResp, 1179
pNumberOfPhySlot, 1179
pUimSlotsStatus, 1179
UIMPinResp, 1179
pEncryptedPIN1, 1180
pIndicationToken, 1180
pRemainingRetries, 1180
UIMPinRespV2, 1180
pCardResult, 1181
pEncryptedPIN1, 1181
pIndicationToken, 1181
pRemainingRetries, 1181
UIMPowerDownReq, 1181
slot, 1181
UIMPowerUpReq, 1181
pIgnoreHotSwapSwitch, 1182
slot, 1182
UIMReadTransparentReq, 1182
fileIndex, 1182
pEncryptData, 1183
pIndicationToken, 1183
readTransparent, 1183
sessionInfo, 1183
UIMReadTransparentResp, 1183
pCardResult, 1183
pEncryptedData, 1183
pIndicationToken, 1183
pReadResult, 1183
UIMRefreshCompleteReq, 1184
refreshComplete, 1184
sessionInfo, 1184
UIMRefreshEvent, 1184
aid, 1185
aidLength, 1185
arrfileInfo, 1185
mode, 1185
numOfFiles, 1185
results, 1186
sessionType, 1186
stage, 1186
UIMRefreshGetLastEventReq, 1186
sessionInfo, 1186
UIMRefreshGetLastEventResp, 1186
pRefreshEvent, 1186
UIMRefreshOKReq, 1186
OKtoRefresh, 1187
sessionInfo, 1187
UIMRefreshRegisterReq, 1187
regRefresh, 1187
sessionInfo, 1187
UIMSessionInformation, 1188
aid, 1188
aidLength, 1188
sessionType, 1188
UIMSetControlKeyProtection
qaGobiApiDms.h, 2038
UIMSetPINProtection
qaGobiApiDms.h, 2039
UIMSetPinProtectionReq, 1188
pIndicationToken, 1189
pKeyReferenceID, 1189
pinProtection, 1189
sessionInfo, 1189
UIMSlotStatus, 1190
bICCID, 1190
bICCIDLength, 1190
bLogicalSlot, 1190
uPhyCardStatus, 1191
uPhySlotStatus, 1191
UIMSlotStatusChangeInfo, 1191
bNumberOfPhySlots, 1191
results, 1191
slotsstatusChange, 1191
UIMSlotsStatus, 1189
uimSlotStatus, 1190
UIMStatusChangeInfo, 1191
results, 1192
statusChange, 1192
UIMSwitchSlotReq, 1192
bLogicalSlot, 1192
ulPhysicalSlot, 1192
UIMUnblockControlKey
qaGobiApiDms.h, 2040
UIMUnblockPIN
qaGobiApiDms.h, 2040
UIMUnblockPinReq, 1192
pIndicationToken, 1193
pKeyReferenceID, 1193
sessionInfo, 1193
unblockPIN, 1193
UIMVerifyPIN
qaGobiApiDms.h, 2041
UIMVerifyPinReq, 1193
pEncryptedPIN1, 1194

pIndicationToken, 1194
pKeyReferenceID, 1194
sessionInfo, 1194
verifyPIN, 1194
ULONG
SwiDataTypes.h, 2396
ULONGLONG
SwiDataTypes.h, 2396
UMTSGrantedQoS
unpack_wds_SLQSGetRuntimeSettings_t, 1546
UMTSInfo, 1194
cellID, 1195
ecio, 1195
geranInst, 1196
GeranInstInfo, 1196
lac, 1196
plmn, 1196
psc, 1196
rscp, 1196
UMTSInstInfo, 1196
uarfcn, 1196
umtsInst, 1196
UMTSInstInfo
nas_UMTSInfo, 616
UMTSInfo, 1196
UMTSLTENbrCell
nas_WCDMAInfoLTENeighborCell, 621
WCDMAInfoLTENeighborCell, 1670
UMTSMinQoS, 1198
deliveryErrSDU, 1199
grntDownlinkBitrate, 1199
grntUplinkBitrate, 1200
maxDownlinkBitrate, 1200
maxSDUSize, 1200
maxUplinkBitrate, 1200
qosDeliveryOrder, 1200
resBerRatio, 1200
sduErrorRatio, 1200
trafficClass, 1200
trafficPriority, 1200
transferDelay, 1200
UMTSQoS, 1200
deliveryErrSDU, 1202
grntDownlinkBitrate, 1202
grntUplinkBitrate, 1202
maxDownlinkBitrate, 1202
maxSDUSize, 1202
maxUplinkBitrate, 1202
qosDeliveryOrder, 1202
resBerRatio, 1202
sduErrorRatio, 1202
trafficClass, 1202
trafficPriority, 1202
transferDelay, 1202
UMTSReqQoS
LibPackUMTSReqQoSSigInd, 403
UMTSReqQoSSigInd, 1203
UMTSReqQoSSigInd, 1202
SigInd, 1203
UMTSReqQoS, 1203
UMTSinstInfo, 1196
umtsEcio, 1196
umtsPsc, 1196
umtsRscp, 1196
umtsUarfcn, 1197
UNIQUE_ID_LEN
dms.h, 1734
qaGobiApiFms.h, 2047
UNUSEDPARAM
common.h, 1722
SwiDataTypes.h, 2395
uPhyCardStatus
slot_t, 1028
UIMSlotStatus, 1191
uPhySlotStatus
slot_t, 1028
UIMSlotStatus, 1191
URLAddrInfo, 1561
urlAddr, 1561
uResult
sGetDeviceSeriesResult, 1024
USBComp
pack_dms_SetUSBComp_t, 714
unpack_dms_GetUSBComp_t, 1232
USBCompConfig, 1561
pUSBComp, 1562
USBCompParams, 1562
pNumSupUSBComps, 1564
pSupUSBComps, 1564
pUSBComp, 1564
USHORT
SwiDataTypes.h, 2396
USSD_DCS_8BIT
qaGobiApiCbk.h, 1914
USSD_DCS_ASCII
qaGobiApiCbk.h, 1914
USSD_DCS_UCS2
qaGobiApiCbk.h, 1914
USSDNoWaitIndicationInfo, 1565
pAlphaIdentifier, 1565
pError, 1565
pFailureCause, 1565
pUSSDData, 1565
USSDNotificationNetworkInfo
unpack_voice_USSDNotificationCallback_ind_t, 1510
USSDRespFNetwork, 1565
pRespData, 1566
pTypeCode, 1566
USSInfo, 1566
ussDCS, 1566
ussData, 1566
ussLen, 1566
USSInformation
pack_voice_SLQSVoiceOrigUSSDNoWait_t, 836
voiceOrigUSSDNoWaitInfo, 1650

USSResp, 1567
pAlphaIDInfo, 1567
pCCSuppsType, 1567
pCallId, 1567
pCcResultType, 1567
pUSSDInfo, 1567
pfailureCause, 1567
UUSData
UUSInfo, 1568
voice_UUSInfo, 1617
UUSDatalen
UUSInfo, 1568
voice_UUSInfo, 1617
UUSDcs
UUSInfo, 1568
voice_UUSInfo, 1617
UUSInfo, 1567
UUSData, 1568
UUSDatalen, 1568
UUSDcs, 1568
UUSType, 1568
UUSType
UUSInfo, 1568
voice_UUSInfo, 1617
uarfcn
lteWcdmaCellInfo, 465
nas_lteWcdmaCellInfo, 548
nas_UMTSInfo, 616
nas_wcdmaUARFCN, 626
UMTSInfo, 1196
wcdmaUARFCN, 1679
ueInIdle
LTEInfoInterfreq, 443
LTEInfoIntrafreq, 445
LTEInfoNeighboringGSM, 446
LTEInfoNeighboringWCDMA, 447
nas_LTEInfoInterfreq, 529
nas_LTEInfoIntrafreq, 531
nas_LTEInfoNeighboringGSM, 532
nas_LTEInfoNeighboringWCDMA, 533
uim.h, 2417
MAX_ICCID_LENGTH, 2420
MAX_NO_OF_SLOTS, 2420
MAX_SLOTS_STATUS, 2420
pack_uim_ChangePin, 2421
pack_uim_GetCardStatus, 2421
pack_uim_ReadTransparent, 2421
pack_uim_SLQSUIMAuthenticate, 2422
pack_uim_SLQSUIMDepersonalization, 2422
pack_uim_SLQSUIMEventRegister, 2423
pack_uim_SLQSUIMGetConfiguration, 2423
pack_uim_SLQSUIMGetFileAttributes, 2423
pack_uim_SLQSUIMGetSlotsStatus, 2424
pack_uim_SLQSUIMPowerDown, 2424
pack_uim_SLQSUIMPowerUp, 2425
pack_uim_SLQSUIMRefreshComplete, 2425
pack_uim_SLQSUIMRefreshGetLastEvent, 2425
pack_uim_SLQSUIMRefreshOK, 2426
pack_uim_SLQSUIMRefreshRegister, 2426
pack_uim_SLQSUIMReset, 2426
pack_uim_SLQSUIMSwitchSlot, 2427
pack_uim_SetPinProtection, 2422
pack_uim_UnblockPin, 2427
pack_uim_VerifyPin, 2427
unpack_uim_ChangePin, 2428
unpack_uim_GetCardStatus, 2428
unpack_uim_GetCardStatusV2, 2429
unpack_uim_ReadTransparent, 2429
unpack_uim_SLQSUIMAuthenticate, 2430
unpack_uim_SLQSUIMDepersonalization, 2430
unpack_uim_SLQSUIMEventRegister, 2431
unpack_uim_SLQSUIMGetConfiguration, 2431
unpack_uim_SLQSUIMGetFileAttributes, 2431
unpack_uim_SLQSUIMGetSlotsStatus, 2432
unpack_uim_SLQSUIMPowerDown, 2432
unpack_uim_SLQSUIMPowerDown_t, 2420
unpack_uim_SLQSUIMPowerUp, 2433
unpack_uim_SLQSUIMPowerUp_t, 2420
unpack_uim_SLQSUIMRefreshCallback_Ind, 2433
unpack_uim_SLQSUIMRefreshComplete, 2433
unpack_uim_SLQSUIMRefreshComplete_t, 2420
unpack_uim_SLQSUIMRefreshGetLastEvent, 2434
unpack_uim_SLQSUIMRefreshOK, 2434
unpack_uim_SLQSUIMRefreshOK_t, 2420
unpack_uim_SLQSUIMRefreshRegister, 2434
unpack_uim_SLQSUIMRefreshRegister_t, 2420
unpack_uim_SLQSUIMReset, 2435
unpack_uim_SLQSUIMReset_t, 2420
unpack_uim_SLQSUIMSetStatusChangeCallBack_ind, 2435
unpack_uim_SLQSUIMSwitchSlot, 2435
unpack_uim_SLQSUIMSwitchSlot_t, 2420
unpack_uim_SetPinProtection, 2429
unpack_uim_SetUimSlotStatusChangeCallback_ind, 2430
unpack_uim_UnblockPin, 2436
unpack_uim_UnblockPinV2, 2436
unpack_uim_VerifyPin, 2436
uim_UIMSessionInformation, 1167
aid, 1168
aidLength, 1168
sessionType, 1168
uim_appStatus, 1144
aidLength, 1147
aidVal, 1147
appState, 1147
appType, 1147
persoFeature, 1147
persoRetries, 1147
persoState, 1147
persoUnblockRetries, 1147
pin1Retries, 1147
pin1State, 1147
pin2Retries, 1147
pin2State, 1147

puk1Retries, 1147
puk2Retries, 1147
univPin, 1147
uim_authenticateResult, 1147
content, 1148
contentLen, 1148
uim_authenticationData, 1148
context, 1149
data, 1149
dataLen, 1149
uim_cardResult, 1149
sw1, 1150
sw2, 1150
uim_cardStatus, 1150
index1xPri, 1151
index1xSec, 1151
indexGwPri, 1151
indexGwSec, 1151
numSlot, 1151
SlotInfo, 1151
uim_changeUIMPIN, 1151
oldPINLen, 1152
oldPINVal, 1152
pinID, 1152
pinLen, 1152
pinVal, 1152
uim_depersonalizationInformation, 1152
ckLen, 1153
ckVal, 1153
feature, 1153
operation, 1153
uim_encryptedPIN1, 1153
pin1Len, 1154
pin1Val, 1154
uim_fileAttributes, 1154
fileID, 1157
fileSize, 1157
fileType, 1157
rawLen, 1157
rawValue, 1157
recordCount, 1157
recordSize, 1157
secActivate, 1157
secActivateMask, 1157
secDeactivate, 1157
secDeactivateMask, 1157
secIncrease, 1157
secIncreaseMask, 1157
secRead, 1157
secReadMask, 1157
secWrite, 1157
secWriteMask, 1157
uim_fileInfo, 1157
fileID, 1158
path, 1158
pathLen, 1158
uim_hotSwapStatus, 1158
hotSwap, 1158
hotSwapLength, 1158
uim_personalizationStatus, 1158
feature, 1159
numFeatures, 1159
unblockLeft, 1159
verifyLeft, 1159
uim_readResult, 1159
content, 1160
contentLen, 1160
uim_readTransparentInfo, 1160
length, 1160
offset, 1160
uim_refreshevent, 1160
aid, 1162
aidLength, 1162
arrfileInfo, 1162
mode, 1162
numOfFiles, 1162
sessionType, 1162
stage, 1162
uim_registerRefresh, 1162
arrfileInfo, 1163
numFiles, 1163
registerFlag, 1163
voteForInit, 1163
uim_remainingRetries, 1163
unblockLeft, 1163
verifyLeft, 1163
uim_select
pack_dms_SwiUimSelect_t, 719
SwiDmsUIMSelectReq, 1101
uim_sessionInformation, 1164
aid, 1164
aidLength, 1164
sessionType, 1164
uim_setPINProtection, 1164
pinID, 1165
pinLength, 1165
pinOperation, 1165
pinValue, 1165
uim_simBusyStatus, 1165
simBusy, 1166
simBusyLength, 1166
uim_slotInfo, 1166
AppStatus, 1167
cardState, 1167
errorState, 1167
numApp, 1167
upinRetries, 1167
upinState, 1167
upukRetries, 1167
uim_unblockUIMPIN, 1168
newPINLen, 1169
newPINVal, 1169
pinID, 1169
pukLen, 1169
pukVal, 1169
uim_validCardStatus, 1169

validCard, 1170
validCardLength, 1170
uim_verifyUIMPIN, 1170
pinID, 1170
pinLen, 1170
pinVal, 1170
uimAutoSwitchActSlot
dms_UimAutoSwitchActSlotTlv, 253
UimAutoSwitchActSlotTlv, 1172
UimAutoSwitchActSlotTlv, 1172
TlvPresent, 1172
uimAutoSwitchActSlot, 1172
uimSelect
dmsSwiGetUIMSelection, 261
unpack_dms_SLQSDmsSwiGetUimSelection_t, 1246
uimSlotStatus
slots_t, 1032
UIMSlotsStatus, 1190
UimStatusTlv
unpack_dms_SwiEventReportCallBack_ind_t, 1265
ulData
DataULongTlv, 238
wds_DataULongTlv, 1683
ulMask
rmTrasnferStaticsReq, 972
swiRMTrasnferStaticsReq, 1117
ulMax
_QmiSwiAvmsSetSettingsPeriodInfo, 87
ulMin
_QmiSwiAvmsSetSettingsPeriodInfo, 87
ulPhysicalSlot
pack_uim_SLQSUIMSwitchSlot_t, 821
UIMSwitchSlotReq, 1192
ulPkgDownloadComplete
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 80
ulPkgDownloadSize
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 80
ullData
DataULongLongTlv, 238
wds_DataULongLongTlv, 1683
umtsEcio
nas_UMTSinstInfo, 617
UMTSinstInfo, 1196
umtsInst
nas_UMTSInfo, 616
UMTSInfo, 1196
umtsLTENbrCell, 1197
cellIsTDD, 1197
earfcn, 1197
pci, 1197
rsrp, 1197
rsrq, 1197
srxlev, 1198
umtsLTENbrCellLen
nas_WCDMAInfoLTENeighborCell, 621
WCDMAInfoLTENeighborCell, 1670
umtsPsc
nas_UMTSinstInfo, 617
UMTSinstInfo, 1196
umtsRscp
nas_UMTSinstInfo, 617
UMTSinstInfo, 1196
umtsUarfcn
nas_UMTSinstInfo, 617
UMTSinstInfo, 1197
UnPackGetProfileSettingOut, 1559
curProfile, 1560
pExtErrCode, 1560
unblockLeft
personalizationStatus, 876
remainingRetries, 963
uim_personalizationStatus, 1159
uim_remainingRetries, 1163
unblockPIN
UIMUnblockPinReq, 1193
unblockRetriesLeft
unpack_dms_UIMGetControlKeyStatus_t, 1267
unpack_dms_UIMSetPINProtection_t, 1271
unpack_dms_UIMUnblockControlKey_t, 1271
unblockUIMPIN, 1203
newPINLen, 1204
newPINVal, 1204
pinID, 1204
pukLen, 1204
pukVal, 1204
uniqueID
CurrImageInfo, 222
image_info_t, 345
univPin
appStats, 140
appStatus, 143
uim_appStatus, 1147
UniversalTime, 1204
day, 1205
dayOfWeek, 1205
hour, 1205
minute, 1205
month, 1205
second, 1205
year, 1205
universalTime
nasNetworkTime, 654
unpack_nas_SLQSNasNetworkTimeCallBack_ind-_t, 1364
unpack_QosFlowStat_t, 1418
bearerId, 1419
tx_bytes, 1419
tx_bytes_drp, 1419
tx_pkt, 1419
tx_pkt_drp, 1419
unpack_RMTransferStatistics_ind_t, 1421
ParamPresenceMask, 1421

RxDropConutTlv, 1421
RxOkByteCountTlv, 1421
RxOkConutTlv, 1422
TxDropConutTlv, 1422
TxOkByteCountTlv, 1422
TxOkConutTlv, 1422
unpack_dms_ActivateAutomatic
dms.h, 1759
unpack_dms_GetActivationState
dms.h, 1759
unpack_dms_GetActivationState_t, 1205
ParamPresenceMask, 1206
state, 1206
unpack_dms_GetBandCapability
dms.h, 1760
unpack_dms_GetBandCapability_t, 1206
BandCapability, 1208
ParamPresenceMask, 1208
Tlvresult, 1208
unpack_dms_GetCrashAction
dms.h, 1760
unpack_dms_GetCrashAction_t, 1208
DevCrashState, 1208
ParamPresenceMask, 1208
Tlvresult, 1209
unpack_dms_GetCustFeature
dms.h, 1760
unpack_dms_GetCustFeature_t, 1209
DHCPRelayEnabled, 1211
DisableIMSI, 1211
GPSLPM, 1211
GPSSel, 1211
GpsEnable, 1211
IPFamSupport, 1211
IsVoiceEnabled, 1211
ParamPresenceMask, 1211
RMAutoConnect, 1211
SMSSupport, 1211
Tlvresult, 1211
unpack_dms_GetCustFeaturesV2
dms.h, 1761
unpack_dms_GetCustFeaturesV2_t, 1211
GetCustomFeatureV2, 1212
ParamPresenceMask, 1212
Tlvresult, 1212
unpack_dms_GetDeviceCap
dms.h, 1761
unpack_dms_GetDeviceCap_t, 1212
DataServiceCapability, 1213
MaxRXChannelRate, 1213
MaxTXChannelRate, 1213
ParamPresenceMask, 1213
RadioIfaces, 1213
RadioIfacesSize, 1213
SimCapability, 1213
Tlvresult, 1213
unpack_dms_GetDeviceCapabilities
dms.h, 1761
unpack_dms_GetDeviceCapabilities_t, 1213
dataServiceCaCapability, 1214
maxRxChannelRate, 1215
maxTxChannelRate, 1215
ParamPresenceMask, 1215
RadioIfaces, 1215
radioIfacesSize, 1215
simCapability, 1215
unpack_dms_GetDeviceHardwareRev
dms.h, 1762
unpack_dms_GetDeviceHardwareRev_t, 1215
ParamPresenceMask, 1215
String, 1215
stringSize, 1215
Tlvresult, 1215
unpack_dms_GetDeviceMfr
dms.h, 1762
unpack_dms_GetDeviceMfr_t, 1216
ParamPresenceMask, 1216
String, 1216
stringSize, 1216
Tlvresult, 1216
unpack_dms_GetDeviceSerialNumbers
dms.h, 1762
unpack_dms_GetDeviceSerialNumbers_t, 1216
ESNString, 1218
esnSize, 1218
IMEIString, 1218
imeiSize, 1218
imeiSvnSize, 1218
ImeiSvnString, 1218
MEIDString, 1218
meidSize, 1218
ParamPresenceMask, 1218
Tlvresult, 1218
unpack_dms_GetFSN
dms.h, 1764
unpack_dms_GetFSN_t, 1222
ParamPresenceMask, 1223
String, 1223
Tlvresult, 1223
unpack_dms_GetFirmwareInfo
dms.h, 1763
unpack_dms_GetFirmwareInfo_t, 1218
appversion_str, 1219
bootversion_str, 1219
carrier_str, 1219
cur_carr_name, 1220
cur_carr_rev, 1220
modelid_str, 1220
packageid_str, 1220
ParamPresenceMask, 1220
priversion_str, 1220
sku_str, 1220
Tlvresult, 1220
unpack_dms_GetFirmwareRevision
dms.h, 1763
unpack_dms_GetFirmwareRevision_t, 1220

AMSSString, 1221
amssSize, 1221
PRIString, 1221
ParamPresenceMask, 1221
Tlvresult, 1221
unpack_dms_GetFirmwareRevisions
dms.h, 1763
unpack_dms_GetFirmwareRevisions_t, 1221
AMSSString, 1222
amssSize, 1222
bootSize, 1222
BootString, 1222
PRIString, 1222
ParamPresenceMask, 1222
priSize, 1222
Tlvresult, 1222
unpack_dms_GetHardwareRevision
dms.h, 1764
unpack_dms_GetHardwareRevision_t, 1223
hwVer, 1223
ParamPresenceMask, 1223
unpack_dms_GetIMSI
dms.h, 1764
unpack_dms_GetIMSI_t, 1223
imsi, 1224
ParamPresenceMask, 1224
Tlvresult, 1224
unpack_dms_GetManufacturer
dms.h, 1765
unpack_dms_GetManufacturer_t, 1224
manufacturer, 1224
ParamPresenceMask, 1224
Tlvresult, 1224
unpack_dms_GetModelID
dms.h, 1765
unpack_dms_GetModelID_t, 1225
modelid, 1225
ParamPresenceMask, 1225
Tlvresult, 1225
unpack_dms_GetNetworkTime
dms.h, 1766
unpack_dms_GetNetworkTime_t, 1225
ParamPresenceMask, 1226
source, 1226
timestamp, 1226
Tlvresult, 1226
unpack_dms_GetOfflineReason
dms.h, 1766
unpack_dms_GetOfflineReason_t, 1226
pReasonMask, 1227
ParamPresenceMask, 1227
pbPlatform, 1227
Tlvresult, 1227
unpack_dms_GetPRLVersion
dms.h, 1767
unpack_dms_GetPRLVersion_t, 1228
ParamPresenceMask, 1229
Tlvresult, 1229
u16PRLVersion, 1229
u8PRLPreference, 1229
unpack_dms_GetPower
dms.h, 1766
unpack_dms_GetPower_t, 1227
HardwareControlledMode, 1228
OfflineReason, 1228
OperationMode, 1228
ParamPresenceMask, 1228
Tlvresult, 1228
unpack_dms_GetSerialNumbers
dms.h, 1767
unpack_dms_GetSerialNumbers_t, 1229
esn, 1230
imei_no, 1230
imeisv_svn, 1230
meid, 1230
ParamPresenceMask, 1230
unpack_dms_GetUSBComp
dms.h, 1767
unpack_dms_GetUSBComp_t, 1230
NumSupUSBComps, 1232
ParamPresenceMask, 1232
SupUSBComps, 1232
Tlvresult, 1232
USBComp, 1232
unpack_dms_GetVoiceNumber
dms.h, 1768
unpack_dms_GetVoiceNumber_t, 1232
MIN, 1233
minSize, 1233
ParamPresenceMask, 1233
Tlvresult, 1233
VoiceNumber, 1233
voiceNumberSize, 1233
unpack_dms_PSMCfgChange_ind
dms.h, 1768
unpack_dms_PSMCfgChange_ind_t, 1234
ActiveTimer, 1234
EnableState, 1234
ParamPresenceMask, 1234
PeriodicUpdateTimer, 1234
Tlvresult, 1234
unpack_dms_ResetToFactoryDefaults
dms.h, 1768
unpack_dms_ResetToFactoryDefaults_t, 1234
ParamPresenceMask, 1235
Tlvresult, 1235
unpack_dms_SLQSDmsSwiGetPCInfo
dms.h, 1772
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1240
has_LpmFlag, 1242
has_PersistentLpm, 1242
has_Wdisable, 1242
LpmFlag, 1243
opMode, 1243
ParamPresenceMask, 1243
PersistentLpm, 1243

PowerOffMode, 1243
Wdisable, 1243
unpack_dms_SLQSDmsSwiGetResetInfo
dms.h, 1773
unpack_dms_SLQSDmsSwiGetResetInfo_Ind
dms.h, 1773
unpack_dms_SLQSDmsSwiGetResetInfo_Ind_t, 1243
ParamPresenceMask, 1244
source, 1244
Tlvresult, 1244
type, 1244
unpack_dms_SLQSDmsSwiGetResetInfo_t, 1244
ParamPresenceMask, 1245
source, 1245
Tlvresult, 1245
type, 1245
unpack_dms_SLQSDmsSwiGetUimSelection
dms.h, 1773
unpack_dms_SLQSDmsSwiGetUimSelection_t, 1245
pUimAutoSwitchActSlot, 1246
ParamPresenceMask, 1246
uimSelect, 1246
unpack_dms_SLQSDmsSwiIndicationRegister
dms.h, 1774
unpack_dms_SLQSDmsSwiIndicationRegister_t, 1246
ParamPresenceMask, 1247
Tlvresult, 1247
unpack_dms_SLQSGetBandCapability
dms.h, 1774
unpack_dms_SLQSGetBandCapability_t, 1247
bandCapability, 1251
LteBandCapability, 1251
ParamPresenceMask, 1251
TdsBandCapability, 1251
unpack_dms_SLQSGetERIFile
dms.h, 1774
unpack_dms_SLQSGetERIFile_t, 1251
eriFile, 1252
ParamPresenceMask, 1252
Tlvresult, 1252
unpack_dms_SLQSGetPowerSaveModeConfig
dms.h, 1775
unpack_dms_SLQSGetPowerSaveModeConfig_t, 1252
pActiveTimer, 1253
pDurationThreshold, 1253
pEarlyWakeupTime, 1253
pPeriodicUpdateTimer, 1253
pPsmEnableState, 1253
pRandomizationWindow, 1253
ParamPresenceMask, 1253
unpack_dms_SLQSSetPowerSaveModeConfig
dms.h, 1775
unpack_dms_SLQSSetPowerSaveModeConfig_t, 1253
ParamPresenceMask, 1254
Tlvresult, 1254
unpack_dms_SLQSSwiClearDyingGaspStatistics
dms.h, 1776
unpack_dms_SLQSSwiClearDyingGaspStatistics_t, 1254
ParamPresenceMask, 1254
Tlvresult, 1254
unpack_dms_SLQSSwiGetCrashInfo
dms.h, 1776
unpack_dms_SLQSSwiGetCrashInfo_t, 1254
crashInfoParam, 1255
ParamPresenceMask, 1255
Tlvresult, 1255
unpack_dms_SLQSSwiGetDyingGaspCfg
dms.h, 1776
unpack_dms_SLQSSwiGetDyingGaspCfg_t, 1255
pGetDyingGaspCfg, 1256
ParamPresenceMask, 1256
Tlvresult, 1256
unpack_dms_SLQSSwiGetDyingGaspStatistics
dms.h, 1777
unpack_dms_SLQSSwiGetDyingGaspStatistics_t, 1256
pGetDyingGaspStatistics, 1256
ParamPresenceMask, 1256
Tlvresult, 1256
unpack_dms_SLQSSwiGetFirmwareCurr
dms.h, 1777
unpack_dms_SLQSSwiGetFirmwareCurr_t, 1256
carrier, 1257
fwvers, 1257
numEntries, 1257
pCurrImgInfo, 1257
ParamPresenceMask, 1257
pkgver, 1257
priver, 1257
unpack_dms_SLQSSwiGetFwUpdateStatus
dms.h, 1777
unpack_dms_SLQSSwiGetFwUpdateStatus_t, 1257
imgType, 1259
logString, 1259
ParamPresenceMask, 1259
refData, 1259
refString, 1259
ResCode, 1259
Tlvresult, 1259
unpack_dms_SLQSSwiGetHostDevInfo
dms.h, 1778
unpack_dms_SLQSSwiGetHostDevInfo_t, 1259
hostID, 1260
manString, 1260
modelString, 1260
ParamPresenceMask, 1260
plasmaIDString, 1260
swVerString, 1260
Tlvresult, 1260
unpack_dms_SLQSSwiGetOSInfo
dms.h, 1778
unpack_dms_SLQSSwiGetOSInfo_t, 1260
nameString, 1261
ParamPresenceMask, 1261
Tlvresult, 1261

versionString, 1261
unpack_dms_SLQSSwiGetSerialNoExt
dms.h, 1778
unpack_dms_SLQSSwiGetSerialNoExt_t, 1261
meidString, 1262
ParamPresenceMask, 1262
Tlvresult, 1262
unpack_dms_SLQSSwiSetDyingGaspCfg
dms.h, 1779
unpack_dms_SLQSSwiSetDyingGaspCfg_t, 1262
ParamPresenceMask, 1262
Tlvresult, 1262
unpack_dms_SLQSSwiSetHostDevInfo
dms.h, 1779
unpack_dms_SLQSSwiSetHostDevInfo_t, 1262
ParamPresenceMask, 1263
Tlvresult, 1263
unpack_dms_SLQSSwiSetOSInfo
dms.h, 1779
unpack_dms_SLQSSwiSetOSInfo_t, 1263
ParamPresenceMask, 1263
Tlvresult, 1263
unpack_dms_SLQSUIMGetState
dms.h, 1780
unpack_dms_SLQSUIMGetState_t, 1263
ParamPresenceMask, 1264
state, 1264
Tlvresult, 1264
unpack_dms_SetActivationStatusCallback
dms.h, 1769
unpack_dms_SetActivationStatusCallback_t, 1235
ParamPresenceMask, 1235
Tlvresult, 1235
unpack_dms_SetCrashAction
dms.h, 1769
unpack_dms_SetCrashAction_t, 1235
notused, 1236
ParamPresenceMask, 1236
unpack_dms_SetCustFeature
dms.h, 1769
unpack_dms_SetCustFeature_t, 1236
ParamPresenceMask, 1236
Tlvresult, 1236
unpack_dms_SetCustFeaturesV2
dms.h, 1770
unpack_dms_SetCustFeaturesV2_t, 1236
ParamPresenceMask, 1237
Tlvresult, 1237
unpack_dms_SetEventReport
dms.h, 1770
unpack_dms_SetEventReport_ind
dms.h, 1770
unpack_dms_SetEventReport_ind_t, 1237
ActivationStatusTlv, 1237
OperatingModeTlv, 1237
ParamPresenceMask, 1238
Tlvresult, 1238
unpack_dms_SetEventReport_t, 1238
ParamPresenceMask, 1238
Tlvresult, 1238
unpack_dms_SetFirmwarePreference
dms.h, 1771
unpack_dms_SetFirmwarePreference_t, 1238
ParamPresenceMask, 1239
Tlvresult, 1239
unpack_dms_SetIndicationRegister
dms.h, 1771
unpack_dms_SetIndicationRegister_t, 1239
ParamPresenceMask, 1239
Tlvresult, 1239
unpack_dms_SetPower
dms.h, 1772
unpack_dms_SetPower_t, 1239
ParamPresenceMask, 1240
Tlvresult, 1240
unpack_dms_SetUSBComp
dms.h, 1772
unpack_dms_SetUSBComp_t, 1240
ParamPresenceMask, 1240
Tlvresult, 1240
unpack_dms_SwiEventReportCallBack_ind
dms.h, 1780
unpack_dms_SwiEventReportCallBack_ind_t, 1264
ParamPresenceMask, 1265
TempTlv, 1265
UimStatusTlv, 1265
VoltTlv, 1265
unpack_dms_SwiSetEventReport
dms.h, 1780
unpack_dms_SwiSetEventReport_t, 1265
ParamPresenceMask, 1265
Tlvresult, 1265
unpack_dms_SwiUimSelect
dms.h, 1781
unpack_dms_SwiUimSelect_t, 1265
ParamPresenceMask, 1266
Tlvresult, 1266
unpack_dms_UIMChangePIN
dms.h, 1781
unpack_dms_UIMGetControlKeyStatus
dms.h, 1781
unpack_dms_UIMGetControlKeyStatus_t, 1266
facilityState, 1267
ParamPresenceMask, 1267
Tlvresult, 1267
unblockRetriesLeft, 1267
verifyRetriesLeft, 1267
unpack_dms_UIMGetICCID
dms.h, 1782
unpack_dms_UIMGetICCID_t, 1267
ParamPresenceMask, 1267
String, 1267
stringSize, 1267
Tlvresult, 1267
unpack_dms_UIMGetPINStatus
dms.h, 1782

unpack_dms_UIMGetPINStatus_t, 1268
p1Status, 1269
p1UnblockRetriesLeft, 1269
p1VerifyRetriesLeft, 1269
p2Status, 1269
p2UnblockRetriesLeft, 1269
p2VerifyRetriesLeft, 1269
ParamPresenceMask, 1269
Tlvresult, 1269
unpack_dms_UIMSetControlKeyProtection
dms.h, 1782
unpack_dms_UIMSetControlKeyProtection_t, 1269
ParamPresenceMask, 1270
Tlvresult, 1270
verifyRetriesLeft, 1270
unpack_dms_UIMSetPINProtection
dms.h, 1783
unpack_dms_UIMSetPINProtection_t, 1270
ParamPresenceMask, 1271
Tlvresult, 1271
unblockRetriesLeft, 1271
verifyRetriesLeft, 1271
unpack_dms_UIMUnblockControlKey
dms.h, 1783
unpack_dms_UIMUnblockControlKey_t, 1271
ParamPresenceMask, 1271
Tlvresult, 1271
unblockRetriesLeft, 1271
unpack_dms_UIMUnblockPIN
dms.h, 1783
unpack_dms_UIMVerifyPIN
dms.h, 1784
unpack_dms_ValidateSPC
dms.h, 1784
unpack_fms_GetImagesPreference
fms.h, 1787
unpack_fms_GetImagesPreference_t, 1271
ImageListSize, 1272
pImageList, 1272
ParamPresenceMask, 1272
Tlvresult, 1272
unpack_fms_GetStoredImages
fms.h, 1787
unpack_fms_GetStoredImages_t, 1272
imageList, 1273
imagelistSize, 1273
ParamPresenceMask, 1273
Tlvresult, 1273
unpack_fms_SetImagesPreference
fms.h, 1788
unpack_fms_SetImagesPreference_t, 1273
ImageTypes, 1273
ImageTypesSize, 1273
ParamPresenceMask, 1273
Tlvresult, 1273
unpack_loc_BestAvailPos_Ind
loc.h, 1800
unpack_loc_BestAvailPos_Ind_t, 1273
pAltitudeWrtEllipsoid, 1279
pAltitudeWrtMeanSeaLevel, 1279
pGpsTime, 1279
pHeading, 1279
pHeadingUnc, 1279
pHorCirConf, 1279
pHorEllpConf, 1279
pHorReliability, 1279
pHorUncCircular, 1279
pHorUncEllipseOrientAzimuth, 1280
pHorUncEllipseSemiMajor, 1280
pHorUncEllipseSemiMinor, 1280
pLatitude, 1280
pLongitude, 1280
pMagneticDeviation, 1280
pPrecisionDilution, 1280
pSensorDataUsage, 1280
pSpeedHorizontal, 1280
pSpeedUnc, 1280
pSpeedVertical, 1280
pSpeedVerticalUnc, 1280
pSvUsedforFix, 1280
pTechnologyMask, 1280
pTimeSrc, 1280
pTimeUnc, 1280
pTimestampUtc, 1280
pVertConfidence, 1280
pVertReliability, 1280
pVertUnc, 1280
pXid, 1280
ParamPresenceMask, 1279
status, 1280
Tlvresult, 1280
unpack_loc_CradleMountCallback_Ind
loc.h, 1801
unpack_loc_CradleMountCallback_Ind_t, 1280
cradleMountConfigStatus, 1281
ParamPresenceMask, 1281
unpack_loc_Delete_Assist_Data_t, 1281
ParamPresenceMask, 1281
Tlvresult, 1281
unpack_loc_DeleteAssistData
loc.h, 1801
unpack_loc_DeleteAssistData_Ind
loc.h, 1801
unpack_loc_DeleteAssistData_Ind_t, 1282
ParamPresenceMask, 1282
status, 1282
Tlvresult, 1282
unpack_loc_DeleteAssistData_t
loc.h, 1794
unpack_loc_EngineState_Ind
loc.h, 1802
unpack_loc_EngineState_Ind_t, 1282
engineState, 1283
ParamPresenceMask, 1283
Tlvresult, 1283
unpack_loc_EventNMEA_Ind

loc.h, 1802
unpack_loc_EventNMEA_Ind_t, 1283
NMEAData, 1284
ParamPresenceMask, 1284
Tlvresult, 1284
unpack_loc_EventRegister
loc.h, 1802
unpack_loc_EventRegister_t, 1284
ParamPresenceMask, 1284
Tlvresult, 1284
unpack_loc_EventTimeSyncCallback_Ind
loc.h, 1803
unpack_loc_EventTimeSyncCallback_Ind_t, 1284
ParamPresenceMask, 1284
timeSyncRefCounter, 1285
unpack_loc_GetOpMode_Ind
loc.h, 1803
unpack_loc_GetOpMode_Ind_t, 1285
pMode, 1286
ParamPresenceMask, 1286
Status, 1286
unpack_loc_GetServer_Ind
loc.h, 1803
unpack_loc_GetServer_Ind_t, 1286
pIPv4AddrInfo, 1287
pIPv6AddrInfo, 1287
pURL, 1287
ParamPresenceMask, 1287
serverStatus, 1288
serverType, 1288
Tlvresult, 1288
unpack_loc_GnssSvInfo_Ind
loc.h, 1804
unpack_loc_GnssSvInfo_Ind_t, 1288
altitudeAssumed, 1288
pSatelliteInfo, 1288
ParamPresenceMask, 1288
Tlvresult, 1288
unpack_loc_InjectPositionCallback_Ind
loc.h, 1804
unpack_loc_InjectPositionCallback_Ind_t, 1288
ParamPresenceMask, 1289
status, 1289
unpack_loc_InjectSensorDataCallback_Ind
loc.h, 1804
unpack_loc_InjectSensorDataCallback_Ind_t, 1289
injectSensorDataStatus, 1290
pAccelSamplesAccepted, 1290
pAccelTempSamplesAccepted, 1290
pGyroSamplesAccepted, 1291
pGyroTempSamplesAccepted, 1291
pOpaqueIdentifier, 1291
ParamPresenceMask, 1291
unpack_loc_InjectTimeSyncDataCallback_Ind
loc.h, 1805
unpack_loc_InjectTimeSyncDataCallback_Ind_t, 1291
injectTimeSyncStatus, 1291
ParamPresenceMask, 1291
unpack_loc_InjectUTCTimeCallback_Ind
loc.h, 1805
unpack_loc_InjectUTCTimeCallback_Ind_t, 1291
ParamPresenceMask, 1292
status, 1292
unpack_loc_PositionRpt_Ind
loc.h, 1805
unpack_loc_PositionRpt_Ind_t, 1292
pAltitudeAssumed, 1298
pAltitudeWrtEllipsoid, 1298
pAltitudeWrtMeanSeaLevel, 1298
pFixId, 1298
pGpsTime, 1298
pHeading, 1298
pHeadingUnc, 1298
pHorConfidence, 1298
pHorReliability, 1298
pHorUncCircular, 1298
pHorUncEllipseOrientAzimuth, 1298
pHorUncEllipseSemiMajor, 1298
pHorUncEllipseSemiMinor, 1298
pLatitude, 1298
pLeapSeconds, 1298
pLongitude, 1298
pMagneticDeviation, 1298
pPrecisionDilution, 1298
pSensorDataUsage, 1298
pSpeedHorizontal, 1298
pSpeedUnc, 1298
pSpeedVertical, 1298
pSvUsedforFix, 1298
pTechnologyMask, 1298
pTimeSrc, 1298
pTimeUnc, 1298
pTimestampUtc, 1298
pVertConfidence, 1299
pVertReliability, 1299
pVertUnc, 1299
ParamPresenceMask, 1298
sessionId, 1299
sessionStatus, 1299
Tlvresult, 1299
unpack_loc_SLQSLOCGetBestAvailPos
loc.h, 1808
unpack_loc_SLQSLOCGetBestAvailPos_t, 1303
ParamPresenceMask, 1304
Tlvresult, 1304
unpack_loc_SLQSLOCGetOpMode
loc.h, 1808
unpack_loc_SLQSLOCGetOpMode_t, 1304
ParamPresenceMask, 1304
Tlvresult, 1304
unpack_loc_SLQSLOCGetServer
loc.h, 1808
unpack_loc_SLQSLOCGetServer_t
loc.h, 1794
unpack_loc_SLQSLOCInjectPosition
loc.h, 1809

unpack_loc_SLQSLOCInjectPosition_t
loc.h, 1794
unpack_loc_SLQSLOCInjectSensorData
loc.h, 1809
unpack_loc_SLQSLOCInjectSensorData_t
loc.h, 1794
unpack_loc_SLQSLOCInjectUTCTime
loc.h, 1809
unpack_loc_SLQSLOCInjectUTCTime_t
loc.h, 1794
unpack_loc_SLQSLOCSetCradleMountConfig
loc.h, 1810
unpack_loc_SLQSLOCSetCradleMountConfig_t
loc.h, 1794
unpack_loc_SLQSLOCSetServer
loc.h, 1810
unpack_loc_SensorStreamingCallback_Ind
loc.h, 1806
unpack_loc_SensorStreamingCallback_Ind_t, 1299
pAccelAcceptReady, 1299
pAccelTempAcceptReady, 1299
pGyroAcceptReady, 1300
pGyroTempAcceptReady, 1300
ParamPresenceMask, 1299
unpack_loc_SetExtPowerConfig_Ind
loc.h, 1806
unpack_loc_SetExtPowerConfig_Ind_t, 1300
ParamPresenceMask, 1300
status, 1300
Tlvresult, 1300
unpack_loc_SetExtPowerState
loc.h, 1806
unpack_loc_SetExtPowerState_t, 1300
ParamPresenceMask, 1301
Tlvresult, 1301
unpack_loc_SetOperationMode
loc.h, 1807
unpack_loc_SetOperationMode_Ind
loc.h, 1807
unpack_loc_SetOperationMode_Ind_t, 1301
ParamPresenceMask, 1302
status, 1302
Tlvresult, 1302
unpack_loc_SetOperationMode_t, 1302
ParamPresenceMask, 1302
Tlvresult, 1302
unpack_loc_SetServer_Ind
loc.h, 1807
unpack_loc_SetServer_Ind_t, 1302
ParamPresenceMask, 1303
serverStatus, 1303
Tlvresult, 1303
unpack_loc_Start
loc.h, 1810
unpack_loc_Start_t, 1304
ParamPresenceMask, 1305
Tlvresult, 1305
unpack_loc_Stop
loc.h, 1811
unpack_loc_Stop_t, 1305
ParamPresenceMask, 1305
Tlvresult, 1305
unpack_nas_GetACCOLC
nas.h, 1846
unpack_nas_GetACCOLC_t, 1305
pAccolc, 1306
ParamPresenceMask, 1306
unpack_nas_GetANAAAAuthenticationStatus
nas.h, 1846
unpack_nas_GetANAAAAuthenticationStatus_t, 1306
pAuthStatus, 1306
ParamPresenceMask, 1306
unpack_nas_GetCDMANetworkParameters
nas.h, 1847
unpack_nas_GetCDMANetworkParameters_t, 1306
Application, 1308
Broadcast, 1308
CustomSCP, 1308
ForceRev0, 1308
ParamPresenceMask, 1308
Protocol, 1308
RegForeignNID, 1308
RegForeignSID, 1308
RegHomeSID, 1309
Roaming, 1309
SCI, 1309
SCM, 1309
unpack_nas_GetHomeNetwork
nas.h, 1847
unpack_nas_GetHomeNetwork3GPP2
nas.h, 1847
unpack_nas_GetHomeNetwork3GPP2_t, 1309
nameSize, 1311
pMCC, 1311
pMNC, 1311
pNID, 1311
pName, 1311
pNw2DescDisp, 1311
pNw2DescEnc, 1311
pNw2DescLen, 1311
pNw2MCC, 1311
pNw2MNC, 1311
pNw2Name, 1311
pSID, 1311
ParamPresenceMask, 1311
unpack_nas_GetHomeNetwork_t, 1311
mcc, 1312
mnc, 1312
name, 1312
nid, 1312
ParamPresenceMask, 1312
sid, 1312
unpack_nas_GetNetworkPreference
nas.h, 1848
unpack_nas_GetNetworkPreference_t, 1312
ActiveTechPref, 1313

Duration, 1313
ParamPresenceMask, 1313
PersistentTechPref, 1313
Tlvresult, 1313
unpack_nas_GetRFInfo
nas.h, 1848
unpack_nas_GetRFInfo_t, 1313
instancesSize, 1314
ParamPresenceMask, 1314
RFBandInfoElements, 1314
unpack_nas_GetServingNetwork
nas.h, 1848
unpack_nas_GetServingNetwork_t, 1314
CSDomain, 1316
DataCaps, 1316
DataCapsLen, 1316
MCC, 1316
MNC, 1316
Name, 1316
nameSize, 1317
PSDomain, 1317
ParamPresenceMask, 1317
RAN, 1317
RadioIfaces, 1317
RadioIfacesSize, 1317
RegistrationState, 1317
Roaming, 1317
unpack_nas_GetServingNetworkCapabilities
nas.h, 1849
unpack_nas_GetServingNetworkCapabilities_t, 1317
DataCaps, 1318
DataCapsLen, 1318
ParamPresenceMask, 1318
unpack_nas_GetSignalStrengths
nas.h, 1849
unpack_nas_GetSignalStrengths_t, 1318
len, 1318
ParamPresenceMask, 1318
radio, 1318
rssi, 1318
unpack_nas_InitiateDomainAttach
nas.h, 1849
unpack_nas_InitiateDomainAttach_t
nas.h, 1823
unpack_nas_PerformNetworkScan
nas.h, 1850
unpack_nas_PerformNetworkScan_t, 1319
p3GppNetworkInfoInstances, 1320
p3GppNetworkInstanceSize, 1320
pLteOpModeTlv, 1320
pPCIInfo, 1320
pPCSInstance, 1320
pPCSInstanceSize, 1320
pRATINstance, 1320
pRATInstanceSize, 1320
pScanResult, 1320
ParamPresenceMask, 1320
unpack_nas_SLQSConfigSigInfo
nas.h, 1854
unpack_nas_SLQSConfigSigInfo_t
nas.h, 1824
unpack_nas_SLQSGetErrorRate
nas.h, 1854
unpack_nas_SLQSGetErrorRate_t, 1325
pCDMAFrameErrRate, 1326
pGSMBER, 1326
pHDRPackErrRate, 1326
pWCDMABER, 1326
ParamPresenceMask, 1326
unpack_nas_SLQSGetNetworkTime
nas.h, 1855
unpack_nas_SLQSGetNetworkTime_t, 1327
p3GPP2TimeInfo, 1327
p3GPPTimeInfo, 1327
ParamPresenceMask, 1327
unpack_nas_SLQSGetOperatorNameData
nas.h, 1855
unpack_nas_SLQSGetOperatorNameData_t, 1327
pNITZInformation, 1328
pOperatorNameString, 1328
pOperatorPLMNList, 1328
pPLMNNetworkName, 1328
pSrvcProviderName, 1328
ParamPresenceMask, 1328
unpack_nas_SLQSGetPLMNName
nas.h, 1855
unpack_nas_SLQSGetPLMNName_t, 1329
longName, 1331
longNameCI, 1331
longNameEn, 1331
longNameLen, 1331
longNameSB, 1331
ParamPresenceMask, 1331
shortName, 1331
shortNameCI, 1331
shortNameEn, 1331
shortNameLen, 1331
shortNameSB, 1331
spn, 1331
spnEncoding, 1331
spnLength, 1332
unpack_nas_SLQSGetServingSystem
nas.h, 1856
unpack_nas_SLQSGetServingSystem_t, 1332
BasestationID, 1335
BasestationLatitude, 1335
BasestationLongitude, 1335
CDMASystemInfoExt, 1335
CallBarStatus, 1335
CellID, 1335
ConcSvcInfo, 1336
CurrentPLMN, 1336
DTMInd, 1336
DataSrvCapabilities, 1336
DefaultRoamInd, 1336
DetailedSvcInfo, 1336

Gpp2TimeZone, 1336
GppNetworkDSTAdjustment, 1336
GppTimeZone, 1336
HdrPersonality, 1336
Lac, 1336
NetworkID, 1336
PRLInd, 1336
ParamPresenceMask, 1336
RoamIndicatorVal, 1336
RoamingIndicatorList, 1336
ServingSystem, 1336
SystemID, 1336
TrackAreaCode, 1336
unpack_nas_SLQSGetSignalStrength
nas.h, 1856
unpack_nas_SLQSGetSignalStrength_t, 1336
ecioList, 1338
ecioListLen, 1338
errorRateList, 1338
errorRateListLen, 1338
Io, 1338
ltersrp, 1339
ltesnr, 1339
ParamPresenceMask, 1339
rsrqInfo, 1339
rxSignalStrengthList, 1339
rxSignalStrengthListLen, 1339
signalStrengthReqMask, 1339
sinr, 1339
unpack_nas_SLQSGetSysInfo
nas.h, 1856
unpack_nas_SLQSGetSysInfo_t, 1339
pAddCDMASysInfo, 1342
pAddGSMSysInfo, 1342
pAddHDRSysInfo, 1342
pAddLTESysInfo, 1342
pCDMASrvStatusInfo, 1342
pCDMASysInfo, 1342
pCampedCiotLteOpMode, 1342
pGSMCallBarringSysInfo, 1342
pGSMCipherDomainSysInfo, 1342
pGSMSrvStatusInfo, 1342
pGSMSysInfo, 1342
pHDRSrvStatusInfo, 1342
pHDRSysInfo, 1342
pLTESrvStatusInfo, 1342
pLTESysInfo, 1342
pLTEVoiceSupportSysInfo, 1342
pWCDMASysInfo, 1343
ParamPresenceMask, 1342
unpack_nas_SLQSGetSysSelectionPref
nas.h, 1857
unpack_nas_SLQSGetSysSelectionPref_t, 1343
pBandPref, 1347
pEmerMode, 1347
pGWAcqOrderPref, 1347
pLTEBandPref, 1347
pModePref, 1347
pNetSelPref, 1347
pPRLPref, 1347
pRoamPref, 1347
pSrvDomainPref, 1347
ParamPresenceMask, 1347
unpack_nas_SLQSGetSysSelectionPrefExt
nas.h, 1857
unpack_nas_SLQSGetSysSelectionPrefExt_t, 1347
pAcqOrderPref, 1349
pBandPref, 1349
pCiotAcqOrderPref, 1349
pCiotLteOpModePref, 1349
pEmerMode, 1350
pGWAcqOrderPref, 1350
pLTEBandPref, 1350
pLteM1BandPref, 1350
pLteNb1BandPref, 1350
pModePref, 1350
pNetSelPref, 1350
pNr5gBandPref, 1350
pPRLPref, 1350
pRatDisabledMask, 1350
pRoamPref, 1350
pSrvDomainPref, 1350
unpack_nas_SLQSInitiateNetworkRegistration
nas.h, 1858
unpack_nas_SLQSInitiateNetworkRegistration_t
nas.h, 1824
unpack_nas_SLQSNASGetForbiddenNetworks
nas.h, 1860
unpack_nas_SLQSNASGetForbiddenNetworks_t, 1356
ParamPresenceMask, 1357
unpack_nas_SLQSNASGeteDRXParams
nas.h, 1859
unpack_nas_SLQSNASGeteDRXParams_t, 1354
pCycleLen, 1355
pEdrxEnable, 1355
ParamPresenceMask, 1355
unpack_nas_SLQSNASGeteDRXParamsExt
nas.h, 1860
unpack_nas_SLQSNASGeteDRXParamsExt_t, 1355
unpack_nas_SLQSNASSeteDRXParams
nas.h, 1863
unpack_nas_SLQSNASSeteDRXParams_t
nas.h, 1824
unpack_nas_SLQSNASSwiGetChannelLock
nas.h, 1864
unpack_nas_SLQSNASSwiGetChannelLock_t, 1366
ParamPresenceMask, 1366
unpack_nas_SLQSNASSwiSetChannelLock
nas.h, 1865
unpack_nas_SLQSNASSwiSetChannelLock_t
nas.h, 1824
unpack_nas_SLQSNasConfigSigInfo2
nas.h, 1858
unpack_nas_SLQSNasConfigSigInfo2_t
nas.h, 1824
unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind

nas.h, 1858
unpack_nas_SLQSNasEdrxChangeInfoCallBack_Ind_t, 1350
unpack_nas_SLQSNasGet3GPP2Subscription
nas.h, 1859
unpack_nas_SLQSNasGet3GPP2Subscription_t, 1351
pDirNum, 1352
ParamPresenceMask, 1352
unpack_nas_SLQSNasGetCellLocationInfo
nas.h, 1859
unpack_nas_SLQSNasGetCellLocationInfo_t, 1352
pCDMAInfo, 1354
pLTEInfoInterfreq, 1354
pLTEInfoIntrafreq, 1354
pUMTSInfo, 1354
ParamPresenceMask, 1353
unpack_nas_SLQSNasGetHDRColorCode
nas.h, 1860
unpack_nas_SLQSNasGetHDRColorCode_t, 1357
pColorCode, 1357
ParamPresenceMask, 1357
unpack_nas_SLQSNasGetRFInfo
nas.h, 1861
unpack_nas_SLQSNasGetRFInfo_t, 1357
pLTEOperationMode, 1358
pRfBandInfoExtFormat, 1358
pRfBandwidthInfo, 1358
pRfDedicatedBandInfo, 1358
rfbandInfoList, 1358
Tlvresult, 1358
unpack_nas_SLQSNasGetSigInfo
nas.h, 1861
unpack_nas_SLQSNasGetSigInfo_t, 1358
CDMASSInfo, 1359
GSMSSInfo, 1359
HDRSSInfo, 1359
LTESSInfo, 1359
ParamPresenceMask, 1359
unpack_nas_SLQSNasGetTxRxInfo
nas.h, 1861
unpack_nas_SLQSNasGetTxRxInfo_t, 1359
pRXChain0Info, 1360
pRXChain1Info, 1360
pTXInfo, 1360
ParamPresenceMask, 1360
unpack_nas_SLQSNasIndicationRegisterExt
nas.h, 1862
unpack_nas_SLQSNasIndicationRegisterExt_t
nas.h, 1824
unpack_nas_SLQSNasNetworkRejectCallback_Ind
nas.h, 1862
unpack_nas_SLQSNasNetworkRejectCallback_Ind_t, 1360
pCsgId, 1363
pLteOpMode, 1363
pPlmnId, 1363
ParamPresenceMask, 1363
radioIf, 1363
rejectCause, 1363
serviceDomain, 1363
unpack_nas_SLQSNasNetworkTimeCallBack_ind
nas.h, 1862
unpack_nas_SLQSNasNetworkTimeCallBack_ind_t, 1363
pDayltSavAdj, 1364
pRadioInterface, 1364
pTimeZone, 1364
ParamPresenceMask, 1364
universalTime, 1364
unpack_nas_SLQSNasSigInfoCallback_ind
nas.h, 1863
unpack_nas_SLQSNasSigInfoCallback_ind_t, 1364
pRscp, 1365
ParamPresenceMask, 1365
unpack_nas_SLQSNasSwiIndicationRegister
nas.h, 1864
unpack_nas_SLQSNasSwiIndicationRegister_t
nas.h, 1824
unpack_nas_SLQSNasSwiModemStatus
nas.h, 1864
unpack_nas_SLQSNasSwiModemStatus_t, 1366
commonInfo, 1367
pLTEInfo, 1367
ParamPresenceMask, 1367
unpack_nas_SLQSNasSwiOTAMessageCallback_ind
nas.h, 1865
unpack_nas_SLQSNasSwiOTAMessageCallback_ind_-t, 1367
Info, 1368
Tlvresult, 1368
unpack_nas_SLQSNasSysInfoCallback_ind
nas.h, 1865
unpack_nas_SLQSNasTimerCallback_ind
nas.h, 1866
unpack_nas_SLQSNasTimerCallback_ind_t, 1368
ParamPresenceMask, 1368
t3396_apn, 1368
t3396_plmn_id, 1368
t3396_val, 1368
unpack_nas_SLQSSetBandPreference
nas.h, 1866
unpack_nas_SLQSSetBandPreference_t
nas.h, 1824
unpack_nas_SLQSSetSignalStrengthsCallback
nas.h, 1866
unpack_nas_SLQSSetSignalStrengthsCallback_t
nas.h, 1824
unpack_nas_SLQSSetSysSelectionPref
nas.h, 1867
unpack_nas_SLQSSetSysSelectionPref_t
nas.h, 1824
unpack_nas_SLQSSetSysSelectionPrefCallBack_ind
nas.h, 1867
unpack_nas_SLQSSetSysSelectionPrefCallBack_ind_t, 1368
Info, 1369

Tlvresult, 1369
unpack_nas_SLQSSetSysSelectionPrefExt
nas.h, 1867
unpack_nas_SLQSSetSysSelectionPrefExt_t
nas.h, 1824
unpack_nas_SLQSSwiGetHDRPersonality
nas.h, 1868
unpack_nas_SLQSSwiGetHDRPersonality_t, 1369
pCurrentPersonality, 1370
pPersonalityListLength, 1370
pProtocolSubtypeElement, 1370
ParamPresenceMask, 1370
unpack_nas_SLQSSwiGetHDRProtSubtype
nas.h, 1868
unpack_nas_SLQSSwiGetHDRProtSubtype_t, 1370
pAppSubType, 1371
pCurrentPrsnlty, 1371
pPersonalityListLength, 1371
ParamPresenceMask, 1371
unpack_nas_SLQSSwiGetHRPDStats
nas.h, 1868
unpack_nas_SLQSSwiGetHRPDStats_t, 1371
pPilotSetData, 1372
pUATI, 1372
ParamPresenceMask, 1372
unpack_nas_SLQSSwiGetLteCQI
nas.h, 1869
unpack_nas_SLQSSwiGetLteCQI_t, 1372
ParamPresenceMask, 1373
ValidityCW0, 1373
ValidityCW1, 1373
unpack_nas_SLQSSwiGetLteSccRxInfo
nas.h, 1869
unpack_nas_SLQSSwiGetLteSccRxInfo_t, 1373
pSccRxInfo, 1373
ParamPresenceMask, 1373
unpack_nas_SLQSSwiHDRPersonalityCallback_Ind
nas.h, 1869
unpack_nas_SLQSSwiHDRPersonalityCallback_Ind_t, 1373
unpack_nas_SLQSSwiNetworkDebug
nas.h, 1870
unpack_nas_SLQSSwiNetworkDebug_t, 1374
pDataStatusDetail, 1375
pDeviceConfigDetail, 1375
pNetworkStat1x, 1375
pNetworkStatEVDO, 1375
pObjectVer, 1375
ParamPresenceMask, 1375
unpack_nas_SLQSSwiPSDetach
nas.h, 1870
unpack_nas_SLQSSwiPSDetach_t
nas.h, 1824
unpack_nas_SLQSSwiRandIndicatorCallback_Ind
nas.h, 1870
unpack_nas_SLQSSwiRandIndicatorCallback_Ind_t, 1375
ParamPresenceMask, 1375
rankIndicatorTlv, 1375
unpack_nas_SLQSSysInfoCallback_ind_t, 1375
pGSMSysInfo, 1379
pHDRSysInfo, 1379
pLTESysInfo, 1379
pLteCiotOpModeTlv, 1379
pNR5GCellStatus, 1379
pSysInfoNoChange, 1379
ParamPresenceMask, 1379
unpack_nas_SetACCOLC
nas.h, 1850
unpack_nas_SetACCOLC_t
nas.h, 1824
unpack_nas_SetCDMANetworkParameters
nas.h, 1850
unpack_nas_SetCDMANetworkParameters_t
nas.h, 1824
unpack_nas_SetDataCapabilitiesCallback_ind
nas.h, 1851
unpack_nas_SetDataCapabilitiesCallback_ind_t, 1320
dataCaps, 1321
dataCapsSize, 1321
ParamPresenceMask, 1321
unpack_nas_SetEventReportInd
nas.h, 1851
unpack_nas_SetEventReportInd_t, 1321
ParamPresenceMask, 1322
RFTlv, 1322
RRTlv, 1322
SLQSSSTlv, 1322
SSTlv, 1322
unpack_nas_SetLURejectCallback
nas.h, 1852
unpack_nas_SetLURejectCallback_t
nas.h, 1824
unpack_nas_SetNasLTECphyCaIndCallback_ind
nas.h, 1852
unpack_nas_SetNasLTECphyCaIndCallback_ind_t, 1322
ParamPresenceMask, 1323
unpack_nas_SetNetworkPreference
nas.h, 1852
unpack_nas_SetNetworkPreference_t, 1323
ParamPresenceMask, 1323
Tlvresult, 1324
unpack_nas_SetRFInfoCallback
nas.h, 1853
unpack_nas_SetRFInfoCallback_t
nas.h, 1824
unpack_nas_SetRoamingIndicatorCallback_ind
nas.h, 1853
unpack_nas_SetRoamingIndicatorCallback_ind_t, 1324
ParamPresenceMask, 1324
roaming, 1324
unpack_nas_SetServingSystemCallback_ind
nas.h, 1853
unpack_nas_SetServingSystemCallback_ind_t, 1324
ParamPresenceMask, 1325

SSInfo, 1325
Tlvresult, 1325
unpack_nas_SlqsGetLTECphyCAInfo
nas.h, 1854
unpack_nas_SlqsGetLTECphyCAInfo_t, 1326
LTECphyCaInfo, 1327
ParamPresenceMask, 1327
Tlvresult, 1327
unpack_omaDmConfigTlv_t, 1379
alertmsg, 1380
alertmsglength, 1380
state, 1380
userInputReq, 1380
userInputTimeout, 1380
unpack_omaDmFotaTlv_t, 1380
description, 1382
descriptionlength, 1382
fwdloadsize, 1382
fwloadComplete, 1382
namelength, 1382
package_name, 1382
sessionType, 1382
severity, 1382
state, 1382
updateCompleteStatus, 1382
userInputReq, 1382
userInputTimeout, 1382
version, 1382
versionlength, 1382
unpack_omaDmNotificationsTlv_t, 1382
notification, 1383
sessionStatus, 1383
unpack_pds_ForceXTRADownload
pds.h, 1886
unpack_pds_ForceXTRADownload_t
pds.h, 1876
unpack_pds_GetPDSDefaults
pds.h, 1886
unpack_pds_GetPDSDefaults_t, 1383
pAccuracy, 1384
pInterval, 1384
pOperation, 1384
pTimeout, 1384
ParamPresenceMask, 1384
unpack_pds_GetPDSState
pds.h, 1886
unpack_pds_GetPDSState_t, 1384
pEnabledStatus, 1385
pTrackingStatus, 1385
ParamPresenceMask, 1385
unpack_pds_GetPortAutomaticTracking
pds.h, 1887
unpack_pds_GetPortAutomaticTracking_t, 1385
ParamPresenceMask, 1385
pbAuto, 1386
unpack_pds_GetServiceAutomaticTracking
pds.h, 1887
unpack_pds_GetServiceAutomaticTracking_t, 1386
ParamPresenceMask, 1386
pbAuto, 1386
unpack_pds_GetXTRAAutomaticDownload
pds.h, 1887
unpack_pds_GetXTRAAutomaticDownload_t, 1386
pInterval, 1387
ParamPresenceMask, 1387
pbEnabled, 1387
unpack_pds_GetXTRANetwork
pds.h, 1888
unpack_pds_GetXTRANetwork_t, 1387
pPreference, 1387
ParamPresenceMask, 1387
unpack_pds_GetXTRAValidity
pds.h, 1888
unpack_pds_GetXTRAValidity_t, 1387
pDuration, 1388
pGPSWeek, 1388
pGPSWeekOffset, 1388
ParamPresenceMask, 1388
unpack_pds_PDSInjectTimeReference
pds.h, 1889
unpack_pds_PDSInjectTimeReference_t
pds.h, 1876
unpack_pds_ResetPDSData
pds.h, 1889
unpack_pds_ResetPDSData_t
pds.h, 1876
unpack_pds_SLQSGetAGPSConfig
pds.h, 1892
unpack_pds_SLQSGetAGPSConfig_t, 1391
pServerAddress, 1392
pServerPort, 1392
pServerURL, 1392
ParamPresenceMask, 1392
unpack_pds_SLQSGetGPSStateInfo
pds.h, 1893
unpack_pds_SLQSGetGPSStateInfo_t, 1392
Altitude, 1396
EngineState, 1396
HorizontalUncertainty, 1396
Iono_valid, 1396
Latitude, 1396
Longitude, 1396
ParamPresenceMask, 1396
Time_uncert_ms, 1396
ValidMask, 1396
VerticalUncertainty, 1396
unpack_pds_SLQSPDSDeterminePosition
pds.h, 1893
unpack_pds_SLQSPDSDeterminePosition_t
pds.h, 1876
unpack_pds_SLQSPDSInjectAbsoluteTimeReference
pds.h, 1893
unpack_pds_SLQSPDSInjectAbsoluteTimeReference_t
pds.h, 1876
unpack_pds_SLQSPDSInjectPositionData
pds.h, 1894

unpack_pds_SLQSPDSInjectPositionData_t
pds.h, 1876
unpack_pds_SLQSSetAGPSConfig
pds.h, 1894
unpack_pds_SLQSSetAGPSConfig_t
pds.h, 1876
unpack_pds_SLQSSetPositionMethodState
pds.h, 1894
unpack_pds_SLQSSetPositionMethodState_t
pds.h, 1876
unpack_pds_SetEventReport_Ind
pds.h, 1889
unpack_pds_SetEventReport_Ind_t, 1388
dLatitude, 1390
dLongitude, 1390
has_PositionDataNMEA, 1390
has_SessionStatus, 1390
has_dLatitude, 1390
has_dLongitude, 1390
has_posSrc, 1390
ParamPresenceMask, 1390
posSrc, 1390
PositionDataNMEA, 1390
SessionStatus, 1390
unpack_pds_SetEventReportCallback
pds.h, 1890
unpack_pds_SetEventReportCallback_t
pds.h, 1876
unpack_pds_SetPDSDefaults
pds.h, 1890
unpack_pds_SetPDSDefaults_t
pds.h, 1876
unpack_pds_SetPDSState
pds.h, 1890
unpack_pds_SetPDSState_t
pds.h, 1876
unpack_pds_SetPdsState_Ind
pds.h, 1891
unpack_pds_SetPdsState_Ind_t, 1390
EnabledStatus, 1391
ParamPresenceMask, 1391
TlvPresent, 1391
TrackingStatus, 1391
unpack_pds_SetPortAutomaticTracking
pds.h, 1891
unpack_pds_SetPortAutomaticTracking_t
pds.h, 1876
unpack_pds_SetServiceAutomaticTracking
pds.h, 1891
unpack_pds_SetServiceAutomaticTracking_t
pds.h, 1876
unpack_pds_SetXTRAAutomaticDownload
pds.h, 1892
unpack_pds_SetXTRAAutomaticDownload_t
pds.h, 1876
unpack_pds_SetXTRANetwork
pds.h, 1892
unpack_pds_SetXTRANetwork_t
pds.h, 1876
unpack_pds_StartPDSTrackingSessionExt
pds.h, 1895
unpack_pds_StartPDSTrackingSessionExt_t
pds.h, 1876
unpack_pds_StopPDSTrackingSession
pds.h, 1895
unpack_pds_StopPDSTrackingSession_t
pds.h, 1876
unpack_qmi_t, 1397
msgid, 1397
type, 1397
xid, 1397
unpack_qos_BindDataPort
qos.h, 2363
unpack_qos_BindDataPort_t, 1397
ParamPresenceMask, 1397
unpack_qos_IPv4Addr_t, 1398
addr, 1398
subnetMask, 1398
unpack_qos_IPv6Addr_t, 1398
addr, 1399
prefixLen, 1399
unpack_qos_IPv6TrafCls_t, 1399
mask, 1399
val, 1399
unpack_qos_Port_t, 1400
port, 1400
range, 1400
unpack_qos_QosFlowInfo_t, 1400
BearerID, 1401
is_RxQFlowGranted_Available, 1401
is_TxQFlowGranted_Available, 1401
NumRxFilters, 1401
NumTxFilters, 1402
QFlowState, 1402
RxQFilter, 1402
RxQFlowGranted, 1402
TxQFilter, 1402
TxQFlowGranted, 1402
unpack_qos_QosFlowInfoState_t, 1402
id, 1402
isNewFlow, 1402
state, 1402
unpack_qos_SLQSQosGetNetworkStatus
qos.h, 2363
unpack_qos_SLQSQosGetNetworkStatus_t, 1402
NWQoSStatus, 1403
ParamPresenceMask, 1403
unpack_qos_SLQSQosSwiReadApnExtraParams
qos.h, 2364
unpack_qos_SLQSQosSwiReadApnExtraParams_t, 1403
ambr_dl, 1404
ambr_dl_ext, 1404
ambr_dl_ext2, 1404
ambr_ul, 1404
ambr_ul_ext, 1404

ambr_ul_ext2, 1404
apnId, 1404
ParamPresenceMask, 1404
unpack_qos_SLQSQosSwiReadDataStats
qos.h, 2364
unpack_qos_SLQSQosSwiReadDataStats_t, 1405
apnId, 1406
numQosFlow, 1406
ParamPresenceMask, 1406
qosFlow, 1406
total_rx_bytes, 1406
total_rx_pkt, 1406
total_tx_bytes, 1406
total_tx_pkt, 1406
unpack_qos_SLQSSetQosEventCallback
qos.h, 2365
unpack_qos_SLQSSetQosEventCallback_ind
qos.h, 2365
unpack_qos_SLQSSetQosEventCallback_ind_t, 1406
NumFlows, 1407
ParamPresenceMask, 1407
QosFlowInfo, 1407
unpack_qos_SLQSSetQosEventCallback_t, 1407
ParamPresenceMask, 1407
unpack_qos_SLQSSetQosNWStatusCallback_ind
qos.h, 2366
unpack_qos_SLQSSetQosNWStatusCallback_ind_t, 1407
status, 1408
unpack_qos_SLQSSetQosPriEventCallback_ind
qos.h, 2366
unpack_qos_SLQSSetQosPriEventCallback_ind_t, 1408
event, 1408
ParamPresenceMask, 1408
unpack_qos_SLQSSetQosStatusCallback_ind
qos.h, 2367
unpack_qos_SLQSSetQosStatusCallback_ind_t, 1408
event, 1410
id, 1410
ParamPresenceMask, 1410
reason, 1410
status, 1410
unpack_qos_Tos_t, 1418
mask, 1418
val, 1418
unpack_qos_dataRate_t, 1398
dataRateMax, 1398
guaranteedRate, 1398
unpack_qos_pktErrRate_t, 1399
exponent, 1400
multiplier, 1400
unpack_qos_swiQosFilter_t, 1410
EspSpi, 1412
IPv4DstAddr, 1412
IPv4SrcAddr, 1412
IPv4Tos, 1412
IPv6DstAddr, 1412
IPv6Label, 1412
IPv6SrcAddr, 1412
IPv6TrafCls, 1412
Id, 1412
index, 1412
is_EspSpi_Available, 1412
is_IPv4DstAddr_Available, 1412
is_IPv4SrcAddr_Available, 1412
is_IPv4Tos_Available, 1412
is_IPv6DstAddr_Available, 1412
is_IPv6Label_Available, 1412
is_IPv6SrcAddr_Available, 1412
is_IPv6TrafCls_Available, 1412
is_Id_Available, 1412
is_NxtHdrProto_Available, 1413
is_Precedence_Available, 1413
is_TCPDstPort_Available, 1413
is_TCPSrcPort_Available, 1413
is_TranDstPort_Available, 1413
is_TranSrcPort_Available, 1413
is_UDPDstPort_Available, 1413
is_UDPSrcPort_Available, 1413
NxtHdrProto, 1413
Precedence, 1413
TCPDstPort, 1413
TCPSrcPort, 1413
TranDstPort, 1413
TranSrcPort, 1413
UDPDstPort, 1413
UDPSrcPort, 1413
version, 1413
unpack_qos_swiQosFlow_t, 1413
DataRate, 1416
index, 1416
is_DataRate_Available, 1416
is_Jitter_Available, 1416
is_Latency_Available, 1416
is_LteQci_Available, 1416
is_MaxAllowedPktSz_Available, 1416
is_MinPolicedPktSz_Available, 1416
is_PktErrRate_Available, 1416
is_ProfileId3GPP2_Available, 1416
is_TokenBucket_Available, 1416
is_TrafficClass_Available, 1416
is_val_3GPP2Pri_Available, 1416
is_val_3GPPImCn_Available, 1416
is_val_3GPPSigInd_Available, 1417
Jitter, 1417
Latency, 1417
LteQci, 1417
MaxAllowedPktSz, 1417
MinPolicedPktSz, 1417
PktErrRate, 1417
ProfileId3GPP2, 1417
TokenBucket, 1417
TrafficClass, 1417
val_3GPP2Pri, 1417
val_3GPPImCn, 1417

val_3GPPResResidualBER, 1417
val_3GPPSigInd, 1417
val_3GPPTraHdlPri, 1417
unpack_qos_tokenBucket_t, 1417
bucketSz, 1418
peakRate, 1418
tokenRate, 1418
unpack_result_code_only
common.h, 1725
unpack_result_t, 1419
ParamPresenceMask, 1419
Tlvresult, 1419
unpack_rms_GetSMSWake
rms.h, 2369
unpack_rms_GetSMSWake_t, 1420
enabled, 1420
ParamPresenceMask, 1420
wake_mask, 1420
unpack_rms_SetSMSWake
rms.h, 2369
unpack_rms_SetSMSWake_t, 1420
ParamPresenceMask, 1421
unpack_sar_SLQSGetRfSarState
sar.h, 2371
unpack_sar_SLQSGetRfSarState_t, 1422
pSarRFState, 1422
ParamPresenceMask, 1422
unpack_sar_SLQSSetRfSarState
sar.h, 2371
unpack_sar_SLQSSetRfSarState_t
sar.h, 2370
unpack_sms_GetSMSCAddress
sms.h, 2384
unpack_sms_GetSMSCAddress_t, 1422
addressSize, 1423
pSMSCAddress, 1423
pSMSCType, 1423
ParamPresenceMask, 1423
typeSize, 1423
unpack_sms_SLQSDeleteSMS
sms.h, 2386
unpack_sms_SLQSDeleteSMS_t, 1427
ParamPresenceMask, 1427
unpack_sms_SLQSGetIndicationRegister
sms.h, 2386
unpack_sms_SLQSGetIndicationRegister_t, 1427
pGetIndicationRegInfo, 1428
ParamPresenceMask, 1428
unpack_sms_SLQSGetMessageWaiting
sms.h, 2387
unpack_sms_SLQSGetMessageWaiting_t, 1428
pGetMsgWaitingInfoResp, 1428
ParamPresenceMask, 1428
unpack_sms_SLQSGetSMS
sms.h, 2387
unpack_sms_SLQSGetSMS_t, 1428
message, 1429
messageFormat, 1429
messageSize, 1429
messageTag, 1429
ParamPresenceMask, 1429
unpack_sms_SLQSGetSMSList
sms.h, 2388
unpack_sms_SLQSGetSMSList_t, 1430
messageList, 1431
messageListSize, 1431
ParamPresenceMask, 1431
unpack_sms_SLQSGetSmsBroadcastConfig
sms.h, 2387
unpack_sms_SLQSGetSmsBroadcastConfig_t, 1429
pBroadcastConfig, 1430
pCDMABroadcastConfig, 1430
ParamPresenceMask, 1430
unpack_sms_SLQSGetTransLayerInfo
sms.h, 2388
unpack_sms_SLQSGetTransLayerInfo_t, 1431
pGetTransLayerInfo, 1431
ParamPresenceMask, 1431
unpack_sms_SLQSGetTransNWRegInfo
sms.h, 2389
unpack_sms_SLQSGetTransNWRegInfo_t, 1431
ParamPresenceMask, 1432
unpack_sms_SLQSModifySMSStatus
sms.h, 2389
unpack_sms_SLQSModifySMSStatus_t, 1432
ParamPresenceMask, 1432
unpack_sms_SLQSNWRegInfoCallback_ind
sms.h, 2389
unpack_sms_SLQSNWRegInfoCallback_ind_t, 1432
NWRegStat, 1433
ParamPresenceMask, 1433
unpack_sms_SLQSSendAsyncSMS
sms.h, 2390
unpack_sms_SLQSSendAsyncSMS_t, 1433
ParamPresenceMask, 1433
unpack_sms_SLQSSetIndicationRegister
sms.h, 2390
unpack_sms_SLQSSetIndicationRegister_t, 1433
ParamPresenceMask, 1434
unpack_sms_SLQSSetSmsBroadcastActivation
sms.h, 2390
unpack_sms_SLQSSetSmsBroadcastActivation_t, 1434
ParamPresenceMask, 1434
unpack_sms_SLQSSetSmsBroadcastConfig
sms.h, 2391
unpack_sms_SLQSSetSmsBroadcastConfig_t, 1434
ParamPresenceMask, 1435
unpack_sms_SLQSSetSmsStorage
sms.h, 2391
unpack_sms_SLQSSetSmsStorage_t, 1435
ParamPresenceMask, 1435
unpack_sms_SLQSSmsGetMaxStorageSize
sms.h, 2391
unpack_sms_SLQSSmsGetMaxStorageSize_t, 1435
pMaxStorageSizeResp, 1436
ParamPresenceMask, 1435

unpack_sms_SLQSSmsGetMessageProtocol
sms.h, 2392
unpack_sms_SLQSSmsGetMessageProtocol_t, 1436
pMessageProtocol, 1436
ParamPresenceMask, 1436
unpack_sms_SLQSSmsSetRoutes
sms.h, 2392
unpack_sms_SLQSSmsSetRoutes_t, 1436
ParamPresenceMask, 1436
unpack_sms_SLQSSwiGetSMSStorage
sms.h, 2392
unpack_sms_SLQSSwiGetSMSStorage_t, 1437
pSmsStorage, 1437
ParamPresenceMask, 1437
unpack_sms_SLQSTransLayerInfoCallback_ind
sms.h, 2393
unpack_sms_SLQSTransLayerInfoCallback_ind_t, 1437
pTransLayerInfo, 1438
ParamPresenceMask, 1438
regInd, 1438
unpack_sms_SLQSWmsAsyncRawSendCallBack_ind
sms.h, 2393
unpack_sms_SLQSWmsAsyncRawSendCallBack_ind_t, 1438
causeCode, 1440
errorClass, 1440
messageID, 1440
RPCause, 1440
sendStatus, 1440
TPCause, 1440
userData, 1440
unpack_sms_SLQSWmsMemoryFullCallBack_ind
sms.h, 2394
unpack_sms_SLQSWmsMemoryFullCallBack_ind_t, 1440
messageMode, 1441
ParamPresenceMask, 1441
storageType, 1441
unpack_sms_SLQSWmsMessageWaitingCallBack_ind
sms.h, 2394
unpack_sms_SLQSWmsMessageWaitingCallBack_ind_t, 1441
msgWaitInfo, 1441
numInstances, 1441
ParamPresenceMask, 1441
unpack_sms_SaveSMS
sms.h, 2384
unpack_sms_SaveSMS_t, 1423
pMessageIndex, 1424
ParamPresenceMask, 1424
unpack_sms_SendSMS
sms.h, 2385
unpack_sms_SendSMS_t, 1424
messageFailureCode, 1424
messageID, 1424
ParamPresenceMask, 1424
unpack_sms_SetNewSMSCallback
sms.h, 2385
unpack_sms_SetNewSMSCallback_ind
sms.h, 2385
unpack_sms_SetNewSMSCallback_ind_t, 1425
ETWSTlv, 1426
IMSTlv, 1426
MMTlv, 1426
NewMMTlv, 1426
ParamPresenceMask, 1426
SMSCTlv, 1426
TRMessageTlv, 1426
unpack_sms_SetNewSMSCallback_t, 1426
ParamPresenceMask, 1426
unpack_sms_SetSMSCAddress
sms.h, 2386
unpack_sms_SetSMSCAddress_t, 1426
ParamPresenceMask, 1427
unpack_swidms_SLQSSwiDmsGetHWWatchdog
swidms.h, 2400
unpack_swidms_SLQSSwiDmsGetHWWatchdog_t, 1441
pHWWatchdog, 1442
ParamPresenceMask, 1442
unpack_swidms_SLQSSwiDmsGetMTU
swidms.h, 2401
unpack_swidms_SLQSSwiDmsGetMTU_t, 1442
pMTUSize3gpp, 1443
ParamPresenceMask, 1443
unpack_swidms_SLQSSwiDmsGetSecureInfo
swidms.h, 2401
unpack_swidms_SLQSSwiDmsGetSecureInfo_t, 1443
jtagAccessAllowed, 1443
memoryDumpAllowed, 1443
ParamPresenceMask, 1443
secureBootEnabled, 1444
TlvResult, 1444
unpack_swidms_SLQSSwiDmsGetUsbComp
swidms.h, 2401
unpack_swidms_SLQSSwiDmsGetUsbComp_t, 1444
pInterfaceCfg, 1444
pSupportedBitmasks, 1444
ParamPresenceMask, 1444
unpack_swidms_SLQSSwiDmsGetUsbNetNum
swidms.h, 2402
unpack_swidms_SLQSSwiDmsGetUsbNetNum_t, 1444
ParamPresenceMask, 1445
usbNetNum, 1445
unpack_swidms_SLQSSwiDmsSetHWWatchdog
swidms.h, 2402
unpack_swidms_SLQSSwiDmsSetHWWatchdog_t, 1445
ParamPresenceMask, 1445
Tlvresult, 1445
unpack_swidms_SLQSSwiDmsSetMTU
swidms.h, 2403
unpack_swidms_SLQSSwiDmsSetMTU_t, 1445
ParamPresenceMask, 1446
Tlvresult, 1446
unpack_swidms_SLQSSwiDmsSetUsbComp

swidms.h, 2403
unpack_swidms_SLQSSwiDmsSetUsbComp_t, 1446
ParamPresenceMask, 1446
Tlvresult, 1446
unpack_swidms_SLQSSwiDmsSetUsbNetNum
swidms.h, 2403
unpack_swidms_SLQSSwiDmsSetUsbNetNum_t
swidms.h, 2397
unpack_swiloc_SwiLocGetAutoStart
swiloc.h, 2405
unpack_swiloc_SwiLocGetAutoStart_t, 1446
fix_rate, 1448
fix_rate_reported, 1448
fix_type, 1448
fix_type_reported, 1448
function, 1448
function_reported, 1448
max_dist, 1448
max_dist_reported, 1448
max_time, 1448
max_time_reported, 1448
ParamPresenceMask, 1448
unpack_swiloc_SwiLocSetAutoStart
swiloc.h, 2405
unpack_swiloc_SwiLocSetAutoStart_t
swiloc.h, 2404
unpack_swioma_SLQSOMADMAlertCallback
swioma.h, 2411
unpack_swioma_SLQSOMADMAlertCallback_ind
swioma.h, 2412
unpack_swioma_SLQSOMADMAlertCallback_ind_t, 1448
eventType, 1449
unpack_swioma_SLQSOMADMAlertCallback_t
swioma.h, 2407
unpack_swioma_SLQSOMADMCancelSession
swioma.h, 2412
unpack_swioma_SLQSOMADMCancelSession_t
swioma.h, 2407
unpack_swioma_SLQSOMADMGetSessionInfo
swioma.h, 2413
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1449
Date, 1452
DateLength, 1452
ParamPresenceMask, 1452
PkgDescLength, 1452
PkgDescription, 1452
PkgName, 1452
PkgNameLength, 1452
RetryCount, 1452
SessionState, 1452
SessionType, 1452
Severity, 1452
Source, 1452
SourceLength, 1452
Status, 1452
Time, 1452
TimeLength, 1452
UpdateCompleteStatus, 1452
unpack_swioma_SLQSOMADMGetSettings
swioma.h, 2413
unpack_swioma_SLQSOMADMGetSettings_t, 1452
Autosdm, 1453
FOTAdownload, 1453
FwAutoCheck, 1454
ParamPresenceMask, 1454
unpack_swioma_SLQSOMADMSendSelection
swioma.h, 2414
unpack_swioma_SLQSOMADMSendSelection_t
swioma.h, 2407
unpack_swioma_SLQSOMADMSetSettings
swioma.h, 2414
unpack_swioma_SLQSOMADMSetSettings_t
swioma.h, 2407
unpack_swioma_SLQSOMADMStartSession
swioma.h, 2414
unpack_swioma_SLQSOMADMStartSession_t, 1454
FwAvailability, 1454
ParamPresenceMask, 1454
unpack_uim_ChangePin
uim.h, 2428
unpack_uim_ChangePin_t, 1454
pEncryptedPIN1, 1455
pIndicationToken, 1455
pRemainingRetries, 1455
ParamPresenceMask, 1455
Tlvresult, 1455
unpack_uim_GetCardStatus
uim.h, 2428
unpack_uim_GetCardStatus_t, 1455
pCardStatus, 1456
pHotSwapStatus, 1456
ParamPresenceMask, 1456
Tlvresult, 1456
unpack_uim_GetCardStatusV2
uim.h, 2429
unpack_uim_GetCardStatusV2_t, 1456
pCardStatus, 1457
pHotSwapStatus, 1457
pSimBusyStatus, 1457
pValidCardStatus, 1457
ParamPresenceMask, 1457
Tlvresult, 1457
unpack_uim_ReadTransparent
uim.h, 2429
unpack_uim_ReadTransparent_t, 1457
pCardResult, 1458
pEncryptedData, 1458
pIndicationToken, 1458
pReadResult, 1458
ParamPresenceMask, 1458
Tlvresult, 1458
unpack_uim_SLQSUIMAuthenticate
uim.h, 2430
unpack_uim_SLQSUIMAuthenticate_t, 1459
pAuthenticateResult, 1460

pCardResult, 1460
pIndicationToken, 1460
ParamPresenceMask, 1460
unpack_uim_SLQSUIMDepersonalization
uim.h, 2430
unpack_uim_SLQSUIMDepersonalization_t, 1460
pRemainingRetries, 1461
ParamPresenceMask, 1461
unpack_uim_SLQSUIMEventRegister
uim.h, 2431
unpack_uim_SLQSUIMEventRegister_t, 1461
eventMask, 1461
ParamPresenceMask, 1461
unpack_uim_SLQSUIMGetConfiguration
uim.h, 2431
unpack_uim_SLQSUIMGetConfiguration_t, 1461
pAutoSelection, 1462
pHaltSubscription, 1462
pPersonalizationStatus, 1462
ParamPresenceMask, 1462
unpack_uim_SLQSUIMGetFileAttributes
uim.h, 2431
unpack_uim_SLQSUIMGetFileAttributes_t, 1462
pCardResult, 1463
pFileAttributes, 1463
pIndicationToken, 1463
ParamPresenceMask, 1463
unpack_uim_SLQSUIMGetSlotsStatus
uim.h, 2432
unpack_uim_SLQSUIMGetSlotsStatus_t, 1463
pNumberOfPhySlot, 1464
pUimSlotsStatus, 1464
ParamPresenceMask, 1464
unpack_uim_SLQSUIMPowerDown
uim.h, 2432
unpack_uim_SLQSUIMPowerDown_t
uim.h, 2420
unpack_uim_SLQSUIMPowerUp
uim.h, 2433
unpack_uim_SLQSUIMPowerUp_t
uim.h, 2420
unpack_uim_SLQSUIMRefreshCallback_Ind
uim.h, 2433
unpack_uim_SLQSUIMRefreshCallback_Ind_t, 1464
ParamPresenceMask, 1464
refreshEvent, 1464
TlvPresent, 1464
unpack_uim_SLQSUIMRefreshComplete
uim.h, 2433
unpack_uim_SLQSUIMRefreshComplete_t
uim.h, 2420
unpack_uim_SLQSUIMRefreshGetLastEvent
uim.h, 2434
unpack_uim_SLQSUIMRefreshGetLastEvent_t, 1464
pRefreshEvent, 1465
ParamPresenceMask, 1465
unpack_uim_SLQSUIMRefreshOK
uim.h, 2434
unpack_uim_SLQSUIMRefreshOK_t
uim.h, 2420
unpack_uim_SLQSUIMRefreshRegister
uim.h, 2434
unpack_uim_SLQSUIMRefreshRegister_t
uim.h, 2420
unpack_uim_SLQSUIMReset
uim.h, 2435
unpack_uim_SLQSUIMReset_t
uim.h, 2420
unpack_uim_SLQSUIMSetStatusChangeCallBack_ind
uim.h, 2435
unpack_uim_SLQSUIMSetStatusChangeCallBack_ind_t, 1465
unpack_uim_SLQSUIMSwitchSlot
uim.h, 2435
unpack_uim_SLQSUIMSwitchSlot_t
uim.h, 2420
unpack_uim_SetPinProtection
uim.h, 2429
unpack_uim_SetPinProtection_t, 1458
pEncryptedPIN1, 1459
pIndicationToken, 1459
pRemainingRetries, 1459
ParamPresenceMask, 1459
Tlvresult, 1459
unpack_uim_SetUimSlotStatusChangeCallback_ind
uim.h, 2430
unpack_uim_SetUimSlotStatusChangeCallback_ind_t, 1459
bNumberOfPhySlots, 1459
ParamPresenceMask, 1459
slotsstatusChange, 1459
unpack_uim_UnblockPin
uim.h, 2436
unpack_uim_UnblockPin_t, 1465
pEncryptedPIN1, 1466
pIndicationToken, 1466
pRemainingRetries, 1466
ParamPresenceMask, 1466
Tlvresult, 1466
unpack_uim_UnblockPinV2
uim.h, 2436
unpack_uim_UnblockPinV2_t, 1466
pCardResult, 1467
pEncryptedPIN1, 1467
pIndicationToken, 1467
pRemainingRetries, 1467
ParamPresenceMask, 1467
Tlvresult, 1467
unpack_uim_VerifyPin
uim.h, 2436
unpack_uim_VerifyPin_t, 1467
pEncryptedPIN1, 1468
pIndicationToken, 1468
pRemainingRetries, 1468
ParamPresenceMask, 1468
Tlvresult, 1468

unpack_valid_nas_GetCDMANetworkParameters
nas.h, 1871
unpack_valid_nas_SLQSGetServingSystem
nas.h, 1871
unpack_valid_nas_SLQSGetSignalStrength
nas.h, 1872
unpack_valid_nas_SLQSNasGetSigInfo
nas.h, 1873
unpack_voice_AnswerUSSD
voice.h, 2455
unpack_voice_AnswerUSSD_t
voice.h, 2443
unpack_voice_CancelUSSD
voice.h, 2456
unpack_voice_CancelUSSD_t
voice.h, 2443
unpack_voice_DTMFEventCallback_ind
voice.h, 2456
unpack_voice_DTMFEventCallback_ind_t, 1470
DTMFInformation, 1471
pOffLength, 1471
pOnLength, 1471
ParamPresenceMask, 1471
unpack_voice_OTASPStatusCallback_ind
voice.h, 2457
unpack_voice_OTASPStatusCallback_ind_t, 1471
callID, 1472
OTASPStatus, 1472
ParamPresenceMask, 1472
unpack_voice_OriginateUSSD
voice.h, 2456
unpack_voice_OriginateUSSD_t
voice.h, 2443
unpack_voice_SLQSOriginateUSSD
voice.h, 2457
unpack_voice_SLQSOriginateUSSD_t, 1472
pAlphaIDInfo, 1475
pCCSuppsType, 1475
pCallId, 1475
pCcResultType, 1475
pUSSDInfo, 1475
ParamPresenceMask, 1475
pfailureCause, 1475
unpack_voice_SLQSVoiceALSSelectLine
voice.h, 2457
unpack_voice_SLQSVoiceALSSelectLine_t
voice.h, 2443
unpack_voice_SLQSVoiceALSSetLineSwitching
voice.h, 2458
unpack_voice_SLQSVoiceALSSetLineSwitching_t
voice.h, 2443
unpack_voice_SLQSVoiceAnswerCall
voice.h, 2458
unpack_voice_SLQSVoiceAnswerCall_t, 1475
pCallId, 1476
ParamPresenceMask, 1476
unpack_voice_SLQSVoiceBindSubscription
voice.h, 2459
unpack_voice_SLQSVoiceBindSubscription_t
voice.h, 2443
unpack_voice_SLQSVoiceBurstDTMF
voice.h, 2459
unpack_voice_SLQSVoiceBurstDTMF_t, 1476
pCallID, 1476
ParamPresenceMask, 1476
unpack_voice_SLQSVoiceDialCall
voice.h, 2459
unpack_voice_SLQSVoiceDialCall_t, 1476
pAlphaIDInfo, 1477
pCCResultType, 1477
pCCSUPSType, 1477
pCallID, 1477
ParamPresenceMask, 1477
unpack_voice_SLQSVoiceEndCall
voice.h, 2460
unpack_voice_SLQSVoiceEndCall_t, 1477
pCallId, 1478
ParamPresenceMask, 1478
unpack_voice_SLQSVoiceGetAllCallInfo
voice.h, 2460
unpack_voice_SLQSVoiceGetAllCallInfo_t, 1478
pArrAlertingPattern, 1481
pArrAlertingType, 1481
pArrAlphaID, 1481
pArrCallEndReason, 1481
pArrCallInfo, 1481
pArrCalledPartyNum, 1481
pArrConnectPartyNum, 1481
pArrDiagInfo, 1481
pArrRedirPartyNum, 1481
pArrRemotePartyName, 1481
pArrRemotePartyNum, 1481
pArrSvcOption, 1481
pArrUUSInfo, 1481
pVoicePrivacy, 1481
ParamPresenceMask, 1481
unpack_voice_SLQSVoiceGetCLIP
voice.h, 2462
unpack_voice_SLQSVoiceGetCLIP_t, 1489
pAlphaIDInfo, 1490
pCCResType, 1490
pCallID, 1490
pFailCause, 1491
ParamPresenceMask, 1490
unpack_voice_SLQSVoiceGetCLIR
voice.h, 2462
unpack_voice_SLQSVoiceGetCLIR_t, 1491
pAlphaIDInfo, 1492
pCCResType, 1492
pCallID, 1492
pFailCause, 1492
ParamPresenceMask, 1492
unpack_voice_SLQSVoiceGetCNAP
voice.h, 2462
unpack_voice_SLQSVoiceGetCNAP_t, 1492
pAlphaIDInfo, 1493

pCCResType, 1493
pCallID, 1493
pFailCause, 1493
ParamPresenceMask, 1493
unpack_voice_SLQSVoiceGetCOLP
voice.h, 2463
unpack_voice_SLQSVoiceGetCOLP_t, 1494
pAlphaIDInfo, 1495
pCCResType, 1495
pCallID, 1495
pFailCause, 1495
ParamPresenceMask, 1495
unpack_voice_SLQSVoiceGetCOLR
voice.h, 2463
unpack_voice_SLQSVoiceGetCOLR_t, 1495
pAlphaIDInfo, 1496
pCCResType, 1496
pCallID, 1496
pFailCause, 1496
ParamPresenceMask, 1496
unpack_voice_SLQSVoiceGetCallBarring
voice.h, 2460
unpack_voice_SLQSVoiceGetCallBarring_t, 1482
pAlphaIDInfo, 1483
pCCResType, 1483
pCallID, 1483
pFailCause, 1483
pSvcClass, 1483
ParamPresenceMask, 1483
unpack_voice_SLQSVoiceGetCallForwardingStatus
voice.h, 2461
unpack_voice_SLQSVoiceGetCallForwardingStatus_t, 1483
pAlphaIDInfo, 1484
pCCResType, 1484
pCallID, 1484
pFailCause, 1484
ParamPresenceMask, 1484
unpack_voice_SLQSVoiceGetCallInfo
voice.h, 2461
unpack_voice_SLQSVoiceGetCallInfo_t, 1485
pAlertType, 1487
pAlertingPattern, 1487
pAlphaIDInfo, 1487
pCallInfo, 1487
pConnectNumInfo, 1487
pDiagInfo, 1487
pOTASPStatus, 1487
pRemotePartyName, 1487
pRemotePartyNum, 1487
pSrvOpt, 1487
pUUSInfo, 1488
pVoicePrivacy, 1488
ParamPresenceMask, 1487
unpack_voice_SLQSVoiceGetCallWaiting
voice.h, 2461
unpack_voice_SLQSVoiceGetCallWaiting_t, 1488
pAlphaIDInfo, 1489
pCCResType, 1489
pCallID, 1489
pFailCause, 1489
pSvcClass, 1489
ParamPresenceMask, 1489
unpack_voice_SLQSVoiceGetConfig
voice.h, 2463
unpack_voice_SLQSVoiceGetConfig_t, 1496
pAirTimerCnt, 1498
pAutoAnswerStat, 1498
pCurAMRConfig, 1498
pCurPrefVoiceSO, 1498
pCurVoiceDomainPref, 1498
pCurVoicePrivacyPref, 1498
pCurrTTYMode, 1498
pRoamTimerCnt, 1498
ParamPresenceMask, 1498
unpack_voice_SLQSVoiceIndicationRegister
voice.h, 2464
unpack_voice_SLQSVoiceIndicationRegister_t
voice.h, 2443
unpack_voice_SLQSVoiceManageCalls
voice.h, 2464
unpack_voice_SLQSVoiceManageCalls_t, 1498
pFailCause, 1499
ParamPresenceMask, 1499
unpack_voice_SLQSVoiceOrigUSSDNoWait
voice.h, 2464
unpack_voice_SLQSVoiceOrigUSSDNoWait_t
voice.h, 2443
unpack_voice_SLQSVoiceSUPSCallback_ind
voice.h, 2467
unpack_voice_SLQSVoiceSUPSCallback_ind_t, 1505
pDataSrc, 1508
pFailCause, 1508
pReason, 1508
pSvcClass, 1508
ParamPresenceMask, 1507
unpack_voice_SLQSVoiceSendFlash
voice.h, 2465
unpack_voice_SLQSVoiceSendFlash_t, 1499
pCallID, 1499
ParamPresenceMask, 1499
unpack_voice_SLQSVoiceSetCallBarringPassword
voice.h, 2465
unpack_voice_SLQSVoiceSetCallBarringPassword_t, 1500
pAlphaIDInfo, 1501
pCCResType, 1501
pCallID, 1501
pFailCause, 1501
ParamPresenceMask, 1501
unpack_voice_SLQSVoiceSetConfig
voice.h, 2465
unpack_voice_SLQSVoiceSetConfig_t, 1501
pAirTimerStatus, 1502
pAutoAnsStatus, 1502
pPrefVoiceSOStatus, 1502

pRoamTimerStatus, 1502
pTTYConfigStatus, 1502
pVoiceDomainPrefStatus, 1502
ParamPresenceMask, 1502
unpack_voice_SLQSVoiceSetPreferredPrivacy
voice.h, 2466
unpack_voice_SLQSVoiceSetPreferredPrivacy_t
voice.h, 2443
unpack_voice_SLQSVoiceSetSUPSService
voice.h, 2466
unpack_voice_SLQSVoiceSetSUPSService_t, 1503
pCallID, 1504
pFailCause, 1504
ParamPresenceMask, 1504
unpack_voice_SLQSVoiceStartContDTMF
voice.h, 2466
unpack_voice_SLQSVoiceStartContDTMF_t, 1504
pCallID, 1504
ParamPresenceMask, 1504
unpack_voice_SLQSVoiceStopContDTMF
voice.h, 2467
unpack_voice_SLQSVoiceStopContDTMF_t, 1504
callID, 1505
ParamPresenceMask, 1505
unpack_voice_SUPSNotificationCallback_ind
voice.h, 2467
unpack_voice_SUPSNotificationCallback_ind_t, 1508
callID, 1510
notifType, 1510
pCUGIndex, 1510
pECTNum, 1510
ParamPresenceMask, 1510
unpack_voice_USSDNotificationCallback_ind
voice.h, 2468
unpack_voice_USSDNotificationCallback_ind_t, 1510
notification_Type, 1510
ParamPresenceMask, 1510
unpack_voice_VoiceInfoRecCallback_ind
voice.h, 2468
unpack_voice_VoiceInfoRecCallback_ind_t, 1510
callID, 1513
pCLIRCause, 1513
pCallWaitInd, 1513
pCalledPartyInfo, 1513
pCallerIDInfo, 1513
pCallerNameInfo, 1513
pCallingPartyInfo, 1513
pConnectNumInfo, 1513
pDispInfo, 1513
pExtDispInfo, 1513
pExtDispRecInfo, 1513
pLineCtrlInfo, 1513
pNSSAudioCtrl, 1513
pNSSRelease, 1513
pRedirNumInfo, 1513
pSignalInfo, 1513
ParamPresenceMask, 1513
unpack_voice_allCallStatusCallback_ind
voice.h, 2455
unpack_voice_allCallStatusCallback_ind_t, 1468
arrCallInfomation, 1470
pArrAlertingPattern, 1470
pArrAlertingType, 1470
pArrAlphaID, 1470
pArrCallEndReason, 1470
pArrCalledPartyNum, 1470
pArrConnectPartyNum, 1470
pArrDiagInfo, 1470
pArrRedirPartyNum, 1470
pArrRemotePartyName, 1470
pArrRemotePartyNum, 1470
pArrSvcOption, 1470
ParamPresenceMask, 1470
unpack_voice_voicePrivacyChangeCallback_ind
voice.h, 2468
unpack_voice_voicePrivacyChangeCallback_ind_t, 1513
callID, 1514
ParamPresenceMask, 1514
voicePrivacy, 1514
unpack_wds_DHCPv4ClientLease_ind
wds.h, 2498
unpack_wds_DHCPv4ClientLease_ind_t, 1514
DHCPv4LeaseOptTlv, 1515
DHCPv4LeaseStateTlv, 1515
IPv4AddrTlv, 1515
ParamPresenceMask, 1515
ProfileIdTlv, 1515
unpack_wds_DHCPv4ClientLeaseChange
wds.h, 2498
unpack_wds_DHCPv4ClientLeaseChange_t
wds.h, 2477
unpack_wds_GetAutoconnect
wds.h, 2498
unpack_wds_GetAutoconnect_t, 1515
ParamPresenceMask, 1515
psetting, 1515
unpack_wds_GetByteTotals
wds.h, 2499
unpack_wds_GetByteTotals_t, 1515
pRXTotalBytes, 1516
pTXTotalBytes, 1516
ParamPresenceMask, 1516
unpack_wds_GetConnectionRate
wds.h, 2499
unpack_wds_GetConnectionRate_t, 1516
currentChannelRXRate, 1517
currentChannelTXRate, 1517
maxChannelRXRate, 1517
maxChannelTXRate, 1517
ParamPresenceMask, 1517
unpack_wds_GetDataBearerTechnology
wds.h, 2499
unpack_wds_GetDataBearerTechnology_t, 1517
pDataBearer, 1518
ParamPresenceMask, 1518

unpack_wds_GetDefaultProfile
wds.h, 2500
unpack_wds_GetDefaultProfile_t, 1518
apnname, 1520
apnsize, 1520
auth, 1520
ipaddr, 1520
ipaddrv6, 1521
name, 1521
namesize, 1521
ParamPresenceMask, 1521
pdptype, 1521
pridns, 1521
pridnsv6, 1521
secdns, 1521
secdnsv6, 1521
username, 1521
usersize, 1521
unpack_wds_GetDefaultProfileNum
wds.h, 2500
unpack_wds_GetDefaultProfileNum_t, 1521
index, 1521
ParamPresenceMask, 1521
unpack_wds_GetDormancyState
wds.h, 2500
unpack_wds_GetDormancyState_t, 1521
dormancyState, 1522
ParamPresenceMask, 1522
unpack_wds_GetLastMobileIPError
wds.h, 2501
unpack_wds_GetLastMobileIPError_t, 1522
error, 1522
ParamPresenceMask, 1523
unpack_wds_GetMobileIP
wds.h, 2501
unpack_wds_GetMobileIP_t, 1523
mipMode, 1523
ParamPresenceMask, 1523
unpack_wds_GetMobileIPProfile
wds.h, 2501
unpack_wds_GetMobileIPProfile_t, 1523
AAASPI, 1525
AAAState, 1525
address, 1525
enabled, 1525
HASPI, 1525
HAState, 1525
NAI, 1525
naiSize, 1525
ParamPresenceMask, 1525
primaryHA, 1525
revTunneling, 1525
secondaryHA, 1525
unpack_wds_GetPacketStatistics
wds.h, 2502
unpack_wds_GetPacketStatistics_t, 1525
pRXDroppedCount, 1527
pRXOKBytesLastCall, 1527
pRXOkBytesCount, 1527
pRXPacketErrors, 1527
pRXPacketOverflows, 1527
pRXPacketSuccesses, 1527
pTXDroppedCount, 1527
pTXOKBytesLastCall, 1527
pTXOkBytesCount, 1527
pTXPacketErrors, 1527
pTXPacketOverflows, 1527
pTXPacketSuccesses, 1527
ParamPresenceMask, 1527
unpack_wds_GetPacketStatus
wds.h, 2502
unpack_wds_GetPacketStatus_t, 1527
ParamPresenceMask, 1529
rXDroppedCount, 1529
rXOKBytesLastCall, 1529
rXOkBytesCount, 1529
rXPacketErrors, 1529
rXPacketOverflows, 1529
rXPacketSuccesses, 1529
tXDroppedCount, 1529
tXOKBytesLastCall, 1529
tXOkBytesCount, 1529
tXPacketErrors, 1529
tXPacketOverflows, 1529
tXPacketSuccesses, 1529
unpack_wds_GetSessionDuration
wds.h, 2502
unpack_wds_GetSessionDuration_t, 1529
callDuration, 1530
ParamPresenceMask, 1530
unpack_wds_GetSessionState
wds.h, 2503
unpack_wds_GetSessionState_t, 1530
connectionStatus, 1530
ParamPresenceMask, 1530
unpack_wds_RMSetTransferStatistics
wds.h, 2503
unpack_wds_RMSetTransferStatistics_t, 1530
ParamPresenceMask, 1531
unpack_wds_RMTransferStatistics_ind
wds.h, 2503
unpack_wds_RMTransferStatistics_ind_t
wds.h, 2477
unpack_wds_SLQSCreateProfile
wds.h, 2506
unpack_wds_SLQSCreateProfile_t, 1531
pCreateProfileOut, 1532
pProfileID, 1532
ParamPresenceMask, 1532
Tlvresult, 1532
unpack_wds_SLQSDUNCallInfoCallBack_ind
wds.h, 2507
unpack_wds_SLQSDUNCallInfoCallBack_ind_t, 1533
unpack_wds_SLQSDeleteProfile
wds.h, 2506
unpack_wds_SLQSDeleteProfile_t, 1532

extendedErrorCode, 1532
ParamPresenceMask, 1532
unpack_wds_SLQSGet3GPPConfigItem
wds.h, 2507
unpack_wds_SLQSGet3GPPConfigItem_t, 1534
_3gppRelease, 1535
defaultPDNEnabled, 1535
LTEAttachProfile, 1535
ParamPresenceMask, 1536
profileList, 1536
unpack_wds_SLQSGetCurrDataSystemStat
wds.h, 2507
unpack_wds_SLQSGetCurrDataSystemStat_t, 1536
currNetworkInfo, 1536
networkInfoLen, 1536
ParamPresenceMask, 1536
prefNetwork, 1537
unpack_wds_SLQSGetCurrentChannelRate
wds.h, 2508
unpack_wds_SLQSGetCurrentChannelRate_t, 1537
max_channel_rx_rate, 1538
max_channel_tx_rate, 1538
ParamPresenceMask, 1538
unpack_wds_SLQSGetDUNCallInfo
wds.h, 2508
unpack_wds_SLQSGetDUNCallInfo_t, 1539
callEndReason, 1541
channelRate, 1541
connectionStatus, 1541
dataBearerTech, 1541
dormancyStatus, 1541
lastCallDataBearerTech, 1541
mdmCallDurationActive, 1542
ParamPresenceMask, 1542
rxOKBytesCount, 1542
txOKBytesCount, 1542
unpack_wds_SLQSGetDataBearerTechnology
wds.h, 2508
unpack_wds_SLQSGetDataBearerTechnology_t, 1538
curDataBearerTechnology, 1538
dataBearerMask, 1538
lastCallDataBearerTechnology, 1539
ParamPresenceMask, 1539
unpack_wds_SLQSGetProfileSettings
wds.h, 2509
unpack_wds_SLQSGetProfileSettings_t, 1542
pProfileSettings, 1542
ParamPresenceMask, 1542
ProfileType, 1542
Tlvresult, 1542
unpack_wds_SLQSGetRuntimeSettings
wds.h, 2509
unpack_wds_SLQSGetRuntimeSettings_t, 1542
APNName, 1545
Authentication, 1545
DomainList, 1545
GPRSGrantedQoS, 1545
GWAddressV4, 1545
IMCNflag, 1545
IPFamilyPreference, 1545
IPV6AddrInfo, 1545
IPV6GWAddrInfo, 1545
IPv4, 1545
Mtu, 1545
PDPType, 1545
ParamPresenceMask, 1545
PrimaryDNSV4, 1545
PrimaryDNSV6, 1545
ProfileID, 1545
ProfileName, 1545
SecondaryDNSV4, 1545
SecondaryDNSV6, 1545
ServerAddrList, 1545
SubnetMaskV4, 1545
Technology, 1545
UMTSGrantedQoS, 1546
Username, 1546
unpack_wds_SLQSModifyProfile
wds.h, 2509
unpack_wds_SLQSModifyProfile_t, 1546
pExtErrorCode, 1546
ParamPresenceMask, 1546
unpack_wds_SLQSResetPacketStatics
wds.h, 2510
unpack_wds_SLQSResetPacketStatics_t
wds.h, 2477
unpack_wds_SLQSSGetDHCPv4ClientConfig
wds.h, 2512
unpack_wds_SLQSSGetDHCPv4ClientConfig_t, 1554
pHwConfig, 1555
ParamPresenceMask, 1555
unpack_wds_SLQSSGetLoopback
wds.h, 2512
unpack_wds_SLQSSGetLoopback_t, 1555
ByteLoopbackMode, 1556
ByteLoopbackMultiplier, 1556
ParamPresenceMask, 1556
unpack_wds_SLQSSSetDHCPv4ClientConfig
wds.h, 2512
unpack_wds_SLQSSSetDHCPv4ClientConfig_t
wds.h, 2477
unpack_wds_SLQSSSetLoopback
wds.h, 2513
unpack_wds_SLQSSSetLoopback_t
wds.h, 2477
unpack_wds_SLQSSet3GPPConfigItem
wds.h, 2510
unpack_wds_SLQSSet3GPPConfigItem_t
wds.h, 2477
unpack_wds_SLQSSetIPFamilyPreference
wds.h, 2510
unpack_wds_SLQSSetIPFamilyPreference_t, 1546
ParamPresenceMask, 1547
Tlvresult, 1547
unpack_wds_SLQSSetPacketSrvStatusCallback
wds.h, 2511

unpack_wds_SLQSSetPacketSrvStatusCallback_t, 1547
bearerID, 1548
conn_status, 1548
ipFamily, 1549
ParamPresenceMask, 1549
reconfigReqd, 1549
sessionEndReason, 1549
techName, 1549
verboseSessnEndReason, 1549
verboseSessnEndReasonType, 1549
unpack_wds_SLQSSetWdsEventCallback
wds.h, 2511
unpack_wds_SLQSSetWdsEventCallback_ind
wds.h, 2511
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1549
currDBTechAvail, 1553
currNWInfo, 1553
dBTechAvail, 1553
dBTechnology, 1554
dBtechExtAvail, 1553
dBtechnologyExt, 1554
dataSysStatAvail, 1553
dormancyStatAvail, 1554
dormancyStatus, 1554
mipStatus, 1554
mipstatAvail, 1554
netInfoLen, 1554
ParamPresenceMask, 1554
prefNetwork, 1554
ratMask, 1554
rx_bytes, 1554
rx_pkts, 1554
soMask, 1554
tx_bytes, 1554
tx_pkts, 1554
xferStatAvail, 1554
unpack_wds_SLQSSetWdsEventCallback_t
wds.h, 2477
unpack_wds_SLQSStartDataSession
wds.h, 2513
unpack_wds_SLQSStartDataSession_t, 1556
pFailureReason, 1556
pVerboseFailReasonType, 1557
pVerboseFailureReason, 1557
ParamPresenceMask, 1556
psid, 1556
unpack_wds_SLQSStopDataSession
wds.h, 2513
unpack_wds_SLQSStopDataSession_t
wds.h, 2477
unpack_wds_SLQSWdsGoActive
wds.h, 2514
unpack_wds_SLQSWdsGoActive_t
wds.h, 2477
unpack_wds_SLQSWdsGoDormant
wds.h, 2514
unpack_wds_SLQSWdsGoDormant_t
wds.h, 2477
unpack_wds_SLQSWdsSetEventReport
wds.h, 2514
unpack_wds_SLQSWdsSetEventReport_t
wds.h, 2477
unpack_wds_SLQSWdsSwiPDPRuntimeSettings
wds.h, 2515
unpack_wds_SLQSWdsSwiPDPRuntimeSettings_t, 1557
apnName, 1559
bearerId, 1559
contextId, 1559
ipv4Address, 1559
ipv4GWAddress, 1559
ipv6Address, 1559
ipv6GWAddress, 1559
ParamPresenceMask, 1559
unpack_wds_SetAutoconnect
wds.h, 2504
unpack_wds_SetAutoconnect_t
wds.h, 2477
unpack_wds_SetDefaultProfile
wds.h, 2504
unpack_wds_SetDefaultProfile_t
wds.h, 2477
unpack_wds_SetDefaultProfileNum
wds.h, 2504
unpack_wds_SetDefaultProfileNum_t
wds.h, 2477
unpack_wds_SetMobileIP
wds.h, 2505
unpack_wds_SetMobileIP_t
wds.h, 2477
unpack_wds_SetMobileIPParameters
wds.h, 2505
unpack_wds_SetMobileIPParameters_t
wds.h, 2477
unpack_wds_SetMobileIPProfile
wds.h, 2505
unpack_wds_SetMobileIPProfile_t, 1531
ParamPresenceMask, 1531
unpack_wds_SetMuxID
wds.h, 2506
unpack_wds_SetMuxID_t
wds.h, 2477
UnpackQmiProfileInfo
wds.h, 2478
unpackWdsProfileParam, 1560
SlqsProfile3GPP, 1560
SlqsProfile3GPP2, 1560
upLink
NSSAudioCtrl, 695
voice_NSSAudioCtrl, 1606
UpdateCompleteStatus
unpack_swioma_SLQSOMADMGetSessionInfo_t, 1452
updateCompleteStatus
omaDmFotaTlv, 701

unpack_omaDmFotaTlv_t, 1382
upgrade_9x07_9x50_fw
qaGobiApiFms.h, 2063
upgrade_mc77xx_fw
qaGobiApiFms.h, 2063
UpgradeFirmware2k
qaGobiApiFms.h, 2063
upinRetries
slotInf, 1030
slotInfo, 1031
uim_slotInfo, 1167
upinState
slotInf, 1030
slotInfo, 1031
uim_slotInfo, 1167
UpkQmiCbkCatEventReportInd
qaCbkCatEventReportInd.h, 1897
UpkQmiCbkSwiOmaDmEventReportInd
qaCbkSwiOmaDmEventReportInd.h, 1898
UpkQmiCbkSwiOmaDmEventReportIndExt
qaCbkSwiOmaDmEventReportInd.h, 1898
UpkQmiNasGetRFBandInfo
qaNasGetRFBandInfo.h, 2349
UpkQmiNasPerformNetworkScan
qaNasPerformNetworkScan.h, 2351
upukRetries
slotInf, 1030
slotInfo, 1031
uim_slotInfo, 1167
urlAddr, 1560
address, 1561
loc_URLAddrInfo, 422
TlvPresent, 1561
URLAddrInfo, 1561
usageMask
loc_sensorDataUsage, 419
sensorDataUsage_s, 991
t_sensor, 1124
UsbMTUSize
swidms_usbMTUSizeTlv, 1096
usbMTUSizeTlv, 1565
usbMTUSizeTlv, 1564
TlvPresent, 1565
UsbMTUSize, 1565
usbNetNum
SwiDmsSLQSGetUsbNetNum, 1100
unpack_swidms_SLQSSwiDmsGetUsbNetNum_t, 1445
User Identity Module Service (UIM), 58
userData
SMSAsyncRawSend_s, 1066
unpack_sms_SLQSWmsAsyncRawSendCallBack-_ind_t, 1440
userInputReq
omaDmConfigTlv, 697
omaDmConfigTlvExt, 699
omaDmFotaTlv, 701
unpack_omaDmConfigTlv_t, 1380
unpack_omaDmFotaTlv_t, 1382
userInputTimeout
omaDmConfigTlv, 697
omaDmConfigTlvExt, 699
omaDmFotaTlv, 701
omaDmFotaTlvExt, 703
unpack_omaDmConfigTlv_t, 1380
unpack_omaDmFotaTlv_t, 1382
Username
unpack_wds_SLQSGetRuntimeSettings_t, 1546
username
unpack_wds_GetDefaultProfile_t, 1521
usersize
unpack_wds_GetDefaultProfile_t, 1521
ussDCS
pack_voice_SLQSOriginateUSSD_t, 825
USSInfo, 1566
voice_USSInfo, 1616
ussData
pack_voice_SLQSOriginateUSSD_t, 825
USSInfo, 1566
voice_USSInfo, 1616
ussLen
pack_voice_SLQSOriginateUSSD_t, 825
USSInfo, 1566
voice_USSInfo, 1616
uusInfo
allCallsUUSInfo, 134
voice_allCallsUUSInfo, 1571

v4sessionId
qaQmiInterfaceInfo, 912
ssdatasession_params, 1086
WdsRunTimeSettings, 1715
v6sessionId
qaQmiInterfaceInfo, 912
ssdatasession_params, 1086
WdsRunTimeSettings, 1715
VOICE_SUPS_SRV_CLASS_DATA
qaGobiApiVoice.h, 2287
VOICE_SUPS_SRV_CLASS_DATACIRCUITASYNC
qaGobiApiVoice.h, 2287
VOICE_SUPS_SRV_CLASS_DATACIRCUITSYNC
qaGobiApiVoice.h, 2287
VOICE_SUPS_SRV_CLASS_FAX
qaGobiApiVoice.h, 2287
VOICE_SUPS_SRV_CLASS_NONE
qaGobiApiVoice.h, 2287
VOICE_SUPS_SRV_CLASS_PACKETACCESS
qaGobiApiVoice.h, 2287
VOICE_SUPS_SRV_CLASS_PADACCESS
qaGobiApiVoice.h, 2287
VOICE_SUPS_SRV_CLASS_SMS
qaGobiApiVoice.h, 2287
VOICE_SUPS_SRV_CLASS_VOICE
qaGobiApiVoice.h, 2287
VDOP
loc_precisionDilution, 416
precisionDilution_s, 890

VOICE_SRV
qaGobiApiCbk.h, 1914
val
IPv6TrafCls, 372
Tos, 1138
unpack_qos_IPv6TrafCls_t, 1399
unpack_qos_Tos_t, 1418
val_3GPP2Pri
unpack_qos_swiQosFlow_t, 1417
val_3GPPImCn
unpack_qos_swiQosFlow_t, 1417
val_3GPPResResidualBER
unpack_qos_swiQosFlow_t, 1417
val_3GPPSigInd
unpack_qos_swiQosFlow_t, 1417
val_3GPPTraHdlPri
unpack_qos_swiQosFlow_t, 1417
ValidBitmasks
supportedIntBitmaskTlv, 1087
swidms_supportedIntBitmaskTlv, 1095
validCard
uim_validCardStatus, 1170
validCardStatus, 1569
validCardLength
uim_validCardStatus, 1170
validCardStatus, 1569
validCardStatus, 1568
validCard, 1569
validCardLength, 1569
ValidMask
GPSStateInfo, 327
unpack_pds_SLQSGetGPSStateInfo_t, 1396
validMask
loc_satelliteInfo, 418
satelliteInfo, 986
ValidateSPC
qaGobiApiDms.h, 2042
ValidityCW0
LteCQIParm, 438
unpack_nas_SLQSSwiGetLteCQI_t, 1373
ValidityCW1
LteCQIParm, 438
unpack_nas_SLQSSwiGetLteCQI_t, 1373
Value
GetM2MSpkrGainResp, 315
SetM2MSpkrGainReq, 1015
value
pack_dms_UIMSetPINProtection_t, 722
pack_dms_UIMVerifyPIN_t, 724
value_length
custSettingInfo, 229
DMScustSettingInfo, 255
pack_dms_SetCustFeaturesV2_t, 711
setCustomSettingV2, 1003
verbFailReason
ssdatasession_params, 1086
verbFailReasonType
ssdatasession_params, 1086
verboseSessnEndReason
_packetSrvStatus, 77
unpack_wds_SLQSSetPacketSrvStatusCallback_t, 1549
verboseSessnEndReasonType
_packetSrvStatus, 77
unpack_wds_SLQSSetPacketSrvStatusCallback_t, 1549
verifyLeft
personalizationStatus, 876
remainingRetries, 963
uim_personalizationStatus, 1159
uim_remainingRetries, 1163
verifyPIN
pack_uim_VerifyPin_t, 823
UIMVerifyPinReq, 1194
verifyRetriesLeft
unpack_dms_UIMGetControlKeyStatus_t, 1267
unpack_dms_UIMSetControlKeyProtection_t, 1270
unpack_dms_UIMSetPINProtection_t, 1271
verifyUIMPIN, 1569
pinID, 1569
pinLen, 1569
pinVal, 1569
version
omaDmFotaTlv, 701
omaDmFotaTlvExt, 703
swiQosFilter, 1111
unpack_omaDmFotaTlv_t, 1382
unpack_qos_swiQosFilter_t, 1413
versionString
pack_dms_SLQSSwiSetOSInfo_t, 718
unpack_dms_SLQSSwiGetOSInfo_t, 1261
versionlength
omaDmFotaTlv, 701
omaDmFotaTlvExt, 703
unpack_omaDmFotaTlv_t, 1382
vertConfidence
pack_loc_SLQSLOCInjectPosition_t, 736
vertReliability
pack_loc_SLQSLOCInjectPosition_t, 736
vertUnc
pack_loc_SLQSLOCInjectPosition_t, 736
VerticalUncertainty
GPSStateInfo, 327
unpack_pds_SLQSGetGPSStateInfo_t, 1396
VirtStream
nas_protocolSubtypeElement, 576
protocolSubtypeElement, 907
Voice Service (VOICE), 56
voice.h
LITE_VOICE_SUPS_SRV_CLASS_DATA, 2443
LITE_VOICE_SUPS_SRV_CLASS_DATACIRCUITASYNC, 2443
LITE_VOICE_SUPS_SRV_CLASS_DATACIRCUITSYNC, 2443
LITE_VOICE_SUPS_SRV_CLASS_FAX, 2443
LITE_VOICE_SUPS_SRV_CLASS_NONE, 2443

LITE_VOICE_SUPS_SRV_CLASS_PACKETACC-ESS, 2443
LITE_VOICE_SUPS_SRV_CLASS_PADACCESS, 2443
LITE_VOICE_SUPS_SRV_CLASS_SMS, 2443
LITE_VOICE_SUPS_SRV_CLASS_VOICE, 2443
voice.h, 2437
liteServiceClassInformation, 2443
MAXVOICEUSSDLENGTH, 2442
pack_voice_AnswerUSSD, 2443
pack_voice_CancelUSSD, 2444
pack_voice_OriginateUSSD, 2444
pack_voice_SLQSOriginateUSSD, 2444
pack_voice_SLQSVoiceALSSelectLine, 2445
pack_voice_SLQSVoiceALSSetLineSwitching, 2445
pack_voice_SLQSVoiceAnswerCall, 2445
pack_voice_SLQSVoiceBindSubscription, 2446
pack_voice_SLQSVoiceBurstDTMF, 2446
pack_voice_SLQSVoiceDialCall, 2447
pack_voice_SLQSVoiceEndCall, 2447
pack_voice_SLQSVoiceGetAllCallInfo, 2447
pack_voice_SLQSVoiceGetCLIP, 2449
pack_voice_SLQSVoiceGetCLIR, 2450
pack_voice_SLQSVoiceGetCNAP, 2450
pack_voice_SLQSVoiceGetCOLP, 2450
pack_voice_SLQSVoiceGetCOLR, 2451
pack_voice_SLQSVoiceGetCallBarring, 2448
pack_voice_SLQSVoiceGetCallForwardingStatus, 2448
pack_voice_SLQSVoiceGetCallInfo, 2448
pack_voice_SLQSVoiceGetCallWaiting, 2449
pack_voice_SLQSVoiceGetConfig, 2451
pack_voice_SLQSVoiceIndicationRegister, 2451
pack_voice_SLQSVoiceManageCalls, 2452
pack_voice_SLQSVoiceOrigUSSDNoWait, 2452
pack_voice_SLQSVoiceSendFlash, 2452
pack_voice_SLQSVoiceSetCallBarringPassword, 2453
pack_voice_SLQSVoiceSetConfig, 2453
pack_voice_SLQSVoiceSetPreferredPrivacy, 2453
pack_voice_SLQSVoiceSetSUPSService, 2454
pack_voice_SLQSVoiceStartContDTMF, 2454
pack_voice_SLQSVoiceStopContDTMF, 2455
unpack_voice_AnswerUSSD, 2455
unpack_voice_AnswerUSSD_t, 2443
unpack_voice_CancelUSSD, 2456
unpack_voice_CancelUSSD_t, 2443
unpack_voice_DTMFEventCallback_ind, 2456
unpack_voice_OTASPStatusCallback_ind, 2457
unpack_voice_OriginateUSSD, 2456
unpack_voice_OriginateUSSD_t, 2443
unpack_voice_SLQSOriginateUSSD, 2457
unpack_voice_SLQSVoiceALSSelectLine, 2457
unpack_voice_SLQSVoiceALSSelectLine_t, 2443
unpack_voice_SLQSVoiceALSSetLineSwitching, 2458
unpack_voice_SLQSVoiceALSSetLineSwitching_t, 2443
unpack_voice_SLQSVoiceAnswerCall, 2458
unpack_voice_SLQSVoiceBindSubscription, 2459
unpack_voice_SLQSVoiceBindSubscription_t, 2443
unpack_voice_SLQSVoiceBurstDTMF, 2459
unpack_voice_SLQSVoiceDialCall, 2459
unpack_voice_SLQSVoiceEndCall, 2460
unpack_voice_SLQSVoiceGetAllCallInfo, 2460
unpack_voice_SLQSVoiceGetCLIP, 2462
unpack_voice_SLQSVoiceGetCLIR, 2462
unpack_voice_SLQSVoiceGetCNAP, 2462
unpack_voice_SLQSVoiceGetCOLP, 2463
unpack_voice_SLQSVoiceGetCOLR, 2463
unpack_voice_SLQSVoiceGetCallBarring, 2460
unpack_voice_SLQSVoiceGetCallForwarding-Status, 2461
unpack_voice_SLQSVoiceGetCallInfo, 2461
unpack_voice_SLQSVoiceGetCallWaiting, 2461
unpack_voice_SLQSVoiceGetConfig, 2463
unpack_voice_SLQSVoiceIndicationRegister, 2464
unpack_voice_SLQSVoiceIndicationRegister_t, 2443
unpack_voice_SLQSVoiceManageCalls, 2464
unpack_voice_SLQSVoiceOrigUSSDNoWait, 2464
unpack_voice_SLQSVoiceOrigUSSDNoWait_t, 2443
unpack_voice_SLQSVoiceSUPSCallback_ind, 2467
unpack_voice_SLQSVoiceSendFlash, 2465
unpack_voice_SLQSVoiceSetCallBarringPassword, 2465
unpack_voice_SLQSVoiceSetConfig, 2465
unpack_voice_SLQSVoiceSetPreferredPrivacy, 2466
unpack_voice_SLQSVoiceSetPreferredPrivacy_t, 2443
unpack_voice_SLQSVoiceSetSUPSService, 2466
unpack_voice_SLQSVoiceStartContDTMF, 2466
unpack_voice_SLQSVoiceStopContDTMF, 2467
unpack_voice_SUPSNotificationCallback_ind, 2467
unpack_voice_USSDNotificationCallback_ind, 2468
unpack_voice_VoiceInfoRecCallback_ind, 2468
unpack_voice_allCallStatusCallback_ind, 2455
unpack_voice_voicePrivacyChangeCallback_ind, 2468
voice_CLIPResp, 1591
ActiveStatus, 1592
ProvisionStatus, 1592
voice_CLIRResp, 1592
ActiveStatus, 1593
ProvisionStatus, 1593
voice_CNAPResp, 1593
ActiveStatus, 1593
ProvisionStatus, 1593

voice_COLPResp, 1594
ActiveStatus, 1594
ProvisionStatus, 1594
voice_COLRResp, 1594
ActiveStatus, 1595
ProvisionStatus, 1595
voice_CUGInfo, 1597
CUGIndex, 1597
SuppOA, 1597
SuppPrefCUG, 1597
voice_DTMFInfo, 1599
callID, 1599
DTMFEvent, 1599
digitBuff, 1599
digitCnt, 1599
voice_DTMFLengths, 1599
DTMFInterdigitInterval, 1600
DTMFPulseWidth, 1600
voice_ECTNum, 1600
ECTCallState, 1601
number, 1601
presentationInd, 1601
voice_NSSAudioCtrl, 1606
downLink, 1606
upLink, 1606
voice_SUPSInfo, 1615
isModByCC, 1615
svcType, 1615
voice_USSDNotificationNetworkInfo, 1615
networkInfo, 1616
tlvPresent, 1616
voice_USSInfo, 1616
ussDCS, 1616
ussData, 1616
ussLen, 1616
voice_UUSInfo, 1616
UUSData, 1617
UUSDatalen, 1617
UUSDcs, 1617
UUSType, 1617
voice_airTimer, 1569
airTimerValue, 1570
namID, 1570
voice_allCallsAlphaIDInfo, 1570
AlphaIDInfo, 1570
callID, 1570
voice_allCallsDiagInfo, 1570
callID, 1571
DiagInfo, 1571
voice_allCallsUUSInfo, 1571
callID, 1571
uusInfo, 1571
voice_alphaIDInfo, 1571
alphaDcs, 1572
alphaLen, 1572
alphaText, 1572
voice_arrAlertingPattern, 1572
alertingPattern, 1573
callID, 1573
numInstances, 1573
voice_arrAlertingType, 1573
AlertingType, 1574
callID, 1574
numInstances, 1574
voice_arrAlphaID, 1574
allCallsAlphaIDInfoArr, 1574
numInstances, 1574
voice_arrCallEndReason, 1575
callEndReason, 1575
callID, 1575
numInstances, 1575
voice_arrCallInfo, 1575
getAllCallInfo, 1576
numInstances, 1576
voice_arrCalledPartyNum, 1574
CalledPartyNum, 1575
numInstances, 1575
voice_arrConnectPartyNum, 1576
ConnectedPartyNum, 1576
numInstances, 1576
voice_arrDiagInfo, 1577
DiagInfo, 1577
numInstances, 1577
voice_arrRedirPartyNum, 1577
numInstances, 1577
RedirPartyNum, 1578
voice_arrRemotePartyName, 1578
GetAllCallRmtPtyName, 1578
numInstances, 1578
voice_arrRemotePartyNum, 1578
numInstances, 1579
RmtPtyNum, 1579
voice_arrSvcOption, 1579
callID, 1579
numInstances, 1579
srvOption, 1579
voice_arrUUSInfo, 1579
AllCallsUUSInfo, 1580
numInstances, 1580
voice_burstDTMFInfo, 1580
digitCnt, 1580
pCallID, 1580
pDigitBuff, 1580
voice_callFWExtInfo, 1585
noReplyTimer, 1586
numLen, 1586
numPlan, 1586
numType, 1586
number, 1586
PI, 1586
SI, 1586
SvcClass, 1586
SvcStatus, 1586
voice_callFWInfo, 1587
noReplyTimer, 1587
numLen, 1587

number, 1587
SvcClass, 1587
SvcStatus, 1587
voice_callFwdTypeAndPlan, 1584
numberPlan, 1585
numberType, 1585
voice_callInfo, 1587
callID, 1589
callState, 1589
callType, 1589
direction, 1589
mode, 1589
voice_calledPartyInfo, 1581
numLen, 1582
numPlan, 1582
numType, 1582
number, 1582
PI, 1582
SI, 1582
voice_calledPartySubAdd, 1582
extBit, 1583
oddEvenInd, 1583
subAddr, 1583
subAddrLen, 1583
subAddrType, 1583
voice_callerIDInfo, 1583
callerID, 1584
callerIDLen, 1584
PI, 1584
voice_callingPartyInfo, 1589
numLen, 1590
numPlan, 1590
numType, 1590
number, 1590
PI, 1591
SI, 1591
voice_ccSUPSType, 1591
reason, 1591
svcType, 1591
voice_connectNumInfo, 1595
callerID, 1596
callerIDLen, 1596
numPlan, 1596
numPresInd, 1596
numType, 1597
screeningInd, 1597
voice_curAMRConfig, 1597
gsmAmrStat, 1598
wcdmaAmrStat, 1598
voice_diagInfo, 1598
diagInfoLen, 1598
diagnosticInfo, 1598
voice_extDispRecInfo, 1601
dispType, 1601
extDispInfo, 1601
extDispInfoLen, 1601
voice_getAllCallInformation, 1602
ALS, 1602
Callinfo, 1602
isEmpty, 1602
voice_getAllCallRmtPtyName, 1602
callID, 1603
RemotePartyName, 1603
voice_getAllCallRmtPtyNum, 1603
callID, 1603
RemotePartyNum, 1603
voice_getCallFWExtInfo, 1603
CallFWExtInfo, 1604
numInstances, 1604
voice_getCallFWInfo, 1604
CallFWInfo, 1604
numInstances, 1604
voice_lineCtrlInfo, 1604
polarityIncluded, 1605
pwrDenialTime, 1605
revPolarity, 1605
toggleMode, 1605
voice_newPwdData, 1605
newPwd, 1606
newPwdAgain, 1606
voice_peerNumberInfo, 1606
callID, 1607
numLen, 1608
numPI, 1608
numPlan, 1608
numSI, 1608
numType, 1608
number, 1608
voice_prefVoiceSO, 1608
evrcCapability, 1610
homeOrigVoiceSO, 1610
homePageVoiceSO, 1610
namID, 1610
roamOrigVoiceSO, 1610
voice_redirNumInfo, 1610
numLen, 1611
numPlan, 1611
numType, 1611
number, 1611
PI, 1611
reason, 1611
SI, 1611
voice_remotePartyName, 1612
callerName, 1612
codingScheme, 1612
nameLen, 1612
namePI, 1612
voice_remotePartyNum, 1612
numLen, 1613
presentationInd, 1613
remPartyNumber, 1613
voice_roamTimer, 1613
namID, 1614
roamTimerValue, 1614
voice_signalInfo, 1614
alertPitch, 1614

signal, 1614
signalType, 1614
voiceALSSelectLineInfo, 1618
lineValue, 1618
voiceALSSetLineSwitchInfo, 1618
switchOption, 1618
voiceAnswerCall, 1618
pCallId, 1619
voiceBindSubscriptionInfo, 1619
subsType, 1619
voiceBurstDTMFInfo, 1619
BurstDTMFInfo, 1620
pBurstDTMFLengths, 1620
voiceCallInfoReq, 1620
callID, 1620
voiceCallInfoResp, 1620
pAlertType, 1622
pAlertingPattern, 1622
pAlphaIDInfo, 1622
pCallInfo, 1622
pConnectNumInfo, 1622
pDiagInfo, 1622
pOTASPStatus, 1622
pRemotePartyName, 1622
pRemotePartyNum, 1622
pSrvOpt, 1623
pUUSInfo, 1623
pVoicePrivacy, 1623
voiceCallRequestParams, 1623
callNumber, 1624
pCLIRType, 1624
pCUGInfo, 1624
pCallPartySubAdd, 1624
pCallType, 1624
pEmergencyCategory, 1624
pSvcType, 1624
pUUSInFo, 1624
voiceCallResponseParams, 1624
pAlphaIDInfo, 1625
pCCResultType, 1625
pCCSUPSType, 1625
pCallID, 1625
voiceContDTMFinfo, 1625
DTMFdigit, 1626
pCallID, 1626
voiceDTMFEventInfo, 1626
DTMFInformation, 1627
pOffLength, 1627
pOnLength, 1627
results, 1627
voiceFlashInfo, 1627
pCallID, 1627
pFlashPayLd, 1628
pFlashType, 1628
voiceGetAllCallInfo, 1628
pArrAlertingPattern, 1630
pArrAlertingType, 1630
pArrAlphaID, 1630
pArrCallEndReason, 1630
pArrCallInfo, 1630
pArrCalledPartyNum, 1630
pArrConnectPartyNum, 1630
pArrDiagInfo, 1630
pArrRedirPartyNum, 1630
pArrRemotePartyName, 1630
pArrRemotePartyNum, 1630
pArrSvcOption, 1630
pArrUUSInfo, 1630
pOTASPStatus, 1630
pVoicePrivacy, 1630
voiceGetCLIPResp, 1636
pAlphaIDInfo, 1637
pCCResType, 1637
pCCSUPSType, 1637
pCLIPResp, 1637
pCallID, 1637
pFailCause, 1637
voiceGetCLIRResp, 1637
pAlphaIDInfo, 1638
pCCResType, 1638
pCCSUPSType, 1638
pCLIRResp, 1638
pCallID, 1638
pFailCause, 1638
voiceGetCNAPResp, 1638
pAlphaIDInfo, 1639
pCCResType, 1639
pCCSUPSType, 1639
pCNAPResp, 1639
pCallID, 1639
pFailCause, 1639
voiceGetCOLPResp, 1639
pAlphaIDInfo, 1640
pCCResType, 1641
pCCSUPSType, 1641
pCOLPResp, 1641
pCallID, 1640
pFailCause, 1641
voiceGetCOLRResp, 1641
pAlphaIDInfo, 1642
pCCResType, 1642
pCCSUPSType, 1642
pCOLRResp, 1642
pCallID, 1642
pFailCause, 1642
voiceGetCallBarringReq, 1630
pSvcClass, 1631
reason, 1631
voiceGetCallBarringResp, 1631
pAlphaIDInfo, 1632
pCCResType, 1632
pCCSUPSType, 1632
pCallID, 1632
pFailCause, 1632
pSvcClass, 1632
voiceGetCallFWReq, 1632

pSvcClass, 1633
Reason, 1633
voiceGetCallFWResp, 1633
pAlphaIDInfo, 1634
pCCResType, 1634
pCCSUPSType, 1634
pCallID, 1634
pFailCause, 1634
pGetCallFWExtInfo, 1634
pGetCallFWInfo, 1634
voiceGetCallWaitInfo, 1634
pAlphaIDInfo, 1635
pCCResType, 1636
pCCSUPSType, 1636
pCallID, 1636
pFailCause, 1636
pSvcClass, 1636
voiceGetConfigReq, 1642
pAMRStatus, 1643
pAirTimer, 1643
pAutoAnswer, 1643
pNamID, 1643
pPrefVoicePrivacy, 1643
pPrefVoiceSO, 1643
pRoamTimer, 1643
pTTYMode, 1644
pVoiceDomainPref, 1644
voiceGetConfigResp, 1644
pAirTimerCnt, 1645
pAutoAnswerStat, 1645
pCurAMRConfig, 1645
pCurPrefVoiceSO, 1645
pCurVoiceDomainPref, 1645
pCurVoicePrivacyPref, 1645
pCurrTTYMode, 1645
pRoamTimerCnt, 1645
voiceIndicationRegisterInfo, 1645
pRegDTMFEvents, 1646
pRegVoicePrivacyEvents, 1646
pSuppsNotifEvents, 1646
voiceInfoRec, 1646
callID, 1648
pCLIRCause, 1648
pCallWaitInd, 1648
pCalledPartyInfo, 1648
pCallerIDInfo, 1648
pCallerNameInfo, 1648
pCallingPartyInfo, 1648
pConnectNumInfo, 1648
pDispInfo, 1648
pExtDispInfo, 1648
pExtDispRecInfo, 1648
pLineCtrlInfo, 1648
pNSSAudioCtrl, 1648
pNSSRelease, 1649
pRedirNumInfo, 1649
pSignalInfo, 1649
results, 1649
voiceManageCallsReq, 1649
pCallID, 1649
SUPSType, 1649
voiceManageCallsResp, 1650
pFailCause, 1650
VoiceNumber
unpack_dms_GetVoiceNumber_t, 1233
voiceNumberSize
unpack_dms_GetVoiceNumber_t, 1233
voiceOTASPStatusInfo, 1650
callID, 1651
OTASPStatus, 1651
results, 1651
voiceOrigUSSDNoWaitInfo, 1650
USSInformation, 1650
voicePrivacy
unpack_voice_voicePrivacyChangeCallback_ind_-t, 1514
voicePrivacyInfo, 1652
voicePrivacyInfo, 1651
callID, 1652
results, 1652
voicePrivacy, 1652
voiceSUPSInfo, 1664
pAlphaIDInfo, 1666
pCLIPstatus, 1666
pCLIRstatus, 1666
pCNAPstatus, 1666
pCOLPstatus, 1666
pCOLRstatus, 1666
pCallBarPasswd, 1666
pCallFWNum, 1666
pCallFWTimerVal, 1666
pCallFwdInfo, 1666
pCallID, 1666
pDataSrc, 1666
pFailCause, 1666
pNewPwdData, 1666
pReason, 1666
pSvcClass, 1666
pUSSInfo, 1666
results, 1666
SUPSInformation, 1666
voiceSUPSNotification, 1666
callID, 1668
notifType, 1668
pCUGIndex, 1668
pECTNum, 1668
results, 1668
voiceSetAllCallStatusCbkInfo, 1652
arrCallInfomation, 1654
pArrAlertingPattern, 1654
pArrAlertingType, 1654
pArrAlphaID, 1654
pArrCallEndReason, 1654
pArrCalledPartyNum, 1654
pArrConnectPartyNum, 1654
pArrDiagInfo, 1654

pArrRedirPartyNum, 1654
pArrRemotePartyName, 1654
pArrRemotePartyNum, 1654
pArrSvcOption, 1654
results, 1654
voiceSetCallBarringPwdInfo, 1654
newPasswd, 1655
newPasswdAgain, 1655
oldPasswd, 1655
Reason, 1655
voiceSetCallBarringPwdResp, 1655
pAlphaIDInfo, 1656
pCCResType, 1656
pCCSUPSType, 1656
pCallID, 1656
pFailCause, 1656
voiceSetConfigReq, 1657
pAirTimerConfig, 1658
pAutoAnswer, 1658
pPrefVoiceDomain, 1658
pPrefVoiceSO, 1658
pRoamTimerConfig, 1658
pTTYMode, 1658
voiceSetConfigResp, 1658
pAirTimerStatus, 1659
pAutoAnsStatus, 1659
pPrefVoiceSOStatus, 1659
pRoamTimerStatus, 1659
pTTYConfigStatus, 1659
pVoiceDomainPrefStatus, 1659
voiceSetPrefPrivacy, 1659
privacyPref, 1660
voiceSetSUPSServiceReq, 1660
pCallBarringPasswd, 1662
pCallForwardingNumber, 1662
pCallFwdTypeAndPlan, 1662
pServiceClass, 1662
pTimerVal, 1662
reason, 1662
voiceSvc, 1662
voiceSetSUPSServiceResp, 1662
pAlphaIDInfo, 1663
pCCResultType, 1663
pCCSUPSType, 1663
pCallID, 1663
pFailCause, 1663
voiceStopContDTMFinfo, 1663
callID, 1664
voiceSvc
pack_voice_SLQSVoiceSetSUPSService_t, 841
voiceSetSUPSServiceReq, 1662
VolValue
SetAudioVolTLBConfigReq, 1002
VoltStat
dms_VoltageTlv, 254
VoltTlv
unpack_dms_SwiEventReportCallBack_ind_t, 1265
Voltage
dms_VoltageTlv, 254
Volume
GetAudioProfileResp, 295
GetAudioVolTLBConfigReq, 296
GetM2MAudioProfileResp, 312
SetAudioProfileReq, 1001
SetAudioVolTLBConfigReq, 1002
voteForInit
registerRefresh, 963
uim_registerRefresh, 1163

WDSNUMPDPS
qaGobiApiWds.h, 2312
WDSPDP1IDX
qaGobiApiWds.h, 2312
WDSPDP2IDX
qaGobiApiWds.h, 2312
WDSPDP3IDX
qaGobiApiWds.h, 2312
WDSPDP4IDX
qaGobiApiWds.h, 2312
WDSPDP5IDX
qaGobiApiWds.h, 2312
WDSPDP6IDX
qaGobiApiWds.h, 2312
WDSPDP7IDX
qaGobiApiWds.h, 2312
WDSPDP8IDX
qaGobiApiWds.h, 2312
WAMSParaChanged
_SwiAvmsEventInd, 113
wAlertMsgLength
_QmiSwiAvmsEventReportConfigResp, 81
WCDMACellInfo
lteWcdmaCellInfo, 465
nas_lteWcdmaCellInfo, 548
WCDMAECIOThresh, 1669
pWCDMAECIOThreshList, 1669
WCDMAECIOThreshListLen, 1669
WCDMAECIOThreshListLen
nas_WCDMAECIOThresh, 620
WCDMAECIOThresh, 1669
WCDMAInfoLTENeighborCell, 1669
UMTSLTENbrCell, 1670
umtsLTENbrCellLen, 1670
wcdmaRRCState, 1670
WCDMARSSIThresh, 1675
pWCDMARSSIThreshList, 1675
WCDMARSSIThreshListLen, 1675
WCDMARSSIThreshListLen
nas_WCDMARSSIThresh, 622
WCDMARSSIThresh, 1675
WCDMASSInfo
unpack_nas_SLQSNasGetSigInfo_t, 1359
WCDMASysInfo, 1675
cellId, 1678
cellIdValid, 1678
hsCallStatus, 1678

hsCallStatusValid, 1678
hsInd, 1678
hsIndValid, 1678
lac, 1678
lacValid, 1678
MCC, 1678
MNC, 1678
networkIdValid, 1678
psc, 1678
pscValid, 1678
regRejectInfoValid, 1678
rejCause, 1679
rejectSrvDomain, 1679
sysInfoWCDMA, 1679
WDS_IsGobiDevice
qaGobiApiWds.h, 2349
WDS_PROFILE_3GPP
wds.h, 2477
WDS_PROFILE_3GPP2
wds.h, 2477
WDS_SRV
qaGobiApiCbk.h, 1914
WDSGetLoopbackData, 1709
ByteLoopbackMode, 1710
ByteLoopbackMultiplier, 1710
WDSSWICurrentChannelRates, 1717
current_channel_rx_rate, 1718
current_channel_tx_rate, 1718
max_channel_rx_rate, 1718
max_channel_tx_rate, 1718
WDSSetLoopbackData, 1717
pLoopbackMode, 1717
pLoopbackMultiplier, 1717
wDescriptionLength
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 80
wErrorCode
_QmiSwiAvmsEventReportDataSessionStatus-Resp, 82
wHTTPStatus
_QmiSwiAvmsEventReportHTTPStatusResp, 83
wNameLength
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 80
WORD
SwiDataTypes.h, 2396
wSessionStatus
_QmiSwiAvmsEventReportNotificationResp, 85
wUpdateCompeteStatus
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 80
wUserInputTimeout
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 80
_QmiSwiAvmsEventReportConfigResp, 81
_QmiSwiAvmsEventReportConnectionRequest-Resp, 81
wVersionLength
_QmiSwiAvmsEventReportBinaryUpdateSession-InfoResp, 80
wWamsChangeMask
_QmiSwiAvmsEventReportWAMSParamChange-Resp, 86
wake_mask
pack_rms_SetSMSWake_t, 794
unpack_rms_GetSMSWake_t, 1420
wcdmaAmrStat
curAMRConfig, 218
voice_curAMRConfig, 1598
wcdmaCellInfo, 1668
cpich_ecno, 1669
cpich_rscp, 1669
psc, 1669
srxlev, 1669
wcdmaLongMsgDecodingParams, 1670
Date, 1672
MessageLen, 1672
pIsUDHPresent, 1672
pMessage, 1672
pPartNum, 1672
pReferenceNum, 1672
pScAddr, 1672
pScAddrLength, 1672
pSenderAddr, 1672
pSenderAddrLength, 1672
pTextMsg, 1672
pTextMsgLength, 1672
pTotalNum, 1672
Time, 1672
wcdmaMsgDecodingParams, 1672
date, 1673
MessageLen, 1673
pMessage, 1673
pScAddrLength, 1673
pSenderAddrLength, 1673
pTextMsgLength, 1673
scAddr, 1674
senderAddr, 1674
textMsg, 1674
time, 1674
wcdmaMsgEncodingParams, 1674
alphabet, 1674
messageSize, 1674
PDUMessage, 1674
pDestAddr, 1674
pTextMsg, 1675
wcdmaRRCState
nas_WCDMAInfoLTENeighborCell, 621
WCDMAInfoLTENeighborCell, 1670
wcdmaUARFCN, 1679
status, 1679
uarfcn, 1679
Wdisable
unpack_dms_SLQSDmsSwiGetPCInfo_t, 1243
wds.h

QMI_LITE_WDS_CURRENT_CALL_DB_MASK, 2478
QMI_LITE_WDS_LAST_CALL_DB_MASK, 2478
wds.h, 2469
BYT_STAT_STAT_MASK, 2477
liteQmiDataBearerMasks, 2478
PACK_WDS_IPV4, 2477
PACK_WDS_IPV6, 2477
pack_wds_DHCPv4ClientLeaseChange, 2478
pack_wds_GetAutoconnect, 2478
pack_wds_GetByteTotals, 2479
pack_wds_GetConnectionRate, 2479
pack_wds_GetDataBearerTechnology, 2480
pack_wds_GetDefaultProfile, 2480
pack_wds_GetDefaultProfileNum, 2480
pack_wds_GetDormancyState, 2481
pack_wds_GetLastMobileIPError, 2481
pack_wds_GetMobileIP, 2482
pack_wds_GetMobileIPProfile, 2482
pack_wds_GetPacketStatistics, 2483
pack_wds_GetPacketStatus, 2483
pack_wds_GetSessionDuration, 2483
pack_wds_GetSessionState, 2484
pack_wds_RMSetTransferStatistics, 2484
pack_wds_SLQSCreateProfile, 2488
pack_wds_SLQSDeleteProfile, 2488
pack_wds_SLQSGet3GPPConfigItem, 2488
pack_wds_SLQSGetCurrDataSystemStat, 2489
pack_wds_SLQSGetCurrentChannelRate, 2489
pack_wds_SLQSGetDUNCallInfo, 2490
pack_wds_SLQSGetDataBearerTechnology, 2490
pack_wds_SLQSGetProfileSettings, 2491
pack_wds_SLQSGetRuntimeSettings, 2491
pack_wds_SLQSModifyProfile, 2491
pack_wds_SLQSResetPacketStatics, 2492
pack_wds_SLQSSGetDHCPv4ClientConfig, 2493
pack_wds_SLQSSGetLoopback, 2494
pack_wds_SLQSSSetDHCPv4ClientConfig, 2494
pack_wds_SLQSSSetLoopback, 2495
pack_wds_SLQSSet3GPPConfigItem, 2492
pack_wds_SLQSSetIPFamilyPreference, 2493
pack_wds_SLQSSetWdsEventCallback, 2493
pack_wds_SLQSStartDataSession, 2495
pack_wds_SLQSStopDataSession, 2495
pack_wds_SLQSWdsGoActive, 2496
pack_wds_SLQSWdsGoDormant, 2496
pack_wds_SLQSWdsSetEventReport, 2497
pack_wds_SLQSWdsSwiPDPRuntimeSettings, 2497
pack_wds_SetAutoconnect, 2485
pack_wds_SetDefaultProfile, 2485
pack_wds_SetDefaultProfileNum, 2485
pack_wds_SetMobileIP, 2486
pack_wds_SetMobileIPParameters, 2486
pack_wds_SetMobileIPProfile, 2487
pack_wds_SetMuxID, 2487
unpack_wds_DHCPv4ClientLease_ind, 2498
unpack_wds_DHCPv4ClientLeaseChange, 2498
unpack_wds_DHCPv4ClientLeaseChange_t, 2477
unpack_wds_GetAutoconnect, 2498
unpack_wds_GetByteTotals, 2499
unpack_wds_GetConnectionRate, 2499
unpack_wds_GetDataBearerTechnology, 2499
unpack_wds_GetDefaultProfile, 2500
unpack_wds_GetDefaultProfileNum, 2500
unpack_wds_GetDormancyState, 2500
unpack_wds_GetLastMobileIPError, 2501
unpack_wds_GetMobileIP, 2501
unpack_wds_GetMobileIPProfile, 2501
unpack_wds_GetPacketStatistics, 2502
unpack_wds_GetPacketStatus, 2502
unpack_wds_GetSessionDuration, 2502
unpack_wds_GetSessionState, 2503
unpack_wds_RMSetTransferStatistics, 2503
unpack_wds_RMTransferStatistics_ind, 2503
unpack_wds_RMTransferStatistics_ind_t, 2477
unpack_wds_SLQSCreateProfile, 2506
unpack_wds_SLQSDUNCallInfoCallBack_ind, 2507
unpack_wds_SLQSDeleteProfile, 2506
unpack_wds_SLQSGet3GPPConfigItem, 2507
unpack_wds_SLQSGetCurrDataSystemStat, 2507
unpack_wds_SLQSGetCurrentChannelRate, 2508
unpack_wds_SLQSGetDUNCallInfo, 2508
unpack_wds_SLQSGetDataBearerTechnology, 2508
unpack_wds_SLQSGetProfileSettings, 2509
unpack_wds_SLQSGetRuntimeSettings, 2509
unpack_wds_SLQSModifyProfile, 2509
unpack_wds_SLQSResetPacketStatics, 2510
unpack_wds_SLQSResetPacketStatics_t, 2477
unpack_wds_SLQSSGetDHCPv4ClientConfig, 2512
unpack_wds_SLQSSGetLoopback, 2512
unpack_wds_SLQSSSetDHCPv4ClientConfig, 2512
unpack_wds_SLQSSSetDHCPv4ClientConfig_t, 2477
unpack_wds_SLQSSSetLoopback, 2513
unpack_wds_SLQSSSetLoopback_t, 2477
unpack_wds_SLQSSet3GPPConfigItem, 2510
unpack_wds_SLQSSet3GPPConfigItem_t, 2477
unpack_wds_SLQSSetIPFamilyPreference, 2510
unpack_wds_SLQSSetPacketSrvStatusCallback, 2511
unpack_wds_SLQSSetWdsEventCallback, 2511
unpack_wds_SLQSSetWdsEventCallback_ind, 2511
unpack_wds_SLQSSetWdsEventCallback_t, 2477
unpack_wds_SLQSStartDataSession, 2513
unpack_wds_SLQSStopDataSession, 2513
unpack_wds_SLQSStopDataSession_t, 2477
unpack_wds_SLQSWdsGoActive, 2514
unpack_wds_SLQSWdsGoActive_t, 2477
unpack_wds_SLQSWdsGoDormant, 2514
unpack_wds_SLQSWdsGoDormant_t, 2477

unpack_wds_SLQSWdsSetEventReport, 2514
unpack_wds_SLQSWdsSetEventReport_t, 2477
unpack_wds_SLQSWdsSwiPDPRuntimeSettings, 2515
unpack_wds_SetAutoconnect, 2504
unpack_wds_SetAutoconnect_t, 2477
unpack_wds_SetDefaultProfile, 2504
unpack_wds_SetDefaultProfile_t, 2477
unpack_wds_SetDefaultProfileNum, 2504
unpack_wds_SetDefaultProfileNum_t, 2477
unpack_wds_SetMobileIP, 2505
unpack_wds_SetMobileIP_t, 2477
unpack_wds_SetMobileIPParameters, 2505
unpack_wds_SetMobileIPParameters_t, 2477
unpack_wds_SetMobileIPProfile, 2505
unpack_wds_SetMuxID, 2506
unpack_wds_SetMuxID_t, 2477
UnpackQmiProfileInfo, 2478
WDS_PROFILE_3GPP, 2477
WDS_PROFILE_3GPP2, 2477
wds_ChannelRateTlv, 1680
ChannelRate, 1680
TlvPresent, 1680
wds_ConnStatusTlv, 1680
MDMConnStatus, 1681
TlvPresent, 1681
wds_DHCPLeaseOptTlv, 1683
numOpt, 1684
optList, 1684
optListData, 1684
TlvPresent, 1684
wds_DHCPLeaseStateTlv, 1684
leaseState, 1684
TlvPresent, 1684
wds_DHCPOpt, 1685
optCode, 1685
optValLen, 1685
pOptVal, 1685
wds_DHCPProfileIdTlv, 1685
profileId, 1686
profileType, 1686
TlvPresent, 1686
wds_DHCPv4HWConfig, 1686
chaddr, 1686
chaddrLen, 1686
hwType, 1686
wds_DHCPv4Option, 1686
optCode, 1687
optVal, 1687
optValLen, 1687
wds_DHCPv4OptionList, 1687
numOpt, 1687
pOptList, 1687
wds_DHCPv4ProfileId, 1688
profileId, 1688
profileType, 1688
wds_DataBearTechTlv, 1682
DataBearerTech, 1682
TlvPresent, 1682
wds_DataULongLongTlv, 1683
TlvPresent, 1683
ullData, 1683
wds_DataULongTlv, 1683
TlvPresent, 1683
ulData, 1683
wds_Domain, 1688
domainLen, 1688
domainName, 1688
wds_DomainNameList, 1689
domain, 1689
numInstances, 1689
wds_DormStatTlv, 1689
DormancyStat, 1689
TlvPresent, 1690
wds_GPRSQoS, 1690
delayClass, 1690
meanThroughputClass, 1690
peakThroughputClass, 1690
precedenceClass, 1690
reliabilityClass, 1690
wds_IPV6AddressInfo, 1691
IPAddressV6, 1691
IPV6PrefixLen, 1691
wds_IPV6GWAddressInfo, 1691
gwAddressV6, 1692
gwV6PrefixLen, 1692
wds_IPv4AdTlv, 1690
IPv4Addr, 1691
TlvPresent, 1691
wds_LastMdmCallEndRsnTlv, 1692
CallEndReason, 1692
TlvPresent, 1692
wds_PCSCFFQDNAddress, 1693
fqdnAddr, 1693
fqdnLen, 1693
wds_PCSCFFQDNAddressList, 1693
numInstances, 1693
pcsfFQDNAddress, 1693
wds_PCSCFIPv4ServerAddressList, 1694
numInstances, 1694
pscsfIPv4Addr, 1694
wds_ProfileIdentifier, 1694
profileIndex, 1695
profileType, 1695
wds_RXBytesOKTlv, 1695
RxByteOKCnt, 1695
TlvPresent, 1696
wds_TXBytesOKTlv, 1697
TlvPresent, 1697
TxByteOKCnt, 1697
wds_TrStatInd, 1696
statsMask, 1697
statsPeriod, 1697
wds_UMTSMinQoS, 1697
deliveryErrSDU, 1699
grntDownlinkBitrate, 1699

grntUplinkBitrate, 1700
maxDownlinkBitrate, 1700
maxSDUSize, 1700
maxUplinkBitrate, 1700
qosDeliveryOrder, 1700
resBerRatio, 1700
sduErrorRatio, 1700
trafficClass, 1700
trafficPriority, 1700
transferDelay, 1700
wds_channelRate, 1679
CurrChanRxRate, 1680
CurrChanTxRate, 1680
wds_currNetworkInfo, 1681
NetworkType, 1682
RATMask, 1682
SOMask, 1682
wds_profileInfo, 1695
SlqsProfile3GPP, 1695
SlqsProfile3GPP2, 1695
wds_transferStatInd, 1696
StatsMask, 1696
StatsPeriod, 1696
WdsByteTotals, 1700
ByteTotalsElmntsV4, 1701
ByteTotalsElmntsV6, 1701
pV4sessionId, 1701
pV6sessionId, 1701
WdsByteTotalsElmnts, 1701
pRXTotalBytes, 1701
pTXTotalBytes, 1701
WdsClientLeaseChange, 1701
pEnableNotification, 1702
WdsConnectionRate, 1702
ConnRateElmntsV4, 1702
ConnRateElmntsV6, 1702
pV4sessionId, 1702
pV6sessionId, 1702
WdsConnectionRateElmnts, 1703
pCurrentChannelRXRate, 1703
pCurrentChannelTXRate, 1703
pMaxChannelRXRate, 1703
pMaxChannelTXRate, 1703
WdsDHCPv4ClientLeaseInd, 1703
pIPv4Addr, 1704
pLeaseState, 1704
pOptList, 1704
pProfileId, 1704
WdsDHCPv4Config, 1704
pHwConfig, 1705
pProfileId, 1705
pRequestOptionList, 1705
WdsDHCPv4HWConfig, 1705
chaddr, 1705
chaddrLen, 1705
hwType, 1705
WdsDHCPv4Option, 1706
optCode, 1706
optVal, 1706
optValLen, 1707
WdsDHCPv4OptionList, 1707
numOpt, 1708
pOptList, 1708
WdsDHCPv4ProfileId, 1709
profileId, 1709
profileType, 1709
wdsDhcpv4HwConfig, 1705
chaddr, 1706
chaddrLen, 1706
hwType, 1706
wdsDhcpv4Option, 1707
optCode, 1707
optVal, 1707
optValLen, 1707
wdsDhcpv4OptionList, 1708
numOpt, 1708
pOptList, 1708
wdsDhcpv4ProfileId, 1708
profileId, 1709
profileType, 1709
WdsIpAddressInfoReq, 1710
ip, 1710
pv4sessionId, 1710
pv6sessionId, 1710
WdsPktStatisticsElmnts, 1711
pRXDroppedCount, 1712
pRXOKBytesLastCall, 1712
pRXOkBytesCount, 1712
pRXPacketErrors, 1712
pRXPacketOverflows, 1712
pRXPacketSuccesses, 1712
pTXDroppedCount, 1712
pTXOKBytesLastCall, 1712
pTXOkBytesCount, 1712
pTXPacketErrors, 1712
pTXPacketOverflows, 1712
pTXPacketSuccesses, 1712
WdsPktStatisticsReq, 1712
pStatMask, 1713
WdsPktStatisticsResp, 1713
pV4sessionId, 1713
pV6sessionId, 1713
PktStatElmntsV4, 1713
PktStatElmntsV6, 1713
WdsProfileParam, 1714
SlqsProfile3GPP, 1714
SlqsProfile3GPP2, 1714
WdsRunTimeSettings, 1714
rts, 1715
v4sessionId, 1715
v6sessionId, 1715
wdsSetEventReportReq, 1715
pCurrChannelRateInd, 1716
pCurrDataBearerTechInd, 1716
pCurrPrefDataSysInd, 1716
pDataBearerTechInd, 1716

pDataCallStatusChangeInd, 1716
pDataSystemStatusChangeInd, 1716
pDormancyStatusInd, 1716
pEVDOPageMonPerChangeInd, 1716
pMIPStatusInd, 1716
pTransferStatInd, 1717
Wireless Data Service (WDS), 44
word
swi_uint256_t, 1092

xAxis
sensorData, 989
sensorData_t, 990
xferStatAvail
unpack_wds_SLQSSetWdsEventCallback_ind_t, 1554
xid
pack_loc_SLQSLOCGetBestAvailPos_t, 730
pack_qmi_t, 792
unpack_qmi_t, 1397
xtra_start_gps_minutes
GPSStateInfo, 327
unpack_pds_SLQSGetGPSStateInfo_t, 1396
xtra_start_gps_week
GPSStateInfo, 327
unpack_pds_SLQSGetGPSStateInfo_t, 1397
xtra_valid_duration_hours
GPSStateInfo, 327
unpack_pds_SLQSGetGPSStateInfo_t, 1397

yAxis
sensorData, 989
sensorData_t, 990
year
nas_timeInfo, 613
nas_UniversalTime, 619
timeInfo, 1134
UniversalTime, 1205

zAxis
sensorData, 989
sensorData_t, 990